

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250279847

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

BARIK; Somsubhra et al.

CODE BLOCK GROUP AND CODE BLOCK BUNDLE ALIGNMENT SIGNALING

Abstract

A wireless device may receive a code block bundle (CBB) grouping algorithm indicator. The wireless device may calculate a CBB configuration based on the CBB grouping algorithm indicator. The wireless device may transmit a first plurality of CBBs based on the calculated CBB configuration. Each code block group (CBG) of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each code block bundle (CBB) of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. To transmit the first plurality of CBBs based on the calculated CBB configuration, the wireless device may interleave code blocks (CBs) associated with each CBB of the first plurality of CBBs. The wireless device may further transmit the interleaved CBs. The transmissions based on the CBB grouping algorithm may apply to both uplink (UL) transmissions and to downlink (DL) transmissions.

Inventors: BARIK; Somsubhra (San Diego, CA), SUN; Jing (San Diego, CA), YANG; Wei (San Diego, CA)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 96880609

Appl. No.: 18/595247

Filed: March 04, 2024

Publication Classification

Int. Cl.: H04L1/00 (20060101); H04W8/22 (20090101)

U.S. Cl.:

CPC H04L1/0057 (20130101); H04L1/0071 (20130101); H04W8/22 (20130101);

Background/Summary

TECHNICAL FIELD

[0001] The present disclosure relates generally to communication systems, and more particularly, to a wireless system for bundling code blocks for transmission.

INTRODUCTION

[0002] Wireless communication systems are widely deployed to provide various telecommunication services such as telephony, video, data, messaging, and broadcasts. Typical wireless communication systems may employ multiple-access technologies capable of supporting communication with multiple users by sharing available system resources. Examples of such multiple-access technologies include code division multiple access (CDMA) systems, time division multiple access (TDMA) systems, frequency division multiple access (FDMA) systems, orthogonal frequency division multiple access (OFDMA) systems, single-carrier frequency division multiple access (SC-FDMA) systems, and time division synchronous code division multiple access (TD-SCDMA) systems.

[0003] These multiple access technologies have been adopted in various telecommunication standards to provide a common protocol that enables different wireless devices to communicate on a municipal, national, regional, and even global level. An example telecommunication standard is 5G New Radio (NR). 5G NR is part of a continuous mobile broadband evolution promulgated by Third Generation Partnership Project (3GPP) to meet new requirements associated with latency, reliability, security, scalability (e.g., with Internet of Things (IoT)), and other requirements. 5G NR includes services associated with enhanced mobile broadband (eMBB), massive machine type communications (mMTC), and ultra-reliable low latency communications (URLLC). Some aspects of 5G NR may be based on the 4G Long Term Evolution (LTE) standard. There exists a need for further improvements in 5G NR technology. These improvements may also be applicable to other multi-access technologies and the telecommunication standards that employ these technologies.

BRIEF SUMMARY

[0004] The following presents a simplified summary of one or more aspects in order to provide a basic understanding of such aspects. This summary is not an extensive overview of all contemplated aspects. This summary neither identifies key or critical elements of all aspects nor delineates the scope of any or all aspects. Its sole purpose is to present some concepts of one or more aspects in a simplified form as a prelude to the more detailed description that is presented later.

[0005] In an aspect of the disclosure, a method, a computer-readable medium, and an apparatus are provided. The apparatus may include a user equipment (UE). The apparatus may receive a code block bundle (CBB) grouping algorithm indicator. The apparatus may calculate a CBB configuration based on the CBB grouping algorithm indicator. The apparatus may transmit a first plurality of CBBs based on the calculated CBB configuration. Each code block group (CBG) of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs.

[0006] In an aspect of the disclosure, a method, a computer-readable medium, and an apparatus are provided. The apparatus may include a network node. The apparatus may transmit a CBB grouping algorithm indicator. The apparatus may receive a first plurality of CBBs based on the CBB grouping algorithm indicator. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs.

[0007] In some aspects, the techniques described herein relate to a method of wireless communication at a UE, including: receiving a CBB grouping algorithm indicator; calculating a

CBB configuration based on the CBB grouping algorithm indicator; and transmitting a first plurality of CBBs based on the calculated CBB configuration, where each CBG of a second plurality of CBGs is associated with a subset of the first plurality of CBBs, where each CBB of the first plurality of CBBs is associated with exactly one of the second plurality of CBGs.

[0008] In some aspects, the techniques described herein relate to a method, where the CBB grouping algorithm indicator indicates the UE to associate code blocks (CBs) with CBGs before associating the CBGs with CBBs, where calculating the CBB configuration based on the CBB grouping algorithm indicator includes: associating each CB of a third plurality of CBs with one CBG of the second plurality of CBGs; and associating each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs after the association of each CB of the third plurality of CBs with one CBG of the second plurality of CBGs.

[0009] In some aspects, the techniques described herein relate to a method, further including calculating a first number of CBs associated with a first CBB of the first plurality CBBs based on a second number of CBs associated with a first CBG of the second plurality of CBGs.

[0010] In some aspects, the techniques described herein relate to a method, where associating each CB of the third plurality of CBs with one CBG of the second plurality of CBGs includes associating each CB of the third plurality of CBs with one CBG of the second plurality of CBGs such that a first number of CBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one.

[0011] In some aspects, the techniques described herein relate to a method, where associating each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs includes associating each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs such that a first number of CBs associated with a first CBB of a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first CBG of the second plurality of CBGs by more than one.

[0012] In some aspects, the techniques described herein relate to a method, where the CBB grouping algorithm indicator indicates the UE to associate CBs with CBBs before associating the CBBs with CBGs, where calculating the CBB configuration based on the CBB grouping algorithm indicator includes: associating each CB of a third plurality of CBs with one CBB of the first plurality of CBBs; and associating each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs after the association of each CB of the third plurality of CBs with one CBB of the first plurality of CBBs.

[0013] In some aspects, the techniques described herein relate to a method, where associating each CB of the third plurality of CBs with one CBB of the first plurality of CBBs includes associating each CB of the third plurality of CBs with one CBB of the first plurality of CBBs such that a first number of CBs associated with a first CBB of the first plurality of CBBs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first plurality of CBBs by more than one.

[0014] In some aspects, the techniques described herein relate to a method, where associating each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs includes associating each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs such that a first number of CBBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one.

[0015] In some aspects, the techniques described herein relate to a method, further including transmitting an indicator of a capability of the UE to associate CBBs and CBGs before the reception of the CBB grouping algorithm indicator.

[0016] In some aspects, the techniques described herein relate to a method, where the indicator indicates at least one of: a processing time for the UE to encode a number of CBs associated with

one of the first plurality of CBBs; a buffer associated with an encoding of CBs associated with one of the first plurality of CBBs; a delay associated with the encoding of CBs associated with one of the first plurality of CBBs; or a maximum number of CBs that the UE is able to associate with one of the first plurality of CBBs.

[0017] In some aspects, the techniques described herein relate to a method, where transmitting the first plurality of CBBs based on the calculated CBB configuration includes, for each CBB of the first plurality of CBBs: interleaving CBs associated with the CBB; and transmitting the interleaved CBs.

[0018] In some aspects, the techniques described herein relate to a method of wireless communication at a network node, including: transmitting a CBB grouping algorithm indicator; and receiving a first plurality of CBBs based on the CBB grouping algorithm indicator, where each CBG of a second plurality of CBGs is associated with a subset of the first plurality of CBBs, where each CBB of the first plurality of CBBs is associated with exactly one of the second plurality of CBGs.

[0019] In some aspects, the techniques described herein relate to a method, where the CBB grouping algorithm indicator indicates a UE to associate CBs with CBGs before associating the CBGs with CBBs.

[0020] In some aspects, the techniques described herein relate to a method, where the CBB grouping algorithm indicator further indicates the UE to calculate a bundle size of one of the first plurality CBBs based on a number of CBs associated with one of the second plurality of CBGs.

[0021] In some aspects, the techniques described herein relate to a method, where the CBB grouping algorithm indicator further indicates the UE to associate each CB of a third plurality of CBs with one CBG of the second plurality of CBGs such that a first number of CBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one.

[0022] In some aspects, the techniques described herein relate to a method, where the CBB grouping algorithm indicator further indicates the UE to associate each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs such that a first number of CBs associated with a first CBB of a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first CBG of the second plurality of CBGs by more than one.

[0023] In some aspects, the techniques described herein relate to a method, where the CBB grouping algorithm indicator indicates a UE to associate CBs with CBBs before associating the CBBs with CBGs.

[0024] In some aspects, the techniques described herein relate to a method, where the CBB grouping algorithm indicator further indicates the UE to associate each CB of a third plurality of CBs with one CBB of the first plurality of CBBs such that a first number of CBs associated with a first CBB of the first plurality of CBBs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first plurality of CBBs by more than one.

[0025] In some aspects, the techniques described herein relate to a method, where the CBB grouping algorithm indicator further indicates the UE to associate each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs such that a first number of CBBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one.

[0026] In some aspects, the techniques described herein relate to a method, further including: receiving an indicator of a capability of a UE to associate CBBs and CBGs; and configuring the CBB grouping algorithm indicator based on the capability.

[0027] In some aspects, the techniques described herein relate to a method, where the indicator

indicates at least one of: a processing time for the UE to encode a number of CBs associated with one of the first plurality of CBBs; a buffer associated with an encoding of CBs associated with one of the first plurality of CBBs; a delay associated with the encoding of CBs associated with one of the first plurality of CBBs; or a maximum number of CBs that the UE is able to associate with one of the first plurality of CBBs.

[0028] In some aspects, the techniques described herein relate to a method, where receiving the first plurality of CBBs based on the CBB grouping algorithm indicator includes, for each of the first plurality of CBBs receiving interleaved CBs of one of the first plurality of CBBs.

[0029] In some aspects, the techniques described herein relate to a method, further including deinterleaving the received first plurality of CBBs based on the CBB grouping algorithm.

[0030] To the accomplishment of the foregoing and related ends, the one or more aspects may include the features hereinafter fully described and particularly pointed out in the claims. The following description and the drawings set forth in detail certain illustrative features of the one or more aspects. These features are indicative, however, of but a few of the various ways in which the principles of various aspects may be employed.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0031] FIG. 1 is a diagram illustrating an example of a wireless communications system and an access network.

[0032] FIG. 2A is a diagram illustrating an example of a first frame, in accordance with various aspects of the present disclosure.

[0033] FIG. 2B is a diagram illustrating an example of downlink (DL) channels within a subframe, in accordance with various aspects of the present disclosure.

[0034] FIG. 2C is a diagram illustrating an example of a second frame, in accordance with various aspects of the present disclosure.

[0035] FIG. 2D is a diagram illustrating an example of uplink (UL) channels within a subframe, in accordance with various aspects of the present disclosure.

[0036] FIG. 3 is a diagram illustrating an example of a base station and user equipment (UE) in an access network.

[0037] FIG. 4 is a diagram illustrating an example of interleaving for code block bundles (CBBs) of code blocks (CBs).

[0038] FIG. 5A is a diagram illustrating an example of grouping for code block groups (CBGs) of CBs and CBBs of CBs.

[0039] FIG. 5B is a diagram illustrating another example of grouping for CBGs of CBs and CBBs of CBs.

[0040] FIG. 6A is a diagram illustrating an example of grouping CBGs of CBs before grouping CBBs within each CBG.

[0041] FIG. 6B is a diagram illustrating an example of grouping CBBs of CBs before grouping the CBBs with CBGs.

[0042] FIG. 7A is a diagram illustrating an example of grouping CBGs of CBs before grouping CBBs within each CBG.

[0043] FIG. 7B is a diagram illustrating an example of grouping CBBs of CBs before grouping the CBBs with CBGs.

[0044] FIG. 8 is a connection flow diagram illustrating an example of signaling between a UE and a network node configured to align grouping of CBs in CBGs and CBBs.

[0045] FIG. 9 is a connection flow diagram illustrating an example of signaling between a UE and a network node configured to align grouping of CBs in CBGs and CBBs.

[0046] FIG. **10** is a flowchart of a method of wireless communication.

[0047] FIG. **11** is a flowchart of a method of wireless communication.

[0048] FIG. **12** is a flowchart of a method of wireless communication.

[0049] FIG. **13** is a flowchart of a method of wireless communication.

[0050] FIG. **14** is a flowchart of a method of wireless communication.

[0051] FIG. **15** is a diagram illustrating an example of a hardware implementation for an example apparatus and/or network entity.

[0052] FIG. **16** is a diagram illustrating an example of a hardware implementation for an example network entity.

[0053] FIG. **17** is a diagram illustrating an example of a hardware implementation for an example network entity.

DETAILED DESCRIPTION

[0054] The following description is directed to examples for the purposes of describing innovative aspects of this disclosure. However, a person having ordinary skill in the art may recognize that the teachings herein may be applied in a multitude of ways. Some or all of the described examples may be implemented in any device, system or network that is capable of transmitting and receiving radio frequency (RF) signals according to one or more of the Institute of Electrical and Electronics Engineers (IEEE) 802.11 standards, the IEEE 802.15 standards, the Bluetooth® standards as defined by the Bluetooth Special Interest Group (SIG), or the Long Term Evolution (LTE), 3G, 4G or 5G (New Radio (NR)) standards promulgated by the 3rd Generation Partnership Project (3GPP), among others. The described examples may be implemented in any device, system or network that is capable of transmitting and receiving RF signals according to one or more of the following technologies or techniques: code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal FDMA (OFDMA), single-carrier FDMA (SC-FDMA), spatial division multiple access (SDMA), rate-splitting multiple access (RSMA), multi-user shared access (MUSA), single-user (SU) multiple-input multiple-output (MIMO) and multi-user (MU)-MIMO. The described examples also may be implemented using other wireless communication protocols or RF signals suitable for use in one or more of a wireless personal area network (WPAN), a wireless local area network (WLAN), a wireless wide area network (WWAN), a wireless metropolitan area network (WMAN), or an internet of things (IoT) network.

[0055] Various aspects relate generally to wireless systems that bundle code blocks for transmission. Some aspects more specifically relate to signaling for aligning assignment of code blocks (CBs) for code block groups (CBGs) and for code block bundles (CBBs).

[0056] In some examples, a wireless device, for example a user equipment (UE), may receive a code block bundle (CBB) grouping algorithm indicator. The wireless device may calculate a CBB configuration based on the CBB grouping algorithm indicator. The wireless device may transmit a first plurality of CBBs based on the calculated CBB configuration. Each code block group (CBG) of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. To transmit the first plurality of CBBs based on the calculated CBB configuration, the wireless device may interleave code blocks (CBs) associated with each CBB of the first plurality of CBBs. The wireless device may further transmit the interleaved CBS. The transmissions of the first plurality of CBBs may apply to both uplink (UL) transmissions and to downlink (DL) transmissions.

[0057] In some examples, a wireless device, for example a network node, may transmit a CBB grouping algorithm indicator. The wireless device may receive a first plurality of CBBs based on the CBB grouping algorithm indicator. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs.

[0058] Particular aspects of the subject matter described in this disclosure can be implemented to realize one or more of the following potential advantages. In some examples, by configuring wireless devices to improve alignment of CBGs and CBBs such that the CBBs are non-overlapping subsets of the CBGs, the described techniques can be used to reduce the average variability in decoding the CBGs. Such an alignment also enables a reduced number of negative acknowledgement transmissions being transmitted for designated CBGs.

[0059] The detailed description set forth below in connection with the drawings describes various configurations and does not represent the only configurations in which the concepts described herein may be practiced. The detailed description includes specific details for the purpose of providing a thorough understanding of various concepts. However, these concepts may be practiced without these specific details. In some instances, well known structures and components are shown in block diagram form in order to avoid obscuring such concepts.

[0060] Several aspects of telecommunication systems are presented with reference to various apparatus and methods. These apparatus and methods are described in the following detailed description and illustrated in the accompanying drawings by various blocks, components, circuits, processes, algorithms, etc. (collectively referred to as “elements”). These elements may be implemented using electronic hardware, computer software, or any combination thereof. Whether such elements are implemented as hardware or software depends upon the particular application and design constraints imposed on the overall system.

[0061] By way of example, an element, or any portion of an element, or any combination of elements may be implemented as a “processing system” that includes one or more processors. When multiple processors are implemented, the multiple processors may perform the functions individually or in combination. Examples of processors include microprocessors, microcontrollers, graphics processing units (GPUs), central processing units (CPUs), application processors, digital signal processors (DSPs), reduced instruction set computing (RISC) processors, systems on a chip (SoC), baseband processors, field programmable gate arrays (FPGAs), programmable logic devices (PLDs), state machines, gated logic, discrete hardware circuits, and other suitable hardware configured to perform the various functionality described throughout this disclosure. One or more processors in the processing system may execute software. Software, whether referred to as software, firmware, middleware, microcode, hardware description language, or otherwise, shall be construed broadly to mean instructions, instruction sets, code, code segments, program code, programs, subprograms, software components, applications, software applications, software packages, routines, subroutines, objects, executables, threads of execution, procedures, functions, or any combination thereof.

[0062] Accordingly, in one or more example aspects, implementations, and/or use cases, the functions described may be implemented in hardware, software, or any combination thereof. If implemented in software, the functions may be stored on or encoded as one or more instructions or code on a computer-readable medium. Computer-readable media includes computer storage media. Storage media may be any available media that can be accessed by a computer. By way of example, such computer-readable media can include a random-access memory (RAM), a read-only memory (ROM), an electrically erasable programmable ROM (EEPROM), optical disk storage, magnetic disk storage, other magnetic storage devices, combinations of the types of computer-readable media, or any other medium that can be used to store computer executable code in the form of instructions or data structures that can be accessed by a computer. While aspects, implementations, and/or use cases are described in this application by illustration to some examples, additional or different aspects, implementations and/or use cases may come about in many different arrangements and scenarios. Aspects, implementations, and/or use cases described herein may be implemented across many differing platform types, devices, systems, shapes, sizes, and packaging arrangements. For example, aspects, implementations, and/or use cases may come about via integrated chip implementations and other non-module-component based devices (e.g.,

end-user devices, vehicles, communication devices, computing devices, industrial equipment, retail/purchasing devices, medical devices, artificial intelligence (AI)-enabled devices, etc.). While some examples may or may not be specifically directed to use cases or applications, a wide assortment of applicability of described examples may occur. Aspects, implementations, and/or use cases may range a spectrum from chip-level or modular components to non-modular, non-chip-level implementations and further to aggregate, distributed, or original equipment manufacturer (OEM) devices or systems incorporating one or more techniques herein. In some practical settings, devices incorporating described aspects and features may also include additional components and features for implementation and practice of claimed and described aspect. For example, transmission and reception of wireless signals necessarily includes a number of components for analog and digital purposes (e.g., hardware components including antenna, RF-chains, power amplifiers, modulators, buffer, processor(s), interleaver, adders/summers, etc.). Techniques described herein may be practiced in a wide variety of devices, chip-level components, systems, distributed arrangements, aggregated or disaggregated components, end-user devices, etc. of varying sizes, shapes, and constitution.

[0063] Deployment of communication systems, such as 5G NR systems, may be arranged in multiple manners with various components or constituent parts. In a 5G NR system, or network, a network node, a network entity, a mobility element of a network, a radio access network (RAN) node, a core network node, a network element, or a network equipment, such as a base station (BS), or one or more units (or one or more components) performing base station functionality, may be implemented in an aggregated or disaggregated architecture. For example, a BS (such as a Node B (NB), evolved NB (CNB), NR BS, 5G NB, access point (AP), a transmission reception point (TRP), or a cell, etc.) may be implemented as an aggregated base station (also known as a standalone BS or a monolithic BS) or a disaggregated base station.

[0064] An aggregated base station may be configured to utilize a radio protocol stack that is physically or logically integrated within a single RAN node. A disaggregated base station may be configured to utilize a protocol stack that is physically or logically distributed among two or more units (such as one or more central or centralized units (CUs), one or more distributed units (DUs), or one or more radio units (RUs)). In some aspects, a CU may be implemented within a RAN node, and one or more DUs may be co-located with the CU, or alternatively, may be geographically or virtually distributed throughout one or multiple other RAN nodes. The DUs may be implemented to communicate with one or more RUs. Each of the CU, DU and RU can be implemented as virtual units, i.e., a virtual central unit (VCU), a virtual distributed unit (VDU), or a virtual radio unit (VRU).

[0065] Base station operation or network design may consider aggregation characteristics of base station functionality. For example, disaggregated base stations may be utilized in an integrated access backhaul (IAB) network, an open radio access network (O-RAN (such as the network configuration sponsored by the O-RAN Alliance)), or a virtualized radio access network (vRAN, also known as a cloud radio access network (C-RAN)). Disaggregation may include distributing functionality across two or more units at various physical locations, as well as distributing functionality for at least one unit virtually, which can enable flexibility in network design. The various units of the disaggregated base station, or disaggregated RAN architecture, can be configured for wired or wireless communication with at least one other unit.

[0066] FIG. 1 is a diagram 100 illustrating an example of a wireless communications system and an access network. The illustrated wireless communications system includes a disaggregated base station architecture. The disaggregated base station architecture may include one or more CUs 110 that can communicate directly with a core network 120 via a backhaul link, or indirectly with the core network 120 through one or more disaggregated base station units (such as a Near-Real Time (Near-RT) RAN Intelligent Controller (RIC) 125 via an E2 link, or a Non-Real Time (Non-RT) RIC 115 associated with a Service Management and Orchestration (SMO) Framework 105, or

both). A CU **110** may communicate with one or more DUs **130** via respective midhaul links, such as an F1 interface. The DUs **130** may communicate with one or more RUs **140** via respective fronthaul links. The RUs **140** may communicate with respective UEs **104** via one or more radio frequency (RF) access links. In some implementations, the UE **104** may be simultaneously served by multiple RUs **140**.

[0067] Each of the units, i.e., the CUS **110**, the DUs **130**, the RUs **140**, as well as the Near-RT RICs **125**, the Non-RT RICs **115**, and the SMO Framework **105**, may include one or more interfaces or be coupled to one or more interfaces configured to receive or to transmit signals, data, or information (collectively, signals) via a wired or wireless transmission medium. Each of the units, or an associated processor or controller providing instructions to the communication interfaces of the units, can be configured to communicate with one or more of the other units via the transmission medium. For example, the units can include a wired interface configured to receive or to transmit signals over a wired transmission medium to one or more of the other units.

Additionally, the units can include a wireless interface, which may include a receiver, a transmitter, or a transceiver (such as an RF transceiver), configured to receive or to transmit signals, or both, over a wireless transmission medium to one or more of the other units.

[0068] In some aspects, the CU **110** may host one or more higher layer control functions. Such control functions can include radio resource control (RRC), packet data convergence protocol (PDCP), service data adaptation protocol (SDAP), or the like. Each control function can be implemented with an interface configured to communicate signals with other control functions hosted by the CU **110**. The CU **110** may be configured to handle user plane functionality (i.e., Central Unit-User Plane (CU-UP)), control plane functionality (i.e., Central Unit-Control Plane (CU-CP)), or a combination thereof. In some implementations, the CU **110** can be logically split into one or more CU-UP units and one or more CU-CP units. The CU-UP unit can communicate bidirectionally with the CU-CP unit via an interface, such as an E1 interface when implemented in an O-RAN configuration. The CU **110** can be implemented to communicate with the DU **130**, as necessary, for network control and signaling.

[0069] The DU **130** may correspond to a logical unit that includes one or more base station functions to control the operation of one or more RUs **140**. In some aspects, the DU **130** may host one or more of a radio link control (RLC) layer, a medium access control (MAC) layer, and one or more high physical (PHY) layers (such as modules for forward error correction (FEC) encoding and decoding, scrambling, modulation, demodulation, or the like) depending, at least in part, on a functional split, such as those defined by 3GPP. In some aspects, the DU **130** may further host one or more low PHY layers. Each layer (or module) can be implemented with an interface configured to communicate signals with other layers (and modules) hosted by the DU **130**, or with the control functions hosted by the CU **110**.

[0070] Lower-layer functionality can be implemented by one or more RUs **140**. In some deployments, an RU **140**, controlled by a DU **130**, may correspond to a logical node that hosts RF processing functions, or low-PHY layer functions (such as performing fast Fourier transform (FFT), inverse FFT (IFFT), digital beamforming, physical random access channel (PRACH) extraction and filtering, or the like), or both, based at least in part on the functional split, such as a lower layer functional split. In such an architecture, the RU(s) **140** can be implemented to handle over the air (OTA) communication with one or more UEs **104**. In some implementations, real-time and non-real-time aspects of control and user plane communication with the RU(s) **140** can be controlled by the corresponding DU **130**. In some scenarios, this configuration can enable the DU(s) **130** and the CU **110** to be implemented in a cloud-based RAN architecture, such as a vRAN architecture.

[0071] The SMO Framework **105** may be configured to support RAN deployment and provisioning of non-virtualized and virtualized network elements. For non-virtualized network elements, the SMO Framework **105** may be configured to support the deployment of dedicated physical

resources for RAN coverage requirements that may be managed via an operations and maintenance interface (such as an O1 interface). For virtualized network elements, the SMO Framework **105** may be configured to interact with a cloud computing platform (such as an open cloud (O-Cloud) **190**) to perform network element life cycle management (such as to instantiate virtualized network elements) via a cloud computing platform interface (such as an O2 interface). Such virtualized network elements can include, but are not limited to, CUs **110**, DUs **130**, RUs **140** and Near-RT RICs **125**. In some implementations, the SMO Framework **105** can communicate with a hardware aspect of a 4G RAN, such as an open eNB (O-eNB) **111**, via an O1 interface. Additionally, in some implementations, the SMO Framework **105** can communicate directly with one or more RUs **140** via an O1 interface. The SMO Framework **105** also may include a Non-RT RIC **115** configured to support functionality of the SMO Framework **105**.

[0072] The Non-RT RIC **115** may be configured to include a logical function that enables non-real-time control and optimization of RAN elements and resources, artificial intelligence (AI)/machine learning (ML) (AI/ML) workflows including model training and updates, or policy-based guidance of applications/features in the Near-RT RIC **125**. The Non-RT RIC **115** may be coupled to or communicate with (such as via an A1 interface) the Near-RT RIC **125**. The Near-RT RIC **125** may be configured to include a logical function that enables near-real-time control and optimization of RAN elements and resources via data collection and actions over an interface (such as via an E2 interface) connecting one or more CUs **110**, one or more DUs **130**, or both, as well as an O-eNB, with the Near-RT RIC **125**.

[0073] In some implementations, to generate AI/ML models to be deployed in the Near-RT RIC **125**, the Non-RT RIC **115** may receive parameters or external enrichment information from external servers. Such information may be utilized by the Near-RT RIC **125** and may be received at the SMO Framework **105** or the Non-RT RIC **115** from non-network data sources or from network functions. In some examples, the Non-RT RIC **115** or the Near-RT RIC **125** may be configured to tune RAN behavior or performance. For example, the Non-RT RIC **115** may monitor long-term trends and patterns for performance and employ AI/ML models to perform corrective actions through the SMO Framework **105** (such as reconfiguration via O1) or via creation of RAN management policies (such as A1 policies).

[0074] At least one of the CU **110**, the DU **130**, and the RU **140** may be referred to as a base station **102**. Accordingly, a base station **102** may include one or more of the CU **110**, the DU **130**, and the RU **140** (each component indicated with dotted lines to signify that each component may or may not be included in the base station **102**). The base station **102** provides an access point to the core network **120** for a UE **104**. The base station **102** may include macrocells (high power cellular base station) and/or small cells (low power cellular base station). The small cells include femtocells, picocells, and microcells. A network that includes both small cell and macrocells may be known as a heterogeneous network. A heterogeneous network may also include Home Evolved Node Bs (eNBs) (HeNBs), which may provide service to a restricted group known as a closed subscriber group (CSG). The communication links between the RUs **140** and the UEs **104** may include uplink (UL) (also referred to as reverse link) transmissions from a UE **104** to an RU **140** and/or downlink (DL) (also referred to as forward link) transmissions from an RU **140** to a UE **104**. The communication links may use multiple-input and multiple-output (MIMO) antenna technology, including spatial multiplexing, beamforming, and/or transmit diversity. The communication links may be through one or more carriers. The base station **102**/UEs **104** may use spectrum up to Y MHz (e.g., 5, 10, 15, 20, 100, 400, etc. MHz) bandwidth per carrier allocated in a carrier aggregation of up to a total of Yx MHz (x component carriers) used for transmission in each direction. The carriers may or may not be adjacent to each other. Allocation of carriers may be asymmetric with respect to DL and UL (e.g., more or fewer carriers may be allocated for DL than for UL). The component carriers may include a primary component carrier and one or more secondary component carriers. A primary component carrier may be referred to as a primary cell

(PCell) and a secondary component carrier may be referred to as a secondary cell (SCell).

[0075] Certain UEs **104** may communicate with each other using device-to-device (D2D) communication link **158**. The D2D communication link **158** may use the DL/UL wireless wide area network (WWAN) spectrum. The D2D communication link **158** may use one or more sidelink channels, such as a physical sidelink broadcast channel (PSBCH), a physical sidelink discovery channel (PSDCH), a physical sidelink shared channel (PSSCH), and a physical sidelink control channel (PSCCH). D2D communication may be through a variety of wireless D2D communications systems, such as for example, Bluetooth™ (Bluetooth is a trademark of the Bluetooth Special Interest Group (SIG)), Wi-Fi™ (Wi-Fi is a trademark of the Wi-Fi Alliance) based on the Institute of Electrical and Electronics Engineers (IEEE) 802.11 standard, LTE, or NR.

[0076] The wireless communications system may further include a Wi-Fi AP **150** in communication with UEs **104** (also referred to as Wi-Fi stations (STAs)) via communication link **154**, e.g., in a 5 GHz unlicensed frequency spectrum or the like. When communicating in an unlicensed frequency spectrum, the UEs **104**/AP **150** may perform a clear channel assessment (CCA) prior to communicating in order to determine whether the channel is available.

[0077] The electromagnetic spectrum is often subdivided, based on frequency/wavelength, into various classes, bands, channels, etc. In 5G NR, two initial operating bands have been identified as frequency range designations FR1 (410 MHz-7.125 GHz) and FR2 (24.25 GHz-52.6 GHz). Although a portion of FR1 is greater than 6 GHz, FR1 is often referred to (interchangeably) as a “sub-6 GHz” band in various documents and articles. A similar nomenclature issue sometimes occurs with regard to FR2, which is often referred to (interchangeably) as a “millimeter wave” band in documents and articles, despite being different from the extremely high frequency (EHF) band (30 GHz-300 GHz) which is identified by the International Telecommunications Union (ITU) as a “millimeter wave” band.

[0078] The frequencies between FR1 and FR2 are often referred to as mid-band frequencies. Recent 5G NR studies have identified an operating band for these mid-band frequencies as frequency range designation FR3 (7.125 GHz-24.25 GHz). Frequency bands falling within FR3 may inherit FR1 characteristics and/or FR2 characteristics, and thus may effectively extend features of FR1 and/or FR2 into mid-band frequencies. In addition, higher frequency bands are currently being explored to extend 5G NR operation beyond 52.6 GHz. For example, three higher operating bands have been identified as frequency range designations FR2-2 (52.6 GHz-71 GHz), FR4 (71 GHz-114.25 GHz), and FR5 (114.25 GHz-300 GHz). Each of these higher frequency bands falls within the EHF band.

[0079] With the above aspects in mind, unless specifically stated otherwise, the term “sub-6 GHz” or the like if used herein may broadly represent frequencies that may be less than 6 GHz, may be within FR1, or may include mid-band frequencies. Further, unless specifically stated otherwise, the term “millimeter wave” or the like if used herein may broadly represent frequencies that may include mid-band frequencies, may be within FR2, FR4, FR2-2, and/or FR5, or may be within the EHF band.

[0080] The base station **102** and the UE **104** may each include a plurality of antennas, such as antenna elements, antenna panels, and/or antenna arrays to facilitate beamforming. The base station **102** may transmit a beamformed signal **182** to the UE **104** in one or more transmit directions. The UE **104** may receive the beamformed signal from the base station **102** in one or more receive directions. The UE **104** may also transmit a beamformed signal **184** to the base station **102** in one or more transmit directions. The base station **102** may receive the beamformed signal from the UE **104** in one or more receive directions. The base station **102**/UE **104** may perform beam training to determine the best receive and transmit directions for each of the base station **102**/UE **104**. The transmit and receive directions for the base station **102** may or may not be the same. The transmit and receive directions for the UE **104** may or may not be the same.

[0081] The base station **102** may include and/or be referred to as a gNB, Node B, eNB, an access

point, a base transceiver station, a radio base station, a radio transceiver, a transceiver function, a basic service set (BSS), an extended service set (ESS), a TRP, network node, network entity, network equipment, or some other suitable terminology. The base station **102** can be implemented as an integrated access and backhaul (IAB) node, a relay node, a sidelink node, an aggregated (monolithic) base station with a baseband unit (BBU) (including a CU and a DU) and an RU, or as a disaggregated base station including one or more of a CU, a DU, and/or an RU. The set of base stations, which may include disaggregated base stations and/or aggregated base stations, may be referred to as next generation (NG) RAN (NG-RAN).

[0082] The core network **120** may include an Access and Mobility Management Function (AMF) **161**, a Session Management Function (SMF) **162**, a User Plane Function (UPF) **163**, a Unified Data Management (UDM) **164**, one or more location servers **168**, and other functional entities. The AMF **161** is the control node that processes the signaling between the UEs **104** and the core network **120**. The AMF **161** supports registration management, connection management, mobility management, and other functions. The SMF **162** supports session management and other functions. The UPF **163** supports packet routing, packet forwarding, and other functions. The UDM **164** supports the generation of authentication and key agreement (AKA) credentials, user identification handling, access authorization, and subscription management. The one or more location servers **168** are illustrated as including a Gateway Mobile Location Center (GMLC) **165** and a Location Management Function (LMF) **166**. However, generally, the one or more location servers **168** may include one or more location/positioning servers, which may include one or more of the GMLC **165**, the LMF **166**, a position determination entity (PDE), a serving mobile location center (SMLC), a mobile positioning center (MPC), or the like. The GMLC **165** and the LMF **166** support UE location services. The GMLC **165** provides an interface for clients/applications (e.g., emergency services) for accessing UE positioning information. The LMF **166** receives measurements and assistance information from the NG-RAN and the UE **104** via the AMF **161** to compute the position of the UE **104**. The NG-RAN may utilize one or more positioning methods in order to determine the position of the UE **104**. Positioning the UE **104** may involve signal measurements, a position estimate, and an optional velocity computation based on the measurements. The signal measurements may be made by the UE **104** and/or the base station **102** serving the UE **104**. The signals measured may be based on one or more of a satellite positioning system (SPS) **170** (e.g., one or more of a Global Navigation Satellite System (GNSS), global position system (GPS), non-terrestrial network (NTN), or other satellite position/location system), LTE signals, wireless local area network (WLAN) signals, Bluetooth signals, a terrestrial beacon system (TBS), sensor-based information (e.g., barometric pressure sensor, motion sensor), NR enhanced cell ID (NR E-CID) methods, NR signals (e.g., multi-round trip time (Multi-RTT), DL angle-of-departure (DL-AoD), DL time difference of arrival (DL-TDOA), UL time difference of arrival (UL-TDOA), and UL angle-of-arrival (UL-AoA) positioning), and/or other systems/signals/sensors.

[0083] Examples of UEs **104** include a cellular phone, a smart phone, a session initiation protocol (SIP) phone, a laptop, a personal digital assistant (PDA), a satellite radio, a global positioning system, a multimedia device, a video device, a digital audio player (e.g., MP3 player), a camera, a game console, a tablet, a smart device, a wearable device, a vehicle, an electric meter, a gas pump, a large or small kitchen appliance, a healthcare device, an implant, a sensor/actuator, a display, or any other similar functioning device. Some of the UEs **104** may be referred to as IoT devices (e.g., parking meter, gas pump, toaster, vehicles, heart monitor, etc.). The UE **104** may also be referred to as a station, a mobile station, a subscriber station, a mobile unit, a subscriber unit, a wireless unit, a remote unit, a mobile device, a wireless device, a wireless communications device, a remote device, a mobile subscriber station, an access terminal, a mobile terminal, a wireless terminal, a remote terminal, a handset, a user agent, a mobile client, a client, or some other suitable terminology. In some scenarios, the term UE may also apply to one or more companion devices

such as in a device constellation arrangement. One or more of these devices may collectively access the network and/or individually access the network.

[0084] Referring again to FIG. 1, in certain aspects, the UE 104 may have a CBB transmission component 198 that may be configured to receive a CBB grouping algorithm indicator. The CBB transmission component 198 may be configured to calculate a CBB configuration based on the CBB grouping algorithm indicator. The CBB transmission component 198 may be configured to transmit a first plurality of CBBs based on the calculated CBB configuration. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. In certain aspects, the base station 102 may have a CBB reception component 199 that may be configured to transmit a CBB grouping algorithm indicator. The CBB reception component 199 may be configured to receive a first plurality of CBBs based on the CBB grouping algorithm indicator. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs.

[0085] FIG. 2A is a diagram 200 illustrating an example of a first subframe within a 5G NR frame structure. FIG. 2B is a diagram 230 illustrating an example of DL channels within a 5G NR subframe. FIG. 2C is a diagram 250 illustrating an example of a second subframe within a 5G NR frame structure. FIG. 2D is a diagram 280 illustrating an example of UL channels within a 5G NR subframe. The 5G NR frame structure may be frequency division duplexed (FDD) in which for a particular set of subcarriers (carrier system bandwidth), subframes within the set of subcarriers are dedicated for either DL or UL, or may be time division duplexed (TDD) in which for a particular set of subcarriers (carrier system bandwidth), subframes within the set of subcarriers are dedicated for both DL and UL. In the examples provided by FIGS. 2A, 2C, the 5G NR frame structure is assumed to be TDD, with subframe 4 being configured with slot format 28 (with mostly DL), where D is DL, U is UL, and F is flexible for use between DL/UL, and subframe 3 being configured with slot format 1 (with all UL). While subframes 3, 4 are shown with slot formats 1, 28, respectively, any particular subframe may be configured with any of the various available slot formats 0-61. Slot formats 0, 1 are all DL, UL, respectively. Other slot formats 2-61 include a mix of DL, UL, and flexible symbols. UEs are configured with the slot format (dynamically through DL control information (DCI), or semi-statically/statically through radio resource control (RRC) signaling) through a received slot format indicator (SFI). Note that the description infra applies also to a 5G NR frame structure that is TDD.

[0086] FIGS. 2A-2D illustrate a frame structure, and the aspects of the present disclosure may be applicable to other wireless communication technologies, which may have a different frame structure and/or different channels. A frame (10 ms) may be divided into 10 equally sized subframes (1 ms). Each subframe may include one or more time slots. Subframes may also include mini-slots, which may include 7, 4, or 2 symbols. Each slot may include 14 or 12 symbols, depending on whether the cyclic prefix (CP) is normal or extended. For normal CP, each slot may include 14 symbols, and for extended CP, each slot may include 12 symbols. The symbols on DL may be CP orthogonal frequency division multiplexing (OFDM) (CP-OFDM) symbols. The symbols on UL may be CP-OFDM symbols (for high throughput scenarios) or discrete Fourier transform (DFT) spread OFDM (DFT-s-OFDM) symbols (for power limited scenarios; limited to a single stream transmission). The number of slots within a subframe is based on the CP and the numerology. The numerology defines the subcarrier spacing (SCS) (see Table 1). The symbol length/duration may scale with 1/SCS.

TABLE-US-00001 TABLE 1 Numerology, SCS, and CP SCS μ $\Delta f = 2^{\mu} \cdot 15$ [kHz]
Cyclic prefix 0 15 Normal 1 30 Normal 2 60 Normal, Extended 3 120 Normal 4 240 Normal 5 480 Normal 6 960 Normal

[0087] For normal CP (14 symbols/slot), different numerologies μ 0 to 4 allow for 1, 2, 4, 8, and 16

slots, respectively, per subframe. For extended CP, the numerology 2 allows for 4 slots per subframe. Accordingly, for normal CP and numerology μ , there are 14 symbols/slot and $2^{\text{sup.}\mu}$ slots/subframe. The subcarrier spacing may be equal to $2^{\text{sup.}\mu} \cdot 15$ kHz, where μ is the numerology 0 to 4. As such, the numerology $\mu=0$ has a subcarrier spacing of 15 kHz and the numerology $\mu=4$ has a subcarrier spacing of 240 kHz. The symbol length/duration is inversely related to the subcarrier spacing. FIGS. 2A-2D provide an example of normal CP with 14 symbols per slot and numerology $\mu=2$ with 4 slots per subframe. The slot duration is 0.25 ms, the subcarrier spacing is 60 kHz, and the symbol duration is approximately 16.67 μ s. Within a set of frames, there may be one or more different bandwidth parts (BWPs) (see FIG. 2B) that are frequency division multiplexed. Each BWP may have a particular numerology and CP (normal or extended).

[0088] A resource grid may be used to represent the frame structure. Each time slot includes a resource block (RB) (also referred to as physical RBs (PRBs)) that extends 12 consecutive subcarriers. The resource grid is divided into multiple resource elements (REs). The number of bits carried by each RE depends on the modulation scheme.

[0089] As illustrated in FIG. 2A, some of the REs carry reference (pilot) signals (RS) for the UE. The RS may include demodulation RS (DM-RS) (indicated as R for one particular configuration, but other DM-RS configurations are possible) and channel state information reference signals (CSI-RS) for channel estimation at the UE. The RS may also include beam measurement RS (BRS), beam refinement RS (BRRS), and phase tracking RS (PT-RS).

[0090] FIG. 2B illustrates an example of various DL channels within a subframe of a frame. The physical downlink control channel (PDCCH) carries DCI within one or more control channel elements (CCEs) (e.g., 1, 2, 4, 8, or 16 CCEs), each CCE including six RE groups (REGs), each REG including 12 consecutive REs in an OFDM symbol of an RB. A PDCCH within one BWP may be referred to as a control resource set (CORESET). A UE is configured to monitor PDCCH candidates in a PDCCH search space (e.g., common search space, UE-specific search space) during PDCCH monitoring occasions on the CORESET, where the PDCCH candidates have different DCI formats and different aggregation levels. Additional BWPs may be located at greater and/or lower frequencies across the channel bandwidth. A primary synchronization signal (PSS) may be within symbol 2 of particular subframes of a frame. The PSS is used by a UE **104** to determine subframe/symbol timing and a physical layer identity. A secondary synchronization signal (SSS) may be within symbol 4 of particular subframes of a frame. The SSS is used by a UE to determine a physical layer cell identity group number and radio frame timing. Based on the physical layer identity and the physical layer cell identity group number, the UE can determine a physical cell identifier (PCI). Based on the PCI, the UE can determine the locations of the DM-RS. The physical broadcast channel (PBCH), which carries a master information block (MIB), may be logically grouped with the PSS and SSS to form a synchronization signal (SS)/PBCH block (also referred to as SS block (SSB)). The MIB provides a number of RBs in the system bandwidth and a system frame number (SFN). The physical downlink shared channel (PDSCH) carries user data, broadcast system information not transmitted through the PBCH such as system information blocks (SIBs), and paging messages.

[0091] As illustrated in FIG. 2C, some of the REs carry DM-RS (indicated as R for one particular configuration, but other DM-RS configurations are possible) for channel estimation at the base station. The UE may transmit DM-RS for the physical uplink control channel (PUCCH) and DM-RS for the physical uplink shared channel (PUSCH). The PUSCH DM-RS may be transmitted in the first one or two symbols of the PUSCH. The PUCCH DM-RS may be transmitted in different configurations depending on whether short or long PUCCHs are transmitted and depending on the particular PUCCH format used. The UE may transmit sounding reference signals (SRS). The SRS may be transmitted in the last symbol of a subframe. The SRS may have a comb structure, and a UE may transmit SRS on one of the combs. The SRS may be used by a base station for channel quality estimation to enable frequency-dependent scheduling on the UL.

[0092] FIG. 2D illustrates an example of various UL channels within a subframe of a frame. The PUCCH may be located as indicated in one configuration. The PUCCH carries uplink control information (UCI), such as scheduling requests, a channel quality indicator (CQI), a precoding matrix indicator (PMI), a rank indicator (RI), and hybrid automatic repeat request (HARQ) acknowledgment (ACK) (HARQ-ACK) feedback (i.e., one or more HARQ ACK bits indicating one or more ACK and/or negative ACK (NACK)). The PUSCH carries data, and may additionally be used to carry a buffer status report (BSR), a power headroom report (PHR), and/or UCI.

[0093] FIG. 3 is a block diagram of a base station **310** in communication with a UE **350** in an access network. In the DL, Internet protocol (IP) packets may be provided to a controller/processor **375**. The controller/processor **375** implements layer 3 and layer 2 functionality. Layer 3 includes a radio resource control (RRC) layer, and layer 2 includes a service data adaptation protocol (SDAP) layer, a packet data convergence protocol (PDCP) layer, a radio link control (RLC) layer, and a medium access control (MAC) layer. The controller/processor **375** provides RRC layer functionality associated with broadcasting of system information (e.g., MIB, SIBs), RRC connection control (e.g., RRC connection paging, RRC connection establishment, RRC connection modification, and RRC connection release), inter radio access technology (RAT) mobility, and measurement configuration for UE measurement reporting; PDCP layer functionality associated with header compression/decompression, security (ciphering, deciphering, integrity protection, integrity verification), and handover support functions; RLC layer functionality associated with the transfer of upper layer packet data units (PDUs), error correction through ARQ, concatenation, segmentation, and reassembly of RLC service data units (SDUs), re-segmentation of RLC data PDUs, and reordering of RLC data PDUs; and MAC layer functionality associated with mapping between logical channels and transport channels, multiplexing of MAC SDUs onto transport blocks (TBs), demultiplexing of MAC SDUs from TBs, scheduling information reporting, error correction through HARQ, priority handling, and logical channel prioritization.

[0094] The transmit (TX) processor **316** and the receive (RX) processor **370** implement layer 1 functionality associated with various signal processing functions. Layer 1, which includes a physical (PHY) layer, may include error detection on the transport channels, forward error correction (FEC) coding/decoding of the transport channels, interleaving, rate matching, mapping onto physical channels, modulation/demodulation of physical channels, and MIMO antenna processing. The TX processor **316** handles mapping to signal constellations based on various modulation schemes (e.g., binary phase-shift keying (BPSK), quadrature phase-shift keying (QPSK), M-phase-shift keying (M-PSK), M-quadrature amplitude modulation (M-QAM)). The coded and modulated symbols may then be split into parallel streams. Each stream may then be mapped to an OFDM subcarrier, multiplexed with a reference signal (e.g., pilot) in the time and/or frequency domain, and then combined together using an Inverse Fast Fourier Transform (IFFT) to produce a physical channel carrying a time domain OFDM symbol stream. The OFDM stream is spatially precoded to produce multiple spatial streams. Channel estimates from a channel estimator **374** may be used to determine the coding and modulation scheme, as well as for spatial processing. The channel estimate may be derived from a reference signal and/or channel condition feedback transmitted by the UE **350**. Each spatial stream may then be provided to a different antenna **320** via a separate transmitter **318Tx**. Each transmitter **318Tx** may modulate a radio frequency (RF) carrier with a respective spatial stream for transmission.

[0095] At the UE **350**, each receiver **354Rx** receives a signal through its respective antenna **352**. Each receiver **354Rx** recovers information modulated onto an RF carrier and provides the information to the receive (RX) processor **356**. The TX processor **368** and the RX processor **356** implement layer 1 functionality associated with various signal processing functions. The RX processor **356** may perform spatial processing on the information to recover any spatial streams destined for the UE **350**. If multiple spatial streams are destined for the UE **350**, they may be combined by the RX processor **356** into a single OFDM symbol stream. The RX processor **356**

then converts the OFDM symbol stream from the time-domain to the frequency domain using a Fast Fourier Transform (FFT). The frequency domain signal includes a separate OFDM symbol stream for each subcarrier of the OFDM signal. The symbols on each subcarrier, and the reference signal, are recovered and demodulated by determining the most likely signal constellation points transmitted by the base station **310**. These soft decisions may be based on channel estimates computed by the channel estimator **358**. The soft decisions are then decoded and deinterleaved to recover the data and control signals that were originally transmitted by the base station **310** on the physical channel. The data and control signals are then provided to the controller/processor **359**, which implements layer 3 and layer 2 functionality.

[0096] The controller/processor **359** can be associated with at least one memory **360** that stores program codes and data. The at least one memory **360** may be referred to as a computer-readable medium. In the UL, the controller/processor **359** provides demultiplexing between transport and logical channels, packet reassembly, deciphering, header decompression, and control signal processing to recover IP packets. The controller/processor **359** is also responsible for error detection using an ACK and/or NACK protocol to support HARQ operations.

[0097] Similar to the functionality described in connection with the DL transmission by the base station **310**, the controller/processor **359** provides RRC layer functionality associated with system information (e.g., MIB, SIBs) acquisition, RRC connections, and measurement reporting; PDCP layer functionality associated with header compression/decompression, and security (ciphering, deciphering, integrity protection, integrity verification); RLC layer functionality associated with the transfer of upper layer PDUs, error correction through ARQ, concatenation, segmentation, and reassembly of RLC SDUs, re-segmentation of RLC data PDUs, and reordering of RLC data PDUs; and MAC layer functionality associated with mapping between logical channels and transport channels, multiplexing of MAC SDUs onto TBs, demultiplexing of MAC SDUs from TBs, scheduling information reporting, error correction through HARQ, priority handling, and logical channel prioritization.

[0098] Channel estimates derived by a channel estimator **358** from a reference signal or feedback transmitted by the base station **310** may be used by the TX processor **368** to select the appropriate coding and modulation schemes, and to facilitate spatial processing. The spatial streams generated by the TX processor **368** may be provided to different antenna **352** via separate transmitters **354Tx**. Each transmitter **354Tx** may modulate an RF carrier with a respective spatial stream for transmission.

[0099] The UL transmission is processed at the base station **310** in a manner similar to that described in connection with the receiver function at the UE **350**. Each receiver **318Rx** receives a signal through its respective antenna **320**. Each receiver **318Rx** recovers information modulated onto an RF carrier and provides the information to a RX processor **370**.

[0100] The controller/processor **375** can be associated with at least one memory **376** that stores program codes and data. The at least one memory **376** may be referred to as a computer-readable medium. In the UL, the controller/processor **375** provides demultiplexing between transport and logical channels, packet reassembly, deciphering, header decompression, control signal processing to recover IP packets. The controller/processor **375** is also responsible for error detection using an ACK and/or NACK protocol to support HARQ operations.

[0101] At least one of the TX processor **368**, the RX processor **356**, and the controller/processor **359** may be configured to perform aspects in connection with the CBB transmission component **198** of FIG. 1.

[0102] At least one of the TX processor **316**, the RX processor **370**, and the controller/processor **375** may be configured to perform aspects in connection with the CBB reception component **199** of FIG. 1.

[0103] FIG. 4 is a diagram **400** illustrating an example of interleaving for CBBs of CBs. A wireless device, such as a UE, may be configured to transmit a set of CBs, such as the CB **402**, the CB **404**,

and the CB **406**. Each of the CBs may include a set of eight resource blocks (RBs), illustrated in diagram **400** as RB0-RB7. While diagram **400** shows an example of three CBs configured to be transmitted, a wireless device may be configured to transmit any number of CBs, for example two CBs, four CBs, or hundreds of CBs.

[0104] In some aspects, a UE may group a set of CBs into a CBB for transmission. The UE may interleave the CBs within a code group. For example, the CBB **408** illustrates the RBs of the CB **402**, the CB **404**, and the CB **406** as being interleaved for transmission of the CBB **408**. In some aspects, the UE may select the interleaving granularity (i.e., units of frequency domain resources allotted to each CB in a bundle) such that, for a given delay spread and/or channel coherence bandwidth, the channels seen by the CBs in a CBB may be highly correlated. The frequency domain resources may be selected as a set of K tones in a frequency domain. A wireless device may interleave the CBs in each CBB together in a frequency domain upon rate matching. While CBB **408** illustrates three CBs interleaved in a CBB, more or less CBs may be interleaved in a CBB, for example two CBs, four CBs, sixteen CBs, or sixty-four CBs. In some aspects, a UE may interleave physical resource groups (PRGs) from other CBBs with a CBB. In other words, the UE may perform PRG-level interleaving across a plurality of CBBs.

[0105] FIG. 5A is a diagram **500** illustrating an example of grouping for CBGs of CBs and CBBs of CBs. A UE may group a set of CBs, illustrated in diagram **500** as CB0-CB 23, into a plurality of CBBs, illustrated in diagram **500** as CBB **502**, CBB **504**, and CBB **506**. Specifically, the UE may group CB0-CB7 into CBB **502**, CB8-CB15 into CBB **504**, and CB16-CB23 into CBB **506**. Each of the CBBs may interleave CBs in the bundle for transmission. If a UE haphazardly groups CBs into CBs, a single CBB may be associated with a plurality of CBGs. As shown in diagram **500**, CB0-CB11 may be associated with CBG **508**, and CB12-CB23 may be associated with CBG **510**.

[0106] A UE may be configured to support HARQ ACK/NACK (referred to as HARQ-ACK feedback) on a per CBG basis when adopting a CBG transmission mechanism. If a CBB crosses CBG boundaries, both CBGs may declare a NACK if the common CBB fails at decoding, thereby increasing Rx/Tx overhead. For example, if the CRC fails on one or more of the CBs in CBB **504**, since all of the CBs in a CBB may experience similar channel conditions, it's likely that decoding the other CBs in CBB **504** may fail decoding. This may lead to a receiving wireless device transmitting a NACK bit in the HARQ-ACK feedback for the CBG **508** and the CBG **510**, and for the CBG **508** and the CBG **510** being retransmitted.

[0107] FIG. 5B is a diagram **550** illustrating another example of grouping for CBGs of CBs and CBBs of CBs. The UE may group the CBs into six CBBs instead of the three CBBs illustrated in FIG. 5A. In other words, the UE may group CB0-CB 23 into six CBs illustrated in diagram **550** as CBB **552**, CBB **554**, CBB **556**, CBB **558**, CBB **560**, and CBB **562**. Each CBB is associated with exactly one CBG, as opposed to the CBB **504** in FIG. 5A which is associated with two CBGs—CBG **508** and CBG **510**. Here, CBG **564** is associated with CBB **552**, CBB **554**, and CBB **556**, and CBG **566** is associated with CBB **558**, CBB **560**, and CBB **562**. Thus, if one CB in a CBB fails, for example on CB in CBB **556**, indicating that all CBs in the CBB may fail at decoding, a receiving wireless device may transmit a NACK bit in the HARQ-ACK feedback for CBG **564** and not any other CBGs.

[0108] In summary, channels experienced by the CBs within each CBB may be highly correlated since CBs are interleaved in the frequency domain in a CBB. Since decoding of CBBs may determine overall decoding performance of the CBG, and since the number of CBBs may be less than the number of CBs, the variability of CBGs may be less.

[0109] In some aspects, a wireless device, for example a UE or a network node, may be configured to confine CBs in a CBB to be within a single CBG, preventing a CBB from overlapping with more than one CBG. In other words, the wireless device may be configured to ensure that a CBB is associated with exactly one CBG (although a CBG may not have any CBBs associated with it, as explained further below). In some aspects, if a given transport block (TB) has M CBGs and N CBs,

where $N > M$, the wireless device may calculate M as $M = \min(\#CBs, M)$, where $\#CBs$ may be the total number of CBs and M may be a configured value of the maximum number of CBGs per TB. In some aspects, a network may configure the value of M , for example an RRC information element (IE) may indicate a configuration (e.g., PDSCH-ServingCellConfig) that has an IE that indicates the value of M (e.g., labeled as maxCodeBlockGroupsPerTransportBlock). In some aspects, a wireless device may be configured such that $M \leq 8$ for a single codeword and $M \leq 4$ for multi-codeword transmissions. In such aspects, the i th CBG may be indicated as having $K_{sub.i}$ CBs and $Q_{sub.i}$ CBBs, for each i from 0 to $M-1$. The total number of CBBs may be calculated as $Q = \sum_{i=0}^{M-1} Q_{sub.i}$.

[0110] FIG. 6A is a diagram 600 illustrating an example of grouping CBGs of CBs before splitting CBGs into CBBs. A wireless device may be configured to transmit a set of CBs 602. The set of CBs 602 are shown in diagram 600 as CB0-CB23 (similar to the CBs of FIG. 5A). A wireless device may first split the set of CBs 602 into CBGs, and then may split the CBGs into sets of CBBs. Here, the wireless device may split the set of CBs 602 into two sets of CBGs—the CBG 604 and the CBG 606. The wireless device may then split each CBG into two sets of CBBs. Here, the wireless device may split CBG 604 into CBB 608 and CBB 610, and may split CBG 606 into CBB 612 and CBB 614.

[0111] In other words, the wireless device may first group CBs into CBGs (i.e., group the set of CBs 602 into the CBG 604 and the CBG 606), then split each CBG further into CBBs (i.e., split the CBG 604 into the CBB 608 and the CBB 610, split the CBG 606 into the CBB 612 and the CBB 614). Instead of computing bundle sizes, or number of CBs associated with a CBB, the wireless device may compute the size of a CBB based on the number of CBs that form the parent CBG.

[0112] In some aspects, the wireless device may group the CBs into CBGs such that the CBG sizes differ by no more than one CB. In other words, the CBG size $K_{sub.l}$ may be K or $K-1$ CBs, where $K = \text{ceil}(N/M)$. This may avoid unbalanced CBG sizes and reduce the variability in HARQ-ACK feedback (i.e., ACK/NACKs) across CBGs. Within each CBG, the wireless device may group the CBBs such that the size of each CBB varies by no more than one CB. The wireless device may also ensure that the max CBB size, which may be indicated in a capability message, is not exceeded.

The wireless device may calculate each $Q_{sub.i}$ as $Q_{sub.i} = \lceil K_{sub.l}/N \rceil$, where N is the CBB size (i.e., number of CBs). The wireless device may form the first $\text{mod}(K_{sub.l}, Q_{sub.i})$ CBBs with N CBs each, where the remaining $(Q_{sub.i} - \text{mod}(K_{sub.l}, Q_{sub.i}))$ CBBs have with $N-1$ CBs each.

[0113] FIG. 6B is a diagram 650 illustrating an example of grouping CBBs of CBs before grouping the CBBs with CBGs. A wireless device may be configured to transmit a set of CBs 602. The set of CBs 602 are shown in diagram 650 as CB0-CB23 (similar to the CBs of FIG. 5A). A wireless device may first split the set of CBs 602 into CBBs, and then may group the CBBs into CBGs. Here, the wireless device may split the set of CBs 602 into four sets of CBBs—the CBB 652, the CBB 654, the CBB 656, and the CBB 658. The wireless device may then group the CBBs into two sets of CBGs. Here, the wireless device may group CBB 652 and CBB 654 into CBG 660, and may group CBB 656 and CBB 658 into CBG 662.

[0114] In other words, the wireless device may first group CBs into CBBs (i.e., group the set of CBs 602 into the CBB 652, the CBB 654, the CBB 656, and the CBB 658), then assign each CBB to one CBG max (i.e., assign the CBB 652 and the CBB 654 to CBG 660, assign the CBB 656 and the CBB 658 to the CBG 662).

[0115] In some aspects, the wireless device may group the CBs into CBBs into a total of Q CBBs. The wireless device may configure the grouping such that the max CBB is not exceeded (e.g., a UE capability may indicate a largest CBB that can be handled for UL/DL). The wireless device may configure the grouping such that the CBBs do not differ in size by more than one CB. The wireless device may then group the Q CBBs into M CBGs such that the size of the CBGs (the number of CBBs per CBG) does not differ by more than 1 CBB. This may avoid unbalanced CBG sizes and reduce the variability in HARQ-ACK feedback (i.e., ACK/NACKs) across CBGs. For example, the

wireless device may group the first $\lceil Q/M \rceil \times \lceil Q/M \rceil$ CBBs into $\text{mod}(Q, M)$ CBGs of size $\lceil Q/M \rceil$ bundles each. The wireless device may then group the rest of the CBBs into $M - \text{mod}(Q, M)$ CBGs of size $\lfloor Q/M \rfloor$ bundles each. In other words, $Q_{\text{sub}.i} = \lceil Q/M \rceil$ for $i=0$ to $\text{mod}(Q, M)-1$, and $\lfloor Q/M \rfloor$ for $i=\text{mod}(Q, M)$ to $M-1$.

[0116] In some aspects, a wireless device that groups CBGs of CBs before splitting CBGs into CBBs may create the same, or similar, groups of CBGs and CBBs as a wireless device that groups CBBs of CBs before grouping the CBBs with CBGs. However, in some aspects, the groups may be different.

[0117] For example, a wireless device may select the number of CBBs Q as $Q = \lceil (\# \text{CBs} / \text{max CBB size}) \rceil$, where the maximum CBB size may be calculated a function of the capability of a wireless device (e.g., UE capability), such as buffer and delay constraints. In some aspects, Q may be less than, or greater than, M . For example, where $Q \leq M$ (e.g., when the number of CBs is small, or the size of the TB is small), the wireless device may group the Q CBBs into Q CBGs with a one-to-one mapping, and leave the rest of the $(M-Q)$ CBGs empty.

[0118] FIG. 7A is a diagram 700 illustrating an example of grouping CBGs of CBs before grouping CBBs within each CBG. The wireless device may be configured to transmit a set of CBs 702. The set of CBs 702 are shown in diagram 700 as CB0-CB15. A wireless device may first split the set of CBs 702 into CBGs, and then may split the CBGs into sets of CBBs. Here, the wireless device may split the set of CBs 702 into eight sets of CBGs—CBG 704, CBG 706, CBG 708, CBG 710, CBG 712, CBG 714, CBG 716, and CBG 718. The wireless device may then split each CBG into sets of CBBs. Here, the wireless device may assign one CBB to each CBG. In other words, the wireless device may assign all of the CBs of CBG 704 to CBB 720, all of the CBs of CBG 706 to CBB 722, all of the CBs of CBG 708 to CBB 724, all of the CBs of CBG 710 to CBB 726, all of the CBs of CBG 712 to CBB 728, all of the CBs of CBG 714 to CBB 730, all of the CBs of CBG 716 to CBB 732, and all of the CBs of CBG 718 to CBB 734.

[0119] FIG. 7B is a diagram 750 illustrating an example of grouping CBBs of CBs before grouping the CBBs with CBGs. A wireless device may be configured to transmit a set of CBs 702. The set of CBs 702 are shown in diagram 750 as CB0-CB15. A wireless device may first split the set of CBs 702 into CBBs, and then may group the CBBs into CBGs. Here, the wireless device may split the set of CBs 702 into four sets of CBBs—the CBB 752, the CBB 754, the CBB 756, and the CBB 758—as the max CB bundle size may support 4 CBs for each CBB. The wireless device may then group the CBBs into four sets of CBGs. Here, the wireless device may group CBB 752 into CBG 760, may group CBB 754 into CBG 762, may group CBB 756 into CBG 764, and may group CBB 758 into CBG 766. However, the wireless device may have eight CBGs. This means that CBG 768, CBG 770, CBG 772, and CBG 774 may be empty CBGs without any CBBs assigned to the CBG. Such a configuration may waste configured CBGs.

[0120] In some aspects, a first wireless device, such as a network node, may be configured to configure a CBB grouping algorithm at a second wireless device, such as the UE, based on the capability of the second wireless device. For example, a UE may report its capability as a max supported CBB size being 4 CBs per CBB. Where $N=16$ and $M=8$, then if the wireless device first groups CBs into CBGs and then splits CBGs into CBBs, then $M = \min(M, N) = 8$, $K_{\text{sub}.l} = 2$, $Q_{\text{sub}.i} = 1$, for $i=0$ to 7, where i is the CBG index. However, if the wireless device first groups CBs into CBBs and then assigns CBBs to CBGs, then $M = \min(M, N) = 8$, $Q = \lceil N/4 \rceil = 4$, $Q_{\text{sub}.i} = 1$, $K_{\text{sub}.l} = 4$, for $i=0$ to 3 and $Q_{\text{sub}.i} = 0$, $K_{\text{sub}.l} = 0$, for $i=4$ to 7.

[0121] As explained above, N may denote the number of CBs, M may denote the configured number of CBGs per TB, M may denote the number of CBGs per TB (e.g., where $M = \min(N, M)$), $K_{\text{sub}.l}$ is the number of CBs contained in the l th CBG from $i=0$ to M , and $Q_{\text{sub}.i}$ is the number of CBBs contained in the i th CBG from $i=0$ to M .

[0122] In some aspects, a first wireless device, for example a UE, may report its capability to support either associate CBs with CBGs before associating CBGs with CBBs, or associate CBs

with CBBs before associating CBBs with CBGs. A second wireless device, for example a network node, may receive the capability, and may then determine which CBB grouping algorithm to use. The second wireless device may signal that information to the first wireless device, so that the first wireless device may calculate the boundaries of each CBG and CBB for processing (e.g., UL or DL). A network node may indicate the CBB grouping algorithm through a bit of a system transmission (e.g., RRC, DCI, MAC-CE).

[0123] FIG. 8 is a connection flow diagram 800 illustrating an example of signaling between a UE 802 and a network node 804 configured to align grouping of CBs in CBGs and CBBs.

[0124] The UE 802 may transmit a UE capability 806 to the network node 804. The network node 804 may receive the UE capability 806 from the UE 802. The UE capability 806 may indicate a capability of the UE 802 to align groups of CBBs and CBGs for transmission of CBBs at the UE 802. In some aspects, the UE capability 806 may indicate at least one of (a) a processing time for the UE 802 to encode a number of CBs associated with a CBB, (b) a buffer used by the UE 802 to encode CBs of a CBB, (c) a delay of the UE 802 to decode CBs of a CBB, or (d) a maximum number of CBs that the UE 802 can group into a CBB.

[0125] At 808, the network node 804 may configure a CBB grouping algorithm for the UE 802. The network node 804 may determine whether to indicate to the UE 802 to associate CBBs and CBGs to CBs based on the UE capability 806. For example, at 808, the network node 804 may configure the UE 802 to associate CBBs and CBGs to CBs if the UE capability 806 indicates that the UE 802 is capable of doing so, or may configure the UE 802 to not associate CBBs and CBGs to CBs if the UE capability 806 indicates that the UE 802 is not capable of doing so. The network node 804 may select whether the UE 802 groups/associates CBs with CBGs before splitting the CBGs into CBBs, or groups/associates CBs with CBBs before assigning CBBs to CBGs based on the UE capability 806. For example, at 808, the network node 804 may configure the UE 802 to group/associate CBs with CBGs before splitting the CBGs into CBBs if the UE capability 806 indicates that the UE 802 has a buffer or processing time less than or equal to a threshold value, or may configure the UE 802 to group/associate CBs with CBBs before assigning CBBs to CBGs if the UE capability 806 indicates that the UE 802 has a buffer or processing time greater than or equal to a threshold value.

[0126] The network node 804 may transmit a CBB grouping algorithm indicator 810 to the UE 802. The UE 802 may receive the CBB grouping algorithm indicator 810 from the network node 804. The CBB grouping algorithm indicator 810 may indicate to the UE 802 the configuration configured at 808 (e.g., whether the UE 802 bundles CBs into CBBs, whether the UE 802 first groups CBs into CBBs and second assigns CBBs to CBGs, whether the UE 802 first groups CBs into CBGs and splits CBGs into CBBs).

[0127] At 812, the UE 802 may calculate a CBB configuration based on the CBB grouping algorithm indicator 810. For example, based on the CBB grouping algorithm indicator 810, the UE 802 may first split a set of CBs into CBGs, and then split each of the CBGs into a set of CBBs, or may indicate for the UE 802 to first split a set of CBs into CBBs, and then assign sets of CBBs to at least some of a plurality of CBGs.

[0128] At 814, the UE 802 may interleave CBBs for transmission to the network node 804. The UE 802 may transmit the set of CBBs 816 at the network node 804. The network node 804 may receive the set of CBBs 816 from the UE 802. At 818, the network node 804 may decode the set of CBBs, for example by deinterleaving the CBBs. Since the UE 802 ensures that each CBB is associated with at most one CBG, if the network node 804 fails to decode a CBB, the network node 804 may transmit a request for the UE 802 to retransmit at most one CBG for each CBB that fails to decode.

[0129] FIG. 9 is a connection flow diagram 900 illustrating an example of signaling between a UE 902 and a network node 904 configured to align grouping of CBs in CBGs and CBBs.

[0130] The UE 902 may transmit a UE capability 906 to the network node 904. The network node 904 may receive the UE capability 906 from the UE 902. The UE capability 906 may indicate a

capability of the UE **902** to decode groups of CBBs for transmission of CBBs at the network node **904**. In some aspects, the UE capability **906** may indicate at least one of (a) a processing time for the UE **902** to decode a number of CBs associated with a CBB, (b) a buffer used by the UE **902** to decode CBs of a CBB, (c) a delay of the UE **902** to decode CBs of a CBB, or (d) a maximum number of CBs that the UE **902** can handle decoding/deinterleaving for a received CBB.

[0131] At **908**, the network node **904** may configure a CBB grouping algorithm for the UE **902**. The network node **904** may determine whether to indicate to the UE **902** that it will be transmitting CBs as CBBs based on the UE capability **906**. For example, at **908**, the network node **904** may configure the UE **902** to receive CBBs having interleaved CBs if the UE capability **906** indicates that the UE **902** is capable of doing so, or may configure the UE **902** to not receive CBBs having interleaved CBs if the UE capability **906** indicates that the UE **902** is not capable of doing so. The network node **904** may select whether the network node **904** will group/associate CBs with CBGs before splitting the CBGs into CBBs, or will group/associate CBs with CBBs before assigning CBBs to CBGs based on the UE capability **906**. For example, at **908**, the network node **904** may configure the network node **904** to group/associate CBs with CBGs before splitting the CBGs into CBBs if the UE capability **906** indicates that the UE **902** has a buffer or processing time less than or equal to a threshold value, or may configure the network node **904** to group/associate CBs with CBBs before assigning CBBs to CBGs if the UE capability **906** indicates that the UE **902** has a buffer or processing time greater than or equal to a threshold value.

[0132] The network node **904** may transmit a CBB grouping algorithm indicator **910** to the UE **902**. The UE **902** may receive the CBB grouping algorithm indicator **910** from the network node **904**. The CBB grouping algorithm indicator **910** may indicate to the UE **902** the configuration configured at **908** (e.g., whether the network node **904** bundles CBs into CBBs, whether the network node **904** first groups CBs into CBBs and second assigns CBBs to CBGs, whether the network node **904** first groups CBs into CBGs and splits CBGs into CBBs).

[0133] At **912**, the network node **904** may calculate a CBB configuration configured at **908**. The configuration may be indicated to the UE **902** by the CBB grouping algorithm indicator **910**. For example, the network node **904** may first split a set of CBs into CBGs, and then split each of the CBGs into a set of CBBs, or may first split a set of CBs into CBBs, and then assign sets of CBBs to at least some of a plurality of CBGs. The UE **902** may understand how the network node **904** assigns the CBBs and CBGs based on the CBB grouping algorithm indicator.

[0134] At **914**, the network node **904** may interleave the set of CBBs **916** for transmission to the UE **902**. The network node **904** may transmit the set of CBBs **916** at the UE **902**. The UE **902** may receive the set of CBBs **916** from the network node **904**. At **918**, the UE **902** may decode the set of CBBs **916**, for example by deinterleaving the CBBs. Since the network node **904** ensures that each CBB is associated with at most one CBG, if the UE **902** fails to decode a CBB, the UE **902** may transmit a request for the network node **904** to retransmit at most one CBG for each CBB that fails to decode.

[0135] FIG. **10** is a flowchart **1000** of a method of wireless communication. The method may be performed by a UE (e.g., the UE **104**, the UE **350**, the UE **802**; the apparatus **1504**). At **1002**, the UE may receive a CBB grouping algorithm indicator. For example, **1002** may be performed by the UE **802** in FIG. **8**, which may receive the CBB grouping algorithm indicator **810** from the network node **804**. Moreover, **1002** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0136] At **1004**, the UE may calculate a CBB configuration based on the CBB grouping algorithm indicator. For example, **1004** may be performed by the UE **802** in FIG. **8**, which may, at **812**, calculate a CBB configuration for the set of CBBs **816** based on the CBB grouping algorithm indicator **810**. Moreover, **1004** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0137] At **1006**, the UE may transmit a first plurality of CBBs based on the calculated CBB configuration. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of

the second plurality of CBGs. For example, **1006** may be performed by the UE **802** in FIG. **8**, which may transmit the set of CBBs **816** based on the CBB configuration calculated at **812**. Each CBG of a plurality of CBGs may be associated with a subset of the set of CBBs **816**, for example the CBG **604** of the group of CBGs that include the CBG **604** and the CBG **606** in FIG. **6A** may be associated with the CBB **608** and the CBB **610** of the group of CBBs that include the CBB **608**, the CBB **610**, the CBB **612**, and the CBB **614**. Each CBB of the set of CBBs **816** may be associated with exactly one of the plurality of CBGs, for example as the CBB **608** is associated with CBG **604** and not CBG **606**, and the CBB **610** is associated with CBG **604** and not CBG **606**. Moreover, **1006** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0138] FIG. **11** is a flowchart **1100** of a method of wireless communication. The method may be performed by a UE (e.g., the UE **104**, the UE **350**, the UE **802**; the apparatus **1504**).

[0139] At **1101**, the UE may transmit an indicator of a capability of the UE to associate CBBs and CBGs. The indicator may indicate a processing time for the UE to encode a number of CBs associated with one of the first plurality of CBBs. The indicator may indicate a buffer associated with an encoding of CBs associated with one of the first plurality of CBBs. The indicator may indicate a delay associated with the encoding of CBs associated with one of the first plurality of CBBs. The indicator may indicate a maximum number of CBs that the UE is able to associate with one of the first plurality of CBBs. For example, **1101** may be performed by the UE **802** in FIG. **8**, which may transmit the UE capability **806** to the network node **804**. The UE capability **806** may include an indicator of a capability of the UE **802** to associate CBBs and CBGs. The indicator may indicate an estimated maximum processing time for the UE **802** to use to encode CBs of a CBB. The indicator may indicate a buffer size that the UE **802** uses to encode CBs of a CBB. The indicator may indicate an estimated maximum delay for the UE **802** to encode CBs of a CBB. The indicator may indicate a maximum number of CBs that the UE **802** is able to associate with a single CBB (e.g., a maximum number of CBs that can be interleaved for transmission of an interleaved CBB). Moreover, **1101** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0140] At **1102**, the UE may receive a CBB grouping algorithm indicator. For example, **1102** may be performed by the UE **802** in FIG. **8**, which may receive the CBB grouping algorithm indicator **810** from the network node **804**. Moreover, **1102** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0141] At **1104**, the UE may calculate a CBB configuration based on the CBB grouping algorithm indicator. For example, **1104** may be performed by the UE **802** in FIG. **8**, which may, at **812**, calculate a CBB configuration for the set of CBBs **816** based on the CBB grouping algorithm indicator **810**. Moreover, **1104** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0142] At **1106**, the UE may transmit a first plurality of CBBs based on the calculated CBB configuration. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. For example, **1106** may be performed by the UE **802** in FIG. **8**, which may transmit the set of CBBs **816** based on the CBB configuration calculated at **812**. Each CBG of a plurality of CBGs may be associated with a subset of the set of CBBs **816**, for example the CBG **604** of the group of CBGs that include the CBG **604** and the CBG **606** in FIG. **6A** may be associated with the CBB **608** and the CBB **610** of the group of CBBs that include the CBB **608**, the CBB **610**, the CBB **612**, and the CBB **614**. Each CBB of the set of CBBs **816** may be associated with exactly one of the plurality of CBGs, for example as the CBB **608** is associated with CBG **604** and not CBG **606**, and the CBB **610** is associated with CBG **604** and not CBG **606**. Moreover, **1106** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0143] At **1108**, the UE may calculate the CBB configuration based on the CBB grouping algorithm indicator by associating each CB of a third plurality of CBs with one CBG of a second plurality of CBGs. The CBB grouping algorithm indicator may indicate the UE to associate CBs with CBGs before associating the CBGs with CBBs. For example, **1108** may be performed by the

UE **802** in FIG. **8**, which may, at **812**, associate each CB of the CBs to transmit to the network node **804** with one CBG of a plurality of CBGs. The CBB grouping algorithm indicator **810** may indicate for UE **802** to associate CBs with CBGs before associating the CBGs with CBBs. For example, the UE **802** may associate a subset of the set of CBs **602** in FIG. **6A** with the CBG **604** before splitting the CBG **604** into the CBB **608** and the CBB **610**. Moreover, **1108** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0144] At **1110**, the UE may calculate the CBB configuration based on the CBB grouping algorithm indicator by associating each CBG of the second plurality of CBGs with one subset of CBBs of a first plurality of CBBs. The CBB grouping algorithm indicator may indicate the UE to associate CBs with CBGs before associating the CBGs with CBBs. For example, **1110** may be performed by the UE **802** in FIG. **8**, which may associate each CBG of a set of CBGs to transmit to the network node **804** (each of which comprise CBs) with one subset of CBBs of the set of CBBs **816** to transmit to the network node **804**. The CBB grouping algorithm indicator **810** may indicate for the UE **802** to associate CBs with CBGs before associating the CBGs with CBBs. For example, the UE **802** may associate a subset of the set of CBs **602** in FIG. **6A** with the CBG **604** before splitting the CBG **604** into the CBB **608** and the CBB **610**. Moreover, **1110** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0145] At **1112**, the UE may associate each CB of the third plurality of CBs with one CBG of a second plurality of CBGs by associating each CB of the third plurality of CBs with one CBG of the second plurality of CBGs such that a first number of CBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one. For example, **1112** may be performed by the UE **802** in FIG. **8**, which may split the set of CBs to transmit to the network node **804** evenly into CBGs such that the size of each CBG differs by at most one CB from any other CBG of the set of CBGs to transmit to the network node **804**. Moreover, **1112** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0146] At **1114**, the UE may calculate a first number of CBs associated with a first CBB of the first plurality CBBs based on a second number of CBs associated with a first CBG of the second plurality of CBGs. For example, **1114** may be performed by the UE **802** in FIG. **8**, which may split the CBBs evenly among a CBG such that the size of each CBB differs by at most one CB from any other CBB of the CBBs associated with the CBG. Moreover, **1114** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0147] At **1116**, the UE may associate each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs by associating each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs such that a first number of CBs associated with a first CBB of a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first CBG of the second plurality of CBGs by more than one. For example, **1116** may be performed by the UE **802** in FIG. **8**, which may split the CBBs evenly among each CBG such that the size of each CBB differs by at most one CB from any other CBB of the CBBs associated with the corresponding CBG. Moreover, **1116** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0148] FIG. **12** is a flowchart **1200** of a method of wireless communication. The method may be performed by a UE (e.g., the UE **104**, the UE **350**, the UE **802**; the apparatus **1504**). At **1202**, the UE may receive a CBB grouping algorithm indicator. For example, **1202** may be performed by the UE **802** in FIG. **8**, which may receive the CBB grouping algorithm indicator **810** from the network node **804**. Moreover, **1202** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0149] At **1204**, the UE may calculate a CBB configuration based on the CBB grouping algorithm indicator. For example, **1204** may be performed by the UE **802** in FIG. **8**, which may, at **812**, calculate a CBB configuration for the set of CBBs **816** based on the CBB grouping algorithm indicator **810**. Moreover, **1204** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0150] At **1206**, the UE may transmit a first plurality of CBBs based on the calculated CBB configuration. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. For example, **1206** may be performed by the UE **802** in FIG. **8**, which may transmit the set of CBBs **816** based on the CBB configuration calculated at **812**. Each CBG of a plurality of CBGs may be associated with a subset of the set of CBBs **816**, for example the CBG **604** of the group of CBGs that include the CBG **604** and the CBG **606** in FIG. **6A** may be associated with the CBB **608** and the CBB **610** of the group of CBBs that include the CBB **608**, the CBB **610**, the CBB **612**, and the CBB **614**. Each CBB of the set of CBBs **816** may be associated with exactly one of the plurality of CBGs, for example as the CBB **608** is associated with CBG **604** and not CBG **606**, and the CBB **610** is associated with CBG **604** and not CBG **606**. Moreover, **1206** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0151] At **1208**, the UE may calculate the CBB configuration based on the CBB grouping algorithm indicator by associating each CB of a third plurality of CBs with one CBB of a first plurality of CBBs. The CBB grouping algorithm indicator may indicate the UE to associate CBs with CBBs before associating the CBBs with CBGs. For example, **1208** may be performed by the UE **802** in FIG. **8**, which may, at **812**, associate each CB of a set of CBs to transmit to the network node **804** with one CBB of the set of CBBs **816** to transmit to the network node **804**. The CBB grouping algorithm indicator **810** may indicate for the UE **802** to associate CBs of the set of CBs to transmit to the network node **804** with CBBs before associating the CBBs with CBGs. For example, the UE **802** may associate a subset of the set of CBs **602** in FIG. **6B** with the CBB **652** before assigning the CBB **652** to the CBG **660**. Moreover, **1208** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0152] At **1210**, the UE may calculate the CBB configuration based on the CBB grouping algorithm indicator by associating each CBB of the first plurality of CBBs with one CBG of a second plurality of CBGs. The CBB grouping algorithm indicator may indicate the UE to associate CBs with CBBs before associating the CBBs with CBGs. For example, **1210** may be performed by the UE **802** in FIG. **8**, which may associate each CBB of the set of CBBs **816** with one CBG of a set of CBGs to transmit to the network node **804**. The CBB grouping algorithm indicator **810** may indicate for the UE **802** to associate CBs of the set of CBs to transmit to the network node **804** with CBBs before associating the CBBs with CBGs. For example, the UE **802** may associate a subset of the set of CBs **602** in FIG. **6B** with the CBB **652** before assigning the CBB **652** to the CBG **660**. Moreover, **1210** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0153] At **1212**, the UE may associate each CB of the third plurality of CBs with one CBB of a first plurality of CBBs by associating each CB of the third plurality of CBs with one CBB of the first plurality of CBBs such that a first number of CBs associated with a first CBB of the first plurality of CBBs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first plurality of CBBs by more than one. For example, **1212** may be performed by the UE **802** in FIG. **8**, which may evenly split the set of CBs to transmit to the network node **804** into the set of CBBs **816** such that the number of CBs associated with each CBB differs by at most one CB from any other CBB of the set of CBBs **816**. Moreover, **1212** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0154] At **1214**, the UE may associate each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs by associating each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs such that a first number of CBBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one. For example, **1214** may be performed by the UE **802** in FIG. **8**, which may evenly distribute the CBBs of the set of CBBs **816** to a set of CBGs such that each CBG differs by at most one CBB from any other CBG. Moreover, **1214** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0155] At **1216**, the UE may interleave CBs associated with the CBB. For example, **1216** may be performed by the UE **802** in FIG. **8**, which may, at **814**, interleave CBs associated with one CBB of the set of CBBs **816**, similar to the interleaving illustrated in FIG. **4**. Moreover, **1216** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0156] At **1218**, the UE may transmit the first plurality of CBBs based on the calculated CBB configuration by transmitting the interleaved CBs. For example, **1218** may be performed by the UE **802** in FIG. **8**, which may transmit the set of CBBs **816** as interleaved CBs such that each CBB is transmitted as interleaved CBs of the CBB. Moreover, **1218** may be performed by the component **198** in FIG. **1**, **3**, or **15**.

[0157] FIG. **13** is a flowchart **1300** of a method of wireless communication. The method may be performed by a base station (e.g., the base station **102**, the base station **310**; the network node **804**; the network entity **1502**, the network entity **1602**, the network entity **1760**). At **1302**, the network node may transmit a CBB grouping algorithm indicator. For example, **1302** may be performed by the network node **804** in FIG. **8**, which may transmit the CBB grouping algorithm indicator **810** to the UE **802**. Moreover, **1302** may be performed by the component **199** in FIG. **1**, **3**, **16**, or **17**.

[0158] At **1304**, the network node may receive a first plurality of CBBs based on the CBB grouping algorithm indicator. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. For example, **1304** may be performed by the network node **804** in FIG. **8**, which may receive the set of CBBs **816** from the UE **802** based on the CBB grouping algorithm indicator **810**. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. For example, the CBG **604** of the group of CBGs that include the CBG **604** and the CBG **606** in FIG. **6A** may be associated with the CBB **608** and the CBB **610** of the group of CBBs that include the CBB **608**, the CBB **610**, the CBB **612**, and the CBB **614**. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. For example, the CBB **608** in FIG. **6A** is associated with CBG **604** and not CBG **606**, and the CBB **610** is associated with CBG **604** and not CBG **606**. Moreover, **1304** may be performed by the component **199** in FIG. **1**, **3**, **16**, or **17**.

[0159] FIG. **14** is a flowchart **1400** of a method of wireless communication. The method may be performed by a base station (e.g., the base station **102**, the base station **310**; the network node **804**; the network entity **1502**, the network entity **1602**, the network entity **1760**).

[0160] At **1402**, the network node may receive an indicator of a capability of a UE to associate CBBs and CBGs. The indicator may indicate a processing time for the UE to encode a number of CBs associated with one of the first plurality of CBBs. The indicator may indicate a buffer associated with an encoding of CBs associated with one of the first plurality of CBBs. The indicator may indicate a delay associated with the encoding of CBs associated with one of the first plurality of CBBs. The indicator may indicate a maximum number of CBs that the UE is able to associate with one of the first plurality of CBBs. For example, **1402** may be performed by the network node **804** in FIG. **8**, which may receive the UE capability **806** from the UE **802**. The UE capability **806** may include an indicator of a capability of the UE **802** to associate CBBs and CBGs. The indicator may indicate an estimated maximum processing time for the UE **802** to use to encode CBs of a CBB. The indicator may indicate a buffer size that the UE **802** uses to encode CBs of a CBB. The indicator may indicate an estimated maximum delay for the UE **802** to encode CBs of a CBB. The indicator may indicate a maximum number of CBs that the UE **802** is able to associate with a single CBB (e.g., a maximum number of CBs that can be interleaved for transmission of an interleaved CBB). Moreover, **1402** may be performed by the component **199** in FIG. **1**, **3**, **16**, or **17**.

[0161] At **1404**, the network node may configure a CBB grouping algorithm indicator based on the capability. For example, **1404** may be performed by the network node **804** in FIG. **8**, which may, at **808**, configure the CBB grouping algorithm indicator **810** based on one or more indicators of the UE capability **806** (e.g., ensuring that the UE **802** is capable of adapting the algorithm without

negatively influencing performance). Moreover, **1404** may be performed by the component **199** in FIG. **1**, **3**, **16**, or **17**.

[0162] At **1406**, the network node may transmit the CBB grouping algorithm indicator. For example, **1406** may be performed by the network node **804** in FIG. **8**, which may transmit the CBB grouping algorithm indicator **810** to the UE **802**. Moreover, **1406** may be performed by the component **199** in FIG. **1**, **3**, **16**, or **17**.

[0163] At **1408**, the network node may receive a first plurality of CBBs based on the CBB grouping algorithm indicator. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. For example, **1408** may be performed by the network node **804** in FIG. **8**, which may receive the set of CBBs **816** from the UE **802** based on the CBB grouping algorithm indicator **810**. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. For example, the CBG **604** of the group of CBGs that include the CBG **604** and the CBG **606** in FIG. **6A** may be associated with the CBB **608** and the CBB **610** of the group of CBBs that include the CBB **608**, the CBB **610**, the CBB **612**, and the CBB **614**. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. For example, the CBB **608** in FIG. **6A** is associated with CBG **604** and not CBG **606**, and the CBB **610** is associated with CBG **604** and not CBG **606**. Moreover, **1408** may be performed by the component **199** in FIG. **1**, **3**, **16**, or **17**.

[0164] At **1410**, the network node may deinterleave the received first plurality of CBBs based on the CBB grouping algorithm. For example, **1410** may be performed by the network node **804** in FIG. **8**, which may, at **818**, deinterleave the set of CBBs **816** received from the UE **802**. Moreover, **1410** may be performed by the component **199** in FIG. **1**, **3**, **16**, or **17**.

[0165] FIG. **15** is a diagram **1500** illustrating an example of a hardware implementation for an apparatus **1504**. The apparatus **1504** may be a UE, a component of a UE, or may implement UE functionality. In some aspects, the apparatus **1104** may include at least one cellular baseband processor **1524** (also referred to as a modem) coupled to one or more transceivers **1522** (e.g., cellular RF transceiver). The cellular baseband processor(s) **1524** may include at least one on-chip memory **1524'**. In some aspects, the apparatus **1504** may further include one or more subscriber identity modules (SIM) cards **1520** and at least one application processor **1506** coupled to a secure digital (SD) card **1508** and a screen **1510**. The application processor(s) **1506** may include on-chip memory **1506'**. In some aspects, the apparatus **1504** may further include a Bluetooth module **1512**, a WLAN module **1514**, an SPS module **1516** (e.g., GNSS module), one or more sensor modules **1518** (e.g., barometric pressure sensor/altimeter; motion sensor such as inertial measurement unit (IMU), gyroscope, and/or accelerometer(s); light detection and ranging (LIDAR), radio assisted detection and ranging (RADAR), sound navigation and ranging (SONAR), magnetometer, audio and/or other technologies used for positioning), additional memory modules **1526**, a power supply **1530**, and/or a camera **1532**. The Bluetooth module **1512**, the WLAN module **1514**, and the SPS module **1516** may include an on-chip transceiver (TRX) (or in some cases, just a receiver (RX)). The Bluetooth module **1512**, the WLAN module **1514**, and the SPS module **1516** may include their own dedicated antennas and/or utilize the antennas **1580** for communication. The cellular baseband processor(s) **1524** communicates through the transceiver(s) **1522** via one or more antennas **1580** with the UE **104** and/or with an RU associated with a network entity **1502**. The cellular baseband processor(s) **1524** and the application processor(s) **1506** may each include a computer-readable medium/memory **1524'**, **1506'**, respectively. The additional memory modules **1526** may also be considered a computer-readable medium/memory. Each computer-readable medium/memory **1524'**, **1506'**, **1526** may be non-transitory. The cellular baseband processor(s) **1524** and the application processor(s) **1506** are each responsible for general processing, including the execution of software stored on the computer-readable medium/memory. The software, when executed by the cellular baseband processor(s) **1524**/application processor(s) **1506**, causes the cellular baseband

processor(s) **1524**/application processor(s) **1506** to perform the various functions described supra. The cellular baseband processor(s) **1524** and the application processor(s) **1506** are configured to perform the various functions described supra based at least in part of the information stored in the memory. That is, the cellular baseband processor(s) **1524** and the application processor(s) **1506** may be configured to perform a first subset of the various functions described supra without information stored in the memory and may be configured to perform a second subset of the various functions described supra based on the information stored in the memory. The computer-readable medium/memory may also be used for storing data that is manipulated by the cellular baseband processor(s) **1524**/application processor(s) **1506** when executing software. The cellular baseband processor(s) **1524**/application processor(s) **1506** may be a component of the UE **350** and may include the at least one memory **360** and/or at least one of the TX processor **368**, the RX processor **356**, and the controller/processor **359**. In one configuration, the apparatus **1504** may be at least one processor chip (modem and/or application) and include just the cellular baseband processor(s) **1524** and/or the application processor(s) **1506**, and in another configuration, the apparatus **1504** may be the entire UE (e.g., see UE **350** of FIG. 3) and include the additional modules of the apparatus **1504**.

[0166] As discussed supra, the component **198** may be configured to receive a CBB grouping algorithm indicator. The component **198** may be configured to calculate a CBB configuration based on the CBB grouping algorithm indicator. The component **198** may be configured to transmit a first plurality of CBBs based on the calculated CBB configuration. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. The component **198** may be within the cellular baseband processor(s) **1524**, the application processor(s) **1506**, or both the cellular baseband processor(s) **1524** and the application processor(s) **1506**. The component **198** may be one or more hardware components specifically configured to carry out the stated processes/algorithm, implemented by one or more processors configured to perform the stated processes/algorithm, stored within a computer-readable medium for implementation by one or more processors, or some combination thereof. When multiple processors are implemented, the multiple processors may perform the stated processes/algorithm individually or in combination. As shown, the apparatus **1504** may include a variety of components configured for various functions. In one configuration, the apparatus **1504**, and in particular the cellular baseband processor(s) **1524** and/or the application processor(s) **1506**, may include means for receiving a CBB grouping algorithm indicator. The apparatus **1504** may include means for calculating a CBB configuration based on the CBB grouping algorithm indicator. The apparatus **1504** may include means for transmitting a first plurality of CBBs based on the calculated CBB configuration. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. The CBB grouping algorithm indicator may indicate the apparatus **1504** to associate CBs with CBGs before associating the CBGs with CBBs. The apparatus **1504** may include means for calculating the CBB configuration based on the CBB grouping algorithm indicator by (a) associating each CB of a third plurality of CBs with one CBG of the second plurality of CBGs, and (b) associating each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs after the association of each CB of the third plurality of CBs with one CBG of the second plurality of CBGs. The apparatus **1504** may include means for calculating a first number of CBs associated with a first CBB of the first plurality CBBs based on a second number of CBs associated with a first CBG of the second plurality of CBGs. The apparatus **1504** may include means for associating each CB of the third plurality of CBs with one CBG of the second plurality of CBGs by associating each CB of the third plurality of CBs with one CBG of the second plurality of CBGs such that a first number of CBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBG, that is not the first

CBG, of the second plurality of CBGs by more than one. The apparatus **1504** may include means for associating each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs by associating each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs such that a first number of CBs associated with a first CBB of a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first CBG of the second plurality of CBGs by more than one. The CBB grouping algorithm indicator may indicate the apparatus **1504** to associate CBs with CBBs before associating the CBBs with CBGs. The apparatus **1504** may include means for calculating the CBB configuration based on the CBB grouping algorithm indicator by (a) associating each CB of a third plurality of CBs with one CBB of the first plurality of CBBs, and (b) associating each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs after the association of each CB of the third plurality of CBs with one CBB of the first plurality of CBBs. The apparatus **1504** may include means for associating each CB of the third plurality of CBs with one CBB of the first plurality of CBBs by associating each CB of the third plurality of CBs with one CBB of the first plurality of CBBs such that a first number of CBs associated with a first CBB of the first plurality of CBBs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first plurality of CBBs by more than one. The apparatus **1504** may include means for associating each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs by associating each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs such that a first number of CBBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one. The apparatus **1504** may include means for transmitting an indicator of a capability of the UE to associate CBBs and CBGs before the reception of the CBB grouping algorithm indicator. The indicator may indicate a processing time for the apparatus **1504** to encode a number of CBs associated with one of the first plurality of CBBs. The indicator may indicate a buffer associated with an encoding of CBs associated with one of the first plurality of CBBs. The indicator may indicate a delay associated with the encoding of CBs associated with one of the first plurality of CBBs. The indicator may indicate a maximum number of CBs that the apparatus **1504** is able to associate with one of the first plurality of CBBs. The apparatus **1504** may include means for transmitting the first plurality of CBBs based on the calculated CBB configuration by, for each CBB of the first plurality of CBBs, (a) interleaving CBs associated with the CBB, and (b) transmitting the interleaved CBs. The means may be the component **198** of the apparatus **1504** configured to perform the functions recited by the means. As described supra, the apparatus **1504** may include the TX processor **368**, the RX processor **356**, and the controller/processor **359**. As such, in one configuration, the means may be the TX processor **368**, the RX processor **356**, and/or the controller/processor **359** configured to perform the functions recited by the means. FIG. **16** is a diagram **1600** illustrating an example of a hardware implementation for a network entity **1602**. The network entity **1602** may be a BS, a component of a BS, or may implement BS functionality. The network entity **1602** may include at least one of a CU **1610**, a DU **1630**, or an RU **1640**. For example, depending on the layer functionality handled by the component **199**, the network entity **1602** may include the CU **1610**; both the CU **1610** and the DU **1630**; each of the CU **1610**, the DU **1630**, and the RU **1640**; the DU **1630**; both the DU **1630** and the RU **1640**; or the RU **1640**. The CU **1610** may include at least one CU processor **1612**. The CU processor(s) **1612** may include on-chip memory **1612'**. In some aspects, the CU **1610** may further include additional memory modules **1614** and a communications interface **1618**. The CU **1610** communicates with the DU **1630** through a midhaul link, such as an F1 interface. The DU **1630** may include at least one DU processor **1632**. The DU processor(s) **1632** may include on-chip memory **1632'**. In some aspects, the DU **1630** may further include additional memory modules **1634** and a communications interface **1638**. The DU **1630** communicates with the RU **1640** through a fronthaul link. The RU **1640** may include at least one RU processor **1642**.

The RU processor(s) **1642** may include on-chip memory **1642'**. In some aspects, the RU **1640** may further include additional memory modules **1644**, one or more transceivers **1646**, antennas **1680**, and a communications interface **1648**. The RU **1640** communicates with the UE **104**. The on-chip memory **1612'**, **1632'**, **1642'** and the additional memory modules **1614**, **1634**, **1644** may each be considered a computer-readable medium/memory. Each computer-readable medium/memory may be non-transitory. Each of the processors **1612**, **1632**, **1642** is responsible for general processing, including the execution of software stored on the computer-readable medium/memory. The software, when executed by the corresponding processor(s) causes the processor(s) to perform the various functions described supra. The computer-readable medium/memory may also be used for storing data that is manipulated by the processor(s) when executing software.

[0167] As discussed supra, the component **199** may be configured to transmit a CBB grouping algorithm indicator. The component **199** may be configured to receive a first plurality of CBBs based on the CBB grouping algorithm indicator. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. The component **199** may be within one or more processors of one or more of the CU **1610**, DU **1630**, and the RU **1640**. The component **199** may be one or more hardware components specifically configured to carry out the stated processes/algorithm, implemented by one or more processors configured to perform the stated processes/algorithm, stored within a computer-readable medium for implementation by one or more processors, or some combination thereof. When multiple processors are implemented, the multiple processors may perform the stated processes/algorithm individually or in combination. The network entity **1602** may include a variety of components configured for various functions. In one configuration, the network entity **1602** may include means for transmitting a CBB grouping algorithm indicator. The network entity **1602** may include means for receiving a first plurality of CBBs based on the CBB grouping algorithm indicator. Each CBG of a second plurality of CBGs may be associated with a subset of the first plurality of CBBs. Each CBB of the first plurality of CBBs may be associated with exactly one of the second plurality of CBGs. The CBB grouping algorithm indicator may indicate a UE to associate CBs with CBGs before associating the CBGs with CBBs. The CBB grouping algorithm indicator may further indicate the UE to calculate a first number of CBs associated with a first CBB of the first plurality of CBBs based on a second number of CBs associated with a first CBG of the second plurality of CBGs. The CBB grouping algorithm indicator may further indicate the UE to associate each CB of a third plurality of CBs with one CBG of the second plurality of CBGs such that a first number of CBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one. The CBB grouping algorithm indicator may further indicate the UE to associate each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs such that a first number of CBs associated with a first CBB of a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first CBG of the second plurality of CBGs by more than one. The CBB grouping algorithm indicator may indicate a UE to associate CBs with CBBs before associating the CBBs with CBGs. The CBB grouping algorithm indicator may further indicate the UE to associate each CB of a third plurality of CBs with one CBB of the first plurality of CBBs such that a first number of CBs associated with a first CBB of the first plurality of CBBs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first plurality of CBBs by more than one. The CBB grouping algorithm indicator may further indicate the UE to associate each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs such that a first number of CBBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one. The network entity **1602** may include means for receiving an indicator of a

capability of a UE to associate CBBs and CBGs. The network entity **1602** may include means for configuring the CBB grouping algorithm indicator based on the capability. The indicator may indicate a processing time for the UE to encode a number of CBs associated with one of the first plurality of CBBs. The indicator may indicate a buffer associated with an encoding of CBs associated with one of the first plurality of CBBs. The indicator may indicate a delay associated with the encoding of CBs associated with one of the first plurality of CBBs. The indicator may indicate a maximum number of CBs that the UE is able to associate with one of the first plurality of CBBs. The network entity **1602** may include means for receiving the first plurality of CBBs based on the CBB grouping algorithm indicator by, for each of the first plurality of CBBs, receiving interleaved CBs of one of the first plurality of CBBs. The network entity **1602** may include means for deinterleaving the received first plurality of CBBs based on the CBB grouping algorithm. The means may be the component **199** of the network entity **1602** configured to perform the functions recited by the means. As described supra, the network entity **1602** may include the TX processor **316**, the RX processor **370**, and the controller/processor **375**. As such, in one configuration, the means may be the TX processor **316**, the RX processor **370**, and/or the controller/processor **375** configured to perform the functions recited by the means.

[0168] FIG. **17** is a diagram **1700** illustrating an example of a hardware implementation for a network entity **1760**. In one example, the network entity **1760** may be within the core network **120**. The network entity **1760** may include at least one network processor **1712**. The network processor(s) **1712** may include on-chip memory **1712'**. In some aspects, the network entity **1760** may further include additional memory modules **1714**. The network entity **1760** communicates via the network interface **1780** directly (e.g., backhaul link) or indirectly (e.g., through a RIC) with the CU **1702**. The on-chip memory **1712'** and the additional memory modules **1714** may each be considered a computer-readable medium/memory. Each computer-readable medium/memory may be non-transitory. The network processor(s) **1712** is responsible for general processing, including the execution of software stored on the computer-readable medium/memory. The software, when executed by the corresponding processor(s) causes the processor(s) to perform the various functions described supra. The computer-readable medium/memory may also be used for storing data that is manipulated by the processor(s) when executing software.

[0169] As discussed supra, the component **199** may be configured to transmit a CBB grouping algorithm indicator. The component **199** may be configured to receive a first plurality of CBBs based on the CBB grouping algorithm indicator. Each of the first plurality of CBBs may include a set of CBs. Each of the set of CBs of one of the first plurality of CBBs may be associated with exactly one of a second plurality of CBGs. The component **199** may be configured to receive the first plurality of CBBs based on the CBB grouping algorithm indicator by receiving interleaved CBs of each of the first plurality of CBBs. The component **199** may be configured to deinterleave the received interleaved CBs for each of the first plurality of CBBs. The component **199** may be within the network processor(s) **1712**. The component **199** may be one or more hardware components specifically configured to carry out the stated processes/algorithm, implemented by one or more processors configured to perform the stated processes/algorithm, stored within a computer-readable medium for implementation by one or more processors, or some combination thereof. When multiple processors are implemented, the multiple processors may perform the stated processes/algorithm individually or in combination. The network entity **1760** may include a variety of components configured for various functions. In one configuration, the network entity **1760** may include means for transmitting a CBB grouping algorithm indicator. The means may be the component **199** of the network entity **1760** configured to perform the functions recited by the means.

[0170] It is understood that the specific order or hierarchy of blocks in the processes/flowcharts disclosed is an illustration of example approaches. Based upon design preferences, it is understood that the specific order or hierarchy of blocks in the processes/flowcharts may be rearranged.

Further, some blocks may be combined or omitted. The accompanying method claims present elements of the various blocks in a sample order, and are not limited to the specific order or hierarchy presented.

[0171] The previous description is provided to enable any person skilled in the art to practice the various aspects described herein. Various modifications to these aspects will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other aspects. Thus, the claims are not limited to the aspects described herein, but are to be accorded the full scope consistent with the language claims. Reference to an element in the singular does not mean “one and only one” unless specifically so stated, but rather “one or more.” Terms such as “if,” “when,” and “while” do not imply an immediate temporal relationship or reaction. That is, these phrases, e.g., “when,” do not imply an immediate action in response to or during the occurrence of an action, but simply imply that if a condition is met then an action will occur, but without requiring a specific or immediate time constraint for the action to occur. The word “exemplary” is used herein to mean “serving as an example, instance, or illustration.” Any aspect described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other aspects. Unless specifically stated otherwise, the term “some” refers to one or more. Combinations such as “at least one of A, B, or C,” “one or more of A, B, or C,” “at least one of A, B, and C,” “one or more of A, B, and C,” and “A, B, C, or any combination thereof” include any combination of A, B, and/or C, and may include multiples of A, multiples of B, or multiples of C. Specifically, combinations such as “at least one of A, B, or C,” “one or more of A, B, or C,” “at least one of A, B, and C,” “one or more of A, B, and C,” and “A, B, C, or any combination thereof” may be A only, B only, C only, A and B, A and C, B and C, or A and B and C, where any such combinations may contain one or more member or members of A, B, or C. Sets should be interpreted as a set of elements where the elements number one or more. Accordingly, for a set of X, X would include one or more elements. When at least one processor is configured to perform a set of functions, the at least one processor, individually or in any combination, is configured to perform the set of functions. Accordingly, each processor of the at least one processor may be configured to perform a particular subset of the set of functions, where the subset is the full set, a proper subset of the set, or an empty subset of the set. A processor may be referred to as processor circuitry. A memory/memory module may be referred to as memory circuitry. If a first apparatus receives data from or transmits data to a second apparatus, the data may be received/transmitted directly between the first and second apparatuses, or indirectly between the first and second apparatuses through a set of apparatuses. A device configured to “output” data or “provide” data, such as a transmission, signal, or message, may transmit the data, for example with a transceiver, may send the data to a component of the device that transmits the data, or may send the data to a component of the device. A device configured to “obtain” data, such as a transmission, signal, or message, may receive, for example with a transceiver, may obtain the data from a component of the device that receives the data, or may obtain the data from a component of the device. Information stored in a memory includes instructions and/or data. All structural and functional equivalents to the elements of the various aspects described throughout this disclosure that are known or later come to be known to those of ordinary skill in the art are expressly incorporated herein by reference and are encompassed by the claims. Moreover, nothing disclosed herein is dedicated to the public regardless of whether such disclosure is explicitly recited in the claims. The words “module,” “mechanism,” “element,” “device,” and the like may not be a substitute for the word “means.” As such, no claim element is to be construed as a means plus function unless the element is expressly recited using the phrase “means for.”

[0172] As used herein, the phrase “based on” shall not be construed as a reference to a closed set of information, one or more conditions, one or more factors, or the like. In other words, the phrase “based on A” (where “A” may be information, a condition, a factor, or the like) shall be construed as “based at least on A” unless specifically recited differently.

[0173] The following aspects are illustrative only and may be combined with other aspects or teachings described herein, without limitation.

[0174] Aspect 1 is a method of wireless communication at a user equipment (UE), comprising: receiving a code block bundle (CBB) grouping algorithm indicator; calculating a CBB configuration based on the CBB grouping algorithm indicator; and transmitting a first plurality of CBBs based on the calculated CBB configuration, wherein each code block group (CBG) of a second plurality of CBGs is associated with a subset of the first plurality of CBBs, wherein each CBB of the first plurality of CBBs is associated with exactly one of the second plurality of CBGs.

[0175] Aspect 2 is the method of aspect 1, wherein the CBB grouping algorithm indicator indicates the UE to associate code blocks (CBs) with CBGs before associating the CBGs with CBBs, wherein calculating the CBB configuration based on the CBB grouping algorithm indicator comprises: associating each CB of a third plurality of CBs with one CBG of the second plurality of CBGs; and associating each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs after the association of each CB of the third plurality of CBs with one CBG of the second plurality of CBGs.

[0176] Aspect 3 is the method of aspect 2, further comprising calculating a first number of CBs associated with a first CBB of the first plurality of CBBs based on a second number of CBs associated with a first CBG of the second plurality of CBGs.

[0177] Aspect 4 is the method of either of aspects 2 or 3, wherein associating each CB of the third plurality of CBs with one CBG of the second plurality of CBGs comprises associating each CB of the third plurality of CBs with one CBG of the second plurality of CBGs such that a first number of CBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one.

[0178] Aspect 5 is the method of any of aspects 2 to 4, wherein associating each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs comprises associating each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs such that a first number of CBs associated with a first CBB of a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first CBG of the second plurality of CBGs by more than one.

[0179] Aspect 6 is the method of any of aspects 1 to 5, wherein the CBB grouping algorithm indicator indicates the UE to associate code blocks (CBs) with CBBs before associating the CBBs with CBGs, wherein calculating the CBB configuration based on the CBB grouping algorithm indicator comprises: associating each CB of a third plurality of CBs with one CBB of the first plurality of CBBs; and associating each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs after the association of each CB of the third plurality of CBs with one CBB of the first plurality of CBBs.

[0180] Aspect 7 is the method of aspect 6, wherein associating each CB of the third plurality of CBs with one CBB of the first plurality of CBBs comprises associating each CB of the third plurality of CBs with one CBB of the first plurality of CBBs such that a first number of CBs associated with a first CBB of the first plurality of CBBs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first plurality of CBBs by more than one.

[0181] Aspect 8 is the method of either of aspects 6 or 7, wherein associating each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs comprises associating each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs such that a first number of CBBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one.

[0182] Aspect 9 is the method of any of aspects 1 to 8, further comprising transmitting an indicator

of a capability of the UE to associate CBBs and CBGs before the reception of the CBB grouping algorithm indicator.

[0183] Aspect 10 is the method of aspect 9, wherein the indicator indicates at least one of: a processing time for the UE to encode a number of code blocks (CBs) associated with one of the first plurality of CBBs; a buffer associated with an encoding of CBs associated with one of the first plurality of CBBs; a delay associated with the encoding of CBs associated with one of the first plurality of CBBs; or a maximum number of CBs that the UE is able to associate with one of the first plurality of CBBs.

[0184] Aspect 11 is the method of any of aspects 1 to 10, wherein transmitting the first plurality of CBBs based on the calculated CBB configuration comprises, for each CBB of the first plurality of CBBs: interleaving code blocks (CBs) associated with the CBB; and transmitting the interleaved CBs.

[0185] Aspect 12 is a method of wireless communication at a network node, comprising: transmitting a code block bundle (CBB) grouping algorithm indicator; and receiving a first plurality of CBBs based on the CBB grouping algorithm indicator, wherein each code block group (CBG) of a second plurality of CBGs is associated with a subset of the first plurality of CBBs, wherein each CBB of the first plurality of CBBs is associated with exactly one of the second plurality of CBGs.

[0186] Aspect 13 is the method of aspect 12, wherein the CBB grouping algorithm indicator indicates a user equipment (UE) to associate code blocks (CBs) with CBGs before associating the CBGs with CBBs.

[0187] Aspect 14 is the method of aspect 13, wherein the CBB grouping algorithm indicator further indicates the UE to calculate a first number of CBs associated with a first CBB of the first plurality of CBBs based on a second number of CBs associated with a first CBG of the second plurality of CBGs.

[0188] Aspect 15 is the method of either of aspects 13 to 14, wherein the CBB grouping algorithm indicator further indicates the UE to associate each CB of a third plurality of CBs with one CBG of the second plurality of CBGs such that a first number of CBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one.

[0189] Aspect 16 is the method of any of aspects 13 to 15, wherein the CBB grouping algorithm indicator further indicates the UE to associate each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs such that a first number of CBs associated with a first CBB of a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first CBG of the second plurality of CBGs by more than one.

[0190] Aspect 17 is the method of any of aspects 12 to 16, wherein the CBB grouping algorithm indicator indicates a user equipment (UE) to associate code blocks (CBs) with CBBs before associating the CBBs with CBGs.

[0191] Aspect 18 is the method of aspect 17, wherein the CBB grouping algorithm indicator further indicates the UE to associate each CB of a third plurality of CBs with one CBB of the first plurality of CBBs such that a first number of CBs associated with a first CBB of the first plurality of CBBs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first plurality of CBBs by more than one.

[0192] Aspect 19 is the method of either of aspects 17 or 18, wherein the CBB grouping algorithm indicator further indicates the UE to associate each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs such that a first number of CBBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one.

[0193] Aspect 20 is the method of any of aspects 12 to 19, further comprising: receiving an

indicator of a capability of a user equipment (UE) to associate CBBs and CBGs; and configuring the CBB grouping algorithm indicator based on the capability.

[0194] Aspect 21 is the method of aspect 20, wherein the indicator indicates at least one of: a processing time for the UE to encode a number of code blocks (CBs) associated with one of the first plurality of CBBs; a buffer associated with an encoding of CBs associated with one of the first plurality of CBBs; a delay associated with the encoding of CBs associated with one of the first plurality of CBBs; or a maximum number of CBs that the UE is able to associate with one of the first plurality of CBBs.

[0195] Aspect 22 is the method of any of aspects 12 to 21, wherein receiving the first plurality of CBBs based on the CBB grouping algorithm indicator comprises, for each of the first plurality of CBBs, receiving interleaved code blocks (CBs) of one of the first plurality of CBBs.

[0196] Aspect 23 is the method of any of aspects 12 to 22, further comprising deinterleaving the received first plurality of CBBs based on the CBB grouping algorithm.

[0197] Aspect 24 is an apparatus for wireless communication, comprising: at least one memory; and at least one processor coupled to the at least one memory and, based at least in part on information stored in the at least one memory, the at least one processor, individually or in any combination, is configured to perform the method of any of aspects 1 to 23.

[0198] Aspect 25 is an apparatus for wireless communication, comprising means for performing each step in the method of any of aspects 1 to 23.

[0199] Aspect 26 is the apparatus of any of aspects 1 to 23, further comprising a transceiver (e.g., functionally connected to the at least one processor of Aspect 24) configured to receive or to transmit in association with the method of any of aspects 1 to 23.

[0200] Aspect 27 is a computer-readable medium (e.g., a non-transitory computer-readable medium) storing computer executable code, the code when executed by at least one processor causes the at least one processor, individually or in any combination, to perform the method of any of aspects 1 to 23.

Claims

1. An apparatus for wireless communication at a user equipment (UE), comprising: at least one memory; and at least one processor coupled to the at least one memory and, based at least in part on information stored in the at least one memory, the at least one processor, individually or in any combination, is configured to: receive a code block bundle (CBB) grouping algorithm indicator; calculate a CBB configuration based on the CBB grouping algorithm indicator; and transmit a first plurality of CBBs based on the calculated CBB configuration, wherein each code block group (CBG) of a second plurality of CBGs is associated with a subset of the first plurality of CBBs, wherein each CBB of the first plurality of CBBs is associated with exactly one of the second plurality of CBGs.
2. The apparatus of claim 1, wherein the CBB grouping algorithm indicator indicates the UE to associate code blocks (CBs) with CBGs before associating the CBGs with CBBs, wherein, to calculate the CBB configuration based on the CBB grouping algorithm indicator, the at least one processor, individually or in any combination, is configured to: associate each CB of a third plurality of CBs with one CBG of the second plurality of CBGs; and associate each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs after the association of each CB of the third plurality of CBs with one CBG of the second plurality of CBGs.
3. The apparatus of claim 2, wherein the at least one processor, individually or in any combination, is further configured to: calculate a first number of CBs associated with a first CBB of the first plurality CBBs based on a second number of CBs associated with a first CBG of the second plurality of CBGs.
4. The apparatus of claim 2, wherein, to associate each CB of the third plurality of CBs with one

CBG of the second plurality of CBGs, the at least one processor, individually or in any combination, is configured to: associate each CB of the third plurality of CBs with one CBG of the second plurality of CBGs such that a first number of CBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one.

5. The apparatus of claim 2, wherein, to associate each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs, the at least one processor, individually or in any combination, is configured to: associate each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs such that a first number of CBs associated with a first CBB of a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first CBG of the second plurality of CBGs by more than one.

6. The apparatus of claim 1, wherein the CBB grouping algorithm indicator indicates the UE to associate code blocks (CBs) with CBBs before associating the CBBs with CBGs, wherein, to calculate the CBB configuration based on the CBB grouping algorithm indicator, the at least one processor, individually or in any combination, is configured to: associate each CB of a third plurality of CBs with one CBB of the first plurality of CBBs; and associate each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs after the association of each CB of the third plurality of CBs with one CBB of the first plurality of CBBs.

7. The apparatus of claim 6, wherein, to associate each CB of the third plurality of CBs with one CBB of the first plurality of CBBs, the at least one processor, individually or in any combination, is configured to: associate each CB of the third plurality of CBs with one CBB of the first plurality of CBBs such that a first number of CBs associated with a first CBB of the first plurality of CBBs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first plurality of CBBs by more than one.

8. The apparatus of claim 6, wherein, to associate each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs, the at least one processor, individually or in any combination, is configured to: associate each CBB of the first plurality of CBBs with one CBG of the second plurality of CBGs such that a first number of CBBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one.

9. The apparatus of claim 1, wherein the at least one processor, individually or in any combination, is further configured to: transmit an indicator of a capability of the UE to associate CBBs and CBGs before the reception of the CBB grouping algorithm indicator.

10. The apparatus of claim 9, wherein the indicator indicates at least one of: a processing time for the UE to encode a number of code blocks (CBs) associated with one of the first plurality of CBBs; a buffer associated with an encoding of CBs associated with one of the first plurality of CBBs; a delay associated with the encoding of CBs associated with one of the first plurality of CBBs; or a maximum number of CBs that the UE is able to associate with one of the first plurality of CBBs.

11. The apparatus of claim 1, wherein, to transmit the first plurality of CBBs based on the calculated CBB configuration, the at least one processor, individually or in any combination, is configured to, for each CBB of the first plurality of CBBs: interleave code blocks (CBs) associated with the CBB; and transmit the interleaved CBs.

12. The apparatus of claim 1, further comprising a transceiver coupled to the at least one processor, wherein the at least one processor, individually or in any combination, is further configured to: receive, via the transceiver, the CBB grouping indicator; and transmit, via the transceiver, the first plurality of CBBs.

13. An apparatus for wireless communication at a network node, comprising: at least one memory; and at least one processor coupled to the at least one memory and, based at least in part on information stored in the at least one memory, the at least one processor, individually or in any

combination, is configured to: transmit a code block bundle (CBB) grouping algorithm indicator; and receive a first plurality of CBBs based on the CBB grouping algorithm indicator, wherein each code block group (CBG) of a second plurality of CBGs is associated with a subset of the first plurality of CBBs, wherein each CBB of the first plurality of CBBs is associated with exactly one of the second plurality of CBGs.

14. The apparatus of claim 13, wherein the CBB grouping algorithm indicator indicates a user equipment (UE) to associate code blocks (CBs) with CBGs before associating the CBGs with CBBs.

15. The apparatus of claim 14, wherein the CBB grouping algorithm indicator further indicates the UE to calculate a first number of CBs associated with a first CBB of the first plurality of CBBs based on a second number of CBs associated with a first CBG of the second plurality of CBGs.

16. The apparatus of claim 14, wherein the CBB grouping algorithm indicator further indicates the UE to associate each CB of a third plurality of CBs with one CBG of the second plurality of CBGs such that a first number of CBs associated with a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBG, that is not the first CBG, of the second plurality of CBGs by more than one.

17. The apparatus of claim 14, wherein the CBB grouping algorithm indicator further indicates the UE to associate each CBG of the second plurality of CBGs with one subset of CBBs of the first plurality of CBBs such that a first number of CBs associated with a first CBB of a first CBG of the second plurality of CBGs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first CBG of the second plurality of CBGs by more than one.

18. The apparatus of claim 13, wherein the CBB grouping algorithm indicator indicates a user equipment (UE) to associate code blocks (CBs) with CBBs before associating the CBBs with CBGs.

19. The apparatus of claim 18, wherein the CBB grouping algorithm indicator further indicates the UE to associate each CB of a third plurality of CBs with one CBB of the first plurality of CBBs such that a first number of CBs associated with a first CBB of the first plurality of CBBs does not differ from a second number of CBs associated with any CBB, that is not the first CBB, of the first plurality of CBBs by more than one.

20. A method of wireless communication at a user equipment (UE), comprising: receiving a code block bundle (CBB) grouping algorithm indicator; calculating a CBB configuration based on the CBB grouping algorithm indicator; and transmitting a first plurality of CBBs based on the calculated CBB configuration, wherein each code block group (CBG) of a second plurality of CBGs is associated with a subset of the first plurality of CBBs, wherein each CBB of the first plurality of CBBs is associated with exactly one of the second plurality of CBGs.
