

FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6A




FIG. 6B




FIG. 7A




FIG. 7B




FIG. 8A




FIG. 8B




FIG. 8C




FIG. 9




FIG. 10A




FIG. 10B




FIG. 11




FIG. 12




FIG. 13




FIG. 14




FIG. 15





FIG. 16






FIG. 18




FIG. 19




FIG. 20





FIG. 22






FIG. 21

FIG. 23




FIG. 24




FIG. 25




FIG. 26




FIG. 27





FIG. 28



1

MULTIPHASE DC-DC SWITCHING CONVERTER CIRCUIT, CORRESPONDING POWER MANAGEMENT INTEGRATED CIRCUIT AND DISPLAY DEVICE

PRIORITY CLAIM

This application claims the priority benefit of Italian Application for Patent No. 102022000008768, filed on May 2, 2022, the content of which is hereby incorporated by reference in its entirety to the maximum extent allowable by law.

TECHNICAL FIELD

The description relates to circuits and methods for sensing (e.g., measuring) the current that flows in an electrical load supplied by a multiphase power converter. For instance, one or more embodiments herein may be applied to power converter integrated circuits for display devices, particularly display devices based on active-matrix organic light-emitting diode (AMOLED) technology.

BACKGROUND

Sensing the load current and the inductor current is a desirable feature in many power converter applications. For instance, knowing the value of the load current facilitates stable and efficient operation of power converters. Furthermore, the information about the magnitude of the load current may be used to properly size the converter switch(es), according to the operating conditions, and consequently improve the converter efficiency curve at light load conditions.

Low silicon area, low power consumption, high accuracy and/or precision, flexibility of use (e.g., the possibility of being tuned) and/or the capability of sensing low load currents are also desirable features of power converters.

Therefore, there is a need in the art to provide improved power converters with load current sensing capabilities that aim at providing one or more of such desirable features.

SUMMARY

An object of one or more embodiments is to contribute to the providing of such improved power converters.

According to one or more embodiments, such an object can be achieved by a multiphase DC-DC switching converter circuit having the features set forth herein.

One or more embodiments may relate to a corresponding power management integrated circuit.

One or more embodiments may relate to a corresponding display device.

In one or more embodiments, a multiphase DC-DC switching converter circuit (e.g., a buck-boost converter) includes a first DC-DC converter arrangement and a second DC-DC converter arrangement. The first DC-DC converter arrangement includes a first switching stage having a first switching node and a first converter output node, the first switching stage including a first high-side switch and a first low-side switch. The first DC-DC converter arrangement includes a first current sensing circuit configured to produce a first detection voltage signal indicative of (e.g., proportional to) the instantaneous current flowing through one of the first high-side switch and the first low-side switch. The first DC-DC converter arrangement includes a first time-averaging circuit configured to receive the first detection

2

voltage signal and produce, as a function thereof (e.g., by time integration), a first time-averaged signal indicative of the average current flowing through the one of the first high-side switch and the first low-side switch during a respective switch conduction interval. The second DC-DC converter arrangement includes a second switching stage having a switching node and a second converter output node, the second switching stage including a second high-side switch and a second low-side switch. The second DC-DC converter arrangement includes a second current sensing circuit configured to produce a second detection voltage signal indicative of (e.g., proportional to) the instantaneous current flowing through one of the second high-side switch and the second low-side switch. The second DC-DC converter arrangement includes a second time-averaging circuit configured to receive the second detection voltage signal and produce, as a function thereof (e.g., by time integration), a second time-averaged signal indicative of the average current flowing through the one of the second high-side switch and the second low-side switch during a respective switch conduction interval. The multiphase DC-DC switching converter circuit further includes signal summation and re-scaling circuitry configured to receive the first time-averaged signal and the second time-averaged signal, add up the first and second time-averaged signals, and re-scale the first and second time-averaged signals by one or more factors indicative of the time period during which the first switching node is electrically coupled to the first converter output node and the time period during which the second switching node is electrically coupled to the second converter output node to produce an output signal indicative of the average output current of the multiphase DC-DC switching converter circuit.

One or more embodiments thus facilitate sensing the current flowing in the load supplied by a DC-DC converter circuit while providing low silicon area occupation, low quiescent current and/or high efficiency at light load of the converter circuit, as well as improved accuracy and/or suitability to sense low output current values.

In one or more embodiments, a power management integrated circuit comprises a first (e.g., boost) DC-DC converter circuit configured to produce a positive supply voltage for a display panel, and a second (e.g., buck-boost) DC-DC converter circuit according to one or more embodiments and configured to produce a negative supply voltage for the display panel.

In one or more embodiments, a display device comprises a display panel including light-emitting diodes arranged in a matrix, and a power management integrated circuit according to one or more embodiments. A positive supply terminal of the display panel is coupled to the first DC-DC converter circuit to receive the positive supply voltage and a negative supply terminal of the display panel is coupled to the second DC-DC converter circuit to receive the negative supply voltage.

BRIEF DESCRIPTION OF THE DRAWINGS

One or more embodiments will now be described, by way of example, with reference to the annexed figures, wherein:

FIG. 1 is a circuit block diagram exemplary of an AMOLED display device according to one or more embodiments of the present description;

FIG. 2 is a circuit block diagram exemplary of a single-phase DC-DC boost converter and related high-side current sensing circuitry;

3

FIG. 3 is a time diagram exemplary of possible time evolution of the load current in a DC-DC boost converter as exemplified in FIG. 2;

FIG. 4 is a circuit block diagram exemplary of a single-phase DC-DC inverting buck-boost converter and related high-side current sensing circuitry;

FIG. 5 is a time diagram exemplary of possible time evolution of the inductor instantaneous current and inductor average current in a single-phase DC-DC inverting buck-boost converter as exemplified in FIG. 4;

FIGS. 6A and 6B are time diagrams exemplary of possible time evolution of the inductor average current, high-side instantaneous current and high-side average current in a single-phase DC-DC inverting buck-boost converter as exemplified in FIG. 4;

FIGS. 7A and 7B are time diagrams exemplary of possible time evolution of the inductor average current, low-side instantaneous current and low-side average current in a single-phase DC-DC inverting buck-boost converter as exemplified in FIG. 4;

FIGS. 8A, 8B and 8C are time diagrams exemplary of possible time evolution of the inductor average current and inductor instantaneous current in a single-phase DC-DC inverting buck-boost converter as exemplified in FIG. 4, according to different operation modes of the converter;

FIG. 9 is a circuit block diagram exemplary of a DC-DC switching converter;

FIGS. 10A and 10B are time diagrams exemplary of possible time evolution of the inductor instantaneous current in a DC-DC switching converter operating in continuous conduction mode and in discontinuous conduction mode, respectively;

FIG. 11 is a circuit diagram exemplary of a load current sensing circuit for use in a DC-DC switching converter according to one or more embodiments of the present description;

FIG. 12 is a circuit diagram exemplary of a boost DC-DC switching converter;

FIG. 13 is a circuit diagram exemplary of a buck-boost DC-DC switching converter;

FIG. 14 is a circuit diagram exemplary of a buck DC-DC switching converter;

FIG. 15 is a circuit block diagram exemplary of a single-phase DC-DC inverting buck-boost converter and related high-side current sensing circuitry;

FIG. 16 is a circuit block diagram exemplary of a multiphase DC-DC converter and related load current sensing circuitry according to one or more embodiments of the present description;

FIG. 17 is a circuit block diagram exemplary of a multiphase DC-DC inverting buck-boost converter and related high-side current sensing circuitry according to one or more embodiments of the present description;

FIG. 18 is a circuit block diagram exemplary of a multiphase DC-DC converter and related load current sensing circuitry according to one or more embodiments of the present description;

FIG. 19 is a time diagram exemplary of possible time evolution of low-side control signals in a multiphase DC-DC inverting buck-boost converter according to one or more embodiments of the present description;

FIG. 20 is a circuit block diagram exemplary of a circuit for producing a low-side control signal according to one or more embodiments of the present description;

FIG. 21 is a circuit block diagram exemplary of another multiphase DC-DC inverting buck-boost converter and

4

related high-side current sensing circuitry according to one or more embodiments of the present description;

FIG. 22 is a time diagram exemplary of possible time evolution of the inductor currents in a multiphase DC-DC inverting buck-boost converter as exemplified in FIG. 21;

FIG. 23 is a circuit block diagram exemplary of another multiphase DC-DC inverting buck-boost converter and related high-side current sensing circuitry according to one or more embodiments of the present description;

FIG. 24 is a circuit block diagram exemplary of a differential input circuit for use in an adder circuit according to one or more embodiments of the present description;

FIG. 25 is a circuit block diagram exemplary of a signal averaging circuit according to one or more embodiments of the present description;

FIG. 26 is a circuit block diagram exemplary of the architecture of an adder circuit according to one or more embodiments of the present description;

FIG. 27 is a circuit block diagram exemplary of a possible implementation of the adder circuit of FIG. 26; and

FIG. 28 is a circuit block diagram exemplary of another possible implementation of the adder circuit of FIG. 26.

DETAILED DESCRIPTION

In the ensuing description, one or more specific details are illustrated, aimed at providing an in-depth understanding of examples of embodiments of this description. The embodiments may be obtained without one or more of the specific details, or with other methods, components, materials, etc. In other cases, known structures, materials, or operations are not illustrated or described in detail so that certain aspects of embodiments will not be obscured.

Reference to “an embodiment” or “one embodiment” in the framework of the present description is intended to indicate that a particular configuration, structure, or characteristic described in relation to the embodiment is comprised in at least one embodiment. Hence, phrases such as “in an embodiment” or “in one embodiment” that may be present in one or more points of the present description do not necessarily refer to one and the same embodiment. Moreover, particular configurations, structures, or characteristics may be combined in any adequate way in one or more embodiments.

The headings/references used herein are provided merely for convenience and hence do not define the extent of protection or the scope of the embodiments.

Throughout the figures annexed herein, unless the context indicates otherwise, like parts or elements are indicated with like references/numerals and a corresponding description will not be repeated for the sake of brevity.

By way of introduction to the detailed description of exemplary embodiments, reference may first be made to FIG. 1, which is a circuit block diagram exemplary of a display device 1, e.g., an AMOLED display device. The display device 1 comprises an AMOLED panel or matrix 10, a driver circuit 12 (e.g., a row driver and column driver for driving the rows and columns of the AMOLED matrix 10), and a power management integrated circuit (PMIC) 14 configured to supply power to the AMOLED panel 10 and/or to the driver circuit 12. In particular, the power supply circuit 14 may comprise a first DC-DC converter 140, a second DC-DC converter 142 and a third multiphase DC-DC converter 144.

The first converter 140 and the third converter 144 may be configured to generate a differential supply voltage for the AMOLED panel 10. For instance, the first DC-DC converter

5

140 includes a boost converter coupled to a positive supply rail **100a** that provides a positive supply voltage **VO1** to the panel **10**. The converter **140** typically operates in continuous conduction mode (CCM), even when the load current is null, in order to provide a flat output voltage **VO1**. Otherwise, flickering may occur in the AMOLED panel **10**. The third DC-DC converter **144** includes a multiphase inverting buck-boost converter coupled to a negative supply rail **100b** that provides a negative supply voltage **VO2** to the panel **10**. For instance, the converter **144** may comprise a first buck-boost converter arrangement **144a** (first phase), a second buck-boost converter arrangement **144b** (second phase) and a synchronization circuit or control circuit **146** that controls operation of the two phases **144a** and **144b**. The converter **144** can typically change its operation mode according to the load current (e.g., the current sunk by the AMOLED panel **10**), without causing any issue to the panel **10** such as flickering.

The second converter **142** may be configured to generate a supply voltage for the driver circuit **12**.

Conventional power supply circuits **14** for AMOLED display panels may rely on dedicated sensing circuitry for sensing the load current in the boost converter **140**. This approach, however, results in additional quiescent current and increased silicon area of the power supply chip **14**. As a consequence of the extra current consumption, the efficiency is lowered, especially at light load. Additionally, the current sensing arrangements provided in conventional power supply circuits can typically measure the current in one direction only, resulting in a measurement error when the converter **140** works in forced continuous conduction mode (FCCM), since in this condition the current that has to be measured can have both positive and negative values.

In this context, FIG. 2 is a circuit diagram exemplary of a DC-DC boost converter **20** (as may be used in converter **140**) and a related high-side current sensing circuit **22** configured to sense the current flowing through the high-side switch of converter **20**.

Converter **20** comprises an input node **202** configured to receive an input DC voltage **VIN**. An inductor **L** (e.g., an external inductor) is arranged between the input node **202** and a switching node **204** of the converter **20**. A high-side switch **HS** (e.g., a p-channel power MOS transistor) is arranged between the switching node **204** and the output node **206** of the converter **20**. A low-side switch **LS** (e.g., an n-channel power MOS transistor) is arranged between the switching node **204** and a reference or ground node **208** of the converter **20** that provides a reference or ground voltage **V_{GND}** (e.g., 0 V). A current **I_{HS}** flows through the high-side switch **HS** and a current **I_{LS}** flows through the low-side switch **LS**. A capacitor (e.g., an external capacitor, not visible in the Figures annexed herein) may be coupled between the output node **206** and the reference node **208** to operate the converter **20**. The high-side switch **HS** and the low-side switch **LS** are controlled by a control unit of the converter **20** (not visible in the Figures annexed herein) according to known control schemes, so that a regulated output DC voltage **V_{OUT}** is produced at the output node **206**.

The current sensing circuit **22** relies on a replica-based architecture with a closed loop in order to sense the waveform of the time-variant current **I_{HS}** flowing through the high-side switch **HS**. In particular, the current sensing circuit **22** comprises a replica **HSr** of the high-side switch **HS**, coupled between node **204** (e.g., at a drain terminal of the replica power MOS transistor **HSr**) and the inverting input of an operational amplifier **210** such as an error amplifier (e.g., at a source terminal of the replica transistor **HSr**). The

6

replica switch **HSr** may be smaller than the high-side switch **HS**: for instance, the channel width of high-side switch **HS** and the channel width of replica switch **HSr** may be in a **N:1** ratio, with **N>1**. The replica switch **HSr** is controlled by the same control signal received by the high-side switch **HS**: the gate terminals of transistors **HS** and **HSr** may be coupled one to the other. The non-inverting input of the operational amplifier **210** is coupled downstream of the high-side switch **HS** (e.g., to the source terminal of transistor **HS**). The output signal of the operational amplifier **210** controls the conductivity of a first transistor **M1**, e.g., it is coupled to the gate terminal of an n-channel MOS transistor **M1**. A first current mirror circuit is arranged between the replica switch **HSr**, the source terminal of transistor **M1** and the ground node **208**. In particular, the first current mirror circuit comprises an n-channel MOS transistor **M2** having a drain terminal coupled to the inverting input of the operational amplifier **202** and a source terminal coupled to the ground node **208**, and an n-channel MOS transistor **M3** having a drain terminal coupled to the source terminal of transistor **M1** and a source terminal coupled to the ground node **208**. The gate terminals of transistors **M2** and **M3** are connected one to the other and connected to the drain terminal of transistor **M3**, so that the current flowing through transistors **M1** and **M3** is mirrored to flow through transistor **M2**. Transistors **M2** and **M3** may provide a mirroring factor of 1:1 (e.g., they may have the same channel width and length). A second current mirror circuit is arranged between the drain terminal of transistor **M1**, a sensing node **212** of the current sensing circuit **22**, and the output node **206** of the converter **10**. In particular, the second current mirror circuit comprises a p-channel MOS transistor **M4** having a drain terminal coupled to the drain terminal of transistor **M1** and a source terminal coupled to the output node **206**, and a p-channel MOS transistor **M5** having a drain terminal coupled to the sensing node **212** and a source terminal coupled to the output node **206**. The gate terminals of transistors **M4** and **M5** are connected one to the other and connected to the drain terminal of transistor **M4**, so that the current flowing through transistors **M1** and **M4** is mirrored to flow through transistor **M5**. Transistors **M4** and **M5** may provide a mirroring factor of 1:1 (e.g., they may have the same channel width and length). A resistor **R_S** is coupled between the sensing node **212** and the ground node **208**. Another resistor **R21** is coupled between the sensing node **212** and an output node **214** of the current sensing circuit **22**. A first capacitor **C1** is coupled between the sensing node **212** and the ground node **208**, and a second capacitor **C2** is coupled between the output node **214** and the ground node **208**, so that the current flowing through transistor **M5** produces a voltage **V_{SENSE}** at the output node **214** that is indicative of (e.g., proportional to) the current **I_{HS}** flowing through the high-side switch **HS**.

As previously discussed, a current sensing circuit **22** as exemplified in FIG. 2 can sense a positive current flowing from the switching node **204** to the output node **206**. Reverse (negative) current flowing from node **206** to node **204** cannot be sensed, resulting in a loss of accuracy for DC-DC converters working in forced continuous conduction mode, where current inversion at light load takes place. To this regard, FIG. 3 is a time diagram that exemplifies a portion of the load current **I_{LOAD}** in light-load CCM that is not sensed by circuit **22** over a clock period **T_{CK}**: the positive area **31** is correctly sensed while the negative areas **32** may not be sensed.

In order to improve the currently available converters, possibly reusing most of the circuitry already present in the chips, and reducing silicon area and power consumption,

one or more embodiments may rely on a different architecture where the load current is sensed in the inverting buck-boost converter **144** of the power management circuit **14**, instead of being measured in the boost converter **140**. Additionally, since the voltage generator **144** for the negative rail **100b** works exclusively in positive current direction, the measurement accuracy at light load may be improved since no negative currents have to be sensed. In one or more embodiments, the sensing operation in the buck-boost converter **144** may be carried out by resorting (at least partially) to a circuit already present in some commercial devices (e.g., conventionally used for control and/or for protection purposes), thereby providing improved power efficiency and/or reduced silicon area.

FIG. 4 is a circuit block diagram exemplary of a possible implementation of a single-phase inverting buck-boost converter, such as converter **144a** or **144b** of FIG. 1, and related high-side current sensing circuitry which may be included in each phase of a multiphase converter **144**. Current sensing circuitry as exemplified in FIG. 4 may be conventionally used for protection and/or loop control purposes.

As exemplified in FIG. 4, an inverting buck-boost converter may comprise an input node **402** configured to receive a DC input voltage V_{DD} (e.g., provided by a battery), and an output node **404** configured to be coupled to the negative rail **100b** of device **1** to supply a regulated voltage VO_2 to the display panel **10**. The converter further comprises a high-side switch **S1** (e.g., an n-channel power MOS transistor) coupled between the input node **402** and a switching node **LX**, and a low-side switch **S2** (e.g., an n-channel power MOS transistor) coupled between the switching node **LX** and the output node **404**. In other words, switches **S1** and **S2** provide a half-bridge arrangement between nodes **402** and **404**. An inductor **L** (e.g., an external inductor) is coupled (e.g., directly) between the switching node **LX** and ground **GND** at voltage V_{gnd} (e.g., 0 V). The instantaneous current flowing through the high-side switch **S1** is indicated herein as $I_{HS,i}$; the instantaneous current flowing through the low-side switch **S2** is indicated herein as $I_{LS,i}$; the instantaneous current flowing through the inductor **L** is indicated herein as $I_{LX,i}$; and the instantaneous current flowing through the load **10** is indicated herein as $I_{O,ph,i}$. Subscript “i” is used here to indicate the i^{th} phase of a multiphase converter device such as converter **144** of FIG. 1.

As exemplified in FIG. 4, the high-side switch **S1** and the low-side switch **S2** have respective control terminals (e.g., gate terminals) configured to receive (e.g., from a control circuit such as circuit **146**) respective drive signals D_{HS} and D_{LS} (e.g., PWM signals). Based on the control signals D_{HS} and D_{LS} , the switches **S1** and **S2** switch from a first (e.g., open) state to a second (e.g., closed) state, and vice versa. In particular, signals D_{HS} and D_{LS} may cyclically vary in time so that the high-side switch **S1** is closed for a time T_{HS} during which the low-side switch **S2** is open, and the low-side switch **S2** is closed for a time T_{LS} during which the high-side switch **S1** is open. This controlled switching facilitates regulating a voltage level at the switching node **LX** and thus the current $I_{LX,i}$ flowing through the inductor **L**.

As exemplified in FIG. 4, the converter **144a**, **144b** may comprise a high-side current sensing arrangement including a further switch **S3** (e.g., an n-channel power MOS transistor) and a resistor **R41**. Resistor **R41** is coupled between the input node **402** and a first terminal (e.g., drain terminal) of switch **S3**. The second terminal (e.g., source terminal) of switch **S3** is coupled to the switching node **LX**. The switch **S3** is configured to receive the same control signal D_{HS} as the high-side switch **S1**. When the high-side switch **S1** is

closed (e.g., turned on), the switch **S3** is also closed (e.g., turned on). As a result, a voltage drop V_{R41} across resistor **R41** can be expressed as $V_{R41} = V_{HS} - V_{S3}$, where V_{HS} is the voltage drop across the high-side switch **S1** and V_{S3} is the voltage drop across the further switch **S3**, as indicated in FIG. 4.

In one or more embodiments, it is desirable that the voltage drop V_{R41} across resistor **R41** be substantially equal to the voltage drop V_{HS} across the high-side switch **S1**, that is, $V_{R41} \approx V_{HS}$. In order to provide such a condition, switches **S1** and **S3** as well as resistor **R41** may be dimensioned so that the product of the current flowing through resistor **R41** and the on-resistance of switch **S3** (R_{onS3})—i.e., voltage V_{S3} —is negligible with respect to the voltage drop V_{HS} across the high-side switch **S1**. For instance, the resistance of resistor **R41** may be much greater than the on-resistance of switch **S1** (R_{onHS}) and the on-resistance of switch **S3** (R_{onS3}). The on-resistance of switch **S3** (R_{onS3}) may be much lower than the resistance of resistor **R41** in order to reduce the voltage partitioning factor and result in $V_{S3} \ll V_{R41}$. Since the lowest impedance path between nodes **402** and **LX** is the one through switch **S1** (order of magnitude lower than the impedance of the path through **R41** and **S3**), the voltage difference between node **402** and node **LX** is substantially determined by switch **S1**. Since the series arrangement of switch **S3** and resistor **R41** is coupled in parallel to switch **S1**, the voltage at the intermediate node is determined by the resistive partitioning between **S3** and **R41**:

$$V_{S3} = V_{HS} \cdot \frac{R_{onS3}}{R_{onS3} + R41}$$

$$V_{R41} = V_{HS} \cdot \frac{R41}{R_{onS3} + R41}$$

In order to produce $V_{S3} \ll V_{R41}$ and thus $V_{R41} \approx V_{HS}$, the on-resistance of switch **S3** (R_{onS3}) may be much lower than the resistance of resistor **R41**: $R_{onS3} \ll R41$ (e.g., R_{onS3} may be two orders of magnitude lower than **R41**, or even less).

As exemplified in FIG. 4, the current sensing arrangement of converter **144a**, **144b** may further include a resistor R_{UP} , a transistor **T1** (e.g., a p-channel MOS transistor) and a resistor R_D coupled in series between the input node **402** and ground node **GND**. In particular, the resistor R_{UP} has a first terminal coupled to the input node **402** and a second terminal coupled to a source terminal of transistor **T1**. The drain terminal of transistor **T1** is coupled to a first terminal of resistor R_D at node **406**. The second terminal of resistor R_D is coupled to ground node **GND**. The current sensing arrangement further includes a buffer stage **450** (e.g., an operational amplifier) having a first (e.g., non-inverting) input terminal coupled to a node intermediate resistor **R41** and switch **S3**, a second (e.g., inverting) input terminal coupled to a node intermediate resistor R_{UP} and transistor **T1**, and an output terminal coupled to the control (e.g., gate) terminal of transistor **T1**. When the high-side transistor **S1** is closed, the voltage drop $V_{R41} \approx V_{HS}$ across resistor **R41** is forced, via the buffer **450**, across resistor R_{UP} . As a result, a current $I_{R_{UP}} = V_{HS} / R_{UP}$ flows through the series arrangement including R_{UP} , **T1** and R_D , thereby producing a voltage drop V_{RD} across resistor R_D equal to:

$$V_{RD} = \frac{V_{HS}}{R_{UP}} \cdot R_D = I_{HS,i}(t) \cdot R_{onHS} \frac{R_D}{R_{UP}} = I_{HS,i}(i) \cdot R_{onHS} \cdot K$$

where R_{onHS} is the resistance of the high-side transistor S1 in the conductive (ON) state, and $K=R_D/R_{UP}$ is the gain factor of the current sensing arrangement. Therefore, voltage V_{RD} at node 406 is indicative of the instantaneous high-side current $I_{HS,i}(t)$. Also, when the high-side transistor S1 is open (e.g., off), voltage V_{RD} is null. In other words, the current sensing arrangement exemplified herein has the role of “referring to ground” a voltage signal indicative of the high-side voltage V_{HS} .

FIG. 5 is a time diagram exemplary of the instantaneous inductor current $I_{LX,i}$ and the average inductor current $\langle I_{LX,i} \rangle$ during operation of a converter 144a, 144b as exemplified in FIG. 4. Substantially, the instantaneous inductor current $I_{LX,i}$ can be considered to be the sum of two contributions, i.e., the high-side current $I_{HS,i}$ that flows through the high-side switch S1 during the high-side period T_{HS} (see also FIG. 6A) and the low-side current $I_{LS,i}$ that flows through the low-side switch S2 during the low-side period T_{LS} (see also FIG. 7A): $I_{LX,i} = I_{HS,i} + I_{LS,i}$. A complete switching cycle has a duration $T_{SW} = T_{HS} + T_{LS}$ (assuming operation in continuous conduction mode, CCM).

The instantaneous inductor current $I_{LX,i}$ may also be expressed as the sum of two contributions, i.e., the average inductor current $\langle I_{LX,i} \rangle$ and a ripple inductor current I_{LX,i_ripple} : $I_{LX,i} = \langle I_{LX,i} \rangle + I_{LX,i_ripple}$. The ripple contribution I_{LX,i_ripple} does not deliver power to the output of the converter 144a, 144b (e.g., to the load) insofar as its average value is null, so that the load current information of interest in various application is related to the value of the average inductor current $\langle I_{LX,i} \rangle$. Therefore, in the following, the inductor current $I_{LX,i}$ may be approximated by its average value $\langle I_{LX,i} \rangle$.

As exemplified in FIGS. 6A and 6B, the following conventions can be used when referring to the high-side current $I_{HS,i}$. The value $\langle I_{HS,i_THS} \rangle$ is the average value of current $I_{HS,i}$ computed over the high-side period T_{HS} , which is equal to the average inductor current $\langle I_{LX,i} \rangle$. The value $\langle I_{HS,i} \rangle$ is the average value of current $I_{HS,i}$ computed over a complete switching cycle T_{SW} , which is equal to $\langle I_{LX,i} \rangle \cdot D_{ph,i}$ where $D_{ph,i}$ is the duty-cycle of the high-side control signal D_{HS} . Similarly, as exemplified in FIGS. 7A and 7B, the following conventions can be used when referring to the low-side current $I_{LS,i}$. The value $\langle I_{LS,i_TLS} \rangle$ is the average value of current $I_{LS,i}$ computed over the low-side period T_{LS} , which is equal to the average inductor current $\langle I_{LX,i} \rangle$. The value $\langle I_{LS,i} \rangle$ is the average value of current $I_{LS,i}$ computed over a complete switching cycle T_{SW} , which is equal to $\langle I_{LX,i} \rangle \cdot (1 - D_{ph,i})$.

Additionally, as exemplified in FIGS. 8A, 8B and 8C, the average inductor current $\langle I_{LX,i} \rangle$ during the high-side phase T_{HS} is the same as during the low-side phase T_{LS} , if the idle time T_{IDLE} is neglected and just the coil magnetization and de-magnetization times are taken into consideration. FIG. 8A is a time diagram exemplary of the instantaneous inductor current $I_{LX,i}$ and the average inductor current $\langle I_{LX,i} \rangle$ in case the converter operates in continuous conduction mode (CCM). FIG. 8B is a time diagram exemplary of the instantaneous inductor current $I_{LX,i}$ and the average inductor current $\langle I_{LX,i} \rangle$ in case the converter operates in critical mode. FIG. 8C is a time diagram exemplary of the instantaneous inductor current $I_{LX,i}$ and the average inductor current $\langle I_{LX,i} \rangle$ in case the converter operates in discontinuous conduction mode (DCM).

More generally, FIG. 9 is a circuit block diagram exemplary of a DC-DC converter 9 that can include one of a variety of different converter topologies (e.g., buck, boost, buck-boost, etc.). Converter 9 controls the current I_L flowing

through the (external) inductor L coupled thereto. Additionally, converter 9 may provide a first signal indicative of the switching period T_{SW} , a second signal indicative of the inductor magnetization period T1 (which can be a high-side period or a low-side period, depending on the converter topology), a third signal indicative of the inductor demagnetization period T2 (which can be a low-side period or a high-side period, depending on the converter topology), and a fourth signal indicative of the instantaneous current $I_L(t)$ flowing in the inductor L, e.g., $R \cdot I_L(t)$, produced by a current sensing arrangement (which can be a high-side sensing arrangement as previously discussed, or a low-side sensing arrangement). In particular, depending on the current sensing arrangement adopted by converter 9, the signal $R \cdot I_L(t)$ may correspond to the voltage drop across the high-side switch or the low-side switch. FIGS. 10A and 10B are time diagrams exemplary of possible time evolution of the inductor current $I_L(t)$ when the converter 9 operates in continuous conduction mode (CCM) and in discontinuous conduction mode (DCM). The following equation applies: $T_{SW} = T1 + T2 + T_{IDLE}$. In continuous conduction mode, the idle time T_{IDLE} is null.

One or more embodiments may rely on a circuit arrangement as exemplified in FIG. 11 to produce a voltage signal $V_{IO_ph,i}$ that is indicative of the average current provided by the converter to the load, as a function of signal $R \cdot I_L(t)$ indicative of the instantaneous inductor current. As exemplified in FIG. 11, one or more embodiments may comprise an average value accumulation circuit block 90 coupled to a sensing node of the converter to receive signal $R \cdot I_L(t)$ and configured to produce a signal at node 902 that is indicative of the average inductor current during the sensing period. The circuit block 90 includes a switch 91, a resistor R_{90} and a capacitor C_{90} . Switch 91 has a first terminal configured to receive signal $R \cdot I_L(t)$ and a second terminal coupled to the first terminal of resistor R_{90} , and is configured to receive a control signal D_{91} to be controlled thereby. The resistor R_{90} has a second terminal coupled to node 902. The capacitor C_{90} is coupled between node 902 and ground node GND and forms an RC filter circuit with resistor R_{90} . Therefore, the RC filter R_{90} , C_{90} can charge and discharge (only) during the turn-on phase of switch 91 (low impedance state or closed state). During the high impedance state, the filter sees an open circuit and there is no closed loop where the current can flow. As a result, voltage V_{902} at node 902 results from sampling and integrating voltage $R \cdot I_L(t)$ over the period during which switch 91 is closed, and is thus indicative of the average of signal $R \cdot I_L(t)$ calculated over the interval in which switch 91 is closed: $\langle I_{LX,i} \rangle$.

As exemplified in FIG. 11, one or more embodiments may comprise a time average circuit block 92 coupled to node 902 and configured to produce a signal at node 922 that is indicative of the average load current $\langle I_{O_ph,i} \rangle$. The circuit block 92 includes a first switch 93, a second switch 94, a resistor R_{92} and a capacitor C_{92} . Switch 93 has a first terminal coupled to node 902 and a second terminal coupled to the first terminal of resistor R_{92} , and is configured to receive a control signal D_{93} to be controlled thereby. Switch 94 has a first terminal coupled to the second terminal of switch 93 and a second terminal coupled to ground node GND, and is configured to receive the complement of control signal D_{93} to be controlled thereby. Resistor R_{92} has a second terminal coupled to node 922. Capacitor C_{92} is coupled between node 922 and ground node GND and forms an RC filter circuit with resistor R_{92} . As a result, voltage $V_{IO_ph,i}$ at node 922 is indicative of the voltage V_{902} multiplied by a factor equal to the duty-cycle of signal D_{93} .

11

In one or more embodiments, a buffer circuit (not visible in the Figures annexed herein) may be arranged between the output of circuit **90** and the input of circuit **92**.

A circuit arrangement as exemplified in FIG. **11** may be used for sensing the load current in a variety of converter topologies, by appropriately driving the switches **91**, **93** and **94**.

For instance, FIG. **12** is a circuit diagram exemplary of a two-switch boost DC-DC converter, where the high-side switch HS is controlled by signal D_{HS} and the low-side switch LS is controlled by signal D_{LS} . In case signal $R \cdot I_L(t)$ is sensed during the low-side conduction period, switch **91** can be driven by signal D_{LS} (i.e., $D_{91}=D_{LS}$), switch **93** can be driven by signal D_{HS} (i.e., $D_{93}=D_{HS}$), and switch **94** can be driven by the complement of signal D_{HS} (i.e., $D_{94}=\overline{D_{HS}}$) to produce an output voltage $V_{IO_ph_i}$ at node **922** that is indicative of the output current of the converter. In case signal $R \cdot I_L(t)$ is sensed during the high-side conduction period, switch **91** can be driven by signal D_{HS} (i.e., $D_{91}=D_{HS}$), switch **93** can be driven by signal D_{HS} (i.e., $D_{93}=D_{HS}$), and switch **94** can be driven by the complement of signal D_{HS} (i.e., $D_{94}=\overline{D_{HS}}$) to produce an output voltage $V_{IO_ph_i}$ at node **922** that is indicative of the output current of the converter. Table I that appears at the end of this description is indicative of the duration of the time intervals during which switches **91**, **93** and **94** are closed in the cases exemplified above, in terms of inductor magnetization times (T1) and demagnetization times (T2).

According to another example, FIG. **13** is a circuit diagram exemplary of a two-switch buck-boost inverting DC-DC converter, where the high-side switch HS is controlled by signal D_{HS} and the low-side switch LS is controlled by signal D_{LS} . In case signal $R \cdot I_L(t)$ is sensed during the high-side conduction period, switch **91** can be driven by signal D_{HS} (i.e., $D_{91}=D_{HS}$), switch **93** can be driven by signal D_{LS} (i.e., $D_{93}=D_{LS}$), and switch **94** can be driven by the complement of signal D_{LS} (i.e., $D_{94}=\overline{D_{LS}}$) to produce an output voltage $V_{IO_ph_i}$ at node **922** that is indicative of the output current of the converter. In case signal $R \cdot I_L(t)$ is sensed during the low-side conduction period, switch **91** can be driven by signal D_{LS} (i.e., $D_{91}=D_{LS}$), switch **93** can be driven by signal D_{LS} (i.e., $D_{93}=D_{LS}$), and switch **94** can be driven by the complement of signal D_{LS} (i.e., $D_{94}=\overline{D_{LS}}$) to produce an output voltage $V_{IO_ph_i}$ at node **922** that is indicative of the output current of the converter. Table II that appears at the end of the description is indicative of the duration of the time intervals during which switches **91**, **93** and **94** are closed in the cases exemplified above, in terms of inductor magnetization/demagnetization times.

According to a further example, FIG. **14** is a circuit diagram exemplary of a two-switch buck DC-DC converter, where the high-side switch HS is controlled by signal D_{HS} and the low-side switch LS is controlled by signal D_{LS} . In case signal $R \cdot I_L(t)$ is sensed during the high-side conduction period, switch **91** can be driven by signal D_{HS} (i.e., $D_{91}=D_{HS}$), switch **93** can be closed during the entire switching period, and switch **94** can be open during the entire switching period to produce an output voltage $V_{IO_ph_i}$ at node **922** that is indicative of the output current of the converter. In case signal $R \cdot I_L(t)$ is sensed during the low-side conduction period, switch **91** can be driven by signal D_{LS} (i.e., $D_{91}=D_{LS}$), switch **93** can be closed during the entire switching period, and switch **94** can be open during the entire switching period to produce an output voltage $V_{IO_ph_i}$ at node **922** that is indicative of the output current of the converter. Table III that appears at the end of the description is indicative of the duration of the time intervals

12

during which switches **91**, **93** and **94** are closed in the cases exemplified above, in terms of inductor magnetization/demagnetization times. Therefore, in a buck converter as exemplified in FIG. **14** the average inductor current corresponds to the average output current; circuit block **92** can be considered to be always active, and thus could even be omitted.

As a further detailed example, FIG. **15** is a circuit diagram exemplary of the single-phase inverting buck-boost converter **144a** or **144b** of FIG. **4**, including the sensing circuitry configured to measure the average inductor current $\langle I_{LX_i} \rangle$ and output current. In the example of FIG. **15**, the average inductor current $\langle I_{LX_i} \rangle$ is computed as a function of the average high-side current $\langle I_{HS_i_THS} \rangle$ flowing through the high-side switch S1 during the high-side phase T_{HS} , based on the fact that $\langle I_{LX_i} \rangle \approx \langle I_{HS_i_THS} \rangle$ (see again FIG. **6B**) during the time interval T_{HS} . As exemplified in FIG. **15**, the average value accumulation circuit block **90** is coupled to the sensing node **406** and is configured to produce, as a function of the high-side current sensed during T_{HS} , a signal at node **902** that is indicative of the average inductor current $\langle I_{LX_i} \rangle$. Switch **91** is thus controlled by signal D_{HS} , i.e., the switching activity of switch **91** is synchronized with the switching activity of the high-side switch S1 (in accordance with the fact that the current is sensed at the high-side switch S1). The resistance of resistor R_{90} is much greater than the resistance of resistor R_D (i.e., $R_{90} \gg R_D$). During the turn-on phase of switch **91** the RC filter R_{90} , C_{90} sees an equivalent sawtooth waveform corresponding to the high-side current ramp solely. As a result, voltage V_{902} at node **902** results from sampling and integrating voltage V_{RD} at node **406** over the high-side phase T_{HS} , and is thus indicative of the average inductor current $\langle I_{LX_i} \rangle$:

$$V_{902} = \langle I_{LX_i} \rangle \cdot R_{onHS} \cdot \frac{R_D}{R_{UP}} = \langle I_{LX_i} \rangle \cdot R_{onHS} \cdot K$$

As exemplified in FIG. **15**, the time average circuit block **92** is configured to produce a signal $V_{IO_ph_i}$ at node **922** that is indicative of the average load current $\langle I_{O_ph_i} \rangle$. Switch **93** is controlled by signal D_{LS} , i.e., the switching activity of switch **93** is synchronized with the switching activity of the low-side switch S2. Switch **94** is controlled by the complement of control signal D_{LS} , i.e., the switching activity of switch **94** is synchronized in anti-phase with the switching activity of the low-side switch S2 and switch **93**. As a result, voltage $V_{IO_ph_i}$ at node **922** is indicative of the average load current $\langle I_{O_ph_i} \rangle$, which also corresponds to the average value $\langle I_{LS_i} \rangle$ of current I_{LS_i} computed over a complete switching cycle T_{SW} :

$$V_{IO_ph_i} = V_{902} \cdot \frac{T_{LS}}{T_{SW}} = \langle I_{LX_i} \rangle \cdot R_{onHS} \cdot K \cdot \frac{T_{LS}}{T_{SW}} = \langle I_{LX_i} \rangle \cdot R_{onHS} \cdot K \cdot (1 - D_{ph_i}) = R_{onHS} \cdot \langle I_{O_ph_i} \rangle \cdot K$$

where D_{ph_i} is the duty-cycle of converter **144a** or **144b**, i.e., $D_{ph_i} = T_{HS}/T_{SW}$.

In a multiphase DC-DC converter architecture such as converter **144** exemplified in FIG. **1**, the overall load current I_O can be expressed as the sum of the individual load currents provided by the single phases **144a** and **144b**: $I_O = I_{O_ph_1} + I_{O_ph_2}$.

13

Therefore, one or more embodiments may rely on the load current sensing architecture exemplified in FIG. 16. Here, a multiphase converter 144 comprises a plurality of phases 144a, 144b, 144c. Each phase is coupled to a respective average value accumulation circuit block 90a, 90b, 90c 5 configured to receive a respective signal $R \cdot I_L(t)_i$ and to produce a respective signal $R \cdot \langle I_L \rangle_i$ that is indicative of the average inductor current during the sensing period. Each circuit block 90a, 90b, 90c is coupled to a respective time average circuit block 92a, 92b, 92c configured to receive the 10 respective signal indicative of the average inductor current and to produce a respective signal $R \cdot \langle I_O \rangle_i$ that is indicative of the respective average load current. Depending on the converter topology, blocks 92a, 92b, 92c can be omitted (e.g., if the converter is a buck converter). Further, an adder circuit 101 may be provided to sum the individual contributions from circuits 92a, 92b, 92c and produce an output 15 voltage signal $R \cdot \langle I_O \rangle_{TOT}$ indicative of the total load current I_O .

For instance, as exemplified in FIG. 17, a simple solution for producing an output voltage signal V_{IO} indicative of the total load current I_O may rely on providing each of the single-phase converters 144a and 144b with a respective load current measuring arrangement as exemplified in FIG. 9, and sum the individual load values (i.e., the individual 25 contributions $V_{IO_ph_1}$ and $V_{IO_ph_2}$ due to each phase of converter 144) at an adder circuit 101 to produce the output signal V_{IO} . Optionally, the signals output from nodes 922a and 922b can be buffered by respective buffers 102a and 102b before being fed to the adder circuit 101 so as to improve the measurement accuracy. The cost (in terms of electrical components and thus silicon area) of the solution 30 exemplified in FIG. 17 is four RC filters, six switches with independent control, four buffers (including the two buffers downstream of nodes 902, not visible in FIG. 17), and one adder circuit. Advantageously, the two load current sensing circuits of converters 144a and 144b are not tied together and therefore the solution exemplified in FIG. 17 is very flexible. For instance, one or more embodiments as exemplified in FIG. 17 allow the two converters 144a and 144b 35 to operate in different regions, with different control loop, and/or to sink different current values.

Alternatively, one or more embodiments may rely on the sensing architecture exemplified in FIG. 18, provided that the two (or more) single-phase converters share the same switching frequency (or switching period T_{SW}). Here, a multiphase converter 144 comprises a plurality of phases 144a, 144b, 144c. Each phase is coupled to a respective average value accumulation circuit block 90a, 90b, 90c 40 configured to receive a respective signal $R \cdot I_L(t)_i$ and to produce a respective signal $R \cdot \langle I_L \rangle_i$ that is indicative of the average inductor current during the sensing period. An adder circuit 149 is provided to sum the individual contributions $R \cdot \langle I_L \rangle_i$ from circuits 90a, 90b, 90c and produce an output signal $R \cdot \langle I_L \rangle_{TOT}$ indicative of the sum of the average inductor currents. A circuit 119 is configured to produce a signal D_{93_AVG} indicative of an equivalent time average value. A single time average circuit block 920 is configured to receive the summed average inductor current signal $R \cdot \langle I_L \rangle_{TOT}$ and the equivalent time average value D_{93_AVG} 45 to produce an output voltage signal $R \cdot \langle I_O \rangle_{TOT}$ indicative of the total load current I_O .

The architecture of FIG. 18 may thus be designed to merge (e.g., unify) the information from the independent, single phases of the converter 144 to measure the overall load current I_O by determining an equivalent output signal $V_{IO_ph_eq}$ (indicative of an equivalent inductor current 50

14

$I_{O_ph_eq}$) and an equivalent duty-cycle D_{ph_eq} , i.e., the inductor current value and duty-cycle value that would cause a single inverting buck-boost converter to produce the same load current I_O , as indicated by the following equation:

$$\begin{aligned} V_{IO_ph_eq} &= V_{IO_ph_1} + V_{IO_ph_2} \\ &= \langle I_{LX_1} \rangle \cdot R_{onHS,1} \cdot K \cdot (1 - D_{ph_1}) + \\ &\quad \langle I_{LX_2} \rangle \cdot R_{onHS,2} \cdot K \cdot (1 - D_{ph_2}) \\ &\approx R_{onHS} \cdot K \cdot (\langle I_{LX_1} \rangle + \langle I_{LX_2} \rangle) (1 - D_{ph_eq}) \\ &= R_{onHS} \cdot K \cdot \langle I_{LX_eq} \rangle (1 - D_{ph_eq}) = R_{onHS} \cdot K \cdot I_{O_ph_eq} \end{aligned}$$

One or more embodiments may thus rely on the approach of summing the independent average coil currents $\langle I_{LX_1} \rangle$ and $\langle I_{LX_2} \rangle$ to produce signal $\langle I_{LX_eq} \rangle$, and multiplying this signal to a custom time average that is the average of the low-side control. To this regard, reference may be made to FIG. 19, which is a time diagram exemplary of a possible time evolution of the low-side control signal $D_{LS,1}$ applied to the first converter (or first phase) 144a, the low-side control signal $D_{LS,2}$ applied to the second converter (or second phase) 144b, and an equivalent low-side control signal $D_{LS,eq}$ that substantially corresponds to $D_{LS,1}$ or $D_{LS,2}$ alternatively at each switching period T_{SW} (e.g., $D_{LS,eq} = D_{LS,2}$ during odd-numbered periods and $D_{LS,eq} = D_{LS,1}$ during even-numbered periods). As a result, the quantity $1 - D_{ph_eq}$ (i.e., the complement of the equivalent duty-cycle D_{ph_eq} of signal $D_{LS,eq}$) can be computed as:

$$1 - D_{ph_eq} = \frac{T_{LS,1} + T_{LS,2}}{2 \cdot T_{SW}}$$

where $T_{LS,1}$ and $T_{LS,2}$ are the durations of the low-side pulses of converters 144a and 144b.

The equivalent low-side control signal $D_{LS,eq}$ may be produced by a circuit 120 as exemplified in FIG. 20. Circuit 120 comprises a D flip-flop (data flip-flop) 122 and a multiplexer 124. The D flip-flop receives the converter clock signal CLK at its clock input terminal. The inverted data output Q of the D flip-flop 122 is fed back to the data input D of the D flip-flop 122. The data output Q of the D flip-flop 122 is provided as a selection signal to the multiplexer 124. The multiplexer 124 receives as a first input signal the low-side control signal $D_{LS,1}$ and as a second input signal the low-side control signal $D_{LS,2}$. Therefore, the D flip-flop 122 may be configured to divide the clock frequency, while the multiplexer 124 may alternatively select and propagate to its output the control signals $D_{LS,1}$ and $D_{LS,2}$ to produce the equivalent control signal $D_{LS,eq}$.

FIG. 21 is a circuit block diagram exemplary of one or more embodiments of an inverting buck-boost converter 144 relying on the general principle discussed with reference to FIG. 18. In particular, the converter 144 exemplified in FIG. 21 includes an architecture that is configured to merge the currents I_{LX_1} and I_{LX_2} output by each phase 144a and 144b of the converter 144.

Therefore, the single-phase converters 144a and 144b exemplified in FIG. 21 differ from the single-phase converter exemplified in FIGS. 4 and 15 in that average value accumulation circuit blocks 90' are arranged upstream of the respective buffers 450. Therefore, in one or more embodiments as exemplified in FIG. 21, each single-phase converter 144a, 144b may comprise an average value accumu-

15

lation circuit block **90'** coupled between switch S3 and the non-inverting input of buffer **450**. The circuit block **90'** includes a switch **91'**, a resistor R_{90} and a capacitor C_{90} . Switch **91'** has a first terminal coupled to node **130** intermediate switch S3 and resistor R41, and a second terminal coupled to the non-inverting input terminal of buffer **450**, and is configured to receive control signal D_{HS} to be controlled thereby, i.e., the switching activity of switch **91'** is synchronized with the switching activity of the high-side switch S1. Resistor R_{90} has a first terminal coupled to the second terminal of switch **91'**, and a second terminal coupled to a first terminal of capacitor C_{90} . Capacitor C_{90} has a second terminal coupled to the input node **402** and forms an RC filter circuit with resistor R_{90} . In one or more embodiments as exemplified in FIG. **21**, thus, the sum of the average inductor currents is carried out by adding currents $\langle I_{LX_1} \rangle$ and $\langle I_{LX_2} \rangle$ at node **131** via resistor R_D and capacitor CD coupled between node **131** and ground node GND. Arranging the average value accumulation circuit blocks **90'** upstream of the buffers **450** allows replicating the instantaneous current I_{LX_i} during the converter high-side-on phase, while the average current keeps flowing during the converter high-side-off phase.

As a result, the voltage drop V_{RD} across resistor R_D (i.e., the voltage at node **131**) is indicative of the sum of the average inductor currents $\langle I_{LX_i} \rangle$:

$$V_{RD} = (I_{HS_1}(t) + I_{HS_2}(t)) \cdot R_{onHS} \cdot \frac{R_D}{R_{UP}}$$

As exemplified in FIG. **21**, the converter **144** may comprise a single time average circuit block **92'** coupled to node **131** and configured to produce a signal at node **132** that is indicative of the equivalent load current $I_{O_ph_eq}$. The circuit block **92'** includes a buffer circuit **134** (e.g., an amplifier such as an operational amplifier), a resistive feedback network including resistors RA and RB, a first switch **93'**, a second switch **94'**, a resistor R_{92} and a capacitor C_{92} . Buffer **134** has a first (e.g., non-inverting) input terminal coupled to node **131** and a second (e.g., inverting) input terminal coupled to the first terminal of resistor RB. Resistor RB has a second terminal coupled to ground node GND. Resistor RA has a first terminal coupled to the second input terminal of buffer **134** and a second terminal coupled to the output terminal of buffer **134**. Switch **93'** has a first terminal coupled to the output terminal of buffer **134** and a second terminal coupled to the first terminal of resistor R_{92} , and is configured to receive the control signal D_{LS_eq} to be controlled thereby. Switch **94'** has a first terminal coupled to the second terminal of switch **93'** and a second terminal coupled to ground node GND, and is configured to receive the complement of control signal D_{LS_eq} to be controlled thereby. Resistor R_{92} has a second terminal coupled to node **132**. Capacitor C_{92} is coupled between node **132** and ground node GND and forms an RC filter circuit with resistor R_{92} . As a result, voltage $V_{IO_ph_eq}$ at node **132** is indicative of the average load current I_O :

$$V_{IO_ph_eq} = V_{RD} \cdot \left(1 + \frac{RA}{RB}\right) \cdot \frac{T_{LS1} + T_{LS2}}{2 \cdot T_{SW}} \\ = (I_{HS_1}(t) + I_{HS_2}(t)) \cdot R_{onHS} \cdot \frac{R_D}{R_{UP}} \cdot$$

16

-continued

$$\left(1 + \frac{RA}{RB}\right) \cdot \frac{T_{LS1} + T_{LS2}}{2 \cdot T_{SW}} \\ = I_{O_ph_eq} \cdot R_{onHS} \cdot K \cdot \left(1 + \frac{RA}{RB}\right)$$

The cost (in terms of electrical components and thus silicon area) of the solution exemplified in FIG. **13** is three RC filters, four switches with independent control, and one buffer.

FIG. **22** is a time diagram exemplary of possible time evolution of the current signals I_{LX_1} , I_{LX_2} and I_{LX_eq} in one or more embodiments as exemplified in FIG. **21**.

FIG. **23** is another circuit block diagram exemplary of one or more embodiments of an inverting buck-boost converter **144** relying on the general principle discussed with reference to FIG. **18**. In particular, the converter **144** exemplified in FIG. **23** includes an architecture that is configured to merge the voltages $V_{902,1}$ and $V_{902,2}$ output by each sensing circuit of the phases **144a** and **144b** of the converter **144**.

Therefore, the single-phase converters **144a** and **144b** exemplified in FIG. **23** differ from the single-phase converter exemplified in FIGS. **4** and **15** in that they do not include respective time average circuit blocks **92**. A single time average circuit block **92"** is arranged downstream of an adder circuit **150**. Therefore, in the embodiments exemplified in FIG. **23**, each single-phase converter **144a**, **144b** may comprise a respective current sensing architecture substantially as disclosed with reference to FIG. **15**, except for the time average circuit block **92**.

As exemplified in FIG. **23**, the converter **144** may comprise an adder circuit **150** configured to sum the voltage signal $V_{902,1}$ at node **902₁** and the voltage signal $V_{902,2}$ at node **902₂**. The adder circuit **150** may comprise a first positive input terminal coupled to node **902₁**, a second positive input terminal coupled to node **902₂**, and a negative (feedback) input terminal coupled to a resistive feedback network. The feedback network may comprise a resistor RA' coupled between the negative input terminal and the output terminal **152** of the adder circuit **150**, and a resistor RB' coupled between the negative input terminal of the adder circuit **150** and ground node GND. Further details on possible implementations of the adder circuit **150** are discussed in the following, with reference to FIGS. **24** to **28**.

The converter **144** as exemplified in FIG. **23** may comprise a single time average circuit block **92"** coupled to node **152** and configured to produce a signal $V_{IO_ph_eq}$ at node **154** that is indicative of the equivalent load current $I_{O_ph_eq}$. The circuit block **92"** includes a first switch **93"**, a second switch **94"**, a resistor R_{92} and a capacitor C_{92} . Switch **93"** has a first terminal coupled to the output terminal **152** of adder **150** and a second terminal coupled to the first terminal of resistor R_{92} , and is configured to receive the control signal D_{LS_eq} to be controlled thereby. Switch **94"** has a first terminal coupled to the second terminal of switch **93"** and a second terminal coupled to ground node GND, and is configured to receive the complement of control signal D_{LS_eq} to be controlled thereby. Resistor R_{92} has a second terminal coupled to node **154**. Capacitor C_{92} is coupled between node **154** and ground node GND and forms an RC filter circuit with resistor R_{92} . As a result, voltage $V_{IO_ph_eq}$ at node **154** is indicative of the average load current I_O :

17

$$\begin{aligned}
V_{IO_ph_eq} &= (\langle I_{LX_1} \rangle + \langle I_{LX_2} \rangle) \cdot R_{onHS} \cdot \\
&\quad \frac{R_D}{R_{UP}} \cdot \left(1 + \frac{RA'}{RB'}\right) \cdot \frac{T_{LS,1} + T_{LS,2}}{2 \cdot T_{SW}} \\
&= \langle I_{LX_eq} \rangle \cdot R_{onHS} \cdot K \cdot \left(1 + \frac{RA'}{RB'}\right) \cdot \frac{T_{LS,1} + T_{LS,2}}{2 \cdot T_{SW}} \\
&= I_{O_ph_eq} \cdot R_{onHS} \cdot K \cdot \left(1 + \frac{RA'}{RB'}\right)
\end{aligned}$$

The cost (in terms of electrical components and thus silicon area) of the solution exemplified in FIG. 23 is three RC filters, four switches with independent control, and one buffer.

In one or more embodiments, the adder circuit 150 may include an analog adder circuit having an architecture based on the recognition that the middle point (or center point) of a resistive star configuration produces a voltage signal that is the average of the voltage signals applied to the vertices of the star configuration, provided that the resistors are matched (i.e., they have the same resistance value).

In one or more embodiments, an analog adder circuit may include one or more instances of a differential circuit 160 as exemplified in FIG. 24. Circuit 160 comprises a first current flow line arranged between a supply rail 161 (e.g., providing a supply voltage V_{DD}) and a first current output node 165. The first current flow line comprises a current source 162 (e.g., current generator) and a p-channel MOS transistor Q1 arranged between the supply rail 161 and the output node 165. Current source 162 is arranged between the supply rail 161 and node 163 and is configured to inject (e.g., source) current I into node 163. Transistor Q1 has a source terminal coupled to node 163, a drain terminal coupled to the output node 165, and a gate terminal coupled to an input node 164 to receive a first input signal V_p . Circuit 160 comprises a second current flow line arranged between the supply rail 161 and a second current output node 169. The second current flow line comprises a current source 166 (e.g., current generator) and a p-channel MOS transistor Q3 arranged between the supply rail 161 and the output node 169. Current source 166 is arranged between the supply rail 161 and node 167 and is configured to inject (e.g., source) current I into node 167. Transistor Q3 has a source terminal coupled to node 167, a drain terminal coupled to the output node 169, and a gate terminal coupled to an input node 168 to receive a second input signal V_n . A resistor R is arranged between nodes 163 and 167 (i.e., between the source terminals of transistors Q1 and Q3). ΔV being the voltage difference between nodes 163 and 167, a current $\Delta V/R$ flows through resistor R from node 163 to node 167 (i.e., it is sunk from node 163 and sourced to node 167). As a result, node 165 outputs a current equal to $I - \Delta V/R$ and node 169 outputs a current equal to $I + \Delta V/R$.

FIG. 25 is a circuit block diagram exemplary of a circuit 170 that produces an output signal V_O that is the average of two input signals V1 and V2. Circuit 170 includes two instances 160₁, 160₂ of the differential circuit 160 arranged as discussed in the following. The first differential circuit 160₁ is configured to receive the first input signal V1 at its input node 164₁, and the second differential circuit 160₂ is configured to receive the second input signal V2 at its input node 164₂. Nodes 168₁ and 168₂ of circuits 160₁ and 160₂ are connected one to the other and provide a common node 168' where the output (average) signal V_O is produced. Further, nodes 169₁ and 169₂ are connected to node 168'. R1 being the resistor coupled between the source terminals of

18

transistors Q1₁ and Q3₁ and VR1 the voltage drop across resistor R1, transistor Q1₁ outputs a current $I3 = I - VR1/R1$ and transistor Q3₁ outputs a current $I1 = I + VR1/R1$. Being R2 the resistor coupled between the source terminals of transistors Q1₂ and Q3₂ and VR2 the voltage drop across resistor R2, transistor Q1₂ outputs a current $I4 = I - VR2/R2$ and transistor Q3₂ outputs a current $I2 = I + VR2/R2$.

Circuit 170 further includes a first current mirror circuit arranged between nodes 165₁ and 169₁ and ground node GND. The first current mirror circuit is configured to sink from node 169₁ a current I3 equal to the current I3 output from node 165₁ of circuit 160₁. In particular, the first current mirror includes an n-channel MOS transistor Q2₁ and an n-channel MOS transistor Q4₁. Transistor Q2₁ is diode-connected and has a drain terminal coupled to node 165₁ and a source terminal coupled to ground node GND. Transistor Q4₁ has a drain terminal coupled to node 169₁ and a source terminal coupled to ground node GND. The gate terminals of transistors Q2₁ and Q4₁ are coupled one to the other.

Circuit 170 further includes a second current mirror circuit arranged between nodes 165₂ and 169₂ and ground node GND. The second current mirror circuit is configured to sink from node 169₂ a current I4 equal to the current I4 output from node 165₂ of circuit 160₂. In particular, the second current mirror includes an n-channel MOS transistor Q2₂ and an n-channel MOS transistor Q4₂. Transistor Q2₂ is diode-connected and has a drain terminal coupled to node 165₂ and a source terminal coupled to ground node GND. Transistor Q4₂ has a drain terminal coupled to node 169₂ and a source terminal coupled to ground node GND. The gate terminals of transistors Q2₂ and Q4₂ are coupled one to the other.

At node 168' the currents I1, I2, I3 and I4 are combined (e.g., added and subtracted) so that node 168' produces a voltage V_O that is the average value of V1 and V2. In particular, circuit 170 may force voltage $VR1 = (V1 - V_O + K1)$ across resistor R1, and voltage $VR2 = (V2 - V_O - K2)$ across resistor R2, where $K1 = VGS1 - VGS2$ and $K2 = VGS3 - VGS4$ ($VGS1$, $VGS2$, $VGS3$ and $VGS4$ being the gate-source voltages of transistors Q1₁, Q3₁, Q3₂ and Q1₂, respectively, as indicated in FIG. 17). The output voltage V_O is stable thanks to the current feedback in node 168'. The current condition in node 168' imposes $I1 + I2 = I3 + I4$, and the loops impose $I1 = I4$ and $I2 = I3$. Therefore, the following equations apply:

$$\begin{aligned}
I1 &= I + \frac{VR1}{R1} = I + \frac{V1 + VGS1 - V_O - VGS2}{R1} \\
I2 &= I + \frac{VR2}{R2} = I + \frac{V2 + VGS4 - V_O - VGS3}{R2} \\
I3 &= I - \frac{VR1}{R1} = I - \frac{V1 + VGS1 - V_O - VGS2}{R1} \\
I4 &= I - \frac{VR2}{R2} = I - \frac{V2 + VGS4 - V_O - VGS3}{R2}
\end{aligned}$$

Using the above identity $I1 + I2 = I3 + I4$, the current I can be removed from the equations above, since it is in common with all of them. The following equation thus applies:

$$\begin{aligned}
&\frac{V1 + VGS1 - V_O - VGS2}{R1} + \\
&\frac{V2 + VGS4 - V_O - VGS3}{R2} = - \frac{V1 + VGS1 - V_O - VGS2}{R1} -
\end{aligned}$$

19

-continued

$$\frac{V2 + VGS4 - V_O - VGS3}{R2}$$

which leads to:

$$R2 \cdot V1 + R2 \cdot VGS1 - R2 \cdot V_O - R2 \cdot VGS2 + R1 \cdot V2 + R1 \cdot VGS4 - R1 \cdot V_O - R1 \cdot VGS3 =$$

which in turn leads to:

$$V_O = R2 \cdot \frac{V1 + VGS1 - VGS2}{R1 + R2} + R1 \cdot \frac{V2 + VGS4 - VGS3}{R1 + R2}$$

Assuming that $R1=R2$, the following equation applies:

$$V_O = \frac{V1 + VGS1 - VGS2 + V2 + VGS4 - VGS3}{2} = \frac{V1 + V2 + \epsilon}{2}$$

where

$$\epsilon = VGS1 - VGS2 + VGS4 - VGS3$$

Since the matching of the parameters can be designed to minimize the difference ϵ (i.e., $\epsilon \approx 0$ V), the following equation may apply:

$$V_O = \frac{V1 + V2}{2}$$

Therefore, the voltage signal V_O at node **168'** may be equal to the average of voltage signals $V1$ and $V2$.

Since the average of two signals is a scaled sum, it is possible to implement an adder circuit by including a gain stage to apply a gain to signal V_O . However, the circuit **170** exemplified in FIG. **25** may not be suitable to implement such a gain stage, because it may not be capable to drive a low impedance load. For instance, if a resistor or a current generator (acting like a load) were to be connected to node **168'**, an offset in the current balance may be generated.

In order to provide the current needed to the load, a high impedance driver may be used. To this aim, an adder circuit architecture as exemplified in FIG. **26** may be resorted to. In particular, the architecture exemplified in FIG. **26** is advantageous insofar as it facilitates decoupling the dynamics of the current adder/subtractor nodes, thereby allowing for a gain stage to be applied to the output node.

In particular, the adder circuit **180** exemplified in FIG. **26** comprises two instances **160₁**, **160₂** of the differential circuit **160** arranged as discussed in the following. The first differential circuit **160₁** is configured to receive the first input signal $V1$ at its input node **164₁**, and the second differential circuit **160₂** is configured to receive the second input signal $V2$ at its input node **164₂**. Nodes **168₁** and **168₂** of circuits **160₁** and **160₂** are connected one to the other and provide a common node **168''** where the average signal $VFB = (V1 + V2)/2$ is produced. Node **165₁** outputs a current $I3 = I - \Delta V1/R$ and node **169₁** outputs a current $I1 = I + \Delta V1/R$, where $\Delta V1 = V1 - VFB$; node **165₂** outputs a current $I4 = I - \Delta V2/R$ and node **169₂** outputs a current $I2 = I + \Delta V2/R$, where $\Delta V2 = V2 - VFB$. It is supposed here that the resistors included in the circuits **160₁**, **160₂** have the same resistance value R , and that the gate-source voltages of the input transistors of circuits **160₁**, **160₂** are matched so that they can be neglected (i.e., $\epsilon \approx 0$ V). A first current adder node **182** is

20

configured to sum the currents $I1$ and $I2$ output from nodes **169₁** and **169₂**, thereby producing a current equal to $2I + (\Delta V1 + \Delta V2)/R$, and a second current adder node **184** is configured to sum the currents $I3$ and $I4$ output from nodes **165₁** and **165₂**, thereby producing a current equal to $2I - (\Delta V1 + \Delta V2)/R$. A current subtractor node **186** is configured to subtract the output current of adder node **184** from the output current of adder node **182**, thereby producing a current error signal I_{err} equal to $2 * (\Delta V1 + \Delta V2)/R = 2 * (V1 - VFB + V2 - VFB)/R$. The adder circuit **180** may further comprise an RC filter circuit coupled to the output of subtractor node **186**. The error current output from subtractor node **186** is forced to flow through the resistor of the RC filter and produces a voltage error signal. The adder circuit **180** may further comprise a buffer circuit coupled downstream of the RC filter to decouple the node dynamics, and a gain stage at the output of the buffer circuit (e.g., a voltage ladder coupled between the output of the buffer circuit and ground node GND) to add a gain factor to the average signal VFB to produce the output sum signal $VOUT$ at node **187**. The voltage error signal is thus buffered and amplified. In particular, still with reference to FIG. **26**, the following equations apply:

$$VOUT = 1 + \frac{R189}{R188} \cdot VFB$$

$$VFB = \frac{V1 + V2}{2}$$

In one or more embodiments where the feedback resistors $R188$ and $R189$ are equal ($R188 = R189$), the output signal $VOUT$ thus provides the sum of the input signals $V1$ and $V2$: $VOUT = V1 + V2$.

FIG. **27** is a circuit diagram exemplary of a possible implementation **180'** of the adder circuit **180** exemplified in FIG. **26**. In particular, FIG. **27** exemplifies an analog adder with class A output stage. The output nodes **165₁** and **165₂** of circuits **160₁** and **160₂** are connected together to implement the current adder node **184** (connection of node **165₂** to node **165₁** is not illustrated in FIG. **27** for the sake of ease of illustration). The output nodes **169₁** and **169₂** of circuits **160₁** and **160₂** are connected together to implement the current adder node **182**. Circuit **180'** further includes a first current mirror circuit arranged between nodes **184** and **191** and ground node GND. The first current mirror circuit is configured to sink from node **191** a current equal to the sum of currents $I3 + I4$ output from adder node **184**. In particular, the first current mirror includes an n-channel MOS transistor $Q5$ and an n-channel MOS transistor $Q6$. Transistor $Q5$ is diode-connected and has a drain terminal coupled to node **184** and a source terminal coupled to ground node GND. Transistor $Q6$ has a drain terminal coupled to node **191** and a source terminal coupled to ground node GND. The gate terminals of transistors $Q5$ and $Q6$ are connected one to the other (connection of such gate terminals is not illustrated in FIG. **27** for the sake of ease of illustration). Circuit **180'** further includes a second current mirror circuit arranged between nodes **182** and **192** and ground node GND. The second current mirror circuit is configured to sink from node **192** a current equal to the sum of currents $I1 + I2$ output from adder node **182**. In particular, the second current mirror includes an n-channel MOS transistor $Q7$ and an n-channel MOS transistor $Q8$. Transistor $Q7$ is diode-connected and has a drain terminal coupled to node **182** and a source terminal coupled to ground node GND. Transistor $Q8$ has a

21

drain terminal coupled to node **192** and a source terminal coupled to ground node GND. The gate terminals of transistors Q7 and Q8 are connected one to the other (connection of such gate terminals is not illustrated in FIG. 27 for the sake of ease of illustration). Node **191** is coupled to node **193** via an n-channel MOS transistor Q9 having a source terminal coupled to node **191** and a drain terminal coupled to node **193**, so that a current I3+I4 is sunk from node **193**. Node **192** is coupled to node **186** via an n-channel MOS transistor Q10 having a source terminal coupled to node **192** and a drain terminal coupled to node **186**, so that a current I1+I2 is sunk from node **186**. The gate terminals of transistors Q9 and Q10 are connected one to the other. A further current mirror circuit is arranged between nodes **193** and **186** and the supply rail **161**. The further current mirror circuit is configured to inject (e.g., source) into node **186** a current equal to the sum of currents I3+I4 sunk by transistor Q9. In particular, the further current mirror may include a simple current mirror or a cascode current mirror implemented with p-channel MOS transistors, as exemplified in FIG. 27. Node **186** thus produces an error signal indicative of the quantity I3+I4-I1-I2, which is propagated to the control (e.g., gate) terminal of a transistor Q11 arranged in the output gain stage of circuit **180'**. Particularly, the output stage includes a p-channel MOS transistor Q11 having a source terminal coupled to the supply rail **161**, a drain terminal coupled to the output node **187** and a gate terminal coupled to node **186**. The voltage ladder including resistors R188 and R189 and node **168"** is arranged as discussed with reference to FIG. 26.

FIG. 28 is a circuit diagram exemplary of a variant embodiment **180"** of the adder circuit **180** exemplified in FIG. 26. In particular, FIG. 28 exemplifies an analog adder with folded cascode structure and class A output stage. The output nodes **165₁** and **165₂** of circuits **160₁** and **160₂** are connected together to implement the current adder node **184** (connection of node **165₂** to node **165₁** is not illustrated in FIG. 28 for the sake of ease of illustration). The output nodes **169₁** and **169₂** of circuits **160₁** and **160₂** are connected together to implement the current adder node **182**. Circuit **180"** further includes a first current generator arranged between node **184** and ground node GND. The first current generator may include an n-channel MOS transistor Q5' having a drain terminal coupled to node **184**, a source terminal coupled to ground node GND and a gate terminal configured to receive a (fixed) biasing voltage VBN. Circuit **180"** further includes a second current generator arranged between node **182** and ground node GND. The second current generator may include an n-channel MOS transistor Q7' having a drain terminal coupled to node **182**, a source terminal coupled to ground node GND and a gate terminal configured to receive the biasing voltage VBN. Node **182** is directly connected to the source terminal of transistor Q9 and node **184** is directly connected to the source terminal of transistor Q10. It is noted that the current equation at node **184** is I3+I4+IQ10=IQ5 (that is, IQ10=IQ5-(I3+I4)) and the current equation at node **182** is I1+I2+IQ9=IQ7 (that is, IQ9=IQ7-(I1+I2)), where IQx indicates the current flowing through transistor x. The current equation at node **186** is IQ9=IQ10, thus IQ7-(I1+I2)=IQ5-(I3+I4). Due to the same biasing of Q5' and Q7', IQ7=IQ5 and thus I3+I4-I1-I2=0. Adder circuit **180"** advantageously improves the input dynamic range of signals V1 and V2, which can be as low as zero.

The circuits exemplified in FIGS. 27 and 28 have approximately the same size of a classical operational transconductance amplifier (OTA) and can be modified to sum more than

22

two signals, just by increasing the number of input stages **160** (i.e., the stages exemplified in FIG. 16) and adjusting the gain.

Therefore, one or more embodiments of the present disclosure provide circuits and methods for measuring the load current (e.g., AMOLED panel current) by sensing the current in the high-side switch S1 of the inverting buck-boost converter **144** (coupled to the negative rail **100b**), using a sample-and-hold circuit and a low-pass weighted filter. One or more embodiments result in improved accuracy at light load current, reduced silicon area and current consumption, reduced quiescent current consumption and/or improved efficiency at light load. Additionally, one or more embodiments can be easily integrated with a trimming for offset cancellation and for sensitivity.

One or more embodiments may thus provide one or more of the following advantages:

- low silicon area occupation, low quiescent current and high efficiency at light load, insofar as the load current measurement is based on a high-side replica circuit (switch S3) already present in the buck-boost converters **144a** and **144b** for loop control and overcurrent protection (OCP);

- improved accuracy, suitability to sense low output current values, and no need for extra circuitry, insofar as the load current is sensed at the inverting buck-boost converter **144** instead of being sensed at the converter **140**; and

- high accuracy/precision and possibility of being easily tuned, insofar as offset and/or sensitivity trimming can be added and tested at Automatic Test Equipment (ATE).

It is noted that one or more embodiments have been disclosed herein with particular reference to an inverting buck-boost converter, but various embodiments can be applied to any other topology of switching power converters, particularly in AMOLED products where ultra-low power consumption and high efficiency are desirable features.

More generally, one or more embodiments may provide a method to measure the relevant currents in a DC-DC converter (i.e., the currents flowing in the switches and in the inductor) by sensing the current of a single switch (e.g., the high-side switch).

Without prejudice to the underlying principles, the details and embodiments may vary, even significantly, with respect to what has been described by way of example, without departing from the extent of protection.

TABLE I

boost converter		
	Low-side sensing	High-side sensing
Switch 91 (signal D ₉₁)	T1	T2
Switch 93 (signal D ₉₃)	T2	T2
Switch 94 (signal D ₉₄)	TSW - T2	TSW - T2

TABLE II

buck-boost converter		
	High-side sensing	Low-side sensing
Switch 91 (signal D ₉₁)	T1	T2
Switch 93 (signal D ₉₃)	T2	T2
Switch 94 (signal D ₉₄)	TSW - T2	TSW - T2

23

TABLE III

buck converter		
	High-side sensing	Low-side sensing
Switch 91 (signal D ₉₁)	T1	T2
Switch 93 (signal D ₉₃)	TSW	TSW
Switch 94 (signal D ₉₄)	0	0

The invention claimed is:

1. An electronic device comprising a multiphase DC-DC switching converter circuit, the multiphase DC-DC switching converter circuit including:

a first DC-DC converter arrangement, including:

a first switching stage having a first switching node and a first converter output node, the first switching stage including a first high-side switch and a first low-side switch;

a first current sensing circuit configured to produce a first detection signal indicative of an instantaneous current flowing through one of said first high-side switch and said first low-side switch; and

a first time-averaging circuit configured to receive said first detection signal and produce, as a function thereof, a first time-averaged signal indicative of an average current flowing through said one of said first high-side switch and said first low-side switch during a respective switch conduction interval;

wherein said first current sensing circuit and said first time-averaging circuit are configured to produce said first time-averaged signal indicative, during said respective switch conduction interval, of the instantaneous current flowing through said one of said first high-side switch and said first low-side switch, and outside of said respective switch conduction interval, of the average current flowing through said one of said first high-side switch and said first low-side switch;

a second DC-DC converter arrangement, including:

a second switching stage having a second switching node and a second converter output node, the second switching stage including a second high-side switch and a second low-side switch;

a second current sensing circuit configured to produce a second detection signal indicative of an instantaneous current flowing through one of said second high-side switch and said second low-side switch; and

a second time-averaging circuit configured to receive said second detection signal and produce, as a function thereof, a second time-averaged signal indicative of an average current flowing through said one of said second high-side switch and said second low-side switch during a respective switch conduction interval;

wherein said second current sensing circuit and said second time-averaging circuit are configured to produce said second time-averaged signal indicative, during said respective switch conduction interval, of the instantaneous current flowing through said one of said second high-side switch and said second low-side switch, and outside of said respective switch conduction interval, of the average current flowing through said one of said second high-side switch and said second low-side switch; and

24

signal summation and re-scaling circuitry comprising:

a current adder circuit configured to produce a voltage signal indicative of a sum of said first and second time-averaged signals; and

a re-scaler circuit configured to re-scale said voltage signal by a factor equal to $(T_a + T_b)/(TSW_a + TSW_b)$, wherein T_a is a time period during which said first switching node is electrically coupled to said first converter output node, T_b is a time period during which said second switching node is electrically coupled to said second converter output node, TSW_a is a switching period of said first DC-DC converter arrangement, and TSW_b is a switching period of said second DC-DC converter arrangement to thereby produce an output signal indicative of an average output current of said multiphase DC-DC switching converter circuit.

2. The electronic device according to claim 1, wherein: said first high-side switch is arranged between an input node of said first DC-DC converter arrangement and said first switching node, and said first low-side switch is arranged between said first switching node and said first converter output node; and

said second high-side switch is arranged between an input node of said second DC-DC converter arrangement and said second switching node, and said second low-side switch is arranged between said second switching node and said second converter output node.

3. The electronic device according to claim 2, wherein each of said first and second current sensing circuits includes:

a respective replica high-side switch and a respective first resistor, the respective replica high-side switch having a first terminal coupled to the respective switching node and a second terminal coupled to a first terminal of said respective first resistor, the respective first resistor having a second terminal coupled to a respective one of the first and second input nodes, wherein a respective voltage signal indicative of a voltage across said respective high-side switch is produced at a node intermediate said respective replica high-side switch and said respective first resistor;

a respective second resistor, a respective transistor and a respective third resistor coupled in series between a respective one of the first and second input nodes and a ground node, the respective second resistor having a first terminal coupled to said respective input node and a second terminal coupled to a source terminal of said respective transistor, said respective transistor having a drain terminal coupled to a first terminal of said respective third resistor, and said respective third resistor having a second terminal coupled to said ground node; and

a respective buffer circuit configured to propagate said respective voltage signal indicative of the voltage across said respective high-side switch to a control terminal of said respective transistor.

4. The electronic device according to claim 1, wherein: said first current sensing circuit is configured to produce said first detection signal indicative of the instantaneous current flowing through said first high-side switch;

said second current sensing circuit is configured to produce said second detection signal indicative of the instantaneous current flowing through said second high-side switch;

said first time-averaging circuit is configured to produce said first time-averaged signal indicative of the average

25

current flowing through said first high-side switch during a respective high-side switch conduction interval; and

said second time-averaging circuit is configured to produce said second time-averaged signal indicative of the average current flowing through said second high-side switch during a respective high-side switch conduction interval.

5. The electronic device according to claim 1, wherein each of said first and second time-averaging circuits comprises a respective switch and a respective resistor arranged in series between an input node and an output node of the respective time-averaging circuit, and a respective capacitor arranged between the output node of the respective time-averaging circuit and a ground node, wherein the switch is driven to a conductive state during said respective switch conduction interval for that time-averaging circuit.

6. The electronic device according to claim 1, wherein said signal summation and re-scaling circuitry includes:

a first re-scaler circuit configured to receive said first time-averaged signal and re-scale said first time-averaged signal by a factor equal to T_a/TSW_a to produce a respective first output signal indicative of the average output current of said first DC-DC converter arrangement;

a second re-scaler circuit configured to receive said second time-averaged signal and re-scale said second time-averaged signal by a factor equal to T_b/TSW_b to produce a respective second output signal indicative of the average output current of said second DC-DC converter arrangement; and

an adder circuit configured to sum the output signal produced by said first re-scaler circuit and the output signal produced by said second re-scaler circuit to produce said output signal indicative of the average output current of said multiphase DC-DC switching converter circuit,

wherein said signal summation and re-scaling circuitry preferably includes a first buffer circuit arranged between said first re-scaler circuit and said adder circuit, and a second buffer circuit arranged between said second re-scaler circuit and said adder circuit.

7. The electronic device according to claim 6, wherein said first and second re-scaler circuits each include a respective first switch and a respective resistor arranged in series between an input node and an output node of the respective re-scaler circuit, a respective second switch arranged between a respective node intermediate the respective first switch and the respective resistor, and a respective capacitor arranged between the respective output node of the re-scaler circuit and a ground node, wherein the respective first switch is driven to a conductive state during a time period during which the respective switching node is electrically coupled to the respective converter output node, and the respective second switch is driven to a conductive state during complementary time periods with respect to said respective first switch.

8. The electronic device according to claim 1, wherein said re-scaler circuit includes a first switch and a resistor arranged in series between an input node and an output node of the re-scaler circuit, a second switch arranged between a node intermediate the first switch and the resistor, and a capacitor arranged between the output node of the re-scaler circuit and a ground node, wherein the first switch is driven to a conductive state during a time period during which first or second switching node is electrically coupled to the respective converter output node, and the second switch is

26

driven to a conductive state during complementary time periods with respect to said first switch.

9. The electronic device according to claim 1, further comprising a power management integrated circuit including a first DC-DC converter circuit configured to produce a positive supply voltage for a display panel, and a second DC-DC converter circuit comprising the multiphase DC-DC switching converter circuit, configured to produce a negative supply voltage for said display panel.

10. The electronic device according to claim 9, further comprising:

a display panel including light-emitting diodes arranged in a matrix, wherein a positive supply terminal of said display panel is coupled to said first DC-DC converter circuit to receive said positive supply voltage and a negative supply terminal of said display panel is coupled to said second DC-DC converter circuit to receive said negative supply voltage.

11. An electronic device comprising a multiphase DC-DC switching converter circuit, the multiphase DC-DC switching converter circuit including:

a first DC-DC converter arrangement, including:

a first switching stage having a first switching node and a first converter output node, the first switching stage including a first high-side switch and a first low-side switch;

a first current sensing circuit configured to produce a first detection signal indicative of an instantaneous current flowing through one of said first high-side switch and said first low-side switch; and

a first time-averaging circuit configured to receive said first detection signal and produce, as a function thereof, a first time-averaged signal indicative of an average current flowing through said one of said first high-side switch and said first low-side switch during a respective switch conduction interval;

a second DC-DC converter arrangement, including:

a second switching stage having a second switching node and a second converter output node, the second switching stage including a second high-side switch and a second low-side switch;

a second current sensing circuit configured to produce a second detection signal indicative of an instantaneous current flowing through one of said second high-side switch and said second low-side switch; and

a second time-averaging circuit configured to receive said second detection signal and produce, as a function thereof, a second time-averaged signal indicative of an average current flowing through said one of said second high-side switch and said second low-side switch during a respective switch conduction interval; and

signal summation and re-scaling circuitry comprising:

a voltage adder circuit configured to produce, at a respective output node, a voltage signal indicative of a sum of said first time-averaged signal and said second time-averaged signal;

a re-scaler circuit configured to re-scale said voltage signal by a factor equal to $(T_a+T_b)/(TSW_a+TSW_b)$, wherein T_a is a time period during which said first switching node is electrically coupled to said first converter output node, T_b is a time period during which said second switching node is electrically coupled to said second converter output node, TSW_a is a switching period of said first DC-DC converter arrangement, and TSW_b is a switching period of said

27

second DC-DC converter arrangement to thereby produce an output signal indicative of an average output current of said multiphase DC-DC switching converter circuit.

12. The electronic device according to claim 11, wherein said voltage adder circuit includes:

a first differential circuit having a first terminal configured to receive said first time-averaged signal produced by said first time-averaging circuit; and

a second differential circuit having a first terminal configured to receive said second time-averaged signal produced by said second time-averaging circuit;

wherein a second terminal of said first differential circuit and a second terminal of said second differential circuit are coupled together to produce an average signal that is an average of said first and second time-averaged signals;

wherein said average signal is passed to an intermediate node of a voltage divider to produce, at a positive node of said voltage divider, said voltage signal indicative of the sum of said first and second time-averaged signals; wherein said first differential circuit is configured to produce a first output current indicative of a difference between said first time-averaged signal and said average signal and a second output current indicative of a complement of the difference between said first time-averaged signal and said average signal;

wherein said second differential circuit is configured to produce a third output current indicative of a difference between said second time-averaged signal and said average signal and a fourth output current indicative of a complement of the difference between said second time-averaged signal and said average signal; and

wherein said voltage adder circuit further includes:

a first current adder node configured to sum said first output current and said third output current;

a second current adder node configured to sum said second output current and said fourth output current;

a third adder node configured to subtract a current output by said second current adder node from a current output by said first current adder node to produce an error signal; and

a buffer circuit configured to propagate said error signal to said positive node of said voltage divider.

13. The electronic device according to claim 11, wherein said re-scaler circuit includes a first switch and a resistor arranged in series between an input node and an output node of the re-scaler circuit, a second switch arranged between a node intermediate the first switch and the resistor, and a capacitor arranged between the output node of the re-scaler circuit and a ground node, wherein the first switch is driven to a conductive state during a time period during which first or second switching node is electrically coupled to the respective converter output node, and the second switch is driven to a conductive state during complementary time periods with respect to said first switch.

14. The electronic device according to claim 11, further comprising a power management integrated circuit including a first DC-DC converter circuit configured to produce a positive supply voltage for a display panel, and

a second DC-DC converter circuit comprising the multiphase DC-DC switching converter circuit, configured to produce a negative supply voltage for said display panel.

15. The electronic device according to claim 14, further comprising:

28

a display panel including light-emitting diodes arranged in a matrix, wherein a positive supply terminal of said display panel is coupled to said first DC-DC converter circuit to receive said positive supply voltage and a negative supply terminal of said display panel is coupled to said second DC-DC converter circuit to receive said negative supply voltage.

16. The electronic device according to claim 11, wherein: said first high-side switch is arranged between an input node of said first DC-DC converter arrangement and said first switching node, and said first low-side switch is arranged between said first switching node and said first converter output node; and

said second high-side switch is arranged between an input node of said second DC-DC converter arrangement and said second switching node, and said second low-side switch is arranged between said second switching node and said second converter output node.

17. The electronic device according to claim 16, wherein each of said first and second current sensing circuits includes:

a respective replica high-side switch and a respective first resistor, the respective replica high-side switch having a first terminal coupled to the respective switching node and a second terminal coupled to a first terminal of said respective first resistor, the respective first resistor having a second terminal coupled to a respective one of the first and second input nodes, wherein a respective voltage signal indicative of a voltage across said respective high-side switch is produced at a node intermediate said respective replica high-side switch and said respective first resistor;

a respective second resistor, a respective transistor and a respective third resistor coupled in series between a respective one of the first and second input nodes and a ground node, the respective second resistor having a first terminal coupled to said respective input node and a second terminal coupled to a source terminal of said respective transistor, said respective transistor having a drain terminal coupled to a first terminal of said respective third resistor, and said respective third resistor having a second terminal coupled to said ground node; and

a respective buffer circuit configured to propagate said respective voltage signal indicative of the voltage across said respective high-side switch to a control terminal of said respective transistor.

18. The electronic device according to claim 11, wherein: said first current sensing circuit is configured to produce said first detection signal indicative of the instantaneous current flowing through said first high-side switch;

said second current sensing circuit is configured to produce said second detection signal indicative of the instantaneous current flowing through said second high-side switch;

said first time-averaging circuit is configured to produce said first time-averaged signal indicative of the average current flowing through said first high-side switch during a respective high-side switch conduction interval; and

said second time-averaging circuit is configured to produce said second time-averaged signal indicative of the average current flowing through said second high-side switch during a respective high-side switch conduction interval.

29

19. The electronic device according to claim 11, wherein each of said first and second time-averaging circuits comprises a respective switch and a respective resistor arranged in series between an input node and an output node of the respective time-averaging circuit, and a respective capacitor
5 arranged between the output node of the respective time-averaging circuit and a ground node, wherein the switch is driven to a conductive state during said respective switch conduction interval for that time-averaging circuit.

20. An electronic device, comprising:

a multiphase DC-DC switching converter circuit with two converter arrangements, wherein each converter arrangement includes:

a switching stage with high-side and low-side switches;
a current sensing circuit for detecting instantaneous
15 current through the high-side switch or the low-side switch; and

a time-averaging circuit for producing averaged signals based on sensed current;

a current adder configured to sum the averaged signals;
20 and

a re-scaler circuit configured to rescale the sum to thereby produce an output signal representing an average output current of the multiphase DC-DC switching converter circuit.

21. The electronic device of claim 20, wherein the first and second high-side switches connect input nodes to respective switching nodes, and the first and second low-side switches connect corresponding respective switching nodes to converter output nodes.

30

22. The electronic device of claim 21, wherein each current sensing circuit includes:

a first resistor coupled to a corresponding one of the input nodes;

a replica high-side switch coupled between a corresponding one of the switching nodes and the first resistor;

a second resistor coupled to the corresponding one of the input nodes;

a third resistor coupled to ground; and

a transistor coupled between the second resistor and the third resistor;

wherein the replica high-side switch and resistors generate a voltage signal reflecting the voltage across the corresponding high-side switch, while a buffer circuit propagates the voltage signal to control the transistor.

23. The electronic device of claim 20, wherein the first and second current sensing circuits detect instantaneous currents through the first and second high-side switches, while the first and second time-averaging circuits produce signals indicative of average currents flowing through the respective high-side switches during conduction intervals.

24. The electronic device of claim 20, wherein the re-scaler circuit comprises first and second re-scaler circuits for re-scaling the averaged signals, an adder circuit to sum the re-scaled signals, and buffer circuits between the first and second re-scaler circuits and the adder circuit to produce an output signal representing the average output current of the multiphase DC-DC switching converter circuit.

* * * * *