

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12401396
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Zhang; Xiaobo

Method and device for multi-antenna transmission in UE and base station

Abstract

A method and a device for multi-antenna transmission in a user equipment and a base station are disclosed in the present disclosure. The user equipment first receives a first signaling, receives a first wireless signal, and transmits first information. K antenna port groups are used to transmit the first wireless signal. The first signaling is used to determine the K antenna port groups. The K antenna port groups respectively correspond to K channel quality values. K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values. The K1 is a positive integer less than or equal to the K. A first proportional sequence corresponds to a ratio(ratios) among the K1 channel quality values. The first information is used to determine the K1 antenna port groups and the first proportional sequence.

Inventors:	Zhang; Xiaobo (Shanghai, CN)
Applicant:	APEX BEAM TECHNOLOGIES LLC (Marshall, TX)
Family ID:	1000008781342
Assignee:	APEX BEAM TECHNOLOGIES LLC (N/A, N/A)
Appl. No.:	18/132467
Filed:	April 10, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240039583 A1	Feb. 01, 2024

Foreign Application Priority Data

CN	201611236923.2	Dec. 28, 2016
----	----------------	---------------

Related U.S. Application Data

continuation parent-doc US 17138945 20201231 US 11626904 child-doc US 18132467
continuation parent-doc US 16454075 20190627 US 10951271 child-doc US 17138945
continuation parent-doc WO PCT/CN2017/094209 20170725 PENDING child-doc US 16454075

Publication Classification

Int. Cl.: **H04B7/04** (20170101); **H04B7/0408** (20170101); **H04B7/0413** (20170101); **H04B7/06** (20060101); **H04W72/542** (20230101)

U.S. Cl.:

CPC **H04B7/0408** (20130101); **H04B7/0413** (20130101); **H04B7/0617** (20130101); **H04W72/542** (20230101);

Field of Classification Search

CPC: H04B (1/0064); H04B (7/024); H04B (7/04); H04B (7/0404); H04B (7/0408); H04B (7/0413); H04B (7/0452); H04B (7/0456); H04B (7/0491); H04B (7/0495); H04B (7/06); H04B (7/0617); H04B (7/0632); H04B (7/0695); H04B (7/086); H04B (7/088); H04L (5/001); H04L (5/0023); H04L (5/0048); H04L (5/0053); H04L (27/2602); H04W (24/02); H04W (52/40); H04W (72/085); H04W (72/23)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6185432	12/2000	Vembu	N/A	N/A
7945222	12/2010	Harel et al.	N/A	N/A
8027374	12/2010	Sun	N/A	N/A
8116693	12/2011	Harel	N/A	N/A
8654667	12/2013	Li	N/A	N/A
8953699	12/2014	Sayana	375/267	H04B 7/024
9131490	12/2014	Feng	N/A	N/A
9178583	12/2014	Nam	N/A	H04L 5/0023
9236992	12/2015	Chung	N/A	N/A
9264195	12/2015	Park	N/A	N/A
9294179	12/2015	Frank	N/A	H04B 7/0639
9294310	12/2015	Wu	N/A	N/A
9379788	12/2015	Clevorn	N/A	N/A
9380568	12/2015	Harrison	N/A	N/A
9425934	12/2015	Seo	N/A	N/A
9461727	12/2015	Xue	N/A	H04B 7/0479
9474063	12/2015	Han	N/A	N/A
9497750	12/2015	Li	N/A	N/A
9510335	12/2015	Ko	N/A	N/A
9520973	12/2015	Kim	N/A	N/A

9538516	12/2016	Seo	N/A	N/A
9572149	12/2016	Zhou	N/A	N/A
9603081	12/2016	Seo	N/A	N/A
9730200	12/2016	Qu	N/A	N/A
9787387	12/2016	Moon	N/A	N/A
9860033	12/2017	Kadous	N/A	N/A
9867176	12/2017	Li	N/A	N/A
9877312	12/2017	Kim	N/A	N/A
9882691	12/2017	Kang	N/A	N/A
9883503	12/2017	Seo	N/A	N/A
9900891	12/2017	Islam	N/A	N/A
9923613	12/2017	Lee	N/A	N/A
9955474	12/2017	Lee	N/A	N/A
10050758	12/2017	Seo	N/A	N/A
10148400	12/2017	Zhang	N/A	N/A
10171212	12/2018	Park	N/A	N/A
10181890	12/2018	Su	N/A	H04B 7/0658
10218461	12/2018	Wang	N/A	N/A
10236951	12/2018	Park	N/A	H04B 7/06
10298372	12/2018	Zhu	N/A	N/A
10299267	12/2018	Wang	N/A	N/A
10425139	12/2018	Guo	N/A	N/A
10432441	12/2018	Papasakellariou	N/A	N/A
10454555	12/2018	Kwak	N/A	N/A
10461994	12/2018	Liu	N/A	N/A
10506576	12/2018	John Wilson	N/A	N/A
10548129	12/2019	Fwu	N/A	N/A
10567057	12/2019	Park	N/A	N/A
10631291	12/2019	Lee	N/A	N/A
10637550	12/2019	Park	N/A	H04B 7/0628
10651901	12/2019	Park	N/A	H04B 7/0626
10700752	12/2019	Jung	N/A	N/A
10778303	12/2019	Kim	N/A	N/A
10779350	12/2019	Xia	N/A	N/A
10785747	12/2019	Kim	N/A	N/A
10790953	12/2019	Kim	N/A	N/A
10951271	12/2020	Zhang	N/A	N/A
10972974	12/2020	Xiong	N/A	N/A
11026217	12/2020	Chae	N/A	N/A
11044744	12/2020	Wang	N/A	N/A
11088747	12/2020	Islam	N/A	N/A
11088749	12/2020	Chang	N/A	N/A
11139933	12/2020	Xu	N/A	N/A
11159213	12/2020	Zhang	N/A	N/A
11223394	12/2021	Lee	N/A	N/A
11233557	12/2021	Lee	N/A	N/A
11265901	12/2021	Freda	N/A	N/A
11310764	12/2021	Kim	N/A	N/A
11419173	12/2021	Deenoo	N/A	N/A
11626904	12/2022	Zhang	N/A	N/A

2006/0164981	12/2005	Olsson	N/A	N/A
2010/0039970	12/2009	Papasakellariou	N/A	N/A
2010/0202382	12/2009	Park	N/A	N/A
2010/0202560	12/2009	Luo	N/A	N/A
2011/0038330	12/2010	Luo	N/A	N/A
2011/0096856	12/2010	Sadowsky	N/A	N/A
2011/0171212	12/2010	Belka	N/A	N/A
2011/0176519	12/2010	Vitthaladevuni	N/A	N/A
2011/0286420	12/2010	Cho	N/A	N/A
2011/0291891	12/2010	Nsenga	342/373	H04B 7/0617
2012/0122495	12/2011	Weng	N/A	N/A
2012/0257515	12/2011	Hugl	N/A	N/A
2012/0314711	12/2011	Trachewsky	N/A	N/A
2013/0083753	12/2012	Lee	N/A	N/A
2013/0148515	12/2012	Ribeiro	N/A	N/A
2013/0182594	12/2012	Kim	N/A	N/A
2013/0195067	12/2012	Khoshnevis	N/A	N/A
2013/0286960	12/2012	Li	N/A	N/A
2013/0301562	12/2012	Liao	N/A	N/A
2013/0308608	12/2012	Hu	N/A	N/A
2014/0036806	12/2013	Chen	N/A	N/A
2014/0140435	12/2013	Zhang	N/A	N/A
2014/0192917	12/2013	Nam	N/A	N/A
2014/0211656	12/2013	Hu	N/A	N/A
2015/0003343	12/2014	Li	N/A	N/A
2015/0009968	12/2014	Yu	N/A	N/A
2015/0036612	12/2014	Kim	N/A	N/A
2015/0055555	12/2014	Kim	N/A	N/A
2015/0063287	12/2014	Mazzarese	N/A	N/A
2015/0141026	12/2014	Jover	N/A	N/A
2015/0195025	12/2014	Kang	N/A	N/A
2015/0230102	12/2014	Kang	N/A	N/A
2015/0282070	12/2014	Salem	N/A	N/A
2015/0341093	12/2014	Ji	N/A	N/A
2015/0358060	12/2014	Park	N/A	N/A
2015/0358848	12/2014	Kim	N/A	N/A
2016/0080052	12/2015	Li	N/A	N/A
2016/0105265	12/2015	Wang	N/A	N/A
2016/0112099	12/2015	Lee	N/A	N/A
2016/0142189	12/2015	Shin	N/A	N/A
2016/0143055	12/2015	Nammi et al.	N/A	N/A
2016/0182137	12/2015	Onggosanusi	N/A	N/A
2016/0183228	12/2015	Song	N/A	N/A
2016/0211902	12/2015	Park	N/A	N/A
2016/0218778	12/2015	Ng et al.	N/A	N/A
2016/0277092	12/2015	Pi	N/A	N/A
2016/0323028	12/2015	Cheng	N/A	N/A
2017/0070277	12/2016	Si	N/A	N/A
2017/0085303	12/2016	Chen	N/A	N/A
2017/0086195	12/2016	Yum	N/A	N/A

2017/0094547	12/2016	Yum	N/A	N/A
2017/0150480	12/2016	Kim	N/A	N/A
2017/0207843	12/2016	Jung	N/A	N/A
2017/0215170	12/2016	Islam	N/A	N/A
2017/0230994	12/2016	You	N/A	N/A
2017/0237478	12/2016	Kwak	N/A	N/A
2017/0288743	12/2016	Nam	N/A	N/A
2017/0331670	12/2016	Parkvall	N/A	N/A
2017/0339667	12/2016	Shen	N/A	N/A
2017/0373743	12/2016	Park	N/A	N/A
2018/0007574	12/2017	Park	N/A	N/A
2018/0007673	12/2017	Fwu	N/A	N/A
2018/0034525	12/2017	Park	N/A	N/A
2018/0054290	12/2017	Park	N/A	N/A
2018/0054348	12/2017	Luo	N/A	N/A
2018/0054790	12/2017	Islam	N/A	N/A
2018/0054800	12/2017	Yeo	N/A	N/A
2018/0083680	12/2017	Guo	N/A	N/A
2018/0092139	12/2017	Novlan	N/A	N/A
2018/0098234	12/2017	Kim	N/A	N/A
2018/0110074	12/2017	Akkarakaran	N/A	N/A
2018/0192443	12/2017	Novlan	N/A	N/A
2018/0227156	12/2017	Papasakellariou	N/A	N/A
2018/0241454	12/2017	Lee	N/A	N/A
2018/0254867	12/2017	Kim	N/A	N/A
2018/0279229	12/2017	Dinan	N/A	N/A
2018/0294859	12/2017	Niu	N/A	N/A
2018/0310283	12/2017	Deenoo	N/A	N/A
2018/0310322	12/2017	Zhang	N/A	N/A
2018/0323842	12/2017	Majmundar	N/A	N/A
2018/0324780	12/2017	Novlan	N/A	N/A
2018/0324843	12/2017	Lee	N/A	N/A
2018/0324865	12/2017	Hui	N/A	N/A
2018/0332605	12/2017	Pelletier	N/A	N/A
2018/0367203	12/2017	Nilsson	N/A	N/A
2018/0367374	12/2017	Liu	N/A	N/A
2018/0368009	12/2017	Xia	N/A	N/A
2018/0375556	12/2017	Wang	N/A	N/A
2019/0028162	12/2018	Lee	N/A	N/A
2019/0052337	12/2018	Kwon	N/A	N/A
2019/0053294	12/2018	Xia	N/A	N/A
2019/0075582	12/2018	Kim	N/A	N/A
2019/0081688	12/2018	Deenoo	N/A	N/A
2019/0081832	12/2018	Marinier	N/A	N/A
2019/0116611	12/2018	Lee	N/A	N/A
2019/0182821	12/2018	You	N/A	N/A
2019/0182856	12/2018	Moroga	N/A	N/A
2019/0229777	12/2018	Guan	N/A	N/A
2019/0281639	12/2018	Yang	N/A	N/A
2019/0319686	12/2018	Chen	N/A	N/A

2019/0349915	12/2018	Ahn	N/A	N/A
2019/0387501	12/2018	Park	N/A	N/A
2020/0014453	12/2019	Takeda	N/A	N/A
2020/0022119	12/2019	Wang	N/A	N/A
2020/0028609	12/2019	Ahn	N/A	N/A
2020/0059958	12/2019	Chen	N/A	N/A
2020/0076492	12/2019	Wu	N/A	N/A
2020/0099437	12/2019	Harada	N/A	N/A
2020/0099499	12/2019	Yeo	N/A	N/A
2020/0186218	12/2019	Wu	N/A	N/A
2020/0374960	12/2019	Deenoo	N/A	N/A
2020/0389220	12/2019	Kang	N/A	N/A
2021/0204346	12/2020	Ye	N/A	N/A
2021/0235479	12/2020	Tang	N/A	N/A
2022/0061025	12/2021	Deng	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
102170335	12/2010	CN	N/A
103918195	12/2013	CN	N/A
104170272	12/2013	CN	N/A
104202073	12/2013	CN	N/A
104885499	12/2014	CN	N/A
105474556	12/2015	CN	N/A
105580468	12/2015	CN	N/A
106034360	12/2015	CN	N/A
106209195	12/2015	CN	N/A
106211338	12/2015	CN	N/A
108633047	12/2017	CN	N/A
108809488	12/2017	CN	N/A
110062398	12/2019	CN	N/A
2712228	12/2013	EP	N/A
2996378	12/2015	EP	N/A
20130130593	12/2012	KR	N/A
2014074894	12/2013	WO	N/A
2014158255	12/2013	WO	N/A
2014201638	12/2013	WO	N/A
2014201638	12/2013	WO	N/A
2015113664	12/2014	WO	N/A
2015131494	12/2014	WO	N/A
2015199414	12/2014	WO	N/A
2016015307	12/2015	WO	N/A
2016025899	12/2015	WO	N/A
2016047505	12/2015	WO	N/A
2016122232	12/2015	WO	N/A
2016072770	12/2015	WO	N/A
2016122257	12/2015	WO	N/A
2016126099	12/2015	WO	N/A
2016130175	12/2015	WO	N/A
2016136143	12/2015	WO	N/A

2017/023352	12/2016	WO	N/A
2017/024516	12/2016	WO	N/A
2017/026983	12/2016	WO	N/A
2017024566	12/2016	WO	N/A
2017/052199	12/2016	WO	N/A
2017/079530	12/2016	WO	N/A
2017/079574	12/2016	WO	N/A
2017/083489	12/2016	WO	N/A
2017/083514	12/2016	WO	N/A
2017/084235	12/2016	WO	N/A
2017/171398	12/2016	WO	N/A
2017/174469	12/2016	WO	N/A
2018/081913	12/2017	WO	N/A
2018/126401	12/2017	WO	N/A
2018/175809	12/2017	WO	N/A
2018/201861	12/2017	WO	N/A
2018/202178	12/2017	WO	N/A
2018/227464	12/2017	WO	N/A

OTHER PUBLICATIONS

3GPPTSG RAN WG1#87, "On Procedures for Beam Selection and Feedback Signalling," Nokia, Alcatel-Lucent Shanghai Bell, 2016, pp. 1-19. cited by applicant

3GPPTSG RAN WG1#86, "Overview on Beam Management," R1-1609080 Samsung, 2016, pp. 1-12. cited by applicant

3Gpptsrg RAN1 86b, "Beam Management for NR," R1-1610145 Qualcomm, Oct. 2016, pp. 1-12. cited by applicant

3GPPTSG RAN WG1#87, "QCL Assumptions Across Antenna Ports of a Same RS Type," R1-1612493 Sumsung, 2016, pp. 1-8. cited by applicant

3GPPTSG RAN1 86b, "Beam Management for NR," Qualcomm, R1-1612056 Nov. 2016, pp. 1-11. cited by applicant

3GPPTSG RAN WG1#86, "On Beam Management in NR—Procedures," R1-1610239 Nokia, Alcatel-Lucent Shanghai Bell, 2016, pp. 1-4. cited by applicant

3GPPTS 36.331, "3rd Generation Partnership Project; Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC); Protocol specification," Advanced LTE Pro, 2016, pp. 627. cited by applicant

ISR received in Application No. PCT/CN2017/094209 dated Oct. 23, 2017. cited by applicant

CN201910037365.4 Notification to Grant Patent Right for Invention dated May 19, 2020. cited by applicant

CN201910037365.4 1st Office Action dated Mar. 17, 2020. cited by applicant

CN201910037365.4 Second Office Action dated Apr. 14, 2020. cited by applicant

CN201611236923.2 Notification to Grant Paten Right for Invention dated Jan. 14, 2019. cited by applicant

CN201611236923.2 1st Office Action dated Dec. 10, 2018. cited by applicant

CN201611236923.2 First Search Report dated Nov. 30, 2018. cited by applicant

R1-1609080, Samsung, dated Oct. 10-14, 2016 (Meeting dates) Sep. 30, 2016 (Publication). cited by applicant

R1-1609414, Huawei, HiSilicon, dated Oct. 10-14, 2016 (Meeting dates) Oct. 1, 2016 (Publication). cited by applicant

R1-1609525, Intel Corporation, dated Oct. 10-14, 2016 (Meeting date) Oct. 1, 2016 (Publication). cited by applicant

R1-1609662, Nokia, Alcatel-Lucent Shanghai Bell, dated Oct. 10-14, 2016 (Meeting date) Sep. 30, 2016 (Publication). cited by applicant

R1-1609739, Nokia, Alcatel-Lucent Shanghai Bell, dated Oct. 10-14, 2016 (Meeting dates) Oct. 1, 2016 (Publication). cited by applicant

R1-1610145, Qualcomm, dated Oct. 10-14, 2016 (Meeting date) Oct. 1, 2016 (Publication). cited by applicant

R1-1610239, Nokia, Alcatel-Lucent Shanghai Bell, dated Oct. 10-14, 2016 (Meeting date) Sep. 30, 2016 (Publication). cited by applicant

R1-1611385, CATT, dated Nov. 14-18, 2016 (Meeting date) Nov. 5, 2016 (Publication). cited by applicant

R1-1611387, CATT, dated Nov. 14-18, 2016 (Meeting dates) Nov. 5, 2016 (Publication). cited by applicant

R1-1611415, ZTE, ZTE Microelectronics, dated Nov. 14-18, 2016 (Meeting date) Nov. 5, 2016 (Publication). cited by applicant

R1-1611417, ZTE, ZTE Microelectronics, dated Nov. 14-18, 2016 (Meeting date) Nov. 5, 2016 (Publication). cited by applicant

R1-1611421, ZTE, ZTE Microelectronics, dated Nov. 14-18, 2016 (Meeting date) Nov. 5, 2016 (Publication). cited by applicant

R1-1612015, Qualcomm, dated Nov. 14-18, 2016 (Meeting dates) Nov. 6, 2016 (Publication). cited by applicant

R1-1612056, Qualcomm, dated Nov. 14-18, 2016 (Meeting dates) Nov. 6, 2016 (Publication). cited by applicant

R1-1612190, CMCC, dated Nov. 14-18, 2016 (Meeting dates) Nov. 6, 2016 (Publication). cited by applicant

R1-1612493, Samsung, dated Nov. 14-18, 2016 (Meeting date) Nov. 4, 2016 (Publication). cited by applicant

R1-1612717, NTT DOCOMO, dated Nov. 14-18, 2016 (Meeting dates) Nov. 5, 2016 (Publication). cited by applicant

R1-1612862, Nokia, Alcatel-Lucent Shanghai Bell, dated Nov. 14-18, 2016 (Meeting date) Nov. 4, 2016 (Publication). cited by applicant

R1-1613589, Samsung, Ericsson, NTT DOCOMO, Intel, Verizon, KT, dated 14-18, 2016 (Meeting dates) Nov. 19, 2016 (Publication). cited by applicant

R1-1613716, ZTE, ZTE Microelectronics, dated Nov. 14-18, 2016 (Meeting date) Nov. 19, 2016 (Publication). cited by applicant

R1-164147, Intel Corporation, dated May 23-27, 2016 (Meeting dates) May 14, 2016 (Publication). cited by applicant

R1-166881, LG Electronics, dated Aug. 22-26, 2016 (Meeting dates) Aug. 13, 2016 (Publication). cited by applicant

R1-167028, KT Corp., dated Aug. 22-26, 2016 (Meeting dates) Aug. 12, 2016 (Publication). cited by applicant

R1-167287, Nokia, Alcatel-Lucent Shanghai Bell, dated Aug. 22-26, 2016 (Meeting dates) Aug. 12, 2016 (Publication). cited by applicant

R1-167520, Lenovo, dated Aug. 22-26, 2016 (Meeting dates) Aug. 12, 2016 (Publication). cited by applicant

R1-1700192, CATT, dated Jan. 16-20, 2017 (Meeting dates) Jan. 10, 2017 (Publication). cited by applicant

R1-1700539, Panasonic, Jan. 16-20, 2017 (Meeting dates) Jan. 10, 2017 (Publication). cited by applicant

R1-1700563, Guangdong OPPO Mobile Telecom, dated Jan. 16-20, 2017 (Meeting dates) Jan. 9, 2017 (Publication). cited by applicant

R1-1700703, InterDigital Communications, dated Jan. 16-20, 2017 (Meeting dates) Jan. 10, 2017 (Publication). cited by applicant

R1-1700771, Ericsson, dated Jan. 16-20, 2017 (Meeting dates) Jan. 10, 2017 (Publication). cited by applicant

R1-1701581, ZTE, ZTE Microelectronics, dated Jan. 13-17, 2017 (Meeting dates) Feb. 7, 2017 (Publication). cited by applicant

R1-1701979, NEC, dated Feb. 13-17, 2017 (Meeting date) Feb. 4, 2017 (Publication). cited by applicant

R1-1702676, Ericsson, dated Feb. 13-17, 2017 (Meeting dates) Feb. 7, 2017 (Publication). cited by applicant

R1-1704342, AT&T, dated Apr. 3-7, 2017 (Meeting dates) Mar. 25, 2017 (Publication). cited by applicant

R1-1704456, MediaTek Inc., dated Apr. 3-7, 2017 (Meeting dates) Mar. 25, 2017 (Publication). cited by applicant

R1-1704465, MediaTek Inc., dated Apr. 3-7, 2017 (Meeting dates) Mar. 25, 2017 (Publication). cited by applicant

R1-1704551, CATT, dated Apr. 3-7, 2017 (Meeting date) Mar. 25, 2017 (Publication). cited by applicant

R1-1704553, CATT, dated Apr. 3-7, 2017 (Meeting date) Mar. 25, 2017 (Publication). cited by applicant

R1-1704618, Guangdong OPPO Mobile Telecom, dated Apr. 3-7, 2017 (Meeting dates) Mar. 25, 2017 (Publication). cited by applicant

R1-1704867, LG Electronics, dated Apr. 3-7, 2017 (Meeting date) Mar. 25, 2017 (Publication). cited by applicant

R1-1705961, Nokia, Alcatel-Lucent Shanghai Bell, dated Apr. 3-7, 2017 (Meeting dates) Mar. 24, 2017 (Publication). cited by applicant

R1-1707475, CATT, dated May 15-19, 2017 (Meeting date) May 6, 2017 (Publication). cited by applicant

R1-1707782, Spreadtrum Communications, dated May 15-19, 2017 (Meeting dates) May 5, 2017 (Publication). cited by applicant

R1-1707830, MediaTek Inc., dated May 15-19, 2017 (Meeting dates) May 7, 2017 (Publication). cited by applicant

R1-1707832, MediaTek Inc., dated May 15-19, 2017 (Meeting dates) May 7, 2017 (Publication). cited by applicant

R1-1707954, Samsung, dated May 15-19, 2017 (Meeting dates) May 6, 2017 (Publication). cited by applicant

R1-1708135, Huawei, HiSilicon, dated May 15-19, 2017 (Meeting dates) May 6, 2017 (Publication). cited by applicant

R1-1708334, InterDigital, Inc., dated May 15-19, 2017 (Meeting dates) May 6, 2017 (Publication). cited by applicant

R1-1708336, InterDigital, Inc., dated May 15-19, 2017 (Meeting dates) May 6, 2017 (Publication). cited by applicant

R1-1710078, CATT, dated Jun. 27-30, 2017 (Meeting dates) Jun. 17, 2017 (Publication). cited by applicant

3G Evolution: HSPA and LTE for Mobile Broadband, 2007, Erik Dahlman, Stefan Parkvall, Johan Skold, Per Beming dated. cited by applicant

3GPP TR 25.892 version 6.0.0 release 6, Jun. 28, 2004, 3rd Generation Partnership Project (3GPP) 3rd Generation. cited by applicant

3GPP TR 36.873 version 12.2.0 release 12, Jul. 3, 2015, 3rd Generation Partnership Project (3GPP) 3rd Generation. cited by applicant

3GPP TR 36.897 version 13.0.0 release 13, Jul. 3, 2015 , 3rd Generation Partnership Project (3GPP) 3rd Generation. cited by applicant

3GPP TR 37.840 version 12.1.0 release 12, Jan. 6, 2014, 3rd Generation Partnership Project (3GPP) 3rd Generation. cited by applicant

3GPP TR 38.802 version 1.2.0 release 14, Mar. 1, 2017, 3rd Generation Partnership Project (3GPP) 3rd Generation. cited by applicant

3GPP TR 38.802 version 14.0.0 release 14, Mar. 25, 2017, 3rd Generation Partnership Project (3GPP) Author(s). cited by applicant

3GPP TS 36.133 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Sep. 9, 2015. cited by applicant

3GPP TS 36.133 version 13.2.0 release 13, 3rd Generation Partnership Project (3GPP), dated Jan. 8, 2016. cited by applicant

3GPP TS 36.211 version 12.3.0 release 12, 3rd Generation Partnership Project (3GPP), dated Oct. 2, 2014. cited by applicant

3GPP TS 36.211 version 12.5.0 release 12, 3rd Generation Partnership Project (3GPP), dated Mar. 16, 2015. cited by applicant

3GPP TS 36.211 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Jan. 26, 2016. cited by applicant

3GPP TS 36.211 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Jan. 6, 2016. cited by applicant

3GPP TS 36.211 version 13.2.0 release 13, 3rd Generation Partnership Project (3GPP), dated Aug. 24, 2016. cited by applicant

3GPP TS 36.211 version 14.2.0 release 14, 3rd Generation Partnership Project (3GPP), dated Apr. 18, 2017. cited by applicant

3GPP TS 36.211 version 8.9.0 release 8, 3rd Generation Partnership Project (3GPP), dated Dec. 9, 2009. cited by applicant

3GPP TS 36.211 version 11.3.0 release 11, 3rd Generation Partnership Project (3GPP), dated Jun. 26, 2013. cited by applicant

3GPP TS 36.211 version 13.0.0 release 13, 3rd Generation Partnership Project (3GPP), dated Jan. 5, 2016. cited by applicant

3GPP TS 36.212 version 12.2.0 release 12, 3rd Generation Partnership Project (3GPP), dated Sep. 23, 2014. cited by applicant

3GPP TS 36.212 version 12.2.0 release 12, 3rd Generation Partnership Project (3GPP), dated Oct. 2, 2014. cited by applicant

3GPP TS 36.212 version 12.4.0 release 12, 3rd Generation Partnership Project (3GPP), dated Mar. 18, 2015. cited by applicant

3GPP TS 36.212 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Mar. 27, 2016. cited by applicant

3GPP TS 36.212 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Apr. 22, 2016. cited by applicant

3GPP TS 36.212 version 13.0.0 release 13, 3rd Generation Partnership Project (3GPP), dated Jan. 5, 2016. cited by applicant

3GPP TS 36.212 version 13.3.0 release 13, 3rd Generation Partnership Project (3GPP), dated Sep. 29, 2016. cited by applicant

3GPP TS 36.212 version 14.2.0 release 14, 3rd Generation Partnership Project (3GPP), dated Apr. 11, 2017. cited by applicant

3GPP TS 36.213 version 12.11.0 release 12, 3rd Generation Partnership Project (3GPP), dated Sep. 29, 2016. cited by applicant

3GPP TS 36.213 version 12.3.0 release 12, 3rd Generation Partnership Project (3GPP), dated Oct. 2, 2014. cited by applicant

3GPP TS 36.213 version 12.8.0 release 12, Project (3GPP) ETSI publication of 3rd Generation, dated May 3, 2016. cited by applicant

3GPP TS 36.213 version 12.8.0 release 12 Annex A, 3rd Generation Partnership Project (3GPP), dated Jan. 6, 2016. cited by applicant

3GPP TS 36.213 version 12.8.0 release 12, Cover, 3rd Generation Partnership Project (3GPP), dated Jan. 6, 2016. cited by applicant

3GPP TS 36.213 version 12.8.0 release 12, Section 14, 3rd Generation Partnership Project (3GPP), dated Jan. 6, 2016. cited by applicant

3GPP TS 36.213 version 12.8.0 release 12, Sections 0-9, 3rd Generation Partnership Project (3GPP), dated Jan. 6, 2016. cited by applicant

3GPP TS 36.213 version 12.8.0 release 12, Sections 10-13, 3rd Generation Partnership Project (3GPP), dated Jan. 6, 2016. cited by applicant

3GPP TS 36.213 version 13.0.0 release 13, 3rd Generation Partnership Project (3GPP), dated Jan. 5, 2016. cited by applicant

3GPP TS 36.213 version 13.2.0 release 13, 3rd Generation Partnership Project (3GPP), dated Aug. 5, 2016. cited by applicant

3GPP TS 36.214 version 12.0.0 release 12, 3rd Generation Partnership Project (3GPP), dated Oct. 2, 2014. cited by applicant

3GPP TS 36.214 version 12.2.0 release 12, 3rd Generation Partnership Project (3GPP), dated Apr. 24, 2015. cited by applicant

3GPP TS 36.214 version 13.0.0 release 13, 3rd Generation Partnership Project (3GPP), dated Dec. 15, 2015. cited by applicant

3GPP TS 36.300 version 12.3.0 release 12, 3rd Generation Partnership Project (3GPP), dated Sep. 29, 2014. cited by applicant

3GPP TS 36.300 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Jan. 4, 2016. cited by applicant

3GPP TS 36.300 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Jan. 18, 2016. cited by applicant

3GPP TS 36.300 version 14.3.0 release 14, Project (3GPP) ETSI publication of 3rd Generation, dated Jul. 27, 2017. cited by applicant

3GPP TS 36.302 version 12.1.0 release 12, 3rd Generation Partnership Project (3GPP), dated Sep. 29, 2014. cited by applicant

3GPP TS 36.302 version 12.6.0 release 12, 3rd Generation Partnership Project (3GPP), dated Jan. 18, 2016. cited by applicant

3GPP TS 36.304 version 12.2.0 release 12, 3rd Generation Partnership Project (3GPP), dated Sep. 29, 2014. cited by applicant

3GPP TS 36.304 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Aug. 25, 2016. cited by applicant

3GPP TS 36.304 version 12.8.0 release 12, Project (3GPP) 3rd Generation Partnership, dated Jul. 1, 2016. cited by applicant

R1-1710596, Lenovo, Motorola Mobility, dated Jun. 27-30, 2017 (Meeting dates) Jun. 16, 2017 (Publication). cited by applicant

R1-1710810, MediaTek Inc., dated Jun. 27-30, 2017 (Meeting dates) Jun. 17, 2017 (Publication). cited by applicant

R1-1710871, InterDigital Inc., dated Jun. 20-27, 2017 (Meeting date) Jun. 16, 2017 (Publication). cited by applicant

R1-1711161, Qualcomm Incorporated, dated Jun. 27-30, 2017 (Meeting dates) Jun. 17, 2017 (Publication). cited by applicant

R2-1700902, Ericsson, dated Feb. 13-17, 2017 (Meeting date) Feb. 4, 2017 (Publication). cited by applicant

R2-1701727, Intel Corporation, dated Feb. 13-17, 2017 (Meeting date) Feb. 4, 2017 (Publication). cited by applicant

R2-1702662, Ericsson, dated Apr. 3-7, 2017 (Meeting dates) Mar. 25, 2017 (Publication). cited by applicant

R2-1703344, LG Electronics, dated Apr. 3-7, 2017 (Meeting date) Mar. 24, 2017 (Publication). cited by applicant

R2-1703561, Qualcomm Incorporated, dated Apr. 3-7, 2017 (Meeting dates) Mar. 25, 2017 (Publication). cited by applicant

R2-1706926, Qualcomm Incorporated, dated Jun. 27-29, 2017 (Meeting dates) Jun. 17, 2017 (Publication). cited by applicant

R4-161779, Qualcomm Incorporated, dated Apr. 11-15, 2016 (Meeting date) Apr. 26, 2016 (Publication). cited by applicant

SINR, RSRP, RSSI and RSRQ Measurements in Long Term Evolution Networks, Farhana Afroz, dated Aug. 2015. cited by applicant

Subcarrier Spacing—How to Make Use of This Degree of Freedom, Frank Schaich, dated Jul. 7, 2016. cited by applicant

Waveform and Numerology to Support 5G Services and Requirements, Ali A. Zaidi, dated Nov. 1, 2016. cited by applicant

Weight Control Scheme for MIMO System with Multiple Transmit and Receive Beamforming, Yoshitaka Hara, dated 2003. cited by applicant

R2-1701727, Intel Corporation, dated Feb. 4, 2017. cited by applicant

R1-1701979, NEC Corporation, Feb. 6, 2017. cited by applicant

R1-166881, LG Electronics, Aug. 13, 2016. cited by applicant

3GPP TR 38.802 V14.0.0 to Radio Access Technology, 3rd Generation Partnership Project, Mar. 2017. cited by applicant

R1-1701581, ZTE Corporation et al., Feb. 7, 2017. cited by applicant

R1-1708135, Huawei Technologies Co., Ltd et al., May 6, 2017. cited by applicant

R1-1704465, MediaTek Inc., Mar. 25, 2017. cited by applicant

R1-1707782, Spreadtrum Communications, May 5, 2017. cited by applicant

R1-1705961, Nokia Corporation et al., Mar. 24, 2017. cited by applicant

R1-1707475, China Academy of Telecommunications Technology (CATT), May 6, 2017. cited by applicant

R1-1700539, Panasonic, Jan. 10, 2017. cited by applicant

R1-1704618, Guangdong OPPO Mobile Telecom, Mar. 25, 2017. cited by applicant

R1-1707830, MediaTek Inc., May 7, 2017. cited by applicant

R1-1708334, InterDigital, Inc., May 6, 2017. cited by applicant

3GPP TS 36.211 version 14.2.0 Release 14 (“TS 36.211”), 3rd Generation Partnership Project (3GPP), Apr. 2017. cited by applicant

3GPP TS 36.212 version 14.2.0 Release 14 (“TS 36.212”), 3rd Generation Partnership Project (3GPP), Apr. 2017. cited by applicant

3GPP TS 36.306 version 14.2.0 Release 14 (“TS 36.306”), 3rd Generation Partnership Project (3GPP), Apr. 2017. cited by applicant

3GPP TS 36.331 version 13.5.0 Release 13 (“TS 36.331”), 3rd Generation Partnership Project (3GPP), Apr. 2017. cited by applicant

3G Evolution: HSPA and LTE for Mobile Broadband (“Dahlman 2007”), Dahlman et al., 2007. cited by applicant

4G: LTE / LTE-Advanced for Mobile Broadband (“Dahlman 2011”), Dahlman et al., 2011. cited by applicant

R1-1611421, ZTE, ZTE Microelectronics, Nov. 5, 2016. cited by applicant

R1-1613589, Samsung, Ericsson, NTT DOCOMO, Intel, Verizon, KT, Nov. 19, 2016. cited by

applicant
R1-1612190, China Mobile Communications Corporation (CMCC), Nov. 5, 2016. cited by applicant
R1-1609080, Samsung, Sep. 30, 2016. cited by applicant
R1-1702676, Ericsson, Feb. 7, 2017. cited by applicant
R1-1704456, MediaTek Inc., Mar. 25, 2017. cited by applicant
R1-1704551, China Academy of Telecommunications Technology (CATT), Mar. 25, 2017. cited by applicant
R1-1613716, ZTE, ZTE Microelectronics, Nov. 19, 2016. cited by applicant
R1-1707954, Samsung, May 6, 2017. cited by applicant
R1-1710871, InterDigital Inc., Jun. 16, 2017. cited by applicant
R1-151535, LG Electronics, Apr. 11, 2015. cited by applicant
R1-153175, Ericsson, May 16, 2015. cited by applicant
R1-154127, Samsung, Aug. 14, 2015. cited by applicant
R1-1609525, Intel Corporation, Oct. 1, 2016. cited by applicant
R1-1610145, Qualcomm, Oct. 1, 2016. cited by applicant
R1-1610239, Nokia, Alcatel-Lucent Shanghai Bell, Sep. 30, 2016. cited by applicant
R1-1611385, China Academy of Telecommunications Technology (CATT), Nov. 5, 2016. cited by applicant
R1-1611415, ZTE, ZTE Microelectronics, Nov. 5, 2016. cited by applicant
R1-1611417, ZTE, ZTE Microelectronics, Nov. 5, 2016. cited by applicant
R1-1612056, Qualcomm, Nov. 5, 2016. cited by applicant
R1-1612493, Samsung, Nov. 4, 2016. cited by applicant
R1-1612862, Nokia, Alcatel-Lucent Shanghai Bell, Nov. 4, 2016. cited by applicant
R4-161779, Qualcomm Incorporated, Apr. 26, 2016. cited by applicant
3GPP TR 36.897 V13.0.0 Release 13, 3rd Generation Partnership Project (3GPP), Jun. 2015. cited by applicant
R1-1704867, LG Electronics, Mar. 25, 2017. cited by applicant
R1-1609662, Nokia, Alcatel-Lucent Shanghai Bell, Sep. 30, 2016. cited by applicant
R2-1703344, LG Electronics, Mar. 24, 2017. cited by applicant
3GPP R1-1704398, Apr. 7, 2017. cited by applicant
3GPP R1-1704877, Apr. 7, 2017. cited by applicant
R1-1609256, Oct. 14, 2016. cited by applicant
Apex Beam Technologies LLC v. Oneplus Technology (Shenzhen) Co., Ltd., Defendant's Invalidity Contentions, Case No. 2:22-cv-00032-JRG, Nov. 21, 2022. cited by applicant
Apex Beam Technologies LLC v. Samsung Electronics Co., Ltd., et al., Defendant's Invalidity Contentions, Case No. 2:22-cv-00188-JRG, Mar. 2, 2023. cited by applicant
Apex Beam Technologies LLC v. ZTE Corporation, Defendant's Invalidity Contentions, Case No. 2:22-cv-00031-JRG-RSP, Mar. 2, 2023. cited by applicant
Apex Beam Technologies LLC v. TCT Mobile International Limited, Defendants' Initial Invalidity Contentions, Docket No. 2:21-cv-00438-JRG, Nov. 9, 2023. cited by applicant
Declaration of Apostolos K. Kakaes, Ph.D. (“Kakaes”), Mar. 28, 2023. cited by applicant
3GPP TS 36.133 v13.2.0 (“Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Requirements for support of radio resource management (Release 13)”) (Jan. 2016). cited by applicant
3GPP TS 36.211 v13.0.0 (“Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Physical channels and modulation (Release 13)”) (Dec. 2015). cited by applicant
3GPP TS 36.212 v13.0.0 (“Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Multiplexing and channel coding (Release 13)”)

(Dec. 2015). cited by applicant
3GPP TS 36.213 v13.0.0 (“Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer procedures (Release 13)”) (Dec. 2015). cited by applicant
3GPP TS 36.214 v13.0.0 (“Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Physical layer; Measurements (Release 13)”) (Dec. 2015). cited by applicant
3GPP TS 36.331 v13.0.0 (“Technical Specification Group Radio Access Network; Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC); Protocol specification (Release 13)”) (Dec. 2015). cited by applicant
3GPP Declaration of Friedhelm Rodermund, Feb. 15, 2023. cited by applicant
Farhana Afroz et al., SINR, RSRP, RSSI and RSRQ Measurements in Long Term Evolution Networks, International Journal of Wireless & Mobile Networks (IJWMN), vol. 7, No. 4, pp. 113-123 (Aug. 2015) (“Afroz”). cited by applicant
Samsung Electronics Co., LTD v. Apex Beam Technologies LLC, Petition for Inter Partes Review, Case No. IPR2023-00747, Mar. 29, 2023. cited by applicant
Samsung Electronics Co., LTD v. Apex Beam Technologies LLC, Petition for Inter Partes Review, Case No. IPR2023-00571, Mar. 29, 2023. cited by applicant
3GPP TS 36.304 version 14.0.0 release 14, 3rd Generation Partnership Project (3GPP), dated Oct. 3, 2016. cited by applicant
3GPP TS 36.304 version 9.1.0 Release 9, 3rd Generation Partnership Project (3GPP), dated Feb. 9, 2010. cited by applicant
3GPP TS 36.306 version 14.2.0 release 14, 3rd Generation Partnership Project (3GPP), dated Apr. 11, 2017. cited by applicant
3GPP TS 36.321 version 12.3.0 release 12, 3rd Generation Partnership Project (3GPP), dated Oct. 28, 2014. cited by applicant
3GPP TS 36.321 version 12.6.0 release 12, 3rd Generation Partnership Project (3GPP), dated Jun. 30, 2015. cited by applicant
3GPP TS 36.321 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Jan. 4, 2016. cited by applicant
3GPP TS 36.321 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Jan. 18, 2016. cited by applicant
3GPP TS 36.321 version 14.3.0 release 14, Project (3GPP) ETSI publication of 3rd Generation, dated Jul. 27, 2017. cited by applicant
3GPP TS 36.331 version 12.3.0 release 12, 3rd Generation Partnership Project (3GPP), dated Sep. 29, 2014. cited by applicant
3GPP TS 36.331 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Jan. 18, 2016. cited by applicant
3GPP TS 36.331 version 13.0.0 release 13, 3rd Generation Partnership Project (3GPP), dated Jan. 6, 2016. cited by applicant
3GPP TS 36.331 version 13.3.0 release 13, 3rd Generation Partnership Project (3GPP), dated Oct. 3, 2016. cited by applicant
3GPP TS 36.331 version 13.5.0 release 13, 3rd Generation Partnership Project (3GPP), dated Apr. 11, 2017. cited by applicant
3GPP TS 38.212 version 15.2.0 release 15, 3rd Generation Partnership Project (3GPP), dated Jun. 29, 2018. cited by applicant
3GPP TS 38.214 version 15.2.0 release 15, 3rd Generation Partnership Project (3GPP), dated Jun. 29, 2018. cited by applicant
3GPP TS 38.306 version 15.5.0 release 15, 3rd Generation Partnership Project (3GPP), dated Apr. 11, 2019. cited by applicant

3GPP TS 36.304 version 13.0.0 release 13, 3rd Generation Partnership Project (3GPP), dated Feb. 2, 2016. cited by applicant

3GPP TS 36.331 version 12.8.0 release 12, 3rd Generation Partnership Project (3GPP), dated Jan. 4, 2016. cited by applicant

4G LTE/LTE Advanced for Mobile Broadband, Erik Dahlman, dated 2011. cited by applicant

4G LTE/LTE Advanced for Mobile Broadband, Erik Dahlman, dated 2014. cited by applicant

1st 5G Algorithm Innovation Competition—Filtered-OFDM, Terasic Inc., dated 2015. cited by applicant

A Comparison of Symbol-wise and Self-contained Frame Structure for 5G Services, Mohamed Ibrahim, dated 2016. cited by applicant

Accurate Determination of Transport Block Size for 5G New Radio, Hao Wu, dated Apr. 30, 2020. cited by applicant

An Enhanced Multiantenna Solution through Beamforming to 3G Long-term Evolution, Ken Long, dated 2009. cited by applicant

Antenna Grouping based Feedback Compression for FDD-based Massive MIMO Systems, Byungju Lee, dated Jul. 21, 2015. cited by applicant

Antenna Grouping Techniques for MIMO Beamforming Systems, Kyungchul Kim, dated 2008. cited by applicant

Beam Selection Strategies for Orthogonal Random Beamforming in Sparse Networks, Jose Lopez Vicario, dated Sep. 2008. cited by applicant

Comparison Between Bit Error Rate And Signal To Noise Ratio in OFDM Using LSE Algorithm, Raghav Pandey, dated 2013. cited by applicant

Delay-Prioritized Scheduling (DPS) for Real Time Traffic in 3GPP LTE System, 2010 Kumbesan Sandrasegaran, dated Apr. 2010. cited by applicant

Dynamic TDD in LTE Small Cells, Jussi Kerttula, dated 2016. cited by applicant

Enabling Massive IoT in 5G and Beyond Systems: PHY Radio Frame Design Considerations, Ayesha Ijaz, dated Jun. 24, 2016. cited by applicant

Enhanced Beam Selection for Multiuser MM-Wave massive MIMO Systems, Jiaxuan Chen, dated Jul. 7, 2016. cited by applicant

Filtered-OFDM: Foundational Waveform for Selfadaptive Air Interface, Terasic Inc., dated 2015. cited by applicant

Joint Transmitter- Receiver Beamforming Over Space-Time Fading Channels, T. Zhang, A. Manikas, dated 2007. cited by applicant

LTE—The UMTS Long Term Evolution from Theory to Practice, Second Edition, Stefania Sesia, dated 2011. cited by applicant

Millimeter Wave Communications for Future Mobile Networks, Ming Xiao, dated May 17, 2017. cited by applicant

MIMO Beamforming for High-Bit-Rate Transmission over Frequency-Selective Fading Channels, Huy Hoang Pham, dated 2004. cited by applicant

Multibeam Selection for Indoor MIMO Systems: Two Cases of Study, Luis Gurrieri, dated Apr. 2007. cited by applicant

Overview of Full- Dimension MIMO in LTE-Advanced Pro, Hyounghu Ji, dated Aug. 10, 2016. cited by applicant

Overview of Narrowband IoT in LTE Rel-13, Rapeepat Ratasuk, dated 2016. cited by applicant

Novel OFDM transmission scheme to overcome caused by multipath delay longer than cyclic prefix, Chiwoo Lim, dated 2005. cited by applicant

R1-130140, ZTE, dated Jan. 28-Feb. 1, 2013 (Meeting dates) Jan. 19, 2013 (Publication). cited by applicant

R1-130269, LG Electronics, dated Jan. 28-Feb. 1, 2013 (Meeting dates) Jan. 18, 2013 (Publication). cited by applicant

R1-144047, LG Electronics, dated Oct. 6-10, 2014 (Meeting dates) Sep. 27, 2014 (Publication). cited by applicant
R1-150779, LG Electronics, ETRI, InterDigital, Qualcomm, Sony Cooperation, dated Feb. 9-13, 2015 (Meeting dates) Feb. 19, 2015 (Publication). cited by applicant
R1-151365, CATT, dated Apr. 20-24, 2015 (Meeting dates) Apr. 11, 2015 (Publication). cited by applicant
R1-151535, LG Electronics, dated Apr. 20-24, 2015 (Meeting date) Apr. 11, 2015 (Publication). cited by applicant
R1-153175, Ericsson, dated May 25-29, 2015 (Meeting date) May 16, 2015 (Publication). cited by applicant
R1-154127, Samsung, dated Aug. 24-28, 2015 (Meeting date) Aug. 14, 2015 (Publication). cited by applicant
R1-1608671, ZTE, ZTE Microelectronics, dated Oct. 10-14, 2016 (Meeting dates) Oct. 1, 2016 (Publication). cited by applicant
Petition for Inter Partes Review of U.S. Pat. No. 11,951,271, Control No. IPR2025-00898, dated May 1, 2025. cited by applicant
Petition for Inter Partes Review of U.S. Pat. No. 10,951,271, Control No. IPR2025-00922, dated May 1, 2025. cited by applicant
Petition for Inter Partes Review of U.S. Pat. No. 11,626,904, Control No. IPR2025-00904, dated May 2, 2025. cited by applicant
Petition for Inter Partes Review of U.S. Pat. No. 11,626,904, Control No. IPR2025-00923, dated May 2, 2025. cited by applicant
Declaration of Dr. Robert Akl for IPR Case IPR2025-00898, dated May 1, 2025. cited by applicant
Original complaint filed in *Apex Beam Technologies LLC v. Apple Inc.*, Case No. 6-24-cv-00223 (WDTX) (Apr. 29, 2024). cited by applicant
Amended Complaint filed in *Apex Beam Technologies LLC v. Apple Inc.*, Case No. 6-24-cv-00223-ADA-DIG (WDTX) (May 2, 2024). cited by applicant
Proof of Service of Amended Complaint in *Apex Beam Technologies LLC v. Apple Inc.*, Case No. 6-24-cv-00223-ADA-DIG (WDTX) (May 14, 2024). cited by applicant
Samsung Electronics Co., Ltd., and Samsung Electronics America, INC.v. Apex Beam Technologies LLC, IPR2023-00571, Institution Decision, entered Nov. 13, 2023. cited by applicant
Samsung Electronics Co., Ltd., and Samsung Electronics America, INC.v. Apex Beam Technologies LLC, IPR2023-00747, Institution Decision, entered Nov. 13, 2023. cited by applicant

Primary Examiner: Duong; Frank

Attorney, Agent or Firm: Zhong Law, LLC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION (1) This application is a continuation of the U.S. application Ser. No. 17/138,945, filed on Dec. 31, 2020, which is a continuation of the U.S. application Ser. No. 16/454,075, filed on Jun. 27, 2019, which is a continuation of International Application No. PCT/CN2017/094209, filed Jul. 25, 2017, claiming the priority benefit of Chinese Patent Application Serial Number 201611236923.2, filed on Dec. 28, 2016, the full disclosure of which is incorporated herein by reference.

BACKGROUND

Technical Field

(1) The present disclosure relates to a scheme for multi-antenna transmission in a wireless communication system.

Related Art

(2) Massive Multiple-Input Multiple-Output (MIMO) has become a research hotspot for next-generation mobile communications. In massive MIMO, multiple antennas can improve communication quality by forming narrower beams pointing in a specific direction through beamforming. Massive MIMO can also form different directions through multiple antennas for serving multiple users to improve the throughput of massive MIMO systems and reduce transmission delay.

(3) According to the discussion of 3rd Generation Partner Project (3GPP) Radio Access Network 1 (RAN1), a hybrid beamforming in combination of analog beamforming and digital precoding has become an important research topic for New Radio Technology (NR) systems.

SUMMARY

(4) Through research, the inventors found that in a massive MIMO system, the base station can perform beam scanning over a period of time resources. The UE selects and reports the beam. However, due to the limitation of air interface resources, the number of beams used for beam scanning and the number of beams reported by the UE are limited. In addition, due to the uncertainty of the UE location, the beam used for beam scanning does not necessarily include the beam that best serves the UE. How to use the information reported by the UE to form the best beam to serve the UE service is an urgent problem to be solved.

(5) In view of the above problem, the present disclosure provides a solution. It should be noted that, in the case of no conflict, the embodiments in the user equipment (UE) and the features in the embodiments of the present disclosure can be applied to the base station, and vice versa. Further, in case of no conflicts, the embodiments of the present disclosure and the features of the embodiments may be arbitrarily combined with each other.

(6) The present disclosure provides a method for multi-antenna transmission in a user equipment (UE), including: receiving a first signaling; receiving a first wireless signal; and transmitting first information; wherein, K antenna port groups are used to transmit the first wireless signal; the first signaling is used to determine the K antenna port groups; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; K_1 antenna port groups of the K antenna port groups correspond to K_1 channel quality values of the K channel quality values; the K_1 is a positive integer less than or equal to the K ; a first proportional sequence corresponds to a ratio(ratios) among the K_1 channel quality values; the first information is used to determine {the K_1 antenna port groups, the first proportional sequence}; the first signaling is used to determine a target threshold; the target threshold is a non-negative real number; a first channel quality is a best channel quality value among the K_1 channel quality values; a second channel quality is a worse channel quality value among the K_1 channel quality values; a ratio between the second channel quality and the first channel quality is greater than or equal to the target threshold.

(7) In the embodiment, the advantage of the foregoing method is that the base station may obtain a proportional relationship among reception qualities corresponding to multiple beams, and may generate a more accurate serving beam for the UE according to the proportional relationship, thereby improving transmission quality.

(8) In one embodiment, the beams and the serving beam are analog beams.

(9) In one embodiment, the antenna port is formed by superimposing multiple physical antennas through antenna virtualization. A mapping coefficient of the antenna port to the plurality of physical antennas constitutes a beamforming vector for the antenna virtualization to form a beam.

(10) In one embodiment, the antenna virtualization includes analog beamforming and digital beamforming. The analog beamforming is a mapping of an RF link output to the plurality of physical antennas and is used to form an analog beam. The digital beamforming is a mapping of the

antenna port to the RF link and is used to form a digital beam.

(11) In one embodiment, the beamforming vector is a product of an analog beamforming matrix and a digital beamforming vector. The analog beamforming matrix is composed of one or more analog beamforming vectors.

(12) In one embodiment, the beamforming vector is a Kronecker product of an analog beamforming vector and a digital beamforming vector.

(13) In one embodiment, the antenna virtualization only includes analog beamforming.

(14) In one embodiment, the antenna port group is composed of one antenna port.

(15) In one embodiment, the antenna port group is composed of a plurality of antenna ports.

(16) In one embodiment, the same analog beamforming vectors and different digital beamforming vectors are used for antenna virtualization of different antenna ports within the antenna port group.

(17) In one embodiment, the K antenna port groups include two antenna port groups, and the numbers of the antenna ports included in the two antenna port groups are different.

(18) In one embodiment, the antenna port corresponds to a reference signal. The reference signal is transmitted through the antenna port.

(19) In one embodiment, the reference signal is a reference symbol.

(20) In one embodiment, the reference signal includes a plurality of reference symbols. One reference symbol occupies one Resource Element (RE).

(21) In one embodiment, the reference signal is a Synchronization Signal (SS).

(22) In one embodiment, the reference signal is a Primary Synchronization Signal (PSS).

(23) In one embodiment, the reference signal is a Secondary Synchronization Signal (SSS).

(24) In one embodiment, the reference signal is a Channel State Information Reference Signal (CSI-RS).

(25) In one embodiment, the reference signal is a Demodulation Reference Signal (DMRS).

(26) In one embodiment, the reference signal is a DMRS of a Physical Broadcast Channel (PBCH).

(27) In one embodiment, the reference signal is a DMRS of a Physical Downlink Shared Channel (PDSCH).

(28) In one embodiment, the first wireless signal is a plurality of multi-carrier symbols.

(29) In one embodiment, the first wireless signal is an SS burst. The SS burst includes a plurality of SS blocks. The SS blocks include at least one synchronization signal.

(30) In one embodiment, the first wireless signal is an CSI-RS burst.

(31) In one embodiment, the first wireless signal is one beam sweep. The beam scanning is an operation of covering a spatial area by a transmitted or received beam in a predetermined manner over a period of time.

(32) In one embodiment, the K antenna port groups respectively correspond to K reference signal groups. The K reference signal groups are respectively transmitted through the K antenna port groups. The first wireless signal is composed of the K reference signal groups.

(33) In one embodiment, K different analog beamforming vectors are used for analog beamforming of the K antenna port groups.

(34) In one embodiment, the time-frequency pattern and the Orthogonal Cover Code (OCC) of at least two reference signals of the K reference signal groups are the same in one time unit. The two reference signals are transmitted on different time resources.

(35) In one embodiment, the time unit is a symbol.

(36) In one embodiment, the time unit is a time slot.

(37) In one embodiment, the time unit is a subframe.

(38) In one embodiment, the time unit is a short Transmission Time Interval (sTTI).

(39) In one embodiment, the first signaling explicitly indicates the K antenna port groups.

(40) In one embodiment, the first signaling implicitly indicates the K antenna port groups.

(41) In one embodiment, the first signaling is higher layer signaling.

(42) In one embodiment, the first signaling is a Radio Resource Control (RRC) signaling.

- (43) In one embodiment, the first signaling is a MAC layer signaling.
- (44) In one embodiment, the first signaling is a MAC Control Element (MAC CE).
- (45) In one embodiment, the first signaling is a physical layer signaling.
- (46) In one embodiment, the first signaling is carried by a Physical Downlink Control Channel (PDCCH).
- (47) In one embodiment, the first signaling is Downlink Control Information (DCI).
- (48) In one embodiment, the first signaling is common to the cell.
- (49) In one embodiment, the first signaling is UE-specific.
- (50) In one embodiment, the first signaling is UE group specific.
- (51) In one embodiment, the channel quality value is one of instantaneous Reference Signal Received Power (RSRP), long-term RSRP, SINR or SNR.
- (52) In one embodiment, the K channel quality values are wideband channel quality values.
- (53) In one embodiment, the first information explicitly indicates the K1 antenna port groups.
- (54) In one embodiment, the first information implicitly indicates the K1 antenna port groups.
- (55) In one embodiment, the first information explicitly indicates the first proportional sequence.
- (56) In one embodiment, the first information implicitly indicates the first proportional sequence.
- (57) In one embodiment, the first information is carried by a Physical Uplink Shared Channel (PUSCH).
- (58) In one embodiment, the first information is carried by a Physical Uplink Control Channel (PUCCH).
- (59) In one embodiment, the first information is transmitted in a CSI report.
- (60) In one embodiment, the first information is transmitted in a plurality of messages.
- (61) In one embodiment, a bitmap is used to determine the K1 antenna port groups.
- (62) In one embodiment, the K1 antenna port groups correspond to the same receiving beamforming vector.
- (63) In one embodiment, the receiving beamforming vector is an analog receiving beamforming vector.
- (64) In one embodiment, the K antenna port groups are represented by a bit string of length K, the bit position corresponding to the K1 antenna port groups is 1, and the other bit positions are 0.
- (65) In one embodiment, the K1 is greater than 1.
- (66) In one embodiment, the K1 is equal to 1.
- (67) In one embodiment, the first proportional sequence includes K1-1 positive real number(s). The K1-1 positive real numbers is(are) a ratio(s) between the channel quality values other than the best channel quality value of the K1 channel quality values and the best channel quality value.
- (68) In one embodiment, the first proportional sequence is composed of quantized values corresponding to the K1-1 positive real number(s).
- (69) In one embodiment, when the K1 is equal to 1, the first proportional sequence is determined to be absent.
- (70) In one embodiment, the first proportional sequence is composed of K1 positive real numbers. The K1 positive real numbers are respectively ratios between the K1 channel quality values and the best channel quality value of the K1 channel quality values.
- (71) In one embodiment, the first proportional sequence is composed of quantized values corresponding to the K1 positive real numbers.
- (72) In one embodiment, the first proportional sequence is composed of K1 positive real numbers less than or equal to 1, and the first proportional sequence includes at least one 1.
- (73) In one embodiment, the K1 beamforming vectors and the first proportional sequence respectively corresponding to the K1 antenna port groups are used to generate a service beam for data transmission with the UE.
- (74) In one embodiment, the transmitter of the first wireless signal determines a correspondence between a service beam related to a relative position of the UE and a collection of the K1 antenna

ports and the first proportional sequence according to the coverage space, and then determines the service beam according to the K1 antenna ports and the first proportional sequence reported by the UE.

(75) In one embodiment, the first antenna port group and the second antenna port group are two antenna port groups of the K1 antenna port groups, and the K1 is equal to 2. A first beamforming vector is used for beamforming of the first antenna port group, and a second beamforming vector is used for beamforming of the second antenna port group. The first proportional sequence is composed of a first element and a second element, wherein the first element corresponds to the first antenna port group, and the second element corresponds to the second antenna port group. The first element is equal to 1, the second element is equal to a , and the a is a positive real number less than 1.

(76) In one embodiment, a transmitter of the first wireless signal uses the first element and the second element to respectively weight the direction corresponding to the first beamforming vector and the direction corresponding to the second beamforming vector so as to obtain a direction corresponding to the service beam.

(77) In one embodiment, a correspondence table is stored in the transmitter of the first wireless signal. The correspondence table is used to determine a correspondence between a serving beam of the UE and a collection of the K1 antenna ports and the first proportional sequence. The transmitter of the first wireless signal retrieves the correspondence table according to the first antenna port group, the second antenna port group and the first proportional sequence to obtain an analog beam direction for communication with the UE.

(78) In one embodiment, the K1 beamforming vectors and the first proportional sequence respectively corresponding to the K1 antenna port groups are used to generate a signal for the next beam scanning. The variables of the generation function of the plurality of beamforming vectors used by the signal are the K1 beamforming vectors and the first proportional sequence.

(79) In one embodiment, a center of the coverage space of the plurality of beamforming vectors is determined by the K1 antenna port groups and the first proportional sequence.

(80) In one embodiment, the K channel quality values are wideband channel quality values.

(81) In one embodiment, the first proportional sequence comprises K1 positive real numbers less than or equal to 1, and the first proportional sequence comprises at least one 1; or the first proportional sequence comprises quantized values corresponding to K1 positive real numbers; or the first proportional sequence includes K1-1 positive real number(s), and the K1-1 positive real numbers is(are) a ratio(ratios) between the channel quality values other than the best channel quality value among the K1 channel quality values and the best channel quality value; or the first proportional sequence comprises a quantized value(s) corresponding to K1-1 positive real number(s).

(82) In one embodiment, K2 antenna port groups in the K antenna port groups correspond to K2 channel quality values in the K channel quality values; the K2 is a positive integer less than or equal to the K; a second proportional sequence corresponds to a ratio among the K2 channel quality values; a first receiving beamforming vector is used to receive signals transmitted through the K1 antenna port groups; a second receiving beamforming vector is used to receive signals transmitted through the K2 antenna port groups; the first receiving beamforming vector and the second receive beamforming vector are different; the first information is further used to determine the K2 antenna port groups and the second proportional sequence.

(83) In the embodiments, the above methods have the advantages that multiple candidate service beams are generated for different receive beamforming vectors through different beamforming vectors and different proportional sequences of different antenna port groups respectively, thereby increasing the transmission diversity effects.

(84) In one embodiment, the antenna ports in the K1 antenna port groups and the antenna ports in the K2 antenna port groups do not overlap.

(85) In one embodiment, the K1 antenna port groups, and the first proportional sequence are used to generate a first transmitting beamforming vector, while the K2 antenna port groups and the second proportional sequence are used to generate a second transmitting beamforming vector. The first transmitting beamforming vector and the first receiving beamforming vector are used for beamforming of data transmission over a first time window; the second transmitting beamforming vector and the second receiving beamforming vector are used for beamforming of data transmission over a second time window. The first time window and the second time window are orthogonal in time domain.

(86) In one embodiment, the first target channel quality is a function of the K1 channel quality values and the second target channel quality is a function of the K2 channel quality values. The first transmitting beamforming vector is used preferentially when the first target channel quality is higher than the second target channel quality.

(87) In one embodiment, the first target channel quality and the second target channel quality are respectively a weighted average of the K1 channel quality values and the K2 channel quality values. The first proportional sequence and the second proportional sequence are used for the weighted average respectively.

(88) In one embodiment, the first target channel quality and the second target channel quality are respectively an average of the K1 channel quality values and the K2 channel quality values.

(89) In one embodiment, the transmitting beamforming vector and the receiving beamforming vector are analog beamforming vectors.

(90) In one embodiment, any two antenna port groups in the K1 antenna port groups are co-located or quasi-co-located (QCL), and any two antenna port groups in the K2 antenna port groups are co-located or quasi-co-located (QCL); or any two antenna port groups in the K1 antenna port groups are on a same carrier, and any two antenna port groups in the K2 antenna port groups are on a same carrier.

(91) In the embodiments, an advantage of the above method is that the base station can utilize the first proportional sequence more efficiently by using the K1 antenna port groups to indicate the co-located (quasi-co-located) or co-carrier antenna ports.

(92) In one embodiment, the first signaling is used to determine the co-located or QCL information.

(93) In one embodiment, the first signaling explicitly indicates the co-located or QCL information.

(94) In one embodiment, the first signaling implicitly indicates the co-located or QCL information.

(95) In one embodiment, the first signaling is used to determine information of the co-carrier.

(96) In one embodiment, the first signaling explicitly indicates the information of the co-carrier.

(97) In one embodiment, the first signaling implicitly indicates the information of the co-carrier.

(98) In one embodiment, the first signaling is also used to determine at least the last one of the K1, the K2 and the target threshold. A third channel quality is a best channel quality value of the K2 channel quality values. A fourth channel quality is the worst channel quality value of the K2 channel quality values. The ratio between the fourth channel quality and the third channel quality is greater than or equal to the target threshold.

(99) In the embodiments, the advantage of the above method is that the target threshold can be used to control the reporting overhead, thereby improving the reporting efficiency.

(100) In one embodiment, the unit of the target threshold is dB.

(101) In one embodiment, the first signaling explicitly indicates at least the last of the K1, the K2 and the target threshold.

(102) In one embodiment, the first signaling implicitly indicates at least the last of the K1, the K2 and the target threshold.

(103) In one embodiment, the first signaling is transmitted in a plurality of messages.

(104) In one embodiment, the first information is further used to determine at least one of the first channel quality or the third channel quality.

(105) In the embodiments, the advantage of the above method is that the base station may

approximately recover the K1 channel qualities (the K2 channel qualities) by using the first channel quality (the third channel quality) and the first proportional sequence (the second proportional sequence), thereby improving flexibility for beam generation and scheduling.

(106) In one embodiment, the first information is transmitted in a plurality of messages.

(107) In one embodiment, the portion of the first information used to determine the first channel quality (the third channel quality) is transmitted in a measurement report; the portion of the first information used to determine the K1 antenna port groups, and the first proportional sequence (the K2 antenna port groups and the second proportional sequence) is transmitted in a CSI report.

(108) In one embodiment, the method for multi-antenna transmission in a UE further comprises: receiving a second wireless signal; wherein a target antenna port group is used to transmit the second wireless signal; the target antenna port group is associated with the K1 antenna port groups and the first proportional sequence, or the target antenna port group is associated with the K2 antenna port groups and the second proportional sequence.

(109) In the embodiment, the above method has the advantages that the beamforming vector corresponding to the K1 antenna port groups and the first proportional sequence, or the beamforming vector corresponding to the K2 antenna port groups and the second proportional sequence are used for beamforming of the second wireless signal to increase beamforming gain acting on the second wireless signal.

(110) In one embodiment, the transmitting beamforming vector corresponding to the K1 antenna port groups is used to generate a transmitting beamforming vector of the second wireless signal.

(111) In one embodiment, the transmitting beamforming vector corresponding to the K2 antenna port groups is used to generate a transmitting beamforming vector of the second wireless signal.

(112) In one embodiment, when the transmitting beamforming vector corresponding to the K1 antenna port groups is used to generate a transmitting beamforming vector of the second wireless signal, the first receiving beamforming vector is used to receive the second a wireless signal; when the transmitting beamforming vector corresponding to the K2 antenna port groups is used to generate a transmit beamforming vector of the second wireless signal, the second receiving beamforming vector is used for receive the he second wireless signal.

(113) In one embodiment, the transmitting beamforming vector and the receiving beamforming vector are analog beamforming vectors.

(114) In one embodiment, the second wireless signal is a signal carried by a PDCCH.

(115) In one embodiment, the second wireless signal is a signal carried by a PDSCH.

(116) In one embodiment, the second wireless signal is a reference signal.

(117) The present disclosure provides a method for multi-antenna transmission in a base station, including: transmitting a first signaling; transmitting a first wireless signal; and receiving first information; wherein, K antenna port groups are used to transmit the first wireless signal; the first signaling is used to determine the K antenna port groups; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values; the K1 is a positive integer less than or equal to the K; a first proportional sequence corresponds to a ratio(ratios) among the K1 channel quality values; the first information is used to determine the K1 antenna port groups and the first proportional sequence; the first signaling is used to determine a target threshold; the target threshold is a non-negative real number; a first channel quality is a best channel quality value among the K1 channel quality values; a second channel quality is a worse channel quality value among the K1 channel quality values; a ratio between the second channel quality and the first channel quality is greater than or equal to the target threshold.

(118) In one embodiment, the K1 beamforming vectors and the first proportional sequence respectively corresponding to the K1 antenna port groups are used to generate a service beam for data transmission with the UE.

(119) In one embodiment, the base determines a correspondence between a service beam related to a relative position of the UE and the collection of the K1 antenna ports and the first proportional sequence according to the coverage space, and then determines the service beam according to the K1 antenna ports and the first proportional sequence reported by the UE.

(120) In one embodiment, a correspondence table is stored in the base station. The correspondence table is used to determine a correspondence between a service beam of the UE and the collection of the K1 antenna ports and the first proportional sequence. The base station retrieves the correspondence table according to the first antenna port group, the second antenna port group and the first proportional sequence to obtain an analog beam direction for communication with the UE.

(121) In one embodiment, the K1 beamforming vectors and the first proportional sequence respectively corresponding to the K1 antenna port groups are used to generate a signal for the next beam scanning. The variables of the generation function of the plurality of beamforming vectors used by the signal are the K1 beamforming vectors and the first proportional sequence.

(122) In one embodiment, a center of the coverage space of the plurality of beamforming vectors is determined by the K1 antenna port groups and the first proportional sequence.

(123) In one embodiment, the K channel quality values are wideband channel quality values.

(124) In one embodiment, the first proportional sequence comprises K1 positive real numbers less than or equal to 1, and the first proportional sequence comprises at least one 1; or the first proportional sequence comprises quantized values corresponding to K1 positive real numbers; Or the first proportional sequence includes K1-1 positive real number(s), and the K1-1 positive real numbers is(are) a ratio(ratios) between the channel quality values other than the best channel quality value among the K1 channel quality values and the best channel quality value; or the first proportional sequence comprises a quantized value(s) corresponding to K1-1 positive real number(s).

(125) In one embodiment, K2 antenna port groups in the K antenna port groups correspond to K2 channel quality values in the K channel quality values; the K2 is a positive integer less than or equal to the K; a second proportional sequence corresponds to a ratio among the K2 channel quality values; a first receiving beamforming vector is used to receive signals transmitted through the K1 antenna port groups; a second receiving beamforming vector is used to receive signals transmitted through the K2 antenna port groups; the first receiving beamforming vector and the second receive beamforming vector are different; the first information is further used to determine the K2 antenna port groups and the second proportional sequence.

(126) In one embodiment, the first information is further used by the base station to determine the first receive beamforming vector and the second receive beamforming vector.

(127) In one embodiment, the first information explicitly indicates the first receive beamforming vector and the second receive beamforming vector.

(128) In one embodiment, the first information implicitly indicates the first receive beamforming vector and the second receive beamforming vector.

(129) In one embodiment, any two antenna port groups in the K1 antenna port groups are co-located or quasi-co-located (QCL), and any two antenna port groups in the K2 antenna port groups are co-located or quasi-co-located (QCL); or any two antenna port groups in the K1 antenna port groups are on a same carrier, and any two antenna port groups in the K2 antenna port groups are on a same carrier.

(130) In one embodiment, the base station generates a service beam by using a co-located (quasi-co-located) or a co-carrier beamforming vector and its corresponding proportional sequence.

(131) In one embodiment, the first signaling is further used to determine at least the last one of the K1, the K2, or the target threshold. A third channel quality is a best channel quality value among the K2 channel quality values. A fourth channel quality is a worse channel quality value among the K2 channel quality values. A ratio between the fourth channel quality and the third channel quality is greater than or equal to the target threshold

(132) In one embodiment, the base station controls reporting overhead by K1, the K2, and the target threshold.

(133) In one embodiment, the first information is further used to determine at least one of the first channel quality or the third channel quality.

(134) In one embodiment, the base station approximately recovers the K1 channel quality values in combination with the first channel quality, the K1 antenna port groups and the first proportional sequence for multi-user MIMO scheduling.

(135) In one embodiment, the base station approximately recovers the K2 channel quality values in combination with the third channel quality, the K2 antenna port groups and the second proportional sequence for multi-user MIMO scheduling.

(136) In one embodiment, the method for multi-antenna transmission in a base station further includes: transmitting a second wireless signal; wherein a target antenna port group is used to transmit the second wireless signal; the target antenna port group is associated with the K1 antenna port groups and, or the target antenna port group is associated with the K2 antenna port groups and the second proportional sequence.

(137) In one embodiment, the K1 beamforming vectors and corresponding to the K1 antenna port groups are used to generate a target beamforming vector. The target beamforming vector is used for beamforming of the target antenna port group.

(138) In one embodiment, the K2 beamforming vectors and corresponding to the K2 antenna port groups are used to generate a target beamforming vector. The target beamforming vector is used for beamforming of the target antenna port group.

(139) The present disclosure provides a user equipment (UE) for multi-antenna transmission, including: a first receiver, receiving a first signaling; a second receiver, receiving a first wireless signal; and a third transmitter, transmitting first information; wherein, K antenna port groups are used to transmit the first wireless signal; the first signaling is used to determine the K antenna port groups; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values; the K1 is a positive integer less than or equal to the K; a first proportional sequence corresponds to a ratio(ratios) among the K1 channel quality values; the first information is used to determine the K1 antenna port groups and; the first signaling is used to determine a target threshold; the target threshold is a non-negative real number; a first channel quality is a best channel quality value among the K1 channel quality values; a second channel quality is a worse channel quality value among the K1 channel quality values; a ratio between the second channel quality and the first channel quality is greater than or equal to the target threshold.

(140) In one embodiment of the above user equipment, the K channel quality values are broadband channel quality values.

(141) In one embodiment of the above user equipment, includes K1 positive real numbers less than or equal to 1, and comprises at least one 1; or the first proportional sequence comprises quantized values corresponding to K1 positive real numbers; the first proportional sequence comprises K1-1 positive real numbers, and the K1-1 positive real numbers is(are) a ratio(ratios) between the channel quality values other than the best channel quality value among the K1 channel quality values and the best channel quality value; or the first proportional sequence comprises a quantized value(s) corresponding to K1-1 positive real number(s).

(142) In one embodiment, K2 antenna port groups in the K antenna port groups correspond to K2 channel quality values in the K channel quality values; the K2 is a positive integer less than or equal to the K; a second proportional sequence corresponds to a ratio among the K2 channel quality values; a first receiving beamforming vector is used to receive signals transmitted through the K1 antenna port groups; a second receiving beamforming vector is used to receive signals transmitted through the K2 antenna port groups; the first receiving beamforming vector and the second

receiving beamforming vector are different; the first information is further used to determine the K2 antenna port groups and the second proportional sequence.

(143) In one embodiment of the above user equipment, any two antenna port groups in the K1 antenna port groups are co-located or quasi-co-located (QCL), and any two antenna port groups in the K2 antenna port groups are co-located or quasi-co-located (QCL); or any two antenna port groups in the K1 antenna port groups are on a same carrier, and any two antenna port groups in the K2 antenna port groups are on a same carrier.

(144) In one embodiment of the above user equipment, the first signaling is also used to determine at least the last one of the K1, the K2, or the target threshold. A third channel quality is a best channel quality value of the K2 channel quality values. A fourth channel quality is the worst channel quality value of the K2 channel quality values. The ratio between the fourth channel quality and the third channel quality is greater than or equal to the target threshold.

(145) In one embodiment of the above user equipment, the first information is further used to determine at least one of the first channel quality or the third channel quality.

(146) In one embodiment of the above user equipment, the second receiver further receives a second wireless signal; wherein a target antenna port group is used to transmit the second wireless signal; the target antenna port group is associated with the K1 antenna port groups and the first proportional sequence; or the target antenna port group is associated with the K2 antenna port groups and the first proportional sequence.

(147) The present disclosure provides a base station for multi-antenna transmission, including: a first transmitter, transmitting a first signaling; a second transmitter, transmitting a first wireless signal; and a third receiver, receiving first information; wherein, K antenna port groups are used to transmit the first wireless signal; the first signaling is used to determine the K antenna port groups; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values; the K1 is a positive integer less than or equal to the K; a first proportional sequence corresponds to a ratio(ratios) among the K1 channel quality values; the first information is used to determine the K1 antenna port groups and the first proportional sequence; the first signaling is used to determine a target threshold; the target threshold is a non-negative real number; a first channel quality is a best channel quality value among the K1 channel quality values; a second channel quality is a worse channel quality value among the K1 channel quality values; a ratio between the second channel quality and the first channel quality is greater than or equal to the target threshold.

(148) In one embodiment of the above base station, the K channel quality values are broadband channel quality values.

(149) In one embodiment of the above base station, the first proportional sequence includes K1 positive real numbers less than or equal to 1, and the first proportional sequence comprises at least one 1; or the first proportional sequence comprises quantized values corresponding to K1 positive real numbers; the first proportional sequence comprises K1-1 positive real numbers, and the K1-1 positive real numbers is(are) a ratio(ratios) between the channel quality values other than the best channel quality value among the K1 channel quality values and the best channel quality value; or the first proportional sequence comprises a quantized value(s) corresponding to K1-1 positive real number(s).

(150) In one embodiment, K2 antenna port groups in the K antenna port groups correspond to K2 channel quality values in the K channel quality values; the K2 is a positive integer less than or equal to the K; a second proportional sequence corresponds to a ratio among the K2 channel quality values; a first receiving beamforming vector is used to receive signals transmitted through the K1 antenna port groups; a second receiving beamforming vector is used to receive signals transmitted through the K2 antenna port groups; the first receiving beamforming vector and the second receiving beamforming vector are different; the first information is further used to determine K2

antenna port groups and the second proportional sequence.

(151) In one embodiment of the above base station, any two antenna port groups in the K1 antenna port groups are co-located or quasi-co-located (QCL), and any two antenna port groups in the K2 antenna port groups are co-located or quasi-co-located (QCL); or any two antenna port groups in the K1 antenna port groups are on a same carrier, and any two antenna port groups in the K2 antenna port groups are on a same carrier.

(152) In one embodiment of the above base station, the first signaling is also used to determine at least the last one of the K1, the K2, or the target threshold. A third channel quality is a best channel quality value of the K2 channel quality values. A fourth channel quality is the worst channel quality value of the K2 channel quality values. The ratio between the fourth channel quality and the third channel quality is greater than or equal to the target threshold.

(153) In one embodiment of the above base station, the first information is further used to determine at least one of the first channel quality or the third channel quality.

(154) In one embodiment of the above base station, the second receiver further receives a second wireless signal; wherein a target antenna port group is used to transmit the second wireless signal; the target antenna port group is associated with the K1 antenna port groups and the first proportional sequence; or the target antenna port group is associated with the K2 antenna port groups and the first proportional sequence.

(155) Compared with the prior art, the present disclosure has the following advantages:

(156) The service beam may be generated and used more flexibly through reporting channel quality ratios to increase beamforming gain.

(157) The robustness and flexibility of subsequent transmissions are increased by multiple sets of reports for varied receiving beamforming.

(158) The flexibility of multi-user scheduling of the base station is increased by the reporting of the best channel quality, combined with the reporting of the channel quality ratio.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Other features, objects, and advantages of the present disclosure will become more apparent from the detailed description of the accompanying drawings.

(2) FIG. 1 shows a flow chart of transmission of a first signaling, a first wireless signal, and first information in accordance with one embodiment of the present disclosure.

(3) FIG. 2 shows a schematic diagram of a network architecture in accordance with one embodiment of the present disclosure.

(4) FIG. 3 shows a schematic diagram of a radio protocol architecture of a user plane and a control plane according to an embodiment of the present disclosure.

(5) FIG. 4 shows a schematic diagram of a base station device and a given user equipment according to an embodiment of the present disclosure.

(6) FIG. 5 shows a flow chart of wireless transmission in accordance with one embodiment of the present disclosure.

(7) FIG. 6 shows a schematic diagram of analog beamforming of K reference signal groups in accordance with an embodiment of the present disclosure.

(8) FIG. 7 shows a timing diagram of K reference signal groups in accordance with one embodiment of the present disclosure.

(9) FIG. 8 shows a schematic diagram of K1 antenna port groups and K2 antenna port groups in accordance with one embodiment of the present disclosure.

(10) FIG. 9 shows a schematic diagram of a second wireless signal beamforming in accordance with an embodiment of the present disclosure.

(11) FIG. 10 shows a block diagram showing the structure of a processing device in a UE in accordance with an embodiment of the present disclosure.

(12) FIG. 11 shows a block diagram showing the structure of a processing device in a base station in accordance with an embodiment of the present disclosure.

DESCRIPTION OF THE EMBODIMENTS

Embodiment 1

(13) Embodiment 1 illustrates a flow chart of transmission of a first signaling, a first wireless signal, and first information in accordance with one embodiment of the present disclosure, as shown in FIG. 1. In FIG. 1, each box represents a step. In Embodiment 1, the user equipment in this disclosure receives a first signaling, receives a first wireless signal, and transmits a first information in sequence. K antenna port groups are used to transmit the first wireless signal. The first signaling is used to determine the K antenna port groups. The K is a positive integer greater than 1. The K antenna port groups respectively correspond to K channel quality values. The K channel quality values are K non-negative real numbers. K_1 antenna port groups of the K antenna port groups correspond to K_1 channel quality values of the K channel quality values. the K_1 is a positive integer less than or equal to the K . A first proportional sequence corresponds to a ratio(ratios) among the K_1 channel quality values. The first information is used to determine the K_1 antenna port groups and the first proportional sequence.

(14) As a sub-embodiment, the first signaling is a higher layer signaling.

(15) As a sub-embodiment, the first signaling is an RRC signaling.

(16) As a sub-embodiment, the first signaling is used to determine configuration of Channel State Information report (CSI).

(17) As a sub-embodiment, the first signaling is an RRC signaling for configuring CSI-RS.

(18) As a sub-embodiment, the first signaling is an RRC signaling for configuring a beamformed CSI-RS (Beamformed CSI-RS).

(19) As a sub-embodiment, the first signaling is a physical layer signaling.

(20) As a sub-embodiment, the first signaling is carried by a PDCCH.

(21) As a sub-embodiment, the first signaling is used to activate RRC pre-configuration.

(22) As a sub-embodiment, the K antenna port groups respectively correspond to K reference signal groups.

(23) As a sub-embodiment, the antenna port group includes only one antenna port.

(24) As a sub-embodiment, the reference signal group includes only one reference signal.

(25) As a sub-embodiment, the K is one of 2, 4, 8, 12, 16, 24, and 32.

(26) As a sub-embodiment, the reference signal is CSI-RS.

(27) As a sub-embodiment, the reference signal is SS.

(28) As a sub-embodiment, the first wireless signal is composed of the K reference signal groups.

(29) As a sub-embodiment, the first wireless signal is composed of K beam-formed CSI-RSs.

(30) As a sub-embodiment, the channel quality value is one of RSRP, SINR, and SNR.

(31) As a sub-embodiment, the channel quality values are wideband channel quality values.

(32) As a sub-embodiment, a wideband channel measurement is used to determine the wideband channel quality values.

(33) As a sub-embodiment, the wideband channel measurement refers to a channel measurement value for the entire system bandwidth obtained by measuring a channel on the entire system bandwidth.

(34) As a sub-embodiment, the wideband channel measurement refers to a channel measurement value for the entire subcarrier bandwidth obtained by measuring a channel on the entire sub-carrier bandwidth.

(35) As a sub-embodiment, the broadband is composed of a plurality of sub-bands, and the sub-bands are composed of one or more Resource Blocks (RBs).

(36) As a sub-embodiment, one RB includes 12 subcarriers.

- (37) As a sub-embodiment, one sub-band includes 5 RBs.
- (38) As a sub-embodiment, the wideband includes 10 sub-bands.
- (39) As a sub-embodiment, the K1 is smaller than the K.
- (40) As a sub-embodiment, the K1 is one of 2, 3, and 4.
- (41) As a sub-embodiment, the first signaling is used to determine the K.
- (42) As a sub-embodiment, the first signaling is used to determine the K1.
- (43) As a sub-embodiment, the K1 channel quality values are a best channel quality values among the K channel quality values.
- (44) As a sub-embodiment, the first information is used to determine the K1 antenna port groups and the first proportional sequence.
- (45) As a sub-embodiment, the first proportional sequence is composed of K1 non-negative real numbers not greater than one.
- (46) As a sub-embodiment, the first proportional sequence is composed of K1 positive real numbers not greater than one.
- (47) As a sub-embodiment, the first information is used to determine K1-1 non-negative real number(s), and the K1-1 positive real number(s) is(are) a ratio(s) between the channel quality values other than the best channel quality value among the K1 channel quality values and the best channel quality value.
- (48) As a sub-embodiment, the first information is used to determine quantized values corresponding to the K1-1 non-negative real number(s).
- (49) As a sub-embodiment, any one of the K1-1 non-negative real number(s) is not less than 0 and not greater than 1.
- (50) As a sub-embodiment, the K1-1 non-negative real number(s) is(are) used to determine the first proportional sequence.
- (51) As a sub-embodiment, the first information is carried by a PUCCH.
- (52) As a sub-embodiment, the first signal is carried by a PUSCH.
- (53) As a sub-embodiment, the first information is Uplink Control Information (UCI).

Embodiment 2

(54) Embodiment 2 illustrates a schematic diagram of a network architecture in accordance with the present disclosure, as shown in FIG. 2. FIG. 2 illustrates a network structure **200** of NR 5G, long-term evolution (LTE) and long-term evolution advanced (LTE-A) systems. The network architecture **200** of NR 5G or LTE may be referred to as an evolve packet system (EPS) **200** or some other suitable terminology. The EPS **200** may include one or more UEs **201**, an NG-RAN **902**, an Evolved Packet Core (EPC)/5G-Core Network (5G-CN) **210**, a home subscriber server (HSS) **220** and an internet service **230**. The EPS **200** may be interconnected with other access networks, but for the sake of simplicity, these entities/interfaces are not shown. As shown in FIG. 2, the EPS provides packet switching services. Those skilled in the art would readily appreciate that the various concepts presented throughout this disclosure can be extended to networks or other cellular networks that provide circuit switching services. The NG-RAN comprises an NR Node B (gNB) **203** and other gNBs **204**. The gNB **203** provides user and control plane protocol terminations for the UE **201**. The gNB **203** can be connected to other gNBs **204** via an Xn interface (e.g., a backhaul). The gNB **203** may also be referred to as a base station, a base transceiver station, a radio base station, a radio transceiver, a transceiver function, a basic service set (BSS), an extended service set (ESS), a transmission and reception point (TRP), or some other suitable terminology. The gNB **203** provides the UE **201** with an access point to the EPC/5G-CN **210**. In the embodiment, the UE **201** comprises cellular telephones, smart phones, Session Initiation Protocol (SIP) phones, laptop computers, personal digital assistants (PDAs), satellite radios, non-ground base station communications, satellite mobile communications, global positioning systems, multimedia devices, video devices, digital audio player (e.g. MP3 players), cameras, game consoles, drones, aircrafts, narrowband physical network devices, machine type communication

devices, land vehicles, cars, wearable devices, or any other similar to functional devices. A person skilled in the art may also refer to UE **201** as a mobile station, a subscriber station, a mobile unit, a subscriber unit, a radio unit, a remote unit, a mobile device, a radio device, a radio communication device, a remote device, a mobile subscriber station, an access terminal, a mobile terminal, a radio terminal, remote terminal, handset, user agent, mobile client, client or some other suitable term. The gNB **203** is connected to the EPC/5G-CN **210** through an S1/NG interface. The EPC/5G-CN **210** comprises an MME/AMF/UPF **211**, other MMEs/AMFs/UPFs **214**, a Service Gateway (S-GW) **212** and a Packet Data Network Gateway (P-GW) **213**. The MME/AMF/UPF **211** is a control node that handles a signaling between the UE **201** and the EPC/5G-CN **210**. In general, the MME/AMF/UPF **211** provides carrier and connection management. All User Internet Protocol (IP) packets are transmitted through the S-GW **212**, and the S-GW **212** itself is connected to the P-GW **213**. The P-GW **213** provides UE IP address allocation as well as other functions. The P-GW **213** is connected to the internet service **230**. The internet service **230** includes an operator-compatible internet protocol service, and may specifically include the Internet, an intranet, an IP Multimedia Subsystem (IMS), and a PS streaming service (PSS).

(55) As a sub-embodiment, the UE **201** corresponds to the user equipment in this disclosure.

(56) As a sub-embodiment, the gNB **203** corresponds to the base station in the present disclosure.

(57) As a sub-embodiment, the UE **201** supports multi-antenna transmission.

(58) As a sub-embodiment, the UE **201** supports wideband channel measurement.

(59) As a sub-embodiment, the gNB **203** supports multi-antenna transmission.

(60) As a sub-embodiment, the gNB **203** supports wideband beamforming.

Embodiment 3

(61) Embodiment 3 illustrates a schematic diagram of a radio protocol architecture of a user plane and a control plane according to an embodiment of the present disclosure, as shown in FIG. 3. FIG. 3 is a schematic diagram illustrating an embodiment of a radio protocol architecture for a user plane and a control plane, and FIG. 3 illustrates a radio protocol architecture for the UE and the base station equipment (gNB or eNB) in three layers: layer 1, layer 2 and layer 3. The Layer 1 (L1 layer) is the lowest layer and implements various signal processing functions of the physical layer (i.e., PHY). The L1 layer will be referred to herein as PHY **301**. The Layer 2 (L2 layer) **305** is above PHY **301** and is responsible for the link between the UE and the gNB through PHY **301**. In the user plane, L2 layer **305** comprises a media access control (MAC) sub-layer **302**, a radio link control (RLC) sub-layer **303** and a packet data convergence protocol (PDCP) sub-layer **304**, and these sub-layers terminate at the gNB of the network side. Although not illustrated in FIG. 3, the UE may have several upper layers above the L2 layer **305**, including a network layer (i.e., an IP layer) terminated at the P-GW of the network side and an application layer terminated at the other side of the connection (i.e., a peer UE, server, etc.). The PDCP sub-layer **304** provides multiplexing between different radio bearers and logical channels. The PDCP sublayer **304** also provides header compression for an upper layer packet to reduce a radio transmission overhead, provides security by encrypting a packet, and provides support for UE handover between gNBs. The RLC sublayer **303** provides segmentation and reassembling of an upper layer data packet, retransmission of a lost packets and reordering of a packet to compensate for the disordered reception resulted from the hybrid automatic repeat request (HARQ). The MAC sublayer **302** provides multiplexing between a logical channel and a transport channel. The MAC sublayer **302** is also responsible for allocating various radio resources (i.e., resource blocks) in one cell between UEs. The MAC sublayer **302** is also responsible for HARQ operation. In the control plane, the radio protocol architecture for the UE and gNB is substantially the same as the radio protocol architecture in the user plane on the physical layer **301** and the L2 layer **305**, but there is no header compression function for the control plane. The control plane also comprises a Radio Resource Control (RRC) sublayer **306** in Layer 3 (L3 layer). The RRC sublayer **306** is responsible for obtaining radio resources (i.e. radio bearers) and configuring the lower layer using an RRC signaling between the gNB and the UE.

(62) In one embodiment, the radio protocol architecture of FIG. 3 is applicable to the user equipment in this disclosure.

(63) In one embodiment, the radio protocol architecture of FIG. 3 is applicable to the base station in this disclosure.

(64) As a sub-embodiment, the first signaling in the present disclosure is generated in the RRC sublayer **306**.

(65) As a sub-embodiment, the first signaling in the present disclosure is generated by the PHY **301**.

(66) As a sub-embodiment, the first wireless signal in the present disclosure is generated by the PHY **301**.

(67) As a sub-embodiment, the first information in the present disclosure is generated by the PHY **301**.

Embodiment 4

(68) Embodiment 4 shows a schematic diagram of a base station device and a given user equipment according to the present disclosure, as shown in FIG. 4. FIG. 4 is a block diagram of a gNB **410** in communication with a UE**450** in an access network.

(69) The base station (**410**) may comprise a controller/processor **440**, a scheduler **443**, a memory **430**, a receiving processor **412**, a transmitting processor **415**, a MIMO transmitting processor **441**, a MIMO detector **442**, a transmitter/receiver **416**, and an antenna **420**.

(70) The user equipment (UE**450**) may comprise a controller/processor **490**, a memory **480**, a data source **467**, a transmitting processor **455**, a receiving processor **452**, a MIMO transmitting processor **471**, a MIMO detector **472**, a transmitter/receiver **466**, and an antenna **460**.

(71) In Downlink (DL) transmission, the processing associated with the base station (**410**) may include the following operations:

(72) The upper layer packet is provided to the controller/processor **440**. The controller/processor **440** provides header compression, encryption, packet segmentation and reordering, and multiplexing between a logical channel and a transport channel so as to implement L2 layer protocols for the user plane and the control plane. The upper layer packet may include data or control information, such as a Downlink Shared Channel (DL-SCH).

(73) The controller/processor **440** can be associated with the memory **430** that stores program codes and data. The memory **430** can be a computer readable medium.

(74) The controller/processor **440** notifies the scheduler **443** to transmit the demand. The scheduler **443** is configured to schedule the air interface resource corresponding to the transmission requirement, and notify the controller/processor **440** of the scheduling result.

(75) The transmitting processor **415** receives the output bitstream of controller/processor **440**, and implements various signal transmission processing functions for the L1 layer (i.e., the physical layer), including encoding, interleaving, scrambling, modulation, power control/allocation and generation of physical layer control signaling (including PBCH, PDCCH, PHICH, PCFICH, a reference signal), etc.

(76) The MIMO transmitting processor **441** performs spatial processing for data symbols, control symbols or reference signal symbols (such as precoding, beam shaping), and outputs baseband signals to the transmitter **416**.

(77) The transmitter **416** is configured to convert the baseband signal provided by the MIMO transmitting processor **441** into a radio frequency signal and to transmit the radio frequency signal via the antenna **420**. Each transmitter **416** samples the respective input symbol streams to obtain a respective sampled signal stream. Each transmitter **416** performs further processing (e.g., digital to analog conversion, amplification, filtering, upconversion, etc.) on a respective sampled stream to obtain a downlink signal.

(78) In Downlink (DL) transmission, the processing associated with the user equipment (UE**450**) may include the following operations:

(79) The receiver **456** is configured to convert the radio frequency signal received through the antenna **460** into a baseband signal and provide the baseband signal to the MIMO detector **472**.

(80) The MIMO detector **472** is configured to perform MIMO detection on the signal received from the receiver **456**, and provide the MIMO-detected baseband signal to the receiving processor **452**.

(81) The receiving processor **452** implements various signal receiving processing functions for the L1 layer (i.e., the physical layer) including decoding, deinterleaving, descrambling, demodulation, and physical layer control signaling extraction, etc.

(82) The controller/processor **490** receives the bitstream output by the receive processor **452**. The controller/processor **490** provides header compression, encryption, packet segmentation and reordering, and multiplexing between a logical channel and a transport channel to implement L2 layer protocols for the user plane and the control plane.

(83) The controller/processor **490** can be associated with the memory **480** that stores program codes and data. The memory **480** can be a computer readable medium.

(84) The first signaling in the present disclosure may be generated by the transmitting processor **415** or transmitted to the controller/processor **440** by higher layer signaling. The scheduler **443** schedules the air interface resources occupied by the first signaling. The MIMO transmission processor **441** performs multi-antenna precoding processing on the symbols output by the transmission processor. The transmitter **416** converts the baseband signal provided by the MIMO transmitting processor **441** into a radio frequency signal and transmits the radio frequency signal via the antenna **420**. The receiver **456** converts the radio frequency signal received by the antenna **460** and the first signaling into a baseband signal and provides the baseband signal to the MIMO detector **472**. The MIMO detector **472** performs MIMO detection on the signal received from the receiver **456**. The receiving processor **452** processes the baseband signal output by the MIMO detector **472** to obtain the first signaling or transmits the baseband signal to the controller/processor **440** for further processing related to a higher layer to obtain the first signaling.

(85) The first wireless signal in the present disclosure is K reference signal groups generated by the transmitting processor **415**. The MIMO transmitting processor **441** performs beamforming processing on the K reference signal groups output by the transmitting processor, and transmits the K reference signal groups to the K antenna port groups for transmission. The transmitter **416** converts the baseband signal provided by the MIMO transmitting processor **441** into a radio frequency signal and transmits the radio frequency signal via the antenna **420**. The receiver **456** converts the radio frequency signal received by the antenna **460** and the first radio signal into a baseband signal and provides the first radio signal to the MIMO detector **472**. The MIMO detector **472** performs MIMO detection on the signal received from the receiver **456**. The receiving processor **452** performs channel measurement based on the baseband signal output by the MIMO detector **472** and the K reference signal groups to obtain the K channel quality values.

(86) In Uplink (UL) transmission, the processing associated with the user equipment (UE**450**) may include the following operations:

(87) The data source **467** provides an upper layer packet to the controller/processor **490**. The controller/processor **490** provides header compression, encryption, packet segmentation and reordering, and multiplexing between logical and transport channels to implement L2 layer protocols for the user plane and the control plane. The upper layer packet may include data or control information, such as an Uplink Shared Channel (UL-SCH).

(88) The controller/processor **490** can be associated with the memory **480** that stores program codes and data. The memory **480** can be a computer readable medium.

(89) The transmitting processor **455** receives the bitstream output by the controller/processor **490**, and implements various signal transmission processing functions for the L1 layer (i.e., the physical layer), including encoding, interleaving, scrambling, modulation, power control/allocation and generation of physical layer control signaling (including PUCCH, Sounding Reference Signal

(SRS)), etc.

(90) The MIMO transmitting processor **471** performs spatial processing for data symbols, control symbols or reference signal symbols (such as precoding, beam shaping), and outputs baseband signals to the transmitter **456**.

(91) The transmitter **456** is configured to convert the baseband signal provided by the MIMO transmitting processor **471** into a radio frequency signal and to transmit the radio frequency signal via the antenna **460**. Each transmitter **456** samples the respective input symbol streams to obtain a respective sampled signal stream. Each transmitter **456** performs further processing (e.g., digital to analog conversion, amplification, filtering, upconversion, etc.) on the respective sample stream to obtain an uplink signal.

(92) In Uplink (UL) transmission, the processing associated with the base station (**410**) may include the following operations:

(93) The receiver **416** is configured to convert the radio frequency signal received by the antenna **420** into a baseband signal and provide the baseband signal to the MIMO detector **442**.

(94) The MIMO detector **442** is configured to perform MIMO detection on the signal received from the receiver **416**, and provide the MIMO-detected baseband signal to the receiving processor **442**.

(95) The receiving processor **412** implements various signal receiving processing functions for the L1 layer (i.e., the physical layer) including decoding, deinterleaving, descrambling, demodulation, and physical layer control signaling extraction, etc.

(96) The controller/processor **440** receives the bitstream output by the receiving processor **412**. The controller/processor **490** provides header compression, encryption, packet segmentation and reordering, and multiplexing between a logical channel and a transport channel to implement L2 layer protocols for the user plane and the control plane.

(97) The controller/processor **440** can be associated with the memory **430** that stores program codes and data. The memory **430** can be a computer readable medium.

(98) The first information in the present disclosure may be generated by the transmitting processor **455** to the controller/processor **490**. The MIMO transmitting processor **471** performs multi-antenna precoding processing on the symbols output by the transmitting processor. The transmitter **456** converts the baseband signal provided by the MIMO transmitting processor **471** into a radio frequency signal and transmits the radio frequency signal via the antenna **460**. The receiver **416** converts the radio frequency signal related to the first information received by the antenna **420** into a baseband signal and provides the baseband signal to the MIMO detector **442**. The MIMO detector **442** performs MIMO detection on the signal received from the receiver **416**. The receiving processor **412** processes the baseband signal output by the MIMO detector **442** to obtain the first information.

(99) As a sub-embodiment, the UE **450** includes: at least one processor and at least one memory. The at least one memory includes computer program code. The at least one memory and the computer program code are configured to use with the at least one processor together. The UE **450** at least: receives a first signaling; receives a first wireless signal; and transmits first information; wherein, K antenna port groups are used to transmit the first wireless signal; the first signaling is used to determine the K antenna port groups; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values; the K1 is a positive integer less than or equal to the K; a first proportional sequence corresponds to a ratio(ratios) among the K1 channel quality values; the first information is used to determine the K1 antenna port groups and the first proportional sequence.

(100) As a sub-embodiment, the UE **450** includes: a memory storing a computer readable instruction program that, when executed by at least one processor, performs operations. The

operations include: receiving a first signaling; receiving a first wireless signal; and transmitting first information; wherein, K antenna port groups are used to transmit the first wireless signal; the first signaling is used to determine the K antenna port groups; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values; the K1 is a positive integer less than or equal to the K; a first proportional sequence corresponds to a ratio(ratios) among the K1 channel quality values; the first information is used to determine the K1 antenna port groups and the first proportional sequence.

(101) As a sub-embodiment, the gNB**410** includes: at least one processor and at least one memory. The at least one memory includes computer program code. The at least one memory and the computer program code are configured to use with the at least one processor together. The UE**450** at least: transmits a first signaling; transmits a first wireless signal; and receives first information; wherein, K antenna port groups are used to transmit the first wireless signal; the first signaling is used to determine the K antenna port groups; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values; the K1 is a positive integer less than or equal to the K; a first proportional sequence corresponds to a ratio(ratios) among the K1 channel quality values; the first information is used to determine the K1 antenna port groups and the first proportional sequence.

(102) As a sub-embodiment, the UE **450** includes: a memory storing a computer readable instruction program that, when executed by at least one processor, performs operations. The operations include: transmitting a first signaling; transmitting a first wireless signal; and receiving first information; wherein, K antenna port groups are used to transmit the first wireless signal; the first signaling is used to determine the K antenna port groups; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values; the K1 is a positive integer less than or equal to the K; a first proportional sequence corresponds to a ratio(ratios) among the K1 channel quality values; the first information is used to determine the K1 antenna port groups and the first proportional sequence.

(103) As a sub-embodiment, the UE **450** corresponds to the user equipment in this disclosure.

(104) As a sub-embodiment, the gNB **410** corresponds to the base station in the present disclosure.

(105) As a sub-embodiment, at least the first three of the receiver **456**, the MIMO detector **472**, the receiving processor **452**, and the controller/processor **490** are used to receive the first signaling in the present disclosure.

(106) As a sub-embodiment, at least the first three of the transmitter **416**, the MIMO transmitter **441**, the transmitting processor **415**, and the controller/processor **440** are used to transmit the first signaling in this disclosure.

(107) As a sub-embodiment, the receiver **456**, the MIMO detector **472** and the receiving processor **452** are used to receive the first wireless signal in the present disclosure.

(108) As a sub-embodiment, the transmitter **416**, the MIMO transmitter **441** and the transmit processor **415** are used to transmit the first wireless signal in this disclosure.

(109) As a sub-embodiment, at least the first three of the transmitter/receiver **456**, the MIMO transmitter **471**, the transmitting processor **455**, and the controller/processor **490** are used to transmit the first information in this disclosure.

(110) As a sub-embodiment, the receiver **416**, the MIMO detector **442**, and the receiving processor **412** are used to receive the first information in this disclosure.

Embodiment 5

(111) Embodiment 5 illustrates a flow chart of wireless transmission, as shown in FIG. 5. In FIG. 5, the base station N1 is a maintaining base station for the serving cell of the UE U2. In FIG. 5, the steps in block F 1 are optional.

(112) For N1, the first signaling is transmitted in step S11; the first wireless signal is transmitted in step S12; the first information is received in step S13; and the second signal is transmitted in step S14.

(113) For U2, the first signaling is received in step S21; the first wireless signal is received in step S22; the first information is transmitted in step S23; and the second signal is received in step S24.

(114) In Embodiment 5, K antenna port groups are used to transmit the first wireless signal. the first signaling is used to determine the K antenna port groups by U2. The K is a positive integer greater than 1. The K antenna port groups respectively correspond to K channel quality values. The K channel quality values are K non-negative real numbers. K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values. the K1 is a positive integer less than or equal to the K. A first proportional sequence corresponds to a ratio(ratios) among the K1 channel quality values. The first information is used to determine the K1 antenna port groups and the first proportional sequence.

(115) As a sub-embodiment, K2 antenna port groups in the K antenna port groups correspond to K2 channel quality values in the K channel quality values. The K2 is a positive integer less than or equal to the K. a second proportional sequence corresponds to a ratio among the K2 channel quality values. A first receiving beamforming vector is used to receive signals transmitted through the K1 antenna port groups by U@. A second receiving beamforming vector is used to receive signals transmitted through the K2 antenna port groups by U2. The first receiving beamforming vector and the second receiving beamforming vector are different; the first information is further used to determine the K2 antenna port groups and the second proportional sequence.

(116) As a sub-embodiment, any two antenna port groups in the K1 antenna port groups, and any two antenna port groups in the K2 antenna port groups are co-located or quasi-co-located (QCL); or, any two antenna port groups in the K1 antenna port groups, and any two antenna port groups in the K2 antenna port groups are on the same carrier.

(117) As a sub-embodiment, the first signaling is further used to determine at least the last one of the K1, the K2, or the target threshold by U2. The target threshold is a non-negative real number. The first channel quality is the best channel quality value of the KT channel quality values. The second channel quality is the worst channel quality value of the K1 channel quality values. The third channel quality is the best channel quality value of the K2 channel quality values. The fourth channel quality is the worst channel quality value of the K2 channel quality values. At least one of a ratio between the second channel quality and the first channel quality, or a ratio between the fourth channel quality and the third channel quality is greater than or equal to the target threshold.

(118) As a sub-embodiment, the first information is further used by U2 to determine at least one of the first channel quality or the third channel quality.

(119) As a sub-embodiment, the target antenna port group is used by N1 to transmit the second wireless signal.

(120) As a sub-embodiment, the target antenna port group is associated with the K1 antenna port groups and the first proportional sequence. The K1 antenna port groups correspond to K1 analog beamforming vectors. The K1 analog beam vectors and the first proportional sequence are used by N1 to generate a first target analog beamforming vector. The first target analog beamforming vector is used for analog beamforming of the target antenna port group. The first receive beamforming vector is used by U2 to receive the second wireless signal.

(121) As a sub-embodiment, the target antenna port group is associated with the K2 antenna port groups and the second proportional sequence. The K2 antenna port groups correspond to K2 analog beamforming vectors. The K2 analog beam vectors and the second proportional sequence are used by N1 to generate a second target analog beamforming vector. The second target analog

beamforming vector is used for analog beamforming of the target antenna port group. The second receive beamforming vector is used by U2 to receive the second wireless signal.

Embodiment 6

(122) Embodiment 6 illustrates a schematic diagram of analog beamforming of K reference signal groups, as shown in FIG. 6.

(123) In Embodiment 6, the K reference signal groups and the K antenna port groups are in one-to-one correspondence. The number of the reference signals in the reference signal group is equal to the number of the antenna ports in the corresponding antenna port group.

(124) In Embodiment 6, a physical antenna corresponding to one antenna port is divided into S antenna groups, and each of the antenna groups includes a plurality of antennas. The S is a positive integer. The antenna port is formed by superposing multiple antennas in the S antenna groups through antenna virtualization. The mapping coefficients of the plurality of antennas in the S antenna groups to the antenna port constitute a beamforming vector. One antenna group is connected to the baseband processor via a radio frequency (RF) link. One beamforming vector is composed of an analog beamforming vector and a digital beamforming vector. The mapping coefficients of the plurality of antennas in the same antenna group to the antenna port constitute an analog beamforming vector of the antenna group. Different antenna groups included in one antenna port corresponding to the same analog beamforming vector. The mapping coefficients of the different RF links included in the antenna port to the antenna port constitute a digital beamforming vector of the antenna port.

(125) As a sub-embodiment, the reference signal group includes only one reference signal, and the reference signal in the reference signal group is transmitted by an antenna port in a corresponding transmitting antenna port group.

(126) As a sub-embodiment, the reference signal group includes only a plurality of the reference signals, and the plurality of reference signals in the reference signal group are respectively sent by multiple antenna ports in the corresponding transmitting antenna port group. Different antenna ports in one antenna port group correspond to one same analog beamforming vector.

(127) As a sub-embodiment, different antenna ports in one antenna port group correspond to the different digital beamforming vectors.

(128) As a sub-embodiment, the K antenna port groups are a subset of M antenna port groups. The UE transmits auxiliary information according to the measurement in the M antenna port groups. The base station determines, according to the auxiliary information, and configures the K antenna port groups for the UE.

Embodiment 7

(129) Embodiment 7 illustrates a timing diagram of K reference signal groups, as shown in FIG. 7.

(130) In Embodiment 7, the K antenna port groups correspond to K reference signal groups. The time domain resources occupied by any two antenna port groups in the K reference signal groups are orthogonal. The analog beamforming vectors corresponding to any two reference signal groups in the K reference signal groups cannot be considered to be the same. The K reference signal groups occupy K time windows. The K time windows are orthogonal in the time domain.

(131) As a sub-embodiment, FIG. 7 depicts one transmission of the K reference signal groups. The K reference signal groups are transmitted periodically.

(132) As a sub-embodiment, the reference signal adopts a pattern of CSI-RS within a time window.

(133) As a sub-embodiment, the reference signal adopts a pattern of SS within a time window.

(134) As a sub-embodiment, the time window in FIG. 7 includes Q1 OFDM symbols, and the Q1 is one of 2, 4, 7 and 14.

Embodiment 8

(135) Embodiment 8 illustrates a schematic diagram of K1 antenna port groups and K2 antenna port groups, as shown FIG. 8. In Embodiment 8, the K antenna port groups are used to transmit the first wireless signal. The K analog beamforming vectors are used for transmitting analog

beamforming of the K antenna port groups respectively. The K antenna port groups respectively correspond to K channel quality values. The best K1+K2 channel quality values of the K channel quality values respectively correspond to the first receive beamforming vector and the second receive beamforming vector. The first receiving beamforming vector performs receiving analog beamforming on the signals transmitted through the K1 antenna port groups. The second receiving beamforming vector performs receiving analog beamforming on the signals transmitted through the K2 antenna port groups.

Embodiment 9

(136) Embodiment 9 illustrates a schematic diagram of a second wireless signal beamforming, as shown in FIG. 9. In FIG. 9, the dotted ellipse represents an analog beam for transmitting a first wireless signal, and the solid ellipse represents an analog beam for transmitting a second wireless signal.

(137) In Embodiment 9, the UE receives the first wireless signal transmitted through the K antenna port groups. The K antenna port groups correspond to the K channel quality values. The UE receives the first signaling to determine that K1 is equal to 2. The first antenna port group and the second antenna port group are two antenna port groups of the K antenna port groups. The first antenna port group corresponds to the first channel quality. The second antenna port group is corresponding to the second channel quality. The first channel quality is a best channel quality value of the K channel quality values. The second channel quality is a second best channel quality value of the K channel quality values. The UE reports {the first antenna port group, the second antenna port group, and the first proportional sequence} to the base station. The first proportional sequence is composed of 1, ratio of the second channel quality and the first channel quality. The first analog beamforming vector is used for analog beamforming of the first antenna port group. The second analog beamforming vector is used for analog beamforming of the second antenna port group. The base station generates a target analog beamforming vector by using a direction corresponding to the first analog beamforming vector, a direction corresponding to the second analog beamforming vector, and the first proportional sequence according to the UE report. The beam direction corresponding to the target analog beamforming vector is between a beam direction corresponding to the first analog beamforming vector and a beam direction corresponding to the second analog beamforming vector. The target analog beamforming vector is used for analog beamforming of the target antenna port group. The target antenna port group is used to transmit the second wireless signal.

Embodiment 10

(138) Embodiment 10 illustrates a block diagram showing the structure of a processing device in a UE. In FIG. 10, a UE **1000** is composed of a first receiver **1001**, a second receiver **1002**, and a third transmitter **1003**.

(139) In Embodiment 10, the first receiver **1001** is configured to receive the first signaling; the second receiver **1002** is configured to receive the first wireless signal; and the third transmitter **1003** is configured to send the first information.

(140) In Embodiment 10, K antenna port groups are used to transmit the first wireless signal; the first signaling is used to determine the K antenna port groups. The K is a positive integer greater than 1. The K antenna port groups respectively correspond to K channel quality values. The K channel quality values are K non-negative real numbers. K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values. The K1 is a positive integer less than or equal to the K. A first proportional sequence corresponds to a ratio(ratios) among the K1 channel quality values. The first information is used to determine the K1 antenna port groups and the first proportional sequence.

(141) As a sub-embodiment, the K2 antenna port groups in the K antenna port groups correspond to K2 channel quality values in the K channel quality values. The K2 is a positive integer less than or equal to the K. A second proportional sequence corresponds to a ratio among the K2 channel

quality values. A first receiving beamforming vector is used to receive signals transmitted through the K1 antenna port groups. A second receiving beamforming vector is used to receive signals transmitted through the K2 antenna port groups. The first receiving beamforming vector and the second receiving beamforming vector are different; the first information is further used to determine the K2 antenna port groups and the second proportional sequence.

(142) As a sub-embodiment, any two antenna port groups in the K1 antenna port groups, and any two antenna port groups in the K2 antenna port groups are co-located or quasi-co-located (QCL); or, any two antenna port groups in the K1 antenna port groups and any two antenna port groups in the K2 antenna port groups are on the same carrier.

(143) As a sub-embodiment, the first signaling is further used to determine at least the last one of the K1, the K2, or the target threshold. The target threshold is a non-negative real number. The first channel quality is a best channel quality value of the K1 channel quality values. The second channel quality is the worst channel quality value of the K1 channel quality values. The third channel quality is a best channel quality value of the K2 channel quality values. The fourth channel quality is the worst channel quality value of the K2 channel quality values. At least one of a ratio between the second channel quality and the first channel quality or a ratio between the fourth channel quality and the third channel quality is greater than or equal to the target threshold.

(144) As a sub-embodiment, the first information is further used to determine at least one of the first channel quality or the third channel quality.

(145) As a sub-embodiment, the second receiver **1002** is also used to receive a second wireless signal. The target antenna port group is used to transmit the second wireless signal. The target antenna port group is associated with the K1 antenna port groups and the first proportional sequence; or, the target antenna port group is associated with the K2 antenna port groups and the second proportional sequence.

Embodiment 11

(146) Embodiment 11 illustrates a block diagram showing the structure of a processing device in a base station, as shown in FIG. **11**.

(147) In FIG. **11**, the base station **1100** includes a first transmitter **1101**, a second transmitter **1102**, and a third receiver **1103**.

(148) In Embodiment 11, the first transmitter **1101** is configured to transmit the first signaling; the second transmitter **1102** is configured to transmit the first wireless signal; and the third receiver **1103** is configured to receive the first information.

(149) In Embodiment 11, K antenna port groups are used to transmit the first wireless signal; the first signaling is used to determine the K antenna port groups. The K is a positive integer greater than 1. The K antenna port groups respectively correspond to K channel quality values. The K channel quality values are K non-negative real numbers. K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values. The K1 is a positive integer less than or equal to the K. A first proportional sequence corresponds to a ratio(ratios) among the K1 channel quality values. The first information is used to determine the K1 antenna port groups and the first proportional sequence.

(150) As a sub-embodiment, the K2 antenna port groups in the K antenna port groups correspond to K2 channel quality values in the K channel quality values. The K2 is a positive integer less than or equal to the K. A second proportional sequence corresponds to a ratio among the K2 channel quality values. A first receiving beamforming vector is used to receive signals transmitted through the K1 antenna port groups. A second receiving beamforming vector is used to receive signals transmitted through the K2 antenna port groups. The first receiving beamforming vector and the second receiving beamforming vector are different; the first information is further used to determine the K2 antenna port groups and the second proportional sequence.

(151) As a sub-embodiment, any two antenna port groups in the K1 antenna port groups, and any two antenna port groups in the K2 antenna port groups are co-located or quasi-co-located (QCL);

or, any two antenna port groups in the K1 antenna port groups, and any two antenna port groups in the K2 antenna port groups are on the same carrier.

(152) As a sub-embodiment, the first signaling is further used to determine at least the last one of the K1, the K2, or the target threshold. The target threshold is a non-negative real number. The first channel quality is a best channel quality value of the K1 channel quality values. The second channel quality is the worst channel quality value of the K1 channel quality values. The third channel quality is a best channel quality value of the K2 channel quality values. The fourth channel quality is the worst channel quality value of the K2 channel quality values. At least one of a ratio between the second channel quality and the first channel quality or a ratio between the fourth channel quality and the third channel quality is greater than or equal to the target threshold.

(153) As a sub-embodiment, the first information is further used to determine at least one of the first channel quality or the third channel quality.

(154) As a sub-embodiment, the second transmitter is further configured to transmit a second wireless signal. The target antenna port group is used to transmit the second wireless signal. The target antenna port group is associated with the K1 antenna port group and the first proportional sequence; or the target antenna port group is associated with the K2 antenna port group and the second proportional sequence.

(155) The ordinary skill in the art may understand that all or part of steps in the above method may be implemented by instructing related hardware through a program. The program may be stored in a computer readable storage medium, for example Read-Only-Memory (ROM), hard disk or compact disc, etc. Optionally, all or part of steps in the above embodiments also may be implemented by one or more integrated circuits. Correspondingly, each module unit in the above embodiment may be implemented in the form of hardware, or in the form of software function modules. The present disclosure is not limited to any combination of hardware and software in specific forms. The UE and terminal in the present disclosure include but are not limited to unmanned aerial vehicles, communication modules on unmanned aerial vehicles, telecontrolled aircrafts, aircrafts, diminutive airplanes, mobile phones, tablet computers, notebooks, vehicle-mounted communication equipment, radio sensor, network cards, terminals for Internet of Things (IOT), RFID terminals, NB-IOT terminals, Machine Type Communication (MTC) terminals, enhanced MTC (eMTC) terminals, data cards, low-cost mobile phones, low-cost tablet computers, etc. The base station in the present disclosure includes but is not limited to macro-cellular base stations, micro-cellular base stations, home base stations, relay base station, gNB (NR node B), Transmitter Receiver Point (TRP), and other radio communication equipment.

(156) The above are merely the preferred embodiments of the present disclosure and are not intended to limit the scope of protection of the present disclosure. Any modification, equivalent substitute and improvement made within the spirit and principle of the present disclosure are intended to be included within the scope of protection of the present disclosure.

Claims

1. A method for multi-antenna transmission in a user equipment (UE), comprising: receiving a first signaling; receiving a first wireless signal; and transmitting first information; wherein, K antenna port groups that comprise K groups of antenna ports are used to collectively transmit the first wireless signal; the first signaling is used to determine the K antenna port groups transmitting the first wireless signal; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; the K channel quality values are Reference Signal Received Powers (RSRPs) or Signal to Interference plus Noise Ratios (SINRs); K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values; the K1 is a positive integer less than or equal to the K; a first proportional sequence corresponds to a

ratio (ratios) among the K1 channel quality values, the first proportional sequence comprising a sequence of K1 proportions, wherein each of the K1 proportions corresponds to a ratio between one channel quality value to itself or to another of the K1 channel quality values; the first information is used to determine the K1 antenna port groups and the first proportional sequence; the first signaling is used to determine a target threshold; the target threshold is a non-negative real number; a first channel quality is a best channel quality value among the K1 channel quality values; a second channel quality is a worse channel quality value among the K1 channel quality values; a ratio between the second channel quality and the first channel quality is greater than or equal to the target threshold; the first information is carried by a PUSCH (Physical Uplink Shared Channel) or a PUCCH (Physical Uplink Control Channel).

2. The method according to claim 1, wherein the K channel quality values are broadband channel quality values; or the first proportional sequence comprises K1 positive real numbers less than or equal to 1, and the first proportional sequence comprises at least one 1; or the first proportional sequence comprises quantized values corresponding to K1 positive real numbers; or the first proportional sequence is composed of K1 positive real numbers, and the K1 positive real numbers are respectively ratios between the K1 channel quality values and the best channel quality value of the K1 channel quality values; or the first proportional sequence comprises K1-1 positive real number(s), and the K1-1 positive real number(s) is (are) a ratio (ratios) between a channel quality value(s) other than the best channel quality value among the K1 channel quality values and the best channel quality value; or the first proportional sequence comprises quantized values corresponding to K1-1 positive real number(s).

3. The method according to claim 1, wherein the first signaling is UE specific; or, the unit of the target threshold is dB; or, the first signaling implicitly indicates the target threshold; or, the K antenna port groups correspond to K reference signal groups, the time domain resources occupied by any two of the K reference signal groups are orthogonal, the analog beamforming vectors corresponding to any two of the K reference signal groups cannot be considered to be the same, the K reference signal groups occupy K time windows, and the K time windows are orthogonal in the time domain.

4. The method according to claim 1, wherein any two antenna ports in the K1 antenna port groups are co-located or quasi-co-located (QCL); or any two antenna ports in the K1 antenna port groups are on a same carrier; or the first signaling is further used to determine the K1, and the first information is further used to determine the first channel quality.

5. The method according to claim 1, wherein the K antenna port groups respectively correspond to K reference signal groups; the K reference signal groups are respectively transmitted through the K antenna port groups; the first wireless signal is composed of the K reference signal groups; the antenna port group is composed of one antenna port, or, the antenna port group is composed of a plurality of antenna ports; the antenna port corresponds to a reference signal; the reference signal is transmitted through the antenna port; the reference signal is a SS (Synchronization Signal) or a CSI-RS (Channel State Information Reference Signal) or a DMRS of a PBCH (Physical Broadcast Channel).

6. A method for multi-antenna transmission in a base station, comprising: transmitting a first signaling; transmitting a first wireless signal; and receiving first information; wherein, K antenna port groups that comprise K groups of antenna ports of the base station are used to collectively transmit the first wireless signal; the first signaling is used to determine the K antenna port groups transmitting the first wireless signal; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; the K channel quality values are Reference Signal Received Powers (RSRPs) or Signal to Interference plus Noise Ratios (SINRs); K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values; the K1 is a positive integer less than or equal to the K; a first proportional sequence corresponds to a

ratio (ratios) among the K1 channel quality values, the first proportional sequence comprising a sequence of K1 proportions, wherein each of the K1 proportions corresponds to a ratio between one channel quality value to itself or to another of the K1 channel quality values; the first information is used to determine the K1 antenna port groups and the first proportional sequence; the first signaling is used to determine a target threshold; the target threshold is a non-negative real number; a first channel quality is a best channel quality value among the K1 channel quality values; a second channel quality is a worse channel quality value among the K1 channel quality values; a ratio between the second channel quality and the first channel quality is greater than or equal to the target threshold; the first information is carried by a PUSCH (Physical Uplink Shared Channel) or a PUCCH (Physical Uplink Control Channel).

7. The method according to claim 6, wherein the K channel quality values are broadband channel quality values; or the first proportional sequence comprises K1 positive real numbers less than or equal to 1, and the first proportional sequence comprises at least one 1; or the first proportional sequence comprises quantized values corresponding to K1 positive real numbers; or the first proportional sequence is composed of K1 positive real numbers, and the K1 positive real numbers are respectively ratios between the K1 channel quality values and the best channel quality value of the K1 channel quality values; or the first proportional sequence comprises K1-1 positive real number(s), and the K1-1 positive real number(s) is (are) a ratio (ratios) between a channel quality value(s) other than the best channel quality value among the K1 channel quality values and the best channel quality value; or the first proportional sequence comprises quantized values corresponding to K1-1 positive real number(s).

8. The method according to claim 6, wherein the first signaling is UE specific; or, the unit of the target threshold is dB; or, the first signaling implicitly indicates the target threshold; or, the K antenna port groups correspond to K reference signal groups, the time domain resources occupied by any two of the K reference signal groups are orthogonal, the analog beamforming vectors corresponding to any two of the K reference signal groups cannot be considered to be the same, the K reference signal groups occupy K time windows, and the K time windows are orthogonal in the time domain.

9. The method according to claim 8, wherein any two antenna ports in the K1 antenna port groups are co-located or quasi-co-located (QCL); or any two antenna ports in the K1 antenna port groups are on a same carrier; or the first signaling is further used to determine the K1, and the first information is further used to determine the first channel quality.

10. The method according to claim 6, wherein the K antenna port groups respectively correspond to K reference signal groups; the K reference signal groups are respectively transmitted through the K antenna port groups; the first wireless signal is composed of the K reference signal groups; the antenna port group is composed of one antenna port, or, the antenna port group is composed of a plurality of antenna ports; the antenna port corresponds to a reference signal; the reference signal is transmitted through the antenna port; the reference signal is a SS (Synchronization Signal) or a CSI-RS (Channel State Information Reference Signal) or a DMRS of a PBCH (Physical Broadcast Channel).

11. A user equipment (UE) for multi-antenna transmission comprising: a first receiver, receiving a first signaling; a second receiver, receiving a first wireless signal; and a third transmitter, transmitting first information; wherein, K antenna port groups that comprise K groups of antenna ports are used to collectively transmit the first wireless signal; the first signaling is used to determine the K antenna port groups transmitting the first wireless signal; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; the K channel quality values are Reference Signal Received Powers (RSRPs) or Signal to Interference plus Noise Ratios (SINRs); K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values; the K1 is a positive integer less than or equal to the K; a

first proportional sequence corresponds to a ratio (ratios) among the K1 channel quality values, the first proportional sequence comprising a sequence of K1 proportions, wherein each of the K1 proportions corresponds to a ratio between one channel quality value to itself or to another of the K1 channel quality values; the first information is used to determine the K1 antenna port groups and the first proportional sequence; the first signaling is used to determine a target threshold; the target threshold is a non-negative real number; a first channel quality is a best channel quality value among the K1 channel quality values; a second channel quality is a worse channel quality value among the K1 channel quality values; a ratio between the second channel quality and the first channel quality is greater than or equal to the target threshold; the first information is carried by a PUSCH (Physical Uplink Shared Channel) or a PUCCH (Physical Uplink Control Channel).

12. The user equipment to claim 11, wherein the K channel quality values are broadband channel quality values; or the first proportional sequence comprises K1 positive real numbers less than or equal to 1, and the first proportional sequence comprises at least one 1; or the first proportional sequence comprises quantized values corresponding to K1 positive real numbers; or the first proportional sequence is composed of K1 positive real numbers, and the K1 positive real numbers are respectively ratios between the K1 channel quality values and the best channel quality value of the K1 channel quality values; or the first proportional sequence comprises K1-1 positive real number(s), and the K1-1 positive real number(s) is (are) a ratio (ratios) between a channel quality value(s) other than the best channel quality value among the K1 channel quality values and the best channel quality value; or the first proportional sequence comprises quantized values corresponding to K1-1 positive real number(s).

13. The user equipment to claim 11, wherein the first signaling is UE specific; or, the unit of the target threshold is dB; or, the first signaling implicitly indicates the target threshold; or, the K antenna port groups correspond to K reference signal groups, the time domain resources occupied by any two of the K reference signal groups are orthogonal, the analog beamforming vectors corresponding to any two of the K reference signal groups cannot be considered to be the same, the K reference signal groups occupy K time windows, and the K time windows are orthogonal in the time domain.

14. The user equipment to claim 13, wherein any two antenna ports in the K1 antenna port groups are co-located or quasi-co-located (QCL); or any two antenna ports in the K1 antenna port groups are on a same carrier; or the first signaling is further used to determine the K1, and the first information is further used to determine the first channel quality.

15. The user equipment to claim 11, wherein the K antenna port groups respectively correspond to K reference signal groups; the K reference signal groups are respectively transmitted through the K antenna port groups; the first wireless signal is composed of the K reference signal groups; the antenna port group is composed of one antenna port, or, the antenna port group is composed of a plurality of antenna ports; the antenna port corresponds to a reference signal; the reference signal is transmitted through the antenna port; the reference signal is a SS (Synchronization Signal) or a CSI-RS (Channel State Information Reference Signal) or a DMRS of a PBCH (Physical Broadcast Channel).

16. A base station for multi-antenna transmission comprising: a first transmitter, transmitting a first signaling; a second transmitter, transmitting a first radio signal; and a third receiver, receiving first information; wherein, K antenna port groups that comprise K groups of antenna ports of the base station are used to collectively transmit the first wireless signal; the first signaling is used to determine the K antenna port groups transmitting the first wireless signal; the K is a positive integer greater than 1; the K antenna port groups respectively correspond to K channel quality values; the K channel quality values are K non-negative real numbers; the K channel quality values are Reference Signal Received Powers (RSRPs) or Signal to Interference plus Noise Ratios (SINRs); K1 antenna port groups of the K antenna port groups correspond to K1 channel quality values of the K channel quality values; the K1 is a positive integer less than or equal to the K; a

first proportional sequence corresponds to a ratio (ratios) among the K1 channel quality values, the first proportional sequence comprising a sequence of K1 proportions, wherein each of the K1 proportions corresponds to a ratio between one channel quality value to itself or to another of the K1 channel quality values; the first information is used to determine the K1 antenna port groups and the first proportional sequence; the first signaling is used to determine a target threshold; the target threshold is a non-negative real number; a first channel quality is a best channel quality value among the K1 channel quality values; a second channel quality is a worse channel quality value among the K1 channel quality values; a ratio between the second channel quality and the first channel quality is greater than or equal to the target threshold; the first information is carried by a PUSCH (Physical Uplink Shared Channel) or a PUCCH (Physical Uplink Control Channel).

17. The base station to claim 16, wherein the K channel quality values are broadband channel quality values; or the first proportional sequence comprises K1 positive real numbers less than or equal to 1, and the first proportional sequence comprises at least one 1; or the first proportional sequence comprises quantized values corresponding to K1 positive real numbers; or the first proportional sequence is composed of K1 positive real numbers, and the K1 positive real numbers are respectively ratios between the K1 channel quality values and the best channel quality value of the K1 channel quality values; or the first proportional sequence comprises K1-1 positive real number(s), and the K1-1 positive real number(s) is (are) a ratio (ratios) between a channel quality value(s) other than the best channel quality value among the K1 channel quality values and the best channel quality value; or the first proportional sequence comprises quantized values corresponding to K1-1 positive real number(s).

18. The base station to claim 16, wherein the first signaling is UE specific; or, the unit of the target threshold is dB; or, the first signaling implicitly indicates the target threshold; or, the K antenna port groups correspond to K reference signal groups, the time domain resources occupied by any two of the K reference signal groups are orthogonal, the analog beamforming vectors corresponding to any two of the K reference signal groups cannot be considered to be the same, the K reference signal groups occupy K time windows, and the K time windows are orthogonal in the time domain.

19. The base station to claim 18, wherein any two antenna ports in the K1 antenna port groups are co-located or quasi-co-located (QCL); or any two antenna ports in the K1 antenna port groups are on a same carrier; or the first signaling is further used to determine the K1, and the first information is further used to determine the first channel quality.

20. The base station to claim 16, wherein the K antenna port groups respectively correspond to K reference signal groups; the K reference signal groups are respectively transmitted through the K antenna port groups; the first wireless signal is composed of the K reference signal groups; the antenna port group is composed of one antenna port, or, the antenna port group is composed of a plurality of antenna ports; the antenna port corresponds to a reference signal; the reference signal is transmitted through the antenna port; the reference signal is a SS (Synchronization Signal) or a CSI-RS (Channel State Information Reference Signal) or a DMRS of a PBCH (Physical Broadcast Channel).
