

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413078
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Komoriya; Mitsuo

Power receiving apparatus, power transmitting apparatus, control method of power receiving apparatus, control method of power transmitting apparatus, and non-transitory computer-readable storage medium

Abstract

A power receiving apparatus **200** wirelessly receives power from a power transmitting apparatus **100**, mutually performs device authentications with the power transmitting apparatus **100**, and determines content related to power reception on the basis of a result of a performed device authentication. The apparatus **200** is capable of performing control such that in response to success in an earlier performed device authentication among the authentications, another device authentication among the authentications is performed, and performing control such that in response to failure in the earlier performed device authentication, said another device authentication is not performed.

Inventors:	Komoriya; Mitsuo (Kanagawa, JP)
Applicant:	CANON KABUSHIKI KAISHA (Tokyo, JP)
Family ID:	68295351
Assignee:	Canon Kabushiki Kaisha (Tokyo, JP)
Appl. No.:	18/503028
Filed:	November 06, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240072546 A1	Feb. 29, 2024

Foreign Application Priority Data

JP	2018-087491	Apr. 27, 2018
----	-------------	---------------

Related U.S. Application Data

continuation parent-doc US 17076669 20201021 US 11837889 child-doc US 18503028
continuation parent-doc WO PCT/JP2019/016397 20190417 PENDING child-doc US 17076669

Publication Classification

Int. Cl.: **H02J7/00** (20060101); **H02J50/12** (20160101); **H02J50/80** (20160101); **H04W12/065** (20210101)

U.S. Cl.:

CPC **H02J7/00045** (20200101); **H02J50/12** (20160201); **H02J50/80** (20160201);
H04W12/065 (20210101);

Field of Classification Search

USPC: 320/108

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2006/0287763	12/2005	Ochi	700/231	H02J 7/00036
2010/0270969	12/2009	Sip	320/108	H02J 50/10
2013/0127410	12/2012	Park	320/108	H02J 7/0069
2013/0234661	12/2012	Yang	320/108	H04W 12/06
2016/0190871	12/2015	Nago	307/104	H02J 50/80
2019/0013703	12/2018	Shichino	N/A	H02J 50/12
2019/0021001	12/2018	Park	N/A	H02J 50/70
2020/0153239	12/2019	Pifferi	N/A	H02J 7/02
2020/0366136	12/2019	Tachiwa	N/A	H02J 50/90
2021/0408838	12/2020	Park	N/A	H02J 7/00034

Primary Examiner: Alam; Mohammed

Attorney, Agent or Firm: Canon U.S.A., Inc. IP Division

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a Continuation, and claims the benefit, of U.S. patent application Ser. No. 17/076,669, presently pending and filed Oct. 21, 2020, which is a Continuation of International Patent Application No. PCT/JP2019/016397, filed Apr. 17, 2019, which claims the benefit of Japanese Patent Application No. 2018-087491, filed Apr. 27, 2018, all of which are hereby incorporated by reference herein in their entireties.

BACKGROUND

Field

(1) The present disclosure relates to a power receiving apparatus, a power transmitting apparatus, a control method of the power receiving apparatus, a control method of the power transmitting apparatus, and a non-transitory computer-readable storage medium.

Background Art

(2) Technological development of a wireless power transmission system has been widely conducted in recent years. PTL1 discloses a power transmitting apparatus and a power receiving apparatus that comply with a standard (hereinafter referred to as “WPC standard”) established by Wireless Power Consortium (WPC), which is the standardization organization of contactless charging standards. PTL2 discloses a method for device authentication between a power transmitting apparatus and a power receiving apparatus for contactless charging. According to PTL2, the power transmitting apparatus transmits challenge data to the power receiving apparatus, and the power receiving apparatus transmits response data, which is generated by performing authentication computation on the challenge data, to the power transmitting apparatus. The power transmitting apparatus verifies the response data received from the power receiving apparatus, thereby executing a device authentication protocol. In PTL2, the configuration described above makes high-security authentication processing feasible.

CITATION LIST

Patent Literature

(3) PTL1: Japanese Patent Laid-Open No. 2016-007116 PTL2: Japanese Patent Laid-Open No. 2010-104097

(4) However, when authentication processing is performed, convenience may be impaired depending on the power transmitting apparatus and the power receiving apparatus. For example, when the power transmitting apparatus and the power receiving apparatus mutually perform authentication processing to enhance security, the following issue occurs. Specifically, even if the validity of the target apparatus is not recognized through the earlier performed authentication processing, it is necessary to wait for the execution of the other authentication processing, resulting in an occurrence of unnecessary processing.

SUMMARY

(5) The present disclosure has been made in view of the foregoing problems, and an object thereof is to reduce unnecessary processing caused when the validity of the target apparatus that performs authentication processing is not recognized.

(6) An aspect of the present disclosure provides a power receiving apparatus which comprises: a power receiving unit configured to wirelessly receive power from a power transmitting apparatus; an authentication unit configured to mutually perform device authentications with the power transmitting apparatus; and a control unit configured to determine content related to power reception on the basis of a result of a performed device authentication, wherein the control unit is capable of performing control such that in response to success in an earlier performed device authentication among the authentications, another device authentication among the authentications is performed, and performing control such that in response to failure in the earlier performed device authentication, said another device authentication is not performed.

(7) Further features of the present disclosure will become apparent from the following description of exemplary embodiments with reference to the attached drawings.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a block diagram illustrating an example configuration of a power transmitting apparatus.

(2) FIG. 2 is a block diagram illustrating an example configuration of a power receiving apparatus.

- (3) FIG. 3 is a block diagram illustrating an example configuration of a contactless charging system.
- (4) FIG. 4 is a diagram illustrating an example operation sequence of the contactless charging system, including USB authentication and WPT authentication.
- (5) FIG. 5A is a flowchart illustrating an example of a GP setting process performed by a control unit of the power transmitting apparatus.
- (6) FIG. 5B is a flowchart illustrating an example of a GP setting process performed by a control unit of the power receiving apparatus.
- (7) FIG. 6A is a diagram illustrating an example relationship between results of device authentication performed by the power transmitting apparatus and set values of GP.
- (8) FIG. 6B is a diagram illustrating an example relationship between results of device authentication performed by the power receiving apparatus and set values of GP.
- (9) FIG. 7 is a flowchart illustrating example state transitions made by the control unit of the power transmitting apparatus up to power transmission.
- (10) FIG. 8A is a diagram illustrating an example sequence for communication between a power transmitting apparatus having no WPT authentication function and a power receiving apparatus having no WPT authentication function.
- (11) FIG. 8B is a diagram illustrating an example sequence for communication between a power transmitting apparatus having a WPT authentication function and a power receiving apparatus having no WPT authentication function.
- (12) FIG. 8C is a diagram illustrating an example sequence for communication between a power transmitting apparatus having no WPT authentication function and a power receiving apparatus having a WPT authentication function.
- (13) FIG. 8D is a diagram illustrating an example sequence for communication between a power transmitting apparatus having a WPT authentication function and a power receiving apparatus having a WPT authentication function.
- (14) FIG. 9 is a flowchart illustrating example state transitions made by the control unit of the power receiving apparatus up to power transmission.
- (15) FIG. 10A is a diagram illustrating an example configuration of a Configuration Packet.
- (16) FIG. 10B is a diagram illustrating an example configuration of a Power Transmitter Capability Packet.
- (17) FIG. 11 is another example of the flowchart illustrating state transitions made by the control unit of the power receiving apparatus up to power transmission.
- (18) FIG. 12 is another example of the flowchart illustrating state transitions made by the control unit of the power transmitting apparatus up to power transmission.

DESCRIPTION OF THE EMBODIMENTS

Embodiment 1

(19) The following describes embodiments of the present disclosure with reference to the accompanying drawings.

(20) (System Configuration)

(21) FIG. 3 illustrates an example configuration of a wireless power transmission system (contactless charging system) according to this embodiment. In FIG. 3, a power transmitting apparatus (hereinafter referred to as “TX”) **100** wirelessly transmits power, which is supplied by wire using an AC adapter **301**, a USB cable **300**, and the like, to a power receiving apparatus (hereinafter referred to as “RX”) **200**. The RX **200** receives the power wirelessly transmitted from the TX **100** and charges, for example, a battery disposed in the RX **200**. The AC adapter **301** converts the power of the commercial power supply, which is supplied via a power supply plug **302**, into a voltage suitable for the TX **100** and supplies the voltage to the TX **100**.

(22) The configuration illustrated in FIG. 3 is an example, and any other configuration may be used. For example, in the following, wired power supply that enables device authentication will be

described as an example, although this is not intended to be limiting. That is, the present disclosure is also applicable to wired power supply that does not involve device authentication. In the following, it is assumed that wired power supply is performed in accordance with the USB Power-Delivery standard and that device authentication is performed in accordance with an Authentication standard supported by the USB Power-Delivery standard. However, any other standard may be used.

(23) While a single TX **100** and a single RX **200** are illustrated in FIG. **3**, a plurality of TXs **100** may receive power supplied by wire and transmit the power to a common single RX **200** or separate RXs **200**. Alternatively, a single TX **100** may transmit power to a plurality of RXs **200**. The following describes a case where contactless charging complying with the WPC (Wireless Power Consortium) standard is performed between the TX **100** and the RX **200**, although this is not intended to be limiting. Contactless charging may be performed in accordance with any other standard.

(24) (Apparatus Configuration)

(25) Next, an example configuration of a power transmitting apparatus (the TX **100**) and a power receiving apparatus (the RX **200**) available in the contactless charging system illustrated in FIG. **3** will be described.

(26) FIG. **1** is a block diagram illustrating an example configuration of the TX **100**. The TX **100** complies with the WPC standard and has functions specified in version 1.2.2 of the WPC standard (hereinafter referred to as “WPC standard v1.2.2”). It is assumed here that the TX **100** has a power supply capacity of outputting up to 15 watts of power to a charging unit of the RX **200** supporting the WPC standard like the TX **100**. In one example, the TX **100** can include a control unit **101**, a power supply unit **102**, a power transmitting unit **103**, a communication unit **104**, a power transmitting coil **105**, a display unit **106**, a memory **107**, a first authentication unit **108**, and a second authentication unit **109**. This embodiment may also be applied to the TX **100** capable of transmitting 15 watts or more of power or to a TX having a capacity of supplying only 15 watts or less of power.

(27) The control unit **101** includes, for example, one or more processors such as a CPU (Central Processing Unit) or an MPU (Micro Processing Unit) and controls the overall operation of the TX **100**. That is, the control unit **101** controls the operation of the power supply unit **102**, the power transmitting unit **103**, the communication unit **104**, the power transmitting coil **105**, the display unit **106**, the memory **107**, the first authentication unit **108**, and the second authentication unit **109**. The control unit **101** may be configured to include, for example, an application-specific integrated circuit (ASIC), an FPGA (field-programmable gate array), or the like. The control unit **101** determines content related to power transmission on the basis of a result of WPT authentication described below and a result of USB authentication for a power supply source (such as the AC adapter **301** and the USB cable **300**). For example, the content is the maximum value of the power value allowable at the time of power transmission.

(28) The power supply unit **102** receives power supply for the operation of the TX **100** from the AC adapter **301** via the USB cable **300** and supplies power for operating at least the control unit **101** and the power transmitting unit **103**. The power supply unit **102** is configured to be capable of supporting wired device authentication and power supply of a power supply device. For example, as illustrated in FIG. **3**, to receive power supply via the USB cable **300**, the power supply unit **102** can support the USB Power-Delivery standard and the Authentication standard for performing device authentication between connected USB devices. The TX **100** may receive power supply in compliance with a standard other than the USB Power-Delivery standard, or may perform device authentication in accordance with a standard other than the Authentication standard. Accordingly, the power supply unit **102** can be configured to be capable of supporting a standard other than these standards. Alternatively, the power supply unit **102** (or the first authentication unit **108** described below) may be configured to be capable of supporting a plurality of standards, and may determine

the standard to be used, for example, in accordance with the form of connection with the power supply source (for example, in accordance with which terminal of the TX **100** is used).

(29) The power transmitting unit **103** generates an AC voltage and an AC current to be transmitted to the RX **200** via the power transmitting coil **105**. The power transmitting unit **103** may convert, for example, a DC voltage to be supplied from the power supply unit **102** into an AC voltage by using a switching circuit having a half-bridge or full-bridge configuration using an FET (Field Effect Transistor). In this case, the power transmitting unit **103** can include a gate driver that controls ON/OFF of the PET.

(30) The communication unit **104** performs control communication with the RX **200** (a communication unit **204** in FIG. 2) for the control of contactless charging based on the WPC standard. The communication unit **104** can communicate with the RX **200** via so-called in-band communication, which is accomplished by modulating the AC voltage or current generated by the power transmitting unit **103** and superimposing information on wireless power. However, this is not intended to be limiting, and the communication unit **104** may communicate with the RX **200** via so-called out-band (out-of-band) communication. The out-band communication can be performed by, for example, NFC, RFID, Wi-Fi (registered trademark), Bluetooth (registered trademark) Low Energy, or the like. The out-band communication, described here, refers to communication performed without superimposing information on wireless power. At least a portion of the frequency band used for out-band communication is not included in the frequency band for power transmission. Further, the frequency band used for out-band communication may not be completely overlapped with the frequency band for power transmission.

(31) The display unit **106** displays information on the state of the TX **100** or the state of the contactless charging system including the devices illustrated in FIG. 3, such as the TX **100**, the RX **200**, the USB cable **300**, and the AC adapter **301**, in such a manner that the user can check the information. The display unit **106** can be constituted by, for example but not limitation, an LED (Light Emitted Diode). For example, the display unit **106** may include, in place of or in addition to the LED, a speaker, a vibration generation circuit, a display, and so on. The memory **107** stores the state of each element and the entire state of the TX **100** and the contactless charging system in FIG. 3.

(32) The first authentication unit **108** performs device authentication with the power supply unit **102** for the devices connected to the power supply unit **102**, namely, the USB cable **300** and the AC adapter **301**. In this embodiment, the first authentication unit **108** is assumed to perform device authentication complying with the USB Authentication standard. However, this is not intended to be limiting, and any other standard supporting device authentication, such as Qualcomm's Quick Charge standard, may be used.

(33) The second authentication unit **109** performs device authentication between the TX **100** and the RX **200** by communication via the communication unit **104**. In this embodiment, device authentication performed by the second authentication unit **109**, described below, is referred to as Wireless Power Transfer authentication or WPT authentication. In addition, the second authentication unit **109** may be divided into a portion to be used to perform WPT authentication on the RX **200**, and a portion to be used to receive WPT authentication from the RX **200**, or these portions may be integrated.

(34) In FIG. 1, the control unit **101**, the power supply unit **102**, the power transmitting unit **103**, the communication unit **104**, the memory **107**, the first authentication unit **108**, and the second authentication unit **109** are illustrated as separate blocks. However, a plurality of desired blocks among these blocks may be implemented in the same chip. For example, the power supply unit **102** supporting USB Power-Delivery and the first authentication unit **108** supporting the USB Authentication standard may be implemented in the same chip as a USB-related chip. In this case, the TX **100** can be configured to connect the control unit **101** and the USB-related chip by, for example, GPIO (General Purpose Input/Output) or serial communication. Further, for example, a

plurality of desired blocks among the second authentication unit **109**, the control unit **101**, the memory **107**, the power transmitting unit **103**, and the communication unit **104** may be implemented in the same chip. Alternatively, in FIG. 1, a single block may be divided into a plurality of blocks and may be implemented in a plurality of chips in some cases.

(35) FIG. 2 is a block diagram illustrating an example configuration of the RX **200**. Like the TX **100**, the RX **200** also complies with the WPC standard and has functions specified in the WPC standard v1.2.2. In one example, the RX **200** can include a control unit **201**, a display unit **202**, a power receiving unit **203**, a communication unit **204**, a power receiving coil **205**, a charging unit **206**, a battery **207**, an authentication unit **208**, and a memory **209**.

(36) The control unit **201** is configured to include, for example, one or more processors such as a CPU or an MPU, an ASIC, an FPGA, or the like and controls the overall operation of the RX **200**. That is, the control unit **201** controls the operation of the display unit **202**, the power receiving unit **203**, the communication unit **204**, the power receiving coil **205**, the charging unit **206**, the battery **207**, the authentication unit **208**, and the memory **209**. Further, the control unit **201** determines content related to power reception on the basis of a result of device authentication for the TX **100** described below. For example, the content is the maximum value of the power value for which a request is made to the TX **100**.

(37) The display unit **202** displays information, such as the state of power supply or the charging state of the RX **200**, in such a manner that the user can check the information. In this embodiment, the display unit **202** is assumed to be an LED. The display unit **202** may include, in addition to or in place of the LED, for example, a speaker, a vibration generation circuit, a display, and so on.

(38) The power receiving unit **203** receives an electromagnetic wave, which is radiated from the power transmitting coil **105**, via the power receiving coil **205** and converts an AC voltage and AC current obtained from received power into a DC voltage and DC current to be used when the control unit **201**, the charging unit **206**, and the like operate. In this embodiment, the power receiving unit **203** is assumed to have a capacity of outputting up to 15 watts of power to the charging unit **206**.

(39) The communication unit **204** performs control communication with the communication unit **104** of the TX **100** for the control of contactless charging based on the WPC standard. The control communication can be performed by load modulation, which is accomplished by varying the load on the RX **200** side to change the state of power transmission between the TX **100** and the RX **200** and varying the current flowing through the power transmitting coil **105** to transmit information. The communication unit **204** may perform control communication by in-band communication such as this load modulation or perform control communication by the out-band communication described above.

(40) The charging unit **206** charges the battery **207** by using the DC voltage and DC current supplied from the power receiving unit **203**. The authentication unit **208** mutually performs device authentication with the second authentication unit **109** of the TX **100** by communication via the communication unit **204**. The memory **209** stores the state of each element and the entire state of the RX **200** and the contactless charging system (FIG. 3). The TX **100** or the RX **200** supporting the WPC standard including WPT authentication is hereinafter expressed as “supporting the WPC standard version A”. It is assumed here that the WPC standard version A is a successor standard of the WPC standard v1.2.2, additionally having at least the WPT authentication function.

(41) In FIG. 2, the power receiving unit **203**, the authentication unit **208**, the control unit **201**, the memory **209**, the communication unit **204**, and the charging unit **206** are illustrated as separate blocks. However, a plurality of desired blocks among these blocks may be implemented in the same chip. Alternatively, in FIG. 2, a single block may be divided into a plurality of blocks and may be implemented in a plurality of chips in some cases.

(42) In the contactless charging system according to this embodiment, the first authentication unit **108** of the TX **100** performs device authentication with the AC adapter **301** and the USB cable **300**

using a first communication protocol (for example, USB authentication via a USB cable). The second authentication unit **109** of the TX **100** mutually performs device authentication with the RX **200** by using a second communication protocol using different media (for example, the power transmitting coil **105** and the power receiving coil **205**) from the first communication protocol.

(43) In this embodiment, the AC adapter **301**, the USB cable **300**, and the TX **100** (the power supply unit **102**) are USB devices. It can be confirmed that, in response to the USB devices supporting USB authentication and succeeding in USB authentication, an issue such as excessive heat generation is less likely to occur even if power determined in USB authentication is applied to these devices. That is, it can be said that if USB authentication is successful, the power supply unit **102** of the TX **100**, the USB cable **300**, and the AC adapter **301** do not excessively generate heat in response to the determined power being supplied to the power supply unit **102** of the TX **100** from the AC adapter **301** via the USB cable **300**.

(44) In contrast, if any of the power supply unit **102**, the USB cable **300**, and the AC adapter **301** does not support USB authentication, USB authentication is not successful. In this case, when the power determined in USB authentication is applied, an issue such as excessive generation of heat from any of the devices or the cable can occur. Devices not supporting USB authentication include a device supporting any of a plurality of versions of USB standards before the establishment of the USB authentication standard. In this embodiment, a USB device supporting any of a plurality of versions of USB standards before the establishment of the USB authentication standard is referred to as a legacy USB device.

(45) If any of the power supply unit **102**, the USB cable **300**, and the AC adapter **301** fails in USB authentication, an issue such as heat generation can occur when the power determined in USB authentication is applied. A failure in USB authentication includes a case where at least any one of the USB cable **300** and the AC adapter **301** can be a USB device nominally supporting but not actually supporting USB authentication.

(46) If the RX **200** and the TX **100** support the WPC standard version A and are mutually successful in WPT authentication, an issue such as excessive generation of heat from the RX **200** and the TX **100** is less likely to occur even if the RX **200** and the TX **100** exchange the predetermined power determined in the standard. If at least one of the RX **200** and the TX **100** does not support the WPC standard version A, in contrast, an issue such as excessive generation of heat from the apparatus not supporting the WPC standard version A can occur when the determined power described above is applied. Devices not supporting the WPC standard version A include a device supporting any of a plurality of versions of WPC standards preceding the WPC standard version A. In this embodiment, a TX or an RX supporting any of a plurality of versions of WPC standards preceding the WPC standard version A is referred to as a legacy TX or RX.

(47) Further, failures in WPT authentication between the TX **100** and the RX **200** include a case where these devices nominally support but do not actually support WPT authentication. Also in this case, WPT authentication is not successful. Thus, an issue such as excessive heat generation can occur when the determined power described above is applied. It should be noted that WPT authentication between devices supporting WPT authentication is always successful.

(48) In this embodiment, when the USB cable **300** and the AC adapter **301** are successful in USB authentication and when the RX **200** and the TX **100** are mutually successful in WPT authentication, it is determined that the predetermined power determined in the standard can be supplied. That is, the power receiving unit **203** of the RX **200** can supply the predetermined power (15 watts) to the load (in this embodiment, the charging unit **206**) in a state where an issue such as excessive heat generation is less likely to occur. If any of the TX **100** (the power supply unit **102**), the USB cable **300**, and the AC adapter **301** is not successful in USB authentication or either of the RX **200** and the TX **100** is not successful in WPT authentication, an issue is likely to occur for the supply of the predetermined power. That is, when the power receiving unit **203** of the RX **200** supplies a predetermined power of 15 watts to the load, an issue such as excessive heat generation

can occur. In the following, to avoid such a risk, the power to be supplied from the power receiving unit **203** is limited to a power value (for example, 5 watts or less) smaller than the predetermined power (15 watts) when authentication is not successful.

(49) (Process Procedure)

(50) Next, an example procedure of a process executed in a contactless wireless communication system will be described. FIG. **4** is a sequence chart illustrating an example procedure of a process including USB authentication and WPT authentication, which are executed in this embodiment. FIG. **5A** is a flowchart illustrating an example procedure of a process executed by the control unit **101** of the power transmitting apparatus (the TX **100**) for the setting of Guaranteed Power (hereinafter referred to as “GP”) according to this embodiment. FIG. **5B** is a flowchart illustrating an example procedure of a process executed by the control unit **201** of the power receiving apparatus (the RX **200**) for the setting of GP.

(51) GP is a power value guaranteed by the TX **100** regarding the output power for the load of the power receiving unit **203** even if the positional relationship between the TX **100** and the RX **200** is shifted and the power transmission efficiency between the power transmitting coil **105** and the power receiving coil **205** is reduced. The load of the power receiving unit **203** is the target to which the power receiving unit **203** supplies power, and includes at least the charging unit **206**. For example, when the GP is 5 watts, the TX **100** controls the power transmitting unit **103** so that the power receiving unit **203** can output 5 watts of power even if the positional relationship between the power transmitting and receiving coils is shifted and the power transmission efficiency between the coils is reduced. In this embodiment, the GP is limited in accordance with the result of authentication. This can prevent, for example, the occurrence of an issue such as excessive heat generation caused by the transmission of the power specified in the standard if authentication is not successful or authentication is not supported. First, an example of limit values of the GP to be used in a Negotiation described below in accordance with the results of USB authentication and WPT authentication will be described with reference to FIG. **6**.

(52) FIG. **6** include diagrams illustrating examples of limit values of the GP to be used in a Negotiation described below in accordance with the results of USB authentication and WPT authentication. FIG. **6A** illustrates the limit values of the GP for the TX **100**, and FIG. **6B** illustrates the limit values of the GP for the RX **200**.

(53) In FIG. **6A**, “not supporting USB authentication” in a column **600** indicates that at least any one of the power supply unit **102** of the TX **100**, the USB cable **300**, and the AC adapter **301** does not support USB authentication (but a device supporting USB authentication is successful in authentication). In a column **601**, “failed USB authentication” indicates that at least any one of the power supply unit **102** of the TX **100**, the USB cable **300**, and the AC adapter **301** (at least nominally) supports USB authentication, but has failed in USB authentication. In column **602**, “successful USB authentication” indicates that all of the power supply unit **102** of the TX **100**, the USB cable **300**, and the AC adapter **301** are successful in USB authentication. Further, a row **603** indicates that the RX **200** does not support WPT authentication, a row **604** indicates that the RX **200** supports WPT authentication, but has failed in WPT authentication, and a row **605** indicates that the RX **200** supports WPT authentication and is successful in WPT authentication. In the table, for fields containing three power values of the GP, namely, “0, 2.5, 5”, setting is performed in advance such that one of the values is employed.

(54) According to FIG. **6A**, when USB authentication is not supported (the column **600**), the GP is limited to 5 watts, regardless of the result of WPT authentication, to avoid excessive heat generation or the like. In the column **600**, when WPT authentication has failed (the row **604**), the GP may be limited to a smaller value than that when WPT authentication is not supported (the row **603**), such as 0 watts (no power transmission) or 2.5 watts (smaller than 5 watts). This is because a failure in WPT authentication indicates the possibility of the RX being, for example, a fake that nominally, but not formally, implements WPT authentication and does not meet the WPC standard.

In terms of excessive heat generation or the like, the GP is desirably limited to 5 watts. On the other hand, limiting the GP to a GP (0 watts or 2.5 watts) lower than that of a legacy RX that does not support WPT authentication but formally implements the standard can suppress or avoid power transmission to a fake that appears to support WPT authentication.

(55) Likewise, when USB authentication has failed (the column **601**), the GP may be limited to a smaller value than that when USB authentication is not supported (the column **600**), such as 0 watts (no power transmission) or 2.5 watts (smaller than 5 watts), regardless of the result of WPT authentication. This is because a failure in USB authentication indicates the possibility of the authentication-target USB device being, for example, a fake that nominally, but not formally, implements USB authentication. Accordingly, limiting the GP to 0 watts or 2.5 watts, which is smaller than that for a legacy USB device that does not support USB authentication but formally implements the standard, can suppress or avoid the supply of power from a fake that appears to support USB authentication.

(56) When USB authentication is successful (the column **602**), excessive heat generation or the like is less likely to occur for the power supply unit **102** of the TX **100**, the USB cable **300**, and the AC adapter **301** even if the RX **200** supplies 15 watts (the maximum value of the GP that can be supplied from the TX **100** to the RX **200**) to the load. Accordingly, the TX **100** sets the GP on the basis of the result of WPT authentication. For example, when WPT authentication is not supported (the row **603**), the TX **100** limits the GP to 5 watts for the reasons described above, and when WPT authentication has failed (the row **604**), the TX **100** limits the GP to a lower value (0 watts or 2.5 watts). When USB authentication is successful (the column **602**) and WPT authentication is also successful (the row **605**), it is determined that an issue such as excessive heat generation is less likely to occur, and the TX **100** sets the limit value of the GP to 15 watts, which is the maximum value of the power transmitting capacity of the TX **100** and the power receiving capacity of the RX **200**. Alternatively, the RX **200** may send to the TX **100** a request for 15 watts of power, which is the maximum value of the power transmitting capacity of the TX **100** and the power receiving capacity of the RX **200**, as the GP.

(57) This embodiment exemplifies a case where USB authentication is performed. If USB authentication is not performed, USB authentication may be regarded as being successful, and the column **602** in FIG. 6A may be held as a table of the limit values of the GP.

(58) The RX **200** does not perform USB authentication since no USB device is connected to the power supply system. Thus, the limit value of the GP is determined by the result of WPT authentication with the TX **100**. In FIG. 6B, a row **613** indicates that the TX **100** does not support WPT authentication, a row **614** indicates that the TX **100** supports WPT authentication, but has failed in WPT authentication, and a row **615** indicates that the TX **100** supports WPT authentication and is successful in WPT authentication. In the table, for a field containing three power values of the GP, namely, “0, 2.5, 5”, setting is performed in advance such that one of the values is employed.

(59) When WPT authentication is not supported (the row **613**), for reasons similar to those for the TX **100**, the GP is limited to 5 watts, and when WPT authentication has failed (the row **614**), the GP is limited to a lower GP (0 watts or 2.5 watts). When WPT authentication is successful (the row **615**), it is determined that the risk described above does not occur, and the RX **200** sets the limit value of the GP to 15 watts, which is the maximum value of the capacities of the TX **100** and the RX **200**.

(60) In this way, the TX **100** determines the maximum value of the GP that can be allowed as the power value for power transmission in a negotiation in a Negotiation phase described below on the basis of the USB authentication result, the WPT authentication result, and the set values illustrated in FIG. 6A. The RX **200** determines the maximum value of the GP for which a request is made to the TX **100** in a negotiation in the Negotiation phase on the basis of the USB authentication result, the WPT authentication result, and the set values illustrated in FIG. 6B. When both USB

authentication and WPT authentication are successful, the transmission power corresponding to the maximum capacity of the TX **100** and the RX **200** can be determined in a negotiation in the Negotiation phase.

(61) Next, an example procedure of a process from the activation of the contactless charging system illustrated in FIG. **3** to power transmission will be described with reference to FIG. **4** and FIG. **5**. If at least one device does not support authentication or has failed in authentication among the authentication-target devices in USB authentication and WPT authentication, the RX **200** operates so as not to send to the TX **100** a request for large power as the value of the GP.

(62) First, when the USB cable **300** and the AC adapter **301** are connected to the power supply unit **102** of the TX **100** (**400**), the control unit **101** of the TX **100** performs USB authentication (**401**, **S501**). In USB authentication, the control unit **101** causes the first authentication unit **108** to operate and determines whether all of the authentication-target USB devices (in this embodiment, both the USB cable **300** and the AC adapter **301**) support USB authentication. The first authentication unit **108** executes USB authentication on all the USB devices, and, if all the executed USB authentications are successful, the first authentication unit **108** determines “successful USB authentication”.

(63) In this embodiment, “not supporting USB authentication” and “failed USB authentication” are provided as authentication results in a case where any USB authentication is not successful. If at least one device supports USB authentication, but has failed in authentication, the first authentication unit **108** determines “failed USB authentication”. If all of the devices that are not successful in USB authentication are devices not supporting USB authentication, the first authentication unit **108** determines “not supporting USB authentication”. The first authentication unit **108** may determine either “failed USB authentication” or “not supporting USB authentication” on the basis of the attribute of a device that has failed in authentication. For example, if there is a device that has failed in authentication, the first authentication unit **108** can identify the attribute of the device and perform determination based on the attribute.

(64) In this embodiment, for example, if the AC adapter **301** is successful in USB authentication, but the USB cable **300** does not support USB authentication, “not supporting USB authentication” is determined. For example, if the USB authentication of the AC adapter **301** is successful and the USB cable **300** supports USB authentication, but has failed in authentication, “failed USB authentication” is determined. For example, if both the AC adapter **301** and the USB cable **300** are successful in USB authentication, “successful USB authentication” is determined. The control unit **101** holds the USB authentication result in the memory **107** (**S502**).

(65) Then, the control unit **101** determines power supply specifications for the AC adapter **301** regarding the voltage and current to be supplied from the AC adapter **301** in accordance with the sequence of USB PD (USB-Power Delivery standard) (**402**). Since the power supply voltage is determined by the internal configuration of the TX **100**, in this case, the current value is determined. In this embodiment, the voltage of the power supply unit **102** is assumed to be 15 V, and the output current of the power supply unit **102** is assumed to be up to 3 A. The control unit **101** of the TX **100**, when reducing the current value, determines the extent of reduction of the current value on the basis of the settings illustrated in FIG. **6A**. For example, when USB authentication is not supported, the maximum value of the GP that can be allowed at the time of power transmission in a negotiation in the Negotiation phase (described below) of the WPC standard is determined to be 5 watts on the basis of the column **600** in FIG. **6A**.

(66) The control unit **101** determines the current value in consideration with a loss in the TX **100**. For example, the system efficiency obtained in a case where the RX **200** outputs a GP of 5 watts when the positions of the power transmitting and receiving coils change and the efficiency between the coils becomes the lowest is assumed to be 50%. In this case, the power supplied from the power supply unit **102** to the power transmitting unit **103** or the control unit **101** is 10 watts ($5\text{ W} \times 2$). Since the power supply voltage is 15 V, the output current is $10\text{ W}/15\text{ V}=0.67\text{ A}$. In this

embodiment, when a USB device does not support USB authentication, the GP is limited to 5 watts. Accordingly, the current value to be determined by the power supply unit **102** by a negotiation with the AC adapter **301** on the basis of the sequence of USB PD is desirably about 0.67 A. The control unit **101** of the TX **100** determines power supply specifications for the AC adapter **301** on the basis of the current value to be determined. If USB authentication is successful, on the other hand, the power supply specifications are determined to be 2.0 A (15 W×2/15 V) so as to support a GP value of 15 watts.

(67) Then, the control unit **101** of the TX **100** activates the power transmitting unit **103** (**403**). The activation of the power transmitting unit **103** can be implemented by, for example, so-called power-on reset in which power is applied to at least any one of the control unit **101**, the power transmitting unit **103**, and the communication unit **104** from the power supply unit **102**.

Alternatively, the first authentication unit **108** may input a reset signal (not illustrated) (LO: about 0 V) to at least any one of the control unit **101**, the power transmitting unit **103**, and the communication unit **104** of the TX **100** to reset at least any one of these functional units. In this case, after the power supply specifications are determined and the value of the GP is determined, the first authentication unit **108** sets the reset signal to HI (for example, 3.3 V) to cancel the reset.

(68) Upon the activation of the power transmitting unit **103**, the TX **100** starts the operation complying with the WPC standard. In this embodiment, in addition to the phases complying with the WPC standard, an Authentication phase is defined as a phase for performing WPT authentication. In the Authentication phase, the TX **100** and the RX **200** execute device authentication based on WPT authentication. When both the TX **100** and the RX **200** support the Authentication phase, the TX **100** and the RX **200** first execute the processing of a Selection phase. Then, the phase transitions to a Ping phase and an Identification & Configuration phase (hereinafter referred to as “I & C phase”), and thereafter the Authentication phase is executed. After the Authentication phase, processing is executed in the order of a Negotiation phase, a Calibration phase, and a Power Transfer phase (hereinafter referred to as “PT phase”).

(69) In the Selection phase, the power transmitting unit **103** transmits an Analog Ping via the power transmitting coil **105** (**404**). The Analog Ping is a signal of small power used to detect an object present near the power transmitting coil **105**. The TX **100** detects the voltage value or current value of the power transmitting coil at the time of the transmission of the Analog Ping. If the voltage is less than a certain threshold or if the current value exceeds a certain threshold, the TX **100** determines that an object is present, and causes a transition to the Ping phase.

(70) In the Ping phase, the TX **100** transmits a Digital Ping (**405**), which is larger than the Analog Ping. The magnitude of the Digital Ping is equal to power sufficient to activate the control unit **201** of the RX **200**, which is present near the power transmitting coil **105**. When activated by the Digital Ping received via the power receiving coil **205**, the control unit **201** of the RX **200** notifies the TX **100** of the magnitude of the received voltage (**406**). Then, the phase transitions to the I & C phase. Upon receipt of the notification of the value of the received voltage, the TX **100** causes a transition to the I & C phase.

(71) In the I & C phase, the RX **200** transmits an ID Packet and a Configuration Packet to the TX **100** (**407** and **408**). The TX **100** responds to the Configuration Packet transmitted from the RX **200** by using acknowledge (ACK). Then, the TX **100** and the RX **200** terminate the I & C phase and cause a transition to the Authentication phase. When the I & C phase is terminated, the TX **100** and the RX **200** can transmit data to each other.

(72) Then, the second authentication unit **109** and the authentication unit **208** of the RX **200** mutually perform WPT authentication processing in the Authentication phase (**409**, **S503**, and **S513**). The authentication target of the TX **100** is the RX **200** serving as a power receiving apparatus in the contactless charging system. The authentication target of the RX **200** is the TX **100** serving as a power transmitting apparatus in the contactless charging system. The details of the Authentication phase will be described below.

(73) The control unit **101** of the TX **100** holds the result of WPT authentication in the memory **107** (S504). The control unit **201** of the RX **200** holds the result of WPT authentication in the memory **209** (S514). The control unit **101** of the TX **100** determines the maximum value of the GP to be used in the Negotiation phase on the basis of the result of USB authentication held in the memory **107** in S502, the result of WPT authentication held in the memory **107** in S504, and FIG. 6A (410a and S505). On the other hand, the control unit **201** of the RX **200** determines the maximum value of the GP to be used in the Negotiation phase on the basis of the result of WPT authentication held in the memory **209** in S514 and FIG. 6B (410b and S515).

(74) Thereafter, the control unit **101** of the TX **100** and the control unit **201** of the RX **200** perform a negotiation in the Negotiation phase and determine the GP (411). Here, the transmission power is negotiated on the basis of the results of device authentications performed by the first authentication unit **108** (USB authentication) and the second authentication unit **109** (WPT authentication) of the TX **100**, and the authentication unit **208** of the RX **200** (WPT authentication). That is, a negotiation is performed such that the transmission power is less than or equal to the transmission power allowed for the limited GP value (410a and 410b).

(75) For example, in the RX **200**, if the result of WPT authentication indicates “successful WPT authentication”, as illustrated in FIG. 6B, the setting of the GP to up to 15 watts is permitted. If the result of WPT authentication indicates “failed WPT authentication”, on the other hand, the GP is limited to 5 watts or a smaller value. In the Negotiation phase, the control unit **201** sends to the TX **100** a request for the GP.

(76) In the TX **100**, if the result of USB authentication indicates “successful USB authentication” and the result of WPT authentication indicates “successful WPT authentication”, as illustrated in FIG. 6A, the setting of the GP to up to 15 watts is permitted. If the result of USB authentication indicates “not supporting USB authentication”, on the other hand, the GP is limited to 5 watts or a smaller value. In this case, in the Negotiation phase, if a request for a GP exceeding 5 watts is sent from the control unit **201** of the RX **200**, the control unit **101** of the TX **100** transmits a NAK in response to the request. In response to a request for a GP less than or equal to the limit value, on the other hand, the control unit **101** transmits acknowledge (ACK).

(77) As described above, the maximum value of the GP is determined on the basis of the results of USB authentication and mutual WPT authentication between the TX **100** and the RX **200**. Accordingly, if any of a plurality of authentications has failed, the magnitude of the GP is limited, and excessive heat generation or the like can be prevented. The control unit **101** can set the GP to the maximum value of the capacity of the power transmitting unit **103** only when all the authentications are successful.

(78) If no USB authentication is performed, the maximum value of the GP is determined on the basis of the result of mutual WPT authentication between the TX **100** and the RX **200**. In this case, as described above, USB authentication may be regarded as being successful on the basis of the result of WPT authentication performed on the RX **200** by the TX **100**, and the GP may be limited on the basis of the column **602** in FIG. 6A.

(79) Then, the TX **100** and the RX **200** send the reason for limiting the GP to each other (412). The control unit **101** of the TX **100** notifies the control unit **201** of the RX **200** of the reason for limiting the GP. In response to the notification of the reason, the RX **200** is notified of the results of device authentications performed by the first authentication unit **108** and the second authentication unit **109**. The control unit **201** of the RX **200** notifies the control unit **101** of the TX **100** of the reason for limiting the GP. In response to the notification of the reason, the TX **100** is notified of the result of the device authentication performed by the authentication unit **208**.

(80) The notification of the reason may be a RESULT packet described below (see 820a and 820b in FIG. 8D). In this embodiment, the control unit **101** of the TX **100** transmits, to the control unit **201** of the RX **200**, a RESULT packet storing the result of WPT authentication and the result of USB authentication relating to the power supply unit **102** of the TX **100**. For example, the control

unit **101** provides the RESULT packet with 1 bit for storing the WPT authentication result such that “1” is stored for successful WPT authentication or “0” is stored otherwise.

(81) Further, the control unit **101** provides the RESULT packet with 1 bit for storing the result of USB authentication with the AC adapter **301** and the USB cable **300** such that “1” is stored for successful USB authentication or “0” is stored otherwise. The control unit **101** transmits a RESULT packet in which the result of device authentication is stored in the manner described above.

(82) The USB authentication result to be transmitted from the TX **100** to the RX **200** will now be described in detail. The USB authentication result is data indicating the result of USB authentication of the TX **100**. In one example, the USB authentication result is transmitted by using a Power Transmitter Capability Packet based on the WPC standard v1.2.2, as illustrated in FIG.

10B. For example, in the packet configuration illustrated in FIG. **10B**, at least either bit 6 and bit 7 (1100) in Bank 1 or bits 2 to 7 (1011) in Bank 2, which are “Reserved”, can be used for the transmission of the USB authentication result. The TX **100** transmits a packet in which these bits store at least any one of “whether the function of sending a notification of the USB authentication result exists”, “whether USB authentication is completed”, and “the result of USB authentication”.

(83) Likewise, the control unit **201** of the RX **200** transmits, to the control unit **101** of the TX **100**, a RESULT packet storing the result of WPT authentication. For example, the control unit **201** provides the RESULT packet with 1 bit for storing the WPT authentication result such that “1” is stored for successful WPT authentication or “0” is stored otherwise. The control unit **201** transmits a RESULT packet storing the result of device authentication in the manner described above.

(84) Thereafter, the control unit **101** of the TX **100** and the control unit **201** of the RX **200** execute the processing of the Calibration phase (**413**) and causes a transition to the PT phase. In the PT phase, power is transmitted from the TX **100** to the RX **200** (**414**). The RX **200** supplies power to the load on the basis of the received power. The control unit **201** of the RX **200** may display power limit on the display unit **202** in accordance with the notification of the reason (**415b**). Likewise, the control unit **101** of the TX **100** may display power limit on the display unit **106** in accordance with the notification of the reason (**415a**).

(85) For example, the message “low-speed charging is in progress because of failed USB authentication (caused by the USB device)” may be displayed on the basis of the bit indicating the USB authentication result or the WPT authentication result in the RESULT packet. As a result of the negotiation, if the GP is determined to be 0 watts, that is, if no power transmission is performed, the message “no charging is performed because of failed USB authentication (caused by the USB device)” may be displayed. With the display described above, the user can know that a longer time is taken for charging than when the power is not limited, or can take measures such as replacing the USB cable or USB adapter with a product supporting USB authentication. The display described above may indicate the result of WPT authentication. Even in this case, similar advantages are achieved.

(86) As a result of the negotiation, if the transmission power is not limited, the message “high-speed charging is in progress” may be displayed. The display described above may be performed by using different LED colors or illumination patterns depending on the case where the transmission power is limited, the case where the transmission power is not limited, and the case where charging is not performed. Alternatively, in these cases, different sounds or vibrations may be used to notify the user, thereby achieving similar advantages.

(87) In this embodiment, in USB authentication, the TX **100** is activated after the determination of whether to limit the transmission power. Alternatively, the USB device and the contactless charging system may be simultaneously activated to perform USB authentication and WPT authentication asynchronously. In this case, if the limiting of the transmission power by USB authentication is recognized after the TX **100** starts power transmission, limiting the transmission power of the contactless charging system by a Negotiation again can achieve similar advantages.

(88) It should be noted that, as in this embodiment, the TX **100** for WPT authentication may be

activated after the determination of whether to limit the transmission power in USB authentication, thereby expecting further advantages. When the TX **100** determines the GP in the Negotiation phase (**411**), it has already been determined in USB authentication whether to limit the transmission power. Thus, there is no need to perform processing for performing a Negotiation again, and the processing can be simplified.

(89) (Operation of WPT Authentication and Backward Compatibility)

(90) When larger power is to be transmitted in accordance with the WPC standard, as described above, it is considered to add the specification of the WPT authentication function to avoid the occurrence of an issue such as excessive heat generation to the existing WPC standard. It is important that a TX having a WPT authentication function can correspond to an RX having a similar WPT authentication function and can ensure backward compatibility with a legacy RX. It is also important that an RX having a WPT authentication function ensures backward compatibility with a legacy TX. However, a technique is not known for taking into account backward compatibility by adding the WPT authentication function while complying with the legacy WPC standard.

(91) FIG. 7 illustrates an example procedure of a process of the control unit **101** of the TX **100** according to this embodiment. FIG. 8 includes sequence charts describing backward compatibility by the version-A-supporting or legacy TX **100** or RX **200**. In the following, a description will be made assuming that WPT authentication is challenge-response device authentication using a digital certificate, like USB authentication, although this is not intended to be limiting. The TX **100** operates an initiator that transmits a challenge text to the RX **200**, and the RX **200** operates as a responder that encrypts the challenge text and transmits the encrypted challenge text to the TX **100**. Likewise, when the RX **200** operates as an initiator that transmits a challenge text to the TX **100**, the TX **100** operates as a responder that encrypts the challenge text and transmits the encrypted challenge text to the RX **200**. The initiator refers to a device that performs WPT authentication, and the responder refers to a device that receives WPT authentication.

(92) FIG. 9 is a flowchart illustrating the operation of the control unit **201** of the RX **200**. FIG. 10A is a diagram illustrating an example bit configuration of a Configuration Packet based on the WPC standard.

(93) First, categories of TXs and RXs based on the WPC standard v1.2.2 will be described prior to the description of the procedure of each process. TXs and RXs with a GP of 5 watts are categorized as Basic Power Profile (BPP). TXs and RXs with a GP greater than 5 watts and less than or equal to 15 watts are categorized as Extended Power Profile (EPP). In the WPC standard v1.2.2, furthermore, the function of performing a negotiation between a TX and an RX regarding the GP is added, and the TXs and RXs categorized as EPP have the Negotiation function. The TXs and RXs categorized as BPP are further categorized into devices supporting the Negotiation function and devices not supporting the Negotiation function.

(94) A TX can determine whether an RX has the Negotiation function, by using the value of a Neg bit (Bank 4, bit 7) in a Configuration Packet (FIG. 10A) containing settings information of the RX. The Neg bit “1” indicates that the RX has the Negotiation function, and the Neg bit “0” indicates that the RX does not have the Negotiation function. In this embodiment, it is assumed that a legacy TX and RX have the Negotiation function and that a Negotiation is executed in the Negotiation phase, unless otherwise specified.

(95) It is important that a TX and an RX based on the WPC standard version A supporting WPT authentication ensure backward compatibility with a legacy RX and TX supporting the WPC standard v1.2.2, respectively. That is, it is important that a TX supporting the WPC standard version A consistently operates also for an RX supporting a WPC standard prior to the version A, and an RX supporting the version A consistently operates also for a TX supporting a WPC standard prior to the version A.

(96) Accordingly, the backward compatibility of the TX **100** and the RX **200**, which support the

version A according to this embodiment, with the WPC standard v1.2.2 will be described with reference to FIG. 7, FIG. 8, and FIG. 9. A TX and an RX supporting the legacy EPP of the WPC standard v1.2.2 causes a state transition in the order of the Selection phase, the Ping phase, the I & C phase, the Negotiation phase, the Calibration phase, and the PT phase. If at least any one of the legacy TX and RX is a BPP device that does not have the Negotiation function, the TX and the RX cause a state transition to the PT phase after the transition to the Selection phase, the Ping phase, and the I & C phase.

(97) As described above, if both the TX and the RX support the Authentication phase, the TX and the RX cause a transition to the Authentication phase after the transition to the Selection phase, the Ping phase, and the I & C phase. After the transition to the Authentication phase, the TX and the RX cause a transition in the order of the Negotiation phase, the Calibration phase, and the PT phase.

(98) The Authentication phase is executed prior to the Negotiation phase, for example. This is because, as described with reference to FIG. 6, the value of the GP changes depending on the result of WPT authentication. When the TX and the RX cause a transition to the Authentication phase after determining the GP by a negotiation in the Negotiation phase, the determined GP can be reset in accordance with the result of the Authentication phase. That is, after the GP is determined, it can be necessary to make a change to reduce the GP to avoid excessive heat generation or the like, depending on the result of WPT authentication. If the GP is re-changed in the way described above, the complexity of the procedure up to the transition to the PT phase can increase, or the time required for the procedure can be long. In contrast, the Authentication phase is executed prior to the Negotiation phase, thereby determining the GP in the Negotiation phase on the basis of the GP limited in the Authentication phase. Accordingly, limiting the GP in the Authentication phase prior to the Negotiation phase makes it possible to cause a quick transition to the PT phase without causing resetting of the GP until the transition to the PT phase.

(99) [Case where Both TX **100** and RX **200** are Legacy]

(100) First, an example process based on the WPC standard v1.2.2 when both the TX **100** and the RX **200** support the legacy EPP will be described with reference to FIG. 7, FIG. 8A, and FIG. 9. In the following, it is assumed that the TX **100** is successful in USB authentication with the USB cable **300** and the AC adapter **301**. In this example process, only a portion of the flowcharts illustrated in FIG. 7 and FIG. 9 regarding the legacy EPP is used. That is, for the legacy TX **100**, the processing of S703 to S708b in FIG. 7 is not present, and for the legacy RX **200**, the processing of S903 to S907b and S908 in FIG. 9 is not present. In FIG. 8A, only the sequence after the I & C phase, which is related to backward compatibility, is illustrated.

(101) After the processing of the Selection phase and the Ping phase is performed between the TX **100** and the RX **200**, a transition to the I & C phase occurs (S701). In the I & C phase, the RX **200** transmits an Identification Packet (ID Packet) to the TX **100** (800 and S901). The ID Packet stores, in addition to individual identification information of the RX **200**, an information element that specifies the version (in this case, v1.2.2) of the WPC standard supported.

(102) Then, the RX **200** transmits a Configuration Packet to the TX **100** (801 and S901). The Configuration Packet based on the WPC standard v1.2.2 includes Maximum Power Value, which is a maximum power value that can be supplied from the RX **200** to the load, and a Neg bit, which is a bit indicating whether the RX **200** has the Negotiation function. Here, the RX **200** sets the Neg bit to “1”, which indicates that the RX **200** has the Negotiation function.

(103) Upon receipt of the ID Packet and the Configuration Packet from the RX **200** (S702), the TX **100** determines whether the RX **200** has the Negotiation function (S704). As described above, the legacy TX **100** does not execute the processing of S703 and proceeds to S704, which is processing corresponding to NO in S703. Since the RX **200** has the Negotiation function (YES in S704), the TX **100** transmits an ACK in response to the Configuration Packet (S713 and 802) and causes a transition to the Negotiation phase (S709).

(104) If the RX **200** is BPP not supporting Negotiation (the Neg bit is 0) (NO in S704), the TX **100** causes a transition to the PT phase without transmitting an ACK (S712). If the TX **100** is BPP and does not support Negotiation, the TX **100** also causes a transition to the PT phase without transmitting an ACK. In this case, the GP is limited to 5 watts.

(105) The RX **200** waits for the reception of an ACK in response to the Configuration Packet (S902). Upon receipt of an ACK (YES in S902), the RX **200** determines that the TX **100** supports the Negotiation function, and causes a transition to the Negotiation phase (S909). Here, as described above, the processing of S908 is not executed. Then, the RX **200** transmits a Specific Request packet representing a request for the power required therefor (for example, 15 watts). Specifically, the RX **200** transmits, to the TX **100**, a Specific Request packet (Specific Request (15 W)) including an information element indicating a request for 15 watts as GP (803).

(106) If no ACK is received within 15 ms from the transmission of the Configuration Packet (NO in S902), the RX **200** based on the WPC standard v1.2.2 determines that the TX **100** is BPP not having the Negotiation function (S911). Then, the RX **200** causes a state transition to the PT phase (S912). As described above, here, the processing of S903 is not executed.

(107) Upon receipt of the Specific Request (15 W), the TX **100** compares the power transmitting capacity thereof and the requested amount of power (15 watts), and transmits a positive response (ACK) to the RX **200** if the requested amount of power can be transmitted. On the other hand, if the requested amount of power cannot be transmitted, the TX **100** transmits a negative response (NAK) to the RX **200**. Here, the TX **100** determines that 15 watts of power can be transmitted, determines the GP to be 15 watts (S710), and transmits an ACK (804).

(108) Then, the TX **100** causes a transition to the Calibration phase (S711). Upon receipt of an ACK from the TX **100** in response to the Specific Request transmitted in 803, the RX **200** causes a state transition to the Calibration phase (S910). In the Calibration phase, the TX **100** adjusts the power transmitted from the TX **100** to the RX **200** on the basis of the correlation between a value measured in the TX **100** and the value of the received power measured in the RX **200**. After the Calibration phase is completed, the TX **100** and the RX **200** cause a state transition to the PT phase and start wireless power transmission (S712 and S912).

(109) As described above, the TX **100** based on the WPC standard v1.2.2 determines, based on the Neg bit, whether the RX **200** is EPP or BPP having the Negotiation function or is BPP not having the Negotiation function. If the RX **200** is EPP or BPP having the Negotiation function, the TX **100** causes a state transition to the Negotiation phase and executes a negotiation regarding transmission power. Then, the TX **100** starts power transmission. On the other hand, if the RX **200** is BPP not having the Negotiation function, the TX **100** causes a transition to the PT phase without the transition to the Negotiation phase, and executes the transmission of relatively low power. If an ACK is received within 15 ms from the transmission of the Configuration Packet, the RX **200** based on the WPC standard v1.2.2 causes a transition to the Negotiation phase. If no ACK is received, the RX **200** causes a transition to the PT phase. The operation described above ensures the compatibility of the TX **100** and the RX **200** having the Negotiation function with the TX **100** and the RX **200** not having the Negotiation function in the WPC standard v1.2.2.

(110) [Case where TX **100** Supports Version A and RX **200** is Legacy]

(111) An example process in a case where the TX **100** supports the version A and the RX **200** is legacy will be described with reference to FIG. 6A, FIG. 7, FIG. 8B, and FIG. 10A. In the following, it is assumed that the TX **100** is successful in USB authentication with the USB cable **300** and the AC adapter **301**. The following description entirely relates to backward compatibility in the WPC standard, and the following discussion is thus applicable even when the TX **100** has a configuration not including the first authentication unit **108**.

(112) First, an Auth bit in the Configuration Packet will be defined prior to the description of the procedure of the process. FIG. 10A is a diagram illustrating the configuration of the Configuration Packet in the WPC standard v1.2.2. Portions not related to the description in this embodiment will

not be described. The Configuration Packet has a plurality of Reserved areas. Examples include a Reserved area 1000 of bits 0 to 7 in Bank 1, a Reserved area 1001 of bits 4 to 6 in Bank 2, and a Reserved area 1002 of bits 0 to 2 in Bank 4. In this embodiment, the Auth bit is arranged in bit 6 in Bank 2. However, the arrangement of the Auth bit is not limited to this, and the Auth bit may be arranged in any other Reserved area. In the WPC standard v1.2.2, all the bits in the Reserved areas are “0”. The RX **200** stores “1” in the Auth bit when the RX **200** supports WPT authentication, and stores “0” in the Auth bit when the RX **200** does not support WPT authentication. Since the Auth bit is stored at a Reserved bit, even an RX supporting an old-generation standard that does not recognize the position at which the Auth bit is stored can store “0” as the value at this position.

(113) The TX **100** determines, based on the Auth bit in the Configuration Packet, whether the RX **200** supports WPT authentication (S703). In this example process, the RX **200** is legacy, and thus the Auth bit is “0”. Accordingly, the TX **100** determines that the RX **200** does not support WPT authentication (NO in S703).

(114) If the RX **200** has the Negotiation function (YES in S704), the TX **100** transmits an ACK in response to the Configuration Packet (S713 and 802), and causes a transition to the Negotiation phase. Upon receipt of a request for 15 watts as GP from the RX **200** (803), the TX **100** transmits, to the RX **200**, a NAK for rejecting the request (805). This is because since the RX **200** does not support WPT authentication, the TX **100** determines that 15 watts of power should not be transmitted to prevent the RX **200** from causing excessive heat generation or the like.

(115) Since the request is rejected by the NAK, the RX **200** transmits a General Request, which is determined in the WPC standard v1.2.2, to know a value of the GP that can be set by the TX **100**. In this embodiment, in the General Request, a message indicating a request for a Transmitter Capability Packet is represented by General Request (capability).

(116) The TX **100** receives the General Request (capability) (806). Then, the TX **100** stores information indicating 5 watts of power in Guaranteed Power Value in the Power Transmitter Capability Packet and transmits the information to the RX **200** (807). A value of 5 watts is a value corresponding to not supporting WPT authentication (the row 603) and successful USB authentication (the column 602), on the basis of the settings illustrated in FIG. 6A, as the maximum value of the GP that can be allowed at the time of power transmission. The Transmitter Capability Packet is a packet defined in the WPC standard v1.2.2, including information on the maximum value of the GP that can be allowed in a Negotiation.

(117) If the RX **200** does not have the Negotiation function (NO in S704), the TX **100** causes a transition to the PT phase without transmitting an ACK (S712). In this case, the GP is limited to 5 watts.

(118) Since the RX **200** is legacy, the RX **200** performs the processing described in the [Case where both TX **100** and RX **200** are Legacy] section.

(119) As described above, the Auth bit defined in this embodiment allows the TX **100** supporting the WPC standard version A to consistently operate also for a legacy RX supporting a WPC standard prior to the version A.

(120) [Case where Both TX **100** and RX **200** Support Version A]

(121) Next, a case where both the TX **100** and the RX **200** support WPT authentication processing will be described with reference to FIG. 6, FIG. 7, FIG. 8D, and FIG. 9. In the following, it is assumed that the TX **100** is successful in USB authentication with the USB cable **300** and the AC adapter **301**. Prior to the description of the processing, the operation of the TX **100** and the RX **200** of the version A supporting WPT authentication will be described.

(122) The RX **200** of the version A transmits, to the TX **100**, a Configuration Packet storing “1” in the Auth Bit (801 and S901). If it is determined, based on the Auth Bit in the Configuration Packet, that the RX **200** supports WPT authentication (YES in S703), the TX **100** of the version A transmits an ACK (auth) to the RX **200** (S705 and 802a). The ACK (auth) is an acknowledge in response to the Configuration Packet having a bit pattern different from and distinguishable from

the ACK and is a packet indicating that the TX **100** supports WPT authentication.

(123) After the transmission of the ACK (auth), the TX **100** causes a transition to the Authentication phase (**S706**). On the other hand, upon receipt of an ACK (auth) rather than an ACK (NO in **S902** and YES in **S903**), the RX **200** determines that the TX **100** supports WPT authentication (**S904**). Then, the RX **200** causes a transition to the Authentication phase (**S905**).

(124) In FIG. **8D**, **814a** to **820a** and **814b** to **820b** are an example of WPT authentication according to this embodiment. The TX **100** first transmits a GET_DIGESTS message to the RX **200** (**814a** and **S707a**). The RX **200** receives the GET_DIGESTS message (**S906a**). The GET_DIGESTS Packet is a Packet indicating a request for information relating to a digital certificate held by the RX **200**. The RX **200** transmits a DIGEST in response to the GET_DIGESTS Packet (**815a**). The DIGEST is information relating to a digital certificate owned by the RX **200**. Then, the TX **100** transmits, to the RX **200**, a GET_CERTIFICATE Packet indicating a request for detailed information relating to the digital certificate (**816a**). The RX **200** transmits a CERTIFICATE in response to the GET_CERTIFICATE Packet (**817a**).

(125) Then, the TX **100** transmits a CHALLENGE message including a challenge text to the RX **200** (**818a**). The RX **200** transmits, to the TX **100**, a RESPONSE obtained by encrypting the challenge text (**819a**). The TX **100** transmits a RESULT (success) to the RX **200** when the validity of the RESPONSE is confirmed (**820a** and **S708a**). The RX **200** receives the RESULT (success) (**S907a**). The RESULT (success) packet indicates that, as a result of the RESPONSE, WPT authentication is successful. As a result of the RESPONSE, if authentication has failed, the TX **100** transmits a RESULT (fail) indicating a failure instead of the RESULT (success).

(126) Then, the RX **200** transmits a GET_DIGESTS message to the TX **100** (**814b** and **S906b**). The TX **100** receives the GET_DIGESTS message (**S707b**). The GET_DIGESTS Packet is a Packet indicating a request for information relating to a digital certificate held by the TX **100**. The TX **100** transmits a DIGEST in response to the GET_DIGESTS Packet (**815b**). The DIGEST is information relating to a digital certificate owned by the TX **100**. Then, the RX **200** transmits, to the TX **100**, a GET_CERTIFICATE Packet indicating a request for detailed information relating to the digital certificate (**816b**). The TX **100** transmits a CERTIFICATE in response to the GET_CERTIFICATE Packet (**817b**).

(127) Then, the RX **200** transmits a CHALLENGE message including a challenge text to the TX **100** (**818b**), and the TX **100** transmits, to the RX **200**, a RESPONSE obtained by encrypting the challenge text (**819b**). If the validity of the RESPONSE is confirmed, the RX **200** transmits a RESULT (success) to the TX **100** (**820b** and **S907b**). The TX **100** receives the RESULT (success) (**S708b**). The RESULT (success) packet indicates that, as a result of the RESPONSE, WPT authentication is successful. As a result of the RESPONSE, if authentication has failed, the RX **200** transmits a RESULT (fail) indicating a failure instead of the RESULT (success).

(128) The TX **100** and the RX **200** transmit the RESULT (success) or the RESULT (fail), and cause a transition to the Negotiation phase upon receipt of the RESULT (success) or the RESULT (fail) (**S709** and **S909**).

(129) If USB authentication and mutual WPT authentication are successful, the TX **100** determines, based on FIG. **6A**, 15 watts of power, which corresponds to successful WPT authentication (the row **605**) and successful USB authentication (the column **602**), to be the allowed maximum value of the GP, and performs a Negotiation. On the other hand, the RX **200** determines, based on FIG. **6B**, 15 watts of power, which corresponds to successful WPT authentication (the row **615**), to be the allowed maximum value of the GP, and performs a Negotiation. That is, the TX **100** is requested by the RX **200** to set the power value of the GP to 15 watts (**803**). Since the TX **100** has determined the power value of the GP to be 15 watts for a negotiation, the TX **100** transmits an ACK to the RX **200** to acknowledge the request (**804**).

(130) If USB authentication or WPT authentication has failed, the TX **100** determines, based on FIG. **6A**, the maximum value of the GP allowed in the Negotiation phase. If WPT authentication

has failed, the RX **200** also determines, based on FIG. 6B, the maximum value of the GP allowed in the Negotiation phase. Upon receipt of the RESULT (fail), the TX **100** may not perform power transmission. Upon receipt of the RESULT (fail), the RX **200** may not perform a power transmission request.

(131) With the configuration described above, content related to power transmission or power reception can be determined more accurately. An additional advantage of enhancing security is also achieved.

(132) Accordingly, the TX **100** according to this embodiment consistently operates not only for an RX supporting a WPC standard prior to the version A but also for an RX supporting the version A.

(133) While an example has been described in which the TX **100** first authenticates the validity of the RX **200** and then the RX **200** authenticates the validity of the TX **100** in the Authentication phase, validity authentication may be performed in the reverse order. That is, the RX **200** may first authenticate the TX **100**, and then the TX **100** may authenticate the RX **200**. In this case, in FIG. 8D, **814a** to **820a** and **814b** to **820b** are performed in the reverse order. Further, in FIG. 7, **S707a** and **S708a** are performed after **S707b** and **S708b**. Further, in FIG. 9, **S906a** and **S907a** are performed after **S906b** and **S907b**.

(134) The order in which the TX **100** and the RX **200** perform authentication may be determined in advance or may not be determined. However, to correctly perform authentication in the Authentication phase, the initiator preferably performs the following operation after transmitting a GET_DIGESTS. Until the initiator transmits the RESULT (success) or the RESULT (fail) to the responder, the initiator suspends or stops responding even if the GET_DIGESTS is received from any other device. After the GET_DIGESTS is received, on the other hand, the responder preferably performs the following operation. Until the RESULT (success) or the RESULT (fail) is received, the responder does not transmit the GET_DIGESTS.

(135) Here, the time interval between packets from GET_DIGESTS (**814a** and **814b**) to RESULT (success) (**820a** and **820b**) will be supplemented. For example, in the Negotiation phase of the WPC standard v1.2.2, it is specified that the TX **100** responds to a packet from the RX **200** such that the time from the rear end of the received packet to the front end of the response packet to be transmitted is within 10 ms. However, the initiator in the Authentication phase needs to perform encryption and decryption processing to confirm the validity of the packets (DIGEST, CERTIFICATE, and RESPONSE) related to the digital certificate, which are transmitted from the responder. Thus, time is taken to make a response in the Authentication phase. In the Authentication phase, therefore, a longer response time than the response time specified in any other phase is provided. In this embodiment, the response time is set to 50 ms. In FIG. 8D, the response time includes a time period from the DIGEST to the GET_CERTIFICATE, a time period from the CERTIFICATE to the CHALLENGE, and a time period from the RESPONSE to the RESULT (success). An increase in the response time reduces the need for the control unit **101** of the TX **100** to operate at high speeds, achieving an advantage of reducing the power consumption of the control unit **101** and achieving low cost due to the use of a low-speed CPU.

(136) While the TX **100** determines, based on the Auth bit in the Configuration Packet, whether the power receiving apparatus supports WPT authentication, the determination may be based on version information of the ID Packet. If the version information indicates the version A (or a later version), it is determined that WPT authentication is supported. If the version information indicates a version prior to the version A, it is determined that WPT authentication is not supported. Similar advantages are achieved.

(137) In the Authentication phase, upon receipt of a packet other than predetermined packets from the RX **200**, the TX **100** may stop the power transmission of the power transmitting unit **103** and cause a transition to the Selection phase. With this operation, stopping power transmission upon receipt of a packet other than predetermined packets due to a failure of the RX **200** or the like can prevent the system from performing an unwanted operation. The predetermined packets include the

GET_DIGESTS, the DIGEST, the GET_CERTIFICATE, the CHALLENGE, the RESPONSE, and the RESULT, which are indicated by **814a** to **820a** and **814b** to **820b**. Examples of the packet other than the predetermined packets include a Signal Strength Packet indicating the voltage value of the received voltage, a Control Error Packet indicating a request for an increase or decrease in the voltage value, an ID Packet, and a Configuration Packet.

(138) Further, the TX **100** and the RX **200** may store a result of operating as an initiator (i.e., confirming the validity of a responder) and identification information of a responder (such as the device ID, the manufacturer ID, and information relating to the certificate) in a non-volatile memory (not illustrated). Only identification information of a responder for which authentication has failed may be stored in the non-volatile memory. The TX **100** and the RX **200** may perform WPT authentication by using the identification information of a responder for which authentication has failed, which is stored in the non-volatile memory. For example, when the TX **100** and the RX **200** perform authentication as initiators, the identification number of a target device that is to perform authentication is checked against the identification number stored in the non-volatile memory, and the identification number of the device can be used to determine the validity of the device.

(139) [Case where TX is Legacy and RX Supports Version A]

(140) A case where the TX **100** is legacy and the RX **200** supports the version A will be described with reference to FIG. 6, FIG. 7, FIG. 8C, and FIG. 9. In the following, it is assumed that the TX **100** is successful in USB authentication with the USB cable **300** and the AC adapter **301**. First, the operation of the RX **200** supporting the version A will be described.

(141) First, the RX **200** notifies the TX **100** that the RX **200** supports WPT authentication by using the Configuration Packet (**801** and **S901**). However, the TX **100** is legacy and ignores the Auth bit. Since the RX **200** of the version A supports the Negotiation function, the TX **100** transmits an ACK and causes a transition to the Negotiation phase (YES in **S704**, **S713**, and **S709**).

(142) Upon receipt of the ACK (**802** and YES in **S902**), the RX **200** determines that the TX **100** does not support WPT authentication (**S908**). This is because since the RX **200** supports WPT authentication, the RX **200** would receive an ACK (auth) rather than an ACK if the TX **100** were supporting WPT authentication. Then, the RX **200** causes a transition to the Negotiation phase (**S909**).

(143) If the RX **200** does not receive an ACK within 15 ms from the transmission of the Configuration Packet (NO in **S902**) or does not receive an ACK (auth) (NO in **S903**), the process proceeds to **S911**. In this case, the RX **200** determines that the TX **100** is BPP and does not support the Negotiation function (**S911**), and causes a transition to the PT phase (**S912**).

(144) The RX **200** performs a negotiation of the GP in the Negotiation phase. As described with reference to FIG. 6B, the RX **200** determines that the reception at 15 watts should be avoided to avoid a risk of excessive heat generation or the like. Then, the RX **200** determines that about 5 watts of power, which corresponds to not supporting WPT authentication (the row **603**) and successful USB authentication (the column **602**), are negotiated as the GP, and transmits a Specific Request (5 W) (**809**). Then, the RX **200** receives an ACK from the TX **100** (**804**), and terminates the Negotiation phase. Then, the RX **200** causes a transition to the Calibration phase (**S910**), and performs predetermined processing. Then, the RX **200** causes a transition to the PT phase (**S912**).

(145) As described above, the RX **200** supporting the WPC standard version A can consistently operate also for the TX **100** supporting a WPC standard prior to the version A.

(146) As described above, in the contactless charging system according to this embodiment, device authentication using the USB protocol is performed between the power supply apparatus (the AC adapter **301**) serving as a power supply source and the power transmitting apparatus, and device authentication using the WPC protocol is mutually performed between the power transmitting apparatus and the power receiving apparatus. The power receiving apparatus controls the transmission power of the power transmitting apparatus of WPC on the basis of the USB-based

device authentication result and the WPC-based device authentication result. Accordingly, in wireless power transmission in which a plurality of types of device authentication protocols are executable, these authentication results can be efficiently used. As a result, appropriate power transmission control can be implemented such that, for example, an issue such as excessive heat generation is less likely to occur in a device present in a path for power supply.

Embodiment 2

(147) The following describes another embodiment of the present disclosure with reference to FIG. **11** and FIG. **12**. Embodiment 1 provides an example in which the power transmitting apparatus and the power receiving apparatus mutually perform WPT authentication in the Authentication phase. This embodiment provides an example process in which if the earlier performed WPT authentication among the respective WPT authentications performed by the power transmitting apparatus and the power receiving apparatus is not successful, the GP is determined without performing the other WPT authentication to be performed subsequently. Accordingly, the processing time in the Authentication phase can be shortened, and the GP can be determined quickly.

(148) In this embodiment, furthermore, the control unit **101** of the TX **100** determines content related to power transmission on the basis of at least the result of the earlier performed WPT authentication. For example, the content is whether to perform power transmission. In the case of power transmission, the content is the allowable maximum value of the power value. On the other hand, the control unit **201** of the RX **200** determines content related to power reception on the basis of at least the result of the earlier performed WPT authentication. For example, the content is whether to perform power reception. In the case of power reception, the content is the maximum value of the power value for which a request is made to the TX **100**.

(149) While this embodiment will be described using a case where the power receiving apparatus initially operates as an initiator and authenticates the validity of the power transmitting apparatus, the power transmitting apparatus may initially operate as an initiator. Similar advantages are achieved. FIG. **11** is a flowchart illustrating state transitions made by the control unit of the power receiving apparatus (the RX **200**) up to power transmission. FIG. **12** is a flowchart illustrating state transitions made by the control unit of the power transmitting apparatus (the TX **100**) up to power transmission.

(150) The following description focuses on processing in the Authentication phase, and a description will be made using a case where both the TX **100** and the RX **200** are of the version A. The same points as those in the embodiment described above will not be described. The same elements as the elements described in the foregoing embodiment are denoted by the same numerals and will not be described.

(151) The RX **200** of the version A transmits, to the TX **100**, a Configuration Packet storing “1” in the Auth Bit (**S901**). If it is determined, based on the Auth Bit in the Configuration Packet, that the RX **200** supports WPT authentication (YES in **S703**), the TX **100** of the version A transmits an ACK (auth) to the RX **200** (**S705**). The RX **200** receives the ACK (auth) (YES in **S903**). In this case, since it is found that the TX **100** supports WPT authentication, the RX **200** transmits an Auth_request (hereinafter referred to as “Auth_req”) to the TX **100** within a predetermined time after the receipt of the ACK (auth) (**S1100**). The Auth_req is a packet indicating an intention to start authentication processing in which the RX **200** serves as an initiator and the TX **100**, which is the transmission destination, serves as a responder.

(152) After the transmission of the ACK (auth) in **S705**, the TX **100** determines whether an Auth_req packet has been received within a predetermined time (**S1200**). The TX **100** receives the Auth_req packet, thereby recognizing the start of WPT authentication. The RX **200** may determine whether the TX **100** supports WPT authentication by using a method other than receiving an ACK (auth), such as acquiring version information.

(153) Upon receipt of the Auth_req (YES in **S1200**), the TX **100** determines whether the TX **100**

can operate as a responder and perform WPT authentication. Specifically, the determination is made in terms of the state of load of the control unit **101** of the TX **100**. More specifically, it is determined whether the control unit **101** has a capacity of controlling the second authentication unit **109**, or, if the second authentication unit **109** is controlled by any other control unit (not illustrated) connected to the RX **200**, it is determined whether the other control unit is capable of controlling the second authentication unit **109**.

(154) After receipt of the Auth_req packet, the TX **100** performs the determination described above within a predetermined time. If it is determined that the TX **100** can be authenticated as a responder, the TX **100** transmits an ACK to the RX **200** in response to the Auth_req (YES in **S1201**). Accordingly, the TX **100** causes a transition to the Authentication phase (**S706**). Upon receipt of the ACK (YES in **S1101**), the RX **200** transmits a GET_DIGESTS to the TX **100** within a predetermined time after the reception of the ACK, and authenticates the validity of the TX **100** (**S906b**). Then, the TX **100** receives the GET_DIGESTS from the RX **200**, and receives the authentication processing performed by the RX **200** (**S707b**).

(155) Then, if it is determined that the result of WPT authentication indicates success (YES in **S1102**) and that the TX **100** supports WPT authentication, the RX **200** transmits a RESULT (success) to the TX **100**. The TX **100** receives the RESULT (success) packet from the RX **200**, thereby recognizing that authentication is successful. In this case, the TX **100** waits for a predetermined time until an Auth_req packet is transmitted from the RX **200** to inquire whether the TX **100** has an intention to perform authentication processing in which the TX **100** serves as an initiator and the RX **200** serves as a responder.

(156) Then, the RX **200** transmits an Auth_req to the TX **100** within a predetermined time after the transmission of the RESULT (success) to inquire whether the TX **100** has an intention to perform WPT authentication on the RX **200** (**S1103**). If the WPT authentication of the TX **100** by the RX **200** is successful (YES in **S1202**), the TX **100** receives the Auth_req transmitted from the RX **200** within a predetermined time (YES in **S1203**). Since the TX **100** has the function of the initiator, the TX **100** transmits an ACK within a predetermined time after the reception of the Auth_req packet (YES in **S1204**). The RX **200** receives the ACK (YES in **S1104**).

(157) The TX **100** transmits a GET_DIGESTS to the RX **200** within a predetermined time after the transmission of the ACK to start WPT authentication to authenticate the validity of the RX **200** (**S707a**). The RX **200** receives the GET_DIGESTS, and authentication performed by the TX **100** is started (YES in **S1105**, and **S906a**).

(158) If WPT authentication for the RX **200** is successful (YES in **S1205**), the TX **100** transmits a RESULT (success) packet to the RX **200** and causes a transition to the Negotiation phase (**S709**). Since the TX **100** also confirms the validity of the RX **200** (YES in **S1205**), a GP of up to 15 watts is allowed on the basis of FIG. 6A. That is, the control unit **101** of the TX **100** determines, as content related to power transmission, a transmission power value allowable for the RX **200** at the time of power transmission on the basis of the results of both WPT authentications.

(159) On the other hand, the RX **200** receives the result of WPT authentication from the TX **100**, and, if authentication is successful (YES in **S1106**), causes a transition to the Negotiation phase (**S909**). Since the RX **200** confirms the validity of the TX **100** (YES in **S1102**), the RX **200** sends to the TX **100** a request for a GP of up to 15 watts as a Specific Request on the basis of FIG. 6B. That is, the control unit **201** of the RX **200** determines, as content related to power reception, the maximum value of the power value for which a request is made to the TX **100** on the basis of the results of both WPT authentications.

(160) If the validity of the TX **100** is not confirmed in the processing of **S907b**, that is, if WPT authentication is not successful (NO in **S1102**), the RX **200** limits the GP to 5 watts (**S1107**). If WPT authentication is not successful in the processing of **S707b** (NO in **S1202**), the TX **100** limits the GP to 5 watts (**S1206**). That is, the control unit **201** of the RX **200** determines, as content related to power reception, the power value for which a request is made to the TX **100** by the RX

200 on the basis of the result of the earlier performed WPT authentication. The control unit **101** of the TX **100** also determines, as content related to power transmission, the transmission power value allowable for the RX **200** at the time of power transmission on the basis of the result of the earlier performed WPT authentication.

(161) While an example is provided in which the RX **200** and the TX **100** determine the GP to be 5 watts, this is not intended to be limiting. Specifically, examples of the content related to power reception, which is determined by the RX **200** if WPT authentication is not successful, include the following items: sending from the RX **200** to the TX **100** a request for a smaller power value than that when mutual WPT authentication is successful, or not receiving power from the TX **100**.

Examples of not receiving power from the TX **100** include requesting the TX **100** to stop power transmission. Accordingly, for example, a packet indicating a stop of power transmission may be transmitted to stop power transmission, and no request may be made for power. Alternatively, the RX **200** may block a current path (not illustrated) so as not to cause a current to flow through the power receiving coil **205** to prevent the RX **200** from receiving power from the TX **100**.

Accordingly, excessive heat generation or the like can be prevented.

(162) Examples of the content related to power transmission, which is determined by the TX **100** if WPT authentication is not successful, include the following items: the TX **100** setting the maximum value of the allowed power to be transmitted to the RX **200** to be a smaller value than that when mutual WPT authentication is successful, or stopping the transmission of power to the RX **200**. Accordingly, excessive heat generation or the like can be prevented.

(163) As illustrated in FIG. **11** and FIG. **12**, if the earlier performed WPT authentication processing (**S707b** and **S906b**) is not successful, the control unit **101** and the control unit **201** control the authentication processing so that the WPT authentication processing to be performed subsequently (**S707a** and **S906a**) is not performed. Specifically, the control unit **201** of the RX **200** does not provide an opportunity to cause the TX **100** to operate as an initiator. More specifically, the control unit **201** of the RX **200** does not transmit the Auth_req in **S1103**. This is because since the RX **200** is not successful in authentication in which the RX **200** serves as an initiator, the RX **200** has determined the requested GP to be 5 watts (see FIG. **6B**). This determination is not changed, regardless of whether the result of authentication in which the TX **100** serves as an initiator indicates success. Accordingly, the processing time in the Authentication phase can be shortened, and a quick transition to the Negotiation phase can occur.

(164) Specific examples of the case where WPT authentication is not successful include the following cases. For example, the validity of the TX **100** is not confirmed in WPT authentication processing in which the RX **200** serves as an initiator, that is, authentication has failed (NO in **S1102**).

(165) Also when a NAK indicating negation is transmitted as a response to the Auth_req since it is not possible to cause the second authentication unit **109** to operate, the TX **100** determines that the RX **200** is not successful in authentication (NO in **S1101** and NO in **S1201**). Also when the RX **200** does not receive an ACK from the TX **100** within a predetermined time after the transmission of the Auth_req, it is determined that the RX **200** is not successful in authentication (NO in **S1201**).

(166) Further, in WPT authentication processing, when the RX **200** does not receive an expected packet from the TX **100** within a predetermined time after the transmission of a packet described below, it is also determined that the RX **200** is not successful in authentication. Specific examples include a case where the DIGEST packet is not received or any other packet is received in response to the GET_DIGESTS packet transmitted from the RX **200**. Other examples include a case where the CERTIFICATE is not received or any other packet is received in response to the GET_CERTIFICATE packet, and a case where the RESPONSE packet is not received or any other packet is received in response to the CHALLENGE packet.

(167) On the other hand, if the TX **100** determines that WPT authentication is not successful, the control unit **101** of the TX **100** does not transmit a packet relating to the processing of WPT

authentication for the RX **200**, such as not transmitting a GET_DIGESTS to the RX **200**.

(168) Examples of the case where the TX **100** determines that WPT authentication is not successful include the following cases. After the transmission of the ACK (auth) (**S705**), the TX **100** does not receive the Auth_req packet within a predetermined time (NO in **S1200**). Other examples include a case where after the reception of the Auth_req packet (YES in **S1200**), the TX **100** does not transmit an ACK within a predetermined time (NO in **S1201**).

(169) Further, in the WPT authentication processing, when the TX **100** does not receive an expected packet from the RX **200** within a predetermined time after the transmission of a packet described below, the TX **100** also determines that authentication is not successful. Specific examples include a case where after the transmission of the ACK (**S1201**), the TX **100** does not receive the GET_DIGESTS packet or receives any other packet. Other examples include a case where after the transmission of the DIGEST packet, the TX **100** does not receive the GET_CERTIFICATE packet or receives any other packet. Other examples include a case where after the transmission of the CERTIFICATE packet, the TX **100** does not receive the CHALLENGE packet or receives any other packet. Other examples include a case where after the transmission of the RESPONSE packet, the TX **100** does not receive the RESULT packet or receives any other packet, and a case where WPT authentication in which the RX **200** serves as an initiator is not successful (NO in **S1202**). The case where WPT authentication is not successful includes a case where after the transmission of the RESPONSE packet, the TX **100** does not receive the RESULT (success) packet within a predetermined time. Other examples include a case where the TX **100** receives a RESULT (fail) packet indicating that authentication has failed.

(170) Likewise, in the processing of **S707a** (**S906a**), if the authentication of the RX **200** in which the TX **100** serves as an initiator is not successful (NO in **S1205** and NO in **S1106**), processing is performed as follows. In the Negotiation phase, the RX **200** sends to the TX **100** a request for, as the GP, a smaller power value than that when mutual WPT authentication is successful.

Alternatively, the RX **200** requests the TX **100** to stop power transmission, and determines processing such as making no request for power. On the other hand, in the Negotiation phase, the TX **100** determines processing such as allowing a smaller power value than that when mutual WPT authentication is successful as the GP or stopping the transmission of power to the RX **200**. In FIG. **11**, the RX **200** determines the GP to be 5 watts (**S1107**), and in FIG. **12**, the TX **100** determines the GP to be 5 watts (**S1206**).

(171) Examples of the case where the RX **200** determines that WPT authentication is not successful include the following cases. Specific examples include a case where after the transmission of the Auth_Req in **S1103**, the RX **200** does not receive an ACK from the TX **100** within a predetermined time (NO in **S1104**). Other examples include a case where after the reception of the ACK (YES in **S1104**), the GET_DIGESTS is not received within a predetermined time (NO in **S1105**).

(172) Also, in the WPT authentication processing, when the RX **200** does not receive an expected packet from the TX **100** within a predetermined time after the transmission of a packet described below, the RX **200** also determines that authentication is not successful. Specific examples include a case where after the transmission of the DIGEST packet, the RX **200** does not receive the GET_CERTIFICATE packet or receives any other packet. Other examples include a case where after the transmission of the CERTIFICATE packet, the RX **200** does not receive the CHALLENGE packet or receives any other packet, and a case where after the transmission of the RESPONSE packet, the RX **200** does not receive the RESULT packet or receives any other packet.

(173) Examples of a case where the TX **100** determines that WPT authentication is not successful include the following cases. After the reception of the RESULT (success) packet, the TX **100** does not receive the Auth_req packet within a predetermined time (NO in **S1203**). Other examples include a case where the TX **100** does not transmit an ACK within a predetermined time in response to the Auth_req packet (NO in **S1204**) or transmits a NAK indicating that it is not possible to cause the second authentication unit **109** to operate.

(174) Further, in the WPT authentication processing in **S707a**, if the TX **100** does not receive an expected packet from the RX **200** within a predetermined time after the transmission of a packet described below, the TX **100** also determines that authentication is not successful (NO in **S1205**). Specific examples include a case where the TX **100** does not receive the DIGEST packet or receives any other packet in response to the GET_DIGESTS packet to be transmitted. Other examples include a case where the TX **100** does not receive the CERTIFICATE or receives any other packet in response to the GET_CERTIFICATE packet to be transmitted. Other examples include a case where the TX **100** does not receive the RESPONSE packet or receives any other packet in response to the CHALLENGE packet that is transmitted.

(175) Further, in **S1103**, the RX **200** transmits an Auth_req to inquire whether the TX **100** has an intention to perform processing in which the TX **100** serves as an initiator and the RX **200** serves as a responder. However, the Auth_req may be transmitted after the determination of whether the TX **100** can become an initiator.

(176) For example, the TX **100** may store, in a portion of the Transmitter Capability Packet, information indicating the presence of the function of the initiator or the presence of the function of the responder. Likewise, the RX **200** may store, in a portion of the Configuration Packet, information indicating the presence of the function of the initiator or the presence of the function of the responder. In **S1103**, the power receiving apparatus RX **200** may transmit an Auth_req if the TX **100** has the function as the initiator, and may not transmit an Auth_req if the TX **100** does not have the function as the initiator. This can shorten the time or the like taken to transmit an Auth_req although the TX **100** does not have the function as the initiator, thereby shortening the processing time.

(177) The Auth_req in **S1103** is a packet that triggers the TX **100** to transmit a GET_DIGESTS. The Auth_req may be a packet for inquiring whether the TX **100** has data to be transmitted to the RX **200** or a packet indicating that the right of transmitting data is provided to the TX **100**. If the TX **100** has data to be transmitted to the RX **200** or the TX **100** wishes to have the right of transmitting data, the TX **100** responds with an ACK (**S1204**), or, otherwise, responds with a NAK, thereby achieving similar advantages.

(178) Prior to the transmission of Auth_req in **S1100**, the RX **200** may transmit a General Request (ID), which is a packet for acquiring the identification information of the TX **100**, to the TX **100** and acquire the identification information from the TX **100**. Then, the RX **200** may store the identification information in the Auth_req packet as the identification information of the responder. This allows the TX **100** to find, upon receipt of the Auth_req, that the TX **100** should become a responder. Then, the TX **100** can wait for the reception of a GET_DIGESTS and can receive WPT authentication. The RX **200** may store the identification information thereof in the Auth_req packet as the identification information of the initiator or store the identification information of the TX **100** as the identification information of the responder. This allows the TX **100** to clarify who (in this case, the RX **200**) and whom (in this case, the TX **100**) to confirm the validity.

(179) In **S1103**, the RX **200** stores the identification information thereof in the Auth_req packet as the identification information of the responder, and stores the identification information of the TX **100** as the identification information of the initiator. This allows the TX **100** to find, upon receipt of the Auth_req, that the TX **100** should become an initiator.

(180) FIG. 11 and FIG. 12 relate to flowcharts for the control units of the RX **200** and the TX **100** when the RX **200** initially becomes an initiator and authenticates the validity of the TX **100**.

However, even when the TX **100** initially becomes an initiator and authenticates the validity of the RX **200**, similar advantages are achieved. In this case, in the flowchart illustrating the processing of the control unit **201** of the RX **200**, the series of processes of **S1100**, **S1101**, **S906b**, and **S1102** and the series of processes of **S1103**, **S1104**, **S1105**, **S906a**, and **S1106** in FIG. 11 are exchanged. In the flowchart illustrating the processing of the control unit **101** of the TX **100**, the series of processes of **S1200**, **S1201**, **S706**, **S707b**, and **S1202** and the series of processes of **S1203**, **S1204**, **S707a**, and

S1205 in FIG. 12 are exchanged.

(181) With the configuration described above, content related to power transmission or power reception can be determined more accurately. An additional advantage of enhancing security is also achieved.

(182) Further, the TX **100** and the RX **200** according to the present disclosure have the function as the initiator in WPT authentication. In addition, the TX **100** and the RX **200** may store the result of operating as the initiator (i.e., confirming the validity of the responder) and the identification information of the responder (such as the device ID, the manufacturer ID, and information relating to the certificate) in the non-volatile memory (not illustrated). Further, only the identification information of a responder for which authentication has failed may be stored in the non-volatile memory. The TX **100** and the RX **200** may operate such that the same apparatus as the responder whose identification information is stored in the non-volatile memory does not perform authentication processing as the initiator. Specifically, upon receipt of a request from an apparatus whose identification information is stored in the non-volatile memory as a responder for which authentication has failed to operate as a responder and check the validity thereof, the TX **100** and the RX **200** operate so as to reject the request.

(183) For example, when the RX **200** operates as an initiator and has failed in the authentication of the TX **100**, the RX **200** stores in the non-volatile memory thereof the identification information of the TX **100** as a responder. Then, a packet for inquiring whether the TX **100** has data to be transmitted to the RX **200** or a packet for providing the right of transmitting data to the TX **100** is transmitted. Then, the RX **200** receives from the TX **100** an ACK, which is a response indicating that the TX **100** has the data to be transmitted or has obtained the right of transmitting data, in response to the transmitted packet. Upon receipt of a packet (Auth_req) indicating an intention to start WPT authentication processing in which the TX **100** serves as an initiator and the RX **200** serves as a responder, the RX **200** transmits a NAK as the response on the basis of the identification information stored in the non-volatile memory. This can prevent an apparatus (in this case, the TX **100**) for which WPT authentication performed by the RX **200** has failed from performing authentication processing in which this apparatus operates as an initiator. That is, if the earlier performed WPT authentication is not successful, the subsequent WPT authentication can be prevented from being performed. Accordingly, if the validity is not recognized through the earlier performed WPT authentication, the processing time in the Authentication phase can be shortened.

(184) The same applies when the TX **100** serving as an initiator has failed in the authentication of the RX **200**. For example, the TX **100** is assumed to store the identification information of the RX **200** in the non-volatile memory as a responder for which authentication has failed. In this state, upon receipt of, from the RX **200**, a packet (Auth_req) indicating an intention to start WPT authentication processing in which the RX **200** serves as an initiator and the TX **100** serves as a responder, the TX **100** transmits a NAK as the response. Even with the operation described above, an apparatus that has failed in authentication in which the apparatus operates as an initiator can be prevented from performing authentication processing, and thus the processing time in the Authentication phase can be shortened.

(185) In addition, if the TX **100** and the RX **200** operate such that a device whose identification information is stored in the non-volatile memory as a responder for which authentication has failed is not permitted to make a request that the TX **100** and the RX **200** operate as responders and to confirm validity, similar advantages are achieved.

(186) For example, the RX **200** having a function of transmitting a packet for inquiring whether the TX **100** has data to be transmitted to the RX **200** or a packet for providing the right of transmitting data to the TX **100** may be controlled in the following way. That is, the packet described above may not be transmitted to an apparatus (i.e., the TX **100**) whose identification information is stored in the non-volatile memory as a responder for which authentication has failed.

(187) The TX **100** having a function of transmitting a packet for inquiring whether the RX **200** has

data to be transmitted to the TX **100** or a packet for providing the right of transmitting data to the RX **200** may be controlled in the following way. That is, the packet described above may not be transmitted to an apparatus (i.e., the RX **200**) whose identification information is stored in the non-volatile memory as a responder for which authentication has failed.

OTHER EMBODIMENTS

(188) The power transmission method for a wireless power transmission system according to the present disclosure is not limited to any specific method. A magnetic field resonance method can be used in which power is transmitted by coupling caused by resonance in a magnetic field created between a resonator (resonance element) of a TX and resonator (resonance element) of an RX.

Alternatively, an electromagnetic induction method, an electric field resonance method, a microwave method, or a power transmission method using a laser or the like may be used.

(189) The TX and the RX may be each, for example, an image input device such as an image capturing device (such as a camera or a video camera) or a scanner, or an image output device such as a printer, a copying machine, or a projector. Alternatively, the TX and the RX may be each a storage device such as a hard disk device or a memory device, or an information processing device such as a personal computer (PC) or a smartphone.

(190) The flowcharts illustrated in FIG. 5, FIG. 7, FIG. 9, FIG. 11, and FIG. 12 are started, for example, when power is applied to the control unit **101** or the control unit **201**. The processes illustrated in FIG. 5A, FIG. 7, and FIG. 12 are implemented by the control unit **101** executing a program stored in the memory **107** of the TX **100**. The flowcharts illustrated in FIG. 5B, FIG. 9, and FIG. 11 are implemented by the control unit **201** executing a program stored in the memory **209** of the RX **200**.

(191) At least a portion of the processes illustrated in the flowcharts illustrated in FIG. 5, FIG. 7, FIG. 9, FIG. 11, and FIG. 12 may be implemented by hardware. In the case of hardware implementation, for example, a predetermined compiler may be used to automatically generate a dedicated circuit on an FPGA (Field Programmable Gate Array) from a program for implementing each step. In addition, a Gate Array circuit may be formed in a manner similar to that for the FPGA and implemented as hardware.

(192) The present disclosure can reduce unnecessary processing cause when the validity of the target apparatus that performs authentication processing is not recognized.

(193) Embodiment(s) of the present disclosure can also be realized by a computer of a system or apparatus that reads out and executes computer executable instructions (e.g., one or more programs) recorded on a storage medium (which may also be referred to more fully as a 'non-transitory computer-readable storage medium') to perform the functions of one or more of the above-described embodiment(s) and/or that includes one or more circuits (e.g., application specific integrated circuit (ASIC)) for performing the functions of one or more of the above-described embodiment(s), and by a method performed by the computer of the system or apparatus by, for example, reading out and executing the computer executable instructions from the storage medium to perform the functions of one or more of the above-described embodiment(s) and/or controlling the one or more circuits to perform the functions of one or more of the above-described embodiment(s). The computer may comprise one or more processors (e.g., central processing unit (CPU), micro processing unit (MPU)) and may include a network of separate computers or separate processors to read out and execute the computer executable instructions. The computer executable instructions may be provided to the computer, for example, from a network or the storage medium. The storage medium may include, for example, one or more of a hard disk, a random-access memory (RAM), a read only memory (ROM), a storage of distributed computing systems, an optical disk (such as a compact disc (CD), digital versatile disc (DVD), or Blu-ray Disc (BD)TM), a flash memory device, a memory card, and the like.

(194) While the present disclosure has been described with reference to exemplary embodiments, it is to be understood that the disclosure is not limited to the disclosed exemplary embodiments. The

scope of the following claims is to be accorded the broadest interpretation so as to encompass all such modifications and equivalent structures and functions.

Claims

1. A power receiving apparatus comprising: a power receiving unit configured to wirelessly receive power from a power transmitting apparatus; a communication unit configured to transmit, to the power transmitting apparatus, a packet to request a certificate and receive, from the power transmitting apparatus, a response for the transmitted packet; and a determination unit configured to determine whether the response is a proper packet, and determine power to accept from the power transmitting apparatus, wherein the determination unit determines the power up to 5 watts based on that the response is not the proper packet.
 2. The power receiving apparatus according to claim 1, wherein the determination unit determines the power up to 5 watts based on that the response is a packet indicating that the power transmitting apparatus cannot be trusted.
 3. The power receiving apparatus according to claim 1, wherein the determination unit determines the power up to 5 watts based on that the response is not received.
 4. A method for a power receiving apparatus wirelessly receiving power from a power transmitting apparatus, the method comprising: transmitting, to the power transmitting apparatus, a packet to request a certificate; receiving, from the power transmitting apparatus, a response for the transmitted packet; determining whether the response is a proper packet; and determining power to accept from the power transmitting apparatus, the power being determined up to 5 watts based on that the response is not the proper packet.
 5. A non-transitory computer-readable storage medium storing a computer program for causing a method for a power receiving apparatus wirelessly receiving power from a power transmitting apparatus, the method comprising: transmitting, to the power transmitting apparatus, a packet to request a certificate; receiving, from the power transmitting apparatus, a response for the transmitted packet; determining whether the response is a proper packet; and determining power to accept from the power transmitting apparatus, the power being determined up to 5 watts based on that the response is not the proper packet.
 6. The power receiving apparatus according to claim 1, wherein the communication unit transmits information on the determined power to the power transmitting apparatus.
 7. The power receiving apparatus according to claim 1, wherein the determination unit determines whether the power transmitting apparatus supports authentication, and the communication unit transmits the packet to request the certificate based on that the power transmitting apparatus supports authentication.
 8. The method according to claim 4, further comprising determining whether the power transmitting apparatus supports authentication, wherein the packet to request the certificate is transmitted based on that the power transmitting apparatus supports authentication.
-