

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250287804

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

KIM; Tae Hoon et al.

DISPLAY DEVICE

Abstract

A display device may include a substrate, pixels, a first common voltage line, an outer common voltage trunk line, a first outer common voltage line, and a second outer common voltage line. The substrate may include a display area and a non-display area. The pixels may be disposed on the display area. The first common voltage line may be at least partially disposed on the display area. The outer common voltage trunk line may be disposed on the non-display area, may be electrically connected through the first common voltage line to the pixels, and may include a groove. The first outer common voltage line may protrude from the outer common voltage trunk line. The second outer common voltage line may protrude from the outer common voltage trunk line. The groove may be disposed between the second outer common voltage line and the first common voltage line.

Inventors: KIM; Tae Hoon (Cheonan-si, KR), KWAK; Won Kyu (Seongnam-si, KR)

Applicant: Samsung Display Co., Ltd. (Yongin-Si, KR)

Family ID: 1000008629180

Appl. No.: 19/220242

Filed: May 28, 2025

Foreign Application Priority Data

KR 10-2019-0114735

Sep. 18, 2019

Related U.S. Application Data

parent US continuation 18424179 20240126 parent-grant-document US 12342698 child US 19220242

parent US continuation 17891910 20220819 parent-grant-document US 11910677 child US 18424179

parent US continuation 17002705 20200825 parent-grant-document US 11424313 child US 17891910

Publication Classification

Int. Cl.: **H10K59/131** (20230101); **G09G3/3258** (20160101); **G09G3/3266** (20160101);
G09G3/3291 (20160101); **H10K59/80** (20230101)

U.S. Cl.:

CPC **H10K59/131** (20230201); **G09G3/3258** (20130101); **G09G3/3266** (20130101);
G09G3/3291 (20130101); **H10K59/8794** (20230201);

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application is a continuation application of U.S. patent application Ser. No. 18/424,179 filed on Jan. 26, 2024, which is a continuation application of U.S. patent application Ser. No. 17/891,910 filed on Aug. 19, 2022 (now U.S. Pat. No. 11,910,677), which is a continuation application of U.S. patent application Ser. No. 17/002,705 filed on Aug. 25, 2020 (now U.S. Pat. No. 11,424,313), which claims priority to and the benefit of Korean Patent Application No. 10-2019-0114735 filed in the Korean Intellectual Property Office on Sep. 18, 2019. The entire contents of the disclosures are incorporated herein by reference in their entirety.

BACKGROUND

(a) Technical Field

[0002] The technical field relates to a display device.

(b) Description of the Related Art

[0003] Display devices may display images. Modern display devices may include light emitting diode display devices.

[0004] A light emitting diode display device does not require a separate light source and thus can have minimized thickness and weight. Advantages of the light emitting diode display may further include low power consumption, high luminance, and/or a high reaction speed.

[0005] Generally, the light emitting diode display includes a substrate, thin film transistors disposed on the substrate, insulating layers disposed between wires connected to the thin film transistors, and light emitting elements respectively connected to the thin film transistors. The light emitting elements may be, for example, organic light emitting elements.

[0006] The display device may include a display area and a non-display area. As the non-display area is minimized, a density of current flows in the non-display area may be significantly high. As a result, much heat may be generated in the non-display area. The Background section is for understanding of the background of embodiments.

[0007] The Background section may contain information that does not form the prior art that is already known in this country to a person of ordinary skill in the art.

SUMMARY

[0008] Embodiments may be related a display device in which undesirable heating of wiring in a non-display area is prevented or mitigated.

[0009] A display device according to an embodiment includes the following elements: a substrate including a display area and a non-display area; an outer common voltage line disposed in the non-display area; and first common voltage lines connected to a plurality of pixels disposed in the display area and one end of the outer common voltage line, wherein the other end of the outer common voltage line is branched into a first outer common voltage line and a second outer common voltage line, and includes a groove disposed between the second outer common voltage

line and the first common voltage line.

[0010] The first outer common voltage line, the second outer common voltage line, and the first common voltage lines may be disposed in parallel to a second direction, and the groove may be disposed in parallel to a first direction perpendicular to the second direction.

[0011] Among the first common voltage lines, the number of first common voltage lines connected to the first outer common voltage line may be larger than the number of first common voltage lines connected to the second outer common voltage line.

[0012] An outer initialization voltage line disposed between the outer common voltage line and the display area and disposed in parallel to the second direction may be further included.

[0013] The outer common voltage line may include a first end and a second end facing each other, the first end and the second end may be disposed on the same side of the display area, an outer driving voltage line disposed between the first end and the second end may be further included, and the outer driving voltage line and each pixel disposed in the display area may be connected by a driving voltage line.

[0014] The outer common voltage line may be disposed to surround the four sides of the display area.

[0015] A portion of pixels among the plurality of pixels may overlap the first common voltage line, and a portion of pixels connected to the first common voltage line may not overlap the driving voltage line.

[0016] A second common voltage line connected to the first common voltage line and crossing the first common voltage line may be further included.

[0017] The first common voltage line may be disposed between the plurality of pixels, and may be disposed in parallel to the driving voltage line connected to each of the plurality of pixels.

[0018] A second common voltage line connected to the first common voltage line and crossing the first common voltage line may be further included.

[0019] At least one outer common sub-voltage line among the outer common voltage line may be disposed in parallel to one side of the display area, and another outer common sub-voltage line among the outer common voltage line may be disposed in parallel to the other side facing one side.

[0020] The portion of pixels among the plurality of pixels may overlap the first common voltage line, and the portion of pixels overlapping the first common voltage line may do not overlap the driving voltage line.

[0021] A second common voltage line connected to the first common voltage line and crossing the first common voltage line may be further included.

[0022] The first common voltage line may be disposed between the plurality of pixels and disposed in parallel to the driving voltage line connected to each of the plurality of pixels.

[0023] A second common voltage line connected to the first common voltage line and crossing the first common voltage line may be further included.

[0024] A display device according to another embodiment includes: a substrate including a display area and a non-display area; an outer common voltage line disposed in the non-display area; and first common voltage lines connected to the plurality of pixels disposed in the display area and one end of the outer common voltage line, wherein the outer common voltage line includes a first outer common voltage line and a second outer common voltage line divided via an opening interposed therebetween.

[0025] The first outer common voltage line, the second outer common voltage line, and the first common voltage lines may be disposed in parallel to a second direction, and the opening may be disposed in parallel to the second direction.

[0026] The opening may further include a region parallel to a first direction perpendicular to the second direction.

[0027] Among the first common voltage lines, the number of first common voltage lines connected to the first outer common voltage line may be larger than the number of first common voltage lines

connected to the second outer common voltage line.

[0028] An outer initialization voltage line disposed between the outer common voltage line and the display area and parallel to the second direction may be further included.

[0029] The outer common voltage line may include a first end and a second end facing each other, the first end and the second end may be disposed on the same side of the display area, an outer driving voltage line may be disposed between the first end and the second end, and the outer driving voltage line and each pixel disposed in the display area may be connected by a driving voltage line.

[0030] The outer common voltage line may be disposed to surround four sides of the display area.

[0031] The portion of pixels among the plurality of pixels may overlap the first common voltage line, and the portion of pixels overlapping the first common voltage line may not overlap the driving voltage line.

[0032] A second common voltage line connected to the first common voltage line and crossing the first common voltage line may be further included.

[0033] The first common voltage line may be disposed between the plurality of pixels and parallel to a driving voltage line connected to each of the plurality of pixels.

[0034] A second common voltage line connected to the first common voltage line and crossing the first common voltage line may be further included.

[0035] At least one outer common sub-voltage line of the outer common voltage line may be disposed in parallel to one side of the display area, and another outer common sub-voltage line of the outer common voltage line may be disposed in parallel to the other side facing the one side.

[0036] The portion of pixels of the plurality of pixels may overlap the first common voltage line, and the portion of pixels overlapping the first common voltage line may not overlap the driving voltage line.

[0037] A second common voltage line connected to the first common voltage line and crossing the first common voltage line may be further included.

[0038] The first common voltage line may be disposed between the plurality of pixels and parallel to a driving voltage line connected to each of the plurality of pixels.

[0039] A second common voltage line connected to the first common voltage line and crossing the first common voltage line may be further included.

[0040] An embodiment may be related to a display device. The display device may include a substrate, pixels, a first common voltage line, an outer common voltage trunk line, a first outer common voltage line, and a second outer common voltage line. The substrate may include a display area and a non-display area. The pixels may be disposed on the display area. The first common voltage line may be at least partially disposed on the display area. The outer common voltage trunk line may be disposed on the non-display area, may be electrically connected through the first common voltage line to the pixels, and may include a groove. The first outer common voltage line may protrude from the outer common voltage trunk line. The second outer common voltage line may protrude from the outer common voltage trunk line. The groove may be disposed between the second outer common voltage line and the first common voltage line.

[0041] A lengthwise direction of the second outer common voltage line may be perpendicular to a lengthwise direction of the groove.

[0042] The shortest electrical path between the first common voltage line and the first outer common voltage line is shorter than the shortest electrical path between the first common voltage line and the second outer common voltage line.

[0043] The display device may include an outer initialization voltage line disposed between the outer common voltage trunk line and the display area and electrically connected to at least some of the pixels.

[0044] The display device may include the following elements: a driving voltage line at least partially disposed on the display area; and an outer driving voltage trunk line disposed on the non-

display area, disposed between a first end of the outer common voltage trunk line and a second end of the outer common voltage trunk line, electrically insulated from the outer common voltage trunk line, and electrically connected to at least some of the pixels through the driving voltage line.

[0045] The outer common voltage trunk line may include a first section, a second section, a third section, a fourth section, and a fifth section. The first section may be opposite the second section in a first direction. The third section may be opposite each of the fourth section and the fifth section in a second direction different from the first direction. The display area may be disposed between the first section and the second section in the first direction. The display area may be disposed between the third section and each of the fourth section and the fifth section in the second direction.

[0046] Some of the pixels overlap the first common voltage line and do not overlap the driving voltage line.

[0047] The display device may include a second common voltage line electrically connected to the first common voltage line and crossing the first common voltage line.

[0048] The first common voltage line may be disposed between a first subset of the pixels and a second subset of the pixels. A lengthwise direction of the first common voltage line may be parallel to a lengthwise direction of the driving voltage line.

[0049] The display device may include a second common voltage line electrically connected to the first common voltage line and crossing the first common voltage line.

[0050] The outer common voltage trunk line may include a first section and a second section. The second section may be opposite the first section. Two opposite sides of the display area may be disposed between the first section of the outer common voltage trunk line and the second section of the outer common voltage trunk line.

[0051] Some of the pixels overlap the first common voltage line and do not overlap the driving voltage line.

[0052] The display device may include a second common voltage line electrically connected to the first common voltage line and crossing the first common voltage line. The first common voltage line may be disposed between a first subset of the pixels and a second subset of the pixels. A lengthwise direction of the first common voltage line may be parallel to a lengthwise direction of the driving voltage line.

[0053] The display device may include a second common voltage line electrically connected to the first common voltage line and crossing the first common voltage line.

[0054] An embodiment may be related to a display device. The display device may include the following elements: a substrate including a display area and a non-display area; pixels disposed on the display area; a first common voltage line at least partially disposed on the display area; a first outer common voltage trunk line configured to transmit a common voltage, disposed on the non-display area, and electrically connected through the first common voltage line to at least a first subset of the pixels; a second outer common voltage trunk line spaced from the first outer common voltage trunk line in at least a first direction, configured to transmit the common voltage, and disposed on the non-display area; a first outer common voltage line protruding from the first outer common voltage trunk line in a second direction and disposed on the non-display area, wherein the second direction may be different from the first direction; and a second outer common voltage line protruding from the second outer common voltage trunk line and disposed on the non-display area.

[0055] Each of a lengthwise direction of the first outer common voltage line, a lengthwise direction of the second outer common voltage line, and a lengthwise direction of the first common voltage lines may be perpendicular to the first direction.

[0056] A first side of the first outer common voltage trunk line may be opposite a first side of the second outer common voltage trunk line in the first direction. A second side of the first outer common voltage trunk line may be opposite a second side of the second outer common voltage trunk line in the second direction.

[0057] The total number of common voltage lines directly connected to the first outer common

voltage trunk line may be larger than the total number of common voltage lines directly connected to the second outer common voltage trunk line.

[0058] The display device may include an outer initialization voltage line disposed between the second outer common voltage trunk line and the display area and electrically connected to at least some of the pixels.

[0059] The display device may include the following elements: a third outer common voltage trunk line spaced from the first outer common voltage trunk line in the first direction, wherein the first outer common voltage trunk line may be disposed between the second outer common voltage trunk line and the third outer common voltage trunk line; a driving voltage line at least partially disposed on the display area; and an outer driving voltage trunk line disposed on the non-display area, disposed between the first outer common voltage trunk line and the third outer common voltage trunk line, electrically insulated from each of the first outer common voltage trunk line and the third outer common voltage trunk line, and electrically connected to at least some of the pixels through the driving voltage line.

[0060] The display area may be disposed between a first section of the second outer common voltage trunk line and a second section of the second outer common voltage trunk line.

[0061] Some of the pixels overlap the first common voltage line and do not overlap the driving voltage line.

[0062] The display device may include a second common voltage line electrically connected to the first common voltage line and crossing the first common voltage line. The first common voltage line may be disposed between a first subset of the pixels and a second subset of the pixels. A lengthwise direction of the first common voltage line may be parallel to a lengthwise direction of the driving voltage line.

[0063] The display device may include a second common voltage line electrically connected to the first common voltage line and crossing the first common voltage line.

[0064] At least one edge of the first outer common voltage line may be parallel to one side of the display area and may be disposed between an edge of the second outer common voltage trunk line and the one side of the display area in the second direction.

[0065] Some of the pixels overlap the first common voltage line and do not overlap the driving voltage line.

[0066] The display device may include a second common voltage line electrically connected to the first common voltage line and crossing the first common voltage line.

[0067] The first common voltage line may be disposed between a first subset of the pixels and a second subset of the pixels. A lengthwise direction of the first common voltage line may be parallel to a lengthwise direction of the driving voltage line.

[0068] The display device may include a second common voltage line electrically connected to the first common voltage line and crossing the first common voltage line.

[0069] According to embodiments, in a display device, heat generated in wires disposed in the non-display area may be minimized and/or effectively dissipated.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0070] FIG. 1 is a view (e.g., a plan view) showing a display device according to an embodiment.

[0071] FIG. 2 is a view showing a flow of a current in a display device according to an embodiment.

[0072] FIG. 3 is a view schematically showing a flow of a current in a display device according to an embodiment.

[0073] FIG. 4 is a view showing the same position as a region A of FIG. 1 in a display device

according to an embodiment.

[0074] FIG. 5 is a view showing the same position as a region A of FIG. 1 in a display device according to an embodiment.

[0075] FIG. 6 is a view (e.g., a plan view) showing a display device including an outer common voltage line, an outer driving voltage line, and an outer initialization voltage line according to an embodiment.

[0076] FIG. 7 is a view showing a display device according to an embodiment.

[0077] FIG. 8 is a view showing a display device according to an embodiment.

[0078] FIG. 9 is a view showing a display device according to an embodiment.

[0079] FIG. 10 is a view showing a display device according to an embodiment.

[0080] FIG. 11 is a view showing a display device according to an embodiment.

[0081] FIG. 12 is a view (e.g., a plan view) showing a display area DA in a display device according to an embodiment.

[0082] FIG. 13 is a view showing a display area DA in a display device according to an embodiment.

[0083] FIG. 14 is a view showing a display area DA in a display device according to an embodiment.

[0084] FIG. 15 is a view showing a display area DA in a display device according to an embodiment.

[0085] FIG. 16 is a view (e.g., a plan view) schematically showing structures of a driving voltage connection line, a driving voltage line, and a first common voltage line in a display area.

[0086] FIG. 17 is a view schematically showing structures of a driving voltage connection line, a driving voltage line, a first common voltage line, and a second common voltage line within a display area in a display device according to an embodiment.

[0087] FIG. 18 is a view schematically showing structures of a driving voltage connection line, a driving voltage line, and a first common voltage line within a display area in a display device according to an embodiment.

[0088] FIG. 19 is a view schematically showing structures of a driving voltage connection line, a driving voltage line, a first common voltage line, and a second common voltage line within a display area in a display device according to an embodiment.

[0089] FIG. 20 is an equivalent circuit diagram of one pixel of an emissive display device according to an embodiment.

[0090] FIG. 21 is a layout view of one pixel area of an organic light emitting device according to an embodiment.

[0091] FIG. 22 is a cross-sectional view taken along a line XXII-XXII' in FIG. 21 according to an embodiment.

[0092] FIG. 23 is a layout view of a pixel area of a display device according to an embodiment.

DETAILED DESCRIPTION OF EMBODIMENTS

[0093] Embodiments are described with reference to the accompanying drawings. The described embodiments may be modified in various ways.

[0094] Same elements or analogous elements may be designated by same reference numerals.

[0095] In the drawings, dimensions may be exaggerated for clarity.

[0096] Although the terms “first,” “second,” etc. may be used to describe various elements, these elements should not be limited by these terms. These terms may be used to distinguish one element from another element. A first element may be termed a second element without departing from teachings of one or more embodiments. The description of an element as a “first” element may not require or imply the presence of a second element or other elements. The terms “first,” “second,” etc. may be used to differentiate different categories or sets of elements. For conciseness, the terms “first,” “second,” etc. may represent “first-type (or first-set),” “second-type (or second-set),” etc., respectively.

[0097] When a first element is referred to as being “on” a second element, the first element can be directly on the second element, or one or more intervening elements may be present between the first element and the second element. When a first element is referred to as being “directly on” a second element, there are no intervening elements (except environmental elements such as air) present between the first element and the second element.

[0098] Unless explicitly described to the contrary, the word “comprise” and variations such as “comprises” or “comprising” may imply the inclusion of stated elements but not the exclusion of any other elements.

[0099] The term “outer common voltage line” may mean “outer common voltage trunk line.” The term “connect” may mean “electrically connect.” The term “insulate” may mean “electrically insulate” or “electrically isolate.” The term “groove” may mean “opening” or “hole.” The term “opening” may mean “gap.” The term “the same as” may mean “substantially the same as,” “substantially identical to,” or “analogous to.”

[0100] FIG. 1 is a view showing a display device **1000** according to an embodiment. Referring to FIG. 1, the display device **1000** includes a display area DA and a non-display area NDA. A substrate (e.g., the substrate **110** shown in FIG. 22) of the display device **1000** may include a display area and a non-display area that respectively correspond to the display area DA and the non-display area NDA.

[0101] Referring to FIG. 1, an outer common voltage line **7410** may substantially surround the display area DA. The outer common voltage line **7410** is connected to a first common voltage line **741a** and a second common voltage line **741b** disposed in the display area DA. The outer common voltage line **7410** applies a common voltage ELVSS (shown in FIG. 20) in the display area DA.

[0102] In FIG. 1, only some first common voltage lines **741a** and some second common voltage lines **741b** are illustrated for convenience of description, but first common voltage lines **741a** and second common voltage lines **741b** may form a mesh throughout the display area DA. In embodiments, first common voltage lines **741a** or second common voltage lines **741b**, but not both, may be disposed in the display area DA.

[0103] Each first common voltage line **741a** may be lengthwise in the second direction DR2, and each second common voltage line **741b** may be lengthwise in the first direction DR1.

[0104] In FIG. 1, the portion labeled by A is enlarged and shown separately for clarity. Referring to FIG. 1, on one edge of the display device **1000**, the outer common voltage line **7410** is directly connected to a first outer common voltage line **7410a** and a second outer common voltage line **7410b**. As shown in FIG. 1, on one edge connected to a pad part of the display device **1000**, the outer common voltage line **7410** may be directly connected to the first outer common voltage line **7410a** and the second outer common voltage line **7410b**.

[0105] Referring to the portion B of FIG. 1, the outer common voltage line **7410** includes a groove **7410c**. Referring to FIG. 1, the groove **7410c** may be lengthwise in a direction parallel to the second common voltage line **741b**, that is, in the first direction DR1.

[0106] The groove **7410c** is disposed between a plurality of first common voltage line **741a** and the second outer common voltage line **7410b**, so that an electrical path is lengthened between the plurality of first common voltage lines **741a** and the second outer common voltage line **7410b**.

[0107] Therefore, a potential problem of heat generation due to an excessive current simultaneously flowing to the second common voltage line **7410b** may be prevented or mitigated. Advantageously, satisfactory reliability and/or durability of the display device **1000** may be attained.

[0108] FIG. 2 is a view showing a current flow in a display device **1000** according to an embodiment. In the display device **1000**, the outer common voltage line **7410** does not include the groove shown in FIG. 1. The flow of current in the display device **1000** illustrated in FIG. 2 is shown by the arrows. In FIG. 2, the thickness of the arrow indicates the amount of current, and the position where significant heat is generated is indicated by C.

[0109] Referring to FIG. 2, near the second outer common voltage line **7410b**, the current flowing from the outer common voltage line **7410** (disposed in the non-display area NDA) and the current flowing from the first common voltage line **741a** (at least partially disposed in the display area DA) are collected. Regarding the first outer common voltage line **7410a**, since the current flowing from the outer common voltage line **7410** flows out to the second outer common voltage line **7410b**, only the current flowing from the common voltage line **741a** is collected.

[0110] Therefore, more current is concentrated toward the second outer common voltage line **7410b** than toward the first outer common voltage line **7410a**, and thus heat generation is more significant near the second outer common voltage line **7410b**.

[0111] Referring to FIG. 1 and FIG. 3, by disposing the groove **7410c** between the second outer common voltage line **7410b** and a plurality of first common voltage lines **741a**, the current of the first common voltage lines **741a** may not significantly flow to the second outer common voltage line **7410b**, but may flow to the first outer common voltage line **7410a**. Therefore, excessive heat generation may be prevented or mitigated.

[0112] FIG. 3 is a view showing a flow of a current in a display device according to an embodiment. Comparing FIG. 3 and FIG. 2, the amount of current flowing to the second outer common voltage line **7410b** is significantly smaller in the embodiment of FIG. 3 than in the embodiment of FIG. 2. Therefore, excessive heat generation of the outer common voltage line **7410** may be effectively prevented or mitigated according to the embodiment of FIG. 3.

[0113] FIG. 4 is a view showing the same position as a region A of FIG. 1 in a display device according to an embodiment. Referring to FIG. 4, in the display device, the first outer common voltage line **7410a** and the second outer common voltage line **7410b** are separated and/or are respectively directly connected to separate trunk lines.

[0114] Referring to FIG. 4, an opening **7410d** may separate the first outer common voltage line **7410a** from the second outer common voltage line **7410b**. The opening **7410d** includes edges parallel to the first direction DR1 and includes edges parallel to the second direction DR2.

[0115] Referring to FIG. 4, the current of the first common voltage lines **741a** is transmitted to the first outer common voltage line **7410a** and is not transmitted to the second outer common voltage line **7410b**. Accordingly, near the second outer common voltage line **7410b**, undesirable heat generation may be prevented or mitigated.

[0116] FIG. 5 is a view showing the same position as a region A of FIG. 1 in a display device according to an embodiment.

[0117] Referring to FIG. 5, the first outer common voltage line **7410a** and the second outer common voltage line **7410c** are completely separated from each other via the opening **7410d**, which may have opposite edges each parallel to the second direction DR2. Therefore, the amount of current flowing into the first outer common voltage line **7410a** and the amount of current flowing into the second outer common voltage line **7410b** may be properly controlled to prevent excessive heat generation. Even if the first outer common voltage line **7410a** and the second outer common voltage line **7410b** are separated from each other, as shown in FIG. 1, they are connected to each other in the display area DA by the second common voltage lines **741b** disposed in the display area DA. Therefore, the common voltage transmitted by the first outer common voltage line **7410a** is equal to the common voltage transmitted by the second outer common voltage line **7410b**.

[0118] Referring to FIG. 5, the total number of first common voltage lines **741a** directly connected to the first outer common voltage line **7410a** may be equal or unequal to the total number of first common voltage lines directly connected to the second outer common voltage line **7410b**. The number of first common voltage lines **741a** directly connected to the first outer common voltage line **7410a** may be significantly greater than the number of first common voltage lines **741a** directly connected to the second outer common voltage line **7410b**. In an embodiment, no first common voltage line **741a** may be directly connected to the second outer common voltage line **7410b**, and some first common voltage line **741a** may be directly connected only to the first outer

common voltage line **7410a**. The number of first common voltage lines **741a** directly connected to the first outer common voltage line **7410a** and the number of first common voltage lines **741a** directly connected to the second outer common voltage line **7410b** may be appropriately selected for minimizing heat at the second outer common voltage line **7410b**.

[0119] FIG. **6** is a view showing a display device **1000** including an outer common voltage line **7410**, an outer driving voltage line **1720**, and an outer initialization voltage line **1270** according to an embodiment. In FIG. **6**, only some wires are shown for convenience of illustration.

[0120] Referring to FIG. **6**, in the non-display area NDA outside the display area DA, the outer common voltage line **7410** may substantially surround the display area DA. The outer driving voltage line **1720** may be disposed between opposite section of the outer common voltage line **7410**.

[0121] TA first outer common voltage line **7410a** and a second outer common voltage line **7410b** may protrude from the outer common voltage line **7410**, and a groove **7410c** is disposed between a first outer common voltage line **7410a** and the second outer common voltage line **7410b**. The outer common voltage line **7410** may be connected to the first common voltage line **741a** and a second common voltage line (analogous to a second common voltage line **741b** shown in FIG. **1**) that extend to the display area DA. In the display area DA, the first common voltage line **741a** may be lengthwise in the second direction DR2, and the second common voltage line may be lengthwise in the first direction DR1.

[0122] The outer driving voltage line **1720** may be disposed between opposite ends of the outer common voltage line **7410**. The outer driving voltage line **1720** may be disposed in a space between opposite sections of the outer common voltage lines **7410**. The outer driving voltage line **1720** transmits the driving voltage ELVDD to the display area DA.

[0123] The outer driving voltage line **1720** is directly connected to driving voltage lines **172**, which may be at least partially disposed in the display area DA. The driving voltage lines **172** may be lengthwise in the second direction DR2. Referring to FIG. **6** and FIG. **12**, driving voltage connection lines **172c** may be lengthwise in the first direction DR1 and may be at least partially disposed in the display area DA. The driving voltage connection lines **172c** may cross the driving voltage lines **172** for evenly transmitting the driving voltage in the display area DA. The driving voltage line **172** and the driving voltage connection line **172c** are form a mesh in the display area DA and are connected to each other, so that pixels not directly connected to the driving voltage line **172** may also receive the driving voltage ELVDD.

[0124] The outer initialization voltage line **1270** is disposed between the outer common voltage line **7410** and the display area DA. The outer initialization voltage line **1270** is directly connected to initialization voltage line **127**, which may be at least partially disposed in the display area DA and may transmit an initialization voltage to the display area DA. The initialization voltage lines **127** may be lengthwise in the first direction DR1.

[0125] Although not shown in FIG. **6**, a second common voltage line lengthwise in the first direction DR1 may be at least partially disposed in the display area DA. The number and position of the wires/lines shown in FIG. **6** may be configured according to embodiments.

[0126] Although only portions of the first common voltage lines **741a** are shown in FIG. **6**, the first common voltage lines **741a** may be connected to sections of the outer common voltage line **7410** disposed at opposite sides of the display area DA. The driving voltage line **172** may also extend in the second direction from one edge of the display area DA to another edge of the display area DA. In embodiments, outer initialization voltage lines **1270** may be disposed at two or more sides of the display area DA. The initialization voltage lines **127** may extend in the first direction DR1 from one edge of the display area DA to another edge of the display area DA.

[0127] FIG. **7** is a view showing a display device according to an embodiment. Referring to FIG. **7**, a first outer common voltage line **7410a** and a second outer common voltage line **7410b** are separated by a gap/opening. No first common voltage lines **741a** may be directly connected to the

second outer common voltage line **7410b**.

[0128] The first outer common voltage line **7410a** and the second outer common voltage line **7410b** are separated by the opening **7410d**, which may have opposite edges parallel to the first direction **DR1** and may have opposite edges parallel to the second direction **DR2**. The current of the first common voltage lines **741a** is transmitted to the first outer common voltage line **7410a**. Thus, the current is not concentrated in the second outer common voltage line **7410b**, and excessive heat generation may be prevented. The first outer common voltage line **7410a** and the second outer common voltage line **7410b** may be electrically connected to each other through the second common voltage lines **741b** disposed in the display area **DA**, so the common voltage transmitted by the first outer common voltage line **7410a** is equal to the common voltage transmitted by the second outer common voltage line **7410b**.

[0129] FIG. **8** is a view showing a display device according to an embodiment. Referring to FIG. **8**, the first outer common voltage line **7410a** and the second outer common voltage line **7410b** are separated. Referring to FIG. **8**, the opening **7410d** may have opposite edges that are lengthwise in the second direction **DR2**. The operation and effect are similar to those in the embodiment of FIG. **7**.

[0130] FIG. **9** is a view showing a display device according to an embodiment. Referring to FIG. **9**, outer common voltage lines **7410** are disposed at opposite sides of the display area **DA**.

[0131] The display area **DA** may not be disposed between outer common voltage lines in the first direction **DR1**. Referring to FIG. **9**, the outer common voltage lines **7410** may include a first outer common sub-voltage line **7410_S1** and a second outer common sub-voltage line **7410_S2**.

[0132] The first outer common sub-voltage line **7410_S1** and the second outer common sub-voltage line **7410_S2** may be electrically connected through first common voltage lines **741a**, which may be at least partially disposed in the display area **DA**. Therefore, the common voltage **ELVSS** may be substantially uniformly provided over the display area **DA**. Since the outer common voltage lines are not disposed at the left and right sides of the display area **DA**, the left and right non-display areas **NDA** may be minimized.

[0133] FIG. **10** is a view showing a display device according to an embodiment. Referring to FIG. **10**, outer common voltage lines **7410_S1** and **7410_S2** are disposed at opposite sides of the display area **DA**. Outer common voltage lines **7410_S2** are spaced in the first direction **DR1** and in the second direction **DR2**. The effect of the separation of the outer common voltage lines **7410** is the same as or analogous to that described with reference to FIG. **9**.

[0134] FIG. **11** is a view showing a display device according to an embodiment. Referring to FIG. **11**, outer common voltage lines **7410_S1** and **7410_S2** are disposed at opposite sides of the display area **DA**. Outer common voltage lines **7410_S2** are spaced in the first direction **DR1**. The effect of the separation of the outer common voltage lines **7410** is the same as or analogous to that described in FIG. **9**.

[0135] One or more structures of the display area **DA** described with reference to one or more of FIG. **12** to FIG. **15** may be applicable to the display area **DA** described with reference to one or more of FIG. **6** to FIG. **11**.

[0136] FIG. **12** is a view showing a display area **DA** in a display device according to an embodiment. Referring to FIG. **12**, one of the driving voltage lines **172** connected to the plurality of pixels **PX1**, **PX2**, and **PX3** is replaced by a first common voltage line **741a**. Therefore, the outer common voltage line **7410** disposed via the display area **DA** in the second direction **DR2** may be connected. When separate outer common voltage lines **7410** are disposed at opposite sides of the display area **DA**, as shown in FIG. **9** to FIG. **11**, the first common voltage line **741a** may electrically connect the separate outer common voltage lines **7410**. Referring to FIG. **6** to FIG. **8**, even if the outer common voltage lines **7410** are electrically connected in the non-display area **NDA**, the common voltage is transmitted to the first common voltage line **741a** inside the display area **DA**, such that the common voltage may be uniformly provided in the display area **DA**.

[0137] Referring to FIG. 12, driving voltage connection lines 172c may cross driving voltage lines 172. The driving voltage connection lines 172c may be electrically connected to the driving voltage lines 172 at the cross points. Therefore, the driving voltage transmitted to a driving voltage line 172 may be transmitted to neighboring pixels. The driving voltage connection line 172c may be disposed on a different layer than the driving voltage line 172.

[0138] FIG. 13 is a view showing a display area DA in a display device according to an embodiment. The display area DA according to the embodiment of FIG. 13 is the same as embodiment of FIG. 12, except for further including the second common voltage line 741b. The first common voltage line 741a may be disposed parallel to the second direction DR2, and the second common voltage line 741b may be disposed parallel to the first direction DR1.

[0139] The display device according to the embodiment of FIG. 13 includes a mesh structure where the first common voltage line 741a and the second common voltage line 741b intersect. In this case, the reduction of the common voltage ELVSS may be effectively prevented. The common voltage ELVSS is evenly transmitted to the pixels in the display area DA along the common voltage lines 741a and 741b having a mesh structure.

[0140] FIG. 14 is a view showing a display area DA in a display device according to an embodiment. Referring to FIG. 14, the display device is different from that of FIG. 12 in that the structure (and/or material) of a first common voltage line 741a may be substantially different from the structure (and/or material) of each of the driving voltage lines 172 connected to the pixels PX1, PX2, and PX3. The first common voltage line 741a may be formed without removing any existing driving voltage line 172.

[0141] FIG. 15 is a view showing a display area DA in a display device according to an embodiment. FIG. 15 is the same as the display device according to the embodiment of FIG. 13, except that a first common voltage line 741a is additionally formed without removing a driving voltage line 172 in the display area DA.

[0142] In FIG. 12 to FIG. 15, the driving voltage connection line 172c, the driving voltage line 172, and the first common voltage line 741a may be respectively directly disposed on different material layers. The driving voltage connection line 172c and the driving voltage line 172 are disposed on different layers, but are connected to each other through a contact hole so that the driving voltage may be evenly transmitted.

[0143] FIG. 16 is a view schematically showing structures of a driving voltage connection line 172c, a driving voltage line 172, and a first common voltage line 741a in a display area. In FIG. 16, PX1, PX2, and PX3 are labeled to distinguish the pixels to which wires are connected.

[0144] Referring to FIG. 16, the driving voltage connection line 172c, the driving voltage line 172, and the first common voltage line 741a are located on different layers, respectively. For example, the driving voltage connection line 172c may be disposed between the substrate and the driving voltage line 172; the driving voltage connection line 172c and the driving voltage line 172 may be disposed between the substrate and the first common voltage line 741a. In embodiments, the driving voltage line 172 and the first common voltage line 741a may be disposed directly on the same layer.

[0145] Referring to FIG. 16, a width of the driving voltage connection line 172c overlapping the first common voltage line 741a may be narrower than a width of the driving voltage connection line 172c overlapping a driving voltage line 172. Therefore, the risk of the first common voltage line 741a and the driving voltage connection line 172c being shorted to each other may be reduced. The driving voltage connection line 172c and the driving voltage line 172 are connected to each other through a contact hole 28.

[0146] FIG. 17 is a view schematically showing structures of a driving voltage connection line 172c, a driving voltage line 172, a first common voltage line 741a, and a second common voltage line 741b within a display area in a display device according to an embodiment. The first common voltage line 741a is connected to the second common voltage line 741b.

[0147] The first common voltage line **741a** and the second common voltage line **741b** may be disposed on the same layer and directly connected to each other. The common voltage lines **741a** and **741b** may form of a mesh. The common voltage lines **741a** and **741b** may be separated and insulated from the driving voltage line **172** by an intervening insulating layer. The driving voltage line **172** may be disposed closer to the substrate than the common voltage lines **741a** and **741b**.

[0148] FIG. **18** is a view schematically showing structures of a driving voltage connection line **172c**, a driving voltage line **172**, and a first common voltage line **741a** within a display area in a display device according to an embodiment. Referring to FIG. **18**, the first common voltage line **741a** is disposed outside the pixels **PX1**, **PX2**, and **PX3**. The first common voltage line **741a** is disposed without removing the existing driving voltage line **172**. Each driving voltage line **172** is connected to a pixel **PX1**, **PX2**, or **PX3**, and the first common voltage line **741a** is disposed between two pixel groups each including pixels **PX1**, **PX2**, and **PX3**. The first common voltage line **741a** may be disposed directly on the same layer as the driving voltage lines **172**.

[0149] FIG. **19** is a view schematically showing structures of a driving voltage connection line **172c**, a driving voltage line **172**, and a first common voltage line **741a** within a display area in a display device according to an embodiment. Common voltage lines include a first common voltage line **741a** and a second common voltage line **741b**.

[0150] The first common voltage line **741a** and the second common voltage line **741b** may be disposed on the same layer and directly connected to each other. The display device may include a mesh structure, wherein first common voltage lines **741a** cross second common voltage lines **741b**. The common voltage lines **741a** and **741b** may be separated and insulated from the driving voltage line **172** by an intervening insulating layer. The driving voltage line **172** may be disposed closer to the substrate than the common voltage lines **741a** and **741b**.

[0151] FIG. **20** is an equivalent circuit diagram of one pixel of an emissive display device according to an embodiment.

[0152] Referring to FIG. **20**, the pixel **PX** of the emissive display device includes a plurality of transistors **T1**, **T2**, **T3**, **T4**, **T5**, **T6**, and **T7**, a storage capacitor **Cst**, and a light emitting diode (LED), which are connected to several signal lines **127**, **151**, **152**, **153**, **158**, **171**, **172**, and **741**.

[0153] The emissive display device includes the display area displaying the image, and these pixels **PX** are arranged in various forms in the display area.

[0154] The plurality of transistors **T1**, **T2**, **T3**, **T4**, **T5**, **T6**, and **T7** include a driving transistor **T1**, a switching transistor connected to a scan line **151**, that is, includes a second transistor **T2** and a third transistor **T3**, and the rest of the transistors are a transistors (hereinafter referred to as compensation transistors) required to operate the light emitting diode (LED). The compensation transistors **T4**, **T5**, **T6**, and **T7** may include a fourth transistor **T4**, a fifth transistor **T5**, a sixth transistor **T6**, and a seventh transistor **T7**.

[0155] The plurality of signal lines **127**, **151**, **152**, **153**, **158**, **171**, **172**, and **741** may include the scan line **151**, a previous scan line **152**, a light emission control line **153**, a bypass control line **158**, a data line **171**, the driving voltage line **172**, an initialization voltage line **127**, and a common voltage line **741**. The bypass control line **158** may be a part of the previous scan line **152** or may be electrically connected thereto.

[0156] The scan line **151** is connected to a gate driver, and transmits a scan signal **Sn** to the second transistor **T2** and the third transistor **T3**. The previous scan line **152** is connected to the gate driver, and transmits a previous scan signal **Sn-1** applied to the pixel **PX** positioned at the previous stage to the fourth transistor **T4**. The light emission control line **153** is connected to a light emission controller, and transmits a light emission control signal **EM** that controls the time that the light emitting diode (LED) emits light to the fifth transistor **T5** and the sixth transistor **T6**. The bypass control line **158** transmits a bypass signal **GB** to the seventh transistor **T7**.

[0157] The data line **171** is a wire for transmitting a data voltage **Dm** generated by a data driver, and the luminance of the light emitting diode (LED) (also called a light-emitting element) changes

according to the data voltage Dm. The driving voltage line 172 applies a driving voltage ELVDD. The initialization voltage line 127 transmits an initialization voltage Vint that initializes the driving transistor T1. The common voltage line 741 applies a common voltage ELVSS. The voltages applied to the driving voltage line 172, the initialization voltage line 127, and the common voltage line 741 may be applied with a constant voltage, respectively.

[0158] The driving transistor T1 is for adjusting the magnitude of the current output according to the applied data voltage Dm. The output driving current (Id) is applied to the light emitting diode (LED) to adjust the brightness of the light emitting diode (LED) according to the data voltage Dm. For this purpose, the first electrode S1 of the driving transistor T1 may allow the driving voltage ELVDD to be applied. The first electrode S1 is connected to the driving voltage line 172 via the fifth transistor T5. In addition, the first electrode S1 of the driving transistor T1 is also connected to the second electrode D2 of the second transistor T2 to receive the data voltage Dm. The second electrode D1 (an output electrode) of the driving transistor T1 may output the current toward the light emitting diode (LED). The second electrode D1 of the driving transistor T1 is connected to the anode of the light emitting diode (LED) via the sixth transistor T6. On the other hand, the gate electrode G1 is connected to one electrode (a second storage electrode E2) of the storage capacitor Cst. The voltage of the gate electrode G1 changes according to the voltage stored in the storage capacitor Cst, thereby the driving current Id output by the driving transistor T1 changes.

[0159] The second transistor T2 receives the data voltage Dm into the pixel PX. The gate electrode G2 is connected to the scan line 151 and the first electrode S2 is connected to the data line 171. The second electrode D2 of the second transistor T2 is connected to the first electrode S1 of the driving transistor T1. When the second transistor T2 is turned on according to a scan signal Sn transmitted through the scan line 151, the data voltage Dm transmitted through the data line 171 is transferred to the first electrode S1 of the driving transistor T1.

[0160] The third transistor T3 transmits a compensation voltage (Dm+Vth) from the driving transistor T1 to the second storage electrode E2 of the storage capacitor Cst. The gate electrode G3 is connected with scan line 151, and the first electrode S3 is connected to the second electrode D1 of the driving transistor T1. The second electrode D3 of the third transistor T3 is connected to the second storage electrode E2 of the storage capacitor Cst and the gate electrode G1 of the driving transistor T1. The third transistor T3 is turned on according to the scan signal Sn received through the scan line 151 to connect the gate electrode G1 and the second electrode D1 of the driving transistor T1, and also to connect the second electrode D1 of the driving transistor T1 and the second storage electrode E2 of the storage capacitor Cst.

[0161] The fourth transistor T4 serves to initialize the gate electrode G1 of the driving transistor T1 and the second storage electrode E2 of the storage capacitor Cst. The gate electrode G4 is connected to the previous scan line 152, and the first electrode S4 is connected to the initialization voltage line 127. The second electrode D4 of the fourth transistor T4 is connected to the second storage electrode E2 of the storage capacitor Cst and the gate electrode G1 of the driving transistor T1 via the second electrode D3 of the third transistor T3. The fourth transistor T4 transfers the initialization voltage Vint to the gate electrode G1 of the driving transistor T1 and the second storage electrode E2 of the storage capacitor Cst according to the previous scan signal Sn-1 received through the previous scan line 152. Accordingly, the gate voltage of the gate electrode G1 of the driving transistor T1 and the storage capacitor Cst are initialized. The initialization voltage Vint has a low voltage value, thereby being a voltage that turns on the driving transistor T1.

[0162] The fifth transistor T5 serves to transmit the driving voltage ELVDD to the driving transistor T1. The gate electrode G5 is connected to the light emission control line 153, and the first electrode S5 is connected to the driving voltage line 172. The second electrode D5 of the fifth transistor T5 is connected to the first electrode S1 of the driving transistor T1.

[0163] The sixth transistor T6 serves to transmit the driving current Id output from the driving transistor T1 to the light emitting diode (LED). The gate electrode G6 is connected to the light

emission control line **153**, and the first electrode **S6** is connected to the second electrode **D1** of the driving transistor **T1**. The second electrode **D6** of the sixth transistor **T6** is connected to the anode of the light emitting diode (LED).

[0164] If the fifth transistor **T5** and the sixth transistor **T6** are simultaneously turned on according to the light emission control signal **EM** transmitted through the light emission control line **153** and the driving voltage **ELVDD** is applied to the first electrode **S1** of the driving transistor **T1** through the fifth transistor **T5**, the driving transistor **T1** outputs the driving current I_d according to the voltage (i.e., the voltage of the second storage electrode **E2** of the storage capacitor **Cst**) of the gate electrode **G1** of the driving transistor **T1**. The output driving current I_d is transmitted to the light emitting diode (LED) through the sixth transistor **T6**. As the current (I_{led}) flows through the light emitting diode (LED), the light emitting diode (LED) emits light.

[0165] The seventh transistor **T7** serves to initialize the anode of the light emitting diode (LED). The gate electrode **G7** is connected to the bypass control line **158**, the first electrode **S7** is connected to the anode of the light emitting diode (LED), and the second electrode **D7** is connected to the initialization voltage line **127**. The bypass control line **158** may be connected to the previous scan line **152**, and the bypass signal **GB** is applied at the same timing signal as the previous scan signal S_{n-1} . The bypass control line **158** may transmit a signal separate from the previous scan signal S_{n-1} without being connected with the previous scan line **152**. When the seventh transistor **T7** is turned on according to the bypass signal **GB**, the initialization voltage V_{int} is applied to the anode of the light emitting diode (LED) and initialized.

[0166] The first storage electrode **E1** of the storage capacitor **Cst** is connected to the driving voltage line **172**, and the second storage electrode **E2** is connected to the gate electrode **G1** of the driving transistor **T1**, the second electrode **D3** of the third transistor **T3**, and the second electrode **D4** of the fourth transistor **T4**. As a result, the second storage electrode **E2** determines the voltage of the gate electrode **G1** of the driving transistor **T1**, and receives the data voltage D_m through the second electrode **D3** of the third transistor **T3** or the initialization voltage V_{int} through the second electrode **D4** of the fourth transistor **T4**.

[0167] On the other hand, the anode of the light emitting diode (LED) is connected to the second electrode **D6** of the sixth transistor **T6** and the first electrode **S7** of the seventh transistor **T7**, and the cathode is connected to the common voltage line **741** transmitting the common voltage **ELVSS**.

[0168] In the embodiment of FIG. **20**, the pixel circuit includes seven transistors (**T1** to **T7**) and one capacitor **Cst**. The number of transistors, the number of capacitors, and their connections may be configured according to embodiments.

[0169] FIG. **21** is a layout view of one pixel area of an organic light emitting device according to an embodiment, and FIG. **22** is a cross-sectional view taken along a line **XXII-XXII'** in FIG. **21** according to an embodiment.

[0170] Referring to FIG. **21**, the emissive display device includes a scan line **151** extending along the first direction **D1** and transmitting the scan signal S_n , a previous scan line **152** transmitting the previous scan signal S_{n-1} , a light emission control line **153** transmitting the light emission control signal **EM**, and an initialization voltage line **127** transmitting the initialization voltage V_{int} . The bypass signal **GB** is transmitted through the previous scan line **152**.

[0171] The emissive display device includes the data line **171** extending in a second direction **DR2** crossing the first direction **DR1** and transmitting the data voltage D_m , and the first common voltage line **741a** transmitting the common voltage **ELVSS**. The first pixel **PX1** described in FIG. **21** and FIG. **22** is the pixel **PX1** in which the driving voltage line **172** is replaced with the first common voltage line **741a**. The first pixel **PX1** of FIG. **21** and FIG. **22** is an embodiment in which the driving voltage line **172** connected to the pixel is replaced with the first common voltage line **741a**. In the second pixel **PX2** shown in FIG. **21**, the driving voltage line **172** is not replaced with the first common voltage line **741a**, and the existing driving voltage line **172** is disposed.

Hereinafter, the first pixel **PX1** is described in comparison with the second pixel **PX2**.

[0172] The emissive display device includes the driving transistor T1, the second transistor T2, the third transistor T3, the fourth transistor T4, the fifth transistor T5, the sixth transistor T6, the seventh transistor T7, the storage capacitor Cst, and the light emitting diode (LED).

[0173] Each channel of the driving transistor T1, the second transistor T2, the third transistor T3, the fourth transistor T4, the fifth transistor T5, the sixth transistor T6, and the seventh transistor T7 is disposed within a semiconductor layer 130 that is elongated. Also, at least part of the first electrode and the second electrode of the plurality of transistors T1, T2, T3, T4, T5, T6, and T7 is disposed in the semiconductor layer 130. The semiconductor layer 130 (a part in which the shade is added in FIG. 21) may be formed to be bent in various shapes. The semiconductor layer 130 may include a polycrystalline semiconductor such as polysilicon, or an oxide semiconductor.

[0174] The semiconductor layer 130 includes a channel channel-doped with an n-type impurity or a p-type impurity, and a first doping region and a second doping region of which a doping concentration is higher than the impurity doped with the channel. The first doping region and the second doping region correspond to the first electrode and the second electrode of the plurality of transistors T1, T2, T3, T4, T5, T6, and T7, respectively. One of the first doping region and the second doping region may be the source region, and the other may be the drain region. Also, in the semiconductor layer 130, a region between the first electrode and the second electrode of different transistors from each other may be doped such that two transistors may be electrically connected to each other.

[0175] Each channel of the plurality of transistors T1, T2, T3, T4, T5, T6, and T7 overlaps the gate electrode of each transistor T1, T2, T3, T4, T5, T6, and T7 and is disposed between the first electrode and the second electrode of each transistor T1, T2, T3, T4, T5, T6, and T7. A plurality of transistors T1, T2, T3, T4, T5, T6, and T7 may have substantially the same stacked structure. Hereinafter, the driving transistor T1 is mainly described in detail, and the remaining transistors T2, T3, T4, T5, T6, and T7 are briefly described.

[0176] The driving transistor T1 includes a channel, a first gate electrode 155, a first electrode S1, and a second electrode D1. The channel of the driving transistor T1 is between the first electrode S1 and the second electrode D1, and overlaps the first gate electrode 155 in a plan view. The channel is curved to form a longer length of the channel in a limited region. As the length of the channel increases, a driving range of the gate voltage V_g applied to the first gate electrode 155 of the driving transistor T1 becomes wider, and the driving current I_d constantly increases according to the gate voltage V_g . As a result, the gray of the light emitted from the light emitting diode (LED) may be controlled more precisely by changing the magnitude of the gate voltage V_g , and the display quality of the emissive display device may be improved. In addition, since the channel is not extended in one direction but extends in various directions, there is a merit in which the directional influence is canceled in the manufacturing process, thereby reducing the effect of process dispersion. Therefore, it is possible to prevent the deterioration of image quality such as an unevenness defect (e.g., a luminance difference is generated depending on the pixel even if the same data voltage D_m is applied) which may be caused by a characteristic difference of the driving transistor T1 depending on the region of display device due to the process dispersion. The shape of such a channel may be varied without being limited to the shown Ω type.

[0177] The first gate electrode 155 overlaps the channel on a plane. The first electrode S1 and the second electrode D1 are located on respective sides of the channel. An extended portion of a storage line 126 is insulated from and disposed above the first gate electrode 155. The extended portion of the storage line 126 overlaps the gate electrode 155 via the second gate insulating layer interposed therebetween on a plane, thereby configuring a storage capacitor Cst. The extended portion of the storage line 126 is the first storage electrode (E1 of FIG. 20) of the storage capacitor Cst, and the first gate electrode 155 is the second storage electrode (E2 of FIG. 20). The extended portion of the storage line 126 has an opening 56 so that the first gate electrode 155 is connected to a first data connecting member 71. Within the opening 56, the upper surface of the first gate

electrode **155** and the first data connecting member **71** are electrically connected through a contact hole **61**. The first data connecting member **71** is connected to the second electrode **D3** of the third transistor **T3** to connect the gate electrode **155** of the driving transistor **T1** and the second electrode **D3** of the third transistor **T3**.

[0178] The gate electrode of the second transistor **T2** may be the part of the scan line **151**. The data line **171** is in contact with the first electrode **S2** of the second transistor **T2** through a contact hole **62**. The first electrode **S2** and the second electrode **D2** may be disposed on the semiconductor layer **130**.

[0179] The third transistor **T3** may be composed of two transistors adjacent to each other. Within the pixel **PX** of FIG. **21**, two parts of **T3** are on the left side and the lower side with respect to the portion where the semiconductor layer **130** is bent. These two parts play the role of the third transistor **T3**, respectively, and have a structure in which the first electrode **S3** of one part of the third transistor **T3** is connected to the second electrode **D3** of the other part of the third transistor **T3**. The gate electrodes of two transistors **T3** may be the part of the scan line **151** or the part protruded upward from the scan line **151**. Such a structure may be referred to as a dual gate structure, and may serve to block a leakage current. The first electrode **S3** of the third transistor **T3** is connected to the first electrode **S6** of the sixth transistor **T6** and the second electrode **D1** of the driving transistor **T1**. The second electrode **D3** of the third transistor **T3** is connected to the first data connecting member **71** through a contact hole **63**.

[0180] The fourth transistor **T4** is composed of two fourth transistors **T4**, and two fourth transistors **T4** are formed at the intersection of the previous scan line **152** and the semiconductor layer **130**. The gate electrode of the fourth transistor **T4** may be the part of the previous scan line **152**. The first electrode **S4** of one part of the fourth transistor **T4** is connected to the second electrode **D4** of the other part of the fourth transistor **T4**. Such a structure may be referred to as a dual gate structure, and may serve to block the leakage current. A second data connecting member **72** is connected to the first electrode **S4** of the fourth transistor **T4** through a contact hole **65**, and the first data connecting member **71** is connected to the second electrode **D4** of the fourth transistor **T4** through the contact hole **63**.

[0181] As such, by using the dual gate structure as the third transistor **T3** and the fourth transistor **T4**, the leakage current may be effectively prevented by blocking an electron moving path of the channel in the off state.

[0182] The gate electrode of the fifth transistor **T5** may be a part of the light emission control line **153**. The driving voltage connection line **172c** is connected to the first electrode **S5** of the fifth transistor **T5** through a contact hole **77**, and the second electrode **D5** is connected to the first electrode **S1** of the driving transistor **T1** through the semiconductor layer **130**.

[0183] The first pixel **PX1** receives the driving voltage **ELVDD** from the adjacent pixel **PX2** through the driving voltage connection line **172c** connected to the driving voltage line **172** of the adjacent pixel **PX2** since the driving voltage line **172** connected to the pixel is replaced with the first common voltage line **741a**.

[0184] However, in the second pixel **PX2**, the driving voltage line **172** is connected to the first electrode **S5** of the fifth transistor **T5** through a contact hole **67**, and the second electrode **D5** is connected to the first electrode **S1** of the driving transistor **T1** through the semiconductor layer **130**.

[0185] The gate electrode of the sixth transistor **T6** may be a part of the light emission control line **153**. A third data connecting member **73** is connected to the second electrode **D6** of the sixth transistor **T6** through a contact hole **69**, and the first electrode **S6** is connected to the second electrode **D1** of the driving transistor through the semiconductor layer **130**.

[0186] The gate electrode of the seventh transistor **T7** may be the part of the previous scan line **152**. The first electrode **S7** of the seventh transistor **T7** is connected to the second electrode **D6** of the sixth transistor **T6**, and the second electrode **D7** is connected to the first electrode **S4** of the fourth transistor **T4**.

[0187] The storage capacitor Cst includes the first storage electrode E1 and the second storage electrode E2 overlapping a second gate insulating layer 142 interposed therebetween. The second storage electrode E2 may correspond to the gate electrode 155 of the driving transistor T1, and the first storage electrode E1 may be the extended portion of the storage line 126. The second gate insulating layer 142 becomes a dielectric material, and the capacitance is determined by the charge stored in the storage capacitor Cst and the voltage between the first and second storage electrodes E1 and E2. By using the first gate electrode 155 as the second storage electrode E2, it is possible to secure a space for forming the storage capacitor Cst in the space narrowed by the channel of the driving transistor T1 that occupies a large area in the pixel.

[0188] The first storage electrode E1 of the first pixel PX1 receives the driving voltage through the driving voltage connection line 172c. Accordingly, the storage capacitor Cst stores the charge corresponding to the difference between the driving voltage ELVDD transmitted to the first storage electrode E1 through the driving voltage connection line 172c and the gate voltage Vg of the gate electrode 155.

[0189] However, the driving voltage line 172 is connected to the first storage electrode E1 of the second pixel PX1 through a contact hole 68. Therefore, the storage capacitor Cst stores the charge corresponding to the difference between the driving voltage ELVDD transmitted to the first storage electrode E1 through the driving voltage line 172 and the gate voltage Vg of the gate electrode 155.

[0190] The second data connecting member 72 is connected to the initialization voltage line 127 through a contact hole 64. The first electrode is connected to the third data connecting member 73 through a contact hole 81. The first electrode may be a pixel electrode.

[0191] A parasitic capacitor control pattern 79 may be disposed between the dual gate electrodes of the compensation transistor T3. There is a parasitic capacitor in the pixel. If the voltage applied to the parasitic capacitor changes, the image quality characteristic may change. In the first pixel PX1 of FIG. 21, the first common voltage line 741a is disposed instead of the driving voltage line 172 such that the driving voltage line 172 and the parasitic capacitor control pattern 79 are not connected, however in the second pixel PX2, the parasitic capacitor control pattern 79 is connected to the driving voltage line 172 through a contact hole 66. Thus, by applying the driving voltage ELVDD having a constant DC voltage to the parasitic capacitor, it is possible to prevent the image quality characteristic from being changed. The parasitic capacitor control pattern 79 may be disposed in a different region than that shown, and a voltage other than the driving voltage ELVDD may be applied.

[0192] One end of the first data connecting member 71 is connected to the gate electrode 155 through the contact hole 61, and the other end is connected to the second electrode D3 of the third transistor T3 and the second electrode D4 of the fourth transistor T4 through the contact hole 63.

[0193] One end of the second data connecting member 72 is connected to the first electrode S4 of the fourth transistor T4 through the contact hole 65, and the other end is connected to the initialization voltage line 127 through the contact hole 64.

[0194] The third data connecting member 73 is connected to the second electrode of the sixth transistor T6 through the connect contact hole 69.

[0195] The cross-sectional structure of the emissive display device according to an embodiment is described with reference to FIG. 22 as well as FIG. 21.

[0196] The emissive display device includes a first substrate 110.

[0197] The first substrate 110 may include a plastic layer and a barrier layer. The plastic layer and the barrier layer may be alternately stacked.

[0198] The plastic layer may include one selected from a group including polyether sulfone (PES), polyacrylate (PAR), polyether imide (PEI), polyethylene naphthalate (PEN), polyethylene terephthalate (PET), polyphenylene sulfide (PPS), polyarylate, polyimide (PI), polycarbonate (PC), poly(arylene ether sulfone), and a combinations of some of the materials.

[0199] The barrier layer may include at least one of a silicon oxide, a silicon nitride, and aluminum

oxide, and may include any inorganic material without being limited thereto.

[0200] A buffer layer **112** is disposed on the first substrate **110**. The buffer layer **112** may include an inorganic insulating material such as a silicon oxide, a silicon nitride, aluminum oxide, or an organic insulating material such as polyimide acryl.

[0201] The semiconductor layer **130** including the channels and the first electrode and the second electrode of the plurality of transistors **T1**, **T2**, **T3**, **T4**, **T5**, **T6**, and **T7** is disposed on the buffer layer **112**.

[0202] A first gate insulating layer **141** covering the semiconductor layer **130** is disposed thereon. A first gate conductor including the first gate electrode **155**, the scan line **151**, the previous scan line **152**, and the light emission control line **153** is disposed on the first gate insulating layer **141**.

[0203] The second gate insulating layer **142** covering the first gate conductor is disposed thereon. The first gate insulating layer **141** and the second gate insulating layer **142** may include the inorganic insulating material such as a silicon nitride, a silicon oxide, and aluminum oxide, or the organic insulating material.

[0204] A second gate conductor including a storage line **126**, an initialization voltage line **127**, and a parasitic capacitor control pattern **79** is disposed on the second gate insulating layer **142**.

[0205] An interlayer insulating layer **160** covering the second gate conductor is disposed on the second gate conductor. The interlayer insulating layer **160** may include the inorganic insulating material such as a silicon nitride, a silicon oxide, and aluminum oxide, or may include the organic insulating material.

[0206] A data conductor including the data line **171**, the driving voltage line **172**, the driving voltage connection line **172c**, the first data connecting member **71**, the second data connecting member **72**, and the third data connecting member **73** is disposed on the interlayer insulating layer **160**. The first data connecting member **71** may be connected to the first gate electrode **155** through the contact hole **61**.

[0207] A passivation layer **180** covering the data conductor is disposed thereon. The passivation layer **180** may be a planarization layer, and may include the organic insulating material or the inorganic insulating material.

[0208] A first electrode **191** is disposed on the passivation layer **180**. The first electrode **191** is connected to the third data connecting member **73** through the contact hole **81** formed in the passivation layer **180**.

[0209] A partition **350** is formed on the passivation layer **180** and the first electrode **191**. The partition **350** has an opening **351** overlapping the first electrode **191**. An emission layer **370** is disposed on the opening **351**. A second electrode **270** is disposed on the emission layer **370** and the partition **350**. The first electrode **191**, the emission layer **370**, and the second electrode **270** form the light-emitting element (LED). The first electrode **191** may be a pixel electrode, and the second electrode **270** may be a common electrode.

[0210] According to an embodiment, the pixel electrode may be an anode which is a hole injection electrode, and the common electrode may be a cathode which is an electron injection electrode. In contrast, the pixel electrode may be the cathode and the common electrode may be the anode. When holes and electrons are injected into the emission layer from the pixel electrode and the common electrode, respectively, an exciton of which the injected holes and electrons are combined emits light when it falls from an excited state to a ground state.

[0211] An encapsulation layer **400** protecting the light-emitting element LED is disposed on the second electrode **270**. The encapsulation layer **400** may be in contact with the second electrode **270** as shown, or may be spaced apart from the second electrode **270** according to an embodiment.

[0212] The encapsulation layer **400** may be a thin film encapsulation layer in which an inorganic film and an organic film are stacked, and may include a triple layer composed of the inorganic film, the organic film, and the inorganic film. According to an embodiment, a capping layer and a functional layer may be located between the second electrode **270** and the encapsulation layer **400**.

[0213] FIG. 23 is a layout view of a pixel area of a display device according to an embodiment. Referring to FIG. 23, the display device includes a plurality of signal lines 127, 151, 152, 153, 171, 172, and 741. The plurality of signal lines may include the scan line 151, the previous scan line 152, and the light emission control line 153 disposed in the first direction DR1, and the data line 171, the driving voltage line 172, the initialization voltage line 127, and the common voltage line 741a disposed in the second direction DR2.

[0214] The display device includes the driving transistor T1, the second transistor T2, the third transistor T3, the fourth transistor T4, the fifth transistor T5, the sixth transistor T6, and the storage capacitor Cst.

[0215] Each channel of the driving transistor T1, the second transistor T2, the third transistor T3, the fourth transistor T4, the fifth transistor T5, and the sixth transistor T6 extends and is disposed within the semiconductor layer 130. At least part among the first electrodes and the second electrodes of the plurality of transistors T1, T2, T3, T4, T5, and T6 is disposed in the semiconductor layer 130.

[0216] Signal lines and the semiconductor layer are connected through a plurality of contact holes 82, 83, 84, 85, 86, 87, and 88.

[0217] Structures of transistors and signal lines may be similar to those shown in FIG. 21.

[0218] Referring to FIG. 23, the first common voltage line 741a is disposed outside the regions of the pixels PX1, PX2, and PX3. That is, in the display device of the embodiment of FIG. 21, the driving voltage line 172 of some pixels PX1 is replaced with the first common voltage line 741a, and the pixel PX1 receives the driving voltage from the neighboring pixel through the driving voltage connection line 172c.

[0219] A separate first common voltage line 741a is disposed outside the regions of the pixels PX1, PX2, and PX3. Therefore, the first common voltage line 741a may be disposed without removing the existing driving voltage line 172 of the pixels PX1, PX2, and PX3.

[0220] While example embodiments have been described, practical embodiments are not limited to the disclosed embodiments. Practical embodiments cover various modifications and equivalent arrangements within the scope of the appended claims.

Claims

1. A display device comprising: a substrate including a display area and a non-display area; pixels disposed on the display area; a first common voltage line at least partially disposed on the display area; an outer common voltage trunk line disposed on the non-display area, electrically connected through the first common voltage line to the pixels, and comprises a groove; a first outer common voltage line protruding from the outer common voltage trunk line; and a second outer common voltage line protruding from the outer common voltage trunk line, wherein the groove is disposed between the second outer common voltage line and the first common voltage line.
