

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12400861
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Lin; Meng-Han et al.

Semiconductor device and method of manufacturing

Abstract

Semiconductor devices and methods of manufacturing are presented wherein a gate dielectric is treated within an analog region of a semiconductor substrate. The gate dielectric may be treated with a plasma exposure and/or an annealing process in order to form a recovered region of the gate dielectric. A separate gate dielectric is formed within a logic region of the semiconductor substrate, and a first gate electrode and second gate electrode are formed over the gate dielectrics.

Inventors: Lin; Meng-Han (Hsinchu, TW), Yeong; Sai-Hooi (Zhubei, TW), Chui; Chi On (Hsinchu, TW)

Applicant: Taiwan Semiconductor Manufacturing Co., Ltd. (Hsinchu, TW)

Family ID: 1000008778731

Assignee: Taiwan Semiconductor Manufacturing Co., Ltd. (Hsinchu, TW)

Appl. No.: 18/359507

Filed: July 26, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20230369053 A1	Nov. 16, 2023

Related U.S. Application Data

division parent-doc US 17397632 20210809 US 11798809 child-doc US 18359507
us-provisional-application US 63211750 20210617

Publication Classification

Int. Cl.: H01L21/28 (20250101); H10D64/27 (20250101); H10D84/01 (20250101); H10D84/03 (20250101); H10D84/83 (20250101)

U.S. Cl.:

CPC H01L21/28185 (20130101); H10D64/518 (20250101); H10D84/0142 (20250101); H10D84/0144 (20250101); H10D84/038 (20250101); H10D84/83 (20250101);

Field of Classification Search

CPC: H01L (29/51); H01L (29/66); H01L (29/78); H01L (29/423); H01L (29/513); H01L (29/665); H01L (29/42376); H01L (29/66545); H01L (27/088); H01L (21/28); H01L (21/28185); H01L (21/3115); H01L (21/31155); H01L (21/8234); H01L (21/8238); H01L (21/823456); H01L (21/823462); H01L (21/823857); H10D (30/01); H10D (30/60); H10D (30/0212); H10D (64/01); H10D (64/27); H10D (64/017); H10D (64/68); H10D (64/518); H10D (84/01); H10D (84/03); H10D (84/83); H10D (84/0124); H10D (84/0144); H10D (84/038); H10D (84/0181)

USPC: 257/401

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
3933530	12/1975	Mueller et al.	N/A	N/A
6087236	12/1999	Chau	438/231	H01L 21/823462
6716685	12/2003	Lahaug	438/157	H01L 21/823462
7435651	12/2007	Varghese	438/981	H01L 21/28202
RE43673	12/2011	Hou	438/287	H01L 21/823462
2004/0067619	12/2003	Niimi et al.	N/A	N/A
2004/0102010	12/2003	Khamankar et al.	N/A	N/A
2007/0285543	12/2006	Uchida	N/A	N/A
2008/0203477	12/2007	Yamazaki et al.	N/A	N/A
2010/0044755	12/2009	Tsuda et al.	N/A	N/A
2011/0014773	12/2010	Lin et al.	N/A	N/A
2012/0220137	12/2011	Ota	118/724	H01L 21/31111
2016/0056233	12/2015	Mitsuiki et al.	N/A	N/A
2016/0079353	12/2015	Chen et al.	N/A	N/A
2016/0322384	12/2015	Zang et al.	N/A	N/A
2016/0343823	12/2015	Akram et al.	N/A	N/A
2019/0088756	12/2018	Fang et al.	N/A	N/A
2019/0131401	12/2018	Lo et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
102018124855	12/2018	DE	N/A
2004179656	12/2003	JP	N/A
2012094656	12/2011	JP	N/A
20070113129	12/2006	KR	N/A
201017453	12/2009	TW	N/A

Primary Examiner: Luu; Chuong A

Attorney, Agent or Firm: Slater Matsil, LLP

Background/Summary

PRIORITY CLAIM AND CROSS-REFERENCE (1) This application is a divisional of U.S. patent application Ser. No. 17/397,632, filed on Aug. 9, 2021, entitled “Semiconductor Device and Method of Manufacturing,” which claims the benefit of U.S. Provisional Application No. 63/211,750, filed on Jun. 17, 2021, which applications are hereby incorporated herein by reference.

BACKGROUND

(1) Semiconductor devices are used in a variety of electronic applications, such as, for example, personal computers, cell phones, digital cameras, and other electronic equipment. Semiconductor devices are typically fabricated by sequentially depositing insulating or dielectric layers, conductive layers, and semiconductor layers of material over a semiconductor substrate, and patterning the various material layers using lithography to form circuit components and elements thereon.

(2) The semiconductor industry continues to improve the integration density of various electronic components (e.g., transistors, diodes, resistors, capacitors, etc.) by continual reductions in minimum feature size, which allow more components to be integrated into a given area. However, as the minimum feature size has been reduced, additional issues arise which should be addressed.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Aspects of the present disclosure are best understood from the following detailed description when read with the accompanying figures. It is noted that, in accordance with the standard practice in the industry, various features are not drawn to scale. In fact, the dimensions of the various features may be arbitrarily increased or reduced for clarity of discussion.

(2) FIG. 1 illustrates a logic region and an analog region of a substrate, in accordance with some embodiments.

(3) FIG. 2 illustrates formation of a first well, in accordance with some embodiments.

(4) FIG. 3 illustrates formation of a second well, in accordance with some embodiments.

(5) FIG. 4 illustrates formation of a first dielectric layer, in accordance with some embodiments.

(6) FIG. 5 illustrates a first treatment of the first dielectric layer, in accordance with some embodiments.

(7) FIG. 6 illustrates an annealing process, in accordance with some embodiments.

(8) FIG. 7 illustrates removal of the first dielectric layer from the logic region, in accordance with some embodiments.

(9) FIG. 8 illustrates formation of a second dielectric layer within the logic region, in accordance with some embodiments.

(10) FIG. 9 illustrates formation of a first gate electrode and a second gate electrode, in accordance with some embodiments.

(11) FIG. 10 illustrates formation of spacers, in accordance with some embodiments.

(12) FIG. 11A illustrates formation of source/drain regions and silicide regions, in accordance with

some embodiments.

(13) FIG. 11B illustrates a chart which illustrates normalized current noise spectral densities, in accordance with some embodiments.

(14) FIG. 12 illustrates a gate-last process, in accordance with some embodiments.

(15) FIG. 13 illustrates another gate-last process with a different order of process steps, in accordance with some embodiments.

DETAILED DESCRIPTION

(16) The following disclosure provides many different embodiments, or examples, for implementing different features of the invention. Specific examples of components and arrangements are described below to simplify the present disclosure. These are, of course, merely examples and are not intended to be limiting. For example, the formation of a first feature over or on a second feature in the description that follows may include embodiments in which the first and second features are formed in direct contact, and may also include embodiments in which additional features may be formed between the first and second features, such that the first and second features may not be in direct contact. In addition, the present disclosure may repeat reference numerals and/or letters in the various examples. This repetition is for the purpose of simplicity and clarity and does not in itself dictate a relationship between the various embodiments and/or configurations discussed.

(17) Further, spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.

(18) Embodiments will now be described with respect to a particular embodiment in which flicker noise is reduced within analog devices (e.g., in a digital to analog device for a LCD panel) through treatment of a gate dielectric. The embodiments described, however, are not intended to limit the ideas presented, and the ideas may be implemented in a wide variety of other embodiments. All such embodiments are fully intended to be included within the scope of the disclosure.

(19) With reference now to FIG. 1, there is illustrated a substrate **101** with shallow trench isolations (STIs) **103** formed therein. The substrate **101** may comprise bulk silicon, doped or undoped, or an active layer of a silicon-on-insulator (SOI) substrate. Generally, an SOI substrate comprises a layer of a semiconductor material such as silicon, germanium, silicon germanium, SOI, silicon germanium on insulator (SGOI), or combinations thereof. Other substrates that may be used include multi-layered substrates, gradient substrates, or hybrid orientation substrates.

(20) Additionally, the substrate **101** may have a logic region **105** and an analog region **107**. Devices that are subsequently formed in the logic region **105** will be used to create logic devices while devices that are subsequently formed in the analog region **107** will be used to create analog devices. In some embodiments the logic region **105** may be located immediately adjacent to the analog region **107**, while in other embodiments the logic region **105** may be located away from the analog region **107** (represented in FIG. 1 by the dashed line labeled **109**).

(21) The STIs **103** may be formed by etching the substrate **101** to form a trench and filling the trench with a dielectric material as is known in the art. For example, the STIs **103** may be filled with a dielectric material such as an oxide material, a high-density plasma (HDP) oxide, or the like. However, any suitable material and any suitable method of deposition may be utilized.

(22) FIG. 2 illustrates formation of a first well **203** in the analog region **107**. To initiate the creation of the first well **203** within the analog region **107**, the logic region **105** is first protected. In an embodiment the logic region **105** may be protected by placing a first photoresist **205** over the substrate **101**, and imaging the photoresist to create a difference between exposed regions and non-

exposed regions. Once imaged, the first photoresist **205** is developed to remove portions of the first photoresist **205** over the analog region **107** and leaving portions of the first photoresist **205** over the logic region **105** to protect the logic region **105**.

(23) Once the logic region **105** has been protected, the first well **203** may be created within the analog region **107** by placing first dopants into the substrate **101**. The first dopants may be dopants that are suitable for the type of device to be manufactured. For example, in an embodiment in which devices to be formed are n-type devices, the first dopants may be p-type dopants such as boron, aluminum, gallium, indium, combinations of these, or the like. In other embodiments in which devices to be formed are p-type devices, the first dopants may be n-type dopants such as phosphorous, arsenic, antimony, combinations of these, or the like. However, any suitable dopants may be utilized.

(24) In an embodiment the first dopants may be placed into the substrate **101** using, e.g., a first implantation process (represented in FIG. 2 by the arrows labeled **201**). In this embodiment ions of the first dopants are formed and then accelerated towards the top surface of the substrate **101**, thereby implanting the ions of the first dopants into the substrate **101**. However, any suitable method for implanting the first dopants, may be utilized.

(25) Once the first dopants have been implanted into the substrate **101** to form the first well **203**, the first photoresist **205** is removed. In an embodiment the first photoresist **205** may be removed using an ashing process, in which a temperature of the first photoresist **205** is raised until the first photoresist **205** undergoes a thermal decomposition and may be easily removed. However, any suitable method or combination of methods, such as wet etching, may also be utilized.

(26) FIG. 3 illustrates that, once the first well **203** has been formed in the analog region **107**, a second well **303** is formed in the logic region **105**. To initiate the creation of the second well **303** within the logic region **105**, the analog region **107** is first protected. In an embodiment the analog region **107** may be protected by placing a second photoresist **305** over the substrate **101**, and imaging the second photoresist **305** to create a difference between exposed regions and non-exposed regions. Once exposed, the second photoresist **305** is developed to remove portions of the second photoresist **305** over the logic region **105** and leaving portions of the second photoresist **305** over the analog region **107**, thereby protecting the analog region **107**.

(27) Once the analog region **107** has been protected, the second well **303** may be created within the logic region **105** by placing second dopants into the substrate **101**. The second dopants may be dopants that are suitable for the type of device to be manufactured. For example, in an embodiment in which devices to be formed are n-type devices, the second dopants may be p-type dopants such as boron, aluminum, gallium, indium, combinations of these, or the like. In other embodiments in which devices to be formed are p-type devices, the second dopants may be n-type dopants such as phosphorous, arsenic, antimony, combinations of these, or the like. However, any suitable dopants may be utilized.

(28) Additionally, any suitable combination of devices between the logic region **105** and the analog region **107** may be used. For example, if the devices formed within the logic region **105** are n-type devices, the devices formed within the analog region **107** may be either n-type devices or p-type devices. Also, if the devices formed within the logic region **105** are p-type devices, the devices formed within the analog region **107** may be either n-type devices or p-type devices. Any suitable combination of devices may be utilized.

(29) In an embodiment the second dopants may be placed into the substrate **101** using, e.g., a second implantation process (represented in FIG. 3 by the arrows labeled **301**). In this embodiment ions of the second dopants are formed and then accelerated towards the top surface of the substrate **101**, thereby implanting the ions of the second dopants into the substrate **101**. In an embodiment the second dopants in the logic region **105** are implanted to have a higher concentration than the first dopants implanted in the analog region **107**. For example, the first dopants may have a first concentration within the first well **203** of between about 1.0×10^{14} cm.⁻³ and about

1.0×10^{18} cm.^{sup.}−3, while the second dopants may have a second concentration within the second well **303** greater than the first concentration of between about 1.0×10^{14} cm.^{sup.}−3 and about 1.0×10^{18} cm.^{sup.}−3. However, any suitable method for implanting the second dopants, and any suitable concentration of first dopants and second dopants, may be utilized.

(30) Once the second dopants have been implanted into the substrate **101** to form the second well **303**, the second photoresist **305** is removed. In an embodiment the second photoresist **305** may be removed using an ashing process, in which a temperature of the second photoresist **305** is raised until the second photoresist **305** undergoes a thermal decomposition and may be easily removed. However, any suitable method or combination of methods, such as wet etching, may also be utilized.

(31) FIG. 4 illustrates deposition of a first dielectric layer **401** over the substrate **101** to begin formation of a gate dielectric for devices within the analog region **107**. The first dielectric layer **401** may be a high-K dielectric material, such as silicon oxide, silicon oxynitride, silicon nitride, an oxide, a nitrogen-containing oxide, aluminum oxide, lanthanum oxide, hafnium oxide, zirconium oxide, hafnium oxynitride, a combination thereof, or the like. The first dielectric layer **401** may have a relative permittivity value greater than about 4.

(32) In an embodiment in which the first dielectric layer **401** comprises an oxide layer, the first dielectric layer **401** may be formed by any oxidation process, such as wet or dry thermal oxidation in an ambient comprising an oxide, H₂O, NO, or a combination thereof, or by chemical vapor deposition (CVD) techniques using tetra-ethyl-ortho-silicate (TEOS) and oxygen as a precursor. In one embodiment, the first dielectric layer **401** may have a first thickness T_{sub.1} of between about 10 Å to about 150 Å in thickness, such as 100 Å in thickness.

(33) In other embodiments in which the first dielectric layer **401** is a metal oxide, such as hafnium oxide, the first dielectric layer **401** may be deposited using a deposition process. For example, the first dielectric layer **401** may be deposited using an atomic layer deposition process, a chemical vapor deposition process, a physical vapor deposition process, combinations of these, or the like. However, any suitable method of deposition may be utilized.

(34) FIG. 5 illustrates that, once the first dielectric layer **401** is deposited, the first dielectric layer **401** is treated. In an embodiment the treatment may be a plasma treatment (represented in FIG. 5 by the cloud labeled **501**) whereby the first dielectric layer **401** is exposed to a plasma of one or more plasma precursors that will help to reduce flicker noise within the devices formed within the analog region **107**. In particular embodiments, the plasma precursors may be precursors such as oxygen, nitrogen, fluorine, chlorine, combinations of these, or the like, although any suitable precursors may be used.

(35) To initiate the plasma treatment **501**, a flow rate of the plasma precursors can be set to be in a range from about 10 sccm to about 100 sccm, and a pressure of the plasma treatment **501** can be in a range from about 10 mTorr to about 10 Torr. The temperature of the plasma treatment **501** can be set to be in a range from about 400° C. to about 800° C. A power of the plasma generator of the plasma treatment **501** can be in a range from about 5 W to about 500 W, and a frequency of the plasma generator can be about 13.56 MHz or greater. The substrate **101** during the plasma treatment **501** can be biased in a range from about 0.5 V to about 500 V. However, any suitable process parameters may be utilized.

(36) During the plasma treatment **501**, the species of the plasma can damage the exposed surfaces and can also diffuse into the exposed surfaces of the first dielectric layer **401** to form a treated region **503** within the first dielectric layer **401**, while an untreated region **505** of the first dielectric layer **401** remains between the treated region **503** and the substrate **101**. For example, the species used for the plasma (e.g., oxygen, nitrogen, fluorine, chlorine, . . . etc.) can be diffused into the materials that form the first dielectric layer **401** to a first depth D_{sub.1} from the treated surface equal to or less than about 100 nm, such as less than or equal to 5 nm. In some particular embodiments, for example when noise is desired to be better controlled, the first depth may be

between about $1/10$ and $1/2$ of the first thickness $T_{\text{sub.1}}$. Finally, the species may be diffused to a concentration in a range from about $1.0 \times 10^{10} \text{ cm}^{-3}$ to about $1.0 \times 10^{15} \text{ cm}^{-3}$. The concentration of the species can decrease from a peak proximate to the respective treated surfaces to a depth in the material.

(37) FIG. 6 illustrates that, once the treated region **503** has been formed, the treated region **503** may be further treated in order to densify the treated region **503** and recover fixed oxide charges and traps, such that the treated region **503** has a different density than a remainder of the first dielectric layer **401**. In an embodiment the treated region **503** may be treated using, e.g., an annealing process (represented in FIG. 6 by the wavy lines labeled **603**) which will create a recovered region **601** from the treated region **503** (see FIG. 5). However, any suitable process may be utilized.

(38) In a particular embodiment the annealing process **603** may be a thermal anneal that is performed in an ambient environment including oxygen (**02**), nitrogen ($N_{\text{sub.2}}$), $N_{\text{sub.2O}}$, ammonia ($NH_{\text{sub.3}}$), combinations of these, or the like. Additionally, the thermal anneal may be performed at a temperature of between about 500°C . and about 1000°C . for a time of between about 10 s and about 1 hr, although any suitable temperature and time may be utilized.

Additionally, while a thermal anneal has been described, any suitable annealing process, such as a milli-second laser anneal, a flash anneal, a spike anneal, or a soak anneal, may be utilized.

(39) After the treated region **503** has been formed and then recovered to become the recovered region **601**, the recovered region **601** may have a second depth $D_{\text{sub.2}}$ extending from the surface of the first dielectric layer **401**. In an embodiment the second depth $D_{\text{sub.2}}$ may be between about 5% and about 30% of the original first thickness $T_{\text{sub.1}}$ of the first dielectric layer **401**. For example, if the first dielectric layer **401** was originally deposited as 100 nm thick, the recovered region may be between 5 nm and about 30 nm. If the second depth $D_{\text{sub.2}}$ is too thin, the flicker noise of the analog device formed will not be improved, while if the second depth $D_{\text{sub.2}}$ is too thick, the plasma energy during the plasma treatment **501** will damage too much of the first dielectric layer **401**, thereby damaging the overall quality of subsequently formed gate dielectrics.

(40) Additionally, while embodiments are described above wherein both the plasma treatment **501** and the annealing process **603** are utilized to form the recovered region **601**, this is intended to be illustrative and is not intended to be limiting upon the embodiments. Rather, any suitable combination of processes, such as using the annealing process **603** by itself, may also be utilized. All such embodiments are fully intended to be included within the scope of the embodiments.

(41) FIG. 7 illustrates that, once the recovered region **601** has been formed within the first dielectric layer **401**, the first dielectric layer **401** is patterned to remove the first dielectric layer **401** from the logic region **105**. In an embodiment the patterning of the first dielectric layer **401** may be initiated by placing a third photoresist **701** over the substrate **101** and imaging the third photoresist **701** to create a difference between exposed regions and non-exposed regions. Once imaged, the third photoresist **701** is developed to remove portions of the third photoresist **701** over the logic region **105** and leaving portions of the third photoresist **701** over the analog region **107**.

(42) Once the third photoresist **701** has been placed and patterned, those portions of the first dielectric layer **401** (including the recovered region **601**) that are located within the logic region **105** are removed. In an embodiment the first dielectric layer **401** may be removed using, e.g., an anisotropic etching process, such as a reactive ion etching process. However, any suitable removal process may be utilized.

(43) Additionally, once the first dielectric layer **401** has been removed from the logic region **105**, the third photoresist **701** is removed. In an embodiment the third photoresist **701** may be removed using, e.g., an ashing process, whereby a temperature of the third photoresist **701** is increased until the third photoresist **701** undergoes a thermal decomposition, whereupon the third photoresist **701** may be easily removed. However, any suitable process may be utilized to remove the third photoresist **701**.

(44) FIG. 8 illustrates formation of a second dielectric layer **801** over the logic region **105**. The

second dielectric layer **801** may be a high-K dielectric material, such as silicon oxide, silicon oxynitride, silicon nitride, an oxide, a nitrogen-containing oxide, aluminum oxide, lanthanum oxide, hafnium oxide, zirconium oxide, hafnium oxynitride, a combination thereof, or the like. The second dielectric layer **801** may have a relative permittivity value greater than about 4.

(45) In an embodiment in which the second dielectric layer **801** comprises an oxide layer, the second dielectric layer **801** may be formed by any oxidation process, such as wet or dry thermal oxidation in an ambient comprising an oxide, H₂O, NO, or a combination thereof, or by chemical vapor deposition (CVD) techniques using tetra-ethyl-ortho-silicate (TEOS) and oxygen as a precursor. In one embodiment, the second dielectric layer **801** may have a second thickness T₂ of between about 10 Å to about 150 Å in thickness, such as 100 Å in thickness.

(46) In other embodiments in which the second dielectric layer **801** is a metal oxide, such as hafnium oxide, the second dielectric layer **801** may be deposited using a deposition process. For example, the second dielectric layer **801** may be deposited using an atomic layer deposition process, a chemical vapor deposition process, a physical vapor deposition process, combinations of these, or the like. However, any suitable method of deposition may be utilized.

(47) Additionally, because the second dielectric layer **801** is not present during the treatment process **501** or the subsequent annealing process **603**, the second dielectric layer **801** is not affected by these processes. As such, the second dielectric layer **801** remains untreated, and may have a constant composition and a constant density throughout the second dielectric layer **801**.

(48) FIG. **9** illustrates a placement and patterning of a first gate electrode **901** (e.g., a logic gate electrode) and a second gate electrode **903** (e.g., an analog gate electrode). The material for the first gate electrode **901** and the second gate electrode **903** is blanket deposited over the first dielectric layer **401** and the second dielectric layer **801**. In an embodiment, the first gate electrode **901** and the second gate electrode **903** may include a conductive material, such as a metal (e.g., tantalum, titanium, molybdenum, tungsten, platinum, aluminum, hafnium, ruthenium), a metal silicide (e.g., titanium silicide, cobalt silicide, nickel silicide, tantalum silicide), a metal nitride (e.g., titanium nitride, tantalum nitride), doped poly-crystalline silicon, other conductive materials, or a combination thereof. In one example, amorphous silicon is deposited and recrystallized to create poly-crystalline silicon (poly-silicon). Additionally, although the first gate electrode **901** and the second gate electrode **903** are illustrated as being a single layer in FIG. **9**, the first gate electrode **901** and the second gate electrode **903** may comprise any number of suitable layers.

(49) In an embodiment the material for the first gate electrode **901** and the second gate electrode **903** is first blanket deposited over the first dielectric layer **401** and the second dielectric layer **801**. Once in place, the material for the first gate electrode **901** and the second gate electrode **903** is then patterned into the separate gate electrodes and the desired shapes using, e.g., one or more photolithographic masking and etching processes to etch through the material of the first gate electrode **901** and the second gate electrode **903**, the first dielectric layer **401**, and the second dielectric layer **801**. However, any suitable methods may be utilized.

(50) In an embodiment the first gate electrode **901** may be patterned to have a first width W₁ (e.g., a first channel length of the logic device formed) of between about 0.05 μm and about 20 μm. Similarly, the second gate electrode **903** may be patterned to have a second width W₂ (e.g., a second channel length of the analog device formed) that is larger than the first width W₁, such as the second width W₂ being between about 0.1 μm and about 20 μm. However, any suitable dimensions may be utilized.

(51) FIG. **10** illustrates the formation of first spacers **1001** on the first gate electrode **901** and second spacers **1003** on the second gate electrode **903**. The first spacers **1001** and the second spacers **1003** may be formed by blanket depositing one or more spacer layers (not shown) over the first gate electrode **901** and the second gate electrode **903**. The spacer layers may comprise SiN, oxynitride, SiC, SiON, oxide, and the like and may be formed by methods such as chemical vapor deposition (CVD), plasma enhanced CVD (PECVD), sputter, combinations of these, or the like.

The spacer layers may be patterned, such as by isotropically or anisotropically etching, thereby removing the spacer layers from the horizontal surfaces of the structure and forming the first spacers **1001** and the second spacers **1003** as illustrated in FIG. **10**.

(52) However, as one of ordinary skill in the art will recognize, the process described above and the resulting shape of the first spacers **1001** and the second spacers **1003** as illustrated in FIG. **10** are intended to be merely illustrative and are not intended to limit the embodiments to these descriptions. Rather, any suitable number and combination of spacer layers and shapes may be utilized in order to form the first spacers **1001** and the second spacers **1003** for the first gate electrode **901** and the second gate electrode **903**, and any suitable combination of spacers may be utilized.

(53) FIG. **11A** illustrates formation of first source/drain regions **1101** in the substrate **101** on opposing sides of the first gate electrode **901** and also illustrates formation of second source/drain regions **1103** in the substrate **101** on opposing sides of the second gate electrode **903**. In an embodiment in which the second well **303** in the logic region **105** comprises n-type dopants, the first source/drain regions **1101** may be formed by first protecting the analog region **107** (by, e.g., placing and patterning a photoresist over the analog region **107**) and then implanting appropriate p-type dopants such as boron, gallium, indium, or the like. In other embodiments in which the second well **303** in the logic region **105** comprises p-type dopants, the first source/drain regions **1101** may be formed by implanting appropriate n-type dopants, such as phosphorous, arsenic, or the like. However, any suitable combination of dopants may be utilized.

(54) Similarly with respect to the second source/drain regions **1103**, in an embodiment in which the first well **203** comprises n-type dopants, the second source/drain regions **1103** may be formed by first protecting the logic region **105** (by, e.g., placing and patterning a photoresist over the device region **105**) and then by implanting appropriate p-type dopants such as boron, gallium, indium, or the like. In other embodiments, in which the first well **203** in the analog region **107** comprises p-type dopants, the second source/drain regions **1103** may be formed by implanting appropriate n-type dopants, such as phosphorous, arsenic, or the like. However, any suitable combination of dopants may be utilized.

(55) While the first source/drain regions **1101** may be implanted using the first gate electrode **901** and the first spacers **1001** as masks, and the second source/drain regions **1103** may be implanted using the second gate electrode **903** and the second spacers **1003** as masks, it should be noted that one of ordinary skill in the art will realize that many other processes, steps, or the like may be used to form these first source/drain regions **1101** and the second source/drain regions **1103**. For example, one of ordinary skill in the art will realize that a plurality of implants may be performed using various combinations of spacers and liners to form the first source/drain regions **1101** and the second source/drain regions **1103** to have a specific shape or characteristic suitable for a particular purpose. Any of these processes may be used to form the first source/drain regions **1101** and the second source/drain regions **1103**, and the above description is not meant to limit the embodiments to the steps presented above.

(56) FIG. **11A** additionally illustrates formation of silicide regions **1105** over the first source/drain regions **1101**, the second source/drain regions **1103**, the first gate electrode **901**, and the second gate electrode **903**. In an embodiment the silicide regions **1105** comprise a nickel silicide, although any other suitable metal silicide, such as titanium silicide, cobalt silicide, palladium silicide, platinum silicide, erbium silicide, and the like, can also be used. The silicide regions **1105** may be formed with an initial blanket deposition of an appropriate metal layer, followed by an annealing step in which the metal reacts with the underlying material of the substrate (e.g., silicon). Unreacted metal is then removed, such as with a selective etch process. The thickness of the silicide regions **1105** may be between about 3 nm and about 50 nm.

(57) Additionally, once the silicide regions **1105** have been formed, a top surface of the first gate electrode **901** may extend less from the substrate **101** than the second gate electrode **903**. For

example, the first gate electrode **901** may extend a second distance D.sub.2 from the substrate **101** of between about 25 nm and about 250 nm, while the second gate electrode **903** may extend a third distance D.sub.3 of between about 25 nm and about 250 nm. However, any suitable distances may be utilized.

(58) FIG. **11B** illustrates improvements that can be achieved by utilizing the embodiments described herein. As illustrated, normalized current noise spectral densities ($S_{id}/I_{d,sup.2}$) are measured along the y-axis, while frequencies are plotted along the x-axis. As can be seen, when compared to devices that do not utilize the embodiments described herein (represented in FIG. **11B** by the data line labeled **1107**), devices that do utilize the embodiments described herein (represented in FIG. **11B** by the data line labeled **1109**) can see a significant decrease. In some cases the significant decrease can result in an **8X** or greater improvement.

(59) In particular, by improving the quality of first dielectric layer **401** of the analog devices formed within the analog region **107**, the flicker noise performance of these MOSFETs (e.g., caused by trapping and detrapping within the first dielectric layer **401**) can be reduced without the use of an additional mask. As such, a low cost process that is fully compatible with the remaining CMOS processes may be utilized to lower the flicker noise, thereby also lower the signal to noise ratio of the analog devices. As such, a better overall performance of the devices may be achieved, especially in devices which are used to transfer digital data (e.g., from a CPU) to an analog signal (e.g., to a color display for an LCD panel).

(60) FIG. **12** illustrates another embodiment which may continue from the structure described above with respect to FIG. **11A** in a “gate-last” process (although the “gate-first process” described with respect to FIGS. **1-11B** may also be used without additional processing). In this embodiment, the material of the first gate electrode **901** and the second gate electrode **903**, instead of being the final material to be used, is instead a dummy material, such as polysilicon, that is subsequently removed. In particular, once the silicide regions **1105** have been formed, a first interlayer dielectric (ILD) **1201** is deposited over the structure illustrated in FIG. **11A**. The first ILD **1201** may be formed of a dielectric material, and may be deposited by any suitable method, such as CVD, plasma-enhanced CVD (PECVD), or FCVD. Dielectric materials may include phospho-silicate glass (PSG), boro-silicate glass (BSG), boron-doped phospho-silicate glass (BPSG), undoped silicate glass (USG), or the like. Other insulation materials formed by any acceptable process may be used. In some embodiments, a contact etch stop layer (CESL—not separately illustrated in FIG. **12**) is disposed between the first ILD **1201** and underlying structures. The CESL may comprise a dielectric material, such as, silicon nitride, silicon oxide, silicon oxynitride, or the like, having a lower etch rate than the material of the overlying first ILD **1201**.

(61) Once the first ILD **1201** has been formed, the first ILD **1201** is planarized in order to expose the first gate electrode **901** and the second gate electrode **903**. In an embodiment the planarization process may be a process such as chemical mechanical polishing, grinding, combinations of these, or the like. After the planarization process, top surfaces of the first gate electrode **901** and the second gate electrode **903** are exposed through the first ILD **1201**.

(62) Once the first gate electrode **901** and the second gate electrode **903** are exposed, the first gate electrode **901** and the second gate electrode **903** are removed in one or more etching step(s), so that recesses are formed. In some embodiments, the first gate electrode **901** and the second gate electrode **903** are removed by an anisotropic dry etch process. For example, the etching process may include a dry etch process using reaction gas(es) that selectively etch the first gate electrode **901** and the second gate electrode **903** with little or no etching of the first ILD **1201** or the first spacers **1001** and second spacers **1003**. During the removal, the first dielectric layer **401** and the second dielectric layer **801** may be used as an etch stop layer when the first gate electrode **901** and the second gate electrode **903** are etched.

(63) Once the recesses have been formed, gate dielectric layers **1205** and gate electrodes **1203** are formed for replacement gates. Gate dielectric layers **1205** are one or more layers deposited in the

recesses, such as on the top surfaces of the first dielectric layer **401** and the second dielectric layer **801** and on sidewalls of the first spacers **1001** and the second spacers **1003**. The gate dielectric layers **1205** may also be formed on the top surface of the first ILD **1201**. In some embodiments, the gate dielectric layers **1205** comprise one or more dielectric layers, such as one or more layers of silicon oxide, silicon nitride, metal oxide, metal silicate, or the like. For example, in some embodiments, the gate dielectric layers **1205** include a high-k dielectric material, such as a metal oxide or a silicate of hafnium, aluminum, zirconium, lanthanum, manganese, barium, titanium, lead, and combinations thereof. The gate dielectric layers **1205** may include a dielectric layer having a k value greater than about 7.0. The formation methods of the gate dielectric layers **1205** may include Molecular-Beam Deposition (MBD), ALD, PECVD, and the like.

(64) The gate electrodes **1203** are deposited over the gate dielectric layers **1205**, respectively, and fill the remaining portions of the recesses. The gate electrodes **1203** may include a metal-containing material such as titanium nitride, titanium oxide, tantalum nitride, tantalum carbide, cobalt, ruthenium, aluminum, tungsten, combinations thereof, or multi-layers thereof. Additionally, although a single layer gate electrode **1203** is illustrated, the gate electrode **1203** may comprise any number of liner layers, any number of work function tuning layers, and a fill material. After the filling of the recesses, a planarization process, such as a CMP, may be performed to remove the excess portions of the gate dielectric layers **1205** and the material of the gate electrodes **1203**, which excess portions are over the top surface of the first ILD **1201**. As such, the gate dielectric layers **1205** may extend along multiple sides of the gate electrodes **1203**, and top surfaces of the gate electrodes **1203** located in both the analog region **107** and the logic region **105** are located an equal distance away from the substrate **101**, such as by being located a fourth distance $D_{sub.4}$ of between about 20 nm and about 200 nm. The remaining portions of material of the gate electrodes **1203** and the gate dielectric layers **1205** thus form replacement gates. The gate electrodes **1203** and the gate dielectric layers **1205** may be collectively referred to as a “gate stack.”

(65) The formation of the gate dielectric layers **1205** in the logic region **105** and the analog region **107** may occur simultaneously such that the gate dielectric layers **1205** in each region are formed from the same materials, and the formation of the gate electrodes **1203** may occur simultaneously such that the gate electrodes **1203** in each region are formed from the same materials. In other embodiments, the gate dielectric layers **1205** in each region may be formed by distinct processes, such that the gate dielectric layers **1205** may be different materials, and/or the gate electrodes **1203** in each region may be formed by distinct processes, such that the gate electrodes **1203** may be different materials. Various masking steps may be used to mask and expose appropriate regions when using distinct processes.

(66) FIG. 13 illustrates another “gate-last” embodiment in which the gate dielectric layers **1205**, instead of being formed after the formation of the first ILD **1201**, are formed prior to formation of the first ILD **1201**. In this embodiment, prior to deposition of the material of the first gate electrode **901** and the second gate electrode **903**, the material of the gate dielectric layers **1205** is deposited over the first dielectric layer **401** and the second dielectric layer **801**. The gate dielectric layers **1205** in this embodiment may be deposited as described above with respect to FIG. 12.

(67) Once deposited, the first gate electrode **901** and the second gate electrode **903** are formed and patterned, whereby the patterning of the first gate electrode **901** and the second gate electrode **903** is also utilized to pattern the gate dielectric layers **1205**. As such, the gate dielectric layers **1205** are patterned to have a single planar section that is located directly over the first dielectric layer **401** and the second dielectric layer **801**.

(68) Once the first gate electrode **901** and the second gate electrode **903** are formed, the first ILD **1201** is deposited and planarized, and the first gate electrode **901** and the second gate electrode **903** are removed. Once removed, the gate electrodes **1203** (but not the gate dielectric layers **1205** because this has already been formed) are deposited to replace the first gate electrode **901** and the second gate electrode **903**. As such, the gate electrodes **1203** are deposited in physical contact with

the first spacers **1001** (in the logic region **105**) and the second spacers (in the analog region **107**). In an embodiment the gate electrodes **1203** are deposited as described above with respect to FIG. **12**. However, any suitable methods and materials may be utilized.

(69) By treating the first dielectric layer **401** to form the recovered region **601**, the trapping and detrapping that normally occurs at sufficient frequencies in an analog devices can be reduced. By reducing the trapping and detrapping, the overall flicker noise of the analog device can be reduced, thereby improving the overall performance of the device. These improvements may be achieved using no additional masks, at a low cost, and with processes that are fully compatible with the remainder of the processes used to form CMOS devices.

(70) Additionally, while the embodiments presented herein are described as embodiments for use in planar devices, the ideas are not intended to be limited to planar devices. Rather, the ideas may be implemented in a wide variety of devices, including fin field effect transistors (finFETs), nanostructure devices, combinations of these, or the like. All such embodiments are fully intended to be included within the scope of the embodiments.

(71) In accordance with an embodiment, a method of manufacturing a semiconductor device, the method including: depositing a first dielectric layer over a logic region and an analog region of a semiconductor substrate; treating the first dielectric layer to form a recovered layer; after the treating the first dielectric layer, removing a first portion of the recovered layer from the logic region; forming a second dielectric layer in the logic region; and depositing a gate electrode material over a remainder of the recovered layer and the second dielectric layer. In an embodiment the treating the first dielectric layer further includes: exposing the first dielectric layer to a plasma to form a treated region; and annealing the treated region. In an embodiment the plasma comprises oxygen, nitrogen, fluorine, or chlorine. In an embodiment the treating the first dielectric layer further comprises annealing the first dielectric layer. In an embodiment the annealing is performed in an oxygen environment. In an embodiment the recovered layer has a first thickness, the first dielectric layer has a second thickness, and the first thickness is between 5% and 30% of the second thickness. In an embodiment the method further includes patterning the gate electrode material into a first gate electrode over the recovered layer and a second gate electrode over the second dielectric layer, the first gate electrode having a larger width than the second gate electrode.

(72) In accordance with another embodiment, a method of manufacturing a semiconductor device, the method including: blanket depositing a first dielectric layer over a first region of a substrate and a second region of the substrate; exposing a top surface of the first dielectric layer to a first plasma to form a treated region within the first dielectric layer over a non-treated region of the first dielectric layer; recovering the treated region with a first annealing process to form a recovered region over the non-treated region; removing the first dielectric layer from the first region; forming a second dielectric layer in the first region; forming a first gate electrode over the first dielectric layer in the second region; and forming a second gate electrode over the second dielectric layer in the first region. In an embodiment the method further includes replacing the first gate electrode and the second gate electrode. In an embodiment the first plasma comprises an oxygen plasma. In an embodiment the first plasma comprises a chlorine plasma. In an embodiment the first plasma comprises a nitrogen plasma. In an embodiment a first thickness of the recovered region is less than 30% of a second thickness of the first dielectric layer. In an embodiment the first region is a logic region and the second region is an analog region.

(73) In yet another embodiment, a semiconductor device includes: a logic device located in a logic region of a substrate, the logic device including: a first dielectric layer having a constant density throughout the first dielectric layer; and a first gate electrode overlying the first dielectric layer; and an analog device located in an analog region of the substrate, the analog device including: a second dielectric layer, the second dielectric layer comprising a recovered region and a non-treated region, the recovered region having a different density than the non-treated region; and a second gate electrode overlying the second dielectric layer. In an embodiment a first top surface of the first gate

electrode is a first distance away from the substrate and wherein a second top surface of the second gate electrode is located a second distance away from the substrate, the second distance being greater than the first distance. In an embodiment a first top surface of the first gate electrode is a first distance away from the substrate and wherein a second top surface of the second gate electrode is located the first distance away from the substrate. In an embodiment the semiconductor device further includes a first high-k dielectric layer between the second dielectric layer and the second gate electrode, wherein the first high-k dielectric layer extends along multiple sides of the second gate electrode. In an embodiment the semiconductor device further includes a first high-k dielectric layer between the second dielectric layer and the second gate electrode, wherein the second gate electrode is in physical contact with a spacer. In an embodiment the second gate electrode has a width that is larger than the first gate electrode.

(74) The foregoing outlines features of several embodiments so that those skilled in the art may better understand the aspects of the present disclosure. Those skilled in the art should appreciate that they may readily use the present disclosure as a basis for designing or modifying other processes and structures for carrying out the same purposes and/or achieving the same advantages of the embodiments introduced herein. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the present disclosure, and that they may make various changes, substitutions, and alterations herein without departing from the spirit and scope of the present disclosure.

Claims

1. A semiconductor device comprising: a first dielectric layer over an analog region of a semiconductor substrate, the first dielectric layer having a recovered layer and a non-treated layer, the non-treated layer being located between the recovered layer and the semiconductor substrate, the recovered layer and the non-treated layer having aligned sidewalls; a second dielectric layer over a logic region of the semiconductor substrate, the second dielectric layer different from the first dielectric layer; and a gate electrode material over the recovered layer and the second dielectric layer.
2. The semiconductor device of claim 1, wherein the gate electrode material is located a first distance away from the semiconductor substrate in the analog region and a second distance away from the semiconductor substrate in the logic region, the first distance being different from the second distance.
3. The semiconductor device of claim 1, wherein the non-treated layer comprises an oxide.
4. The semiconductor device of claim 1, wherein the treated layer has a thickness of between about 5 nm and about 30 nm.
5. The semiconductor device of claim 1, wherein the second dielectric layer has a thickness of between about 10 Å to about 150 Å.
6. The semiconductor device of claim 1, wherein the recovered layer comprises nitrogen.
7. The semiconductor device of claim 1, wherein the recovered layer comprises fluorine.
8. A semiconductor device comprising: a non-treated layer of a first dielectric material over an analog region of a semiconductor substrate; a recovered layer of the first dielectric material over the non-treated layer, the recovered layer being aligned with the non-treated layer; a first gate electrode over a first dielectric layer; a second dielectric material over a logic region of the semiconductor substrate; and a second gate electrode over the second dielectric material in the logic region.
9. The semiconductor device of claim 8, wherein the first gate electrode extends away from the semiconductor substrate further than the second gate electrode.
10. The semiconductor device of claim 8, wherein the first gate electrode extends away from the semiconductor substrate the same as the second gate electrode.

11. The semiconductor device of claim 8, wherein the first gate electrode has a larger width than the second gate electrode.
 12. The semiconductor device of claim 8, wherein the recovered layer comprises nitrogen.
 13. The semiconductor device of claim 8, wherein the recovered layer comprises fluorine.
 14. The semiconductor device of claim 8, wherein the recovered layer comprises chlorine.
 15. A semiconductor device comprising: a logic device located in a logic region of a substrate, the logic device comprising: a first dielectric layer; and a first gate electrode overlying the first dielectric layer; and an analog device located in an analog region of the substrate, the analog device comprising: a second dielectric layer, the second dielectric layer comprising a recovered layer and a non-treated layer, the non-treated layer being located between the recovered layer and a semiconductor substrate, the recovered layer and the non-treated layer having coterminus sidewalls; and a second gate electrode overlying the second dielectric layer.
 16. The semiconductor device of claim 15, wherein a first top surface of the first gate electrode is a first distance away from the substrate and wherein a second top surface of the second gate electrode is located a second distance away from the substrate, the second distance being greater than the first distance.
 17. The semiconductor device of claim 15, wherein a first top surface of the first gate electrode is a first distance away from the substrate and wherein a second top surface of the second gate electrode is located the first distance away from the substrate.
 18. The semiconductor device of claim 15, further comprising a first high-k dielectric layer between the second dielectric layer and the second gate electrode, wherein the first high-k dielectric layer extends along multiple sides of the second gate electrode.
 19. The semiconductor device of claim 15, further comprising a first high-k dielectric layer between the second dielectric layer and the second gate electrode, wherein the second gate electrode is in physical contact with a spacer.
 20. The semiconductor device of claim 15, wherein the second gate electrode has a width that is larger than the first gate electrode.
-