

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12411239
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Wu; Tung-Yu et al.

Time-of-flight ranging device and time-of-flight ranging method

Abstract

A time-of-flight ranging device and a time-of-flight ranging method are provided. The time-of-flight ranging device includes a light source, a sensing array, and a time-to-digital converter. The light source emits a laser pulse signal towards a sensing target. The sensing array includes a plurality of sensing units. The sensing array is configured to sense reflected pulse light generated when the sensing target reflects the laser pulse signal. The time-to-digital converter is coupled to the sensing array. The time-to-digital converter performs an integration operation on a plurality of sensing results of the sensing units during a plurality of consecutive integration periods to generate histogram data. At least part of the integration periods have different time lengths, such that at least part of a plurality of bins in the histogram data have different bin widths.

Inventors: Wu; Tung-Yu (Hsinchu, TW), Po; Tang-Hung (Hsinchu, TW), Wan; Sheng (Hsinchu, TW)

Applicant: Egis Technology Inc. (Hsinchu, TW)

Family ID: 78877568

Assignee: Egis Technology Inc. (Hsinchu, TW)

Appl. No.: 17/522927

Filed: November 10, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20220179078 A1	Jun. 09, 2022

Foreign Application Priority Data

CN	202111154878.7	Sep. 29, 2021
----	----------------	---------------

Related U.S. Application Data

us-provisional-application US 63121243 20201204

Publication Classification

Int. Cl.: **G01S17/00** (20200101); **G01S7/48** (20060101); **G01S7/4863** (20200101); **G01S7/4865** (20200101); **G01S17/46** (20060101)

U.S. Cl.:

CPC **G01S17/46** (20130101); **G01S7/4808** (20130101); **G01S7/4863** (20130101); **G01S7/4865** (20130101);

Field of Classification Search

USPC: 356/5.01

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9874629	12/2017	Kostamovaara	N/A	G01C 3/08
10801886	12/2019	Mandai	N/A	G01J 1/44
11172186	12/2020	Van Nieuwenhove	N/A	H04N 13/128
11233966	12/2021	Niclass	N/A	H04N 17/002
11639990	12/2022	Henderson	356/4.01	G01S 7/4863
11650292	12/2022	Zhang	356/4.01	H01S 5/02257
11709266	12/2022	Meinherz	356/5.01	G01S 7/497
2005/0223371	12/2004	Nefian	714/E11.197	G06F 11/3452
2012/0257187	12/2011	Stutz et al.	N/A	N/A
2013/0129022	12/2012	Wei	375/343	H04B 17/26
2015/0092847	12/2014	Su	375/240.12	H04N 19/33
2015/0177369	12/2014	Kostamovaara	N/A	N/A
2015/0379175	12/2014	Parnami	716/134	G06F 30/30
2018/0164415	12/2017	Buckley et al.	N/A	N/A
2018/0209846	12/2017	Mandai et al.	N/A	N/A
2018/0211152	12/2017	Migacz	N/A	G06N 3/04
2018/0259645	12/2017	Shu	N/A	G01S 7/497
2018/0299552	12/2017	Shu	N/A	H10F 39/18
2019/0056497	12/2018	Pacala	N/A	G01S 7/497
2019/0114786	12/2018	Sanghvi	N/A	G06T 7/223
2020/0158835	12/2019	Yu	N/A	N/A

2020/0233066	12/2019	Kulesh et al.	N/A	N/A
2020/0233068	12/2019	Henderson	N/A	H04N 25/773
2020/0236342	12/2019	Van Nieuwenhove et al.	N/A	N/A
2020/0278447	12/2019	Meinherz et al.	N/A	N/A
2020/0309909	12/2019	Zhang et al.	N/A	N/A
2022/0043128	12/2021	Pacala	N/A	G01S 17/89
2023/0296739	12/2022	Aßmann	356/3	G01S 17/10

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
105093206	12/2014	CN	N/A
105164550	12/2014	CN	N/A
109143252	12/2018	CN	N/A
111413706	12/2019	CN	N/A
111935424	12/2019	CN	N/A
111965658	12/2019	CN	N/A
3370079	12/2017	EP	N/A
102010172	12/2018	KR	N/A
201946404	12/2018	TW	N/A
202002259	12/2019	TW	N/A
202024665	12/2019	TW	N/A
I703341	12/2019	TW	N/A

OTHER PUBLICATIONS

S. W. Hutchings et al., “A Reconfigurable 3-D-Stacked SPAD Imager With In-Pixel Histogramming for Flash LIDAR or High-Speed Time-of-Flight Imaging,” in IEEE Journal of Solid-State Circuits, vol. 54, No. 11, pp. 2947-2956, Nov. 2019 (Year: 2019). cited by examiner

H. Seo et al., “A 36-Channel SPAD-Integrated Scanning LiDAR Sensor with Multi-Event Histogramming TDC and Embedded Interference Filter,” 2020 IEEE Symposium on VLSI Circuits, Honolulu, HI, USA, 2020, pp. 1-2 (Year: 2020). cited by examiner

“Office Action of Taiwan Counterpart Application”, issued on Oct. 3, 2022, p. 1-p. 7. cited by applicant

“Office Action of Taiwan Related Application No. 110136143”, issued on Jun. 27, 2022, pp. 1-7. cited by applicant

Sun; Ruizhi et al., “Single-Photon Detection Based on High Dynamic Range Time-To-Digital Converter”, Journal of Jilin University (Information Science Edition), Jul. 2018, with English abstract, pp. 381-385, vol. 36, No. 4. cited by applicant

“Office Action of China Counterpart Application”, issued on Sep. 1, 2023, p. 1-p. 6. cited by applicant

Primary Examiner: Hulka; James R

Attorney, Agent or Firm: JCIPRNET

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION (1) This application claims the priority benefit of U.S. provisional application Ser. No. 63/121,243, filed on Dec. 4, 2020, and China application serial no. 202111154878.7, filed on Sep. 29, 2021. The entirety of each of the above-mentioned patent applications is hereby incorporated by reference herein and made a part of this specification.

BACKGROUND

Technical Field

(1) The disclosure relates to a ranging technology, and in particular, relates to a time-of-flight ranging device and a time-of-flight ranging method.

Description of Related Art

(2) At present, in the applications of direct time of flight (D-ToF) sensing, the integration time of a time-to-digital converter (TDC) determines the distance accuracy of a ranging device. In this regard, when the total measurement time is fixed, if the integration time decreases, the converted distance resolution increases, and the error of ranging may thus be lowered. As the integration time of the time-to-digital converter decreases, the number of bins in the histogram generated by the time-to-digital converter may increase. In this regard, an increase in the number of bins in the histogram may require increased storage space to store the results measured by the time-to-digital converter each time. As a result, the costs of the processing chip and the chip area of the distance measuring device may be considerably increased. However, if the integration time of the time-to-digital converter is increased in consideration of the costs of the processing chip of the ranging device, the distance resolution may drop and the error of measuring may increase. In particular, in the ranging process, when two objects approach each other, the ranging device may not be able to accurately distinguish the gap between the two objects.

SUMMARY

(3) In view of the foregoing problems, the disclosure provides a time-of-flight ranging device and a time-of-flight ranging method capable of providing an accurate ranging function.

(4) The disclosure provides a time-of-flight ranging device including a light source, a sensing array, and a time-to-digital converter. The light source is configured to emit a laser pulse signal towards a sensing target. The sensing array includes a plurality of sensing units and is configured to sense reflected pulse light generated when the sensing target reflects the laser pulse signal. The time-to-digital converter is coupled to the sensing array and is configured to perform an integration operation on a plurality of sensing results of the sensing units during a plurality of consecutive integration periods to generate histogram data. At least part of the integration periods have different time lengths, such that at least part of a plurality of bins in the histogram data have different bin widths.

(5) The disclosure further provides a time-of-flight ranging method, and the method includes the following steps. A light source emits a laser pulse signal towards a sensing target. A plurality of sensing units of a sensing array sense reflected pulse light generated when the sensing target reflects the laser pulse signal. A time-to-digital converter performs an integration operation on a plurality of sensing results of the sensing units during a plurality of consecutive integration periods to generate histogram data. At least part of the integration periods have different time lengths, such that at least part of a plurality of bins in the histogram data have different bin widths.

(6) To sum up, in the time-of-flight ranging device and the time-of-flight ranging method provided by the disclosure, the bin widths of part of the bins in the histogram data may be dynamically adjusted, such that part of the bins in the histogram data that are close to the actual sensing distance have narrow bin widths, and accurate sensing data may thus be provided.

(7) To make the aforementioned more comprehensible, several embodiments accompanied with drawings are described in detail as follows.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) The accompanying drawings are included to provide a further understanding of the disclosure, and are incorporated in and constitute a part of this specification. The drawings illustrate exemplary embodiments of the disclosure and, together with the description, serve to explain the principles of the disclosure.
- (2) FIG. 1 is a schematic diagram of a time-of-flight ranging device according to an embodiment of the disclosure.
- (3) FIG. 2 is a flow chart of a time-of-flight ranging method according to a first embodiment of the disclosure.
- (4) FIG. 3A is an integration timing diagram according to the first embodiment of the disclosure.
- (5) FIG. 3B is a schematic chart of histogram data according to the first embodiment of the disclosure.
- (6) FIG. 4A is another integration timing diagram according to the first embodiment of the disclosure.
- (7) FIG. 4B is a schematic chart of another histogram data according to the first embodiment of the disclosure.
- (8) FIG. 5 is a flow chart of a time-of-flight ranging method according to a second embodiment of the disclosure.
- (9) FIG. 6 is a schematic chart of histogram data according to the second embodiment of the disclosure.
- (10) FIG. 7 is a schematic chart of histogram data according to a third embodiment of the disclosure.

DESCRIPTION OF THE EMBODIMENTS

- (11) In order to make the disclosure more comprehensible, several embodiments are described below as examples of implementation of the disclosure. Moreover, elements/components/steps with the same reference numerals are used to represent the same or similar parts in the drawings and embodiments.
- (12) FIG. 1 is a schematic diagram of a time-of-flight ranging device according to an embodiment of the disclosure. With reference to FIG. 1, a time-of-flight ranging device **100** includes a time-of-flight sensor **110**, a control circuit **120**, and a storage device **130**. The time-of-flight sensor **110** includes a sensing array **111**, a time-to-digital converter (TDC) **112**, and a light source **113**. The control circuit **120** is coupled to the time-to-digital converter **112**, the light source **113**, and the storage device **130**. The time-to-digital converter **112** is coupled to the sensing array **111**. In this embodiment, the time-of-flight sensor **110** may perform a direct time of flight (D-ToF) sensing operation. The sensing array **111** may include a plurality of sensing units (sensing pixels) arranged in an array. In this embodiment, the sensing units may be a plurality of single photon avalanche diodes (SPADs). The light source **113** may be a laser light source and is configured to emit a laser pulse signal, and the laser pulse signal may be an infrared (IR) laser.
- (13) In this embodiment, the control circuit **120** may be configured to be a microcontroller unit (MCU) in the time-of-flight ranging device **100**, but the disclosure is not limited thereto. In an embodiment, the control circuit **120** may be a central processing unit (CPU) of a terminal apparatus, and the time-of-flight ranging device **100** is disposed on the terminal apparatus. In this embodiment, the storage device **130** may be a memory disposed in the time-of-flight ranging device **100**, but the disclosure is not limited thereto. In an embodiment, the storage device **130** may be a storage device of the terminal apparatus.
- (14) In this embodiment, the light source **113** may emit a laser pulse signal towards a sensing target **200**. The laser pulse signal may be emitted to a surface of the sensing target **200** and reflects off the

surface of the sensing target **200**, and corresponding reflected pulse light is generated. The sensing units of the sensing array **111** may sense the reflected pulse light generated when the sensing target **200** reflects the laser pulse signal, and the sensing array **111** may output a plurality of sensing results of the sensing units to the time-to-digital converter **112**. Based on the characteristics of the single photon avalanche diodes, each single photon avalanche diode may generate a sensing signal after receiving one or a few photons, and may store the sensing signal in a storage capacitor of the sensing unit. In this embodiment, the time-to-digital converter **112** may perform a plurality of times of integration operations on the sensing results of the single photon avalanche diodes during a plurality of consecutive integration periods to generate histogram data. The histogram data may be stored in a memory of the time-of-flight sensor **110** or a buffer of the time-to-digital converter **112**. In this embodiment, the control circuit **120** may read out the histogram data and analyze the histogram data, so as to calculate a distance parameter between the time-of-flight ranging device **100** and the sensing target **200** according to the histogram data.

(15) FIG. 2 is a flow chart of a time-of-flight ranging method according to a first embodiment of the disclosure. With reference to FIG. 1 and FIG. 2, the time-of-flight ranging device **100** may execute steps S210 to S230 shown in FIG. 2 to implement a time-of-flight operation. In step S210, the time-of-flight ranging device **100** may emit a laser pulse signal towards the sensing target **200** through the light source **113**. In step S220, the time-of-flight ranging device **100** may sense, through the sensing units of the sensing array **111**, reflected pulse light generated when the sensing target **200** reflects the laser pulse signal. In step S230, the time-of-flight ranging device **100** may perform, through the time-to-digital converter **112**, an integration operation on a plurality of sensing results of the sensing units during a plurality of consecutive integration periods to generate histogram data. Note that in this embodiment, at least part of the integration periods may have different time lengths, such that at least part of a plurality of bins in the histogram data have different bin widths.

(16) With reference to FIG. 1, FIG. 3A, and FIG. 3B, FIG. 3A is an integration timing diagram according to the first embodiment of the disclosure, and FIG. 3B is a schematic chart of histogram data according to the first embodiment of the disclosure. For instance, as shown in FIG. 3A, when the sensing array **111** senses the reflected pulse light generated when the sensing target **200** reflects the laser pulse signal, the time-to-digital converter **112** may perform an integration operation on the sensing results of the sensing units during consecutive integration periods EP1 to EP12 between time t_0 and time t_{12} to generate histogram data **310** as shown in FIG. 3B. In this embodiment, the integration periods EP5 to EP10 may have integration time lengths different from that of the integration periods EP1 to EP4, EP11, and EP12. For instance, the integration time lengths of the integration periods EP5 to EP10 may be shorter than the integration time lengths of the integration periods EP1 to EP4, EP11, and EP12. In other words, a time resolution between time t_4 and time t_{10} may be greater than that of other time intervals.

(17) The control circuit **120** may store the histogram data of FIG. 3B into the storage device **130** and may analyze the histogram data of FIG. 3B. As shown in FIG. 3B, the sensing results of the sensing units during the consecutive integration periods EP1 to EP12 may be presented as a plurality of bins of the histogram data **310** in FIG. 3B. Since the bin widths of the bins between time t_4 and time t_{10} are narrow, the time resolution is high. In other words, if the time when the sensing array **111** receives the reflected pulse light is between time t_4 and time t_{10} , the time-of-flight ranging device **100** provided by this embodiment may obtain the sensing result of the distance parameter exhibiting high distance accuracy by analyzing the histogram data **310** in FIG. 3B.

(18) In this embodiment, the control circuit **120** may determine the time when the sensing array **111** receives the reflected pulse light according to a plurality of count values corresponding to the bins of the histogram data **310** in FIG. 3B. Further, the control circuit **120** may calculate the distance parameter between the time-of-flight ranging device **100** and the sensing target **200** according to a

time difference between emitting of the laser pulse signal (the emitting time is known) by the light source **113** and receiving of the reflected pulse light by the sensing array **111**. In this embodiment, the sensing array **111** may also sense ambient light and thereby outputs a sensing result of the ambient light. Therefore, the control circuit **120** may determine whether the count values of consecutive bins among the bins in the histogram data **310** exceed a pre-designed count value and whether a number of the consecutive bins exceeds a predetermined number of consecutive bins. If yes is determined, the control circuit **120** may determine the time when the sensing array **111** receives the reflected pulse light through calculating the count values of the consecutive bins. For instance, the control circuit **120** may average the consecutive count values to obtain an average count value. Next, the control circuit **120** may calculate the time difference (td) between emitting of the laser pulse signal by the light source **113** and sensing of the reflected pulse light by the sensing array **111** according to the average count value and calculates the corresponding distance parameter, such as $D=td \times c$, according to the time difference, where D is the distance parameter, and c is the speed of light. Alternatively, in another embodiment, the control circuit **120** may determine a bin exceeding a threshold as a criterion for determination and analyze whether the distribution of adjacent multiple bins (front and rear adjacent bins) of this bin conform to the photon distribution of a reflector. If the distribution of the adjacent multiple bins of this bin conform to the photon distribution of the reflector, the control circuit **120** may determine the time when the sensing array **111** receives the reflected pulse light through calculating the count values of the consecutive bins. Alternatively, in still another embodiment, the control circuit **120** may also analyze multiple bins of the histogram data **310** in other ways to determine the time for reflecting the reflected pulse light, and the disclosure is not limited to the abovementioned embodiments.

(19) Note that the integration time lengths of the integration periods EP1 to EP12 may be predetermined and are not limited to the time length distribution shown in FIG. 3A. In an embodiment, the integration time lengths of the integration periods EP1 to EP12 may include a plurality of time length designs and are not limited to the two designs shown in FIG. 3A. The integration time lengths of the integration periods EP1 to EP12 may also change gradually, for example, the time lengths may increase or decrease gradually. Furthermore, a number of integration periods is not limited to the number shown in FIG. 3A. In another embodiment, the control circuit **120** may dynamically adjust a plurality of time lengths of another plurality of integration periods in a next sensing operation according to the distance parameter which is obtained according to the analysis and calculating results of the histogram data **310** in FIG. 3B. In other words, as shown in FIG. 3B, when the control circuit **120** determines that the count value corresponding to the integration period EP4 is the highest, the control circuit **120** may adaptively adjust the integration time lengths of the integration period EP1 to EP12.

(20) FIG. 4A is another integration timing diagram according to the first embodiment of the disclosure. FIG. 4B is a schematic chart of another histogram data according to the first embodiment of the disclosure. For instance, as shown in FIG. 1, FIG. 4A, and FIG. 4B, as described above, the control circuit **120** may decrease the integration periods close to the time when the sensing array **111** receives the reflected pulse light in the next sensing operation. Continuing from the description of FIG. 3A and FIG. 3B, in the next sensing operation, the control circuit **120** may shorten a time length of at least one (i.e., corresponding to at least one integration period adjacent to the one with the highest count value in previous sensing) of a plurality of integration periods EP1' to EP12' and increase time lengths of other integration periods. As shown in FIG. 4A, the control circuit **120** may shorten the time lengths of the integration periods EP3' to EP6' and increase the time lengths of other integration periods. During the next time the sensing array **111** senses the reflected pulse light generated when the sensing target **200** reflects the laser pulse signal, the time-to-digital converter **112** may perform an integration operation on the sensing results of the sensing units during the consecutive integration periods EP1' to EP12' between time t0' and time t12' to generate histogram data **410** as shown in FIG. 4B.

(21) The control circuit **120** may store the histogram data **410** of FIG. **4B** into the storage device **130** and may analyze the histogram data **410** of FIG. **4B**. As shown in FIG. **4B**, since the bin widths of the bins between time $t2'$ and time $t6'$ are narrow, the time resolution is high. In other words, if the time when the sensing array **111** receives the reflected pulse light is between time $t2'$ and time $t6'$, the time-of-flight ranging device **100** provided by this embodiment may obtain the sensing result of the distance parameter exhibiting high distance accuracy by analyzing the histogram data **410** in FIG. **4B**. In other words, the time-of-flight ranging device **100** of this embodiment may adaptively adjust (dynamically adjust) the time lengths of at least part of the integration periods, and the sensing accuracy of the sensing results may thus be effectively improved.

(22) Note that in this embodiment, after the time lengths of the integration periods EP1' to EP12' in the next sensing operation are adjusted, a sensing total time length corresponding to the integration periods EP1' to EP12' may remain unchanged. In other words, the sensing total time length corresponding to the integration periods EP1 to EP12 is identical to the sensing total time length corresponding to the integration periods EP1' to EP12', but the disclosure is not limited thereto. Further, after the time lengths of the integration periods EP1' to EP12' in the next sensing operation are adjusted, the number of integration periods of the integration periods EP1' to EP12' may remain unchanged. In other words, the number of integration periods of the integration periods EP1 to EP12 is identical to the number of integration periods of the integration periods EP1' to EP12', but the disclosure is not limited thereto. In other words, if the sensing total time length and the number of integration periods may remain unchanged, the histogram data **310** in FIG. **3B** and the histogram data **410** in FIG. **4B** may be stored in the storage device **130** and occupy a same storage space. In this way, in the time-of-flight ranging device **100** of this embodiment, a distance parameter exhibiting high distance accuracy may be obtained without an increase in the storage space.

(23) FIG. **5** is a flow chart of a time-of-flight ranging method according to a second embodiment of the disclosure. With reference to FIG. **1** and FIG. **5**, the time-of-flight ranging device **100** may execute steps S510 to S540 shown in FIG. **5** to implement a time-of-flight operation. In step S510, the time-of-flight ranging device **100**, through the light source **113**, may sequentially emit a plurality of laser pulse signals towards the sensing target **200**. In this embodiment, the light source **113** may emit the laser pulse signals at a same time interval. In step S520, the time-of-flight ranging device **100** may sense, through the sensing units of the sensing array **111**, a plurality of rays of reflected pulse light generated when the sensing target **200** reflects the laser pulse signals. In step S530, the time-of-flight ranging device **100** may perform, through the time-to-digital converter **112**, a plurality of integration operations on a plurality of sensing results of the sensing units during a plurality of consecutive ranging periods to generate a plurality of pieces of first histogram data. In step S540, the time-of-flight ranging device **100** may perform a mathematical operation on the pieces of first histogram data to generate second histogram data. Note that the abovementioned mathematical operation may refer to methods such as an accumulation operation, an averaging operation, or a difference operation, for example, and the following embodiments in FIG. **6** and FIG. **7** are illustrated by way of an accumulation operation.

(24) Note that the abovementioned ranging periods have a plurality of delay periods among one another, such that a plurality of periods of start time of the pieces of first histogram data are sequentially delayed by a plurality of time lengths. In addition, the time lengths of the delay periods are less than a plurality of bin widths of a plurality of bins in the pieces of first histogram data. In this way, each first number of bins in each of the first histogram data is less than a number of bins in the second histogram data, and a plurality of first bin widths in each piece of first histogram data are greater than a plurality of second bin widths in the second histogram data.

(25) With reference to FIG. **6**, FIG. **6** is a schematic chart of histogram data according to the second embodiment of the disclosure. For instance, the time-to-digital converter **112** may perform a plurality of integration operations on a plurality of sensing results of the sensing units of the sensing array **111** during three consecutive ranging periods (without overlapping) to generate three

pieces of first histogram data **610** to **630** as shown in FIG. 6, where time **a0** to time **a14** are configured to represent timing relationships of relative time of the first histogram data **610** to **630** during different ranging periods. In this example, the three consecutive ranging periods are individually synchronized with the time when the light source **113** sequentially emits three laser pulse signals towards the sensing target **200**. During a first ranging period, the first histogram data **610** generated by the time-to-digital converter **112** may have six bins between time **a0** and time **a12**. During a second ranging period, the first histogram data **620** generated by the time-to-digital converter **112** may have six bins between time **a1** and time **a13**. During a third ranging period, the first histogram data **630** generated by the time-to-digital converter **112** may have six bins between time **a2** and time **a14**. The time lengths of the integration periods of the first ranging period are identical, such that the bin widths of the bins in the first histogram data **610** to **630** are identical (e.g., a time length t , the time length from time **a0** to time **a2**, for example). A delay period having a time length of $t/2$ (e.g., the time length from time **a0** to time **a1**) may be provided between the first ranging period and the second ranging period, and a delay period having a time length of $t/2$ (e.g., the time length from time **a1** to time **a2**) may be provided between the second ranging period and the third ranging period.

(26) In this example, the control circuit **120** may accumulate the first histogram data **610** to **630** to generate second histogram data **640**, and the second histogram data **640** may have twelve bins between time **a0** and time **a14**. In other words, each number of bins in each of the first histogram data **610** to **630** is less than the number of bins in the second histogram data **640**, and the bin widths in each of the first histogram data **610** to **630** are greater than the bin widths in the second histogram data **640**. Therefore, compared to the first histogram data **610** to **630**, the control circuit **120** may calculate the sensing result of the distance parameter with high distance accuracy between the time-of-flight ranging device **100** and the sensing target **200** according to the second histogram data **640**. As shown in FIG. 6, the control circuit **120** may, through the second histogram data **640**, determine the highest count value between time **a5** and time **a6**, and further calculates the distance parameter. Compared to the first histogram data **610**, the control circuit **120** may determine the highest count value between time **a4** and time **a6** only through the first histogram data **610**.

(27) From another perspective, if the time lengths of a plurality of identical delay periods are t/M , the time resolution of the second histogram data may be increased by approximately M times, such that the distance accuracy of the distance parameter calculated through the second histogram data may also be increased by approximately M times. Nevertheless, the time lengths of the delay periods are not limited to the description provided above in the disclosure. In an embodiment, the time lengths of the delay periods may also increase proportionally or increase non-proportionally.

(28) FIG. 7 is a schematic chart of histogram data according to a third embodiment of the disclosure. With reference to FIG. 1 and FIG. 7, the time-to-digital converter **112** may perform a plurality of integration operations on a plurality of sensing results of the sensing units of the sensing array **111** during two consecutive ranging periods (without overlapping) to generate two pieces of third histogram data **710** to **720** as shown in FIG. 7, where time **b0** to time **b13** are configured to represent the timing relationships of the relative time of the third histogram data **710** to **720** during different ranging periods. In this example, the two consecutive ranging periods are individually synchronized with the time when the light source **113** sequentially emits two laser pulse signals towards the sensing target **200**. During a ranging period, the third histogram data **710** generated by the time-to-digital converter **112** may have eight bins between time **b0** and time **b12**. During a next ranging period, the third histogram data **720** generated by the time-to-digital converter **112** may have eight bins between time **b1** and time **b13**.

(29) Note that in this embodiment, at least part of the consecutive integration periods of each of the integration operations may have different time lengths, such that at least part of a plurality of bins in each of the third histogram data **710** and **720** have different bin widths. As shown in FIG. 7, in the third histogram data **710**, the bin widths from time **b0** to time **b2**, from time **b6** to time **b8**, from

time **b8** to time **b10**, and from time **b10** to time **b12** may be a time length t' , and in the third histogram data **710**, the bin widths from time **b2** to time **b3**, from time **b3** to time **b4**, from time **b4** to time **b5**, and from time **b5** to time **b6** may be a time length $t'/2$. In the third histogram data **720**, the bin widths from time **b1** to time **b3**, from time **b3** to time **b5**, from time **b5** to time **b7**, and from time **b11** to time **b13** may be the time length t' , and in the third histogram data **720**, the bin widths from time **b7** to time **b8**, from time **b8** to time **b9**, from time **b9** to time **b10**, and from time **b10** to time **b11** may be the time length $t'/2$. Further, a delay period having the time length t' (e.g., the time length from time **b0** to time **b1**) may be provided between two ranging periods. Note that in an embodiment, a delay period may not be provided between two ranging periods (that is, $t'=0$).

(30) In this embodiment, the control circuit **120** may accumulate the third histogram data **710** and **720** to generate fourth histogram data **730**, the fourth histogram data **730** may have thirteen bins between time **b0** and time **b13**, and each bin in the fourth histogram data **730** may have a bin width of the time length $t'/2$. As shown in FIG. 7, the number of bins in the fourth histogram data **730** is greater than each number of bins in the third histogram data **710** and **720**, and overall time accuracy of the fourth histogram data **730** is greater than each overall time accuracy of the third histogram data **710** and **720**. Therefore, compared to the third histogram data **710** and **720**, the control circuit **120** may calculate the sensing result of the distance parameter with high distance accuracy between the time-of-flight ranging device **100** and the sensing target **200** according to the fourth histogram data **730**.

(31) Note that this embodiment may be applied to the abovementioned first embodiment. For instance, a delay period may be provided or may not be provided between the two ranging periods in FIG. 3B and FIG. 4B. The control circuit **120** may accumulate the histogram data **310** and **410** of FIG. 3B and FIG. 4B to obtain histogram data exhibiting good overall time accuracy. Besides, this embodiment may also be applied to the abovementioned second embodiment. For instance, at least part of the bins in each of the histogram data **610** to **630** may have different bin widths, and therefore, the control circuit **120** may accumulate the histogram data **610** to **630** having different bin widths to obtain histogram data exhibiting good overall time accuracy.

(32) In view of the foregoing, in the time-of-flight ranging device and the time-of-flight ranging method provided by the disclosure, through the time-to-digital converter, the time lengths of the integration periods during one ranging period may be dynamically adjusted, and/or an mathematical operation may be performed on the ranging periods in which the start time of each other's integration period is provided with a delay period, such that histogram data exhibiting good overall time accuracy may be obtained. In other words, in the time-of-flight ranging device and the time-of-flight ranging method provided by the disclosure, histogram data exhibiting good overall time accuracy may be obtained without an increase in the storage space and/or without a change in the sensing total time length, and therefore, a distance parameter exhibiting good distance accuracy may be further calculated.

(33) It will be apparent to those skilled in the art that various modifications and variations can be made to the disclosed embodiments without departing from the scope or spirit of the disclosure. In view of the foregoing, it is intended that the disclosure covers modifications and variations provided that they fall within the scope of the following claims and their equivalents.

Claims

1. A time-of-flight ranging device, comprising: a light source, configured to emit a laser pulse signal towards a sensing target; a sensing array, comprising a plurality of sensing units, sensing reflected pulse light generated when the sensing target reflects the laser pulse signal; a time-to-digital converter, coupled to the sensing array, performing an integration operation on a plurality of sensing results of the sensing units during a plurality of consecutive integration periods to generate histogram data; and a control circuit, coupled to the light source, the sensing array, and the time-to-

digital converter, configured to calculate a distance parameter between the time-of-flight ranging device and the sensing target according to the histogram data, wherein at least part of the integration periods have different time lengths, such that at least part of a plurality of bins in the histogram data have different bin widths, wherein the control circuit determines whether count values of consecutive bins among the bins in the histogram data exceed a pre-designed count value and whether a number of the consecutive bins exceeds a predetermined number of consecutive bins to calculate time when the sensing array receives the reflected pulse light, wherein the control circuit dynamically adjusts a plurality of time lengths of another plurality of integration periods in a next sensing operation according to the time when the sensing array receives the reflected pulse light.

2. The time-of-flight ranging device according to claim 1, wherein the control circuit determines a time difference between emitting of the laser pulse signal by the light source and receiving of the reflected pulse light by the sensing array according to a plurality of count values corresponding to the bins of the histogram data.

3. The time-of-flight ranging device according to claim 1, wherein the control circuit decreases at least one of the another plurality of integration periods close to the time when the sensing array receives the reflected pulse light in the next sensing operation, and the control circuit increases the time length of at least another one of the another plurality of integration periods.

4. The time-of-flight ranging device according to claim 1, wherein after the time lengths of the another plurality of integration periods in the next sensing operation are adjusted, a sensing total time length corresponding to the another plurality of integration periods remains unchanged.

5. The time-of-flight ranging device according to claim 1, wherein after the time lengths of the another plurality of integration periods in the next sensing operation are adjusted, a number of integration periods of the another plurality of integration periods remains unchanged.

6. The time-of-flight ranging device according to claim 1, further comprising: a storage device, coupled to the control circuit, wherein the time-to-digital converter performs an integration operation on another plurality of sensing results of the sensing units during the another plurality of consecutive integration periods in the next sensing operation to generate another histogram data, wherein the histogram data and the another histogram data occupy a same storage space in the storage device.

7. The time-of-flight ranging device according to claim 1, wherein the sensing units are a plurality of single photon avalanche diodes.

8. A time-of-flight ranging method, comprising: emitting, through a light source, a laser pulse signal towards a sensing target; sensing, through a plurality of sensing units of a sensing array, reflected pulse light generated when the sensing target reflects the laser pulse signal; performing, through a time-to-digital converter, an integration operation on a plurality of sensing results of the sensing units during a plurality of consecutive integration periods to generate histogram data; calculating, through a control circuit, a distance parameter between a time-of-flight ranging device and the sensing target according to the histogram data, wherein at least part of the integration periods have different time lengths, such that at least part of a plurality of bins in the histogram data have different bin widths; determining, through the control circuit, whether count values of consecutive bins among the bins in the histogram data exceed a pre-designed count value and whether a number of the consecutive bins exceeds a predetermined number of consecutive bins to calculate time when the sensing array receives the reflected pulse light; and dynamically adjusting, through the control circuit, a plurality of time lengths of another plurality of integration periods in a next sensing operation according to the time when the sensing array receives the reflected pulse light.

9. The time-of-flight ranging method according to claim 8, wherein the step of calculating the distance parameter further comprises: determining a time difference between emitting of the laser pulse signal by the light source and receiving of the reflected pulse light by the sensing array

according to a plurality of count values corresponding to the bins of the histogram data.

10. The time-of-flight ranging method according to claim 8, wherein the step of dynamically adjusting the time lengths further comprises: decreasing at least one of the another plurality of integration periods close to the time when the sensing array receives the reflected pulse light in the next sensing operation; and increasing the time length of at least another one of the another plurality of integration periods.

11. The time-of-flight ranging method according to claim 8, wherein after the time lengths of the another plurality of integration periods in the next sensing operation are adjusted, a sensing total time length corresponding to the another plurality of integration periods remains unchanged.

12. The time-of-flight ranging method according to claim 8, wherein after the time lengths of the another plurality of integration periods in the next sensing operation are adjusted, a number of integration periods of the another plurality of integration periods remains unchanged.

13. The time-of-flight ranging method according to claim 8, wherein the step of dynamically adjusting the time lengths further comprises: performing, through the time-to-digital converter, an integration operation on another plurality of sensing results of the sensing units during the another plurality of consecutive integration periods in the next sensing operation to generate another histogram data, wherein the histogram data and the another histogram data occupy a same storage space in the storage device.

14. The time-of-flight ranging method according to claim 8, wherein the sensing units are a plurality of single photon avalanche diodes.
