

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12412299
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Yamaguchi; Yuya et al.

Information processing device, information processing method, and program

Abstract

There is provided an information processing device, an information processing method, and a program that improve detection accuracy in detecting a motion or posture of a person or an object using an inertial sensor. A posture of a measurement target is estimated based on a position and orientation of each of a plurality of measurement devices arranged at a plurality of parts of the measurement target and based on a connection relationship between the measurement devices that is set based on positions and orientations of the measurement devices, each measurement device including an inertial sensor. The present technology can be applied to a motion capture system.

Inventors:	Yamaguchi; Yuya (Tokyo, JP), Kato; Takaaki (Kanagawa, JP), Gomita; Jun (Tokyo, JP)
Applicant:	SONY GROUP CORPORATION (Tokyo, JP)
Family ID:	78845518
Assignee:	SONY GROUP CORPORATION (Tokyo, JP)
Appl. No.:	17/927487
Filed (or PCT Filed):	May 28, 2021
PCT No.:	PCT/JP2021/020353
PCT Pub. No.:	WO2021/251171
PCT Pub. Date:	December 16, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20230245340 A1	Aug. 03, 2023

Foreign Application Priority Data

JP	2020-102548	Jun. 12, 2020
----	-------------	---------------

Publication Classification

Int. Cl.: G06T7/73 (20170101); G06T7/246 (20170101)

U.S. Cl.:

CPC G06T7/73 (20170101); G06T7/246 (20170101); G06T2207/30196 (20130101)

Field of Classification Search

References Cited**U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2007/0265741	12/2006	Oi	701/527	G01C 21/12
2020/0033937	12/2019	Erivantcev	N/A	G06T 7/246
2023/0245340	12/2022	Yamaguchi	382/103	G06T 7/75

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2007-303886	12/2006	JP	N/A
2012068772	12/2011	JP	N/A
2020013560	12/2019	JP	G06T 7/73
WO-2020070928	12/2019	WO	A63F 13/212

OTHER PUBLICATIONS

Filippeschi et al., Survey of Motion Tracking Methods Based on Inertial Sensors: A Focus on Upper Limb Human Motion, MDPI, 2017, pp. 1-40. cited by applicant

Primary Examiner: Gilliard; Delomia L

Attorney, Agent or Firm: Paratus Law Group, PLLC

Background/Summary**CROSS REFERENCE TO PRIOR APPLICATION**

(1) This application is a National Stage Patent Application of PCT International Patent Application No. PCT/JP2021/020353 (filed on May 28, 2021) under 35 U.S.C. § 371, which claims priority to Japanese Patent Application No. 2020-102548 (filed on Jun. 12, 2020), which are all hereby incorporated by reference in their entirety.

TECHNICAL FIELD

(2) The present technology relates to an information processing device, an information processing method, and a program, and more particular, to an information processing device, an information processing method, and a program that improve detection accuracy in detecting a motion or posture of a person or an object using an inertial sensor.

BACKGROUND ART

(3) NPL 1 discloses an inertial measurement unit (IMU) and a motion capture system that combines the IMU and a marker to detect, human motion.

CITATION LIST**Non Patent Literature**

(4) [NPL 1] A. Filippeschi, N. Schmitz, M. Miezal, Bleser, E. Ruffaldi, and D. Stricker, "Survey of Motion Tracking Methods Based on Inertial Sensors: A Focus on Upper Limb Human Motion," In: Sensors 17.6 (2017), p. 1257.

SUMMARY**Technical Problem**

(5) There is a demand for improving detection accuracy in detecting a motion or posture of a person or object using an inertial sensor.

(6) The present technology has been made in view of such circumstances, and aims to improve detection accuracy in detecting a motion or posture of a person or an object using an inertial sensor.

Solution to Problem

(7) An information processing device or a program according to the present technology is an information processing device including a posture estimation unit that estimates a posture of a measurement target based on a position and orientation of each of a plurality of measurement devices arranged at a plurality of parts of the measurement target and based on a connection relationship between the measurement devices that is set based on positions and orientations of the measurement devices, each measurement device including an inertial sensor, or a program for causing a computer to function as such an information processing device.

(8) An information processing method according to the present technology is an information processing method including, by a posture estimation unit of an information processing device, estimating a posture of a measurement target based on a position and orientation of each of a plurality of measurement devices arranged at a plurality of parts

of the measurement target and based on a connection relationship between the measurement devices that is set based on positions and orientations of the measurement devices, each measurement device including an inertial sensor.

(9) According to the present technology, a posture of a measurement target is estimated based on a position and orientation of each of a plurality of measurement devices arranged at a plurality of parts of the measurement target and based on a connection relationship between the measurement devices that is set based on positions and orientations of the measurement devices, each measurement device including an inertial sensor.

Description

BRIEF DESCRIPTION OF DRAWINGS

(1) FIG. 1 is an explanatory diagram for explaining an optical motion capture system.

(2) FIG. 2 is an explanatory diagram for explaining a type of motion capture system using image recognition.

(3) FIG. 3 is an explanatory diagram for explaining a type of motion capture system using an inertial sensor.

(4) FIG. 4 is an overall diagram illustrating a configuration example of a motion capture system to which the present technology is applied.

(5) FIG. 5 is a block diagram illustrating a functional configuration of a measurement device of FIG. 4.

(6) FIG. 6 is a diagram for explaining processing of initializing measurement devices.

(7) FIG. 7 is a flowchart illustrating an example of a procedure of the processing of initializing the measurement devices.

(8) FIG. 8 is a diagram illustrating an example of a correspondence relationship between a predetermined feature point of a subject and feature points on a pair of parallax images.

(9) FIG. 9 is a diagram illustrating an example of how feature points are tracked.

(10) FIG. 10 is a block diagram illustrating an example of a functional configuration of the information processing device of FIG. 4.

(11) FIG. 11 is a diagram illustrating an example of a connection relationship image representing a connection relationship of measurement devices.

(12) FIG. 12 is a flowchart illustrating an example of a procedure for setting the connection relationship of the measurement devices.

(13) FIG. 13 is a diagram illustrating an example of measurement devices to be updated in the connection relationship image of FIG. 11.

(14) FIG. 14 is a flowchart illustrating an example of a procedure of processing of correcting positions and orientations of the measurement devices, performed by a pose correction processing unit.

(15) FIG. 15 is a block diagram illustrating a configuration example of hardware of a computer that executes a series of processing according to a program.

DESCRIPTION OF EMBODIMENTS

(16) Hereinafter, embodiments of the present technology will be described with reference to the drawings.

(17) <<Well-Known Motion Capture System>>

(18) <Optical Type>

(19) FIG. 1 is an explanatory diagram for explaining an optical motion capture system.

(20) A motion capture system 11 in FIG. 1 includes a plurality of infrared cameras 12 installed in a studio. Reflective markers 14 that reflect infrared light are attached to the joints, head, or the like of a subject person 13 whose motion is to be captured. The infrared cameras 12 project infrared light onto the subject person 13 to capture images of the reflective markers 14. With this configuration, the positions of the reflective markers 14 are tracked by the images captured by the infrared cameras 12, so that the motion of the subject person 13 is acquired. In this motion capture system 11, it is necessary to install a plurality of infrared cameras so as to surround the subject person 13 in order to acquire all the reflective markers. Therefore, there are drawbacks such as high cost and time and effort required for setting up the system.

(21) <Image Recognition Type>

(22) FIG. 2 is an explanatory diagram for explaining a type of motion capture system, using image recognition.

(23) In a motion capture system 21 of FIG. 2, a human body is decomposed into skeletons that connect parts such as the head, neck, shoulders, elbows, wrists, waists, knees, and ankles, as in a skeleton configuration example 22L. Also in the motion capture system 21, image recognition using deep learning or the like is performed on an image 22R of a subject person captured by one camera. As a result of the image recognition, the positions of the parts of the subject person corresponding to parts J0 to J13 of the skeleton configuration example 22L are identified or estimated.

(24) This motion capture system 21 has drawbacks, such as learning required in advance, false detection occurring due to a difference in appearance from the time of learning, occlusion occurring, and always capturing the subject person with a camera.

(25) <Type Using Inertial Sensor>

(26) FIG. 3 is an explanatory diagram for explaining a type of motion capture system using an inertial sensor.

(27) In a motion capture system 31 of FIG. 3, IMUs, which are inertial sensors, are attached to parts of the subject

person whose motion is to be captured. Then, the positions and postures of the parts of the subject person are detected from pieces of sensor data obtained from the IMUs at the parts of the subject person. This motion capture system **31** reduces the drawbacks of the motion capture system **11** of FIG. **1** and the motion capture system **21** of FIG. **2**.

(28) By contrast, the motion capture system **31** of FIG. **3** has a drawback of low degree of freedom, for example, restricted motion of the subject person due to the predetermined positions at which the IMUs are attached on the subject person. In addition, it has a drawback that sufficient accuracy cannot be expected because motion capture (posture detection) using only the IMUs fails to fully control the biases (drifts) inherent in the IMUs.

(29) A motion capture system that combines inertial sensors and reflective markers has also been proposed (for example, NPL 1).

(30) However, the problems of the IMUs and the reflective markers as described above have not yet been solved.

(31) In the technical fields of augmented reality (AR) and virtual reality (VR), devices have been developed that combine images and IMUS to estimate the position and posture of the users head. However, from the viewpoint of power consumption and camera size, it is not suitable as a motion capture system for a person or an object with multiple joints that move individually. It is also difficult to deal with occlusion occurring. In addition, in order to estimate the positions and postures of related joints, mutual information exchange is required, resulting in a problem that, as the number of joints increases, the amount of information to be handled and processed by the IMUs attached to the joints becomes enormous, which is difficult to achieve.

(32) The present technology solves such problems.

(33) <<Motion Capture System to which Present Technology is Applied>>

(34) FIG. **4** is an overall diagram illustrating a configuration example of a motion capture system to which the present technology is applied. Note that in the present embodiment, the system to which the present technology is applied is a motion capture system, but it may be a posture estimation system that estimates (detects) the posture of a person or the like.

(35) A motion capture system **51** in FIG. **4** includes a measurement device **61**, a communication device **63**, and an information processing device **64**.

(36) (Measurement Device **61**)

(37) Measurement devices **61** are each attached to any one of a plurality of parts of the subject person whose motion is to be captured by means of an attachment member **62**. The attachment member **62** holds the measurement device **61** and is detachably mounted in a ring shape on any one of the parts of the human body such as the head, neck, shoulders, elbows, wrists, waists, knees, and ankles. However, the attachment member **62** may have any form. The part on which the measurement device **61** is to be mounted is not limited to a specific part. The target whose motion is to be captured (measurement target) may be an object instead of a person.

(38) The measurement device **61** includes an image sensor **71**, a logic circuit board **72**, and an IMU **73**.

(39) The image sensor **71**, the logic circuit board **72**, and the IMU **73** are integrated in, for example, a package. An optical member (such as a lens) (not illustrated) is installed on the light receiving surface side of the image sensor **71**. The optical member collects light from a subject and forms an image of the subject on the light receiving surface.

(40) The image sensor **71** photoelectrically converts the image (optical image) formed on the light receiving surface to acquire an electric signal. The image sensor **71** supplies the acquired image to a processing circuit of the logic circuit board **72**. The image acquired (captured) by the image sensor **71** may be a still image for one frame, or may be a moving image composed of continuous frames. In this specification, the latter case will be described as an example.

(41) The logic circuit board **72** includes a processing circuit that performs processing described later on images from the image sensor **71** and sensor data from the IMU **73**. The logic circuit board **72** includes a communication circuit that controls communication with an external device. The communication circuit exchanges various types of data with the communication device **63** through wireless communication conforming to the Wi-Fi (registered trademark) standard, for example. Note that exchange of various types of data between the measurement device **61** and the communication device **63** is not limited to a specific form.

(42) The IMU **73** detects the acceleration in the directions of three orthogonal axes and the angular velocity about the three orthogonal axes generated in the IMU **73** itself, and supplies them as sensor data to the processing circuit of the logic circuit board **72**. A three-dimensional coordinate system set in the IMU **73** is referred to as a local coordinate system. The acceleration in the directions of three orthogonal axes and the angular velocity about the three orthogonal axes are referred to as the 3-orthogonal-axis acceleration and the 3-orthogonal-axis angular velocity, respectively.

(43) (Communication Device **63**)

(44) The communication device **63** relays transmission of various types of data between the measurement device **61** and the information processing device **64**.

(45) The communication device **63** controls communication with the measurement device **61** (the communication circuit of the logic circuit board **72**) and communication with the information processing device **64**. The communication device **63** exchanges various types of data with the communication circuit of the measurement device **61** through, for example, wireless communication conforming to the Wi-Fi (registered trademark) standard. The communication device **63** exchanges various types of data with the information processing device **64** through, for example, wireless communication conforming to the Wi-Fi (registered trademark) standard. The communication device **63** transfers data

from the information processing device **64** or transfers data from the information processing device **64** to the measurement device **61**.

(46) Exchange of various types of data between the communication device **63** and the measurement device **61** and between the measurement device **61** and the information processing device **64** is not limited to a specific method. Direct communication between the measurement device **61** and the information processing device **64** may eliminate the need for the communication device **63**.

(47) (Information Processing Device **64**)

(48) The information processing device **64** acquires, via the communication device **63**, various types of data from the measurement devices **61** attached to the parts of the subject person whose motion is to be captured. The information processing device **64** highly accurately calculates pose data (pose information) representing the overall posture of the subject person based on the acquired various types of data. The information processing device **64** may be any device having an arithmetic processing function of, for example, a personal computer, a doublet terminal, a smart phone, a mobile terminal, or the like.

(49) <Functional Configuration of Measurement Device **61**>

(50) FIG. **5** is a block diagram illustrating a functional configuration of the measurement device **61** of FIG. **4**.

(51) The measurement device **61** includes the image sensor **71**, the IMU **73**, an image correction processing unit **81**, a feature point detection and tracking processing unit **82**, an IMU correction processing unit **83**, a self-position estimation processing unit **84**, an initialization processing unit **85**, a RAM **86**, and a data transmission and reception unit **87**. The image correction processing unit **81**, the feature point detection and tracking processing unit **82**, the IMU correction processing unit **83**, the self-position estimation processing unit **84**, the initialization processing unit **85**, the RAM **86**, and the data transmission and reception unit **87** are components implemented by the processing circuit of the logic circuit board **72** of FIG. **4**.

(52) The image sensor **71** performs photoelectric conversion on an image formed on the light receiving surface as illustrated in FIG. **4**, and supplies the resulting image to the image correction processing unit **81**.

(53) As illustrated in FIG. **4**, the IMU **73** detects the 3-orthogonal-axis acceleration and angular velocity generated in the IMU **73** itself, and supplies them as sensor data to the processing circuit of the logic circuit board **72**.

(54) The image correction processing unit **81** performs necessary processing, such as defect correction, noise reduction, and aberration correction, on the image from the image sensor **71**. When the measurement device **61** is used in, for example, an outdoor environment, automatic exposure control or automatic gain control may be performed to control the signal value of an image within a certain range so that the feature point detection and tracking processing unit **82** in the subsequent stage can appropriately perform feature point detection. In addition or instead, tone correction may be performed such as y correction.

(55) The image correction processing unit **81** supplies the processed image to the feature point detection and tracking processing unit **82**.

(56) The feature point detection and tracking processing unit **82** performs image recognition processing on the image from the image correction processing unit **81**. The image recognition processing detects the positions of feature points of a predetermined pattern on an image plane. A feature point may be an edge, a corner, or the like of an object. A two-dimensional coordinate system set on the image plane is referred to as an image coordinate system.

(57) The feature point detection and tracking processing unit **82** performs tracking processing for tracking the detected positions of the feature points from within the image on the image of the frame in which the feature points have been detected. The feature point detection and tracking processing unit **82** supplies the detected positions of the feature points to the self-position estimation processing unit **84**.

(58) The IMU correction processing unit **83** corrects the sensor data of acceleration and angular velocity from the IMU **73** to reduce bias components (including drift components) and noise components, which are included in the sensor data. The correction processing in the IMU correction processing unit **83** is not limited to specific processing. The IMU **73** may include a geomagnetic sensor, and the IMU correction processing unit **83** may correct the sensor data of acceleration and angular velocity from the IMU **73** by using sensor data from the geomagnetic sensor.

(59) The IMU correction processing unit **83** calculates the position, orientation, and velocity of the corresponding measurement device **61** based on the acceleration and angular velocity (corrected acceleration and angular velocity, hereinafter the same) from the IMU **73**.

(60) The IMU correction processing unit **83** supplies the acceleration and angular velocity from the IMU **73** and the position, orientation, and velocity calculated from the acceleration and angular velocity to the self-position estimation processing unit **84**. In other words, the IMU correction processing unit **83** supplies the position, orientation, velocity, acceleration, and angular velocity of the corresponding measurement device **61** to the self-position estimation processing unit **84**.

(61) Based on the positions of the feature points from the feature point detection and tracking processing unit **82** and the position, orientation, velocity, acceleration, and angular velocity of the corresponding measurement device **61** from the IMU correction processing unit **83**, the self-position estimation processing unit **84** estimates the position, orientation, and the like of the corresponding measurement device **61** in a world coordinate system. Self-position estimation processing for estimating the position and orientation of the measurement device **61** will be described later. The world

coordinate system is a three-dimensional coordinate system set in a three-dimensional space in which the subject person who wears the measurement device **61** is located.

(62) The self-position estimation processing unit **84** supplies data such as the estimated position and orientation of the corresponding measurement device **61** to the data transmission and reception unit **87**.

(63) The initialization processing unit **85** performs initialization processing based on data temporarily stored in the RAM **86** and the data from the self-position estimation processing unit **84**. In the initialization processing, an initial position, initial orientation, and the like of the measurement device **61** in the world coordinate system are calculated. Details of the initialization processing will be described later. The initialization processing unit **85** supplies data such as the calculated initial position, initial orientation, and the like of the measurement device **61** to the self-position estimation processing unit **84**.

(64) The RAM **86** temporarily stores data necessary for the initialization processing in the initialization processing unit **85** and the like.

(65) The data transmission and reception unit **87** controls communication with the communication device **63** of FIG. **4** to exchange various types of data with the information processing device **64** via the communication device **63**. The data transmission and reception unit **87** supplies various types of data such as the position, orientation, and the like from the self-position estimation processing unit **84** to the information processing device **64** via the communication device **63** of FIG. **4**.

(66) <Processing of Initializing Measurement Devices **61**>

(67) FIG. **6** is a diagram for explaining processing of initializing measurement devices **61**.

(68) In FIG. **6**, measurement devices **D0** to **D13**, which correspond to measurement devices **61**, are attached to parts of a subject person **101** whose motion is to be captured. The measurement devices **D0** to **D13** are attached to the neck, head, right shoulder, right elbow, right wrist, left shoulder, left elbow, left wrist, right waist, right knee, right ankle, left waist, left knee, and left ankle, respectively. Note that the parts and the number of measurement devices **61** to be attached to the subject person **101** are not limited to those illustrated in FIG. **6**.

(69) At the time of performing the initialization processing, the measurement devices **61** (**D0** to **D13**) attached to the parts of the subject person **101** capture an image of a chart **102** disposed at a predetermined position by their respective image sensors **71** (see FIGS. **4** and **5**) to acquire the image of the chart **102**.

(70) The chart **102** has, for example, a pattern in which a large number of grid points arranged vertically and horizontally at regular intervals are drawn on the surface of a rectangular panel. The interval of the grid points is known.

(71) The feature point detection and tracking processing unit **82** of each measurement device **61** detects the position of each grid point of the chart **102** in the image coordinate system (the position on the image plane) from the image acquired by the image sensor **71**, and supplies the detected position to the initialization processing unit **85** via the self-position estimation processing unit **84**.

(72) Based on the position of each grid point of the chart **102** from the feature point detection and tracking processing unit **82**, the initialization processing unit **85** calculates a relative orientation (including a relative position) of the corresponding measurement device **61** with respect to the chart **102** in the world coordinate system.

(73) For example, a predetermined point on the surface of the chart **102** is set as the origin of the world coordinate system, two of the three orthogonal axes of the world coordinate system are set in the vertical and horizontal directions of the surface of the chart **102**, and the other axis is set in the vertical direction perpendicular to the surface of the chart **102**. However, the three orthogonal axes of the world coordinate system and the chart **102** only need to have a certain relationship. Thus, the initialization processing unit **85** can identify the position and orientation of the corresponding measurement device **61** in the world coordinate system based on the relative orientation in the world coordinate system between the chart **102** and the corresponding measurement device **61**.

(74) Based on the positions of the grid points of the chart **102**, the interval of adjacent grid points, the gradient of grid points that connects grid points vertically and horizontally, and the like, which are from the feature point detection and tracking processing unit **82**, the initialization processing unit **85** calculates and identifies the position and orientation (initial position and initial orientation) of the corresponding measurement device **61** in the world coordinate system at the time when the chart **102** was captured.

(75) Data necessary for calculating the initial orientation and initial position are supplied from the information processing device **64** to each measurement device **61** and then stored in the RAM **86**, to be referred to by the initialization processing unit **85**.

(76) The self-position estimation processing unit **84** of each measurement device **61** starts the self-position estimation processing when the initial position and the initial orientation are identified by the initialization processing. In the self-position estimation processing, the self-position estimation processing unit **84** estimates the position and orientation of the corresponding measurement device **61** based on the acceleration and angular velocity detected by the IMU **73** and based on the image acquired by the image sensor **71**.

(77) The measurement devices **61** do not need to be subjected to the initialization processing at the same time. For example, when the subject person **101** changes his/her own position, orientation, or posture, the chart **102** is switched between the measurement devices **61** within the capture range in this way, the measurement devices **61** may be subjected to the initialization processing step by step instead of at the same time.

(78) When the self-position estimation processing unit **84** of the measurement device **61** that has been subjected to the initialization processing starts the self-position estimation processing, the position and orientation of the measurement device **61** estimated by the self-position estimation processing are transmitted to the information processing device **64**. (79) The information processing device **64** determines whether or not the processing of initializing each measurement device **61** has been completed depending on either whether or not the information processing device **64** has received data such as the position and orientation from the measurement device **61** or whether or not the information processing device **64** has received a notification from the measurement device **61** indicating that the processing of initializing the measurement device **61** has been completed.

(80) When the processing of initializing all the measurement devices **61** is completed, the information processing device **64** causes a display **64A** of the information processing device **64** of FIG. 6 to display a device layout image **103**. The device layout image **103** is a two-dimensional image that represents the positions (three-dimensional coordinates) in the world coordinate system supplied from the measurement devices **61**. As a result, positions PD0 to PD13 of the measurement devices D0 to D13 worn by the subject person **101** are displayed as the device layout image **103** on the display **64A**. The user refers to the device layout image **103** to set a connection relationship of the measurement devices D0 to D13 based on, for example, the human skeleton. Setting of the connection relationship of the measurement devices **61** will be described later.

(81) <Procedure of Initialization Processing>

(82) FIG. 7 is a flowchart illustrating an example of a procedure of the processing of initializing the measurement devices **61**.

(83) In FIG. 7, in step S11, the information processing device **64** (see FIG. 4) instructs each measurement device **61** to perform the initialization processing, and thus causes the image sensor **71** of the measurement device **61** to capture an image of the chart **102** so that, the feature point detection and tracking processing unit **82** recognizes the chart **102**. The processing proceeds from step S11 to step S12.

(84) In step S12, the initialization processing unit **85** of each measurement device **61** obtains a relative orientation of the measurement device **61** with respect to the chart **102** in the world coordinate system based on the chart **102** recognized in step S11. The processing proceeds from step S12 to step S13.

(85) In step S13, the initialization processing unit **85** of each measurement device **61** determines whether or not the relative orientation has successfully been obtained in step S12.

(86) If it is determined in step S13 that the relative orientation has not successfully been obtained, the processing is returned from step S13 to step S11, and is repeated from step S11.

(87) If it is determined in step S13 that the relative orientation has successfully been obtained, the processing proceeds to step S14, and then the self-position estimation processing unit **84** starts the self-position estimation processing. The processing proceeds from step S14 to step S15.

(88) In step S15, the information processing device **64** determines whether all the measurement devices **61** have been initialized.

(89) If it is determined in step S15 that not all measurement devices **61** have been initialized, the processing is returned from step S15 to step S11, and is repeated from step S11 for the measurement devices that are yet to be initialized.

(90) If it is determined in step S15 that all the measurement devices **61** have been initialized, the processing of initializing the devices ends.

(91) <Other Methods for Initializing Measurement Devices **61**>

(92) The processing of initializing the measurement devices **61** described above is an example, and it is not limited to the above-described method.

(93) As another method for processing of initializing the measurement devices **61**, a first method or a second method described below may be used.

(94) (First Method for Another Initialization Processing)

(95) In the first method for another processing of initializing the measurement devices **61**, a distance measurement device such as a time-of-flight (ToF) camera or a stereo camera is used to acquire an image of the chart **102** in advance. The position of the distance measurement device when the image was captured is also acquired. The position of the distance measurement device is a position in the world coordinate system set with reference to the chart **102** as in the above-described method for initialization. The image of the chart **102** acquired by the distance measurement device is supplied as a key frame from the information processing device **64** to each measurement device **61** and stored in the RAM **85**. Similarly, the position of the distance measurement device when the key frame was acquired is stored in the RAM **85**.

(96) The initialization processing unit **85** of each measurement device **61** compares the image from the image sensor **71** with the key frame image stored in the RAM **85** to obtain the degree of similarity between the images. As a result, when the degree of similarity reaches or exceeds a predetermined threshold value, the initialization processing unit **85** obtains a relative orientation of the image plane of the image from the image sensor **71** with respect to the image plane (perspective projection plane) of the key frame image in the world coordinate system (for example, A. Kasyanov, F. Engelmann, J. Stuckler, and B. Leibe. "Keyframe-Based Visual-Inertial Online SLAM with Relocalization," In IROS, 2017). The initialization processing unit **85** then identifies the initial orientation and initial position of the measurement

device **61** in the world coordinate system based on the obtained relative orientation and the position of the distance measurement device stored in the RAM **85**.

(97) The comparison (matching) between the image from the image sensor **71** and the key frame image may be performed not on the entire image but on feature points in the image. In this comparison, extracted features are transformed to feature descriptions, such as Scale-Invariant Feature Transform (SIFT) or Speeded Up Robust Features (SURF), to evaluate the features by matching them,

(98) (Second Method for Another Initialization Processing)

(99) In the second method for another processing of initializing the measurement devices **61** the initialization processing unit **85** acquires a pair of parallax images (movement parallax images) captured by an image sensor **71** at, two different positions when the position of a measurement devices **61** change. The initialization processing unit **85** detects the positions of image feature points, in the acquired pair of parallax images, corresponding to predetermined feature points of a subject (physical).

(100) Then, the initialization processing unit **85** uses the positions of the image feature points detected in the pair of parallax images and the amount of movement of the camera (image sensor **71**) to obtain three-dimensional coordinates of the feature points on the physical subject corresponding to the image feature points in the camera coordinate system with the origin being the camera in the manner of triangulation.

(101) FIG. **8** is a diagram illustrating an example of a correspondence relationship between a predetermined feature point of a subject and feature points on a pair of parallax images.

(102) A subject **120** in FIG. **8** is, for example, a cuboid object captured by the image sensor **71**, and image planes (perspective projection planes) **121** and **122** represent virtual image planes on which a pair of parallax images captured by the image sensor **71** at different positions is projected.

(103) Viewpoints (principal points) **121A** and **122A** represent the focal positions of lenses when the subject projected onto the image planes **121** and **122** was captured, respectively.

(104) It is assumed that images **120-1** and **120-2** of the subject **120** captured from the viewpoints **121A** and **122A** appear on the image planes **121** and **122**, respectively.

(105) It is also assumed that vertices of the subject **120** are set as feature points, and image feature points corresponding to the feature points of the subject **120** are detected.

(106) In this case, when the image sensor **71** is at the position of the viewpoint **121A**, an image feature point **120F-1** is detected at a position where a line segment connecting a feature point **120F** of the subject **120** and the viewpoint **121A** intersects the image plane **121**.

(107) Further, when the image sensor **71** is at the position of the viewpoint **122A**, an image feature point **120F-2** is detected at a position where a line segment connecting the feature point **120F** of the subject **120** and the viewpoint **122A** intersects the image plane **122**. The other vertices of the subject **120** are similarly detected as image feature points in the pair of parallax images.

(108) Assuming that the amount of parallax (the distance between the viewpoints **121A** and **122A**) is known, the three-dimensional coordinates of the subject in the camera coordinate system can be determined based on the positions of the image feature points detected in each of the image planes **121** and **122**, or using the principle of triangulation or the like. By redefining this camera coordinate system as a world coordinate system and registering the three-dimensional coordinates and camera image of this subject as a key frame, the position and orientation of the camera in the common world coordinate system can be obtained when the same subject is captured by another measurement device **61**. Accordingly, the position and orientation of the measurement device **61** in the world coordinate system can be identified. A three-dimensional structure (including the positions of the vertices, etc.) of the subject **120** in the world coordinate system can also be calculated.

(109) On the other hand, the amount of parallax can be detected using an existing method of monocular visual-inertial SLAM initialization processing. Specifically, the position of the measurement device **61** is estimated by integrating the IMU **73** (inertial measurement) of the measurement device **61** and visual simultaneous localization and mapping (SLAM) using the image sensor **71**. As a result, the bias included in the sensor data from the IMU **73** is corrected, and a moving distance is detected from the image with high accuracy, so that the amount of parallax can be detected with high accuracy (for example, Tong Qin, Peiliang Li, and Shaojie Shen, "VINS-Mono: A Robust and Versatile Monocular Visual-Inertial State Estimator," arXiv 2017, arXiv:1708.03852).

(110) When the processing of initializing the measurement devices **61** is performed, the feature point detection and tracking processing unit **82** detects the positions of feature points of a predetermined pattern in the image from the image sensor **71** and supplies the positions to the initialization processing unit **85**.

(111) When the positions of the feature points supplied from the feature point detection and tracking processing unit **82** are changed, the initialization processing unit **85** acquires the positions of the image feature points before and after the change in the pair of parallax images.

(112) Based on the sensor data from the IMU **73** and the image from the image sensor **71**, the initialization processing unit **85** (or the self-position estimation processing unit **84**) estimates the position of the measurement device **61** by integrating the IMU **73** (inertial measurement) and visual SLAM. As a result, the initialization processing unit **85** detects the amount of parallax, and identifies the initial position and initial orientation of the measurement device **61** in

the world coordinate system by the above-described processing.

(113) In the measurement device **61** that has been subjected to the initialization processing in this way, the image used in the initialization processing may be used as a key frame, and the key frame and the three-dimensional structure of the subject may be supplied to another measurement device **61**. As a result, the other measurement device **61** obtains a relative orientation of the image plane of the image from the image sensor **71** with respect to the image plane of the key frame image based on the three-dimensional structure of the subject, so that the initial position and initial orientation of the measurement device **61** can be identified.

(114) <Self-Position Estimation Processing>

(115) Next, processing after the processing of initializing the measurement devices **61** will be described.

(116) After the processing of initializing the measurement devices **61** is completed, the image from the image sensor **71** is supplied to the image correction processing unit **81**, and the acceleration and angular velocity output from the IMU **73** are supplied to the IMU correction processing unit **83**.

(117) (Processing in Image Correction Processing Unit **81** and Feature Point Detection and Tracking Processing Unit **82**)

(118) The image supplied to the image correction processing unit **81** is subjected to predetermined correction processing and then supplied to the feature point detection and tracking processing unit **82**.

(119) The feature point detection and tracking processing unit **82** detects feature points and tracks the feature points in the image from the image correction processing unit **81**.

(120) The feature points may be a pattern suitable for image matching in subsequent steps (pattern to facilitate identification).

(121) Any method such as the Harris algorithm can be used as a method of detecting the feature points.

(122) When detecting feature points in the image of a predetermined frame from the image correction processing unit **81**, the feature point detection and tracking processing unit **82** tracks the feature points in the subsequent frame images to determine the positions of the detected feature points appearing in the images.

(123) Any method such as a zero-mean normalized crosscorrelation (ZNCC) method or a Kanade-Lucas-Tomasi (KLT) method can be used as a method of tracking the feature points.

(124) In tracking of the feature points by the ZNCC method or the KLT method, a small image of, for example, 8×8 pixels including the image of a feature point is set as the small image to be tracked. Then, a small area most similar to the small image to be tracked is detected from among predetermined search areas in the frame image in which the feature point is to be tracked.

(125) The search areas may be limited to areas according to results of predicting the motion of the measurement device **61** using the sensor data from the IMU **73**.

(126) FIG. **9** is a diagram illustrating an example of how feature points are tracked.

(127) In FIG. **9**, images **151** and **152** are images from the image sensor **71** supplied to the feature point detection and tracking processing unit **82**. The image **152** is a frame image supplied after a predetermined time step with respect to the image **151**.

(128) In the image **151**, vertices of a subject **153** are detected as feature points **152A** to **152F**.

(129) In the image **152**, the position or the like of the subject **153** in the image **152** has changed due to a change in the position or orientation of the measurement device **61** as compared to the image **151** when captured.

(130) By tracking the feature points on the image **152** in the feature point detection and tracking processing unit **82**, the positions of the feature points **152A** to **152F** in the image **152** corresponding to the feature points **152A** to **152E** in the image **151** are detected. A feature point **152G** in the image **152** that has not been detected in the image **151** is newly detected.

(131) The positions of the image feature points detected by the feature point detection and tracking processing unit **82** are supplied as two-dimensional coordinates on the image plane (in the image coordinate system) from the feature point detection and tracking processing unit **82** to the self-position estimation processing unit **84**.

(132) In a case where the positions of the feature points on the physical subject corresponding to the image feature points can be detected as the positions (three-dimensional coordinates) in the world coordinate system, not only the positions (two-dimensional coordinates) of the image feature points but also the positions (three-dimensional coordinates) of the feature points on the physical subject may be supplied from the feature point detection and tracking processing unit **82** to the self-position estimation processing unit **84**.

(133) (Processing in IMU Correction Processing Unit **83**)

(134) The IMU correction processing unit **83** integrates the acceleration and angular velocity supplied from the IMU **73** in time series to calculate the position, orientation, and velocity of the corresponding measurement device **61** according to inertial navigation.

(135) In calculating the position and orientation of the corresponding measurement device **61**, the initial position and initial orientation of the measurement device **61** (IMU **73**) are obtained from the initialization processing unit **85**.

(136) The sensor data from the IMU **73** includes a measurement error called a bias. The bias is an offset, and as it is integrated, the error is gradually enhanced. In order to suppress this enhanced error, it is necessary to estimate and correct the bias value. In addition, the IMU **73** alone cannot detect the translational velocity and cannot distinguish

whether the subject is stationary or is translationally moving at a constant velocity, so that it is necessary to estimate the initial velocity. As such necessary information, an estimated value estimated by the self-position estimation processing unit **84** described later can be used.

(137) An acceleration and an angular velocity, which are observation values observed by the IMU **73** at a time t , are expressed by the following Equations (1) and (2). Variables $a_{\text{sub.t}}$ and $\omega_{\text{sub.t}}$ with a caret on the left side represent an acceleration and an angular velocity (both vectors) observed by the IMU **73**, respectively.

[Math. 1]

$$\hat{a}_{\text{sub.t}} = a_{\text{sub.t}} + b_{\text{sub.a}} + R_{\text{sub.w.sup.I.sup.tg.sup.w}} + n_{\text{sub.a}} \quad (1)$$

where $a_{\text{sub.t}}$ is a true acceleration, $b_{\text{sub.a}}$ is an acceleration bias, $R_{\text{sub.w.sup.I.sup.tg.sup.w}}$ is a transformation from world coordinates to local coordinates, $R_{\text{sub.w.sup.I.sup.tg.sup.w}}$ is the acceleration of gravity in local coordinate system, and n_a is an acceleration noise.

[Math. 2]

$$\{\text{circumflex over } (\omega)\}_{\text{sub.t}} = \omega_{\text{sub.t}} + b_{\text{sub.}\omega} + n_{\text{sub.}\omega} \quad (2)$$

where $\omega_{\text{sub.t}}$ is a true angular velocity, $b_{\text{sub.}\omega}$ is an angular velocity bias, and $n_{\text{sub.}\omega}$ is an angular velocity noise.

(138) According to inertial navigation using the observed values from the IMU **73**, the position, velocity, and orientation of the measurement device **61** are calculated by the following Equations (3) to (5), respectively.

[Math. 3]

$$(139) \quad p_{b_{k+1}}^w = p_{b_k}^w + v_{b_k}^w t_k + \int \int_{t \in [t_k, t_{k+1}]} (R_{l_t}^w (\hat{a}_t - b_{a_t} - n_a) - g^w) dt^2 \quad (3)$$

[Math. 4]

$$v_{b_{k+1}}^w = v_{b_k}^w + \int_{t \in [t_k, t_{k+1}]} (R_{l_t}^w (\hat{a}_t - b_{a_t} - n_a) - g^w) dt \quad (4)$$

[Math. 5]

$$q_{b_{k+1}}^w = q_{b_k}^w \cdot \text{Math.} \int_{t \in [t_k, t_{k+1}]} \frac{1}{2} (\hat{a}_t - b_{a_t} - n_a) q_t^{b_k} dt \quad (5)$$

where $q_{\text{sub.b.sub.k.sup.w}}$ is a quaternion, and $\cdot \text{Math.}$ is a quaternion product operator.

(140) Here, $\Omega(\omega)$ is represented by the following Equations (6) and (7).

[Math. 7]

[Math. 6]

$$(141) \quad \begin{pmatrix} 0 \\ -z \\ -y \end{pmatrix} = \begin{bmatrix} \text{ } & \text{ } & \text{ } \\ \text{ } & \text{ } & \text{ } \\ - & T & 0 \end{bmatrix}_x \quad (6) \quad \begin{bmatrix} \text{ } & \text{ } & \text{ } \\ \text{ } & \text{ } & \text{ } \\ - & y & x \end{bmatrix}_x = \begin{bmatrix} 0 & -z & y \\ z & 0 & -x \\ -y & x & 0 \end{bmatrix} \quad (7)$$

(142) In Equations (3) to (5), k represents a frame number given to the image frame acquired from the image sensor **71** in chronological order. In a case where the sensor data acquired from the IMU **73** is indicated by a data number in chronological order, $b_{\text{sub.k}}$ represents the data number when an image with frame number k was acquired.

(143) The acceleration bias and angular velocity bias (hereinafter also referred to as the biases of the IMU **73**) included in the sensor data from the IMU **73** and the initial velocity of the measurement device are estimated by the self-position estimation processing unit **84** and supplied to the IMU correction processing unit **83**.

(144) The position, velocity, and orientation of the corresponding measurement device **61** calculated by Equations (3) to (5) are supplied to the self-position estimation processing unit **84**. The position and velocity are three-dimensional vectors, and the orientation is a quaternion (four-dimensional vector).

(145) (Processing in Self-Position Estimation Processing Unit **84**)

(146) The self-position estimation processing unit **84** estimates the biases of the IMU **73** and the initial velocity of the measurement device **61** by optimization processing to be iterated or filtering processing based on a Kalman filter.

(147) In either processing, the biases of the IMU **73** and the initial velocity of the measurement device are estimated and also the position and orientation of the measurement device **61** are corrected so that the error in a reprojected image is reduced, so that a difference is reduced between the position and orientation of the measurement device **61** estimated using only the IMU **73** and the position and orientation of the measurement device **61** estimated through the processing in the self-position estimation processing unit **84**, and so that the variation in the biases of the IMU **73** is minimized.

(148) The processing of correcting the position and orientation of the measurement device **61** is referred to as self-position estimation processing.

(149) As methods of self-position estimation processing, specifically, there are known a method in which the IMU **73** (inertial measurement) of the measurement device **61** and visual simultaneous localization and mapping (SLAM) using the image sensor **71** are integrated (for example, Qin, T., Li, P.; Shen, S., "VINS-Mono: A Robust and Versatile Monocular Visual-Inertial State Estimator," arXiv 2017, arXiv:1708.03852) and a method based on the following Kalman filter (for example, P. Geneva, K. Eickenhoff, W. Lee, Y. Yang, and G. Huang, "OpenVINS: A Research Platform for Visual-Inertial Estimation," IROS Workshop on Visual-Inertial Navigation: Challenges and Applications, 2019).

(150) In the present embodiment, only the outline of a case based on the latter method (multi-state constraint Kalman

filter (MSCKF) method) with less processing load will be described.

(151) In the self-position estimation processing unit **84**, a state to be estimated (state variable) is represented by $x_{\text{sub}.k}$. The state variable $x_{\text{sub}.k}$ is represented by the following Equation (8).

[Math. 8]

$$x_{\text{sub}.k} = [x_{\text{sub}.I.\text{sup}.T}, x_{\text{sub}.C.\text{sup}.T}, x_{\text{sub}.W.\text{sup}.T}] \quad (8)$$

(152) Here, $x_{\text{sub}.I}$, $x_{\text{sub}.C}$, and $x_{\text{sub}.W}$ are represented by the following Equations (9) to (11).

[Math. 9]

$$x_{\text{sub}.I} = [(q_{\text{sub}.I.\text{sub}.k.\text{sup}.W}.\text{sup}.T, (p_{\text{sub}.I.\text{sub}.k.\text{sup}.W}.\text{sup}.T, (v_{\text{sub}.I.\text{sub}.k.\text{sup}.W}.\text{sup}.T, (b_{\text{sub}.\omega.\text{sub}.k}.\text{sup}.T, (b_{\text{sub}.a.\text{sub}.k}.\text{sup}.T)] \quad (9)$$

[Math. 10]

$$x_{\text{sub}.C} = [(q_{\text{sub}.I.\text{sub}.k-1.\text{sup}.W}.\text{sup}.T, (p_{\text{sub}.I.\text{sub}.k-1.\text{sup}.W}.\text{sup}.T, \dots (q_{\text{sub}.I.\text{sub}.k-c.\text{sup}.W}.\text{sup}.T, (p_{\text{sub}.I.\text{sub}.k-c.\text{sup}.W}.\text{sup}.T)] \quad (10)$$

[Math. 11]

$$x_{\text{sub}.W} = [(q_{\text{sub}.I.\text{sup}.C}.\text{sup}.T, (p_{\text{sub}.I.\text{sup}.c}.\text{sup}.T)] \quad (11)$$

(153) Here, the state variable $x_{\text{sub}.I}$ represents an orientation q , a position p , a velocity v , an angular velocity bias b_{ω} , and an acceleration bias $b_{\text{sub}.a}$ of the IMU **73**. The orientation q is a quaternion, and the position p , velocity v , angular velocity bias $b_{\text{sub}.\omega}$, and acceleration bias $b_{\text{sub}.a}$ are each a three-dimensional vector.

(154) The state variable $x_{\text{sub}.C}$ represents the history of the past orientation q and position p of the corresponding measurement device **61**.

(155) Besides, k represents a time step (number) at which the image of a k -th frame is acquired from the image sensor **71**.

(156) An error covariance of the system based on the Kalman filter (analysis error covariance) is represented by the following Equation (12).

[Math. 12]

$$P_{\text{sub}.k|k-1} = \Phi_{\text{sub}.k-1} P_{\text{sub}.k-1|k-1} \Phi_{\text{sub}.k-1}^{\text{sup}.T} + Q_{\text{sub}.k-1} \quad (12)$$

where $\Phi_{\text{sub}.k-1}$ is a propagation matrix for the system, and $Q_{\text{sub}.k-1}$ is a covariance of system noise.

(157) The subscript $k|k-1$ indicates a predicted value of the state variable at time step k predicted from the value at time step $k-1$.

(158) The Kalman gain K is represented by the following Equation (13).

[Math. 13]

$$K_{\text{sub}.k} = P_{\text{sub}.k|k-1} H_{\text{sub}.k}^{\text{sup}.T} (H_{\text{sub}.k} P_{\text{sub}.k|k-1} H_{\text{sub}.k}^{\text{sup}.T} + R_{\text{sub}.m,k})^{-1} \quad (13)$$

(159) Meanwhile, an estimated value of the state variable is calculated by the following Equation (14).

[Math. 14]

$$\{\text{circumflex over } (x)\}_{\text{sub}.k|k} = \{\text{circumflex over } (x)\}_{\text{sub}.k|k-1} + K_{\text{sub}.k} (z_{\text{sub}.m,k} - h(\{\text{circumflex over } (x)\}_{\text{sub}.k|k-1})) \quad (14)$$

(160) The first term on the right side is a predicted value of the state variable at time step k calculated based on a propagation formula for the IMU **73** using a propagation matrix Φ_{k-1} for the system, and also represents a predicted value of the state variable at time step k predicted from the value at time step $k-1$.

(161) Besides, $z_{m,k}$ represents the position of an image feature point detected from the image at time step k (position in the image coordinate system). Also, $z_{m,k}$ is an observed value given from the feature point detection and tracking processing unit **82** to the self-position estimation processing unit **84**.

(162) It is assumed that the positions of the feature points, in the world coordinate system, on the subject (feature points on the physical subject) corresponding to the detected image feature points are determined. It is also assumed that the predicted value of the state variable at time step k is applied as the current (time step k) position and orientation of the measurement device **61**. In this case, the position of the image feature point corresponding to a feature point on the physical subject is estimated based on the predicted value of the position and orientation of the measurement device **61** at time k .

(163) In Equation (14), the estimated position (two-dimensional coordinates) of the image feature point is the value of $h(x)$ (as simply expressed) in parentheses in the second term on the right side. Then, in Equation. (14), a reprojection error, which is a difference between the value of $h(x)$ and $z_{m,k}$, is obtained, and the state variable is updated with the reprojection error weighted with the Kalman gain K . As a result, an estimated value of the state variable is calculated such that the reprojection error is closer to zero.

(164) The Kalman gain K at time step k in Equation (13) is calculated based on an error covariance P of the system at time step k predicted from the value at time step $k-1$ (analysis error covariance P) and based on an error covariance R observed at time step k (observation error covariance R). Specifically, the Kalman gain K at time step k is updated such that, of the predicted value of the state variable at time step k predicted from the value at time step $k-1$ and the observed value observed at time k , the one with higher reliability is given a higher weight (such that the smaller the error covariance, the higher the weight).

(165) The error covariance P of the system at time step k is updated by the following Equation (15).

[Math. 15]

$$P_{\text{sub.k}}|k = P_{\text{sub.k}}|k-1 - K_{\text{sub.k}}H_{\text{sub.k}}P_{\text{sub.k}}|k-1 \quad (15)$$

(166) According to the multi-state constraint Kalman filter (MSCKF) method, not only the current state variable value of the measurement device **61** (IMU **73**) but also the past state variable values are simultaneously updated by the Kalman filter. As a result, the value of the state variable such as the position and orientation of the measurement device **61** is estimated with high accuracy such that it is consistent with the past values.

(167) The self-position estimation processing unit **84** transmits the estimated value of the state variable estimated as described above from the data transmission and reception unit **87** (see FIG. 5) to the information processing device **64** via the communication device **63** (see FIG. 4).

(168) Specifically, the self-position estimation processing unit **84** transmits the estimated value of the current (latest) position and orientation of the corresponding measurement device **61** as position and orientation data to the information processing device **64**.

(169) The self-position estimation processing unit **84** transmits to the information processing device **64** the feature point data related to two-dimensional coordinates and three-dimensional coordinates of the feature points in each frame, which are tracked over multiple frames from the feature point detection and tracking processing unit **82** used to estimate the state variable, and the error covariance data related to the error covariance P of the system calculated by Equation (15).

(170) The self-position estimation processing unit **84** provides the estimated values of the acceleration bias and angular velocity bias of the IMU **7** (biases of the IMU **73**); and the velocity of the measurement device **61**, which are included in the estimated state variable, to the IMU correction processing unit **83**. The IMU correction processing unit **83** uses the estimated values supplied from the self-position estimation processing unit **84** to calculate the position, velocity, and orientation of the corresponding measurement device **61** by using Equations (3) to (5).

(171) <Functional Configuration of Information Processing Device **64**>

(172) FIG. 10 is a block diagram illustrating an example of a functional configuration of the information processing device **64** of FIG. 4.

(173) In FIG. 10, the information processing device **64** includes a posture estimation unit **171**. The posture estimation unit **171** acquires the position and posture data, feature point data, and error covariance data from each of the measurement devices **61** attached to the parts of the subject person **101**.

(174) The posture estimation unit **171** sets a connection relationship of the measurement devices **61**.

(175) Then, the posture estimation unit **171** corrects (updates) the position and orientation (estimated value) supplied from each measurement devices **61** based on the data supplied from each measurement device **61** and the connection relationship of the measurement devices **61**, and outputs to another processing unit the resulting positions and orientations as pose data that represents the overall posture of the subject person. The pose data output from the posture estimation unit **171** may be used for any processing, and is not limited to being used for specific processing.

(176) The posture estimation unit **171** corrects the position and orientation from each measurement device **61** in consideration of the connection relationship of the measurement devices **61**, so that the posture (or motion) of the subject person can be detected with high accuracy.

(177) The posture estimation unit **171** includes a data transmission and reception unit **181**, a device connection relationship determination unit **182**, and a pose correction processing unit **183**.

(178) The data transmission and reception unit **181** controls communication with the communication device **63** of FIG. 4 to exchange various types of data with each measurement device **61** via the communication device **63**. The data transmission and reception unit **181** acquires the position and orientation data, feature point data, and error covariance data, which have been transmitted from the self-position estimation processing unit **84** of each measurement device **61**.

(179) The data transmission and reception unit **181** supplies the data acquired from each measurement device **61** to the device connection relationship determination unit **182** and the pose correction processing unit **183**.

(180) The device connection relationship determination unit **182** (connection relationship setting unit) sets a connection relationship of the measurement devices **61** based on the position and orientation (estimated value) of each measurement device **61**, which is the position and orientation data from each measurement device **61**. The device connection relationship determination unit **182** supplies the set connection relationship to the pose correction processing unit **183**.

(181) The pose correction processing unit **183** corrects (updates) the position and orientation of each measurement device **61** based on the data from each measurement device **61** and the connection relationship of the measurement devices **61** from the device connection relationship determination unit **182**. The pose correction processing unit **183** outputs to another processing unit or the like the corrected positions and orientations of the measurement devices **61** as pose data that represents the overall posture of the subject person **101**. The pose correction processing unit **183** transmits to each measurement device **61** via the data transmission and reception unit **181** the corresponding corrected position and orientation.

(182) In the self-position estimation processing unit **84** of each measurement device **61**, the estimated value estimated as the position and orientation of the measurement device **61** are changed to the corrected position and orientation supplied from the pose correction processing unit **183**. As a result, a predicted value of the state variable at the next time step is calculated using the corrected position and orientation values supplied from the pose correction processing unit **183**.

(183) (Processing in Device Connection Relationship Determination Unit 182)

(184) The device connection relationship determination unit **182** performs processing of setting a connection relationship of the measurement devices **61** as initial setting.

(185) For example, when the initialization processing is completed for all the measurement devices **61** in the processing of initializing the measurement devices **61** and then the self-position estimation processing is started, the device connection relationship determination unit **182** causes the display **64A** of the information processing device **64** illustrated in FIG. **6** to display the device layout image **103** based on the positions of the measurement devices **61** supplied from the measurement devices **61**.

(186) The device layout image **103** of FIG. **6** represents a case where the measurement devices **D0** to **D13** as the measurement devices **61** are attached to the parts of the subject person **101**. In this case, the positions **PD0** to **PD13** of the measurement devices **D0** to **D13** in the world coordinate system are displayed two-dimensionally in the device layout image **103**.

(187) The user refers to the device layout image **103** to set a connection relationship of the measurement devices **D0** to **D13** based on, for example, the skeletons.

(188) Among combinations of any two measurement devices **61** out of the measurement devices **D0** to **D13**, a combination in which no other measurement device is attached to a part along the skeleton between two measurement devices **61** is referred to as two measurement devices **61** having an adjacency relationship or two adjacent measurement devices **61**. Further, among the combinations of two measurement devices **61** having such an adjacency relationship, a combination in which the distance between two measurement devices **61** is substantially constant even if the posture of the subject person **101** changes (a change in the distance is equal to or less than a predetermined threshold value) is referred to as two measurement devices **61** having a narrowly defined adjacency relationship.

(189) The user sets a measurement device **61** (**D0**) at any position (for example, the position **PD0**) as a start point, and selects measurement devices **61** (**D1**, **D2**, and **D5**) having an adjacency relationship with the measurement device **61** (**D0**) by, for example, clicking their positions (positions **PD1**, **PD2**, and **PD5**) on the screen of the device layout image **103**. Then, the user selects measurement devices **61** having an adjacency relationship (no for **D1**, **D3** for **D2**, and **D6** for **D5**) with each of the measurement devices **61** (**D1**, **D2**, and **D5**) selected as having an adjacency relationship with the measurement device **61** (**D0**) as the start point. The user repeats such selection to set a connection relationship of all the measurement devices **61** (**D0** to **D13**) worn by the subject person **101**.

(190) The user may select only a combination of two measurement devices **61** having a narrowly defined adjacency relationship. Normally, two measurement devices **61** having an adjacency relationship are expected to be attached to the subject person **101** so that they have a narrowly defined adjacency relationship. Accordingly, in the following description, it is assumed that the two measurement devices **61** having an adjacency relationship have a narrowly defined adjacency relationship.

(191) The setting of a connection relationship of the measurement devices **61** may be automatically performed by the information processing device **64** instead of being based on a user's selection. For example, if the skeleton of the subject person **101** is regarded as a general human skeleton, it is possible to estimate which part of the subject person **101** each measurement device **61** is attached to and automatically set a connection relationship of the measurement devices **61**. Only two measurement devices **61** having a narrowly defined adjacency relationship may be automatically set as having an adjacency relationship.

(192) When the connection relationship of the measurement devices **61** is set based on a user's selection and the like, the device connection relationship determination unit **182** of FIG. **10** connects the positions of the measurement devices **61** having an adjacency relationship with a straight line (referred to as a connection line).

(193) FIG. **11** is a diagram illustrating an example of a connection relationship image representing a connection relationship of the measurement devices **61**.

(194) The connection relationship image **201** in FIG. **11** corresponds to an example of attaching the measurement device **61** of FIG. **6**, and the positions **PD0** to **PD13** of the measurement devices **D0** to **D13** illustrated in FIG. **6** appear in the connection relationship image **201**.

(195) On the other hand, the positions of the measurement devices **61** having an adjacency relationship are connected by straight connection lines **B1** to **B13** based on the connection relationship set by a user's selection or the like. These connection lines **B1** to **B13** represent the skeleton of the subject person **101**. The device connection relationship determination unit **182** displays the connection relationship image **201** on the display of the information processing device **64** to allow the user to confirm whether the connection relationship is correctly set and to present which part of the subject person **101** each of the measurement devices **D0** to **D13** is attached to.

(196) (Processing Procedure for Setting Device Connection Relationship)

(197) FIG. **12** is a flowchart illustrating an example of a procedure for setting the connection relationship of the measurement devices **61**.

(198) In FIG. **12**, in step **S31**, the device connection relationship determination unit **182** recognizes the presence of each measurement device **61** by receiving position and orientation data from the measurement device **61**, for example. Then, the device connection relationship determination unit **182** connects the measurement devices **61** by connection lines based on the adjacency relationship of the measurement devices **61** selected by the user. The processing proceeds from

step S31 to step S32.

(199) In step S32, the device connection relationship determination unit **182** determines whether or not all the measurement devices **61** have been connected to any other measurement device **61**.

(200) If it is determined in step S32 that not all the measurement devices **61** have been connected to any other measurement device **61**, the processing is returned to step S31 to repeat steps S31 and S32.

(201) If it is determined in step S32 that all the measurement devices **61** have been connected to any other measurement device **61**, the processing of this flowchart ends.

(202) (Processing in Pose Correction Processing Unit **183**)

(203) Based on the data from each measurement device **61**, the pose correction processing unit **183** first sets, of all the measurement devices **61**, measurement devices **61** for which the estimated values of the positions and orientations (hereinafter simply referred to as positions and orientations) supplied from the measurement devices **61** are to be corrected (updated).

(204) Specifically, a measurement device **61** for which the error covariance of the system supplied from the measurement device **61** is equal to or greater than a predetermined threshold value, or a measurement device **61** in which the number of feature points supplied from the measurement device **61** is equal to or less than a predetermined threshold value, is set as an unreliable measurement device **61** to be updated.

(205) In addition, if the distance between two measurement devices **61** having an adjacency relationship is equal to or greater than a predetermined threshold value, the measurement device **61** with the higher error covariance of the two measurement devices **61** is set to be updated. The threshold value for that distance may be a value obtained by adding a predetermined distance to a past distance, used as a reference, between two measurement devices **61** having an adjacency relationship.

(206) If the position and orientation are represented by one multidimensional vector (referred to as a position and orientation vector), the distance between two measurement devices **61** corresponds to the norm of the difference between the position and orientation vectors supplied from the two measurement devices **61** (size of difference in position and orientation). The term “distance” or “norm” as used herein may be a distance involving only the position, a norm involving only the orientation, or a norm involving both the position and orientation. The term “position and orientation vector” as used herein may be a vector representing the position and orientation, a position vector representing only the position, or an orientation vector (quaternion) representing only the orientation.

(207) One or two of the above three conditions may be set as conditions for update.

(208) FIG. **13** is a diagram illustrating an example of measurement devices to be updated in the connection relationship image of FIG. **11**.

(209) In FIG. **13**, the measurement devices D3, D4, D5, D10, and D13 (see FIG. **6**) attached at the positions PD4, PD4, PD5, PD10, and PD13 indicated by white circles are set to be updated. In the following description, the example of FIG. **13** will be referred to as appropriate.

(210) When the measurement devices **61** to be updated are set, the pose correction processing unit **183** then focuses on measurement devices **61** to be updated that are each led to any one of the measurement devices **61** not to be updated via only one connection line. Of the measurement devices D3, D4, D5, D10, and D13 to be updated in FIG. **13**, the measurement devices D3, D5, D10, and D13 have a single connection line B3, B5 (or B6 or B11), B10, and B13 leading to the measurement devices D2, D0 (or D6 or D11) D9, and D12 not to be updated, respectively. Accordingly, the pose correction processing unit **183** focuses on the measurement devices D3, D4, D5, D10, and D13 to be updated, other than the measurement device D4.

(211) Subsequently, for each of the measurement devices **61** to be updated of interest, the pose correction processing unit **183** updates (corrects) the position and orientation (position and orientation vector) of the measurement device **61** supplied as the position and orientation data from the measurement device **61** to a value that satisfies the following Conditional Expression (16). Specifically, the estimated value of the position and orientation of the measurement device **61** of interest is corrected so that the value in the curly brackets of Expression (16) is minimized. The value of the position and orientation of the measurement device **61** after the correction (update) is referred to as the updated value.

(212)

[Math . 16]

$$\min_{p_j, q_j} \{W_b (e_B)^2 + w_c (e_C)^2 + w_r (e_R)^2\} \quad (16)$$

(213) In Expression (16), e.sub.B represents a difference between the estimated value of the position and orientation (position and orientation vector) supplied as the position and orientation data from the measurement device **61** of interest and the updated value of the updated position and orientation (position and orientation vector). The first term in the curly brackets of Expression (16) indicates a value obtained by multiplying the square of the norm of e.sub.B by a weight w.sub.b. The weight w.sub.b is set to a larger value as the error covariance supplied as the error covariance data from the measurement device **61** of interest is smaller, for example. This ensures that the updated value of the position and orientation do not change too much from the estimated value.

(214) Besides, e.sub.C represents a difference (reprojection error) between the position of a feature point supplied as feature point data from the measurement device **61** of interest and the position of the feature point calculated from the

updated value of the position and orientation of the measurement device **61** of interest. The second term in the curly brackets of Expression (16) indicates a value obtained by multiplying a weight $w_{sub.c}$ by a value obtained by adding up the square of the norm of $e_{sub.C}$ for all the feature points. As the weight $w_{sub.c}$, for example, the variance of the reprojection error can be used. This makes it possible to normalize and add up $e_{sub.B}$ and $e_{sub.C}$.

(215) Besides, $e_{sub.R}$ represents a change in distance (norm), with respect to past distance (for example, last updated), between the position and orientation of the measurement device **61** of interest (position and orientation vector representing the updated value) and the position and orientation (position and orientation vector of the estimated value) of a measurement device **61** not to be updated to which the measurement device **61** of interest is connected by a single connection line. The past distance (norm) to be referred to is not limited to the last updated distance, but may be any value based on a past norm, and the same value set and detected at initialization may be reused. Calculation of $e_{sub.R}$ is represented by Equation (17).

[Math. 17]

$$e_{sub.R} = |p_{sub.j.sub.k} - p_{sub.n.sub.k}| - |p_{sub.j.sub.k-1} - p_{sub.n.sub.k-1}| \quad (17)$$

(216) Here, j represents the number of the measurement device **61** of interest, and k represents the k -th time step; n represents the number of a measurement device **61** not to be updated that is connected to the measurement device **61** of interest by a single connection line, that is, adjacent to the measurement device **61** of interest; and a capital letter P represents the updated position and orientation (position and orientation vector) of the measurement device **61** of interest, and a small letter p represents the position and orientation (position and orientation vector) of the measurement device **61** not to be updated of the number n .

(217) The third term in the curly brackets of Expression (16) indicates a value obtained by multiplying a weight $w_{sub.r}$ by a value obtained by adding up the square of the norm of $e_{sub.R}$ for all the measurement devices not to be updated.

(218) For the position and orientation of the measurement device **61** of interest, the pose correction processing unit **183** obtains the position and orientation as an updated value such that the value in the curly brackets of Expression (16) is minimized.

(219) However, the IMU **73** has observability in the direction of gravity, but does not have observability in the direction (yaw) on a plane perpendicular to the direction of gravity. Therefore, for the position and orientation vector, the quaternion indicating the orientation is decomposed into (Ψ, ϕ, θ) (Ψ is yaw, ϕ is pitch, θ is roll) as the corresponding orientation, and (ϕ, θ) are fixed, to calculate an optimal updated value.

(220) Instead of Expression (16), an expression excluding any one of the first to third terms in the curly brackets of Expression (16), or an expression with only the second or third term may be used to calculate the updated value.

(221) Subsequently, the pose correction processing unit **183** focuses on measurement devices **61** to be updated that are each led to any one of the measurement devices **61** not to be updated via two connection lines. In FIG. **13**, of the measurement devices to be updated **D3**, **D4**, **D5**, **D10**, and **D13**, the measurement device **D4** is led to the measurement device **D2** not to be updated via two connection lines **B3** and **B4**. Accordingly, the pose correction processing unit **183** focuses on the measurement device **D4** of the measurement devices **D3**, **D4**, **D5**, **D10**, and **D13** to be updated. For the updated measurement devices **D3**, **D5**, **D10**, and **D13**, their positions and orientations may be used as updated values, and they may be treated as non-updated measurement devices **61** that are not to be updated.

(222) Likewise for each of the measurement devices **61** to be updated newly focused on, the pose correction processing unit **183** updates (corrects) the position and orientation (position and orientation vector) of the measurement device **61** supplied as the position and orientation data from the measurement device **61** to a value that satisfies Expression (16). In the calculation based on Expression (16), the pose correction processing unit **183** uses the value of the position and orientation of a measurement device **61** to be updated that is led to the measurement device **61** of interest via a single connection line. As the position and orientation to be used at that time, the pose correction processing unit **183** uses the already-obtained updated value.

(223) As described above, the pose correction processing unit **183** calculates the update value of the position and orientation in order from the measurement device to be updated that is led to the measurement device **61** not to be updated via the smallest number of connection lines, among all the measurement devices to be updated.

(224) Then, the pose correction processing unit **183** corrects the positions and orientations of the measurement devices **61** to be updated of the positions and orientations supplied from the measurement devices **61** to the updated values, thereby generating pose data that represents the overall posture of the subject person **101**. The pose correction processing unit **183** supplies the generated pose data to another processing unit and each measurement device **61**.

(225) <Procedure for Processing of Correcting (Updating) Positions and Orientations of Measurement Devices>

(226) FIG. **14** is a flowchart illustrating an example of a procedure of processing of correcting positions and orientations of the measurement devices **61**, performed by the pose correction processing unit **183**.

(227) In FIG. **14**, in step **S51**, the pose correction processing unit **183** sets, of the measurement devices **61** worn by the subject person, the measurement devices **61** to be updated for which the positions and orientations supplied from the measurement devices **61** are to be corrected (updated).

(228) The pose correction processing unit **183** sets, as the measurement devices **61** to be updated, a measurement device **61** for which the error covariance is equal to or greater than a predetermined threshold value, a measurement device **61** in which the number of feature points is equal to or less than a predetermined threshold value, or if the distance between

two measurement devices **61** having an adjacency relationship is equal to or greater than a predetermined threshold value, the measurement device **61** with the higher error covariance of the two measurement devices **61**. The processing proceeds from step **S51** to step **S52**. There may be a case where there is no measurement device to be updated, and in that case, the processing proceeds to step **S57** without performing the update.

(229) In step **S52**, a parameter **n** is set to 1. The processing proceeds from step **S52** to step **S53**.

(230) In step **S53**, the pose correction processing unit **183** updates, of the measurement devices to be updated, a measurement device to be updated that is led to any one of the measurement devices not to be updated via **n** connection lines, based on Equation (16). The processing proceeds from step **S53** to step **S54**, if there is no measurement device to be updated having **n** connection lines, the processing skips steps **S53** and **S54** and then proceeds to step **S55**.

(231) In step **S54**, the pose correction processing unit **183** determines whether or not the positions and orientations of all the measurement devices to be updated that are each led to any one of the measurement devices not to be updated via **n** connection lines have been updated.

(232) If it is determined in step **S54** that the positions and orientations of all measurement devices to be updated that is led to any one of the measurement devices not to be updated via **n** connection lines has not been updated, the processing is returned to step **S53** and is repeated from step **S53**.

(233) If it is determined in step **S54** that the positions and orientations of all the measurement devices to be updated that are each led to any one of the measurement devices not to be updated via **n** connection lines have been updated, the processing proceeds from step **S54** to step **S55**.

(234) In step **S55**, the pose correction processing unit **183** determines whether or not the positions and orientations of all the measurement devices to be updated have been updated.

(235) If it is determined in step **S55** that the position and orientation of a measurement device to be updated that is led to any one of the measurement devices not to be updated via **n** connection lines has not been updated, the processing proceeds from step **S55** to step **S56**, and then the parameter **n** is incremented. The processing is returned from step **S56** to step **S53** and is repeated from step **S53**.

(236) If it is determined in step **S55** that the positions and orientations of all the measurement devices to be updated have been updated, the processing proceeds to step **S57**.

(237) In step **S57**, the pose correction processing unit **183** sets the positions and orientations of the measurement devices **61** not to be updated as the estimated values of the positions and orientations supplied from the measurement devices **61**, and sets the positions and orientations of the measurement devices **61** to be updated as the updated values updated in step **S53**. Then, the pose correction processing unit **183** outputs to another processing unit the positions and orientations of all the measurement devices **61** as pose data that represents the posture of the subject person. After step **S57**, the processing is returned to step **S51**, and is repeated from step **S51** each time new data is supplied from each measurement device **61**.

(238) As described above, according to the motion capture system **51** to which the present technology is applied, it is possible to construct an environment-independent motion capture system without the need to prepare an external environment such as a camera. Specifically, no external camera to be needed makes it possible to reduce restrictions and problems such as a restriction on the movable range due to camera placement and loss of motion data due to occlusion. In addition, it is easy to carry, so that motion capture can be performed in a relatively free location.

(239) Moreover, the user is allowed to freely set the positional relationship of the joints, resulting in easy maintenance.

(240) Each measurement device **61** is required only to exchange data with the information processing device **64**, so that there is no need to transmit and receive data between the measurement devices **61**. Accordingly, even if the number of parts to be estimated increases, it is possible to estimate the position and the like of each measurement device **61** with high accuracy without affecting the amount of calculation processing in the measurement device **61**.

(241) Moreover, when the power consumption is severe, it is also possible to operate only the IMU **73** partially, which has the effect of reducing the power consumption of the entire system.

(242) Furthermore, the position and orientation detected by each measurement device **61** are corrected in consideration of the connection relationship with other measurement devices **61**, and thus, the position and orientation of each measurement device **61** is corrected with high accuracy against reduced accuracy due to the bias (drift) of the IMU, so that the detection accuracy of the posture of the subject person (measurement target) is improved.

(243) <Program>

(244) The above-described image correction processing unit **81**, feature point detection and tracking processing unit **82**, IMU correction processing unit **83**, self-position estimation processing unit **84**, and initialization processing unit **85**, which are included in the measurement device **61**, and part or all of the above-described series of processing in the information processing device **64** can be implemented by hardware or by software. In a case in which the series of processing is performed by software, a program including the software is installed in a computer. Here, the computer includes a computer embedded in dedicated hardware or, for example, a general-purpose computer capable of executing various functions by installing various programs.

(245) FIG. **15** is a block diagram showing a configuration example of hardware of a computer that executes the above-described series of processing according to a program.

(246) In the computer, a central processing unit (CPU) **401**, a read-only memory (ROM) **402**, and a random access

memory (RAM) **403** are connected to each other by a bus **404**.

(247) An input/output interface **405** is further connected to the bus **404**. An input unit **406**, an output unit **407**, a storage unit **408**, a communication unit **409**, and a drive **410** are connected to the input/output interface **405**.

(248) The input unit **406** is constituted by a keyboard, a mouse, a microphone, or the like. The output unit **407** is constituted of a display, a speaker, or the like. The storage unit **408** is a hard disk, non-volatile memory, or the like. The communication unit **409** is a network interface or the like. The drive **410** drives a removable medium **411** such as a magnetic disk, an optical disc, a magneto-optical disk, or a semiconductor memory.

(249) In the computer configured as described above, for example, the CPU **401** loads a program stored in the storage unit **408** into the RAM **403** via the input/output interface **405** and the bus **404** and executes the program to perform the above-described series of processing.

(250) The program executed by the computer (the CPU **401**) can be recorded on, for example, the removable medium **411** serving as a package medium for supply. The program can be supplied via a wired or wireless transmission medium such as a local area network, the Internet, or digital satellite broadcasting.

(251) In the computer, by mounting the removable medium **411** on the drive **410**, it is possible to install the program in the storage unit **408** via the input/output interface **405**. The program can be received by the communication unit **409** via a wired or wireless transfer medium and can be installed in the storage unit **408**. In addition, this program may be installed in advance in the ROM **402** or the storage unit **408**.

(252) Note that the program executed by a computer may be a program that performs processing chronologically in the order described in the present specification or may be a program that performs processing in parallel or at a necessary timing such as a called time.

(253) The present technique can be also configured as follows: (1) An information processing device including a posture estimation unit that estimates a posture of a measurement; target based on a position and orientation of each of a plurality of measurement devices arranged at a plurality of parts of the measurement target and based on a connection relationship between the measurement devices that is set based on positions and orientations of the measurement devices, each measurement device including an inertial sensor. (2) The information processing device according to (1), wherein the posture estimation unit sets the measurement device to be updated based on the connection relationship, and updates the posture of the measurement target based on the position and orientation of the measurement device to be updated. (3) The information processing device according to (2), wherein the posture estimating unit; updates the posture of the measurement target by correcting the position and orientation of the measurement device to be updated. (4) The information processing device according to (2) or (3), wherein the posture estimation unit sets as the measurement device to be updated a measurement device for which an error covariance related to the position and orientation of the measurement device is equal to or greater than a predetermined threshold value, or a measurement device in which a difference in position and orientation between the measurement device and an adjacent measurement device is equal to or greater than a predetermined threshold value. (5) The information processing device according to any one of (2) to (4), wherein the posture estimation unit corrects the position and orientation of the measurement device to be updated such that a change of difference in position and orientation, with respect to a past difference, between the measurement device to be updated and a measurement device adjacent to the measurement device to be updated is reduced. (6) The information processing device according to (5), wherein, in a case where there are a plurality of measurement devices adjacent to the measurement device to be updated, the posture estimation unit corrects the position and orientation of the measurement device to be updated such that a value obtained by adding up a square of the change of difference with respect to the past difference for the plurality of measurement devices adjacent to the measurement device to be updated is reduced. (7) The information processing device according to (5) or (6), wherein the measurement device adjacent to the measurement device to be updated is a measurement device not to be updated. (8) The information processing device according to any one of (4) to (7), wherein, when a difference in position and orientation between two adjacent measurement devices is equal to or greater than a predetermined threshold value, the posture estimation unit sets as the measurement device to be updated the measurement device with the higher error covariance of the two measurement devices. (9) The information processing device according to any one of (4) to (8), wherein, when no other measurement device is arranged at a part on a skeleton of the measurement target between two measurement devices, the posture estimation unit sets one of the two measurement devices as the adjacent measurement device. (10) The information processing device according to (9), wherein, only in a case where the two measurement devices are arranged at parts of the measurement target such that a change of distance between the two measurement devices is equal to or less than a predetermined threshold value, the posture estimation unit sets one of the two measurement devices as the adjacent measurement device. (11) The information processing device according to any one of (4) to (10), further including a connection relationship setting unit that sets the adjacent measurement device for each of the plurality of measurement devices based on a users selection. (12) The information processing device according to (2), wherein the measurement device includes an image sensor, detects a feature point in an image captured by the image sensor, and outputs the position of the detected feature point. (13) The information processing device according to (12), wherein the posture estimation unit sets as the measurement device to be updated a measurement device in which the number of detected feature points is equal to or less than a predetermined threshold, of the plurality of measurement devices. (14) The information processing device according to (12) or (13), wherein the posture estimation

unit corrects the position and orientation of the measurement device to be updated such that a difference between the position of the feature point output from the measurement device to be updated and a position of the feature point detected for the corrected position and orientation of the measurement device to be updated is reduced. (15) The information processing device according to (14), wherein, when a plurality of feature points are detected by the measurement device to be updated, the posture estimation unit corrects the position and orientation of the measurement device to be updated such that a value obtained by adding up a square of the difference for the plurality of feature points is reduced. (16) The information processing device according to any one of (12) to (15), wherein the measurement device estimates the position and orientation of the measurement device by a Kalman filter using the positions of the feature points detected in the image as observation values. (17) The information processing device according to any one of (3) to wherein the posture estimation unit supplies the corrected position and orientation of the measurement device to be updated to the measurement device to be updated. (18) An information processing method including, by a posture estimation unit of an information processing device, estimating a posture of a measurement target based on a position and orientation of each of a plurality of measurement devices arranged at a plurality of parts of the measurement target and based on a connection relationship between the measurement devices that is set based on positions and orientations of the measurement devices, each measurement device including an inertial sensor. (19) A program for causing a computer to function as: a posture estimation unit that estimates a posture of a measurement target based on a position and orientation of each of a plurality of measurement devices arranged at a plurality of parts of the measurement target and based on a connection relationship between the measurement devices that is set based on positions and orientations of the measurement devices, each measurement device including an inertial sensor.

REFERENCE SIGNS LIST

(254) **51** Motion capture system **61** Measurement device **63** Communication device **64** Information processing device **71** Image sensor **72** Logic circuit board **81** Image correction processing unit **82** Feature point detection and tracking processing unit **83** IMU correction processing unit **84** Self-position estimation processing unit **85** Initialization processing unit **171** Posture estimation unit **182** Device connection relationship determination unit **183** Pose correction processing unit

Claims

1. An information processing device comprising: circuitry configured to estimate a posture of a measurement target based on a position and an orientation of each of a plurality of measurement devices arranged at a plurality of parts of the measurement target and based on a connection relationship between the plurality of measurement devices that is set based on the position and the orientation of each of the plurality of measurement devices, each measurement device including an inertial sensor, set a measurement device to be updated based on the connection relationship, and correct the position and the orientation of the measurement device to be updated according to a change of a difference in the position and the orientation of the measurement device to be updated, with respect to a past difference.
2. The information processing device according to claim 1, wherein the circuitry is further configured to update the posture of the measurement target based on the position and orientation of the measurement device to be updated.
3. The information processing device according to claim 2, wherein the circuitry updates the posture of the measurement target by correcting the position and orientation of the measurement device to be updated.
4. The information processing device according to claim 2, wherein the circuitry sets as the measurement device to be updated a measurement device for which an error covariance related to the position and the orientation of the measurement device is equal to or greater than a predetermined threshold value, or a measurement device in which the difference in the position and the orientation between the measurement device and an adjacent measurement device is equal to or greater than a predetermined threshold value.
5. The information processing device according to claim 2, wherein the circuitry corrects the position and orientation of the measurement device to be updated such that the change of the difference in the position and the orientation is reduced, with respect to the past difference, between the measurement device to be updated and a measurement device adjacent to the measurement device to be updated.
6. The information processing device according to claim 5, wherein, in a case where there are a plurality of measurement devices adjacent to the measurement device to be updated, the circuitry corrects the position and the orientation of the measurement device to be updated such that a value obtained by adding up a square of the change of the difference with respect to the past difference is reduced for the plurality of measurement devices adjacent to the measurement device to be updated.
7. The information processing device according to claim 5, wherein the measurement device adjacent to the measurement device to be updated is a measurement device not to be updated.
8. The information processing device according to claim 4, wherein, when the difference in the position and the orientation between two adjacent measurement devices is equal to or greater than a predetermined threshold value, the circuitry sets as the measurement device to be updated the measurement device with the higher error covariance of the two measurement devices.
9. The information processing device according to claim 4, wherein, when no other measurement device is arranged at a

part on a skeleton of the measurement target between two measurement devices, the circuitry sets one of the two measurement devices as the adjacent measurement device.

10. The information processing device according to claim 9, wherein, only in a case where the two measurement devices are arranged at parts of the measurement target such that a change of distance between the two measurement devices is equal to or less than a predetermined threshold value, the circuitry sets one of the two measurement devices as the adjacent measurement device.

11. The information processing device according to claim 4, wherein the circuitry is further configured to set the adjacent measurement device for each of the plurality of measurement devices based on a selection by a user.

12. The information processing device according to claim 2, wherein each measurement device includes an image sensor configured to detect a feature point in an image captured by the image sensor, and output a position of the detected feature point.

13. The information processing device according to claim 12, wherein the circuitry sets as the measurement device to be updated a measurement device in which a number of detected feature points is equal to or less than a predetermined threshold, among the plurality of measurement devices.

14. The information processing device according to claim 12, wherein the circuitry corrects the position and orientation of the measurement device to be updated such that a difference is reduced between the position of the detected feature point output from the measurement device to be updated and a position of the feature point detected for the corrected position and the corrected orientation of the measurement device to be updated.

15. The information processing device according to claim 14, wherein, when a plurality of feature points are detected by the measurement device to be updated, the circuitry corrects the position and the orientation of the measurement device to be updated to reduce a value obtained by adding up a square of the difference for the plurality of feature points.

16. The information processing device according to claim 12, wherein the measurement device estimates the position and orientation of the measurement device by a Kalman filter using the positions of the feature points detected in the image as observation values.

17. The information processing device according to claim 3, wherein the circuitry supplies the corrected position and orientation of the measurement device to be updated to the measurement device to be updated.

18. An information processing method comprising: estimating a posture of a measurement target based on a position and an orientation of each of a plurality of measurement devices arranged at a plurality of parts of the measurement target and based on a connection relationship between the plurality of measurement devices that is set based on the position and the orientation of the plurality of measurement devices, each measurement device including an inertial sensor; setting a measurement device to be updated based on the connection relationship; and correcting the position and the orientation of the measurement device to be updated according to a change of a difference in the position and the orientation of the measurement device to be updated, with respect to a past difference.

19. A non-transitory computer-readable storage medium having embodied thereon a program, which when executed by a computer causes the computer to execute a method, the method comprising: estimating a posture of a measurement target based on a position and an orientation of each of a plurality of measurement devices arranged at a plurality of parts of the measurement target and based on a connection relationship between the plurality of measurement devices that is set based on the position and the orientation of each of the plurality of measurement devices, each measurement device including an inertial sensor; setting a measurement device to be updated based on the connection relationship; and correcting the position and the orientation of the measurement device to be updated according to a change of a difference in the position and the orientation of the measurement device to be updated, with respect to a past difference.
