

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413335
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Im; Juhyuk et al.

UE performing blind decoding, communication system including the same, and operation method of the UE and the communication system

Abstract

An operating method of a terminal, the operating method includes determining a decoding priority of a plurality of aggregation levels based on reference information, the plurality of aggregation levels corresponding to a downlink control channel, performing candidate filtering-based blind decoding on one or more control channel candidates corresponding to the plurality of aggregation levels according to the decoding priority to obtain a decoding result, and receiving downlink control information based on the decoding result.

Inventors: Im; Juhyuk (Gunpo-si, KR), Kim; Daeson (Seoul, KR), Ji; Hoguen (Hwaseong-si, KR)

Applicant: Samsung Electronics Co., Ltd. (Suwon-si, KR)

Family ID: 78851320

Assignee: Samsung Electronics Co., Ltd. (Gyeonggi-do, KR)

Appl. No.: 17/539710

Filed: December 01, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20220182177 A1	Jun. 09, 2022

Foreign Application Priority Data

KR	10-2020-0167662	Dec. 03, 2020
KR	10-2021-0014401	Feb. 01, 2021

Publication Classification

Int. Cl.: H04L1/00 (20060101); H04W72/0453 (20230101); H04W72/23 (20230101)

U.S. Cl.:

CPC H04L1/0045 (20130101); H04W72/0453 (20130101); H04W72/23 (20230101);

Field of Classification Search

CPC: H04L (1/0045); H04L (1/0038); H04W (72/23); H04W (72/0453)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9537634	12/2016	Seo et al.	N/A	N/A
10728004	12/2019	Wang et al.	N/A	N/A
11032824	12/2020	Hosseini et al.	N/A	N/A
2008/0225786	12/2007	Han et al.	N/A	N/A
2009/0088148	12/2008	Chung	455/423	H04L 1/0032
2009/0154607	12/2008	Lindoff	375/341	H04L 1/0091
2018/0083733	12/2017	Chen	N/A	H04L 1/0048
2019/0223164	12/2018	He et al.	N/A	N/A
2019/0268206	12/2018	Yang	N/A	H04L 5/0051
2019/0349911	12/2018	Seo	N/A	H04W 72/23
2020/0177306	12/2019	Choi	N/A	H04L 5/0053
2020/0280393	12/2019	Qu et al.	N/A	N/A
2020/0344616	12/2019	Hwang et al.	N/A	N/A
2020/0404669	12/2019	Seo	N/A	H04L 25/0238
2021/0067268	12/2020	Seo	N/A	H04L 25/0238

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
10-2010-0053060	12/2009	KR	N/A
202029814	12/2019	TW	N/A
2019143164	12/2018	WO	N/A
WO-2019139300	12/2018	WO	H04L 1/00

OTHER PUBLICATIONS

European Search Report dated Apr. 21, 2022 for corresponding EP Patent Application No. 21209503.8. cited by applicant

Extended European Search Report dated Sep. 13, 2022 for corresponding EP Patent Application No. 21209503.8. cited by applicant

Taiwan Office Action issued Apr. 8, 2025 in Taiwan Patent Application No. 110145244. cited by applicant

Korean Office Action issued Jul. 30, 2025 in Korean Patent Application No. 10-2021-0014401. cited by applicant

Primary Examiner: Ferris; Derrick W

Assistant Examiner: Choi; Won Jun

Attorney, Agent or Firm: Harness, Dickey & Pierce, P.L.C.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS

(1) This application is based on and claims priority under 35 U.S.C. § his application is based on and claim 10-2020-0167662 and 10-2021-0014401, filed on Dec. 3, 2020 and Feb. 1, 2021, respectively, in the Korean Intellectual Property Office, the disclosures of both of which are incorporated by reference herein in their entirety.

BACKGROUND

(2) The inventive concepts relate to a terminal that performs blind decoding, a communication system including the same, and/or an operating method of the terminal and the communication system.

(3) In order to support transmission of downlink and uplink transmission channels in a communication system, downlink control information (DCI) related thereto is used. A terminal may receive the downlink control channel from a base station, perform decoding on the downlink control channel, and receive the DCI based on results of decoding.

(4) The downlink control channel may have various formats, and the terminal may not be previously aware of the format selected by the base station. In addition, because time/frequency resources defined as a search space may be transmitted through an arbitrary or unknown resource in a set, the exact time/frequency resource through which the downlink control channel is transmitted is not previously known to the terminal. Therefore, the terminal performs decoding on the downlink control channel based on blind decoding. Blind decoding refers to an operation of decoding a downlink control channel with respect to all possible downlink control channel formats and all possible time/frequency resource combinations in a given search space by the terminal.

(5) The time/frequency resource combination on which blind decoding is performed may include control channel candidates included in each of a plurality of aggregation levels, and the terminal performs a decoding operation on each of the control channel candidates. In next-generation communication, as the number of aggregation levels and the number of control channel candidates increase, the time and power consumed by the terminal for blind decoding increase, which causes a challenge in the performance improvement of the terminal.

SUMMARY

(6) The inventive concepts provide a terminal reducing time and power consumed in blind decoding by reducing operations in blind decoding, and ultimately improving communication performance, a communication system including the terminal, and an operating method of the terminal and the communication system.

(7) According to an aspect of the inventive concepts, there is provided an operating method of a terminal including determining a decoding priority of a plurality of aggregation levels based on reference information, the plurality of aggregation levels corresponding to a downlink control channel, performing candidate filtering-based blind decoding on one or more control channel candidates corresponding to the plurality of aggregation levels according to the decoding priority to obtain a decoding result, and receiving downlink control information based on the decoding result.

(8) According to an aspect of the inventive concepts, there is provided a terminal including processing circuitry configured to determine a decoding priority with respect to a plurality of

aggregation levels based on reference information, the plurality of aggregation levels corresponding to a downlink control channel, perform candidate filtering-based blind decoding on one or more control channel candidates corresponding to the plurality of aggregation levels according to the decoding priority to obtain a decoding result, and receive downlink control information based on the decoding result.

(9) According to an aspect of the inventive concepts, there is provided a communication system including a base station, and a first terminal connected to the base station, the base station being configured to transmit a first downlink control channel to the first terminal, and the first terminal being configured to perform first candidate filtering-based blind decoding on a plurality of first control channel candidates corresponding to a plurality of aggregation levels based on a first priority, the plurality of aggregation levels corresponding to the first downlink control channel, and receive first downlink control information.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Embodiments of the inventive concepts will be more clearly understood from the following detailed description taken in conjunction with the accompanying drawings in which:

(2) FIG. 1 is a block diagram illustrating a communication system according to embodiments of the inventive concepts;

(3) FIG. 2 is a diagram illustrating a basic structure of a time-frequency domain in the communication system of FIG. 1;

(4) FIG. 3 is a diagram illustrating a physical downlink control channel (PDCCH) and an enhanced PDCCH (EPDCCH) in a communication system supporting long term evolution (LTE);

(5) FIG. 4 is a diagram illustrating an example of a control resource set in which a PDCCH is transmitted in a communication system supporting new radio (NR);

(6) FIG. 5 is a diagram illustrating an example of a basic unit of time and frequency resources constituting a PDCCH in a communication system supporting NR;

(7) FIGS. 6A and 6B are diagrams illustrating an example of a search space of a PDCCH to which embodiments of the inventive concepts are applied;

(8) FIG. 7 is a flowchart illustrating an operating method of a terminal according to embodiments of the inventive concepts;

(9) FIGS. 8A and 8B are flowcharts illustrating a method of generating and storing reference information of a terminal according to embodiments of the inventive concepts;

(10) FIG. 9 is a detailed flowchart illustrating operation S120 of FIG. 7 according to embodiments of the inventive concepts;

(11) FIG. 10 is a flowchart additionally illustrating a method of receiving downlink control information (DCI) using a second threshold from FIG. 9;

(12) FIG. 11 is a diagram illustrating an operation of excluding overlapping candidates from blind decoding according to embodiments of the inventive concepts;

(13) FIG. 12 is a flowchart illustrating an operating method of a terminal using a first threshold according to embodiments of the inventive concepts;

(14) FIGS. 13A and 13B are detailed flowcharts illustrating embodiments of FIG. 12;

(15) FIG. 14 is a flowchart illustrating a blind decoding method of a terminal according to embodiments of the inventive concepts;

(16) FIG. 15 is a detailed flowchart illustrating embodiments of FIG. 14;

(17) FIGS. 16A and 16B are detailed flowcharts illustrating embodiments of FIG. 15;

(18) FIG. 17 is a flowchart illustrating an operating method of a terminal according to embodiments of the inventive concepts;

(19) FIGS. **18** and **19** are diagrams illustrating an operating method of a communication system according to embodiments of the inventive concepts;

(20) FIG. **20** is a block diagram illustrating an electronic device according to embodiments of the inventive concepts; and

(21) FIG. **21** is a diagram illustrating communication devices performing a decoding operation according to embodiments of the inventive concepts.

DETAILED DESCRIPTION

(22) Hereinafter, embodiments of the inventive concepts will be described in detail with reference to the accompanying drawings.

(23) FIG. **1** is a block diagram illustrating a communication system **1** according to embodiments of the inventive concepts. The communication system **1**, as a non-limiting example, may be a New Radio (NR) system, a 5th Generation (5G) system, a Long Term Evolution (LTE) system, a Code Division Multiple Access (CDMA) system, a Global System for Mobile Communications (GSM) system, a Wireless Local Area Network (WLAN) system, and/or any other wireless communication system. Hereinafter, the communication system **1** may be described as the NR system, the LTE system or a system capable of supporting NR and LTE-based communication, but it will be understood that the inventive concepts are not limited thereto.

(24) Referring to FIG. **1**, the communication system **1** may include a base station **10** and a terminal **100**. The terminal **100**, as a wireless communication device, may have mobility, and may transmit, and receive, data and control information by communicating with the base station **10** through a downlink channel DL and an uplink channel UL. The terminal **100** may be referred to as, for example, user equipment (UE), a mobile station (MS), a mobile terminal (MT), a user terminal, a subscriber station (SS), a wireless device, a handheld device and/or the like.

(25) The base station **10** may refer to a fixed station communicating with the terminal **100** and/or other base stations. The base station **10** may be referred to as, for example, a cell, a node B, an evolved-node B (eNB), a sector, a site, a base transceiver system (BTS), an access point (AP), a relay node, a remote radio head (RRH), radio unit (RU), and/or the like.

(26) Scheduling information of data (or downlink data) transmitted through the downlink channel DL or data (or uplink data) transmitted through the uplink channel UL may be included in downlink control information (hereinafter referred to as DCI) and transmitted from the base station **10** to the terminal **100**. The DCI may be defined in various formats and operate by applying a DCI format determined according to whether it is scheduling information of uplink data or scheduling information of downlink data, whether it is a compact DCI with a small size of control information, and whether to apply spatial multiplexing using multiple antennas, whether it is a DCI for power control, etc.

(27) The DCI may be transmitted from the base station **10** to the terminal **100** through a physical downlink control channel (hereinafter referred to as PDCCH) or an enhanced PDCCH (EPDCCH) via a channel coding and modulation process. For convenience of description, in FIG. **1**, it is described in embodiments of the inventive concepts that the DCI is the PDCCH, but it will be fully understood that the DCI may be applied to the EPDCCH. A cyclic redundancy check (CRC) may be added to a payload of the DCI (or a DCI message), and may be scrambling with a radio network temporary identifier (RNTI) corresponding to the identity of the terminal **100**. The terminal **100** may receive the DCI transmitted on the PDCCH, determine the CRC using the allocated RNTI, and when it is determined that the CRC is good (e.g., upon successful verification of the CRC), may be known that the DCI is transmitted to the terminal **100**.

(28) The terminal **100** may include a plurality of antennas AT, a radio frequency (RF) integrated circuit (IC) **110**, a baseband IC **120**, a processor **130**, and/or a memory **140**. Meanwhile, the implementation example of the terminal **100** shown in FIG. **1** is merely an example, and embodiments are not limited thereto, and the terminal **100** may include more or fewer configurations (e.g., components). In addition, in embodiments, the RFIC **110** and the baseband IC

120 may be included in one integrated circuit.

(29) The RFIC **110** may perform a function of transmitting and receiving a signal using the plurality of antennas AT through a wireless channel such as band conversion and amplification of the signal. Specifically, the RFIC **110** may up-convert a baseband signal provided from the baseband IC **120** into an RF band signal, then transmit the RF band signal through the antennas AT, and down-convert the RF band signal received through the antennas AT into the baseband signal. For example, the RFIC **110** may include a transmission filter, a reception filter, an amplifier, a mixer, an oscillator, a digital to analog converter (DAC), an analog to digital converter (ADC), etc. In addition, the RFIC **110** may further include a plurality of RF chains (not shown), and may perform beamforming using the antennas AT. The RFIC **110** may adjust the phase and size of each of signals transmitted and received through the antennas AT for beamforming. Further, the RFIC **110** may perform a multi input multi output (MIMO) operation and, when performing the MIMO operation, receive multiple layers.

(30) The baseband IC **120** may perform a conversion operation between the baseband signal and a bit string according to a physical layer standard of the system. For example, the baseband IC **120** may generate complex symbols by encoding and modulating a transmission bit stream during data transmission. In addition, the baseband IC **120** may demodulate and decode the baseband signal provided from the RFIC **110** when receiving data to restore a reception bit stream.

(31) The RFIC **110** and the baseband IC **120** may transmit and receive signals as described above. The RFIC **110** and the baseband IC **120** may be referred to as a transmitter, a receiver, a transceiver, or a communicator. Furthermore, at least one of the RFIC **110** and the baseband IC **120** may include a plurality of communication modules for supporting a plurality of different wireless access technologies. In addition, at least one of the RFIC **110** and the baseband IC **120** may include different communication modules to process signals of different frequency bands. For example, different wireless access technologies may include new radio (NR) technology, LTE technology, etc. In addition, different frequency bands may include a super high frequency band, a millimeter wave band, etc. The terminal **100** may communicate with the base station **10** using the RFIC **110** and the baseband IC **120**.

(32) The memory **140** may store data such as a basic program, an application program, and/or setting information for the operation of the terminal **100**. Also, the memory **140** may store a program, in the form of a code, executed when the processor **130** performs candidate filtering-based blind decoding according to embodiments of the inventive concepts. In embodiments, the memory **140** may store reference information **142** referenced for candidate filtering-based blind decoding.

(33) The processor **130** may control overall operations of the terminal **100**. In embodiments, the processor **130** may include a decoding circuit **132** that performs candidate filtering-based blind decoding to detect the PDCCH without knowing information about the PDCCH transmitted from the base station **10**. In general, the search space representing a set of control-channel elements (CCEs) may be defined for blind decoding. The search space includes sets of a plurality of CCEs according to an aggregation level, and the aggregation level is not explicitly signaled and may be implicitly defined through a function and subframe number based on the identity of a terminal. Blind decoding may be performed on all possible control channel candidates (or resource candidates) that may be created from the CCEs in the search space set in each subframe, and DCI transmitted through the PDCCH may be received through determination of the CRC. Hereinafter, for convenience of description, control channel candidates may also be referred to as candidates.

(34) In embodiments, the decoding circuit **132** may determine a decoding priority with respect to aggregation levels based on the reference information **142** read from the memory **140**. The decoding circuit **132** may prioritize an aggregation level having a high availability for transmitting the PDCCH, and may determine a decoding priority so that candidate filtering-based blind decoding may be performed. Meanwhile, the decoding circuit **132** may perform candidate filtering-

based blind decoding on the PDCCH for each transmission time interval (TTI). The aggregation levels may each include control channel candidates including a defined number of CCEs. The decoding circuit **132** may perform candidate filtering-based blind decoding in a certain order with respect to the aggregation levels according to the decoding priority. In embodiments, the decoding circuit **132** may be implemented as software logic, hardware logic, or mixed software/hardware logic. The operation of the decoding circuit **132** to be described below may also be defined as an operation of the processor **130** or the terminal **100**.

(35) In embodiments, the reference information **142** may include history information indicating results of blind decoding that has been previously performed. For example, the history information may indicate the number of control channel candidates that are determined that the CRC is good (e.g., the number of control channel candidates for which a respective CRC has been successfully verified) for each aggregation level in a blind decoding history of at least one previous TTI. The decoding circuit **132** may determine decoding priorities with respect to the aggregation levels in the order of the highest number of control channel candidates that are determined that the CRC is good (e.g., correspond to a successfully verified CRC).

(36) In embodiments, the reference information **142** may include history information indicating a trend of a format used by the base station **10** (e.g., one or more formats previously used by the base station **10**, or a frequency or rate of use of the one or more formats,) to transmit the PDCCH. As an example, the history information may indicate a frequency for each aggregation level used when the base station **10** transmits the PDCCH to the terminal **100** for a certain period (e.g., a frequency or rate at which the base station **10** has transmitted the PDCCH on each different aggregation level to the terminal **100** for the certain period). The decoding circuit **132** may determine the decoding priority of the aggregation levels in the order of the highest frequency.

(37) In embodiments, the reference information **142** may include state information indicating a state of the downlink channel DL. As an example, the state information may include results of measurement of at least one indicator indicating the state of the downlink channel DL. For example, the state information may include results of measurement of at least one indicator of Reference Signals Received Power (RSRP), Reference Signal Received Quality (RSRQ), Signal to Interference plus Noise Ratio (SINR), Received Signal Code Power (RSCP), and/or received energy from pilot signal to noise (E_c/N_0). The base station **10** may receive the state of the downlink channel DL from the terminal **100**, and the base station **10** may select an aggregation level for transmission of the PDCCH in consideration of the state of the downlink channel DL. Meanwhile, the base station **10** may transmit the PDCCH by selecting a relatively low aggregation level when the state of the downlink channel DL is good and by selecting a relatively high aggregation level when the state of the downlink channel DL is bad. The decoding circuit **132** may determine the decoding priority with respect to the aggregation levels based on the state of the downlink channel DL in consideration of a PDCCH transmission method of the base station **10** as described above.

(38) In embodiments, the reference information **142** may include information processed from the above-described history information and/or state information. Furthermore, the reference information **142** may include various pieces of information that may be referenced for the decoding circuit **132** to determine the decoding priority with respect to the aggregation levels.

(39) In embodiments, the decoding circuit **132** may perform candidate filtering-based blind decoding with respect to control channel candidates corresponding to each of the aggregation levels according to decoding priority. As an example, the decoding circuit **132** may exclude at least one control channel candidate that is determined that the CRC is good among the control channel candidates and overlapping with a control channel candidate of which reliability exceeds a first threshold from candidate filtering-based blind decoding. That is, the decoding circuit **132** may filter control channel candidates by removing at least one control channel candidate including at least one CCE overlapping with a control channel candidate satisfying a certain condition while performing blind decoding, and perform blind decoding on the control channel candidates.

Hereinafter, a blind decoding operation of the terminal **100** to be described may mean a candidate filtering-based blind decoding operation.

(40) In embodiments, the decoding circuit **132** may exclude only control channel candidates corresponding to some aggregation levels among overlapping control channel candidates from blind decoding. For example, the decoding circuit **132** may select a candidate-excluded aggregation level direction based on a network state of the terminal **100**, and exclude control channel candidates corresponding to some aggregation levels from among all overlapping control channel candidates based on the selected direction from blind decoding.

(41) In embodiments, the decoding circuit **132** may perform first blind decoding to receive the PDCCH using results of decoding of a control channel candidate that is determined that the CRC is good and has a reliability exceeding a second threshold. However, when the decoding circuit **132** fails to receive the PDCCH through the control channel candidate according to the network state between the base station **10** and the terminal **100**, or, when there is no control channel candidate that is determined that the CRC is good, and has a reliability exceeding the second threshold, the decoding circuit **132** may perform second blind decoding on the at least one control channel candidate excluded from first blind decoding.

(42) In embodiments, the decoding circuit **132** may manage the first threshold used to determine the decoding priority and the second threshold used to determine the control channel candidate used for reception of the PDCCH in the same manner or differently. For example, the first threshold may be set larger than the second threshold so that the criterion for excluding other control channel candidates from blind decoding may be strict, and the first threshold may be set smaller than the second threshold so that the number of control channel candidates on which blind decoding is performed may be simplified. In embodiments, the first threshold may be variably set according to the network state of the terminal **100**, and accordingly, the first threshold may be dynamically larger or smaller than the second threshold.

(43) In embodiments, the decoding circuit **132** may periodically or aperiodically collect the decoding history information to generate the reference information **142** and store or update the reference information **142** in the memory **140**. In addition, in embodiments, the decoding circuit **132** may periodically or aperiodically measure the state of the downlink channel DL to generate the reference information **142** and store or update the reference information **142** in the memory **140**.

(44) The terminal **100** according to embodiments of the inventive concepts may selectively perform blind decoding with respect to an aggregation level with a high availability for transmitting the PDCCH, and exclude the overlapping control channel candidates from blind decoding, thereby optimizing or reducing the time and power consumed for blind decoding, and as a result, there is an effect of improving the communication performance of the terminal **100**.

(45) FIG. 2 is a diagram illustrating a basic structure of a time-frequency domain in the communication system **1** of FIG. 1.

(46) Referring to FIG. 2, the horizontal axis represents a time domain, and the vertical axis represents a frequency domain. The minimum or smallest transmission unit in the time domain is an Orthogonal Frequency Division Multiplexing (OFDM) symbol, $N_{\text{sub.symb}}$ **202** OFDM symbols may constitute one slot **206**, and two slots may constitute one subframe **205**. For example, the length of the slot **206** may be 0.5 ms, and the length of the subframe may be 1.0 ms. In addition, a radio frame **214** may be a time domain unit including 10 subframes **205**. The subframe **205** may correspond to one TTI.

(47) The minimum or smallest transmission unit in a frequency domain is a subcarrier, and the bandwidth of an entire system transmission bandwidth may include the total of $N_{\text{sub.BW}}$ **204** subcarriers. In the time-frequency domain, a basic unit of a resource is a resource element (RE) **212** and may be represented by an OFDM symbol index and a subcarrier index. A resource block (RB) **208** may be defined as the $N_{\text{sub.symb}}$ **202** consecutive OFDM symbols in the time domain and the $N_{\text{sub.RB}}$ **210** consecutive subcarriers in the frequency domain. Accordingly, one RB **208** may

include $(N_{\text{sub.symb}} \cdot N_{\text{sub.RB}})$ REs **212**. An RB pair is a unit that connects two RBs on a time axis and may include $(N_{\text{sub.symb}} \cdot 2N_{\text{sub.RB}})$ REs **212**. Meanwhile, a PDCCH may be transmitted from a base station to a terminal in a communication system through resources in the time-frequency domain as shown in FIG. 2, and DCI may be transmitted through the PDCCH. The DCI may include information about downlink scheduling assignment including physical downlink shared channel (PDSCH) resource designation, a transmission format, HARQ information, and/or spatial multiplexing-related control information.

(48) FIG. 3 is a diagram illustrating a PDCCH **301** and an EPDCCH **302** in a communication system supporting LTE.

(49) Referring to FIG. 3, the PDCCH **301** may be time multiplexed with a PDSCH **303** which is a data transmission channel and may be transmitted over the entire system bandwidth. The PDCCH **301** may be expressed in the number of OFDM symbols, which may be indicated to the terminal through a control format indicator (CFI) transmitted through a physical control format indicator channel (PCFICH). The PDCCH **201** may be assigned to an OFDM symbol in the beginning of a subframe, and thus the terminal may decode the downlink scheduling assignment quickly. One PDCCH may carry one DCI, and a plurality of terminals may be simultaneously or contemporaneously scheduled in downlink and uplink, and thus a plurality of PDCCHs may be simultaneously or contemporaneously transmitted within each terminal.

(50) A cell-specific reference signal (CRS) **304** is used as a reference signal for decoding the PDCCH **301**. The CRS **304** may be transmitted every subframe over the entire band, and scrambling and resource mapping may vary according to the identity (ID) of a base station (or a cell). Because the CRS **304** is a reference signal commonly used by all terminals, terminal-specific beamforming may not be used. Therefore, a multi-antenna transmission method with respect to the PDCCH of LTE is limited to open-loop transmission diversity. The number of ports of the CRS **304** may be implicitly known to the terminal from decoding of a physical broadcast channel (PBCH).

(51) Resource allocation of the PDCCH **301** is based on a CCE, and one CCE includes 9 resource element groups (REGs), that is, the total of 36 REs. The number of CCEs used for the specific PDCCH **301** may be 1, 2, 4, or 8, which varies depending on a channel coding rate of a payload of the DCI. As described above, different numbers of CCEs may be used to implement link adaptation of the PDCCH **301**.

(52) The terminal should detect a signal without knowing information about the PDCCH **301**, and search spaces representing a set of CCEs have been defined for blind decoding. Search space are classified into a terminal-specific search space and a common search space. A certain group of UEs or all UEs may examine the common search space of the PDCCH **301** in order to receive control information common to a base station such as a dynamic scheduling or paging message with respect to system information. For example, scheduling allocation information of a DL-SCH for transmission of a system information block (SIB)-1 including operator information of the base station, etc. may be received by examining the common search space of the PDCCH **301**. In addition, the terminal-specific DCI, such as scheduling information about uplink data and/or scheduling information about downlink data, is transmitted through a mode terminal-specific search space.

(53) Meanwhile, the EPDCCH **302** may be transmitted after being frequency multiplexed with the PDSCH **303**. The base station may appropriately allocate resources of the EPDCCH **302** and the PDSCH **303** through scheduling, thereby effectively supporting coexistence with data transmission for the terminal.

(54) The plurality of EPDCCHs **302** constitute one EPDCCH set **306**, and are allocated in units of a physical resource block (PRB) pair. Location information about the EPDCCH set **306** is set terminal-specifically, which may be signaled through remote radio control (RRC). Two EPDCCH sets **306** to the maximum (e.g., highest number) may be set for each terminal, and one EPDCCH set **306** may be multiplexed to different terminals and set at the same time or contemporaneously.

(55) In the EPDCCH **302**, a demodulation reference signal (DMRS) **305** is used as an RS for decoding. The DMRS **305** of the EPDCCH **302** uses the same pattern as, or a similar pattern o, the PDSCH **303**. However, unlike the PDSCH **303**, the DMRS **305** in the EPDCCH **302** may support four antenna ports to the maximum (e.g., highest number). The DMRS **305** of the EPDCCH **302** may be transmitted only in the corresponding PRB through which the EPDCCH **302** is transmitted.

(56) A blind decoding operation according to embodiments of the inventive concepts may be applied to both the PDCCH and the EPDCCH described with reference to FIG. 3. In addition, further, in a communication system supporting LTE, the blind decoding operation according to embodiments of the inventive concepts may be applied to all of the Machine Type Communication PDCCH (MPDCCH), Short TTI PDCCH (SPDCCH), and/or NB-IOT PDCCH (NPDCCH).

(57) FIG. 4 is a diagram illustrating an example of a control resource set CORESET in which a PDCCH is transmitted in a communication system supporting NR.

(58) FIG. 4 shows the example in which a UE bandwidth part **410** is set in a frequency axis and two control resource set CORESET (control resource set #1 **401** and control resource set #2 **402**) are set within a 1 slot **420** in a time axis. The control resource set #1 **401** and the control resource set #2 **402** may be set in specific frequency resources **403** within the entire UE bandwidth part **410** in the frequency axis. The control resource set #1 **401** and the control resource set #2 **402** may be set to one or a plurality of OFDM symbols in the time axis, which may be defined as a control resource set duration **404**. Referring to the example of FIG. 4, the control resource set #1 **401** may be set to a control resource set duration corresponding to two symbols, and the control resource set #2 **402** may be set to a control resource set duration corresponding to one symbol.

(59) A control resource set in the NR may be set by a base station to a UE through higher layer signaling (e.g., system information, master information block (MIB), and RRC signaling). Setting the control resource set to the UE may mean providing information such as a control resource set identifier (Identity), a frequency position of the control resource set, and a symbol duration of the control resource set.

(60) FIG. 5 is a diagram illustrating an example of a basic unit of time and frequency resources constituting a PDCCH in a communication system supporting NR.

(61) Referring to FIG. 5, the basic unit of time and frequency resources constituting the PDCCH may be referred to as an REG **503**. The REG **503** may be defined as a 1 OFDM symbol **501** in a time axis and a 1 physical resource block (PRB) **502**, that is, 12 subcarriers, in a frequency axis. A base station may configure a PDCCH allocation unit by concatenating the REG **503**.

(62) As shown in FIG. 5, when the basic unit to which the PDCCH is allocated in the NR is a CCE **504**, a 1 CCE **504** may include a plurality of REGs **503**. For example, the REG **503** shown in FIG. 5 may include 12 REs, and when the 1 CCE **504** includes 6 REGs **503**, the 1 CCE **504** may include 72 REs. When a downlink control region is set, the corresponding region may include a plurality of CCEs **504**, and a specific PDCCH may be mapped to one or a plurality of CCEs **504** according to an aggregation level in the control region and then transmitted. The CCEs **504** in the control region are classified by numbers, and in this regard, the numbers of the CCEs **504** may be assigned according to a logical mapping method.

(63) The basic unit of the PDCCH shown in FIG. 5, that is, the REG **503**, may include both REs to which DCI is mapped and a region to which a DMRS **505** which is a reference signal for decoding the REs is mapped. As shown in FIG. 5, three DMRSs **505** may be transmitted in the 1 REG **503**. The number of CCEs used to transmit the PDCCH may be 1, 2, 4, 8, or 16 depending on the aggregation level, and different numbers of CCEs may be used to implement link adaptation of the PDCCH. For example, when the aggregation level is 'L', one PDCCH may be transmitted through 'L' CCEs.

(64) A parameter of a search space with respect to the PDCCH may be set from a base station to a terminal by higher layer signaling (e.g., SIB, MIB, or RRC signaling). For example, the base station may set, to the terminal, the number of control channel candidates for each aggregation

level, a monitoring period with respect to the search space, a monitoring occasion in a symbol unit within a slot with respect to the search space, a search space type (a common search space or a terminal-specific search space), a combination of a DCI format to be monitored in the search space and RNTI, a control region index to be monitored in the search space, etc.

(65) A blind decoding operation according to embodiments of the inventive concepts may be applied to both the PDCCH described in FIGS. 4 and 5.

(66) FIGS. 6A and 6B are diagrams illustrating an example of a search space **802** of a PDCCH to which embodiments of the inventive concepts are applied. However, embodiments illustrated in FIGS. 6A and 6B are merely examples for better understanding, and it is clear that the inventive concepts are not limited thereto.

(67) Referring to FIG. 6A, a PDCCH region **801** may include CCEs, and the configuration of CCEs may be based on logical mapping. Actual physical mapping with respect to the PDCCH region **801** may be determined by time and frequency resources set to the PDCCH. The search space **802** may be a common search space or a terminal-specific search space.

(68) In embodiments, an aggregation level '1' may include first to fourth candidates #11 to #41 each including one CCE, an aggregation level '2' may include fifth to eighth candidates #12 to #42 each including two CCEs, an aggregation level '4' may include a ninth candidate #13 including four CCEs, and an aggregation level '8' may include a tenth candidate #14 including eight CCEs in the search space **802**.

(69) A base station may transmit the PDCCH to a terminal through any one of the first to tenth candidates #11 to #41, #12 to #42, #13, and/or #14. As shown in FIG. 6A, for example, when a state of a downlink channel with the terminal is good, the base station may assign a greater number of candidates to the low aggregation levels '1' and '2' than the high aggregation levels '4' and '8'.

(70) Referring further to FIG. 6B, the aggregation level '1' may include the first and second candidates #11 and #21 including one CCE, the aggregation level '2' may include the third and fourth candidates #12 and #22 including two CCEs, the aggregation level '4' may include the fifth to seventh candidates #13 to #33 including four CCEs, and the aggregation level '8' may include the eighth and ninth candidates #14 and #15 including eight CCEs in the search space **802**. The base station may transmit the PDCCH to the terminal through any one of the first to ninth candidates #11, #21, #12, #22, #13 to #33, #14, and #15. As shown in FIG. 6B, for example, when the state of the downlink channel with the terminal is not good, the base station may allocate a greater number of candidates to the high aggregation levels '4' and '8' than the low aggregation levels '1' and '2'.

(71) The terminal according to embodiments of the inventive concepts may determine a decoding priority with respect to aggregation levels in the search region **802** and perform candidate filtering-based blind decoding based on the decoding priority. Embodiments in this regard will be described later.

(72) FIG. 7 is a flowchart illustrating an operating method of a terminal according to embodiments of the inventive concepts.

(73) Referring to FIG. 7, in operation **S100**, the terminal may receive a PDCCH from a base station. In operation **S110**, the terminal may determine a decoding priority with respect to aggregation levels based on reference information. In operation **S120**, the terminal may perform candidate filtering-based blind decoding on control channel candidates included in each of the aggregation levels based on the determined decoding priority. In operation **S130**, the terminal may receive DCI using results of decoding. According to embodiments, the terminal may generate a signal (e.g., a communication signal) based on the DCI, and/or may transmit the signal to the base station based on the DCI.

(74) FIGS. 8A and 8B are flowcharts illustrating a method of generating and storing reference information of a terminal according to embodiments of the inventive concepts.

(75) Referring to FIG. 8A, in operation **S200a**, the terminal may collect information about results

of decoding performed in the past. The results of decoding performed in the past may indicate the number of control channel candidates that are determined that the CRC is good for each aggregation level for a certain period (e.g., a plurality of TTIs). In addition, the results of decoding performed in the past may indicate the frequency for each aggregation level used by the base station when transmitting the PDCCH. In addition to this, the terminal may additionally collect results of decoding suitable for determining decoding priority with respect to aggregation levels.

(76) In operation **S210a**, the terminal may generate history information based on the collected results. In operation **S220a**, the terminal may store the history information as reference information. In embodiments, the terminal may periodically or aperiodically repeat operations **S200a** and **S210a** to update the reference information.

(77) Referring to FIG. **8B**, in operation **S200b**, the terminal may measure a state of a downlink channel. For example, the terminal may determine the state of the downlink channel by measuring at least one indicator of RSRP, RSRQ, SINR, RSCP, and/or EcN0. In operation **S210b**, the terminal may generate measurement information based on results of the measurement. In operation **S220b**, the terminal may store the measurement information as reference information. In embodiments, the terminal may periodically or aperiodically repeat operations **S200b** and **S210b** to update the reference information.

(78) FIG. **9** is a detailed flowchart illustrating operation **S120** of FIG. **7** according to embodiments of the inventive concepts.

(79) Referring to FIG. **9**, in operation **S121** following operation **S110** (FIG. **7**), a terminal may select an aggregation level based on a decoding priority. In operation **S122**, the terminal may perform decoding on a k-th candidate of the selected aggregation level (where k is an integer greater than or equal to 1 and starts from 1). In operation **S123**, the terminal may determine whether a CRC is good as a result of decoding the k-th candidate. When a result of operation **S123** is 'YES', following operation **S124_1**, the terminal may measure the reliability of the k-th candidate. Measuring the reliability of a candidate may be interpreted as measuring the reliability of results of decoding of the candidate. As an example, the terminal may measure a symbol error rate (SER) as the reliability by comparing data before encoding with data included in the results of decoding of the candidate based on an effective decoding reliability metric and counting the number of errors. As another example, the terminal may measure, as the reliability, a correlation value between an input of a polar decoder in the terminal that decodes the candidate based on a soft-correlation metric and an encoded codeword received by the terminal. In addition to this, the terminal may measure various indicators indicating the reliability of the candidate.

(80) In operation **S124_2**, the terminal may determine whether the reliability of the k-th candidate exceeds a first threshold. When a result of operation **S124_2** is 'YES', following operation **S124_3**, the terminal may exclude a candidate overlapping (e.g., with respect to frequency and/or time) with the k-th candidate in least one aggregation level different from the selected aggregation level from decoding (e.g., skip, block, etc., decoding for the excluded candidate). When the result of operation **S124_2** is 'NO', or following operation **S127** after operation **S124_3**, the terminal may determine whether the k-th candidate is the last candidate of the selected aggregation level. Similarly, when the result of operation **S123** is 'NO', or following operation **S127** after operation **S123**, the terminal may determine whether the k-th candidate is the last candidate of the selected aggregation level. When a result of operation **S127** is 'NO', following operation **S128**, the terminal may count up (e.g., increment) k and perform operation **S122**. When the result of operation **S127** is 'YES', following operation **S129**, the terminal may determine whether the selected aggregation level is the last aggregation level. When a result of operation **S129** is 'NO', following operation **S121**, the terminal may select a next aggregation level based on the decoding priority. When the result of operation **S129** is 'YES', operation **S130** (FIG. **7**) may follow.

(81) FIG. **10** is a flowchart additionally illustrating a method of receiving DCI using a second threshold from FIG. **9**. Hereinafter, descriptions redundant with those of FIG. **9** will be omitted.

(82) Referring to FIG. 10, in operation S124_4 after operation S124_1, a terminal may determine whether the reliability of a k-th candidate exceeds the second threshold. In embodiments, the second threshold may be the same as or different from a first threshold. For example, the first threshold may be set to be greater than the second threshold, so that operation S124_3 may be performed under a more strict condition than operation S124_5. As another example, the first threshold may be set smaller than the second threshold, so that operation S124_3 may be performed under a rougher condition than operation S124_5. When a result of operation S124_4 is 'YES', following operation S124_5, the terminal may determine the k-th candidate as a candidate used for receiving the DCI. When the result of operation S124_4 is 'NO', or following operation S127 after operation S124_5, the terminal may determine whether the k-th candidate is the last candidate of a selected aggregation level. According to embodiments, when the result of operation S124_2 is 'NO', operation 124_4 may be followed and, when the result of operation 124_4 is 'NO', operation 127 may be followed. According to embodiments, when the result of operation S124_4 is 'NO', operation 124_2 may be followed and, when the result of operation 124_2 is 'NO', operation 127 may be followed.

(83) FIG. 11 is a diagram illustrating an operation of excluding overlapping candidates from blind decoding according to embodiments of the inventive concepts.

(84) Referring to FIG. 11, a terminal may selectively perform decoding on the ninth candidate #13 of the aggregation level '4' based on a decoding priority. As a result of decoding with respect to the ninth candidate #13, when it is determined that a CRC is good and a reliability exceeds a first threshold, the terminal may exclude the first, fifth and tenth candidates #11, #12, and #14 including at least one CCE overlapping the ninth candidate #13 from blind decoding. The above exclusion operation may also be performed in decoding with respect to other aggregation levels.

(85) FIG. 12 is a flowchart illustrating an operating method of a terminal using a first threshold according to embodiments of the inventive concepts.

(86) Referring to FIG. 12, in operation S200, the terminal may set the first threshold based on a network state with a base station. The network state considered for setting the first threshold may include a state of a downlink channel between the terminal and the base station, and/or a battery state of the terminal. In operation S210, the terminal may perform blind decoding for detection of a PDCCH using the set first threshold.

(87) Meanwhile, the terminal may periodically or aperiodically repeat operation S200 to set the first threshold adaptive to the network state.

(88) FIGS. 13A and 13B are detailed flowcharts illustrating embodiments of FIG. 12.

(89) Referring to FIG. 13A, in operation S201a, a terminal may measure the quality of a signal received from a base station. The quality of the received signal may be an indicator for determining a state of a downlink channel. In operation S202a, the terminal may determine whether the measured quality exceeds a third threshold. When a result of operation S202a is 'YES', in operation S203a, the terminal may set a relatively small first threshold (e.g., decrease the first threshold). That is, the terminal may detect the PDCCH relatively easily when the state of the downlink channel is good, and thus a small first threshold may be set to exclude overlapping candidates from blind decoding as many as possible, thereby simplifying a blind decoding operation. When the result of operation S202a is 'NO', in operation S204a, the terminal may set a relatively large first threshold (e.g., increase the first threshold). That is, the terminal may not easily detect the PDCCH when the state of the downlink channel is not good, and thus a large first threshold may be set to perform blind decoding on candidates as many as possible, thereby increasing the probability of success of receiving DCI.

(90) Referring to FIG. 13B, in operation S201b, the terminal may measure a state of a battery. In operation S202b, the terminal may determine whether the remaining battery amount exceeds a fourth threshold. When a result of operation S202b is 'YES', in operation S203b, the terminal may set a relatively large first threshold (e.g., increase the first threshold). That is, because the

remaining battery amount is sufficient, the terminal may perform blind decoding on many candidates, and thus a large first threshold may be set, thereby maximizing or increasing the probability of receiving the DCI. When the result of operation **S202b** is 'NO', in operation **S204b**, the terminal may set a relatively small first threshold (e.g., decrease the first threshold). That is, because the remaining battery amount is not sufficient, the terminal may simplify candidates targeted for blind decoding, thereby reducing power consumed for blind decoding.

(91) However, embodiments of FIGS. **13A** and **13B** are only examples, and the inventive concepts are not limited thereto, and the first threshold may be variously set in consideration of more factors and communication environments.

(92) FIG. **14** is a flowchart illustrating a blind decoding method of a terminal according to embodiments of the inventive concepts.

(93) Referring to FIG. **14**, in operation **S300**, the terminal may select some of candidates overlapping with a currently decoded candidate and exclude the selected candidates from blind decoding. For example, aggregation levels may include first to third aggregation levels, as a result of performing decoding on the first aggregation level first, when it is determined that a first candidate of the first aggregation level has a good CRC, and has a reliability exceeding a first threshold, the terminal may select any one of the second and third aggregation levels and exclude a candidate overlapping with the first candidate among candidates of the selected aggregation level from blind decoding. That is, the terminal may not exclude all candidates overlapping with the currently decoded candidate from blind decoding but select and exclude only some of all the overlapping candidates. In operation **S310**, the terminal may perform decoding on the other candidates that are not excluded.

(94) FIG. **15** is a detailed flowchart illustrating embodiments of FIG. **14**.

(95) Referring to FIG. **15**, in operation **S302**, a terminal may select a candidate exclusion aggregation level based on a network state. In embodiments, the network state may include a state of a downlink channel between the terminal and a base station. As an example, when the state of the downlink channel is not good, the terminal may select a candidate exclusion aggregation level direction so that overlapping candidates of an aggregation level lower than an aggregation level to be currently decoded are excluded. As another example, when the state of the downlink channel is good, the terminal may select the candidate exclusion aggregation level direction so that overlapping candidates of an aggregation level higher than the aggregation level to be currently decoded are excluded. In operation **S304**, the terminal may exclude a candidate based on the selected candidate exclusion aggregation level (e.g., the selected aggregation level direction).

(96) FIGS. **16A** and **16B** are detailed diagrams illustrating embodiments of FIG. **15**. Hereinafter, descriptions redundant with those of FIGS. **6A** and **11** will be omitted.

(97) Referring to FIG. **16A**, a terminal may exclude only the candidates #11 and #12 of the aggregation levels '1' and '2' corresponding to a level direction **D1** lower than the aggregation level '4' among the candidates #11, #12, and #14 overlapping with the ninth candidate #13 of the aggregation level '4' on which decoding is currently performed from blind decoding.

(98) Referring to FIG. **16B**, the terminal may exclude only the candidate #14 of the aggregation level '8' corresponding to a level direction **D2** higher than the aggregation level '4' among the candidates #11, #12, and #14 overlapping with the ninth candidate #13 of the aggregation level '4' on which decoding is currently performed from blind decoding.

(99) FIG. **17** is a flowchart illustrating an operating method of a terminal according to embodiments of the inventive concepts.

(100) Referring to FIG. **17**, in operation **S400**, the terminal may perform primary blind decoding on all candidates (e.g., all non-excluded candidates) of aggregation levels based on a decoding priority. In operation **S410**, the terminal may determine whether DCI has been successfully received. When a result of operation **S410** is 'YES', the terminal may end blind decoding in the corresponding TTI. When the result of operation **S410** is 'NO', the terminal may perform second

blind decoding on candidates excluded from first blind decoding in operation S420. In embodiments, second blind decoding may be candidate filtering-based blind decoding in the same manner as, or a similar manner to, first blind decoding. In embodiments, the terminal may perform second blind decoding on all candidates excluded from first blind decoding differently from first blind decoding.

(101) FIGS. **18** and **19** are diagrams illustrating an operating method of a communication system according to embodiments of the inventive concepts.

(102) Referring to FIG. **18**, the communication system may include a base station BS and a first terminal TE1. The first terminal TE1 may receive a first PDCCH from the base station BS. The first terminal TE1 may perform blind decoding to detect the first PDCCH. As described above, the first terminal TE1 may determine a decoding priority with respect aggregation levels based on reference information, and perform candidate filtering-based blind decoding on each of candidates of the aggregation levels according to the decoding priority.

(103) In embodiments, the first terminal TE1 may filter candidates among all candidates assigned from the base station BS to select first filtered candidates, and perform blind decoding on the first filtered candidates. Meanwhile, the first terminal TE1 may adjust the number NO1 of candidates excluded from blind decoding for each TTI according to a network state with the base station BS. For example, the first terminal TE1 may variably adjust the number NO1 by using a method of adaptively setting a first threshold described in FIG. **12**.

(104) Referring to FIG. **19**, the communication system may further include a second terminal TE2. The first terminal TE2 may receive a second PDCCH from the base station BS. The second terminal TE2 may perform blind decoding to detect the second PDCCH. As described above, the second terminal TE2 may determine a decoding priority with respect aggregation levels based on reference information, and perform candidate filtering-based blind decoding on each of candidates of the aggregation levels according to the decoding priority.

(105) In embodiments, the second terminal TE2 may filter candidates among all candidates assigned from the base station BS to select second filtered candidates, and perform blind decoding on the second filtered candidates. Meanwhile, the second terminal TE2 may adjust the number NO2 of candidates excluded from blind decoding for each TTI according to a network state with the base station BS.

(106) In embodiments, the number NO1 of candidates excluded from the first terminal TE1 may be different from the number of candidates NO2 excluded from the second terminal TE2 in consideration of differences in a decoding history of each of the first and second terminals TE1 and TE2, the network state including a state of a downlink channel, etc.

(107) FIG. **20** is a block diagram illustrating an electronic device **1000** according to embodiments of the inventive concepts.

(108) Referring to FIG. **20**, the electronic device **1000** may include a memory **1010**, a processor unit **1020**, an input/output control unit **1040**, a display unit **1050**, an input device **1060**, and/or a communication processing unit **1090**. Here, the electronic device **1000** may include a plurality of memories **1010**. Each element is as follows.

(109) The memory **1010** may include a program storage unit **1011** that stores a program for controlling an operation of the electronic device **1000**, and a data storage unit **1012** that stores data generated during execution of the program. The data storage unit **1012** may store data used for the operation of an application program **1013** and a decoding program **1014**. In embodiments, the data storage unit **1012** may store reference information RI of the electronic device **1000** for blind decoding according to embodiments of the inventive concepts. Also, the reference information RI may be periodically or aperiodically updated.

(110) The program storage unit **1011** may include the application program **1013** and the decoding program **1014**. Here, the program included in the program storage unit **1011** may be expressed as an instruction set. The application program **1013** may include program codes for executing various

applications operating in the electronic device **1000**. That is, the application program **1013** may include codes (or commands) related to various applications driven by the processor **1022**. The decoding program **1014** may include control codes for performing blind decoding according to embodiments of the inventive concepts.

(111) In embodiments, the processor **1022** may determine a decoding priority of aggregation levels by executing the decoding program **1014** and perform candidate filtering-based blind decoding based on the decoding priority.

(112) Meanwhile, the electronic device **1000** may include a communication processing unit **1090** that performs a communication function for sound communication and data communication. The processor **1022** may receive a PDCCH including DCI from a base station through the communication processing unit **1090**.

(113) A peripheral device interface **1023** may control a connection between the input/output control unit **1040**, the communication processing unit **1090**, the processor **1022**, and/or the memory interface **1021**. The processor **1022** may control a plurality of base stations to provide corresponding services using at least one software program. In this regard, the processor **1022** may execute at least one program stored in the memory **1010** to provide a service corresponding to the corresponding program.

(114) The input/output control unit **1040** may provide an interface between an input/output device such as the display unit **1050** and the input device **1060** and the peripheral device interface **1023**. The display unit **1050** displays state information, input characters, moving pictures, still pictures, etc. For example, the display unit **1050** may display application program information driven by the processor **1022**.

(115) The input device **1060** may provide input data generated by selection of an electronic device to the processor unit **1020** through the input/output control unit **1040**. In this case, the input device **1060** may include a keypad including at least one hardware button and a touch pad sensing touch information. For example, the input device **1060** may provide touch information, such as a touch, a touch movement, and a touch release, sensed through the touch pad, to the processor **1022** through the input/output control unit **1040**.

(116) FIG. **21** is a diagram illustrating communication devices performing a decoding operation according to embodiments of the inventive concepts.

(117) Referring to FIG. **21**, a home gadget **2100**, a home appliance **2120**, an entertainment device **2140**, and/or an access point (AP) **2200** may each perform a decoding operation according to embodiments of the inventive concepts. In embodiments, the home gadget **2100**, the home appliance **2120**, the entertainment device **2140**, and/or the AP **2200** may configure an Internet of Things (IoT) network system. It will be understood that the communication devices shown in FIG. **21** are only examples, and other communication devices not shown in FIG. **21** may also include a wireless communication device according to embodiments of the inventive concepts.

(118) Conventional devices for receiving downlink control information from a base station perform blind decoding on all control channel candidates included in each of a plurality of aggregation levels. Accordingly, the conventional devices consume excessive amounts of resources (e.g., power, processor, memory, delay, etc.) during decoding, especially when higher numbers of aggregation levels are used.

(119) However, according to embodiments, improved devices are provided for receiving downlink control information from a base station. For example, the improved devices may decode control channel candidates according to a priority order of aggregation levels based on a decoding history, and exclude an overlapping control channel candidate from the decoding. Accordingly, the improved devices are able to receive the downlink control information while performing fewer decoding operations as compared to the conventional devices. Thus, the improved devices overcome the deficiencies of the conventional devices to reduce resource consumption (e.g., power, processor, memory, delay, etc.) during decoding, especially when higher numbers of aggregation

levels are used.

(120) According to embodiments, operations described herein as being performed by the base station **10**, the terminal **100**, the RFIC **110**, the baseband IC **120**, the processor **130**, the decoding circuit **132**, the electronic device **1000**, the processor unit **1020**, the input/output control unit **1040**, the communication processing unit **1090**, the memory interface **1021**, the processor **1022**, the peripheral device interface **1023**, the home gadget **2100**, the home appliance **2120**, the entertainment device **2140**, and/or the AP **2200** may be performed by processing circuitry. The term ‘processing circuitry,’ as used in the present disclosure, may refer to, for example, hardware including logic circuits; a hardware/software combination such as a processor executing software; or a combination thereof. For example, the processing circuitry more specifically may include, but is not limited to, a central processing unit (CPU), an arithmetic logic unit (ALU), a digital signal processor, a microcomputer, a field programmable gate array (FPGA), a System-on-Chip (SoC), a programmable logic unit, a microprocessor, application-specific integrated circuit (ASIC), etc.

(121) The various operations of methods described above may be performed by any suitable device capable of performing the operations, such as the processing circuitry discussed above. For example, as discussed above, the operations of methods described above may be performed by various hardware and/or software implemented in some form of hardware (e.g., processor, ASIC, etc.).

(122) The software may comprise an ordered listing of executable instructions for implementing logical functions, and may be embodied in any “processor-readable medium” for use by or in connection with an instruction execution system, apparatus, or device, such as a single or multiple-core processor or processor-containing system.

(123) The blocks or operations of a method or algorithm and functions described in connection with embodiments disclosed herein may be embodied directly in hardware, in a software module executed by a processor, or in a combination of the two. If implemented in software, the functions may be stored on or transmitted over as one or more instructions or code on a tangible, non-transitory computer-readable medium. A software module may reside in Random Access Memory (RAM), flash memory, Read Only Memory (ROM), Electrically Programmable ROM (EPROM), Electrically Erasable Programmable ROM (EEPROM), registers, hard disk, a removable disk, a CD ROM, or any other form of storage medium known in the art.

(124) While inventive concepts has been particularly shown and described with reference to embodiments thereof, it will be understood that various changes in form and details may be made therein without departing from the spirit and scope of the following claims.

Claims

1. An operating method of a terminal, the operating method comprising: determining a decoding priority of a plurality of aggregation levels based on reference information, the plurality of aggregation levels corresponding to a downlink control channel; performing candidate filtering-based blind decoding on one or more control channel candidates corresponding to the plurality of aggregation levels according to the decoding priority to obtain a decoding result; and receiving downlink control information based on the decoding result, wherein the plurality of aggregation levels comprise a first aggregation level, a second aggregation level lower than the first aggregation level and a third aggregation level higher than the first aggregation level, and the performing candidate filtering-based blind decoding comprises performing decoding on a first control channel candidate of the first aggregation level to obtain a first decoding result, the first control channel candidate being among the one or more control channel candidates, and selecting one among a second control channel candidate of the second aggregation level and a third control channel candidate of the third aggregation level to be excluded from blind decoding based on a network state in response to determining the first decoding result exceeds a first threshold, the network state

corresponding to a comparison result between a measured signal quality and a second threshold, wherein the first control channel candidate overlaps with the second and third control channel candidates.

2. The operating method of claim 1, wherein the reference information comprises a blind decoding history in at least one previous transmission time interval (TTI), the blind decoding history indicating a number of control channel candidates corresponding to a successfully verified cyclic redundancy check (CRC) for each of the plurality of aggregation levels.
3. The operating method of claim 1, wherein the reference information indicates a frequency of use of a format by a base station to transmit the downlink control channel.
4. The operating method of claim 1, wherein the reference information indicates a state of a downlink channel with a base station, the downlink control channel being received from the base station.
5. The operating method of claim 1, wherein the plurality of aggregation levels further comprise a fourth aggregation level; and the performing candidate filtering-based blind decoding further comprises excluding at least one fourth control channel candidate overlapping with the first control channel candidate among a plurality of fourth control channel candidates included in the fourth aggregation level from the candidate filtering-based blind decoding based on the first decoding result.
6. The operating method of claim 5, wherein the excluding the at least one fourth control channel candidate excludes the at least one fourth control channel candidate in response to determining the first decoding result indicates a successful CRC verification and that a reliability exceeds the first threshold.
7. The operating method of claim 6, wherein the receiving the downlink control information receives the downlink control information using a particular control channel candidate corresponding to a successful CRC verification and having a reliability exceeding a third threshold.
8. The operating method of claim 7, wherein the first threshold is different from the third threshold.
9. The operating method of claim 5, wherein the performing the candidate filtering-based blind decoding performs decoding on remaining ones of the plurality of fourth control channel candidates other than the at least one fourth control channel candidate.
10. The operating method of claim 5, further comprising: performing candidate filtering-based blind decoding on the at least one fourth control channel candidate in response to a failure to receive the downlink control information.
11. The operating method of claim 1, wherein the first threshold is variably set based on the network state.
12. The operating method of claim 1, wherein the first threshold is variably set based on a state of battery of the terminal.
13. A terminal comprising: processing circuitry configured to, determine a decoding priority with respect to a plurality of aggregation levels based on reference information, the plurality of aggregation levels corresponding to a downlink control channel, perform candidate filtering-based blind decoding on one or more control channel candidates corresponding to the plurality of aggregation levels according to the decoding priority to obtain a decoding result, and receive downlink control information based on the decoding result, wherein the plurality of aggregation levels comprise a first aggregation level, a second aggregation level lower than the first aggregation level and a third aggregation level higher than the first aggregation level, and the processing circuitry is configured to perform the candidate filtering-based blind decoding including performing decoding on a first control channel candidate of the first aggregation level to obtain a first decoding result, the first control channel candidate being among the one or more control channel candidates, and select one among a second control channel candidate of the second aggregation level and a third control channel candidate of the third aggregation level to be excluded from blind decoding based on a network state in response to determining the first decoding result

exceeds a first threshold, the network state corresponding to a comparison result between a measured signal quality and a second threshold, wherein the first control channel candidate overlaps with the second and third control channel candidates.

14. The terminal of claim 13, wherein the reference information comprises history information indicating results of blind decoding in at least one previous transmission time interval (TTI) or indicating a frequency of use of formats by a base station to transmit the downlink control channel.

15. The terminal of claim 13, wherein the reference information indicates a state of a downlink channel with a base station, the downlink control channel being received from the base station.

16. The terminal of claim 13, wherein the processing circuitry is configured to exclude at least one control channel candidate among the one or more control channel candidate overlapping with a first control channel candidate among the one or more control channel candidate, the first control channel candidate corresponding to a successful cyclic redundancy check (CRC) verification and having a reliability exceeding the first threshold.

17. The terminal of claim 16, wherein the processing circuitry is configured to variably set the first threshold based on the network state.

18. The terminal of claim 16, wherein the processing circuitry is configured to: select a candidate exclusion aggregation level direction based on the network state; and exclude the at least one control channel candidate based on the candidate exclusion aggregation level direction.

19. The terminal of claim 16, wherein the processing circuitry is configured to perform candidate filtering-based blind decoding on the at least one control channel candidate in response to a failure to receive the downlink control information.

20. A communication system comprising: a base station; and a first terminal connected to the base station, wherein the base station is configured to transmit a first downlink control channel to the first terminal, and wherein the first terminal is configured to perform first candidate filtering-based blind decoding on a plurality of first control channel candidates corresponding to a plurality of aggregation levels based on a first priority, the plurality of aggregation levels corresponding to the first downlink control channel, and receive first downlink control information, wherein the plurality of aggregation levels comprise a first aggregation level, a second aggregation level lower than the first aggregation level and a third aggregation level higher than the first aggregation level, and the first terminal is configured to perform the first candidate filtering-based blind decoding including performing decoding on a first control channel candidate of the first aggregation level to obtain a first decoding result, the first control channel candidate being among the plurality of first control channel candidates, and select one among a second control channel candidate of the second aggregation level and a third control channel candidate of the third aggregation level to be excluded from blind decoding based on a network state in response to determining the first decoding result exceeds a first threshold, the network state corresponding to a comparison result between a measured signal quality and a second threshold, wherein the first control channel candidate overlaps with the second and third control channel candidates.
