

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250287142

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

Li; Chunjian et al.

Sound Generation Apparatus and Electronic Device

Abstract

A sound generation apparatus comprises a transducer, a driving apparatus, and a control circuit. The driving apparatus is connected to the transducer. The control circuit is electrically connected to the transducer and the driving apparatus. The control circuit is configured to drive a vibration member of the transducer to vibrate, and the control circuit is further configured to control the driving apparatus to drive the transducer to perform periodic motion. The transducer is disposed to emit a first sound wave to the outside while performing periodic motion.

Inventors: Li; Chunjian (Shanghai, CN), Chen; Jiayi (Beijing, CN), Ding; Yujiang (Shanghai, CN), Huang; Zhen (Shanghai, CN), Pan; Chunjiao (Beijing, CN), Hu; Chengbo (Shanghai, CN)

Applicant: Huawei Technologies Co., Ltd. (Shenzhen, CN)

Family ID: 91162303

Appl. No.: 19/219158

Filed: May 27, 2025

Foreign Application Priority Data

CN 202211492788.3

Nov. 25, 2022

CN 202310387490.4

Mar. 31, 2023

Related U.S. Application Data

parent WO continuation PCT/CN2023/128776 20231031 PENDING child US 19219158

Publication Classification

Int. Cl.: H04R1/28 (20060101); **H04R1/02** (20060101); **H04R1/34** (20060101); **H04R3/04** (20060101)

U.S. Cl.:

CPC H04R1/2826 (20130101); **H04R1/025** (20130101); **H04R1/028** (20130101); **H04R1/288** (20130101); **H04R1/345** (20130101); **H04R3/04** (20130101); H04R2499/11 (20130101)

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This is a continuation of International Patent Application No. PCT/CN2023/128776 filed on Oct. 31, 2023, which claims priority to Chinese Patent Application No. 202211492788.3 filed on Nov. 25, 2022 and Chinese Patent Application No. 202310387490.4 filed on Mar. 31, 2023. All of the aforementioned patent applications are hereby incorporated by reference in their entireties.

TECHNICAL FIELD

[0002] This application relates to the field of audio technologies, and in particular, to a sound generation apparatus and an electronic device.

BACKGROUND

[0003] Microspeakers are widely used in many current consumer electronic products, providing audio entertainment and enhancing audio experience for a vast quantity of consumers.

[0004] In terms of physics teaching of sound wave propagation, in a human audible frequency range (usually 20 hertz (Hz) to 20 kilohertz (kHz)), sound pressure generated when another speaker drives a diaphragm to vibrate may be expressed as $P = \rho S \cdot d / 2\pi r A$, where $S \cdot d$ is a surface area of the diaphragm, and A is acceleration of the diaphragm. That is, the sound pressure P is directly proportional to a product of the surface area $S \cdot d$ of the diaphragm and the acceleration A of the diaphragm. In addition, a relationship between displacement D of the diaphragm and the acceleration A of the diaphragm may be expressed as $A = -\omega^2 D$, where ω is an angular frequency of a sound wave. An air push volume caused when the other speaker drives the diaphragm to vibrate is $V = D \cdot S \cdot d$. Therefore, the sound pressure may be rewritten as $P = -\rho \omega^2 / 2\pi r V$. That is, the sound pressure is directly proportional to the air push volume V and directly proportional to a square of the angular frequency ω .

[0005] For example, in another electrodynamic speaker, a coil and a magnet are configured to generate a driving force for a diaphragm. A 1-kHz sound is generated when the diaphragm vibrates at 1 kHz over a specific surface area, and a 100-Hz sound is generated when the diaphragm vibrates at 100 Hz. If sound pressure levels (SPLs) at the two frequencies are the same, an air push volume required at 100 Hz is 100 times that required at 1 KHz. In other words, if the air push volumes at the two frequencies are the same, the sound pressure level at 100 Hz is 40 decibels (dB) less than that at 1 KHz.

[0006] In the other electrodynamic speaker, there is consistent displacement and a consistent air push volume for the diaphragm in a low frequency interval before a resonance frequency. Therefore, as an observation frequency is doubled, the sound pressure level is increased by 12 dB. In other words, as the observation frequency is halved, the sound pressure level is decreased by 12 dB. For example, if a sound pressure level of another speaker at 400 Hz is 90 dB under a test condition, a sound pressure level at 200 Hz is 78 dB under the same test condition. Therefore, the other speaker has a distinct low-frequency extension characteristic, a low-frequency roll-off reaches-12 dB, and a slope is large, resulting in an insufficient low-frequency sound pressure level of the speaker.

[0007] To increase the low-frequency sound pressure level of the speaker and improve audio experience, the displacement D of the diaphragm or the surface area A of the diaphragm needs to be increased. An increase in the surface area A of the diaphragm results in an increase in lateral space of the speaker, and an increase in the displacement D of the diaphragm results in an increase in longitudinal space of the speaker. Both the two manners require larger space of the speaker. Consequently, the speaker has an excessively large volume and cannot be stacked into an electronic product with a small volume. Therefore, how to increase the low-frequency sound pressure level of the speaker with a limited volume is an urgent problem to be resolved in the industry.

SUMMARY

[0008] This application provides a sound generation apparatus and an electronic device in which the sound generation apparatus is used. The sound generation apparatus has a small volume, and a low-frequency sound pressure level of an audible sound that can be formed is high.

[0009] According to a first aspect, this application provides a sound generation apparatus. The sound generation apparatus includes a transducer, a driving apparatus, and a control circuit. The driving apparatus is connected to the transducer. The control circuit is electrically connected to the transducer and the driving apparatus. The control circuit is configured to drive a vibration member of the transducer to vibrate, and the control circuit is further configured to control the driving apparatus to drive the transducer to perform periodic motion.

[0010] It may be understood that the sound generation apparatus no longer uses another speaker structure, but instead the transducer is disposed to emit a first sound wave to the outside while performing periodic motion. In this case, a sound pressure amplitude at least one position in space changes, and the first sound wave is modulated to form a second sound wave. The second sound wave may include an audible sound.

[0011] In some implementations, the transducer may send an ultrasonic wave to the outside while performing periodic motion at a frequency greater than or equal to 20 kHz. In this case, because the ultrasonic wave has specific directivity, main lobe energy of the ultrasonic wave moves synchronously in a moving process, so that a sound wave amplitude at least one position in the space changes. In this way, the ultrasonic wave can be modulated in the space to form the second sound wave. The second sound wave may include an audible sound.

[0012] It may be understood that compared with another speaker that generates a sound at a same sound pressure level, vibration displacement of the vibration member of the transducer in this implementation is less than vibration displacement of a diaphragm of the other speaker.

[0013] It may be understood that the sound generation apparatus may obtain an audible sound at a high sound pressure level through small displacement vibration of the vibration member of the ultrasonic transducer. A low-frequency response of the sound generation apparatus has no or basically has no roll-off characteristic, a low-frequency roll-off of the sound generation apparatus is significantly less than 12 dB, and the sound generation apparatus can have a high low-frequency sound pressure level in a case of a small volume. The sound generation apparatus with a small volume has wider applicability in scenarios with space requirements. In addition, the sound generation apparatus may be used in a back cavity with a limited volume, and may still achieve strong low-frequency performance.

[0014] In addition, the audible sound formed by modulating the first sound wave may have sound wave directivity. Therefore, the sound generation apparatus may be suitable for some private scenarios. The sound generation apparatus may play a sound in a specific direction or toward a specific user. For example, in a private call scenario, when a user makes a call and does not want another person to hear a downlink sound of the call, the sound has directivity, so that the sound is emitted only toward the user and cannot be heard by a surrounding person. For another example, in a music exclusive scenario, when another person rests around and a user wants to enjoy audio and video entertainment, the sound has directivity, so that the sound is emitted only toward the user and cannot be heard by a surrounding person, so as not to disturb the surrounding person.

[0015] In a possible implementation, the control circuit controls the driving apparatus to drive the transducer to perform continuous rotation, reciprocating rotation, or reciprocating translational motion.

[0016] It may be understood that the transducer may emit a first sound wave to the outside while performing continuous rotation, reciprocating rotation, or reciprocating translational motion. In this case, a sound pressure amplitude at least one position in space changes, and the first sound wave is modulated to form a second sound wave. The second sound wave may include an audible sound. A frequency of the audible sound may be less than a frequency of the first sound wave.

[0017] In some implementations, the transducer may send an ultrasonic wave to the outside while performing continuous rotation, reciprocating rotation, or reciprocating translational motion at a frequency greater than or equal to 20 kHz. In this case, because the ultrasonic wave has specific directivity, main lobe energy of the ultrasonic wave moves synchronously in a moving process, so that a sound wave amplitude at least one position in the space changes. In this way, the ultrasonic wave can be modulated in the space to form the second sound wave. The second sound wave may include an audible sound.

[0018] In a possible implementation, when the control circuit controls the driving apparatus to drive the transducer to perform continuous rotation or reciprocating rotation, a rotating shaft of the transducer is parallel to a plane on which the transducer is located, or a rotating shaft of the transducer intersects with the transducer, or a rotating shaft of the transducer is perpendicular to the transducer, and the rotating shaft of the transducer deviates from a center of the transducer. In this way, the transducer may emit a first sound wave to the outside while performing continuous rotation, reciprocating rotation, or reciprocating translational motion. In this case, a sound pressure amplitude at least one position in space may change.

[0019] In a possible implementation, the sound generation apparatus further includes a base, and the transducer is disposed on the base; and the driving apparatus includes a first cantilever and a second cantilever, a movable end of the first cantilever is connected to a first side of the base, and a movable end of the second cantilever is connected to a second side of the base; and the control circuit is configured to drive the movable end of the first cantilever and the movable end of the second cantilever to perform reciprocating vibration, and in a same time period, vibration directions of the movable end of the first cantilever and the movable end of the second cantilever are opposite.

[0020] It may be understood that the movable end of the first cantilever drives the first side of the base to perform reciprocating vibration, the movable end of the second cantilever drives the second side of the base to perform reciprocating vibration, and in the same time period, the vibration directions of the movable end of the first cantilever and the movable end of the second cantilever are opposite, so that the base can perform periodic motion of reciprocating rotation around a virtual rotating shaft.

[0021] It may be understood that the movable end of the first cantilever drives the first side of the base to perform reciprocating vibration, and the movable end of the second cantilever drives the second side of the base to perform reciprocating vibration, so that the base can perform reciprocating rotation at a high frequency.

[0022] In a possible implementation, a rotation angle of the base is θ , and θ satisfies: $-45^\circ \leq \theta \leq 45^\circ$.

[0023] It may be understood that when the base drives the transducer to rotate within $-45^\circ \leq \theta \leq 45^\circ$, it can be ensured that the audible sound generated by the sound generation apparatus has good linearity and very high energy.

[0024] In a possible implementation, the sound generation apparatus further includes a base, and the transducer is disposed on the base; and the driving apparatus includes a first motor, and a first output shaft of the first motor is connected to the base, and is configured to drive the base to perform reciprocating rotation or continuous rotation.

[0025] In a possible implementation, there are a plurality of transducers, and the plurality of transducers are arranged on the base at an interval in a rotation direction.

[0026] It may be understood that the first sound wave jointly emitted by the plurality of transducers has a plurality of side lobes or a plurality of beams. In this way, a requirement for a rotation frequency can be greatly lowered. For example, if there are n transducers and n side lobes, an equivalent rotation frequency of the n side lobes in a rotation process is $n \times f$. Therefore, the n side lobes can reduce the rotation frequency to $f \cdot \frac{2}{n}$.

[0027] In a possible implementation, the sound generation apparatus further includes a base, and the transducer is disposed on the base; and the driving apparatus includes a telescopic arm, the telescopic arm is connected to the base, and the telescopic arm extends and retracts to drive the base to perform reciprocating translational motion.

[0028] It may be understood that the telescopic arm extends and retracts to drive the base to perform reciprocating translational motion, so that the base can perform a reciprocating translational motion at a high frequency.

[0029] In a possible implementation, the control circuit is configured to generate a first control signal and a second control signal, the first control signal is configured to drive the vibration member of the transducer to vibrate to generate a first sound wave, and the second control signal is configured to control the driving apparatus to drive the transducer to perform periodic motion to modulate the first sound wave, to form a second sound wave.

[0030] In a possible implementation, a frequency of the first control signal includes a first frequency $f_{\text{sub.1}}$, and the first frequency $f_{\text{sub.1}}$ is a single frequency or a wide band; and a frequency of the second control signal includes a second frequency $f_{\text{sub.2}}$, and the second frequency $f_{\text{sub.2}}$ is a single frequency or a wide band.

[0031] It may be understood that the transducer is disposed to emit the first sound wave at the first frequency of $f_{\text{sub.1}}$ to the outside while performing periodic motion at the second frequency of $f_{\text{sub.2}}$. In this case, in a process of periodic motion of the transducer, a sound pressure amplitude received at least one position in the space changes, and in this case, the first sound wave is modulated to form the second sound wave. The second sound wave may include sound waves at two frequencies, and the frequencies of the sound waves are respectively $|f_{\text{sub.1}} + f_{\text{sub.2}}|$ and $|f_{\text{sub.1}} - f_{\text{sub.2}}|$. In this way, values of the first frequency $f_{\text{sub.1}}$ and the second frequency $f_{\text{sub.2}}$ may be set, so that a frequency of one sound wave in the second sound wave falls within a range of an ultrasonic wave, and a frequency of the other sound wave falls within a frequency range of an audible sound. Because the ultrasonic wave may be automatically filtered out by a human ear, the user may hear one sound wave in the space, and the sound wave is an audible sound.

[0032] In a possible implementation, at least a part of the second sound wave includes an audible sound, and the first frequency $f_{\text{sub.1}}$ and the second frequency $f_{\text{sub.2}}$ satisfy: $20 \text{ Hz} \leq |f_{\text{sub.1}} - f_{\text{sub.2}}| \leq 20 \text{ kHz}$. In this way, the second sound wave from the sound generation apparatus includes an audible sound, that is, the sound generation apparatus can emit an audible sound.

[0033] In a possible implementation, a frequency of the second sound wave includes $|f_{\text{sub.1}} - f_{\text{sub.2}}|$ and $|f_{\text{sub.1}} + f_{\text{sub.2}}|$.

[0034] In a possible implementation, the first frequency $f_{\text{sub.1}}$ and the second frequency $f_{\text{sub.2}}$ further satisfy: $f_{\text{sub.1}} \geq 20 \text{ kHz}$ and $f_{\text{sub.2}} \geq 20 \text{ kHz}$.

[0035] It may be understood that both $f_{\text{sub.1}}$ and $f_{\text{sub.2}}$ are set to ultrasonic wave frequencies, to ensure that $|f_{\text{sub.1}} + f_{\text{sub.2}}|$ can definitely fall within an ultrasonic wave range, and ensure that a sound wave at the frequency of $|f_{\text{sub.1}} + f_{\text{sub.2}}|$ in the space cannot be heard by a human.

[0036] In addition, because $f_{\text{sub.1}} \geq 20 \text{ kHz}$, the transducer may send an ultrasonic wave to the outside. Because the ultrasonic wave has specific directivity, main lobe energy of the ultrasonic wave moves synchronously in a moving process, so that a sound wave amplitude at least one position in the space changes. In this way, the ultrasonic wave can be modulated in the space to

form the second sound wave. The second sound wave may include an audible sound. In this way, the sound generation apparatus may obtain an audible sound at a high sound pressure level through small displacement vibration of the vibration member of the transducer. A low-frequency response of the sound generation apparatus has no or basically has no roll-off characteristic, a low-frequency roll-off of the sound generation apparatus is significantly less than 12 dB, and the sound generation apparatus can have a high low-frequency sound pressure level in a case of a small volume. The sound generation apparatus with a small volume has wider applicability in scenarios with space requirements. In addition, the sound generation apparatus may be used in a back cavity with a limited volume, and may still achieve strong low-frequency performance.

[0037] In addition, the audible sound formed by modulating the first sound wave with directivity has sound wave directivity. Therefore, the sound generation apparatus may be suitable for some private scenarios. The sound generation apparatus may play a sound in a specific direction or toward a specific user. For example, in a private call scenario, when a user makes a call and does not want another person to hear a downlink sound of the call, the sound has directivity, so that the sound is emitted only toward the user and cannot be heard by a surrounding person. For another example, in a music exclusive scenario, when another person rests around and a user wants to enjoy audio and video entertainment, the sound has directivity, so that the sound is emitted only toward the user and cannot be heard by a surrounding person, so as not to disturb the surrounding person.

[0038] In a possible implementation, the first frequency $f_{\text{sub.1}}$ and the second frequency $f_{\text{sub.2}}$ further satisfy: $|f_{\text{sub.1}}+f_{\text{sub.2}}|\geq 20$ KHz.

[0039] It may be understood that the second sound wave may include sound waves at two frequencies, and the frequencies of the sound waves are respectively $|f_{\text{sub.1}}+f_{\text{sub.2}}|$ and $|f_{\text{sub.1}}-f_{\text{sub.2}}|$. The first frequency $f_{\text{sub.1}}$ and the second frequency $f_{\text{sub.2}}$ are set to further satisfy $|f_{\text{sub.1}}+f_{\text{sub.2}}|\geq 20$ kHz, so that a sound wave at the frequency of $|f_{\text{sub.1}}+f_{\text{sub.2}}|$ can fall within a frequency range of an ultrasonic wave. In this way, the sound wave at the frequency of $|f_{\text{sub.1}}+f_{\text{sub.2}}|$ in the space cannot be heard by a human.

[0040] In a possible implementation, a vibration frequency of the vibration member of the transducer includes the first frequency $f_{\text{sub.1}}$, and the first frequency $f_{\text{sub.1}}$ is a single frequency or a wide band; and a motion frequency of the transducer includes the second frequency $f_{\text{sub.2}}$, and the second frequency $f_{\text{sub.2}}$ is a single frequency or a wide band.

[0041] It may be understood that the transducer is disposed to emit the first sound wave at the first frequency of $f_{\text{sub.1}}$ to the outside while performing periodic motion at the second frequency of $f_{\text{sub.2}}$. In this case, in a process of periodic motion of the transducer, a sound pressure amplitude received at least one position in the space changes, and in this case, the first sound wave is modulated to form the second sound wave. The second sound wave may include sound waves at two frequencies, and the frequencies of the sound waves are respectively $|f_{\text{sub.1}}+f_{\text{sub.2}}|$ and $|f_{\text{sub.1}}-f_{\text{sub.2}}|$. In this way, values of the first frequency $f_{\text{sub.1}}$ and the second frequency $f_{\text{sub.2}}$ may be set, so that a frequency of one sound wave in the second sound wave falls within a range of an ultrasonic wave, and a frequency of the other sound wave falls within a frequency range of an audible sound. Because the ultrasonic wave may be automatically filtered out by a human ear, the user may hear one sound wave in the space, and the sound wave is an audible sound.

[0042] In a possible implementation, at least a part of the second sound wave includes an audible sound, and the first frequency $f_{\text{sub.1}}$ and the second frequency $f_{\text{sub.2}}$ satisfy: $20\text{ Hz}\leq |f_{\text{sub.1}}-f_{\text{sub.2}}|\leq 20$ kHz. In this way, the second sound wave from the sound generation apparatus includes an audible sound, that is, the sound generation apparatus can emit an audible sound.

[0043] In a possible implementation, the frequency of the second sound wave includes $|f_{\text{sub.1}}-f_{\text{sub.2}}|$ and $|f_{\text{sub.1}}+f_{\text{sub.2}}|$.

[0044] In a possible implementation, the sound generation apparatus further includes a casing, the casing is provided with a sound outlet hole, the sound outlet hole communicates with an inner cavity and external space of the casing, both the transducer and the driving apparatus are disposed

in the inner cavity of the casing, and the control circuit is disposed in the inner cavity or the external space of the casing.

[0045] It may be understood that the casing may be configured to provide isolation from, a connection to, and fastening to another part of an electronic device. In addition, the transducer and the driving apparatus are packaged into an integral structure through the casing, to achieve good integrity of the sound generation apparatus. This facilitates adaptation to application of the sound generation apparatus to an integrated machine, that is, facilitates arrangement of the sound generation apparatus in the electronic device.

[0046] In a possible implementation, an included angle between an axial direction of the vibration member of the transducer and an extension direction of the sound outlet hole is α ; and α satisfies: $45^\circ \leq \alpha \leq 135^\circ$.

[0047] It may be understood that α is set to satisfy $45^\circ \leq \alpha \leq 135^\circ$, so that a direction at a higher sound pressure level in the audible sound faces the sound outlet hole of the casing. In this case, a sound pressure level of an audible sound transmitted out of the casing is higher.

[0048] In a possible implementation, the sound generation apparatus further includes a sound-absorbing part, and the sound-absorbing part is disposed on an inner surface of the casing and disposed in a staggered manner with the sound outlet hole.

[0049] It may be understood that the sound-absorbing part is disposed on the inner surface of the casing, and the sound-absorbing part may absorb a sound wave propagated to the inner surface of the casing, to reduce reflection of the sound wave in the casing and reduce distortion of an audible sound.

[0050] In a possible implementation, the casing is provided with a sound wave guiding structure, the sound wave guiding structure is disposed at an interval from the sound outlet hole, and the sound wave guiding structure communicates the inner cavity of the casing with the external space of the casing.

[0051] It may be understood that the sound wave guiding structure may be configured to export a sound wave in the inner cavity of the casing to the external space of the casing. In this way, the sound wave guiding structure may be configured to implement atmospheric pressure balance between the inner cavity of the casing and the outside of the casing, so that the transducer can smoothly vibrate, and a sound wave with a small distortion degree is formed under driving of the first control signal.

[0052] In a possible implementation, the sound wave guiding structure is a hole structure and/or a pipe structure; and a minimum width of the sound wave guiding structure is greater than a thickness $d_{\text{sub} \mu}$ of a viscous layer, and the thickness $d_{\text{sub} \mu}$ of the viscous layer satisfies:

$$[00001] d_{\text{sub} \mu} = 0.22 \text{mm} \times \sqrt{\frac{100 \text{Hz}}{f_1}},$$

where $f_{\text{sub} 1}$ is a frequency of the first sound wave.

[0053] In a possible implementation, the sound generation apparatus further includes an adjustment mechanism, the adjustment mechanism has a first sound output hole, and a size of the first sound output hole is capable of becoming larger or smaller; and the adjustment mechanism is disposed on the casing, and the first sound output hole of the adjustment mechanism communicates with the sound outlet hole of the casing.

[0054] It may be understood that when the size of the first sound output hole of the adjustment mechanism becomes larger, an area of a channel in which the audible sound is conducted is large. In this way, the audible sound is not prone to diffraction at the first sound output hole. Therefore, directivity of the audible sound conducted to the casing is not prone to change. When the size of the first sound output hole of the adjustment mechanism becomes smaller, an area of a channel in which the audible sound is conducted is small. In this way, the audible sound is prone to diffraction at the first sound output hole. Therefore, directivity of the audible sound conducted to the casing is prone to change.

[0055] It may be understood that when low-frequency directivity is required, an area of the first

sound output hole is increased. A suitable scenario herein may be that the sound generation apparatus plays a sound in a specific direction or toward a specific user. For example, in a private call scenario, when a user makes a call and does not want another person to hear a downlink sound of the call, an aperture of the first sound output hole is adjusted to be larger, and the sound has directivity, so that the sound is emitted only toward the user and cannot be heard by a surrounding person. For another example, in a music exclusive scenario, when another person rests around and a user wants to enjoy audio and video entertainment, an aperture of the first sound output hole is adjusted to be larger, and the sound has directivity, so that the sound is emitted only toward the user and cannot be heard by a surrounding person, so as not to disturb the surrounding person.

[0056] When low-frequency directivity is not required, an area of the first sound output hole is decreased. A suitable scenario herein may be that the sound generation apparatus plays a sound toward users in a plurality of directions. For example, when people around a user want to listen to the sound together, the first sound output hole may be adjusted to be smaller, and the audible sound has no directivity, so that all people around the user can hear the sound.

[0057] In a possible implementation, the sound generation apparatus further includes a front cavity filter, the front cavity filter is fastened to the casing, and a second sound output hole of the front cavity filter communicates with the sound outlet hole of the casing; and a hole wall of the second sound output hole is of a variable cross-sectional structure, or the second sound output hole has a Helmholtz resonator.

[0058] It may be understood that the sound generation apparatus may generate at least two sound wave frequencies, for example, $|f_{\text{sub.1}} + f_{\text{sub.2}}|$ and $|f_{\text{sub.1}} - f_{\text{sub.2}}|$. An undesired sound wave frequency in the space may be filtered out through the front cavity filter, to leave a sound wave at one frequency. For example, a sound wave at the frequency of $|f_{\text{sub.1}} + f_{\text{sub.2}}|$ may be filtered out, to retain a sound wave at $|f_{\text{sub.1}} - f_{\text{sub.2}}|$; or a sound wave at the frequency of $|f_{\text{sub.1}} - f_{\text{sub.2}}|$ may be filtered out, to retain a sound wave at $|f_{\text{sub.1}} + f_{\text{sub.2}}|$.

[0059] In a possible implementation, a phase $q(r)$ of the first sound wave transmitted by the vibration member of the transducer satisfies:

$$[00002] \quad q(r) = \frac{2}{\Delta} * (\sqrt{f^2 + r^2} - f)$$

[0060] Herein, r is a distance between any point on the vibration member and a center of the vibration member, Δ is a wavelength corresponding to the first sound wave emitted by the vibration member, and f is a focal length corresponding to the first sound wave emitted by the vibration member.

[0061] It may be understood that when the phase $q(r)$ of the sound wave emitted by the vibration member satisfies the foregoing relational expression, the phase of the sound wave emitted by the vibration member may be focused, to enhance directivity of the sound wave emitted by the vibration member and increase a sound pressure level of the audible sound.

[0062] In a possible implementation, the transducer may further include a sound wave directing member, and the sound wave directing member is disposed on the vibration member of the transducer; and an emission surface of the sound wave directing member is in a conical shape.

[0063] It may be understood that the sound wave directing member is configured to limit a radiation direction of the first sound wave generated by the transducer, to enhance the directivity of the sound wave emitted by a diaphragm and increase the sound pressure level of the audible sound. In addition, the conical emission surface can narrow the directivity of the first sound wave to approximately 60° , to greatly enhance the directivity of the sound wave emitted by the diaphragm.

[0064] In a possible implementation, the base is provided with accommodation space, and at least a part of the transducer is located in the accommodation space.

[0065] It may be understood that there is an overlapping region between the transducer and the base in a thickness direction, to facilitate thinning of the sound generation apparatus in the thickness direction.

[0066] In a possible implementation, the base is a part of the transducer, and the base is provided with accommodation space; and the vibration member of the transducer is connected to a wall surface of the accommodation space through a connecting piece.

[0067] It may be understood that the vibration member of the transducer is connected to the wall surface of the accommodation space through the connecting piece, so that the transducer may not include a support member. In this way, the transducer and the base may form an integral structure. The transducer can save a structure of the support member, so that the transducer and the base are arranged more compactly and the sound generation apparatus has a simpler structure.

[0068] According to a second aspect, this application provides an electronic device. The electronic device includes the sound generation apparatus described above. The electronic device may emit an audible sound, and the audible sound has a high sound pressure level.

Description

BRIEF DESCRIPTION OF DRAWINGS

[0069] FIG. 1 is a diagram of a partial structure of an electronic device according to an embodiment of this application;

[0070] FIG. 2 is a block diagram of a sound generation apparatus in some embodiments according to an embodiment of this application;

[0071] FIG. 3 is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. 2 in an implementation;

[0072] FIG. 4 is a diagram of a structure of a transducer shown in FIG. 3 in an implementation;

[0073] FIG. 5 is a diagram of a sound wave emitted by the transducer shown in FIG. 4 in an implementation;

[0074] FIG. 6 is a first diagram of a sound generation principle of the sound generation apparatus shown in FIG. 3;

[0075] FIG. 7 is a diagram of energy distribution of a sound wave emitted by the sound generation apparatus shown in FIG. 3 and energy distribution of a main lobe of a first sound wave emitted by a transducer;

[0076] FIG. 8 is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. 2 in another implementation;

[0077] FIG. 9 is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. 2 in still another implementation;

[0078] FIG. 10 is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. 2 in still another implementation;

[0079] FIG. 11A is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. 2 in still another implementation;

[0080] FIG. 11B is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. 2 in still another implementation;

[0081] FIG. 12 is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. 2 in still another implementation;

[0082] FIG. 13A is a partial cross-sectional view of an implementation of the sound generation component shown in FIG. 12 along a line A-A;

[0083] FIG. 13B is a partial cross-sectional view of another implementation of the sound generation component shown in FIG. 12 along a line A-A;

[0084] FIG. 14 is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. 2 in still another implementation;

[0085] FIG. 15 is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. 2 in still another implementation;

[0086] FIG. **16** is a partial cross-sectional view of an implementation of the sound generation component shown in FIG. **15** along a line B-B;

[0087] FIG. **17** is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. **2** in still another implementation;

[0088] FIG. **18** is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. **2** in still another implementation;

[0089] FIG. **19** is a partial cross-sectional view of an implementation of the sound generation component shown in FIG. **18** along a line C-C;

[0090] FIG. **20** is a diagram of a structure of an ultrasonic transducer in some embodiments according to an embodiment of this application;

[0091] FIG. **21** is a schematic cross-sectional view of a sound generation component of the sound generation apparatus shown in FIG. **2** in still another implementation;

[0092] FIG. **22** is a schematic cross-sectional view of a sound generation component of the sound generation apparatus shown in FIG. **2** in still another implementation;

[0093] FIG. **23** is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. **2** in still another implementation;

[0094] FIG. **24** is a diagram of energy distribution of a main lobe of a first sound wave emitted by a plurality of transducers shown in FIG. **23**;

[0095] FIG. **25** is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. **2** in still another implementation; and

[0096] FIG. **26** is a diagram of a structure of a sound generation component of the sound generation apparatus shown in FIG. **2** in still another implementation.

DESCRIPTION OF EMBODIMENTS

[0097] The following describes technical solutions of embodiments of this application with reference to accompanying drawings. In the descriptions of embodiments of this application, unless otherwise specified, “/” represents “or”. For example, A/B may represent A or B. In this specification, “and/or” is merely an association relationship for describing associated objects, and represents that three relationships may exist. For example, A and/or B may represent the following three cases: Only A exists, both A and B exist, and only B exists. In addition, in the descriptions of embodiments of this application, “a plurality of” means two or more.

[0098] In the following, terms such as “first” and “second” are used only for description purposes, and cannot be understood as an indication or implication of relative importance or an implicit indication of a quantity of indicated technical features. Therefore, a feature limited by “first” or “second” may explicitly or implicitly include one or more features.

[0099] The orientation terms such as “upper”, “lower”, “inner”, “outer”, “side”, “top”, and “bottom” in embodiments of this application are merely directions described with reference to the accompanying drawings. Therefore, the orientation terms are used to better and more clearly describe and understand embodiments of this application, instead of indicating or implying that a specified apparatus or element needs to have a specific orientation, or be constructed and operated in a specific orientation. Therefore, this cannot be understood as a limitation on embodiments of this application.

[0100] In the descriptions of embodiments of this application, it should be noted that unless otherwise explicitly specified and limited, the terms “mounted”, “connected”, “connection”, and “disposed on . . . ” should be understood in a broad sense. For example, a “connection” may be a detachable connection, a non-detachable connection, a direct connection, or an indirect connection implemented through an intermediate medium. A “fixed connection” may mean that parts are connected to each other and a relative position relationship remains unchanged after the parts are connected. A “rotatable connection” may mean that parts are connected to each other and can rotate relative to each other after being connected. A “slidable connection” may mean that parts are connected to each other and can slide relative to each other after being connected. An “electrical

connection” means that an electrical signal may be conducted between each other.

[0101] Embodiments of this application provide a sound generation apparatus and an electronic device in which the sound generation apparatus is used. The sound generation apparatus uses a sound generation method different from that of another speaker. The sound generation apparatus emits a first sound wave at a first frequency of $f_{sub.1}$ to space while performing periodic motion at a second frequency of $f_{sub.2}$ through a transducer, and the first sound wave is modulated in the space, to form a second sound wave. The first frequency $f_{sub.1}$ may be a single frequency or a wide band. The second frequency $f_{sub.2}$ may be a single frequency or a wide band. In addition, the second sound wave may include an audible sound, and a frequency of the audible sound may be less than a vibration frequency of the transducer of the sound generation apparatus. The sound generation apparatus in this application may have a high low-frequency sound pressure level while having a small volume. In addition, the audible sound emitted by the sound generation apparatus has sound directivity, which can satisfy some requirements for private calls, thereby greatly improving user experience. The electronic device may be an electronic device that needs to output audio through the sound generation apparatus, for example, a mobile phone, a tablet, a hearing aid, or a smart wearable device. The smart wearable device may be a smartwatch, augmented reality (AR) glasses, an AR helmet, virtual reality (VR) glasses, or the like. The sound generation apparatus may alternatively be a device that can output an audible sound, for example, a headset or a player. In addition, the sound generation apparatus may be further applied to fields such as a whole house, a smart home, and a vehicle, and is used as an audio device or a part of an audio device.

[0102] FIG. 1 is a diagram of a partial structure of an electronic device **1** according to an embodiment of this application. In the embodiment shown in FIG. 1, an example in which the electronic device **1** is a mobile phone is used for description.

[0103] As shown in FIG. 1, the electronic device **1** includes a sound generation apparatus **100**, a housing **200**, and a screen **300**. Because the sound generation apparatus **100** is an internal component of the electronic device **1**, FIG. 1 schematically shows the sound generation apparatus **100** through a dashed line. It may be understood that FIG. 1 and the following related accompanying drawings merely schematically show some parts included in the electronic device **1000**. Actual shapes, actual sizes, actual positions, and actual structures of these parts are not limited by FIG. 1 and the following accompanying drawings. In addition, when the electronic device **1000** is a device in another form, the electronic device **1000** may not include the housing **200** and the screen **300**.

[0104] The screen **300** is mounted on the housing **200**. The screen **300** and the housing **200** may enclose an inner cavity of the electronic device **1**. The sound generation apparatus **100** may be mounted in the inner cavity of the electronic device **1**. The housing **200** has a sound outlet **201**. The sound outlet **201** communicates with the inner cavity of the electronic device **1** and external space of the electronic device **1**. In this case, a sound emitted by the sound generation apparatus **100** may be transmitted out of the electronic device **1** through the sound outlet **201**. It may be understood that a shape of the sound outlet **201** is not limited to a cylindrical hole shown in FIG. 1. The shape of the sound outlet **201** may alternatively be a special-shaped hole. The sound outlet **201** is not limited to five outlets shown in FIG. 1.

[0105] FIG. 2 is a block diagram of a sound generation apparatus **100** in some embodiments according to an embodiment of this application.

[0106] With reference to FIG. 2, the sound generation apparatus **100** may include a sound generation component **20** (also referred to as a sound generation unit, a sound generation module, or the like), a signal processing circuit **30**, and a control circuit **40**. In another implementation, the sound generation apparatus **100** may further include more or fewer parts. For example, in some embodiments, the sound generation apparatus **100** may further include a casing configured to place the sound generation component **20**, the signal processing circuit **30**, and the control circuit **40**. In

this way, the sound generation component **20**, the signal processing circuit **30**, and the control circuit **40** may be protected through the casing. For another example, in some embodiments, the sound generation apparatus **100** may further include at least one of a micro-electro-mechanical system (MEMS) speaker, a moving iron speaker, and a moving coil speaker. In this case, the sound generation apparatus **100** may have functions of a plurality of sound generation units. In this case, the sound generation apparatus **100** may assume sound generation on a specific frequency band. In another embodiment, the sound generation apparatus **100** may serve as an independent unit to generate a sound and assume full-band sound generation.

[0107] In an implementation, the signal processing circuit **30** is configured to convert an audio signal into an electrical signal. The signal processing circuit **30** may include a chip and a related link configured to perform signal processing, for example, a system on chip (SoC) or a central processing unit (CPU). The audio signal may be output by a sound source. The audio signal may be a digital signal or an analog signal. When the audio signal is an analog signal, the audio signal may be converted into a digital signal by an analog-to-digital conversion circuit. The analog-to-digital conversion circuit may be a part of the signal processing circuit **30**, or may be another circuit independent of the signal processing circuit **30**. This is not strictly limited in this embodiment of this application.

[0108] In addition, the control circuit **40** is electrically connected to the sound generation component **20** and the signal processing circuit **30**. The control circuit **40** may include a circuit structure such as a power amplification chip and a related link. In addition, the control circuit **40** may be configured to form a control signal based on an electrical signal, and send the control signal to the sound generation component **20**. The control signal may have information such as a preset voltage and preset power. The sound generation component **20** is configured to emit a first sound wave based on the control signal. The first sound wave is modulated in space to form a second sound wave. The second sound wave may include an audible sound (a frequency of the audible sound falls within a range of 20 Hz to 20 kHz). A principle of modulating the first sound wave to form an audible sound is described in detail below with reference to related accompanying drawings. Details are not described herein again.

[0109] It may be understood that the sound generation apparatus **100** may be a modular component, and the signal processing circuit **30** and the control circuit **40** of the sound generation apparatus **100** may be integrated into a circuit assembly of the sound generation apparatus **100**. The circuit assembly usually may include one or more circuit boards, one or more chips, and matching elements thereof. Alternatively, in some embodiments, when the sound generation apparatus **100** is used in an electronic device, the signal processing circuit **30** and/or the control circuit **40** of the sound generation apparatus **100** may alternatively be fastened to or integrated into another part of the electronic device. This is not strictly limited in this embodiment of this application.

[0110] FIG. 3 is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. 2 in an implementation.

[0111] As shown in FIG. 3, the sound generation component **20** of the sound generation apparatus **100** includes a base **21**, a transducer **22**, and a driving apparatus **23**.

[0112] The base **21** may be a platform structure. The base **21** includes a first surface **211** and a second surface **212** that are disposed facing away from each other, that is, the first surface **211** and the second surface **212** are disposed back to back. Both the first surface **211** and the second surface **212** may be planar. In addition, a shape of the base **21** is not limited to a disc structure shown in FIG. 3. It may be understood that a specific structure of the base **21** is not specifically limited in this application.

[0113] FIG. 4 is a diagram of a structure of the transducer **22** shown in FIG. 3 in an implementation.

[0114] With reference to FIG. 4 and with reference to FIG. 3, the transducer **22** includes a vibration member **222** and a support member **221**. The vibration member **222** is fastened to the support

member **221**. The vibration member **222** is configured to reciprocally vibrate under driving of the control signal, to form the first sound wave. The first sound wave may be an ultrasonic wave (a sound wave at a frequency greater than 20 kHz). Alternatively, the first sound wave may be a sound wave of an audible sound or a sound wave on another frequency band. When the first sound wave is an ultrasonic wave, the transducer **22** may be referred to as an ultrasonic transducer. The first sound wave may alternatively be a sound wave of an audible sound. In this case, the transducer **22** may be referred to as an audible sound transducer.

[0115] It may be understood that the transducer **22** may use a piezoelectrically driven vibration member, or may use a magnetoelectrically driven vibration member. In addition, the transducer may be a transducer manufactured by using a MEMS process, or may be a transducer of another structure (for example, a moving coil transducer or a moving iron transducer). A structure of the transducer **22** is not specifically limited in this application.

[0116] As shown in FIG. 3 and FIG. 4, the transducer **22** is fastened to the base **21**. For example, the support member **221** of the transducer **22** may be fixedly connected to the first surface **211** of the base **21** by using adhesive or in another manner. The first sound wave emitted by the transducer **22** may be emitted through a side on which the first surface **211** is located.

[0117] In another implementation, when the transducer **22** is of another structure, the transducer **22** and the base **21** may alternatively be connected in another manner.

[0118] As shown in FIG. 3, the driving apparatus **23** may be a vibrating driving apparatus, may be a rotating driving apparatus, or may be a translational driving apparatus. It may be understood that the vibrating driving apparatus may mean that a cantilever of the driving apparatus reciprocally vibrates up and down. The rotating driving apparatus may mean that an output shaft of the driving apparatus may reciprocally rotate at a specific angle, or may continuously rotate at 360°. The translational driving apparatus may mean that the driving apparatus reciprocally moves in one direction.

[0119] In addition, the driving apparatus **23** may be a driving apparatus with a piezoelectric driving force, a driving apparatus with an electromagnetic driving force, a driving apparatus with an electrostatic driving force, or a driving apparatus with a magnetostrictive driving force. It may be understood that a structure of the driving apparatus **23** is not specifically limited in this application.

[0120] The following describes several specific structures of the driving apparatus **23** with reference to related accompanying drawings.

[0121] In an implementation, the driving apparatus **23** may be a driving apparatus **23** with a piezoelectric driving force. Further, the driving apparatus **23** includes a first piezoelectric driving mechanism **23a** and a second piezoelectric driving mechanism **23b**.

[0122] The first piezoelectric driving mechanism **23a** includes a first fixed base **231** and a first cantilever **233**. A first end of the first cantilever **233** is fixedly connected to the first fixed base **231**. A second end of the first cantilever **233** extends relative to the first fixed base **231**. It may be understood that the first end of the first cantilever **233** is a fixed end relative to the first fixed base **231**. The second end of the first cantilever **233** is a movable end relative to the first fixed base **231**. For example, the first cantilever **233** includes a piezoelectric sheet (not shown in the figure). When the piezoelectric sheet is energized, the piezoelectric sheet may be deformed, and the second end of the first cantilever **233** may reciprocally vibrate in a direction of a Z-axis.

[0123] It may be understood that for ease of description, a sound outlet direction of the transducer **22** is defined as the direction of the Z-axis. A length direction of the first cantilever **233** is an X-axis. A Y-axis is perpendicular to the X-axis and the Z-axis. It may be understood that the coordinate system may alternatively be flexibly set based on a specific requirement. This is not specifically limited in this application.

[0124] In addition, the second piezoelectric driving mechanism **23b** includes a second fixed base **232** and a second cantilever **234**. A first end of the second cantilever **234** is fixedly connected to the second fixed base **232**. A second end of the second cantilever **234** extends relative to the second

fixed base **232**. It may be understood that the first end of the second cantilever **234** is a fixed end relative to the second fixed base **232**. The second end of the second cantilever **234** is a movable end relative to the second fixed base **232**. For example, the second cantilever **234** also includes a piezoelectric sheet (not shown in the figure). When the piezoelectric sheet is energized, the piezoelectric sheet may be deformed, and the second end of the second cantilever **234** may reciprocally vibrate in the direction of the Z-axis.

[0125] In this implementation, in a same time period, a vibration direction of the first cantilever **233** is opposite to a vibration direction of the second cantilever **234**. For example, a half period is used as an example for description. During $(0, T/4)$, the first cantilever **233** vibrates in a positive direction of the Z-axis, and the second cantilever **234** vibrates in a negative direction of the Z-axis. During $(T/4, T/2)$, the first cantilever **233** vibrates in the negative direction of the Z-axis, and the second cantilever **234** vibrates in the positive direction of the Z-axis. For example, when the second end of the first cantilever **233** moves in the positive direction of the Z-axis, the second end of the second cantilever **234** moves in the negative direction of the Z-axis, and the second end of the first cantilever **233** and the second end of the second cantilever **234** move in opposite directions.

[0126] As shown in FIG. 3, the base **21** is located between the first piezoelectric driving mechanism **23a** and the second piezoelectric driving mechanism **23b**. The second end (that is, the movable end) of the first cantilever **233** is connected to a first side **213** of the base **21**. The second end (that is, the movable end) of the second cantilever **234** is connected to a second side **214** of the base **21**. For example, both the second end (that is, the movable end) of the first cantilever **233** and the second end (that is, the movable end) of the second cantilever **234** may be connected to the second surface **212** of the base **21**.

[0127] In an implementation, the base **21** and the driving apparatus **23** may alternatively form a modular assembly. Further, the base **21** and the driving apparatus **23** may form an integral structural member, that is, the base **21** is a part of the driving apparatus **23**.

[0128] It may be understood that in the same time period, the vibration direction of the first cantilever **233** is opposite to the vibration direction of the second cantilever **234**, and therefore a movement direction of the first side **213** of the base **21** is opposite to a movement direction of the second side **214** of the base **21**. For example, a half period is used as an example for description. During $(0, T/4)$, the first cantilever **233** drives the first side **213** of the base **21** to vibrate in the positive direction of the Z-axis, and the second cantilever **234** drives the second side **214** of the base **21** to vibrate in the negative direction of the Z-axis. During $(T/4, T/2)$, the first cantilever **233** drives the first side **213** of the base **21** to vibrate in the negative direction of the Z-axis, and the second cantilever **234** drives the second side **214** of the base **21** to vibrate in the positive direction of the Z-axis. In this way, the base **21** can rotate relative to a rotating shaft **G1** (schematically shown through a dashed line in FIG. 3). A connection position between the first cantilever **233** and the base **21** is a first position. A connection position between the second cantilever **234** and the base **21** is a second position. The rotating shaft **G1** may be a virtual axis that passes through centers of the first position and the second position. For example, in the coordinate system in FIG. 3, the rotating shaft **G1** may be a virtual axis that is parallel to the Y-axis and that may pass through a center of the base **21**.

[0129] In an implementation, an angle at which the base **21** drives the transducer **22** to rotate is θ , and θ satisfies: $-45^\circ \leq \theta \leq 45^\circ$, that is, the base **21** may drive the transducer **22** to rotate within $-45^\circ \leq \theta \leq 45^\circ$. For example, θ may be equal to -45° , -30° , -20° , -10° , 10° , 20° , 30° , or 45° . For example, with reference to FIG. 3, $\theta \leq 0^\circ$ may be an angle at which the base **21** rotates counterclockwise on a plane X-Z when the first cantilever **233** drives the first side **213** of the base **21** to vibrate in the positive direction of the Z-axis, and the second cantilever **234** drives the second side **214** of the base **21** to vibrate in the negative direction of the Z-axis; $\theta > 0^\circ$ may be an angle at which the base **21** rotates clockwise on the plane X-Z when the first cantilever **233** drives the first side **213** of the base **21** to vibrate in the negative direction of the Z-axis, and the second cantilever

234 drives the second side **214** of the base **21** to vibrate in the positive direction of the Z-axis; and $\theta=0^\circ$ may mean that the base **21** does not rotate relative to the plane X-Z when the first cantilever **233** does not drive the first side **213** of the base **21** to vibrate along the Z-axis, and the second cantilever **234** does not drive the second side **214** of the base **21** to vibrate along the Z-axis.

[0130] In an implementation, an angle at which the base **21** drives the transducer **22** to rotate is 0, and 0 satisfies: $-30^\circ \leq \theta \leq 30^\circ$, that is, the base **21** may drive the transducer **22** to rotate within $-30^\circ \leq \theta \leq 30^\circ$. For example, 0 may be equal to -30° , -20° , -10° , 10° , 20° , or 30° .

[0131] In an implementation, an angle at which the base **21** drives the transducer **22** to rotate is θ , and θ satisfies: $-10^\circ \leq \theta \leq 10^\circ$, that is, the base **21** may drive the transducer **22** to rotate within $-10^\circ \leq \theta \leq 10^\circ$. For example, θ may be equal to -10° , -5° , 5° , 8° , 10° , or the like. In another implementation, θ may satisfy another range.

[0132] In an implementation, the base **21** and the driving apparatus **23** may alternatively form a modular assembly. Further, the base **21** and the driving apparatus **23** may form an integral structural member, that is, the base **21** is a part of the driving apparatus **23**.

[0133] As shown in FIG. 2 and FIG. 3, the control circuit **40** is electrically connected to the transducer **22** and the driving apparatus **23**. The control circuit **40** is configured to generate a first control signal and a second control signal. It may be understood that the first control signal may include one or more signals, the second control signal may include one or more signals, and the first control signal and the second control signal are different signals.

[0134] In addition, the first control signal is coupled to the transducer **22**, and the first control signal is used to drive the vibration member **222** of the transducer **22** to reciprocally vibrate, so that the transducer **22** generates the first sound wave. It may be understood that the coupling may be a direct electrical connection, or may be an indirect electrical connection. In some implementations, a frequency of the first control signal includes a first frequency $f_{\text{sub.1}}$, and the first frequency $f_{\text{sub.1}}$ is a single frequency or a wide band. For example, the first frequency $f_{\text{sub.1}}$ is a single frequency, and the first frequency $f_{\text{sub.1}}$ may be greater than or equal to 20 kHz. The vibration member **222** of the transducer **22** can reciprocally vibrate under driving of the first control signal, and a vibration frequency of the vibration member **222** may be greater than or equal to 20 kHz, that is, the vibration frequency of the vibration member **222** is an ultrasonic frequency. In this way, the first sound wave is an initial ultrasonic wave.

[0135] It may be understood that in a vibration process of the vibration member **222** of the transducer **22**, the vibration member **222** of the transducer **22** may vibrate at different speeds or at a same speed at different moments or in different time periods.

[0136] In addition, the second control signal is coupled to the driving apparatus **23**. The second control signal is used to control the driving apparatus **23**, to drive the base **21** to drive the transducer **22** to perform periodic motion. In some implementations, a frequency of the second control signal includes a second frequency $f_{\text{sub.2}}$, and the second frequency $f_{\text{sub.2}}$ is a single frequency or a wide band. For example, the second frequency $f_{\text{sub.2}}$ of the second control signal may be greater than or equal to 20 kHz. In this case, the driving apparatus **23** can drive the base **21** to drive the transducer **22** to perform periodic motion, and a frequency of periodic motion between the base **21** and the transducer **22** may be greater than or equal to 20 KHz.

[0137] It may be understood that the periodic motion includes reciprocating rotation, continuous rotation, and reciprocating translation. In a process in which the base **21** drives the transducer **22** to perform periodic motion, speeds at which the base **21** drives the transducer **22** to move may be different or may be the same at different moments or in different time periods.

[0138] Driving apparatuses of different structures may correspond to different periodic motion. For example, the driving apparatus **23** shown in FIG. 3 is used as an example for description. For example, the second control signal is configured to control the movable end of the first cantilever **233** and the movable end of the second cantilever **234** to perform reciprocating vibration. The movable end of the first cantilever **233** and the movable end of the second cantilever **234** drive the

base **21** to drive the transducer **22** to perform reciprocating rotation. In this way, the driving apparatus **23** shown in FIG. 3 may implement periodic motion of reciprocating rotation for the base **21**. That the driving apparatus **23** is configured to implement periodic motion of continuous rotation and reciprocating motion for the base **21** is described in detail below with reference to related accompanying drawings. Details are not described herein again.

[0139] It may be understood that in this implementation, the transducer **22** emits the first sound wave at the first frequency of $f_{\text{sub.1}}$ to the outside while performing periodic motion at the second frequency of $f_{\text{sub.2}}$. In this case, the first sound wave can be modulated in the space to form the second sound wave. The second sound wave may include an audible sound. A frequency of the audible sound may be less than a frequency of the first sound wave. In some implementations, the transducer **22** emits an ultrasonic wave (at a frequency greater than or equal to 20 kHz) to the outside while performing periodic motion at a frequency greater than or equal to 20 kHz. In this case, because the ultrasonic wave has specific directivity, main lobe energy of the ultrasonic wave moves synchronously in a moving process, so that a sound wave amplitude at least one position in the space changes. In this way, the ultrasonic wave can be modulated in the space to form the second sound wave. The second sound wave may include an audible sound.

[0140] With reference to the foregoing accompanying drawings, the following describes in detail a principle of generating an audible sound by the sound generation apparatus **100**.

[0141] FIG. 5 is a diagram of a sound wave emitted by the transducer **22** shown in FIG. 4 in an implementation.

[0142] It is assumed that the frequency of the first control signal includes the first frequency $f_{\text{sub.1}}$, and the first frequency $f_{\text{sub.1}}$ is a single frequency or a wide band. For example, the first control signal V' includes a term (1):

$$[00003] V_1 \sin(2 f_1 t) \quad (1)$$

[0143] Herein, $V_{\text{sub.1}}$ is a constant.

[0144] As shown in FIG. 5, the transducer **22** emits the first sound wave under the driving of the first control signal. In this case, the first sound wave $s(t)$ in the space includes a term (2):

$$[00004] S_0 \sin(2 f_1 t) \quad (2)$$

[0145] Herein, $S_{\text{sub.0}}$ is a constant. It may be learned from the term (2) that the vibration frequency of the vibration member **222** of the transducer **22** includes the first frequency $f_{\text{sub.1}}$, and the first frequency $f_{\text{sub.1}}$ is a single frequency or a wide band.

[0146] It may be learned from FIG. 5 that in the expression of the first sound wave, each moment t corresponds to one sound pressure value $s(t)$, and each sound pressure value $s(t)$ is related to an amplitude $S_{\text{sub.0}}$. For example, when $t=t_{\text{sub.1}}$, $s(t)$ includes $S_{\text{sub.0}} \sin(2\pi f_{\text{sub.1}} t_{\text{sub.1}})$, that is, a moment $t_{\text{sub.1}}$ corresponds to a sound pressure value $s(t_{\text{sub.1}})$, and is related to the amplitude $S_{\text{sub.0}}$. For another example, when $t=t_{\text{sub.2}}$, $s(t)$ includes $S_{\text{sub.0}} \sin(2\pi f_{\text{sub.1}} t_{\text{sub.2}})$, that is, a moment $t_{\text{sub.2}}$ corresponds to a sound pressure value $s(t_{\text{sub.2}})$, and is related to the amplitude $S_{\text{sub.0}}$.

[0147] In addition, it is assumed that the frequency of the second control signal includes the second frequency $f_{\text{sub.2}}$, and the second frequency $f_{\text{sub.2}}$ is a single frequency or a wide band. For example, the second control signal V'' includes a term (3):

$$[00005] V_2 \sin(2 f_2 t) \quad (3)$$

[0148] Herein, $V_{\text{sub.2}}$ is a constant.

[0149] FIG. 6 is a first diagram of a sound generation principle of the sound generation apparatus **100** shown in FIG. 3. As shown in FIG. 6, when the driving apparatus **23** drives, under control of the second control signal at the second frequency of $f_{\text{sub.2}}$, the base **21** to drive the transducer **22** to perform periodic motion, the base **21** drives the transducer **22** to perform periodic motion. The following uses an example in which the base **21** drives the transducer **22** to perform a periodic motion of reciprocating rotation for description.

[0150] In this way, under control of the second frequency f.sub.2 of the second control signal, the angle θ at which the base **21** drives the transducer **22** to rotate includes a term (4):

$$[00006] k_1 V_2 \sin(2 f_2 t) \quad (4)$$

[0151] Herein, k.sub.1 is a constant.

[0152] In addition, it may be learned from the term (4) that a motion frequency of the transducer **22** includes the second frequency f.sub.2, and the second frequency f.sub.2 is a single frequency or a wide band.

[0153] For example, in a process in which the base **21** drives the transducer **22** to perform reciprocating rotation, the angle at which the base **21** drives the transducer **22** to rotate is θ . When $\theta=0^\circ$, the vibration member **222** of the transducer **22** may be parallel to a plane XY. When $\theta=\theta_1$ ($\theta_1 > 0$ or $\theta_1 \leq 0$), the vibration member **222** of the transducer **22** may intersect with or not be parallel to the plane XY. FIG. 6 shows energy distribution of a main lobe of the first sound wave when $\theta=0^\circ$ through a solid line similar to a water drop shape. FIG. 6 shows energy distribution of a main lobe of the first sound wave when $\theta=\theta_1$ through a dashed line similar to a water drop shape.

[0154] It may be understood that it is assumed that the first sound wave is observed at an observation position (the position is shown by using a cross in FIG. 6). When $\theta=0^\circ$, the observation position is located directly in front of a sound output surface of the transducer **22**, and directly faces a position of a sound pressure amplitude 1 of the first sound wave (that is, a position of a maximum value of a sound pressure amplitude), that is, the sound pressure amplitude 1. When $\theta=\theta_1$ ($\theta_1 > 0$ or $\theta_1 \leq 0$), the sound pressure amplitude changes from the sound pressure amplitude 1 to a sound pressure amplitude 2, and the sound pressure amplitude 2 is less than the sound pressure amplitude 1. When the base **21** drives the transducer **22** to perform reciprocating rotation, the sound pressure amplitude reciprocally changes.

[0155] It may be understood that in this implementation, the observation position directly faces the position of the maximum value of the sound pressure amplitude when $\theta=0^\circ$. In another implementation, the observation position may be flexibly set. For example, the observation position may alternatively directly face any position on an edge of energy of the main lobe of the first sound wave when $\theta=0^\circ$, that is, any position on an edge of the water drop shape in FIG. 6. Certainly, in another implementation, the observation position may alternatively directly face any position on the edge of the energy of the main lobe of the first sound wave when $\theta=\theta_1$.

[0156] The transducer **22** is driven by the base **21** to form reciprocating rotation at a frequency of f.sub.2, and a sound pressure amplitude at least one position in the space changes accordingly. It may be obtained that a sound field $s'(t)$ in the space includes a term (5):

$$[00007] S_1 \sin(2 f_1 t) \sin(2 f_2 t) \quad (5)$$

[0157] Herein, S.sub.1 is a constant.

[0158] The term (5) may be converted as follows by using mathematical product-to-sum formulas:

$$[00008] A \cos[2 (f_1 + f_2) t] + B \cos[2 (f_1 - f_2) t] \quad (6)$$

[0159] Herein, A and B are constants.

[0160] In addition, based on the term (6), it may be found that the first sound wave emitted by the transducer **22** is modulated to form the second sound wave. The second sound wave may include at least sound waves at two frequencies, and the frequencies of the sound waves are respectively $|f_{\text{sub.1}} + f_{\text{sub.2}}|$ and $|f_{\text{sub.1}} - f_{\text{sub.2}}|$.

[0161] In some specific embodiments, the transducer **22** is disposed to emit the first sound wave at the first frequency of f.sub.1 to the outside while performing reciprocating rotation at the second frequency of f.sub.2. In this case, in a process of reciprocating rotation of the transducer **22**, a sound pressure amplitude received at least one position in the space changes, and in this case, the first sound wave is modulated to form the second sound wave. The second sound wave may include sound waves at two frequencies. It may be understood that this modulation manner may also be referred to as sound pressure amplitude modulation.

[0162] It may be understood that in the term (5), a value of $S_{\text{sub}.1}$ is related to a rotation angle of the base **21**. A larger rotation angle of the base **21** indicates higher energy of the audible sound. A smaller rotation angle of the base **21** indicates better linearity of the audible sound. In an implementation, when the base **21** drives the transducer **22** to rotate within $-45^\circ \leq \theta \leq 45^\circ$, it can be ensured that the audible sound has good linearity and very high energy. In an implementation, when the base **21** drives the transducer **22** to rotate within $-30^\circ \leq \theta \leq 30^\circ$, the audible sound has good linearity and high energy. In an implementation, when the base **21** drives the transducer **22** to rotate within $-10^\circ \leq \theta \leq 10^\circ$, it can be ensured that the audible sound has high energy and very good linearity.

[0163] It may be understood that it may be learned from the foregoing that the first sound wave emitted by the transducer **22** is modulated to form the second sound wave. The second sound wave may include at least sound waves at two frequencies, and the frequencies of the sound waves are respectively $|f_{\text{sub}.1} + f_{\text{sub}.2}|$ and $|f_{\text{sub}.1} - f_{\text{sub}.2}|$. Therefore, a sound wave at the frequency of $|f_{\text{sub}.1} + f_{\text{sub}.2}|$ may be filtered out by using a sound wave filtering technology, to retain a sound wave at $|f_{\text{sub}.1} - f_{\text{sub}.2}|$. Alternatively, a sound wave at the frequency of $|f_{\text{sub}.1} - f_{\text{sub}.2}|$ is filtered out, to retain a sound wave at $|f_{\text{sub}.1} + f_{\text{sub}.2}|$.

[0164] In some implementations, values of the first frequency $f_{\text{sub}.1}$ and the second frequency $f_{\text{sub}.2}$ may be set, so that a frequency of one sound wave in the second sound wave falls within a range of an ultrasonic wave, and a frequency of the other sound wave falls within a frequency range of an audible sound. In this way, because the ultrasonic wave may be automatically filtered out by a human ear, the user may hear one sound wave in the space, and the sound wave is an audible sound.

[0165] It may be understood that to more concisely determine a relationship between the frequencies of $|f_{\text{sub}.1} - f_{\text{sub}.2}|$ and $|f_{\text{sub}.1} + f_{\text{sub}.2}|$, the expressions of the two frequencies are further simplified. Further, $f_{\text{sub}.1} = f_{\text{sub}.0}$ Hz and $f_{\text{sub}.2} = (f_{\text{sub}.0} - \Delta)$ Hz are defined. In this way, $|f_{\text{sub}.1} + f_{\text{sub}.2}| = (2f_{\text{sub}.0} - \Delta)$ Hz and $|f_{\text{sub}.1} - f_{\text{sub}.2}| = \Delta$ Hz.

[0166] In an implementation, Δ is set to be in a range of 20 to 48000, that is, $20 \leq \Delta \leq 48000$. For example, Δ may be 20, 200, 2000, 24000, 48000, or the like. In this way, in this case, the frequency of $|f_{\text{sub}.1} - f_{\text{sub}.2}|$ falls within a range of 20 Hz to 48 KHz.

[0167] In an implementation, Δ is set to be in a range of 20 to 24000, that is, $20 \leq \Delta \leq 24000$. For example, Δ may be 20, 200, 2000, 24000, or the like. In this way, in this case, the frequency of $|f_{\text{sub}.1} - f_{\text{sub}.2}|$ falls within a range of 20 Hz to 24 kHz.

[0168] In an implementation, Δ is set to be in a range of 20 to 20000, that is, $20 \leq \Delta \leq 20000$. For example, Δ may be 20, 200, 2000, 20000, or the like. In this way, the frequency of $|f_{\text{sub}.1} - f_{\text{sub}.2}|$ falls within a range of 20 Hz to 20 kHz, that is, a sound wave at the frequency of $|f_{\text{sub}.1} - f_{\text{sub}.2}|$ may fall within a frequency range of an audible sound. In this case, at least a part of the second sound wave includes an audible sound. In another implementation, Δ may alternatively be another value.

[0169] In an implementation, $(2f_{\text{sub}.0} - \Delta)$ is set to be greater than 20000, that is, $(2f_{\text{sub}.0} - \Delta) \geq 20$ KHz. For example, $(2f_{\text{sub}.0} - \Delta)$ may be 40 kHz, 50 kHz, 80 kHz, or the like. In this way, in this case, the frequency $|f_{\text{sub}.1} + f_{\text{sub}.2}|$ is greater than 20 kHz, that is, a sound wave at the frequency of $|f_{\text{sub}.1} + f_{\text{sub}.2}|$ can fall within a frequency range of an ultrasonic wave, and the sound wave at the frequency of $|f_{\text{sub}.1} + f_{\text{sub}.2}|$ in the space cannot be heard by a human. In another implementation, $(2f_{\text{sub}.0} - \Delta)$ may alternatively be another value.

[0170] In an implementation, both $f_{\text{sub}.1}$ and $f_{\text{sub}.2}$ are ultrasonic frequencies, that is, the first frequency $f_{\text{sub}.1}$ is greater than 20 kHz, and the second frequency $f_{\text{sub}.2}$ is greater than 20 kHz. For example, $f_{\text{sub}.1} = 40$ kHz and $f_{\text{sub}.2} = 30$ kHz. It may be understood that both $f_{\text{sub}.1}$ and $f_{\text{sub}.2}$ are set to ultrasonic wave frequencies, to ensure that $|f_{\text{sub}.1} + f_{\text{sub}.2}|$ can definitely fall within an ultrasonic wave range, and ensure that a sound wave at the frequency of $|f_{\text{sub}.1} + f_{\text{sub}.2}|$ in the space cannot be heard by a human.

[0171] FIG. 7 is a diagram of energy distribution of a sound wave emitted by the sound generation

apparatus **100** shown in FIG. 3 and energy distribution of a main lobe of the first sound wave emitted by the transducer **22**.

[0172] FIG. 7 shows the energy distribution of the main lobe of the first sound wave through a dashed line in a shape of “8”. FIG. 7 shows energy distribution of the audible sound through a solid line in a shape of “8”. It may be understood that the first sound wave has directivity. The first sound wave has greater energy distribution in the direction of the Z-axis, that is, the first sound wave has a higher sound pressure level in the direction of the Z-axis. However, the audible sound formed by modulating the first sound wave has greater energy distribution in a direction of the X-axis, that is, the audible sound has a higher sound pressure level in the direction of the X-axis. Therefore, the audible sound formed by modulating the first sound wave also has sound wave directivity.

Therefore, the sound generation apparatus in this implementation may be suitable for some private scenarios. The sound generation apparatus **100** may play a sound in a specific direction or toward a specific user. For example, in a private call scenario, when a user makes a call and does not want another person to hear a downlink sound of the call, the sound has directivity, so that the sound is emitted only toward the user and cannot be heard by a surrounding person. For another example, in a music exclusive scenario, when another person rests around and a user wants to enjoy audio and video entertainment, the sound has directivity, so that the sound is emitted only toward the user and cannot be heard by a surrounding person, so as not to disturb the surrounding person.

[0173] It may be understood that it may be learned from the derivation process of the formula (1) to the formula (6) that the transducer **22** emits the first sound wave at the first frequency of $f_{sub.1}$ under the driving of the first control signal. For an audio signal that can generate music, the audio signal is a wideband signal. In this case, the first sound wave $s(t)$ includes a term (7):

[00009] $S_0 a(t) \sin(2 f_0 t)$ (7)

[0174] Herein, $a(t)$ is music information, $S_{sub.0}$ is a sound wave amplitude, and $f_{sub.0}$ is a working frequency.

[0175] In addition, because the base **21** rotates at the working frequency of $f_{sub.0}$ to modulate the sound wave, the second sound wave $s'_{sup.}(t)$ includes a term (8):

[00010] $S_1 a(t) \sin(2 f_0 t) \sin(2 f_0 t)$ (8)

[0176] Herein, $S_{sub.1}$ is a constant.

[0177] It may be understood that for generation of the formula (8), refer to the derivation process of the formula (1) to the formula (6). Details are not described herein again.

[0178] The structure and the sound generation principle of the sound generation apparatus **100** are described in detail above with reference to the related accompanying drawings. It may be understood that in this implementation, the sound generation apparatus **100** no longer uses another speaker structure, but instead the transducer **22** is disposed to emit the first sound wave at the first frequency of $f_{sub.1}$ to the outside while performing periodic motion at the second frequency of $f_{sub.2}$. In this case, the first sound wave can be modulated in the space to form the second sound wave. The second sound wave may include an audible sound. In some implementations, the transducer **22** emits an ultrasonic wave (at a frequency greater than or equal to 20 kHz) to the outside while performing periodic motion at a frequency greater than or equal to 20 kHz. In this case, because the ultrasonic wave has specific directivity, main lobe energy of the ultrasonic wave moves synchronously in a moving process, so that a sound wave amplitude at least one position in the space changes. In this way, the ultrasonic wave can be modulated in the space to form the second sound wave. The second sound wave may include an audible sound.

[0179] In some implementations, the first sound wave is an ultrasonic wave, that is, the transducer **22** is an ultrasonic transducer. This is implemented by a vibration action of the vibration member **222** of the transducer **22**. The frequency of the audible sound is less than the frequency of the first sound wave. Therefore, the frequency of the audible sound is less than the vibration frequency of the vibration member **222**. Compared with another speaker that generates a sound at a same sound

pressure level, vibration displacement of the vibration member **222** of the transducer **22** in this implementation is less than vibration displacement of a diaphragm of the other speaker.

[0180] It may be understood that the sound generation apparatus **100** may obtain an audible sound at a high sound pressure level through small displacement vibration of the vibration member **222** of the ultrasonic transducer **22**. A low-frequency response of the sound generation apparatus **100** has no or basically has no roll-off characteristic, a low-frequency roll-off of the sound generation apparatus **100** is significantly less than 12 dB, and the sound generation apparatus **100** can have a high low-frequency sound pressure level in a case of a small volume. The sound generation apparatus **100** with a small volume has wider applicability in scenarios with space requirements.

[0181] It may be understood that the sound generation apparatus **100** in this implementation may be used in a back cavity with a limited volume, and may still achieve strong low-frequency performance.

[0182] In an implementation, Fourier transform is applied to the formula (7), to obtain a frequency domain that includes a term $A(f-f_{sub.0})+A(f+f_{sub.0})$. Herein, $A(f)$ is a spectrum of the music. In addition, there are sound waves on a lower sideband ($f-f_{sub.0}$) and an upper sideband ($f+f_{sub.0}$) near the working frequency $f_{sub.0}$. In this implementation, when the first control signal is provided to the transducer **22**, the first control signal may be filtered, so that the first control signal includes only the upper sideband or the lower sideband, and a sound wave on the corresponding sideband participates in modulation. In this case, the frequency domain of the first control signal may include a term $A(f-f_{sub.0})$ or a term $A(f+f_{sub.0})$.

[0183] In addition, Fourier transform is applied to the term (8), to obtain a frequency domain that includes a term $A(f)+A(f-2f_{sub.0})+A(f+2f_{sub.0})$. It may be learned from this term that the term (8) has a spectrum $A(f)$ of the music.

[0184] A sound generation principle of the transducer **22** is described above with reference to the related accompanying drawings. With reference to related accompanying drawings, the following describes in detail several structures of the driving apparatus **23** for driving the base **21** to perform periodic motion.

[0185] FIG. **8** is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in another implementation.

[0186] In an implementation, the driving apparatus **23** may be a driving apparatus **23** with an electromagnetic driving force. For example, the driving apparatus **23** is a motor, which is also referred to as a motor. In another implementation, the driving apparatus **23** may alternatively be a motor with a piezoelectric driving force. The motor is not specifically limited in this application.

[0187] The driving apparatus **23** includes a first motor **23c** and a second motor **23d**. The first motor **23c** has a first output shaft **235**. When the first motor **23c** is energized, the first output shaft **235** may rotate. The second motor **23d** has a second output shaft **236**. When the second motor **23d** is energized, the second output shaft **236** may rotate.

[0188] In this implementation, the base **21** is located between the first motor **23c** and the second motor **23d**. The first output shaft **235** of the first motor **23c** is connected to the first side **213** of the base **21**. The second output shaft **236** of the second motor **23d** is connected to the second side **214** of the base **21**. For example, the first output shaft **235** of the first motor **23c** may be transmitted or linked to the first side **213** of the base **21** through a transmission mechanism such as a gear or a linkage mechanism. The second output shaft **236** of the second motor **23d** may also be transmitted or linked to the second side **214** of the base **21** through a structure such as a gear.

[0189] For example, in a same time period, a rotation direction of the first output shaft **235** of the first motor **23c** is the same as a rotation direction of the second output shaft **236** of the second motor **23d**. In this case, in the same time period, a rotation direction of the first side **213** of the base **21** is the same as a rotation direction of the second side **214** of the base **21**. For example, a half period is used as an example for description. During $(0, T/4)$, the first output shaft **235** of the first motor **23c** drives the first side **213** of the base **21** to rotate in a clockwise direction of an X-axis,

and the second output shaft **236** of the second motor **23d** drives the second side **214** of the base **21** to rotate in the clockwise direction of the X-axis. During (T/4, T/2), the first output shaft **235** of the first motor **23c** drives the first side **213** of the base **21** to rotate in a counterclockwise direction of the X-axis, and the second output shaft **236** of the second motor **23d** drives the second side **214** of the base **21** to rotate in the counterclockwise direction of the X-axis. In this way, the base **21** can rotate relative to a virtual rotating shaft. The virtual rotating shaft may be an extension line of the first output shaft **235**, an extension line of the second output shaft **236**, or a connection line between the first output shaft **235** and the second output shaft **236**.

[0190] It may be understood that for ease of description, a sound outlet direction of the transducer **22** is defined as a direction of a Z-axis. A length direction of the first output shaft **235** is the X-axis. A Y-axis is perpendicular to the X-axis and the Z-axis. It may be understood that the coordinate system in this implementation may alternatively be flexibly set based on a specific requirement.

[0191] For example, the first output shaft **235** of the first motor **23c** and the second output shaft **236** of the second motor **23d** are disposed in parallel. In this way, the first motor **23c** and the second motor **23d** may synchronously drive the base **21** to perform reciprocating rotation or continuous rotation.

[0192] In an implementation, the first output shaft **235** of the first motor **23c** and the second output shaft **236** of the second motor **23d** may be configured to drive the base **21** to perform reciprocating rotation.

[0193] In an implementation, an angle at which the base **21** drives the transducer **22** to rotate is θ , and θ satisfies: $-45^\circ \leq \theta \leq 45^\circ$. For example, θ may be equal to -45° , -20° , -10° , 10° , 20° , or 45° . In this way, the base **21** may rotate in a range of -45° to 45° .

[0194] In an implementation, an angle at which the base **21** drives the transducer **22** to rotate is θ , and θ satisfies: $-30^\circ \leq \theta \leq 30^\circ$. For example, θ may be equal to -30° , -20° , -10° , 10° , 20° , or 30° . In this way, the base **21** may rotate in a range of -30° to 30° .

[0195] In an implementation, an angle at which the base **21** drives the transducer **22** to rotate is θ , and θ may alternatively satisfy: $-10^\circ \leq \theta \leq 10^\circ$. For example, θ may be equal to -10° , -5° , 5° , 8° , 10° , or the like. In this way, the base **21** may rotate in a range of -10° to 10° .

[0196] In another implementation, θ may alternatively fall within another range, for example, in a range of 0° to 120° , a range of 0° to 150° , a range of 0° to 200° , a range of 0° to 240° , a range of 0° to 300° , or a range of 0° to 330° . This is not specifically limited in this application.

[0197] It may be understood that the first motor **23c** and the second motor **23d** can perform reciprocating rotation under the second control signal. In this case, the first motor **23c** and the second motor **23d** can drive the base **21** to drive the transducer **22** to perform reciprocating rotation. In an implementation, a frequency of reciprocating motion between the base **21** and the transducer **22** may be greater than or equal to 20 kHz. In addition, the vibration member **222** of the transducer **22** can vibrate under driving of the first control signal. In an implementation, a vibration frequency of the vibration member **222** is greater than or equal to 20 kHz, that is, the vibration frequency of the vibration member **222** is an ultrasonic frequency, and the first sound wave is an initial ultrasonic wave. In this way, the transducer **22** emits the first sound wave to the outside while performing reciprocal rotation at a specific frequency. The first sound wave can be modulated in the space to form the second sound wave. The second sound wave may include an audible sound.

[0198] In an implementation, both an extension direction of the first output shaft **235** of the first motor **23c** and an extension direction of the second output shaft **236** of the second motor **23d** may pass through a central position of the base **21**. In this way, the base **21** has good stability in a rotation process. In another implementation, both a connection position between the first output shaft **235** of the first motor **23c** and the base **21** and a connection position between the second output shaft **236** of the second motor **23d** and the base **21** are not specifically limited.

[0199] In this implementation, the first motor **23c**, the second motor **23d**, and the base **21** are

arranged in a direction of the X-axis. In another implementation, the first motor **23c**, the second motor **23d**, and the base **21** may alternatively be arranged in a direction of the Z-axis. In this case, the first output shaft **235** of the first motor **23c** may be connected to the first surface **211** of the base **21**, and the second output shaft **236** of the second motor **23d** may be connected to the second surface **212** of the base **21**. It may be understood that the first output shaft **235** of the first motor **23c** may be perpendicular to the first surface **211** of the base **21**, or may be disposed at an acute angle with the first surface **211** of the base **21**. The second output shaft **236** of the second motor **23d** may be perpendicular to the second surface **212** of the base **21**, or may be disposed at an acute angle with the second surface **212** of the base **21**.

[0200] In an implementation, the first output shaft **235** of the first motor **23c** and the second output shaft **236** of the second motor **23d** may be configured to drive the base **21** to perform continuous rotation. In this case, an angle θ at which the base **21** drives the transducer **22** to rotate falls within a range of 0° to 360° . In this case, the base **21** drives the transducer **22** to perform continuous rotation within 360° .

[0201] It may be understood that the first motor **23c** and the second motor **23d** can perform continuous rotation under the second control signal. In this case, the first motor **23c** and the second motor **23d** can drive the base **21** to drive the transducer **22** to perform continuous rotation. In an implementation, a frequency of continuous motion between the base **21** and the transducer **22** may be greater than or equal to 20 kHz. In addition, the vibration member **222** of the transducer **22** can vibrate under driving of the first control signal. A vibration frequency of the vibration member **222** is greater than or equal to 20 kHz, that is, the vibration frequency of the vibration member **222** is an ultrasonic frequency, and the first sound wave is an initial ultrasonic wave. In this way, the transducer **22** emits the first sound wave to the outside while performing continuous rotation at a specific frequency. The first sound wave can be modulated in air to form the second sound wave. The second sound wave may include an audible sound.

[0202] FIG. **9** is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in still another implementation.

[0203] As shown in FIG. **9**, in an implementation, the first output shaft **235** of the first motor **23c** is connected to the base **21**. The first output shaft **235** of the first motor **23c** may run through the first surface **211** of the base **21** to the second surface **212**. In this way, when the first motor **23c** is energized, the first output shaft **235** of the first motor **23c** may drive the base **21** to rotate. A rotating shaft of the base **21** may be the first output shaft **235**. It may be understood that for an angle range in which the first motor **23c** drives the base **21** to rotate, refer to the foregoing setting of the angle θ at which the first motor **23c** and the second motor **23d** drive the base **21** to drive the transducer **22** to rotate. This is not specifically limited in this application.

[0204] It may be understood that the first output shaft **235** of the first motor **23c** runs through the first surface **211** of the base **21** to the second surface **212**, so that the base **21** can be more stable in a rotation process. In another implementation, the first output shaft **235** may not need to run to the second surface **212**. In another implementation, the first output shaft **235** may run through the second surface **212** of the base **21** to the first surface **211**.

[0205] It may be understood that FIG. **3** and FIG. **8** show that the rotating shaft (for example, the first output shaft **235** of the first motor **23c**) of the base **21** may be located on a plane on which the base **21** is located (for example, the rotating shaft of the base **21** is parallel to the plane on which the base **21** is located). However, in this implementation, the rotating shaft (for example, the first output shaft **235** of the first motor **23c**) of the base **21** may be perpendicular to or intersect with the plane on which the base **21** is located.

[0206] It may be understood that to change a sound wave amplitude at least one position in the space and implement that the first sound wave can be modulated in the space to form the second sound wave, where the second sound wave may include an audible sound, a position of a rotating shaft of the transducer **22** is set in a specific manner. The following analyzes in detail the three

driving apparatuses **23** shown in FIG. 3, FIG. 8, and FIG. 9.

[0207] It may be understood that in the three implementations shown in FIG. 3, FIG. 8, and FIG. 9, the driving apparatus **23** drives, through the base **21**, the transducer **22** to perform continuous rotation or reciprocating rotation. In this way, the rotating shaft of the base **21** and the rotating shaft of the transducer **22** are the same. Therefore, a setting of the rotating shaft of the transducer **22** is the same as a setting of the rotating shaft of the base **21**. The following uses the rotating shaft of the base **21** as an example for description.

[0208] When the transducer **22** is disposed at the center of the base **21**, and the rotating shaft of the base **21** uses the manner (that is, the rotating shaft of the base **21** is located on the plane on which the base **21** is located) shown in FIG. 3 and FIG. 8, a position of the rotating shaft of the base **21** is not specifically limited.

[0209] When the transducer **22** is disposed at the center of the base **21**, and the rotating shaft of the base **21** uses the manner (the rotating shaft of the base **21** is perpendicular to or intersects with the plane on which the base **21** is located) shown in FIG. 9, a specific position of the rotating shaft of the base **21** is related to perpendicular and intersecting solutions.

[0210] For example, when the rotating shaft of the base **21** is perpendicular to the plane on which the base **21** is located, the position of the rotating shaft of the base **21** may be set based on an energy shape of the main lobe of the first sound wave. When the energy shape of the main lobe of the first sound wave is a symmetric structure, the position of the rotating shaft of the base **21** may be set to be eccentric (that is, the position of the rotating shaft deviates from the center of the base **21**). When the energy shape of the main lobe of the first sound wave is an asymmetric structure, the position of the rotating shaft of the base **21** may be any position. It may be understood that FIG. 9 shows that the rotating shaft of the base **21** is perpendicular to the plane on which the base **21** is located. Therefore, considering that the energy shape of the main lobe of the first sound wave is a symmetric structure, FIG. 9 shows that the first output shaft **235** of the first motor **23c** is connected to the first side **213** of the base **21** to set the position of the rotating shaft of the base **21** to be eccentric. Certainly, in another implementation, the first output shaft **235** of the first motor **23c** is connected to the second side **214** of the base **21** to set the position of the rotating shaft of the base **21** to be eccentric.

[0211] For another example, when the rotating shaft of the base **21** intersects with the plane on which the base **21** is located, the position of the rotating shaft of the base **21** may be any position.

[0212] When the transducer **22** is not disposed at the center of the base **21**, regardless of whether the rotating shaft of the base **21** uses the manner shown in FIG. 3 and FIG. 8 or the manner shown in FIG. 9, a position of the rotating shaft of the base **21** is not specifically limited.

[0213] In another implementation, when the sound generation apparatus **100** does not include the base **21**, the driving apparatus **23** may directly drive the transducer **22** to perform continuous rotation or reciprocating rotation. In this case, to change a sound wave amplitude at least one position in the space and implement that the first sound wave can be modulated in the space to form the second sound wave, where the second sound wave may include an audible sound, a position of a rotating shaft of the transducer **22** is set in a specific manner. The following analyzes in detail the three driving apparatuses **23** shown in FIG. 3, FIG. 8, and FIG. 9.

[0214] When the rotating shaft of the transducer **22** uses the manner shown in FIG. 3 and FIG. 8, that is, the rotating shaft of the transducer **22** is located on a plane on which the transducer **22** is located (for example, the rotating shaft of the transducer **22** is parallel to the plane on which the transducer **22** is located), the position of the rotating shaft of the transducer **22** is not specifically limited.

[0215] When the rotating shaft of the transducer **22** uses the manner shown in FIG. 9 (the rotating shaft of the transducer **22** is perpendicular to or intersects with a plane on which the transducer **22** is located), a specific position of the rotating shaft of the transducer **22** is related to perpendicular and intersecting solutions.

[0216] For example, when the rotating shaft of the transducer **22** is perpendicular to the plane on which the transducer **22** is located, the position of the rotating shaft of the transducer **22** may be set based on an energy shape of the main lobe of the first sound wave. When the energy shape of the main lobe of the first sound wave is a symmetric structure, the position of the rotating shaft of the transducer **22** may be set to be eccentric (that is, the position of the rotating shaft of the transducer **22** deviates from a center of the transducer **22**). When the energy shape of the main lobe of the first sound wave is an asymmetric structure, the position of the rotating shaft of the transducer **22** may be any position.

[0217] For another example, when the rotating shaft of the transducer **22** intersects with the plane on which the transducer **22** is located, the position of the rotating shaft of the transducer **22** may be any position.

[0218] The driving apparatus **23** described above is described by using an example in which the base **21** is driven to rotate. The following further describes a driving apparatus **23** in detail with reference to related accompanying drawings. The driving apparatus **23** may be configured to drive the base **21** to drive the transducer **22** to perform translational motion within a specific displacement range.

[0219] FIG. **10** is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in still another implementation.

[0220] As shown in FIG. **10**, in an implementation, the driving apparatus **23** includes a telescopic mechanism **23e**. The telescopic mechanism **23e** may be a magnetostrictively driven mechanism, or may be an electromagnetically driven mechanism, a piezoelectrically driven mechanism, an electrostatically driven mechanism, or a mechanism driven in another manner.

[0221] Further, the telescopic mechanism **23e** includes a fixed base **237** and a telescopic arm **238**. A first end of the telescopic arm **238** is fixedly connected to the fixed base **237**. A second end of the telescopic arm **238** extends relative to the fixed base **237**. It may be understood that the first end of the telescopic arm **238** is a fixed end relative to the fixed base **237**. The second end of the telescopic arm **238** is a movable end relative to the fixed base **237**. For example, the telescopic arm **238** may include a piezoelectric sheet (not shown in the figure). When the piezoelectric sheet is energized, the piezoelectric sheet may be deformed (for example, warped, bent, or arched). In this case, the telescopic arm **238** may perform reciprocating extension and retraction motion in a direction of an X-axis. For example, the telescopic arm **238** may perform extension motion in a positive direction of the X-axis. The telescopic arm **238** may further perform retraction motion in a negative direction of the X-axis. In another implementation, a direction in which the telescopic arm **238** extends and retracts may be any direction on a plane X-Y, or may be a direction of a Z-axis. This is not specifically limited in this application.

[0222] As shown in FIG. **10**, the second end (that is, the movable end) of the telescopic arm **238** is connected to the first side **213** of the base **21**. In this way, when the telescopic arm **238** performs reciprocating translational motion in the direction of the X-axis, the telescopic arm **238** may drive the base **21** to drive the transducer **22** to perform reciprocating translational motion in the direction of the X-axis. For example, one period is used as an example for description. During $(0, T/4)$, the telescopic arm **238** may drive the base **21** to drive the transducer **22** to perform translational motion from an initial position to a first position in the positive direction of the X-axis. During $(T/4, T/2)$, the telescopic arm **238** may drive the base **21** to drive the transducer **22** to perform translational motion from the first position to the initial position in the negative direction of the X-axis. During $(T/2, 3T/4)$, the telescopic arm **238** may drive the base **21** to drive the transducer **22** to perform translational motion from the initial position to a second position in the negative direction of the X-axis. During $(3T/4, T)$, the telescopic arm **238** may drive the base **21** to drive the transducer **22** to perform translational motion from the second position to the initial position in the positive direction of the X-axis.

[0223] It may be understood that the telescopic mechanism **23e** can perform reciprocating

extension and retraction motion under the second control signal. In this case, the telescopic mechanism **23e** can drive the base **21** to drive the transducer **22** to perform reciprocating translational motion. In an implementation, a frequency of reciprocating motion between the base **21** and the transducer **22** may be greater than or equal to 20 kHz. In addition, the vibration member **222** of the transducer **22** can reciprocally vibrate under driving of the first control signal, and a vibration frequency of the vibration member **222** is greater than or equal to 20 kHz, that is, the vibration frequency of the vibration member **222** is an ultrasonic frequency, and the first sound wave is an initial ultrasonic wave. In this way, the transducer **22** emits an ultrasonic wave to the outside while performing reciprocating translational motion at a specific frequency. In this case, the ultrasonic wave can be modulated in the space to form the second sound wave. The second sound wave may include an audible sound.

[0224] The structure of the driving apparatus **23** is not limited to the several structures described above. It may be understood that all driving apparatuses **23** that can implement reciprocating motion under the second control signal may be used as the driving apparatus **23** in this application. This is not specifically limited in this application. The following further describes several structures of the sound generation apparatus in detail with reference to related accompanying drawings.

[0225] FIG. **11A** is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in still another implementation.

[0226] As shown in FIG. **11A**, in an implementation, the base **21** is provided with accommodation space **215**. The accommodation space **215** may be of a groove structure or a through-hole structure. An example in which the accommodation space **215** is of a groove structure is used for description. The accommodation space **215** forms an opening on the first surface **211** of the base **21**. At least a part of the transducer **22** is located in the accommodation space **215**. In this way, there is an overlapping region between the transducer **22** and the base **21** in a thickness direction, to facilitate thinning of the sound generation apparatus **100** in the thickness direction.

[0227] In an implementation, a top surface of the transducer **22** may be flush with the first surface **211** of the base **21**, or a top surface of the transducer **22** is lower than the first surface **211** of the base **21**. In this way, a dimension of the sound generation apparatus **100** in the thickness direction may be greatly reduced.

[0228] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. Details are not described herein again.

[0229] FIG. **11B** is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in still another implementation.

[0230] As shown in FIG. **11B**, in an implementation, the base **21** is provided with accommodation space **215**. The accommodation space **215** may be of a groove structure or a through-hole structure. An example in which the accommodation space **215** is of a through-hole structure is used for description. The accommodation space **215** forms openings on the first surface **211** and the second surface **212** of the base **21**.

[0231] In this implementation, the vibration member **222** is connected to a wall surface of the accommodation space **215** through a connecting piece **223**. The connecting piece **223** may be of a rod structure, or may be of a cantilever structure. The connecting piece **223** may alternatively be of a connecting arm structure formed by disposing a groove on the base **21**. Further, the connecting piece **223** is not specifically limited in this application.

[0232] It may be understood that compared with the transducer **22** in the foregoing implementations, the transducer **22** in this implementation does not include the support member **221**. The transducer **22** in this implementation and the base **21** may form an integral structure. In this way, the transducer **22** in this implementation can save a structure of the support member **221**, so that the transducer **22** and the base **21** are arranged more compactly and the sound generation apparatus **100** has a simpler structure.

[0233] For example, the transducer **22** and the base **21** may implement an integral structure by using a MEMS process.

[0234] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. Details are not described herein again.

[0235] FIG. **12** is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in still another implementation. FIG. **13A** is a partial cross-sectional view of an implementation of the sound generation component **20** shown in FIG. **12** along a line A-A.

[0236] As shown in FIG. **12** and FIG. **13A**, in an implementation, the sound generation apparatus **100** further includes a casing **50**. The casing **50** is provided with a sound outlet hole **51**. The sound outlet hole **51** communicates with an inner cavity and external space of the casing **50**. The sound outlet hole **51** may be located on a top part of the casing **50**. In another implementation, a position of the sound outlet hole **51** is not specifically limited. For example, the sound outlet hole **51** may alternatively be located on a side part or a bottom part.

[0237] All of the base **21**, the transducer **22**, and the driving apparatus **23** are disposed in the inner cavity of the casing **50**. The driving apparatus **23** may be connected to the casing **50**. In addition, the implementations shown in FIG. **1** and FIG. **2** show that both the signal processing circuit **30** and the control circuit **40** are mounted inside the housing **10** of the headset **100**. In this case, both the signal processing circuit **30** and the control circuit **40** are located in the external space of the casing **50**. In another implementation, at least one of the signal processing circuit **30** and the control circuit **40** may alternatively be disposed in the inner cavity of the casing **50**. In another implementation, a part of the signal processing circuit **30** is disposed in the inner cavity of the casing **50**, and a part is disposed in the external space of the casing **50**. In another implementation, a part of the control circuit **40** is disposed in the inner cavity of the casing **50**, and a part is disposed in the external space of the casing **50**.

[0238] It may be understood that the casing **50** may be a core structure of the sound generation apparatus **100**. The casing **50** may be configured to provide isolation from, a connection to, and fastening to another part of the electronic device. In addition, the base **21**, the transducer **22**, and the driving apparatus **23** are packaged into an integral structure through the casing **50**, to achieve good integrity of the sound generation apparatus **100**. This facilitates adaptation to application of the sound generation apparatus **100** to an integrated machine, that is, facilitates arrangement of the sound generation apparatus **100** in the electronic device.

[0239] In addition, the sound outlet hole **51** is usually a through-hole structure or a pipe structure on the casing **50**. The sound outlet hole **51** may conduct a sound wave emitted by the sound generation apparatus **100** to the external space of the casing **50**, conduct the sound wave to a position of a sound output hole of the electronic device, and then conduct the sound wave to the outside of the electronic device through a sound outlet hole of the electronic device.

[0240] For example, the casing **50** may be an open casing, or there are closed structures at all positions other than the position of the sound outlet hole **51**.

[0241] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. Details are not described herein again.

[0242] FIG. **13B** is a partial cross-sectional view of another implementation of the sound generation component **20** shown in FIG. **12** along a line A-A.

[0243] In an implementation, the driving apparatus **23** and the base **21** may divide the inner cavity of the casing **50** into a first inner cavity **52a** and a second inner cavity **52b**. The first inner cavity **52a** communicates with the sound outlet hole **51**. The audible sound generated by the sound generation apparatus **100** may be conducted to external space of the sound generation apparatus **100** through the first inner cavity **52a** and the sound outlet hole **51**.

[0244] For example, the driving apparatus **23** is described by using the structure shown in FIG. 3 as an example. The first piezoelectric driving mechanism **23a**, the second piezoelectric driving mechanism **23b**, and the base **21** divide the inner cavity of the casing **50** into the first inner cavity **52a** and the second inner cavity **52b**.

[0245] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. Details are not described herein again.

[0246] FIG. 14 is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. 2 in still another implementation.

[0247] As shown in FIG. 14, in an implementation, the sound generation apparatus **100** further includes a sound-absorbing part **60**. The sound-absorbing part **60** may be a sound-absorbing material (for example, sound-absorbing cotton), a sound-absorbing structure (for example, a micro-perforated panel), or the like.

[0248] The sound-absorbing part **60** is disposed on an inner surface of the casing **50** and disposed in a staggered manner with the sound outlet hole **51**. For example, the sound-absorbing part **60** may be connected to the inner surface of the casing **50** through filling, attaching, or the like. In addition, the sound-absorbing part **60** may completely cover the inner surface of the casing **50**, or may partially cover the inner surface of the casing **50**.

[0249] The sound-absorbing part **60** is mounted in a manner. For example, the sound-absorbing part **60** may be of a plate structure or a layered structure. In some implementations, the sound-absorbing part **60** may be fastened to a bottom wall of the housing, and the sound-absorbing part **60** completely or partially covers a region of the bottom wall. In some other manners, the sound-absorbing part **60** may alternatively be fastened to a side wall of the housing, to increase a sound-absorbing area of the sound-absorbing part **60**. In some other embodiments, the sound-absorbing part **60** may alternatively be a three-dimensional structural member, and is fastened to a top part of the transducer **22**. It may be understood that a specific spacing is formed between the sound-absorbing part **60** and the vibration member **222**, and space corresponding to the spacing is used as vibration space of the vibration member **222**, to avoid interference caused by the sound-absorbing part **60** to vibration of the vibration member **222**.

[0250] It may be understood that the sound-absorbing part **60** is disposed on the inner surface of the casing **50**, and the sound-absorbing part **60** may absorb a sound wave propagated to the inner surface of the casing **50**, to reduce reflection of the sound wave in the casing **50** and reduce distortion of an audible sound.

[0251] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. Details are not described herein again.

[0252] FIG. 15 is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. 2 in still another implementation. FIG. 16 is a partial cross-sectional view of an implementation of the sound generation component **20** shown in FIG. 15 along a line B-B.

[0253] As shown in FIG. 15 and FIG. 16, in an implementation, the casing **50** is provided with a sound wave guiding structure **70**. The sound wave guiding structure **70** is disposed at an interval from the sound outlet hole **51**. The sound wave guiding structure **70** may communicate the inner cavity of the casing **50** with the external space of the casing **50**. The sound wave guiding structure **70** may be a structure such as a hole or a pipe.

[0254] It may be understood that the sound wave guiding structure **70** may be configured to export a sound wave in the inner cavity of the casing **50** to the external space of the casing **50**. In this way, the sound wave guiding structure **70** may be configured to implement atmospheric pressure balance between the inner cavity of the casing **50** and the outside of the casing **50**, so that the transducer **22** can smoothly vibrate, and a sound wave with a small distortion degree is formed under driving of

the first control signal.

[0255] In an implementation, when the sound generation apparatus **100** is used in the electronic device, the sound wave guiding structure **70** does not communicate with the sound outlet hole of the electronic device, that is, the sound wave guiding structure **70** is not used as a main sound outlet channel of the electronic device.

[0256] In an implementation, an extension direction of the sound wave guiding structure **70** is different from an extension direction of the sound outlet hole **51** of the casing **50**. For example, when the sound outlet hole **51** is disposed on the top part of the casing **50**, the sound wave guiding structure **70** may be disposed on the side part or the bottom part of the casing **50**. In this way, the sound wave guiding structure **70** may be disposed away from the sound outlet hole **51**.

[0257] In an implementation, an extension direction of the sound wave guiding structure **70** is opposite or perpendicular to an extension direction of the sound outlet hole **51** of the casing **50**. For example, when the sound outlet hole **51** is disposed on the top part of the casing **50**, the sound wave guiding structure **70** may be disposed on the side part or the bottom part of the casing **50**.

[0258] It may be understood that a position of the sound wave guiding structure **70** on the casing **50** is not specifically limited in this application. For example, the position of the sound wave guiding structure **70** on the casing **50** may be set based on a structure of an actual electronic device. In addition, the sound wave guiding structure **70** is not limited to two structures shown in FIG. **15**. In another implementation, a quantity of sound wave guiding structures **70** is not limited. For example, the quantity of sound wave guiding structures **70** may be determined based on factors such as a radiation sound pressure level and a rotation angle of the vibration member **222** of the sound generation apparatus **100**.

[0259] In an implementation, a minimum width of the sound wave guiding structure **70** is greater than a thickness $d_{\text{sub.}\mu}$ of a viscous layer, and the thickness $d_{\text{sub.}\mu}$ of the viscous layer satisfies:

$$[00011]d = 0.22\text{mm} \times \sqrt{\frac{100\text{Hz}}{f_1}},$$

where f is a frequency at which the transducer **22** emits the first sound wave.

[0260] It may be understood that the minimum width of the sound wave guiding structure **70** is a dimension at a narrowest position of a single sound wave guiding structure **70**. For example, when the sound wave guiding structure **70** is a hole structure, a minimum width of a hole is a dimension at a narrowest position of a single hole.

[0261] In another implementation, a size of the sound wave guiding structure **70** is not specifically limited. For example, the size of the sound wave guiding structure **70** may also be determined based on factors such as the radiation sound pressure level and the rotation angle of the vibration member **222** of the sound generation apparatus.

[0262] In an implementation, the sound generation apparatus **100** may be further provided with a damping mesh fabric (not shown in the figure), and the damping mesh fabric may be fastened to the casing **50** through bonding or in another manner, and covers the sound wave guiding structure **70**. The damping mesh fabric is breathable, to achieve atmospheric pressure balance between the inner cavity of the casing **50** and the outside of the casing **50**. In addition, the damping mesh fabric can implement acoustic isolation for the atmospheric pressure balance between the inner cavity of the casing **50** and the outside of the casing **50**, and can reduce leakage of a sound wave in the inner cavity **52** to the outside of the fastening casing **50a**. Breathability means that media on two sides of an interface can be exchanged, and acoustic isolation means to reduce or isolate leakage of sound wave energy. A quantity, shapes, and the like of damping mesh fabrics are adapted to a front discharge hole. In some other embodiments, the sound generation apparatus **100** may not be provided with the second damping mesh fabric.

[0263] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. Details are not described herein again.

[0264] FIG. **17** is a diagram of a structure of the sound generation component **20** of the sound

generation apparatus **100** shown in FIG. **2** in still another implementation.

[0265] As shown in FIG. **17**, in an implementation, an included angle between an axial direction of the vibration member **222** of the transducer **22** and an extension direction of the sound outlet hole **51** is α ; and α satisfies: $45^\circ \leq \alpha \leq 135^\circ$. For example, α is equal to 45° , 60° , 90° , 100° , 120° , or 135° . FIG. **17** shows that α is equal to 90° . It may be understood that the axial direction of the vibration member **222** is a direction perpendicular to a plane on which the vibration member **222** is located. [0266] It may be understood that with reference to FIG. **7**, compared with the main lobe energy of the ultrasonic wave in the space being in a positive “8” shape, main lobe energy of the audible sound in the space is approximately in an inverted “8” shape. At the defined coordinates, the audible sound in this implementation has a highest sound pressure level in the direction of the X-axis. Therefore, α is set to satisfy $45^\circ \leq \alpha \leq 135^\circ$, so that a direction at a higher sound pressure level in the audible sound faces the sound outlet hole **51** of the casing **50**. In this case, a sound pressure level of an audible sound transmitted out of the casing **50** is higher. It may be understood that when α is equal to 90° , a direction at a highest sound pressure level in the audible sound faces the sound outlet hole **51** of the casing **50**. In this way, the sound pressure level of the audible sound transmitted out of the casing **50** can be highest.

[0267] In another implementation, an included angle α between an axial direction of the vibration member **222** of the transducer **22** and an extension direction of the sound outlet hole **51** is not specifically limited. For example, a value of α affects a sound pressure level and directivity of the audible sound. Therefore, a design may be made based on an actual architecture.

[0268] It may be understood that an example in which the driving apparatus **23** in FIG. **3** is used in the driving apparatus **23** shown in FIG. **17** is used for description. When the first cantilever **233** drives the first side **213** of the base **21** to vibrate in the positive direction of the Z-axis(that is, a right side in FIG. **17**), and the second cantilever **234** drives the second side **214** of the base **21** to vibrate in the negative direction of the Z-axis(that is, a left side in FIG. **17**), the base **21** rotates counterclockwise relative to the virtual rotating shaft **G1**. In this case, in a process in which the base **21** drives the transducer **21** to rotate, the angle α becomes larger. When the first cantilever **233** drives the first side **213** of the base **21** to vibrate in the negative direction of the Z-axis(that is, a left side in FIG. **17**), and the second cantilever **234** drives the second side **214** of the base **21** to vibrate in a positive direction of the Z-axis(that is, a right side in FIG. **17**), the base **21** rotates clockwise relative to the virtual rotating shaft **G1**. In this case, in a process in which the base **21** drives the transducer **21** to rotate, the angle α becomes smaller.

[0269] It may be understood that an example in which the driving apparatus **23** in FIG. **8** is used in the driving apparatus **23** shown in FIG. **17** is used for description. With reference to FIG. **8** and FIG. **17**, the first output shaft **235** of the first motor **23c** and the second output shaft **236** of the second motor **23d** are respectively connected to the two sides of the base **21**. The first output shaft **235** and the second output shaft **236** may be parallel to the Y-axis (a direction perpendicular to a paper surface). In this case, the base **21** may drive the transducer **22** to perform reciprocating rotation or continuous rotation. Reciprocating rotation is used as an example for description. The first output shaft **235** and the second output shaft **236** may first drive the base **21** and the transducer **22** to rotate in the negative direction of the Z-axis(that is, a left side in FIG. **17**), and then drive the base **21** and the transducer **22** to rotate in the positive direction of the Z-axis(that is, a right side in FIG. **17**).

[0270] It may be understood that an example in which the driving apparatus **23** in FIG. **10** is used in the driving apparatus **23** shown in FIG. **17** is used for description. With reference to FIG. **10** and FIG. **17**, the telescopic arm **238** of the telescopic mechanism **23e** may perform extension and retraction motion to drive the base **21** to perform reciprocal motion in the direction of the X-axis or the direction of the Y-axis (a direction perpendicular to a paper surface). In this implementation, in a process in which the base **21** drives the transducer **21** to perform reciprocating translation in the direction of the X-axis or the direction of the Y-axis, the angle α remains unchanged.

[0271] In an implementation, the transducer **22** may be disposed as close as possible to the sound outlet hole **51**, so that the vibration member **222** of the transducer **22** may be disposed close to the sound outlet hole **51** to a large extent. In this way, most of the audible sound may be propagated to the outside of the sound generation apparatus **100** through the sound outlet hole **51**.

[0272] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. Details are not described herein again.

[0273] FIG. **18** is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in still another implementation. FIG. **19** is a partial cross-sectional view of an implementation of the sound generation component **20** shown in FIG. **18** along a line C-C.

[0274] As shown in FIG. **18** and FIG. **19**, in an implementation, the sound generation apparatus **100** further includes an adjustment mechanism **80**. The adjustment mechanism **80** has a first sound output hole **81**. A size of the first sound output hole **81** is capable of becoming larger or smaller.

[0275] For example, the adjustment mechanism **80** includes a plurality of blades. The plurality of blades jointly enclose the first sound output hole **81**. An aperture of the first sound output hole **81** is adjusted by controlling motion of the plurality of blades, to increase or decrease the size of the first sound output hole **81**.

[0276] As shown in FIG. **18** and FIG. **19**, the adjustment mechanism **80** is disposed on the casing **50**. The first sound output hole **81** of the adjustment mechanism **80** communicates with the sound outlet hole **51** of the casing **50**. In this case, the audible sound generated by the sound generation apparatus **100** may be transmitted to the outside of the sound generation apparatus **100** through the sound outlet hole **51** of the casing **50** and the first sound output hole **81** of the adjustment mechanism **80**.

[0277] It may be understood that when the size of the first sound output hole **81** of the adjustment mechanism **80** becomes larger, an area of a channel in which the audible sound is conducted is large. In this way, the audible sound is not prone to diffraction at the first sound output hole **81**. Therefore, directivity of the audible sound conducted to the casing **50** is not prone to change. When the size of the first sound output hole **81** of the adjustment mechanism **80** becomes smaller, an area of a channel in which the audible sound is conducted is small. In this way, the audible sound is prone to diffraction at the first sound output hole **81**. Therefore, directivity of the audible sound conducted to the casing **50** is prone to change.

[0278] It may be understood that when low-frequency directivity is required, an area of the first sound output hole **81** is increased. A suitable scenario herein may be that the sound generation apparatus **100** plays a sound in a specific direction or toward a specific user. For example, in a private call scenario, when a user makes a call and does not want another person to hear a downlink sound of the call, the aperture of the first sound output hole **81** is adjusted to be larger, and the sound has directivity, so that the sound is emitted only toward the user and cannot be heard by a surrounding person. For another example, in a music exclusive scenario, when another person rests around and a user wants to enjoy audio and video entertainment, the aperture of the first sound output hole **81** is adjusted to be larger, and the sound has directivity, so that the sound is emitted only toward the user and cannot be heard by a surrounding person, so as not to disturb the surrounding person.

[0279] When low-frequency directivity is not required, an area of the first sound output hole **81** is decreased. A suitable scenario herein may be that the sound generation apparatus **100** plays a sound toward users in a plurality of directions. For example, when people around a user want to listen to the sound together, the first sound output hole **81** may be adjusted to be smaller, and the audible sound has no directivity, so that all people around the user can hear the sound.

[0280] In another implementation, the adjustment mechanism **80** may alternatively be a mobile blocking part. The mobile blocking part may selectively block the sound outlet hole **51**, or change a

size for blocking the sound outlet hole **51**, to change a size of the sound outlet hole **51**. Further, a specific structure of the adjustment mechanism **80** is not limited in this application.

[0281] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. Details are not described herein again.

[0282] FIG. **20** is a diagram of a structure of an ultrasonic transducer **22** in some embodiments according to an embodiment of this application.

[0283] As shown in FIG. **20**, in some embodiments, the transducer **22** may be a piezoelectric ultrasonic transducer. The transducer **22** includes a support member **221** and a vibration member **222**. The vibration member **222** includes a diaphragm **2221** and a piezoelectric sheet **2222**. A peripheral edge of the diaphragm **2221** is fastened to the support member **221**, and the piezoelectric sheet **2222** is fastened to the diaphragm **2221**. For example, the piezoelectric sheet **2222** includes a piezoelectric material layer. In this case, the ultrasonic transducer **22** is a piezoelectric single crystal ultrasonic transducer **22**. The piezoelectric material layer may be made of a piezoelectric material such as lead zirconate titanate (PZT) piezoelectric ceramics. The piezoelectric sheet **2222** may be bonded to the diaphragm **2221** through an adhesive layer **2223**. The piezoelectric sheet **2222** may be located on an upper surface or a lower surface of the diaphragm **2221**. This is not strictly limited in this embodiment of this application. The diaphragm **2221** may be made of a material such as aluminum. In this embodiment, because of a high Q value characteristic of the piezoelectric sheet **2222**, the ultrasonic transducer **22** has high energy conversion efficiency. A Q value is referred to as a quality factor, and a high Q value means a low sound wave energy loss (an attenuation ratio is directly proportional to a square of a frequency).

[0284] By adjusting a material and a geometric dimension of the ultrasonic transducer **22**, a resonance frequency of the vibration member **222** of the ultrasonic transducer **22** can be adjusted, so that the resonance frequency falls within a desired frequency range. For example, the resonance frequency of the vibration member **222** is designed to be 40 kHz, to be applicable to a sound generation apparatus **100** that needs to form a medium- or low-frequency audible sound. An example in which the piezoelectric sheet **2222** is of a circular sheet structure is used for description. The piezoelectric material is PZT-5H, and a polarization direction is a thickness direction of the piezoelectric sheet **2222**. A voltage is applied to upper and lower surfaces of the piezoelectric sheet **2222**. The piezoelectric sheet **2222** has a radius of 4 mm and a thickness of 0.8 mm. The diaphragm **2221** is made of aluminum and has a thickness of 0.2 mm. In this case, the resonance frequency of the vibration member **222** is 40 kHz or close to 40 kHz.

[0285] In some implementations, the resonance frequency of the vibration member **222** may be increased by reducing an area of the piezoelectric sheet **2222**, and/or increasing the thickness of the piezoelectric sheet **2222**, and/or increasing a thickness of the material of the diaphragm **2221**, and/or increasing hardness of the material of the diaphragm **2221**, so that the resonance frequency matches a frequency of a desired initial ultrasonic wave. A specific solution may be designed based on an actual requirement. Details are not described herein again.

[0286] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. Details are not described herein again.

[0287] As shown in FIG. **20**, in some implementations, a phase of a sound wave emitted by the vibration member **222** is focused. For example, the phase $q(r)$ of the sound wave emitted by the vibration member **222** satisfies:

$$[00012] \quad q(r) = \frac{2}{\lambda} * (\sqrt{f^2 + r^2} - f)$$

[0288] Herein, r is a distance between any point on a surface of the vibration member **222** and a center of the vibration member **222**, λ is a wavelength corresponding to the sound wave emitted by the vibration member **222**, and f is a focal length corresponding to the sound wave emitted by the

vibration member **222**.

[0289] It may be understood that when the phase $q(r)$ of the sound wave emitted by the vibration member **222** satisfies the foregoing relational expression, the phase of the sound wave emitted by the vibration member **222** may be focused, to enhance directivity of the sound wave emitted by the diaphragm **2221** and increase a sound pressure level of the audible sound.

[0290] It may be understood that there is a plurality of solutions for focusing the phase $\phi(r)$ of the sound wave emitted by the vibration member **222**. In an implementation, a shape of the vibration member **222** may be set (for example, the surface of the vibration member **222** may be set to be in a shape similar to that of a surface of a convex lens or a shape similar to that of a surface of a Fresnel lens), to implement a focusing design of the phase $q(r)$ of the sound wave emitted by the vibration member **222**. In another implementation, a focusing structure (for example, the following sound wave directing member **91**) may alternatively be disposed on the surface of the vibration member **222**, and the focusing structure may implement a focusing design of the phase $\phi(r)$ of the sound wave emitted by the vibration member **222**.

[0291] As shown in FIG. **20**, in some implementations, the transducer **22** may further include a sound wave directing member **91**. The sound wave directing member **91** is located above the vibration member **222**, and the sound wave directing member **91** is configured to limit a radiation direction of an ultrasonic wave generated by the ultrasonic transducer **22**, to enhance the directivity of the sound wave emitted by the diaphragm **2221** and increase the sound pressure level of the audible sound. The sound wave directing member **91** may include an emission surface. The emission surface is in a conical shape. The conical emission surface can narrow the directivity of the initial ultrasonic wave to approximately 60° , to greatly enhance the directivity of the sound wave emitted by the diaphragm **2221**.

[0292] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. Details are not described herein again.

[0293] FIG. **21** is a schematic cross-sectional view of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in still another implementation. FIG. **22** is a schematic cross-sectional view of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in still another implementation.

[0294] As shown in FIG. **21** and FIG. **22**, in some implementations, the sound generation apparatus **100** further includes a front cavity filter **92**. The front cavity filter **92** has a second sound output hole **921**. The front cavity filter **92** is fastened to the casing **50**, and the second sound output hole **921** communicates with the sound outlet hole **51** of the casing **50**. In some implementations, the front cavity filter **92** may be fastened to the casing **50** by using adhesive or in another manner. In some implementations, the front cavity filter **92** and the casing **50** may alternatively form an integral structural member.

[0295] In this implementation, the front cavity filter **92** may be configured to filter out a non-target sound wave. In other words, the non-target sound wave cannot pass through the front cavity filter **92**. A target sound wave may pass through the front cavity filter **92**.

[0296] It may be understood that the transducer **22** emits the first sound wave at a frequency of $f_{\text{sub.1}}$ under the driving of the first control signal. In addition, the base **21** moves at a frequency of $f_{\text{sub.2}}$ under the driving of the second control signal. In this case, a sound field in the space changes, and modulation is generated to form an audible sound. The sound field in the space includes two sound wave frequencies: $|f_{\text{sub.1}}+f_{\text{sub.2}}|$ and $|f_{\text{sub.1}}-f_{\text{sub.2}}|$. One of sound waves at the two frequencies in the space may be filtered out, to leave a sound wave at one frequency. For example, a sound wave at the frequency of $|f_{\text{sub.1}}+f_{\text{sub.2}}|$ is filtered out, to retain a sound wave at $|f_{\text{sub.1}}-f_{\text{sub.2}}|$. In this case, a frequency of the target sound wave is $|f_{\text{sub.1}}-f_{\text{sub.2}}|$, and a frequency of the non-target sound wave is $|f_{\text{sub.1}}+f_{\text{sub.2}}|$. In this implementation, the front cavity filter **92** may be configured to: filter out the non-target sound wave, that is, the sound wave at the

frequency of $|f_{\text{sub.1}}+f_{\text{sub.2}}|$, and pass the sound wave at the frequency of $|f_{\text{sub.1}}-f_{\text{sub.2}}|$. [0297] In an implementation, the non-target sound wave is a high-frequency sound wave, and the target sound wave is a low-frequency sound wave. In other words, the front cavity filter **92** may be configured to filter out the high-frequency sound wave, so that the low-frequency sound wave passes through the front cavity filter **92**. For example, an example in which $f_{\text{sub.1}}=40$ KHz and $f_{\text{sub.2}}=41$ KHz is used for description. The front cavity filter **92** may be configured to: pass a sound wave at a frequency of $|f_{\text{sub.1}}-f_{\text{sub.2}}|=1$ KHz, and filter out a sound wave at a frequency of $|f_{\text{sub.1}}+f_{\text{sub.2}}|=41$ KHz. In other words, the high-frequency sound wave (41 KHz) may be dissipated in the front cavity filter **92** due to thermal viscosity and other effects. In this case, the high-frequency sound wave (41 KHz) cannot be propagated to the outside of the sound generation apparatus **100**.

[0298] The following describes several specific structures of the front cavity filter **92** with reference to related accompanying drawings.

[0299] As shown in FIG. **21**, a hole wall of the second sound output hole **921** is of a variable cross-sectional structure, that is, the front cavity filter **92** is a variable cross-sectional pipe. For example, the second sound output hole **921** of the front cavity filter **92** includes a plurality of narrow regions **9211** and a plurality of wide regions **9212**. The plurality of narrow regions **9211** and the plurality of wide regions **9212** are alternately arranged. In this case, the hole wall of the second sound output hole **921** of the front cavity filter **92** is approximately of a concave-convex structure. It may be understood that a width of the narrow region **9211** is less than a width of the wide region **9212**. Widths of all the narrow regions **9211** may not be strictly equal. Widths of all the wide regions **9212** may not be strictly equal.

[0300] As shown in FIG. **21**, the width **L1** of the wide region **9212** falls within a range of 0.1 mm to 50 mm. In addition, a distance **L2** (that is, a height of the wide region **9212**) between two adjacent narrow regions **9211** is greater than 0.1 mm. It may be understood that a frequency of a sound wave filtered out by the front cavity filter **92** is related to both the width **L1** of the wide region **9212** and the distance **L2** between two adjacent narrow regions **9211**. An example in which $f_{\text{sub.1}}=40$ KHz and $f_{\text{sub.2}}=41$ KHz is used for description. The sound wave at $|f_{\text{sub.1}}+f_{\text{sub.2}}|=41$ KHz needs to be filtered out, and corresponds to a wavelength of $10=8.4$ mm in the air. If the width **L1** of the wide region **9212** may be set to 2.5 mm, and the distance **L2** between two adjacent narrow regions **9211** is set to 2 mm, a sound pressure level may be decreased by more than 20 dB after the sound wave at 41 KHz passes through the second sound output hole **921**.

[0301] As shown in FIG. **22**, the second sound output hole (**921**) has an acoustic Helmholtz resonator. In this case, the front cavity filter **92** has a resonant cavity **922**. The resonant cavity **922** communicates with the second sound output hole **921**. In this way, the front cavity filter **92** may be configured to: filter out the high-frequency sound wave, and pass the low-frequency sound wave. It may be understood that the resonant cavity **922** is not limited to one cavity shown in FIG. **22**, and there may be a plurality of resonant cavities **922**. The plurality of resonant cavities **922** may differ in dimension.

[0302] The resonant cavity **922** includes a first cavity **9221** and a second cavity **9222**. A cross-sectional width of the first cavity **9221** is less than a cross-sectional width of the second cavity **9222**. The first cavity **9221** communicates with the second sound output hole **921**.

[0303] For example, a characteristic length of the first cavity **9221** is greater than 0.01 mm, and a characteristic length of the second cavity **9222** falls within a range of 0.1 mm to 50 mm. It may be understood that the characteristic length of the first cavity **9221** means a distance between two farthest points in the first cavity **9221**. For example, the first cavity **9221** is spherical, and the characteristic length of the first cavity **9221** is a diameter of the sphere. For another example, the first cavity **9221** is cylindrical, and the characteristic length of the first cavity **9221** is a height of the cylinder or the like. In addition, the characteristic length of the second cavity **9222** means a

distance between two farthest points in the second cavity **9222**. For an example of the characteristic length of the second cavity **9222**, refer to the example of the characteristic length of the first cavity **9221**. Details are not described herein again.

[0304] It may be understood that a frequency of a sound wave filtered out by the front cavity filter **92** is related to both the characteristic length of the first cavity **9221** and the characteristic length of the second cavity **9222**. An example in which $f_{\text{sub.1}}=40$ KHz and $f_{\text{sub.2}}=41$ KHz is used for description. The sound wave at $|f_{\text{sub.1}}+f_{\text{sub.2}}|=41$ KHz needs to be filtered out, and corresponds to a wavelength of $20=8.4$ mm in the air. If a diameter of the second sound output hole **921** is 1 mm, the characteristic length of the first cavity **9221** may be set to 0.5 mm, and the characteristic length of the second cavity **9222** may be set to 4.5 mm. In this way, a sound pressure level may be decreased by more than 20 dB after the sound wave 41 KHz passes through the second sound output hole **921**.

[0305] In another implementation, the front cavity filter **92** may alternatively use another pipe or cavity structure. The pipe or cavity may satisfy a principle such as pipe resonance and transmission. In this way, the front cavity filter **92** may be configured to: filter out the high-frequency sound wave, and pass the low-frequency sound wave.

[0306] In another implementation, the front cavity filter **92** may alternatively use another low-pass structure or another band-stop structure.

[0307] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. For example, when this implementation is combined with the implementations in FIG. **18** and FIG. **19**, the adjustment mechanism **80** may be located on a top part of the front cavity filter **92**. The first sound output hole **81** of the adjustment mechanism **80** communicates with the second sound output hole **921** of the front cavity filter **92**. Details are not described herein again.

[0308] FIG. **23** is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in still another implementation. FIG. **24** is a diagram of energy distribution of a main lobe of a first sound wave emitted by a plurality of transducers **22** shown in FIG. **23**.

[0309] As shown in FIG. **23** and FIG. **24**, in some implementations, there are a plurality of transducers **22**. The plurality of transducers **22** are arranged on the base **21** at an interval in a rotation direction. In this way, when the driving apparatus **23** drives the base **21** to rotate, the base **21** drives the plurality of transducers **22** to rotate around a rotating shaft (shown by using a point P in FIG. **23**).

[0310] It may be understood that when the rotation angle θ of the base **21** is equal to 0° , the plurality of transducers **22** emit the first sound wave at the frequency of $f_{\text{sub.1}}$ under the driving of the first control signal. FIG. **23** schematically shows the transducer **22** and a conduction direction of the first sound wave when $\theta=0^\circ$ through a curved solid line. When the rotation angle θ of the base **21** is equal to θ_1 ($\theta_1 > 0$ or $\theta_1 \leq 0$), the plurality of transducers **22** also emit the first sound wave at the frequency of $f_{\text{sub.1}}$ under the driving of the first control signal. FIG. **23** schematically shows the transducer **22** and a conduction direction of the first sound wave when $\theta=0^\circ$ through a curved dashed line. In a process in which the plurality of transducers **22** perform reciprocating rotation, the sound pressure amplitude of the first sound wave reciprocally changes. In this case, the first sound wave is modulated to form the second sound wave. The second sound wave may include an audible sound. It may be understood that because the plurality of transducers **22** are arranged on the base **21** at an interval in the rotation direction, in a rotation process of the plurality of transducers **22**, each transducer **22** may pass through a position of another transducer **22**. In this way, the first sound wave jointly emitted by the plurality of transducers **22** has a plurality of side lobes or a plurality of beams. Each side lobe may be used as a main lobe shown in FIG. **7**. In this way, a requirement for a rotation frequency can be greatly lowered. For example, if there are n transducers **22** and n side lobes, an equivalent rotation frequency of the n side lobes in a rotation process is $n \times f$.

Therefore, the n side lobes can reduce the rotation frequency to $f_{\text{sub.2}}/n$.

[0311] In an implementation, the base **21** is cylindrical. The plurality of transducers **22** are fastened on an outer surface of the cylindrical base **21** at an interval. The driving apparatus **23** may be a motor. An output shaft of the motor is connected to a top surface or a bottom surface of the cylindrical base **21**. For example, the output shaft of the motor may be parallel to a central axis of the cylindrical base **21**. In this way, when the output shaft of the motor rotates, the output shaft of the motor may drive the cylindrical base **21** to drive the plurality of transducers **22** to rotate.

[0312] In another implementation, a plurality of side lobes or a plurality of beams may alternatively be disposed by using another acoustic multipole structure.

[0313] It may be understood that the structural feature in this implementation may be combined with the sound generation apparatus **100** in the foregoing implementations. Details are not described herein again.

[0314] FIG. **25** is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in still another implementation.

[0315] As shown in FIG. **25**, the sound generation apparatus **100** further includes a reflector **90**. The reflector **90** has a reflective surface **93**.

[0316] In addition, the reflector **90** is disposed at an interval from the transducer **22**. The reflective surface **93** of the reflector **90** faces the vibration member **222** of the transducer **22**. It may be understood that the transducer **22** is disposed to emit the first sound wave at the frequency of $f_{\text{sub.2}}$ to the outside while performing periodic motion at the frequency of $f_{\text{sub.1}}$. In this case, in a process in which the transducer **22** performs periodic motion, the sound pressure amplitude of the first sound wave periodically changes. The first sound wave may be modulated to form the second sound wave. After being reflected by the reflector **90**, the second sound wave may be transmitted to the external space of the casing **50** through the sound outlet hole **51**. Therefore, the reflector **90** in this implementation may be configured to adjust a propagation angle of the second sound wave. In this way, the position of the sound outlet hole **51** may be more flexibly set. As shown in FIG. **25**, when the transducer **22** performs reciprocating rotation at the frequency of $f_{\text{sub.2}}$, the first sound wave propagated in the positive direction of the Z-axis may be reflected for propagation in the direction of the X-axis.

[0317] FIG. **26** is a diagram of a structure of the sound generation component **20** of the sound generation apparatus **100** shown in FIG. **2** in still another implementation.

[0318] As shown in FIG. **26**, in an implementation, the casing **50** is provided with a mounting hole **55**. The mounting hole **55** communicates with the inner cavity **52** and the external space of the casing **50**. The mounting hole **55** is disposed in a staggered manner with the sound outlet hole **51**. For example, the sound outlet hole **51** is disposed on a top wall **531** of the casing **50**. The mounting hole **55** is disposed on a side wall **533** of the casing **50**.

[0319] The reflector **90** is fixedly connected to a hole wall of the mounting hole **55**.

[0320] For example, the reflector **90** includes a first fixed shaft **94a** and a second fixed shaft **94b**. The first fixed shaft **94a** and the second fixed shaft **94b** are convexly disposed on two side faces that are disposed facing away from each other. Both the first fixed shaft **94a** and the second fixed shaft **94b** are fixedly connected to the hole wall of the mounting hole **55**. In another implementation, the first fixed shaft **94a** and the second fixed shaft **94b** may pass through the reflector **90**, and are connected to form a rotating shaft.

[0321] In an implementation, a part of the reflector **90** is located in the inner cavity **52** of the casing **50**, a part is located in the mounting hole **55**, and a part is located in the external space of the casing **50**. In this way, the reflector **90** may use space of the mounting hole **55** and the external space of the casing **50** to a large extent, to facilitate miniaturization of the sound generation apparatus. In addition, the reflector **90** may avoid a component in the inner cavity **52** of the casing **50** to a large extent, to avoid interference between the reflector **90** and another component in a rotation process.

[0322] The sound generation apparatus **100** is described in detail above with reference to related

accompanying drawings. The following schematically provides some transducers **22** that can emit ultrasonic waves. The following transducer **22** is referred to as an ultrasonic transducer. [0323] In some embodiments, the ultrasonic transducer may alternatively be a polyvinylidene difluoride (PVDF) piezoelectric film ultrasonic transducer. The vibration member of the ultrasonic transducer is a polyvinylidene difluoride piezoelectric film. The polyvinylidene difluoride piezoelectric film may implement ultrasonic wave emission on a curved surface or a plane by using a simple constraint method, and a frequency is high. A resonance frequency of the vibration member usually falls within a range of 1 megahertz (MHz) to 100 MHz. In this case, the vibration member of the ultrasonic transducer can easily obtain a resonance frequency greater than 400 kHz. Certainly, in some other embodiments, the resonance frequency of the vibration member of the ultrasonic transducer may alternatively be another resonance frequency, for example, less than 400 kHz.

[0324] In some other embodiments, the ultrasonic transducer may alternatively be a micromachined ultrasonic transducer (MUT). For example, the ultrasonic transducer may be a capacitive micromachined ultrasonic transducer (CMUT) or a piezoelectric MUT (PMUT). The resonance frequency of the vibration member of the ultrasonic transducer in this embodiment is usually high, for example, may be greater than or equal to 400 kHz. Certainly, in some other embodiments, the resonance frequency of the vibration member of the ultrasonic transducer may alternatively be less than 400 kHz.

[0325] Both the capacitive micromachined ultrasonic transducer and the piezoelectric micromachined ultrasonic transducer are micro-ultrasonic transducers manufactured by using a MEMS process. For the capacitive micromachined ultrasonic transducer, a cavity is usually formed on a silicon substrate, a top surface of the cavity is made of a diaphragm material, for example, nitride, and a signal is applied by using an electrode material, to implement ultrasonic wave emission. For the piezoelectric micromachined ultrasonic transducer, a piezoelectric material, for example, lead zirconate titanate piezoelectric ceramics, is usually stacked on a silicon substrate. Similarly, after a signal is applied through an electrode, an ultrasonic wave is generated due to a converse piezoelectric effect. The two types of ultrasonic transducers based on the MEMS process can be conveniently designed in an array. This helps increase a sound pressure level of an initial ultrasonic wave formed by the vibration member, thereby increasing a sound pressure level of a modulated ultrasonic wave formed by the sound generation apparatus **100**. Therefore, a sound pressure level of an audible sound is high.

[0326] It may be understood that in addition to the foregoing embodiments, the ultrasonic transducer may have another implementation structure. This is not strictly limited in this embodiment of this application.

[0327] It may be understood that embodiments of this application and features in embodiments may be combined with each other if there is no conflict, and any combination of features in different embodiments also falls within the protection scope of this application. In other words, the plurality of embodiments described above may be further randomly combined based on an actual requirement.

[0328] It may be understood that all the foregoing accompanying drawings are example illustrations of this application, and do not represent actual sizes of products. In addition, a dimension proportion relationship between parts in the accompanying drawings is not intended to limit an actual product in this application.

[0329] The foregoing descriptions are merely specific implementations of this application, but are not intended to limit the protection scope of this application. Any variation or replacement readily figured out by a person skilled in the art within the technical scope disclosed in this application shall fall within the protection scope of this application. If there is no conflict, embodiments of this application and the features in embodiments may be combined with each other. Therefore, the protection scope of this application shall be subject to the protection scope of the claims.

Claims

1. An electronic device, comprising: a sound generation apparatus comprising: a transducer comprising a vibration member; a driving apparatus coupled to the transducer; and a control circuit electrically coupled to the transducer and the driving apparatus and configured to: drive the vibration member to vibrate; and control the driving apparatus to drive the transducer to perform a periodic motion.
2. The electronic device of claim 1, wherein the control circuit is further configured to control the driving apparatus to drive the transducer to perform continuous rotation, reciprocating rotation, or reciprocating translational motion.
3. The electronic device of claim 2, wherein the transducer further comprises a rotating shaft, and wherein, when the transducer performs continuous rotation or reciprocating rotation, the rotating shaft deviates from a center of the transducer and is parallel to a plane on which the transducer is located, intersects with the transducer, or is perpendicular to the transducer.
4. The electronic device of claim 1, wherein the sound generation apparatus further comprises a base comprising a first side and a second side, wherein the transducer is disposed on the base, wherein the driving apparatus comprises: a first cantilever comprising a first movable end coupled to the first side; and a second cantilever comprising a second movable end coupled to the second side, wherein the control circuit is further configured to drive the first movable end and the second movable end to perform reciprocating vibration, and wherein, in a same time period, vibration directions of the first movable end and the second movable end are opposite.
5. The electronic device of claim 4, wherein the base has a rotation angle (θ), and wherein θ satisfies: $-45^{\circ} \leq \theta \leq 45^{\circ}$.
6. The electronic device of claim 1, wherein the sound generation apparatus further comprises a base, wherein the transducer is disposed on the base, wherein the driving apparatus comprises a first motor, and wherein the first motor comprises a first output shaft coupled to the base and configured to drive the base to perform reciprocating rotation or continuous rotation.
7. The electronic device of claim 6, wherein the sound generation apparatus further comprises a plurality of transducers arranged on the base at an interval in a rotation direction.
8. The electronic device of claim 1, wherein the sound generation apparatus further comprises a base, wherein the transducer is disposed on the base, and wherein the driving apparatus comprises a telescopic arm coupled to the base and configured to extend and retract to drive the base to perform reciprocating translational motion.
9. The electronic device of claim 1, wherein the control circuit is further configured to: generate a first control signal configured to drive the vibration member to vibrate for generating a first sound wave; and generate a second control signal configured to control the driving apparatus to drive the transducer in a periodic motion to modulate the first sound wave to generate a second sound wave.
10. The electronic device of claim 9, wherein the first control signal comprises a first frequency ($f_{\text{sub.1}}$), wherein $f_{\text{sub.1}}$ is a first single frequency or a first wideband frequency, wherein the second control signal comprises a second frequency ($f_{\text{sub.2}}$), and wherein $f_{\text{sub.2}}$ is a second single frequency or a second wideband frequency.
11. The electronic device of claim 10, wherein the second sound wave comprises an audible sound, and wherein $f_{\text{sub.1}}$ and $f_{\text{sub.2}}$ satisfy: $20 \text{ Hz} \leq |f_{\text{sub.1}} - f_{\text{sub.2}}| \leq 20 \text{ KHz}$.
12. The electronic device of claim 10, wherein the second sound wave comprises a third frequency, and wherein the third frequency is $|f_{\text{sub.1}} - f_{\text{sub.2}}|$ and $|f_{\text{sub.1}} + f_{\text{sub.2}}|$.
13. The electronic device of claim 12, wherein $f_{\text{sub.1}}$ and $f_{\text{sub.2}}$ further satisfy: $f_{\text{sub.1}} \geq 20$ and $f_{\text{sub.2}} \geq 20 \text{ KHz}$.
14. The electronic device of claim 12, wherein $f_{\text{sub.1}}$ and $f_{\text{sub.2}}$ further satisfy: $|f_{\text{sub.1}} + f_{\text{sub.2}}| \geq 20 \text{ KHz}$.

15. The electronic device of claim 9, wherein the vibration member comprises a vibration frequency, wherein the vibration frequency comprises a first frequency (f.sub.1), wherein f.sub.1 is a first single frequency or a first wideband frequency, wherein the transducer comprises a motion frequency, wherein the motion frequency comprises a second frequency (f.sub.2), wherein f.sub.2 is a second single frequency or a second wideband frequency, wherein the second sound wave comprises a third frequency, wherein the third frequency comprises $|f.sub.1 - f.sub.2|$ and $|f.sub.1 + f.sub.2|$, wherein at least a part of the second sound wave comprises an audible sound, and wherein f.sub.1 and f.sub.2 satisfy: $20\text{ Hz} \leq |f.sub.1 - f.sub.2| \leq 20\text{ KHz}$.

16. The electronic device of claim 1, wherein the sound generation apparatus further comprises a casing, and wherein the casing comprises: an inner cavity, wherein both the transducer and the driving apparatus are disposed in the inner cavity; an external space, wherein the control circuit is disposed in the inner cavity or the external space; and a sound outlet hole that communicates with the inner cavity and the external space.

17. The electronic device of claim 16, wherein the sound outlet hole comprises an extension direction, wherein there is an included angle (a) between an axial direction of the vibration member and the sound outlet hole, and wherein a satisfies: $45^\circ \leq a \leq 135^\circ$.

18. The electronic device of claim 16, wherein the casing comprises an inner surface, and wherein the sound generation apparatus further comprises a sound-absorbing part disposed on the inner surface and arranged in a staggered manner with the sound outlet hole.

19. The electronic device of claim 16, wherein the casing further comprises a sound wave guiding structure disposed at an interval from the sound outlet hole and communicating the inner cavity with the external space.

20. The electronic device of claim 19, wherein the sound wave guiding structure is a hole structure and/or a pipe structure, wherein a minimum width of the sound wave guiding structure is greater than a thickness (d_u) of a viscous layer, wherein d_u satisfies: $d = 0.22\text{mm} \times \sqrt{\frac{100\text{Hz}}{f_1}}$, and wherein f.sub.1 is a frequency of a first sound wave.
