

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250284008

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

Ferrara; James et al.

SYSTEMS AND METHODS OF LIDAR SENSOR SYSTEMS HAVING INTEGRATED SEMICONDUCTOR DEVICES

Abstract

A light detection and ranging (LIDAR) sensor system includes a circuit module. The circuit module includes a silicon substrate having a first thermal feature. The circuit module includes a III-V semiconductor substrate coupled to the silicon substrate, the III-V semiconductor substrate having a second thermal feature. The circuit board includes an optical device coupled to the III-V semiconductor substrate, the optical device configured to output a transmit beam. The circuit module further includes a plurality of vias disposed in a particular portion of the silicon substrate, where the particular portion corresponds to the III-V semiconductor substrate, at least one of the plurality of vias having a third thermal feature. The LIDAR system further includes a scanner configured to direct the transmit beam to an environment of the vehicle.

Inventors: Ferrara; James (Oakland, CA), Jujjavarapu; Pruthvi (Palo Alto, CA), Liang; Yongxuan Edward (Fremont, CA), Lin; Sen (Mountain View, CA), Tang; Zhizhong (Palo Alto, CA)

Applicant: Aurora Operations, Inc. (Pittsburgh, PA)

Family ID: 1000008620846

Appl. No.: 19/217754

Filed: May 23, 2025

Related U.S. Application Data

parent US continuation 18109125 20230213 parent-grant-document US 12352868 child US 19217754

Publication Classification

Int. Cl.: G01S17/931 (20200101); **B60W10/18** (20120101); **B60W10/20** (20060101); **B60W60/00** (20200101); **G01S7/481** (20060101); **G01S17/58** (20060101); **H01L23/00** (20060101); **H01L23/48** (20060101); **H01L25/16** (20230101)

U.S. Cl.:

CPC G01S17/931 (20200101); **B60W10/18** (20130101); **B60W10/20** (20130101); **B60W60/001** (20200201); **G01S7/4817** (20130101); **G01S17/58** (20130101); **H01L23/481** (20130101); **H01L25/167** (20130101); B60W2420/408 (20240101); B60W2554/4042 (20200201); B60W2554/802 (20200201); H01L24/14 (20130101); H01L24/16 (20130101); H01L24/48 (20130101); H01L24/73 (20130101); H01L2224/14181 (20130101); H01L2224/16145 (20130101); H01L2224/48145 (20130101); H01L2224/73207 (20130101); H01L2224/73257 (20130101)

Background/Summary

BACKGROUND

[0001] Optical detection of range using lasers, often referenced by a mnemonic, LIDAR (for “light detection and ranging”), also sometimes referred to as “laser RADAR,” is used for a variety of applications, including imaging and collision avoidance. LIDAR provides finer scale range resolution with smaller beam sizes than conventional microwave ranging systems, such as radio-wave detection and ranging (RADAR).

SUMMARY

[0002] At least one aspect relates to a light detection and ranging (LIDAR) sensor system for a vehicle. The LIDAR system includes a circuit module. The circuit module includes a silicon substrate having a first thermal feature (e.g., a thermal property, a thermomechanical property, etc.). The circuit module includes a III-V semiconductor substrate coupled to the silicon substrate, the III-V semiconductor substrate having a second thermal feature. The circuit board includes an optical device disposed on the III-V semiconductor substrate, the optical device configured to output a transmit beam. The circuit module further includes a plurality of vias disposed in a particular portion of the silicon substrate, where the particular portion corresponds to the III-V semiconductor substrate, at least one of the plurality of vias having a third thermal feature. The LIDAR system further includes a scanner configured to direct the transmit beam to an environment of the vehicle.

[0003] At least one aspect relates to an autonomous vehicle control system. The autonomous vehicle control system includes a LIDAR sensor system. The LIDAR sensor system includes a circuit module that includes a silicon substrate having a first thermal feature. The circuit module includes a III-V semiconductor substrate coupled to the silicon substrate, the III-V semiconductor substrate having a thermal feature. The circuit module includes an optical device coupled to the III-V semiconductor substrate, the optical device configured to output a transmit beam. The circuit module further includes a plurality of vias disposed in a particular portion of the silicon substrate that corresponds to the III-V semiconductor substrate, each via having a third thermal feature. The LIDAR sensor system further includes a scanner configured to direct the transmit beam to an environment of the vehicle. The autonomous vehicle control system further includes one or more processors configured to determine at least one of a range to the object or a velocity of an object based on a return beam from at least one of reflection or scattering of the transmit beam by the object and control operation of an autonomous vehicle based on the at least one of the range or the velocity.

[0004] At least one aspect relates to an autonomous vehicle. The autonomous vehicle includes a LIDAR sensor system. The LIDAR sensor system includes a circuit module that includes a silicon substrate having a first thermal feature. The circuit module includes a III-V semiconductor substrate coupled to the silicon substrate, the III-V semiconductor substrate having a thermal feature. The circuit module includes an optical device coupled to the III-V semiconductor substrate, the optical device configured to output a transmit beam. The circuit module further includes a plurality of vias disposed in a particular portion of the silicon substrate that corresponds to the III-V semiconductor substrate, each via having a third thermal feature. The LIDAR sensor system further includes a scanner configured to direct the transmit beam to an environment of the vehicle. The autonomous vehicle includes a steering system. The autonomous vehicle includes a braking system. The autonomous vehicle further includes a vehicle controller having one or more processors configured to determine at least one of a range to the object or a velocity of an object based on a return beam from at least one of reflection or scattering of the transmit beam by the object and control operation of at least one of the steering system or the braking system based on the at least one of the range or the velocity.

[0005] At least one aspect relates to a LIDAR sensor system. The LIDAR sensor system includes a circuit module. The circuit module includes a silicon substrate having a first thermal feature. The circuit module includes a III-V semiconductor substrate coupled to the silicon substrate at a bonding interface, the III-V semiconductor substrate having a second thermal feature. The bonding interface includes a metal bonding layer coupled to the silicon substrate and the III-V semiconductor substrate, the metal bonding layer having a third thermal feature. The circuit module further includes an optical device coupled to the III-V semiconductor substrate, the optical device configured to output a transmit beam. The LIDAR sensor system further includes a scanner configured to direct the transmit beam to an environment of the vehicle.

[0006] Those skilled in the art will appreciate that the summary is illustrative only and is not intended to be in any way limiting. Any of the features described herein may be used with any other features, and any subset of such features can be used in combination according to various embodiments. Other aspects, inventive features, and advantages of the devices and/or processes described herein, as defined solely by the claims, will become apparent in the detailed description set forth herein and taken in conjunction with the accompanying drawings.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0007] Implementations are illustrated by way of example, and not by way of limitation, in the figures of the accompanying drawings in which like reference numerals refer to similar elements and in which:

[0008] FIG. 1 is a block diagram of an example of a system environment for autonomous vehicles;

[0009] FIG. 2 is a block diagram of an example of a system environment for autonomous commercial trucking vehicles,

[0010] FIG. 3 is a block diagram of an example of a system environment for autonomous commercial trucking vehicles,

[0011] FIG. 4 is a block diagram of an example of a system environment for autonomous commercial trucking vehicles;

[0012] FIG. 5 is a block diagram of an example of a LIDAR sensor system;

[0013] FIG. 6 is a block diagram of an example of an optic module of a LIDAR sensor system;

[0014] FIG. 7 is a schematic cross-sectional view of an example of a circuit module, in portion or in entirety, of a LIDAR sensor system;

[0015] FIG. 8 is a schematic cross-sectional view of a portion of the circuit module of the LIDAR

sensor system as depicted in FIG. 7;

[0016] FIG. 9 is a schematic cross-sectional view of a portion of the circuit module of the LIDAR sensor system as depicted in FIG. 7;

[0017] FIG. 10 is a schematic X-Y cross-sectional view of a portion of the circuit module along line AA' of the LIDAR sensor system as depicted in FIG. 7;

[0018] FIG. 11 is a table of example materials and their corresponding coefficient of thermal expansion (CTE) at room temperature;

[0019] FIG. 12 is a schematic relationship between effective CTE.sub.eff of a silicon substrate and an amount of TSVs included in the silicon substrate;

[0020] FIG. 13 is a flow diagram showing an example of a method of integrating semiconductor substrates in a circuit module of a LIDAR sensor system;

[0021] FIG. 14 is a schematic cross-sectional view of an example of a circuit module, in portion or in entirety, of a LIDAR sensor system;

[0022] FIG. 15 is a schematic cross-sectional view of an example of a circuit module, in portion or in entirety, of a LIDAR sensor system;

[0023] FIG. 16 is a schematic cross-sectional view of a portion of the circuit module of the LIDAR sensor system as depicted in each of FIG. 14 and FIG. 15; and

[0024] FIG. 17 is a schematic cross-sectional view of a portion of the circuit module of the LIDAR sensor system as depicted in each of FIG. 14 and FIG. 15.

DETAILED DESCRIPTION

[0025] A LIDAR sensor system can generate and transmit a light beam that an object can reflect or otherwise scatter as a return beam corresponding to the transmitted beam. The LIDAR sensor system can receive the return beam, and process the return beam or characteristics thereof to determine parameters regarding the object such as range and velocity. The LIDAR sensor system can apply various frequency or phase modulations to the transmitted beam, which can facilitate relating the return beam to the transmitted beam in order to determine the parameters regarding the object.

[0026] Integrated circuit (IC) packages (or modules) integrating III-V semiconductor devices (or dies) that include GaAs, InP, or other optoelectronic, with silicon substrates (or silicon devices) can be used in vehicle LIDAR sensor systems to facilitate various optical and electronic data communication and signal processing operations. However, coupling of dissimilar materials, such as a III-V semiconductor material and silicon, may be affected by mismatch in one or more material property or feature between the dissimilar materials. One such material feature relevant to the coupling of III-V semiconductor materials with silicon is coefficient of thermal expansion (CTE). The mismatch in CTE (alternatively referred to as ΔCTE hereafter) between III-V semiconductor material and silicon can result in mechanical stress at a bonding interface in the presence of thermal stress, which can arise from heat generated by optical components of the LIDAR sensor systems, including under vehicle temperature conditions, a bonding process between the materials (the formation of a solder bonding layer, for example) and/or from a thermal cycle reliability test. In some examples, the temperature for forming a AuSn-based solder bonding layer can be more 300° C. and the thermal cycle reliability test (which can be used to test the devices described herein for operation in LIDAR sensor systems under vehicle operation conditions) may subject the coupled materials to a few hundreds to thousands of cyclic stress from -40° C. or lower to 85° C. or higher. Such mechanical stress may cause defects (e.g., cracks) forming in the solder bonding layer, defects forming in one or both of the semiconductor materials, and/or or delamination of the solder bonding layer from one or both of the semiconductor materials.

[0027] Systems and methods in accordance with the present disclosure can facilitate more robust coupling between materials in LIDAR sensor systems, including between silicon and III-V semiconductor materials. For example, the LIDAR sensor systems can include components to

locally reduce the mismatch in CTE between the III-V semiconductor material substrate and the silicon substrate while meeting optical and signal processing performance targets. For example, an overall CTE of the silicon substrate can be increased by including an array of conductive through-silicon (or substrate)-vias (TSVs) in a particular portion of the silicon substrate in contact with the III-V semiconductor substrate. By adjusting configuration and composition of the array of TSVs embedded in the particular portion of the silicon substrate, the composite CTE of that portion of the silicon substrate can be tuned to more closely resemble that of the III-V semiconductor substrate, thereby reducing occurrence of mechanical stress at the bonding interface as well as mechanical stress within the III-V semiconductor substrate and the silicon substrate, respectively, which can improve the process yield and reliability of the final product.

1. System Environments for Autonomous Vehicles

[0028] FIG. 1 is a block diagram illustrating an example of a system environment for autonomous vehicles according to some implementations. FIG. 1 depicts an example autonomous vehicle **100** within which the various techniques disclosed herein may be implemented. The vehicle **100**, for example, may include a powertrain **102** including a prime mover **104** powered by an energy source **106** and capable of providing power to a drivetrain **108**, as well as a control system **110** including a direction control **112**, a powertrain control **114**, and a brake control **116**. The vehicle **100** may be implemented as any number of different types of vehicles, including vehicles capable of transporting people and/or cargo, and capable of traveling in various environments. The aforementioned components **102-116** can vary widely based upon the type of vehicle within which these components are utilized, such as a wheeled land vehicle such as a car, van, truck, or bus. The prime mover **104** may include one or more electric motors and/or an internal combustion engine (among others). The energy source may include, for example, a fuel system (e.g., providing gasoline, diesel, hydrogen, etc.), a battery system, solar panels or other renewable energy source, and/or a fuel cell system. The drivetrain **108** can include wheels and/or tires along with a transmission and/or any other mechanical drive components to convert the output of the prime mover **104** into vehicular motion, as well as one or more brakes configured to controllably stop or slow the vehicle **100** and direction or steering components suitable for controlling the trajectory of the vehicle **100** (e.g., a rack and pinion steering linkage enabling one or more wheels of the vehicle **100** to pivot about a generally vertical axis to vary an angle of the rotational planes of the wheels relative to the longitudinal axis of the vehicle). In some implementations, combinations of powertrains and energy sources may be used (e.g., in the case of electric/gas hybrid vehicles), and in some instances multiple electric motors (e.g., dedicated to individual wheels or axles) may be used as a prime mover.

[0029] The direction control **112** may include one or more actuators and/or sensors for controlling and receiving feedback from the direction or steering components to enable the vehicle **100** to follow a desired trajectory. The powertrain control **114** may be configured to control the output of the powertrain **102**, e.g., to control the output power of the prime mover **104**, to control a gear of a transmission in the drivetrain **108**, etc., thereby controlling a speed and/or direction of the vehicle **100**. The brake control **116** may be configured to control one or more brakes that slow or stop vehicle **100**, e.g., disk or drum brakes coupled to the wheels of the vehicle.

[0030] Other vehicle types, including but not limited to off-road vehicles, all-terrain or tracked vehicles, construction equipment, may utilize different powertrains, drivetrains, energy sources, direction controls, powertrain controls and brake controls. Moreover, in some implementations, some of the components can be combined, e.g., where directional control of a vehicle is primarily handled by varying an output of one or more prime movers.

[0031] Various levels of autonomous control over the vehicle **100** can be implemented in a vehicle control system **120**, which may include one or more processors **122** and one or more memories **124**, with each processor **122** configured to execute program code instructions **126** stored in a memory **124**. The processors(s) can include, for example, graphics processing unit(s) (“GPU(s)”)

and/or central processing unit(s) (“CPU(s)”).

[0032] Sensors **130** may include various sensors suitable for collecting information from a vehicle's surrounding environment for use in controlling the operation of the vehicle. For example, sensors **130** can include radar sensor **134**, LIDAR (Light Detection and Ranging) sensor **136**, a 3D positioning sensors **138**, e.g., any of an accelerometer, a gyroscope, a magnetometer, or a satellite navigation system such as GPS (Global Positioning System), GLONASS (Globalnaya Navigazionnaya Sputnikovaya Sistema, or Global Navigation Satellite System), BeiDou Navigation Satellite System (BDS), Galileo, Compass, etc. The 3D positioning sensors **138** can be used to determine the location of the vehicle on the Earth using satellite signals. The sensors **130** can include a camera **140** and/or an IMU (inertial measurement unit) **142**. The camera **140** can be a monographic or stereographic camera and can record still and/or video images. The IMU **142** can include multiple gyroscopes and accelerometers capable of detecting linear and rotational motion of the vehicle in three directions. One or more encoders (not illustrated), such as wheel encoders may be used to monitor the rotation of one or more wheels of vehicle **100**. Each sensor **130** can output sensor data at various data rates, which may be different than the data rates of other sensors **130**.

[0033] The outputs of sensors **130** may be provided to a set of control subsystems **150**, including a localization subsystem **152**, a planning subsystem **156**, a perception subsystem **154**, and a control subsystem **158**. The localization subsystem **152** can perform functions such as precisely determining the location and orientation (also sometimes referred to as “pose”) of the vehicle **100** within its surrounding environment, and generally within some frame of reference. The location of an autonomous vehicle can be compared with the location of an additional vehicle in the same environment as part of generating labeled autonomous vehicle data. The perception subsystem **154** can perform functions such as detecting, tracking, determining, and/or identifying objects within the environment surrounding vehicle **100**. A machine learning model in accordance with some implementations can be utilized in tracking objects. The planning subsystem **156** can perform functions such as planning a trajectory for vehicle **100** over some timeframe given a desired destination as well as the static and moving objects within the environment. A machine learning model in accordance with some implementations can be utilized in planning a vehicle trajectory. The control subsystem **158** can perform functions such as generating suitable control signals for controlling the various controls in the vehicle control system **120** in order to implement the planned trajectory of the vehicle **100**. A machine learning model can be utilized to generate one or more signals to control an autonomous vehicle to implement the planned trajectory.

[0034] Multiple sensors of types illustrated in FIG. **1** can be used for redundancy and/or to cover different regions around a vehicle, and other types of sensors may be used. Various types and/or combinations of control subsystems may be used. Some or all of the functionality of a subsystem **152-158** may be implemented with program code instructions **126** resident in one or more memories **124** and executed by one or more processors **122**, and these subsystems **152-158** may in some instances be implemented using the same processor(s) and/or memory. Subsystems may be implemented at least in part using various dedicated circuit logic, various processors, various field programmable gate arrays (“FPGA”), various application-specific integrated circuits (“ASIC”), various real time controllers, and the like, as noted above, multiple subsystems may utilize circuitry, processors, sensors, and/or other components. Further, the various components in the vehicle control system **120** may be networked in various manners.

[0035] In some implementations, the vehicle **100** may also include a secondary vehicle control system (not illustrated), which may be used as a redundant or backup control system for the vehicle **100**. In some implementations, the secondary vehicle control system may be capable of fully operating the autonomous vehicle **100** in the event of an adverse event in the vehicle control system **120**, while in other implementations, the secondary vehicle control system may only have limited functionality, e.g, to perform a controlled stop of the vehicle **100** in response to an adverse event

detected in the primary vehicle control system **120**. In still other implementations, the secondary vehicle control system may be omitted.

[0036] Various architectures, including various combinations of software, hardware, circuit logic, sensors, and networks, may be used to implement the various components illustrated in FIG. **1**. Each processor may be implemented, for example, as a microprocessor and each memory may represent the random access memory (“RAM”) devices comprising a main storage, as well as any supplemental levels of memory, e.g., cache memories, non-volatile or backup memories (e.g., programmable or flash memories), read-only memories, etc. In addition, each memory may be considered to include memory storage physically located elsewhere in the vehicle **100**, e.g., any cache memory in a processor, as well as any storage capacity used as a virtual memory, e.g., as stored on a mass storage device or another computer controller. One or more processors illustrated in FIG. **1**, or entirely separate processors, may be used to implement additional functionality in the vehicle **100** outside of the purposes of autonomous control, e.g., to control entertainment systems, to operate doors, lights, convenience features, etc.

[0037] In addition, for additional storage, the vehicle **100** may include one or more mass storage devices, e.g., a removable disk drive, a hard disk drive, a direct access storage device (“DASD”), an optical drive (e.g., a CD drive, a DVD drive, etc.), a solid state storage drive (“SSD”), network attached storage, a storage area network, and/or a tape drive, among others.

[0038] Furthermore, the vehicle **100** may include a user interface **164** to enable vehicle **100** to receive a number of inputs from and generate outputs for a user or operator, e.g., one or more displays, touchscreens, voice and/or gesture interfaces, buttons and other tactile controls, etc. Otherwise, user input may be received via another computer or electronic device, e.g., via an app on a mobile device or via a web interface.

[0039] Moreover, the vehicle **100** may include one or more network interfaces, e.g., network interface **162**, suitable for communicating with one or more networks **170** (e.g., a Local Area Network (“LAN”), a wide area network (“WAN”), a wireless network, and/or the Internet, among others) to permit the communication of information with other computers and electronic device, including, for example, a central service, such as a cloud service, from which the vehicle **100** receives environmental and other data for use in autonomous control thereof. Data collected by the one or more sensors **130** can be uploaded to a computing system **172** via the network **170** for additional processing. In some implementations, a time stamp can be added to each instance of vehicle data prior to uploading.

[0040] Each processor illustrated in FIG. **1**, as well as various additional controllers and subsystems disclosed herein, generally operates under the control of an operating system and executes or otherwise relies upon various computer software applications, components, programs, objects, modules, data structures, etc., as will be described in greater detail below. Moreover, various applications, components, programs, objects, modules, etc. may also execute on one or more processors in another computer coupled to vehicle **100** via network **170**, e.g., in a distributed, cloud-based, or client-server computing environment, whereby the processing required to implement the functions of a computer program may be allocated to multiple computers and/or services over a network.

[0041] In general, the routines executed to implement the various implementations described herein, whether implemented as part of an operating system or a specific application, component, program, object, module or sequence of instructions, or even a subset thereof, will be referred to herein as “program code”. Program code can include one or more instructions that are resident at various times in various memory and storage devices, and that, when read and executed by one or more processors, perform the steps necessary to execute steps or elements embodying the various aspects of the present disclosure. Moreover, while implementations have and hereinafter will be described in the context of fully functioning computers and systems, it will be appreciated that the various implementations described herein are capable of being distributed as a program product in

a variety of forms, and that implementations can be implemented regardless of the particular type of computer readable media used to actually carry out the distribution.

[0042] Examples of computer readable media include tangible, non-transitory media such as volatile and non-volatile memory devices, floppy and other removable disks, solid state drives, hard disk drives, magnetic tape, and optical disks (e.g., CD-ROMs, DVDs, etc.) among others.

[0043] In addition, various program code described hereinafter may be identified based upon the application within which it is implemented in a specific implementation. Any particular program nomenclature that follows is used merely for convenience, and thus the present disclosure should not be limited to use solely in any specific application identified and/or implied by such nomenclature. Furthermore, given the typically endless number of manners in which computer programs may be organized into routines, procedures, methods, modules, objects, and the like, as well as the various manners in which program functionality may be allocated among various software layers that are resident within a typical computer (e.g., operating systems, libraries, API's, applications, applets, etc.), the present disclosure is not limited to the specific organization and allocation of program functionality described herein.

2. LIDAR for Automotive Applications

[0044] A truck can include a LIDAR system (e.g., vehicle control system **120** in FIG. **1**, LIDAR sensor system **500** in FIG. **5**, among others described herein). In some implementations, the LIDAR sensor system **500** can use frequency modulation to encode an optical signal and scatter the encoded optical signal into free-space using optics. By detecting the frequency differences between the encoded optical signal and a returned signal reflected back from an object, the frequency modulated (FM) LIDAR sensor system can determine the location of the object and/or precisely measure the velocity of the object using the Doppler effect. In some implementations, an FM LIDAR sensor system may use a continuous wave (referred to as, "FMCW LIDAR") or a quasi-continuous wave (referred to as, "FMQW LIDAR"). In some implementations, the LIDAR sensor system can use phase modulation (PM) to encode an optical signal and scatters the encoded optical signal into free-space using optics.

[0045] In some instances, an object (e.g., a pedestrian wearing dark clothing) may have a low reflectivity, in that it only reflects back to the sensors (e.g., sensors **130** in FIG. **1**) of the FM or PM LIDAR sensor system a low amount (e.g., 10% or less) of the light that hit the object. In other instances, an object (e.g., a shiny road sign) may have a high reflectivity (e.g., above 10%), in that it reflects back to the sensors of the FM LIDAR sensor system a high amount of the light that hit the object.

[0046] Regardless of the object's reflectivity, an FM LIDAR sensor system may be able to detect (e.g., classify, recognize, discover, etc.) the object at greater distances (e.g., 2×) than a conventional LIDAR sensor system. For example, an FM LIDAR sensor system may detect a low reflectively object beyond 300 meters, and a high reflectivity object beyond 400 meters.

[0047] To achieve such improvements in detection capability, the FM LIDAR sensor system may use sensors (e.g., sensors **130** in FIG. **1**). In some implementations, these sensors can be single photon sensitive, meaning that they can detect the smallest amount of light possible. While an FM LIDAR sensor system may, in some applications, use infrared wavelengths (e.g., 950 nm, 1550 nm, etc.), it is not limited to the infrared wavelength range (e.g., near infrared: 800 nm-1500 nm; middle infrared: 1500 nm-5600 nm; and far infrared: 5600 nm-1,000,000 nm). By operating the FM or PM LIDAR sensor system in infrared wavelengths, the FM or PM LIDAR sensor system can broadcast stronger light pulses or light beams than conventional LIDAR sensor systems.

[0048] Thus, by detecting an object at greater distances, an FM LIDAR sensor system may have more time to react to unexpected obstacles. Indeed, even a few milliseconds of extra time could improve response time and comfort, especially with heavy vehicles (e.g., commercial trucking vehicles) that are driving at highway speeds.

[0049] The FM LIDAR sensor system can provide accurate velocity for each data point

instantaneously. In some implementations, a velocity measurement is accomplished using the Doppler effect which shifts frequency of the light received from the object based at least one of the velocity in the radial direction (e.g., the direction vector between the object detected and the sensor) or the frequency of the laser signal. For example, for velocities encountered in on-road situations where the velocity is less than 100 meters per second (m/s), this shift at a wavelength of 1550 nanometers (nm) amounts to the frequency shift that is less than 130 megahertz (MHz). This frequency shift is small such that it is difficult to detect directly in the optical domain. However, by using coherent detection in FMCW, PMCW, or FMQW LIDAR sensor systems, the signal can be converted to the RF domain such that the frequency shift can be calculated using various signal processing techniques. This enables the autonomous vehicle control system to process incoming data faster.

[0050] Instantaneous velocity calculation also makes it easier for the FM LIDAR sensor system to determine distant or sparse data points as objects and/or track how those objects are moving over time. For example, an FM LIDAR sensor (e.g., sensors **130** in FIG. **1**) may only receive a few returns (e.g., hits) on an object that is 300 m away, but if those return give a velocity value of interest (e.g., moving towards the vehicle at >70 mph), then the FM LIDAR sensor system and/or the autonomous vehicle control system may determine respective weights to probabilities associated with the objects.

[0051] Faster identification and/or tracking of the FM LIDAR sensor system gives an autonomous vehicle control system more time to maneuver a vehicle. A better understanding of how fast objects are moving also allows the autonomous vehicle control system to plan a better reaction.

[0052] The FM LIDAR sensor system can have less static compared to conventional LIDAR sensor systems. That is, the conventional LIDAR sensor systems that are designed to be more light-sensitive typically perform poorly in bright sunlight. These systems also tend to suffer from crosstalk (e.g., when sensors get confused by each other's light pulses or light beams) and from self-interference (e.g., when a sensor gets confused by its own previous light pulse or light beam). To overcome these disadvantages, vehicles using the conventional LIDAR sensor systems often need extra hardware, complex software, and/or more computational power to manage this “noise.”

[0053] In contrast, FM LIDAR sensor systems do not suffer from these types of issues because each sensor is specially designed to respond only to its own light characteristics (e.g., light beams, light waves, light pulses). If the returning light does not match the timing, frequency, and/or wavelength of what was originally transmitted, then the FM sensor can filter (e.g., remove, ignore, etc.) out that data point. As such, FM LIDAR sensor systems produce (e.g., generates, derives, etc.) more accurate data with less hardware or software requirements, enabling smoother driving.

[0054] The FM LIDAR sensor system can be easier to scale than conventional LIDAR sensor systems. As more self-driving vehicles (e.g., cars, commercial trucks, etc.) show up on the road, those powered by an FM LIDAR sensor system likely will not have to contend with interference issues from sensor crosstalk. Furthermore, an FM LIDAR sensor system uses less optical peak power than conventional LIDAR sensors. As such, some or all of the optical components for an FM LIDAR can be produced on a single chip, which produces its own benefits, as discussed herein.

2.1 Commercial Trucking

[0055] FIG. **2** is a block diagram illustrating an example of a system environment for autonomous commercial trucking vehicles, according to some implementations. The environment **100B** includes a commercial truck **102B** for hauling cargo **106B**. In some implementations, the commercial truck **102B** may include vehicles configured to long-haul freight transport, regional freight transport, intermodal freight transport (i.e., in which a road-based vehicle is used as one of multiple modes of transportation to move freight), and/or any other road-based freight transport applications. In some implementations, the commercial truck **102B** may be a flatbed truck, a refrigerated truck (e.g., a reefer truck), a vented van (e.g., dry van), a moving truck, etc. In some implementations, the cargo **106B** may be goods and/or produce. In some implementations, the commercial truck **102B** may

include a trailer to carry the cargo **106B**, such as a flatbed trailer, a lowboy trailer, a step deck trailer, an extendable flatbed trailer, a sidekit trailer, etc.

[0056] The environment **100B** includes an object **110B** (shown in FIG. 2 as another vehicle) that is within a distance range that is equal to or less than 30 meters from the truck.

[0057] The commercial truck **102B** may include a LIDAR sensor system **104B** (e.g., an FM LIDAR sensor system, vehicle control system **120** in FIG. 1, LIDAR sensor system **500** in FIG. 5) for determining a distance to the object **110B** and/or measuring the velocity of the object **110B**. Although FIG. 2 shows that one LIDAR sensor system **104B** is mounted on the front of the commercial truck **102B**, the number of LIDAR sensor system and the mounting area of the LIDAR sensor system on the commercial truck are not limited to a particular number or a particular area. The commercial truck **102B** may include any number of LIDAR sensor systems **104B** (or components thereof, such as sensors, modulators, coherent signal generators, etc.) that are mounted onto any area (e.g., front, back, side, top, bottom, underneath, and/or bottom) of the commercial truck **102B** to facilitate the detection of an object in any free-space relative to the commercial truck **102B**.

[0058] As shown, the LIDAR sensor system **104B** in environment **100B** may be configured to detect an object (e.g., another vehicle, a bicycle, a tree, street signs, potholes, etc.) at short distances (e.g., 30 meters or less) from the commercial truck **102B**.

[0059] FIG. 3 is a block diagram illustrating an example of a system environment for autonomous commercial trucking vehicles, according to some implementations. The environment **100C** includes the same components (e.g., commercial truck **102B**, cargo **106B**, LIDAR sensor system **104B**, etc.) that are included in environment **100B**.

[0060] The environment **100C** includes an object **110C** (shown in FIG. 3 as another vehicle) that is within a distance range that is (i) more than 30 meters and (ii) equal to or less than 150 meters from the commercial truck **102B**. As shown, the LIDAR sensor system **104B** in environment **100C** may be configured to detect an object (e.g., another vehicle, a bicycle, a tree, street signs, potholes, etc.) at a distance (e.g., 100 meters) from the commercial truck **102B**.

[0061] FIG. 4 is a block diagram illustrating an example of a system environment for autonomous commercial trucking vehicles, according to some implementations. The environment **100D** includes the same components (e.g., commercial truck **102B**, cargo **106B**, LIDAR sensor system **104B**, etc.) that are included in environment **100B**.

[0062] The environment **100D** includes an object **110D** (shown in FIG. 4 as another vehicle) that is within a distance range that is more than 150 meters from the commercial truck **102B**. As shown, the LIDAR sensor system **104B** in environment **100D** may be configured to detect an object (e.g., another vehicle, a bicycle, a tree, street signs, potholes, etc.) at a distance (e.g., 300 meters) from the commercial truck **102B**.

[0063] In commercial trucking applications, it is important to effectively detect objects at all ranges due to the increased weight and, accordingly, longer stopping distance required for such vehicles. FM LIDAR sensor systems (e.g., FMCW and/or FMQW systems) or PM LIDAR sensor systems are well-suited for commercial trucking applications due to the advantages described above. As a result, commercial trucks equipped with such systems may have an enhanced ability to move both people and goods across short or long distances. In various implementations, such FM or PM LIDAR sensor systems can be used in semi-autonomous applications, in which the commercial truck has a driver and some functions of the commercial truck are autonomously operated using the FM or PM LIDAR sensor system, or fully autonomous applications, in which the commercial truck is operated entirely by the FM or LIDAR sensor system, alone or in combination with other vehicle systems.

3. LIDAR Sensor Systems

[0064] FIG. 5 depicts an example of a LIDAR sensor system **500**. The LIDAR sensor system **500** can be used to determine parameters regarding objects, such as range and velocity, and output the

parameters to a remote system. For example, the LIDAR sensor system **500** can output the parameters for use by a vehicle controller that can control operation of a vehicle responsive to the received parameters (e.g., vehicle controller **598**) or a display that can present a representation of the parameters. The LIDAR sensor system **500** can be a coherent detection system. The LIDAR sensor system **500** can be used to implement various features and components of the systems described with reference to FIGS. **1-4**. The LIDAR sensor system **500** can include components for performing various detection approaches, such as to be operated as an amplitude modular LIDAR system or a coherent LIDAR system. The LIDAR sensor system **500** can be used to perform time of flight range determination. In some implementations, various components or combinations of components of the LIDAR sensor system **500**, such as laser source **504** and modulator **514**, can be in a same housing, provided in a same circuit board or other electronic component, or otherwise integrated. In some implementations, various components or combinations of components of the LIDAR sensor system **500** can be provided as separate components, such as by using optical couplings (e.g., optical fibers) for components that generate and/or receive optical signals, such as light beams, or wired or wireless electronic connections for components that generate and/or receive electrical (e.g., data) signals. Various components of the LIDAR sensor system **500** can be arranged with respect to one another such that light (e.g., beams of light) between the components is directed through free space, such as a space provided by an air (or vacuum) gap, a space that is not through an optical fiber, a space that is free of structural components around a path along which the light is directed (e.g., an empty space at least on the order of millimeters away from a direct line path between the components; an empty space of a size greater than an expected beam width of the light, such as where the light is a collimated beam), or various combinations thereof.

[0065] In some implementations, a semiconductor substrate and/or semiconductor package include one or more components of at least one of a transmission (Tx) path or a receiving (Rx) path of the LIDAR sensor system **500**. This can include, for example, optical and/or electronic components that can generate heat that may be transferred into the semiconductor substrate and/or semiconductor package during operation. In some implementations, the semiconductor substrate and/or semiconductor package include at least one of silicon photonics circuitry, planar lightwave circuitry (PLC), or III-V semiconductor circuitry.

[0066] In some implementations, the optical and/or electronic components formed on or coupled to the semiconductor substrate and/or semiconductor package to perform a plurality of functions in the LIDAR sensor system **500** are collectively referred to as a circuit module. In some implementations, the circuit module includes III-V semiconductor circuitry coupled to at least one of silicon photonics circuitry or PLC. In the present disclosure, “coupling” may refer to a physical connection, an electrical connection, or both, between two components.

[0067] In some implementations, a first semiconductor substrate and/or a first semiconductor package include the Tx path and a second semiconductor substrate and/or a second semiconductor package may include the Rx path. In some arrangements, the Rx input/output ports and/or the Tx input/output ports may occur (or be formed/disposed/located/placed) along one or more edges of one or more semiconductor substrates and/or semiconductor packages.

[0068] In some implementations, the circuit module include at least one of silicon photonics circuitry, PLC, or III-V semiconductor circuitry in which all of its components (e.g., optical paths, optical amplifiers, phase modulators, etc.) are formed on, disposed over, or otherwise coupled to a single substrate. In some implementations, all of the components of the circuit module are formed on, disposed over, or otherwise coupled to a single layer to form a horizontal structure of an integrated circuit. In some implementations, components of the circuit module are formed on, disposed over, or otherwise coupled to multiple layers stacked on a single substrate to form a vertical structure of an integrated circuit. For example, the circuit module may include phase modulators implemented as one or more PLC modules, optical paths implemented as silicon photonics circuitry, and SOAs implemented as III-V modules, all of which are formed on, disposed

over, or otherwise coupled to a single III-V substrate. The III-V semiconductor materials may include at least one of gallium arsenide (GaAs), indium phosphide (InP), indium arsenide (InAs), or combinations thereof.

[0069] The LIDAR sensor system **500** can include a laser source **504** that generates and emits a beam **506**, such as a carrier wave light beam. An optic element **508** can split the beam **506** into a beam **510** and a reference beam **512** (e.g., reference signal). In some implementations, any suitable optical, electronic, or optoelectronic elements are used to provide the beam **510** and the reference beam **512** from the laser source **504** to other elements. For example, the optic element **508** can be a splitter or a circulator.

[0070] A modulator **514** can modulate one or more properties of the input beam **510** to generate a beam **516** (e.g., target beam). In some implementations, the modulator **514** can modulate a frequency of the input beam **510** (e.g., optical frequency corresponding to optical wavelength, where $c=\lambda v$, where c is the speed of light, λ is the wavelength, and v is the frequency). For example, the modulator **514** can modulate a frequency of the input beam **510** linearly such that a frequency of the beam **516** increases or decreases linearly over time. As another example, the modulator **514** can modulate a frequency of the input beam **510** non-linearly (e.g., exponentially). In some implementations, the modulator **514** can modulate a phase of the input beam **510** to generate the beam **516**. However, the modulation techniques are not limited to the frequency modulation and the phase modulation. Any suitable modulation techniques can be used to modulate one or more properties of a beam. Returning to FIG. 5, the modulator **514** can modulate the beam **510** subsequent to splitting of the beam **506** by the optic element **508**, such that the reference beam **512** is unmodulated, or the modulator **514** can modulate the beam **506** and provide a modulated beam to the optic element **508** for the optic element **508** to split into a target beam and a reference beam. In some implementations, the modulator **514** includes a circuit module having at least one of silicon photonics circuitry, PLC, or III-V semiconductor circuitry.

[0071] The beam **516**, which is used for outputting a transmitted signal, can have most of the energy of the beam **506** outputted by the laser source **504**, while the reference beam **512** can have significantly less energy, yet sufficient energy to enable mixing with a return beam **548** (e.g., returned light) scattered from an object. The reference beam **512** can be used as a local oscillator (LO) signal. The reference beam **512** passes through a reference path and can be provided to a mixer **560**. An amplifier **520** can amplify the beam **516** to output a beam **522**.

[0072] The LIDAR sensor system **500** can include an optic module **524**, which can receive the beam **522**. The optic module **524** can be a free space optic. For example, the optic module **524** can include one or more optics (e.g., lenses, mirrors, waveguides, grating couplers, prisms, waveplates) arranged to have a gap (e.g., air gap) between the one or more optics, allowing for free space transmission of light (e.g., rather than all light being coupled between optics by fibers). The optic module **524** can perform functions such as collimating, filtering, and/or polarizing the beam **522** to output a beam **530** to optics **532** (e.g., scanning optics).

[0073] Referring to FIG. 6, the optic module **524** can include at least one collimator **604** and at least one circulator **608**. For example, the circulator **608** can be between the collimator **604** and the optics **532** of FIG. 5. The circulator **608** can receive a collimated beam **612** outputted by the collimator **604** and output a beam **616** (e.g., the beam **530** depicted in FIG. 5) to the optics **532**. In some implementations, the circulator **608** can be between the laser source **504** and the collimator **604**. At least one of the collimator **604** or the circulator **608** can be free space optics (and can be coupled with one another in free space), such as by being optically coupled via air gaps rather than optical fibers.

[0074] Referring further to FIG. 5, the optic module **524** can receive return beam **548** from the optics **532** and provide the return beam **548** to the mixer **560**. The optics **532** can be scanning optics, such as one or more steering mirrors or polygon reflectors or deflectors to adjust the angle of received beams relative to outputted beams based on the orientation of outer surfaces (e.g.,

facets) of the optics relative to the received beam, or solid-state components (e.g., phased arrays, electro-optic crystals) configured to modify the direction of received light.

[0075] The optics **532** can define a field of view **544** that corresponds to angles scanned (e.g., swept) by the beam **542** (e.g., a transmitted beam). For example, the beam **542** can be scanned in the particular plane, such as an azimuth plane or elevation plane (e.g., relative to an object to which the LIDAR sensor system **500** is coupled, such as an autonomous vehicle). The optics **532** can be oriented so that the field of view **544** sweeps an azimuthal plane relative to the optics **532**.

[0076] At least one motor **540** can be coupled with the optics **532** to control at least one of a position or an orientation of the optics **532** relative to the beam **530**. For example, where the optics **532** include a mirror, reflector, or deflector, the motor **540** can rotate the optics **532** relative to an axis **534** (e.g., an axis orthogonal to the frame of reference depicted in FIG. 5) so that surfaces of the optics **532** at which the beam **530** is received vary in angle or orientation relative to the beam **530**, causing the beam **542** to be varied in angle or direction as the beam **542** is outputted from the optics **532**.

[0077] The beam **542** can be outputted from the optics **532** and reflected or otherwise scattered by an object (not shown) as a return beam **548** (e.g., return signal). The return beam **548** can be received on a reception path, which can include the circulator **608**, and provided to the mixer **560**.

[0078] The mixer **560** can be an optical hybrid, such as a 90 degree optical hybrid. The mixer **560** can receive the reference beam **512** and the return beam **548**, and mix the reference beam **512** and the return beam **548** to output a signal **564** responsive to the reference beam **512** and the return beam **548**. The signal **564** can include an in-phase (I) component **568** and a quadrature (Q) component **572**.

[0079] The LIDAR sensor system **500** can include a receiver **576** that receives the signal **564** from the mixer **560**. The receiver **576** can generate a signal **580** responsive to the signal **564**, which can be an electronic (e.g., radio frequency) signal. The receiver **576** can include one or more photodetectors that output the signal **580** responsive to the signal **564**.

[0080] The LIDAR sensor system **500** can include a processing system **590**, which can be implemented using features of the vehicle control system **120** described with reference to FIG. 1. The processing system **590** can process data received regarding the return beam **548**, such as the signal **580**, to determine parameters regarding the object such as range and velocity. The processing system **590** can include a scanner controller **592** that can provide scanning signals to control operation of the optics **532**, such as to control the motor **540** to cause the motor **540** to rotate the optics **532** to achieve a target scan pattern, such as a sawtooth scan pattern or step function scan pattern. The processing system **590** can include a Doppler compensator **594** that can determine the sign and size of a Doppler shift associated with processing the return beam **548** and a corrected range based thereon along with any other corrections. The processing system **590** can include a modulator controller **596** that can send one or more electrical signals to drive the modulator **514**.

[0081] The processing system **590** can include or be communicatively coupled with a vehicle controller **598** to control operation of a vehicle for which the LIDAR sensor system **500** is installed (e.g., to provide complete or semi-autonomous control of the vehicle). For example, the vehicle controller **598** can be implemented by at least one of the LIDAR sensor system **500** or control circuitry of the vehicle. The vehicle controller **598** can control operation of the vehicle responsive to at least one of a range to the object or a velocity of the object determined by the processing system **590**. For example, the vehicle controller **598** can transmit a control signal to at least one of a steering system or a braking system of the vehicle to control at least one of speed or direction of the vehicle.

4. LIDAR Sensor Systems Including Integrated Semiconductor Devices and Methods of Manufacturing

[0082] LIDAR sensor systems in accordance with the present disclosure can have chips that include III-V semiconductor materials, which can allow for high-performance silicon photonics

operations to be performed under vehicle operation conditions. For example, a CTE of a silicon substrate can be increased by including an array of conductive TSVs in a particular portion of the silicon substrate in contact with or corresponding to a III-V semiconductor die coupled to the silicon substrate. By adjusting configuration and composition of the array of TSVs embedded in the particular portion of the silicon substrate, the composite CTE of that portion of the silicon substrate can be tuned to more closely resemble that of the III-V semiconductor die, thereby reducing occurrence of mechanical defects at a bonding interface between the III-V die and the silicon substrate and improving the overall product yield and reliability.

[0083] FIG. 7 depicts an example of a circuit module **700** configured to perform a plurality of functions in the LIDAR sensor system **500**. The circuit module **700** can include at least one of silicon photonics circuitry, PLC, or III-V semiconductor circuitry. In some implementations, the circuit module **700** can include a III-V semiconductor circuitry on a III-V semiconductor substrate (e.g., a III-V substrate) coupled to at least one of silicon photonics circuitry or PLC.

[0084] For example, still referring to FIG. 7, the circuit module **700** can include at least one integrated circuit (IC) substrate (e.g., an IC die or an IC chip) **710** and at least one III-V substrate (e.g., a III-V chip or a III-V die) **750** coupled to a semiconductor substrate **702**.

[0085] In some implementations, the semiconductor substrate **702** is coupled to a substrate **708** using one or more conductive connectors **706**. The substrate **708** can include additional active devices (e.g., transistors, diodes, etc.) and/or passive devices (e.g., resistors, capacitors, etc.). Examples of the conductive connectors **706** include microbumps, solder bumps, a hybrid bonding structure, or combinations thereof. In this regard, the circuit module **700** can be considered a package, such as an integrated circuit package, having a plurality of devices (e.g., chips or dies) coupled together and packaged using one or more insulating components. As depicted in FIG. 7, the IC substrate **710** and the III-V substrate **750** can be coupled to a first side (e.g., front side) **702a** of the semiconductor substrate **702** and the substrate **708** can be coupled to a second side (e.g., back side) **702b** of the semiconductor substrate **702**. Optical devices, such as the laser **504** or other components of the LIDAR sensor system **500**, can be formed from, disposed over, or otherwise coupled to the III-V substrate **750** or a portion thereof. Various such optical devices can generate heat during operation, which transfers into the III-V substrate **750** and semiconductor substrate **702** and thus can cause expansion of the III-V substrate **750** and semiconductor substrate **702**.

[0086] The IC substrate **710** can include any active components configured to perform functions of at least one of silicon photonics circuitry or PLC. In some implementations, the IC substrate **710** can include a silicon substrate or a III-V semiconductor substrate. In some implementations, the III-V substrate **750** can include a III-V semiconductor substrate including, for example, GaAs, InAs, InP, other suitable III-V semiconductor materials, or combinations thereof.

[0087] The semiconductor substrate **702** can include any suitable semiconductor material, such as silicon. In some implementations, the semiconductor substrate **702** can consist of silicon, such that a bulk property (e.g., coefficient of thermal expansion, or CTE) of the semiconductor substrate **702** can be characterized or approximated based on that of silicon. In this regard, the semiconductor substrate **702** can be referred to as a silicon substrate **702**. In some implementations, the semiconductor substrate **702** can include trace amount (e.g., less than about 3% by weight) of impurities, so long as the impurities do not substantially affect the bulk property of the semiconductor substrate **702**.

[0088] In some implementations, the semiconductor substrate **702** has a composition different from that of the III-V substrate **750**. For example, the semiconductor substrate **702** is free, or substantially free, of any III-V semiconductor materials, such as GaAs, InAs, and InP. In an example implementation, the semiconductor substrate **702** includes silicon and the III-V substrate **750** includes GaAs. In another example implementation, the semiconductor substrate **702** includes silicon and the III-V substrate **750** includes InP. In yet another example implementation, the semiconductor substrate **702** includes silicon and the III-V substrate **750** includes InAs.

[0089] The IC substrate **710** can be coupled to the semiconductor substrate **702** using a plurality of conductive connectors **712**, which can be similar to the conductive connectors **706** described above. The III-V substrate **750** can be coupled to the semiconductor substrate **702** at a bonding interface **752**. In some implementations, referring to FIG. **8**, which depicts a portion of the circuit module **700** including the bonding interface **752**, a first side (e.g., a back side) **750b** of the III-V substrate **750** is coupled to the semiconductor substrate **702** by a solder bonding layer **770**. The solder bonding layer **770** can include any suitable material, such as a gold (Au), silver (Ag), gold-tin (AuSn) alloy, or combinations thereof. In some implementations, referring to FIG. **9**, the first side **750b** of the III-V substrate **750**, which is opposite to a second side (e.g., a front side) **750a**, is directly bonded to the semiconductor substrate **702** at the bonding interface **752**, i.e., the coupling between the III-V substrate **750** and the semiconductor substrate **702** does not include a solder bonding layer. In this regard, the III-V substrate **750** can be epitaxially grown onto a surface (i.e., the first side **702a**) of the semiconductor substrate **702**.

[0090] Referring back to FIG. **7**, the IC substrate **710** can be coupled to the substrate **708** by a multi-layer interconnect (MLI) structure **720** formed in the semiconductor substrate **702** between the first side **702a** and the second side **702b**. The MLI structure **720** can include horizontal interconnect structures that extend laterally along the X-axis and/or the Y-axis and vertical interconnect structures that extend along the Z-axis (e.g., in the frame of reference of FIG. **7** in which the X and Z axes lie in the plane of FIG. **7**). For example, the horizontal interconnect structures can include a plurality of metal layers, such as a metal layer (M1) **722**, a metal layer (M2) **724**, and a metal layer (M3) **726**. In addition, the MLI structure **720** can include a metal layer **744** formed or disposed on the front side of the semiconductor substrate **702** to laterally couple portions of the MLI structure **720** with the III-V substrate **750**.

[0091] The vertical interconnect structures can include a plurality of vias **730** and at least one TSV **732**. In some implementations, the vias **730** can be coupled to interconnect structures along the Z-axis, e.g., coupling the metal layers **722-726** to one another or coupling one of the metal layers **722-726** to the TSV **732**. In this regard, the vias **730** can partially extend through the semiconductor substrate **702** and therefore not directly contact any component formed or disposed on the back side of the semiconductor substrate **702**. The TSV **732**, on the other hand, can extend through the semiconductor substrate **702** to directly contact or couple with a redistribution structure **740** formed or disposed on the back side of the semiconductor substrate **702**. The redistribution structure **740** can include interconnect structures that extend along the X-axis and/or the Y-axis to laterally couple to other components.

[0092] In some implementations, components of the MLI structure **720** (e.g., the metal layers **722-726** and **744**, the vias **730**, and the TSV **732**) each include a conductive layer. The conductive layer can include any suitable conductive material, such as tungsten (W), copper (Cu), ruthenium (Ru), aluminum (Al), titanium nitride (TiN), tantalum nitride (TaN), other suitable conductive materials, or combinations thereof. Components of the MLI structure **720** can be formed by patterning the semiconductor substrate **702** to form an opening, depositing a conductive material in the opening, and optionally planarizing and/or etching back portions of the semiconductor substrate **702**. The patterning process can include a series of lithography and etching processes. The conductive material can be deposited by a suitable process, such as chemical vapor deposition (CVD), physical vapor deposition (PVD), atomic layer deposition (ALD), plating, and/or other processes. The depicted configuration of the MLI structure **720** is for illustration purposes only and can include any suitable number of metal layers, vias, and TSVs according to specific design requirements.

[0093] The circuit module **700** can include a wire bond **746** that couples a front side of the III-V substrate **750** to the MLI structure **720**. In some implementations, only end portions of the wire bond **746** contact the III-V substrate **750** and the MLI structure **720**, respectively (i.e., a length of the wire bond **746** between each end of the wire bond **746** does not contact either the III-V substrate **750** or the MLI structure **720**). In some implementations, the IC substrate **710** and the III-

V substrate **750** are laterally coupled to one another via the MLI structure **720** (e.g., the metal layers **726** and/or **744**) and/or the wire bond **746**

[0094] In some implementations, still referring to FIG. 7, the semiconductor substrate **702** includes a region (or portion) **704** that is disposed below (e.g., in the frame of reference of FIG. 7 in which the III-V substrate **750** is proximate an upper end of the circuit module **700** opposite a lower end of the circuit module **700** proximate the substrate **708**) the III-V substrate **750**. In some implementations, vertical boundaries of the region **704** are aligned, or substantially aligned, with vertical sidewalls of the III-V substrate **750** in the X-Z cross-sectional view. In this regard, the III-V substrate **750** can be defined by a width $W1$ along the X-axis, and the region **704** of the semiconductor substrate **702** can be defined by a width $W2$ along the X-axis. In some implementations, the width $W2$ is substantially the same as the width $W1$. This may be the case when the III-V substrate **750** is epitaxially grown on the semiconductor substrate **702**. In some implementations, the width $W2$ is slightly larger than the width $W1$ by about 1 μm to about 10 μm , for example. This may be the case when the III-V substrate **750** is coupled (or bonded) to the semiconductor substrate **702** by the solder bonding layer **770**. In some implementations, the region **704** is defined by a thickness T , which is a distance extending from the back side of the III-V substrate **750** to the back side of the semiconductor substrate **702**.

[0095] In some implementations, one or more TSVs **762** and **764** can be in the semiconductor substrate **702**, including being positioned in the region **704**. For example, as depicted in FIG. 7, the region **704** includes an array **760** of TSVs extending vertically along the Z-axis through the semiconductor substrate **702** to stop on the second side **702b** of the semiconductor substrate **702**. The array **760** can include more than one TSV, e.g., TSVs **762** and/or **764**, separated from one another along the X-axis and the Y-axis (not depicted in FIG. 7). In some implementations, the TSVs **762** and **764** are arranged in a configuration such that two neighboring TSVs (e.g., two neighboring TSVs **762**, two neighboring TSVs **764**, or neighboring TSVs **762** and **764**) are separated by a pitch P , which can be a distance between approximate centers of two neighboring TSVs along the X-axis and Y-axis, respectively. In some implementations, the TSVs **762** and **764** each extend a height H along the Z-axis, where the height H is less than the thickness T of the region **704**. In some implementations, a ratio of the height H to the thickness T can be between about 2:3 and about 99:100. For example, the ratio of the height H to the thickness T may be about 95:100, where the height H may be about 95 μm and the thickness T may be about 100 μm . In some implementations, the TSVs **762** and **764** each have a diameter D in an X-Y cross-sectional view along line AA' (see FIG. 10 described in detail below). In some implementations, the array **760** can include any number of the TSVs **762**, the TSVs **764**, or combinations of both. For purposes of illustration, the number of the TSVs **762** and/or **764** can be defined as N . As described further herein, the TSVs **762** and **764** can be sized and arranged to facilitate improved heat transfer and dissipation through and out of the circuit module **700**, such as to facilitate more uniform thermal expansion of the semiconductor substrate **702** and the III-V substrate **750** in response to heat in and around the circuit module **700**.

[0096] In some implementations, the TSVs **762** and **764** are configured with the same, or substantially the same, dimensions with respect to the height H , the diameter D , and the pitch P . Additionally, the TSVs **762** and/or **764** extend through the semiconductor substrate **702** to stop on the back side of the semiconductor substrate **702**. In some implementations, both the TSVs **762** and **764** can be similar to the TSV **732** described above with respect to composition and method of formation. For example, at least one of the TSVs **762** and **764** can each include copper (disposed over a seed layer in some implementations) and be formed by a series of patterning, deposition, and/or planarization processes described above.

[0097] In some implementations, the TSV **762** differs from the TSV **764** in terms of their coupling (or the lack thereof) to the III-V substrate **750**. For example, the TSV **762** is electrically isolated from the III-V substrate **750** and the TSV **764** is coupled to the III-V substrate **750**. With respect to

the TSV **762**, a portion of the semiconductor substrate **702** is disposed between the TSV **762** and the III-V substrate **750** to provide isolation. In contrast, the TSV **764** is coupled to the III-V substrate **750** (at its first side **750b**) by one or more vias **754**. The vias **754** can be similar to the vias **730** of the MLI structure **720** with respect to composition and method of formation. In some implementations, the vias **754** provide routing options to couple the III-V substrate **750** from its first side **750b**, which is in addition to the routing options provided by the wire bond **746** and/or the metal layer **744** at its second side **750a**. In other words, the III-V substrate **750** can be coupled to the substrate **708** without passing through additional interconnect structures, such as the wire bond **746** and/or components of the MLI structure **720**.

[0098] FIG. **10** depicts a schematic illustration of an example configuration of the array **760** in the X-Y cross-sectional view along line AA' of FIG. **7**. In the depicted implementation, a cross-section of each of the TSVs **762** and **764** is in a circular shape as shown, though the present disclosure is not limited to such configuration and other shapes may also be applicable. In some implementations, an area A_i of the region **704** in the X-Y cross-sectional view is defined by the width W_2 measured along the X-axis described above and a width W_3 measured along the Y-axis, where $A_{sub.1} = W_2 * W_3$. In some implementations, the area $A_{sub.1}$ of the region **704** corresponds to an area of the III-V substrate **750** in the X-Y cross-sectional view.

[0099] In some implementations, referring to FIG. **10**, the array **760** is arranged in a periodic pattern defined by the pitch P along the X-axis and the Y-axis, and the TSV **762/764** can each be defined by the diameter D . Accordingly, an area $A_{sub.2}$ of each TSV **762/764** can be defined as $\pi * (D/2)^{sup.2}$. As shown, the TSVs **762** and/or **764** within the array **760** can be interspersed throughout the region **704** to form a composite structure **780** in the silicon of the semiconductor substrate **702**, such that a fraction R of the area $A_{sub.1}$ occupied by the TSVs in the array **760** corresponds to the extent of such interspersion, where $R = N * A_{sub.2} / A_{sub.1}$. In some implementations, the fraction R , which is based on an area calculation, is correlated to a volume fraction of the semiconductor substrate **702** (i.e., the region **704**) occupied by the TSVs **762** and/or **764**.

[0100] Still referring to FIG. **10**, the fraction R can be approximated using available fabrication parameters, such as the pitch P and the diameter D , to calculate a ratio of the area $A_{sub.2}$ of each TSV **762/764** to an area $A_{sub.3}$ of a sub-region **790** of the region **704** that includes the TSV **762/764**. The sub-region **790** can be configured to have a substantially square shape and its area $A_{sub.3}$ can then be defined as $P^{sup.2}$. Accordingly, the fraction R can be approximated by $R \sim A_{sub.2} / A_{sub.3} = \pi * (D/2)^{sup.2} / P^{sup.2} = \pi * D^2 / (4P^{sup.2})$.

[0101] Coefficient of thermal expansion, or CTE, generally describes a material's physical expansion (e.g., increase in physical dimension) in response to elevated temperature and associated heat transfer to the material, and thus can be a thermal feature of that material. For purposes of discussion, "thermal feature," alternatively referred to as "thermal property" or "thermomechanical property," generally describes a mechanical response of a material, such as expansion, contraction, or other changes in shape (e.g., mechanical deformation), to changes in temperature (e.g., thermal stress). For example, a thermal feature/thermal property/thermomechanical property can include a feature or property of a material, such as CTE, detectable by thermomechanical analysis, such as analysis for detecting CTE.

[0102] In the present disclosure, the CTE is an approximately linear CTE of a given material at a particular temperature or range of temperatures. Bonding or otherwise coupling two materials having different CTEs can potentially cause mechanical defects, or even failures, at or near a bonding interface when the coupled materials are subjected to thermomechanical stress, such as heat generated by components of the LIDAR sensor system **500** or transferred from an environment around the LIDAR sensor system **500**. The III-V semiconductor material in the III-V substrate **750** can have a $CTE_{sub.III-V}$ that is greater than a $CTE_{sub.sub}$ of the semiconductor substrate **702**. The mismatch between the $CTE_{sub.III-V}$ and the $CTE_{sub.sub}$ can be addressed by incorporating

a plurality of TSVs in the array **760** into the semiconductor substrate **702** to form the composite structure **780**, where the TSVs **762** and/or **764** include a conductive material with a CTE.sub.TSV that is greater than both the CTE.sub.III-V and the CTE.sub.sub. For example, the circuit module **700** can be made with materials and/or volumes of materials such that the CTE.sub.TSV is between about two times and about ten times greater than that of the CTE.sub.III-V and/or CTE.sub.sub. [0103] An effective CTE.sub.eff (e.g., composite CTE; combined effective CTE) of the composite structure **780** can correspond to the CTE.sub.III-V and the CTE.sub.sub, adjusted by the fraction R. The effective CTE.sub.eff can be an approximately average CTE over a volume of the circuit module **700** or a portion thereof, such as an average CTE of the region **704** resulting from the inclusion of the TSVs **762** and/or **764** in the region **704**. For example, by modeling and experiment, the CTE.sub.eff of the composite structure **780** at room temperature can be approximated as an approximately linear function $\text{CTE.sub.eff} = R * \text{CTE.sub.TSV} + (1 - R) * \text{CTE.sub.sub}$. Given particular values of the CTE.sub.sub and the CTE.sub.TSV, the mismatch in CTE between the III-V substrate **750** and the semiconductor substrate **702** can be reduced by tuning the fraction R to achieve a CTE.sub.eff that is within a target threshold (e.g., a threshold greater than zero percent and less than or equal to about ten percent, or $0\% < \text{target threshold} \leq 10\%$) of the CTE.sub.III-V, which is the CTE of the material included in the III-V substrate **750**.

[0104] For example, referring to Table **1100** of FIG. **11**, at room temperature copper (Cu) has a CTE.sub.Cu of about 16 ppm, GaAs has a CTE.sub.GaAs of about 5.7 ppm, InP has a CTE.sub.InP of about 4.5 ppm, and silicon (Si) has a CTE.sub.Si of about 2.6 ppm, i.e., $\text{CTE.sub.Si} < \text{CTE.sub.III-V} < \text{CTE.sub.Cu}$. When the TSVs **762** and/or **764** include copper and the semiconductor substrate **702** includes silicon, the effective CTE.sub.eff can be approximated by $R * \text{CTE.sub.Cu} + (1 - R) * \text{CTE.sub.Si}$. In this regard, if the fraction R is 5%, then the effective CTE.sub.eff is about 3.27; if the fraction R is 10%, then the effective CTE.sub.eff is about 3.94; and if the fraction R is 15%, then the effective CTE.sub.eff is about 4.61. Thus, increasing the fraction R increases the effective CTE.sub.eff and reduces a mismatch (or difference), ΔCTE , between the effective CTE.sub.eff and the CTE.sub.III-V (e.g., the CTE.sub.GaAs, the CTE.sub.InP, or the CTE.sub.InAs). The fraction R can be selected to ensure that the ΔCTE is kept below a target threshold across the region **704** (e.g., as compared with a step function-like transition in CTE from the semiconductor substrate **702** and III-V substrate **750**, the fraction R can facilitate transitions in CTE between materials of the circuit module **700** that are lesser in absolute value and in gradient). In some examples, the fraction R may be at least about 5% to about 15% to facilitate the robust coupling between the semiconductor substrate **702** and the III-V substrate **750**. The fraction R can be selected such that the effective CTE.sub.eff is between about one time and two times that of the CTE.sub.Si, and between about one fifth and two thirds of that of the CTE.sub.InP or the CTE.sub.GaAs. Other values of the fraction R may also be applicable depending on composition and/or dimension of one or more of the semiconductor substrate **702**, the III-V substrate **750**, and the TSVs **762/764**. FIG. **12** illustrates a schematic plot **1200** of the approximately linear relationship between the effective CTE.sub.eff and the fraction R described herein.

[0105] In some examples, the effective CTE.sub.eff of the composite structure **780** can vary across a volume of the region **704**, depending on size metrics of the TSVs **762** and/or **764**. For example, the height H may differ between different TSVs **762** and/or **764** in the array **760**, such that the volume fraction, which can be estimated by the fraction R, occupied by the TSVs in the region **704** varies along the Z-axis, giving rise to a gradient of effective CTE.sub.eff across the region **704**.

[0106] The vias **754** can also contribute to the calculation of the effective CTE.sub.eff in a manner similar to the TSVs **762** and/or **764**. For example, the composition (i.e., a specific value of CTE of the vias **754**) and distribution (i.e., the fraction R) of the vias **754** can also be tuned to adjust the effective CTE.sub.eff of the composite structure **780** for improved heat transfer and dissipation through and out of the circuit module **700** in response to heat generated in and around the circuit

module **700**.

[0107] Additionally, in examples in which the solder bonding layer **770** is used to couple the III-V substrate **750** to the semiconductor substrate **702** (as depicted in FIG. **9**), a material having a CTE that is greater than the CTE.sub.sub (e.g., the CTE.sub.Si) can be selected for the solder bonding layer **770** to accommodate any thermal expansion at or near the bonding interface **752**. In this regard, the Δ CTE in a portion of the region **704** near the bonding interface **752** can be reduced by a different amount than in a portion of the region **704** away from the bonding interface **752** (e.g., the portion that includes the array **760**), depending on the material selected for and an area of the solder bonding layer **770**. In other words, the effective CTE.sub.eff can be tuned independently in different locations of the composite structure **780** to achieve the target threshold in the reduction of the Δ CTE. In some examples, the solder bonding layer **770** can include gold and/or silver, which can each have a CTE different from that of copper but greater than that of silicon.

[0108] FIG. **13** illustrates a flow diagram of a method **1300** for integrating the III-V substrate **750** with the semiconductor substrate **702**, which can be further coupled to other devices. The method **1300** is merely an example and is not intended to limit the present disclosure. Accordingly, it is understood that additional operations may be provided before, during, and after the method **1300**.

[0109] At **1302**, the III-V substrate **750** can be coupled to the region **704** of the semiconductor substrate **702**. The III-V substrate **750** can include a III-V semiconductor material, such as GaAs, InP, InAs, or combinations thereof, having the CTE.sub.III-V (at room temperature, for example), and the semiconductor substrate **702** includes silicon, having the CTE.sub.Si that is less than the CTE.sub.III-V according to the Table **1100**, for example. The semiconductor substrate **702** can include the MLI structure **720** embedded therein and other active and/or passive devices coupled thereto. In some implementations, the semiconductor substrate **702** can be coupled to the substrate **708** via the conductive connectors as shown in FIG. **7**.

[0110] At **1304**, the fraction R of the region **704** in which the array **760** (i.e., the TSVs **762** and/or **764**) are provided can be determined. In some implementations, the TSVs **762** and/or **764** include copper having the CTE.sub.Cu, a value of which can be found in the Table **1100**. As described above, the CTE.sub.eff of the resulting composite structure **780** in the region **704** varies linearly with the fraction R and depends on at least the CTE.sub.Si and the CTE.sub.Cu, where $CTE_{sub.eff} = R * CTE_{sub.Cu} + (1 - R) * CTE_{sub.Si}$. Given the values of the CTE.sub.Si and the CTE.sub.Cu as shown the Table **1100**, $CTE_{sub.eff} = 2.6 + 13.4 * R$. To reduce the Δ CTE between the CTE.sub.eff and the CTE.sub.III-V (e.g., the CTE.sub.GaAs, the CTE.sub.InP, or the CTE.sub.InAs), e.g., to tune the CTE.sub.eff to be approximately the same as the CTE.sub.III-V, R can be calculated as $(CTE_{sub.III-V} - 2.6) / 13.4$. For example, if the III-V substrate **750** includes InP, which has the CTE.sub.InP of about 4.5, then the fraction R is approximately 0.142 or 14.2% to arrive at a CTE.sub.eff of about 4.5. It is noted that the value of 0.142 for the fraction R is for illustration purposes only and not intended to limit the present disclosure thereto.

[0111] In some implementations, thermomechanical stress due to Δ CTE between the CTE.sub.Si and the CTE.sub.III-V can still be relieved even if the CTE.sub.eff is slightly less than the CTE.sub.III-V. For example, if the III-V substrate **750** includes InP, a CTE.sub.eff of about 3.27 may be obtained if the fraction R is tuned to about 0.05 or 5%. While 3.27 is still less than 4.5, it is still greater than the CTE.sub.Si and therefore capable of reducing the thermomechanical stress at the bonding interface **752**.

[0112] At **1306**, an arrangement of the TSVs **762** and/or **764** in the array **760** based on the calculated fraction R can be determined. In practice, as one of the two dimensions, the diameter D and the pitch P, can be determined based on manufacturing conditions and/or predefined design requirements, the other one of the dimensions can be determined based on the fraction R and the relationship $R \sim \pi * (D/2)^2 / P^2 = \pi * D^2 / (4P^2)$ described in detail above. The diameters D and the pitch P can be then be used to determine the size and distribution of the array **760** of TSVs.

[0113] At **1308**, the vias **754** can be formed in the region **704** to couple the TSVs **764** to the III-V

substrate **750**. In some implementations, the vias **754** are similar to the vias **730** with respect to the composition and method of formation as described in detail above. For implementations in which the array **760** does not include any TSV **764**, the formation of the vias **754** can be omitted.

[0114] At **1310**, the TSVs **762** and/or **764** can be formed according to the calculated fraction R. In some implementations, the TSVs **762** and/or **764** are similar to the TSV **732** with respect to the composition and method of formation as described in detail above. For example, the second side **702b** of the semiconductor substrate **702** can be patterned in accordance to the diameter D and the pitch P of the TSVs **762** and/or **764**, which are at least partially determined based on the fraction R. In some implementations, the TSVs **762** and/or **764** are formed together with the TSV **732** (and other TSVs in the semiconductor substrate **702**) to simplify the manufacturing process.

[0115] In some implementations, the TSVs **762** are formed to extend from the second side **702a** of the semiconductor substrate **702**, at least partially through the semiconductor substrate **702**, such that a portion of the semiconductor substrate **702** remains between the TSVs **762** and the III-V substrate **750**. In some implementations, the TSVs **764** can be formed to extend through the semiconductor substrate **702** to contact the vias **754**, which couple the TSVs **764** to the III-V substrate **750**. In some implementations, the TSVs **762** and/or **764** can be formed before, during, or after the formation of various devices (e.g., transistors, capacitors, resistors, etc.) on or coupled to the semiconductor substrate **702**. In some implementations, the TSVs **762** and/or **764** can be formed before, during, or after the coupling of the III-V substrate **750** to the semiconductor substrate **702**.

[0116] At **1312**, the III-V substrate **750** is coupled to the semiconductor substrate **702**. In some implementations, the III-V substrate **750** is coupled to the semiconductor substrate **702** by forming the solder bonding layer **770** at the bonding interface **752** as illustrated in FIG. **8**. In some implementations, the solder bonding layer **770** can be thermally activated at a temperature of at least 300° C. to bond the III-V substrate **750** to the semiconductor substrate **702**. In some implementations, the III-V substrate **750** can be epitaxially grown onto the semiconductor substrate **702**. In this regard, the method **1300** can pattern the front side of the semiconductor substrate **702** to form a recess, perform an epitaxial growth process to grow a III-V semiconductor layer including GaAs, InP, and/or InAs, for example, from the semiconductor substrate **702**. The epitaxial growth process can be implemented by any suitable method, such as molecular beam epitaxy (MBE), CVD (e.g., metal organic CVD, or MOCVD), other suitable methods, or combinations thereof. Devices can then be formed on or coupled to the III-V semiconductor layer.

[0117] In some implementations, additional fabrication processes are performed. For example, the method **1300** can form additional devices of the circuit module **700** on or to couple to the semiconductor substrate **702**, where the additional devices can be configured to perform various functions of the LIDAR system **500**. Additionally or alternatively, the method **1300** can form components (e.g., bonding layers, gap fill layers, etc.) to complete formation of the circuit module **700** as a semiconductor IC package.

[0118] FIGS. **14-17** depict examples of a circuit module **1400** configured to perform a plurality of functions in the LIDAR sensor system **500**. The circuit module **1400** can incorporate features of various circuit modules described herein, including but not limited to the circuit module **700**. In this regard, components of the circuit module **1400** that are the same those of the circuit module **700** are described using the same reference numerals.

[0119] For example, the circuit module **1400** can include a III-V semiconductor circuitry on a III-V semiconductor substrate (e.g., a III-V substrate) coupled to at least one of silicon photonics circuitry or PLC. Referring to FIGS. **14** and **17**, the circuit module **1400** can include at least one integrated circuit (IC) substrate (e.g., an IC die or an IC chip) **710** and at least one III-V substrate (e.g., a III-V chip or a III-V die) **750** coupled to the semiconductor substrate **702**, which can be further coupled to the substrate **708**.

[0120] As described above with respect to the circuit module **700**, the semiconductor substrate **702**

has a composition different from that of the III-V substrate **750**. For example, the semiconductor substrate **702** can include silicon and can be free, or substantially free, of any III-V semiconductor materials, such as GaAs, InAs, and InP. Such a difference in composition can lead to a mismatch in CTE between the semiconductor substrate **702**, having the CTE.sub.sub, and the III-V substrate **750**, having the CTE.sub.III-V generally greater than the CTE.sub.sub, potentially causing mechanical defects at or near a bonding interface therebetween under thermal stress.

[0121] In some implementations, as shown in at least FIG. 7, the mismatched CTEs in the circuit module **700** can be reduced by embedding the TSVs **762/764**, which have the higher CTE.sub.TSV than the CTE.sub.sub, in a region **704** of the semiconductor substrate **702** to form the composite structure **780** contacting with or corresponding to the III-V substrate **750**. In this regard, the effective, or composite, CTE.sub.eff of the composite structure **780** is increased to a value similar to (e.g., within a target threshold of) the CTE.sub.III-V, thereby reducing the mismatch in CTE at the bonding interface **752** in an effort to mitigate potential mechanical defects in the circuit module **700** and improve the overall produce yield and reliability.

[0122] In some implementations, as shown in FIGS. 14-17 collectively, the circuit module **1400** includes a bonding interface **1410** having a composite structure configured to reduce the mismatch in CTE between the semiconductor substrate **702** and the III-V substrate **750**, such that an effective CTE.sub.eff_1430 of the composite structure is increased to a value similar to the CTE.sub.III-V. In some implementations, the effective CTE.sub.eff_1430 is within a target threshold that is greater than zero percent and less than or equal to about ten percent of the CTE.sub.III-V.

[0123] The bonding interface **1410** extends across a portion of the III-V substrate **750** (at its first side **750b**) along the X-axis, such that a lower portion of the III-V substrate **750** is embedded in an upper portion of the semiconductor substrate **702**. The region **704** of the semiconductor substrate **702** is positioned below the III-V substrate **750**, where the III-V substrate **750** proximate to an upper end of the circuit module **1400** is opposite to a lower end of the circuit module **1400** proximate the substrate **708**. In this regard, the bonding interface **1410** couples the region **704** of the semiconductor substrate **702** to the III-V substrate **750** in a manner similar to the bonding interface **752** depicted in FIGS. 7-9. However, the bonding interface **752** and the bonding interface **1410** may be configured with different materials.

[0124] Furthermore, in some implementations, such as depicted in FIG. 14, the circuit module **1400** differs from the circuit module **700** in that the circuit module **1400** may include fewer or no TSVs **762** or **764** embedded in the semiconductor substrate **702** (as compared with the circuit module **700** depicted in FIG. 7). In this regard, the structure and composition of semiconductor substrate **702** within the region **704** can be the same, or substantially the same, as that outside the region **704**. As will be described in detail below, the increase in the effective CTE.sub.eff_1430 of the region **704** can be attributed to the structure and composition of the bonding interface **1410**.

[0125] In some implementations, referring to FIG. 15, which depicts a detailed cross-sectional view of the bonding interface **1410** as shown in FIG. 14, the bonding interface **1410** includes a metal bonding layer **1420** disposed between the semiconductor substrate **702** and the III-V substrate **750**, where the metal bonding layer **1420** and the region **704** of the semiconductor substrate **702** form a composite structure **1430**. The metal bonding layer **1420** can include any suitable material with a CTE.sub.metal that is significantly larger than the CTE.sub.sub (e.g., the CTE.sub.metal may be at least about three times, such as about six times, the CTE.sub.sub). In some implementations, the CTE.sub.metal is also significantly larger than the CTE.sub.III-V (e.g., the CTE.sub.metal may be at least about two times, such as three times, the CTE.sub.III-V). In some implementations, the metal bonding layer **1420** and the TSVs **762** and **764** have similar or the same compositions. For example, the metal bonding layer **1420** can include Cu such that the CTE.sub.metal is equivalent to the CTE.sub.Cu. For implementations in which the semiconductor substrate **702** includes Si, the CTE.sub.sub is equivalent to CTE.sub.Si. For implementations in which the III-V substrate **750** includes GaAs, the CTE.sub.III-V is equivalent to CTE.sub.GaAs.

Furthermore, still referring to FIG. 16, the metal layer 1420 has a thickness T1 and the semiconductor substrate 702 has a thickness T2, where the thicknesses T1 and T2 are measured along the Z-axis.

[0126] Analogous to the calculation of the effective CTE.sub.eff of the composite structure 780 described above, the effective CTE.sub.eff_1430 of the composite structure 1430 at room temperature can be determined as an approximately linear function

CTE.sub.eff_1430=R.sub.metal1*CTE.sub.metal+(1-R.sub.metal)*CTE.sub.sub, where a fraction R.sub.metal is correlated to a volume fraction of the metal bonding layer 1420 in the composite structure 1430. In some implementations, assuming a planar area (area in the X-Y plane from a top view, for example) occupied by the metal bonding layer 1420 is substantially the same as that of the semiconductor substrate 702, the fraction R.sub.metal can be approximated as a ratio of the thickness T1 to a sum of the thicknesses T1 and T2, or $R_{\text{sub.metal}} \sim T1/(T1+T2)$. Furthermore, as the CTE.sub.metal is significantly larger than both the CTE.sub.eff_1430 and the CTE.sub.sub, the thickness T1 is generally less than the thickness T2 according to the approximately linear function provided herein.

[0127] In this regard, reducing the mismatch in CTE between the semiconductor substrate 702 and the III-V substrate 750 can then be achieved by tuning the fraction R.sub.metal (e.g., tuning the thicknesses T1 and/or T2) that would result in an effective CTE.sub.eff_1430 within the target threshold of the CTE.sub.III-V. In some implementations, the semiconductor substrate 702 includes Si, the metal bonding layer 1420 includes Cu, and the III-V substrate 750 includes GaAs such that $CTE_{\text{sub.eff}_1430} \sim CTE_{\text{sub.GaAs}} = R_{\text{sub.metal}} * CTE_{\text{sub.Cu}} + (1 - R_{\text{sub.metal}}) * CTE_{\text{sub.Si}}$, where the fraction R.sub.metal is approximated to be 23.1% based on the example values provided in FIG. 11. In some implementations, the fraction R.sub.metal generally decreases with a decreasing CTE.sub.III-V. For example, if the III-V substrate 750 includes InP, which has a CTE.sub.InP of about 4.5 that is less than the CTE.sub.GaAs, the fraction R.sub.metal is approximated to be 14.2%.

[0128] Accordingly, by tuning the thicknesses T1 and/or T2 to obtain a suitable fraction R.sub.metal, the effective CTE.sub.eff_1430 of the composite structure 1430 can be configured to be similar to the CTE.sub.III-V within the target threshold described above (e.g., reducing the mismatch between the effective CTE.sub.eff_1430 and the CTE.sub.III-V), thereby reducing the mechanical defects, or even failures, that may occur at or near the bonding interface 1410. In some implementations, reducing the mismatch in CTE helps mitigate thermal stress, such as heat generated by components of the LIDAR sensor system 500 or transferred from an environment around the LIDAR sensor system 500, exerted to the circuit module 1400.

[0129] It is noted that, although the present disclosure provides a method of approximating the fraction R.sub.metal based on the thicknesses T1 and T2, other methods of determining the fraction R.sub.metal may also be employed. For example, the fraction R.sub.metal may be determined by directly measuring a volume of the metal bonding layer 1420 and a volume of the semiconductor substrate 702.

[0130] In some implementations, the metal bonding layer 1420 is patterned to form one or more optical windows (not depicted) for exposing grating couplers of a silicon photonic circuitry formed over the semiconductor substrate 702. The metal bonding layer 1420 may be etched or punched out to form a suitable pattern that functions as an optical window. In this regard, any portions of the metal bonding layer 1420 removed to form such a pattern can be figured into (e.g., by subtraction, for example) the fraction R.sub.metal (e.g., determined by direct measurement) to obtain the effective CTE.sub.eff_1430 accordingly.

[0131] In some implementations, referring to FIG. 16, which depicts a detailed cross-sectional view of the bonding interface 1410 as shown in FIG. 14, the bonding interface 1410 includes the metal bonding layer 1420 disposed between the semiconductor substrate 702 and the III-V substrate 750. The bonding interface 1410 further includes an optional solder bonding layer 1426

disposed between the metal bonding layer **1420** and the semiconductor substrate **702**, such that the semiconductor substrate **702**, the metal bonding layer **1420** and the solder bonding layer **1426** together constitute a composite structure **1440**. In some implementations, the solder bonding layer **1426** facilitates the bonding or coupling between the metal bonding layer **1420** and the semiconductor substrate **702**, similar to the function of the solder bonding layer **770** described in detail above.

[0132] The solder bonding layer **1426** can be similar to the solder bonding layer **770** in composition. For example, the solder bonding layer **1426** can include Au, Ag, AuSn alloy, or combinations thereof. In some implementations, the solder bonding layer **1426** has a CTE.sub.solder different from the CTE.sub.metal and has a thickness **T3** less than the thickness **T1**. Accordingly, to reflect the inclusion of the solder bonding layer **1426** in the determination of an effective CTE.sub.eff_1440 of the composite structure **1440**, a modified term $R_{\text{sub.metal}} + \text{AuSn} * \text{CTE}\{\text{circumflex over ()}\}$ replaces the term $R_{\text{sub.metal}} + \text{AuSn} * \text{CTE.sub.metal}$ in the approximately linear function provided herein. In some implementations, the fraction $R_{\text{sub.metal}} + \text{AuSn}$ is approximated as $R_{\text{sub.metal}} + \text{AuSn} \sim (T1 + T3) / (T1 + T2 + T3)$. Similar to the manner that the effective CTE.sub.eff_1430 is determined as a composite value based on the CTE.sub.metal, the CTE.sub.sub, the thickness **T1**, and the thickness **T2**, the $\text{CTE}\{\text{circumflex over ()}\}$ can also be determined as a composite value based on the CTE.sub.metal, the CTE.sub.solder, the thickness **T1**, and the thickness **T3**.

[0133] In some implementations, the thickness **T3** is significantly less than the thickness **T1** such that the effect of the CTE.sub.solder on the $\text{CTE}\{\text{circumflex over ()}\}$ is substantially negligible. In this regard, the effective CTE.sub.eff_1440 of the composite structure **1440** can be equated to the effective CTE.sub.eff_1430 of the composite structure **1430** described in detail above.

[0134] In some implementations, referring to FIG. 17, the circuit module **1400** additionally includes the array **760** of TSVs embedded in the semiconductor substrate **702**. In this regard, the region **704** of the semiconductor substrate **702** positioned below the bonding interface **1410** includes the TSVs **762** and/or **764** extending vertically along the Z-axis through the semiconductor substrate **702**, as described in detail with respect to the circuit module **700**. In some implementations, the TSVs **762** and **764** can each be optionally coupled to the first side **750b** of the III-V substrate **750** by one or more of the vias **754**.

[0135] In some implementations, the effective CTE.sub.eff_1430 of the composite structure **1430** (or **1440**), determined based on characteristics of the region **704** and the metal bonding layer **1420** (and the solder bonding layer **1426**, if applicable) described above, can benefit from the effective CTE.sub.eff of the composite structure **780**, which is based on the CTE.sub.TSV and the fraction **R** of the TSVs **762** and/or **764** in the region **704**. For instance, the effective CTE.sub.eff_1430 of the composite structure **1430** can be determined based on $\text{CTE.sub.eff}_1430 = R_{\text{sub.metal}} * \text{CTE.sub.metal} + (1 - R_{\text{sub.metal}}) * \text{CTE.sub.sub}$, where the CTE.sub.sub can reflect the CTE of the region **704** without any TSVs, as depicted in FIG. 14. Alternatively, referring to FIG. 17, the CTE.sub.sub can be a composite CTE that takes into account the TSVs **762** and/or **764** embedded in the region **704**.

[0136] Accordingly, in some implementations, increasing the effective CTE.sub.eff_1430 to a value within the target threshold of the CTE.sub.III-V can be accomplished by incorporating the metal bonding layer **1420** (as shown in FIG. 14). In some implementations, increasing the effective CTE.sub.eff_1430 can be accomplished by incorporating a combination of the metal bonding layer **1420** and the TSVs **762** and/or **764** (as shown in FIG. 17). For both scenarios, characteristics (e.g., the material of the metal bonding layer **1420**, the material of the TSVs **762** and/or **764**, the thicknesses **T1** and **T2**, the size of the TSVs **762** and/or **764**, etc.) of the components of the circuit module **1400** can be tuned independently or collectively to arrive at a suitable effective CTE.sub.eff_1430 for reducing the mismatch in CTE between the semiconductor substrate **702** and

the III-V substrate **750**.

[0137] Having now described some illustrative implementations, it is apparent that the foregoing is illustrative and not limiting, having been presented by way of example. In particular, although many of the examples presented herein involve specific combinations of method acts or system elements, those acts and those elements can be combined in other ways to accomplish the same objectives. Acts, elements and features discussed in connection with one implementation are not intended to be excluded from a similar role in other implementations or implementations.

[0138] The phraseology and terminology used herein is for the purpose of description and should not be regarded as limiting. The use of “including” “comprising” “having” “containing” “involving” “characterized by” “characterized in that” and variations thereof herein, is meant to encompass the items listed thereafter, equivalents thereof, and additional items, as well as alternate implementations consisting of the items listed thereafter exclusively. In one implementation, the systems and methods described herein consist of one, each combination of more than one, or all of the described elements, acts, or components.

[0139] Any references to implementations or elements or acts of the systems and methods herein referred to in the singular can also embrace implementations including a plurality of these elements, and any references in plural to any implementation or element or act herein can also embrace implementations including only a single element. References in the singular or plural form are not intended to limit the presently disclosed systems or methods, their components, acts, or elements to single or plural configurations. References to any act or element being based on any information, act or element can include implementations where the act or element is based at least in part on any information, act, or element.

[0140] Any implementation disclosed herein can be combined with any other implementation or embodiment, and references to “an implementation,” “some implementations,” “one implementation” or the like are not necessarily mutually exclusive and are intended to indicate that a particular feature, structure, or characteristic described in connection with the implementation can be included in at least one implementation or embodiment. Such terms as used herein are not necessarily all referring to the same implementation. Any implementation can be combined with any other implementation, inclusively or exclusively, in any manner consistent with the aspects and implementations disclosed herein.

[0141] Where technical features in the drawings, detailed description or any claim are followed by reference signs, the reference signs have been included to increase the intelligibility of the drawings, detailed description, and claims. Accordingly, neither the reference signs nor their absence have any limiting effect on the scope of any claim elements.

[0142] Systems and methods described herein may be embodied in other specific forms without departing from the characteristics thereof. Further relative parallel, perpendicular, vertical or other positioning or orientation descriptions include variations within $\pm 10\%$ or ± 10 degrees of pure vertical, parallel or perpendicular positioning. References to “approximately,” “about” “substantially” or other terms of degree include variations of $\pm 10\%$ from the given measurement, unit, or range unless explicitly indicated otherwise. Coupled elements can be electrically, mechanically, or physically coupled with one another directly or with intervening elements. Scope of the systems and methods described herein is thus indicated by the appended claims, rather than the foregoing description, and changes that come within the meaning and range of equivalency of the claims are embraced therein.

[0143] The term “coupled” and variations thereof includes the joining of two members directly or indirectly to one another. Such joining may be stationary (e.g., permanent or fixed) or moveable (e.g., removable or releasable). Such joining may be achieved with the two members coupled directly with or to each other, with the two members coupled with each other using a separate intervening member and any additional intermediate members coupled with one another, or with the two members coupled with each other using an intervening member that is integrally formed as

a single unitary body with one of the two members. If “coupled” or variations thereof are modified by an additional term (e.g., directly coupled), the generic definition of “coupled” provided above is modified by the plain language meaning of the additional term (e.g., “directly coupled” means the joining of two members without any separate intervening member), resulting in a narrower definition than the generic definition of “coupled” provided above. Such coupling may be mechanical, electrical, or fluidic.

[0144] References to “or” can be construed as inclusive so that any terms described using “or” can indicate any of a single, more than one, and all of the described terms. A reference to “at least one of ‘A’ and ‘B’” can include only ‘A’, only ‘B’, as well as both ‘A’ and ‘B’. Such references used in conjunction with “comprising” or other open terminology can include additional items.

[0145] Modifications of described elements and acts such as variations in sizes, dimensions, structures, shapes and proportions of the various elements, values of parameters, mounting arrangements, use of materials, colors, orientations can occur without materially departing from the teachings and advantages of the subject matter disclosed herein. For example, elements shown as integrally formed can be constructed of multiple parts or elements, the position of elements can be reversed or otherwise varied, and the nature or number of discrete elements or positions can be altered or varied. Other substitutions, modifications, changes and omissions can also be made in the design, operating conditions and arrangement of the disclosed elements and operations without departing from the scope of the present disclosure.

[0146] References herein to the positions of elements (e.g., “top,” “bottom,” “above,” “below”) are merely used to describe the orientation of various elements in the FIGURES. It should be noted that the orientation of various elements may differ according to other exemplary embodiments, and that such variations are intended to be encompassed by the present disclosure

Claims

1.-20. (canceled)

21. A light detection and ranging (LIDAR) sensor system for a vehicle, comprising: a circuit module, comprising: a silicon substrate having a first coefficient of thermal expansion (CTE) and a first surface opposite a second surface; a III-V semiconductor substrate having a third surface opposite a fourth surface, the third surface facing the first surface and coupled to the silicon substrate, the III-V semiconductor substrate having a second CTE; an optical device coupled to the III-V semiconductor substrate, the optical device configured to output a transmit beam; and a bonding interface coupling the first surface of the silicon substrate to the third surface of the III-V semiconductor substrate, wherein at least a portion of the bonding interface has a third CTE.

22. The LIDAR sensor system of claim 21, wherein a portion of the III-V semiconductor substrate including the third surface of the III-V semiconductor substrate is embedded within a portion of the silicon substrate.

23. The LIDAR sensor system of claim 21, wherein the bonding interface comprises a metal bonding layer disposed between the silicon substrate and the III-V semiconductor substrate.

24. The LIDAR system of claim 23, wherein the metal bonding layer and a region of the silicon substrate form a composite structure having the third CTE.

25. The LIDAR system of claim 23, wherein the metal bonding layer has a fourth CTE that is larger than the first CTE.

26. The LIDAR system of claim 25, wherein the fourth CTE has value of about three times to about six times the first CTE.

27. The LIDAR system of claim 25, wherein the fourth CTE has a value of about two times to about three times the second CTE.

28. The LIDAR sensor system of claim 23, wherein the metal bonding layer comprises copper.

29. The LIDAR sensor system of claim 23, wherein the metal bonding layer is patterned to expose

one or more grating couplers formed on the silicon substrate.

30. The LIDAR sensor system of claim 23, the bonding interface further comprising a solder bonding layer disposed between the metal bonding layer and the silicon substrate.

31. The LIDAR sensor system of claim 30, wherein a thickness of the solder bonding layer is less than a thickness of the metal bonding layer.

32. The LIDAR sensor system of claim 21, wherein the III-V semiconductor substrate includes GaAs, InP, or a combination thereof.

33. The LIDAR sensor system of claim 21, wherein the second CTE is greater than the first CTE.

34. The LIDAR sensor system of claim 21, wherein the third CTE has a value of about zero to ten percent of the second CTE.

35. The LIDAR sensor system of claim 21, further comprising: a scanner configured to direct the transmit beam to an environment of the vehicle.

36. The LIDAR sensor system of claim 21, the circuit module further comprising a plurality of vias disposed in a particular portion of the silicon substrate that is under the III-V semiconductor substrate, the plurality of vias extending in the silicon substrate between the first surface and the second surface and towards the third surface.

37. The LIDAR sensor system of claim 36, wherein an amount of the plurality of vias in the particular portion of the silicon substrate is such that the particular portion has a fourth CTE that is different than the first CTE and the second CTE.

38. The LIDAR sensor system of claim 36, wherein at least one via of the plurality of vias includes Cu.

39. An autonomous vehicle control system, comprising: a LIDAR sensor system, comprising: a circuit module, comprising: a silicon substrate having a first coefficient of thermal expansion (CTE) and a first surface opposite a second surface; a III-V semiconductor substrate having a third surface opposite a fourth surface, the third surface facing the first surface and coupled to the silicon substrate, the III-V semiconductor substrate having a second CTE; an optical device coupled to the III-V semiconductor substrate, the optical device configured to output a transmit beam; and a bonding interface coupling the first surface of the silicon substrate to the third surface of the III-V semiconductor substrate, wherein at least a portion of the bonding interface has a third CTE.

40. An autonomous vehicle, comprising: a LIDAR sensor system, comprising: a circuit module, comprising: a silicon substrate having a first coefficient of thermal expansion (CTE) and a first surface opposite a second surface; a III-V semiconductor substrate having a third surface opposite a fourth surface, the third surface facing the first surface and coupled to the silicon substrate, the III-V semiconductor substrate having a second CTE; an optical device coupled to the III-V semiconductor substrate, the optical device configured to output a transmit beam; and a bonding interface coupling the first surface of the silicon substrate to the third surface of the III-V semiconductor substrate, wherein at least a portion of the bonding interface has a third CTE.
