

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12401261
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Kim; Seungbeom Kevin et al.

Power converters with current sensing

Abstract

A power converter can include first, second, third, and fourth power switches, and a driver for operating the drive switches to modify an input voltage. An AC coupling capacitor can be coupled between the first and fourth power switches. Bootstrap capacitors can be used for driving the first and second power switches, which can be high-side switches. In some embodiments, a current sensing circuit can be used to measure current through the third and/or fourth power switches and for determining the current through the power converter. In some embodiments, the power converter can monitor the voltage across the AC coupling capacitor and can determine the current through the power converter based on the monitored voltages. In some embodiments, the AC coupling capacitor can be pre-charged before the power converter begins normal operation.

Inventors: Kim; Seungbeom Kevin (Whittier, CA), Cornish, III; Jack Walter (Irvine, CA), Jayawant; Saurabh Anil (Laguna Niguel, CA), Parto; Parviz (Laguna Niguel, CA)

Applicant: FARADAY SEMI, INC. (Irvine, CA)

Family ID: 1000008778097

Assignee: FARADAY SEMI, INC. (Irvine, CA)

Appl. No.: 18/506941

Filed: November 10, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240266957 A1	Aug. 08, 2024

Related U.S. Application Data

division parent-doc US 17371885 20210709 US 11855534 child-doc US 18506941

Publication Classification

Int. Cl.: H02M3/158 (20060101); H02M1/00 (20060101); H02M1/08 (20060101)

U.S. Cl.:

CPC H02M1/0009 (20210501); H02M1/0095 (20210501); H02M3/158 (20130101); H02M1/0006 (20210501); H02M1/08 (20130101)

Field of Classification Search

CPC: H02M (1/0009); H02M (1/0095); H02M (3/1582); H02M (3/1584); H02M (3/1586); H02M (3/1588)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
3327202	12/1966	Mills	N/A	N/A
3329887	12/1966	Schaeve	N/A	N/A
3474289	12/1968	Stone	N/A	N/A
3678937	12/1971	Cole et al.	N/A	N/A
3795247	12/1973	Thaler	N/A	N/A
3888260	12/1974	Fischell	N/A	N/A
3978838	12/1975	Oister	N/A	N/A
4163968	12/1978	Davis	N/A	N/A
4184197	12/1979	Cuk et al.	N/A	N/A
4412212	12/1982	Kolegraff et al.	N/A	N/A
4471283	12/1983	Presley	N/A	N/A
5287261	12/1993	Ehsani	N/A	N/A
5663634	12/1996	Fawal	N/A	N/A
5663635	12/1996	Vinciarelli et al.	N/A	N/A
5747976	12/1997	Wong	N/A	N/A
5773966	12/1997	Steigerwald	N/A	N/A
5886508	12/1998	Jutras	N/A	N/A
5949264	12/1998	Lo	N/A	N/A
6034514	12/1999	Sakai	N/A	N/A
6051961	12/1999	Jang et al.	N/A	N/A
6278264	12/2000	Burstein et al.	N/A	N/A
6304065	12/2000	Wittenbreder	N/A	N/A
6304460	12/2000	Cuk	N/A	N/A
6342822	12/2001	So	N/A	N/A
6346743	12/2001	Figueroa	N/A	N/A
6366070	12/2001	Cooke et al.	N/A	N/A
6377032	12/2001	Andruzzi et al.	N/A	N/A
6381159	12/2001	Oknaian et al.	N/A	N/A
6388896	12/2001	Cuk	N/A	N/A

6445233	12/2001	Pinai et al.	N/A	N/A
6462962	12/2001	Cuk	N/A	N/A
6583610	12/2002	Groom	N/A	N/A
6642698	12/2002	Pohlman	N/A	N/A
6713995	12/2003	Chen	N/A	N/A
6714426	12/2003	Guo et al.	N/A	N/A
6737843	12/2003	Kanakubo et al.	N/A	N/A
6784644	12/2003	Xu et al.	N/A	N/A
6803750	12/2003	Zhang	N/A	N/A
6815936	12/2003	Wiktor et al.	N/A	N/A
6897641	12/2004	Herbert	N/A	N/A
6949916	12/2004	Chapuis	N/A	N/A
6967429	12/2004	Bachmaier et al.	N/A	N/A
RE38940	12/2005	Isham et al.	N/A	N/A
7000125	12/2005	Chapuis et al.	N/A	N/A
7002328	12/2005	Kernahan et al.	N/A	N/A
7019504	12/2005	Pullen et al.	N/A	N/A
7026795	12/2005	So	N/A	N/A
7045992	12/2005	Silva et al.	N/A	N/A
7057380	12/2005	Kuo et al.	N/A	N/A
7058373	12/2005	Grigore	N/A	N/A
7102340	12/2005	Ferguson	N/A	N/A
7135841	12/2005	Tomiyoshi et al.	N/A	N/A
7148442	12/2005	Murai et al.	N/A	N/A
7157889	12/2006	Kernahan	N/A	N/A
7173403	12/2006	Chen et al.	N/A	N/A
7180757	12/2006	Chen et al.	N/A	N/A
7196503	12/2006	Wood et al.	N/A	N/A
7205821	12/2006	Rutter	N/A	N/A
7230405	12/2006	Jang et al.	N/A	N/A
7288924	12/2006	Trandafir et al.	N/A	N/A
7298122	12/2006	Bernacchia et al.	N/A	N/A
7342385	12/2007	Capodivacca et al.	N/A	N/A
7372241	12/2007	Tomiyoshi	N/A	N/A
7391190	12/2007	Rajagopaian	N/A	N/A
7436233	12/2007	Yee et al.	N/A	N/A
7439721	12/2007	Weng et al.	N/A	N/A
7446513	12/2007	Dikken et al.	N/A	N/A
7474086	12/2008	Chen et al.	N/A	N/A
7482791	12/2008	Stoichita et al.	N/A	N/A
7482795	12/2008	Parto et al.	N/A	N/A
7508181	12/2008	Chen et al.	N/A	N/A
7554310	12/2008	Chapuis et al.	N/A	N/A
7567067	12/2008	Lee et al.	N/A	N/A
7595624	12/2008	Tateishi et al.	N/A	N/A
7638987	12/2008	Sugiyama	N/A	N/A
7649346	12/2009	Sohma	N/A	N/A
7710084	12/2009	Guo	N/A	N/A
7714547	12/2009	Fogg et al.	N/A	N/A
7764057	12/2009	Groom	N/A	N/A

7777587	12/2009	Stevenson et al.	N/A	N/A
7778064	12/2009	Parkinson et al.	N/A	N/A
7782639	12/2009	Vinciarelli	N/A	N/A
7834606	12/2009	Liu et al.	N/A	N/A
7859324	12/2009	Yamashita et al.	N/A	N/A
7868599	12/2010	Rahman et al.	N/A	N/A
7902803	12/2010	Peng et al.	N/A	N/A
7906942	12/2010	Sugahara et al.	N/A	N/A
7919952	12/2010	Fahrenbruch	N/A	N/A
7936160	12/2010	Sheehan	N/A	N/A
7944153	12/2010	Greenfeld et al.	N/A	N/A
7986135	12/2010	Kenly et al.	N/A	N/A
8004070	12/2010	Chen	N/A	N/A
8022746	12/2010	Signoretti et al.	N/A	N/A
8040121	12/2010	Ishida et al.	N/A	N/A
8054639	12/2010	Hsu	N/A	N/A
8093878	12/2011	Katsuya et al.	N/A	N/A
8120345	12/2011	Akiyama et al.	N/A	N/A
8148815	12/2011	Girdhar et al.	N/A	N/A
8154268	12/2011	Philbrick et al.	N/A	N/A
8159263	12/2011	Tuan	N/A	N/A
8164320	12/2011	Latham et al.	N/A	N/A
RE43414	12/2011	Walters et al.	N/A	N/A
8198880	12/2011	Ouyang	N/A	N/A
8248046	12/2011	Hasegawa	N/A	N/A
8253398	12/2011	Nakamura et al.	N/A	N/A
8278898	12/2011	Davoudi et al.	N/A	N/A
8283905	12/2011	Chang et al.	N/A	N/A
8330435	12/2011	Qiu et al.	N/A	N/A
8344709	12/2012	Zhang et al.	N/A	N/A
8400129	12/2012	Ouyang	N/A	N/A
8410765	12/2012	Hung et al.	N/A	N/A
8427853	12/2012	Uno	N/A	N/A
8441235	12/2012	Shi et al.	N/A	N/A
8446135	12/2012	Chen et al.	N/A	N/A
8450989	12/2012	Wiktor et al.	N/A	N/A
8476882	12/2012	Luo et al.	N/A	N/A
8487599	12/2012	Lee et al.	N/A	N/A
8508206	12/2012	Wan et al.	N/A	N/A
8524532	12/2012	Joshi	N/A	N/A
8570020	12/2012	Tang et al.	N/A	N/A
8575911	12/2012	Cheng et al.	N/A	N/A
8582333	12/2012	Oraw et al.	N/A	N/A
8618779	12/2012	Garrett et al.	N/A	N/A
8629666	12/2013	Carroll et al.	N/A	N/A
8659282	12/2013	Chen	N/A	N/A
8676525	12/2013	Holmberg et al.	N/A	N/A
8679896	12/2013	Joshi et al.	N/A	N/A
8698475	12/2013	Dong et al.	N/A	N/A
8717002	12/2013	Xi	N/A	N/A

8749216	12/2013	Li et al.	N/A	N/A
8773090	12/2013	Ouyang et al.	N/A	N/A
8786267	12/2013	Lu et al.	N/A	N/A
8803495	12/2013	Nguyen et al.	N/A	N/A
8810294	12/2013	Lynch et al.	N/A	N/A
8829866	12/2013	Lethellier	N/A	N/A
8860387	12/2013	Kobayashi	N/A	N/A
8860396	12/2013	Giuliano	N/A	N/A
8890501	12/2013	Evans et al.	N/A	N/A
8901911	12/2013	Wen et al.	N/A	N/A
8912773	12/2013	Parto et al.	N/A	N/A
8941367	12/2014	Li et al.	N/A	N/A
8957653	12/2014	Yang et al.	N/A	N/A
8975885	12/2014	Philbrick et al.	N/A	N/A
8994346	12/2014	Rahardjo et al.	N/A	N/A
9030177	12/2014	Nakashima	N/A	N/A
9035624	12/2014	Rahimi et al.	N/A	N/A
9058043	12/2014	Lin et al.	N/A	N/A
9065337	12/2014	Tanabe et al.	N/A	N/A
9070642	12/2014	Standing et al.	N/A	N/A
9071125	12/2014	Michishita	N/A	N/A
9077260	12/2014	Zhao et al.	N/A	N/A
9088202	12/2014	Mizutani et al.	N/A	N/A
9110489	12/2014	Svorc	N/A	N/A
9190383	12/2014	Cho et al.	N/A	N/A
9214415	12/2014	Denison et al.	N/A	N/A
9231471	12/2015	Cuk	N/A	N/A
9252661	12/2015	Grbo et al.	N/A	N/A
9337735	12/2015	Odaohhara	N/A	N/A
9389625	12/2015	Hu et al.	N/A	N/A
9406674	12/2015	Briere	N/A	N/A
9437570	12/2015	Cho et al.	N/A	N/A
9502980	12/2015	Rahimi et al.	N/A	N/A
9563263	12/2016	Maiyuran et al.	N/A	N/A
9575096	12/2016	Wang et al.	N/A	N/A
9577522	12/2016	Jayawant et al.	N/A	N/A
9584006	12/2016	McDonald et al.	N/A	N/A
9588532	12/2016	Rahimi et al.	N/A	N/A
9653996	12/2016	Parto et al.	N/A	N/A
9711279	12/2016	Dodorov et al.	N/A	N/A
9729059	12/2016	Parto	N/A	N/A
9767947	12/2016	Ikriannikov	N/A	N/A
10193442	12/2018	Parto	N/A	N/A
10234930	12/2018	Lee et al.	N/A	N/A
10254314	12/2018	Li	N/A	H02M 3/1582
10504848	12/2018	Parto	N/A	N/A
10924011	12/2020	Parto	N/A	N/A
11063516	12/2020	Kim et al.	N/A	N/A
11069624	12/2020	Standing	N/A	N/A

11557962	12/2022	Parto	N/A	N/A
11621230	12/2022	Standing	N/A	N/A
11652062	12/2022	Parto	N/A	N/A
11855534	12/2022	Kim	N/A	N/A
2003/0042880	12/2002	Kataoka	N/A	N/A
2004/0125618	12/2003	De Rooij et al.	N/A	N/A
2005/0040796	12/2004	Sutardja	N/A	N/A
2005/0245001	12/2004	Hyvonen et al.	N/A	N/A
2005/0280404	12/2004	LeFevre et al.	N/A	N/A
2006/0220629	12/2005	Saito et al.	N/A	N/A
2007/0001653	12/2006	Xu	N/A	N/A
2008/0067666	12/2007	Hsu	N/A	N/A
2008/0211746	12/2007	Caligiore	N/A	N/A
2008/0273314	12/2007	Cho et al.	N/A	N/A
2009/0108908	12/2008	Yamadaya	N/A	N/A
2010/0001699	12/2009	Dragojevic	N/A	N/A
2010/0134985	12/2009	Hsu	N/A	N/A
2011/0058285	12/2010	Wibben	N/A	N/A
2011/0227546	12/2010	Nishijima et al.	N/A	N/A
2012/0049826	12/2011	Hsu et al.	N/A	N/A
2012/0274296	12/2011	Higuchi	N/A	N/A
2012/0302012	12/2011	Zeng	N/A	N/A
2013/0074907	12/2012	Saunders	N/A	N/A
2014/0084884	12/2013	Lee	N/A	N/A
2014/0159689	12/2013	Chen	N/A	N/A
2015/0062989	12/2014	Su	N/A	N/A
2015/0180355	12/2014	Freeman et al.	N/A	N/A
2015/0311792	12/2014	Amaro et al.	N/A	N/A
2015/0311797	12/2014	Okamatsu et al.	N/A	N/A
2016/0118325	12/2015	Wang et al.	N/A	N/A
2016/0218559	12/2015	Mehas et al.	N/A	N/A
2016/0261190	12/2015	Shenoy	N/A	H02M 3/1584
2016/0294277	12/2015	Romeo	N/A	N/A
2017/0231094	12/2016	Blackshear et al.	N/A	N/A
2018/0183330	12/2017	Assaad et al.	N/A	N/A
2018/0204665	12/2017	Peng et al.	N/A	N/A
2018/0294719	12/2017	Khatib et al.	N/A	N/A
2019/0081567	12/2018	Jacobson	N/A	N/A
2019/0379272	12/2018	Carpenter	N/A	N/A
2020/0075541	12/2019	Sturcken	N/A	N/A
2020/0075553	12/2019	Delacruz et al.	N/A	N/A
2020/0402934	12/2019	Kim	N/A	N/A
2021/0050779	12/2020	Deng	N/A	N/A
2021/0067041	12/2020	Cho	N/A	H02M 3/156
2023/0268827	12/2022	Parto	N/A	N/A
2023/0412079	12/2022	Parto	N/A	N/A
2024/0055360	12/2023	Standing	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
104143547	12/2013	CN	N/A
104158392	12/2013	CN	N/A
2005-143284	12/2004	JP	N/A
2006-223088	12/2005	JP	N/A
2008-235773	12/2007	JP	N/A
4427667	12/2009	JP	N/A
2010-129877	12/2009	JP	N/A
2010-207068	12/2009	JP	N/A
2011-138812	12/2010	JP	N/A
2013-062943	12/2012	JP	N/A
5433880	12/2013	JP	N/A
5474488	12/2013	JP	N/A
2015-047017	12/2014	JP	N/A
2015-133905	12/2014	JP	N/A
2016-503963	12/2015	JP	N/A
WO 2008/013871	12/2007	WO	N/A
WO 2010/139358	12/2009	WO	N/A

OTHER PUBLICATIONS

“Bootstrap Circuit in the Buck Converter,” ROHM Semiconductor, Switching Regulator IC Series, dated Nov. 2018, in 5 pages. cited by applicant

Bryson: “Using auto-zero comparator techniques to improve PWM performance (Part 1 of 2), Jun. 23, 2008.” www.eetimes.com. cited by applicant

Bryson: “Using auto-zero comparator techniques to improve PWM performance (Part 2 of 2), Jun. 23, 2008.” www.eetimes.com. cited by applicant

Burton, Intel Corp. APEC 2015, Package and Platform View of Intel's Fully Integrated Voltage Regulators (FIVR) (23 pgs). cited by applicant

Enhancement-Mode Gallium Nitride Technology, Efficient Power Conversion, product brief, 2016. cited by applicant

Guo, Oct. 19-23, 2003, High Performance Forward Converter in Non-Isolated Configurations, IEICE/IEEE Intelec'03, pp. 98-103. cited by applicant

Intel, Dual Intel, Xeon, Processor Voltage Regulator Down (VRD) Design Guidelines, Jul. 2003, 22 pages. cited by applicant

Intel, Voltage Regulator-Down (VRD) 11.0, Processor Power Delivery Design Guidelines for Desktop LGA775 Socket, Nov. 2006 (88 pgs). cited by applicant

Nakanishi, “A two-stage converter with a coupled-inductor,” Power Elec & Drive Sys, PEDS (2007) 7th Int'l conf of IEEE, pp. 653-657. cited by applicant

Shortt et al., Apr. 1987, A 600-W Four-Stage Phase-Shifted-Parallel DC-to-DC Converter, IEEE Transactions on Power Electronics, PE-2(2):101-108. cited by applicant

TPS54A20 8-V to 14-V Input, 10-A, up to 10-MHz Swift™ Step Down Converter, Texas Instruments, data sheet, Apr. 2016. cited by applicant

TPS8268x 1600-mA High Efficiency MicroSIP™ Step-Down Converter Module, Texas Instruments, data sheet, Oct. 2014. cited by applicant

Wei, May 7, 2002, Investigation of High-Input-Voltage Non-Isolated Voltage Regulator Modules Topology Candidates, Master of Science in Electrical Engineering Thesis, Virginia Polytechnic Institute and State University, 112 pp. cited by applicant

Zhang et al., 2004, Study of the Multilevel Converters in DC-DC Applications, 35th Annual IEEE

Power Electronics Specialists Conference, Aachen, Germany, pp. 1702-1706. cited by applicant
Jun. 8, 2018 Int'l Search Report & Written Opinion from PCT/US2018/017109 (16 pgs). cited by applicant
Aug. 13, 2019, International Preliminary Report on Patentability from PCT/US2018/017109 (13 pgs). cited by applicant
Sep. 15, 2020, International Search Report and Written Opinion from PCT/US2020/028585 (12 pgs.). cited by applicant
International Search Report and Written Opinion dated Nov. 2, 2021 in application No. PCT/US2021/041453. cited by applicant
Toshiba Electronic Devices & Storage Corporation, Nov. 12, 2019, Resonant Circuits and Soft Switching: Application Note, 32 pp. cited by applicant

Primary Examiner: Torres-Rivera; Alex

Attorney, Agent or Firm: Knobbe, Martens, Olson & Bear, LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a divisional of U.S. patent application Ser. No. 17/371,885, filed Jul. 9, 2021, and titled POWER CONVERTERS, which is a divisional of U.S. patent application Ser. No. 16/942,602, filed Jul. 29, 2020, and titled POWER CONVERTERS. The entirety contents of each of the above-identified application(s) are hereby incorporated by reference herein and made part of this specification for all that they disclose.

BACKGROUND OF THE INVENTION

Field of the Invention

(1) This disclosure relates to electronic systems and power converters, such as direct current to direct current (DC-DC) buck converters.

Description of the Related Art

(2) Although various power converters are known, there exists a need for improved power converters.

SUMMARY OF THE INVENTION

(3) Certain example embodiments are summarized below for illustrative purposes. The embodiments are not limited to the specific implementations recited herein. Embodiments may include several novel features, no single one of which is solely responsible for its desirable attributes or which is essential to the embodiments.

(4) Various embodiments disclosed herein can relate to a power converter, which can include an input configured to receive an input voltage, an output configured to output an output voltage that is different than the input voltage, a first inductor, and a second inductor. A first power switch can be a high-side switch, and a second power switch can be a high-side switch. The power converter can include a third power switch and a fourth power switch. The second power switch and the third power switch can be configured to control current through the second inductor. The first power switch and the fourth power switch can be configured to control current through the first inductor. A driver can be configured to operate the first, second, third, and fourth power switches to change the input voltage to provide the output voltage. A first bootstrap capacitor can be coupled to the first power switch. The first bootstrap capacitor can charge during a state when the first power switch is off. The first bootstrap capacitor can discharge during a state when the first power switch is on to provide an elevated voltage to maintain the first power switch on. A second bootstrap

capacitor can be coupled to the second power switch. The second bootstrap capacitor can charge during a state when the second power switch is off. The second bootstrap capacitor can discharge during a state when the second power switch is on to provide an elevated voltage to maintain the second power switch on.

(5) The power converter can include one or more switches that have a first configuration that couples the first bootstrap capacitor to ground so that the first bootstrap capacitor charges, and a second configuration that couples the first bootstrap capacitor to the first power switch so that the first bootstrap capacitor discharges to maintain the first power switch on. The power converter can include a first switch electrically coupled between the first bootstrap capacitor and ground. The power converter can include a second switch electrically coupled between a voltage source and the first bootstrap capacitor. The power converter can include a third switch electrically coupled between the first bootstrap capacitor and the source of the first power switch. The first switch and the second switch can be on while the third switch is off in a first configuration so that the first bootstrap capacitor is coupled between the voltage source and ground so that the first bootstrap capacitor charges. The first switch and the second switch can be off while the third switch is on in a second configuration so that the first bootstrap capacitor discharges to provide an elevated voltage to keep the first power switch on.

(6) The power converter can include a first switch electrically coupled between the first bootstrap capacitor and ground, and a second switch electrically coupled to the first bootstrap capacitor. The first switch can be on while the second switch is off in a first configuration so that the first bootstrap capacitor is coupled between a voltage source and ground so that the first bootstrap capacitor charges. The first switch can be off while the second switch is on in a second configuration so that the first bootstrap capacitor provides an elevated voltage to keep the first power switch on. The power converter can include a diode between the voltage source and the first bootstrap capacitor. The diode can be configured to permit current to flow from the voltage source to the first bootstrap capacitor and to impede current from the first bootstrap capacitor to the voltage source.

(7) The first bootstrap capacitor and the second bootstrap capacitor can be coupled so that the second bootstrap capacitor charges the first bootstrap capacitor in the state when the second power switch is on. The second bootstrap capacitor can have more capacitance than the first bootstrap capacitor. The first bootstrap capacitor can be electrically coupled to a source of the first power switch all the time.

(8) The first bootstrap capacitor and the second bootstrap capacitor can be integrated into the same integrated circuit as the first power switch, the second power switch, the third power switch, the fourth power switch, and the driver. The first bootstrap capacitor can be integrated into the same integrated circuit as the first power switch and the driver. The driver can include an input for receiving a first drive signal that corresponds to the state when the first power switch is off, and a second drive signal that corresponds to the state when the first power switch is on, an output coupled to the first power switch, a high voltage supply, and a low voltage supply. The first bootstrap capacitor can be coupled between the high voltage supply and the low voltage supply. A pull-up switch can be coupled between the high voltage supply and the output. A pull-down switch can be coupled between the low voltage supply and the output. A pull-up drive signal generator can be configured to produce a pull-up signal pulse to turn on the pull-up switch in response to a transition from the first drive signal to the second drive signal, to thereby turn on the first power switch and charge up an internal capacitance of the first power switch to the elevated voltage provided by the first bootstrap capacitor. The pull-up drive signal generator can be configured to end the pull-up signal pulse and turn off the pull-up switch while the first drive signal is still being applied. The internal capacitance of the first power switch can keep the first power switch on until a transition from the second drive signal to the first drive signal. A pull-down drive signal generator can be configured to produce a pull-down signal pulse to turn on the pull-down switch in response

to the transition from the second drive signal to the first drive signal, to thereby discharge the internal capacitance of the first power switch and turn off the first power switch. The integrated circuit can include a driver controller for producing the first driver signal and the second drive signal. The first drive signal can be a low signal and the second drive signal can be a high signal. The pull-up drive signal generator can be configured to produce the pull-up signal pulse in response to a rising edge transition from the low signal to the high signal. The pull-down drive signal generator can be configured to produce the pull-down signal pulse in response to the falling edge transition from the high signal to the low signal. The power converter can include a first amplifier between the pull-up drive signal generator and the pull-up switch. The first amplifier can be configured to amplify the pull-up signal pulse to turn on the pull-up switch. The power converter can include a second amplifier between the pull-down drive signal generator and the pull-down switch. The second amplifier can be configured to amplify the pull-down signal pulse to turn on the pull-down switch.

(9) The driver can include a second input for receiving a third drive signal that corresponds to the state when the second power switch is off, and a fourth drive signal that corresponds to the state when the second power switch is on. The driver can include a second output that is coupled to the second power switch, a second high voltage supply, and a second low voltage supply. The second bootstrap capacitor can be coupled between the second high voltage supply and the second low voltage supply. A second pull-up switch can be coupled between the second high voltage supply and the second output. A second pull-down switch can be coupled between the second low voltage supply and the second output. A second pull-up drive signal generator can be configured to produce a second pull-up signal pulse to turn on the second pull-up switch in response to a transition from the third drive signal to the fourth drive signal, to thereby turn on the second power switch and charge up an internal capacitance of the second power switch to the elevated voltage provided by the second bootstrap capacitor. The second pull-up drive signal generator can be configured to end the second pull-up signal pulse and turn off the second pull-up switch while the third drive signal is still being applied. The internal capacitance of the second power switch can keep the second power switch on until a transition from the third drive signal to the fourth drive signal. A second pull-down drive signal generator can be configured to produce a second pull-down signal pulse to turn on the second pull-down switch in response to the transition from the fourth drive signal to the third drive signal, to thereby discharge the internal capacitance of the second power switch and turn off the second power switch. The second pull-down signal pulse can be longer than the first pull-down signal pulse.

(10) The first power switch and the second power switch can be N-channel FETs. The power converter can be a buck converter configured so that the output voltage at the output is lower than the input voltage at the input. The driver can be configured to provide various states of operation. In a first state of operation the first power switch is on, the second power switch is off, the third power switch is on, and the fourth power switch is off. In a second state of operation the first power switch is off, the second power switch is off, the third power switch is on, and the fourth power switch is on. In a third state of operation the first power switch is off, the second power switch is on, the third power switch is off, and the fourth power switch is on. In a fourth state of operation, the first power switch is off, the second power switch is off, the third power switch is on, and the fourth power switch is on. The power converter can include an AC coupling capacitor that is coupled between the first power switch and the first inductor.

(11) The power converter can include a printed circuit board (PCB) comprising a lower printed circuit board (PCB) part and an upper printed circuit board (PCB) part. Embedded circuitry can be between the lower PCB part and the upper PCB part. The embedded circuitry can include the first power switch, the second power switch, the third power switch, the fourth power switch, and/or the driver. The first inductor and the second inductor can be positioned over the upper PCB part. Vias can electrically couple the first inductor and the second inductor to the embedded circuitry. A

footprint of the first inductor can at least partially overlap a footprint of the embedded circuitry. A footprint of the second inductor can at least partially overlap a footprint of the embedded circuitry. The embedded circuitry can include the first bootstrap capacitor and the second bootstrap capacitor.

(12) The power converter can include a current sensing circuit for measuring a current through the fourth power switch. The power converter can include current sensing processing circuitry, which can be configured to determine a current through the power converter based at least in part on the measured current through the fourth power switch. The power converter can include a communication interface for outputting information regarding the determined current. The current sensing circuit can include a sensing switch in parallel with the fourth power switch. The sensing switch can be configured to be on when the second power switch and the fourth power switch are on. The sensing switch can be configured to be off when the either of the second power switch and the fourth power switch is off. The current sensing circuit can include a current mirror. The current sensing circuit can be configured to produce a voltage signal that is indicative of the current through the fourth power switch. The current sensing processing circuitry can be configured to apply a gain to increase the voltage signal. The current sensing processing circuitry can be configured to invert the voltage signal.

(13) The power converter can include a first current sensing circuit for measuring a current through the third power switch and a second current sensing circuit for measuring a current through the fourth power switch. Current sensing processing circuitry can be configured to determine a power converter current based at least in part on the measured current through the third power switch and the measured current through the fourth power switch. A communication interface can output information regarding the determined power converter current. The first current sensing circuit can include a first sensing switch in parallel with the third power switch. The first sensing switch can be configured to be on when the third power switch and the fourth power switch are on. The first sensing switch can be configured to be off when the either of the third power switch and the fourth power switch is off. The second current sensing circuit can include a second sensing switch in parallel with the fourth power switch. The second sensing switch can be configured to be on when the third power switch and the fourth power switch are on. The second sensing switch can be configured to be off when the either of the third power switch and the fourth power switch is off. The first current sensing circuit can include a first current mirror. The second current sensing circuit can include a second current mirror. The first current sensing circuit can be configured to produce a first voltage signal that is indicative of the current through the third power switch. The second current sensing circuit can be configured to produce a second voltage signal that is indicative of the current through the fourth power switch. The current sensing processing circuitry can be configured to apply a gain to increase the first voltage signal and the second voltage signal. The current sensing processing circuitry can be configured to invert the first voltage signal and to invert the second voltage signal.

(14) The power converter can include a capacitor that is coupled between the first power switch and the first inductor. Current sensing processing circuitry can be coupled to the capacitor and configured to monitor a voltage across the capacitor, and to determine a power converter current based at least in part on the monitored voltage across the capacitor. A communication interface can output information regarding the determined power converter current. The current sensing processing circuitry can identify a highest voltage across the capacitor and a lowest voltage across the capacitor during a switching cycle. The current sensing processing circuitry can determine the power converter current based at least in part on a difference between the highest voltage and the lowest voltage. The power converter can be configured to measure a first voltage across the capacitor at a first time, measure a second voltage across the capacitor at a second time, determine (e.g., using the current sensing processing circuitry) the power converter current based at least in part on a voltage difference between the first voltage and the second voltage and a time difference between the first time and the second time.

(15) The power converter can include a capacitor that is coupled between the first power switch and the fourth power switch. A pre-charge circuit can be configured to charge the capacitor before the driver operates the first, second, third, and fourth power switches to change the input voltage to provide the output voltage. The pre-charge circuit can include a switch electrically coupled between the input and the capacitor and voltage monitoring circuitry for monitoring a voltage of the capacitor. The switch can be on when the monitored voltage is below a threshold, and the switch can turn off when the monitored voltage is above the threshold.

(16) Various embodiments disclosed herein can relate to a power converter, which can include an input configured to receive an input voltage, an output configured to output an output voltage that is different than the input voltage, a first inductor, and a second inductor. The power converter can include a first power switch, a second power switch, a third power switch, and a fourth power switch. The first, second, third, and fourth power switches can be configured to control current through the first inductor and the second inductor. A driver can be configured to operate the first, second, third, and fourth power switches to change the input voltage to provide the output voltage.

(17) The power converter can include a current sensing circuit for measuring a current through the fourth power switch, and current sensing processing circuitry configured to determine a power converter current based at least in part on the measured current through the fourth power switch. The power converter can include a communication interface for outputting information regarding the determined power converter current. The current sensing circuit can include a sensing switch in parallel with the fourth power switch. The sensing switch can be configured to be on when the second power switch and the fourth power switch are on. The sensing switch can be configured to be off when the either of the second power switch and the fourth power switch is off. The current sensing circuit can include a current mirror. The current sensing circuit can be configured to produce a voltage signal that is indicative of the current through the fourth power switch. The current sensing processing circuitry can be configured to apply a gain to increase the voltage signal. The current sensing processing circuitry can be configured to invert the voltage signal.

(18) The power converter can include another current sensing circuit for measuring a current through the third power switch. The current sensing processing circuitry can be configured to determine the power converter current based at least in part on the measured current through the third power switch and the measured current through the fourth power switch. The current sensing circuit for the third power switch can include a first sensing switch in parallel with the third power switch. The first sensing switch can be configured to be on when the third power switch and the fourth power switch are on. The first sensing switch can be configured to be off when the either of the third power switch and the fourth power switch is off. The current sensing circuit for the fourth power switch can include a second sensing switch in parallel with the fourth power switch. The second sensing switch can be configured to be on when the third power switch and the fourth power switch are on. The second sensing switch can be configured to be off when the either of the third power switch and the fourth power switch is off. The current sensing circuit for the third power switch can include a first current mirror. The current sensing circuit for the fourth power switch can include a second current mirror. The current sensing circuit for the third power switch can be configured to produce a first voltage signal that is indicative of the current through the third power switch. The current sensing circuit for the fourth power switch can be configured to produce a second voltage signal that is indicative of the current through the fourth power switch. The current sensing processing circuitry can be configured to apply a gain to increase the first voltage signal and the second voltages signal. The current sensing processing circuitry can be configured to invert the first voltage signal and to invert the second voltage signal.

(19) Various embodiments disclosed herein can relate to a power converter that includes an input configured to receive an input voltage, an output configured to output an output voltage that is different than the input voltage, a first inductor, a second inductor, a first power switch, a second power switch, a third power switch, and a fourth power switch. The first, second, third, and fourth

power switches can be configured to control current through the first inductor and the second inductor. A driver can be configured to operate the first, second, third, and fourth power switches to change the input voltage to provide the output voltage. A capacitor that can be coupled between the first power switch and the first inductor. Current sensing processing circuitry can be coupled to the capacitor and configured to monitor a voltage across the capacitor, and to determine a power converter current based at least in part on the monitored voltage across the capacitor. A communication interface can output information regarding the determined power converter current.

(20) The current sensing processing circuitry can identify a high voltage across the capacitor and a low voltage across the capacitor during a switching cycle. The current sensing processing circuitry can be configured to determine the power converter current based at least in part on a difference between the high voltage and the low voltage. The power converter can be configured to measure a first voltage across the capacitor at a first time, measure a second voltage across the capacitor at a second time, and determine, using the current sensing processing circuitry, the power converter current based at least in part on a voltage difference between the first voltage and the second voltage and a time difference between the first time and the second time.

(21) Various embodiments disclosed herein can relate to a power converter, which can include an input configured to receive an input voltage, an output configured to output an output voltage that is different than the input voltage, a first inductor, a second inductor, a first power switch, a second power switch, a third power switch, and a fourth power switch. The first, second, third, and fourth power switches can be configured to control current through the first inductor and the second inductor. A driver can be configured to operate the first, second, third, and fourth power switches to change the input voltage to provide the output voltage. A capacitor can be coupled between the first power switch and the fourth power switch. A pre-charge circuit can be configured to charge the capacitor before the driver operates the first, second, third, and fourth power switches to change the input voltage to provide the output voltage.

(22) The pre-charge circuit can include a switch electrically coupled between the input and the capacitor, and voltage monitoring circuitry for monitoring a voltage of the capacitor, wherein the switch is on when the monitored voltage is below a threshold, and wherein the switch turns off when the monitored voltage is above the threshold.

(23) Various embodiments disclosed herein can relate to a power converter, which can include an input configured to receive an input voltage, an output configured to output an output voltage that is different than the input voltage, a first inductor, a second inductor, a first power switch, a second power switch, a third power switch, and a fourth power switch. The first, second, third, and fourth power switches can be configured to control current through the first inductor and the second inductor. A driver configured to operate the first, second, third, and fourth power switches to change the input voltage to provide the output voltage. A capacitor can be coupled between the first power switch and the first inductor. A bootstrap capacitor can be coupled to the first power switch. The bootstrap capacitor can charge during a state when the first power switch is off. The bootstrap capacitor discharges during a state when the first power switch is on to provide an elevated voltage to maintain the first power switch on.

(24) The power converter can include another bootstrap capacitor coupled to the second power switch. Therein the other bootstrap capacitor can charge during a state when the second power switch is off. The other bootstrap capacitor can discharge during a state when the second power switch is on (e.g., to provide an elevated voltage to maintain the second power switch on). The bootstrap capacitor for the second power switch can be configured to charge the bootstrap capacitor for the first power switch. The first power switch and the bootstrap capacitor can be integrated into the same integrated circuit. The power converter can include a switch electrically coupled between the bootstrap capacitor and ground. The switch can have an on state for charging the bootstrap capacitor, and an off state that enables the bootstrap capacitor to discharge and produce the elevated voltage to keep the first power switch on.

(25) Various embodiments disclosed herein can relate to a power converter, which can include an input configured to receive an input voltage, an output configured to output an output voltage that is different than the input voltage, a first inductor, and a second inductor. The power converter can have an integrated circuit that includes a first power switch, a second power switch, a third power switch, and a fourth power switch. The first, second, third, and fourth power switches can be configured to control current through the first inductor and the second inductor. A driver can be configured to operate the first, second, third, and fourth power switches to change the input voltage to provide the output voltage. The power converter can include a bootstrap capacitor.

(26) The bootstrap capacitor can be coupled to the first power switch. The bootstrap capacitor can charge during a state when the first power switch is off. The bootstrap capacitor can discharge during a state when the first power switch is on to provide an elevated voltage. The bootstrap capacitor can be configured to provide the elevated voltage to charge up an internal capacitance of the first power switch, so that internal capacitance of the first power switch keeps the first power switch on after the bootstrap capacitor is disconnected from the first power switch. The driver can include an input for receiving a first drive signal that corresponds to the state when the first power switch is off, and a second drive signal that corresponds to the state when the first power switch is on. The driver can include an output coupled to the first power switch, a high voltage supply, and a low voltage supply. The first bootstrap capacitor can be coupled between the high voltage supply and the low voltage supply. A pull-up switch can be coupled between the high voltage supply and the output. A pull-down switch can be coupled between the low voltage supply and the output. A pull-up drive signal generator can be configured to produce a pull-up signal pulse to turn on the pull-up switch in response to a transition from the first drive signal to the second drive signal (e.g., to thereby turn on the first power switch and charge up an internal capacitance of the first power switch to the elevated voltage provided by the first bootstrap capacitor). The pull-up drive signal generator can be configured to end the pull-up signal pulse and turn off the pull-up switch while the first drive signal is still being applied. The internal capacitance of the first power switch can keep the first power switch on until a transition from the second drive signal to the first drive signal. A pull-down drive signal generator can be configured to produce a pull-down signal pulse to turn on the pull-down switch in response to the transition from the second drive signal to the first drive signal (e.g., to thereby discharge the internal capacitance of the first power switch and turn off the first power switch). The integrated circuit can include a first bootstrap capacitor for the first power switch and a second bootstrap capacitor for the second power switch.

(27) Various method disclosed herein can relate to a method of operating a power converter. The method can include receiving an input voltage at an input, turning on a first power switch to provide an electrical path from the input, through an AC coupling capacitor, through an inductor, to an output. The method can include increasing a voltage signal using a first bootstrap capacitor to produce a first elevated voltage, and delivering the first elevated voltage to the first power switch to keep the first power switch on.

(28) The method can include turning off the first power switch and turning on another switch to provide an electrical path from a voltage source, through the first bootstrap capacitor, to ground, so that the first bootstrap capacitor recharges. The method can include turning on a second power switch to provide an electrical path from the AC coupling capacitor, through another inductor, to the output. The method can include increasing a voltage signal using a second bootstrap capacitor to produce a second elevated voltage, and delivering the second elevated voltage to the second power switch to keep the second power switch on. The method can include delivering the second elevated voltage to the first bootstrap capacitor to recharge the first bootstrap capacitor. The method can include charging an internal capacitance of the first power switch using the elevated voltage from the first bootstrap capacitor, and disconnecting the first elevated voltage from the first power switch. The internal capacitance of the first power switch can keep the first power switch on. The method can include discharging the internal capacitance of the first power switch in response to a

drive signal to turn off the first power switch. The first bootstrap capacitor and the first power switch can be parts of the same integrated circuit.

(29) Various embodiments disclosed herein can relate to a DC-DC buck converter, which can include an input configured to receive an input voltage, an output configured to output an output voltage that is lower than the input voltage, a first inductor, a second inductor, a first power switch, a second power switch, a third power switch, a fourth power switch, and a driver configured to send drive signals to the power switches to operate the buck converter in multiple states of operation. In a first state of operation that drives current through the first inductor, the first power switch is on, the second power switch is off, the third power switch is on, and the fourth power switch is off. In a second state of operation the first power switch is off, the second power switch is off, the third power switch is on, and the fourth power switch is on. In a third state of operation, which drives current through the second inductor, the first power switch is off, the second power switch is on, the third power switch is off, and the fourth power switch is on. In a fourth state of operation the first power switch is off, the second power switch is off, the third power switch is on, and the fourth power switch is on.

(30) A first bootstrap capacitor can be configured to provide an elevated voltage for keeping the first power switch on during the first state of operation. The first bootstrap capacitor can discharge during the first state of operation to provide the elevated voltage. The first bootstrap capacitor can recharge during one or more of the second, third, and fourth states of operation. A second bootstrap capacitor can be configured to provide an elevated voltage for keeping the second power switch on during the third state of operation. The second bootstrap capacitor can discharge during the third state of operation to provide the elevated voltage. The second bootstrap capacitor can recharge during one or more of the first, second, and fourth states of operation. The second bootstrap capacitor can be configured to recharge the first bootstrap capacitor. The first bootstrap capacitor can be integrated into the same integrated circuit with the first power switch.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Certain embodiments will be discussed in detail with reference to the following figures, wherein like reference numerals refer to similar features throughout. These figures are provided for illustrative purposes and the embodiments are not limited to the specific implementations illustrated in the figures.

(2) FIG. 1 shows an example embodiment of a power converter.

(3) FIG. 2A shows an example embodiment of a power converter in a first state of operation.

(4) FIG. 2B shows an example embodiment of a power converter in a second state of operation.

(5) FIG. 2C shows an example embodiment of a power converter in a third state of operation.

(6) FIG. 2D shows an example embodiment of a power converter in a fourth state of operation.

(7) FIG. 3 shows an example embodiment of portions of a power converter that includes bootstrap capacitors.

(8) FIG. 4A shows an example embodiment of a power converter in a state for charging a bootstrap capacitor.

(9) FIG. 4B shows an example embodiment of a power converter in a state for discharging a bootstrap capacitor.

(10) FIG. 5 shows an example embodiment of circuitry for controlling the charging and discharging of a bootstrap capacitor.

(11) FIG. 6 shows another example embodiment of a power converter that includes bootstrap capacitors.

(12) FIG. 7 shows another example embodiment of a power converter that includes bootstrap

capacitors.

(13) FIG. **8** shows the values for various signals during operation of an example embodiment of a power converter.

(14) FIG. **9** shows an example embodiment of a power switch with an internal capacitance.

(15) FIG. **10** shows an example embodiment of circuitry for operating a power switch using a bootstrap capacitor.

(16) FIG. **11** shows the values for various signals during operation of a first power switch in an example embodiment of a power converter.

(17) FIG. **12** shows the values for various signals during operation of a second power switch in an example embodiment of a power converter.

(18) FIG. **13** shows the values for current and various other signals during operation of an example embodiment of a power converter.

(19) FIG. **14** shows the values for current during operation of an example embodiment of a power converter.

(20) FIG. **15** shows an example embodiment of a power converter configured to provide current sensing.

(21) FIG. **16** shows an example embodiment of current sensing circuitry.

(22) FIG. **17** shows an example embodiment of circuitry for applying gain to a signal indicative of the current.

(23) FIG. **18** shows an example embodiment of circuitry combining current sensing values from multiple channels.

(24) FIG. **19** shows another example embodiment of circuitry for applying gain to a signal indicative of the current.

(25) FIG. **20** shows a plot of the actual current through the power converter and the sensed current.

(26) FIG. **21** shows another example embodiment of a power converter configured to provide current sensing.

(27) FIG. **22** shows another example embodiment of a power converter configured to provide current sensing.

(28) FIG. **23** shows the values for various signals during operation of an example embodiment of a power converter.

(29) FIG. **24** shows an example embodiment of a power converter that is configured to pre-charge a capacitor.

(30) FIG. **25** shows an example embodiment of circuitry for applying pre-charge to a capacitor in a power converter.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

(31) AC Coupled Power Converters

(32) FIG. **1** shows a schematic diagram of an example embodiment of a power converter **100**. The power converter **100** can be a direct current to direct current (DC-DC) power converter, such as a buck converter. The power converter **100** can be used as a point-of-load converter that receives power from a power supply of an electronic device and supplies a particular voltage to a component of the electronic device. The power converter **100** can include an input **102**, which can receive an input voltage $V_{sub.in}$. The input voltage $V_{sub.in}$ can be received from a power supply of an electronic device, a battery, an external power source, etc. The input **102** can receive a direct current DC voltage. The power converter **100** can have an output **104**, which can provide an output voltage $V_{sub.o}$. The output **104** can be coupled to a device, such as a load $R_{sub.L}$, that receives power from the power converter **100**. The power converter **100** can operate so that the output voltage $V_{sub.o}$ is different than the input voltage $V_{sub.in}$. For a power converter **100** that is a buck converter, the output voltage $V_{sub.o}$ can be lower than the input voltage $V_{sub.in}$. The power converter can include an output capacitor $C_{sub.o}$ **108**, which can smooth the output voltage $V_{sub.o}$ provided by the output. The output voltage $V_{sub.o}$ can be a direct current DC voltage.

- (33) The power converter **100** can include a first inductor **L1 110** and a second inductor **L2 112**. The first inductor **110** can include a first winding of wire around a core (e.g., a magnetic core), and the second inductor **112** can include a second winding of wire around the same core. Alternatively, the first inductor **110** and the second inductor **112** can have separate cores (e.g., magnetic cores). Any suitable type of inductors can be used.
- (34) The power converter **100** can include power switches, which can operate to direct current so as to change the input voltage $V_{sub.in}$ to the output voltage $V_{sub.o}$. The power converter **100** can include a first power switch **Q1 114**, a second power switch **Q2 116**, a third power switch **Q3 118**, and fourth power switch **Q4 120**. The first power switch **114** and the second power switch **116** can be high-side switches, which can be on the high voltage side of the circuit between the input **102** and the output **104** to the powered device **106** or load $R_{sub.L}$. The third power switch **118** and the fourth power switch **120** can be low-side switches, which can be on the low voltage side of the circuit between the output **104**, or powered device **106**, or load $R_{sub.L}$ and ground **124** or low voltage side of the power source. The power switches **114**, **116**, **118**, and **120** can be N-channel transistors, such as N-channel metal-oxide-semiconductor field-effect transistors (MOSFETs), or gallium-nitride field-effect transistors (GaN FETs), or enhanced-gallium-nitride field-effect transistors (eGaN FETs), or any combination thereof. In some embodiments, P-channel transistors (e.g., P-channel MOSFETs, GaN FETs, or cGaN FETs), or any other suitable type of switching devices can be used for one or more of the power switches **114**, **116**, **118**, and **120**.
- (35) The first power switch **Q1 114** can have a drain that is coupled to the input **102**, such as to a positive voltage side of a power source. The source of the first power switch **114** can be coupled to the drain of the second power switch **Q2 116**. The drain of the second power switch **116** can be coupled to the second inductor **112**. Additionally, a first side of a capacitor **C.sub.B 122** can be coupled to the source of the first power switch **114** and to the drain of the second power switch **116**, and the second side of the capacitor **122** can be coupled to the first inductor **110**. The inductors **110** and **112** can be coupled to the output **104**. The inductors **110** and **112** can be coupled in parallel to the output **104**.
- (36) The third power switch **Q3 118** can have a drain that is coupled to the source of the second power switch **Q2** and to the second inductor **112**. The source of the third power switch **118** can be coupled to ground **124** and/or to the low voltage side of a power source. The fourth power switch **Q4 120** can have a drain that is coupled to the capacitor **122** (e.g., the second side thereof) and to the first inductor **110**. The source of the fourth power switch **120** can be coupled to ground **124** and/or to the low voltage side of a power source. The power switches **114**, **116**, **118**, **120** can each have a gate for receiving drive signals, which can be used to turn on the corresponding switch (e.g., making the switch conductive to enable current to flow through the switch), and to turn off the corresponding switch (e.g., making the switch nonconductive to prevent or impede current from flowing through the switch). The power converter **100** can include a driver (not shown in FIG. 1), which can send drive signals to the gates of the power switches **114**, **116**, **118**, and **120** to turn the corresponding switches on and off.
- (37) The capacitor **122** can be between the first power switch **114** and the fourth power switch **120**, for example to AC couple the first power switch **114** to the fourth power switch **120**. The capacitor **122** can be between the first power switch **114** and the first inductor **110**, for example to AC couple the first power switch **114** to the first inductor **110**. The capacitor **122** can be between the second power switch **116** and the fourth power switch **120**, for example to AC couple the second power switch **116** to the fourth power switch **120**. The capacitor **122** can be between the second power switch **116** and the first inductor **110**, for example to AC couple the second power switch **116** to the first inductor **110**. The capacitor **122** can AC couple components so as to permit alternating current (AC) signals to be transferred between the components, while generally impeding direct current (DC) signals from being transmitted.
- (38) FIGS. 2A-D show four states of operation for the power converter **100**. FIG. 2A shows a first

state of operation where the first power switch **114** and the third power switch **118** are on, and where the second power switch **116** and the fourth power switch **120** are off. In the first state of operation (FIG. 2A), current can flow from the input **102**, through the first power switch **114**, through the capacitor **122**, through the first inductor **110**, to the output **104** and the load device **106**. During the first state of operation (FIG. 2A), the second inductor **112** can draw a current through the third power switch **118**. During the first state of operation, the input voltage can cause the current through the first inductor **110** to increase, thereby storing energy in the first inductor **110**. During the first state of operation, the voltage across the capacitor **122** can increase, thereby storing energy in the capacitor **122**.

(39) The capacitor **122** can have sufficient capacity (e.g., can store enough charge) that it can supply a current to the inductor **112** when the power switch **116** is conductive (e.g., at the third state of operation in FIG. 2C), without the capacitor **122** becoming substantially discharged. The power converter can transition to the fourth state of operation (e.g., FIG. 2D) before the capacitor **122** become substantially discharged.

(40) FIG. 2B shows a second state of operation where the third power switch **118** and the fourth power switch **120** are on, and where the first power switch **114** and the second power switch **116** are off. The first inductor **110** can draw a current through the fourth power switch **120**, and the second inductor **112** can draw a current through the third power switch **118**. The current through the first inductor **110** can decrease as the first inductor **110** outputs some of its stored energy, and the current through the second inductor **112** can decrease as the second inductor **112** outputs some of its stored energy.

(41) FIG. 2C shows a third state of operation where the second power switch **116** and the fourth power switch **120** are on, and where the first power switch **114** and the third power switch **118** are off. At least some of the energy stored in the capacitor **122** (during the first state) can be output in the third stage of operation, and some of that energy can be stored in the second inductor **112**. The voltage from the capacitor can cause the current through the second inductor to increase, thereby storing energy in the second inductor **112**. The first inductor **110** can draw a current through the fourth power switch **120**. Also, current through the fourth power switch **120** can be directed to the capacitor **122**.

(42) FIG. 2D shows a fourth state of operation where the third power switch **118** and the fourth power switch **120** are on, and where the first power switch **114** and the second power switch **116** are off. The first inductor **110** can draw a current through the fourth power switch **120**, and the second inductor **112** can draw a current through the third power switch **118**. The current through the first inductor **110** can decrease as the first inductor **110** outputs some of its stored energy, and the current through the second inductor **112** can decrease as the second inductor **112** outputs some of its stored energy.

(43) By controlling the timing of the four states of operation (FIGS. 2A-D), the power converter can set an output voltage that is different (e.g., lower) than the input voltage. The value of the output voltage can depend on the relative amounts of time that the system spends in the different states of operation. The power converter **100** can include controller components that are not shown in FIGS. 2A-D, such as a driver configured to generate drive signals for turning the power switches **114**, **116**, **118**, and **120** on and off, and a controller (e.g., a pulse width modulator (PWM) controller) configured to control the timing of the drive signals provided by the driver. In some embodiments, an integrated circuit (IC) can include the first power switch **114**, the second power switch **116**, the third power switch **118**, the fourth power switch **120**, the driver, the PWM controller, or any combinations thereof. In some cases, a PWM controller can be external to the IC, for example, a shared PWM controller could be used to control multiple power converter stages.

(44) In some embodiments, the power converter **100** can include a chip-embedded IC, or embedded circuitry. For example, the IC or circuitry can be embedded inside a printed circuit board (PCB). For example a multi-layer PCB can include an upper PCB layer above the embedded IC or circuitry

and a lower PCB layer below the embedded IC or circuitry. In some embodiments, the first inductor **110** and/or the second inductor **112** can be external to the PCB (e.g., mounted on a top side of the PCB). The first inductor **110** and/or the second inductor **112** can have a footprint that at least partially overlaps the embedded IC or embedded circuitry. The overlap can be a portion of, the majority of, or the entirety of the footprint of the first inductor **110** and/or the second inductor **112**, or of the embedded IC or circuitry. The output capacitor **108** can be external to the PCB (e.g., mounted on a top side of the PCB). The output capacitor **108** can have a footprint that at least partially, majoritarily, or entirely overlaps the embedded IC or circuitry. The capacitor **122** can be external to the PCB (e.g., mounted on a top side of the PCB). The capacitor **122** can have a footprint that at least partially, majoritarily, or entirely overlaps the embedded IC or circuitry. One or more of the first inductor **110**, the second inductor **112**, the output capacitor **108**, and the capacitor **122**, or any combinations thereof can be coupled to the embedded IC or circuitry by one or more vias. The power converters disclosed herein can use the features and details disclosed in U.S. Pat. No. 10,193,442, issued Jan. 29, 2019, and titled CHIP EMBEDDED POWER CONVERTERS, which is hereby incorporated by reference for all that it discloses, including the details and features related to chip-embedded power converters.

(45) FIG. 3 shows a schematic diagram of an example embodiment of a power converter **100**. The power converter **100** can include an input **102**, and output **104**, a first inductor **110**, a second inductor **112**, a first power switch **114**, a second power switch **116**, a third power switch **118**, a fourth power switch **120**, and a ground **124** or low voltage connection, which can be similar to the embodiments of FIGS. 1 and 2A-D. The power converter **100** can include an integrated circuit **126**, which can be chip-embedded, such as inside a printed circuit board, as discussed herein. The integrated circuit **126** can include terminals for inputting and/or outputting signals, and the terminals are represented in FIG. 3 by squares on the boarder of the integrated circuit **126**. For example, the integrated circuit **126** can include terminals for the input **102** for power voltage in PV.sub.in and the output **104** for voltage out V.sub.O. A terminal can be included for ground **124**. Although not shown in FIG. 3, a capacitor **122** can be coupled between the terminals CS1 and CS2. The capacitor **122** can be external to the integrated circuit **126**, such as mounted to the exterior of the PCB (e.g., at least partially overlapping the integrated circuit **126**). Locations corresponding to CS1 and CS2 are also shown in FIG. 1, for reference. The capacitor **122** can AC couple the first power switch **114** to the fourth power switch **120**, or other components similar to the discussion in connection with FIG. 1. Although not shown in FIG. 3, the power converter **100** can include an output capacitor **108**, such as coupled to the output **104** or V.sub.O terminal. The output capacitor **108** can be external to the integrated circuit **126**, such as mounted to the exterior of the PCB (e.g., at least partially overlapping the integrated circuit **126**). FIG. 3 shows the first inductor **110** and the second inductor **112** as being part of the integrated circuit **126**. In some embodiments, one or both of the inductors **110**, **112** can be external to the integrated circuit **126**, such as mounted to the exterior of the PCB (e.g., at least partially overlapping the integrated circuit **126**). The integrated circuit **126** can include terminals for providing signals to or from one or both of the external inductors **110**, **112** (e.g., similar to the terminals CS1 and CS2). The first inductor **110**, second inductor **112**, output capacitor **108**, capacitor **122**, or any combination thereof can be coupled to the integrated circuit **126** by vias, such as extending through the PCB.

(46) The power converter **100** can include driver circuitry for sending drive signals to the power switches **114**, **116**, **118**, **120**, and in some embodiments, the driver circuitry can be included in the integrated circuit **126**. The driver circuitry can include a driver controller **128**, which can be configured to output signals that are delivered to, or otherwise control, the respective gates of the power switches **114**, **116**, **118**, **120**. The driver controller **128** can include gate drive logic. The driver controller **128** can output a first drive signal HDrv1 for controlling the first power switch Q1 **114**, a second drive signal HDrv2 for controlling the second power switch Q2 **116**, a third drive signal LDrv2 for controlling the third power switch Q3 **118**, and a fourth drive signal LDrv1 for

controlling the fourth power switch **Q4 120**. The driver circuitry can include one or more amplifiers for amplifying the drive signals. The drive signals output by the driver controller can be logic signals, which in some cases can have voltages below the voltage values that operate the power switches **114, 116, 118, 120**. The amplifiers **130, 132, 134, 136** can amplify the corresponding drive signals (e.g., **HDrv1, HDrv2, LDrv2, and LDrv1**) to appropriate voltages for operating the power switches **114, 116, 118, 120**. The amplifiers **130, 132, 134, 136** can be operational amplifiers. (47) The power converter **100** can include a pulse width modulation (PWM) pulse generator **138**, which can provide PWM signals to the driver controller, which can control the duty cycle or timing of the drive signals, for example. Although PWM is disclosed in connection with this embodiment, any suitable modulation or control approach can be used to generate drive signals to operate the power switches **114, 116, 118, 120**.

(48) The integrated circuit **126** can include additional features. In some cases, components not shown in FIG. 3 can be included in the integrated circuit **126**. Components that are shown as part of the integrated circuit **126** in FIG. 26 could be outside the integrated circuit **126** or in a different integrated circuit. In some embodiments, some or all of the components disclosed in connection with FIG. 3 can be embedded circuitry (e.g., inside a PCB) that is not integrated into an IC. In some embodiments, the IC or circuitry is not chip embedded and can be external to a PCB (e.g., mounted thereto).

(49) High-Side Power Switch Drivers

(50) In some embodiments, N-channel transistors or FETs can be used for the first power switch **114**, the second power switch **116**, the third power switch **118**, the fourth power switch **120**, or any combinations thereof. Although some embodiments are discussed herein as using MOSFETs, it will be understood that GaN FETs or eGaN FETs or other types of transistors could be used instead. In some embodiments, it can be advantageous to use an N-channel FET rather than a P-channel FET (e.g., for the power switches **114, 116, 118, 120**), such as to reduce chip size, to reduce cost, and/or to increase performance and/or efficiency. An N-channel MOSFET is on (e.g., conductive) when the voltage at the gate is higher than the voltage at the source (such as by a threshold amount), and the N-channel MOSFET is off (e.g., nonconductive) when the voltage at the gate is not higher than the voltage at the source (such as by a threshold amount). For low-side switches, such as power switches **118** and **120**, the source of the MOSFET can be coupled to ground and/or to a low voltage side of a power source, so that delivering a high voltage to the gate can turn on the MOSFET and keep it on while the high voltage is maintained at the gate. However, in some instances, for high-side switches, such as power switches **114, 116**, the source of the MOSFET can receive a high voltage when the switch turns on. Thus delivering a high voltage to the gate of the high-side switch can turn the switch on, but once the high voltage reaches the source the switch can turn off. Thus, it can be advantageous to provide a voltage raising circuit or feature for driving a switch, such as a high-side switch that uses an N-channel FET. In some embodiments, a charge pump circuit can be used, or a bootstrap circuit can be used, or any suitable circuitry or feature that raises the voltage applied to the gate, and a number of example embodiments are disclosed herein.

(51) The power converter **100** can include a first bootstrap capacitor **C1 140**, which can be configured to provide an elevated voltage to the first power switch **Q1 114**. The power converter **100** can include a second bootstrap capacitor **C2 142**, which can be configured to provide an elevated voltage to the second power switch **Q2 116**. Each of the bootstrap capacitors **140, 142** can operate by charging up the bootstrap capacitor **140** or **142** during a first period of time (e.g., while the corresponding power switch **114** or **116** is off), so that energy is stored in the bootstrap capacitor **140** or **142**, and then discharging the bootstrap capacitor **140** or **142** during a second period of time (e.g., while the corresponding power switch **114** or **116** is on), so that energy from the bootstrap capacitor **140** or **142** is released to raise the voltage at the gate of the corresponding power switch **114** or **116**.

(52) FIG. 3 shows the first bootstrap capacitor **140** and the second bootstrap capacitor **142** as being

part of the integrated circuit **126**. In some embodiments, one or both of the bootstrap capacitors **140**, **142** can be external to the integrated circuit **126**, such as mounted to the exterior of the PCB (e.g., at least partially overlapping the integrated circuit **126**). The integrated circuit **126** can include terminals for providing signals to or from one or both of the bootstrap capacitors **140**, **142** (e.g., similar to the terminals CS1 and CS2). The first bootstrap capacitor **140** and/or the second bootstrap capacitor **142** can be coupled to the integrated circuit **126** by vias, such as extending through the PCB. In some embodiments, a power converter **100** can include one of the bootstrap capacitors **140** or **142**, but not both, such as if a different voltage raising approach is used for one of the power switches **114**, **116**.

(53) Example Bootstrap Circuits and Control

(54) Operation of the first bootstrap capacitor **140** will be discussed in connection with FIGS. 4A and 4B. FIG. 4A shows a schematic diagram of an example embodiment of a power converter **100** in a first configuration that charges the first bootstrap capacitor **140**. FIG. 4B shows a schematic diagram of an example embodiment of a power converter **100** in a second configuration that discharges the first bootstrap capacitor **140**. The power converter **100** can have circuitry, such as including one or more switches **144**, for changing the power converter between the first configuration that charges the first bootstrap capacitor **140** (e.g., FIG. 4A) and the second configuration that discharges the first bootstrap capacitor **140** (e.g., FIG. 4B).

(55) The first bootstrap capacitor **140** can have a first side that is coupled to a voltage source **146**. The first bootstrap capacitor **140** can have a second side that can be selectively coupled to ground **124** (e.g., FIG. 4A) and can be selectively coupled to the source of the first power switch **114** (e.g., FIG. 4B). In some embodiments, the voltage source **146** can provide voltage to the amplifier **130** and to the first bootstrap capacitor **140**. In some embodiments, a diode can be used to enable current to flow from the voltage source **146** to the capacitor **140** and/or to the amplifier **130**, and to impede current from flowing the other direction to the voltage source **146**. In some embodiments, the diodes shown between the bootstrap capacitors **140**, **142** and the respective voltage sources **146**, **148** can be replaced with switches (e.g., MOSFETs or other transistors) that can be driven (e.g., with signals from the driver controller **128**) to be on when charging the respective bootstrap capacitor **140** or **142**, and to be off when the respective bootstrap capacitor **140** or **142** is discharging, as discussed herein.

(56) In the first configuration, the one or more switches **144** can couple the first bootstrap capacitor **140** to ground **124**, which can be the same ground connection **124** shown in FIGS. 1 and/or 3, or a different ground or low voltage connection. In the first configuration (e.g., FIG. 4A), current can flow between a voltage source **146** and the first bootstrap capacitor **140**, and between the first bootstrap capacitor **140** and ground **124**, while the first bootstrap capacitor **140** charges. The one or more switches **144** can have a first configuration that creates a path from the voltage source **146** to the first bootstrap capacitor **140** to ground **124**. The first bootstrap capacitor **140** can be charged to about a voltage $V_{sub.cc}$ of the voltage source **146**. In some embodiments, a small voltage drop can be created by the diode between the voltage source **146** and the first bootstrap capacitor **140**, so that the charged capacitor **140** has a voltage slightly less than, but still about the level of, the Voltage $V_{sub.cc}$, from the voltage source **146**. In some embodiments, a switch (e.g., transistor) can be used in place of the diode, as discussed, to reduce or avoid the small voltage drop. In some embodiments, the first bootstrap capacitor **140** can be charged substantially to saturation, although in some embodiments, a capacitor could be selected that would be charged only partially and have enough stored energy so that during the discharge phase the first power switch **114** can be on for the appropriate time, such during the first state of operation (e.g., FIG. 2A). In some embodiments, the path for charging the first bootstrap capacitor **140** does not go through any of the power switches **114**, **116**, **118**, **120**. In some embodiments, the one or more switches **144** does not include any of the power switches **114**, **116**, **118**, **120**.

(57) The one or more switches **144** can be in the first configuration to charge the first bootstrap

capacitor **140** during part or all of the time that the first power switch **114** is off (e.g., non-conductive or open), such as during at least a portion of the second state of operation (e.g., FIG. 2B), the third state of operation (e.g., FIG. 2C), and the fourth state of operation (e.g., FIG. 2D). In some embodiments, the one or more switches are not in the first configuration during the first state of operation (e.g., FIG. 2A), when the first power switch **113** is on (e.g., conductive or closed). For example, a low or off signal for the drive signal HDrv1 for driving the first power switch **114** can be used to set the one or more switches **144** in the first configuration (e.g., FIG. 4A). Also, drive signals for one or more of the other power switches **116**, **118**, **120** can be used to operate the one or more switches **144**. A high or on signal for the drive signal HDrv2 for driving the second power switch **116** can be used to set the one or more switches **144** in the first configuration. The first power switch **114** is off when the second power switch **116** is on, in the third state of operation (e.g., FIG. 2C). A high or on signal for the drive signal LDrv1 for driving the fourth power switch **120** can be used to set the one or more switches **144** in the first configuration. The first power switch **114** is off when the fourth power switch **120** is on, in the second, third, and fourth states of operation (e.g., FIGS. 2B, 2C, and 2D), so using the LDrv1 signal for driving the one or more switches **144** can facilitate providing enough time in the first configuration to sufficiently charge the first bootstrap capacitor **140**.

(58) In the second configuration, the one or more switches **144** can couple the first bootstrap capacitor **140** to the source of the first power switch **114**. In the second configuration (e.g., FIG. 4B), current can flow from a voltage source, such as the input **102** with voltage input $V_{sub.in}$, through the first power switch **114**, and to the first bootstrap capacitor **140**. Current can flow from the first bootstrap capacitor **140** to the amplifier **130**, such as to the positive voltage supply connection of the amplifier **130**. In the second configuration (e.g., FIG. 4B) the energy stored in the capacitor can step up the voltage that is delivered to the amplifier **130**. The increased voltage provided to the amplifier **130** can be the voltage at the source of the first power switch **114** (e.g., about $V_{sub.in}$) plus the voltage across the first bootstrap capacitor **140** (e.g., about $V_{sub.cc}$). The diode between the first bootstrap capacitor **140** and the voltage source **146** (or, alternatively, an open or off switch) can prevent current from flowing from the first bootstrap capacitor **140** to the voltage source **146** in the second configuration, especially since the elevated voltage (e.g., about $V_{sub.in}+V_{sub.cc}$) can be higher than the voltage $V_{sub.cc}$ at the voltage source **146**. The amplifier **130** can be configured to provide the elevated voltage (e.g., about $V_{sub.in}+V_{sub.cc}$) to the gate of the first power switch **114** (e.g., when the HDrv1 signal is high or on). The amplifier **130** for driving the first power switch **114** can have a positive or high voltage supply coupled to the voltage source **146** and to the first bootstrap capacitor **140**. The amplifier **130** for driving the first power switch **114** can have a negative or low voltage supply coupled to the source of the first power switch **114**. By way of example, when the first power switch **114** is on, the source of the first power switch can have a voltage of about $V_{sub.in}$, and the voltage at the gate of about $V_{sub.in}+V_{sub.cc}$ can be sufficiently higher than the voltage at the source to cause the first power switch **114** to remain on (e.g., conductive). The voltage applied to the gate can be large than the source voltage by about the amount of voltage increase provided by the first bootstrap capacitor **140**. In some cases, the voltage increase can drop over time as the capacitor **140** discharges, and the capacitor **140** can be selected to have enough capacity to keep the elevated voltage sufficiently high for the desired time (e.g., during the first state of operation while the first power switch **114** is on).

(59) The one or more switches **144** can be in the second configuration (e.g., to discharge the first bootstrap capacitor **140**) while the first power switch **114** is on (e.g., conductive or closed), such as during the first state of operation (e.g., FIG. 2A). In some embodiments, the one or more switches are not in the second configuration during the second state of operation (e.g., FIG. 2B), the third state of operation (e.g., FIG. 2C), and/or the fourth state of operation (e.g., FIG. 2D). For example, a high or on signal for the drive signal HDrv1 for driving the first power switch **114** can be used to set the one or more switches **144** in the second configuration (e.g., FIG. 4B). Also, drive signals for

one or more of the other power switches **116**, **118**, **120** can be used to operate the one or more switches **144**. A low or off signal for the drive signal LDrv1 for driving the fourth power switch **120** can be used to set the one or more switches **144** in the second configuration. The first power switch **114** is on when the fourth power switch **116** is off, in the first state of operation (e.g., FIG. 2A).

(60) The one or more switches **144** can be a single switch that has the first and second configurations, or the one or more switches **144** can include multiple switches that can be controlled to have the first and second configurations. The one or more switches **114** can include one or more relays, or MOSFETs, or other FETs, or other types of transistors, or any other suitable type of switch. In some embodiments, the one or more switches **114** for the first and second configurations associated with charging and discharging the first bootstrap capacitor are not the power switches **114**, **116**, **118**, **120**. In some embodiments, the current path for charging the first bootstrap capacitor **140** (e.g., in the first configuration) does not go through any of the power switches **114**, **116**, **118**, **120**.

(61) FIG. 5 is a schematic diagram of an example embodiment of circuitry for controlling the charging and discharging of the first bootstrap capacitor **140**. In FIG. 5, the one or more switches **144** can include a first switch **150**, a second switch **152**, and a third switch **154**, which can be MOSFETs, or other FETs, or any other suitable type of transistor or other switch type. By way of example, the first switch **150** can be an N-channel MOSFET, the second switch **152** can be a P-channel MOSFET, and the third switch **154** can be an N-channel MOSFET, although other configurations and switch types can be used. The first switch **150** can be coupled between the first bootstrap capacitor **140** and ground **124**. The second switch **152** can be coupled between the first bootstrap capacitor **140** and the voltage source **146**. The third switch **154** can be coupled between the first bootstrap capacitor **140** and the first power switch **114** (e.g., the source thereof).

(62) A drive signal **156** can be used to control the switches **150**, **152**, **154** to produce the first configuration for charging the first bootstrap capacitor **140** and the second configuration for discharging the first bootstrap capacitor **140**, as discussed herein. The drive signal **156** can be the LDrv1 drive signal that is used for driving the fourth power switch **120**, although other drive signals can be used, as discussed herein, such as the HDrv1 drive signal associated with the first power switch **114**, or the inverse thereof. An amplifier **158** can receive the drive signal **156**, which can be a logic signal, and can amplify the voltage to a voltage suitable for operating the first switch **150**. An amplifier **160** can receive drive signal **156**, which can be a logic signal, and can amplify the voltage to a voltage suitable for operating the second switch **152** and/or the third switch **154**. The amplifiers **160** can be operational amplifiers. An inverter can be used (e.g., in connection with the amplifier **160**) so that different signals are provided to the first switch **150** and to the second and third switches **152**, **154**. Different configurations are possible, depending on the drive signal used and the types of switches used. For example, the inverter can be omitted or can be used to invert the signal to the first switch **150** instead of inverting the signal to the second and third switches **152**, **154**. In some cases, the amplifiers can be omitted and the drive signal **156** can have sufficient voltage for operating the switches **150**, **152**, **154**. In some embodiments, a level shifter **162** can be used to modify the input drive signal **156** that is used, such as for the second and/or third switches **152**, **154**, although in some configurations the level shifter **162** can be omitted or used differently, such as for the first switch **150**. The level shifter **162** can shift the input voltage signals to a level appropriate for the amplifiers **160** and/or **158**, for example.

(63) In the example embodiment of FIG. 5, the drain of the first switch **150** is coupled to the first bootstrap capacitor **140** (e.g., to a second side thereof), the source of the first switch **150** is coupled to ground **124**, and the gate of the first switch **150** is coupled to the drive signal source **156**, such as through the amplifier **158**. The second switch **152** can have a drain that is coupled to the voltage source **146**, a source that is coupled to the bootstrap capacitor **140** (e.g., to a first side thereof), and a gate that is coupled to the drive signal source **156**, such as through the level shifter **162** and/or

amplifier/inverter **160**. The source of the second switch **152** and the first bootstrap capacitor **140** (e.g., the first side thereof) can also be coupled to the amplifier **130**, such as to the positive voltage supplier of the amplifier **130**, through the connection labeled **BST1**. **BST1** is also labeled in at least FIGS. **4A** and **4B** for reference. The source of the second switch **152** and the first bootstrap capacitor **140** (e.g., the first side thereof) can also be coupled to the amplifier **160**, such as to the positive voltage supplier of the amplifier **160**. The third switch **154** can have a drain that is coupled to the source of the first power switch **Q1 114**, a source coupled to the bootstrap capacitor **140** (e.g., to the second side thereof), and a gate that is coupled to the drive signal source **156**, such as through the level shifter **162** and/or inverting amplifier **160**. The source of the third power switch **154** can also be coupled to the drain of the first switch **150**, such as through a node that is between the first switch **150** and the capacitor **140**. The source of the third switch **154** (e.g., as well as the drain of switch **150** and the capacitor **140**) can be coupled to the amplifier **160**, such as to the negative voltage supply thereof.

(64) The drive signal **156** can have a first value (e.g., high) for the first configuration. In the first configuration, the high drive signal **156** can turn the first switch **150** on (e.g., conductive), and the high drive signal **156** (e.g., inverted to low by the inverting amplifier **160**) can turn the second switch **152** on (e.g., conductive) and can turn the third switch **154** off (e.g., non-conductive). In the first configuration, current can flow from the voltage source **146**, through the second switch **152** to the first bootstrap capacitor **140**, and current can flow from the first bootstrap capacitor **140**, through the first switch **150**, to ground **124**. The first bootstrap capacitor **140** can be charged in the first configuration, such as to a voltage of about $V_{sub.cc}$, as discussed herein.

(65) The drive signal **156** can have a second value (e.g., low) for the second configuration. In the second configuration, the low drive signal **156** can turn the first switch **150** off (e.g., non-conductive), and the low drive signal **156** (e.g., inverted to high by the inverting amplifier **160**) can turn the second switch **152** off (e.g., non-conductive) and can turn the third switch **154** on (e.g., conductive). In the second configuration, the charging path from the voltage source **146**, through the capacitor **140**, to ground **124** is interrupted, by the first switch **150** and/or the second switch **152** being in the off state. In the second configuration, the third switch **154** can be on to couple the first bootstrap capacitor **140** to the source of the first power switch **114**. The first bootstrap capacitor **140** can discharge in the second configuration. In the second configuration, current can flow from a voltage source (e.g., about $V_{sub.in}$), through the first power switch **114**, and to the first bootstrap capacitor **140**. Current can flow from the first bootstrap capacitor **140** to the amplifier **130**, such as through connection **BST1** to the positive voltage supply connection of the amplifier **130**. In the second configuration, the energy stored in the capacitor can step up the voltage that is delivered to the amplifier **130**. The increased voltage provided to the amplifier **130** can be the voltage at the source of the first power switch **114** (e.g., about $V_{sub.in}$) plus the voltage across the first bootstrap capacitor **140** (e.g., about $V_{sub.cc}$). The amplifier **130** can be configured to provide the elevated voltage (e.g., about $V_{sub.in} + V_{sub.cc}$) to the gate of the first power switch **114** so that the first power switch **114** can be kept in the on state, as discussed herein. The capacitor **140** can also operate as a bootstrap capacitor for the third switch **154**. In the second configuration, the capacitor **140** can step up the voltage that is supplied to the amplifier **160**, so that the third switch **154** can be kept in the on state.

(66) Many variations are possible, such as the use of different drive signals **156**, different switch configuration, etc. In some embodiments, a diode can be used instead of the second switch **152**, as discussed herein.

(67) Operation of the second bootstrap capacitor **140** will be discussed. As can be seen in FIGS. **3**, **4A** and **4B** and as described herein, in some embodiments the power converter **100** can have a state that charges the second bootstrap capacitor **142**, such as while the second power switch **116** is off (e.g., non-conductive), and the power converter **100** can have a different state that discharges the second bootstrap capacitor **142**, such as to provide an elevated voltage for holding the second

power switch **116** in an on (e.g., conductive) state.

(68) The second bootstrap capacitor **142** can have a first side that is coupled to a voltage source **148** (e.g., V.sub.cc). The second bootstrap capacitor **142** can have a second side that can be selectively coupled to ground **124** when the third power switch Q3 **118** is on (e.g., conductive). The second bootstrap capacitor **142** (e.g., the second side thereof) can be coupled to the source of the second power switch **116**. In some embodiments, the voltage source **148** can provide voltage to the amplifier **132** and to the second bootstrap capacitor **142**. In some embodiments, a diode can be used to enable current to flow from the voltage source **148** to the capacitor **142** and/or to the amplifier **132**, and to impede current from flowing the other direction to the voltage source **148**. In some embodiments, either of the diodes shown between the bootstrap capacitors **140**, **142** and the respective voltage sources **146**, **148** can be replaced with switches (e.g., MOSFETs or other transistors) that can be driven (e.g., with signals from the driver controller **128**) to be on when charging the respective bootstrap capacitor **140** or **142**, and to be off when the respective bootstrap capacitor **140** or **142** is discharging, as discussed herein.

(69) In the first, second, and/or fourth states of operation (e.g., FIGS. 2A, 2B, and 2D) the third power switch **118** can be on (e.g., while the second power switch **116** is off), which can enable current to flow from the voltage source **148** to the second bootstrap capacitor **142**, and from the bootstrap capacitor **142**, through the third power switch **118**, to ground **124**, which can charge the bootstrap capacitor **142**. When the third power switch **118** is on, the SW2 node can go to a voltage near ground, so that the second bootstrap capacitor C2 **142** has about V.sub.cc on one side and about ground on the other, which can cause the second bootstrap capacitor **142** to charge up. The second bootstrap capacitor **142** can be charged to about a voltage V.sub.cc, such as from the voltage source **148**. In some embodiments, a small voltage drop can be created by the diode between the voltage source **148** and the second bootstrap capacitor **142**, so that the charged capacitor **142** has a voltage slightly less than, but still about the level of, the Voltage V.sub.cc, from the voltage source **148**. In some embodiments, a switch (e.g., transistor) can be used in place of the diode, as discussed, to reduce or avoid the small voltage drop. In some embodiments, the second bootstrap capacitor **142** can be charged substantially to saturation, although in some embodiments, a capacitor **142** could be selected that would be charged only partially and have enough stored energy so that during the discharge phase the second power switch **116** can be on for the appropriate time, such during the third state of operation (e.g., FIG. 2C). The power converter can be in the state to charge the second bootstrap capacitor **142** during part or all of the time that the second power switch **116** is off (e.g., non-conductive or open), such as during at least a portion of the first state of operation (e.g., FIG. 2A), the second state of operation (e.g., FIG. 2B), and the fourth state of operation (e.g., FIG. 2D), which can facilitate providing enough time to sufficiently charge the second bootstrap capacitor **142**.

(70) In the third state of operation (e.g., FIG. 2C), the third power switch **118** can be off (e.g., non-conductive), which can disconnect the second bootstrap capacitor **142** from the ground connection **124**, and the second power switch **116** can be on (e.g., conductive), which can provide a voltage through the second power switch **116** to the second bootstrap capacitor **142**, which can step up the voltage and deliver the increased voltage to the amplifier **132**, which can apply the increased voltage to the gate of the second power switch **116**, to keep the second power switch **116** on. By way of example, the capacitor **122** can be charged in the first state of operation (e.g., FIG. 2A), such as to a voltage differential of about $\frac{1}{2}V_{sub.in}$ applied across the capacitor **122**, although other voltage values are possible. In the first state of operation (e.g., FIG. 2A), the voltage on the first side of the capacitor **122** can be about V.sub.in and the voltage on the second side of the capacitor **122** (e.g., at CS1 and/or SW1) can be about $\frac{1}{2}V_{sub.in}$. The capacitor **122** can discharge in the third state of operation (e.g., FIG. 2C) and apply a voltage, such as of about $\frac{1}{2}V_{sub.in}$, through the second power switch **116** to the second bootstrap capacitor **142**, which can discharge to elevate the voltage, such as by about V.sub.cc, so that an elevated voltage, such as about $\frac{1}{2}V_{sub.in} + V_{sub.cc}$,

is delivered to the amplifier **132**, such as to the positive voltage supply thereof. The amplifier **132** for driving the second power switch **116** can have a positive or high voltage supply coupled to the voltage source **148** and to the second bootstrap capacitor **142**. The amplifier **132** for driving the second power switch **116** can have a negative or low voltage supply coupled to the source of the second power switch **116**. The diode between the second bootstrap capacitor **142** and the voltage source **148** (or, alternatively, an open or off switch) can prevent current from flowing from the second bootstrap capacitor **142** to the voltage source **148** in this state, especially since the elevated voltage (e.g., about $\frac{1}{2}V_{\text{sub.in}}+V_{\text{sub.cc}}$) can be higher than the voltage $V_{\text{sub.cc}}$ at the voltage source **148**.

(71) The amplifier **132** can be configured to provide the elevated voltage (e.g., about $\frac{1}{2}V_{\text{sub.in}}+V_{\text{sub.cc}}$) to the gate of the second power switch **116** (e.g., when the HDrv2 signal is high or on). The amplifier **132** for driving the second power switch **116** can have a high voltage supply coupled to the voltage source **148** and to the second bootstrap capacitor **142**. The amplifier **132** for driving the second power switch **116** can have a low voltage supply coupled to the source of the second power switch **116**. By way of example, when the second power switch **116** is on, the source of the second power switch can have a voltage of about $\frac{1}{2}V_{\text{sub.in}}$ (e.g., applied by the capacitor **122**), and the voltage at the gate of about $\frac{1}{2}V_{\text{sub.in}}+V_{\text{sub.cc}}$ can be sufficiently higher than the voltage at the source to cause the second power switch **116** to remain on (e.g., conductive). The voltage applied to the gate can be larger than the source voltage by about the amount of voltage increase provided by the second bootstrap capacitor **142**. In some cases, the voltage increase can drop over time as the capacitor **142** discharges, and the capacitor **142** can be selected to have enough capacity to keep the elevated voltage sufficiently high for the desired time (e.g., during the third state of operation while the second power switch **116** is on).

(72) Additional Example Bootstrap Circuits and Control

(73) FIGS. **6** and **7** are schematic drawings that show additional embodiments of bootstrap circuits that can be used for the power converter **100**. FIG. **8** shows voltage levels for various nodes and locations at various times during steady state operation. The power converter **100** can include a first bootstrap capacitor **140**, which can be used to provide a voltage increase that can keep the first power switch **114** on, as discussed herein. The first bootstrap capacitor **140** can be coupled to the source of the first power switch **114** (e.g., all the time, as opposed to other embodiments disclosed herein where the capacitor **140** can be selectively coupled and selectively detached from the source of the first power switch **114**). The first bootstrap capacitor **140** can be coupled to the gate of the first power switch **114**, so that the capacitor **140** can increase voltage provided to the gate when the first power switch **114** is to be in the on state. For example, a first side of the capacitor **140** can be coupled to an amplifier **130** (e.g., through the BST1 node or connection), such as to a positive (or high) voltage supply of an operational amplifier **130**. A second side of the capacitor **140** can be coupled to the source of the first power switch **114**.

(74) The power converter **100** can include a second bootstrap capacitor **142**, which can be used to provide a voltage increase that can keep the second power switch **116** on, as discussed herein. The second bootstrap capacitor **142** can be coupled to the source of the second power switch **116**. The second bootstrap capacitor **142** can be coupled to the gate of the second power switch **116**, so that the capacitor **142** can increase voltage provided to the gate when the second power switch **116** is to be in the on state. For example, a first side of the capacitor **142** can be coupled to an amplifier **132** (e.g., through the BST2 node or connection), such as to a positive voltage supply of an operational amplifier **132**. A second side of the capacitor **142** can be coupled to the source of the second power switch **116**. A voltage source **148** can be coupled to the capacitor **142** (e.g., to the first side thereof). A diode can be positioned to permit current to flow from the voltage source **148** to the capacitor **142** and/or to the amplifier **130**, and to impede current from flowing the other direction to the voltage source **148**. The diode can be replaced by a switch, as discussed herein. The second bootstrap capacitor **142** and associated circuitry can operate similar to the corresponding

components of the embodiments discussed in connection with FIGS. 3 and 4A-B. When the third power switch **118** is on, the capacitor **142** can be charged (e.g., to $V_{sub.cc}$) by current along a path from the voltage source **148**, to the capacitor **142**, through the third power switch **118**, and to ground **124**. When the second power switch **116** is on and the third power switch **118** is off, a voltage (e.g., $\frac{1}{2}V_{sub.in}$) can be applied from the capacitor **122**, through the second power switch **116**, to the capacitor **142**, which can increase the voltage (e.g., to $\frac{1}{2}V_{sub.in} + V_{sub.cc}$), and the increased voltage can be delivered to the amplifier **132** (e.g., through the BST2 node or connection) so that the amplifier **132** can apply the increased voltage to the gate of the second power switch **116** to keep the second power switch **116** on, as discussed herein.

(75) In some embodiments, the second bootstrap capacitor **142** can charge the first bootstrap capacitor **140**. For example, when in the third state of operation (e.g., FIG. 2C) the first bootstrap capacitor **140** can be coupled to the second bootstrap capacitor **142** so that the second bootstrap capacitor **142** charges the first bootstrap capacitor **140**. When the second power switch **116** is on, current can flow between the CS1 node or location and the SW2 node or location, e.g., via the second power switch **116**. Then in the first state of operation (e.g., FIG. 2A), the first bootstrap capacitor **140** can discharge to increase the voltage applied to the amplifier **130** so that the voltage delivered to the gate of the first power switch **114** is high enough to keep the first power switch on.

(76) With reference to FIGS. 7 and 8, for example, the second bootstrap capacitor **142** (e.g., the first side thereof) can be coupled to the first bootstrap capacitor **140** (e.g., to the first side thereof). In some embodiments, a diode can permit current to flow from the second bootstrap capacitor **142** to the first bootstrap capacitor, and the diode can impede current flow in the other direction from the first bootstrap capacitor **140** to the second bootstrap capacitor **142**. In some embodiments, the diode can be omitted. In some embodiments, a switch can be used instead of the diode, and the switch can be driven to be on when the first bootstrap capacitor **140** is to be charged (e.g., in the third state of operation, or when the second power switch **116** is on), and can be driven to be off when the first bootstrap capacitor **140** is to be discharged (e.g., in the first state of operation, or when the first power switch **114** is on). The drive signals HDrv1 and/or HDrv2 or some combination thereof can be used to control the switch in place of the diode between the capacitors **140** and **142**.

(77) In the third state of operation (e.g., FIG. 2C), the HDrv2 drive signal can be high and the second power switch **116** can be on. The voltage at the CS1 location and the SW2 location can be substantially equal (e.g., about $\frac{1}{2}V_{sub.in}$). That voltage can be provided to the second bootstrap capacitor **142** (e.g., through the second power switch **116**), and the capacitor **142** can increase the voltage (e.g., to about $\frac{1}{2}V_{sub.in} + V_{sub.cc}$), as discussed herein. The increased voltage can be used to keep the second power switch **116** on, as discussed herein, and the increased voltage can also be delivered to the first bootstrap capacitor **140** (e.g., to the first side thereof), to thereby charge the capacitor **140**. By way of example, the voltage on the first side of the capacitor **140** can be about $\frac{1}{2}V_{sub.in} + V_{sub.cc}$, and the voltage on the second side of the capacitor **140** can be about $\frac{1}{2}V_{sub.in}$ (e.g., provided from the capacitor **122**, such as through CS1), and the capacitor **140** can be charged to a voltage of about $V_{sub.cc}$. Thus, the second bootstrap capacitor **142** can be used to charge the first bootstrap capacitor **140**, such as during the third state of operation (e.g., FIG. 2C).

(78) Then, the first bootstrap capacitor **140** can be used to provide an elevated voltage for keeping the first power switch **114** on, such as during the first state of operation (e.g., FIG. 2A). When the first power switch **114** is on, the voltage from the input **102** (e.g., about $V_{sub.in}$) can be provided through the first power switch **114** to the source of the first power switch **114**, as well as to the first bootstrap capacitor **140** (e.g., second side thereof), and also to CS1 in some cases. The first bootstrap capacitor **140** can increase the voltage (e.g., to about $V_{sub.in} + V_{sub.cc}$), which can be provided to the amplifier **130** (e.g., through BST1). The increased voltage can be delivered to the gate of the first power switch **114**, and can be sufficiently higher than the voltage at the source (e.g., by about $V_{sub.cc}$) so that the first power switch **114** stays on.

(79) With reference to FIG. 8, the voltage for the drive signal HDrv1 can be high for the first state of operation (e.g., to turn on the first power switch **114**) and low for the second, third, and fourth states of operation (e.g., to turn off the first power switch **114**). The voltage for the drive signal HDrv2 can be high for the third state of operation (e.g., to turn on the second power switch **116**) and low for the first, second, and fourth states of operation (e.g., to turn off the second power switch **116**). The voltage at BST1 can increase (e.g., to about $V_{sub.in} + V_{sub.cc}$) at the first state of operation. As discussed herein, the first bootstrap capacitor **140** can increase the voltage at BST1. The elevated voltage at BST1 can decrease over the course of the first state of operation, as the first bootstrap capacitor **140** partially discharges. At the second state of operation, the voltage at BST1 can drop. The voltage applied to the second side of the capacitor **140** can drop from about $V_{sub.in}$ (e.g., applied from the input **102** through the first power switch **114**) to about $\frac{1}{2}V_{sub.in}$ (e.g., applied from the capacitor **122**) due to the transition from the first state of operation to the second state of operation. During the second state of operation, the voltage of BST1 can be about $\frac{1}{2}V_{sub.in} + V_{sub.cc}$ minus the amount that capacitor **140** was discharged. During the third state of operation, the capacitor **140** can be charged up, such as to about $\frac{1}{2}V_{sub.in} + V_{sub.cc}$. During the third operational state, the capacitor **140** can recover the amount of charge that it lost during the first operational state. As discussed herein, the second bootstrap capacitor **142** can be used to charge up the first bootstrap capacitor **140**, such as during the third state of operation. During the fourth state of operation, the voltage at BST1 can be about $\frac{1}{2}V_{sub.in} + V_{sub.cc}$.

(80) The voltage at BST2 can be stable (e.g., about $V_{sub.cc}$) during the first and second states of operation. BST2 can be coupled to the voltage source **148** that provides a voltage (e.g., of $V_{sub.cc}$). At the third state of operation, the voltage at BST2 can increase (e.g., to about $\frac{1}{2}V_{sub.in} + V_{sub.cc}$). As discussed herein, the second bootstrap capacitor **142** can be used to provide an elevated voltage, such as during the third state of operation. The elevated voltage at BST2 can decrease over the course of the third state of operation, as the second bootstrap capacitor **142** partially discharges. At the fourth state of operation, the voltage at BST2 can decrease (e.g., to about $V_{sub.cc}$). The voltage applied to the second side of the capacitor **142** can change from about $\frac{1}{2}V_{sub.in}$ (e.g., applied from the capacitor **122** through the second power switch **116**) to ground (e.g., applied through the third power switch **118**) as a result of the transition from the third state of operation to the fourth state of operation.

(81) The voltage at the location or node CS1 can increase (e.g., to about $V_{sub.in}$) during the first state of operation. Voltage $V_{sub.in}$ can be applied from the input **102**, through the first power switch **114**, to the location CS1 during the first state of operation. The voltage at CS1 can decrease (e.g., to about $\frac{1}{2}V_{sub.in}$) at the second state of operation. The voltage at CS1 can be about $\frac{1}{2}V_{sub.in}$ during the third and fourth states of operation.

(82) The voltage at the location or node SW2 can be ground during the first, second, and fourth states of operation. When the third power switch **118** is on, the SW2 location can be coupled to ground. During the third state of operation, the third power switch **118** can be off, and SW2 can be coupled to the capacitor **122** through the second power switch **116**. During the third state of operation, the voltage at SW2 can increase $\frac{1}{2}V_{sub.in}$. In the third state of operation the voltages at SW2 and CS1 can be the same (e.g., coupled through the second power switch **116**). When the second power switch **116** turns off and the third power switch turns on, at the fourth operational state, the voltage at SW2 can return to ground.

(83) The voltage at the location SW1 (e.g., which can also be the voltage at CS2) can be ground during the second, third, and fourth states of operation. When the fourth power switch **120** is on, the SW1 and/or CS2 locations can be coupled to ground. During the first state of operation, the fourth power switch **120** can be off, and SW1 and/or CS2 can be increase (e.g., to about $\frac{1}{2}V_{sub.in}$). In the third state of operation the voltages at SW2 and CS1 can be the same (e.g., coupled through the second power switch **116**). When the fourth power switch **120** turns on again, e.g., at the second operational state, the voltage at SW1 and/or CS2 can return to ground.

(84) The capacitor **122** can be between **CS1** and **CS2**. During the first state of operation, the voltage between **CS1** and **CS2** can be about $V_{sub.in} - \frac{1}{2}V_{sub.in}$, which equals about $\frac{1}{2}V_{sub.in}$. During the second, third, and fourth states of operation, the voltage between **CS1** and **CS2** can be about $\frac{1}{2}V_{sub.in} - \text{ground}$, which equals about $\frac{1}{2}V_{sub.in}$. Accordingly, the voltage across the capacitor **122** can be about $\frac{1}{2}V_{sub.in}$ during steady state operation of the power converter **100**. In some cases, the capacitor **122** can be partially discharged during the third state of operation, and can be charged during the first state of operation.

(85) FIG. **8** shows a voltage difference between **BST1** (e.g., which can be the voltage applied through the amplifier **130** to the gate of the first power switch **114** when the drive signal **HDrv1** is high) and **CS1** (e.g., which can be the voltage at the source of the first power switch **114**). The voltage difference between **BST1** and **CS1** can be about $V_{sub.cc}$. During the first state of operation, the voltage difference between **BST1** and **CS1** can decrease as the capacitor **140** is partially discharged. During the third state of operation, the voltage difference between **BST1** and **CS1** can increase as the capacitor **140** is recharged. The voltage difference between **BST1** (e.g., applied to the gate of power switch **114**) and **CS1** (e.g., at the source of the power switch **114**) can be sufficiently high to keep the power switch **114** on.

(86) FIG. **8** shows a voltage difference between **BST2** (e.g., which can be the voltage applied through the amplifier **132** to the gate of the second power switch **116** when the drive signal **HDrv2** is high) and **SW2** (e.g., which can be the voltage at the source of the second power switch **116**). The voltage difference between **BST2** and **SW2** can be about $V_{sub.cc}$. During the third state of operation, the voltage difference between **BST2** and **SW2** can decrease as the capacitor **142** is partially discharged. During the fourth state of operation, the voltage difference between **BST2** and **SW2** can increase as the capacitor **142** is recharged. The voltage difference between **BST2** (e.g., applied to the gate of power switch **116**) and **SW2** (e.g., at the source of the power switch **116**) can be sufficiently high to keep the power switch **116** on.

(87) The second bootstrap capacitor **142** can provide an elevated voltage for keeping the second power switch **116** on and to also charge the first bootstrap capacitor **140** at the same time. The second bootstrap capacitor **142** can be partially discharged by both of these functions. In some configurations, the second bootstrap capacitor **142** can be selected to have a larger capacitance than the first bootstrap capacitor **140**, such as by about 20%, about 30%, about 40%, about 50%, about 60%, about 70%, about 80%, about 90%, about 100%, about 120%, about 150%, about 200%, or more, or any values or ranges therebetween, although other values could be used. The second bootstrap capacitor **142** can have sufficient capacity to replace the charge lost by the first bootstrap capacitor **140** (e.g., while keeping the first power switch **114** on) and provide charge to keep the second power switch **116** on, at the same time.

(88) As discussed herein, in some embodiments, the integrated circuit **126** can include terminals for providing signals to or from one or both of the bootstrap capacitors **140**, **142** (e.g., similar to how the external capacitor **122** can be coupled to the circuitry of the integrated circuit via the terminals **CS1** and **CS2**). For example, the first bootstrap capacitor **140** can be coupled between the **BST1** and **CS1** terminals. The second bootstrap capacitor **142** can be coupled between the **BST2** and **SW2** terminals. The first bootstrap capacitor **140** and/or the second bootstrap capacitor **142** can be external to the integrated circuit **126**, which can enable the use of bootstrap capacitors **140** and/or **142** that have sufficient capacitance and/or size to hold the associated power switches **114** and/or **116** on, as discussed herein.

(89) Internal Bootstrap Capacitor Embodiments

(90) In some embodiments, the power converter **100** can include a bootstrap circuit inside the integrated circuit (IC), which can also include the first power switch **114**, the second power switch **116**, the third power switch **118**, the fourth power switch **120**. In some embodiments, the IC can also include the driver controller **128**, the amplifiers **130**, **132**, **134**, and **136**, the PWM pulse generator **138**, or any combinations thereof, and other components of the power converter **100**, as

discussed herein. The one or more bootstrap capacitors **140** and/or **142** can be made from the same silicon and can reside on the same silicon chip as the corresponding power switches **114** and/or **116**, or other semiconductor chip, or other components discussed herein. For example, an integrated circuit **126** similar to FIG. **3** can include one or more bootstrap capacitors **140**, **142**. In some implementations, because space is limited in the IC, the one or more bootstrap capacitors **140**, **142** that are internal to the IC would need to be sufficiently small to fit into the IC, which can limit the amount of capacitance for the internal bootstrap capacitor(s) **140**, **142**.

(91) In some cases, the internal bootstrap capacitor(s) **140** and/or **142** does not store enough energy to maintain the elevated voltage for the full time that the corresponding power switch(es) **114** and/or **116** are on. The bootstrap capacitor **140** or **142** can be used to provide an elevated voltage to turn on the corresponding power switch **114** or **116**, and the bootstrap capacitor **140** or **142** can then be disconnected from the power switch **114** or **116**. The capacitance that is internal to the power switch **114** or **116** can maintain the power switch **114** or **116** in the on (e.g., conductive) state for the remainder of the time appropriate for the state of operation.

(92) With reference to FIG. **9**, the power switch **114** can be a FET (e.g., an N-channel MOSFET) that has an internal capacitance, such as an internal gate capacitance. Although the first power switch **114** is shown in FIG. **9**, the second power switch **116** can be similar and can have an internal gate capacitance. The power switch **114** can have a gate portion **164** that is separated from a body portion **166** by an insulating (e.g., dielectric) layer **168**, which can form a gate capacitor **170**. The power switch **114** can also have a drain portion **172** and a source portion **174**. In some cases, the gate capacitance can be between the gate portion **164** and the source portion **174**. By way of example, when a voltage is applied to the gate portion **164** of the power switch **114**, the internal gate capacitor **170** can first charge up, and then after the gate capacitor **170** is charged, the gate voltage can increase. Then, when the gate voltage increases to a threshold amount (e.g., relative to the source voltage at the source portion **174**), the power switch **114** can turn on (e.g., to provide conductivity between the drain portion **172** and the source portion **174**). Accordingly, the actual activation of the power switch **114** can be delayed slightly from the time that the elevated voltage is applied to the gate, while the internal gate capacitor **170** of the switch **114** charges.

(93) As discussed herein, a bootstrap capacitor **140** can be used to apply an elevated first voltage **V1** to the gate portion **164** of the power switch **114**. The elevated voltage **V1** can be applied for sufficient time for the gate capacitor **170** to be charged to the level of the elevated voltage **V1** (e.g., substantially to saturation). The gate voltage can increase to a threshold level above the source voltage (e.g., to the elevated first voltage **V1**), and the power switch **114** can turn on, which can enable a second voltage **V2** to pass through the power switch **114** from the drain portion **172** to the source portion **174**. The source portion **174** can then have a voltage level of the second voltage **V2**. The elevated first voltage **V1** can be sufficiently higher than the second voltage **V2** (e.g., due to the bootstrap capacitor **140**, in some embodiments) so that the power switch **114** can be in the on (e.g., conductive) state. The gate portion **164** can then be disconnected from the elevated first voltage **V1**. For a time, the charge stored on the gate capacitor **170** can keep the gate voltage elevated above the first voltage **V1** sufficiently to keep the power switch **114** on. The amount of time that the gate capacitor **170** can keep the power switch **114** on can depend on the amount of charge stored on the gate capacitor **170** (e.g., its capacitance and the level of the elevated first voltage **V1**), and the rate at which the charge on the gate capacitor **170** is dissipated after being disconnected from the first voltage **V1**. The power converter **100** (e.g., the integrated circuit **126** thereof) can be configured so that the gate capacitor **170** of the power switch **114** can keep the power switch **114** on for long enough to satisfy the duration of the first state of operation (e.g., FIG. **2A**). For example, when disconnected from the elevated first voltage **V1**, the gate portion **164** can be coupled to a lower voltage through a resistor with enough resistance to produce a low enough discharge current from the gate capacitor **170**, that the gate capacitor **170** can retain enough charge for long enough to keep the power switch **114** on during the first state of operation (e.g., FIG. **2A**). When it is time to turn

off the power switch **114** (e.g., when transitioning to the second state of operation of FIG. 2B), the gate capacitor **170** can be discharged, such as by coupling the gate portion **164** to a lower voltage or ground. The power switch **116** can operate similarly, such as during the third state of operation (e.g., FIG. 2C).

(94) FIG. **10** shows an example embodiment of a circuit for controlling or driving the first power switch **114**, and the second power switch **116** can also be controlled or driven similarly. For example, the circuit of FIG. **10** can be the corresponding amplifier **130** that is discussed herein. The amplifier **130** can be an operational amplifier. The circuit can receive an input **176**, which can be a drive signal (e.g., HDrv1), such as from a driver controller **128**. The circuit can have output **178** for sending a signal to control the power switch **114** (Q1), such as to the gate of the switch **114**. The circuit can include a positive or high voltage supply **180**, which can be coupled to a bootstrap supply voltage node (BST) (e.g., BST1). The circuit can include a negative or low voltage supply **182**, which in some cases can be coupled to a switching node (SW) (e.g., CS1, SW1, or SW2). A bootstrap capacitor **140** can be coupled between the positive or high voltage supply **180** (e.g., BST) and the negative or low voltage supply **182** (e.g., SW). The bootstrap capacitor **140** can be an integrated part of the amplifier **130**, or in some cases, the bootstrap capacitor **140** can be external to the amplifier **130**, but still coupled between the high and low voltage supplies **180** and **182**. The bootstrap capacitor **140** can be part of the same IC as the amplifier **130**, or in some cases could be an external bootstrap capacitor **140**.

(95) The circuit can include a pull-up switch **186**, which can be coupled between the positive or high voltage supply **180** (e.g., BST) and the output **178**, and a pull-down switch **188**, which can be coupled between the negative or low voltage supply **182** (e.g., SW) and the output **178**. When the pull-up switch **186** is on (e.g., and the pull-down switch **188** is off), the output **178** can be coupled to the positive or high voltage supply **180** (e.g., BST), which can send a high output signal via the output **178** to the power switch **114**. When the pull-down switch **188** is on (e.g., and the pull-up switch **186** is off), the output **178** can be coupled to the negative or low voltage supply **182** (e.g., SW), which can send a low output signal via the output **178** to the power switch **114**. Turning on the pull-up switch **186** can turn on the power switch **114**, and turning on the pull-down switch **188** can turn off the power switch **114**. In some embodiments, the pull-up switch **186** and/or the pull-down switch **188** can be MOSFETs, or other FETs, or any other suitable type of transistor or other switch type. By way of example, the pull-up switch **186** can be a P-channel MOSFET, and the pull-down switch **188** can be an N-channel MOSFET, although other configurations and switch types can be used. For example, the pull-up switch **186** can be an N-channel MOSFET, and the pull-down switch **188** can be a P-channel MOSFET, for example, different (e.g., inverted) drive signals are provided to the switches **186**, **188**. The pull-up switch **186** and the pull-down switch **188** can be the same type of switch, and the drive circuitry can be configured to provide appropriate drive signals to operate the switches **186** and **188** as disclosed herein.

(96) In some embodiments, the circuit can include a level shifter **190**, a pull-up drive signal generator **192**, an amplifier **194**, a pull-down drive signal generator **196**, and an amplifier **198**. The level shifter **190** can be used to modify the signal provided at the input **176** (e.g., HDrv1), such as by shifting the level of the voltage signals, although in some configurations the level shifter **190** can be omitted or used differently. For example, the level shifter **190** can adjust the input signals so that they are appropriate for the pull-up drive signal generator **192**, amplifier **194**, pull-down drive signal generator **196**, and/or amplifier **198**. The pull-up drive signal generator **192** can receive the input signals, such as from the input **176** or the level shifter **190**, and the pull-up drive signal generator **192** can output a signal for controlling the pull-up switch **186**. The amplifier **194** can amplify the signal from the pull-up drive signal generator **192** (e.g., which can be a logic signal) so that it has sufficient voltage for operating the pull-up switch **186**. The pull-down drive signal generator **196** can receive the input signals, such as from the input **176** or the level shifter **190**, and the pull-down drive signal generator **196** can output a signal for controlling the pull-down switch

188. The amplifier **198** can amplify the signal from the pull-down drive signal generator **196** (e.g., which can be a logic signal) so that it has sufficient voltage for operating the pull-down switch **188**. The amplifiers **194** and **198** can be operational amplifiers. An inverter can be used (e.g., in connection with the amplifier **194**), which can cause different signals to be provided to the pull-up switch **186** and the pull-down switch **188**. Many variations are possible. For example, the amplifier **198** can include the inverter instead of the amplifier **194**, or neither or both of the amplifiers **194** and **198** can include inverters, for example depending on the types of switches **186** and **188** used and the operation of the drive signal generators **192** and **196**. Various components can be rearranged, or in some cases omitted. The drive signal generators **192** and **196** can output sufficient voltage to operate the corresponding switches **186** and **188**. The signals could be amplified (e.g., by amplifiers **194** and **198**, or a common amplifier) before being delivered to the drive signal generators **192** and **196**.

(97) The pull-up switch **186** can have its well isolated and connected to a well switch **184**. The well switch **184** can include a first switch **185** and a second switch **187**, which can be MOSFETs, or other FETs, or any other suitable type of transistor or other switch type. By way of example, the switches **185** and **187** can be a P-channel FETs (e.g., MOSFETs). The drain of the first switch **185** can be coupled to the high voltage supply **180** (e.g., the BST signal), the source of the first switch **185** can be coupled to the well of the pull-up switch **186**, and the gate of the first switch **185** can be coupled to the output signal **178**. The drain of the second switch **187** can be coupled to the output signal **178**, the source of the second switch **187** can be coupled to the well of the pull-up switch **186**, and the gate of the second switch **187** can be coupled to the high voltage supply **180** (e.g., the BST signal). The first and second switches **185**, **187** can select the higher voltage signal between the high voltage supply **180** (e.g., the BST signal) and the output signal **178**, and can supply the higher voltage signal to the well of the pull-up switch **186**. The well switch **184** can bias the well of the switch **186** to the higher of the two voltage signals **178** and **180**. This configuration can impede the gate capacitance of switch **114** from unintentionally discharging. If the well and source of switch **186** were shorted and the well switch **184** were omitted, then even when the switch **186** is off, the body diode formed by the source and well of the switch **186** could let the voltage held on the gate capacitance of power device **114** discharge.

(98) FIG. **11** shows signals associated with example embodiments of a pull-up drive signal generator **192** and a pull-down drive signal generator **196**, such as for controlling a first power switch **114**. The drive signal (e.g., HDrv1) can be a high signal **200** at the first state of operation, and low for the second, third, and fourth states of operation. The pull-up drive signal generator **192** can produce a low output signal in response to a low input signal (e.g., low HDrv1). In the embodiment of FIG. **11**, the pull-up drive signal generator **192** can produce a pulse **202** of a high signal in response to the transition from a low input signal to a high input signal (e.g., the rising edge of HDrv1). The high output pulse **202** from the pull-up drive signal generator can turn on the pull-up switch **186**. Rather than keep the pull-up switch **186** on during the full time of the high drive signal HDrv1 **200** (as can be done in some other embodiments described herein, such as those having larger external bootstrap capacitor(s)), in the embodiment of FIG. **11**, the pull-up drive signal generator **192** can complete the high signal pulse **202** and drop the output to a low signal while the drive signal HDrv1 is still high. The high signal pulse **202** can last for a sufficient time to charge the associated power switch **114**, **116** (Q1 or Q2) to the appropriate level.

(99) The pull-down drive signal generator **196** can produce a low signal while the drive signal HDrv1 is high (e.g., during the first state of operation). When the drive signal (e.g., HDrv1) transitions from the high signal **200** to a low signal (e.g., for the transition from the first state of operation to the second state of operation), the pull-down drive signal generator **196** can produce a high output signal pulse **204**, which can turn on the pull-down switch **188**. Rather than keep the pull-down switch **186** on during the full time that the drive signal HDrv1 is low (which could be done in some embodiments), in the embodiment of FIG. **11**, the pull-down drive signal generator

196 can complete the high signal pulse **204** and drop the output to a low signal while the drive signal HDrv1 is still low. In some cases, the high output pulse **204** from the pull-down drive signal generator **196** can be similar to the high output pulse **202** from the pull-up drive signal generator **192**, except that it occurs at a different time and location. Many variations are possible. The high and low signals could be inverted depending on the types of switches or other components used. In some implementations, the pull-down drive signal can be held high for a longer time (e.g., for the full second state of operation, or for the full time that the HDrv1 signal is low).

(100) The bootstrap capacitor **140** can be charged up before the drive signal (e.g., HDrv1) goes high (e.g., before the first state of operation at the far left side of FIG. **11**). The states can repeat, and the bootstrap capacitor **140** can be charged up in a previous fourth state of operation or other previous state. The bootstrap capacitor **140** can charge up when current flows from the BST node (e.g., at the high voltage supply **180**) to the bootstrap capacitor **140**, and from the bootstrap capacitor **140** to the SW node (e.g., the low voltage supply **182**). By way of example, the low voltage supply **182** (e.g., SW node) can be coupled to ground (or to some other relatively low voltage), and the high voltage supply **180** (e.g., BST) can be coupled to V.sub.cc (or some other relatively high voltage), which can cause the bootstrap capacitor **140** to charge up (e.g., to about V.sub.cc). The first side of the bootstrap capacitor **140** can be at a higher voltage (e.g., about V.sub.cc) can the second side of the bootstrap capacitor (e.g., about ground). The pull-up switch **186** can be off while the bootstrap capacitor **140** charges up. The pull-down switch **188** can be off while the bootstrap capacitor **140** charges up. In some situations, the pull-down switch **188** could be on while the bootstrap capacitor **140** charges up. The power switch **114** can be off (e.g., during the second, third, or forth states of operation discussed herein) when the bootstrap capacitor **140** charges up. The bootstrap capacitor **140** can be an internal component of the IC (e.g., of the amplifier **130**).

(101) When the drive signal (e.g., HDrv1) goes to a high signal **200**, the pull-up drive signal generator **192** can produce a high signal pulse **202** that can turn on the pull-up switch **186**. When the pull-up switch **186** is on, it can connect the high voltage supply (e.g., BST, which can have a voltage of about $\frac{1}{2}V_{sub.in} + V_{sub.cc}$ at this time) to the gate of the power switch **114**. Since the gate of the power switch **114** is higher than the source (which can be $\frac{1}{2}V_{sub.in}$ at this time), the power switch **114** can turn on. In some cases, the gate capacitor **170** can be charged to a first voltage (e.g., about $\frac{1}{2}V_{sub.in} + V_{sub.cc}$), such as when the power switch **114** turns on. When the power switch **114** is on, the bootstrap capacitor **140** can discharge to provide an elevated voltage to the gate of the power switch **114**. In some cases, the source of the power switch **114** can be coupled to the low voltage supply **182** (e.g., SW). When the power switch **114** is on, a voltage (e.g., about V.sub.in) can pass from the drain to the source. The second side of the bootstrap capacitor **140** can be provided with a voltage (e.g., about V.sub.in, such as from the source of the power switch **114**), which can cause the bootstrap capacitor **140** to discharge, thereby elevating the voltage (e.g., by about V.sub.cc since that was the voltage that the bootstrap capacitor was charged to). The elevated voltage (e.g., about V.sub.in + V.sub.cc) can be delivered through the pull-up switch **186** to the gate of the power switch **114**. The gate capacitor **170** of the power switch **114** can be charged to the elevated voltage level (e.g., about V.sub.in + V.sub.cc). In some cases, the gate voltage can be raised to the elevated voltage, which can keep the power switch **114** on for a time (e.g., since the elevated gate voltage of about V.sub.in + V.sub.cc is higher than the source voltage of about V.sub.in).

(102) Rather than keep the pull-up switch **186** on during the full time that the first power switch **114** is to be on (e.g., during the first state of operation), the high output pulse **202** provided to the pull-up switch **186** can end while the drive signal (e.g., HDrv1) is still a high signal **200**, as shown in FIG. **11**. When the high output pulse **202** ends, the lower signal provided to the pull-up switch **186** can turn off the pull-up switch **186**. During the time between the end of the pulse **202** and the end of the drive signal **200**, the pull-up switch **186** and the pull-down switch **188** can be off. The charge that was previously delivered to the gate of the power switch **114** (e.g., to charge up the gate

capacitor **170**) can be substantially isolated or held in the power switch **114** during this time. Since the power switch **114** is only intended to be on for a short amount of time, the charge stored on the gate capacitor **170** can be sufficient to keep the power switch **114** on for the intended time.

(103) Various elements of the power converter **100** can be configured to enable the internal gate capacitance to hold the power switch **114** on long enough (e.g., during the first state of operation). For example, the power switch **114** can be configured to have sufficient gate capacitance, the bootstrap capacitor **140** can have sufficient capacitance, and the elevated voltage can be sufficiently elevated (e.g., a high enough V_{sub} value), and/or the high output pulse **202** can be long enough to sufficiently charge the gate capacitor **170**, to enable the power switch **114** to remain on for sufficient time, as described herein. Various different values can be used for these components or features, depending on the particular configuration. In some cases, the gate of the power switch **114** can be initially charged to a voltage that is elevated (e.g., over the source voltage) by at least about 1 volt, about 1.5 volts, about 2 volts, about 2.5 volts, about 3 volts, about 3.5 volts, about 4 volts, about 4.5 volts, about 5 volts, about 5.5 volts, about 6 volts, about 6.5 volts, about 7 volts, or more, to have sufficient charge to keep the power switch **114** on (e.g., during the first state of operation), or any values or ranges therebetween, although other values could be used, such as depending various factors so that the voltage is high enough to turn on the power switch **114** to the desired strength for the desired period of time. The elevated gate voltage can drop over time after the pull-up switch **186** is turned off, but since the power switch **114** only stays on for a short time, the internal capacitance of the gate can be sufficient.

(104) When the drive signal HD_{rv1} transitions to a low signal, the pull-down drive signal generator **196** can produce a high signal (e.g., the high signal pulse **204** in FIG. **11**), which can turn on the pull-down switch **188**. The pull-down switch **188** can couple the gate of the power switch **114** to a relatively low voltage source, such as the low voltage supply **182** (e.g., SW). Some or all of the remaining charge on the gate of the power switch **114** can be discharged by a current through the pull-down switch **188**. Once, the gate voltage of the power switch **114** has dropped to within a threshold of the source voltage, the power switch **114** can turn off. In some cases, the gate capacitor **170** can be discharged to ground or to some voltage that is sufficiently low to turn off the power switch **114**.

(105) In some embodiments, the high signal pulse **204** for turning on the pull-down switch **188** can turn off after a short period of time. The pull-down switch **188** can be on for a sufficient amount of time to discharge the gate of the power switch **114** enough to turn off the power switch **114**, without fully discharging the gate capacitor **170**. Thus, the gate capacitor **170** can be more quickly charged up during the next time the pull-up switch **186** is on. In some embodiments, the pull down switch **188** can be pulsed on by the high signal pulse **204**. In other embodiments, the pull down switch **188** can be held on for a longer time. The pull down switch **188** can be on (e.g., pulsed or otherwise) for a sufficient amount of time for the gate charge to be depleted from the power switch **114** to a level that is low enough to completely turn off the power switch **114**. Once the power switch **114** is off, the bootstrap capacitor voltage may continue to deplete without adversely affecting operation. In some cases, the pull-down switch **188** can be held on for a longer time (e.g., for the full second state, or for the full second, third, and fourth states, or any time therebetween), which can discharge the gate capacitor **170** more completely. The duration of the pulses **202** and/or **204** can be determined by feedback. For example, when the pulse **202** is high and the pull-up switch **186** is on, the gate voltage is can increase, and the system can turn off the pulse **202** when the gate voltage is above a threshold voltage. When the pulse **204** is high and the pull-down switch **188** is on, the gate voltage can decrease, and the system can turn off the pulse **204** when the gate voltage is below a threshold voltage. For example, the pulse **202** can end (e.g., which can stop the discharging of the gate capacitor **170**) when the voltage of the output **178** equals the voltage at the source of the first power switch **114**. In some embodiments, the duration of the pulses **202** and/or **204** can be defined by a timer (e.g., set time durations).

(106) In some cases the pull-down switch **188** is not pulsed on. For example, the bootstrap capacitor voltage can be depleted, which can cause the waveform to appear as though it is being pulsed. In some embodiments, the bootstrap capacitor **140** would not become depleted, such as for some embodiments where the bootstrap capacitor **140** is charged during the second, third, and fourth states of operation (e.g., see FIG. 5). In some embodiments (e.g., FIG. 7), the bootstrap capacitor **140** is only charged during the third state of operation, and can become depleted. In some cases, there can be additional circuits or components that are powered using the bootstrap capacitor **140** (e.g., the level shifter). During both the first and second states, these circuits can discharge the bootstrap capacitor **140**. The bootstrap capacitor **140** can be selected to have sufficient charge to charge up the gate of the power switch **114** in the first state of operation, to provide additional charge to other circuits in the first state, and to discharge the gate of the power switch **114** in the second state. During the remainder of the second state, it can be acceptable for the bootstrap capacitor **140** to discharge as the gate of power switch **114** has already been discharged. The functionality can be similar but somewhat different for operation of second power switch **116**. For the second power switch **116**, as soon as the fourth state of operation is entered, the bootstrap capacitor **142** will be recharged, thus preventing any further discharging of the bootstrap capacitor **142**.

(107) When the power switch **114** is off, the bootstrap capacitor **140** can be recharged. For example, the low voltage supply **182** can be coupled to the source of the power switch **114**, and can be ground (or some other relatively low voltage) when the power switch **114** is off. The higher voltage (e.g., from BST) on the first side of the capacitor **140** and the lower voltage (e.g., from SW) on the second side of the capacitor **140** can cause the bootstrap capacitor **140** to charge up. Since the bootstrap capacitor **140** is used to charge up the internal gate capacitor **170** of the power switch **114**, a relatively low capacity bootstrap capacitor **140** can be used, and the bootstrap capacitor **140** can be small enough to be incorporated into the IC. In some cases, the bootstrap capacitor **140** can have sufficient capacitance that it holds its voltage enough that it does not need to be recharged after each time it charges up the gate capacitor **170** of the power switch **114**.

(108) Charging of the gate capacitor **170** of the first power switch **114** can be triggered by the rising edge of the drive signal (e.g., HDrv1). The bootstrap capacitor **140** can elevate the charge on the gate capacitor **170** so that the charge on the gate capacitor **170** can keep the power switch **114** on (e.g., during the remainder of the first state of operation). Discharging of the gate capacitor **170** of the first power switch **114** can be triggered by the falling edge of the drive signal (e.g., HDrv1). The bootstrap capacitor **170** can have relatively low capacity and small size, and can be incorporated into the IC, because in some cases it only has to charge up the gate capacitor **170** of the power switch **114**. This approach can work, in some cases because of the low parasitics in the system. In some cases, if an external bootstrap capacitor were used, it would need to have a larger capacitance (e.g., larger size) so that it could have more charge and overcome the higher parasitics associated with using the external capacitor. Using a bootstrap capacitor that is internal to the IC can yield lower parasitics, which can enable the use of a smaller capacitor, which can enable the capacitor to be integrated into the IC.

(109) Many variations are possible, for example, in some embodiments, the pull-up switch **186** can be held on during the time that the power switch **114** is to be on (e.g., during the first state of operation for the first power switch **114**), or the pull-down switch **188** could be held on during the time that the power switch **114** is to be off.

(110) In some embodiments, the second power switch **116** can be controlled in a manner similar to the first power switch **114**, for example as discussed in connection with FIGS. 9, 10, and 11. A circuit similar to FIG. 10 can be used to control the second power switch **116**. For controlling the first power switch **114**, the input can be HDrv1, the high voltage supply **180** can be BST1, the low voltage supply **182** can be CS1, the bootstrap capacitor can be capacitor **140**, and the output **178** can be coupled to the gate of the first power switch **114**. By comparison, for controlling the second

power switch **116**, the input **176** can be HDrv2, the high voltage supply **180** can be BST2, the low voltage supply **182** can be SW2, the bootstrap capacitor can be capacitor **142**, and the output **178** can be coupled to the gate of the second power switch **116**.

(111) FIG. **12** shows signals associated with example embodiments of a pull-up drive signal generator and a pull-down drive signal generator, such as for controlling a second power switch **116**. The drive signal (e.g., HDrv2) can be a high signal **206** at the third state of operation, and low for the first, second, and fourth states of operation. The pull-up drive signal generator **192** can produce a low output signal in response to a low input signal (e.g., low HDrv2). In the embodiment of FIG. **12**, the pull-up drive signal generator **192** can produce a pulse **208** of a high signal in response to the transition from a low input signal to a high input signal **206** (e.g., the rising edge of HDrv2). The high output pulse **208** from the pull-up drive signal generator can turn on the pull-up switch **186**. Rather than keep the pull-up switch **186** on during the full time of the high drive signal HDrv2 **206** (as can be done in some other embodiments), in the embodiment of FIG. **12**, the pull-up drive signal generator **192** can end the high signal pulse **208** and drop the output to a low signal while the drive signal HDrv2 is still high. The high signal pulse **208** can have durations similar to the discussion herein relating to the high signal pulse **208**, and can last for a percentage of the high drive signal HDrv2 similar to the discussion relating to the pulse **202**.

(112) The pull-down drive signal generator **196** can produce a low signal while the drive signal HDrv2 is high (e.g., during the third state of operation). When the drive signal (e.g., HDrv2) transitions from the high signal **208** to a low signal (e.g., for the transition from the third state of operation to the fourth state of operation), the pull-down drive signal generator **196** can produce a high output signal **210**, which can turn on the pull-down switch **188**. In the embodiment of FIG. **12**, the pull-down switch **188** can be held on (e.g., during the fourth state of operation). The high output signal **210** can last for the fourth state of operation. For example, the transition to the first state of operation can cause the high output signal **210** to end, and the pull-down switch **188** to turn off. The high output signal **210** can last for different amounts of times in other embodiments, such as for a short pulse similar to the pulse **204**, or for the full time that the second power switch is off (e.g., during the fourth, first, and second states of operation), or any amounts of time therebetween. In some embodiments, the bootstrap capacitor **142** can charge during the fourth state of operation, and will not deplete any further than it was at the end of the third state of operation. The second power switch **116** can be biased properly in the fourth state of operation because the switches **186** and **188** are biased properly.

(113) The bootstrap capacitor **142** can be charged while the second power switch **116** is off, and can be discharged to elevate the voltage provided to the gate of the power switch **116** to charge up the internal gate capacitor **170** of the second power switch **116**, similar to the discussion relating to FIGS. **9**, **10**, and **11**. The charge on the gate capacitor **170** of the second power switch **116** can keep the second power switch **116** on for a time (e.g., during the third state of operation), and the gate capacitor **170** can be discharged to turn the second power switch **116** off, similar to the discussion relating to FIGS. **9**, **10**, and **11**. Charging of the gate capacitor **170** of the second power switch **116** can be triggered by the rising edge of the drive signal (e.g., HDrv2). The charge on the gate capacitor **170** can keep the power switch **116** on (e.g., during the remainder of the third state of operation). Discharging of the gate capacitor **170** of the second power switch **116** can be triggered by the falling edge of the drive signal (e.g., HDrv2). The gate of the second power switch **116** can be held low (e.g., such as during the fourth state of operation or longer).

(114) In some cases, a shared bootstrap capacitor can be used for both the first and second power switches **114** and **116**, for example, since the first and second power switches **114** and **116** can be on at different times. The shared bootstrap capacitor can be used to turn on the first power switch **114** during a first state of operation (e.g., FIG. **2A**), can be used to turn on the second power switch **114** during a third state of operation (e.g., FIG. **2C**), and can be charged during one or both of the second and fourth states of operation (e.g., FIGS. **2B** and **2D**). A shared bootstrap capacitor could

be used with a suitable isolation approach and sufficient time in the second and fourth states to charge the shared bootstrap capacitor.

(115) Current Sensing

(116) In some embodiments, the power converter **100** can perform current sensing. In some embodiments, the power converter **100** can include a communication output that can be used to output information about the current through the power converter **100**. The power converter **100** can measure current on each channel and can report out the current information (e.g., when requested). The current reporting can be of either channel, or both channels individually, or the sum of both channels, or the average of both channels, or the total current through the power converter, or the output current from the power converter **100**. The channels can correspond to current associated with the two inductors **110** (e.g., first channel of current) and **112** (e.g., second channel of current).

(117) For the AC coupled power converters, the shape of the current can be different from some other power converters. FIG. **13** shows an example current shape for an embodiment of an AC coupled power converter (e.g., current through the fourth power switch **120**). FIG. **13** also shows signals for other components in the AC coupled power converter. In the AC coupled power converter of FIG. **13**, during the first state of operation, the first power switch **114** and the third power switch **118** can be on, and the current through power switch **120** will be about 0 amps because it is off. At the second state of operation, the third power switch **118** and the fourth power switch **120** can be on, and the current can jump to a first value and then decay over time. At the third state of operation, the second power switch **116** and the fourth power switch **120** can be on, which can cause the current to jump to a second, higher value and then increase over time to a third, even higher value. At the fourth state of operation, the third power switch **118** and the fourth power switch **120** can be on, which can cause the current to drop and then decay over time (e.g., at approximately the same pace or slope as during the second state of operation). Then the power converter **100** can return to the first state of operation, and the current can drop (e.g., to about zero amps).

(118) The currents in FIGS. **13** and **14** are not the inductor currents, and thus do not directly represent the output current. FIG. **13** shows the current through power switch **120**, while FIG. **14** shows the current through power switch **118**. The inductor currents (e.g., whose sum is the output current) are being sensed individually by monitoring the current through the third and fourth power switches **118** and **120**. Aside from the third state of operation, the current through power switch **120** can look like a non-AC coupled converter. There is no current sensed in the first state of operation, because power switch **120** is off. During the second and fourth state of operation, the sensed current is equal to the inductor current. During the third state of operation, however, due to the AC-coupled architecture, the current through the power switch **120** is the sum of both inductor **110** current and inductor **112** current. This is because power switch **120** is delivering both inductor **110** current, and is also delivering the current for inductor **112** via flying capacitor **122** and power switch **116**.

(119) In FIG. **13**, the signal labeled “csen” shows when current sensing is enabled, in some embodiments. For example, the current sensing can be enabled during the second state of operation and during the fourth state of operation, but not during the first state of operation or during the third state of operation. For example, current sensing can be enabled when the low drive signals LDrv1 and LDrv2 are both high, or when both of the third and fourth power switches **118** and **120** are on. The current sensing can be enabled after, such as a short time (e.g., about 1 ns to 10 ns, or about 5 ns, or any other suitable time) after, one of the low drive signals LDrv1 or LDrv2 goes high, and current sensing can be disabled before, such as a short time (e.g., about 1 ns to 10 ns, or about 5 ns, or about 2 ns, or any other suitable time) before, one of the low drive signals LDrv1 or LDrv2 goes low.

(120) FIG. **14**, by comparison, shows an example current shape for the current flowing through the

third power switch **118**. In FIG. **14**, the current can jump up to a first value, and then decay over time, and the current can then drop (e.g., to about zero amps), and the pattern can repeat. The current of the power converter in FIG. **14** does not jump a second time up to the second current value or increase to the third current value, as in FIG. **13**. For the AC-coupled architecture, the current through the power switch **118** can look similar to or the same as the current through a non-AC coupled power converter.

(121) FIG. **15** shows an example embodiment of a power converter **100** that is configured to perform current sensing. In some embodiments, the power converter **100** can use one or more current mirrors to determine the current through portions of the power converter **100**. The power converter can be similar to the power converter of FIG. **1**, or various other power converter **100** embodiments disclosed herein. The power converter **100** can include a first sensing circuit **212** for measuring current through the third power switch **118** (e.g., by using a current mirror to mirror the current through the third power switch **118**), and a second current sensing circuit **214** for measuring current through the fourth power switch **120** (e.g., by using a current mirror to mirror the current through the fourth power switch **120**). One or more components of a first current sensing circuit **212** can be coupled in parallel with the third power switch **118**. One or more components of the second current sensing circuit **214** can be coupled in parallel with the fourth power switch **120**. As shown in FIG. **16**, the first current sensing circuit **212** can include a first sensing MOSFET (or other switch type) **220** which can be configured to conduct current when the third power switch **118** conducts current, but at a smaller amount. The second current sensing circuit **214** can include a second sensing MOSFET (or other switch type) **222** which can be configured to conduct current when the fourth power switch **120** conducts current, but at a smaller amount. In some cases, a ratio of 740 to 1 can be used for the ratio between the current through the third or fourth power switch **118** or **120** and the mirrored current through the corresponding sensing switch **220** or **222**. Various other ratios could be used, such as about 100:1, about 200:1, about 300:1, about 400:1, about 450:1, about 500:1, about 550:1, about 600:1, about 650:1, about 700:1, about 750:1, about 800:1, about 850:1, about 900:1, about 950:1, about 1000:1, about 1100:1, about 1200:1, about 1300:1, or more, or any values or ranges therebetween, although other ratios could be used, depending on the design and capabilities of the power converter **100**. For example, ratios much higher than 1:1 can be used to reduce the solution footprint and power losses. However, high ratio values can negatively affect current sensing accuracy. Any suitable ratio can be used depending on the design and capabilities of the power converter.

(122) The power converter **100** can include current sensing processing circuitry **216**, which can process signals from one or both of the current sensing circuits **212** and/or **214** to determine a current (e.g., a current through the power converter **100**). The current sensing processing circuitry **216** can apply a gain to the signals from the current sensing circuits **212** and **214**, can invert the signals in some cases, and/or can combine (e.g., average) the signals. The power converter **100** can include an output **218** for outputting information regarding the determined current. The output **218** can use wired or wireless communication. In some cases the output **218** can use a Power Management Bus (PMBUS), and the communication interface can be configured to implement an inter-integrated circuit (I2C) protocol, in some implementations. Any suitable communication interface or output mechanism can be used to deliver the information regarding the current.

(123) FIG. **16** shows an example embodiment of a portion of a power converter **100** that includes current sensing circuitry, such as for the current sensing circuits **212** and **214** of FIG. **15**. As with some other embodiments, the third power switch **118** can be coupled between the node SW2 and ground, and the fourth power switch **120** can be coupled between the node SW1 and ground. The third power switch **118** can receive a drive signal (e.g., LDrv2), such as at a gate of the third power switch **118**, to control the third power switch **118**. The fourth power switch **120** can receive a drive signal (e.g., LDrv1), such as at a gate of the fourth power switch **120**, to control the fourth power switch **120**.

(124) A first sensing switch **220** (e.g., a sensing MOSFET) can be coupled in parallel with the third power switch **118**. A drain of the first sensing switch **220** can be coupled to the node SW2 and to the drain of the third power switch **118**. A source of the first sensing switch **220** can be coupled to ground and to the source of the third power switch **118**. A sensing resistor **224** can be coupled between the source of the first sensing switch **220** and ground. Current that flows through the sensing switch **220** can flow through the sensing resistor **224**, which can result in a voltage drop. Thus, voltage signal (e.g., SN2) at an output **226** of the current mirror **212** can provide a voltage value that is indicative of the current through the sensing switch **220**, which can be proportional to (and thus indicative of) the current through the third power switch **118**. The current mirror **212** can be used to determine the current through the third power switch **118** and to output a corresponding voltage value.

(125) A second sensing switch **222** (e.g., a sensing MOSFET) can be coupled in parallel with the fourth power switch **120**. A drain of the second sensing switch **222** can be coupled to the node SW1 and to the drain of the fourth power switch **120**. A source of the second sensing switch **222** can be coupled to ground and to the source of the fourth power switch **120**. A sensing resistor **228** can be coupled between the source of the second sensing switch **222** and ground. Current that flows through the second sensing switch **222** can flow through the sensing resistor **228**, which can result in a voltage drop. Thus voltage signal (e.g., SN1) at an output **230** of the current mirror **214** can provide a voltage value that is indicative of the current through the second sensing switch **222**, which can be proportional to (and thus indicative of) the current through the fourth power switch **120**. The current mirror **214** can be used to determine the current through the fourth power switch **120** and to output a corresponding voltage value.

(126) A current sensing enable signal **232** (e.g., csen) can be delivered to the gate of one or both of the first and second sensing switches **220** and **222**. The current sensing enable signal **232** can be on or high when LDrv1 and LDrv2 are both on or high, and the current sensing enable signal **232** can be off or low when either of LDrv1 and LDrv2 are off or low. Thus, the current sensing can be performed only when both of the third and fourth power switches **118** and **120** are on, in some embodiments. When the current sensing enable signal is on or high, the sensing switches **220** and **222** can be turned on, for example to enable mirrored current to flow through the sensing switches **220** and **222**.

(127) In some embodiments, the power converter **100** can apply a gain to the one or more signals from the current sensing circuits **212** and/or **214**, such as to the voltage signals SN2 and/or SN1. FIG. 17 shows an example embodiment of a circuit for applying gain to a voltage signal (e.g., SN2 or SN1), which can be indicative of current (e.g., through the third power switch **118** or the fourth power switch **120**). The power converter **100** can have a separate gain circuit for each of the current sensing circuits **212**, **214**. A first gain circuit (e.g., of FIG. 17 or 18) can operate on the voltage signal SN2 from the first current sensing circuit **212**, which can be indicative of current through the third power switch **118** (e.g., a second channel). A second gain circuit (e.g., of FIG. 17 or 18) can operate on the voltage signal SN1 from the second current mirror **214**, which can be indicative of current through the fourth power switch **120** (e.g., a first channel). In some cases, the voltage signals SN2 and/or SN1 can be negative values, and the gain circuit (e.g., of FIG. 17 or 18) can invert the voltage signals as well as applying the gain, to produce a gained up positive voltage value that is indicative of current in the power converter **100**.

(128) With reference to FIG. 17, an input voltage signal (e.g., SN2 or SN1) can be provided to an input **232** of the gain circuit. The input voltage signal **232** can be coupled through a first resistor R1 to a first terminal (e.g., a negative terminal) of a first amplifier **234**, which can be an operational amplifier. The gain circuit can include a bias voltage **236**, which can be coupled through a resistor R2 to a second terminal (e.g., a positive terminal) of the first amplifier **234**. The second terminal of the first amplifier **234** can also be coupled through a third resistor R3 to an additional input **237**. Input **237** can be a lower tap for resistor **224** or **228** (e.g., shown in FIG. 16), which in this case is

labeled as ground. The signal can be referenced to the power switch **118** ground and the power switch **120** ground, respectively. The output of the first amplifier **234** can be coupled through a fourth resistor to the first terminal of the first amplifier **234**. The amplifier **234** can be configured to apply a gain to the signal at the input **232** (e.g., a gain of 4, although other gain amounts can be used). The gain circuit of FIG. **17** can include a second amplifier **238**. The output of the first amplifier **234** can be coupled, through a fifth resistor **R5**, to a first terminal (e.g., a negative terminal) of the second amplifier **238**. The second terminal (e.g., a positive terminal) of the second amplifier **238** can be coupled to a node between the second resistor **R2** and the input **236** (e.g., a bias voltage). The output of the second amplifier **238** can be coupled, through a sixth resistor **R6**, to the to the first terminal of the second amplifier **238**. The output of the second amplifier **238** can be coupled, through the sixth resistor **R6** and the fifth resistor **R5**, to the output of the first amplifier **234**. The output of the second amplifier **238** can be coupled to an output **240**, which can output a positive voltage signal with the gain applied, for example. In some cases, the second amplifier **238** can apply a gain to the output of the first amplifier **234**. In some embodiments, the first amplifier **234** can apply a gain of 4 and the second amplifier **238** can apply a gain of 70, which yield a total gain of 280 for the gain circuit of FIG. **17**, although various other amounts of gain can be applied instead. In some embodiments, a capacitor **242** can be coupled, via a seventh resistor **R7**, to the output **240** and the output of the second amplifier **238**. The capacitor **242** can be a smoothening capacitor to smooth the output signal **240**. Filtering can be used, for example, to average the output over a time interval.

(129) In some embodiments, the power converter **100** can include combining or averaging circuitry. FIG. **18** shows an example embodiment of combining or averaging circuitry. The combining circuitry can receive two inputs, such as a first input **240a** (which can be a signal or processed signal from the first current sensing circuit **212**) and a second input **240b** (which can be a signal or processed signal from the second current sensing circuit **214**). The inputs **240a** and **240b** can be inverted and/or gained signals, such as received from corresponding gain circuits such as the circuit shown in FIG. **17**. The first input **240a** can be coupled to a second terminal (e.g., a positive terminal) of an amplifier **244**, through a first resistor **R1** and a second resistor **R2**. The second input **240b** can be coupled to the second terminal of the amplifier **244**, through a third resistor **R3** and the second resistor **R2**. A capacitor **248** can be coupled to a location between the second resistor **R2** and the second terminal of the amplifier **244**. The other end of capacitor **248** may go to ground, for example, or another voltage signal. This other voltage signal could be whatever voltage is desired for the output **246** to be with respect to, in an AC coupled sense. The output of the amplifier **244** can be coupled to the first terminal (e.g., a negative terminal) of the amplifier **244**. The output of the amplifier **244** can provide a combined output signal **246** that combines the signals **240a** and **240b**. The circuit of FIG. **18** can output an average of the first input **240a** and the second input **240b**.

(130) By way of example, the signal **SN2** at **226** can be provided by the following equation: $SN2 = I_{sub.3} / 740 \times 0.1$, where $I_{sub.3}$ is the current through the third power switch **118**, where dividing by 740 is due to the 740:1 ratio provided by the current mirror, and where multiplying by 0.1 is due to the sensing resistor **224**. Similarly, the signal **SN1** at **230** can be provided by the following equation: $SN1 = I_{sub.4} / 740 \times 0.1$, where $I_{sub.4}$ is the current through the fourth power switch **120**. The **SN1** and **SN2** signals can be provided to gain circuits according to FIG. **17** (e.g., as the input **232**). The outputs **Vgain** at **240** can be provided by the following equations:

$V_{gain.sub.2} = V_b - SN2 \times 280$ and $V_{gain.sub.1} = V_b - SN1 \times 280$, where V_b is the bias voltage at **236**. The bias voltage can be 250 mV, for example, although various other values could be used. The $V_{gain.sub.1}$ and $V_{gain.sub.2}$ signals can be provided to the signal combining circuit, for example as inputs **240a** and **240b** of FIG. **18**. The combining circuit can provide a combined signal **C.sub.save** that can be provided by the following equation:

$C_{sub.save} = \frac{1}{2}(V_{gain.sub.1} + V_{gain.sub.2})$. The **C.sub.save** signal can be a voltage that is indicative

of an average current through the power converter **100**.

(131) Many variations are possible. Various different values can be used for the gain, mirror current ratio, sense resistor value, bias voltage, etc. FIG. **17** shows a two-stage gain circuit that has two amplifiers **234** and **238**. FIG. **19** shows an example embodiment of an alternative, single stage gain circuit that includes one amplifier **248**, which can provide a gain of 300. Other amounts of gain could be applied. An input voltage signal (e.g., SN2 or SN1) can be provided to an input **232** of the gain circuit. The input voltage signal **232** can be coupled through a first resistor R1 to a first terminal (e.g., a negative terminal) of the amplifier **248**, which can be an operational amplifier. The gain circuit can include a bias voltage **236**, which can be coupled through a resistor R2 to a second terminal (e.g., a positive terminal) of the amplifier **248**. The second terminal of the amplifier **248** can also be coupled through a third resistor R3 to an additional input **237**. Input **237** can be a lower tap for resistor **224** or **228** of FIG. **16**, which in this case is labeled as ground. It can be referenced to the ground of the power switch **118** and the power switch **120**, respectively. The output of the amplifier **248** can be coupled through a fourth resistor to the first terminal of the amplifier **248**. The amplifier **248** can be configured to apply a gain to the signal at the input **232** (e.g., a gain of 300, although other gain amounts can be used). The output of the amplifier **248** can be coupled to an output **250**, which can output a positive voltage signal with the gain applied, for example. In some embodiments, a capacitor **252** can be coupled, via a fifth resistor R5, to the output **250** and the output of the amplifier **248**, similar to FIG. **17**.

(132) FIG. **20** is a graph showing the actual current **251** that is output from each phase of the power converter **100** as it increased from about 0 amps to about 10 amps. FIG. **20** shows the current going through each inductor **110** and **112**. Thus, the 5 A shown in FIG. **20** corresponds to an output of 10 A (e.g., with about 5 A for each inductor **110** and **112**). FIG. **20** also shows the sensed voltage that is indicative of the current using the approach described in connection with FIGS. **15-19**. When the actual output current **251** is about 0 amps, the sensed voltage **253** can be about 250 mV. As the actual output current **251** increases to about 5 amps per phase, the sensed voltage **253** can increase to about 400 mV. The sensed voltage **253** can be proportional to the actual output current **251**. Accordingly, a current sensing system can read the sensed voltage **253** to determine the output current **251**.

(133) In some situations, errors can be more likely to occur when the power switches are in the off state, so the power converter **100** can be configured to measure the current when both the third power switch **118** (Q3) and the fourth power switch **120** (Q4) are on, which can be the second and fourth states of operation. Other embodiments can measure the current at other times, such as during the first or third states of configuration. Various methods and devices can be used to measure the output current of the power converter **100**.

(134) Current Sensing Using the Fourth Power Switch

(135) In some embodiment, a single current mirror or sensing circuit can be used, for determining current through only the fourth power switch **120**. As shown in FIG. **2C**, in the third state of operation (e.g., with the second and fourth power switches **116** and **120** on and the first and third power switches **114** and **118** off) the total load current can go through the fourth power switch **120**. According, the current through the fourth power switch **120** (Q4) can provide the sum for both channels of current. For example, in the third state of operation, the capacitor **122** C.sub.B can charge the second inductor **112** (L2), e.g., via a charge path of the fourth power switch **120**, the capacitor **122**, the second power switch **116**, and then the second inductor **112**. At the same time, L1 can be discharging through the fourth power switch **120** (Q4). Therefore, during this state, the fourth power switch carries the total current associated with both the first inductor **110** (L1) and the second inductor **112** (L2). The current across the fourth power switch **120** can be measured similar to other embodiments disclosed herein, such as similar to the embodiments disclosed in connection with FIGS. **15-19**, except that the current sensing can be performed at a different time (e.g., during a third state of operation) and the sensing of current at the third power switch **118** can be omitted.

(136) FIG. 21 shows an example embodiment of a power converter **100**, which can be configured to sense a current across the fourth power switch **120**. The power converter **100** can include a current mirror **214** or other current sensing circuit for the fourth power switch, which can be similar to FIGS. 15 and 16. The current mirror **212** from FIGS. 15 and 16 can be omitted. The current mirror **214** or sensing circuit can be similar to the right side of FIG. 16. The “csen” signal at **232** can operate differently than in FIG. 16, so that the current for the fourth power switch **120** is measured at the third state of operation. The “csen” signal can be high or on when the LDrv1 and HDrv2 signal are high or on (e.g., to close or turn on the second and fourth power switches **116** and **120**). When either of the LDrv1 or HDrv2 signals is low or off, the “csen” signal can be low or off. The power converter **100** can include a current sensing processing circuitry **216** which can invert the raw signal (e.g., a voltage signal) and/or can apply gain to the signal, as discussed herein. The combiner or averaging circuit (e.g., of FIG. 18) can be omitted when the current is measured at only the fourth power switch **120**. The power converter **100** can include an output **218** for outputting information regarding the determined current, as discussed herein. Any other suitable method or technique could be used to measure the voltage for the fourth power switch **120**.

(137) Current Sensing Using the AC Coupling Capacitor

(138) In some embodiments, the voltage across the capacitor **122** can be sensed, and the current through the power converter **100** (e.g., total output current) can be calculated from the determined voltage across the capacitor **122**. As discussed herein, the power converter **100** can include a capacitor **122**, which can AC couple the first power switch **114** to the first inductor **110**. A first side of the capacitor **122** can be coupled to a node between the first power switch **114** and the second power switch **116**. A second side of the capacitor **122** can be coupled to a node between the first inductor **110** and the fourth power switch **120**. In some cases, the capacitor **122** can be considered a flying capacitor.

(139) FIG. 22 shows an example embodiment of a power converter **100** that is configured to sense the voltage across the capacitor **122**. A first line can be used to measure a voltage on the first side of the capacitor **122**. A second line can be used to measure a voltage on the second side of the capacitor **122**. The power converter **100** can include a current sensing processing circuitry **254** and an output **256**. The current sensing processing circuitry **254** can be coupled to the first side of the capacitor **122** and to the second side of the capacitor **122**, so that it can determine voltage differential across the capacitor **122**. The current sensing processing circuitry **254** can determine the current (e.g., the total output current) based on the voltage values, such as based on the changes in the voltage values over time. The output can output the current information, as discussed herein.

(140) FIG. 23 shows the values of various parameters of an example embodiment of a power converter as it transitions between the four states of operation. FIG. 23 shows that during the first state of operation, the voltage $V_{\text{sub.gs}}$ between the gate and source of the first power switch **114** (Q1) goes high, which can turn on the first power switch **114**. The voltage $V_{\text{sub.SW1}}$ at the node SW1 can raise (e.g., from ground to $V_{\text{sub.in}}/2$). The current $I_{\text{sub.L1}}$ through the first inductor **110** can increase during the first state of operation. As shown in FIG. 2A, the current through the first inductor **L1** goes through the capacitor **122**, which can increase the voltage differential $V_{\text{sub.CB}}$ across the capacitor **122**, as shown in FIG. 23. The more current flows through the power converter **100** during the first state of operation, the more the voltage $V_{\text{sub.CB}}$ on the capacitor **122** will increase. During the second and fourth states of operation, both of the first and second power switches **114** and **116** are off, and the inductors **110** and **112** are driven in the opposite direction. The current through the inductors $I_{\text{sub.L1}}$ and $I_{\text{sub.L2}}$ can both decay during the second and fourth states of operation. $V_{\text{sub.CB}}$ can remain approximately constant. During the third state of operation, the voltage $V_{\text{sub.gs}}$ between the gate and source of the second power switch **116** (Q2) can be high, which can turn on the second power switch **116**. The voltage $V_{\text{sub.SW2}}$ at the node SW2 can increase (e.g., from ground to $V_{\text{sub.in}}/2$). The current $I_{\text{sub.L2}}$ through the second inductor **112** can increase during the third state of operation. As shown in FIG. 2C, the capacitor

122 can discharge to drive the current $I_{\text{sub.L2}}$ through the second inductor **112** in the third state of operation, which can cause the voltage $V_{\text{sub.CB}}$ of the capacitor **122** to decrease, as shown in FIG. **23**. The more current that flows through the power converter **100** during the third state of operation, the more the voltage $V_{\text{sub.CB}}$ of the capacitor **122** will decrease. Accordingly, the amount of change in the voltage $V_{\text{sub.CB}}$ across the capacitor **122** can be indicative of the current through the power converter **100**. In FIG. **23**, $\Delta V_{\text{sub.CB}}$ indicates the voltage difference between the highest voltage $V_{\text{sub.CB}}$ and the lowest voltage $V_{\text{sub.CB}}$ that occur during the switching cycle through the four states of operation.

(141) With reference to FIGS. **22** and **23**, the current sensing processing circuitry **254** can sense and monitor the voltage $V_{\text{sub.CB}}$ across the capacitor **122**, and can determine the current through the power converter **100** based at least in part on the sensed or monitored voltage values for $V_{\text{sub.CB}}$. For example, the current through the power converter **100** during a first switching cycle (e.g., through the four states of operation) can be determined based at least in part on the voltage difference $\Delta V_{\text{sub.CB}}$, the difference between the highest voltage $V_{\text{sub.CB}}$ and the lowest voltage $V_{\text{sub.CB}}$ that occurred during the switching cycle through the four states of operation. Many variations are possible. For example, a first current during a first portion of the switching cycle can be determined based at least in part on an amount that the voltage $V_{\text{sub.CB}}$ rises, and a second current during a second portion of the switching cycle can be determined based at least in part on an amount that the voltage $V_{\text{sub.CB}}$ drops. The current (i) through the capacitor **122** can be determined using the following equation: $i = C_{\text{sub.B}} \cdot \Delta V / \Delta t$. In this equation $C_{\text{sub.B}}$ is the capacitance of the capacitor **122**, ΔV is the voltage change across the capacitor, and Δt is the time interval that ΔV is measured over. The current through the capacitor **122** can be indicative of the output current of the power converter **100**. The output current of the power converter **100** can be determined based on periodic measurements of the voltage across the capacitor **122** and the timing information of those measurements.

(142) Capacitor Pre-Charge

(143) When in the steady state, the capacitor **122** ($C_{\text{sub.B}}$) can be charged to a voltage $V_{\text{sub.CB}}$ of about $\frac{1}{2}V_{\text{in}}$. In some embodiments, the capacitor **122** can separate one or both of the third and fourth power switches **118** and **120** from the full V_{in} voltage, when the power converter is operating at steady state. For example, the third and/or fourth power switches **118** and **120** can receive a reduced voltage (e.g., about $V_{\text{in}} - V_{\text{sub.CB}}$ or about $\frac{1}{2}V_{\text{in}}$). It can be advantageous in some embodiments to use lower voltage switches for the third and/or fourth power switches **118**, **120**, as compared to the first and/or second power switches **114**, **116**, which can receive the full V_{in} voltage. For example, the lower voltage switches can have reduced conduction losses for a given silicon area. However, the lower voltage switches can be damaged or destroyed if exposed to the full V_{in} voltage. During steady state operation, the lower voltage switches (e.g., **Q3** and **Q4**) can be protected. However, in some configurations the third and/or fourth power switches **118**, **120** (**Q3** and **Q4**) can be exposed to higher voltages during startup, before the steady state is reached. At time T_0 , when the startup begins, the capacitor **122** can have no charge yet. Then if the first power switch **114** (**Q1**) is turned on (e.g., to start the first state of operation), the full input voltage V_{in} would be delivered to the fourth power switch **120**, which in some cases can damage the fourth power switch **120**.

(144) One solution can be to first turn on the fourth power switch **120** at startup and prior to any switching cycle. That can couple the second side of the capacitor **122** to ground. The other side of the capacitor (e.g., **CS1**) can be charged (e.g., to $\frac{1}{2}V_{\text{in}}$). This approach can work for some applications. However, some powered devices require a startup into a pre-biased output without discharging the output. The pre-bias can be a voltage present on the output **104** when the power converter **100** is turned on. Turning on switch **120** before normal operation would discharge that output, which would violate the pre-bias startup condition. Accordingly, this approach would not be acceptable for some devices. Also, in some cases, this approach could cause the voltage to go

negative, which can be a problem for some devices

(145) In some embodiments, the power converter **100** can perform a pre-charge operation on the capacitor **122** before starting the switching cycles. The pre-charge operation can charge up the capacitor **122**, so that when the switching cycles start, the third and/or fourth power switches are protected when the switching cycles begin. For the pre-charge operation, the power converter **100** can turn on one or more switches to provide a charging path for current to charge the capacitor **122**. The power converter **100** can monitor the voltage across the capacitor **122** (e.g., similar to FIG. **22**), and when the voltage across the capacitor **122** reaches a threshold, the power converter **100** can turn off the one or more switches to stop charging the capacitor. The voltage threshold for stopping the pre-charge operation can be about half of the input voltage $\frac{1}{2}V_{in}$. With reference to FIG. **24**, a first switch **258** can selectively couple the input **102** (V_{in}) to the capacitor **122**. A second switch **260** can selectively couple the capacitor **122** to ground (or to some other voltage lower than V_{in}). In some embodiments, the capacitor **122** can be coupled to a buffered version of V_{out} **104** (e.g., buffered by amplifier **270**), as shown in FIG. **25**. The buffer **270** can sync the charging current in order to keep V_{out} unchanged. This is to eliminate the possibility of discharging a pre-biased output V_{out} . Discharging the output may be acceptable for some applications, and may be unacceptable in others. Charging with a pre-biased output can be preferable over charging with no pre-bias (e.g., shorted to ground), in some cases.

(146) To pre-charge the capacitor **122**, the power converter **100** (e.g., a driver or controller thereof) can turn on the switches **258** and **260**, so that current can flow from the input to the first side of the capacitor **122**, and from the second side of the capacitor **122** to ground, which can charge up the capacitor **122**. When the voltage across the capacitor **122** reaches a threshold (e.g., about $\frac{1}{2}V_{in}$), the switches **258** and **260** can turn off. The power converter **100** can then begin normal operation, such as by starting the switching cycles through the operational states discussed herein. Although not shown in FIG. **24**, a voltage monitor circuit can be coupled to the capacitor **122** for determining when the voltage threshold has been reached to stop the pre-charge operation. Many variations are possible. In some embodiments, the first power switch **114** can be used as the switch **258**. In some embodiments, the switch **260** (or a different switch not shown in FIG. **24**) can disconnect the fourth power switch **120** from the capacitor **122** during the pre-charge operation, and can reconnect the fourth power switch **120** to the capacitor **122** after the pre-charge operation. In some embodiments, the capacitor **122** can be coupled to the output $V_{sub.O}$ or other low voltage to provide the pre-charge current path. This mode of operation (e.g., coupling the capacitor **122** to $V_{sub.O}$) can be preferable, in some cases.

(147) FIG. **25** shows an example embodiment of circuitry for performing the pre-charge operation. The circuitry can include a switch **262** (e.g., a P-channel MOSFET or other suitable type of switch) that can selectively couple V_{in} to the first (e.g., top) side of the capacitor **122**. The voltage ($V_{sub.ctop}$) on the first or top side of the capacitor **122** can increase during the pre-charge operation. The switch **262** can be controlled to turn on to start the pre-charge operation, and to turn off when the voltage across the capacitor **122** reaches a threshold, such as about $\frac{1}{2}V_{in}$. A controller **264** can provide signals to control the switch **262**. In some embodiments, the controller **264** can provide a signal that turns on a switch **266** so that a signal **268** is delivered through the switch **266** to the switch **262** to turn on the switch **262**. In some cases, the signal **268** can be tied to ground. The signal **268** can be tied to a different voltage value that is sufficiently low to allow switch **266** to turn on via the output of NOR gate **286** or other device providing a control signal to switch **266**.

(148) The second side of the capacitor **122** can be coupled to V_{out} (or ground or some other low voltage), such as through an amplifier **270**. The amplifier **270** can be an operational amplifier. The amplifier **270** can be used as a unity gain amplifier. A first terminal (e.g., positive terminal) of the amplifier **270** can be coupled to V_{out} (or other low voltage), and the output of the amplifier can be coupled to the second terminal (e.g., negative terminal) of the amplifier **270**. The voltage ($V_{sub.cbott}$) on the second (e.g., bottom) side of the capacitor **122** can be coupled to ground

through two resistors, with a first (e.g., positive) terminal of an amplifier 272 coupled between the resistors, to provide a voltage divider 274. The second (e.g., negative) terminal of the amplifier 272 can be coupled to the output of the amplifier 272. The amplifier 272 can operate as a unit gain amplifier, in some cases. The output of the voltage divider 274 (e.g., and the output of the amplifier 272) can be $\frac{1}{4} V_{\text{sub.cb0t}}$.

(149) The output of the amplifier 272 can be coupled to a second (e.g., negative) terminal of an amplifier 276 through a resistor. The output of the amplifier 276 can be coupled through another resistor to the second (e.g., negative) terminal of the amplifier 276. The first (e.g., positive) terminal of the amplifier 276 can receive a voltage of $\frac{1}{8} V_{\text{sub.ctop}}$. A voltage divider 277 can provide the voltage of $\frac{1}{8} V_{\text{sub.ctop}}$. The first (e.g., top) side of the capacitor 122 can be coupled to ground through a number of resistors, and the terminal of the amplifier 276 can be coupled between the resistors to provide the voltage divider. In the embodiment of FIG. 25, 8 resistors can be used, with 7 on one side and 1 on the other to provide $\frac{1}{8} V_{\text{sub.ctop}}$. In some cases, fewer resistors can be used (e.g., depending on the resistance values used). In some cases, the amplifier 276 can operate as a diff amp, which can output the difference between voltage signals. The amplifier 276 can output a voltage $V_{\text{sub.m}} = (\frac{1}{8} * V_{\text{ctop}} - \frac{1}{4} * V_{\text{cb0t}}) + \frac{1}{8} * V_{\text{ctop}}$ which equals $\frac{1}{4}(V_{\text{ctop}} - V_{\text{cb0t}})$ which is $\frac{1}{4} V_{\text{sub.CB}}$.

(150) The second (e.g., positive) terminal of amplifier 278 can receive the output ($V_{\text{sub.m}}$) from the amplifier 276, which can be equal to $\frac{1}{4}$ the voltage across the capacitor 122 ($\frac{1}{4} V_{\text{sub.cb}}$). The first (e.g., negative) terminal of the amplifier 278 can be $\frac{1}{8} V_{\text{in}}$. The circuitry can include a voltage divider 282 for providing the signal of $\frac{1}{8} V_{\text{in}}$ to the amplifier 278. A number of resistors can be coupled between V_{in} and ground, with a connection to the amplifier 278 between the resistors. In the embodiment of FIG. 25, 8 resistors are shown, with 7 on one side and 1 on the other, to provide a voltage of $\frac{1}{8} V_{\text{in}}$. Fewer resistors could be used, depending on the resistance values used. In some cases a capacitor 284 can be coupled between the $\frac{1}{8} V_{\text{in}}$ signal and ground (e.g., between the first or negative terminal of the amplifier 278 and ground. In some instances, V_{in} can be noisy and have significant ripple from supplying power through the converter 100 to the output 104. The capacitor 284, along with the voltage divider 282, can form a resistor-capacitor (RC) network that is used to filter out this noise and ripple. This can allow for better accuracy in the charging voltage $V_{\text{sub.CB}}$. The amplifier 278 can operate as a comparator, which can detect whether the voltage across the capacitor $V_{\text{sub.cb}}$ has reached a threshold, such as $\frac{1}{2} V_{\text{in}}$. In the embodiment of FIG. 25, the comparator amplifier 278 can detect when $\frac{1}{4} V_{\text{sub.cb}} \geq \frac{1}{8} V_{\text{in}}$, which is the same as $V_{\text{sub.cb}} \geq \frac{1}{2} V_{\text{in}}$. So when the voltage of the capacitor 122 is less than half the input voltage, the output 280 of the amplifier 278 can have a first value (e.g., high), which can enable the pre-charge operation to continue. When the voltage of the capacitor 122 is reaches the value of half the input voltage, the output 280 of the amplifier 278 can have a second value (e.g., low), which can stop the pre-charge operation. For example, the output 280 can be delivered as input to the controller 264, and a high signal can enable the pre-charge operation, whereas a low signal can disable the pre-charge operation. So when the output 280 goes low, the controller 264 can stop the pre-charge operation, such as by turning off the switch 266 and/or the switch 262. In some cases, the switch 266 can be coupled to a NOR gate 286. The NOR gate 286 can turn on the switch 266 if both inputs are 0 or low. One input can be coupled to the controller 264, as shown. The controller can output a low signal to turn on the pre-charge operation. The other input to the NOR gate 286 can be coupled to the output 280. In some cases, the amplifier 278 can be configured to produce a high output 280 when the capacitor 122 voltage $V_{\text{sub.CB}}$ reaches the threshold. That high signal output 280 can be delivered to the NOR gate 286, which can then turn off the switch 266. Many variations are possible, such as using different logic gates, or other signals. An AND gate could be used, for example, to output a high signal to turn on the switch 266 only when high signals are received from both the controller 264 and the amplifier 278. In some embodiments, the NOR gate 186 can be omitted, and the controller 264 can be configured to output the signals for controlling switch 266

without the NOR gate **186**. In some cases, the controller **264** can be omitted. A d-type flip-flop can be used (e.g., in place of the controller **264**) with the NOR gate **286** to control the switch **266**. Many different combinations of resistor divider ratios may be used to generate the appropriate voltages and functionality.

(151) Additional Details

(152) The principles and advantages described herein can be implemented in various apparatuses. Examples of such apparatuses can include, but are not limited to, consumer electronic products, parts of the consumer electronic products, electronic test equipment, etc. Examples of parts of consumer electronic products can include clocking circuits, analog-to-digital converters, amplifiers, rectifiers, programmable filters, attenuators, variable frequency circuits, etc. Examples of the electronic devices can also include memory chips, memory modules, circuits of optical networks or other communication networks, cellular communications infrastructure such as base stations, radar systems, and disk driver circuits, etc. Consumer electronic products can include, but are not limited to, wireless devices, a mobile phone (for example, a smart phone), a wearable computing device such as a smart watch or an car piece, healthcare monitoring devices, vehicular electronics systems, a telephone, a television, a computer monitor, a computer, a hand-held computer, a tablet computer, a laptop computer, a personal digital assistant (PDA), a microwave, a refrigerator, a stereo system, a cassette recorder or player, a DVD player, a CD player, a digital video recorder (DVR), a VCR, an MP3 player, a radio, a camcorder, a camera, a digital camera, a portable memory chip, a washer, a dryer, a washer/dryer, a copier, a facsimile machine, a scanner, a multi-functional peripheral device, a wrist watch, a clock, etc. Further, apparatuses can include unfinished products.

(153) In some embodiments, the methods, techniques, microprocessors, and/or controllers described herein are implemented by one or more special-purpose computing devices. The special-purpose computing devices may be hard-wired to perform the techniques, or may include digital electronic devices such as one or more application-specific integrated circuits (ASICs) or field programmable gate arrays (FPGAs) that are persistently programmed to perform the techniques, or may include one or more general purpose hardware processors programmed to perform the techniques pursuant to program instructions in firmware, memory, other storage, or a combination thereof. The instructions can reside in RAM memory, flash memory, ROM memory, EPROM memory, EEPROM memory, registers, hard disk, a removable disk, a CD-ROM, or any other form of a non-transitory computer-readable storage medium. Such special-purpose computing devices may also combine custom hard-wired logic, ASICs, or FPGAs with custom programming to accomplish the techniques. The special-purpose computing devices may be desktop computer systems, server computer systems, portable computer systems, handheld devices, networking devices or any other device or combination of devices that incorporate hard-wired and/or program logic to implement the techniques.

(154) The microprocessors and/or controllers described herein may implement the techniques described herein using customized hard-wired logic, one or more ASICs or FPGAs, firmware and/or program logic which causes microprocessors and/or controllers to be a special-purpose machine. According to one embodiment, parts of the techniques disclosed herein are performed in a controller in response to executing one or more sequences of instructions contained in a memory. Such instructions may be read into the memory from another storage medium, such as storage device. Execution of the sequences of instructions contained in the memory causes the processor or controller to perform the process steps described herein. In alternative embodiments, hard-wired circuitry may be used in place of or in combination with software instructions.

(155) Moreover, the various illustrative logical blocks and modules described in connection with the embodiments disclosed herein can be implemented or performed by a machine, such as a processor device, a digital signal processor (DSP), an application specific integrated circuit (ASIC), a field programmable gate array (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the

functions described herein. A processor device can be a microprocessor, but in the alternative, the processor device can be a controller, microcontroller, or state machine, combinations of the same, or the like. A processor device can include electrical circuitry configured to process computer-executable instructions. In another embodiment, a processor device includes an FPGA or other programmable device that performs logic operations without processing computer-executable instructions. A processor device can also be implemented as a combination of computing devices, e.g., a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration. Although described herein primarily with respect to digital technology, a processor device may also include primarily analog components. For example, some or all of the techniques described herein may be implemented in analog circuitry or mixed analog and digital circuitry.

(156) Unless the context clearly requires otherwise, throughout the description and the claims, the words “comprise,” “comprising,” “include,” “including,” and the like are to be construed in an inclusive sense, as opposed to an exclusive or exhaustive sense; that is to say, in the sense of “including, but not limited to.” The words “coupled” or “connected,” as generally used herein, refer to two or more elements that can be either directly connected, or connected by way of one or more intermediate elements. Additionally, the words “herein,” “above,” “below,” and words of similar import, when used in this application, shall refer to this application as a whole and not to any particular portions of this application. Where the context permits, words in the Detailed Description using the singular or plural number can also include the plural or singular number, respectively. The words “or” in reference to a list of two or more items, is intended to cover all of the following interpretations of the word: any of the items in the list, all of the items in the list, and any combination of the items in the list. All numerical values provided herein are intended to include similar values within a range of measurement error.

(157) Although this disclosure contains certain embodiments and examples, it will be understood by those skilled in the art that the scope extends beyond the specifically disclosed embodiments to other alternative embodiments and/or uses and obvious modifications and equivalents thereof. In addition, while several variations of the embodiments have been shown and described in detail, other modifications will be readily apparent to those of skill in the art based upon this disclosure. It is also contemplated that various combinations or sub-combinations of the specific features and aspects of the embodiments may be made and still fall within the scope of this disclosure. It should be understood that various features and aspects of the disclosed embodiments can be combined with, or substituted for, one another in order to form varying modes of the embodiments. Any methods disclosed herein need not be performed in the order recited. Thus, it is intended that the scope should not be limited by the particular embodiments described above.

(158) Conditional language, such as, among others, “can,” “could,” “might,” or “may,” unless specifically stated otherwise, or otherwise understood within the context as used, is generally intended to convey that certain embodiments include, while other embodiments do not include, certain features, elements and/or steps. Thus, such conditional language is not generally intended to imply that features, elements and/or steps are in any way required for one or more embodiments or that one or more embodiments necessarily include logic for deciding, with or without user input or prompting, whether these features, elements and/or steps are included or are to be performed in any particular embodiment. Any headings used herein are for the convenience of the reader only and are not meant to limit the scope.

(159) Further, while the devices, systems, and methods described herein may be susceptible to various modifications and alternative forms, specific examples thereof have been shown in the drawings and are herein described in detail. It should be understood, however, that the disclosure is not to be limited to the particular forms or methods disclosed, but, to the contrary, this disclosure covers all modifications, equivalents, and alternatives falling within the spirit and scope of the various implementations described. Further, the disclosure herein of any particular feature, aspect,

method, property, characteristic, quality, attribute, element, or the like in connection with an implementation or embodiment can be used in all other implementations or embodiments set forth herein. Any methods disclosed herein need not be performed in the order recited. The methods disclosed herein may include certain actions taken by a practitioner; however, the methods can also include any third-party instruction of those actions, either expressly or by implication.

(160) The ranges disclosed herein also encompass any and all overlap, sub-ranges, and combinations thereof. Language such as “up to,” “at least,” “greater than,” “less than,” “between,” and the like includes the number recited. Numbers preceded by a term such as “about” or “approximately” include the recited numbers and should be interpreted based on the circumstances (e.g., as accurate as reasonably possible under the circumstances, for example $\pm 5\%$, $\pm 10\%$, $\pm 15\%$, etc.). For example, “about 3.5 mm” includes “3.5 mm.” Phrases preceded by a term such as “substantially” include the recited phrase and should be interpreted based on the circumstances (e.g., as much as reasonably possible under the circumstances). For example, “substantially constant” includes “constant.” Unless stated otherwise, all measurements are at standard conditions including ambient temperature and pressure.

Claims

1. A power converter comprising: an input configured to receive an input voltage; an output configured to output an output voltage that is different than the input voltage; a first inductor; a second inductor; a first power switch; a second power switch; a third power switch; a fourth power switch; wherein the first, second, third, and fourth power switches are configured to control current through the first inductor and the second inductor; a driver configured to operate the first, second, third, and fourth power switches to change the input voltage to provide the output voltage; a current sensing circuit for measuring a current through the fourth power switch, wherein the current sensing circuit is configured to produce a voltage signal that is indicative of the current through the fourth power switch; current sensing processing circuitry configured to determine a power converter current based at least in part on the measured current through the fourth power switch, wherein the current sensing processing circuitry is configured to apply a gain to increase the voltage signal, and wherein the current sensing processing circuitry is configured to invert the voltage signal; and a communication interface for outputting information regarding the determined power converter current.
2. The power converter of claim 1, wherein the current sensing circuit includes a sensing switch in parallel with the fourth power switch, wherein the sensing switch is configured to be on when the second power switch and the fourth power switch are on, wherein the sensing switch is configured to be off when the either of the second power switch and the fourth power switch is off.
3. The power converter of claim 1, wherein the current sensing circuit includes a current mirror.
4. The power converter of claim 1, comprising another current sensing circuit for measuring a current through the third power switch, wherein the current sensing processing circuitry is configured to determine the power converter current based at least in part on the measured current through the third power switch and the measured current through the fourth power switch.
5. The power converter of claim 4, wherein the current sensing circuit for the third power switch includes a first current mirror, and wherein the current sensing circuit for the fourth power switch includes a second current mirror.
6. The power converter of claim 4, wherein: the current sensing circuit for the third power switch is configured to produce a first voltage signal that is indicative of the current through the third power switch; and the current sensing circuit for the fourth power switch is configured to produce a second voltage signal that is indicative of the current through the fourth power switch.
7. The power converter of claim 6, wherein the current sensing processing circuitry is configured to apply a gain to increase the first voltage signal and the second voltages signal.

8. The power converter of claim 4, wherein: the current sensing circuit for the third power switch includes a first sensing switch in parallel with the third power switch; the first sensing switch is configured to be on when the third power switch and the fourth power switch are on; the first sensing switch is configured to be off when the either of the third power switch and the fourth power switch is off; the current sensing circuit for the fourth power switch includes a second sensing switch in parallel with the fourth power switch; the second sensing switch is configured to be on when the third power switch and the fourth power switch are on; and the second sensing switch is configured to be off when the either of the third power switch and the fourth power switch is off.

9. A power converter comprising: an input configured to receive an input voltage; an output configured to output an output voltage that is different than the input voltage; a first inductor; a second inductor; a first power switch; a second power switch; a third power switch; a fourth power switch; wherein the first, second, third, and fourth power switches are configured to control current through the first inductor and the second inductor; a driver configured to operate the first, second, third, and fourth power switches to change the input voltage to provide the output voltage; a current sensing circuit for measuring a current through the fourth power switch; another current sensing circuit for measuring a current through the third power switch; current sensing processing circuitry configured to determine a power converter current based at least in part on the measured current through the third power switch and the measured current through the fourth power switch; and a communication interface for outputting information regarding the determined power converter current; wherein the current sensing circuit for the third power switch includes a first sensing switch in parallel with the third power switch; wherein the first sensing switch is configured to be on when the third power switch and the fourth power switch are on; wherein the first sensing switch is configured to be off when the either of the third power switch and the fourth power switch is off; wherein the current sensing circuit for the fourth power switch includes a second sensing switch in parallel with the fourth power switch; wherein the second sensing switch is configured to be on when the third power switch and the fourth power switch are on; and wherein the second sensing switch is configured to be off when the either of the third power switch and the fourth power switch is off.

10. The power converter of claim 9, wherein the current sensing circuit includes a current mirror.

11. A power converter comprising: an input configured to receive an input voltage; an output configured to output an output voltage that is different than the input voltage; a first inductor; a second inductor; a first power switch; a second power switch; a third power switch; a fourth power switch; wherein the first, second, third, and fourth power switches are configured to control current through the first inductor and the second inductor; a driver configured to operate the first, second, third, and fourth power switches to change the input voltage to provide the output voltage; a current sensing circuit for measuring a current through the fourth power switch, wherein the current sensing circuit for the fourth power switch is configured to produce a second voltage signal that is indicative of the current through the fourth power switch; another current sensing circuit for measuring a current through the third power switch, wherein the current sensing circuit for the third power switch is configured to produce a first voltage signal that is indicative of the current through the third power switch; current sensing processing circuitry configured to determine a power converter current based at least in part on the measured current through the third power switch and the measured current through the fourth power switch, wherein the current sensing processing circuitry is configured to apply a gain to increase the first voltage signal and the second voltage signal, and wherein the current sensing processing circuitry is configured to invert the first voltage signal and to invert the second voltage signal; and a communication interface for outputting information regarding the determined power converter current.

12. The power converter of claim 11, wherein the current sensing circuit includes a current mirror.
