

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250279798

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

Hunt; Jeffrey H. et al.

Adaptive Control and Testing System for an Adaptive Receiver

Abstract

An adaptive receiver comprising a current buffer, an inverter that receives input from the current buffer, an average current control loop that feeds back from the inverter to the current buffer, a variable gain circuit that receives input from the inverter, a differential voltage amplifier that receives input from the variable gain circuit, an automatic gain control loop that feeds back from the differential voltage amplifier to the inverter and variable gain circuit, and a differential buffer that receives input from the differential amplifier.

Inventors: Hunt; Jeffrey H. (Thousand Oaks, CA), Aghlmand; Fatemeh (Pasadena, CA), Emami; Azita (Pasadena, CA)

Applicant: The Boeing Company (Arlington, VA); California Institute of Technology (Pasadena, CA)

Family ID: 87069080

Appl. No.: 19/212151

Filed: May 19, 2025

Related U.S. Application Data

parent US division 18151996 20230109 parent-grant-document US 12341546 child US 19212151
us-provisional-application US 63298121 20220110

Publication Classification

Int. Cl.: H04B1/12 (20060101); H04B1/18 (20060101); H04B10/27 (20130101); H04B10/61 (20130101)

U.S. Cl.:

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application is a Divisional of U.S. patent application Ser. No. 18/151,996, attorney docket no. 19-3977-US-NP[3], filed Jan. 9, 2023, allowed Apr. 17, 2025, and entitled “Adaptive Control and Testing System for an Adaptive Receiver,” which claims the benefit of U.S. Provisional Patent Application No. 63/298, 121, attorney docket no. 19-3977-US-PSP, filed Jan. 10, 2022, and entitled “AN 8GBPS ADAPTIVE RECEIVER FOR RF OVER FSO IN 28NM CMOS,” which is incorporated herein by reference in its entirety. [0002] This application is related to the following pending U.S. Patent Applications, filed Jan. 9, 2023, and entitled “Optical Communications System”: Ser. No. 18/151,934, attorney docket no. 19-3977-US-NP[1]; and Ser. No. 18/151,970, attorney docket no. 19-3977-US-NP[2]; assigned to the same assignee, and incorporated herein by reference in their entirety.

BACKGROUND INFORMATION

1. Field

[0003] The present disclosure relates generally to optical communications and in particular, to optical communications using embedded radio frequency signals encoding data.

2. Background

[0004] The communication of data between space and ground platforms is currently performed using radio frequencies or microwave carrier frequencies. In some examples, data is encoded in signals using megahertz bandwidths. In some examples, the signals can be converted to data and the data can be encoded in optical signals. The optical signals can then be transmitted between space and ground platforms. The encoding and decoding of data from one type of carrier to another carrier can increase the amount of time needed. Further, the locations where these conversions are performed can be bottlenecks for communications.

[0005] The use of radio frequency to transmit data can be more challenging than desired in various environments. For example, in a physically cluttered environment it can be challenging to create a line of sight communications using radio frequency signals.

[0006] Therefore, it would be desirable to have a method and apparatus that take into account at least some of the issues discussed above, as well as other possible issues.

SUMMARY

[0007] An embodiment of the present disclosure provides an adaptive receiver comprising a current buffer, an inverter based transimpedance circuit, an average current control loop, a variable gain circuit, an automatic gain control loop, and a differential buffer. The current buffer receives an input current. The inverter based transimpedance circuit receives a buffered current from the current buffer and converts the buffered current to a variable gain voltage. The average current control loop feeds back from the inverter based transimpedance circuit to the current buffer, wherein the average current control loop adaptively controls an average current into the current buffer. The variable gain circuit receives variable gain voltage from the inverter based transimpedance circuit and outputs a differential voltage. The differential voltage amplifier receives the differential voltage output from the variable gain circuit and outputs an amplified differential voltage. The automatic gain control loop feeds back from the differential voltage amplifier to the inverter based transimpedance circuit and variable gain circuit, wherein the automatic gain control loop adaptively controls a peak to peak voltage output by the differential voltage amplifier based on a desired peak-to-peak level for the output of the differential voltage amplifier. The differential buffer receives the amplified differential voltage output from the differential voltage amplifier and

outputs recovered radio frequency signals.

[0008] Another embodiment of the present disclosure provides an optical test system comprising a transmitter system, a propagation medium simulator, an optical receiver system, and an analog to digital system. The transmitter system transmits modulated coherent optical signals modulated using radio frequency signals encoding test data. The propagation medium simulator receives the modulated coherent optical signals from the transmitter system, changes a set of optical attributes for the modulated coherent optical signals to model propagation of the modulated coherent optical signals through a propagation environment to form varied modulated coherent optical signals, and outputs the varied modulated coherent optical signals. The optical receiver system receives varied modulated coherent optical signals from the propagation medium simulator, recovers the radio frequency signals encoding the test data from the varied modulated coherent optical signals in a manner that adjusts for changes in the varied modulated coherent optical signals caused by a variation in a set of optical attributes in varied modulated coherent optical signals generated by the propagation medium simulator. The analog to digital system extracts the test data from the radio frequency signals, and outputs recovered data.

[0009] The features and functions can be achieved independently in various embodiments of the present disclosure or may be combined in yet other embodiments in which further details can be seen with reference to the following description and drawings.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0010] FIG. 1 is an illustration of a telecommunications system in accordance with an illustrative embodiment;

[0011] FIG. 2 is an illustration of a communications environment in which communications are facilitated using coherent optical signals modulated using radio frequency signals encoding data in accordance with an illustrative embodiment;

[0012] FIG. 3 is an illustration of a block diagram of a communications environment in accordance with an illustrative embodiment;

[0013] FIG. 4 is an illustration of a block diagram of a communications system in accordance with an illustrative embodiment;

[0014] FIG. 5 is an illustration of a block diagram of a communications system depicting details of the optical transmitter and optical receiver in accordance with an illustrative embodiment;

[0015] FIG. 6 is an illustration of a block diagram of an adaptive receiver integrated circuit in accordance with an illustrative embodiment;

[0016] FIG. 7 is an illustration of a circuit diagram of an example implementation of the adaptive receiver integrated circuit in accordance with an illustrative embodiment;

[0017] FIG. 8 is an illustration of a block diagram of an optical test system is depicted in accordance with an illustrative embodiment;

[0018] FIG. 9 is an illustration of a block diagram of a transmitter system in accordance with an illustrative embodiment;

[0019] FIG. 10 is an illustration of a block diagram for a receiver system in accordance with an illustrative embodiment;

[0020] FIG. 11 is a flowchart of a process for method for communicating data with a platform in accordance with an illustrative embodiment;

[0021] FIG. 12 is a flowchart of a process for method for communicating data with a platform in accordance with an illustrative embodiment;

[0022] FIG. 13 is a flowchart of a process for method for communicating data with a vehicle in accordance with an illustrative embodiment;

[0023] FIG. **14** is a flowchart of a process for method for communicating data with a vehicle in accordance with an illustrative embodiment;
[0024] FIG. **15** is a flowchart of a process for method for communicating sensor data in accordance with an illustrative embodiment;
[0025] FIG. **16** is a flowchart of a process for method for communicating sensor data in accordance with an illustrative embodiment;
[0026] FIG. **17** is an illustration of a flowchart of a process for testing a receiver system in accordance with an illustrative embodiment; and
[0027] FIG. **18** is a flowchart of a process for selecting settings for and adaptive receiver in accordance with an illustrative embodiment.

DETAILED DESCRIPTION

[0028] The illustrative embodiments recognize and take into account a number of different considerations as described herein. The illustrative embodiments recognize and take into account that wireless signals operate in the radio frequency (RF) or microwave frequencies, while internet signals have carriers in the optical frequencies. The illustrative embodiments also recognize and take into account that it would be desirable to change from one carrier frequency to another while maintaining the information carried by the RF or microwave signal.

[0029] The illustrative embodiments also recognize and take into account that, while the information signals are generated in the MHz frequencies, it would be desirable to send the signals on optical carriers, since the beam spread (due to diffraction) would be orders of magnitude smaller in the optical frequencies.

[0030] The illustrative embodiments also recognize and take into account that changing from one of these carrier frequencies to the other involves detection and retransmission, which creates significant temporal bottlenecks that cannot be removed simply by adding more transmission bandwidth (i.e., optical fiber).

[0031] The illustrative embodiments provide a system that writes a signal carried by an RF or microwave carrier directly onto an optical carrier. Because the optical carrier is orders of magnitude higher than the RF signal, it is possible to put more information onto the optical system.

[0032] The illustrative embodiments also recognize and take into account that the use of radio frequency to transmit data can be more challenging than desired in various environments. For example, in a physically cluttered environment it can be challenging to create a line of sight communications using radio frequency signals. For example, establishing a communications link between two buildings can be achieved using a radio frequency repeater or by enlarging the propagation cone or radiation pattern. However, these types of structures can be larger than desired based on the wavelength for the carrier signals.

[0033] The communication of data between space and ground platforms is currently performed using radio frequencies or microwave carrier frequencies. In some examples, data is encoded in signals using megahertz bandwidths. In some examples, the signals can be converted to data and the data can be encoded in optical signals. The optical signals can then be transmitted between space and ground platforms. The encoding and decoding of data from one type of carrier to another carrier can increase the amount of time needed. Further, the locations where these conversions are performed can be bottlenecks for communications.

[0034] FIG. **1** is an illustration of a

[0035] telecommunications system in accordance with an illustrative embodiment. Telecommunications system **100** comprises a number of ground stations **102**, **104**, **106** and a number of satellites **108**, **110**, **112**.

[0036] Telecommunications system **100** includes a number of fiber-optic links **114**, **116** connecting ground stations **102**, **104**, **106** and a number of inter-satellite links **118**, **120** connecting satellites **108**, **110**, **112**. Space-to-ground links **122**, **124** connect the satellites **110** and **112** with the ground stations **106** and **102**, respectively. In the example illustrated in FIG. **1**, the inter-satellite links **118**,

120 and space-to-ground links **122**, **124** comprises free-space optical beams.

[0037] Ground stations **102**, **104**, **106** and satellites **108**, **110**, **112** may comprise a transmitter (TX), a receiver (RX), or both.

[0038] With reference to FIG. 2, an illustration of a communications environment in which communications are facilitated using coherent optical signals modulated using radio frequency signals encoding data is depicted in accordance with an illustrative embodiment. As depicted, communications environment **200** is an environment in which radio frequency signals encoding data can be encoded in coherent optical signals for transmission. This type of encoding of radio frequency signals encoded with data can increase at least one of the bandwidth or speed at which data can be transferred. For example, multiple radio frequency signals encoding data can be combined and used to modulate a coherent optical signal. This modulation of the coherent optical signal results in a modulated coherent optical signal that encode the radio frequency signals that are encoded with data. The different radio frequency signals encoding data can have different expanse. In other words, each of the radio frequency signals encoding data can occupy a different frequency range. In other words, these radio frequency signals can be transmitted in parallel within modulated coherent optical signals.

[0039] A using at least one of as used herein, “a number of” when used with reference to items, means one or more items. For example, “a number of different types of networks” is one or more different types of networks.

[0040] Further, the phrase “at least one of,” when used with a list of items, means different combinations of one or more of the listed items can be used, and only one of each item in the list may be needed. In other words, “at least one of” means any combination of items and number of items may be used from the list, but not all of the items in the list are required. The item can be a particular object, a thing, or a category.

[0041] For example, without limitation, “at least one of item A, item B, or item C” may include item A, item A and item B, or item B. This example also may include item A, item B, and item C or item B and item C. Of course, any combinations of these items can be present. In some illustrative examples, “at least one of” can be, for example, without limitation, two of item A; one of item B; and ten of item C; four of item B and seven of item C; or other suitable combinations.

[0042] In this illustrative example, various platforms are present on which optical communication systems can be implemented for facilitating communication of data using coherent optical signals that are modulated with radio frequency signals encoding data. In this illustrative example, the data can take various forms. For example, the data can be voice communications, sensor data, commands, programs, transactions, messages, images, or other types of data.

[0043] As depicted, examples of platforms that can be used to facilitate optical communications in communications environment **200** include space platforms located in space **206**. In this example, space **206** is the part of communications environment **200** that is beyond the Earth's atmosphere in this illustrative example. In this example, space **206** is not completely empty. In other words, space can still have a low density of particles such as a plasma of hydrogen and helium. Electromagnetic radiation, magnetic fields, neutrinos, dust, and cosmic rays can also be present in space **206**. The demarcation where Earth's atmosphere ends may be not defined with a definite altitude above surface of the Earth. In another example, space **206** can be defined to begin at the Kármán line, which is about 100 km or 62 miles above sea level. The division between space **206** and Kármán line is a specific definition for where space **206** can begin as set by the Fédération aéronautique internationale (FAI).

[0044] Other platforms shown in communications environment **200** are terrestrial platforms. These terrestrial platforms are located within the Earth's atmosphere in this illustrative example. Some of these terrestrial platforms are located on land **208** or on water **210**. In this example, other platforms can be located in air **212**.

[0045] In this depicted example, space platforms in space **206** include, for example, satellite **202**

and satellite **204**. As shown in this illustrative example, terrestrial platforms on land **208** include office building **214**, office building **216**, signal light camera **217**, and vehicle **227** in urban area **218**. As depicted, terrestrial platforms can also include building **220** in suburban area **221**.

[0046] As another example, terrestrial platforms can include sensor unit **219** in field **222**. As another example, communications tower **224** in mountains **226** can also be used to facilitate optical communications. Ship **228** on water **210** can be an optical communication system. Unmanned aerial vehicle **230** in air **212** can also facilitate optical communications.

[0047] In this illustrative example, these different platforms can be used to establish communications links to communicate data in communications environment **200**. The communications links can be established in a manner that facilitates at least one of increased efficiency or increased bandwidth in transmitting data as compared to current techniques.

[0048] For example, communications link **240** can be established in urban area **218** as point-to-point communications link that enables line of sight communications between office building **214** and office building **216** within a substantial number of buildings in urban area **218**. This line of sight communications provided by communications link **240** within urban area **218** that can be more easily established as compared to current techniques that use radio frequency signals.

[0049] With the use of modulated coherent signals modulated using radio frequency signals encoding data, a smaller carrier wavelength is possible as compared to current techniques using radio frequency signals. As a result, receivers and transmitters for urban platforms such as office building **214** and office building **216** in urban area **218** can more easily transmit and receive these optical signals.

[0050] The use of these modulated optical signals can provide a well-defined propagation direction that results in easier relaying of signals around obstacles in urban area **218** as compared to current systems. Further, smaller transmitter and receiver units can be used on office building **214** and office building **216** to establish communications link **240** in these examples as compared to systems using radio frequency transmissions. In this example, communications link **240** can be a unidirectional or bidirectional communications link.

[0051] Further, modulated coherent optical frequency signals that are modulated using radio frequency signals encoding data can provide increased access and bandwidth for suburban area **221**. For example, with current infrastructure in suburban area **221** and other remote areas may not have access to high-speed access lines such as optical fiber making communications in these areas unreliable and slow. Further, even the densely populated areas such as urban area **218**, the “last mile” issue can result in slower than desired communications. Whether communications are considered slow or sufficiently fast can be defined using at least one of service level objectives (SLOs), service level agreements (SLAs), or other suitable standards.

[0052] As another example, communications link **244** can be used to exchange data between office building **214** and satellite **202**. Communications link **246** is present between satellite **202** and satellite **204**. Communications link **248** is present between satellite **204** and communications tower **224**.

[0053] As depicted, building **220** has communications link **242** with communications tower **224**. In this example, communications tower **224** also has communications link **225** with ship **228**, communications link **266** with unmanned aerial vehicle **230**, and communications link **268** with sensor unit **219**. In this example, communications link **252** is between satellite **204** and train **229**. Train **229** also has communications link **256** with ship **228** and communications link **250** with office building **216**. Office building **216** also has communications link **262** with signal light camera **217** and communication link **260** with vehicle **227**.

[0054] As depicted, these optical communications links can provide increased efficiency communicating data between the various platforms depicted in communications environment **200** through modulating coherent optical signals using radio frequency signals encoding the data in transmitting the modulated coherent optical signals from transmitter systems in the platforms to

receiver systems in platforms that recover the radio frequency signals encoding data from the modulated coherent optical signals.

[0055] In the illustrative examples, adaptive receivers are present in the receiver systems to reduce issues that can be present with transmitting coherent optical signals through the atmosphere or through space. For example, the adaptive receivers in the receiver systems take into account variations in characteristics of the modulated coherent optical signals. For example, the adaptive receivers can take into account changes in intensity in the modulated coherent optical signals caused by atmospheric conditions such as rain, fog, pollution, volcanic ash, and other conditions that can cause attenuation and variation in the intensity of the modulated coherent optical signals that are received.

[0056] With reference now to FIG. 3, an illustration of a block diagram of a communications environment is depicted in accordance with an illustrative embodiment. In this illustrative example, communications environment **300** includes components that can be implemented in hardware such as the hardware shown in communications environment **200** in FIG. 2.

[0057] In this example, optical communications system **302** can facilitate communications using modulated coherent optical signals **304** that have been modulated using radio frequency signals **306** encoding data **308**. In other words, radio frequency signals **306** can be modulated to encode data **308**. Coherent optical signals can be modulated using radio frequency signals **306** encoding data **308** to form modulated coherent optical signals **304** modulated using radio frequency signals **306** encoding data **308**.

[0058] In one illustrative example, platform **310** can be first platform **312** in which receiver system **314** is connected to platform **310** in optical communications system **302**. Further in this example, transmitter system **316** can be connected to second platform **318** in optical communications system **302**.

[0059] In this illustrative example, receiver system **314** can be implemented using receiver system **806** in FIG. 10. Also, transmitter system **316** can be implemented using transmitter system **802** in FIG. 9.

[0060] When one component is “connected” to another component, the connection is a physical connection. For example, a first component, such as receiver system **314**, can be considered to be physically connected to a second component, first platform **312**, by at least one of being secured to the second component, bonded to the second component, mounted to the second component, welded to the second component, fastened to the second component, or connected to the second component in some other suitable manner. The first component also can be connected to the second component using a third component. The first component can also be considered to be physically connected to the second component by being formed as part of the second component, an extension of the second component, or both.

[0061] As depicted, second platform **318** can transmit modulated coherent optical signals **304** using transmitter system **316**. Modulated coherent optical signals **304** are coherent optical signals that are modulated using radio frequency signals **306** encoding data **308**. In this example, the modulation is performed by modulating the intensity of the coherent optical signals.

[0062] In this example, modulated coherent optical signals **304** can be directed at first platform **312** and received by receiver system **314** in first platform **312**. In response to receiving modulated coherent optical signals **304**, receiver system **314** can process these optical signals to recover and output radio frequency signals **306** encoding data **308**. Further, receiver system **314** can also recover data **308** encoded in radio frequency signals **306**.

[0063] In this illustrative example, receiver system **314** comprises a number of different components. As depicted, receiver system **314** includes optical receiver **320** and adaptive receiver **322**.

[0064] In this depicted example, optical receiver **320** receives modulated coherent optical signals **304** modulated using radio frequency signals **306** encoding data **308** and generates an input current

330 in response to receiving the modulated coherent optical signals **304**. Input current **330** is an electrical current in these examples and can be generated using a device such as a photodetector. [0065] As depicted, adaptive receiver **322** is connected to optical receiver **320** and receives input current **330** from optical receiver **320**. An adaptive receiver connected to the optical receiver, wherein the adaptive receiver **322** recovers radio frequency signals **306** encoding data **308** from input current **330**. This recovery of radio frequency signals **306** encoding data **308** is performed in a manner that adjusts for changes in the modulated coherent optical signals **304** caused by a variation in optical intensity **332** of modulated coherent optical signals **304** occurring during propagation of the modulated coherent optical signals **304**. Adaptive receiver **322** outputs radio frequency signals **306** encoding data **308**.

[0066] In some illustrative examples, optical receiver **320** can also recover data **308** from radio frequency signals **306** recovered from modulated coherent optical signals **304**. For example, receiver system **314** can also include analog to digital converter that recovers data **308** from radio frequency signals **306**.

[0067] Transmitter system **316** connected to second platform **318** encodes data **308** into radio frequency signals **306** and modulates coherent optical signal using radio frequency signals **306** encoding data **308** to form modulated coherent optical signals **304**. Transmitter system **316** transmits modulated coherent optical signals **304** modulated using radio frequency signals **306** encoding data **308**.

[0068] In this illustrative example, transmitter system **316** comprises a number of different components. As depicted, transmitter system **316** comprises radio frequency modulator **336**, coherent light generator **338**, optical modulator **340**, and transmitter telescope **341**.

[0069] In this example, radio frequency modulator **336** encodes data **308** in radio frequency signals **306**. Coherent light generator **338** generates a coherent light. Coherent light generator **338** can be a laser beam generator in these examples. Optical modulator **340** modulates the coherent light using radio frequency signals **306** encoding data **308** to form modulated coherent optical signals **304**. Transmitter telescope **341** transmits modulated coherent optical signals **304** modulated using radio frequency signals **306** encoding data **308**.

[0070] In this illustrative example, first platform **312** can also have transmitter system **343** and second platform **318** can have receiver system **342**. With these components, bidirectional communication can occur between first platform **312** and second platform **318**. In this example, transmitter system **343** can generate modulated coherent optical signals **344** that have been modulated using radio frequency signals **346** encoding data **348**.

[0071] Further, data **308** encoded in radio frequency signals **306** with radio frequency signals **306** used to modulate modulated coherent optical signals **304** and data **348** encoded in radio frequency signals **346** with radio frequency signals **346** used to modulate modulated coherent optical signals **344** can take selected from at least one of voice communications, sensor data, commands, programs, transactions, messages, images, or other types of data.

[0072] In the illustrative examples, the transmission of at least one of modulated coherent optical signals **304** or modulated coherent optical signals **344** can form communications link **349**. In other words, communications link **349** can be unidirectional communications link **361** or bidirectional communications link **362** depending on the particular implementation. For example, with unidirectional communications link **361**, modulated coherent optical signals **304** can be transmitted from second platform **318** to first platform **312** or modulated coherent optical signals **344** can be transmitted from first platform **312** to second platform **318**. With bidirectional communications link **362**, both modulated coherent optical signals **304** and modulated coherent optical signals **344** can be transmitted between these two platforms.

[0073] First platform **312** and second platform **318** can take a number different forms and can be used for many different types of applications in communications environment **300**. For example, a platform, such as first platform **312** and second platform **318**, can be selected one of a mobile

platform, a stationary platform, a land-based structure, an aquatic-based structure, a space-based structure, an aircraft, a commercial aircraft, a rotorcraft, a tilt-rotor aircraft, a tilt wing aircraft, a vertical takeoff and landing aircraft, an electrical vertical takeoff and landing vehicle, a personal air vehicle, a surface ship, a tank, a personnel carrier, a train, a spacecraft, a space station, a satellite, a submarine, an automobile, a power plant, a bridge, a dam, a house, a manufacturing facility, a building, a utility pole, and a transmission tower.

[0074] In some illustrative examples, first platform **312** can be a terrestrial platform while second platform **318** can be a space platform. Communications link **349** can be used to provide indications between terrestrial locations. For example, first platform **312** can be example of satellite **204** in space **206** in FIG. 2 and second platform **318** can be an example of train **229** on land **208** in FIG. 2. In this manner, communications between space and terrestrial platforms can be performed using at least one of modulated coherent optical signals **344** and modulated coherent optical signals **344**.

[0075] Further, communications link **349** can be a point-to-point communications link **366**. For example, point-to-point communications link **366** can be an example of communications link **240** with first platform **312** being office building **214** and second platform **318** being office building **216**.

[0076] When at least one of first platform **312** and second platform **318** takes the form of a vehicle, optical communications system is referred to as vehicle communications system **370**. Vehicle communications system **370** is a system in which at least one of the platforms is a vehicle.

[0077] In another example, when sensor system **380** is used in at least one of first platform **312** or second platform **318**, optical communications system **302** is sensor data system **372**. Sensor data system **372** can take a number different forms. For example, sensor data system **372** can be comprised of at least one of at least one of a pressure sensor, a temperature sensor, a vibration sensor, a force sensor, an accelerometer, a humidity sensor, a camera, a pitot tube, a light detection and ranging sensor, a global positioning sensor device, a flow sensor, an eddy current sensor, or other sensor.

[0078] With this example, data **308** can be sensor data **307** and data **348** can be sensor data **347**. For example, second platform **318** transmitting sensor data **307** can be unmanned aerial vehicle **230** or sensor unit **219** in FIG. 2. In this example, first platform **312** can be communications tower **224**.

[0079] Sensor data **307** and sensor data **347** can take a number of different forms. For example, the sensor data can be selected from at least one of a temperature, a humidity, a pressure, a proximity, a speed, a rotation, a chemical level, a gas level, a pH, a flow rate, an elevation, a location, an attitude, an orientation, an image, an audio, or other parameters that can be measured or detected by sensor system **380**.

[0080] Additionally, radio frequency signals **306** can be formed from set of radio frequency signals that in which each radio frequency signal has a different frequency range from another radio frequency signal. These radio frequency signals can be referred to as baseband signals and used to encode data. As a result, each of these baseband signals can encode different data from other baseband signals. In this manner, these radio frequency signals encoding can be combined to form radio frequency signals **306**.

[0081] The illustration of communications environment **200** in FIG. 2 and communications environment **300** in FIG. 3 is not meant to imply physical or architectural limitations to the manner in which an illustrative embodiment may be implemented. Other components in addition to or in place of the ones illustrated may be used. Some components may be unnecessary. Also, the blocks are presented to illustrate some functional components. One or more of these blocks may be combined, divided, or combined and divided into different blocks when implemented in an illustrative embodiment.

[0082] For example, one or more platforms in addition to or in place of first platform **312** and second platform **318** can be present in communications environment **300**. As yet another example, some platforms operating in water **210** can be subsurface platforms such as a submarine.

[0083] FIG. 4 is an illustration of a block diagram of a communications system in accordance with an illustrative embodiment. Communications system **400** may be employed in communications environment **200** shown in FIG. 2 and communications environment **300** shown in FIG. 3.

[0084] Communications system **400** comprises transmitter system **402** and receiver system **404**. In this example, transmitter system **402** and receiver system **404** can each be an integrated circuit. Transmitter system **402** generates a modulated coherent optical signal **406** from a number of baseband signals **408** encoding data. Baseband is the range of frequencies occupied by a signal that has not been modulated to higher frequencies. For example, human voice is a baseband signal that is modulated higher frequencies (i.e., RF) to send and receive it via telecommunications. This RF signal is modulated by the baseband (voice) signal. The modulated coherent optical signal **406** travels over an atmospheric channel **410**, resulting in distorted modulated coherent optical signal **412**. Receiver system **404** converts this distorted modulated coherent optical signal **412** back to recovered baseband signals **414** encoding the data.

[0085] Transmitter system **402** comprises an optical transmitter **416** that receives a collective RF signal **418** produced by multiplexing a number of RF signals from RF modulators **420**, **422**, **424**. RF modulators **420**, **422**, **424** generate the RF signals from baseband signals **426**, **428**, **430**, respectively.

[0086] Receiver system **404** comprises an optical receiver **432** that produces an input current **434** in response to the distorted modulated coherent optical signal **412**. An adaptive receiver **436** converts the input current **434** into a recovered RF signal **438**. The recovered RF signal **438** is demodulated by a number of RF demodulators **440**, **442**, **444** into respective recovered baseband signals **446**, **448**, **450**.

[0087] FIG. 5 is an illustration of a block diagram of a communications system depicting details of the optical transmitter and optical receiver in accordance with an illustrative embodiment.

[0088] Optical transmitter **416** comprises a laser generator **502** that generates a coherent light (optical carrier) that travels along a fiber optic **504**. Optical modulator **506** modulates the coherent light to encode an amplified RF signal **508** to a modulated coherent optical signal **510**. The amplified RF signal **508** is generated by an optical modulator driver **512** from the collective RF signal **418**. A transmitter telescope **514** transmits the modulated coherent optical signal **510** to optical receiver **432**.

[0089] Optical receiver **432** comprises a receiver telescope **516** that receives the distorted modulated optical signal and passed it to adaptive optics **518**. Adaptive optics **518** may comprise, for example, a number of corrective mirrors and a beam splitter for performing wavefront modification. The adaptive optics **518** pass the optical signal to optical amplifier **520**, which produces an amplified optical signal **522**. Optical bandpass filter **524** generates an amplified band-limited optical signal **526**, which photodiode **528** uses to generate input current **434**.

[0090] FIG. 6 is an illustration of a block diagram of an adaptive receiver in accordance with an illustrative embodiment. FIG. 6 provides a more detailed view of the adaptive receiver **436** in FIG. 4.

[0091] Adaptive receiver **436** comprises a current buffer **602** that receives the input current **434** from photodiode **528**. Adaptive receiver **436** may be implemented as an integrated circuit (IC). Current buffer **602** may be a feedback-applied current buffer that provides minimum impedance at the input node while consuming the least DC power.

[0092] An inverter-based transimpedance **604** receives input from the current buffer **602**. Inverter-based transimpedance **604** may be a variable gain, inverter-based, transimpedance amplifier. In this example, the average current control loop **606** adaptively controls the average current into current buffer **602**. An average current control loop **606** feeds back from the inverter-based transimpedance **604** to the current buffer **602**. Average current control loop **606** comprises a low-pass filter **608**, amplifier **610**, and a voltage-controlled current source **611**. The average current control loop **606** automatically subtracts the photodiode's excessive average current from the input node to avoid

saturation of early stages of adaptive receiver **436**.

[0093] In this illustrative example, the low-pass filter **608** has an input connected to an output of inverter-based transimpedance **604**. The low-pass filter **608** receives a variable gain voltage (Out+) from inverter-based transimpedance **604** and outputs an average level of the variable gain voltage (Out+) as an average voltage (VX). The amplifier **610** has a first input that receives the average voltage (VX) from the low pass filter and a second input that receives a reference voltage (Vref). The amplifier **610** outputs an output voltage. The voltage output from the amplifier **610** becomes greater as the average voltage (VX) from the low-pass filter **608** becomes greater than reference voltage (Vref). The voltage-controlled current source **611** is controlled by the output voltage (VO) output from the amplifier. The voltage-controlled current source **611** reduces the average current into the current buffer **602** as the output voltage received from the amplifier increases.

[0094] In this example, the loop controls the output voltage (VX) from the low-pass filter **608** to be equal to the reference voltage (Vref). This reference voltage (Vref) can be set at conditions without turbulence or scintillation. These conditions can be optimum or desired conditions for the propagation of coherent light signals through the atmosphere.

[0095] Thus, the average current control loop **606** extracts the average level of the output voltage (Out+) output from inverter-based transimpedance **604** using low-pass filter **608** and comparing the voltage Out+ with the reference voltage (Vref). Low-pass filter **608** can be a passive low pass filter. The amplifier **610** amplifies the difference between the desired average voltage set by the reference voltage (Vref) and the average voltage (VX) and drives the voltage-controlled current source **611**. For example, if output (VX) from the low-pass filter **608** is larger than the reference voltage (Vref), the amplifier **610** provides larger voltage to the voltage-controlled current source **611**, which causes higher average current being drawn from the input node, leading to lower average current to the block current buffer **602**. As a result, a lower average voltage (VX) is output by inverter-based transimpedance **604**.

[0096] As result, in these illustrative examples, the average current control loop **606** provided feedback can automatically subtract the average current for input current **434** received from the photodiode to reduce the occurrence of saturation within adaptive receiver **436**.

[0097] A variable gain circuit **612** receives input from the inverter-based transimpedance **604**. Variable gain circuit **612** comprises a differential transadmittance (Gm) amplifier **614** that converts input voltage to current and a differential transimpedance amplifier **616** that converts the current back to voltage. The variable gain circuit **612** uses Miller capacitances C1, C2 to decrease total capacitance at output of the differential transadmittance amplifier, thereby increasing bandwidth. Based on the Miller theorem, when a capacitor is connected between input/output of an amplifier, the equivalent circuit is composed of two capacitors in the input and output as shown. If the gain A is positive, the input capacitor will be negative ($\approx CM(-A)$). Same in the circuit, the equivalent negative capacitances of C1 and C2 at nodes A and B will be added to the parasitic capacitances that already exist on these nodes and hence reduce the total capacitances in them making them non-dominant poles.

[0098] A differential voltage amplifier **618** receives input from the variable gain circuit **612**. Output from the differential voltage amplifier **618** is fed into an automatic gain control loop **620** and offset cancellation loop **626**.

[0099] Automatic gain control loop **620** comprises a peak detector **622** and an integrator **624**. Automatic gain control loop **620** detects the peak of differential output of differential voltage amplifier **618** and generates the controlling voltage to the inverter-based transimpedance **604** and variable gain circuit **612**.

[0100] As depicted, the peak detector **622** detects a peak voltage of a differential voltage (Va+ and Va-) output from the differential voltage amplifier **618**. In this example, Va+ and Va- are amplified voltages V+ and V-. The differential voltage is the difference between Vat and Va- output from differential voltage amplifier **618**. Peak detector **622** outputs a peak voltage (VP) at a detector

output. The peak voltage (VP) is the greatest differential voltage output by differential voltage amplifier **618**.

[0101] The integrator **624** receives the peak voltage (VP) from the peak detector **622** and a reference peak voltage (VPR). The integrator **624** outputs an integrated gain controlling voltage signal (VAGC) that controls a peak-to-peak value of the differential voltage output by the variable gain circuits.

[0102] In this example, the variable gain circuits are inverter-based transimpedance **604** and differential transimpedance amplifier **616**. As depicted, metal-oxide-semiconductor field-effect transistor (MOSFET) **670** and metal-oxide-semiconductor field-effect transistor (MOSFET) **671** are used to change the resistance to control the gain. For example, increased resistance increases the gain through the circuits. Decreasing the resistance decreases the gain for the circuits. When peak voltage (VP) is greater than reference peak voltage (VPR), the gain is reduced for both inverter-based transimpedance **604** and differential transimpedance amplifier **616**. In this manner, the situation in which nonlinearity occurs in these circuits can be reduced or avoided. In this example, reference peak voltage (VPR) is set at a voltage to cause a reduction gain when peak voltage (VP) is higher than the reference peak voltage (VPR).

[0103] As result, automatic gain control loop **620** can reduce errors or distortions in the recovery of coherent light signals modulated with radio frequency signals encoding data caused by atmospheric conditions. For example, turbulence or other atmospheric conditions can cause the peak-to-peak level of the received signal to vary. As a result, when the adaptive receiver **436** detects the incoming coherent light has very high amplitude, the variable gain circuits in the adaptive receiver **436** can leave the linear region and enter the non-linear region.

[0104] In this example, automatic gain control loop **620** can operate to avoid this situation. As a result, a loss of information caused by operating in a nonlinear region can be reduced or avoided. In these examples, when a circuit operates in a nonlinear region, radio frequency signal encoding data in the noncoherent light can be clipped, resulting in reduced quality of the signal and potential loss of data.

[0105] Thus, the automatic gain control loop **620** extracting the peak voltage (VP) for the output voltage of differential voltage amplifier **618** using a peak detector **622** and comparing the peak voltage (VP) with a preset reference peak voltage (VPR). The result of this comparison is integrated in a capacitor C1 and generates the gain controlling voltage (VAGC). If the peak voltage (VP) is higher than preset reference voltage (VPR), the gain controlling voltage (VAGC) reduces the gain of inverter-based transimpedance **604** and the variable gain circuit **612** by decreasing the variable resistors in the feedback of these components. As a result, the gain can be reduced and a lower peak voltage (VP) is achieved such that the operation of these components can be within the desired operating range to reduce data loss.

[0106] The offset cancellation loop **626** averages the voltages received from differential voltage amplifier **618**. The offset cancellation loop **626** comprises a low-pass filter **628**, a second differential amplifier, **630** and a differential transadmittance (Gm) amplifier **632**. Offset cancellation loop **626** feeds back from the differential voltage amplifier **618** to variable gain circuit **612** and uses the differential transadmittance amplifier **632** to draw the corrective currents from the differential transadmittance amplifier **614** output. In this example, the offset cancellation loop **626** feeds back from the differential voltage amplifier **618** to the variable gain circuit **612** that adaptively controls a bias point of the differential voltage amplifier **618** to obtain a desired bias point for the differential voltage amplifier **618**. The control of the bias point can be set to obtain the highest quality signal in terms of the allowed swing and also improving linearity in the operation of the differential stages, the variable gain circuit **612**, the differential voltage amplifier **618**, and the differential buffer **634**. Without maintaining a desired level for the bias point, the top or bottom of the signal may be clipped resulting in data loss.

[0107] As depicted, the low-pass filter **628** receives the differential voltage output from the

differential voltage amplifier **618**. The differential voltage is the difference between V_{a+} and V_{a-} . In this example V_{a+} and V_{a-} are amplified voltages V_+ and V_- output from differential voltage amplifier **618**. Low-pass filter **628** outputs filtered voltages (V_{f+} and V_{f-}) that are averages of the differential voltage voltages V_{a+} and V_{a-} . Differential amplifier **630** receives the average outputs (V_{f+} and V_{f-}) from low-pass filter **628**. Differential amplifier **630** outputs amplified difference voltages (V_{o1} and V_{o2}).

[0108] In this example, the differential transadmittance amplifier **632** receives the amplified difference voltages (V_{o1} and V_{o2}) output from the differential amplifier **630**. The differential transadmittance amplifier **632** is connected to outputs of differential transadmittance amplifier **614**, in the variable gain circuit **612** that controls the bias point of the differential voltage amplifier **618**. A differential buffer **634** receives input from the differential voltage amplifier **618** and outputs the recovered RF signal **438**. In this example, the differential buffer **634** outputs a recovered RF signal **438** encoding data. The differential buffer **634** has inductive load to interface the adaptive receiver **436** to measurement equipment while providing inductive peaking for bandwidth enhancement.

[0109] Thus, the offset cancellation loop **626** extracts the average voltage level (V_{f+} and V_{f-}) of each output voltage (V_{a+} and V_{a-}) from the differential voltage amplifier **618** and amplifies the difference between these output voltages (V_{f+} and V_{f-}) to output amplified voltages (V_{o1} and V_{o2}). The difference between these two voltages ($V_{o2}-V_{o1}$) is the amplified offset voltage of the signal at the output of differential voltage amplifier **618**. This differential voltage ($V_{o2}-V_{o1}$) is converted to a differential current using a G_m stage, differential transadmittance amplifier **632**, and supplies or subtracts corrective currents to/from node A and B in the variable gain circuit **612** until the average level of differential voltage amplifier **618** differential voltages output by differential voltage amplifier **618** equal each other, resulting in a zero offset.

[0110] FIG. 7 is an illustration of a circuit diagram of an example implementation of the adaptive receiver **436** in accordance with an illustrative embodiment.

[0111] With reference next to FIG. 8, an illustration of a block diagram of an optical test system is depicted in accordance with an illustrative embodiment. In this illustrative example, optical test system **800** is an example of a test system that can be used to test and adjust components can receiver, such as adaptive receiver **436** in receiver system **404** in FIG. 4.

[0112] In this illustrative example, optical test system **800** comprises a number of different components. As depicted, optical test system **800** comprises transmitter system **802**, propagation medium simulator **804**, receiver system **806**, analog-to-digital (ADC) system **808**, and analyzer **810**.

[0113] In this illustrative example, transmitter system **802** transmits modulated coherent optical signals **820** that have been modulated using radio frequency signals **822** encoding test data **824**. In other words, radio frequency signals **822** encoding test data **824** are encoded in modulated coherent optical signals **820**.

[0114] As depicted, propagation medium simulator **804** receives modulated coherent optical signals **820** from transmitter system **802**. Propagation medium simulator **804** changes a set of optical attributes **826** for modulated coherent optical signals **820** to model propagation of modulated coherent optical signals **820** through propagation environment to form varied modulated coherent optical signals **828** and outputs varied modulated coherent optical signals **828**. As depicted, varied modulated coherent optical signals **828** encode radio frequency signals **822** encoding test data **824**.

[0115] In this example, the change in the set of optical attributes **826** can include a variation in optical intensity. Other attributes that can be changed include, for example, a phase, the wavelength, or other attributes for modulated coherent optical signals **820**.

[0116] In this example, receiver system **806** receives varied modulated coherent optical signals **828** from propagation medium simulator **804**. Receiver system **806** recovers radio frequency signals **822** encoding test data **824** from varied modulated coherent optical signals **828** in a manner that adjusts for changes in the varied modulated coherent optical signals **828** caused by variation in the

set of optical attributes **826** in varied modulated coherent optical signals **828** generated by the propagation medium simulator **804**. As depicted, receiver system **806** outputs radio frequency signals **822** encoding test data **824** recovered from varied modulated coherent optical signals **828**. [0117] In this example, analog to digital system **808** can extract test data **824** from radio frequency signals **822**, and outputs recovered data **830**. In this example, analyzer **810** can compare recovered data **830** with test data **824** used to modulate radio frequency signals **822** to encode test data **824** in radio frequency signals **822**.

[0118] In this illustrative example, analyzer **810** is located in computer system **832**. Computer system **832** is a physical hardware system and includes one or more data processing systems. When more than one data processing system is present computer system **832**, those data processing systems are in communication with each other using a communications medium. The communications medium may be a network. The data processing systems may be selected from at least one of a computer, a server computer, a tablet, or some other suitable data processing system. [0119] As depicted, computer system **832** includes a number of processor units **834** that are capable of executing program instructions **836** implementing processes such as those for analyzer **810** in the illustrative examples. In other words, program instructions **836** are computer readable program instructions.

[0120] As used herein, a processor unit in the number of processor units **834** is a hardware device and is comprised of hardware circuits such as those on an integrated circuit that respond to and process instructions and program code that operate a computer. When the number of processor units **834** executes program instructions **836** for a process, the number of processor units **834** can be one or more processor units that are on the same computer or on different computers. In other words, the process can be distributed between processor units **834** on the same or different computers in a computer system **832**. Further, the number of processor units **834** can be of the same type or different type of processor units. For example, a number of processor units **834** can be selected from at least one of a single core processor, a dual-core processor, a multi-processor core, a general-purpose central processing unit (CPU), a graphics processing unit (GPU), a digital signal processor (DSP), or some other type of processor unit.

[0121] In the depicted example, optical test system **800** can also include fiber simulator **840**. In this example, fiber simulator **840** can be located within receiver system **806** and can simulate a change in the set of optical attributes **826** to model propagation of the modulated coherent optical signals through a set of optical fibers. For example, fiber simulator **840** can simulate losses such as those in signal amplitude from modulated coherent signals traveling through a set of optical fibers.

[0122] With reference next to FIG. 9, an illustration of a block diagram of a transmitter system is depicted in accordance with an illustrative embodiment. In this illustrative example, an example of an implementation for transmitter system **802** in optical test system **800** in FIG. 8 is illustrated. As depicted in this example, transmitter system **802** comprises radio frequency signal generator **900**, laser source **904**, and optical modulator **906**.

[0123] Radio frequency signal generator **900** can generate radio frequency signals **822** encoding test data **824**. These radio frequency signals encoding test data **824** are sent to optical modulator **906** which modulates laser beam **910** generated by laser source **904**. The modulation of laser beam **910** generates modulated coherent optical signals **820** that are modulated using radio frequency signals **822** encoding test data **824**. These modulated coherent optical signals can then be sent to propagation medium simulator **804**.

[0124] Tuning to FIG. 10, an illustration of a block diagram for a receiver system is depicted in accordance with an illustrative embodiment. In this illustrative example, an example of an implementation for receiver system **806** in optical test system **800** in FIG. 8 is illustrated. As depicted in this example, receiver system **806** comprises receiver telescope **1000**, optical amplifier **1001**, optical bandpass filter **1002**, photodiode **1004**, adaptive receiver **1006**. As depicted, fiber simulator **840** connects optical bandpass filter **1002** to photodiode **1004**.

[0125] As depicted, receiver telescope **1000** comprises optics and other components that receive varied modulated coherent optical signals **828** from propagation medium simulator **804**. In this illustrative example, receiver telescope **1000** sends varied modulated coherent optical signals **828** to optical amplifier **1001**. Optical amplifier **1001** amplifies varied modulated coherent optical signals **828** to form amplified modulated coherent optical signals **1020**. These amplified signals are output and sent to optical bandpass filter **1002**.

[0126] Optical bandpass filter **1002** receives amplified modulated coherent optical signals **1020** and filters amplified modulated coherent optical signals **1020** to form band limited modulated coherent optical signals **1022** that encodes radio frequency signals **822** encoding test data **824**. In this example, optical bandpass filter **1002** passes a range of frequencies in which radio frequency signals **822** encoding test data **824** are expected to be present within the modulated optical signals.

[0127] In this illustrative example, band limited modulated coherent optical signals **1022** are received by fiber simulator **840**. In this example, fiber simulator **840** changes the set of optical attributes **826** in band limited modulated coherent optical signals **1022** to model propagation of the modulated coherent optical signals through a set of optical fibers. In this example, fiber simulator **840** outputs attenuated modulated coherent optical signals **1024**. This change to the set of optical attributes **826** can be used to model losses such as those in signal amplitude from optical signals traveling through optical fibers.

[0128] In this example, photodiode **1004** receives attenuated modulated coherent optical signals **1024** from fiber simulator **840** and generates input current **1026** in response to detecting attenuated modulated coherent optical signals **1024**. Input current **1026** is sent to adaptive receiver **1006**. Which recovers radio frequency signals **822** encoding test data **824**.

[0129] In this illustrative example, propagation medium simulator **804** and fiber simulator **840** can set modulated optical attributes **826** to simulate ideal or desired conditions for operating receiver system **806**. Under these ideal conditions, various outputs for components within adaptive receiver **1006** can be used to select voltages for operating the adaptive receiver **1006**.

[0130] For example, an average current control loop in adaptive receiver **1006** can have a reference voltage for an amplifier in the average current control loop used as a reference voltage for that amplifier output under the desired or ideal conditions. As another example, in an automatic gain control loop in adaptive receiver **1006**, the reference peak voltage for an integrator in the automatic gain control loop can have its reference voltage set as the peak voltage of the differential voltage output by the integrator under the desired conditions.

[0131] Turning next to FIG. **11**, a flowchart of a process for method for communicating data with a platform is depicted in accordance with an illustrative embodiment. The process in FIG. **11** can be implemented in hardware, software, or both. When implemented in software, the process can take the form of program instructions that is run by one of more processor units located in one or more hardware devices in one or more computer systems. For example, the process can be implemented in platform **310** which can be first platform **312** using receiver system **314** in FIG. **3**.

[0132] The process begins by receiving modulated coherent optical signals modulated using radio frequency signals encoding data (operation **1100**). The process generates an input current using modulated coherent optical signals modulated using radio frequency signals encoding data in response to receiving the modulated coherent optical signals at a receiver system in the platform (operation **1102**). The process recovers the radio frequency signals from the input current in a manner that adjusts for changes in the modulated coherent optical signals caused by variations in received optical intensity occurring during propagation of the modulated coherent optical signals (operation **1104**).

[0133] The process outputs the radio frequency signals encoding the data (operation **1106**). The process terminates thereafter.

[0134] With reference to FIG. **12**, a flowchart of a process for method for communicating data with a platform is depicted in accordance with an illustrative embodiment. The process in FIG. **12** can

be implemented in hardware, software, or both. When implemented in software, the process can take the form of program instructions that is run by one of more processor units located in one or more hardware devices in one or more computer systems. For example, the process can be implemented in second platform **318** using transmitter system **316** in FIG. **3**. The operations in this flowchart can be additional operations performed with the operations depicted in FIG. **11**.

[0135] The process begins by encoding the data into the radio frequency signals (operation **1200**). The process modulates a coherent optical signal using the radio frequency signals encoding the data to form the modulated coherent optical signals (operation **1202**).

[0136] The process transmits the modulated coherent optical signals modulated using the radio frequency signals encoding the data to the second platform (operation **1204**). The process terminates thereafter.

[0137] Turning to FIG. **13**, a flowchart of a process for method for communicating data with a vehicle is depicted in accordance with an illustrative embodiment. The process in FIG. **13** can be implemented in hardware, software, or both. When implemented in software, the process can take the form of program instructions that is run by one of more processor units located in one or more hardware devices in one or more computer systems. For example, the process can be implemented in first platform **312** using receiver system **314** in FIG. **3**.

[0138] The process begins by receiving modulated coherent optical signals modulated using radio frequency signals encoding the data (operation **1300**). The process generates an input current using the modulated coherent optical signals modulated using radio frequency signals encoding the data in response to receiving the modulated coherent optical signals at a receiver system in the vehicle (operation **1302**). The process recovers the radio frequency signals from the input current in a manner that adjusts for changes in the modulated coherent optical signals caused by variations in received optical intensity occurring during propagation of the modulated coherent optical signals (operation **1304**).

[0139] The process outputs the radio frequency signals encoding the data (operations **1306**). The process terminates thereafter.

[0140] With reference to FIG. **14**, a flowchart of a process for method for communicating data with a vehicle is depicted in accordance with an illustrative embodiment. The process in FIG. **14** can be implemented in hardware, software, or both. When implemented in software, the process can take the form of program instructions that is run by one of more processor units located in one or more hardware devices in one or more computer systems. For example, the process can be implemented in second platform **318** using transmitter system **316** in FIG. **3**. The operations in this flowchart can be additional operations performed with the operations depicted in FIG. **13**.

[0141] The process begins by encoding the data into the radio frequency signals (operation **1400**). The process modulates a coherent optical signal using the radio frequency signals encoding the data to form the modulated coherent optical signals (operation **1402**).

[0142] The process transmits the modulated coherent optical signals modulated using radio frequency signals encoding data (operation **1404**). The process terminates thereafter.

[0143] In FIG. **15**, a flowchart of a process for method for communicating sensor data is depicted in accordance with an illustrative embodiment. The process in FIG. **15** can be implemented in hardware, software, or both. When implemented in software, the process can take the form of program instructions that is run by one of more processor units located in one or more hardware devices in one or more computer systems. For example, the process can be implemented in first platform **312** using receiver system **314** in FIG. **3** to receive sensor data such as sensor data **307** and sensor data **347** in FIG. **3**.

[0144] The process begins by receiving modulated coherent optical signals modulated using radio frequency signals encoding sensor data (operation **1500**). The process generates an input current using modulated coherent optical signals modulated using radio frequency signals encoding sensor data in response to receiving the modulated coherent optical signals (operation **1502**). The process

recovers the radio frequency signals from the input current in a manner that adjust for changes in the modulated coherent optical signals caused by variation in received optical intensity occurring during propagation of the modulated coherent optical signals (operation **1504**). The process outputs the radio frequency signals encoding the sensor data (operation **1506**). The process terminates thereafter.

[0145] Turning to FIG. **16**, a flowchart of a process for method for communicating sensor data is depicted in accordance with an illustrative embodiment. The process in FIG. **16** can be implemented in hardware, software, or both. When implemented in software, the process can take the form of program instructions that is run by one of more processor units located in one or more hardware devices in one or more computer systems. For example, the process can be implemented in second platform **318** using transmitter system **343** and sensor system **380** in FIG. **3** to transmit to receive sensor data such as sensor data **307** and sensor data **347** in FIG. **3**. The operations in this flowchart can be additional operations performed with the operations depicted in FIG. **15**.

[0146] The process begins by encoding the sensor data in the radio frequency signals (operation **1600**). The process modulates a coherent optical signal using the radio frequency signals encoding the sensor data to form the modulated coherent optical signals (operation **1602**).

[0147] The process transmits the modulated coherent optical signals modulated using the radio frequency signals encoding the sensor data (operation **1604**). The process terminates thereafter.

[0148] Turning next to FIG. **17**, an illustration of a flowchart of a process for testing a receiver system is depicted in accordance with an illustrative embodiment. In this illustrative example, the process can be performed using optical system test system **800** in FIG. **8**.

[0149] The process begins by identifying test data for transmission (operation **1700**). The process identifies a propagation environment through which optical signals are to be propagated (operation **1702**). This test propagation environment can have various parameters that affect the propagation of coherent optical signals through that test environment. For example, the parameters for the environment can be visibility, moisture, particles, distance, and other parameters that are set based on the conditions for which the test is to be performed. For example, these parameters may be selected for conditions such as cloud cover, rain, snow, a thunderstorm, an ash from active volcano, pollution, ozone, or other environments. In one illustrative example, the environment can be set as an ideal environment in which the optimum conditions are present for propagating optical signals.

[0150] The process selects a propagation medium simulator to change the optical attributes for the modulated coherent optical signals that encode radio frequency signals encoding test data to simulate the parameters in the propagation environment (operation **1704**).

[0151] In operation **1704**, the propagation medium simulator changes the optical attributes in a manner that can reflect fluctuations in optical attributes such as intensity. This this simulator can change the intensity to reflect increases and decreases that may occur through the propagation of the modulated coherent optical signals through the atmosphere. Thus, optical attributes such as intensity can change as the modulated coherent optical signal that is received by the receiver system. For example, the modulated coherent optical signal can have a greater intensity at one time and a lower at another time because of the propagation through the atmosphere.

[0152] In this example, the optical attributes are selected to model the propagation of the modulated coherent signals through the propagation environment. For example, the parameters for the environment can be visibility, moisture, particles, and other parameters. The propagation medium simulator can be implemented using various types of modeling techniques. For example, the propagation medium simulator can take the form of a machine learning model, measurements made over time for the environment to be simulated, and other techniques. In this example, the propagation medium simulator can propagate different propagation environments such as space to ground transmission environments, point-to-point transmission environments in an urban area, and other types of environments.

[0153] The process identifies parameters for a particular environment that can be used to set optical

attributes such as attenuation, intensity fluctuations, phase change, frequency and other attributes that are affected based on the parameters for the selected test environment (operation **1706**). In this example, these selected parameters can change.

[0154] The process selects a fiber simulator to change the optical attributes to simulate propagation of a modulated coherent optical signal through a set of optical fibers (operation **1708**).

[0155] The process generates radio frequency signals encoding the test data (operation **1710**). The process generates modulated coherent optical signals modulated using the radio frequency signals encoding the test data (operation **1712**).

[0156] The process transmits modulated coherent optical signals modulated using radio frequency signals encoding test data through the propagation medium simulator and the fiber simulator to the adaptive receiver in the receiver system (operation **1714**). The process recovers the radio frequency signals encoding the test data using the adaptive receiver (operation **1716**). The process recovers data from the radio frequency signals encoding the test data (operation **1718**). The process adjusts optical attributes for the modulated coherent optical signals using the selected propagation medium simulator (operation **1720**). The process compares the recovered data with the test data used to create the radio frequency signals to generate the comparison (operation **1722**). The process terminates thereafter.

[0157] Turning next to FIG. **18**, a flowchart of a process for selecting settings four and adaptive receiver is depicted in accordance with an illustrative embodiment. In this illustrative example, the process can be performed using optical test system **800** in FIG. **8**.

[0158] The process begins by identifying a propagation environment through which optical signals are to be propagated when desired conditions are present (operation **1800**). For example, with a satellite to ground station transmission environment, the desired conditions can be optimal conditions present the for transmitting signals between a satellite and ground station. As another example, an environment in which signals are propagated between aircraft in flight can be selected.

[0159] The process selects a propagation simulator for the selected propagation environment (operation **1802**). In this example, the propagation simulator can set optical attributes to simulate the propagation of modulated coherent optical signals in the desired conditions. In other words, these optical attributes reflect changes in intensity, phase, or other parameters that can occur under desired conditions.

[0160] The process initiates a test using the optical test system with the selected propagation simulator (operation **1804**). The process monitors outputs from components in the adaptive receiver (operation **1806**). The process selects reference values for inputs to the adaptive receiver based on the outputs from the components detected during the test (operation **1808**). The process terminates thereafter.

[0161] For example, reference voltages to components can be selected for use in the adaptive operation of the adaptive receiver. These reference voltages can be selected to cause the adaptive receiver to maintain the operation of the components within the desired operating range. In one example, the output of an amplifier in an average current control loop can be used as the reference voltage for that amplifier. As another example, a peak voltage of a differential voltage output by a differential amplifier can be used as the reference peak voltage for an integrator in the automatic gain control loop in the adaptive receiver. In other words, the operation of components within the adaptive receiver can be controlled to reduce or avoid nonlinearity in the processing of a current to recover radio frequency signals encoding data.

[0162] The flowcharts and block diagrams in the different depicted embodiments illustrate the architecture, functionality, and operation of some possible implementations of apparatuses and methods in an illustrative embodiment. In this regard, each block in the flowcharts or block diagrams can represent at least one of a module, a segment, a function, or a portion of an operation or step. For example, one or more of the blocks can be implemented as program instructions, hardware, or a combination of the program instructions and hardware. When implemented in

hardware, the hardware can, for example, take the form of integrated circuits that are manufactured or configured to perform one or more operations in the flowcharts or block diagrams. When implemented as a combination of program instructions and hardware, the implementation may take the form of firmware. Each block in the flowcharts or the block diagrams can be implemented using special purpose hardware systems that perform the different operations or combinations of special purpose hardware and program instructions run by the special purpose hardware.

[0163] In some alternative implementations of an illustrative embodiment, the function or functions noted in the blocks may occur out of the order noted in the figures. For example, in some cases, two blocks shown in succession may be performed substantially concurrently, or the blocks may sometimes be performed in the reverse order, depending upon the functionality involved. Also, other blocks may be added in addition to the illustrated blocks in a flowchart or block diagram.

[0164] The description of the different illustrative embodiments has been presented for purposes of illustration and description and is not intended to be exhaustive or limited to the embodiments in the form disclosed. The different illustrative examples describe components that perform actions or operations. In an illustrative embodiment, a component can be configured to perform the action or operation described. For example, the component can have a configuration or design for a structure that provides the component an ability to perform the action or operation that is described in the illustrative examples as being performed by the component. Further, to the extent that terms “includes”, “including”, “has”, “contains”, and variants thereof are used herein, such terms are intended to be inclusive in a manner similar to the term “comprises” as an open transition word without precluding any additional or other elements.

[0165] Many modifications and variations will be apparent to those of ordinary skill in the art. Further, different illustrative embodiments may provide different features as compared to other desirable embodiments. The embodiment or embodiments selected are chosen and described in order to best explain the principles of the embodiments, the practical application, and to enable others of ordinary skill in the art to understand the disclosure for various embodiments with various modifications as are suited to the particular use contemplated.

Claims

1. An optical test system that comprises: a transmitter system configured to transmit modulated coherent optical signals modulated based upon radio frequency signals that encode test data; a propagation medium simulator configured to: receive the modulated coherent optical signals from the transmitter system; change a set of optical attributes for the modulated coherent optical signals to model propagation of the modulated coherent optical signals through a propagation environment to form varied modulated coherent optical signals; and output the varied modulated coherent optical signals; and an optical receiver system configured to: receive the varied modulated coherent optical signals from the propagation medium simulator; and recover the radio frequency signals that encode the test data from the varied modulated coherent optical signals in a manner that adjusts for changes in the varied modulated coherent optical signals caused by a variation in a set of optical attributes in the varied modulated coherent optical signals generated by the propagation medium simulator; and an analog to digital system configured to extract the test data from the radio frequency signals, and outputs recovered data.
2. The optical test system of claim 1, further comprising an analyzer configured to compare the test data with the recovered data and form a comparison.
3. The optical test system of claim 1, further comprising a fiber simulator configured to change the set of optical attributes to model propagation of the modulated coherent optical signals through a set of optical fibers.
4. The optical test system of claim 1, wherein the optical receiver system comprises: an optical receiver that receives the varied modulated coherent optical signals and generates an input current

using the varied modulated coherent optical signals.

5. The optical test system of claim 1, wherein the optical receiver system comprises: an optical receiver configured to receive the varied modulated coherent optical signals and generates an input current using the varied modulated coherent optical signals; and an adaptive receiver configured to receive the input current and recovers the radio frequency signals that encode the test data from the varied modulated coherent optical signals in the manner that adjusts for changes in the varied modulated coherent optical signals caused by the variation in a received varied optical intensity generated by the propagation medium simulator, extracts the test data from the radio frequency signals, and outputs the recovered data.

6. The optical test system of claim 5, wherein the optical receiver comprises: an optical amplifier that receives the varied modulated coherent optical signals and amplifies the varied modulated coherent optical signals to form amplified modulated coherent optical signals; an optical bandpass filter that receives the amplified modulated coherent optical signals and filters the amplified modulated coherent optical signals to form band limited modulated coherent optical signals; and a photodiode system that receives the band limited modulated coherent optical signals and generates the input current in response to receiving the band limited modulated coherent optical signals.

7. The optical test system of claim 5, wherein the optical receiver comprises: an optical amplifier that receives the varied modulated coherent optical signals and amplifies the varied modulated coherent optical signals to form amplified modulated coherent optical signals; and an optical bandpass filter that receives the amplified modulated coherent optical signals and filters the amplified modulated coherent optical signals to form band limited modulated coherent optical signals.

8. The optical test system of claim 5, wherein the optical receiver comprises: an optical amplifier that receives the varied modulated coherent optical signals and amplifies the varied modulated coherent optical signals to form amplified modulated coherent optical signals; an optical bandpass filter that receives the amplified modulated coherent optical signals and filters the amplified modulated coherent optical signals to form band limited modulated coherent optical signals; a fiber simulator that receives the band limited modulated coherent optical signals and adjust a set of optical attributes for band limited modulated coherent optical signals that simulates change in the set of optical attributes for the band limited modulated coherent optical signals to model propagation of the band limited modulated coherent optical signals through an optical fiber to form simulated optical signals; and a photodiode system that receives simulated optical signal and generates the input current in response to the simulated optical signals.

9. The optical test system of claim 1, wherein the optical receiver system comprises: an optical amplifier that amplifies the varied modulated coherent optical signals to form amplified modulated coherent optical signals; and an optical bandpass filter receives the amplified modulated coherent optical signals from an output of the amplifier and outputs a filtered modulated coherent optical signals within a frequency range, wherein a fiber simulator receives the filtered modulated coherent optical signals within the frequency range output from the optical bandpass filter.

10. The optical test system of claim 1, wherein the optical receiver system comprises: an optical amplifier that amplifies the varied modulated coherent optical signals to form amplified modulated coherent optical signals; an optical bandpass filter receives the amplified modulated coherent optical signals from an output of the amplifier and outputs a filtered modulated coherent optical signals within a frequency range, wherein a fiber simulator receives the filtered modulated coherent optical signals within the frequency range output from the optical bandpass filter; a photodiode that receives the filtered modulated coherent optical signals within the frequency range and outputs an input current; and an adaptive receiver that receives the input current from the photodiode, recovers the radio frequency signals that encode the test data from the input current in a manner that adjusts for changes in the varied modulated coherent optical signals caused by variation in received optical intensity caused by propagation medium simulator, and outputs the radio frequency signals that

encode the test data.

11. The optical test system of claim 1, wherein the optical receiver system comprises: an optical amplifier that amplifies the varied modulated coherent optical signals to form amplified modulated coherent optical signals; an optical bandpass filter receives the amplified modulated coherent optical signals from an output of the amplifier and outputs a filtered modulated coherent optical signals within a frequency range, wherein a fiber simulator receives the filtered modulated coherent optical signals within the frequency range output from the optical bandpass filter; a photodiode that receives the filtered modulated coherent optical signals within the frequency range and outputs an input current; an adaptive receiver that receives the input current from the photodiode, recovers the radio frequency signals that encode the test data from the input current in a manner that adjusts for changes in the varied modulated coherent optical signals caused by variation in received optical intensity caused by propagation medium simulator, and outputs the radio frequency signals encoding the test data; and an analog to digital converter that receives the radio frequency signals encoding the data, converts the radio frequency signals that encode the test data into recovered data, and outputs the recovered data.

12. The optical test system of claim 5, wherein the adaptive receiver comprises: a current buffer that receives the input current; an inverter based transimpedance circuit that receives a buffered current from the current buffer and converts the buffered current to a variable gain voltage; an average current control loop that feeds back from the inverter based transimpedance circuit to the current buffer, wherein the average current control loop adaptively controls an average current that goes into the current buffer; a variable gain circuit that receives the variable gain voltage from the inverter based transimpedance circuit and outputs a differential voltage; a differential amplifier that receives the differential voltage output from the variable gain circuit and outputs an amplified differential voltage; an automatic gain control loop that feeds back from the differential amplifier to the inverter based transimpedance circuit and variable gain circuit, wherein the automatic gain control loop adaptively controls a peak to peak voltage output by the differential amplifier based on a desired peak-to-peak level for the output of the differential amplifier; and a differential buffer that receives the amplified differential voltage output from the differential amplifier and outputs the radio frequency signals that encode the test data.

13. The optical test system of claim 12, wherein the propagation medium simulator is further configured to: change a set of optical attributes of the modulated coherent optical signals to model propagation of the modulated coherent optical signals through a propagation environment; and output the varied modulated coherent optical signals as a simulator output.

14. The optical test system of claim 13, wherein the average current control loop comprises: a low pass filter having an input connected to an output of the inverter based transimpedance circuit, wherein the low pass filter is configured to receive the variable gain voltage from the inverter based transimpedance circuit and outputs an average level of the variable gain voltage as an average voltage; an amplifier having a first input configured to receive the average voltage from the low pass filter and a second input that receives a reference voltage and outputs an output voltage, wherein as the voltage output from the amplifier becomes greater as the average voltage from the low pass filter becomes greater than reference voltage; and a voltage-controlled current source controlled by the output of the amplifier, wherein the voltage-controlled current source reduces the average current into the current buffer as the output voltage received from the amplifier increases, wherein the reference voltage is set as the output voltage at the desired conditions.

15. The optical test system of claim 14, wherein the automatic gain control loop comprises: a peak detector configured to: detect a peak voltage of a differential voltage output from the differential amplifier; and output a peak voltage at a detector output.

16. The optical test system of claim 14, wherein the automatic gain control loop comprises: a peak detector configured to: detect a peak voltage of a differential voltage output from the differential amplifier; and output a peak voltage at a detector output; and an integrator configured to: receive

the peak voltage from the peak detector and a reference peak voltage; and output an integrated gain controlling voltage signal that controls a peak-to-peak value of the differential voltage output by the variable gain circuit, wherein the reference peak voltage is set at the peak voltage of the differential voltage at the desired conditions.

17. An optical test system that comprises: a transmitter system configured to transmit modulated coherent optical signals modulated using radio frequency signals that encode test data in modulated coherent optical signals based upon at least one of an intensity or a phase of a coherent light; a propagation medium simulator configured to: receive the modulated coherent optical signals from the transmitter system; change a set of optical attributes for the modulated coherent optical signals to model propagation of the modulated coherent optical signals through a propagation environment to form varied modulated coherent optical signals; and output the varied modulated coherent optical signals; and an optical receiver system configured to: receive the varied modulated coherent optical signals from the propagation medium simulator; and recover the radio frequency signals encoding the test data from the varied modulated coherent optical signals in a manner that adjusts for changes in the varied modulated coherent optical signals caused by a variation in a set of optical attributes in the varied modulated coherent optical signals generated by the propagation medium simulator; and an analog to digital system configured to extract the test data from the radio frequency signals, and outputs recovered data.

18. A process for testing an optical system, the process comprising: transmitting, from a transmitter system, modulated coherent optical signals modulated using radio frequency signals encoding test data; receiving, in a propagation medium simulator, the modulated coherent optical signals from the transmitter system; changing a set of optical attributes for the modulated coherent optical signals to model propagation of the modulated coherent optical signals through a propagation environment to form varied modulated coherent optical signals; outputting, from the propagation medium simulator, the varied modulated coherent optical signals; and receiving, in an optical receiver system, the varied modulated coherent optical signals from the propagation medium simulator; recovering the radio frequency signals encoding the test data from the varied modulated coherent optical signals in a manner adjusting for changes in the varied modulated coherent optical signals caused by a variation in a set of optical attributes in the varied modulated coherent optical signals generated by the propagation medium simulator; extracting, in an analog to digital system, the test data from the radio frequency signals; and outputting, from the analog to digital system, the recovered data.

19. The process of claim 18 further comprising comparing, using an analyzer, the test data with the recovered data to form a comparison.

20. The process of claim 18, further comprising encoding the radio frequency signals encoding data in modulated coherent optical signals by modulating at least one of an intensity or a phase of a coherent light.
