

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12406946
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Kuenemund; Thomas et al.

Integrated circuit for prevention of circuit design theft

Abstract

Various embodiments describe an integrated circuit. The integrated circuit includes at least seven planar field effect transistors provided in a common substrate next to one another with a maximum feature size in accordance with a technology node of a maximum of 65 nm. Each field effect transistor of the at least seven planar field effect transistors includes a first source/drain diffusion region, a second source/drain diffusion region, a channel region between the drain diffusion region and the source diffusion region, and a gate terminal. Each field effect transistor of the at least seven planar field effect transistors includes at least one common source/drain diffusion region with another field effect transistor of the at least seven planar field effect transistors. The common source/drain diffusion regions are free of vertical terminal contact material.

Inventors: Kuenemund; Thomas (Munich, DE), Gruetzner; Markus (Munich, DE), Egger; Peter (Baldham, DE)

Applicant: Infineon Technologies AG (Neubiberg, DE)

Family ID: 77271277

Assignee: Infineon Technologies AG (Neubiberg, DE)

Appl. No.: 17/163597

Filed: February 01, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20210272916 A1	Sep. 02, 2021

Foreign Application Priority Data

DE	10 2020 105 474.2	Mar. 02, 2020
----	-------------------	---------------

Publication Classification

Int. Cl.: H01L21/70 (20060101); H01L21/336 (20060101); H01L23/00 (20060101);
H03K19/003 (20060101); H10D84/85 (20250101); H10D89/10 (20250101)

U.S. Cl.:

CPC H01L23/573 (20130101); H03K19/00315 (20130101); H10D84/85 (20250101);
H10D89/10 (20250101);

Field of Classification Search

CPC: H01L (27/088); H01L (27/092); H01L (23/573); H01L (27/0207); H03K (19/00315);
H10D (84/85)

USPC: 438/128-129; 438/279; 257/206; 257/390

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
4409434	12/1982	Basset et al.	N/A	N/A
4680736	12/1986	Schrenk	365/218	G07F 7/1083
4716308	12/1986	Matsuo et al.	N/A	N/A
5783846	12/1997	Baukus et al.	N/A	N/A
5866933	12/1998	Baukus et al.	N/A	N/A
5977790	12/1998	Sanwo	327/170	H03K 19/00361
6005270	12/1998	Noguchi	257/30	H01L 27/11543
6037636	12/1999	Crippen	257/357	H10D 89/811
7471113	12/2007	Lim	326/87	H03K 19/0008
9330763	12/2015	Zhang	N/A	G11C 16/26
9337156	12/2015	Kuenemund et al.	N/A	N/A
9385726	12/2015	Kuenemund et al.	N/A	N/A
9431352	12/2015	Kuenemund et al.	N/A	N/A
9496872	12/2015	Kuenemund	N/A	N/A
9548737	12/2016	Kuenemund et al.	N/A	N/A
9806881	12/2016	Kuenemund et al.	N/A	N/A
2004/0056280	12/2003	Murata et al.	N/A	N/A
2005/0263815	12/2004	Park	257/315	H10D 30/6891
2014/0293702	12/2013	Dong	365/185.17	H10B 41/10

2018/0091155	12/2017	Kuenemund	N/A	H03K 19/00315
2018/0174985	12/2017	Kuenemund	N/A	G06F 21/72
2018/0182794	12/2017	Go	N/A	H10F 39/011
2020/0411453	12/2019	Lu	N/A	H01L 27/0207
2021/0257363	12/2020	Kuenemund	N/A	H10D 84/0172

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
102015105417	12/2014	DE	N/A
102015105879	12/2014	DE	N/A
102015110431	12/2014	DE	N/A
102016113128	12/2016	DE	N/A
102016121449	12/2017	DE	N/A

OTHER PUBLICATIONS

Torrance, R. et al.; “The State-of-the-Art in Semiconductor Reverse Engineering”; Proceedings of the 48th Design Automation Conference, DAC 2011; dated Jun. 2011; 33 pages;
https://www.researchgate.net/publication/221058794_The_state-of-the-art_in_semiconductor_reverse_engineering (Year: 2011). cited by examiner
 Kleindiek Nanotechnik GMBH; 2019;
<https://web.archive.org/web/20191215171345/https://www.nanotechnik.com/ps8.html> cited by examiner

Torrance, R. et al.; “The State-of-the-Art in IC Reverse Engineering”; Proceedings of the 11th International Workshop on Cryptographic Hardware and Embedded Systems, dated 2009; pp. 363-381; Springer Verlag; Lausanne, Switzerland.

<https://www.iacr.org/archive/ches2009/57470361/57470361.pdf> (Year: 2009). cited by examiner
 German Office Action issued for corresponding DE application 10 2020 105 474.2 dated Nov. 4, 2020, 8 pages (for informational purposes only). cited by applicant

Office Action for corresponding German Patent Application No. 10 2020 105 474.2, dated May 8, 2023, 7 pages (for Informational purposes only). cited by applicant

Torrance, R. et al.; “The State-of-the-Art in Semiconductor Reverse Engineering”; Proceedings of the 48th Design Automation Conference, DAC 2011; dated Jun. 2011; 33 pages; San Diego, California, USA. cited by applicant

Rajendran, J. et al.; “Security Analysis of Integrated Circuit Camouflaging”; Proceedings of the 2013 ACM SIGSAC conference on Computer & communications security, CCS'13; dated Nov. 2013; 12 pages; Berlin, Germany. cited by applicant

Primary Examiner: Rosario; Joshua Benitez

Assistant Examiner: Bauman; Scott E

Attorney, Agent or Firm: Viering, Jentschura & Partner mbB

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION

(1) This application claims priority to German Patent Application Serial No. 10 2020 105 474.2, which was filed Mar. 2, 2020, and is incorporated herein by reference in its entirety.

TECHNICAL FIELD

(2) Various embodiments relate to an integrated circuit.

BACKGROUND

(3) Data theft, reverse engineering and reconstruction of integrated circuits are regarded as one of the greatest threats or dangers in the semiconductor industry since reverse engineering for example can be abused in order to steal and/or to copy a circuit design (for example by reconstruction). By way of example, the stolen circuit design can be used to produce and sell similar (for example copied) integrated circuits, to use and/or sell the circuit design, to disclose the design to competitors, etc. For all these reasons it may be necessary to develop concepts and methods which hinder or prevent theft of a circuit design or of a circuit technology.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) In the drawings, like reference characters generally refer to the same parts throughout the different views. The drawings are not necessarily to scale, emphasis instead generally being placed upon illustrating the principles of the invention. In the following description, various embodiments of the invention are described with reference to the following drawings, in which:

(2) FIG. 1 shows a schematic illustration of a NAND logic gate;

(3) FIG. 2A shows a NAND-based integrated circuit in accordance with various embodiments;

(4) FIG. 2B shows a contact plane of a NAND-based integrated circuit in accordance with various embodiments;

(5) FIG. 3 shows a schematic illustration of a NAND-based RS flip-flop;

(6) FIG. 4 shows an integrated circuit which realizes a NAND-based RS flip-flop, in accordance with various embodiments;

(7) FIG. 5 shows an integrated circuit in accordance with various embodiments;

(8) FIG. 6A shows an integrated circuit which realizes a NAND-based RS flip-flop, in accordance with various embodiments;

(9) FIG. 6B shows a contact plane of an integrated circuit which realizes a NAND-based RS flip-flop, in accordance with various embodiments;

(10) FIG. 6C shows an integrated circuit which realizes a NAND-based RS flip-flop, in accordance with various embodiments;

(11) FIG. 6D shows a contact plane of an integrated circuit which realizes a NAND-based RS flip-flop, in accordance with various embodiments;

(12) FIG. 7A shows a transistor arrangement of an integrated circuit in accordance with various embodiments;

(13) FIG. 7B shows a layout of an integrated circuit in accordance with various embodiments;

(14) FIG. 8 shows a transistor arrangement of an integrated circuit in accordance with various embodiments;

(15) FIG. 9 shows a transistor arrangement of an integrated circuit in accordance with various embodiments;

(16) FIG. 10 shows a transistor arrangement of an integrated circuit in accordance with various embodiments;

(17) FIG. 11 shows a transistor arrangement of an integrated circuit in accordance with various embodiments;

(18) FIG. 12 shows a transistor arrangement of an integrated circuit in accordance with various

embodiments;

(19) FIG. 13 shows a transistor arrangement of an integrated circuit in accordance with various embodiments; and

(20) FIG. 14 shows a transistor arrangement of an integrated circuit in accordance with various embodiments.

DESCRIPTION

(21) The following detailed description refers to the accompanying drawings that show, by way of illustration, specific details and embodiments in which the invention may be practiced.

(22) The word “exemplary” is used herein to mean “serving as an example, instance, or illustration”. Any embodiment or design described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other embodiments or designs.

(23) In the following detailed description, reference is made to the accompanying drawings, which form part of this description and show for illustration purposes specific embodiments in which the invention can be implemented. In this regard, direction terminology such as, for instance, “at the top”, “at the bottom”, “at the front”, “at the back”, “front”, “rear”, etc. is used with respect to the orientation of the figure(s) described. Since components of embodiments can be positioned in a number of different orientations, the direction terminology serves for illustration and is not restrictive in any way whatsoever. It goes without saying that other embodiments can be used and structural or logical changes can be made, without departing from the scope of protection of the present invention. It goes without saying that the features of the various exemplary embodiments described herein can be combined with one another, unless specifically indicated otherwise.

Therefore, the following detailed description should not be interpreted in a restrictive sense, and the scope of protection of the present invention is defined by the appended claims.

(24) In the context of this description, the terms “connected” and “coupled” are used to describe both a direct and an indirect connection and a direct or indirect coupling. The term “connected” can mean electrically connected, for example. In the figures, identical or similar elements are provided with identical reference signs, insofar as this is expedient.

(25) The design of an integrated circuit may afford a crucial advantage vis-à-vis competitors, for example by virtue of the arrangement (for example of transistors), by virtue of various characteristics of transistors, by virtue of selected threshold values (for example voltage threshold values), etc. By means of reverse engineering of an integrated circuit, the design (such as, for example, the transfer properties of the transistors) of the integrated circuit may be stolen and for example sold and/or used. An integrated circuit in accordance with various embodiments is described below. The integrated circuit may include a plurality of transistors and the transistors can be arranged or coupled in such a way that analyzing the properties of the switching elements is hindered, for example prevented.

(26) An integrated circuit in various embodiments for a NAND-based circuit is described below. It is pointed out that the integrated circuit can be any type of integrated circuit in which transistors are interconnected to form logic circuits, such as, for example, a NOR-based circuit, an AND-NOR-based circuit or an OR-NAND-based circuit, etc.

(27) FIG. 1 shows a schematic illustration of a NAND logic gate **100**. A NAND (NOT AND) logic gate may include a first input **A1** and a second input **A0**. The NAND logic gate may furthermore include an output **Z**. The NAND (NOT AND) logic gate can be described by the Boolean equation $Z = \text{NAND}(A1, A0)$ or $Z = \text{NOT}(A1 * A0)$.

(28) FIG. 2A shows a NAND-based integrated circuit **200** in accordance with various embodiments. The integrated circuit **200** may include a first field effect transistor **202**. The first field effect transistor **202** can be an n-channel field effect transistor. It is pointed out that all field effect transistors described herein for example can be MOSFETs (metal oxide semiconductor field effect transistors) and can be formed by means of CMOS (complementary metal oxide semiconductor) technology. The integrated circuit **200** may include a second field effect transistor

204. The second field effect transistor **204** can be an n-channel field effect transistor. The first field effect transistor **202** and/or the second field effect transistor **204** can be arranged in a p-doped well **206**. The p-doped well **206** may include silicon, for example, which is doped (for example implanted) with an element having 3 valence electrons. The integrated circuit **200** may furthermore include a third field effect transistor **208**. The third field effect transistor **208** can be a p-channel field effect transistor. The integrated circuit **200** may include a fourth field effect transistor **210**. The fourth field effect transistor **210** can be a p-channel field effect transistor. The third field effect transistor **208** and/or the fourth field effect transistor **210** can be arranged in an n-doped well **212**. The n-doped well **212** may include silicon, for example, which is doped (for example implanted) with an element having five valence electrons. The first field effect transistor **202**, the second field effect transistor **204**, the third field effect transistor **206** and the fourth field effect transistor **208** may include a first source/drain diffusion region, a second source/drain diffusion region, a channel region between the drain diffusion region and the source diffusion region, and a gate terminal. It is pointed out that, unless explicitly indicated otherwise, each field effect transistor described below may include a first source/drain diffusion region, a second source/drain diffusion region, a channel region between the drain diffusion region and the source diffusion region, and a gate terminal. Furthermore, it is pointed out, that unless specifically indicated otherwise, each integrated circuit described below may include one or more metallization planes for electrically contacting the field effect transistors contained in the substrate. The field effect transistors can be electrically contacted by means of contacts composed of vertical terminal contact material.

(29) The integrated circuit **200** may include a first input **214** (for example the input **A0** of the NAND logic gate **100**). The first input **214** can be connected to the gate terminal of the first field effect transistor (FET) **202** by means of a first gate contact **216**. The first input **214** can furthermore be connected to the gate terminal of the third FET **208** by means of the first gate contact **216**. It is pointed out that, unless explicitly indicated otherwise, each contact (for example gate contact, for example source contact, for example drain contact) described below may include a vertical terminal composed of vertical terminal contact material.

(30) The vertical terminal contact material may include or substantially consist of a metal, such as, for example, tungsten, aluminum, gold, silver, copper, etc., or a metal alloy. Furthermore, it is pointed out that if a contact (for example gate contact, for example source contact, for example drain contact) described below is connected to an input, an output and/or some other contact (for example more than one other contact), the contact can be connected to the input, the output and/or the other contact by means of a metal layer.

(31) The integrated circuit **200** may include a second input **218** (for example the input **A1** of the NAND logic gate **100**). The second input **218** can be connected to the gate terminal of the second FET **204** by means of a second gate contact **220**. The second input **218** can furthermore be connected to the gate terminal of the fourth FET **210** by means of the second gate contact **220**.

(32) The integrated circuit **200** may include a first source contact **222**. The first source contact **222** can be connected to the source diffusion region of the first FET **202**. The first source contact **222** can be connected to a low supply potential **VSS**.

(33) The integrated circuit **200** may include a common source/drain diffusion region **224**. The common source/drain diffusion region **224** can be a common source/drain diffusion region of the first FET **202** and of the second FET **204**. The common source/drain diffusion region **224** can be connected to a drain terminal of the first FET **202**. The common source/drain diffusion region **224** can be connected to a source terminal of the second FET **204**. The integrated circuit **200** may include a first drain contact **226**. The first drain contact **226** can be connected to the drain diffusion region of the second FET **204**.

(34) The integrated circuit **200** may include a common source contact **228**. The common source contact **228** can be connected to the source diffusion region of the third FET **208**. The common source contact **228** can furthermore be connected to the source diffusion region of the fourth FET

210. The common source contact **228** can be connected to a high supply potential VDD.

(35) The integrated circuit **200** may include a second drain contact **230**. The second drain contact **230** can be connected to the drain diffusion region of the third FET **208**. The integrated circuit **200** may include a third drain contact **232**. The third drain contact **232** can be connected to the drain diffusion region of the fourth FET **210**. The third drain contact **232** can be connected to the second drain contact **230**.

(36) The integrated circuit **200** may include an output **234** (for example the output Z of the NAND logic gate **100**). In accordance with various embodiments, the first drain contact **226** and the third drain contact **232** can be connected to the output **234**.

(37) FIG. 2B shows a contact plane of the NAND-based integrated circuit **200** in accordance with various embodiments. The contact plane of the integrated circuit **200** can be exposed for example by removal (for example by means of chemical etching, for example by means of physical etching) of layers (for example metal and insulation layers) of the integrated circuit. This may be necessary for example for analyzing transfer properties of the field effect transistors (for example determining threshold voltages).

(38) By way of example, in various nano-examination methods, the gate contact, the source contact and the drain contact of an individual field effect transistor can be contacted (for example by means of a plurality of examination needles) and properties of the field effect transistor can be analyzed. With regard to the integrated circuit **200** illustrated in FIG. 2B, analyzing properties of the third FET **208** for example necessitates contacting the first gate contact **216**, the common source contact **228** and the second drain contact **230**. In this example, three examination needles are necessary for analyzing properties of the third FET **208**. In order to analyze properties of the first FET **202** or of the second FET **204**, it is necessary to contact the first gate contact **216**, the first source contact **222**, the second gate contact **220** and the first drain contact **226**. Consequently, in this example, four examination needles are necessary for analyzing properties of the first FET **202** or of the second FET **204**. Consequently, as the number of field effect transistors arranged next to one another (for example connected in series) increases, the number of necessary examination needles increases in order to analyze properties of an individual field effect transistor of the field effect transistors arranged next to one another (for example connected in series). The number of available examination needles is limited on account of various factors, such as, for example, the limited number of examination needles in commercially available examination systems, on account of the reliability and the reproducibility of the positioning of the individual examination needles (for example in relation to one another), on account of space limitations owing to other devices of the examination system, on account of problems in relation to the alignment of a plurality of examination needles, etc.

(39) In accordance with various embodiments, an integrated circuit is described below in which a plurality of field effect transistors are connected in such a way that the number required for analyzing properties of an individual field effect transistor is increased (for example is greater than the number of examination needles present in commercially available examination systems).

(40) FIG. 3 shows a schematic illustration of a NAND-based RS flip-flop **300**. The NAND-based RS flip-flop (RS-FF) **300** may include a first NAND logic gate **302** and a second NAND logic gate **304**. The first NAND logic gate **302** may include a first input contact **306**, a second input contact **308** and an output contact **310**. The second NAND logic gate **304** may include a first input contact **312**, a second input contact **314** and an output contact **316**. The NAND-based RS-FF **300** may include a first input **318** (SZ). The first input **318** can be connected to the first input contact **306** of the first NAND logic gate. The NAND-based RS-FF **300** may include a second input **320** (SY). The second input **320** can be connected to the second input contact **314** of the second NAND logic gate. The NAND-based RS-FF **300** may include a first output **322** (ZN). The first output **322** can be connected to the output contact **310** of the first NAND logic gate **302**. The first output **322** can furthermore be connected to the first input contact **312** of the second NAND logic gate **304**. The

NAND-based RS-FF **300** may include a second output **324** (YN). The second output **324** can be connected to the output contact **316** of the second NAND logic gate **304**. The second output **324** can furthermore be connected to the second input contact **308** of the first NAND logic gate **302**. (41) FIG. **4** shows an integrated circuit **400** which realizes a NAND-based RS flip-flop, in accordance with various embodiments.

(42) The integrated circuit **400** may include a first field effect transistor **402**. The first field effect transistor **402** can be an n-channel field effect transistor. The integrated circuit **400** may include a second field effect transistor **404**. The second field effect transistor **404** can be an n-channel field effect transistor. The first field effect transistor **402** and/or the second field effect transistor **404** can be arranged in a p-doped well. The integrated circuit **400** may include a third field effect transistor **406**. The third field effect transistor **406** can be a p-channel field effect transistor. The integrated circuit **400** may include a fourth field effect transistor **408**. The fourth field effect transistor **408** can be a p-channel field effect transistor. The third field effect transistor **406** and/or the fourth field effect transistor **408** can be arranged in an n-doped well.

(43) The integrated circuit **400** may include a fifth field effect transistor **410**. The fifth field effect transistor **410** can be an n-channel field effect transistor. The integrated circuit **400** may include a sixth field effect transistor **412**. The sixth field effect transistor **412** can be an n-channel field effect transistor. The fifth field effect transistor **410** and/or the sixth field effect transistor **412** can be arranged in a p-doped well. The integrated circuit **400** may furthermore include a seventh field effect transistor **414**. The seventh field effect transistor **414** can be a p-channel field effect transistor. The integrated circuit **400** may include an eighth field effect transistor **416**. The eighth field effect transistor **416** can be a p-channel field effect transistor. The seventh field effect transistor **414** and/or the eighth field effect transistor **416** can be arranged in an n-doped well.

(44) The integrated circuit **400** may include a first input **418** (for example the input SZ of the NAND-based RS-FF **300**). The first input **418** can be connected to the gate terminal of the second FET **404** by means of a first gate contact **420**. The first input **418** can furthermore be connected to the gate terminal of the fourth FET **408** by means of the first gate contact **420**.

(45) The integrated circuit **400** may include a second input **422** (for example the input SY of the NAND-based RS-FF **300**). The second input **422** can be connected to the gate terminal of the fifth FET **410** by means of a second gate contact **424**. The second input **422** can furthermore be connected to the gate terminal of the seventh FET **414** by means of the second gate contact **424**.

(46) The integrated circuit **400** may include a first source contact **426**. The first source contact **426** can be connected to the source diffusion region of the first FET **402**. The first source contact **426** can be connected to a low supply potential VSS. The integrated circuit **400** may include a second source contact **428**. The second source contact **428** can be connected to the source diffusion region of the sixth FET **412**. The second source contact **428** can be connected to the low supply potential VSS.

(47) The integrated circuit **400** may include a first common source/drain diffusion region **430**. The first common source/drain diffusion region **430** can be a common source/drain diffusion region of the first FET **402** and of the second FET **404**. The first common source/drain diffusion region **430** can be connected to the drain terminal of the first FET **402**. The first common source/drain diffusion region **430** can be connected to the source terminal of the second FET **404**.

(48) The integrated circuit **400** may include a second common source/drain diffusion region **432**. The second common source/drain diffusion region **432** can be a common source/drain diffusion region of the fifth FET **410** and of the sixth FET **412**. The second common source/drain diffusion region **432** can be connected to the drain terminal of the sixth FET **412**. The second common source/drain diffusion region **432** can be connected to the source terminal of the fifth FET **410**.

(49) The integrated circuit **400** may include a first common source contact **434**. The first common source contact **434** can be connected to the source diffusion region of the third FET **406**. The first common source contact **434** can furthermore be connected to the source diffusion region of the

fourth FET **408**. The first common source contact **434** can be connected to a high supply potential VDD.

(50) The integrated circuit **400** may include a second common source contact **436**. The second common source contact **436** can be connected to the source diffusion region of the seventh FET **414**. The second common source contact **436** can furthermore be connected to the source diffusion region of the eighth FET **416**. The second common source contact **436** can be connected to the high supply potential VDD.

(51) The integrated circuit **400** may include a first output **438** (for example the output ZN of the NAND-based RS-FF **300**). The first output **438** can be connected to a first drain contact **440**. The first drain contact **440** can be connected to the drain diffusion region of the third FET **406**. The integrated circuit **400** may furthermore include a second drain contact **442**. The second drain contact **442** can be connected to the drain diffusion region of the fourth FET **408**. The second drain contact **442** can furthermore be connected to the first drain contact **440**. The integrated circuit **400** may furthermore include a third drain contact **444**. The third drain contact **444** can be connected to the drain diffusion region of the second FET **404**. The third drain contact **444** can furthermore be connected to the second drain contact **442**. The third drain contact **444** can furthermore be connected to a third gate contact **446**. The third gate contact **446** can be connected to the gate terminal of the sixth FET **412**. The third gate contact **446** can furthermore be connected to the gate terminal of the eighth FET **416**.

(52) The integrated circuit **400** may include a second output **448** (for example the output YN of the NAND-based RS-FF **300**). The second output **448** can be connected to a fourth drain contact **450**. The fourth drain contact **450** can be connected to the drain diffusion region of the eighth FET **416**. The integrated circuit **400** may furthermore include a fifth drain contact **452**. The fifth drain contact **452** can be connected to the drain diffusion region of the fifth FET **410**. The integrated circuit **400** may furthermore include a sixth drain contact **454**. The sixth drain contact **454** can be connected to the drain diffusion region of the seventh FET **414**. The sixth drain contact **454** can furthermore be connected to the fourth drain contact **450**. The sixth drain contact **454** can furthermore be connected to the fifth drain contact **452**. The sixth drain contact **454** can furthermore be connected to a fourth gate contact **456**. The fourth gate contact **456** can be connected to the gate terminal of the first FET **402**. The fourth gate contact **456** can furthermore be connected to the gate terminal of the third FET **406**.

(53) The first FET **402** and the second FET **404**, which can be connected in series by means of the first common source/drain diffusion region **430**, can have substantially the same transfer properties (for example transconductance). The fifth FET **410** and the sixth FET **412**, which can be connected in series by means of the second common source/drain diffusion region **432**, can have substantially the same transfer properties (for example transconductance), wherein the transfer properties of the fifth FET **410** and of the sixth FET **412** can be different than the transfer properties of the first FET **402** and of the second FET **404**. The signal provided at the first output **438** can be dependent on whether the transconductance of the first FET **402** and of the second FET **404** is greater than the transconductance of the fifth FET **410** and of the sixth FET **412** or whether the transconductance of the first FET **402** and of the second FET **404** is less than the transconductance of the fifth FET **410** and of the sixth FET **412**. The signal provided at the second output **448** can be dependent on whether the transconductance of the first FET **402** and of the second FET **404** is greater than the transconductance of the fifth FET **410** and of the sixth FET **412** or whether the transconductance of the first FET **402** and of the second FET **404** is less than the transconductance of the fifth FET **410** and of the sixth FET **412**.

(54) In order to analyze the electronic properties of the first FET **402** or of the second FET **404**, it is necessary to contact the fourth gate contact **456**, the first source contact **426**, the first gate contact **420** and the third drain contact **444**. Consequently, in this example, four examination needles are necessary for detecting the electronic properties of the first FET **402** or of the second FET **404**.

Consequently, as the number of field effect transistors connected next to one another (for example in series) increases, the number of necessary examination needles increases in order to analyze properties of an individual field effect transistor of the field effect transistors connected next to one another (for example in series).

(55) As described with reference to FIG. 2B, in order to detect properties of a field effect transistor, the number of necessary examination needles increases with the number of field effect transistors connected in series.

(56) A plurality of field effect transistors can be connected in series for example in such a way that the source terminal of a first field effect transistor of the plurality of field effect transistors is connected to a source contact and that the drain terminal of the first field effect transistor is connected to a source terminal of a second field effect transistor by means of a common source/drain diffusion region, that the drain terminal of a third field effect transistor of the plurality of field effect transistors is connected to a drain contact and that the drain terminal of the third field effect transistor is connected to a drain terminal of a fourth field effect transistor by means of a common source/drain diffusion region. The plurality of field effect transistors can furthermore be connected in series in such a way that additional field effect transistors are connected between the second field effect transistor and the fourth field effect transistor, wherein each field effect transistor of the additional field effect transistors may include a first common source/drain diffusion region with a first adjacent field effect transistor, and a second common source/drain diffusion region with a second adjacent field effect transistor (different than the first adjacent field effect transistor). Furthermore, the gate terminal of each of the plurality of field effect transistors can be connected to a gate contact.

(57) FIG. 5 shows an integrated circuit **500** in accordance with various embodiments. The integrated circuit **500** may include a plurality of field effect transistors. By way of example, the integrated circuit **500** may include at least seven (for example planar) field effect transistors (for example exactly seven field effect transistors, for example more than seven field effect transistors).

(58) The plurality of field effect transistors (for example the at least seven planar field effect transistors) can be provided next to one another. The plurality of field effect transistors can be provided next to one another in a common substrate. The plurality of field effect transistors can be provided next to one another with a maximum feature size in accordance with a technology node of a maximum of 65 nm. The plurality of field effect transistors provided next to one another can be connected in series, for example.

(59) Each field effect transistor of the plurality of field effect transistors may include a first source/drain diffusion region, a second source/drain diffusion region, a channel region between the drain diffusion region and the source diffusion region, and a gate terminal.

(60) Furthermore, by way of example, each field effect transistor of the plurality of field effect transistors may include at least one common source/drain diffusion region with another field effect transistor of the plurality of field effect transistors. Each common source/drain diffusion region of the plurality of common source/drain diffusion regions can be free of vertical terminal contact material. By way of example, it is possible for each common source/drain diffusion region of the plurality of common source/drain diffusion regions not to be contacted by means of a source contact and not to be contacted by means of a drain contact.

(61) By way of example, two field effect transistors of the plurality of field effect transistors may each include a source/drain diffusion region with a vertical terminal connected thereto and composed of vertical terminal contact material for electrically contacting the respective source/drain diffusion region. The respective source/drain diffusion region with a vertical terminal connected thereto and composed of vertical terminal contact material can be different than the plurality of common source/drain diffusion regions, for example.

(62) The vertical terminal contact material may include or substantially consist of a metal, such as, for example, tungsten, aluminum, gold, silver, copper, etc., or a metal alloy.

(63) By way of example, a first field effect transistor of the two field effect transistors may include a source contact (drain contact) and a second field effect transistor of the two field effect transistors may include a drain contact (source contact).

(64) In accordance with various embodiments, the gate terminal of each field effect transistor of the plurality of field effect transistors may include a vertical terminal connected thereto and composed of vertical terminal contact material for electrically contacting the respective gate terminal. By way of example, the gate terminal of each field effect transistor of the plurality of field effect transistors may include a gate contact.

(65) In accordance with the embodiment illustrated by way of example in FIG. 5, the integrated circuit **500** includes seven field effect transistors provided next to one another. In accordance with various embodiments, each field effect transistor of the seven field effect transistors can be an n-channel field effect transistor. In accordance with various embodiments, each field effect transistor of the seven field effect transistors can be a p-channel field effect transistor.

(66) The integrated circuit may include a first FET **502**, a second FET **504**, a third FET **506**, a fourth FET **508**, a fifth FET **510**, a sixth FET **512** and a seventh FET **514**. The source diffusion region **516** of the first FET **502** can be connected to a source contact **518**, for example. The source contact **518** can be a vertical terminal connected to the source diffusion region **516** and composed of vertical terminal contact material for electrically contacting the source diffusion region **516**. The drain diffusion region **520** of the seventh FET **514** can be connected to a drain contact **522**, for example. The drain contact **522** can be a vertical terminal connected to the drain diffusion region **520** and composed of vertical terminal contact material for electrically contacting the drain diffusion region **520**.

(67) The first FET **502** and the second FET **504** may include a first common source/drain diffusion region **524**. The first common source/drain diffusion region **524** can be connected to the drain terminal of the first FET **502** and can be connected to the source terminal of the second FET **504**. The first common source/drain diffusion region **524** can be free of vertical terminal contact material. By way of example, the first common source/drain diffusion region **524** may include neither a source contact nor a drain contact.

(68) The second FET **504** and the third FET **506** may include a second common source/drain diffusion region **526**. The second common source/drain diffusion region **526** can be connected to the drain terminal of the second FET **504** and can be connected to the source terminal of the third FET **506**. The second common source/drain diffusion region **526** can be free of vertical terminal contact material.

(69) The third FET **506** and the fourth FET **508** may include a third common source/drain diffusion region **528**. The third common source/drain diffusion region **528** can be connected to the drain terminal of the third FET **506** and can be connected to the source terminal of the fourth FET **508**. The third common source/drain diffusion region **528** can be free of vertical terminal contact material.

(70) The fourth FET **508** and the fifth FET **510** may include a fourth common source/drain diffusion region **530**. The fourth common source/drain diffusion region **530** can be connected to the drain terminal of the fourth FET **508** and can be connected to the source terminal of the fifth FET **510**. The fourth common source/drain diffusion region **530** can be free of vertical terminal contact material.

(71) The fifth FET **510** and the sixth FET **512** may include a fifth common source/drain diffusion region **532**. The fifth common source/drain diffusion region **532** can be connected to the drain terminal of the fifth FET **510** and can be connected to the source terminal of the sixth FET **512**. The fifth common source/drain diffusion region **532** can be free of vertical terminal contact material.

(72) The sixth FET **512** and the seventh FET **514** may include a sixth common source/drain diffusion region **534**. The sixth common source/drain diffusion region **534** can be connected to the

drain terminal of the sixth FET **512** and can be connected to the source terminal of the seventh FET **514**. The sixth common source/drain diffusion region **534** can be free of vertical terminal contact material.

(73) The gate terminal of each field effect transistor of the seven field effect transistors **502, 504, 506, 508, 510, 512, 514** can each be connected to a gate contact. Each gate contact of the plurality of gate contacts can be a vertical terminal connected to the gate terminal and composed of vertical terminal contact material for electrically contacting the gate terminal. By way of example, the integrated circuit **500** may include a first gate contact **536** connected to the gate terminal of the first FET **502**. By way of example, the integrated circuit **500** may include a second gate contact **538** connected to the gate terminal of the second FET **504**. By way of example, the integrated circuit **500** may include a third gate contact **540** connected to the gate terminal of the third FET **506**. By way of example, the integrated circuit **500** may include a fourth gate contact **542** connected to the gate terminal of the fourth FET **508**. By way of example, the integrated circuit **500** may include a fifth gate contact **544** connected to the gate terminal of the fifth FET **510**. By way of example, the integrated circuit **500** may include a sixth gate contact **546** connected to the gate terminal of the sixth FET **512**. By way of example the integrated circuit **500** may include a seventh gate contact **548** connected to the gate terminal of the seventh FET **514**.

(74) In accordance with various embodiments, the third gate contact **540** can be connected to the first gate contact **536** by way of M1 (the first metallization layer). The third gate contact **540** can furthermore be connected to the fifth gate contact **544**. In accordance with various embodiments, the fourth gate contact **542** can be connected to the second gate contact **538**. The fourth gate contact **542** can furthermore be connected to the sixth gate contact **546**. The seventh gate contact **548** can be connected to an input **550** of the integrated circuit **500**.

(75) The plurality of field effect transistors (for example the seven field effect transistors **502, 504, 506, 508, 510, 512, 514**) can be part of a NAND-based circuit, of a NOR-based circuit, of an AND-NOR-based circuit, of an OR-NAND circuit, etc. By way of example, the plurality of field effect transistors can form a NAND-based circuit, a NOR-based circuit, an AND-NOR-based circuit, an OR-NAND-based circuit, etc. In accordance with various embodiments, the plurality of field effect transistors (for example the seven field effect transistors **502, 504, 506, 508, 510, 512, 514**) can be part of an RS flip-flop. By way of example, the plurality of field effect transistors can be part of a NAND-based RS flip-flop, of a NOR-based RS flip-flop, of an AND-NOR-based RS flip-flop, of an OR-NAND-based RS flip-flop, etc.

(76) FIGS. **6A** and **6C** both show an integrated circuit **600** which realizes a NAND-based RS flip-flop, in accordance with various embodiments.

(77) The integrated circuit **600** may include a first group of field effect transistors **602**. The first group of field effect transistors **602** may include a plurality of field effect transistors. By way of example, the first group of field effect transistors **602** may include at least seven (for example planar) field effect transistors (for example exactly seven field effect transistors, for example more than seven field effect transistors). The integrated circuit **600** may furthermore include a second group of field effect transistors **604**. The second group of field effect transistors **604** may include a plurality of field effect transistors. By way of example, the second group of field effect transistors **604** may include at least seven (for example planar) field effect transistors (for example exactly seven field effect transistors, for example more than seven field effect transistors). In accordance with various embodiments, the number of field effect transistors of the first group of field effect transistors **602** corresponds to the number of field effect transistors of the second group of field effect transistors **604**.

(78) The plurality of field effect transistors of the first group of field effect transistors **602** can be MOSFETs (metal oxide semiconductor field effect transistors). The plurality of field effect transistors of the first group of field effect transistors **602** (for example the at least seven planar field effect transistors) can be provided next to one another. The plurality of field effect transistors

of the first group of field effect transistors **602** can be provided next to one another in a common substrate. The substrate may include or substantially consist of a semiconductor material or a semiconductor composite material. The substrate may include or substantially consist of a semiconductor material or a semiconductor composite material which is selected from a group of materials consisting of: silicon, silicon carbide, gallium arsenide, gallium nitride, etc. The plurality of field effect transistors of the first group of field effect transistors **602** can be provided next to one another with a maximum feature size in accordance with a technology node of a maximum of 65 nm. The plurality of field effect transistors provided next to one another in the first group of field effect transistors **602** can be connected in series, for example.

(79) The plurality of field effect transistors of the second group of field effect transistors **604** can be MOSFETs (metal oxide semiconductor field effect transistors). The plurality of field effect transistors of the second group of field effect transistors **604** (for example the at least seven planar field effect transistors) can be provided next to one another. The plurality of field effect transistors of the second group of field effect transistors **604** can be provided next to one another in a common substrate. The substrate may include or substantially consist of a semiconductor material or a semiconductor composite material. The substrate may include or substantially consist of a semiconductor material or a semiconductor composite material which is selected from a group of materials consisting of: silicon, silicon carbide, gallium arsenide, gallium nitride, etc. The plurality of field effect transistors of the second group of field effect transistors **604** can be provided next to one another with a maximum feature size in accordance with a technology node of a maximum of 65 nm. The plurality of field effect transistors provided next to one another in the second group of field effect transistors **604** can be connected in series, for example.

(80) In accordance with various embodiments, at least some of the field effect transistors of the first group of field effect transistors **602** can have a different nominal transconductance than at least some of the field effect transistors of the second group of field effect transistors **604**.

(81) The field effect transistors of the first group of field effect transistors **602** can have a first conductivity type. Some of the field effect transistors of the second group of field effect transistors **604** can have a second conductivity type. The second conductivity type can be different than the first conductivity type.

(82) In accordance with various embodiments, the threshold voltages of some of the field effect transistors of the first group of field effect transistors **602** can differ from the threshold voltages of some of the field effect transistors of the second group of field effect transistors **604**. By way of example, the threshold voltages of some of the field effect transistors of the first group of field effect transistors **602** can differ from the threshold voltages of some of the field effect transistors of the second group of field effect transistors **604** by at least approximately 50 mV to approximately 150 mV.

(83) In accordance with various embodiments, the current-voltage characteristic curves of some of the field effect transistors of the first group of field effect transistors **602** can differ from the current-voltage characteristic curves of some of the field effect transistors of the second group of field effect transistors **604**.

(84) In accordance with various embodiments, the transfer characteristic of some of the field effect transistors of the first group of field effect transistors **602** can differ from the transfer characteristic of some of the field effect transistors of the second group of field effect transistors **604**.

(85) The field effect transistors of the first group of field effect transistors **602** and the field effect transistors of the second group of field effect transistors **604** can be interconnected to form a NAND-based RS flip-flop, to form a NOR-based RS flip-flop, to form an AND-NOR-based RS flip-flop or to form an OR-NAND-based RS flip-flop.

(86) In accordance with the embodiments illustrated by way of examples in FIG. 6A and 6C, the integrated circuit **600** includes seven field effect transistors provided next to one another in the first group of field effect transistors **602** and seven field effect transistors provided next to one another

in the second group of field effect transistors **604**. In accordance with various embodiments, each field effect transistor of the seven field effect transistors of the first group of field effect transistors **602** can be an n-channel field effect transistor and/or each field effect transistor of the seven field effect transistors of the second group of field effect transistors **604** can be an n-channel field effect transistor (e.g., FIG. 6A). In accordance with various embodiments, each field effect transistor of the seven field effect transistors of the first group of field effect transistors **602** can be a p-channel field effect transistor and/or each field effect transistor of the seven field effect transistors of the second group of field effect transistors **604** can be a p-channel field effect transistor (e.g., FIG. 6C). In accordance with the embodiment illustrated by way of example in FIG. 6A, each field effect transistor of the seven field effect transistors of the first group of field effect transistors **602** is an n-channel field effect transistor and each field effect transistor of the seven field effect transistors of the second group of field effect transistors **604** is an n-channel field effect transistor.

(87) The integrated circuit **600** may include the integrated circuit **500**, wherein the seven field effect transistors **502, 504, 506, 508, 510, 512, 514** can form the first group of field effect transistors **602**. The source contact **518** can be a first source contact **518**. The drain contact **522** can be a first drain contact **522**. The input **550** can be a first input **550** (SZ).

(88) The second group of field effect transistors **604** may include seven field effect transistors, for example: an eighth FET **606**, a ninth FET **608**, a tenth FET **610**, an eleventh FET **612**, a twelfth FET **614**, a thirteenth FET **616**, and a fourteenth FET **618**. As described below, the field effect transistors **606, 608, 610, 612, 614, 616, 618** of the second group of field effect transistors **604** can be similar to the field effect transistors **502, 504, 506, 508, 510, 512, 514** of the first group of field effect transistors **602**. The source diffusion region **620** of the eighth FET **606** can be connected to the first source contact **518**. The gate terminal of the eighth FET **606** can be connected to the first gate contact **536**. The integrated circuit **600** may include an eighth gate contact **622**. The eighth gate contact **622** can be connected to the ninth gate terminal of the ninth FET **608**. The gate terminal of the tenth FET **610** can be connected to the third gate contact **540**. The integrated circuit **600** may include a ninth gate contact **624**. The ninth gate contact **624** can be connected to the gate terminal of the eleventh FET **612**. The gate terminal of the twelfth FET **614** can be connected to the fifth gate contact **544**. The integrated circuit **600** may include a tenth gate contact **626**. The tenth gate contact **626** can be connected to the gate terminal of the thirteenth FET **616**. The integrated circuit **600** may include an eleventh gate contact **628**. The eleventh gate contact **628** can be connected to the gate terminal of the fourteenth FET **618**. The eleventh gate contact **628** can furthermore be connected to a second input **630** (SY). The drain diffusion region **632** of the fourteenth FET **618** can be connected to a drain contact **634**.

(89) The integrated circuit **600** may furthermore include a fifteenth FET **636**. The fifteenth FET **636** can be an n-channel field effect transistor. The source diffusion region of the fifteenth FET **636** can be connected to a second source contact **638**. The second source contact **638** can be connected to a low supply potential VSS. The drain diffusion region of the fifteenth FET **636** can be connected to a second drain contact **640**. The integrated circuit **600** may include a twelfth gate contact **642** (T0). The twelfth gate contact **642** can be connected to the second drain contact **640**. The twelfth gate contact **642** can be connected to the first source contact **518**. The twelfth gate contact **642** can be connected to the gate terminal of a sixteenth FET **644**. The sixteenth FET **644** can be a p-channel field effect transistor. The source diffusion region of the sixteenth FET **644** can be connected to a third source contact **645**. The third source contact **645** can be connected to a high supply potential VDD. The drain diffusion region of the sixteenth FET **644** can be connected to a third drain contact **646**. The integrated circuit **600** may include a thirteenth gate contact **648** (T1). The thirteenth gate contact **648** can be connected to the gate terminal of the fifteenth FET **636**. The thirteenth gate contact **648** can be connected to the third drain contact **646**. The thirteenth gate contact **648** can furthermore be connected to the first gate contact **536**.

(90) The integrated circuit **600** may furthermore include a seventeenth FET **650**, an eighteenth FET

652, a nineteenth FET **654** and a twentieth FET **656**. The seventeenth FET **650**, the eighteenth FET **652**, the nineteenth FET **654** and/or the twentieth FET **656** can be p-channel field effect transistors. The source diffusion region of the seventeenth FET **650** can be connected to a fourth source contact **658**. The source diffusion region of the eighteenth FET **652** can be connected to a fifth source contact **660**. The source diffusion region of the nineteenth FET **654** can be connected to a sixth source contact **662**. The source diffusion region of the twentieth FET **656** can be connected to a seventh source contact **664**. The fourth source contact **658**, the fifth source contact **660**, the sixth source contact **662** and/or the seventh source contact **664** can be connected to the high supply potential VDD.

(91) The integrated circuit **600** may include a fourteenth gate contact **666**. The fourteenth gate contact **666** can be connected to the gate terminal of the seventeenth FET **650**. The fourteenth gate contact **666** can be connected to the eleventh gate contact **628**.

(92) The seventeenth FET **650** and the eighteenth FET **652** may include a first common drain diffusion region **668**. The first common drain diffusion region **668** can be connected to a fourth drain contact **670**. The fourth drain contact **670** can be connected to the second drain contact **634**. The fourth drain contact **670** can be connected to a second output **672** (YN).

(93) The nineteenth FET **654** and the twentieth FET **656** may include a second common drain diffusion region **674**. The second common drain diffusion region **674** can be connected to a fifth drain contact **676**. The fifth drain contact **676** can be connected to the first drain contact **522**. The fifth drain contact **676** can be connected to a first output **678** (ZN). The fifth drain contact **676** can furthermore be connected to a fifteenth gate contact **680**. The fifteenth gate contact **680** can be connected to the gate terminal of the eighteenth FET **652**.

(94) The integrated circuit **600** may furthermore include a sixteenth gate contact **682**. The sixteenth gate contact **682** can be connected to the gate terminal of the nineteenth FET **654**. The sixteenth gate contact **682** can be connected to the seventh gate contact **548**. The integrated circuit **600** may include a seventeenth gate contact **684**. The seventeenth gate contact **684** can be connected to the gate terminal of the twentieth FET **656**. The seventeenth gate contact **684** can be connected to the sixth gate contact **546**. The seventeenth gate contact **684** can furthermore be connected to the fourth drain contact **670** (for example by means of a sixth drain contact **686**).

(95) FIGS. **6B** and **6D** both show a contact plane of the integrated circuit **600** which realizes a NAND-based RS flip-flop, in accordance with various embodiments.

(96) The contact plane of the integrated circuit **600** can be exposed for example by removal (for example by means of mechanical grinding, chemical etching or physical etching) of layers (for example metal and insulation layers) of the integrated circuit. This may be necessary for example for analyzing properties of the field effect transistors (for example determining threshold voltages).

(97) As described above, the number of necessary examination needles increases with the number of field effect transistors arranged next to one another (for example connected in series) and the number of available examination needles may be limited (for example be limited to a maximum of eight examination needles) on account of various factors. In order to analyze the electronic properties of a field effect transistor of the first group **602** of field effect transistors, it is necessary to contact the first gate contact **536**, the second gate contact **538**, the third gate contact **540**, the fourth gate contact **542**, the fifth gate contact **544**, the sixth gate contact **546**, the seventh gate contact **548**, the first source contact **518** and the first drain contact **522** with an examination needle. In order to analyze the electronic properties of a field effect transistor of the second group **604** of field effect transistors, it is necessary to contact the first gate contact **536**, the eighth gate contact **622**, the third gate contact **540**, the ninth gate contact **624**, the fifth gate contact **544**, the tenth gate contact **626**, the eleventh gate contact **628**, the first source contact **518** and the second drain contact **634** with an examination needle. Consequently, nine examination needles are necessary in these cases. The number of necessary examination needles may for example be greater than the number of examination needles available (for example commercially) in an apparatus.

(98) FIG. 7A shows a transistor arrangement of an integrated circuit **700A** in accordance with various embodiments. FIG. 7B shows a layout **700B** of the transistor arrangement of the integrated circuit **700A** in accordance with various embodiments. The transistor arrangement of the integrated circuit **700A** can be used in the integrated circuit **600**, for example.

(99) The integrated circuit **700A** may include the plurality of field effect transistors of the first group of field effect transistors **602**. The first group of field effect transistors **602** may include a first FET **702**, a second FET **704**, a third FET **706**, a fourth FET **708**, a fifth FET **710** and a sixth FET **712**. The first FET **702**, the second FET **704**, the third FET **706**, the fourth FET **708**, the fifth FET **710** and the sixth FET **712** can be arranged next to one another (for example connected in series and/or parallel).

(100) The integrated circuit **700A** may furthermore include the plurality of field effect transistors of the second group of field effect transistors **604**. The second group of field effect transistors **604** may include a seventh FET **714**, an eighth FET **716**, a ninth FET **718**, a tenth FET **720**, an eleventh FET **722** and a twelfth FET **724**. The seventh FET **714**, the eighth FET **716**, the ninth FET **718**, the tenth FET **720**, the eleventh FET **722** and the twelfth FET **724** can be arranged next to one another (for example connected in series and/or parallel).

(101) The source diffusion region **726** of the first FET **702** can be connected to a first source contact **728**. The source diffusion region **730** of the sixth FET **712** can be connected to a second source contact **732**. The source diffusion region **734** of the seventh FET **714** can be connected to a third source contact **736**. The source diffusion region **738** of the twelfth FET **724** can be connected to a fourth source contact **740**. The first source contact **728**, the second source contact **732**, the third source contact **736** and/or the fourth source contact **740** can be connected to a common source diffusion region **742**.

(102) The integrated circuit **700A** may include a first gate contact **744**. The first gate contact **744** can be connected to the gate terminal of the first FET **702**. The first gate contact **744** can furthermore be connected to the gate terminal of the seventh FET **714**. The integrated circuit **700A** may include a second gate contact **746**. The second gate contact **746** can be connected to the gate terminal of the second FET **704**. The second gate contact **746** can furthermore be connected to the gate terminal of the eighth FET **716**. The integrated circuit **700A** may include a third gate contact **748**. The third gate contact **748** can be connected to the gate terminal of the fifth FET **710**. The third gate contact **748** can furthermore be connected to the gate terminal of the eleventh FET **722**. The integrated circuit **700A** may include a fourth gate contact **750**. The fourth gate contact **740** can be connected to the gate terminal of the sixth FET **712**. The fourth gate contact **750** can furthermore be connected to the gate terminal of the twelfth FET **724**.

(103) The integrated circuit **700A** may include a fifth gate contact **752**. The fifth gate contact **752** can be connected to the gate terminal of the third FET **706**. The integrated circuit **700A** may include a sixth gate contact **754**. The sixth gate contact **754** can be connected to the gate terminal of the fourth FET **708**. The integrated circuit **700A** may include a seventh gate contact **756**. The seventh gate contact **756** can be connected to the gate terminal of the ninth FET **718**. The integrated circuit **700A** may include an eighth gate contact **758**. The eighth gate contact **758** can be connected to the gate terminal of the tenth FET **720**.

(104) The first FET **702** and the second FET **704** may include a first common source/drain diffusion region **760**. The second FET **704** and the third FET **706** may include a second common source/drain diffusion region **762**. The fourth FET **708** and the fifth FET **710** may include a third common source/drain diffusion region **764**. The fifth FET **710** and the sixth FET **712** may include a fourth common source/drain diffusion region **766**. The seventh FET **714** and the eighth FET **716** may include a fifth common source/drain diffusion region **768**. The eighth FET **716** and the ninth FET **718** may include a seventh common source/drain diffusion region **770**. The tenth FET **720** and eleventh FET **722** may include a seventh common source/drain diffusion region **772**. The eleventh FET **722** and the twelfth FET **724** may include an eighth common source/drain diffusion region

774.

(105) In accordance with various embodiments, the third FET **706** and the fourth FET **708** may include a first common drain diffusion region **776**. Furthermore, the ninth FET **718** and the tenth FET **720** may include a second common drain diffusion region **778**. The first common drain diffusion region **776** can be connected to a drain contact **780**. The drain contact **780** can furthermore be connected to the second common drain diffusion region **778**.

(106) In accordance with various embodiments, the drain contact **780** can be arranged between the fifth gate contact **752**, the sixth gate contact **754**, the seventh gate contact **756** and the eighth gate contact **758**. By way of example, the fifth gate contact **752**, the sixth gate contact **754**, the seventh gate contact **756** and the eighth gate contact **758**, illustratively, can be arranged substantially respectively on a corner of a rectangle (for example of a square) and the drain contact **780** can be arranged substantially in the center of the rectangle (for example of the square). The drain contact **780**, the fifth gate contact **752**, the sixth gate contact **754**, the seventh gate contact **756** and the eighth gate contact **758** can be arranged in such a way that they are arranged at a distance from one another that is the minimum that can be realized technologically.

(107) As described above, analyzing properties of a field effect transistor of the first group of field effect transistors **602** or respectively a field effect transistor of the second group of field effect transistors **604** may necessitate contacting the gate contacts of each field effect transistor arranged next to one another in the first group of field effect transistors **602** or respectively in the second group of field effect transistors **604** with an examination needle and furthermore contacting the respective source contact and the respective drain contact. Consequently, it may be necessary to contact the fifth gate contact **752**, the sixth gate contact **754** and the drain contact **780** with an examination needle in order to analyze properties of a field effect transistor of the first group of field effect transistors **602**, and it may be necessary to contact the seventh gate contact **756**, the eighth gate contact **758** and the drain contact **780** with an examination needle in order to detect the electronic properties of a field effect transistor of the second group of field effect transistors **604**. The arrangement of the drain contact **780** between the fifth gate contact **752**, the sixth gate contact **754**, the seventh gate contact **756** and the eighth gate contact **758** has the effect that on account of a minimum size (for example a minimum diameter) of a respective examination needle, it may not be possible to contact the fifth gate contact **752**, the sixth gate contact **754** and the drain contact **780** simultaneously with an examination needle or respectively to contact the seventh gate contact **756**, the eighth gate contact **758** and the drain contact **780** simultaneously with an examination needle. Illustratively, the examination needles of the same apparatus obstruct one another when contacting the gate contacts and/or the drain contact. This has the effect that an analysis of the electronic properties of a field effect transistor of the first group of field effect transistors **602** and/or of a field effect transistor of the second group of field effect transistors **604** is restricted, for example prevented.

(108) FIGS. **8** to **10** show various transistor arrangements of integrated circuits **800**, **900**, **1000** in accordance with various embodiments. The integrated circuits **800**, **900**, **1000** may include seven field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6**. The seven field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6** can be connected in series and/or in parallel. The seven field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6** can be arranged in such a way that no contacts are formed between adjacent field effect transistors. Nine examination needles are necessary for analyzing the electronic properties of a field effect transistor of the seven field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6** of the transistor arrangements illustrated in FIGS. **8** to **10**.

(109) FIG. **8** shows a transistor arrangement of the integrated circuit **800**, wherein the seven field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6** are connected in series.

(110) FIG. **9** shows a transistor arrangement of the integrated circuit **900**, wherein field effect transistors of the seven field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6** are connected in series and wherein field effect transistors of the seven field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6**

are connected in parallel.

(111) FIG. **10** shows a transistor arrangement of the integrated circuit **1000**, wherein field effect transistors of the seven field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6** are connected in series and wherein field effect transistors of the seven field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6** are connected in parallel.

(112) FIG. **11** shows a transistor arrangement of an integrated circuit **1100** in accordance with various embodiments. The integrated circuit **1100** may include eight field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6**, **T7**. FIG. **12** shows a transistor arrangement of an integrated circuit **1200** in accordance with various embodiments. The integrated circuit **1200** may include nine field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6**, **T7**, **T8**. FIG. **13** shows a transistor arrangement of an integrated circuit **1300** in accordance with various embodiments. The integrated circuit **1300** may include ten field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6**, **T7**, **T8**, **T9**. The field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6**, **T7** (and/or **T8**, and/or **T9**) can be connected in series and/or in parallel. The field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6**, **T7** (and/or **T8**, and/or **T9**) can be arranged in such a way that no contacts are formed between adjacent field effect transistors. Ten examination needles are necessary for analyzing properties of a field effect transistor of the field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6**, **T7** of the transistor arrangement illustrated in FIG. **11**. Eleven examination needles are necessary for analyzing properties of a field effect transistor of the field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6**, **T7**, **T8** of the transistor arrangement illustrated in FIG. **12**. Twelve examination needles of an examination apparatus are necessary for analyzing properties of a field effect transistor of the field effect transistors **T0**, **T1**, **T2**, **T3**, **T4**, **T5**, **T6**, **T7**, **T8**, **T9** of the transistor arrangement illustrated in FIG. **13**.

(113) FIG. **14** shows a transistor arrangement of an integrated circuit **1400** in accordance with various embodiments. The integrated circuit **1400** may include eighteen field effect transistors **T0** to **T17**. The field effect transistors **T0** to **T17** can be connected in series and/or in parallel. The field effect transistors **T0** to **T17** can be arranged in such a way that no contacts are formed between adjacent field effect transistors. Twenty examination needles are necessary for analyzing properties of a field effect transistor of the field effect transistors **T0** to **T17**.

(114) In accordance with various embodiments, an integrated circuit may include a multiplicity of field effect transistors, wherein the field effect transistors of the multiplicity of field effect transistors can be connected in series and/or in parallel. The field effect transistors can be arranged in such a way that no contacts are formed between adjacent field effect transistors. This has the effect that, in order to analyze various properties of a field effect transistor, the number of necessary examination needles increases with the number of field effect transistors. In accordance with various embodiments, contacts (such as, for example, gate contacts, drain contacts and/or source contacts) of the integrated circuit can be arranged in such a way that a distance between the contacts is reduced, for example minimized. This has the effect that simultaneous electrical contacting of the contacts in order to detect properties of a field effect transistor is restricted, for example prevented.

(115) Various embodiments provide an integrated circuit by means of which a circuit design can be (physically) obfuscated (for example disguised).

(116) In the course of the reverse engineering of an integrated circuit with the aim of extracting the circuit design, it may be necessary, for example, to analyze properties of switching elements. Therefore, hindering, for example preventing, the analyzing may necessitate hindering, for example preventing, determination of transistor transfer properties.

(117) The integrated circuit which is described herein in accordance with various embodiments can hinder, for example prevent, by way of example the analyzing of properties of switching elements of the integrated circuit. By way of example, an analysis of subcircuits of the integrated circuit can be prevented since illustratively the integrated circuit is not divisible in a meaningful way with regard to an analysis of the switching elements.

(118) In accordance with various embodiments, an integrated circuit may include for example: at least seven planar field effect transistors provided in a common substrate next to one another with a maximum feature size in accordance with a technology node of a maximum of 65 nm. Each field effect transistor of the at least seven planar field effect transistors may include for example a first source/drain diffusion region, a second source/drain diffusion region, a channel region between the drain diffusion region and the source diffusion region, and a gate terminal. Furthermore, for example each field effect transistor of the at least seven planar field effect transistors include at least one common source/drain diffusion region with another field effect transistor of the at least seven planar field effect transistors, wherein the common source/drain diffusion regions can be free of vertical terminal contact material.

(119) A technology node can relate to an architecture of an integrated circuit. A technology node can specify a smallest possible feature size, for example. The smallest possible feature size can relate for example to the smallest possible distance between two structural elements. A technology node can be for example technology nodes having a smallest possible feature size of 1 μm , 800 nm, 600 nm, 350 nm, 250 nm, 180 nm, 130 nm, 90 nm, 65 nm, 45 nm, 32 nm, 22 nm, 14 nm, 10 nm, 7 nm, 5 nm etc.

(120) An integrated circuit of a first example may include at least seven planar field effect transistors provided in a common substrate next to one another in a maximum feature size in accordance with a technology node of a maximum of 65 nm. Each field effect transistor of the at least seven planar field effect transistors includes a first source/drain diffusion region, a second source/drain diffusion region, a channel region between the drain diffusion region and the source diffusion region, and a gate terminal. Each field effect transistor of the at least seven planar field effect transistors includes at least one common source/drain diffusion region with another field effect transistor of the at least seven planar field effect transistors. The common source/drain diffusion regions are free of vertical terminal contact material.

(121) Two field effect transistors of the at least seven planar field effect transistors may each include a source/drain diffusion region with a vertical terminal connected thereto and composed of vertical terminal contact material for electrically contacting the respective source/drain diffusion region. This has the effect that the common source/drain diffusion regions of the other field effect transistors of the at least seven planar field effect transistors can be contacted indirectly by means of the two vertical terminals. The feature described in this paragraph in combination with the first example forms a second example.

(122) A vertical terminal can be any type of connection which can connect (for example electrically connect) semiconductor elements in different planes (such as, for example, in different metallization planes) of an integrated circuit. A vertical terminal can be embodied substantially vertically. A vertical terminal may include a through contact (for example a contact consisting of metal or a metal alloy), such as, for example, contacts to source/drain terminals of MOSFETs (contacting to metal 1 through the insulation layer lying between source/drain and metal 1). The gate terminal of each field effect transistor of the at least seven planar field effect transistors may include a vertical terminal connected thereto and composed of vertical terminal contact material for electrically contacting the respective gate terminal. This has the effect that the gate terminal of each field effect transistor of the at least seven field effect transistors can be individually electrically contacted (for example individually driven). The feature described in this paragraph in combination with the first example or the second example forms a third example.

(123) The vertical terminal contact material may include or substantially consist of a metal or a metal alloy. The features described in this paragraph in combination with one or more of the first example to the third example form a fourth example.

(124) The at least seven planar field effect transistors can form a first group of field effect transistors. The integrated circuit may furthermore include a second group of field effect transistors having at least seven planar field effect transistors. At least some of the planar field effect

transistors of the first group of field effect transistors can have a different nominal transconductance than at least some of the planar field effect transistors of the second group of field effect transistors. This has the effect that the field effect transistors of the first group of field effect transistors and the field effect transistors of the second group of field effect transistors can be interconnected to form a logic circuit. The features described in this paragraph in combination with one or more of the first example to the fourth example form a fifth example.

(125) The planar field effect transistors of the first group of field effect transistors can be field effect transistors of a first conductivity type. Some of the planar field effect transistors of the second group of field effect transistors can be field effect transistors of a second conductivity type. The second conductivity type can be different than the first conductivity type. The features described in this paragraph in combination with the fifth example form a sixth example.

(126) The threshold voltages of some of the planar field effect transistors of the first group of field effect transistors can differ from the threshold voltages of some of the planar field effect transistors of the second group of field effect transistors, for example by at least approximately 50 mV to approximately 150 mV. The features described in this paragraph in combination with the fifth example or the sixth example form a seventh example.

(127) The current-voltage characteristic curves of some of the planar field effect transistors of the first group of field effect transistors can differ from the current-voltage characteristic curves of some of the planar field effect transistors of the second group of field effect transistors. The feature described in this paragraph in combination with one or more of the fifth example to the seventh example forms an eighth example.

(128) The transfer characteristic of some of the planar field effect transistors of the first group of field effect transistors can differ from the transfer characteristic of some of the planar field effect transistors of the second group of field effect transistors. The feature described in this paragraph in combination with one or more of the fifth example to the eighth example forms a ninth example.

(129) The at least seven planar field effect transistors can form a NAND-based circuit, a NOR-based circuit, an AND/NOR-based circuit or an OR-NAND-based circuit. The features described in this paragraph in combination with one or more of the first example to the ninth example form a tenth example.

(130) The at least seven planar field effect transistors can be part of a flip-flop, for example of an RS flip-flop. This has the effect that at least two of the at least seven planar field effect transistors have substantially identical transfer properties (for example transconductance). The feature described in this paragraph in combination with one or more of the first example to the tenth example forms an eleventh example.

(131) The at least seven planar field effect transistors can be part of a NAND-based RS flip-flop, of a NOR-based RS flip-flop, of an AND-NOR-based RS flip-flop or of an OR-NAND-based RS flip-flop. The features described in this paragraph in combination with the tenth example and the eleventh example form a twelfth example.

(132) The planar field effect transistors of the first group of field effect transistors and the planar field effect transistors of the second group of field effect transistors can be interconnected to form a NAND-based RS flip-flop, to form a NOR-based RS flip-flop, to form an AND-NOR-based RS flip-flop or to form an OR-NAND-based RS flip-flop. The features described in this paragraph in combination with one or more of the fifth example to the twelfth example form a thirteenth example.

(133) The field effect transistors of the first group of field effect transistors can be metal oxide semiconductor (MOS) field effect transistors. The features described in this paragraph in combination with one or more of the fifth example to the thirteenth example forms a fourteenth example.

(134) The field effect transistors of the second group of field effect transistors can be metal oxide semiconductor (MOS) field effect transistors. The feature described in this paragraph in

combination with one or more of the fifth example to the fourteenth example forms a fifteenth example.

(135) The substrate may include or substantially consist of a semiconductor material or a semiconductor composite material. The feature described in this paragraph in combination with one or more of the fifth example to the fifteenth example forms a sixteenth example.

(136) The substrate may include or substantially consist of a semiconductor material or a semiconductor composite material which is selected from a group of materials consisting of: silicon, silicon carbide, gallium arsenide, gallium nitride. The features described in this paragraph in combination with the sixteenth example form a seventeenth example.

(137) The integrated circuit may furthermore include one or more metallization planes for electrically contacting the field effect transistors contained in the substrate by means of contact vias composed of vertical terminal contact material. The features described in this paragraph in combination with one or more of the fifth example to the seventeenth example form an eighteenth example.

(138) While the invention has been particularly shown and described with reference to specific embodiments, it should be understood by those skilled in the art that various changes in form and detail may be made therein without departing from the spirit and scope of the invention as defined by the appended claims. The scope of the invention is thus indicated by the appended claims and all changes which come within the meaning and range of equivalency of the claims are therefore intended to be embraced.

Claims

1. An integrated circuit, comprising: seven planar field effect transistors provided in a common substrate next to one another, wherein the seven planar field effect transistors are connected in series with one another; wherein each field effect transistor of the seven planar field effect transistors comprises a first source/drain diffusion region, a second source/drain diffusion region, a channel region between the first source/drain diffusion region and the second source/drain diffusion region, and a gate terminal; wherein each field effect transistor of the seven planar field effect transistors comprises at least one common source/drain diffusion region with another field effect transistor of the seven planar field effect transistors and wherein, in the at least one common source/drain diffusion region, a drain of a first transistor and a source of a second transistor, adjacent to the first transistor, share a conductor common to both the drain of the first transistor and the source of the second transistor; wherein any common source/drain diffusion regions defined by the first source/drain diffusion region and the second source/drain diffusion region are free of vertical terminal contact material; wherein the gate terminal of each field effect transistor of the seven planar field effect transistors comprises a vertical terminal connected thereto and composed of vertical terminal contact material for electrically contacting the respective gate terminal; further comprising a first gate group, in which gates of at least two planar field effect transistors of the seven planar field effect transistors are connected via a first common conductor, and a second gate group, in which gates of at least two other planar field effect transistors of the seven planar field effect transistors are connected via a second common conductor, different from the first common conductor.

2. The integrated circuit of claim 1, wherein two field effect transistors of the seven planar field effect transistors each comprise a source/drain diffusion region with a vertical terminal connected thereto and composed of vertical terminal contact material for electrically contacting the respective source/drain diffusion region.

3. The integrated circuit of claim 1, wherein the vertical terminal contact material comprises a metal or a metal alloy.

4. The integrated circuit of claim 1, wherein the seven planar field effect transistors form a first

group of field effect transistors; wherein the integrated circuit furthermore comprises a second group of field effect transistors comprising seven planar field effect transistors; wherein at least two of the planar field effect transistors of the first group of field effect transistors have a different transconductance than at least two of the planar field effect transistors of the second group of field effect transistors.

5. The integrated circuit of claim 4, wherein the planar field effect transistors of the first group of field effect transistors are field effect transistors of a first conductivity type; wherein at least some of the planar field effect transistors of the second group of field effect transistors are field effect transistors of a second conductivity type, which is different than the first conductivity type.

6. The integrated circuit of claim 4, wherein at least two threshold voltages of the planar field effect transistors of the first group of field effect transistors differ from at least two threshold voltages of the planar field effect transistors of the second group of field effect transistors by at least approximately 50 mV to approximately 150 mV.

7. The integrated circuit of claim 4, wherein the planar field effect transistors of the first group of field effect transistors and the planar field effect transistors of the second group of field effect transistors are interconnected to form a NAND-based RS flip-flop, to form a NOR-based RS flip-flop, to form an AND-NOR-based RS flip-flop or to form an OR-NAND-based RS flip-flop.

8. The integrated circuit of claim 4, wherein the field effect transistors of the first group of field effect transistors are metal oxide semiconductor (MOS) field effect transistors.

9. The integrated circuit of claim 4, wherein the field effect transistors of the second group of field effect transistors are metal oxide semiconductor (MOS) field effect transistors.

10. The integrated circuit of claim 4, wherein the substrate comprises a semiconductor material or a semiconductor composite material.

11. The integrated circuit of claim 10, wherein the substrate comprises a semiconductor material or a semiconductor composite material which is selected from a group of materials consisting of: silicon; silicon carbide; gallium arsenide; and gallium nitride.

12. The integrated circuit of claim 1, wherein the seven planar field effect transistors form a part of a NAND-based circuit, a NOR-based circuit, an AND/NOR-based circuit or an OR-NAND-based circuit.

13. The integrated circuit of claim 12, wherein the seven planar field effect transistors are part of a NAND-based RS flip-flop, of a NOR-based RS flip-flop, of an AND-NOR-based RS flip-flop or of an OR-NAND-based RS flip-flop.
