

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407472
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Zhou; Yan et al.

Beam failure detection (BFD) in dormancy bandwidth part (BWP)

Abstract

Wireless communications systems and methods related to beam failure detection (BFD) in a dormancy bandwidth part (BWP) are provided. A user equipment (UE) determines to operate in a dormancy mode for a cell of a wireless communication network. The UE operates in the dormancy mode for the cell of the wireless communication network, where the operating in the dormancy mode includes performing a beam failure detection (BFD) in a dormancy bandwidth part (BWP) based on a configuration. The configuration may include a control resource set (CORESET) configuration for the dormancy BWP.

Inventors:	Zhou; Yan (San Diego, CA), Luo; Tao (San Diego, CA), Cheng; Peng (Beijing, CN), Chen; Wanshi (San Diego, CA)
Applicant:	QUALCOMM Incorporated (San Diego, CA)
Family ID:	77489766
Assignee:	QUALCOMM Incorporated (San Diego, CA)
Appl. No.:	17/760414
Filed (or PCT Filed):	February 23, 2021
PCT No.:	PCT/CN2021/077400
PCT Pub. No.:	WO2021/169935
PCT Pub. Date:	September 02, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20230069021 A1	Mar. 02, 2023

Foreign Application Priority Data

Publication Classification**Int. Cl.:** H04L5/00 (20060101)**U.S. Cl.:****CPC** H04L5/0053 (20130101); H04L5/0051 (20130101); H04L5/0094 (20130101);**Field of Classification Search****CPC:** H04L (47/746); H04L (5/0037); H04L (5/0042); H04L (5/0048); H04L (5/0092); H04W (24/04); H04W (72/042); H04W (72/0453); H04W (72/046); H04W (72/0493); H04W (72/08); H04W (76/18); H04W (76/19)

References Cited**U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2015/0215929	12/2014	Damnjanovic	370/241	H04W 72/21
2019/0037498	12/2018	Tseng et al.	N/A	N/A
2019/0306842	12/2018	Cirik	N/A	H04B 7/0617
2019/0306909	12/2018	Zhou	N/A	H04W 72/23
2019/0372830	12/2018	Zhang et al.	N/A	N/A
2019/0394660	12/2018	He et al.	N/A	N/A
2020/0052769	12/2019	Cirik	N/A	H04L 5/0051
2020/0221428	12/2019	Moon	N/A	H04B 7/024
2021/0058136	12/2020	Yang	N/A	H04W 72/0453
2021/0226684	12/2020	Koskela	N/A	H04L 5/0042
2021/0243741	12/2020	Lin	N/A	H04W 76/28
2022/0330155	12/2021	Cheng	N/A	H04W 72/0453

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
110392380	12/2018	CN	N/A
2018169848	12/2017	WO	N/A
2019216418	12/2018	WO	N/A
2020015530	12/2019	WO	N/A
2020028792	12/2019	WO	N/A
2020032653	12/2019	WO	N/A

OTHER PUBLICATIONS

LG Electronics: "Considerations On Power Saving for NR", 3GPP TSG RAN WG1 Ah-Hoc Meeting 1901, R1-1900602, Taipei, Taiwan, Jan. 21-25, 2019, Jan. 11, 2019, 5 Pages. (Year: 2019). cited by examiner

LG Electronics: "Considerations on Power Saving for NR", 3GPP TSG RAN WG1 Ah-Hoc Meeting 1901, R1-1900602, 3rd Generation Partnership Project, Mobile Competence Centre, 650, Route Des Lucioles, F-06921 Sophia-Antipolis Cedex, France, vol. RAN WG1, No. Taipei,

Taiwan, Jan. 21, 2019-Jan. 25, 2019, Jan. 20, 2019 (Jan. 20, 2019), 5 Pages, XP051593449, Section 2, p. 3, p. 4. cited by applicant

Nokia, et al., “BED on dormant SCell”, R2-2000678, 3rd Generation Partnership Project, Mobile Competence Centre, 650, Route Des Lucioles, F-06921 Sophia-Antipolis Cedex, France, vol. RAN WG2, No. Elbonia, Feb. 24, 2020-Mar. 6, 2020, Feb. 14, 2020, XP051849253, 1 Page, p. 1. cited by applicant

Qualcomm Incorporated: “Solutions for Fast SCG and SCell Activation”, R1-1900922, 3rd Generation Partnership Project, Mobile Competence Centre, 650, Route Des Lucioles, F-06921 Sophia-Antipolis Cedex, France, vol. RAN WG1, No. Taipei, Taiwan, Jan. 21, 2019-Jan. 25, 2019, Jan. 12, 2019, XP051576459, 6 Pages, p. 3. cited by applicant

Supplementary European Search Report—EP21760730—Search Authority—Munich—Mar. 5, 2024. cited by applicant

International Search Report and Written Opinion—PCT/CN2020/076401—ISA/EPO—Nov. 26, 2020. cited by applicant

International Search Report and Written Opinion—PCT/CN2021/077400—ISA/EPO—May 8, 2021. cited by applicant

LG Electronics: “Discussion on Power Saving for CA Operation,” 3GPP TSG RAN WG1 Meeting #94bis, R1-1810312, Chengdu, China, Oct. 8-12, 2018, Oct. 13, 2018 (Oct. 13, 2018), p. 2, 3 pages. cited by applicant

OPPO: “Introduction of Dormancy Behavior in NR”, 3GPP TSG-RAN WG2 Meeting #107bis, R2-1913942, ChongQing, China, Oct. 14-18, 2019, Oct. 19, 2019 (Oct. 19, 2019), pp. 1-4, 4 pages. cited by applicant

LG Electronics: “Considerations On Power Saving for NR”, 3GPP TSG RAN WG1 Ah-Hoc Meeting 1901, R1-1900602, Taipei, Taiwan, Jan. 21-25, 2019, Jan. 11, 2019, 5 Pages. cited by applicant

Nokia, et al., “BFD on Dormant SCell”, 3GPP TSG-RAN WG2 Meeting #109e, R2-2000678, Elbonia, Feb. 24-Mar. 6, 2020, Feb. 14, 2020, 1 page. cited by applicant

Qualcomm Incorporated: “Solutions for Fast SCG and SCell Activation”, 3GPP TSG-RAN WG1 Ad-Hoc Meeting 1901, R1-1900922, Taipei, Taiwan, Jan. 21-25, 2019, Jan. 12, 2019, pp. 1-6. cited by applicant

Primary Examiner: Ohri; Romani

Attorney, Agent or Firm: Haynes and Boone, LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS

(1) The present application is a 35 U.S.C. 371 National Phase entry of Patent Cooperation Treaty (PCT) Application No. PCT/CN2021/077400, filed Feb. 23, 2021, which claims priority to and the benefit of Patent Cooperation Treaty (PCT) Application No. PCT/CN2020/076401, filed Feb. 24, 2020. The aforementioned applications are hereby incorporated by reference in their entireties as if fully set forth below and for all applicable purposes.

TECHNICAL FIELD

(2) The present disclosure is directed to wireless communication systems and methods. Certain embodiments can enable and provide techniques for beam failure detection (BFD) in a dormancy bandwidth part (BWP).

INTRODUCTION

(3) Wireless communications systems are widely deployed to provide various types of communication content such as voice, video, packet data, messaging broadcast, and so on. These systems may be capable of supporting communication with multiple users by sharing the available system resources (e.g., time, frequency, and power). A wireless multiple-access communications system may include a number of base stations (BSs), each simultaneously supporting communications for multiple communication devices, which may be otherwise known as user equipment (UE).

(4) To meet the growing demands for expanded mobile broadband connectivity, wireless communication technologies are advancing from the long-term evolution (LTE) technology to a next generation new radio (NR) technology, which may be referred to as 5th Generation (5G). For example, NR is designed to provide a lower latency, a higher bandwidth or a higher throughput, and a higher reliability than LTE. NR is designed to operate over a wide array of spectrum bands, for example, from low-frequency bands below about 1 gigahertz (GHz) and mid-frequency bands from about 1 GHz to about 6 GHz, to high-frequency bands such as millimeter wave (mmWave) bands. NR is also designed to operate across different spectrum types, from licensed spectrum to unlicensed and shared spectrum. Spectrum sharing enables operators to opportunistically aggregate spectrums to dynamically support high-bandwidth services. Spectrum sharing can extend the benefit of NR technologies to operating entities that may not have access to a licensed spectrum.

(5) NR may utilize beamforming in combination with BWPs to benefit from the wider channel bandwidth available at higher frequencies (e.g., in a mmWave band). For instance, pathloss can be high in the higher frequency bands and wideband operations in the wider channel bandwidth can be costly. To overcome the high pathloss, a BS and/or a UE may perform analog and/or digital beamforming to create narrow directional beams for communications. To avoid having UEs to operate in the wide channel bandwidth, BWPs allows UEs to communicate with a BS using a frequency bandwidth smaller or narrower than the channel bandwidth. BWPs refers to the partitioning of a channel bandwidth into smaller frequency bands. For instance, in NR, a BS may configure a UE with a maximum of four BWPs in a channel bandwidth and the BS may activate one BWP for communications with the UE at any given time. The UE is not required to transmit or receive outside of the configured frequency range of the active BWP, and thus may provide power saving at the UE.

BRIEF SUMMARY OF SOME EXAMPLES

(6) The following summarizes some aspects of the present disclosure to provide a basic understanding of the discussed technology. This summary is not an extensive overview of all contemplated features of the disclosure and is intended neither to identify key or critical elements of all aspects of the disclosure nor to delineate the scope of any or all aspects of the disclosure. Its sole purpose is to present some concepts of one or more aspects of the disclosure in summary form as a prelude to the more detailed description that is presented later.

(7) For example, in an aspect of the disclosure, a method of wireless communication by a first user equipment (UE), the method includes determining to operate in a dormancy mode for a cell of a wireless communication network; and operating in the dormancy mode for the cell of the wireless communication network, where the operating in the dormancy mode includes performing a beam failure detection (BFD) in a dormancy bandwidth part (BWP) based on a configuration.

(8) In an additional aspect of the disclosure, a method of wireless communication performed by a base station (BS), the method includes determining a user equipment (UE) is operating in a dormancy mode for a cell of a wireless communication network; and transmitting, to the UE, a configuration for performing a beam failure detection (BFD) in a dormancy bandwidth part (BWP) associated with the dormancy mode.

(9) In an additional aspect of the disclosure, a user equipment (UE) includes a processor configured to determine to operate in a dormancy mode for a cell of a wireless communication network; and operate in the dormancy mode for the cell of the wireless communication network, where the

operating in the dormancy mode includes performing a beam failure detection (BFD) in a dormancy bandwidth part (BWP) based on a configuration.

(10) In an additional aspect of the disclosure, a base station (BS) includes a processor configured to determine a user equipment (UE) is operating in a dormancy mode for a cell of a wireless communication network; and a transceiver configured to transmit, to the UE, a configuration for performing a beam failure detection (BFD) in a dormancy bandwidth part (BWP) associated with the dormancy mode.

(11) Other aspects, features, and embodiments of the present invention will become apparent to those of ordinary skill in the art, upon reviewing the following description of specific, exemplary embodiments of the present invention in conjunction with the accompanying figures. While features of the present invention may be discussed relative to certain embodiments and figures below, all embodiments of the present invention can include one or more of the advantageous features discussed herein. In other words, while one or more embodiments may be discussed as having certain advantageous features, one or more of such features may also be used in accordance with the various embodiments of the invention discussed herein. In similar fashion, while exemplary embodiments may be discussed below as device, system, or method embodiments it should be understood that such exemplary embodiments can be implemented in various devices, systems, and methods.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 illustrates a wireless communication network according to some aspects of the present disclosure.

(2) FIG. 2 illustrates a radio frame structure according to some aspects of the present disclosure.

(3) FIG. 3 illustrates a BWP configuration scheme according to some aspects of the present disclosure.

(4) FIG. 4 illustrates a BWP configuration scheme according to some aspects of the present disclosure.

(5) FIG. 5 is a block diagram of a user equipment (UE) according to some aspects of the present disclosure.

(6) FIG. 6 is a block diagram of an exemplary base station (BS) according to some aspects of the present disclosure.

(7) FIG. 7 is a signaling diagram of a BFD method according to some aspects of the present disclosure.

(8) FIG. 8 is a flow diagram of a BFD method according to some aspects of the present disclosure.

(9) FIG. 9 is a flow diagram of a BFD method according to some aspects of the present disclosure.

(10) FIG. 10 is a flow diagram of a BFD method for operations in a dormancy mode according to some aspects of the present disclosure.

(11) FIG. 11 illustrates a BFD RS measurement scheme according to some aspects of the present disclosure.

(12) FIG. 12A illustrates a dormancy BWP configuration scheme according to some aspects of the present disclosure.

(13) FIG. 12B illustrates a dormancy BWP configuration scheme according to some aspects of the present disclosure.

(14) FIG. 12C illustrates a dormancy BWP configuration scheme according to some aspects of the present disclosure.

(15) FIG. 13 is a flow diagram of a wireless communication method according to some aspects of the present disclosure.

(16) FIG. 14 is a flow diagram of a wireless communication method according to some aspects of the present disclosure.

(17) FIG. 15 is a flow diagram of a wireless communication method according to some aspects of the present disclosure.

(18) FIG. 16 is a flow diagram of a wireless communication method according to some aspects of the present disclosure.

DETAILED DESCRIPTION

(19) The detailed description set forth below, in connection with the appended drawings, is intended as a description of various configurations and is not intended to represent the only configurations in which the concepts described herein may be practiced. The detailed description includes specific details for the purpose of providing a thorough understanding of the various concepts. However, it will be apparent to those skilled in the art that these concepts may be practiced without these specific details. In some instances, well-known structures and components are shown in block diagram form in order to avoid obscuring such concepts.

(20) This disclosure relates generally to wireless communications systems, also referred to as wireless communications networks. In various embodiments, the techniques and apparatus may be used for wireless communication networks such as code division multiple access (CDMA) networks, time division multiple access (TDMA) networks, frequency division multiple access (FDMA) networks, orthogonal FDMA (OFDMA) networks, single-carrier FDMA (SC-FDMA) networks, LTE networks, Global System for Mobile Communications (GSM) networks, 5th Generation (5G) or new radio (NR) networks, as well as other communications networks. As described herein, the terms “networks” and “systems” may be used interchangeably.

(21) An OFDMA network may implement a radio technology such as evolved UTRA (E-UTRA), Institute of Electrical and Electronics Engineers (IEEE) 802.11, IEEE 802.16, IEEE 802.20, flash-OFDM and the like. UTRA, E-UTRA, and GSM are part of universal mobile telecommunication system (UMTS). In particular, long term evolution (LTE) is a release of UMTS that uses E-UTRA. UTRA, E-UTRA, GSM, UMTS and LTE are described in documents provided from an organization named “3rd Generation Partnership Project” (3GPP), and cdma2000 is described in documents from an organization named “3rd Generation Partnership Project 2” (3GPP2). These various radio technologies and standards are known or are being developed. For example, the 3rd Generation Partnership Project (3GPP) is a collaboration between groups of telecommunications associations that aims to define a globally applicable third generation (3G) mobile phone specification. 3GPP long term evolution (LTE) is a 3GPP project which was aimed at improving the UMTS mobile phone standard. The 3GPP may define specifications for the next generation of mobile networks, mobile systems, and mobile devices. The present disclosure is concerned with the evolution of wireless technologies from LTE, 4G, 5G, NR, and beyond with shared access to wireless spectrum between networks using a collection of new and different radio access technologies or radio air interfaces.

(22) 5G networks contemplate diverse deployments, diverse spectrum, and diverse services and devices that may be implemented using an OFDM-based unified, air interface. In order to achieve these goals, further enhancements to LTE and LTE-A are considered in addition to development of the new radio technology for 5G NR networks. The 5G NR will be capable of scaling to provide coverage (1) to a massive Internet of things (IoTs) with a ultra-high density (e.g., ~1M nodes/km.sup.2), ultra-low complexity (e.g., ~10 s of bits/sec), ultra-low energy (e.g., ~10+ years of battery life), and deep coverage with the capability to reach challenging locations; (2) including mission-critical control with strong security to safeguard sensitive personal, financial, or classified information, ultra-high reliability (e.g., ~99.9999% reliability), ultra-low latency (e.g., ~1 ms), and users with wide ranges of mobility or lack thereof and (3) with enhanced mobile broadband including extreme high capacity (e.g., ~10 Tbps/km.sup.2), extreme data rates (e.g., multi-Gbps rate, 100+ Mbps user experienced rates), and deep awareness with advanced discovery and

optimizations.

(23) The 5G NR may be implemented to use optimized OFDM-based waveforms with scalable numerology and transmission time interval (TTI); having a common, flexible framework to efficiently multiplex services and features with a dynamic, low-latency time division duplex (TDD)/frequency division duplex (FDD) design; and with advanced wireless technologies, such as massive multiple input, multiple output (MIMO), robust millimeter wave (mmWave) transmissions, advanced channel coding, and device-centric mobility. Scalability of the numerology in 5G NR, with scaling of subcarrier spacing, may efficiently address operating diverse services across diverse spectrum and diverse deployments. For example, in various outdoor and macro coverage deployments of less than 3 GHz FDD/TDD implementations, subcarrier spacing may occur with 15 kHz, for example over 5, 10, 20 MHz, and the like bandwidth (BW). For other various outdoor and small cell coverage deployments of TDD greater than 3 GHz, subcarrier spacing may occur with 30 kHz over 80/100 MHz BW. For other various indoor wideband implementations, using a TDD over the unlicensed portion of the 5 GHz band, the subcarrier spacing may occur with 60 kHz over a 160 MHz BW. Finally, for various deployments transmitting with mmWave components at a TDD of 28 GHz, subcarrier spacing may occur with 120 kHz over a 500 MHz BW.

(24) The scalable numerology of the 5G NR facilitates scalable TTI for diverse latency and quality of service (QoS) requirements. For example, shorter TTI may be used for low latency and high reliability, while longer TTI may be used for higher spectral efficiency. The efficient multiplexing of long and short TTIs to allow transmissions to start on symbol boundaries. 5G NR also contemplates a self-contained integrated subframe design with UL/downlink scheduling information, data, and acknowledgement in the same subframe. The self-contained integrated subframe supports communications in unlicensed or contention-based shared spectrum, adaptive UL/downlink that may be flexibly configured on a per-cell basis to dynamically switch between UL and downlink to meet the current traffic needs.

(25) Various other aspects and features of the disclosure are further described below. It should be apparent that the teachings herein may be embodied in a wide variety of forms and that any specific structure, function, or both being disclosed herein is merely representative and not limiting. Based on the teachings herein one of an ordinary level of skill in the art should appreciate that an aspect disclosed herein may be implemented independently of any other aspects and that two or more of these aspects may be combined in various ways. For example, an apparatus may be implemented or a method may be practiced using any number of the aspects set forth herein. In addition, such an apparatus may be implemented or such a method may be practiced using other structure, functionality, or structure and functionality in addition to or other than one or more of the aspects set forth herein. For example, a method may be implemented as part of a system, device, apparatus, and/or as instructions stored on a computer readable medium for execution on a processor or computer. Furthermore, an aspect may comprise at least one element of a claim.

(26) To apply beamforming techniques for communications, a BS and a UE may perform beam measurements and beam selections to determine one or more optimal beams for communications. An optimal beam may refer to a transmission beam that can provide a receiver with a high receive power and/or a high signal-to-noise ratio (SNR). For instance, the BS may transmit a set of reference signals, such as synchronization signal block (SSBs), by sweeping through a number of spatial directions to facilitate initial beam measurements and selections. Additionally, the BS may configure the UE with a set of reference signals, which may include SSBs, tracking reference signals (TRSs), and/or channel state information-reference signals (CSI-RSs), for beam failure detection (BFD). The set of reference signals configured for BFD may be referred to as BFD reference signals (BFD RSs). For instance, the UE may monitor the BFD RSs and determine link quality or beam quality from measurements of the BFD RSs. The UE may detect a beam failure condition, for example, when a link quality measurement falls below a certain threshold. Upon

detecting a beam failure, the UE may perform beam recovery with the BS, for example, by requesting the BS to use a transmission beam in a different spatial direction.

(27) In a certain wireless communication network, a BS may configure a UE to monitor BFD RSs that are spatially quasi-co-located (QCLed) with a physical downlink control channel (PDCCH) demodulation reference signal (DMRS). In other words, the DL beams (or DL channel conditions) used for transmitting the BFD RSs may correspond to the DL beams (or DL channel conditions) used for transmitting the PDCCH DMRSs. In NR, there are several types of quasi colocation relationship, for example, in terms of delay spread, doppler spread, doppler shift, average delay, and/or spatial receive parameters. A BS may configure a UE with one or more control resource sets (CORESETs) in a BWP and may configure the UE with one or more PDCCH search spaces based on the CORESETs. Each CORESET may include one or more transmission configuration indication (TCI) states, which may indicate DL reference signals (e.g., SSBs, CSI-RSs, and/or TRSs) that are QCLed with a corresponding PDCCH DMRS.

(28) In some aspects, a BS can configure a UE to operate in a dormancy BWP, for example, for power saving. Since the UE is not expected to perform PDCCH monitoring in the dormancy BWP, the BS may not configure the UE with a CORESET in the dormancy BWP. However, the BS expects the UE to perform BFD while operating in the dormancy BWP. Without a CORESET configured in the dormancy BWP, the UE may be unable to determine which resource(s) or BFD RSs to monitor for BFD.

(29) The present disclosure describes mechanisms for BFD in a dormancy BWP. For example, a BS may configure a UE to operate in a dormancy mode for a cell in a network. The cell can be a primary cell (PCell) or a secondary cell (SCell). The BS may configure the UE with a BFD configuration for performing BFD when the UE operates in a dormancy BWP. In some aspects, the BS may configure the UE to exclude performing BFD in a dormancy BWP. In some aspects, the BS may configure the UE with a set of rules to determine BFD RSs and corresponding resources for BFD RS monitoring when the UE operates in the dormancy BWP.

(30) In some aspects, the BS may configure the UE to perform BFD RS monitoring while operating in a dormancy BWP if the UE is configured with explicit BFD RSs. The BS may configure the UE to refrain from performing BFD if the UE is not configured with any explicit BFD RS. In some aspects, the BS may configure the UE to perform the BFD in the dormancy BWP by monitoring for one or more BFD RSs quasi-co-located (QCLed) with a CORESET in a non-dormancy BWP before the UE switches to the dormancy BWP. In some aspects, the BS may configure the UE with a non-dormancy BWP paired with the dormancy BWP. The BS may configure the UE to monitor for one or more BFD RSs that are QCLed with a CORESET in the paired non-dormancy BWP when the UE operates in the dormancy BWP. In some aspects, the BS may configure the UE with a CORESET in the dormancy BWP, but may configure a zero number of PDCCH candidates for the CORESET. The BS may configure the UE to monitor for one or more BFD RSs that are QCLed with a CORESET in the dormancy BWP.

(31) In some aspects, the BS may configure the UE to perform BFD RS monitoring in a dormancy BWP if the UE is configured with implicit BFD RSs. The BS may configure the UE to refrain from performing BFD if the UE is not configured with any implicit BFD RS. In some aspects, the BS may configure the UE to monitor for one or more BFD RSs associated with a TCI state of a CORESET in a non-dormancy BWP before the UE switches to the dormancy BWP, a paired non-dormancy BWP, or the dormancy BWP.

(32) In some aspects, the BS may transmit one or more BFD RSs fully within the dormancy BWP, partially within the dormancy BWP, and/or outside the dormancy BWP. In some aspects, the BS may configure the UE to perform measurements on a BFD RS that is fully within the dormancy BWP. In some aspects, when a BFD RS is partially within the dormancy BWP, the BS may configure the UE to measure the portion of the BFD RS that is within the dormancy BWP. Alternatively, the BS may configure the UE to measure the entire BFD RS including the portion

outside the dormancy BWP. In some aspects, when a BFD RS is outside the dormancy BWP, the BS may configure the UE exclude measurements on the BFD RS. Alternatively, the BS may configure the UE to switch to the BWP where the BFD RS is located or extend the BWP to include the BWP where the BFD RS is located and measure the BFD RS.

(33) In some aspects, the BS may configure UE with a non-dormancy BWP via a radio resource control (RRC) configuration and later switches the RRC configured BWP to a dormancy BWP via downlink control information (DCI), media access control-control element (MAC-CE), or a wakeup signal (WUS). The transition of the BWP to the dormancy mode can be permanent or for a certain duration.

(34) Aspects of the present disclosure can provide several benefits. For example, the configuring of rules for determining explicit BFD RSs QCLed with CORESET(s) in a certain BWP and/or implicit BFD RSs associated with TCI state(s) of CORESET(s) in a certain BWP enables a UE to perform BFD while operating in a dormancy BWP. Accordingly, the UE may monitor for beam quality in the dormancy BWP and may perform a beam recovery procedure with the BS to switch to another beam or beam pair (e.g., UL and/or DL beams) upon detecting a beam failure condition. In this way, when the BS determines to switch the UE back to a non-dormancy BWP at a later time, the BS and the UE may be ready for communication using beams from the most recent beam selection (e.g., based on the most recent beam recovery) instead of having to perform beam selection at the switching time. Accordingly, the present disclosure can reduce the activation time for switching from a dormancy BWP to a non-dormancy BWP.

(35) FIG. 1 illustrates a wireless communication network **100** according to some aspects of the present disclosure. The network **100** may be a 5G network. The network **100** includes a number of base stations (BSs) **105** (individually labeled as **105a**, **105b**, **105c**, **105d**, **105e**, and **105f** and other network entities. ABS **105** may be a station that communicates with UEs **115** and may also be referred to as an evolved node B (eNB), a next generation eNB (gNB), an access point (e.g., an IEEE 802.11 AP), and the like. Each BS **105** may provide communication coverage for a particular geographic area. In 3GPP, the term “cell” can refer to this particular geographic coverage area of a BS **105** and/or a BS subsystem serving the coverage area, depending on the context in which the term is used.

(36) A BS **105** may provide communication coverage for a macro cell or a small cell, such as a pico cell or a femto cell, and/or other types of cell. A macro cell generally covers a relatively large geographic area (e.g., several kilometers in radius) and may allow unrestricted access by UEs with service subscriptions with the network provider. A small cell, such as a pico cell, would generally cover a relatively smaller geographic area and may allow unrestricted access by UEs with service subscriptions with the network provider. A small cell, such as a femto cell, would also generally cover a relatively small geographic area (e.g., a home) and, in addition to unrestricted access, may also provide restricted access by UEs having an association with the femto cell (e.g., UEs in a closed subscriber group (CSG), UEs for users in the home, and the like). ABS for a macro cell may be referred to as a macro BS. ABS for a small cell may be referred to as a small cell BS, a pico BS, a femto BS or a home BS. In the example shown in FIG. 1, the BSs **105d** and **105e** may be regular macro BSs, while the BSs **105a-105c** may be macro BSs enabled with one of three dimension (3D), full dimension (FD), or massive MIMO. The BSs **105a-105c** may take advantage of their higher dimension MIMO capabilities to exploit 3D beamforming in both elevation and azimuth beamforming to increase coverage and capacity. The BS **105f** may be a small cell BS which may be a home node or portable access point. A BS **105** may support one or multiple (e.g., two, three, four, and the like) cells.

(37) The network **100** may support synchronous or asynchronous operation. For synchronous operation, the BSs may have similar frame timing, and transmissions from different BSs may be approximately aligned in time. For asynchronous operation, the BSs may have different frame timing, and transmissions from different BSs may not be aligned in time.

(38) The UEs **115** are dispersed throughout the wireless network **100**, and each UE **115** may be stationary or mobile. A UE **115** may also be referred to as a terminal, a mobile station, a subscriber unit, a station, or the like. A UE **115** may be a cellular phone, a personal digital assistant (PDA), a wireless modem, a wireless communication device, a handheld device, a tablet computer, a laptop computer, a cordless phone, a wireless local loop (WLL) station, an IEEE 802.11 terminal station (STA), or the like. In one aspect, a UE **115** may be a device that includes a Universal Integrated Circuit Card (UICC). In another aspect, a UE may be a device that does not include a UICC. In some aspects, the UEs **115** that do not include UICCs may also be referred to as IoT devices or internet of everything (IoE) devices. The UEs **115a-115d** are examples of mobile smart phone-type devices accessing network **100**. A UE **115** may also be a machine specifically configured for connected communication, including machine type communication (MTC), enhanced MTC (eMTC), narrowband IoT (NB-IoT) and the like. The UEs **115e-115h** are examples of various machines configured for communication that access the network **100**. The UEs **115i-115k** are examples of vehicles equipped with wireless communication devices configured for communication that access the network **100**. A UE **115** may be able to communicate with any type of the BSs, whether macro BS, small cell, or the like. In FIG. 1, a lightning bolt (e.g., communication links) indicates wireless transmissions between a UE **115** and a serving BS **105**, which is a BS designated to serve the UE **115** on the downlink (DL) and/or uplink (UL), desired transmission between BSs **105**, backhaul transmissions between BSs, or sidelink transmissions between UEs **115**.

(39) In operation, the BSs **105a-105c** may serve the UEs **115a** and **115b** using 3D beamforming and coordinated spatial techniques, such as coordinated multipoint (CoMP) or multi-connectivity. The macro BS **105d** may perform backhaul communications with the BSs **105a-105c**, as well as small cell, the BS **105f**. The macro BS **105d** may also transmit multicast services which are subscribed to and received by the UEs **115c** and **115d**. Such multicast services may include mobile television or stream video, or may include other services for providing community information, such as weather emergencies or alerts, such as Amber alerts or gray alerts.

(40) The BSs **105** may also communicate with a core network. The core network may provide user authentication, access authorization, tracking, Internet Protocol (IP) connectivity, and other access, routing, or mobility functions. At least some of the BSs **105** (e.g., which may be an example of a gNB or an access node controller (ANC)) may interface with the core network through backhaul links (e.g., NG-C, NG-U, etc.) and may perform radio configuration and scheduling for communication with the UEs **115**. In various examples, the BSs **105** may communicate, either directly or indirectly (e.g., through core network), with each other over backhaul links (e.g., X1, X2, etc.), which may be wired or wireless communication links.

(41) The network **100** may also support mission critical communications with ultra-reliable and redundant links for mission critical devices, such as the UE **115e**, which may be a drone. Redundant communication links with the UE **115e** may include links from the macro BSs **105d** and **105e**, as well as links from the small cell BS **105f**. Other machine type devices, such as the UE **115f** (e.g., a thermometer), the UE **115g** (e.g., smart meter), and UE **115h** (e.g., wearable device) may communicate through the network **100** either directly with BSs, such as the small cell BS **105f**, and the macro BS **105e**, or in multi-step-size configurations by communicating with another user device which relays its information to the network, such as the UE **115f** communicating temperature measurement information to the smart meter, the UE **115g**, which is then reported to the network through the small cell BS **105f**. The network **100** may also provide additional network efficiency through dynamic, low-latency TDD/FDD communications, such as V2V, V2X C-V2X communications between a UE **115i**, **115j**, or **115k** and other UEs **115**, and/or vehicle-to-infrastructure (V2I) communications between a UE **115i**, **115j**, or **115k** and a BS **105**.

(42) In some implementations, the network **100** utilizes OFDM-based waveforms for communications. An OFDM-based system may partition the system BW into multiple (K)

orthogonal subcarriers, which are also commonly referred to as subcarriers, tones, bins, or the like. Each subcarrier may be modulated with data. In some instances, the subcarrier spacing between adjacent subcarriers may be fixed, and the total number of subcarriers (K) may be dependent on the system BW. The system BW may also be partitioned into subbands. In other instances, the subcarrier spacing and/or the duration of TTIs may be scalable.

(43) In some aspects, the BSs **105** can assign or schedule transmission resources (e.g., in the form of time-frequency resource blocks (RB)) for downlink (DL) and uplink (UL) transmissions in the network **100**. DL refers to the transmission direction from a BS **105** to a UE **115**, whereas UL refers to the transmission direction from a UE **115** to a BS **105**. The communication can be in the form of radio frames. A radio frame may be divided into a plurality of subframes or slots, for example, about 10. Each slot may be further divided into mini-slots. In a FDD mode, simultaneous UL and DL transmissions may occur in different frequency bands. For example, each subframe includes a UL subframe in a UL frequency band and a DL subframe in a DL frequency band. In a TDD mode, UL and DL transmissions occur at different time periods using the same frequency band. For example, a subset of the subframes (e.g., DL subframes) in a radio frame may be used for DL transmissions and another subset of the subframes (e.g., UL subframes) in the radio frame may be used for UL transmissions.

(44) The DL subframes and the UL subframes can be further divided into several regions. For example, each DL or UL subframe may have pre-defined regions for transmissions of reference signals, control information, and data. Reference signals are predetermined signals that facilitate the communications between the BSs **105** and the UEs **115**. For example, a reference signal can have a particular pilot pattern or structure, where pilot tones may span across an operational BW or frequency band, each positioned at a pre-defined time and a pre-defined frequency. For example, a BS **105** may transmit cell specific reference signals (CRSs) and/or channel state information—reference signals (CSI-RSs) to enable a UE **115** to estimate a DL channel. Similarly, a UE **115** may transmit sounding reference signals (SRSs) to enable a BS **105** to estimate a UL channel. Control information may include resource assignments and protocol controls. Data may include protocol data and/or operational data. In some aspects, the BSs **105** and the UEs **115** may communicate using self-contained subframes. A self-contained subframe may include a portion for DL communication and a portion for UL communication. A self-contained subframe can be DL-centric or UL-centric. A DL-centric subframe may include a longer duration for DL communication than for UL communication. A UL-centric subframe may include a longer duration for UL communication than for UL communication.

(45) In some aspects, the network **100** may be an NR network deployed over a licensed spectrum. The BSs **105** can transmit synchronization signals (e.g., including a primary synchronization signal (PSS) and a secondary synchronization signal (SSS)) in the network **100** to facilitate synchronization. The BSs **105** can broadcast system information associated with the network **100** (e.g., including a master information block (MIB), remaining system information (RMSI), and other system information (OSI)) to facilitate initial network access. In some instances, the BSs **105** may broadcast the PSS, the SSS, and/or the MIB in the form of synchronization signal block (SSBs) over a physical broadcast channel (PBCH) and may broadcast the RMSI and/or the OSI over a physical downlink shared channel (PDSCH).

(46) In some aspects, a UE **115** attempting to access the network **100** may perform an initial cell search by detecting a PSS from a BS **105**. The PSS may enable synchronization of period timing and may indicate a physical layer identity value. The UE **115** may then receive a SSS. The SSS may enable radio frame synchronization, and may provide a cell identity value, which may be combined with the physical layer identity value to identify the cell. The PSS and the SSS may be located in a central portion of a carrier or any suitable frequencies within the carrier.

(47) After receiving the PSS and SSS, the UE **115** may receive a MIB. The MIB may include system information for initial network access and scheduling information for RMSI and/or OSI.

After decoding the MIB, the UE **115** may receive RMSI and/or OSI. The RMSI and/or OSI may include radio resource control (RRC) information related to random access channel (RACH) procedures, paging, control resource set (CORESET) for physical downlink control channel (PDCCH) monitoring, physical UL control channel (PUCCH), physical UL shared channel (PUSCH), power control, and SRS.

(48) After obtaining the MIB, the RMSI and/or the OSI, the UE **115** can perform a random access procedure to establish a connection with the BS **105**. In some examples, the random access procedure may be a four-step random access procedure. For example, the UE **115** may transmit a random access preamble and the BS **105** may respond with a random access response. The random access response (RAR) may include a detected random access preamble identifier (ID) corresponding to the random access preamble, timing advance (TA) information, a UL grant, a temporary cell-radio network temporary identifier (C-RNTI), and/or a backoff indicator. Upon receiving the random access response, the UE **115** may transmit a connection request (e.g., RRC connection request) to the BS **105** and the BS **105** may respond with a connection response. The connection response may indicate a contention resolution. In some examples, the random access preamble, the RAR, the connection request, and the connection response can be referred to as message 1 (MSG1), message 2 (MSG2), message 3 (MSG3), and message 4 (MSG4), respectively. In some examples, the random access procedure may be a two-step random access procedure, where the UE **115** may transmit a random access preamble and a connection request in a single transmission and the BS **105** may respond by transmitting a random access response and a connection response in a single transmission.

(49) After establishing a connection, the UE **115** and the BS **105** can enter a normal operation stage, where operational data may be exchanged. For example, the BS **105** may schedule the UE **115** for UL and/or DL communications. The BS **105** may transmit UL and/or DL scheduling grants to the UE **115** via a PDCCH. The scheduling grants may be transmitted in the form of DL control information (DCI). The BS **105** may transmit a DL communication signal (e.g., carrying data) to the UE **115** via a PDSCH according to a DL scheduling grant. The UE **115** may transmit a UL communication signal to the BS **105** via a PUSCH and/or PUCCH according to a UL scheduling grant.

(50) In some aspects, the BS **105** may communicate with a UE **115** using HARQ techniques to improve communication reliability, for example, to provide a URLLC service. The BS **105** may schedule a UE **115** for a PDSCH communication by transmitting a DL grant in a PDCCH. The BS **105** may transmit a DL data packet to the UE **115** according to the schedule in the PDSCH. The DL data packet may be transmitted in the form of a transport block (TB). If the UE **115** receives the DL data packet successfully, the UE **115** may transmit a HARQ ACK to the BS **105**. Conversely, if the UE **115** fails to receive the DL transmission successfully, the UE **115** may transmit a HARQ NACK to the BS **105**. Upon receiving a HARQ NACK from the UE **115**, the BS **105** may retransmit the DL data packet to the UE **115**. The retransmission may include the same coded version of DL data as the initial transmission. Alternatively, the retransmission may include a different coded version of the DL data than the initial transmission. The UE **115** may apply soft-combining to combine the encoded data received from the initial transmission and the retransmission for decoding. The BS **105** and the UE **115** may also apply HARQ for UL communications using substantially similar mechanisms as the DL HARQ.

(51) In some aspects, the network **100** may operate over a system BW or a component carrier (CC) BW. The network **100** may partition the system BW into multiple BWPs (e.g., portions). A BS **105** may dynamically assign a UE **115** to operate over a certain BWP (e.g., a certain portion of the system BW). The assigned BWP may be referred to as the active BWP. The UE **115** may monitor the active BWP for signaling information from the BS **105**. The BS **105** may schedule the UE **115** for UL or DL communications in the active BWP. In some aspects, a BS **105** may assign a pair of BWPs within the CC to a UE **115** for UL and DL communications. For example, the BWP pair may

include one BWP for UL communications and one BWP for DL communications. Mechanisms for BWP configurations will be described more fully below in FIGS. 3 and 4.

(52) In some aspects, the network **100** may operate over a higher frequency band (e.g., a mmWave band). The BSs **105** and the UEs **115** may apply analog and/or digital beamforming to form narrow directional beams for communications. To facilitate beamforming, a BS **105** and a UE **115** may perform beam measurements and selections to determine one or more optimal beams for communications. An optimal beam may refer to a transmission beam that can provide a receiver with a high receive power and/or a high SNR. For instance, the BS **105** may transmit a set of reference signals, such as SSBs, in various spatial directions to facilitate initial beam measurements and selections. After the UE **115** successfully establishes a connection with the network **100**, the BS **105** may configure the UE **115** with a set of reference signals, which may be SSBs, TRSSs, and/or CSI-RSs, for BFD. For instance, the UE **115** may monitor the BFD RSs and determine the link quality from measurements of the BFD RSs. The UE **115** may detect a beam failure condition, for example, when a link quality measurement falls below a certain threshold, and may request the BS for a beam in a different spatial direction. In some aspects, a BS **105** may configure a UE **115** to operate in a dormancy BWP, for example, for power saving, and may configure the UE with a set of rules for performing BFD RS monitoring for BFD. Mechanisms for performing BFD in a dormancy mode are described in greater detail herein.

(53) FIG. 2 is a timing diagram illustrating a radio frame structure **200** according to some aspects of the present disclosure. The radio frame structure **200** may be employed by BSs such as the BSs **105** and UEs such as the UEs **115** in a network such as the network **100** for communications. In particular, the BS may communicate with the UE using time-frequency resources configured as shown in the radio frame structure **200**. In FIG. 2, the x-axes represent time in some arbitrary units and the y-axes represent frequency in some arbitrary units. The transmission frame structure **200** includes a radio frame **201**. The duration of the radio frame **201** may vary depending on the aspects. In an example, the radio frame **201** may have a duration of about ten milliseconds. The radio frame **201** includes M number of slots **202**, where M may be any suitable positive integer. In an example, M may be about 10.

(54) Each slot **202** includes a number of subcarriers **204** in frequency and a number of symbols **206** in time. The number of subcarriers **204** and/or the number of symbols **206** in a slot **202** may vary depending on the aspects, for example, based on the channel bandwidth, the subcarrier spacing (SCS), and/or the CP mode. One subcarrier **204** in frequency and one symbol **206** in time forms one resource element (RE) **212** for transmission. A resource block (RB) **210** is formed from a number of consecutive subcarriers **204** in frequency and a number of consecutive symbols **206** in time.

(55) In an example, a BS (e.g., BS **105** in FIG. 1) may schedule a UE (e.g., UE **115** in FIG. 1) for UL and/or DL communications at a time-granularity of slots **202** or mini-slots **208**. Each slot **202** may be time-partitioned into K number of mini-slots **208**. Each mini-slot **208** may include one or more symbols **206**. The mini-slots **208** in a slot **202** may have variable lengths. For example, when a slot **202** includes N number of symbols **206**, a mini-slot **208** may have a length between one symbol **206** and (N-1) symbols **206**. In some aspects, a mini-slot **208** may have a length of about two symbols **206**, about four symbols **206**, or about seven symbols **206**. In some examples, the BS may schedule UE at a frequency-granularity of a resource block (RB) **210** (e.g., including about 12 subcarriers **204**).

(56) FIG. 3 is discussed in relation to FIG. 4 to illustrate BWP configuration mechanisms. FIG. 3 illustrates a BWP configuration scheme **300** according to some aspects of the present disclosure. The scheme **300** may be employed by BSs such as the BSs **105** and UEs such as the UEs **115** in a network such as the network **100**. In particular, a BS (e.g., the BSs **105**) may configure a UE (e.g., the UEs **115**) with multiple BWPs as shown in the scheme **300**. In FIG. 3, the x-axis represents time in some arbitrary units, and the y-axis represents frequency in some arbitrary units. In the scheme **300**, the BS and the UE may operate in a channel over a frequency band **301**. The

frequency band **301** may be located at any frequency and may span any suitable frequency bandwidth. In some instances, the frequency band **301** may be a mmWave band and may include a wide bandwidth (e.g., about 40 MHz, 80 MHz, 100 MHz, 500 MHz or more). For simplicity of illustration and discussion, FIG. 3 illustrates the frequency band **301** partitioned into two BWPs **310** (shown as **310a** and **310b**). However, the frequency band **301** can be partitioned into any suitable BWPs **310**. Additionally, the BWPs **310** can be non-overlapping as shown or partially overlapping.

(57) In the illustrated example of FIG. 3, the BS configures the UE with two BWPs **310a** and **310b**. The BS may configure the UE with one or more CORESETs **320** in a BWP **310**. Each CORESET **320** includes a set of physical time and frequency resources (e.g., a group of PRBs similar to the RBs **210**) where PDCCH may be transmitted. For instance, the BS configures the UE with two CORESETs **320** in the BWP **310b**. In some aspects, the BS may configure the BWP **310b** as an active BWP for communication with the UE. In some aspects, the BS may configure the UE to operate in a dormancy mode in the BWP **310a**, which may be referred to as a dormancy BWP. In some aspects, the BS may not configure any CORESET in the dormancy BWP **310a** since the UE is not expected to perform PDCCH monitoring in the dormancy BWP **310a**. In some aspects, the BS may configure the UE with a BWP configuration as shown in FIG. 4.

(58) FIG. 4 illustrates a BWP configuration scheme **400** according to some aspects of the present disclosure. The scheme **400** may be employed by BSs such as the BSs **105** and UEs such as the UEs **115** in a network such as the network **100**. In particular, a BS (e.g., the BSs **105**) may configure a UE (e.g., the UEs **115**) with a BWP configuration **410** as shown in the scheme **400**. In some aspects, the BWP configuration **410** is an RRC configuration. The BS may indicate the BWP configuration **410** in the form of an RRC information element (IE) carried in an RRC message. The BWP configuration **410** may include various information, such as the frequency location, bandwidth, subcarrier spacing, and/or cyclic prefix, related to a BWP (e.g., the BWPs **310**). The BWP configuration **410** may also include a PDCCH configuration **420** (e.g., an RRC message IE) for the respective BWP. The PDCCH configuration **420** may include various information, such as CORESETs and/or PDCCH search spaces, for PDCCH monitoring. In some aspects, the BS may configure the UE with up to about 3 CORESETs and about 10 PDCCH search space sets within a configured BWP. The search space set provides the UE with time domain parameter related to PDCCH monitoring, for example, when the UE may monitor for PDCCH in a certain CORESET. The search space set may include parameters such as aggregation levels and/or number of PDCCH candidates that the UE may use for performing blind decoding on the PDCCH.

(59) In the illustrated example of FIG. 4, the PDCCH configuration **420** includes a CORESET configuration **430**. The CORESET configuration **430** indicates a CORESET #0 and a CORESET #1, which may be similar to the CORESETs **320**. The CORESET configuration **430** may include various information, such as resource information (including a start PRB index, a number of PRBs, a start symbol index, and/or a number of symbols) and/or TCI state information, for each CORESET. As shown, the CORESET #0 may include a TCI state 0 and a TCI state 1, and the CORESET #1 may include a TCI state M-1. The TCI state information may provide the UE with QCL information between PDCCHDMRSs and other references signals (e.g., SSBs, CSI-RSs, and/or TRSs).

(60) In some aspects, the BS may configure the UE with a TCI state table **440**. The UE may determine QCL information associated with a CORESET from the TCI state table **440**. Each row in the TCI state table **440** provides references signal resource information and QCL type information for a certain TCI state. The references signal resource information may indicate the location of the time and/or frequency resources (e.g., symbols and/or subcarriers) where a BS may transmit a respective references signal. The QCL type information may indicate a QCL type A, a QCL type B, a QCL type C, and/or a QCL type D. QCL type A may refer to doppler spread, doppler shift, delay spread, and/or average delay channel characteristics. QCL type B may refer to doppler shift and

doppler spread channel characteristics. QCL type C may refer to average delay and doppler shift channel characteristics. QCL type D may refer to spatial receive parameters. Thus, when TCI state 0 defines the source reference signal(s) for a certain physical signal or channel (e.g., PDCCH), the UE can configure its receive beam(s) in the same way it is configured for receiving the SSB with the index #n. Similarly, when TCI state 1 defines the source reference signal(s) for a certain physical signal or channel (e.g., PDCCH), the UE can configure its receive beam(s) in the same way it is configured for receiving the CSI-RS with the index #k. When TCI state M-1 defines the source reference signal(s) for a certain physical signal or channel (e.g., PDCCH), the UE can configure its receive beam(s) in the same way it is configured for receiving the SSB with the index #p.

(61) As such, when the BS configures the UE to monitor BFD RSs that are spatially QCLed with a PDCCH DMRS in a BWP (e.g., the BWP **310**), the UE may configure its receive beams for BFD RS monitoring based on the TCI state(s) indicated in the CORESET configuration **430**. As an example, the CORESET #1 and CORESET #2 may correspond to the CORESETs **320** in the BWP **310a** of FIG. 3. Thus, based on the CORESET configuration **430** and the TCI state table **440**, the UE may perform BFD RS monitoring by monitoring SSB with index #n, CSI-RS with index #k, and SSB with index #p. The UE may determine whether a beam failure has occurred based on measurements performed on SSB with index #n, CSI-RS with index #k, and/or SSB with index #p.

(62) As described above, the BS may not configure any CORESET in a dormancy BWP (e.g., the BWP **310b**) since the UE is not expected to monitor for PDCCH in the dormancy BWP. For instance, the BS may configure an RRC configuration similar to the RRC configuration **410** for the dormancy BWP, but may not include a PDCCH configuration IE in the BWP configuration. Thus, the UE may be unable to determine which BFD RSs to monitor for the BFD.

(63) Accordingly, the present application provides techniques for a UE to perform BFD RS monitoring while operating in a dormancy mode or dormancy BWP. For instance, a BS may configure the UE with various rules in determining which BFD RSs to monitor for BFD.

(64) FIG. 5 is a block diagram of an exemplary UE **500** according to some aspects of the present disclosure. The UE **500** may be a UE **115** discussed above in FIG. 1. As shown, the UE **500** may include a processor **502**, a memory **504**, a BFD module **508**, a transceiver **510** including a modem subsystem **512** and a radio frequency (RF) unit **514**, and one or more antennas **516**. These elements may be in direct or indirect communication with each other, for example via one or more buses.

(65) The processor **502** may include a central processing unit (CPU), a digital signal processor (DSP), an application specific integrated circuit (ASIC), a controller, a field programmable gate array (FPGA) device, another hardware device, a firmware device, or any combination thereof configured to perform the operations described herein. The processor **502** may also be implemented as a combination of computing devices, e.g., a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration.

(66) The memory **504** may include a cache memory (e.g., a cache memory of the processor **502**), random access memory (RAM), magnetoresistive RAM (MRAM), read-only memory (ROM), programmable read-only memory (PROM), erasable programmable read only memory (EPROM), electrically erasable programmable read only memory (EEPROM), flash memory, solid state memory device, hard disk drives, other forms of volatile and non-volatile memory, or a combination of different types of memory. In an aspect, the memory **504** includes a non-transitory computer-readable medium. The memory **504** may store, or have recorded thereon, instructions **506**. The instructions **506** may include instructions that, when executed by the processor **502**, cause the processor **502** to perform the operations described herein with reference to the UEs **115** in connection with aspects of the present disclosure, for example, aspects of FIGS. 1-4 and 7-13. Instructions **506** may also be referred to as program code. The program code may be for causing a wireless communication device to perform these operations, for example by causing one or more

processors (such as processor **502**) to control or command the wireless communication device to do so. The terms “instructions” and “code” should be interpreted broadly to include any type of computer-readable statement(s). For example, the terms “instructions” and “code” may refer to one or more programs, routines, sub-routines, functions, procedures, etc. “Instructions” and “code” may include a single computer-readable statement or many computer-readable statements.

(67) The BFD module **508** may be implemented via hardware, software, or combinations thereof. For example, the BFD module **508** may be implemented as a processor, circuit, and/or instructions **506** stored in the memory **504** and executed by the processor **502**. In some instances, the BFD module **508** can be integrated within the modem subsystem **512**. For example, the BFD module **508** can be implemented by a combination of software components (e.g., executed by a DSP or a general processor) and hardware components (e.g., logic gates and circuitry) within the modem subsystem **512**.

(68) The BFD module **508** may be used for various aspects of the present disclosure, for example, aspects of FIGS. **1-4** and **7-13**. For instance, the BFD module **508** is configured to determine to operate in a dormancy mode for a cell of a wireless communication network. The wireless communication network may be similar to the network **100**. In some aspects, the cell of the network includes a secondary cell. In some aspects, the cell of the network includes a primary cell. In some aspects, the BFD module **508** may determine to operate in the dormancy mode based on a configuration or trigger received from a BS (e.g., the BSs **105**, **600**, and/or **702**). The BFD module **508** is further configured to operate in the dormancy mode for the cell of the wireless communication network. The BFD module **508** is further configured to operate in the dormancy mode by performing a BFD in accordance with a BFD configuration.

(69) In some aspects, the BFD module **508** is configured to perform the BFD by refraining from performing the BFD in a dormancy BWP (e.g., the BWP **310a**). In some aspects, the BFD module **508** is configured to perform the BFD by monitoring for one or more BFD RSs in a dormancy BWP. In some aspects, the BFD module **508** is further configured to receive a CORESET configuration for the dormancy BWP and monitor for the one or more BFD RSs further based on the CORESET configuration for the dormancy BWP. In some aspects, the CORESET may include a zero number of PDCCH candidates per aggregation level and per search space.

(70) In some aspects, the BFD module **508** is configured to perform the BFD by monitoring for one or more BFD RSs in a BWP when the BFD configuration explicitly indicates the one or more BFD RSs and refrain from performing the BFD when the BFD configuration fails to explicitly indicate the one or more BFD RSs. In some aspects, the BFD module **508** is configured to monitor for the one or more BFD RSs QCLed with a CORESET. When there are more than one QCL type for the CORESET, the BFD module **508** is configured to monitor the BFD RS with a type D quasi-colocation with the CORESET.

(71) In some aspects, the BFD module **508** is configured to perform the BFD by monitoring for one or more BFD RSs in a BWP when the BFD configuration implicitly indicates the one or more BFD RSs and refrain from performing the BFD when the BFD configuration fails to implicitly indicate the one or more BFD RSs. In some aspects, the BFD module **508** is configured to monitor for the one or more BFD RSs associated with a TCI state of a CORESET. When there are more than one TCI states for the CORESET, the BFD module **508** is configured to monitor the BFD RS in a TCI state with a type D quasi-colocation with the CORESET.

(72) In some aspects, the BFD module **508** is configured to perform the BFD by at least one of monitoring for one or more explicit BFD RSs in a BWP when the BFD configuration explicitly indicates the one or more explicit BFD RSs; or monitoring for one or more implicit BFD RSs in the BWP when the BFD configuration fails to explicitly indicate the one or more explicit BFD RSs.

(73) In some aspects, the BFD module **508** is configured to perform the BFD by monitoring for one or more BFD RSs in a BWP, wherein the BWP includes a BWP utilized by the UE **500** before operating in the dormancy mode.

(74) In some aspects, the BFD module **508** is configured to perform the BFD by monitoring for one or more BFD RSs in a BWP, where the BWP includes a first BWP utilized by the UE **500** before operating in the dormancy mode and a dormancy BWP utilized by the UE **500** when operating in the dormancy mode.

(75) In some aspects, the BFD module **508** is configured to perform the BFD by monitoring for one or more BFD RSs fully within a dormancy BWP. In some other aspects, the BFD module **508** is configured to perform the BFD by monitoring for one or more BFD RSs partially within a dormancy BWP, where a first portion of each of the one or more BFD RSs is within the dormancy BWP and a second portion of each of the one or more BFD RSs is outside the dormancy BWP. In some aspects, the BFD module **508** is configured to perform the BFD by measuring at least one parameter of the first portion of each of the one or more BFD RSs. In some aspects, the BFD module **508** is configured to perform the BFD by measuring at least one parameter of each of the one or more BFD RSs based on the first and second portions. In some aspects, the BFD module **508** is configured to perform the BFD by refraining from monitoring for one or more BFD RSs outside of a dormancy BWP. In yet other aspects, the performing the BFD at block **1320** may include monitoring for one or more BFD RSs outside of a dormancy BWP.

(76) In some aspects, the BFD module **508** is further configured to receive the BFD configuration. In some aspects, the BFD module **508** is further configured to receive the BFD configuration via at least one of DCI, a MAC-CE, or a WUS. In some aspects, the BFD configuration indicates a first BWP is associated with the dormancy mode and a second BWP is associated with a non-dormancy mode. In some aspects, the BFD configuration has a first duration. In some aspects, the first duration is permanent. In some aspects, the first duration is based on at least one of a timer or a predetermined value. In some aspects, the first duration is based on a number of transitions between the dormancy mode and the non-dormancy mode. Mechanisms for performing BFD monitoring and measurements when operating in a dormancy BWP are described in greater detail herein.

(77) As shown, the transceiver **510** may include the modem subsystem **512** and the RF unit **514**. The transceiver **510** can be configured to communicate bi-directionally with other devices, such as the BSs **105**. The modem subsystem **512** may be configured to modulate and/or encode the data from the memory **504** and/or the BFD module **508** according to a modulation and coding scheme (MCS), e.g., a low-density parity check (LDPC) coding scheme, a turbo coding scheme, a convolutional coding scheme, a polar coding scheme, a digital beamforming scheme, etc. The RF unit **514** may be configured to process (e.g., perform analog to digital conversion or digital to analog conversion, etc.) modulated/encoded data (e.g., PUSCH, PUCCH, beam measurements, beam failure indication) from the modem subsystem **512** (on outbound transmissions) or of transmissions originating from another source such as a UE **115** or a BS **105**. The RF unit **514** may be further configured to perform analog beamforming in conjunction with the digital beamforming. Although shown as integrated together in transceiver **510**, the modem subsystem **512** and the RF unit **514** may be separate devices that are coupled together at the UE **115** to enable the UE **115** to communicate with other devices.

(78) The RF unit **514** may provide the modulated and/or processed data, e.g. data packets (or, more generally, data messages that may contain one or more data packets and other information), to the antennas **516** for transmission to one or more other devices. The antennas **516** may further receive data messages transmitted from other devices. The antennas **516** may provide the received data messages for processing and/or demodulation at the transceiver **510**. The transceiver **510** may provide the demodulated and decoded data (e.g., PDCCH, PDSCH, BFD configuration, BWP configuration, BWP activation, BWP state transition trigger, WUS, BFD RSs, SSBs, CSI-RSs, TRSs) to the BFD module **508** for processing. The antennas **516** may include multiple antennas of similar or different designs in order to sustain multiple transmission links. The RF unit **514** may configure the antennas **516**.

(79) In an aspect, the UE **500** can include multiple transceivers **510** implementing different RATs (e.g., NR and LTE). In an aspect, the UE **500** can include a single transceiver **510** implementing multiple RATs (e.g., NR and LTE). In an aspect, the transceiver **510** can include various components, where different combinations of components can implement different RATs.

(80) FIG. **6** is a block diagram of an exemplary BS **600** according to some aspects of the present disclosure. The BS **600** may be a BS **105** in the network **100** as discussed above in FIG. **1**. As shown, the BS **600** may include a processor **602**, a memory **604**, a beam configuration/transmission module **608**, a transceiver **610** including a modem subsystem **612** and a RF unit **614**, and one or more antennas **616**. These elements may be in direct or indirect communication with each other, for example via one or more buses.

(81) The processor **602** may have various features as a specific-type processor. For example, these may include a CPU, a DSP, an ASIC, a controller, a FPGA device, another hardware device, a firmware device, or any combination thereof configured to perform the operations described herein. The processor **602** may also be implemented as a combination of computing devices, e.g., a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration.

(82) The memory **604** may include a cache memory (e.g., a cache memory of the processor **602**), RAM, MRAM, ROM, PROM, EPROM, EEPROM, flash memory, a solid state memory device, one or more hard disk drives, memristor-based arrays, other forms of volatile and non-volatile memory, or a combination of different types of memory. In some aspects, the memory **604** may include a non-transitory computer-readable medium. The memory **604** may store instructions **606**. The instructions **606** may include instructions that, when executed by the processor **602**, cause the processor **602** to perform operations described herein, for example, aspects of FIGS. **1-4**, **7-12**, and **14**. Instructions **606** may also be referred to as code, which may be interpreted broadly to include any type of computer-readable statement(s) as discussed above with respect to FIG. **5**.

(83) The beam configuration/transmission module **608** may be implemented via hardware, software, or combinations thereof. For example, the beam configuration/transmission module **608** may be implemented as a processor, circuit, and/or instructions **606** stored in the memory **604** and executed by the processor **602**. In some instances, the beam configuration/transmission module **608** can be integrated within the modem subsystem **612**. For example, the beam configuration/transmission module **608** can be implemented by a combination of software components (e.g., executed by a DSP or a general processor) and hardware components (e.g., logic gates and circuitry) within the modem subsystem **612**.

(84) The beam configuration/transmission module **608** may be used for various aspects of the present disclosure, for example, aspects of FIGS. **1-4**, **7-12**, and **14**. For instance, the beam configuration/transmission module **608** is configured to determine that a UE (e.g., the UEs **115** and/or **500**) is operating in a dormancy mode for a cell of a wireless communication network. The wireless communication network may be similar to the network **100**. In some aspects, the cell of the network includes a secondary cell. In some aspects, the cell of the network includes a primary cell. In some aspects, the beam configuration/transmission module **608** is configured to determine that the UE is operating in the dormancy mode based on a configuration or a trigger transmitted by the beam configuration/transmission module **608**. The beam configuration/transmission module **608** is also configured to transmit, in response to determining the UE is operating in the dormancy mode, one or more BFD RSs in accordance with a BFD configuration.

(85) In some aspects, the beam configuration/transmission module **608** is configured to transmit the BFD RSs by transmitting the one or more BFD RSs in a dormancy BWP (e.g., the BWP **310a**). In some aspects, the beam configuration/transmission module **608** is configured to transmit a CORESET configuration for the dormancy BWP and transmit the one or more BFD RSs based on the CORESET configuration for the dormancy BWP.

(86) In some aspects, the beam configuration/transmission module **608** is configured to transmit, to

the UE, the BFD configuration. In some aspects, the BFD configuration explicitly indicates the one or more BFD RSs. In some aspects, the BFD configuration implicitly indicates the one or more BFD RSs. In some aspects, the configuration/transmission module **608** is configured to transmit the BFD configuration via at least one of DCI, MAC-CE or a WUS.

(87) In some aspects, the beam configuration/transmission module **608** is configured to transmit the one or more BFD RSs by transmitting the one or more BFD RSs QCLed with a CORESET. In some aspects, the beam configuration/transmission module **608** is configured to transmit the one or more BFD RSs by transmitting the one or more BFD RSs based on a TCI state of a CORESET.

(88) In some aspects, the beam configuration/transmission module **608** is configured to transmit the one or more BFD RSs by transmitting the one or more BFD RSs in a BWP, where the BWP includes a BWP utilized by the UE before operating in the dormancy mode.

(89) In some aspects, the beam configuration/transmission module **608** is configured to transmit the one or more BFD RSs by transmitting the one or more BFD RSs in a BWP, where the BWP includes a BWP utilized by the UE before operating in the dormancy mode and a dormancy BWP utilized by the UE when operating in the dormancy mode.

(90) In some aspects, the beam configuration/transmission module **608** is configured to transmit the one or more BFD RSs by transmitting the one or more BFD RSs fully within a dormancy BWP. In some aspects, the beam configuration/transmission module **608** is configured to transmit the one or more BFD RSs by transmitting the one or more BFD RSs partially within a dormancy BWP, where a first portion of each of the one or more BFD RSs is within the dormancy BWP and a second portion of each of the one or more BFD RSs is outside the dormancy BWP. In some aspects, the beam configuration/transmission module **608** is configured to transmit the one or more BFD RSs by transmitting the one or more BFD RSs outside of a dormancy BWP.

(91) In some aspects, the BFD configuration indicates a first BWP is associated with the dormancy mode and a second BWP is associated with a non-dormancy mode. In some aspects, the BFD configuration has a first duration. In some aspects, the first duration is permanent. In some aspects, the first duration is based on at least one of a timer or a predetermined value. In some aspects, the first duration is based on a number of transitions between the dormancy mode and the non-dormancy mode. Mechanisms for facilitating BFD RS monitoring and measurements for FD at a UE when the UE operates in a dormancy BWP are described in greater detail herein.

(92) As shown, the transceiver **610** may include the modem subsystem **612** and the RF unit **614**. The transceiver **610** can be configured to communicate bi-directionally with other devices, such as the UEs **115** and/or **500** and/or another core network element. The modem subsystem **612** may be configured to modulate and/or encode data according to a MCS, e.g., a LDPC coding scheme, a turbo coding scheme, a convolutional coding scheme, a polar coding scheme, a digital beamforming scheme, etc. The RF unit **614** may be configured to process (e.g., perform analog to digital conversion or digital to analog conversion, etc.) modulated/encoded data (e.g., PDCCH, PDSCH, BFD configuration, BWP configuration, BWP activation, BWP state transition trigger, WUS, BFD RSs, SSBs, CSI-RSs, TRSs) from the modem subsystem **612** (on outbound transmissions) or of transmissions originating from another source such as a UE **115** and/or UE **500**. The RF unit **614** may be further configured to perform analog beamforming in conjunction with the digital beamforming. Although shown as integrated together in transceiver **610**, the modem subsystem **612** and/or the RF unit **614** may be separate devices that are coupled together at the BS **105** to enable the BS **105** to communicate with other devices.

(93) The RF unit **614** may provide the modulated and/or processed data, e.g. data packets (or, more generally, data messages that may contain one or more data packets and other information), to the antennas **616** for transmission to one or more other devices. This may include, for example, transmission of information to complete attachment to a network and communication with a camped UE **115** or **500** according to some aspects of the present disclosure. The antennas **616** may further receive data messages transmitted from other devices and provide the received data

messages for processing and/or demodulation at the transceiver **610**. The transceiver **610** may provide the demodulated and decoded data (e.g., PUSCH, PUCCH, beam measurements, beam failure indication) to the beam configuration/transmission module **608** for processing. The antennas **616** may include multiple antennas of similar or different designs in order to sustain multiple transmission links.

(94) In an aspect, the BS **600** can include multiple transceivers **610** implementing different RATs (e.g., NR and LTE). In an aspect, the BS **600** can include a single transceiver **610** implementing multiple RATs (e.g., NR and LTE). In an aspect, the transceiver **610** can include various components, where different combinations of components can implement different RATs.

(95) FIG. 7 is a signaling diagram of a BFD method **700** according to some aspects of the present disclosure. The method **700** may be implemented between a BS (e.g., BSs **105** and/or **600**) and a UE (e.g., UEs **115** and/or **500**). The BS may utilize one or more components, such as the processor **602**, the memory **604**, the beam configuration/transmission module **608**, the transceiver **610**, the modem **612**, and the one or more antennas **616**, to implement aspects of the method **700**. The UE may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to implement aspects of the method **700**. The method **700** may employ similar mechanisms as in the schemes **300** and **400** described above with respect to FIGS. 3 and 4, respectively. As illustrated, the method **700** includes a number of enumerated steps, but embodiments of the method **700** may include additional steps before, after, and in between the enumerated steps. In some aspects, one or more of the enumerated steps may be omitted or performed in a different order.

(96) At action **705**, a BS **702** (e.g., the BSs **105** and/or **600**) and a UE **704** (e.g., the UEs **115** and/or **500**) establish a connection for communications. The connection may be established using techniques, such as random access and RRC connection setup procedures discussed above with respect to FIG. 1. In some instances, the connection may include two or more component carriers (CCs) operating in a carrier aggregation mode. For instance, the connection may include a primary cell (PCell) and a secondary cell (SCell). In some aspects, the UE may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to establish the connection with the BS. The BS may utilize one or more components, such as the processor **602**, the memory **604**, the beam configuration/transmission module **608**, the transceiver **610**, the modem **612**, and the one or more antennas **616**, to establish the connection with the UE.

(97) At action **710**, the BS **702** configures BWPs (e.g., the BWPs **310**) for the connection. In some instances, the BS **702** may configure up to about 4 BWPs for the connection. When there are multiple CCs associated with the connection, the BS **702** may configure one or more BWPs for each CC. In some aspects, the BS **702** may configure the UE **704** with BWPs based on the UE **704**'s capabilities. In some aspects, the BS may utilize one or more components, such as the processor **602**, the memory **604**, the beam configuration/transmission module **608**, the transceiver **610**, the modem **612**, and the one or more antennas **616**, to configure BWPs.

(98) At action **715**, the BS **702** transmits a BWP configuration to the UE **704**. The BWP configuration may be similar to the BWP configuration **410**. In some aspects, the BS may utilize one or more components, such as the processor **602**, the memory **604**, the beam configuration/transmission module **608**, the transceiver **610**, the modem **612**, and the one or more antennas **616**, to transmit the BWP configuration.

(99) At action **716**, upon receiving the BWP configuration, the UE **704** stores information associated with the BWP configuration in a memory (e.g., the memory **504**) of the UE.

(100) At action **720**, the BS **702** configures a BFD configuration. The BFD configuration may include various rules for determining which reference signals the UE **704** may use for BFD RS monitoring and/or how BFD RSs can be measured when the UE operates in a dormancy BWP. In some aspects, the BS **702** may configure the UE **704** not perform BFD in the dormancy BWP. In

some aspects, the BS 702 may configure UE 704 monitor BFD RSs based on an explicit BFD RS configuration and/or an implicit BFD RS configuration for a particular BWP. In some aspects, the particular BWP may be a non-dormancy BWP before the UE 704 switches to the dormancy BWP. In some aspects, the particular BWP may be a non-dormancy BWP paired with the dormancy BWP. In some aspects, the particular BWP may correspond to the dormancy BWP with a CORESET configured with a zero number of PDCCH candidates. In some aspects, the BS may utilize one or more components, such as the processor 602, the memory 604, the beam configuration/transmission module 608, the transceiver 610, the modem 612, and the one or more antennas 616, to configure the BFD configuration. Mechanisms for determining BFD RSs for BFD will be described more fully below in FIGS. 8-11.

(101) At action 725, the BS 702 transmits the BFD configuration to the UE 704. In some aspects, the BS may utilize one or more components, such as the processor 602, the memory 604, the beam configuration/transmission module 608, the transceiver 610, the modem 612, and the one or more antennas 616, to transmit the BFD configuration.

(102) At action 726, upon receiving the BFD configuration, the UE 704 stores information (e.g., rules for BFD RS monitoring) related to the BFD configuration in the memory.

(103) At action 730, the BS 702 determines to activate one of configured BWPs. In some aspects, the BS may utilize one or more components, such as the processor 602, the memory 604, the beam configuration/transmission module 608, the transceiver 610, the modem 612, and the one or more antennas 616, to determine to activate a configured BWP.

(104) At action 735, the BS 702 transmits a BWP activation to the UE 704 to activate the determined BWP. In some aspects, the BS may utilize one or more components, such as the processor 602, the memory 604, the beam configuration/transmission module 608, the transceiver 610, the modem 612, and the one or more antennas 616, to transmit the BWP activation.

(105) At action 740, after the BWP activation, the BS 702 communicates with the UE 704 in the active BWP. The communications may include PDCCH, PDSCH, PUSCH, and/or PUCCH signals. In some aspects, the BS may utilize one or more components, such as the processor 602, the memory 604, the beam configuration/transmission module 608, the transceiver 610, the modem 612, and the one or more antennas 616, to communicate with the UE in the active BWP. The UE may utilize one or more components, such as the processor 502, the memory 504, the BFD module 508, the transceiver 510, the modem 512, and the one or more antennas 516, to communicate with the BS in the active BWP.

(106) At action 750, the BS 702 switches the UE 704 to operate in a dormancy mode. In some aspects, the BS may utilize one or more components, such as the processor 602, the memory 604, the beam configuration/transmission module 608, the transceiver 610, the modem 612, and the one or more antennas 616, to switch the UE 704 to operate in the dormancy mode. In some aspects, the BS 702 may configure the UE 704 to operate in the dormancy BWP via an RRC configuration, downlink control information (DCI) signaling (e.g., in a PDCCH), medium access control-control element (MAC-CE) signaling, and/or a wakeup signal (WUS) as will be discussed more fully below.

(107) At action 755, when the UE 704 operates in the dormancy BWP, the BS 702 transmits BFD RSs according to the rules in the BFD configuration to facilitate BFD at the UE 704. In some aspects, the BS may utilize one or more components, such as the processor 602, the memory 604, the beam configuration/transmission module 608, the transceiver 610, the modem 612, and the one or more antennas 616, to transmit BFD RSs to the UE based on the BFD configuration.

(108) At action 760, the UE 704 performs BFD RS monitoring based on the rules in the BFD configuration. In some aspects, the UE may utilize one or more components, such as the processor 502, the memory 504, the BFD module 508, the transceiver 510, the modem 512, and the one or more antennas 516, to retrieve the BFD rules from the memory and monitor for BFD RS for BFD based on the rules indicated by the BFD configuration.

(109) FIGS. 8-11 illustrate various mechanisms for a BS (e.g., the BSs 105, 600, and/or 702) to configure a UE (e.g. the UEs 115, 500, and/or 704) for BFD RS monitoring when the UE operates in a dormancy BWP (e.g., the BWP 310a).

(110) FIG. 8 is a flow diagram of a BFD method 800 according to some aspects of the present disclosure. Aspects of the method 800 can be executed by a computing device (e.g., a processor, processing circuit, and/or other suitable component) of a wireless communication device or other suitable means for performing the steps. For example, a wireless communication device, such as the UEs 115, 500, and/or 702 may utilize one or more components, such as the processor 502, the memory 504, the BFD module 508, the transceiver 510, the modem 512, and the one or more antennas 516, to execute the steps of method 800. The method 800 may employ similar mechanisms as in the schemes 300 and 400 discussed above with reference to FIGS. 3 and 4, respectively. As illustrated, the method 800 includes a number of enumerated steps, but aspects of the method 800 may include additional steps before, after, and in between the enumerated steps. In some aspects, one or more of the enumerated steps may be omitted or performed in a different order.

(111) In the method 800, a BS (e.g., the BSs 105, 600, and/or 702) may configure a UE (e.g., the UEs 115, 500, and/or 704) to perform BFD in a dormancy BWP (e.g., the BWP 310a). The BS may configure the UE to perform BFD if the UE is configured with explicit BFD RSs for the dormancy BWP. Otherwise, the UE may not perform BFD in the dormancy BWP. An explicit BFD RS configuration may indicate resources (in frequency and time) where the BS may transmit reference signals that the UE may monitor for BFD.

(112) At block 810, the UE operates in a dormancy mode for a cell of a wireless communication network. The network may be similar to the network 100. In some aspects, the cell may be a PCell. In some aspects, the cell may be a SCell. The UE may determine to operate in the dormancy mode in the dormancy BWP based on a configuration from a BS. In some aspects, the UE may utilize one or more components, such as the processor 502, the memory 504, the BFD module 508, the transceiver 510, the modem 512, and the one or more antennas 516, to operate in the dormancy mode, for example, for power saving. The UE may configure at least one some of the RF components in the transceiver 510 to operate at a low-power state or power down state.

(113) At block 820, the UE determines whether the UE is configured with explicit BFD RSs for the dormancy BWP. For instance, an explicit BFD RS configuration may include a list of one or more resources (in frequency and time) where the BS may transmit reference signals (e.g., SSBs, CSI-RSs, and/or TRSs) and the reference signals can be used for BFD. In some aspects, the UE may utilize one or more components, such as the processor 502, the memory 504, the BFD module 508, the transceiver 510, the modem 512, and the one or more antennas 516, to determine whether the UE is configured with explicit BFD RSs for the dormancy BWP. If the UE determines that no explicit BFD RSs are configured for the dormancy BWP, the UE may proceed to block 825.

(114) At block 825, the UE refrains from performing BFD RS monitoring. In some aspects, the UE may utilize one or more components, such as the processor 502, the memory 504, the BFD module 508, the transceiver 510, the modem 512, and the one or more antennas 516, to disable BFD RS monitoring operations at the UE.

(115) Returning to block 820, if the UE determines that the UE is configured with explicit BFD RSs for the dormancy BWP, the UE may proceed to block 830. At block 830, the UE monitors for the BFD RS(s) according to the explicit BFD RS configuration. In some aspects, the UE may utilize one or more components, such as the processor 502, the memory 504, the BFD module 508, the transceiver 510, the modem 512, and the one or more antennas 516, to perform BFD RS monitoring according to the BFD RSs in the explicit BFD RS configuration. The UE may configure the transceiver 510 and/or the one or more antennas 516 to monitor for a BFD RS in a certain spatial direction according to spatial parameters (e.g., QCL parameters) associated with the BFD RS.

(116) When the UE is configured with explicit BFD RS(s), the UE may monitor and measure BFD RS(s) that are QCLed with CORESET(s) (e.g., the CORESETs **320**) in a particular BWP as shown by the block **840**. In some aspects, the particular BWP may correspond to a non-dormancy BWP before the UE operates in the dormancy BWP as shown by the block **842**. As an example, the non-dormancy BWP may be configured with a CORESET similar to the CORESET #0 shown in the CORESET configuration **430** of FIG. **4**. The UE may look up a TCI state (e.g., the TCI state 0 for CORESET #0) from the CORESET configuration **430** and look up a reference signal (e.g., the SSB index #n) indicated by the TCI state in the TCI state table **440**. The UE may monitor an explicitly configured BFD RS that is QCLed with the SSB index #n indicated by the TCI state 0. Additionally or alternatively, UE may perform similar look up for the TCI state 1 of the CORESET #0 and monitor an explicitly configured BFD RS that is QCLed with the CSI-RS index #k indicated by the TCI state 1. In some aspects, when there are more than one QCL type for a CORESET, the UE may select a configured BFD RS that is QCLed with the CORESET in type D. Thus, referring to the same example, the UE may monitor a configured BFD RS that is QCLed with the SSB index #n indicated by the TCI state 0 based on the QCL type D indication for the SSB index #n. Accordingly, the BS may transmit one or more BFD RSs (e.g., SSBs, CSI-RSs, and/or TRSs) in accordance with the QCL relationship indicated by the CORESET in the non-dormancy BWP before the UE switches to the dormancy BWP.

(117) In some other aspects, the particular BWP may correspond to a non-dormancy BWP paired with the dormancy BWP as shown by the block **844**. Referring to the example illustrated in FIG. **3**, the BS may configure the non-dormancy BWP **310b** paired with the dormancy BWP **310a**. Thus, for BFD, the UE may monitor reference signals that are QCLed with the CORESETs **320** in the BWP **310b**. The UE may determine the BFD RSs for monitoring using substantially similar mechanisms as described for block **842**. The BS may transmit one or more BFD RSs (e.g., SSBs, CSI-RSs, and/or TRSs) in accordance with the QCL relationship indicated by the CORESET in the paired non-dormancy BWP.

(118) In yet other aspects, the particular BWP may correspond to the dormancy BWP as shown by the block **846**. For instance, the BS may configure a CORESET for the dormancy BWP so that the UE may utilize QCL relationship configured for the CORESET to determine BFD RSs for monitoring. However, the BS may configure the CORESET with zero number of PDCCH candidates per aggregation level and per search space so that the UE may not perform PDCCH monitoring in the dormancy BWP. The BS may transmit one or more BFD RSs (e.g., SSBs, CSI-RSs, and/or TRSs) in accordance with the QCL relationship indicated by the CORESET in the dormancy BWP.

(119) FIG. **9** is a flow diagram of a BFD method **900** according to some aspects of the present disclosure. Aspects of the method **900** can be executed by a computing device (e.g., a processor, processing circuit, and/or other suitable component) of a wireless communication device or other suitable means for performing the steps. For example, a wireless communication device, such as the UEs **115**, **500**, and/or **702** may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to execute the steps of method **900**. The method **900** may employ similar mechanisms as in the schemes **300** and **400** discussed above with reference to FIGS. **3** and **4**, respectively. As illustrated, the method **900** includes a number of enumerated steps, but aspects of the method **800** may include additional steps before, after, and in between the enumerated steps. In some aspects, one or more of the enumerated steps may be omitted or performed in a different order.

(120) In the method **900**, a BS (e.g., the BSs **105**, **600**, and/or **702**) may configure a UE (e.g., the UEs **115**, **500**, and/or **704**) to perform BFD in a dormancy BWP (e.g., the BWP **310a**). The BS may configure the UE to perform BFD if the UE is configured with implicit BFD RSs for the dormancy BWP. Otherwise, the UE may not perform BFD in the dormancy BWP. An implicit BFD RS may

refer to a reference signal indicated by a TCI state of a CORESET in a particular BWP.

(121) Generally speaking, the method **900** includes features similar to method **800** in many respects. For example, blocks **910**, **925**, **942**, **944**, and **946** are similar to blocks **810**, **825**, **842**, **844**, and **846**, respectively. Accordingly, for sake of brevity, details of those blocks will not be repeated here. Please refer to the corresponding descriptions above.

(122) At block **920**, the UE determines whether the UE is configured with one or more implicit BFD RSs for the dormancy BWP. For instance, the BS may configure the UE to monitor reference signals indicated by a TCI state of a CORESET in a particular BWP. In some aspects, the UE may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to determine whether the UE is configured with one or more implicit BFD RSs for the dormancy BWP. If the UE determines that the UE is configured with one or more implicit BFD RSs for the dormancy BWP, the UE may proceed to block **930**. Otherwise, the UE may proceed to block **925** and refrain from BFD RS monitoring.

(123) At block **930**, the UE monitors for the BFD RSs according to the implicit BFD RS configuration. In some aspects, the UE may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to perform BFD RS monitoring according to the BFD RSs in the implicit BFD RS configuration. The UE may configure the transceiver **510** and/or the one or more antennas **516** to monitor for a BFD RS in a certain spatial direction according to spatial parameters (e.g., QCL parameters) associated with the BFD RS.

(124) When the UE is configured with implicit BFD RS(s), the UE may monitor and measure a reference signal (e.g., a BFD RS) that is indicated by a TCI state of a CORESET in a particular BWP as shown by the block **940**. Similar to the block **840**, the particular BWP may correspond to a non-dormancy BWP before the UE operates in the dormancy BWP as shown by the block **942**. As an example, the non-dormancy BWP may be configured with a CORESET similar to the CORESET #0 shown in the CORESET configuration **430** of FIG. 4. The UE may look up a TCI state (e.g., the TCI state 0 for CORESET #0) from the CORESET configuration **430** and look up a reference signal (e.g., the SSB index #n) indicated by the TCI state in the TCI state table **440**. The UE may monitor the SSB identified by the index #n indicated by the TCI state 0 for BFD. Additionally or alternatively, UE may perform similar look up for the TCI state 1 of the CORESET #0 and monitor the CSI-RS identified by the index #k indicated by the TCI state 1 for BFD. In some aspects, when there are more than one reference signals in a TCI state for a CORESET, the UE may select the reference signal with a QCL type D in the TCI state for BFD monitoring. For instance, if the TCI state 0 of CORESET #0 may indicate a QCL Type A reference signal and a QCL type D reference signal, the UE may monitor the QCL type D reference signal. Accordingly, the BS may transmit one or more BFD RSs (e.g., SSBs, CSI-RSs, and/or TRSs) in accordance with the reference signals indicated by the TCI state of the CORESET in the non-dormancy BWP before the UE switches to the dormancy BWP.

(125) In some other aspects, the particular BWP may correspond to a non-dormancy BWP paired with the dormancy BWP as shown by the block **944** similar to the block **844**. Referring to the example illustrated in FIG. 3, the BS may configure the non-dormancy BWP **310b** paired with the dormancy BWP **310a**. Thus, for BFD, the UE may monitor reference signal(s) indicated by a TCI state of the CORESETs **320** in the BWP **310b**. The UE may determine the BFD RSs for monitoring using substantially similar mechanisms as described for block **942**. The BS may transmit one or more BFD RSs (e.g., SSBs, CSI-RSs, and/or TRSs) in accordance with the reference signals indicated by the TCI state of the CORESET in the paired non-dormancy BWP.

(126) In yet other aspects, the particular BWP may correspond to the dormancy BWP as shown by the block **946** similar to the block **846**. For instance, the BS may configure a CORESET for the dormancy BWP so that the UE may monitor reference signal(s) indicated by a TCI state of the

CORESET in the dormancy BWP. Similarly, the BS may configure the CORESET with zero number of PDCCH candidates per aggregation level and per search space so that the UE may not perform PDCCH monitoring in the dormancy BWP. In other words, the UE may determine that there is no search space or PDCCH candidates to be monitored in the dormancy BWP even though a CORESET is configured for the dormancy BWP. In some aspects, the BS may configure the UE with a CORESET (associated with a certain TCI state) in the dormancy BWP to facilitate BFD RS monitoring at the UE, but may refrain from configuring or assigning any PDCCH search space (e.g., no common search space) associated with the CORESET in the dormancy BWP. A common search space is a search that is shared across all UEs. Accordingly, the UE may receive a CORESET configuration for the dormancy BWP, but may not receive any PDCCH search space configuration (e.g., no common search space configuration) for the dormancy BWP, and thus may not perform PDCCH monitoring in the dormancy BWP. In this regard, the BS may configure the UE with a PDCCH configuration including a CORESET configuration (for one or more CORESETs in the BWP), but may not include any other PDCCH monitoring or search space parameters. In some aspects, when there are more than one reference signals in a TCI state for a CORESET, the UE may select the reference signal with a QCL type D in the TCI state for BFD monitoring. For instance, if the TCI state 0 of CORESET #0 may indicate a QCL Type A reference signal and a QCL type D reference signal, the UE may monitor the QCL type D reference signal. In other words, the BS may transmit a QCL Type A reference signal and a QCL type D reference signal in the dormancy BWP, and may receive a beam recovery request from the UE based on the QCL type D reference signal (monitored by the UE). Accordingly, the BS may transmit one or more BFD RSs (e.g., SSBs, CSI-RSs, and/or TRSs) in accordance with the reference signals indicated by the TCI state of the CORESET in the dormancy BWP.

(127) FIG. 10 is a flow diagram of a BFD method **1000** according to some aspects of the present disclosure. Aspects of the method **1000** can be executed by a computing device (e.g., a processor, processing circuit, and/or other suitable component) of a wireless communication device or other suitable means for performing the steps. For example, a wireless communication device, such as the UEs **115**, **500**, and/or **702** may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to execute the steps of method **1000**. The method **1000** may employ similar mechanisms as in the schemes **300** and **400** discussed above with reference to FIGS. 3 and 4, respectively, and/or the methods **800** and **900** discussed above with reference to FIGS. 8 and 9, respectively. As illustrated, the method **1000** includes a number of enumerated steps, but aspects of the method **1000** may include additional steps before, after, and in between the enumerated steps. In some aspects, one or more of the enumerated steps may be omitted or performed in a different order.

(128) In the method **1000**, a BS (e.g., the BSs **105**, **600**, and/or **702**) may configure a UE (e.g., the UEs **115**, **500**, and/or **704**) to perform BFD in a dormancy BWP (e.g., the BWP **310a**). The BS may configure the UE to perform BFD if the UE is configured with explicit BFD RSs for the dormancy BWP. Otherwise, the UE may perform BFD based on an implicit BFD configuration.

(129) At block **1010**, the UE operates in a dormancy mode for a cell of a wireless communication network, for example, by performing similar operations as at block **810**.

(130) At block **1020**, the UE determines whether the UE is configured with explicit BFD RSs for the dormancy BWP. The explicitly BFD RS may be configured in a similar manner as discussed above with reference to FIG. 8. In some aspects, the UE may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to determine whether the UE is configured with explicit BFD RSs for the dormancy BWP. If the UE determines that the UE is configured with explicit BFD RSs for the dormancy BWP, the UE may proceed to block **1030**.

(131) At block **1030**, the UE may perform BFD RS monitoring based on the explicit BFD RS, for

example, as discussed above at blocks **830** and **840** with reference to FIG. **8**.

(132) Returning to the block **1020**, if the UE determines that the UE is not configured with an explicit BFD RS, the UE proceeds to block **1025**. At block **1025**, the UE may perform BFD RS monitoring based on an implicit BFD RS configuration, for example, as discussed above at blocks **930** and **940** with reference to FIG. **9**.

(133) FIG. **11** illustrates a BFD RS measurement scheme **1100** according to some aspects of the present disclosure. The scheme **1100** may be employed by BSs such as the BSs **105** and UEs such as the UEs **115** in a network such as the network **100**. In particular, a BS (e.g., the BSs **105**) may configure a UE (e.g., the UEs **115**) to perform BFD RS measurements as shown in the scheme **1100**. In FIG. **11**, the y-axis represents frequency in some arbitrary units. The scheme **1100** is described using the same frequency band configuration as in the scheme **300**, and may use the same reference numerals for simplicity's sake.

(134) The BS may transmit various reference signals in the frequency band **301**. For instance, the BS may transmit SSBs in the frequency band **301** to facilitate system synchronization and network access. Additionally, the BS may transmit CSI-RS in the frequency band **301** to enable UEs to perform channel measurements and determine precoding feedback to assist the BS in determining precoding for DL beam formation. Further, the BS may transmit TRSs in the frequency band **301** to facilitate time and/or frequency tracking at the UEs. Each of the SSB, the CSI-RS, and the TRS may span a certain frequency portion in the frequency band **301**.

(135) As shown in FIG. **11**, the BS may transmit a reference signal **1110**, a reference signal **1120**, and a reference signal **1130**, each spanning a certain frequency band. The reference signals **1110**, **1120**, **1130** may include an SSB, a CSI-RS, and/or a TRS. Depending on a BWP configuration, the reference signals **1110**, **1120**, and/or **1130** may be fully within a certain BWP, partially within a certain BWP, or outside a certain BWP. Referring to the same example discussed above in FIG. **3**, the BS may configure the BWP **310a** as a dormancy BWP for a UE. Thus, the reference signal **1110** is fully within the dormancy BWP **310a**. The reference signal **1130** is partially within the dormancy BWP **310a**. The reference signal **1120** is outside the dormancy BWP **310a**. While the reference signals **1110**, **1120**, and **1130** are shown to occupy contiguous frequency in the frequency band **301**, the reference signals **1110**, **1120**, and/or **1130** can occupy non-contiguous frequency in the frequency band **301**. In general, a reference signal may be transmitted in one or more contiguous or distributed PRBs (e.g., the RBs **210**).

(136) The BS may configure the UE to perform BFD RS measurements using the reference signals **1110**, **1120**, and/or **1130** in various ways. The BS may configure the UE with a BFD RS corresponding to the reference signal **1110**, **1120**, or **1130**. The configuration can be an explicit configuration or an implicit configuration as discussed above with reference to FIGS. **8** and **9** respectively. In some aspects, the BS may configure the UE to measure a BFD RS if the BFD RS (e.g., the reference signal **1110**) is fully within the dormancy BWP **310a**. Accordingly, the UE may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to receive the BFD RS and determine a measurement (e.g., a reference signal received power (RSRP), a reference signal received quality (RSRQ), and/or a channel quality indicator (CQI)) for the BFD RS.

(137) In some other aspects, the BS may configure the UE to measure a BFD RS (e.g., the reference signal **1120**) that is partially within the dormancy BWP **310a**. In some instances, the BS may configure the UE to perform measurement for the portion (e.g., the portion **1122**) of the BFD RS that is within the dormancy BWP **310a** and exclude measurement for the portion (e.g., the portion **1124**) of the BFD RS outside of the dormancy BWP **310a**. Accordingly, the UE may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to receive the portion of the BFD RS that is within the dormancy BWP **310a** and determine a measurement for the portion of the BFD RS in the dormancy BWP **310a**. In some other instances, the BS may configure the UE to

perform measurement on the entire BFD RS including the portion outside the dormancy BWP **310a**. Accordingly, the UE may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to receive the entire BFD RS (including the portion **1122** in the dormancy BWP **310a** and the portion **1124** outside the dormancy BWP **310b**) and determine a measurement for the entire BFD RS. In some instance, the UE may configure RF components (e.g., filters, gain stages, and/or ADC) to operate at a wider bandwidth that extends outside the dormancy BWP **310a**.

(138) In some other aspects, the BS may configure the UE with a BFD RS (e.g., the reference signal **1130**) that is outside the dormancy BWP **310a**. In some instances, the BS may configure the UE to exclude measurement on BFD RSs that are outside the dormancy BWP **310a**. In some other instances, the BS may configure the UE to extend its frequency band outside the dormancy BWP **310a** so that the UE may determine measurement for the BFD RS. Accordingly, the UE may configure RF components (e.g., filters, gain stages, and/or ADC) to operate at a wider bandwidth including the BWP where the BFD RS is located and utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to receive the BFD RS outside the dormancy BWP **310b** and determine a measurement for the BFD RS. In some instance, the BS may configure the UE to switch to the BWP (e.g., the BWP **310b**) where the BFD RS is located for BFD RS measurements. Accordingly, the UE may configure RF components (e.g., filters, gain stages, and/or ADC) to switch to the BWP **310b** where the BFD RS is located and utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to receive the BFD RS in dormancy BWP **310b** and determine a measurement for the BFD RS.

(139) As discussed above, a BS (e.g., the BSs **105**, **600**, and/or **702**) may configure a UE (e.g., the UEs **115**, **500**, and/or **704**) to operate in a dormancy mode via RRC signaling, DCI signaling, MAC-CE signaling, and/or a WUS. The use of DCI signaling, MAC-CE signaling, and/or WUS to indicate a dormancy mode may allow the BS to dynamically configure the UE to transition between a dormancy mode and a non-dormancy mode or between a switching a BWP between a dormancy BWP and a non-dormancy BWP.

(140) FIGS. **12A-12C** illustrate various mechanisms for a BS (e.g., the BSs **105**, **600**, and/or **702**) to configure a UE (e.g., the UEs **115**, **500**, and/or **704**) to transition between a dormancy state and a non-dormancy state for a configured BWP. FIG. **12A** illustrates a dormancy BWP configuration scheme **1202** according to some aspects of the present disclosure. FIG. **12B** illustrates a dormancy BWP configuration scheme **1204** according to some aspects of the present disclosure. FIG. **12C** illustrates a dormancy BWP configuration scheme **1206** according to some aspects of the present disclosure.

(141) In each of the schemes **1202**, **1204**, **1206**, the BS may configure the UE with a BWP and may configure a non-dormancy state **1210** for the BWP, for example, via an RRC configuration. The UE may perform PDCCH monitoring, communicate UL and/or DL communications with the BS, and/or perform BFD in the configured BWP while in the non-dormancy state **1210**. The BS may send a trigger **1212** to the UE to transition the BWP to a dormancy state **1220**. The UE may not monitor for PDCCH in the dormancy BWP, but may perform BFD as described herein. In some aspects, the trigger **1212** can be a DCI message. In some other aspects, the trigger **1212** can be a MAC-CE message. In yet other aspects, the trigger **1212** can be a WUS. For example, for power saving, the BS may configure the UE to operate in a power saving mode cycling through wake/sleep cycles. The BS may configure the UE **704** to monitor for a WUS while operating in the power saving mode. The BS may transmit a WUS to the UE to wake the UE up from a power saving mode. The BS may include the trigger **1212** in the WUS.

(142) In the scheme **1202**, the transition to the dormancy state **1220** may be permanent. In other words, the trigger **1212** may overwrite the RRC configured BWP permanently. The UE may remain

in the dormancy state when operating in the configured BWP.

(143) In the scheme **1204**, the UE may operate in the dormancy state **1220** in the RRC configured BWP for a certain duration. In some aspects, the duration can be predetermined, for example, based on a certain wireless communication protocol standard. In some aspects, the duration can be configurable. For instance, the BS may indicate the duration in the trigger **1212** or in a separate configuration message. The UE may configure a timer with an expiration based on the duration configured for the dormancy state **1220**. Upon a time expiration trigger **1222**, the UE may transition back to the non-dormancy state.

(144) In the scheme **1206**, the UE may stay in the dormancy state **1220** until a next trigger is received from the BS. For instance, the BS may transmit trigger **1224** to switch the UE from the dormancy state **1220** back to the non-dormancy state **1210**. The trigger **1224** can be substantially similar to the trigger **1212**. For instance, the trigger **1224** may be another DCI, MAC-CE, or WUS.

(145) In some aspects, when the trigger **1212** indicates a non-dormancy BWP (e.g., the BWP **310b**) paired with the dormancy BWP (e.g., the RRC configured BWP transitioning to the dormancy state **1220**) and the UE is configured with an explicit BFD RS configuration, the UE may monitor and measure BFD RSs that are QCLed with CORESETs in the paired non-dormancy BWP. In some aspects, when the trigger **1212** indicates a non-dormancy BWP (e.g., the BWP **310b**) paired with the dormancy BWP (e.g., the RRC configured BWP transitioning to the dormancy state **1220**) and the UE is configured with an implicit BFD RS configuration, the UE may monitor and measure BFD RSs that are indicated in TCI states of CORESETs in the paired non-dormancy BWP.

(146) FIG. **13** is a flow diagram of a wireless communication method **1300** according to some aspects of the present disclosure. Aspects of the method **1300** can be executed by a computing device (e.g., a processor, processing circuit, and/or other suitable component) of a wireless communication device or other suitable means for performing the steps. For example, a wireless communication device, such as the UEs **115**, **500**, and/or **704** may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to execute the steps of method **1300**. The method **1300** may employ similar mechanisms as in the schemes **300**, **400**, **1100**, **1202**, **1204**, and/or **1206** discussed above with reference to FIGS. **3**, **4**, **11**, **12A**, **12B**, and/or **12C**, respectively, and/or the methods **700**, **800**, **900**, and/or **1000** discussed above with reference to FIGS. **7**, **8**, **9**, and/or **12**, respectively. As illustrated, the method **1300** includes a number of enumerated steps, but aspects of the method **1300** may include additional steps before, after, and in between the enumerated steps. In some aspects, one or more of the enumerated steps may be omitted or performed in a different order.

(147) At block **1310**, a wireless communication device (e.g., the UEs **115**, **500**, and/or **704**) determines, to operate in a dormancy mode for a cell of a wireless communication network. The wireless communication network may be similar to the network **100**. In some aspects, the cell of the network includes a secondary cell. In some aspects, the cell of the network includes a primary cell. In some aspects, the wireless communication device may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to determine to operate in the dormancy mode. In some aspects, the wireless communication device may determine to operate in the dormancy mode based on a configuration or trigger received from a BS (e.g., the BSs **105**, **600**, and/or **702**).

(148) At block **1320**, the wireless communication device operates in the dormancy mode for the cell of the wireless communication network. The operating in the dormancy mode includes performing a BFD in accordance with a BFD configuration.

(149) In some aspects, the performing the BFD at block **1320** may include refraining from performing the BFD in a dormancy BWP (e.g., the BWP **310a**). In some aspects, the performing the BFD at block **1320** may include monitoring for one or more BFD RSs in a dormancy BWP. In some aspects, the wireless communication device may further receive a CORESET configuration for the dormancy BWP, where the monitoring for the one or more BFD RSs is further based on the

CORESET configuration for the dormancy BWP. The wireless communication device may operate in the dormancy BWP may when operating in the dormancy mode. The CORESET configuration may indicate one or more CORESETs in the dormancy BWP. However, any CORESET in the dormancy BWP is not for monitoring by the wireless communication device. In some instances, the wireless communication device may determine that there is no search configuration (e.g., a common search space configuration) for the dormancy BWP. In some aspects, the CORESET may include a zero number of PDCCH candidates per aggregation level and per search space.

(150) In some aspects, the performing the BFD at block **1320** may include monitoring for one or more BFD RSs in a BWP when the BFD configuration explicitly indicates the one or more BFD RSs, for example, as discussed above in the method **800** with reference to FIG. **8**. In some aspects, the performing the BFD at block **1320** may include refraining from performing the BFD when the BFD configuration fails to explicitly indicate the one or more BFD RSs. In some aspects, the monitoring for the one or more BFD RSs QCLed with a CORESET. In some aspects, the wireless communication device may further determine a first QCL type and a second QCL type are associated with the CORESET, where the monitoring for the one or more BFD RSs QCLed with the CORESET includes monitoring for the one or more BFD RSs QCLed with the CORESET based on the second QCL type. In some aspects, the second QCL type includes QCL type D.

(151) In some aspects, the performing the BFD at block **1320** may include monitoring for one or more BFD RSs in a BWP when the BFD configuration implicitly indicates the one or more BFD RSs, for example, as discussed above in the method **900** with reference to FIG. **9**. In some aspects, the performing the BFD at block **1320** may include refraining from performing the BFD when the BFD configuration fails to implicitly indicate the one or more BFD RSs. In some aspects, the monitoring for the one or more BFD RSs includes monitoring for the one or more BFD RSs associated with a TCI state of a CORESET. In some aspects, the wireless communication device may further determine a first QCL type and a second QCL type are associated with the TCI state of the CORESET, where monitoring for the one or more BFD RSs associated with the TCI state of the CORESET includes monitoring for the one or more BFD RSs associated with the TCI state of the CORESET based on the second QCL type. In some aspects, the second QCL type includes QCL type D.

(152) In some aspects, the performing the BFD at block **1320** may include at least one of monitoring, by the wireless communication device, for one or more explicit BFD RSs in a BWP when the BFD configuration explicitly indicates the one or more explicit BFD RSs; or monitoring for one or more implicit BFD RSs in the BWP when the BFD configuration fails to explicitly indicate the one or more explicit BFD RSs, for example, as discussed above in the method **1000** with reference to FIG. **10**.

(153) In some aspects, the performing the BFD at block **1320** may include monitoring for one or more BFD RSs in a BWP, wherein the BWP includes a BWP utilized by the wireless communication device before operating in the dormancy mode, for example, as discussed above in the block **842** and **942** with reference to FIGS. **8** and **9**, respectively.

(154) In some aspects, the performing the BFD at block **1320** may include monitoring for one or more BFD RSs in a BWP, where the BWP includes a first BWP utilized by the wireless communication device before operating in the dormancy mode and a dormancy BWP utilized by the wireless communication device when operating in the dormancy mode, for example, as discussed above in the block **844** and **944** with reference to FIGS. **8** and **9**, respectively.

(155) In some aspects, the performing the BFD at block **1320** may include monitoring for one or more BFD RSs (e.g., the reference signal **1110**) fully within a dormancy BWP. In some other aspects, performing the BFD at block **1320** may include monitoring for one or more BFD RSs (e.g., the reference signal **1120**) partially within a dormancy BWP, where a first portion of each of the one or more BFD RSs is within the dormancy BWP and a second portion of each of the one or more BFD RSs is outside the dormancy BWP. In yet other aspects, the performing the BFD at

block **1320** may include measuring at least one parameter of the first portion of each of the one or more BFD RSs. In some aspects, the performing the BFD at block **1320** may include measuring at least one parameter of each of the one or more BFD RSs based on the first and second portions. In some aspects, the performing the BFD at block **1320** may include refraining from monitoring for one or more BFD RSs outside of a dormancy BWP. In some aspects, the performing the BFD at block **1320** may include monitoring for one or more BFD RSs (e.g., the reference signal **1130**) outside of a dormancy BWP.

(156) In some aspects, the wireless communication device may further receive the BFD configuration. In some aspects, the receiving the BFD configuration includes receiving the BFD configuration via at least one of DCI, a MAC-CE, or a WUS. In some aspects, the BFD configuration indicates a first BWP is associated with the dormancy mode and a second BWP is associated with a non-dormancy mode. In some aspects, the BFD configuration has a first duration. In some aspects, the first duration is permanent. In some aspects, the first duration is based on at least one of a timer or a predetermined value. In some aspects, the first duration is based on a number of transitions between the dormancy mode and the non-dormancy mode.

(157) FIG. **14** is a flow diagram of a wireless communication method **1400** according to some aspects of the present disclosure. Aspects of the method **1400** can be executed by a computing device (e.g., a processor, processing circuit, and/or other suitable component) of a wireless communication device or other suitable means for performing the steps. For example, a wireless communication device, such as the BSs **105**, **600**, and/or **702** may utilize one or more components, such as the processor **602**, the memory **604**, the beam configuration and transmission module **608**, the transceiver **610**, the modem **612**, and the one or more antennas **616**, to execute the steps of method **1400**. The method **1400** may employ similar mechanisms as in the schemes **300**, **400**, **1100**, **1202**, **1204**, and/or **1206** discussed above with reference to FIGS. **3**, **4**, **11**, **12A**, **12B**, and/or **12C**, respectively, and/or the methods **700**, **800**, **900**, and/or **1000** discussed above with reference to FIGS. **7**, **8**, **9**, and/or **12**, respectively. As illustrated, the method **1400** includes a number of enumerated steps, but aspects of the method **1400** may include additional steps before, after, and in between the enumerated steps. In some aspects, one or more of the enumerated steps may be omitted or performed in a different order.

(158) At block **1410**, a first wireless communication device (e.g., the BSs **105**, **600**, and/or **702**) determines a second wireless communication device (e.g., the UEs **115**, **500**, and/or **704**) is operating in a dormancy mode for a cell of a wireless communication network. The wireless communication network may be similar to the network **100**. In some aspects, the cell of the network includes a secondary cell. In some aspects, the cell of the network includes a primary cell. In some aspects, the first wireless communication device may utilize one or more components, such as the processor **602**, the memory **604**, the beam configuration and transmission module **608**, the transceiver **610**, the modem **612**, and the one or more antennas **616**, to determine that the second wireless communication device is operating in the dormancy mode. In some aspects, the first wireless communication device may determine that the second wireless communication device is operating in the dormancy mode based on a configuration or a trigger transmitted by the first wireless communication device.

(159) At block **1420**, the first wireless communication device transmits, in response to determining the second wireless communication device is operating in the dormancy mode, one or more BFD RSs in accordance with a BFD configuration. In some aspects, the first wireless communication device may utilize one or more components, such as the processor **602**, the memory **604**, the beam configuration and transmission module **608**, the transceiver **610**, the modem **612**, and the one or more antennas **616**, to transmit the one or more BFD RSs.

(160) In some aspects, the transmitting the BFD RSs at block **1420** includes transmitting the one or more BFD RSs in a dormancy BWP (e.g., the BWP **310a**). In some aspects, the first wireless communication device further transmits a CORESET configuration for the dormancy BWP, where

the transmitting the one or more BFD RSs at block **1420** is further based on the CORESET configuration for the dormancy BWP.

(161) In some aspects, the first wireless communication device further transmits, to the second wireless communication device, the BFD configuration. In some aspects, the BFD configuration explicitly indicates the one or more BFD RSs, for example, as discussed above in the method **800** with reference to FIG. **8**. In some aspects, the BFD configuration implicitly indicates the one or more BFD RSs, for example, as discussed above in the method **900** with reference to FIG. **9**. In some aspects, the transmitting the BFD configuration includes transmitting to the second wireless communication device, the BFD configuration via at least one of DCI, MAC-CE or a WUS.

(162) In some aspects, the transmitting the one or more BFD RSs at block **1420** includes transmitting the one or more BFD RSs QCLed with a CORESET. In some aspects, the transmitting the one or more BFD RSs at block **1420** includes transmitting the one or more BFD RSs based on a TCI state of a CORESET.

(163) In some aspects, the transmitting the one or more BFD RSs at block **1420** includes transmitting the one or more BFD RSs in a BWP, where the BWP includes a BWP utilized by the second wireless communication device before operating in the dormancy mode, for example, as discussed above in the block **842** and **942** with reference to FIGS. **8** and **9**, respectively.

(164) In some aspects, the transmitting the one or more BFD RSs at block **1420** includes transmitting the one or more BFD RSs in a BWP, where the BWP includes a BWP utilized by the second wireless communication device before operating in the dormancy mode and a dormancy BWP utilized by the second wireless communication device when operating in the dormancy mode, for example, as discussed above in the block **844** and **944** with reference to FIGS. **8** and **9**, respectively.

(165) In some aspects, the transmitting the one or more BFD RSs at block **1420** includes transmitting the one or more BFD RSs (e.g., the reference signal **1110**) fully within a dormancy BWP. In some aspects, the transmitting the one or more BFD RSs at block **1420** includes transmitting the one or more BFD RSs (e.g., the reference signal **1120**) partially within a dormancy BWP, where a first portion of each of the one or more BFD RSs is within the dormancy BWP and a second portion of each of the one or more BFD RSs is outside the dormancy BWP. In some aspects, the transmitting the one or more BFD RSs at block **1420** includes transmitting the one or more BFD RSs (e.g., the reference signal **1130**) outside of a dormancy BWP.

(166) In some aspects, the BFD configuration indicates a first BWP is associated with the dormancy mode and a second BWP is associated with a non-dormancy mode. In some aspects, the BFD configuration has a first duration. In some aspects, the first duration is permanent. In some aspects, the first duration is based on at least one of a timer or a predetermined value. In some aspects, the first duration is based on a number of transitions between the dormancy mode and the non-dormancy mode.

(167) FIG. **15** is a flow diagram of a wireless communication method **1500** according to some aspects of the present disclosure. Aspects of the method **1500** can be executed by a computing device (e.g., a processor, processing circuit, and/or other suitable component) of a wireless communication device or other suitable means for performing the steps. For example, a wireless communication device, such as the UEs **115**, **500**, and/or **704** may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to execute the steps of method **1500**. The method **1500** may employ similar mechanisms as in the schemes **300**, **400**, **1100**, **1202**, **1204**, and/or **1206** discussed above with reference to FIGS. **3**, **4**, **11**, **12A**, **12B**, and/or **12C**, respectively, and/or the methods **700**, **800**, **900**, **1000**, and/or **1300** discussed above with reference to FIGS. **7**, **8**, **9**, **10**, and/or **13**, respectively. As illustrated, the method **1300** includes a number of enumerated steps, but aspects of the method **1300** may include additional steps before, after, and in between the enumerated steps. In some aspects, one or more of the enumerated steps may be omitted or performed in a different

order.

(168) At block **1510**, a UE (e.g., the UEs **115**, **500**, and/or **704**) determines, to operate in a dormancy mode for a cell of a wireless communication network. The wireless communication network may be similar to the network **100**. In some aspects, the UE may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to determine operate in the dormancy mode.

(169) At block **1520**, the UE operates in the dormancy mode for the cell of the wireless communication network. The operating in the dormancy mode includes performing a beam failure detection (BFD) in a dormancy bandwidth part (BWP) based on a configuration, for example, as discussed above with reference to FIG. **9**. In some aspects, the UE may utilize one or more components, such as the processor **502**, the memory **504**, the BFD module **508**, the transceiver **510**, the modem **512**, and the one or more antennas **516**, to operate in the dormancy mode.

(170) In some aspects, the UE further receives the configuration including a control resource set (CORESET) configuration for the dormancy BWP. The performing the BFD at block **1520** includes monitoring in the dormancy BWP based on the CORESET configuration for the dormancy BWP, for one or more BFD reference signals (RSs). In some aspects, the CORESET configuration indicates a CORESET in the dormancy BWP, and the monitoring for the one or more BFD RSs includes monitoring for the one or more BFD RSs associated with a transmission configuration indication (TCI) state of the CORESET. In some aspects, the UE further determines a first QCL type and a second QCL type are associated with the TCI state of the CORESET, and the monitoring for the one or more BFD RSs associated with the TCI state of the CORESET includes monitoring for the one or more BFD RSs associated with the TCI state of the CORESET based on the second QCL type. In some aspects, the second QCL type includes QCL Type D. In some aspects, the operating in the dormancy mode at block **1520** includes refraining from performing physical downlink control channel (PDCCH) monitoring in the dormancy BWP based on the CORESET configuration. In some aspects, the CORESET configuration indicates a CORESET in the dormancy BWP, but does not include any PDCCH search space configuration associated with the CORESET in the dormancy BWP.

(171) FIG. **16** is a flow diagram of a wireless communication method **1600** according to some aspects of the present disclosure. Aspects of the method **1600** can be executed by a computing device (e.g., a processor, processing circuit, and/or other suitable component) of a wireless communication device or other suitable means for performing the steps. For example, a wireless communication device, such as the BSs **105**, **600**, and/or **702** may utilize one or more components, such as the processor **602**, the memory **604**, the beam configuration and transmission module **608**, the transceiver **610**, the modem **612**, and the one or more antennas **616**, to execute the steps of method **1600**. The method **1600** may employ similar mechanisms as in the schemes **300**, **400**, **1100**, **1202**, **1204**, and/or **1206** discussed above with reference to FIGS. **3**, **4**, **11**, **12A**, **12B**, and/or **12C**, respectively, and/or the methods **700**, **800**, **900**, **1000**, and/or **1400** discussed above with reference to FIGS. **7**, **8**, **9**, **10**, and/or **14**, respectively. As illustrated, the method **1600** includes a number of enumerated steps, but aspects of the method **1600** may include additional steps before, after, and in between the enumerated steps. In some aspects, one or more of the enumerated steps may be omitted or performed in a different order.

(172) At block **1610**, a BS (e.g., the BSs **105**, **600**, and/or **702**) determines a UE (e.g., the UEs **115**, **500**, and/or **704**) is operating in a dormancy mode for a cell of a wireless communication network. In some aspects, the BS may utilize one or more components, such as the processor **602**, the memory **604**, the beam configuration and transmission module **608**, the transceiver **610**, the modem **612**, and the one or more antennas **616**, to determine that the UE is operating in the dormancy mode.

(173) At block **1620**, the BS transmitting, to the UE, a configuration for performing a beam failure detection (BFD) in a dormancy bandwidth part (BWP) associated with the dormancy mode. In

some aspects, the transmitting the configuration includes transmitting the configuration including a control resource set (CORESET) configuration for the dormancy BWP. In some aspects, the BS may utilize one or more components, such as the processor **602**, the memory **604**, the beam configuration and transmission module **608**, the transceiver **610**, the modem **612**, and the one or more antennas **616**, to transmit the configuration for performing the BFD in the dormancy BWP. (174) In some aspects, the BS further transmits, in the dormancy BWP based on the CORESET configuration for the dormancy BWP, one or more BFD RSs. In some aspects, the CORESET configuration indicates a CORESET in the dormancy BWP, and the transmitting the one or more BFD RSs includes transmitting the one or more BFD RSs based on a transmission configuration indication (TCI) state of the CORESET. In some aspects, the transmitting the one or more BFD RSs associated with the TCI state of the CORESET includes transmitting at least one of a first BFD RS of the one or more BFD RSs associated with the TCI state of the CORESET based on a first QCL type or a second BFD RS of the one or more BFD RSs associated with the TCI state of the CORESET based on a second QCL type different from the first QCL type. In some aspects, the second QCL type includes QCL Type D. In some aspects, the BS further determines one or more control resource sets (CORESETs) for the UE in the dormancy BWP, the CORESET configuration indicating the one or more CORESETs. The BS may also further refrains from assigning any physical downlink control channel (PDCCH) search space in the dormancy BWP for the UE. (175) Information and signals may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the above description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof. (176) The various illustrative blocks and modules described in connection with the disclosure herein may be implemented or performed with a general-purpose processor, a DSP, an ASIC, an FPGA or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor, but in the alternative, the processor may be any conventional processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices (e.g., a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration). (177) The functions described herein may be implemented in hardware, software executed by a processor, firmware, or any combination thereof. If implemented in software executed by a processor, the functions may be stored on or transmitted over as one or more instructions or code on a computer-readable medium. Other examples and implementations are within the scope of the disclosure and appended claims. For example, due to the nature of software, functions described above can be implemented using software executed by a processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations. Also, as used herein, including in the claims, “or” as used in a list of items (for example, a list of items prefaced by a phrase such as “at least one of” or “one or more of”) indicates an inclusive list such that, for example, a list of [at least one of A, B, or C] means A or B or C or AB or AC or BC or ABC (i.e., A and B and C). (178) As those of some skill in this art will by now appreciate and depending on the particular application at hand, many modifications, substitutions and variations can be made in and to the materials, apparatus, configurations and methods of use of the devices of the present disclosure without departing from the spirit and scope thereof. In light of this, the scope of the present disclosure should not be limited to that of the particular embodiments illustrated and described

herein, as they are merely by way of some examples thereof, but rather, should be fully commensurate with that of the claims appended hereafter and their functional equivalents.

Claims

1. A method of wireless communication by a first user equipment (UE), the method comprising: determining to operate in a dormancy mode for a cell of a wireless communication network; receiving a configuration including a control resource set (CORESET) configuration for a dormancy bandwidth part (BWP); and operating in the dormancy mode for the cell of the wireless communication network, wherein the operating in the dormancy mode includes: monitoring, in the dormancy BWP based on the CORESET configuration for the dormancy BWP, for a beam quality of one or more BFD reference signals (RSs), and performing a beam failure detection (BFD) in the dormancy BWP based on the configuration and the monitoring.
2. The method of claim 1, wherein the CORESET configuration indicates a CORESET in the dormancy BWP, and wherein the monitoring for the one or more BFD RSs includes: monitoring for the one or more BFD RSs associated with a transmission configuration indication (TCI) state of the CORESET.
3. The method of claim 2, further comprising: determining a first QCL type and a second QCL type are associated with the TCI state of the CORESET; and wherein the monitoring for the one or more BFD RSs associated with the TCI state of the CORESET includes: monitoring for the one or more BFD RSs associated with the TCI state of the CORESET based on the second QCL type.
4. The method of claim 3, wherein the second QCL type includes QCL Type D.
5. The method of claim 1, wherein the operating in the dormancy mode includes: refraining from performing physical downlink control channel (PDCCH) monitoring in the dormancy BWP based on the CORESET configuration.
6. The method of claim 1, wherein the CORESET configuration indicates a CORESET in the dormancy BWP, and wherein the configuration does not include any PDCCH search space configuration associated with the CORESET in the dormancy BWP.
7. A method of wireless communication performed by a base station (BS), the method comprising: determining a user equipment (UE) is operating in a dormancy mode for a cell of a wireless communication network; transmitting, to the UE, a configuration for performing a beam failure detection (BFD) in a dormancy bandwidth part (BWP) associated with the dormancy mode, wherein the configuration includes a control resource set (CORESET) configuration for the dormancy BWP; and transmitting, in the dormancy BWP based on the CORESET configuration for the dormancy BWP, one or more BFD RSs.
8. The method of claim 7, wherein the CORESET configuration indicates a CORESET in the dormancy BWP, and wherein the transmitting the one or more BFD RSs includes: transmitting the one or more BFD RSs based on a transmission configuration indication (TCI) state of the CORESET.
9. The method of claim 8, wherein the transmitting the one or more BFD RSs associated with the TCI state of the CORESET includes transmitting at least one of: a first BFD RS of the one or more BFD RSs associated with the TCI state of the CORESET based on a first QCL type; or a second BFD RS of the one or more BFD RSs associated with the TCI state of the CORESET based on a second QCL type different from the first QCL type.
10. The method of claim 9, wherein the second QCL type includes QCL Type D.
11. The method of claim 7, further comprising: determining one or more control resource sets (CORESETs) for the UE in the dormancy BWP, the CORESET configuration indicating the one or more CORESETs; and refraining from assigning any physical downlink control channel (PDCCH) search space in the dormancy BWP for the UE.
12. A user equipment (UE) comprising: a memory; and a processor coupled with the memory and

configured to, when executing instructions stored on the memory, to cause the UE to: determine to operate in a dormancy mode for a cell of a wireless communication network; receive a configuration including a control resource set (CORESET) configuration for a dormancy bandwidth part (BWP); and operate in the dormancy mode for the cell of the wireless communication network, wherein the operating in the dormancy mode includes; monitoring, in the dormancy BWP based on the CORESET configuration for the dormancy BWP, for a beam quality of one or more BFD reference signals (RSs), and performing a beam failure detection (BFD) in the dormancy BWP based on the configuration and the monitoring.

13. The UE of claim 12, wherein the CORESET configuration indicates a CORESET in the dormancy BWP, and wherein the processor configured to monitor for the one or more BFD RSs is configured to: monitor for the one or more BFD RSs associated with a transmission configuration indication (TCI) state of the CORESET.

14. The UE of claim 13, wherein the processor is further configured to: determine a first QCL type and a second QCL type are associated with the TCI state of the CORESET; and wherein the processor configured to monitor for the one or more BFD RSs associated with the TCI state of the CORESET is configured to: monitor for the one or more BFD RSs associated with the TCI state of the CORESET based on the second QCL type.

15. The UE of claim 14, wherein the second QCL type includes QCL Type D.

16. The UE of claim 12, wherein the processor configured to operate in the dormancy mode is configured to: refrain from performing physical downlink control channel (PDCCH) monitoring in the dormancy BWP based on the CORESET configuration.

17. The UE of claim 12, wherein the CORESET configuration indicates a CORESET in the dormancy BWP, and wherein the configuration does not include any PDCCH search space configuration associated with the CORESET in the dormancy BWP.

18. A base station (BS) comprising: a memory; and a processor coupled with the memory and configured to, when executing instructions stored on the memory, to cause the BS to: determine a user equipment (UE) is operating in a dormancy mode for a cell of a wireless communication network; transmit, to the UE, a configuration for performing a beam failure detection (BFD) in a dormancy bandwidth part (BWP) associated with the dormancy mode, wherein the configuration includes a control resource set (CORESET) configuration for the dormancy BWP; and transmit, in the dormancy BWP based on the CORESET configuration for the dormancy BWP, one or more BFD RSs.

19. The BS of claim 18, wherein the CORESET configuration indicates a CORESET in the dormancy BWP, and wherein the processor configured to transmit the one or more BFD RSs is configured to: transmit the one or more BFD RSs based on a transmission configuration indication (TCI) state of the CORESET.

20. The BS of claim 19, wherein the processor configured to transmit the one or more BFD RSs associated with the TCI state of the CORESET is configured to transmit at least one of: a first BFD RS of the one or more BFD RSs associated with the TCI state of the CORESET based on a first QCL type; or a second BFD RS of the one or more BFD RSs associated with the TCI state of the CORESET based on a second QCL type different from the first QCL type.

21. The BS of claim 20, wherein the second QCL type includes QCL Type D.

22. The BS of claim 18, wherein the processor is further configured to: determine one or more control resource sets (CORESETs) for the UE in the dormancy BWP, the CORESET configuration indicating the one or more CORESETs; and refrain from assigning any physical downlink control channel (PDCCH) search space in the dormancy BWP for the UE.
