

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12411372
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Koide; Gen et al.

Display device

Abstract

In one embodiment, a display device includes a display area, a peripheral area, scanning lines, signal lines, a first driver in the peripheral area, and a second driver in the peripheral area. The display area has an arc-shaped corner. The first driver includes first and second buffers configured to apply voltage to the scanning lines, a first shift register unit configured to control the first buffer unit, and a second shift register unit configured to control the second buffer unit. At the corner, extension directions of the first buffer unit and the first shift register unit are equal to each other. Extension directions of the second buffer unit and the second shift register unit are different from each other.

Inventors: Koide; Gen (Tokyo, JP), Noshita; Shimpei (Tokyo, JP), Kitamura; Junichi (Tokyo, JP)

Applicant: Magnolia White Corporation (Tokyo, JP)

Family ID: 63446518

Assignee: Magnolia White Corporation (Tokyo, JP)

Appl. No.: 18/636726

Filed: April 16, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240264477 A1	Aug. 08, 2024

Foreign Application Priority Data

JP	2017-043028	Mar. 07, 2017
----	-------------	---------------

Related U.S. Application Data

continuation parent-doc US 18169391 20230215 US 11988911 child-doc US 18636726
continuation parent-doc US 17365591 20210701 US 11609445 20230321 child-doc US 18169391
continuation parent-doc US 16879257 20200520 US 11086153 20210810 child-doc US 17365591
continuation parent-doc US 15908940 20180301 US 10698239 20200630 child-doc US 16879257

Publication Classification

Int. Cl.: **G09G3/30** (20060101); **G02F1/133** (20060101); **G02F1/1335** (20060101); **G02F1/1337** (20060101); **G02F1/1343** (20060101); **G02F1/1345** (20060101); **G09G3/3225** (20160101); **G09G3/3266** (20160101); **G09G3/3275** (20160101); G02F1/1362 (20060101); G09G3/3233 (20160101)

U.S. Cl.:

CPC **G02F1/13306** (20130101); **G02F1/133514** (20130101); **G02F1/1337** (20130101); **G02F1/1343** (20130101); **G02F1/13454** (20130101); **G09G3/3225** (20130101); **G09G3/3266** (20130101); **G09G3/3275** (20130101); G02F1/136286 (20130101); G02F2201/56 (20130101); G09G3/3233 (20130101)

Field of Classification Search

CPC: G02F (1/13306); G02F (1/133514); G02F (1/1337); G02F (1/1343); G02F (1/13454); G02F (1/136286); G02F (2201/56); G09G (3/3225); G09G (3/3266); G09G (3/3275); G09G (3/3233); G09G (3/3677); G11C (19/28)

USPC: 345/76; 345/100; 349/33

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2009/0102758	12/2008	Anzai	345/76	G09G 3/3266
2010/0141570	12/2009	Horiuchi	345/100	G11C 19/28
2015/0355487	12/2014	Emmert	349/33	G02F 1/13306
2016/0247478	12/2015	Ishige	N/A	G09G 3/3677
2017/0123285	12/2016	Suzuki et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
106448535	12/2016	CN	N/A

OTHER PUBLICATIONS

Office Action issued on Jun. 26, 2024, in corresponding Chinese Patent Application No. 202110930119.9, 16 pages. cited by applicant
Combined Chinese Office Action and Search Report issued Nov. 3, 2020 in Patent Application No. 201810186982.6 (submitting English machine translation only), citing FD No. 1 therein, 13 pages. cited by applicant

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. application Ser. No. 18/169,391, filed on Feb. 15, 2023, which is a continuation of U.S. application Ser. No. 17/365,591, filed on Jul. 1, 2021, which is a continuation of U.S. application Ser. No. 16/879,257 filed on May 20, 2020, which is a continuation of U.S. application Ser. No. 15/908,940 filed Mar. 1, 2018, and which is based upon and claims the benefit of priority from Japanese Patent Application No. 2017-043028, filed Mar. 7, 2017, the entire contents of each of which are incorporated herein by reference.

FIELD

(1) Embodiments described herein relate generally to a display device.

BACKGROUND

(2) A display device such as a liquid crystal display device or an organic electroluminescent display device has a display area in which pixels are arranged and a peripheral area which surrounds the display area. Peripheral circuits which drive the pixels are arranged in the peripheral area.

(3) Recently, various techniques for narrowing the frame of the display device have been considered. To narrow the frame of the display device, the area of the peripheral area needs to be reduced by arranging the peripheral circuits more efficiently.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a schematic plan view of an example of the structure of a display device according to one embodiment.

(2) FIG. 2 is a schematic plan view of an example of the structure related to a touch detection function of the display device.

(3) FIG. 3 is a schematic sectional view of a display panel taken along line III-III of FIG. 2.

(4) FIG. 4 is a schematic plan view of an example of the structures of peripheral circuits near a corner of a display area.

(5) FIG. 5 is a diagram showing a specific example of the equivalent circuit applicable to a scanning line driver.

(6) FIG. 6 is a timing chart showing an example of driving of scanning lines.

(7) FIG. 7 is a schematic plan view of a specific example of the structures of the peripheral circuits near the corner of the display area.

(8) FIG. 8 is a diagram showing an example of the layout of a buffer unit.

(9) FIG. 9 is a diagram showing an example of the cross-section of a buffer circuit taken along line IX-IX of FIG. 8.

(10) FIG. 10 is a diagram showing an example of a detailed circuit of a shift register unit.

(11) FIG. 11 is a timing chart showing an example of the operation of the circuit of FIG. 10.

DETAILED DESCRIPTION

(12) In general, according to one embodiment, a display device includes a display area including a plurality of pixels, a peripheral area around the display area, a plurality of scanning lines extending in a first direction in the display area, a plurality of signal lines extending in a second direction crossing the first direction in the display area, a first driver arranged in the peripheral area and connected to the scanning lines, and a second driver arranged in the peripheral area and connected

to the signal lines. The display area has an arc-shaped corner. The first driver includes a first buffer unit and a second buffer unit which are configured to apply voltage to the corresponding scanning lines, a first shift register unit configured to control the first buffer unit, and a second shift register unit configured to control the second buffer unit. At the corner, an extension direction of the first buffer unit and an extension direction of the first shift register unit are equal to each other. An extension direction of the second buffer unit and an extension direction of the second shift register unit are different from each other.

(13) According to this structure, a display device having a narrow frame can be obtained.

(14) An embodiment will be described hereinafter with reference to the accompanying drawings. The disclosure is merely an example, and proper changes in keeping with the spirit of the invention, which are easily conceivable by a person of ordinary skill in the art, come within the scope of the invention as a matter of course. In addition, in some cases, in order to make the description clearer, the widths, thicknesses, shapes, etc., of the respective parts are illustrated in the drawings schematically, rather than as an accurate representation of what is implemented. However, such schematic illustration is merely exemplary, and in no way restricts the interpretation of the invention. In addition, in the specification and drawings, structural elements which function in the same or a similar manner to those described in connection with preceding drawings are denoted by like reference numbers, detailed description thereof being omitted unless necessary.

(15) In the embodiment, a liquid crystal display device having a touch detection function will be described as an example of the display device. This liquid crystal display device can be used in various devices such as a smartphone, a tablet computer, a mobile phone, a notebook computer, a vehicle-mounted device and a game console. The main structure disclosed in the embodiment is applicable to a self-luminous display device such as an organic electroluminescent display device, an electronic paper-type display device including an electrophoretic element, etc., a display device adopting micro-electromechanical systems (MEMS), a display device adopting electrochromism, etc. Further, the structure related to image display disclosed in the embodiment is also applicable to a display device which does not have a touch detection function.

(16) FIG. 1 is a schematic plan view of an example of the structure of a display device DSP according to the present embodiment. In the drawing, a first direction X and a second direction Y orthogonally cross each other, and a third direction Z crosses the first direction X and the second direction Y. The first direction X, the second direction Y and the third direction Z are assumed to orthogonally cross each other, for example, but may cross each other at an angle other than an angle of 90 degrees. In the description, the direction of the pointing end of an arrow showing the third direction Z is referred to as upward (or simply above), and the direction opposite to the pointing end of the arrow is referred to as downward (or simply below).

(17) The display device DSP includes a display panel PNL, a wiring board F and a controller CT. The display panel PNL includes a first substrate SUB1, a second substrate SUB2 and a liquid crystal layer LC interposed between the first substrate SUB1 and the second substrate SUB2 (see FIG. 3 for details). Further, the display panel PNL has a display area DA in which an image is displayed, and a frame-like peripheral area SA which surrounds the display area DA.

(18) The display panel PNL has a first edge E1, a second edge E2 located on the other side of the display area DA from the first edge E1, a third edge E3 and a fourth edge E4 located on the other side of the display area DA from the third edge E3. In the example shown in FIG. 1, the edges E1 and E2 are parallel to the first direction X, and the edges E3 and E4 are parallel to the second direction Y. At the edges E2, E3 and E4, the edges of the first substrate SUB1 and the edges of the second substrate SUB2 are aligned with each other. The first edge E1 corresponds to the edge of the first substrate SUB1. The edge of the second substrate SUB2 on the first edge E1 side is located on the display area DA side from the edge of the first substrate SUB1. That is, the display panel PNL has an unopposed area NA (or a terminal area) in which the first substrate SUB1 is not opposed to the second substrate SUB2 between the first edge E1 and the display area DA.

- (19) The first substrate SUB1 has a corner C11 between the edge E1 and the edge E3, a corner C12 between the edge E1 and the edge E4, a corner C13 between the edge E2 and the edge E3 and a corner C14 between the edge E2 and edge E4. The second substrate SUB2 has a corner C21 near the corner C11, a corner C22 near the corner C12, a corner C23 near the corner C13 and a corner C24 near the corner C14. The display area DA has a corner C31 near the corner C11, a corner C32 near the corner C12, a corner C33 near the corner C13 and a corner C34 near the corner C14.
- (20) In the example shown in FIG. 1, all of the corners C11 to C14 of the first substrate SUB1, the corners C21 to C24 of the second substrate SUB2 and the corners C31 to C34 of the display area DA have the shape of an arc. For example, the corners C11 to C14 of the first substrate SUB1 and the corners C23 and C24 of the second substrate SUB2 have a first radius of curvature, the corners C21 and C22 of the second substrate SUB2 have a second radius of curvature, and the corners C31 to C34 of the display area DA have a third radius of curvature. The first radius of curvature, the second radius of curvature and the third radius of curvature differ from each other, and are assumed to satisfy the first radius of curvature>the second radius of curvature>the third radius of curvature, for example. The relationships among the corners C11 to C14, C21 to C24 and C31 to C34 are not limited to those described above. Further, at least one of the corners C11 to C14, C21 to C24 and C31 to C34 may not have the shape of an arc but may be square.
- (21) The display panel PNL includes a plurality of scanning lines G and a plurality of signal lines S in the display area DA. The scanning lines G extend in the first direction X and are arranged in the second direction Y at intervals. The signal lines S extend in the second direction Y and are arranged in the first direction X at intervals.
- (22) The display area DA includes a plurality of pixels PX arranged in the first direction X and the second direction Y. Each pixel PX includes subpixels SP which display different colors from each other. For example, the pixel PX includes a subpixel SPR corresponding to red, a subpixel SPG corresponding to green and a blue subpixel SPB corresponding to blue. The pixel PX does not necessarily have this structure and may further include a subpixel which displays white, for example, or may include a plurality of subpixels corresponding to the same color. In the description, a subpixel may also be referred to simply as a pixel.
- (23) Each subpixel SP includes a switching element SW, a pixel electrode PE and a common electrode CE. The common electrode CE is formed over several subpixels SP, for example. The switching element SW is electrically connected to the scanning line G, the signal line S and the pixel electrode PE.
- (24) The display panel PNL includes scanning line drivers GD1 and GD2 (first drivers) connected to the scanning lines G, and a signal line driver SD (second driver) connected to the signal lines S. The scanning line driver GD1 is arranged between the display area DA and the third edge E3, and the scanning line driver GD2 is arranged between the display area DA and the fourth edge E4. The signal line driver SD is arranged between the display area DA and the unopposed area NA. One of the scanning line drivers GD1 and GD2 may be omitted.
- (25) In the example shown in FIG. 1, the scanning line driver GD1 is curved in an arc shape similarly to the corners C31 and C33 near the corners C31 and C33. That is, the scanning line driver GD1 includes a portion extending parallel to the second direction Y (a middle portion in the second direction Y), and portions extending in directions crossing the first direction X and the second direction Y (end portions in the second direction Y).
- (26) Further, the scanning line driver GD2 is curved in an arc shape similarly to the corners C32 and C34 near the corners C32 and C34. That is, the scanning line driver GD2 includes a portion extending parallel to the second direction Y (a middle portion in the second direction Y), and portions extending in directions crossing the first direction X and the second direction Y (end portions in the second direction Y).
- (27) Still further, the signal line driver SD is curved in an arc shape similarly to the corners C31 and C32 near the corners C31 and C32. That is, the signal line driver SD includes a portion

extending parallel to the first direction X (a middle portion in the first direction X), and portions extending in directions crossing the first direction X and the second direction Y (end portions in the first direction X).

(28) An end of the signal line driver SD near the corner C31 is located between the scanning line driver GD1 and the display area DA. An end of the signal line driver SD near the corner C32 is located between the scanning line driver GD2 and the display area DA.

(29) The scanning line drivers GD1 and GD2 supply scanning signals to the scanning lines G. The signal line driver SD supplies video signals to the signal lines S. If a scanning signal is supplied to the scanning line G corresponding to a switching element SW and a video signal is supplied to the signal line S connected to this switching element SW, the switching element SW is set to an on state by the scanning signal and a voltage corresponding to the video signal is applied to the pixel electrode PE. At this time, an electric field is generated between the pixel electrode PE and the common electrode CE and the alignment of liquid crystal molecules of the liquid crystal layer LC is changed from an initial alignment state. Through these operations, an image is displayed in the display area DA.

(30) A connection terminal T is provided along the first edge E1 in the unopposed area NA, and the wiring board F is connected to the connection terminal T. In the example shown in FIG. 1, the controller CT is mounted on the wiring board F. The controller CT includes a display driver R1 which controls the scanning line drivers GD1 and GD2 and the signal line driver SD, and a detection driver R2 for touch detection. The display driver R1 and the detection driver R2 are not necessarily mounted in these manners and may be mounted on the first substrate SUB1, for example. Further, the display driver R1 and the detection driver R2 may be mounted on different members, respectively.

(31) FIG. 2 is a plan view of the display device DSP schematically showing an example of the structure related to the touch detection function. The display device DSP includes a plurality of detection electrodes RX. The detection electrodes RX extend in the first direction X and are arranged in the second direction Y in the display area DA. Further, in the example shown in FIG. 2, the common electrodes CE are arranged in the display area DA. The common electrodes CE extend in the second direction Y and are arranged in the first direction X.

(32) The common electrodes CE function not only as electrodes for image display but also as driving electrodes for detecting an object approaching the display area DA in cooperation with the detection electrodes RX. The present embodiment will be described based on the assumption that the common electrodes CE are arranged on the first substrate SUB1 and the detection electrodes RX are arranged on the second substrate SUB2. However, the display device DSP can also adopt such a structure where driving electrodes are provided separately from the common electrodes CE. Further, the detection electrodes RX and the common electrodes CE (or the driving electrodes) may be arranged in various other manners. For example, the common electrodes CE (or the driving electrodes) may be provided on the second substrate SUB2, or the detection electrodes RX and the driving electrodes which are provided separately from the common electrodes CE may be provided on a transparent base arranged on the display surface of the display panel PNL.

(33) In the example shown in FIG. 2, each detection electrode RX is electrically connected to a pad P arranged in the peripheral area SA via a connection hole H. The pad P is electrically connected to the connection terminal T via a lead line L1 arranged in the peripheral area SA. As illustrated in the drawing, the odd-numbered detection electrodes RX from the second edge E2 are connected to the pads P arranged between the third edge E3 and the display area DA, and the even-numbered detection electrodes RX from the second edge E2 are connected to the pads P arranged between the fourth edge E4 and the display area DA.

(34) FIG. 3 is a schematic sectional view of the display panel PNL taken along line III-III of FIG. 2. The first substrate SUB1 includes a first base 10 such as a glass substrate or a resin substrate, a first insulating layer 11, a second insulating layer 12, a first alignment film 13, and the common

electrodes CE and the pixel electrodes PE. The first substrate SUB1 also includes the scanning lines G, the signal lines S, the switching elements SW, etc., but illustrations thereof are omitted in FIG. 3.

(35) The pads P and the lead lines L1 are arranged on the first base 10. An insulating layer may be interposed between the pads P and the lead lines L1, and the first base 10. The first insulating layer 11 covers the pads P and the lead lines L1. The common electrodes CE are arranged on the first insulating layer 11. The second insulating layer 12 covers the common electrodes CE and the first insulating layer 11. The pixel electrodes PE are arranged on the second insulating layer 12 and are opposed to the common electrodes CE via the second insulating layer 12. The first alignment film 13 covers the pixel electrodes PE and the second insulating layer 12.

(36) The second substrate SUB2 includes a second base 20 such as a glass substrate or a resin substrate, a color filter layer 21 and a second alignment film 22. The color filter layer 21 is arranged below the second base 20. The color filter layer 21 includes color filters having colors corresponding to the subpixels SPR, SPG and SPB. The second alignment film 22 covers the color filter layer 21. The color filter layer 21 may be arranged on the first substrate SUB1.

(37) The second substrate SUB1 and the second substrate SUB2 are attached to each other via a sealant SL. The liquid crystal layer LC is sealed in a space enclosed with the first alignment film 13, the second alignment film 22 and the sealant SL.

(38) The detection electrodes RX are arranged on the second base 20. The connection holes H penetrate the second base 20, the color filter layer 21, the second alignment film 22, the sealant SL, the first alignment film 13, the second insulating layer 12 and the first insulating layer 11. The connection holes H may further penetrate the pads P. For example, the connection holes H taper down toward the pads P as illustrated in the drawing, but the connection holes H are not limited to this example. A conductive connection member C is arranged in the interior of each connection hole H. Each detection electrode RX is electrically connected to the pad P via the connecting member C.

(39) The pixel electrodes PE and the common electrodes CE can be formed of a transparent conductive material such as indium tin oxide (ITO), for example. The detection electrodes RX, the pads P and the lead lines L1 can be formed of a transparent conductive material such as ITO or a metal material. In the case of using a metal material for the detection electrodes RX, for example, an electrode pattern of single-layered or multi-layered metal wiring lines arranged in a mesh-like manner or wave-like manner can be used as the detection electrodes RX.

(40) The cross-section structure shown in FIG. 3 is merely an example and various other structures can be applied to the display panel PNL. For example, the common electrodes CE may be arranged between the pixel electrodes PE and the liquid crystal layer LC, may be arranged on the same layer together with the pixel electrodes PE, or may be arranged on the second substrate SUB2. Further, the first alignment film 13, the color filter layer 21 or the second alignment film 22 may not be arranged in the locations of the connection holes H.

(41) In the above-described structure, a first capacitance is formed between the detection electrodes RX and the common electrodes CE. Further, if an object such as a user's finger approaches the display area DA, a second capacitance is formed between the object and the detection electrodes RX. The detection driver R2 supplies drive signals for object detection to the common electrodes CE. At this time, detection signals are output from the detection electrodes RX to the detection driver R2 via the first capacitance. The detection signals vary depending on the presence or absence of the second capacitance or the magnitude of the second capacitance. Therefore, the detection driver R2 can detect the presence or absence of an object approaching the display area DA or the location of an object in the display area DA based on the detection signals.

(42) The detection method described above is called a mutual-capacitive detection method. The object detection method is not limited to a mutual-capacitive detection method and may be a self-capacitive detection method. In a self-capacitive detection method, drive signals are supplied to the

detection electrodes RX and detection signals are read from the detection electrodes RX, and the presence or absence of an object approaching the display area DA or the location of an object in the display area DA can be detected based on these detection signals.

(43) Next, the structures of the peripheral circuits (the scanning line drivers GD1 and GD2, the signal line driver SD, etc.) arranged in the peripheral area SA will be described.

(44) FIG. 4 is a schematic plan view of an example of the structures of the peripheral circuits near the corners C11, C21 and C31. The scanning driver GD1 includes a plurality of shift register units 30 and a plurality of buffer units 40, each of which is connected to each of the shift register units 30 and is also connected to at least one scanning line G. The shift register units 30 constitute a shift register which controls the timings for sequentially supplying scanning signals to the scanning lines G. Each buffer unit 40 includes at least one buffer circuit 41. Each buffer circuit 41 supplies a scanning signal (scanning voltage) to the scanning line G under the control of the shift register unit 30.

(45) The first substrate SUB1 includes a video line group VG including a plurality of video lines V in the peripheral area. The video line group VG is arranged along the signal line driver SD. The video line group VG is curved along the corner C31 of the display area DA. The video lines V constituting the video line group VG are electrically connected to the display driver R1 via the connection terminal T and the wiring board F. In the example shown in FIG. 4, the signal line driver SD is arranged between the video line group VG and the display area DA. Further, in an area in which the signal line driver SD is arranged between the scanning line driver GD1 and the display area DA, the video line group VG extends between the scanning line driver GD1 and the signal line driver SD.

(46) The signal line driver SD includes a plurality of selector units 50. Each selector unit 50 includes at least one selector circuit 51 (selector switch). The selector circuit 51 is connected to N video lines V and M signal lines S, where M is greater than N ($M > N$). For example, N is two and M is six ($N = 2$ and $M = 6$). The selector circuit 51 switches the signal lines S to be connected to the video lines V in a time sharing manner. Accordingly, video signals can be supplied to the signal lines S by using the video lines V fewer than the signal lines S arranged in the display area DA.

(47) The lead lines L1 connecting the detection electrodes RX to the connection terminal T are arranged along the edges of the first substrate SUB1. That is, the scanning line driver GD1, the signal line driver SD and the video line group VG are located between the lead lines L1 and the display area DA. The lead lines L1 are curved in an arc shape similarly to the corner C11 near the corner C11. The distance between the lead lines L1 and the edges of the first substrate SUB1 is entirely constant in the example shown in FIG. 4 but may vary from one portion to another. For example, the distance between the lead lines L1 and the edges of the first substrate SUB1 may gradually increase toward the first edge E1 near the corner C11.

(48) The scanning line driver GD1 and the signal line driver SD are curved along the corner C31 near the corner C31 of the display area DA. Therefore, part of the signal line driver SD near the corner C31 is located on the second edge E2 side (on the upper side in the drawing) from an outer edge EDA1 of the display area DA which is closest to the first edge E1. Further, part of the scanning line driver GD1 near the corner C31 is located on the fourth edge E4 side (on the right side in the drawing) from an outer edge EDA2 of the display area DA which is closest to the third edge E3.

(49) The number of the selector circuits 51 included in each selector unit 50 varies such that, as the selector unit 50 is closer to the end of the signal line driver SD, the selector unit 50 includes a smaller number of selector circuits 51. Accordingly, the width of each selector unit 50 in the first direction X varies such that, as the selector unit 50 is closer to the end of the signal line driver SD, the selector unit 50 becomes narrower in the first direction X.

(50) In the example shown in FIG. 4, the video line group VG has a stepped area in which a portion extending in the first direction X and a portion extending in the second direction Y are alternately

repeated, and each of the selector units **50** is arranged with respect to each of the steps of the stepped area. Some of the selector units **50** may be arranged with respect to one of the steps. Further, at least part of the video line group VG may extend in a direction crossing the first direction X and the second direction Y.

(51) Here, as one example, shift register units **30A**, **30B** and **30C** and buffer units **40A**, **40B** and **40C** connected thereto will be noted among the shift register units **30** and the buffer units **40**. The shift register unit **30A** and the shift register unit **30B** are adjacent to each other, and the shift register unit **30B** and the shift register unit **30C** are adjacent to each other. Further, the buffer unit **40A** and the buffer unit **40B** are adjacent to each other, and the buffer unit **40B** and the buffer unit **40C** are adjacent to each other.

(52) The distance between the shift register unit **30A** and the shift register unit **30B** in the first direction X is defined as dx_{11} , the distance between the shift register unit **30B** and the shift register unit **30C** in the first direction X is defined as dx_{12} , the distance between the shift register unit **30A** and the shift register unit **30B** in the second direction Y is defined as dy_{11} , and the distance between the shift register unit **30B** and the shift register unit **30C** in the second direction Y is defined as dy_{12} . In this case, the distance dx_{11} and the distance dx_{12} differ from each other in the example shown in FIG. 4. More specifically, the distance dx_{11} is less than the distance dx_{12} ($dx_{11} < dx_{12}$), and since the shift register units **30A** and **30B** are not misaligned with each other in the first direction X, the distance dx_{11} is zero. Further, the distance dy_{11} and the distance dy_{12} differ from each other in the example shown in FIG. 4. More specifically, the distance dy_{11} is less than the distance dy_{12} ($dy_{11} < dy_{12}$). As other examples, the shift register units **30A**, **30B** and **30C** may be arranged in such a manner as to satisfy $dx_{11} > dx_{12}$ or may be arranged in such a manner as to satisfy $dy_{11} \geq dy_{12}$.

(53) In the example shown in FIG. 4, similarly to the distances dx_{11} and dx_{12} , the distance between the buffer unit **40A** and the buffer unit **40B** in the first direction X and the distance between the buffer unit **40B** and the buffer unit **40C** in the first direction X differ from each other. Further, similarly to the distances dy_{11} and dy_{12} , the distance between the buffer unit **40A** and the buffer unit **40B** in the second direction Y and the distance between the buffer unit **40B** and the buffer unit **40C** in the second direction Y differ from each other.

(54) Further, as one example, selector units **50A**, **50B** and **50C** will be noted among the selector units **50**. The selector unit **50A** and the selector unit **50B** are adjacent to each other, and the selector unit **50B** and the selector unit **50C** are adjacent to each other. The selector units **50A**, **50B** and **50C** are not aligned with each other in the first direction X and the second direction Y.

(55) The distance between the selector unit **50A** and the selector unit **50B** in the first direction X is defined as dx_{21} , the distance between the selector unit **50B** and the selector unit **50C** in the first direction X is defined as dx_{22} , the distance between the selector unit **50A** and the selector unit **50B** in the second direction Y is defined as dy_{21} , and the distance between the selector unit **50B** and the selector unit **50C** in the second direction Y is defined as dy_{22} . In this case, the distance dx_{21} and the distance dx_{22} differ from each other in the example shown in FIG. 4. More specifically, the distance dx_{21} is less than the distance dx_{22} ($dx_{21} < dx_{22}$). Further, the distance dy_{21} and the distance dy_{22} are substantially equal to each other in the example shown in FIG. 4. As other examples, the selector units **50A**, **50B** and **50C** may be arranged in such a manner as to satisfy $dx_{21} \geq dx_{22}$ or may be arranged such that the distance dy_{21} and the distance dy_{22} differ from each other.

(56) In this way, the scan line driver GD1 can be curved in an arc shape along the corner C31 by adjusting the distances between the shift register units **30** and the distances of the buffer units **40** in the respective directions X and Y near the corner C31. Similarly, the signal line driver SD can be curved in an arc shape along the corner C31 by adjusting the distances of the selector units **50** in the respective directions X and Y near the corner C31.

(57) In the above description, the distance (dx_{11} , dx_{12} , dx_{21} , dx_{22} , etc.) between two adjacent

units in the first direction X corresponds to the distance between the centers of the units in the first direction X. Further, the distance (dy11, dy12, dy21, dy22, etc.) between two adjacent units in the second direction Y corresponds to the distance between the centers of the units in the second direction Y.

(58) Each shift register unit **30** includes a plurality of elements as will be described later, and the elements in the shift register units **30** are arranged in substantially equal manners. Further, each buffer unit **40** includes the plurality of buffer circuits **41**, and the buffer circuits **41** in the buffer units **40** are arranged in arbitrary directions.

(59) In FIG. 4, the shift register unit **30** is represented as a rectangle vertically elongated in the second direction Y. This shows that the elements constituting the shift register unit **30** are arranged in the second direction Y. Further, the buffer unit **40** is represented as a rectangle vertically elongated in the second direction Y on the upper side of the drawing and is represented as a rectangle horizontally elongated in the first direction X on the lower side of the drawing. This shows that the buffer circuits **41** are arranged in the second direction Y in the vertically long rectangle and the buffer circuits **41** are arranged in the first direction X in the horizontally long rectangle.

(60) Near the corner C31 of the display area DA, the width of the peripheral area SA in the first direction X increases from the upper side to the lower side of the drawing. Further, in accordance with the width of the peripheral area SA, the buffer unit **40** transitions from the vertically long rectangle to the horizontally long rectangle. That is, the width of the peripheral area SA in the first direction X in the buffer unit **40A** is not large enough to arrange the buffer circuits **41** in the first direction X, but the width of the peripheral area SA in the first direction X in the buffer unit **40B** is large enough to arrange the buffer circuits **41** in the first direction X.

(61) Although the width of the peripheral area SA in the first direction X is large in areas in which the buffer units **40B** and **40C** are formed, since the selector units **50A** and **50B** need to be formed side by side in the first direction X, the distance between two adjacent units in the first direction X and the distance between two adjacent units in the second direction Y, and the number of the video lines V to be arranged, etc., need to be taken into consideration.

(62) Further, on the lower side of the drawing, the width of the peripheral area SA increases in the first direction X, but the width of the peripheral area SA decreases in the second direction Y and becomes limited to a certain width. Therefore, the positional relationship between the shift register units **30** and the buffer units **40** will be determined in consideration of the area in which the selector units **50** are formed.

(63) The structure of the scanning line driver GD1 near the corner C33 of the display area DA shown in FIG. 1 is the same as the structure of the scanning line driver GD1 near the corner C31. Further, the structures of the scanning line driver GD2, the signal line driver SD, the video line group VG and the lead lines L1 near the corner C32 of the display area DA are the same as structures thereof near the corner C31. Still further, the structure of the scanning line driver GD2 near the corner C34 of the display area DA is the same as the structure of the scanning line driver GD1 near the corner C33. The structure of the peripheral area SA near the corners C31 to C34 is not limited to the illustrated example and can be appropriately modified in consideration of the layouts of circuits and wiring lines to be arranged.

(64) FIG. 5 is a diagram showing a specific example of the equivalent circuit applicable to the scanning line driver GD1. Here, the shift register unit **30A**, the buffer unit **40A**, the shift register unit **30B** and the buffer unit **40B** will be noted among the shift register units **30** and the buffer units **40**.

(65) The shift register unit **30A** includes logic circuits **31a**, **32a** and **33a**, a clock supply switch **34a** and a constant voltage supply switch **35a**. The buffer unit **40A** includes four buffer circuits **41**. The buffer circuits **41** are connected to scanning lines Ga1 to Ga4, respectively. Each buffer circuit **41** includes a gate pulse supply switch **42a** and a gate low voltage supply switch **43a**. The number of

buffer circuits **41** included in the buffer unit **40A** is not limited to four.

(66) The clock supply switch **34a** and the gate pulse supply switch **42a** are formed of an n-type thin film transistor (TFT) and a p-type TFT. The constant voltage supply switch **35a** and the gate low voltage supply switch **43a** are formed of an n-type TFT.

(67) The shift register unit **30B** includes logic circuits **31b**, **32b** and **33b**, a clock supply switch **34b** and a constant voltage supply switch **35b**. Since the buffer unit **40B** has the same structure as that of the buffer unit **40A**, a circuit structure thereof is not illustrated. In the example shown in FIG. 5, the buffer unit **40B** is connected to scanning lines Gb1 to Gb4. The clock supply switch **34b** is formed of an n-type TFT and a p-type TFT. The constant voltage supply switch **35b** is formed of a p-type TFT.

(68) A scanning direction setting switch **60a** including switches **61a** and **62a** is connected to the logic circuit **31a**. A scanning direction setting switch **60b** including switches **61b** and **62b** is connected to the logic circuit **31b**. These scanning direction setting switches **60a** and **60b** determine the scanning directions of the shift register units **30**, respectively. More specifically, the shift register units **30** are scanned in the order of the shift register unit **30** previous to the shift register unit **30A**, the shift register unit **30A**, the shift register unit **30B**, and the shift register unit **30** subsequent to the shift register unit **30B**. All of the switches **61a**, **62a**, **61b** and **62b** are formed of an n-type TFT and a p-type TFT.

(69) A signal *ina* from the scanning direction setting switch **60a** and a signal *backa* are input to the logic circuit **31a**. The logic circuit **31a** outputs a signal corresponding to the inverted logical sum of the signals *ina* and *backa*, to the logic circuit **32a**, the p-type TFT of the clock supply switch **34a** and the constant voltage supply switch **35a**. The logic circuit **32a** inverts the signal from the logic circuit **31a** and outputs the inverted signal to the n-type TFT of the clock supply switch **34a**. In accordance with the signal from the logic circuit **31a**, one of the clock supply switch **34a** and the constant voltage supply switch **35a** is turned on. The clock supply switch **34a** outputs a clock CKV when the clock supply switch **34a** is on. On the other hand, the constant voltage supply switch **35a** outputs a constant low voltage VGL when the constant voltage supply switch **35a** is on. The clock CKV and the low voltage VGL are output to the buffer unit **40A** as an output signal *out1* and are also output to the logic circuit **31a** as the signal *backa*. Further, the output signal *out1* is inverted in the logic circuit **33a** and is output to the buffer unit **40A** as an output signal *xout1*.

(70) In the buffer unit **40A**, the output signal *out1* is input to the n-type TFTs of the gate pulse supply switches **42a**. The output signal *xout1* is input to the p-type TFTs of the gate pulse supply switches **42** and the gate low voltage supply switches **43a**. If the output signal *out1* is at an L level (low voltage) and the output signal *xout1* is at an H level (high voltage), the gate pulse supply switches **42a** are turned off and the gate low voltage supply switches **43a** are turned on. In this case, the low voltage VGL is output from the gate low voltage supply switches **43a** to the scanning lines Ga1 to Ga4. The low voltage VGL turns off the switching elements SW.

(71) On the other hand, if the output signal *out1* is at an H level and the output signal *xout1* is at an L level, the gate pulse supply switches **42a** are turned on and the gate low voltage supply switches **43a** are turned off. In this case, enable signals *enb1* to *enb4* are output from the gate pulse supply switches **42a** to the scanning lines Ga1 to Ga4, respectively.

(72) The output signal *xout1* is output to the logic circuit **31b** of the shift register unit **30B** as a signal *inb* via the scanning direction setting switch **60b**. A signal *backb* is also input to the logic circuit **31b**. The logic circuit **31b** outputs a signal corresponding to the logical sum of the inverted signals *inb* and *backb* to the logic circuit **32b**, the p-type TFT of the clock supply switch **34b** and the constant voltage supply switch **35b**. The logic circuit **32b** inverts the signal from the logic circuit **31b** and outputs the inverted signal to the p-type TFT of the clock supply switch **34b**. In accordance with the signal from the logic circuit **31b**, one of the clock supply switch **34b** and the constant voltage supply switch **35b** is turned on. The clock supply switch **34b** outputs the clock CKV when the clock supply switch **34b** is on. On the other hand, the constant voltage supply

switch **35b** outputs a constant high voltage VGH when the constant voltage supply switch **35b** is on. The clock CKV and the high voltage VGH are output to the buffer unit **40B** as an output signal xout2 and are also output to the logic circuit **31b** as the signal backb. Further, the output signal xout2 is inverted in the logic circuit **33b** and is output to the buffer unit **40B** as an output signal out2. The output signal out2 is also output to the scanning direction setting switch corresponding to the subsequent shift register unit **30**. The buffer unit **40B** is driven by the output signals out2 and xout2 in the same manner that the buffer unit **40A** is driven by the output signals out1 and xout1. (73) The clock CKV and the enable signals enb1 to enb4, etc., are supplied from the display driver **R1**, for example.

(74) An example of the driving of the scanning lines Ga1 to Ga4 by the circuit structure shown in FIG. 5 will be described with reference to the timing chart shown in FIG. 6. If the signal ina transitions from an L level to an H level, the signal output from the logic circuit **31a** is set to an L level, and the clock supply switch **34a** is turned on and the constant voltage supply switch **35a** is turned off. At this time, if the H-level clock CKV is supplied, the output signals out1 and xout1 are set to an H level and an L level, respectively, and the gate pulse supply switches **42a** are turned on and the gate low voltage supply switches **43a** are turned off. Accordingly, the enable signals enb1 to enb4 are supplied to the scanning signal lines Ga1 to Ga4. The enable signals enb1 to enb4 are four-phase clocks which divide a period in which the clock CKV is at an H level or an L level into four. That is, the enable signals enb1 to enb4 sequentially transition to an H level in the H-level period of the clock CKV as shown in FIG. 6. Accordingly, pulsed scanning signals are sequentially supplied to the scanning signal lines Ga1 to Ga4.

(75) Subsequently, if the clock CKV transitions to an L level, the signal inb is set to an H level, and the signal output from the logic circuit **31b** is set to an H level. Accordingly, the clock supply switch **34b** is turned on and the constant voltage supply switch **35b** is turned off, and the output signals out2 and xout2 are set to an H level and an L level, respectively. In this state, the enable signals enb1 to enb4 sequentially transition to an H level, and pulsed scanning signals are sequentially supplied to the scanning lines Gb1 to Gb4.

(76) It is possible to supply scanning signals sequentially to the scanning lines G by applying the structure corresponding to the shift register unit **30A** and the buffer unit **40A** and the structure corresponding to the shift register unit **30B** and the buffer unit **40B** alternately to the shift register units **30** and the buffer units **40** of the scanning line driver **GD1**. The same structure can also be applied to the scanning line driver **GD2**.

(77) Next, a specific example of the structures of the peripheral circuits near the corner **C31** of the display area DA will be described with reference to a plan view shown in FIG. 7. The illustrated structures are also applicable to the peripheral circuits near the corner **C32** of the display area DA. Further, the structures of the shift register units **30** and the buffer units **40** are also applicable to the peripheral circuits near the other corners **C32**, **C33** and **C34** of the display area DA.

(78) The peripheral circuits shown in FIG. 7 include the shift register units **30A**, **30B**, **30C** and **30D**, the buffer units **40A**, **40B**, **40C** and **40D**, the selector units **50A**, **50B** and **50C**, and the video line group VG. The shift register unit **30D** is adjacent to the shift register unit **30C**. The buffer unit **40D** is connected to the shift register unit **30D**.

(79) Each of the buffer units **40A**, **40B**, **40C** and **40D** includes four buffer circuits **41**. Each buffer circuit **41** is connected to one scanning line G. Each of the selector unit **50A** and the selector unit **50B** includes three selector circuits **51**, and the selector unit **50C** includes four selector circuits **51**. Each selector circuit **51** is connected to two video lines V and six signal lines S. In the selector units **50A**, **50B** and **50C**, the selector circuits **51** are arranged in the first direction X. The scanning lines G and the signal lines S extend over the display area DA. The subpixels SP in the display area DA are arranged stepwise near the corner **C31**, and the arc-shaped corner **C31** shown in FIG. 4, etc., can be realized by adjusting the number of subpixels SP constituting each of the steps.

(80) In the example shown in FIG. 7, an extension direction **D11** of the shift register units **30A**,

30B and **30C** and an extension direction **D12** of the shift register unit **30D** differ from each other. Here, the extension direction of the shift register unit **30** corresponds to the longitudinal direction of the shift register unit **30**, for example. The extension direction of the shift register unit **30** may be the direction of arrangement of elements such as TFTs included in the shift register unit **30**.

(81) Further, in the example shown in FIG. 7, an extension direction **D21** of the buffer units **40A** and **40D** and an extension direction **D22** of the buffer units **40B** and **40C** differ from each other. Here, the extension direction of the buffer unit **40** corresponds to the longitudinal direction of the buffer unit **40**, for example. The extension direction of the buffer unit **40** may be the direction of arrangement of the buffer circuits **41** included in the buffer unit **40**.

(82) For example, the extension directions **D11** and **D21** are parallel to the second direction **Y**, and the extension directions **D12** and **D22** are parallel to the first direction **X**. In this case, the extension direction of the shift register unit **30A** is the same as the extension direction of the buffer unit **40A**. On the other hand, the extension direction of the shift register unit **30B** differs from the extension direction of the buffer unit **40B**, the extension direction of the shift register unit **30C** differs from the extension direction of the buffer unit **40C**, and the extension direction of the shift register unit **30D** differs from the extension direction of the buffer unit **40D**. The extension directions **D11**, **D12**, **D21** and **D22** may also be directions crossing the first direction **X** or the second direction **Y**.

(83) The space of the peripheral area **SA** can be efficiently used by appropriately adjusting the extension directions of the pair of the shift register unit **30** and the buffer unit **40** to the same direction or different directions. As a result, the area of the peripheral area **SA** can be reduced, and the frame of the display device **DSP** can be narrowed.

(84) In the example shown in FIG. 7, the buffer units **40A**, **40B** and **40C** are arranged on the outer side of the video line group **VG** (on the opposite side of the video line group **VG** from the display area **DA**), but the buffer unit **40D** is arranged between the video line group **VG** and the display area **DA**. The space of the peripheral area **SA** can be more efficiently used by adjusting the arrangement locations of the buffer units **40**.

(85) Next, the extension direction of the buffer unit **40** will be described with reference to a layout diagram shown in FIG. 8. FIG. 8 is a detailed view of the buffer circuit **41** of the buffer unit **40A** shown in FIG. 5 and is a layout diagram of elements constituting the buffer circuit **41**. FIG. 9 is a sectional view of the buffer circuit **41** taken along line **IX-IX** of FIG. 8. The illustrated structure is also applicable to the peripheral circuits near the corners **C32**, **C33** and **C34** of the display area **DA**. FIG. 9 shows the detailed structure of the buffer circuit **41** from the first base **10** to the first insulating layer **11** shown in the sectional view of FIG. 3.

(86) In FIG. 8, the n-type TFT of the gate pulse supply switch **42a** (hereinafter referred to as a first n-type transistor), the p-type TFT of the gate pulse supply switch **42a** (hereinafter referred to as a first p-type transistor) and the gate low voltage supply switch **43a** (hereinafter referred to as a second n-type transistor) are arranged side by side on a same semiconductor layer **451**.

(87) The gate of the first n-type transistor is indicated as **421**, and a wiring line **471** is connected and the output signal **out1** shown in FIG. 5 is supplied to the gate **421** of the first n-type transistor. To clarify wiring lines, signal names are added to the drawing. An area functioning as the drain of the first n-type transistor and the source of the first p-type transistor is indicated as **443**. A wiring line **473** is connected and the enable signal **enb1** shown in FIG. 5 is supplied to the area **443**. An area functioning as the source of the first n-type transistor and the source of the second n-type transistor is indicated as **425**. If the output signal **out1** is set to an H level, the first n-type transistor is set to an on state, and the enable signal **enb1** is output from the source **425** of the first n-type transistor to a wiring line **463**.

(88) The gate of the first p-type transistor is indicated as **441**, and a wiring line **475** is connected and the output signal **xout1** shown in FIG. 5 is supplied to the gate **441** of the first p-type transistor. The drain of the first p-type transistor is indicated as **445**. If the output signal **xout1** is set to an L level, the first p-type transistor is set to an on state, and the enable signal **enb1** is output from the

drain **445** of the first p-type transistor to a wiring line **465**.

(89) Since the output signal **xout1** is the inverted output signal **out1**, the first n-type transistor and the first p-type transistor are concurrently set to an on state and output the enable signal **enb1**.

(90) The gate of the second n-type transistor is indicated as **431**, and a wiring line **477** is connected and the output signal **xout1** shown in FIG. 5 is supplied to the gate **431** of the second n-type transistor. The drain of the second n-type transistor is indicated as **433**. If the output signal **xout 1** is set to an H level, the second n-type transistor is set to an on state, and the low voltage **VGL** applied via a wiring line **479** is output from the source **425** of the second n-type transistor to the wiring line **463**.

(91) As shown in the sectional view of FIG. 9 taken along line IX-IX of FIG. 8, the semiconductor layer **451** is formed on the first base **10** such as a glass substrate or a resin substrate. In the semiconductor layer **451**, the drain **445** of the first p-type transistor, the area **443** functioning as the drain of the first n-type transistor and the source of the first p-type transistor, the area **425** functioning as the source of the first n-type transistor and the source of the second n-type transistor, and the drain **433** of the second n-type transistor are formed by implanting impurities, etc. An underlying layer **111** is formed between the semiconductor layer **451** and the first base **10**.

(92) An insulating film **113** is formed on the semiconductor layer **451**, and the gate **441** of the first p-type transistor, the gate **421** of the first n-type transistor and the gate **431** of the second n-type transistor are formed on the insulating film **113**. An insulating film **115** is formed on the gates **421**, **431** and **441**, and the wiring line (power supply line) **479** which applies the low voltage **VGL**, the wiring line **473** which supplies the enable signal **enb1**, the wiring line **463** which is connected to the area **425** functioning as the sources of the first and second n-type transistors, and the wiring line **465** which is connected to the drain **445** of the first p-type transistor are formed on the insulating film **115**.

(93) The output of the buffer circuit **41** is connected to the wiring line **465** via the wiring line **463**, and the wiring line **465** is connected to the scanning line **Ga1**.

(94) A plurality of through holes **461** are formed in the insulating film **115**. The drain **445** of the first p-type transistor is electrically connected to the wiring line **465**, the wiring line **473** is electrically connected to the area **443** functioning as the drain of the first n-type transistor and the source of the first p-type transistor, the area **425** functioning as the sources of the first and second n-type transistors is electrically connected to the wiring line **463**, and the drain **433** of the second n-type transistor is electrically connected to the wiring line **479** which applies the low voltage **VGL**, respectively, via the through holes **461**.

(95) Regarding the signal flow in FIG. 8, the output signals **out1** and **xout1** from the shift register unit **30** located on the left side of the drawing are input to the buffer circuit **41**, and the signal from the buffer circuit **41** is output to the scanning line **G** located on the right side of the drawing. Accordingly, the signals flow in the first direction **X**. Further, the shape of the buffer circuit **41** is defined by the shape of the semiconductor layer **451**. The semiconductor layer **451** has a rectangular shape in such a manner as to become the same in the gate pulse supply switch **42a** and the gate low voltage supply switch **43a**, and the sides extending in the first direction **X** are longer than the sides extending in the second direction **Y** in the drawing.

(96) Further, the drain **433** of the second n-type transistor, the area **425** functioning as the source of the first n-type transistor and the source of the second-n-type transistor, the area **443** functioning as the drain of the first n-type transistor and the source of the first p-type transistor, and the drain **445** of the first p-type transistor are arranged in the first direction **X** along the long sides of the rectangular semiconductor layer **451**.

(97) The buffer unit **40** shown in FIG. 5 includes the plurality of buffer circuits **41** shown in FIG. 8. In the structure of the buffer circuit **41** shown in FIG. 8, if the buffer circuits **41** are arranged side by side, two adjacent buffer circuits **41** are arranged such that the long sides of the semiconductor layers **451** are opposed to each other. Accordingly, in FIG. 8, the buffer circuits **41** are arranged in

the second direction Y, and the extension direction of the buffer unit **40** will be the second direction Y.

(98) As described above, the buffer units **40** have two extension directions, i.e., the extension direction of a rectangle elongated in the second direction Y and the extension direction of a rectangle elongated in the first direction X in accordance with the width of the peripheral area SA near the corners **C31**, **C32**, **C33** and **C34** of the display area DA. In the buffer unit **40** represented as a rectangle elongated in the second direction Y, the buffer circuits **41** are formed in the second direction Y, and the buffer unit **40** extends in the second direction Y. In the buffer unit **40** represented as a rectangle elongated in the first direction X, the buffer circuits **41** are formed in the first direction X, and the buffer unit **40** extends in the first direction X.

(99) Next, the detailed circuits of the shift register units **30A** and **30B** are shown in FIG. **10**. Although FIG. **10** is a circuit diagram, the arrangement and positional relationship of the circuit symbols of the transistors indicate the arrangement and positional relationship of the transistors formed on the first base **10**.

(100) In FIG. **10**, p-type transistors **311** and **313** and n-type transistors **315** and **317** constitute the logic circuit (NOR) **31a** shown in FIG. **5**. The signal ina is input to the gate of the p-type transistor **311** and the gate of the n-type transistor **315**. The outputs of the p-type transistor **311** and the n-type transistor **315** are connected to a node n1. The node n1 is connected to the gate of the p-type transistor **341** and the gate of the n-type transistor **351** (the constant voltage supply switch **35a**). The logic circuit (inverter) **32a**, and the n-type transistor of the clock supply switch (transfer gate) **34a** shown in FIG. **5** are omitted in FIG. **10**. Therefore, the clock supply switch **34a** is formed of the p-type transistor **341**.

(101) If the node n1 is at an L level, the p-type transistor **341** is set to an on state, and the clock CKV is output as the output signal out1 and the signal backa. If the node n1 is at an H level, the n-type transistor **351** is set to an on state, and the low voltage VGL is output as the output signal out1 and the signal backa. If the signal backa is at an L level, the p-type transistor **313** is set to an on state, and if the signal backa is at an H level, the n-type transistor **317** is set to an on state. If the p-type transistors **313** and **311** are set to an on state, the high voltage VGH is applied to the node n1. On the other hand, if the n-type transistor **317** is set to an on state, the low voltage VGL is applied to the node n1.

(102) An n-type transistor **331** and a p-type transistor **333** constitute the logic circuit (inverter) **33a** shown in FIG. **5**. The signal output from the logic circuit **33a** is inverted and output as the output signal xout1. The output signal xout1 is output to the logic circuit (NOR) **31b** of the shift register unit **30B** as the signal inb via the n-type transistor **611** and the p-type transistor **613** which constitute the switch **61b**. If a scanning direction control line **612** is at an H level and a scanning direction control line **623** is at an L level, a signal shifts from the shift register unit **30a** to the shift register unit **30b**. If the scanning direction control line **621** is at an L level and the scanning direction control line **623** is at an H level, a signal shifts from the shift register unit **30b** to the shift register unit **30a**.

(103) The logic circuit **31b** is formed of n-type transistors **321** and **323** and p-type transistors **325** and **327**. The signal inb is input to the gate of the n-type transistor **321** and the gate of the p-type transistor **325**. The outputs of the n-type transistor **323** and the p-type of the transistor **325** are connected to a node n2. The node n2 is connected to the gate of the p-type transistor **343** (the constant voltage supply switch **35b**) and the gate of the n-type transistor **353**. The logic circuit (inverter) **32b**, and the p-type transistor of the clock supply switch (transfer gate) **34b** shown in FIG. **5** are omitted in FIG. **10**. Therefore, the clock supply switch **34b** is formed of the n-type transistor **353**.

(104) If the node n2 is at an H level, the n-type transistor **353** is set to an on state, and the clock CKV is output as the output signal xout2 and the signal backb. If the node n2 is at an L level, the p-type transistor **343** is set to an on state, and the high voltage VGH is output as the output signal

xout2 and the signal backb. If the signal backb is at an H level, the n-type transistor **323** is set to an on state, and if the signal backb is at an L level, the p-type transistor **327** is set to an on state. If the n-type transistors **323** and **321** are set to an on state, the low voltage VGL is applied to the node n2. On the other hand, if the p-type transistor **327** is set to an on state, the high voltage VGH is applied to the node n2.

(105) An n-type transistor **337** and a p-type transistor **335** constitute the logic circuit (inverter) **33b** shown in FIG. **5**. The signal is inverted in the logic circuit **33b** and is output as the output signal out2.

(106) Next, the operations of the circuits shown in FIG. **10** will be described with reference to a timing chart shown in FIG. **11**. At time t1, the signal ina from the shift register unit **30** previous to the shift register unit **30a** shifts from an L level to an H level. If the signal ina is at an L level, the n-type transistor **315** is set to an on state, and the node n1 is set to an L level. When the node n1 is set to an L level, the p-type transistor **341** is set to an on state, but from the time t1 to time t2, the clock CKV is at an L level, and therefore the output signal out1 and the signal backa are at an L level.

(107) Subsequently, when the time t2 comes, the clock CKV shifts from an L level to an H level, and from the time t2 to time t3, the output signal out1 and the signal backa are set to an H level. When the signal backa is at an H level, the n-type transistor **351** is set to an on state, and therefore the node n1 is set to an L level and the p-type transistor **341** is maintained in an on state. Further, from the time t2 to the time t3, the signal xout1 corresponding to the signal inverted in the inverter **33a** is at an L level, and the signal inb to be input to the shift register unit **30a** is at an L level.

(108) When the time t3 comes, the clock CKV shifts from an L level to an H level and the signal backa is set to an L level, and therefore the n-type transistor **317** is set to an off state and the p-type transistor **313** is set to an on state. At the time t3, the signal ina is at an L level, and therefore the p-type transistor **311** is set to an on state. Consequently, the node n1 is set to an H level by the high voltage VGH, and after the time t3, the node n1 is maintained at an H level.

(109) As described above, the arrangement and positional relationship of the circuit symbols of the transistors indicate the arrangement and positional relationship of the transistors on the first base **10** in FIG. **10**. In FIG. **10**, the main transistors constituting the shift register unit **30** are formed in an area sandwiched between a wiring line **481** which applies the high voltage VGH and a wiring line **483** which applies the low voltage VGL. That is, the logic circuits **31a**, **33a**, **31b** and **33b**, the clock supply switches **34a** and **34b**, and the constant voltage supply switches **35a** and **35b** which constitute the shift register unit **30** are formed in the second direction Y in which the wiring lines **481** and **483** extend. Therefore, the extension direction of the shift register units **30a** and **30b** is the second direction Y in which the wiring lines **481** and **483** extend.

(110) The high voltage VGH and the low voltage VGL are appropriately set such that the low voltage VGL becomes lower than the high voltage VGH. The high voltage VGH and the low voltage VGL are power supply voltages of the logic circuits **31a**, **33a**, **31b** and **33b**, the clock supply switches **34a** and **34b** and the constant voltage supply switches **35a** and **35b**, and are also voltages which perform on-off control of the elements.

(111) As described above, the shift register unit **30** has two extension directions, i.e., the extension direction of a rectangle elongated in the second direction and the extension direction of a rectangle elongated in the first direction in accordance with the width of the peripheral area SA near the corners C31, C32, C33 and C34 of the display area DA. In the shift register unit **30** represented as a rectangle elongated in the second direction Y, the wiring lines which apply the high voltage VGH and the low voltage VGL are formed in the second direction Y, and the shift register unit **30** extends in the second direction Y. In the shift register unit **30** represented as a rectangle elongated in the first direction X, the wiring lines which apply the high voltage VGH and the low voltage VGL are formed in the first direction X, and the shift register unit **30** extends in the first direction X.

(112) If the buffer units **40** and the shift register units **30** have a plurality of extension directions as described above, the arrangement locations of the buffer units **40** and the shift register units **30** can

be adjusted, and consequently the space of the peripheral area SA can be used more efficiently. (113) Further, as described above with reference to FIG. 4, if the distance between the adjacent shift register units 30, the distance between the adjacent buffer units 40 and the distance between the adjacent selector units 50 are not fixed but are at least partially variable, the overall shapes of the scanning line drivers GD1 and GD2 and the signal line driver SD can be adjusted. Accordingly, even if the display area DA has a non-rectangular shape such as the display area DA having the arc-shaped corners C31 to C34 as described in the present embodiment, the scanning line drivers GD1 and GD2 and the signal line driver SD can be optimally shaped, and the area of the peripheral area SA can be reduced.

(114) Still further, in the case of controlling a plurality of buffer units 40 by a single shift register unit 30 as described with reference to FIGS. 5 and 6, the number of shift register units 30 included in the scanning line drivers GD1 and GD2 can be reduced. As a result, the area of the peripheral area SA can be further reduced.

(115) A plurality of elements identical or similar to each other such as the shift register units 30, the buffer units 40, the selector units 50, the scanning lines G and the signal lines S described in the present embodiment can be differentiated from each other by appropriately adding words such as “the first”, “the second”, “the third”, “the nth”.

(116) Further, it is normal for a person of ordinary skill in the art to conceive various modifications of the present invention within the scope of the technical concept of the present invention, and such modifications will fall within the scope of the present invention. For example, a person of ordinary skill in the art may make an addition, a deletion or a design change of a structural element, or make an addition, an omission or a condition change of a manufacturing process to the above-described embodiment, but such modifications will also come within the scope of the present invention as long as they fall within the scope and spirit of the present invention.

(117) Still further, when it comes to advantages other than those described in the embodiment, advantages obvious from the description of the present invention and advantages appropriately conceivable by a person having ordinary skill in the art are considered as advantages achievable from the present invention as a matter of course.

Claims

1. A display device comprising: a plurality of pixels in a display area; a plurality of signal lines arrayed in a first direction in the display area; a plurality of scanning lines arrayed in a second direction crossing the first direction in the display area; and a scanning line driver in a peripheral area outside of the display area, wherein the display area includes a corner portion, pixels in the corner portion are arranged in a stepped pattern, the scanning line driver includes a plurality of shift register units and a plurality of switch groups, each of the plurality of switch groups includes plural switches, each of the plural switches is connected to a respective one of the plurality of shift register units, each of the plural switches is connected to a respective one of the scanning lines, the plurality of shift register units are arranged along the stepped pattern of the pixels, the plurality of switch groups are arranged along the stepped pattern of the pixels, an A number of the plural switches of one of the switch groups are arrayed along the first direction, a B number of the plural switches of other one of the switch groups are arrayed along the second direction, the other one of the switch groups is a next switch group of the one of the switch groups, and the A number and the B number are integers greater than 2.
2. The display device of claim 1, wherein the plural switches include a gate pulse supply switch.
3. The display device of claim 1, wherein the plural switches include a gate low voltage supply switch.
4. The display device of claim 1, wherein the plural switches include a gate pulse supply switch and a gate low voltage supply switch.

5. The display device of claim 2, wherein the gate pulse supply switch includes a n-type transistor and a p-type transistor.
 6. The display device of claim 1, wherein the A number is a same number as the B number.
 7. The display device of claim 1, wherein the plurality of switch groups include a first switch group and a second switch group, the first switch group is the A number of the plural switches arrayed along the first direction, the second switch group is the B number of the plural switches arrayed along the second direction, the first switch group has a first extension direction parallel to the first direction and a second extension direction parallel to the second direction, the second switch group has a first extension direction parallel to the first direction and a second extension direction parallel to the second direction, the first extension direction of the first switch group is longer than the first extension direction of the second switch group, and the second extension direction of the first switch group is shorter than the second extension direction of the second switch group.
 8. The display device of claim 7, wherein the plurality of shift register units include a first shift register unit and a second shift register unit, the first shift register unit is connected to the first switch group, the second shift register unit is connected to the second switch group, the first shift register unit has a first extension direction parallel to the first direction and a second extension direction parallel to the second direction, the second shift register unit has a first extension direction parallel to the first direction and a second extension direction parallel to the second direction, the first extension direction of the first shift register unit is shorter than the first extension direction of the second shift register unit, and the second extension direction of the first shift register unit is longer than the second extension direction of the second shift register unit.
 9. The display device of claim 8, wherein a distance between the first switch group and the first shift register unit in the first direction is shorter than a distance between the second switch group and the second shift register unit in the first direction.
 10. The display device of claim 7, further comprising: a signal line driver in the peripheral area and a video line group in the peripheral area, wherein the video line group is connected to the signal line driver, the plurality of signal lines are connected to the signal line driver, the signal line driver is between the video line group and the plurality of signal lines, and a part of the video line group is formed along the stepped pattern of the pixels.
 11. The display device of claim 10, wherein the first switch group is located between the plurality of shift register units and the video line group, and the second switch group is located between the video line group and the display area.
 12. The display device of claim 11, wherein the second switch group is connected to one of the shift register units by a first connection line, and the first connection line crosses the video line group.
 13. The display device of claim 12, wherein the first switch group is connected to another one of the shift register units by a second connection line, and the second connection line does not overlap the video line group.
-