

# US Patent & Trademark Office

## Patent Public Search | Text View

---

|                      |                    |
|----------------------|--------------------|
| United States Patent | 12401555           |
| Kind Code            | B2                 |
| Date of Patent       | August 26, 2025    |
| Inventor(s)          | Pundole; Faraidoon |

---

### Remote device telemetry and communication

---

#### Abstract

Aspects of the disclosure provide for a method implemented by a control system for communicating with a remote device. In at least some examples, the method includes determining a frequency of operation of the remote device and determining whether the frequency of operation of the remote device varies from a programmed frequency. The method further includes determining a frequency scaling factor based on whether the frequency of operation of the remote device varies from a programmed frequency. The method further includes generating a frequency shift keying (FSK) signal, scaling the FSK signal to generate a frequency scaled shift keying (FSSK) signal, and transmitting the FSSK signal to the remote device.

---

|                   |                                            |
|-------------------|--------------------------------------------|
| <b>Inventors:</b> | <b>Pundole; Faraidoon (Sugar Land, TX)</b> |
| <b>Applicant:</b> | <b>Pundole; Faraidoon (Sugar Land, TX)</b> |
| <b>Family ID:</b> | <b>1000008781857</b>                       |
| <b>Appl. No.:</b> | <b>18/525326</b>                           |
| <b>Filed:</b>     | <b>November 30, 2023</b>                   |

#### Prior Publication Data

| Document Identifier | Publication Date |
|---------------------|------------------|
| US 20240113925 A1   | Apr. 04, 2024    |

#### Related U.S. Application Data

continuation parent-doc US 17780122 US 11870621 WO PCT/US2020/062494 20201127 child-doc US 18525326  
us-provisional-application US 63093948 20201020  
us-provisional-application US 63093944 20201020  
us-provisional-application US 62941011 20191127  
us-provisional-application US 62941014 20191127

## Publication Classification

**Int. Cl.:** H04L27/12 (20060101)

**U.S. Cl.:**

**CPC** H04L27/12 (20130101);

## Field of Classification Search

**CPC:** H04L (27/04); H04L (27/10); H04L (27/12); H04L (27/16)

---

## References Cited

### U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name | U.S. Cl. | CPC         |
|--------------|-------------|---------------|----------|-------------|
| 5852630      | 12/1997     | Langberg      | N/A      | N/A         |
| 10049211     | 12/2017     | Lukacs        | N/A      | G06F 21/566 |
| 10078879     | 12/2017     | Nalluri       | N/A      | G09G 5/001  |
| 10079699     | 12/2017     | Li            | N/A      | N/A         |
| 10764097     | 12/2019     | Rey           | N/A      | N/A         |
| 2004/0022328 | 12/2003     | Laamanen      | N/A      | N/A         |
| 2004/0218696 | 12/2003     | Suissa        | N/A      | N/A         |
| 2010/0329195 | 12/2009     | Abraham       | N/A      | N/A         |
| 2014/0003823 | 12/2013     | Roberts       | N/A      | N/A         |
| 2018/0131234 | 12/2017     | Uchimoto      | N/A      | N/A         |

### FOREIGN PATENT DOCUMENTS

| Patent No. | Application Date | Country | CPC |
|------------|------------------|---------|-----|
| 2018148616 | 12/2017          | WO      | N/A |
| 2021108762 | 12/2020          | WO      | N/A |

### OTHER PUBLICATIONS

International Search Report and Written Opinion dated Apr. 1, 2021, PCT/US2020/062494 filed on Nov. 27, 2020. cited by applicant

Office Action dated May 11, 2023, U.S. Appl. No. 17/780,122, filed May 26, 2023. cited by applicant

Notice of Allowance dated Aug. 24, 2023, U.S. Appl. No. 17/780,122, filed May 26, 2023. cited by applicant

---

*Primary Examiner:* Lee; Siu M

*Attorney, Agent or Firm:* Conley Rose, P.C.

---

## Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of and claims priority under 35 U.S.C. § 120 to U.S. patent application Ser. No. 17/780,122, filed May

26, 2022, entitled, "REMOTE DEVICE TELEMETRY AND COMMUNICATION," which is a filing under 35 U.S.C. 371 as the National Stage of International Application No. PCT/US2020/062494, filed on Nov. 27, 2020, entitled, "REMOTE DEVICE TELEMETRY AND COMMUNICATION," which claims the benefit of and claims priority to: 1) U.S. Provisional Patent Application No. 62/941,011, which was filed Nov. 27, 2019, and is titled "Safety Sub,,"; 2) U.S. Provisional Patent Application No. 63/093,944, which was filed Oct. 20, 2020, and is titled "Safety Sub,,"; 3) U.S. Provisional Patent Application No. 62/941,014, which was filed Nov. 27, 2019, and is titled "Downhole Communication Systems and Methods,,"; and 4) U.S. Provisional Patent Application No. 63/093,948, which was filed Oct. 20, 2020, and is titled "Downhole Communication Systems and Methods,," all of which are hereby incorporated herein by reference in its entirety for all purposes.

## BACKGROUND

(1) Oil and gas tools are used to complete oil and gas wells by performing certain tasks inside a well bore at a certain depth in order to facilitate the flow of hydrocarbons into the wellbore. Such operations involve multiple tools at different producing zones at different depths where it may be required to control distinct functions separately. These tools are usually brought to the producing zone(s) by wireline, tubing or downhole tractors.

(2) Similarly, various other types of tools used in industries such as mining, demolition, pyrotechnics, and the like also rely on the operation of several types of tools in series. While these tools are not disposed within a wellbore, they are often arranged over large distances to place the user at a distance from the tools.

## SUMMARY

(3) Aspects of the disclosure provide for a method implemented by a control system for communicating with a remote device. In at least some examples, the method includes determining a frequency of operation of the remote device and determining whether the frequency of operation of the remote device varies from a programmed frequency. The method further includes determining a frequency scaling factor based on whether the frequency of operation of the remote device varies from a programmed frequency. The method further includes generating a frequency shift keying (FSK) signal, scaling the FSK signal to generate a frequency scaled shift keying (FSSK) signal, and transmitting the FSSK signal to the remote device.

(4) Other aspects of the disclosure provide for a control system. In at least some examples, the control system includes a microcontroller including a memory and executable code stored as firmware in the memory. When executed by the microcontroller, the executable code configures the microcontroller to generate a FSK signal including a command for a remote device. The executable code further configures the microcontroller to condition the FSK signal according to operating characteristics of the remote device and characteristics of a communication channel coupling the control system to the remote device to generate a conditioned FSK signal. The executable code further configures the microcontroller to transmit the conditioned FSK signal to the remote device via the communication channel.

(5) Other aspects of the disclosure provide for a remote device. In at least some examples, the remote device includes an electrically erasable programmable read-only memory (EEPROM), a microcontroller including a memory and coupled to the EEPROM, and executable code stored as firmware in the memory. When executed by the microcontroller, the executable code configures the microcontroller to receive power from a wireline coupled between a control system and the remote device, read a switch state from the memory and from the EEPROM, and determine whether the switch state read from the memory matches the switch state read from the EEPROM. The executable code further configures the microcontroller to control a switch to have the switch state when the switch state read from the memory matches the switch state read from the EEPROM match and fail to a safe state by controlling the switch to have a switch state of off when the switch

state read from the memory does not match the switch state read from the EEPROM match.

(6) Other aspects of the disclosure provide for a method. In at least some examples, the method includes reading a switch state from redundant memory locations and determining whether the switch state read from the redundant memory locations matches. The method also includes controlling a switch to have the switch state when the switch state read from the redundant memory locations matches. The method also includes failing to a safe state by controlling the switch to have a switch state of off when the switch state read from the redundant memory locations does not match.

(7) Other aspects of the disclosure provide for a remote device. In at least some examples, the remote device includes a battery, a microcontroller including a memory and adapted to receive power from the battery, and executable code stored as firmware in the memory. When executed by the microcontroller, the executable code configures the microcontroller to determine that a predetermined period of time has elapsed since the microcontroller received power via a physical coupling to a control system and control a switch to have a switch state of off responsive to the determination that the predetermined period of time has elapsed.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a diagram of an example system in accordance with various examples.

(2) FIG. 2 is an example schematic diagram of the control system in accordance with various examples.

(3) FIG. 3 is a diagram of an example of a control signal having pre-emphasis in accordance with various examples.

(4) FIG. 4 is a state diagram of a state machine in accordance with various examples.

(5) FIG. 5 is a block diagram of an example remote device in accordance with various examples.

(6) FIG. 6 is a block diagram of an example isolated drive circuit in accordance with various examples.

(7) FIG. 7 is a diagram of an example of a Manchester encoded waveform having pre-emphasis in accordance with various examples.

(8) FIG. 8 is a state diagram of a state machine in accordance with various examples.

### DETAILED DESCRIPTION

(9) Various devices are implemented remote to a user or controller of the remote devices. However, for the user to maintain control of a remote device, a control system in proximity to the user maintains communicative connectivity to the remote device. In some examples, the connectivity is implemented as a wireline or physical connection, providing reliable communication between the control system and the remote device. In at least some examples, the wireline is of a length such that losses or other alterations to a signal transmitted on the wireline occur between opposite ends of the wireline. Also in at least some examples, the wirelines passes through, or into, an environment such that losses or other alterations to a signal transmitted on the wireline occur between opposite ends of the wireline (e.g., such as when the wirelines passes through, or into, areas having vastly varying temperatures between opposite ends of the wireline).

(10) In various examples, the remote devices are control and/or telemetry devices. One such control device is a switch circuit for controlling a flow of current to a downstream device for which the switch is an intermediary between the downstream device and the control device. The switch circuit is, for example, a safety circuit that prevents an unintentional passage of current between input and output terminals of the switch circuit. In this sense, the switch circuit is, in some examples, implemented as a blocking device to block the transfer of power between two points coupled to respective input and output terminals of the switch circuit. The switch circuit may also

include at least some telemetry functionality. For example, the switch circuit may capture and transmit voltage, current, temperature, or other measurements to the control system. Such remote devices may be implemented in situations in which it is advantageous, or preferred, for the user to remain physically distant from the remote devices. For example, a remote device may be implemented between a user and a downstream tool or device that is a detonation charge, such as in mining, demolition, wellbore perforation, or other situations in which it may be dangerous or disadvantageous for a user to be in proximity of the detonation charge. In other examples, the remote device may be implemented between the user and a downstream tool that is not inherently dangerous such as a detonation charge, but is located inconveniently for facilitating physical proximity of the user to the downstream device.

(11) In a particular implementation example, a perforating gun is selectively disposed and used inside a wellbore to facilitate a flow of hydrocarbons into the wellbore. For example, the perforating gun directs an explosive charge into a casing of the wellbore in one or more locations, perforating the casing in at least some of the one or more locations and facilitating the flow of hydrocarbons into the wellbore through the perforations in the casing of the wellbore. While the example of a perforating gun, a wellbore, and more generally oil field uses and implementations of the present disclosure are described herein, the present disclosure is not limited to only these implementations, as discussed above. For example, the systems and methods disclosed herein may also be used in mining and demolition settings.

(12) To control detonation of the explosive charge of the perforating gun, a remote control device can be implemented between a user controlling a control system and the perforating gun. The remote device is, in some examples, a switch as described above that enables the user to transmit a control signal from the control system to control when current is provided, via the switch, to the perforating gun to enable or facilitate detonation of the explosive charge or communication with the perforating gun by the remote control device and/or the control system. The switch is, in some examples, a bidirectional switch that facilitates transmitting uplink communication from the switch to the control system and receiving downlink communication at the switch from the control system. Multiple switches may be disposed along a wireline and be uniquely addressable and controllable via the uplink and downlink communication capabilities to facilitate unique control of multiple perforating guns.

(13) The control system, in at least some examples, calibrates communication with the remote control device. For example, as a temperature of an environment surrounding the remote control device increases, a frequency at which the remote control device operates may change. In some examples, when the temperature of the environment surrounding the remote control device increases, frequency at which the remote control device operates decreases. In at least some implementations, the control system determines an amount of the decrease in frequency at which the remote control device is operating and modifies a frequency of communication of the control system with the remote control device to match the frequency at which the remote control device is operating. Similarly, in at least some examples, an amplitude of communication signals transmitted by the control system to the remote control device may decrease or decay as a length of the wireline between the control system and the remote control device increases. In at least some implementations, the control system determines the decrease in the amplitude of communication signals transmitted by the control system to the remote control device and modifies the amplitude of the communication signals transmitted by the control system to the remote control device to compensate for the decrease in amplitude.

(14) In at least some examples, a voltage passed from the control system to the downstream tool, passing through the remote control device, can have a voltage of 1000 volts (V) or greater, such as 1500 V, 1700 V, etc. Accordingly, at least some examples of the remote control device are capable of blocking transmission of these voltages from the control system to the downstream tool. Some approaches to this blocking by the remote control device involve electromechanical switches.

However, electromechanical switches can face mechanical failures that can render them inoperable when located remote to the control system, detrimentally affecting operation of the remote control device.

(15) At least some aspects of the disclosure provide for a control system configured to communicate with a remote device coupled to the control system via a wireline. The control system is configured to superimpose a frequency-shift keying (FSK) encoded control signal on a power signal transmitted via the wireline. The control signal, in at least some examples, is uniquely addressed to the remote device such that the control system may communicate uniquely with multiple remote devices coupled to the wireline. In some examples, an operating frequency of the remote device varies from a frequency at which the control system is configured to transmit the control signal. In such examples, the control system may determine the operating frequency of the remote device and calibrate its transmission frequency to the operating frequency of the remote device. Similarly, in some examples the control signal may become attenuated from an amplitude at which it is transmitted by the control system and an amplitude at which it is received by the remote device. In such examples, the control system may determine an amount of the attenuation and compensate for the attenuation prior to transmitting the control signal. In other examples, the control system may provide a default or programmed amount of compensation to the control signal to compensate for the attenuation prior to transmitting the control signal. In some implementations, the control system can be configured to monitor the wirelines to receive communication from the remote device. The communication is, in some examples, conveyed via a Manchester encoded pattern.

(16) Other aspects of the disclosure provide for a remote device, as described above. The remote device is, in some examples, a switch circuit as described above. The remote device can be configured to be located remotely to a controller, such as the control system described above. In at least some examples, the remote device operates as a blocking device on a wireline, selectively blocking or allowing passage of voltage and current from the control system located upstream to the remote device to a downstream device located downstream to the remote device. The remote device, in some examples, receives a control signal from the control system and determines data included in the control signal. The data is, in some examples, encoded into the control signal according to FSK. Based on the data of the control signal, the remote device may permit or deny a flow of power and/or the control signal (or another control signal) from the control system to the downstream device. In some examples, the remote device includes multiply-redundant safety measures for preventing unintentional passage of power from the control system to the downstream device. For example, the remote device may include redundant switches isolating the control system from the downstream device. Similarly, the remote device may include redundant data storage devices that independently store a status (e.g., on or off, closed or open, etc.) of the switches, where in the event of a mismatch between the statuses stored in the redundant data stores, the remote devices fails to a safe state in which the switches are controlled to be off. In some examples, the remote device provides upstream communication to the control system via a Manchester encoded pattern, encoded onto the wirelines coupling the remote device to the control system.

(17) As a specific example in the oilfield context of the uses described above, a switch can be used in conjunction with each detonator or ignitor in a string of perforating guns to select and determine a sequence of firing. There are distinct types of switches such as a diode switch that allows two guns (or a gun and a plug) to be fired, one with positive and the other with negative voltage. Another type is a percussion switch that uses the force of detonation of one gun to electrically to connect electrically to the next gun starting from the bottom gun and working up. These switches are used to selectively fire three or more guns. These devices also electrically disconnect a fired gun thereby preventing electrical shorting. A problem with these switches is that in the event any switch fails to actuate, the firing sequence cannot continue, and the string must be pulled out from

the well bore, redressed and run again. Another problem lies in the fact that the system on the surface depends on detecting the change in current to identify gun position in a changing environment which is not reliable.

(18) Nowadays another type of communicable electronic switch is used, that has the ability of bidirectional communication and has no limitations to the number of guns that can be fired in a run. A common occurrence now seen is that as the spacing in the well is reduced a greater number of electronic switches are used at a much shorter spacing. This creates an issue with the communication head voltage due to the voltage drop across these devices. In addition to this having a substantial number of devices downhole means that each device has a greater probability of having its reference time base being affected by temperature.

(19) The challenge in this environment is that the lateral portion of the well is far longer than before. Extended reach lateral wells require a long wireline and the longer the wireline the more lossy it is contributing to signal distortion. Also, the new E-coil units that run an electric cable or signal down coil tubing are very lossy methods of communication. The need for a novel communication system that addresses these challenges is described.

(20) The systems and methods described herein can also apply to electronic blasting systems used in various industries such as mining, engineering, building removal systems, etc. In general, these systems are similar to wellbore perforating systems in the use of a communication system that can selectively control the detonation of one or more charges. For example, in the mining industry, the electronic detonators are used to fire the charges, and the electronic detonators can be programmable to achieve a desired firing sequence. The electronic detonators can be in communication with logging and control equipment over a communication link. In order to implement a desired blast design and initiate a blast according to that design, the various components of the system can communicate with each other over the communication links as required. The communication link can be wireless or wired, for example using wires, plugs, connectors, adaptors, and the like. When using wired communications, the environments in which the communication links are used can result in loss. For example, in mining applications, the communication link can pass through wet environments having varying temperatures and obstacles. The obstacles can result in damage to the wires and/or connectors, thereby presenting problems with communication link. This can result in the communication link suffering from loss and communication difficulties.

(21) An object of the present description is to provide a system that accounts for and overcomes the challenges of communicating over lossy, long and distorted communication channels or links like wireline, E-slickline and E-coil tubing in hydrocarbon wells, and communication links in mining and engineering uses.

(22) Also provided is a method for compensating the communication frequencies used to match the change in reference time base of a device (e.g., downhole device, mining device, etc.) due to temperature effects. As the number of devices or end units (e.g., downhole device, mining device or detonators, etc.) used increases, the amount by which the communication unit (e.g., surface communication unit, control unit, etc.) has to accommodate a deviation in the frequencies used also increases. The present communication system provides a solution to this by measuring the time base of the received responses from the end units and then adjusting the surface communication time base to match that of each end device. The term frequency scaled shift keying is introduced to distinguish it from other used digital modulation schemes such as frequency shift keying. In this scheme the mark and space frequencies are both shifted by the same percentage as the end unit time base has shifted.

(23) Each communication channel acts like a filter attenuating different frequencies at various levels. Most end units (e.g., wireline, E-slickline, E-coil units, etc.) act as a low pass filter. The transition boundary between a mark and space frequency and vice versa is also affected due to the channel characteristics. To overcome this, a method of changing the amplitude of the waveform at

the transition boundary is employed to reduce or nullify these effects. This technique of wave shaping along with the technique of frequency scaling applied at the transition boundary allows for a significant improvement in communication system reliability.

(24) While the systems and method described herein are described in terms of a wellbore environment, the same systems and methods can apply to other uses and industries such as the mining and engineering industries. For example, communication with downhole units is equivalent to communication with end units in mining such as programmable detonators and/or sensors. In addition, the form factor for the end units and communication equipment may be different, but the same communication and operating principles described herein still apply.

(25) Just as the downhole communication from the surface to the downhole device gets affected due to long cables so does the communication from the downhole to the surface get affected. To overcome that a wave shaping technique is used to vary the amplitude of the current Manchester at the transition boundaries. Waveform shaping using Manchester encoding provides for a robust uplink system that is not affected by the cable impedance or characteristics.

(26) Also provided is a method for checking these devices in a tool string before lowering the tool string into a wellbore comprising the steps of sending a signal to one or more control units located on the devices in the tool string; identifying the status of each control unit; and processing the signal with the appropriate commands. The status or payload of one or more devices located in the tool string is controlled when the device processes a valid signal and a signal validating action is returned from the control unit.

(27) Also provided is a communication system that allows both serial and parallel control of downhole devices including tractors, auxiliary tractor tools, well logging tools, release mechanisms, and sensors. The advantage of parallel control is that individual devices can be interrogated without going through a series path, thereby being more accessible. Each tool in the parallel arrangement has a control unit that carries a tool identifier (ID) as part of its uplink communication.

(28) Another embodiment of the communication system allows for uplink communication from a downhole device while shooting power is applied from a surface control unit. When high voltage and current are applied from the surface it is quite challenging to receive small signals from the downhole unit. The use of the uplink communication wave shaping technique is utilized to overcome this shortcoming.

(29) Also provided is a system for bi-directional communication with other devices such as selectively fired perforating guns, setting tool, pressure sensing tool, Gamma-Ray, Digital CCL, release devices, and downhole sensors. It features a system to select and fire specific guns in a perforating string. The downhole device may or may not have a unique addressing mechanism.

(30) Referring now to FIG. 1, a diagram of an example system **100** is shown in accordance with aspects of the disclosure. The system **100** is representative of a hydrocarbon drilling implementation of the disclosure. However, as discussed above, the teachings of the disclosure are equally applicable to other implementations, such as mining, demolition, fireworks detonation, remote release mechanisms, etc. The system **100** includes a control system **102**, a remote device **104**, and a downstream device **106**. The control system **102** is, in some examples, implemented on a vehicle, such as a vehicle that includes a wireline **108** on which the remote device **104** and the downstream device **106** are disposed. Although the system **100** illustrates only one remote device **104** and one downstream device **106**, in various examples the system may include any number of remote devices **104** and/or downstream devices **106** disposed in any arrangement along the wirelines **108**.

(31) In at least some examples, the control system **102** is configured to provide power and/or a control signal to the downstream device **106**. The remote device **104** is disposed on the wireline **108** in series between the control system **102** and the downstream device **106** and is configured to selectively block, or permit, the power and/or control signal provided by the control system **102**

from reaching the downstream device **106**. As discussed above, in at least some examples, an operating frequency of the remote device **104** varies from a frequency of data transmission of the control system **102**. In such examples, the control system **102** may determine the operating frequency of the remote device **104** and match or synchronize a frequency of the control signal transmitted by the control system **102** to the remote device **104**. For example, the control system **102** may receive a signal from the remote device **104** and measure a time base of the received signal. When the time base of the received signal varies from a time base of the control system **102**, the control system **102** may modify its time base to match or synchronize with the time base determined from the received signal. For example, the control system **102** may perform term frequency scaled shift keying (FSSK) to shift mark and space frequencies of the FSK control signal based on the detected time base variance of the received signal.

(32) Further, in at least some examples, communication channels, such as the wireline **108**, can include characteristics that cause the communication channels to function in part as a filter, such as a low pass filter. This filtering behavior may attenuate the control signal transmitted by the control system **102** to the Manchester remote device **104**, degrading communication between the control system **102** and the remote device **104**. For example, transition boundaries between marks and spaces of the FSK control signal may be altered by the filtering of the wireline **108**. To compensate for and reduce the effect of this alteration, in some examples, the control system **102** modifies the amplitude of the control signal.

(33) The remote device **104**, in at least some examples, receives a power signal from the control system **102**. The power signal, in some examples, includes the control signal, encoded according to FSK, superimposed on the power signal. In some examples, the power signal is an alternating current (AC) signal. In other examples, the power signal is a direct current (DC) signal of positive or negative polarity (e.g., such that the remote device **104** is power signal polarity agnostic). At least some implementations of the remote device **104** are configured to detect the control signal and convert the control signal to a square wave data signal. The control signal, and the resulting data signal, may include a plurality of binary data bits. Based on look-up tables or other programming of the remote device **104**, the remote device **104** may control one or more switches to permit, or deny, power received by the remote device **104** from the control system **102** to pass to the downstream device **106** via the wireline **108**. In some examples, the remote device **104** may further transmit control signals to, or receive signals from, the downstream device **106**. In yet further examples, the remote device **104** may determine sensor feedback, such as voltage and/or temperature feedback. The remote device **104** may generate a response signal and transmit the response signal via the wireline **108** to the control system **102**. For example, the remote device **104** may encode the response signal onto the wireline **108** via Manchester encoding, such as described in Institute of Electrical and Electronics Engineers (IEEE) standard 802.3, which is incorporated herein by reference. Manchester encoding, as described in IEEE 802.3, is a return to zero communication protocol in which a binary 1 is represented by a high to low transition in a signal and a binary 0 is represented by a low to high transition in the signal. Other forms of Manchester encoding may represent a binary 1 as a low to high transition in a signal and a binary 0 as a high to low transition in the signal.

(34) In at least some examples, the system **100** also includes a test system **110**. The test system **110**, in some examples, is configured to test functionality of the remote device **104**. The test system **110** operates substantially similar to the control system **102**, but at lower voltages, and is discussed in greater detail below.

(35) Referring now to FIG. 2, an example schematic diagram of the control system **102** is shown in accordance with aspects of the disclosure. In at least some examples, the control system **102** is referred to as a surface communication unit. The control system **102**, in at least some examples, includes a power source **202**, a power supply **204**, an inductor **206**, a capacitor **207**, a transformer **208**, an amplifier **210**, a digital-to-analog converter (DAC) **212**, a microcontroller **214**, an

input/output (I/O) interface **216**, a resistor **218**, a differential amplifier **220**, a current limit circuit **222**, a fuse **224**, and a voltage feedback circuit **226**. In at least some implementations of the control system **102**, the current limit circuit includes a plurality of transistors, such as NPN transistors, that drop voltage across each of the transistors as current flowing through the transistors increases. The voltage feedback circuit **226**, in some examples, includes a voltage divider followed by a buffer such that an output signal of the voltage feedback circuit **226** is a scaled representation of an input signal of the voltage feedback circuit **226**. In an example architecture of the control system **102**, the power source **202** is coupled to the power supply **204**. The inductor **206** is coupled between the power supply **204** and a node **228**. The capacitor **207** is coupled between the node **228** and a second winding of the transformer **208**. The resistor **218** is coupled between the node **228** and a node **230**. The current limit circuit **222** and the fuse **224** are coupled in series between the node **230** and a node **232**. The voltage feedback circuit **226** is coupled to the node **232**. The node **232** is, in some examples, an I/O node or terminal of the control system **102**. In at least some examples, the control system **102** couples to the wirelines **108** at the node **232**. The differential amplifier has a first input coupled to the node **228**, a second input coupled to the node **230**, and an output coupled to the microcontroller **214**. The microcontroller **214** is further coupled to the I/O interface **216**. Although only one I/O interface **216** is shown in FIG. 2, in various examples the microcontroller **214** may couple to any number of I/O interfaces **216**, such as graphical user interfaces, user input devices, communication devices such as Universal Serial Bus communication interfaces, etc. The microcontroller **214** is further coupled to the DAC **212**, which has an output coupled to an input of the amplifier **210**. The amplifier **210** has an output coupled to a first winding of the transformer **208**. Although not shown in FIG. 2, in at least some examples, an output of the voltage feedback circuit **226** is coupled to an input of the microcontroller **214**. In other examples, the output of the voltage feedback circuit **226** is coupled to any suitable component for monitoring voltages in, or operation of, the control system **102**.

(36) In an example of operation of the control system **102**, a power signal is provided by the power source **202** to the power supply **204**. The power source **202**, in at least some examples, provides power in a voltage range of about 12 V to about 18 V to the power supply **204**. The power supply **204** is, in some examples, a power converter that increases or decreases a voltage of the power received from the power source **202**. For example, in at least some implementations the power supply **204** is a boost power converter that boosts or increases the received voltage in the range of about 12 V to 18 V to a range of about 20 V to 70 V based on configuration of the power supply **204**. In other examples, the power supply **204** may increase, or decrease, the voltage to any suitable value in any suitable range for a use case of the control system **102**. In at least some examples, a voltage output by the power supply **204** may be determined at least in part according to voltage needs of a remote device or downstream device with which the control system **102** will communicate (e.g., such as the remote device **104** and/or the downstream device **106**, each of FIG. 1) and/or a length of a wireline (and therefore voltage losses associated with the wirelines) over which the control system **102** will communicate with the remote device or downstream device.

(37) The microcontroller **214**, based at least in part on an input signal received via the I/O interface **216** and/or the differential amplifier **220**, generates a data output signal and transmits that data output signal in a digital domain (e.g., as a series of discreet data bits) to the DAC **212**, which converts that data output signal into an analog domain (e.g., as a sinusoidal, or sine, wave) and transmits the data output signal to the amplifier **210**. The data output signal is, in some examples, a signal for interacting with a remote device such as the remote device **104** and/or the downstream device **106**, each of FIG. 1. The data output signal may include an address of a device (or devices) to which the data output signal is addressed and one or more commands for the device(s). The amplifier **210** receives the data output signal and amplifies a value of the data output signal. In some examples, the amplifier **210** is a current amplifier that increases a value of the data output signal prior to providing the data output signal to a first winding of the transformer **208**. The sine

wave, in some examples, has a frequency and an amplitude that is programmable, such as by altering operating characteristics of the microcontroller **214**, the DAC **212**, and/or the amplifier **210**.

(38) The transformer **208** is configured as an impedance matching transformer to adapt to match an impedance at an output of the amplifier **210** to an impedance present at the node **228**. A turns ratio of the first winding of the transformer **208** to the second winding of the transformer **208** is configured to match the impedance at the output of the amplifier **210** to the impedance present at the node **228** and determines a voltage of the data output signal as output by the second winding of the transformer **208**. The capacitor **207** is a coupling capacitor that couples the data output signal output by the transformer **208**, as an AC signal, to the node **228** while blocking any DC component of the data output signal. The data output signal as provided at the node **228** is, in some examples, referred to herein as a control signal and is imposed on a power signal, as described above with respect to FIG. 1. The inductor **206**, in at least some examples, prevents or blocks the control signal, based on the AC nature of the control signal, from flowing to the power supply **204** and potentially damaging or altering operation of the power supply **204**.

(39) The control signal is superimposed on the voltage output by the power supply **204** and flows through the resistor **218**. A voltage drop occurs between the node **228** and the node **230** due to an impedance of the resistor **218**. Accordingly, in at least some implementations, the resistor **218** is referred to as a current viewing resistor. The difference in voltages present at the node **228** and the node **230** is sensed by the differential amplifier **220** and provided to the microcontroller **214** as feedback. The microcontroller **214** may use the feedback for any suitable purpose, such as determining whether the control system **102**, or any of its components are operating properly.

(40) The current limit circuit **222** is configured to monitor a current flowing from the node **230** to the node **232** to determine whether a value of the current exceeds a safe level for one or more other devices coupled to the control system **102**, such as the remote device **104** and/or the downstream device **106**, each of FIG. 1. The fuse **224** is similarly configured to respond to a current flowing through the fuse **224** exceeding a rated value for the fuse **224** by creating an open circuit, or electrical disconnection, in the control system **102** in place of the fuse **224**. The voltage feedback circuit **226**, in at least some examples, monitors the node **232** to provide feedback indicating a voltage that is present at the node **232**. The feedback, in some examples, indicates whether the control system **102** is operating properly.

(41) As discussed above, in at least some examples, the control signal is encoded according to FSK. For example, a first portion of the control signal that represents a value of digital logic “1” or high value has a first frequency and a second portion of the control signal that represents a value of digital logic “0” or low value has a second frequency. In at least one implementation of the control system **102**, the first frequency is about 5500 Hertz (Hz) and the second frequency is about 3000 Hz. In such an example, the control signal has a baud rate of about 500 bits/second, or a bit time of about 2.0 milliseconds. In at least some examples, a device receiving the control signal is configured to communicate and/or operate at a substantially same frequency as the control system **102** and the control signal. However, as discussed above, in some circumstances the control system **102** may be in communication with a device, such as the remote device **104** of FIG. 1, that may be operating at a different frequency as a result of environmental conditions (such as temperature) surrounding the device. In such an example, an oscillator crystal of the device may slow, resulting in a decrease in operating frequency of the device. This decrease in operating frequency may introduce errors into communication between the control system **102** and the device, such that the device misinterprets the control signal.

(42) To compensate for this variation in frequency, the control system **102** may measure a time base of a signal received from the device. For example, the control system **102** may determine the time base of the signal received from the device based on feedback provided to the microcontroller **214** by the differential amplifier **220** based on changes in voltage detected across the resistor **218**.

The microcontroller **214** may compare the detected time base to an expected or programmed time base and determine whether a variation exists between the detected time base and the expected or programmed time base. When a variation exists, the microcontroller **214** may modify generation of the data output signal to cause the control signal as provided at the node **228** to be at a frequency synchronized (e.g., approximately the same as) the operating frequency of the device. In at least some examples, the microcontroller **214** modifies generation of the data output signal, or generates the data output signal, according to FSSK.

(43) Further as discussed above, in at least some examples losses can occur in the control signal during transmission over a wireline of certain length. For example, a wireline of certain length may function effectively as a low pass filter from a perspective of the control signal. When the control signal is at low frequency, such as about 3000 Hz, as discussed above, the control signal may have a greater amount of energy than when the control signal is a high frequency, such as about 5500 Hz, also as discussed above. At a transition boundary, such as when the control signal changes from about 3000 Hz to about 5500 Hz to indicate a change in value from a digital logic low to a digital logic high, an amplitude of the 5500 Hz control signal following the transition boundary may be attenuated. This attenuation can distort the control signal and adversely affect receipt, interpretation, and/or processing of the control signal by a device receiving the control signal. To compensate for, or mitigate, the attenuation, the control system **102** can provide a pre-emphasis on the control signal following a transition boundary from about 3000 Hz to about 5500 Hz. In various examples, the pre-emphasis is applied for any number of cycles of the control signal following the transition boundary. For example, as a capacitance of the wirelines increases (such as in a multi-conductor cable), the attenuation described above may also increase. Therefore, as capacitance of the wireline increases, so too may the number of cycles of the control signal following the transition boundary for which pre-emphasis is applied. In at least one implementation, the pre-emphasis is applied for two cycles following the transition boundary.

(44) The pre-emphasis increases an amplitude of the control signal following the transition boundary from about 3000 Hz to about 5500 Hz for a period of time that the control system **102** applies the pre-emphasis, thus compensating for, or negating, losses associated with the wireline over which the control system **102** transmits the control signal. For example, the microcontroller **214** may increase a value of the digital output signal provided to the DAC **212** for an amount of time, a number of cycles, or any other suitable timeframe for which the control signal will include the pre-emphasis. In at least some examples, the microcontroller **214** also modifies generation and output of the digital output signal to perform wave shaping that varies a wave shape of the control signal from that of a pure sinewave. An example of a control signal having pre-emphasis as described herein is shown in FIG. **3** in which signal component **302** is a component of the control signal having the frequency of about 3000 Hz and signal component **304** is a component of the control signal having the frequency of about 5500 Hz. As illustrated in FIG. **3**, the signal component **304** includes pre-emphasis for between about 1 to about 5 cycles, or about 2 cycles or periods of the control signal. However, in other examples, the signal component **304** may include the pre-emphasis for any number of cycles or periods of the control signal as determined by the control system **102** or programmed by a user.

(45) Returning to FIG. **2**, in at least some examples, the control system **102** is modified to create the test system **110**. In at least some examples, the test system **110** is referred to as a surface check system. In implementations of the control system **102** modified to form the test system **110**, the power source **202** may be implemented as a battery, for example, to facilitate portability and to provide a limited amount of power, such as may be insufficient to detonate an explosive device with which the test system **110** communicates. The power supply **204** may be programmed to provide no more than a preset amount of current, such as, in some examples, about 15 milliamps. The current limit circuit **222** may be implemented as a pair of redundant, series-connected current limit and trip circuits. The current limit and trip circuits, in at least some examples, an integrated

circuit or other component that measures a voltage drop, such as across a resistor, and generates an output signal that controls a switch. The output signal may become asserted when the integrated circuit determines based on the measured voltage drop that a current flowing through the current limit and trip circuit has exceeded a programmed value. The switch, when activated based on the asserted output signal, changes states to prevent the excessive current from flowing out from the test system **110**. In this way, the test system **110** may be safely used to test live explosives, or other potentially dangerous devices, in a safe manner resulting at least partially from the current limit and trip circuits preventing current sufficient to trigger the dangerous devices from detonating or otherwise disadvantageously activating. In at least some examples, the test system **110** includes multiple redundant safety measures such that it has no single failure point that, if failed, would allow an uncontrolled amount of current to pass out from the test system **110**.

(46) Referring now to FIG. 4, a diagram of an example state machine **400** is shown in accordance with aspects of the disclosure. In at least some examples, the state machine **400** is implemented by the control system **102**, such as by the microcontroller **214**, as discussed elsewhere herein. The state machine **400** is implemented to, in some examples, synchronize a frequency of a control signal provided by the control system **102** to an operating frequency of the a device receiving the control signal, and communicate with the device to provide data to the device and receive data from the device.

(47) At state **402**, the control system **102** is powered-on and initialized. In at least some examples, the state machine **400** controls the control system **102** to perform a self-test to verify functionality of the control system **102**. When an aspect of state **402** fails (POWERUP\_FAIL), such as a failure to power-on, an initialization failure, or a self-test failure, in at least some examples, the state machine **400** remains at, and repeats at least a portion of functions of, the state **402**. When the functions of the state **402** are successfully executed (POWERUP\_DONE), the state machine **400** proceeds to state **404**.

(48) At state **404**, the state machine **400** receives a command for execution by the control system **102**, such as via the state machine **400**. The command is received, in some examples, from a user via an I/O interface, such as the I/O interface **216** discussed above. The command may be a command to synchronize the control system **102** to an operating frequency, or communication time base, of a remote device with which the control system **102** is communicatively coupled (e.g., such as the remote device **104** and/or the downstream device **106**, as discussed above with respect to FIG. 1). In other examples, the command may be for a remote device to control a switch to open to facilitate a flow of power, or close to inhibit a flow of power, along a wireline. In yet other examples, the command may be any suitable command for an application environment of the control system **102**. When no command is received at state **404** (SAME\_STATE), the state machine **400** remains at state **404** and awaits a command. When a valid command is received at state **404** (CMD\_RECEIVED), the state machine **400** proceeds to state **406**.

(49) At state **406**, the state machine **400** modifies the command received at the state **404** to generate a control signal. The control signal is, in some examples, an FSK encoded signal generated based on the command received at the state **404**. In some examples, to generate the control signal the state machine **400** applies a scaling factor to a FSK encoded signal generated by the microcontroller **214** according to the command received at the state **404**. The scaling factor, in at least some examples, compensates for variation in communication frequency of the control system **102** and operating frequency of the remote device with which the control system **102** is communicatively coupled. In some examples, the state machine **400** obtains the scaling factor from a storage location, such as a memory coupled to the microcontroller or a memory of the microcontroller **214**. The storage location is, in some examples, a volatile memory such that data stored in the storage location is lost when the control system **102** is power cycled. In other examples, the storage location is a non-volatile storage location such that data stored in the storage location is not lost when the control system **102** is power cycled and instead persists until removed

or overwritten.

(50) When the scaling factor is not stored in the storage location, the state machine **400** transmits a FSSK command to the remote device with which the control system **102** is communicatively coupled. The FSSK command, in at least some examples, is a calibration command instructs the remote device to return a response to the control system **102** for the control system **102** to use for communication frequency or other calibration. The control system **102** determines a time base, or frequency, of the response and compares that to either an expected value, a programmed value, or a default value of the control system **102**. When the time base, or frequency, of the response does not match the expected, programmed, or default value, the state machine **400** determines the scaling factor and stores the scaling factor in the storage location. For example, when the state machine **400** determines that the time base, or frequency, of the response varies from the expected, programmed, or default value by -5%, the state machine **400** may store a scaling factor of 0.95. Similarly, when the state machine **400** determines that the time base, or frequency, of the response varies from the expected, programmed, or default value by +5%, the state machine **400** may store a scaling factor of 1.05.

(51) In at least some examples, at state **406** the state machine **400** further modifies an amplitude of the control signal. For example, the state machine **400** may apply pre-emphasis to the control signal, increasing an amplitude of the control signal for a programmed number of periods of the control signal to compensate for transmission losses associated with a communication channel through which the control system **102** and the remote device are coupled. The processing of the control signal performed at state **406**, in at least some examples, conditions the control signal for transmission via the communication channel through which the control system **102** and the remote device are coupled. Conditioning the control signal, in at least some examples, provides compensation in the control signal for effects of transmitting the control signal, such as via the communication channel and/or to the remote device. When the control signal is not yet generated, scaled, and shaped (e.g., based on the application of pre-emphasis), the state machine **400** remains (SAME\_STATE) at the state **406**. When the control signal is generated and scaled and/or shaped as determined by the state machine **400** to be advantageous, the (FSK\_SCALED), the state machine **400** proceeds to state **408**.

(52) At state **408**, the control signal is transmitted to the remote device via the communication channel through which the control system **102** and the remote device are coupled. In at least some examples, the communication channel is a wireline. The control signal is transmitted, in some examples, by the control system **102** superimposing the control signal over an AC or DC power signal being provided to the remote device via the communication channel. When the control signal is not yet transmitted, the state machine **400** remains (SAME\_STATE) at the state **408**. When the control signal has been transmitted (FSK\_TRANSMITTED), the state machine proceeds to state **410**.

(53) At state **410**, the state machine receives a response from the remote device via the communication channel through which the control system **102** and the remote device are coupled. In at least some examples, the response is a Manchester encoded response, as described elsewhere herein. Based on the response, the state machine **400** may generate and output feedback for a user, such as to inform the user about a condition, state, or status of, or reported by, the remote device. When the state machine **400** has not yet received the response from the remote device, the state machine **400** remains (SAME\_STATE) at the state **410**. When the state machine **400** has received a response from the remote device, but the response has failed for some reason, the state machine **400** proceeds (FAIL\_RX) to the state **406**. In at least some examples, when the state machine **400** proceeds from the state **410** to the state **406**, the state machine **400** discards a scaling factor stored by the control system **102** and re-determines the scaling factor, as described above with respect to the state **406**. When the state machine **400** has successfully received and processed the response from the remote device, the state machine **400** proceeds (RESPONSE\_RX) to the state **404** and

awaits a next command.

(54) Referring now to FIG. 5, a block diagram of an example remote device **104** is shown in accordance with aspects of the disclosure. In at least some examples, the remote device **104** is referred to as a safety sub or a universal safety sub. The remote device **104**, in at least some examples, includes a rectifier **502**, a fuse **504**, a shunt **506**, a power supply **508**, a power supply **510**, a microcontroller **512**, an electrically erasable programmable read-only memory (EEPROM) **514**, a downlink circuit **516**, an uplink circuit **518**, a switch circuit **519**, an isolated drive circuit **520**, a switch circuit **521**, and an isolated drive circuit **522**. In at least some examples, the remote device **104** also includes one or more of a battery **524**, a sensor circuit **526**, a self-test circuit **528**, and/or a self-test circuit **530**.

(55) In an example architecture of the remote device **104**, the rectifier **502** is coupled between a terminal **532**, configured to couple to a conductor of the wireline **108**, and an armor, or sheathing, of the wireline **108** that functions as a chassis ground for the remote device **104**. The rectifier **502** has an output coupled through the fuse **504** to a node **534**. The shunt **506** is coupled between the node **534** and an earth ground. The power supply **508** has an input coupled to the node **534** and an output coupled to a node **536**. The power supply **510** has an input coupled to the node **536** and an output coupled to an input of the microcontroller **512**. In example of the remote device **104** that include the battery **524**, the power supply **510** may have a second input coupled to an output of the battery **524**. The EEPROM **514** is coupled bidirectionally to the microcontroller **512**. The downlink circuit **516** is coupled between the node **536** and another input of the microcontroller **512**. The uplink circuit **518** is coupled between an output of the microcontroller **512** and the node **536**. The switch circuit **519** and the switch circuit **521** are coupled in series between the terminal **532** and a terminal **538**. The isolated drive circuit **520** is coupled between another output of the microcontroller **512** and a control input of the switch circuit **519**. The isolated drive circuit **522** is coupled between another output of the microcontroller **512** and a control input of the switch circuit **521**. In examples of the remote device **104** that include the sensor circuit **526**, an output of the sensor circuit may be coupled to another input of the microcontroller **512**. In examples of the remote device **104** that include the self-test circuit **528**, the self-test circuit **528** is coupled between a node between the switch circuit **519** and the switch circuit **521** and another input of the microcontroller **512**. In examples of the remote device **104** that include the self-test circuit **530**, the self-test circuit **530** is coupled between the terminal **538** and another input of the microcontroller **512**.

(56) In an example of operation of the remote device **104**, a signal is received at the terminal **532**. The signal is, in some examples, a power signal having a control signal superimposed on the power signal. In at least some examples, the signal received at the terminal **532** may have a voltage of up to about 1800 V or greater. Such a voltage may be received, for example, from a firing power supply or other device, component, or circuit configured to provide a high-voltage on the wireline. By default, the switch circuit **519** and the switch circuit **521** are each configured to be open (e.g., normally open switches) to block the signal received at the terminal **532** from being passed to the terminal **538** without the microcontroller **512** permitting such signal passage. Thus, when the remote device **104** is not receiving power at the terminal **532**, the switch circuit **519** and the switch circuit **521** are each in an open state. The power signal is, in some examples, an AC signal. In other examples, the power signal is a DC signal.

(57) The rectifier **502** receives the signal and rectifies the signal. The rectifier **502** may be of any suitable architecture, the scope of which is not limited herein. For example, the rectifier **502** may be any of a half-wave, full-wave, or bridge rectifier. Generally, the rectifier **502** provides a rectified signal to the fuse **504** regardless of a polarity of the signal received at the terminal **532**. The fuse **504** is configured to prevent current exceeding a rating of the fuse **504** from damaging components of the remote device **104**, such as the microcontroller **512**. For example, the fuse **504** is configured to respond to a current flowing through the fuse **504** exceeding a rated value for the fuse **504** by

creating an open circuit, or electrical disconnection in the remote device in place of the fuse **504**. The shunt **506** is configured to provide a low impedance path to the earth ground from the node **534** to further protect components of the remote device **104**, such as the microcontroller **512**, from damage resulting from high current or high voltage being present at the node **534**. For example, the shunt **506** includes spark gaps that cause the fuse **504** to short in the event of an over voltage event and radio frequency (RF) circuitry to shunt RF waves that may be present at the terminal **532**, preventing those RF waves from passing through the remote device **104** to the terminal **538**.

(58) The power supply **508** is, in some examples, configured to reduce a voltage of a signal received by the power supply **508** to about 12 V. In other examples, the power supply **508** may be configured to provide an output voltage of any suitable or programmed value. The power supply **508** is, in various examples, capable of withstanding input voltages of up to about 1800 V and operating with input voltages as low as about 18 V. The power supply **508** may have a linear architecture, a switching architecture, or any other suitable architecture, the scope of which is not limited herein. The power supply **510** is, in some examples, configured to generate a voltage for use by the microcontroller **512**. In some examples, as will be used for discussion herein, that voltage is about 5 V. However, in other examples that voltage may be about 3.3 V, about 3 V, about 1.8 V, etc. In at least some examples, the power supply **510** is a linear power supply. In other examples, the power supply **510** has any suitable architecture, the scope of which is not limited herein.

(59) When the microcontroller **512** receives power from the power supply **510**, the microcontroller **512** powers on and queries the EEPROM **514** to determine a switch state for each of the switch circuit **519** and the switch circuit **521**. The switch state, in at least some examples, indicates whether the microcontroller **512** was most recently controlling the switch circuit **519** and the switch circuit **521** to be open or closed. The microcontroller **512** also queries an internal memory (not shown) of the microcontroller **512** for the switch state. When the internally stored switch state of the microcontroller **512** and the switch state as stored by the EEPROM **514** match, the microcontroller **512** provides control signals to the isolated drive circuit **520** and the isolated drive circuit **522** to return the switch circuit **519** and the switch circuit **521**, respectively, to their prior switch state. After providing the control signals, the microcontroller **512** may wait to receive a command from the downlink circuit **516**, as will be further discussed below. When the internally stored switch state of the microcontroller **512** and the switch state as stored by the EEPROM **514** do not match, the microcontroller **512** provides control signals to the isolated drive circuit **520** and the isolated drive circuit **522** to maintain the switch circuit **519** and the switch circuit **521**, respectively, in an open state. Further, when the internally stored switch state of the microcontroller **512** and the switch state as stored by the EEPROM **514** do not match, the microcontroller may transmit a response message to a control system, such as the control system **102** via the wirelines **108**, each of FIG. 1, through the uplink circuit **518**, as will be further discussed below, informing the control system of the mismatched switch states and/or actions taken by the microcontroller **512**.

(60) Based on the control signals received from the microcontroller **512**, the isolated drive circuit **520** and the isolated drive circuit **522** control the switch circuit **519** and the switch circuit **521**, respectively. In at least some examples, the switch circuit **519** and the switch circuit **521** each include field-effect transistors, such as n-channel silicon-carbide metal oxide semiconductor field-effect (NMOS) transistors implemented as switches. In other examples, the field-effect transistors are of silicon, silicon-on-insulator, gallium-nitride, or any other suitable construction, process, chemistry, or process technology. Each of the switch circuit **519** and the switch circuit **521** may include a pair of back to back coupled NMOS transistors, controlled from a common control source such as the isolated drive circuit **520** and the isolated drive circuit **522**, respectively, to facilitate bi-directional flow of current through the switch circuit **519** and the switch circuit **521**. To cause current to flow through an NMOS transistor, a value of a signal present at a gate terminal of the NMOS transistor must exceed a voltage present at a source terminal of the NMOS transistor by a

threshold amount. Thus, to turn on the switch circuit **519** and the switch circuit **521**, in some examples, the isolated drive circuit **520** and the isolated drive circuit **522** are required to provide a voltage at the gate terminals of the NMOS transistors of the switch circuit **519** and the switch circuit **521**, respectively, that is greater in value than a signal that is, or will be, present at the source terminals of the NMOS transistors of the switch circuit **519** and the switch circuit **521**. However, as discussed above, the wireline may carry high voltages of up to about 1800 V, or more. Therefore, in some circumstances, the isolated drive circuit **520** and the isolated drive circuit **522** may be required to provide a voltage greater than 1800 V at the gate terminals of the NMOS transistors of the switch circuit **519** and the switch circuit **521**, respectively, to turn on the NMOS transistors and therefore turn on the switch circuit **519** and the switch circuit **521**. Because the microcontroller operates at a voltage of 5 V, and therefore drives the isolated drive circuit **520** and the isolated drive circuit **522** with a control signal having a value of no more than approximately 5 V, challenges can sometimes arise in the isolated drive circuit **520** and the isolated drive circuit **522** controlling the switch circuit **519** and the switch circuit **521**, respectively, to turn on.

(61) Referring now to FIG. **6**, a block diagram of an example isolated drive circuit is shown in accordance with aspects of the disclosure. In at least some examples, the isolated drive circuit is suitable for implementation as the isolated drive circuit **520** and/or the isolated drive circuit **522**, each of FIG. **5**. Accordingly, for description the isolated drive circuit of FIG. **6** will be described with reference to the isolated drive circuit **520**. However, the isolated drive circuit **520** may be substantially similar in architecture and operation to the isolated drive circuit **522**. In at least one example, the isolated drive circuit **520** includes a driver **602**, a transformer **604**, a rectifier **606**, and a protection circuit **608**. As discussed above, isolated drive circuit **520** is configured to couple between the microcontroller **512** and the switch circuit **519** to control the switch circuit **519** based on a control signal received from the microcontroller **512**. The switch circuit **519**, in at least some examples, includes a NMOS transistor **610** and a NMOS transistor **612**.

(62) In an example of the isolated drive circuit **520**, the driver **602** has an input configured to receive a control signal from the microcontroller **512** and an output coupled to a first winding of the transformer **604**. A second winding of the transformer **604** is coupled to the rectifier **606**. In at least some examples, the transformer **604** is an isolation transformer having a winding ratio of 1:1.2 such that an output voltage of the transformer is approximately equal to an input voltage of the transformer. The rectifier **606** is configured to rectify a voltage provided by the second winding of the transformer **604** with reference to a voltage present at a node **614**. For example, when the voltage present at the node **614** is X and an output voltage of the transformer **604** is Y, the rectifier **606** outputs a voltage approximately equal to X+Y volts, minus any losses associated with a critical path of the rectifier **606** (such as diode loss(es), etc.). Each of the NMOS transistor **610** and the NMOS transistor **612** have their source terminals coupled to the node **614**. Therefore, when a rectified signal provided at an output terminal of the rectifier **606**, which is coupled to gate terminals of the NMOS transistor **610** and the NMOS transistor **612**, is approximately Y volts greater than a voltage present at the source terminal of the NMOS transistor **610** and the NMOS transistor **612**. When Y volts is greater than a gate-to-source voltage threshold of the NMOS transistor **610** and the NMOS transistor **612**, the NMOS transistor **610** and the NMOS transistor **612** turn on and conduct current. Therefore, the arrangement of the rectifier **606**, in at least some examples, mitigates at least some challenges associated with controlling the switch circuit **519** based on a 5 V control signal output by the microcontroller **512**, as discussed above with respect to FIG. **5**.

(63) In at least some examples, the protection circuit **608** is coupled between the output terminal of the rectifier **606** and the node **614**. The protection circuit **608**, in at least some examples, is any circuit or component suitable for protecting the NMOS transistor **610** and the NMOS transistor **612** from damage resulting from overvoltage or overcurrent signals being provided to their respective gate terminals.

(64) In some examples, the driver **602** is instead implemented as an open drain transistor configured to drive the transformer **604**. In other examples, the driver **602** is omitted and the transformer **604** is driver directly by the microcontroller **512**. In some examples, the transformer **604** may be an iron core or air core transformer operating in forward mode or fly back mode. In other examples, the transformer may be implemented via metal traces on a di-electric substrate with the di-electric substrate as coupling for the transformer. In yet other examples, a voltage multiplier, charge pump, inductive coupler, or other suitable component may be used in place of, or in conjunction with, the transformer **604**.

(65) Returning again to FIG. 5, the downlink circuit **516** monitors the node **536** to receive the control signal and provide data included in the control signal to the microcontroller. For example, the downlink circuit **516** may detect the FSK or FSSK encoded pattern of the control signal and convert the FSK or FSSK encoded pattern to a series of binary data bits. The downlink circuit **516** may provide the binary data bits to the microcontroller **512** and the microcontroller **512** may interpret the binary data bits as a command to be executed, based on a programmed routine, function, application, firmware, or other executable code of the microcontroller **512**. The downlink circuit **516** may detect the FSK or FSSK encoded pattern of the control signal and convert the FSK or FSSK encoded pattern to a series of binary data bits according to any suitable process and via any suitable hardware architecture, the scope of which is not limited herein.

(66) Similarly, the microcontroller **512** may output a plurality of binary data bits to the uplink circuit **518**. Based on the binary data bits, the uplink circuit **518** may modify a load placed on the node **536**, which is reflected in a value of a load present at the terminal **532** and is visible by a control system, such as the control system **102** of FIG. 1, by viewing a change in voltage across a resistor, such as the resistor **218** of FIG. 2. The uplink circuit **518** may modify the load placed on the node **536**, in at least some examples, according to Manchester encoding such that the control system may detect and view a Manchester encoded pattern on a wireline coupled to the terminal **532**. In other examples, the uplink circuit **518** may modify the load placed on the node **536**, in at least some examples, according to any suitable encoding scheme. In various examples, the uplink circuit **518** may have any hardware architecture suitable for implementing an encoding scheme implemented by the uplink circuit **518**. The uplink circuit **518** modifying the load by modulating a current present on the wireline by an amount in a range of about 25 milliamps to about 100 milliamps.

(67) As discussed above with respect to the control system **102**, losses may occur in transmission between a control system and a remote device, such as the remote device **104**. To compensate for, or mitigate, these losses, the uplink circuit **518** may have multiple operation modes. For example, the uplink circuit **518** may include a normal operation mode and a pre-emphasis operation mode. Other examples of the uplink circuit **518** may omit the pre-emphasis operation mode. The pre-emphasis operation mode may increase a load placed on the node **536** when compared to a load placed on the node **536** during the normal operation mode. The pre-emphasis compensates for losses in a manner similar to the pre-emphasis described above with respect to the control system **102**. An example of Manchester encoded waveforms having pre-emphasis as described herein are shown in FIG. 7. As shown in FIG. 7, the waveform **702** is representative of a logic signal having a **00**, the waveform **704** is representative of a logic signal **10**, the waveform **706** is representative of a logic signal **01**, and the waveform **708** is representative of a logic signal **11**. As further shown in FIG. 7, the pre-emphasis applied to the Manchester encoding, in at least some examples, is applied for about 10% of an asserted time for a data bit following a boundary transition.

(68) Returning again to FIG. 5, as discussed above, some examples of the remote device **104** include a battery **524**. In such examples, the battery **524** provides power to the power supply **510** in the absence of a power signal being received at the terminal **532**. The power supply **510** in turn provides power to the microcontroller **512** enabling a clock of the microcontroller **512** to remain operational. When the timer reaches a predetermined value, such as a predetermined amount of

time since a last timer reset, which may occur each time a valid command is received by the remote device **104** (or at any other suitable time), the microcontroller **512** may enter a battery timer state. When the microcontroller **512** enters the battery timer state, the microcontroller **512** may shutdown the remote device **104**, controlling the isolated drive circuit **520** and the isolated drive circuit **522** to control the switch circuit **519** and the switch circuit **521**, respectively, to open and saving a switch state of open for each of the switch circuit **519** and the switch circuit **521** to the internal memory of the microcontroller **512** and the EEPROM **514**.

(69) Also as discussed above, some examples of the remote device **104** include a sensor circuit **526**. The sensor circuit **526** may include, or be coupled to, any suitable sensors such as temperature sensors and/or voltage sensors. The microcontroller **512** may received data from the sensor circuit **526** and act on the received data, either by transmitting the received data to a control system via the uplink circuit **518**, as discussed above, or by controlling the switch circuit **519** and the switch circuit **521** at least partially based on the received data. Also as discussed above, some examples of the remote device **104** include a self-test circuit **528**, and/or a self-test circuit **530**. In at least some examples, the self-test circuit **528**, and the self-test circuit **530** are each of any suitable architecture for detecting a voltage having a value up to about 1800 V and reporting a result of that detection to the microcontroller in a voltage range between 0 V and about 5 V.

(70) Referring now to FIG. **8**, a diagram of an example state machine **800** is shown in accordance with aspects of the disclosure. In at least some examples, the state machine **800** is implemented by the remote device **104**, such as by the microcontroller **512**, as discussed elsewhere herein. The state machine **800** is implemented to, in some examples, to receive commands from a control system for controlling one or more switch circuits, control the switch circuits, and transmit response messages to the control system.

(71) At state **802**, when power is applied to the microcontroller **512**, the state machine **800** reads switch states from the EEPROM **514** and the internal memory of the microcontroller **512**. When the switch states read from the EEPROM **514** and the internal memory of the microcontroller **512** do not match or are otherwise unavailable or invalid, the state machine **800** proceeds

(POWERUP\_FAIL) to state **804** and remains at state **804** until being power cycled. When the switch states read from the EEPROM **514** and the internal memory of the microcontroller **512** match, the state machine **800** controls the isolated drive circuit **520** and the isolated drive circuit **522** to control the switch circuit **519** and the switch circuit **521**, respectively, to place the switch circuit **519** and the switch circuit **521** in the read switch state and then proceeds (POWERUP\_DONE) to state **806**. Alternatively, if the state machine **800** determines that a timer has expired while the microcontroller **512** is on battery power, the state machine **800** proceeds (BATT\_TIMER) to state **808** at which a programmed action is performed. In at least some examples, that programmed action is a safe shutdown of the remote device **104** in which the switch circuit **519** and the switch circuit **521** are each controlled to open. In at least some examples, the state machine **800** remains at state **808** until power other than battery power is again applied to the microcontroller **512**.

(72) At state **806**, the state machine **800** waits to receive a tool identifier. The tool identifier is, in some examples, an identifier of a downstream tool to which the remote device **104** is blocking the transfer of power from the control system. The tool identifier is received, in some examples, from the downlink circuit **816** based on a FSK or FSSK encoded control signal received from a control system and decoded by the downlink circuit **516** to binary bits that are provided to the microcontroller **512** and state machine **800**. When the tool identifier is invalid, the state machine **800** remains (SAME\_STATE) at the state **806**. When the tool identifier is valid, the state machine **800** proceeds (VALID\_MESSAGE) to state **810**.

(73) At state **810**, the state machine **800** waits to receive a command. The command is, in some examples, a command to provide power to the tool identified by the tool identifier. In other various examples, the command is any suitable command for which the microcontroller **512** and/or state

machine **800** are programmed. The command is received, in some examples, from the downlink circuit **516** based on a FSK or FSSK encoded control signal (either the same control signal as at state **808** or a new control signal) received from the control system and decoded by the downlink circuit **516** to binary bits that are provided to the microcontroller **512** and state machine **800**. When no command has yet been received, the state machine **800** remains (SAME\_STATE) at the state **810**. When the command is invalid, the state machine **800** controls the uplink circuit **518** to transmit a response to the control system indicating that an invalid command was received and then proceeds (INVALID\_COMMAND) back to the state **808**. When the command is valid, the state machine **800** proceeds (VALID\_COMMAND) to state **812**.

(74) At state **812**, the state machine **800** executes the command received at state **810**. In some examples, executing the command includes communicating with a downstream device and waiting for a response from the downstream device. In other examples, executing the command includes controlling the isolated drive circuit **520** and the isolated drive circuit **522** to control the switch circuit **519** and the switch circuit **521**, respectively, to place the switch circuit **519** and the switch circuit **521** in a state indicated by the command. After executing the command, the state machine **800** controls the uplink circuit **518** to transmit a response associated with the command to the control system and then proceeds (TRANSMIT\_DONE) back to the state **806**.

(75) In at least some examples, of the state machine **800**, the state **806** is omitted. In such an example, the state machine **800** may proceed from the state **802** to the state **810** under the same conditions in which the state machine **800** would proceed from state **802** to state **806** in the above description. Also, in such an example, the state machine **800** may remain (SAME\_STATE) at the state **810**, or return to the state **820**, in response to receiving an invalid command at the state **810**. Further in the example of the state machine **800** in which the state **806** is omitted, the state **812** may proceed after transmission (TRANSMIT\_DONE) to the state **810** under the same conditions in which the state machine **800** would proceed from state **812** to state **806** in the above description.

(76) While a communication scheme between a control system and a remote device has been described herein, a similar communication may also be implemented in a substantially similar manner between a remote device and a downstream device. For example, a control system may query a remote device that may then itself query one or more downstream devices and/or other remote devices, which may themselves query one or more downstream devices and/or yet other remote devices. The first remote device may receive responses from the queried one or more downstream devices and/or other remote devices and report those responses to the control system. Thus, a number of communication roundtrips between the control system and downstream devices is reduced, correspondingly reducing an amount of time consumed in the control system receiving information from multiple of the downstream devices. Such a communication scheme, utilizing at least some of the teachings of the present disclosure, is included within the scope of the present disclosure. The remote device may power the downstream device and also include communication with the downstream device using digital encoding only, e.g., sending digital data directly. The current embodiment of the downstream devices can also decode digital data when fed into node **536**.

(77) Various systems and methods associated with control devices, communication protocols, and downhole systems are described herein. Certain aspects of a safety sub system can include, but are not limited to:

(78) In a first aspect, a safety sub for use with one or more downhole tools comprises: a processor, a memory; and a control program stored in the memory that, when executed on the processor, configures the processor to: receive power from a wireline coupled to the safety sub; read one or more switch statuses from the memory; receive, from a control unit, a tool ID; validate the tool ID and the one or more switch statuses; receive, from the control unit, a command signal; validate the command signal; determine that the tool ID, the one or more switch statuses, and the command signal are valid; and communicate with one or more downhole tools in response to the

determination that the tool ID, the one or more switches, and the command signal are valid, wherein the safety sub is disposed between the control unit and the one or more downhole tools.

(79) A second aspect can include the safety sub of the first aspect, further comprising: sending, to the control unit, a confirmation of the communication with the one or more downhole tools.

(80) A third aspect can include the safety sub of the first or second aspect, further comprising: one or more isolation drives, wherein the control program further configures the processor to: isolate the control unit from the one or more downhole tools using the one or more isolation drives when the tool ID, the one or more switch statuses, or the command signal are invalid.

(81) A fourth aspect can include the safety sub of the third aspect, wherein the one or more isolation drives comprise an air or iron core transformer configured to be driven by an amplifier or an open drain transistor.

(82) A fifth aspect can include the safety sub of the fourth aspect, wherein transformer is configured to deliver a waveform scaled based on a transfer ratio presented at the primary coil.

(83) A sixth aspect can include the safety sub of the fourth aspect, wherein the transformer is configured to be used in forward mode or flyback mode for conversion of a drive signal along the wireline.

(84) A seventh aspect can include the safety sub of the fourth aspect, wherein the transformer is configured to be driven by a microcontroller drive or a separate oscillator.

(85) An eighth aspect can include the safety sub of any one of the first to seventh aspects, wherein the memory comprises an EEPROM.

(86) A ninth aspect can include the safety sub of any one of the first to eighth aspects, further comprising: a rectifier, wherein the rectifier is configured to power the safety sub irrespective of polarity received at the safety sub.

(87) A tenth aspect can include the safety sub of any one of the first to ninth aspects, further comprising: a current interrupt device, wherein the current interrupt device is configured to place the safety sub in a fail-safe mode when an overvoltage is received at the safety sub.

(88) An eleventh aspect can include the safety sub of the tenth aspect, further comprising: an RF shunt, wherein the RF shunt is configured to open the current interrupt device in response to a detected high voltage or RF signal above a threshold.

(89) A twelfth aspect can include the safety sub of any one of the first to eleventh aspects, further comprising: an uplink circuit, wherein the uplink circuit is configured to provide communication between the control unit and the safety sub.

(90) A thirteenth aspect can include the safety sub of any one of the first to twelfth aspects, further comprising: a downlink circuit, wherein the downlink circuit is configured to communicate with the one or more downhole tools.

(91) A fourteenth aspect can include the safety sub of any one of the first to thirteenth aspects, further comprising: a protection circuit, wherein the protection circuit is configured to isolate the control system of the safety sub in the event of a damaging signal.

(92) A fifteenth aspect can include the safety sub of any one of the first to fourteenth aspects, further comprising: a protection device, wherein the protection device comprises one or more semiconductor switches configured to limit the voltage and current from reaching the output of the safety sub.

(93) A sixteenth aspect can include the safety sub of the fifteenth aspect, wherein the semiconductor switches comprise Silicon, Silicon On Insulator, Silicon Carbide, Gallium Nitride, or any combination thereof.

(94) A seventeenth aspect can include the safety sub of any one of the first to sixteenth aspects, further comprising: a self-test circuit, wherein the self-test circuit is configured to check an integrity of semiconductor protection components.

(95) An eighteenth aspect can include the safety sub of any one of the first to seventeenth aspects, further comprising at least one of a voltage sensor or a temperature sensor.

- (96) In a nineteenth aspect, a method for providing signal isolation to a tool in a wellbore comprises: receiving, from surface equipment, a signal at a control unit, wherein the control unit is located between the surface equipment and one or more perforating guns; processing the signal with a state machine; controlling a position of one or more switches; and allowing the surface equipment to communicate with one or more perforating guns based on the controlling of the position of the one or more switches.
- (97) A twentieth aspect can include the method of the nineteenth aspect, wherein the control unit is located in a tractor.
- (98) A twenty first aspect can include the method of the twentieth aspect, wherein the state machine is located between the tractor and the one or more perforating guns.
- (99) A twenty second aspect can include the method of any one of the nineteenth to twenty first aspects, further comprising: sending a validation signal to the surface equipment in response to allowing the surface equipment to communicate with the one or more perforating guns.
- (100) In a twenty third aspect, a method for validating a function of a downhole tool comprises: receiving a signal at a pre-check controller, wherein the pre-check controller is disposed in a tool string and coupled to one or more control units on one or more downhole tools; verify the functioning of the one or more downhole tools using the pre-check controller; and sending, by the pre-check controller, a validation signal to a surface control unit when the functioning of the one or more downhole tools is verified.
- (101) A twenty fourth aspect can include the method of the twenty third aspect, further comprising: inserting the tool string into a wellbore after verifying the functioning of the one or more downhole tools.
- (102) A twenty fifth aspect can include the method of any one of the nineteenth to twenty fourth aspects, further comprising: turning on the control unit after a predetermined amount of time, wherein receiving the signal at the control unit occurs after turning on the control unit.
- (103) In a twenty sixth aspect, a safety device for use with one or more end devices comprises: a processor, a memory; and a control program stored in the memory that, when executed on the processor, configures the processor to: receive power from a communication line coupled to the safety device; read one or more switch statuses from the memory; receive, from a control unit, a device ID; validate the device ID and the one or more switch statuses; receive, from the control unit, a command signal; validate the command signal; determine that the device ID, the one or more switch statuses, and the command signal are valid; and communicate with one or more end devices in response to the determination that the device ID, the one or more switches, and the command signal are valid, wherein the safety device is disposed between the control unit and the one or more end devices.
- (104) A twenty seventh aspect can include the safety device of the twenty sixth aspect, further comprising: sending, to the control unit, a confirmation of the communication with the one or more end devices.
- (105) A twenty eighth aspect can include the safety device of the twenty sixth or twenty seventh aspect, further comprising: one or more isolation drives, wherein the control program further configures the processor to: isolate the control unit from the one or more end devices using the one or more isolation drives when the device ID, the one or more switch statuses, or the command signal are invalid.
- (106) A twenty ninth aspect can include the safety device of the twenty eighth aspect, wherein the one or more isolation drives comprise an air or iron core transformer configured to be driven by an amplifier or an open drain transistor.
- (107) A thirtieth aspect can include the safety device of the twenty ninth aspect, wherein transformer is configured to deliver a waveform scaled based on a transfer ratio presented at the primary coil.
- (108) A thirty first aspect can include the safety device of the twenty ninth aspect, wherein the

transformer is configured to be used in forward mode or flyback mode for conversion of a drive signal along the communication line.

(109) A thirty second aspect can include the safety device of the twenty ninth aspect, wherein the transformer is configured to be driven by a microcontroller drive or a separate oscillator.

(110) A thirty third aspect can include the safety device of any one of the twenty sixth to thirty second aspects, wherein the memory comprises an EEPROM.

(111) A thirty fourth aspect can include the safety device of any one of the twenty sixth to thirty third aspects, further comprising: a rectifier, wherein the rectifier is configured to power the safety device irrespective of polarity received at the safety device.

(112) A thirty fifth aspect can include the safety device of any one of the twenty sixth to thirty fourth aspects, further comprising: a current interrupt device, wherein the current interrupt device is configured to place the safety device in a fail-safe mode when an overvoltage is received at the safety device.

(113) A thirty sixth aspect can include the safety device of the thirty fifth aspect, further comprising: an RF shunt, wherein the RF shunt is configured to open the current interrupt device in response to a detected high voltage or RF signal above a threshold.

(114) A thirty seventh aspect can include the safety device of any one of the twenty sixth to thirty sixth aspects, further comprising: an uplink circuit, wherein the uplink circuit is configured to provide communication between the control unit and the safety device.

(115) A thirty eighth aspect can include the safety device of any one of the twenty sixth to thirty seventh aspects, further comprising: a downlink circuit, wherein the downlink circuit is configured to communicate with the one or more end devices.

(116) A thirty ninth aspect can include the safety device of any one of the twenty sixth to thirty eighth aspects, further comprising: a protection circuit, wherein the protection circuit is configured to isolate the control system of the safety device in the event of a damaging signal.

(117) A fortieth aspect can include the safety device of any one of the twenty sixth to thirty ninth aspects, further comprising: a protection device, wherein the protection device comprises one or more semiconductor switches configured to limit the voltage and current from reaching the output of the safety device.

(118) A forty first aspect can include the safety device of the fortieth aspect, wherein the semiconductor switches comprise Silicon, Silicon On Insulator, Silicon Carbide, Gallium Nitride, or any combination thereof.

(119) A forty second aspect can include the safety device of any one of the twenty sixth to forty first aspects, further comprising: a self-test circuit, wherein the self-test circuit is configured to check an integrity of semiconductor protection components.

(120) A forty third aspect can include the safety device of any one of the twenty sixth to forty second aspects, further comprising at least one of a voltage sensor or a temperature sensor.

(121) In a forty fourth aspect, a method for providing signal isolation to an end device comprises: receiving, from a controller unit, a signal at a control unit, wherein the control unit is located between the controller unit and one or more end units; processing the signal with a state machine; controlling a position of one or more switches; and allowing the controller unit to communicate with one or more end units based on the controlling of the position of the one or more switches.

(122) A forty fifth aspect can include the method of the forty fourth aspect, wherein the control unit is located in a programmable detonator.

(123) A forty sixth aspect can include the method of the forty fifth aspect, wherein the state machine is located between the programmable detonator and the one or more end units.

(124) A forty seventh aspect can include the method of any one of the forty fourth to forty sixth aspects, further comprising: sending a validation signal to the controller unit in response to allowing the controller unit to communicate with the one or more end units.

(125) In a forty eighth aspect, a method for validating a function of an end unit comprises:

receiving a signal at a pre-check controller, wherein the pre-check controller is coupled to one or more control units on one or more end units; verify the functioning of the one or more end units using the pre-check controller; and sending, by the pre-check controller, a validation signal to a controller unit when the functioning of the one or more end units is verified.

(126) A forty ninth aspect can include the method of the forty eighth aspect, further comprising: inserting the end units into a mine after verifying the functioning of the one or more end units.

(127) A fiftieth aspect can include the method of any one of the forty fourth to forty ninth aspects, further comprising: turning on the control unit after a predetermined amount of time, wherein receiving the signal at the control unit occurs after turning on the control unit.

(128) Certain aspects of a downhole communications system can include, but are not limited to:

(129) In a first aspect, a method for compensating the communication frequencies comprises: measuring a downhole time base of a received responses from a downhole unit; determining a shift in the downhole time based of the received response; and adjusting a surface communication time base to match that of the downhole unit.

(130) A second aspect can include the method of the first aspect, wherein adjusting the surface communication time base uses frequency scaled shift keying to shift mark and space frequencies by a same percentage as the shift in the downhole time base.

(131) A third aspect can include the method of the first or second aspects, wherein adjusting the surface communication time base comprises matching a change in a reference time base of the downhole unit due to temperature effects on the downhole unit.

(132) A fourth aspect can include the method of any one of the first to third aspects, wherein adjusting the surface communication time base comprises: adjusting a transition boundary between a mark and space frequency or between a space and mark frequency.

(133) A fifth aspect can include the method of the fourth aspect, wherein adjusting the transition boundary comprises: changing an amplitude of a waveform at the transition boundary.

(134) A sixth aspect can include the method of any one of the first to fifth aspects, further comprising: reducing or nullify communication errors based on the adjusting of the surface communication time base.

(135) In a seventh aspect, a method of compensating communications from downhole devices to a surface unit comprises: generating, at a downhole device, a signal; varying an amplitude at a transition boundary of the signal from a current encoding unit to provide a shaped signal; and transmitting the shaped signal to the surface unit.

(136) An eighth aspect can include the method of the seventh aspect, wherein the current encoding unit uses Manchester encoding.

(137) A ninth aspect can include the method of the seventh or eighth aspect, wherein varying the amplitude at the transition boundary is configured to overcome a cable impedance of a cable connecting the downhole device and the surface unit.

(138) A tenth aspect can include the method of any one of the seventh to ninth aspects, further comprising: applying power to the downhole device while transmitting the shaped signal to the surface unit, wherein the power is sufficient to initiate a perforating charge.

(139) An eleventh aspect can include the method of the tenth aspect, wherein the power is greater than a magnitude of the shaped signal.

(140) A twelfth aspect can include the method of any one of the seventh to eleventh aspects, wherein the downhole device comprises at least one of: a selectively fired perforating gun, a setting tool, a pressure sensing tool, a Gamma-Ray, a Digital CCL, a release device, or a downhole sensor.

(141) A thirteenth aspect can include the method of any one of the seventh to twelfth aspects, wherein the downhole device comprises an addressing system.

(142) In a fourteenth aspect, a method for checking a downhole device, the method comprising: sending a signal to one or more control units located on the downhole device in the tool string; identifying a status of each control unit; processing the signal with the appropriate commands;

determining that the downhole device is functioning based on the processing; and lowering the downhole device into a wellbore in response to determining that the downhole device is functioning.

(143) A fifteenth aspect can include the method of the fourteenth aspect, wherein identifying the status of each control unit comprises: processing, by the control unit for each downhole device, a signal; sending, from the control unit to a surface unit, a validation signal; and receiving, by the surface unit, the validation signal from the control unit for the downhole device.

(144) A sixteenth aspect can include the method of the fourteenth or fifteenth aspect, further comprising: scaling, by the surface unit, a waveform and shape of an instruction signal; sending, from the surface unit to the control unit, the instruction signal to perform a function while the downhole device is within the wellbore.

(145) In a seventeenth aspect, a method for compensating the communication frequencies comprises: measuring a time base of a received responses from an end unit; determining a shift in the time base based of the received response; and adjusting a controller communication time base to match that of the end unit.

(146) An eighteenth aspect can include the method of the seventeenth aspect, wherein adjusting the controller communication time base uses frequency scaled shift keying to shift mark and space frequencies by a same percentage as the shift in the time base of the end unit.

(147) An nineteenth aspect can include the method of the seventeenth or eighteenth aspect, wherein adjusting the controller communication time base comprises matching a change in a reference time base of the end unit due to temperature effects on the end unit.

(148) A twentieth aspect can include the method of any one of the seventeenth to nineteenth aspects, wherein adjusting the controller communication time base comprises: adjusting a transition boundary between a mark and space frequency or between a space and mark frequency.

(149) A twenty first aspect can include the method of the twentieth aspect, wherein adjusting the transition boundary comprises: changing an amplitude of a waveform at the transition boundary.

(150) A twenty second aspect can include the method of any one of the seventeenth to twenty first aspects, further comprising: reducing or nullify communication errors based on the adjusting of the controller communication time base.

(151) In a twenty third aspect, a method of compensating communications from an end devices to a controller unit comprises: generating, at an end device, a signal; varying an amplitude at a transition boundary of the signal from a current encoding unit to provide a shaped signal; and transmitting the shaped signal to the controller unit.

(152) A twenty fourth aspect can include the method of the twenty third aspect, wherein the current encoding unit uses Manchester encoding.

(153) A twenty fifth aspect can include the method of the twenty third or twenty fourth aspect, wherein varying the amplitude at the transition boundary is configured to overcome a cable impedance of a cable connecting the end device and the controller unit.

(154) A twenty sixth aspect can include the method of any one of the twenty third to twenty fifth aspects, further comprising: applying power to the end device while transmitting the shaped signal to the controller unit, wherein the power is sufficient to initiate a blasting charge.

(155) A twenty seventh aspect can include the method of the twenty sixth aspect, wherein the power is greater than a magnitude of the shaped signal.

(156) A twenty eighth aspect can include the method of any one of the twenty third to twenty seventh aspects, wherein the end device comprises at least one of: a selectively fired blasting charge, or a pressure sensing tool.

(157) A twenty ninth aspect can include the method of any one of the twenty third to twenty eighth aspects, wherein the end device comprises an addressing system.

(158) In a thirtieth aspect, a method for checking an end device comprises: sending a signal to one or more control units located on the end device; identifying a status of each control unit; processing

the signal with the appropriate commands; determining that the end device is functioning based on the processing; and placing the end device into a mine shaft in response to determining that the end device is functioning.

(159) A thirty first aspect can include the method of the thirtieth aspect, wherein identifying the status of each control unit comprises: processing, by the control unit for each end device, a signal; sending, from the control unit to a controller unit, a validation signal; and receiving, by the controller unit, the validation signal from the control unit for the end device.

(160) A thirty second aspect can include the method of the thirtieth or thirty first aspect, further comprising: scaling, by the controller unit, a waveform and shape of an instruction signal; and sending, from the controller unit to the control unit, the instruction signal to perform a function while the end device is within the mine shaft.

(161) In the foregoing discussion and in the claims, the terms “including” and “comprising” are used in an open-ended fashion, and thus mean “including, but not limited to . . . .”

(162) The term “couple” is used throughout the specification. The term may cover connections, communications, or signal paths that enable a functional relationship consistent with the description of the present disclosure. For example, if device A generates a signal to control device B to perform an action, in a first example device A is coupled to device B, or in a second example device A is coupled to device B through intervening component C if intervening component C does not substantially alter the functional relationship between device A and device B such that device B is controlled by device A via the control signal generated by device A.

(163) An element or feature that is “configured to” perform a task or function may be configured (e.g., programmed or structurally designed) at a time of manufacturing by a manufacturer to perform the function and/or may be configurable (or re-configurable) by a user after manufacturing to perform the function and/or other additional or alternative functions. The configuring may be through firmware and/or software programming of the device, through a construction and/or layout of hardware components and interconnections of the device, or a combination thereof. Additionally, uses of the phrases “ground” or similar in the foregoing discussion include a chassis ground, an Earth ground, a floating ground, a virtual ground, a digital ground, a common ground, and/or any other form of ground connection applicable to, or suitable for, the teachings of the present disclosure. Unless otherwise stated, “about,” “approximately,” or “substantially” preceding a value means  $\pm 10$  percent of the stated value.

(164) The above discussion is illustrative of the principles and various embodiments of the present disclosure. Numerous variations and modifications will become apparent to those skilled in the art once the above disclosure is fully appreciated. The following claims should be interpreted to embrace all such variations and modifications.

## Claims

1. A remote device, comprising: an electrically erasable programmable read-only memory (EEPROM); a microcontroller including a memory and coupled to the EEPROM; and executable code stored as firmware in the memory that, when executed by the microcontroller, configures the microcontroller to: receive power from a wireline coupled between a control system and the remote device; read a switch state from the EEPROM; determine whether the switch state read from a first memory location of a plurality of memory locations in the EEPROM matches the switch state read from a second memory location of the plurality of memory locations in the EEPROM; and at least one of: control a switch to have the switch state when the switch state read from the first memory location matches the switch state read from the second memory location; or fail to a safe state by controlling the switch to have a switch state of off when the switch state read from the first memory location does not match the switch state read from the second memory location.

2. The remote device of claim 1, wherein the executable code further configures the

microcontroller to: receive, from the control system, a control signal; validate the control signal; and control the switch to have a switch state determined based on the control signal.

3. The remote device of claim 2, wherein the control signal is received from the control system as a frequency shift keying (FSK) encoded signal and the remote device decodes the FSK encoded signal to obtain binary data bits representative of the control signal.
4. The remote device of claim 3, wherein the FSK encoded signal has a time base synchronized by the control system to a time base of the remote device.
5. The remote device of claim 2, wherein the executable code further configures the microcontroller to transmit a response message to the control system, responsive to receiving, validating, or controlling the switch according to the control signal.
6. The remote device of claim 5, wherein the remote device encodes the response message on the wireline via Manchester encoding by modulating a current on the wireline by an amount in a range of 25 milliamps to 100 milliamps.
7. The remote device of claim 1, wherein the remote device is power signal polarity agnostic such that the remote device is operational when receiving a positive polarity power signal or a negative polarity power signal.
8. The remote device of claim 1, wherein the remote device is disposed in series on a wireline between the control system and a downstream device including a detonation charge, and wherein the switch is configured to permit or deny signal flow via the wireline from the control system to the downstream device based on control of the microcontroller.
9. The remote device of claim 1, wherein the remote device is a safety sub disposed between the control system and a perforating gun and which controls provision of power to the perforating gun from the control system.
10. The remote device of claim 1, further comprising a battery, wherein the microcontroller is configured to control the switch to have a switch state of off a predetermined period of time after termination of receipt of power from the wireline.
11. The remote device of claim 1, wherein the microcontroller is further configured to: receive power from a wireline coupled between a control system and the remote device at a first voltage; and determine whether the first voltage is equal to or greater than a threshold voltage, wherein the microcontroller is configured to control the switch to have the switch state when the first voltage is equal to or greater than the threshold voltage, or control the switch to the safe state when the first voltage is less than the threshold voltage.
12. A method, comprising: reading a switch state from redundant memory locations; determining whether the switch state read from the redundant memory locations matches; controlling a switch to have the switch state when the switch state read from the redundant memory locations matches; and failing to a safe state by controlling the switch to have a switch state of off when the switch state read from the redundant memory locations does not match.
13. The method of claim 12, further comprising: receiving, from a control system, a command; validating the command; controlling the switch to have a switch state determined based on the command; receiving, from the control system, a device identifier; and validating the device identifier.
14. The method of claim 13, wherein the command and the device identifier are each included in frequency shift keying (FSK) encoded control signals provided by the control system superimposed on a power signal, and wherein the FSK encoded control signals have a time based variable configured by the control system to synchronize to a time base of a device executing the method, the time based variable based on a temperature of an environment in which the device is executing the method.
15. The method of claim 13, further comprising transmitting a response message to the control system, responsive to receiving, validating, or controlling the switch according to a control signal, wherein the response message is encoded according to Manchester encoding.

16. The method of claim 13, wherein controlling the switch to have a switch state determined based on the command comprises controlling the switch to have a state of on based on the command, wherein a signal flows from the control system to a downstream device when the switch has the state of on.
17. The method of claim 13, wherein controlling the switch to have a switch state determined based on the command comprises controlling the switch to have the state of off based on the command, wherein a signal is blocked from flowing from the control system to a downstream device when the switch has the state of off.
18. The method of claim 12, wherein the method is implemented by a safety sub disposed in series on a wireline between a control system and a downstream device including a detonation charge, and wherein the switch is configured to permit or deny signal flow via the wireline from the control system to the downstream device based on control of a microcontroller.
19. The method of claim 12, further comprising: receiving power from a wireline coupled between a control system and a remote device comprising the redundant memory locations at a first voltage; and determining whether the first voltage is equal to or greater than a threshold voltage, wherein controlling the switch to have the switch state occurs when the first voltage is equal to or greater than the threshold voltage, or failing the switch to the safe state occurs when the first voltage is less than the threshold voltage.
20. A remote device, comprising: a battery; a microcontroller including a memory and adapted to receive power from the battery; and executable code stored as firmware in the memory that, when executed by the microcontroller, configures the microcontroller to: determine that a predetermined period of time has elapsed since the microcontroller received power via a physical coupling to a control system; and control a switch to have a switch state of off responsive to the determination that the predetermined period of time has elapsed.
-