

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12386562
Kind Code	B2
Date of Patent	August 12, 2025
Inventor(s)	Cariello; Giuseppe et al.

Dynamic status registers array

Abstract

Methods, systems, and devices for dynamic status registers array are described. An apparatus may include one or more memory dice coupled with a data bus. The apparatus may further include a controller coupled with each of the memory dice via the data bus that is configured to transmit a first command associated with a first operation to a first memory die. The first command may assign an associated operation (e.g., the first operation) to a queue slot of a status bank that is associated with at least the first memory die. The controller may further transmit second command to the first memory die to request a status of the first operation. The controller may receive a status of the first operation via a channel (e.g., a first channel) of the data bus that is based on the assigned queue slot of the status bank.

Inventors:	Cariello; Giuseppe (Boise, ID), Basu; Reshmi (Boise, ID)
Applicant:	Micron Technology, Inc. (Boise, ID)
Family ID:	85178030
Assignee:	Micron Technology, Inc. (Boise, ID)
Appl. No.:	18/633028
Filed:	April 11, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240345775 A1	Oct. 17, 2024

Related U.S. Application Data

continuation parent-doc US 17399889 20210811 US 11972144 child-doc US 18633028

Publication Classification

Int. Cl.: G06F3/06 (20060101)

U.S. Cl.:

CPC G06F3/0659 (20130101); G06F3/061 (20130101); G06F3/0679 (20130101);

Field of Classification Search

CPC: G06F (3/061); G06F (3/0659); G06F (3/0679); G11C (16/0483); G11C (16/08)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2018/0349240	12/2017	Ji	N/A	G06F 11/1441
2019/0227749	12/2018	Wakchaure et al.	N/A	N/A
2021/0117335	12/2020	Kondo	N/A	N/A

Primary Examiner: Mackall; Larry T

Attorney, Agent or Firm: Holland & Hart LLP

Background/Summary

CROSS REFERENCE (1) The present Application for Patent is a continuation of U.S. patent application Ser. No. 17/399,889 by Cariello et al., entitled “DYNAMIC STATUS REGISTERS ARRAY,” filed Aug. 11, 2021, assigned to the assignee hereof, and is expressly incorporated by reference in its entirety herein.

FIELD OF TECHNOLOGY

(1) The following relates generally to one or more systems for memory and more specifically to dynamic status registers array.

BACKGROUND

(2) Memory devices are widely used to store information in various electronic devices such as computers, user devices, wireless communication devices, cameras, digital displays, and the like. Information is stored by programming memory cells within a memory device to various states. For example, binary memory cells may be programmed to one of two supported states, often corresponding to a logic 1 or a logic 0. In some examples, a single memory cell may support more than two possible states, any one of which may be stored by the memory cell. To access information stored by a memory device, a component may read, or sense, the state of one or more memory cells within the memory device. To store information, a component may write, or program, one or more memory cells within the memory device to corresponding states.

(3) Various types of memory devices exist, including magnetic hard disks, random access memory (RAM), read-only memory (ROM), dynamic RAM (DRAM), synchronous dynamic RAM (SDRAM), static RAM (SRAM), ferroelectric RAM (FeRAM), magnetic RAM (MRAM), resistive RAM (RRAM), flash memory, phase change memory (PCM), 3-dimensional cross-point memory

(3D cross point), not-or (NOR) and not-and (NAND) memory devices, and others. Memory devices may be volatile or non-volatile. Volatile memory cells (e.g., DRAM cells) may lose their programmed states over time unless they are periodically refreshed by an external power source. Non-volatile memory cells (e.g., NAND memory cells) may maintain their programmed states for extended periods of time even in the absence of an external power source.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 illustrates an example of a system that supports dynamic status registers array in accordance with examples as disclosed herein.
- (2) FIG. 2 illustrates an example of a system that supports dynamic status registers array in accordance with examples as disclosed herein.
- (3) FIG. 3 illustrates an example of a block diagram that supports dynamic status registers array in accordance with examples as disclosed herein.
- (4) FIGS. 4A and 4B illustrate examples of timing diagrams that support dynamic status registers array in accordance with examples as disclosed herein.
- (5) FIG. 5 shows a block diagram of a memory system controller that supports dynamic status registers array in accordance with examples as disclosed herein.
- (6) FIG. 6 shows a block diagram of a memory device that supports dynamic status registers array in accordance with examples as disclosed herein.
- (7) FIGS. 7 and 8 show flowcharts illustrating a method or methods that support dynamic status registers array in accordance with examples as disclosed herein.

DETAILED DESCRIPTION

(8) A system may include a host system and a memory system that stores data for the host system. In some examples, the memory system may include multiple memory devices attached to an interface. For example, the memory system may include multiple NAND devices attached to the same interface (e.g., Open NAND Flash Interface (ONFI) channel). The host system may transmit access commands (e.g., read commands, program commands, erase commands) to the memory system. In such examples, the memory system may execute operations in response to the commands received from the host system. In examples where multiple memory devices are included in the memory system, the memory devices may perform concurrent operations—e.g., operations that may not be initiated at the same time but proceed in parallel. That is, the memory system may initiate a first operation at a first memory device, then a second operation at a second memory device, then a third operation at a third memory device, and the first, second, and third operations may be executed at least partially in parallel. In some examples, the host system controller or memory system controller may execute round robin polling of the status register of each active memory device to determine if a given memory device is ready to be serviced—e.g., the controller may poll the first memory device, then the second memory device, and then the third memory device, to determine if the first, second, or third memory device is ready to be serviced. In some examples, performing round robin polling may increase latency and power consumption in the system. For example, the second memory device may be ready to be serviced before the first memory device but may wait idly until the system is done polling the status register of the first memory device. Also switching from one memory device to another memory device to poll the memory devices in the round robin polling may utilize additional power consumption for the bus transitions. And finally, a memory device idly waiting for a subsequent command may increase power consumption as well.

(9) Systems, techniques, and devices are described herein to perform concurrent or parallel status polling via a dedicated command in a memory system with multiple memory devices. For example,

a controller in the memory system may transmit commands to multiple memory devices to assign each operation to a queue slot of a status bank. Accordingly, the controller may subsequently poll a status bank using a command (e.g., a bank selection polling command) and devices with operations assigned to queue slots of the status bank may output the status on channels of a data bus that are associated with the queue slots for the status bank. For example, for an eight (8) bit data bus coupled with a memory device having eight (8) banks, the polling status of 256 concurrent operations may be supported. By performing concurrent parallel status polling utilizing status banks, the memory system may decrease power consumption and latency. That is, the polling based on status banks may assist in identifying which memory devices are ready to be serviced first, and thus enable faster servicing of the commands of the given memory devices. This may reduce a quantity of time each memory device waits idly for servicing or subsequent commands, reducing power consumption and latency of the system.

(10) Features of the disclosure are initially described in the context of systems and devices with reference to FIGS. 1 and 2. Features of the disclosure are described in the context of block diagrams and timing diagrams with reference to FIGS. 3 and 4. These and other features of the disclosure are further illustrated by and described in the context of an apparatus diagram and flowchart that relate to dynamic status registers array with reference to FIGS. 5-8.

(11) FIG. 1 illustrates an example of a system **100** that supports dynamic status registers array in accordance with examples as disclosed herein. The system **100** includes a host system **105** coupled with a memory system **110**.

(12) A memory system **110** may be or include any device or collection of devices, where the device or collection of devices includes at least one memory array. For example, a memory system **110** may be or include a Universal Flash Storage (UFS) device, an embedded Multi-Media Controller (eMMC) device, a flash device, a universal serial bus (USB) flash device, a secure digital (SD) card, a solid-state drive (SSD), a hard disk drive (HDD), a dual in-line memory module (DIMM), a small outline DIMM (SO-DIMM), or a non-volatile DIMM (NVDIMM), among other possibilities.

(13) The system **100** may be included in a computing device such as a desktop computer, a laptop computer, a network server, a mobile device, a vehicle (e.g., airplane, drone, train, automobile, or other conveyance), an Internet of Things (IoT) enabled device, an embedded computer (e.g., one included in a vehicle, industrial equipment, or a networked commercial device), or any other computing device that includes memory and a processing device.

(14) The system **100** may include a host system **105**, which may be coupled with the memory system **110**. In some examples, this coupling may include an interface with a host system controller **106**, which may be an example of a control component configured to cause the host system **105** to perform various operations in accordance with examples as described herein. The host system **105** may include one or more devices, and in some cases may include a processor chipset and a software stack executed by the processor chipset. For example, the host system **105** may include an application configured for communicating with the memory system **110** or a device therein. The processor chipset may include one or more cores, one or more caches (e.g., memory local to or included in the host system **105**), a memory controller (e.g., NVDIMM controller), and a storage protocol controller (e.g., peripheral component interconnect express (PCIe) controller, serial advanced technology attachment (SATA) controller). The host system **105** may use the memory system **110**, for example, to write data to the memory system **110** and read data from the memory system **110**. Although one memory system **110** is shown in FIG. 1, the host system **105** may be coupled with any quantity of memory systems **110**.

(15) The host system **105** may be coupled with the memory system **110** via at least one physical host interface. The host system **105** and the memory system **110** may in some cases be configured to communicate via a physical host interface using an associated protocol (e.g., to exchange or otherwise communicate control, address, data, and other signals between the memory system **110** and the host system **105**). Examples of a physical host interface may include, but are not limited to,

a SATA interface, a USB interface, an eMMC interface, a PCIe interface, a Fiber Channel interface, a Small Computer System Interface (SCSI), a Serial Attached SCSI (SAS), a Double Data Rate (DDR) interface, a DIMM interface (e.g., DIMM socket interface that supports DDR), an Open NAND Flash Interface (ONFI), and a Low Power Double Data Rate (LPDDR) interface. In some examples, one or more such interfaces may be included in or otherwise supported between a host system controller **106** of the host system **105** and a memory system controller **115** of the memory system **110**. In some examples, the host system **105** may be coupled with the memory system **110** (e.g., the host system controller **106** may be coupled with the memory system controller **115**) via a respective physical host interface for each memory device **130** included in the memory system **110**, or via a respective physical host interface for each type of memory device **130** included in the memory system **110**.

(16) The memory system **110** may include a memory system controller **115** and one or more memory devices **130**. A memory device **130** may include one or more memory arrays of any type of memory cells (e.g., non-volatile memory cells, volatile memory cells, or any combination thereof). Although two memory devices **130-a** and **130-b** are shown in the example of FIG. **1**, the memory system **110** may include any quantity of memory devices **130**. Further, if the memory system **110** includes more than one memory device **130**, different memory devices **130** within the memory system **110** may include the same or different types of memory cells.

(17) The memory system controller **115** may be coupled with and communicate with the host system **105** (e.g., via the physical host interface) and may be an example of a control component configured to cause the memory system **110** to perform various operations in accordance with examples as described herein. The memory system controller **115** may also be coupled with and communicate with memory devices **130** to perform operations such as reading data, writing data, erasing data, or refreshing data at a memory device **130**—among other such operations—which may generically be referred to as access operations. In some cases, the memory system controller **115** may receive commands from the host system **105** and communicate with one or more memory devices **130** to execute such commands (e.g., at memory arrays within the one or more memory devices **130**). For example, the memory system controller **115** may receive commands or operations from the host system **105** and may convert the commands or operations into instructions or appropriate commands to achieve the desired access of the memory devices **130**. In some cases, the memory system controller **115** may exchange data with the host system **105** and with one or more memory devices **130** (e.g., in response to or otherwise in association with commands from the host system **105**). For example, the memory system controller **115** may convert responses (e.g., data packets or other signals) associated with the memory devices **130** into corresponding signals for the host system **105**.

(18) The memory system controller **115** may be configured for other operations associated with the memory devices **130**. For example, the memory system controller **115** may execute or manage operations such as wear-leveling operations, garbage collection operations, error control operations such as error-detecting operations or error-correcting operations, encryption operations, caching operations, media management operations, background refresh, health monitoring, and address translations between logical addresses (e.g., logical block addresses (LBAs)) associated with commands from the host system **105** and physical addresses (e.g., physical block addresses) associated with memory cells within the memory devices **130**.

(19) The memory system controller **115** may include hardware such as one or more integrated circuits or discrete components, a buffer memory, or a combination thereof. The hardware may include circuitry with dedicated (e.g., hard-coded) logic to perform the operations ascribed herein to the memory system controller **115**. The memory system controller **115** may be or include a microcontroller, special purpose logic circuitry (e.g., a field programmable gate array (FPGA), an application specific integrated circuit (ASIC), a digital signal processor (DSP)), or any other suitable processor or processing circuitry.

(20) The memory system controller **115** may also include a local memory **120**. In some cases, the local memory **120** may include read-only memory (ROM) or other memory that may store operating code (e.g., executable instructions) executable by the memory system controller **115** to perform functions ascribed herein to the memory system controller **115**. In some cases, the local memory **120** may additionally or alternatively include static random access memory (SRAM) or other memory that may be used by the memory system controller **115** for internal storage or calculations, for example, related to the functions ascribed herein to the memory system controller **115**.

(21) A memory device **130** may include one or more arrays of non-volatile memory cells. For example, a memory device **130** may include NAND (e.g., NAND flash) memory, ROM, phase change memory (PCM), self-selecting memory, other chalcogenide-based memories, ferroelectric random access memory (RAM) (FeRAM), magneto RAM (MRAM), NOR (e.g., NOR flash) memory, Spin Transfer Torque (STT)-MRAM, conductive bridging RAM (CBRAM), resistive random access memory (RRAM), oxide based RRAM (OxRAM), electrically erasable programmable ROM (EEPROM), or any combination thereof. Additionally or alternatively, a memory device **130** may include one or more arrays of volatile memory cells. For example, a memory device **130** may include RAM memory cells, such as dynamic RAM (DRAM) memory cells and synchronous DRAM (SDRAM) memory cells.

(22) In some examples, a memory device **130** may include (e.g., on a same die or within a same package) a local controller **135**, which may execute operations on one or more memory cells of the respective memory device **130**. A local controller **135** may operate in conjunction with a memory system controller **115** or may perform one or more functions ascribed herein to the memory system controller **115**. For example, as illustrated in FIG. 1, a memory device **130-a** may include a local controller **135-a** and a memory device **130-b** may include a local controller **135-b**.

(23) In some cases, a memory device **130** may be or include a NAND device (e.g., NAND flash device). A memory device **130** may be or include a memory die **160**. For example, in some cases, a memory device **130** may be a package that includes one or more dies **160**. A die **160** may, in some examples, be a piece of electronics-grade semiconductor cut from a wafer (e.g., a silicon die cut from a silicon wafer). Each die **160** may include one or more planes **165**, and each plane **165** may include a respective set of blocks **170**, where each block **170** may include a respective set of pages **175**, and each page **175** may include a set of memory cells.

(24) In some cases, a NAND memory device **130** may include memory cells configured to each store one bit of information, which may be referred to as single level cells (SLCs). Additionally or alternatively, a NAND memory device **130** may include memory cells configured to each store multiple bits of information, which may be referred to as multi-level cells (MLCs) if configured to each store two bits of information, as tri-level cells (TLCs) if configured to each store three bits of information, as quad-level cells (QLCs) if configured to each store four bits of information, or more generically as multiple-level memory cells. Multiple-level memory cells may provide greater density of storage relative to SLC memory cells but may, in some cases, involve narrower read or write margins or greater complexities for supporting circuitry.

(25) In some cases, planes **165** may refer to groups of blocks **170**, and in some cases, concurrent operations may take place within different planes **165**. For example, concurrent operations may be performed on memory cells within different blocks **170** so long as the different blocks **170** are in different planes **165**. In some cases, performing concurrent operations in different planes **165** may be subject to one or more restrictions, such as identical operations being performed on memory cells within different pages **175** that have the same page address within their respective planes **165** (e.g., related to command decoding, page address decoding circuitry, or other circuitry being shared across planes **165**).

(26) In some cases, a block **170** may include memory cells organized into rows (pages **175**) and columns (e.g., strings, not shown). For example, memory cells in a same page **175** may share (e.g.,

be coupled with) a common word line, and memory cells in a same string may share (e.g., be coupled with) a common digit line (which may alternatively be referred to as a bit line).

(27) For some NAND architectures, memory cells may be read and programmed (e.g., written) at a first level of granularity (e.g., at the page level of granularity) but may be erased at a second level of granularity (e.g., at the block level of granularity). That is, a page **175** may be the smallest unit of memory (e.g., set of memory cells) that may be independently programmed or read (e.g., programmed or read concurrently as part of a single program or read operation), and a block **170** may be the smallest unit of memory (e.g., set of memory cells) that may be independently erased (e.g., erased concurrently as part of a single erase operation). Further, in some cases, NAND memory cells may be erased before they can be re-written with new data. Thus, for example, a used page **175** may in some cases not be updated until the entire block **170** that includes the page **175** has been erased.

(28) The system **100** may include any quantity of non-transitory computer readable media that support reduced pin status register. For example, the host system **105**, the memory system controller **115**, or a memory device **130** may include or otherwise may access one or more non-transitory computer readable media storing instructions (e.g., firmware) for performing the functions ascribed herein to the host system **105**, memory system controller **115**, or memory device **130**. For example, such instructions, if executed by the host system **105** (e.g., by the host system controller **106**), by the memory system controller **115**, or by a memory device **130** (e.g., by a local controller **135**), may cause the host system **105**, memory system controller **115**, or memory device **130** to perform one or more associated functions as described herein.

(29) In some cases, a memory system **110** may utilize a memory system controller **115** to provide a managed memory system that may include, for example, one or more memory arrays and related circuitry combined with a local (e.g., on-die or in-package) controller (e.g., local controller **135**). An example of a managed memory system is a managed NAND (MNAND) system.

(30) In some examples, memory system controller **115** may perform polling operations on the memory devices **130** to determine a status of the operations being performed by each memory device **130**. In some cases, the memory system controller **115** may conduct the polling operation in a round robin system. For example, the memory system controller **115** may first request a status of a first operation being executed at the memory device **130-a** and then request a status of a second operation being executed at the memory device **130-b**. In some cases, the second operation may be executed before the first operation. In such examples, the memory device **130-b** may idly wait for the memory system controller **115** to request the status of the second operation. The idle wait period may increase the power consumption and latency of the system.

(31) As described herein, the memory system controller **115** may perform a concurrent polling operation on the memory devices **130** by utilizing one or more banks (e.g., status banks). For example, the memory system controller **115** may transmit a command (e.g., a first command) to the memory device **130-a**. The command may assign an operation (e.g., a first operation) to a queue slot of a status bank associated with the memory device **130-a**. In some instances, the memory system controller **115** may transmit multiple commands to one or more of the memory devices **130** to assign operations to queue slots of respective status banks. Subsequently, the memory system controller **115** may transmit a command (e.g., a second command, a polling command) to multiple memory devices **130** that requests a status associated with the status bank. The memory device **130-a** may output the status of the operation, such that if memory device **130-a** is ready to be serviced then the memory system controller **115** may proceed to service the memory device **130-a**. Accordingly, the association between the operation, the queue slot of the status bank, and the channel of the bus may allow the memory system controller **115** to service the first memory device **130** of the status bank that is ready for service, thus reducing the idle time and decreasing the latency and power consumption of the system.

(32) FIG. 2 illustrates an example of a system **200** that supports dynamic status registers array in

accordance with examples as disclosed herein. System **200** may be an example of a memory system **110** as described with reference to FIG. **1**. System **200** may include a memory system controller **215** and memory devices **230** which may be examples of memory system controller **115** and memory devices **130** as described with reference to FIG. **1**. The memory system controller **215** may be coupled with the memory devices **230** via a data bus **205**. The memory system controller **215** may also be coupled with each memory device **230** via a chip enable line **210**—e.g., memory device **230-a** may be coupled with the memory system controller **215** via chip enable line **210-a**. In some examples, there may be eight (8) memory devices **230** coupled with memory system controller **215**. In other examples, there may be more than or less than eight (8) memory devices **230** coupled with the memory system controller **215**. It should be noted, a quantity of memory devices **230** in the system **200** are not limiting on the claims.

(33) As described with reference to FIG. **1**, memory system controller **215** may be configured to communicate commands from a host system (e.g., host system **105**) to memory devices **230**. In some examples, the memory system controller **215** may be configured to transmit a command **235** to the memory devices **230** via the data bus **205**. In such examples, the memory system controller **215** may be configured to activate a memory device **230-a** via a chip enable line **210** to transmit the command **235** from the memory system controller **215** to a given memory device **230**. For example, the memory system controller **215** may activate memory device **230-a** via chip enable line **210-a** and then transmit a command **235** to initiate an operation to the memory device **230-a**. In some examples, the memory system controller **215** may be configured to transmit commands **235** to initiate concurrent operations—e.g., operations that may not be initiated at the same time but proceed in parallel. For example, the memory system controller **215** may be configured to activate memory device **230-a** by transmitting a chip enable signal via the chip enable line **210-a**. The memory system controller **215** may then transmit a command **235** to the memory device **230-a** to initiate a first operation. The memory system controller **215** may then activate memory device **230-b** via the chip enable line **210-b** and transmit a second command **235** to the memory device **230-b** to initiate a second operation. In such examples, the first operation and the second operations may be performed concurrently (e.g., in parallel) by the memory device **230-a** and the memory device **230-b**.

(34) In some examples, the memory system controller **215** may be configured to communicate data **240** to and from the memory devices **230**. For example, the memory system controller **215** may transmit data **240** to the memory devices **230** during a program command and receive data **240** from the memory devices **230** during a read command. The memory system controller **215** may also be configured to receive a status **245** from each memory device **230**—e.g., the status **245** may indicate the status of a given operation being performed at a given memory device **230** and whether the given memory device **230** is ready to be serviced. As described with reference to FIG. **1**, the memory devices **230** may associate commands with one or more status banks that each have one or more queue slots. The memory system controller **215** may transmit a command to a memory device **230** that assigns an operation (e.g., a first operation) to a queue slot, and the queue slot may be associated with an address channel or a data channel of the data bus **205** for a status bank. Accordingly, during a polling operation, the memory system controller **215** may determine the status of the memory device **230** (or a portion, e.g., a plane, of the memory device **230**) based on the assigned queue slot and associated channel of the data bus **205**.

(35) Data bus **205** may be configured to communicate signals, commands **235**, data **240**, and statuses **245** between the memory system controller **215** and the memory devices **230**—e.g., the data bus **205** may be a multiplexed (e.g., tri-state, bi-directional) bus configured to communicate both addresses and data **240**. In some examples, the data bus **205** may be configured to have a quantity of bits equal to a quantity of data input/output (DQ) pins of the memory system controller **215**. For example, the data bus **205** may be an eight (8) bit data bus **205** when the memory system controller **215** has eight (8) DQ pins. In some examples, the data bus **205** may also include a

quantity of lines (e.g., channels) equal to the quantity of bits—e.g., each channel of the data bus **205** may be configured to communicate a bit of information. In some examples, the data bus **205** may also communicate a status **245** of each memory device **230** performing an operation concurrently. That is, the data bus **205** may be configured to multiplex the statuses **245** from the memory devices **230** to the memory system controller **215**—e.g., a first status **245** from memory device **230-a** may be communicated on a first line of the data bus **205** to the memory system controller **215** and a second status **245** from memory device **230-h** may be concurrently communicated on a second line of the data bus **205** to the memory system controller **215**. As described herein, which channel of the data bus **205** a status is communicated on may be based on an operation being assigned to an associated queue slot of a status bank.

(36) Memory devices **230** may be configured to store data. In some examples, the memory devices **230** may be configured to receive commands **235** from the memory system controller **215**. The memory devices **230** may be configured to concurrently perform operations in response to commands received from the memory system controller **215**. Each memory device **230** may be configured to communicate data **240** to and from the memory system controller **215**. In some examples, the memory devices **230** may also be configured to communicate a status **245** of an operation to the memory system controller **215**. The status **245** may be a single bit indicating whether the memory device **230** is ready to be serviced—e.g., a status **245** of a given operation being performed at memory device **230**. The memory devices **230** may be configured to access the data bus **205** based on the chip enable signal received from the memory system controller **215**. For example, the memory device **230** may refrain from driving a status **245** or refrain from receiving a command **235** from the data bus **205** when the chip enable signal is in an inactivated (e.g., high) state. Alternatively, the memory device **230** may drive a status **245** or receive a command **235** from the data bus when the chip enable signal is in an activated (e.g., low) state—e.g., the memory system controller **215** may decouple the memory device **230** from the data bus **205** by driving the chip enable signal high. In some examples, each memory device **230** may include multiple independent sections (e.g., banks, partitions, planes). In some examples, a queue slot of a status bank may be configured to store a status associated with a particular bank, partition, plane, etc. of a memory device **230**.

(37) In some examples, the memory system controller **215** may receive a command from the host system. The memory system controller **215** may then activate a memory device **230** based on the command received from the host system—e.g., the memory system controller **215** may activate memory device **230-a**, memory device **230-b**, or memory device **230-h** (e.g., via chip enable lines **210-a**, **210-b**, and **210-c** respectively) based on the command received. After activating a memory device **230**, the memory system controller **215** may transmit a command **235** to initiate an operation (e.g., a read, program, or erase operation) at the memory device **230**. For example, the memory system controller may transmit a first command **235** to initiate an erase operation at memory device **230-a**, a second command **235** to initiate a program operation at memory device **230-b**, and a third command **235** to initiate a read operation at memory device **230-h**. The memory system controller **215** may transmit the commands **235** sequentially (e.g., to memory device **230-a** first and memory device **230-h** last) while the operations may be performed concurrently at least in part. After each operation is initiated, the memory system controller **215** may perform a poll to determine a status of each operation and determine if the memory devices **230** are ready to be serviced.

(38) In some examples, the memory system controller **215** may perform a round robin polling of a status register of each active memory device **230**—e.g., each memory device **230** performing an operation. For example, the memory system controller **215** may deactivate the chip enable lines **210-b** and **210-c** to disconnect the data bus **205** from memory device **230-b** and memory device **230-c** while maintaining the chip enable line **210-a** in an activated state. The memory system controller **215** may then transmit a command **235** to memory device **230-a** to request a status **245**

of the operation being performed at the memory device **230-a**. The memory device **230-a** may then transmit a status **245** utilizing the eight bits of data bus **205** to the memory system controller **215**. The memory system controller **215** may then repeat the process to determine the status of the operations at memory devices **230-b** and **230-h**. In some examples, the memory device **230-h** may complete its respective operation first. For example, the memory device **230-h** may complete the read operation before the memory device **230-a** completes the erase operation. That is, some operations may take a longer duration to perform than others—e.g., read operations may be performed in a first duration, program operations may be performed in a second duration, and erase operations may be performed in third duration, where the first duration is less than the second and third duration, and the second duration is less than the third duration. In such examples, the memory device **230-h** may sit idly waiting for the memory system controller **215** to request the status **245** of the operation. This may increase the latency and power consumption of the system.

(39) As described herein, the memory system controller **215** may perform a concurrent polling of the status register of each active memory device **230**. For example, after assigning operations to respective queue slots of one or more status banks, the memory system controller **215** may transmit a command **235** to each of memory devices **230-a**, **230-b**, and **230-h** (e.g., by activating each of chip enable lines **210-a**, **210-b**, and **210-h** while transmitting the command) requesting the status of operations associated with a given status bank. The memory devices **230** having operations associated with queue slots of the given status bank may then drive a status **245** on respective channels the data bus **205**. For example, the memory devices **230** may concurrently drive a status **245** on respective channels (e.g., address channels or data channels) that are based on the assigned queue slot of the associated operation. In such examples, the memory devices **230** may drive a first value to indicate the memory device **230** is busy and a second value to indicate the memory device **230** is ready to be serviced. Accordingly, the memory system controller **215** may determine which memory device **230** is ready to be serviced first and transmit subsequent commands **235** based on the determination. For example, the memory device **230-h** may drive the second value on a first channel of the data bus **205** that is associated with a second queue slot of the status bank, which may indicate that the memory device **230-h** is ready for service. The memory system controller **215** may then request the data **240** indicated by the read command from the memory device **230-h** while the memory device **230-a** and memory device **230-b** may continue to execute their respective operations. By performing concurrent polling by assigning operations to queue slots of status banks, the memory system controller **215** may reduce latency and decrease extraneous power consumption.

(40) FIG. 3 illustrates an example of a block diagram **300** that supports dynamic status registers array in accordance with examples as disclosed herein. The block diagram **300** may illustrate a memory system controller **305** that is coupled with memory devices **310** via a plurality of channels **315** of a data bus. Memory system controller **305**, memory devices **310**, and the data bus may be examples of memory system controller **215**, memory devices **230**, and data bus **205** as described with reference to FIG. 2. In some examples, memory system controller **305** may store a mapping **320** (e.g., a table including mappings) between queue slots of a status bank of the memory devices **310** and planes of the memory devices **310**, which may allow the memory system controller **305** to associate a received status with a particular memory device and plane. By performing polling operations as described herein, the memory system controller **305** may service the first memory device **310** that is ready for servicing, thus reducing the idle time and decreasing the latency and power consumption of the system.

(41) As shown in FIG. 3, the memory devices **310** may include four (4) memory dice **325**. For example, the memory devices **310** may include a first memory die **325-a**, a second memory die **325-b**, a third memory die **325-c**, and a fourth memory die **325-d**. Each memory die **325** may include any quantity of planes, where each plane may be configured for performing access operations independent of the other planes of the memory die **325**. Moreover, although the queue

slots **345** for one status bank are pictured in FIG. 3 for each memory die **325**, each of the memory die **325** may include a plurality of status banks **340**, and each status bank **340** may include a plurality of queue slots **345**. For example, each memory die **325** may have a same quantity of queue slots **345** as the data bus has channels **315**, and may have multiple status banks, each having the quantity of queue slots **345**. As shown in FIG. 3, a first channel **315-a** may be associated with a first queue slot, a second channel **315-b** may be associated with a second queue slot, and an Nth channel **315-n** may be associated with an Nth queue slot of the illustrated status bank. Thus, a system employing multiple memory dice **325** having eight (8) status banks, each status bank **340** having eight (8) queue slots **345** (e.g., corresponding to eight (8) channels **315** of a data bus), may support concurrent polling (by status bank) of 256 operations.

(42) The memory system controller **305** may be configured to transmit a command (e.g., a first command) to the first memory die **325-a**. The command may be associated with an operation (e.g., a read operation, a write operation, an erase operation) on a plane of the first memory die **325-a**. For example, the first operation may be performed on plane **2** of the first memory die **325-a**. The command may also include an assignment of the first operation to a queue slot of a status bank associated with the first memory die **325-a**. As shown in FIG. 3, the first operation may be assigned to a queue slot of a first status bank of the memory device **310**. The queue slot may be associated with a first channel **315-a** (e.g., channel “**0**”) of a data bus for the first status bank. In some instances, the assignment may be stored to a portion of the first memory die **325-a**.

(43) In some examples, additional operations may be performed on various planes of the memory dice **325**. For example, an operation may be performed on plane **1** of the first memory die **325-a**, and the operation may be assigned to a fourth queue slot of the first status bank of the memory die **325**. Additionally or alternatively, operations may be performed on plane **3** and plane **0** of the second memory die **325-b**, plane **2** of the third memory die **325-c** and plane **1** of the fourth memory die **325-d**. The operations may be assigned to queue slots of the first status bank of the memory die **325** as illustrated in FIG. 3.

(44) The memory system controller **305** may store a mapping **320** between memory dice **325**, planes (e.g., operations performed on planes), and channels **315** of the data bus. For example, the mapping **320** may indicate that an operation was performed on plane **2** of memory die **0** (e.g., memory die **325-a**) that is associated with the first queue slot of the first status bank. Additionally or alternatively, the mapping **320** may not include any entries for queue slots of a status bank if no commands have been transmitted and assigned to the given queue slots. For example, no commands may have been transmitted to the memory dice **325** that are associated with the sixth or the seventh queue slots (e.g., associated with channels **315-f** and **315-g**, respectively) for the illustrated status bank, which is denoted by the mapping **320** indicating an “**X**” for the die and an “**X**” for the respective queue slots. However, if a command is transmitted with status associated with the sixth or the seventh queue slots for the status bank, the mapping **320** may be updated accordingly. In addition, although the mapping for memory system controller **305** is illustrated for one status bank, the mapping may include a quantity of status banks, each status bank having a quantity of queue slots (e.g., corresponding to the quantity of channels **315**).

(45) In some instances, the memory system controller **305** may transmit a command (e.g., a second command) requesting the status of one or more operations. For example, the second command may be transmitted to the first memory die **325-a**, and a memory controller associated with the first memory die **325-a** may generate status bit(s) and output the status bit(s) on the first channel **315-a** and fourth channel **315-d** of the data bus. As described herein, the status bit(s) may indicate whether the associated planes of memory die **325-a** are ready to be serviced. In other examples, the second command may be transmitted to multiple memory die **325** concurrently, and each memory die **325** may output zero, one, or more than one status bits. For example, if the second command is transmitted to memory die **325-a**, **325-b**, **325-c**, and **325-d** and indicates to output status associated with the illustrated status bank, memory die **325-a** may output the status for plane **2** on channel

315-a and plane **1** on channel **315-d**, memory die **325-b** may output the status for plane **3** on channel **315-b** and plane **0** on channel **315-n**, memory die **325-c** may output the status for plane **2** on channel **315-c**, and memory die **325-d** may output the status for plane **1** on channel **315-c**. Memory system controller **305** may thus perform concurrent polling of multiple operations across multiple memory die **325**, and may service the first memory die **325** having an operation with its status assigned to the selected status bank that indicates it is ready for service. In addition, the memory system controller **305** may maintain multiple status banks, with each status bank able to support concurrent polling for one or more memory die **325**. Once a memory die **325** is serviced, the associated portion of the mapping **320** stored to the memory system controller **305** and an associated mapping stored to the memory die **325** may be removed or replaced. For example, when plane **2** of the first memory die **325-a** is serviced, the assignment of the plane to the queue slot of the status bank may be removed (e.g., changed to having an “X” value). Thus, a subsequent operation may be assigned to the first queue slot of the first status bank of the memory die **325-a**, or for a different memory die **325**.

(46) By performing concurrent polling by assigning operations to queue slots of status banks, the memory system controller **305** may reduce latency and decrease extraneous power consumption. Moreover, the memory system controller **305** may be configured to manage polling operations for a relatively large quantity of operations in parallel.

(47) FIG. 4A illustrates an example of a timing diagram **400-a** that supports dynamic status registers array in accordance with examples as disclosed herein. The timing diagram **400-a** may be performed by processing logic that may include hardware (e.g., processing system, circuitry, dedicated logic, programmable logic, microcode, hardware of a device, integrated circuit, etc.), software (e.g., instructions run or executed on a processing device), or a combination thereof. In some examples, the timing diagram **400-a** may be performed by a system (e.g., system **200**) as described with reference to FIG. 2. For example, the timing diagram may be performed by a memory system controller (e.g., memory system controller **215** as described with reference to FIG. 2) and memory devices (e.g., memory devices **230** as described with reference to FIG. 2). In some examples, the memory system controller may execute a set of codes to control the functional elements of the memory system to perform the functions described below. FIG. 4A may illustrate the system **100** communicating signals and commands (e.g., command **235**, data **240**, and status **245** as described with reference to FIG. 2) between a memory system controller and a memory device while conducting a concurrent polling operation.

(48) FIG. 4A may illustrate a snap read command transmitted from a memory system controller to a memory device (e.g., a memory die of a memory device). The snap read command may be associated with an operation (e.g., a read operation) and may also assign the first operation to a queue slot of a status bank as described with reference to FIG. 3. In some instances, a snap read command may be transmitted to a memory device before a status operation is performed as described below with respect to FIG. 4B.

(49) A snap read command may include a first field **403** (e.g., **00h**), which may indicate a type of command (e.g., a memory command indicated by “**00h**”). In some instances, the first field **403** may be or may include an opcode for read commands. A second field **407** (e.g., **ADD**) may include a column and a row address, and a third field **409** (e.g., random read (**RR**)) may indicate the command for the snap read (e.g., random read). Additionally or alternatively, a snap read command may include a fourth field **411** (e.g., **SR#**), which may indicate a queue slot of a status bank (e.g., a status register) of the memory device to assign the associated operation to. For example, as described with reference to FIG. 3, the **SR#** may assign an operation associated with a plane associated with the command to a particular queue slot and status bank of the memory device. Accordingly, when a status operation is performed, a status bit may be output and the memory system controller may determine the plane and die associated with the status bit based on a mapping (e.g., a mapping **320** as described with reference to FIG. 3). Moreover, the snap read

command may include a fifth field **413** (e.g., **21h**), which may indicate that polling for the command will be via the status bank. In some instances, the fifth field **413** may specify a particular type of read to be performed. For example, the fifth field **413** may specify a 4 kB iWL read to be performed.

(50) FIG. **4B** illustrates an example of a timing diagram **400-b** that supports dynamic status registers array in accordance with examples as disclosed herein. The timing diagram **400-b** may be performed by processing logic that may include hardware (e.g., processing system, circuitry, dedicated logic, programmable logic, microcode, hardware of a device, integrated circuit, etc.), software (e.g., instructions run or executed on a processing device), or a combination thereof. In some examples, the timing diagram **400-b** may be performed by a system (e.g., system **200**) as described with reference to FIG. **2**. For example, the timing diagram may be performed by a memory system controller (e.g., memory system controller **215** as described with reference to FIG. **2**) and memory devices (e.g., memory devices **230** as described with reference to FIG. **2**). In some examples, the memory system controller may execute a set of codes to control the functional elements of the memory system to perform the functions described below. FIG. **4A** may illustrate the system **100** communicating signals and commands (e.g., command **235**, data **240**, and status **245** as described with reference to FIG. **2**) between a memory system controller and a memory device while conducting a concurrent polling operation.

(51) In some instances, the timing diagram **400-b** may illustrate a polling operation performed after one or more commands (e.g., including the snap read command illustrated in FIG. **4A**) have been issued. For example, multiple snap read commands may have been previously issued that resulted in assignments of operations as illustrated in FIG. **3**.

(52) In some examples, cycle type **405** may indicate the current cycle of the memory system controller or memory device—e.g., the type of signal communicated between the memory system controller and one or more memory devices via a data bus (e.g., data bus **205** as described with reference to FIG. **2**). DQ pins may be examples of data lines **410** (e.g., channels **410**) on the data bus and a quantity of DQ pins on the memory system controller. In examples where the data bus is an eight (8) bit data bus, the data bus may include eight (8) data lines—e.g., data lines **0-7**. In some examples, a memory device may output a status on a given data bus line based on a snap read command (e.g., based on the SR# of a snap read command as described with reference to FIG. **4A**). In examples where a memory device has multiple status banks, each queue slot may be associated with a dedicated channel of the data bus—e.g., memory device **230-a** may be configured to output a first status associated with a first queue slot of a selected status bank on channel **0** (e.g., DQ**0**) and a second status associated with a second queue slot on channel **1** (e.g., DQ**1**).

(53) In some cases, CE **415** may indicate a chip enable signal transmitted to a given memory device by a memory system controller via a chip enable line (e.g., chip enable line **210** as described with reference to FIG. **2**). For example, CE **0** may indicate a chip enable signal driven to a first memory device. As described with reference to FIG. **2**, the CE signals may be active-low polarity. That is, a chip enable signal on chip enable line **210** driven low may enable the memory device (e.g., coupling the data bus for commands, data input or output, or status output) and a chip enable signal driven high may disable the memory device (e.g., the memory device may decouple inputs and drivers from the data bus). Alternatively, the CE signals may operate in a similar way using active-high polarity.

(54) At **420**, a command may be transmitted. For example, a memory system controller may transmit a command (e.g., a second command) with the fields “7 Bh” and “SB#” to a memory device via a data bus. The memory system controller may transmit the command to request a status output from a particular status bank. For example, the SB# field may indicate the status bank selected to output status information from. As described herein, the memory system controller may have initiated an operation at the memory device based on issuing a snap read command as described above with reference to FIG. **4A**, and the selected status bank may be configured as

illustrated in FIG. 3.

(55) At **425**, a status of the devices under test (Dut) may be received. For example, a memory system controller may receive a status from the status bank indicated by the command **420**. The status of the devices may be received concurrently on channels **0** through **7** according to the operations assigned to the queue slots of the selected status bank. For example, as described with reference to FIG. 3, the memory system controller may be configured to determine the memory die and plane associated with a status based on the mapping **320**. In some examples, the memory device may transmit “**0b**,” which may indicate that a plane or planes associated with the respective status bank is busy. For example, each channel **410** may be driven with “**0b**” until a plane associated with a status bank has completed an operation and is ready to be serviced. For example, the first channel **410** (e.g., DQ**0**) may be driven with “**0b**” until plane **2** of the first memory die **325-a**, as described with reference to FIG. 3, has completed the operation and is ready for service. In such examples, the first channel **410** (e.g., DQ**0**) may then begin to drive a signal “**1b**” indicating plane **2** is ready to be serviced.

(56) In addition, as described with reference to FIG. 3, status may be received from additional memory die having planes associated with queue slots for the selected status bank from the command **420**. For example, at **425**, channel DQ [**1**] may be driven according to the status of D**1**P**3** (e.g., plane **3** of memory die **325-b**), channel DQ [**2**] may be driven according to the status of D**2**P**2** (e.g., plane **2** of memory die **325-c**), channel DQ [**3**] may be driven according to the status of D**0**P**1** (e.g., plane **1** of memory die **325-a**), channel DQ [**4**] may be driven according to the status of D**3**P**1** (e.g., plane **1** of memory die **325-d**), and channel DQ [**7**] may be driven according to the status of D**1**P**0** (e.g., plane **0** of memory die **325-b**), while channels DQ[**5**] and DQ [**6**] may not be associated with operations for any of the memory die **325** for the selected status bank, and may thus be left floating with drivers set to “**Xb**” (e.g., high impedance) by each of the memory die **325**. Accordingly, at **425**, any queue slot having been assigned an operation within the status bank selected by the command at **420** (e.g., by a snap read command) may output a status of the respective operation. As illustrated in FIG. 4B, plane **2** of the first memory die **325-a** may be ready for service first of the operations associated with the selected status bank, and the memory system controller may detect that plane **2** of the first memory die **325-a** has completed the operation and is ready for service.

(57) At **430**, another command may be transmitted. For example, the memory system controller may transmit the command to plane **2** of the first memory die **325-a**, as described with reference to FIG. 3, based on plane **2** being ready to be serviced. In some examples, the memory system may transmit the command to request data from plane **2** of the first memory die **325-a** associated with the completed operation. The command transmitted may indicate a type of command (e.g., read command indicated by “**06h**”), a column and row address (e.g., C & R Add), and additional information pertinent to the second command (e.g., “**E0h**”). For example, the memory system controller may indicate the read command is a single plane read, a multi-plane read, a single page read, a multi-page read, or a cache read after transmitting the second command (e.g., by transmitting “**E0h**”).

(58) At **435**, data may be received. For example, the memory system controller may receive data from plane **2** of the first memory die **325-a** in response to transmitting the command **430**. In examples where the operation performed was a program operation, at step **435** the memory system controller may transmit data to plane **2** of the first memory die **325-a**. In other examples, when the operation is an erase operation, at step **435** the memory die **325-a** may transmit a response indicating the operation was completed to the memory system controller.

(59) Subsequent to **435**, a memory system controller may transmit additional snap read commands or commands (e.g., second commands) to request a status output from the same status bank (or a different status bank). For example, after reading the data from plane **2** of the first memory die, the memory system controller may transmit a second command to again request status output from the

same status bank as shown in the command at **420**. Thus the memory system controller may again perform concurrent polling associated with the status bank to determine if any additional planes or memory die are ready for servicing and perform additional servicing commands. By performing concurrent polling by assigning operations to queue slots of status banks, the memory system controller may reduce latency and decrease extraneous power consumption. Moreover, the memory system controller may be configured to manage polling operations for a relatively large quantity of operations in parallel.

(60) FIG. 5 shows a block diagram **500** of a memory system controller **520** that supports dynamic status registers array in accordance with examples as disclosed herein. The memory system controller **520** may be an example of aspects of a memory system controller as described with reference to FIGS. 1 through 4. The memory system controller **520**, or various components thereof, may be an example of means for performing various aspects of dynamic status registers array as described herein. For example, the memory system controller **520** may include a transmission component **525**, a reception component **530**, a determination component **535**, or any combination thereof. Each of these components may communicate, directly or indirectly, with one another (e.g., via one or more buses).

(61) The transmission component **525** may be configured as or otherwise support a means for transmitting a first command associated with a first operation to a first memory die of a plurality of memory dice, where the first command includes an assignment of the first operation to a queue slot of a status bank. In some examples, the transmission component **525** may be configured as or otherwise support a means for transmitting a second command to the first memory die based at least in part on transmitting the first command, where the second command requests a status associated with the status bank.

(62) In some examples, the transmission component **525** may be configured as or otherwise support a means for transmitting a third command associated with a second operation to a second memory die of the plurality of memory dice subsequent to transmitting the first command, where the third command includes an assignment of the second operation to a second queue slot of the status bank. In some examples, the transmission component **525** may be configured as or otherwise support a means for transmitting the second command concurrently to the first memory die and the second memory die based at least in part on transmitting the first command and the third command, where the second command is further configured to request the status associated with the status bank from the second memory die.

(63) In some examples, the transmission component **525** may be configured as or otherwise support a means for transmitting a fourth command associated with a third operation to the first memory die of the plurality of memory dice based at least in part on receiving the indication of completion of the first operation, where the fourth command includes an assignment of the third operation to a queue slot of the status bank. In some examples, the transmission component **525** may be configured as or otherwise support a means for transmitting the first command via an address channel or a data channel coupled with the first memory die, where the first command includes an association between the queue slot of the status bank and the first channel of the data bus.

(64) The reception component **530** may be configured as or otherwise support a means for receiving, via a first channel of the data bus determined based at least in part on the assigned queue slot of the status bank, the status of the first operation based at least in part on transmitting the second command to the first memory die. In some examples, the reception component **530** may be configured as or otherwise support a means for receiving, via a second channel of the data bus determined based at least in part on the assigned second queue slot of the status bank, the status of the second operation based at least in part on transmitting the second command concurrently to the first memory die and the second memory die.

(65) In some examples, the first command is configured to initiate the first operation on at least one plane of the first memory die, and the determination component **535** may be configured as or

otherwise support a means for determining that the received status of the first operation is associated with the at least one plane of the first memory die based at least in part on the assigned queue slot of the status bank. In some examples, the determination component **535** may be configured as or otherwise support a means for determining that the received status of the first operation is associated with the at least one plane of the first memory die by identifying a mapping between the assigned queue slot of the status bank and the first memory die.

(66) In some examples, the first memory die includes a plurality of queue slots of each of a plurality of status banks. In some examples, each queue slot of the plurality of queue slots of each of the plurality of status banks is associated with a respective channel of the data bus.

(67) FIG. **6** shows a block diagram **600** of a memory device **620** that supports dynamic status registers array in accordance with examples as disclosed herein. The memory device **620** may be an example of aspects of a memory device as described with reference to FIGS. **1** through **4B**. The memory device **620**, or various components thereof, may be an example of means for performing various aspects of dynamic status registers array as described herein. For example, the memory device **620** may include a reception component **625**, a bit generation component **630**, an output component **635**, a queue assignment component **640**, a mapping component **645**, or any combination thereof. Each of these components may communicate, directly or indirectly, with one another (e.g., via one or more buses).

(68) The reception component **625** may be configured as or otherwise support a means for receiving a first command associated with a first operation on data, where the first command includes an assignment of the first operation to a queue slot of a status bank. In some examples, the reception component **625** may be configured as or otherwise support a means for receiving a second command requesting a status of the first operation based at least in part on receiving the first command, where the second command is associated with an output of status for the status bank on a data bus coupled with a plurality of devices, a device of the plurality of devices including the memory array and the controller.

(69) In some examples, the reception component **625** may be configured as or otherwise support a means for receiving a third command associated with a second operation on the data, where the third command is associated with a third plane of the memory array, and where the first command includes an assignment of the second operation to a second queue slot of the status bank that is different than the queue slot.

(70) The bit generation component **630** may be configured as or otherwise support a means for generating a bit indicating the status of the first operation performed on the memory array based at least in part on receiving the second command.

(71) The output component **635** may be configured as or otherwise support a means for outputting the bit onto a first channel of the data bus based at least in part on generating the bit and an association between the assigned queue slot of the status bank and the first channel.

(72) In some examples, the queue assignment component **640** may be configured as or otherwise support a means for assigning the queue slot to the first operation based at least in part on receiving the first command, where the first command is associated with a first plane of the memory array, where the generated bit indicates the status of the first operation performed on the first plane of the memory array, and the bit is output onto the first channel of the data bus based at least in part on assigning the queue slot to the first operation.

(73) In some examples, the mapping component **645** may be configured as or otherwise support a means for storing a mapping between the assigned queue slot of the status bank and the first plane of the memory array that is associated with the first operation.

(74) In some examples, a second channel of the data bus is associated with a concurrent output of a status associated with a second operation on a second plane of the memory array according to an assignment of the second operation with a second queue slot of the status bank associated with the second channel.

(75) FIG. 7 shows a flowchart illustrating a method **700** that supports dynamic status registers array in accordance with examples as disclosed herein. The operations of method **700** may be implemented by a memory system controller or its components as described herein. For example, the operations of method **700** may be performed by a memory system controller as described with reference to FIGS. 1 through 5. In some examples, a memory system controller may execute a set of instructions to control the functional elements of the device to perform the described functions. Additionally or alternatively, the memory system controller may perform aspects of the described functions using special-purpose hardware.

(76) At **705**, the method may include transmitting a first command associated with a first operation to a first memory die of a plurality of memory dice, where the first command includes an assignment of the first operation to a queue slot of a status bank. The operations of **705** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **705** may be performed by a transmission component **525** as described with reference to FIG. 5.

(77) At **710**, the method may include transmitting a second command to the first memory die based at least in part on transmitting the first command, where the second command requests a status associated with the status bank. The operations of **710** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **710** may be performed by a transmission component **525** as described with reference to FIG. 5.

(78) At **715**, the method may include receive, via a first channel of the data bus determined based at least in part on the assigned queue slot of the status bank, the status of the first operation based at least in part on transmitting the second command to the first memory die. The operations of **715** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **715** may be performed by a reception component **530** as described with reference to FIG. 5.

(79) In some examples, an apparatus as described herein may perform a method or methods, such as the method **700**. The apparatus may include, features, circuitry, logic, means, or instructions (e.g., a non-transitory computer-readable medium storing instructions executable by a processor) for transmitting a first command associated with a first operation to a first memory die of a plurality of memory dice, where the first command includes an assignment of the first operation to a queue slot of a status bank, transmitting a second command to the first memory die based at least in part on transmitting the first command, where the second command requests a status associated with the status bank, and receive, via a first channel of the data bus determined based at least in part on the assigned queue slot of the status bank, the status of the first operation based at least in part on transmitting the second command to the first memory die.

(80) Some examples of the method **700** and the apparatus described herein may further include operations, features, circuitry, logic, means, or instructions for transmitting a third command associated with a second operation to a second memory die of the plurality of memory dice subsequent to transmitting the first command, where the third command includes an assignment of the second operation to a second queue slot of the status bank.

(81) Some examples of the method **700** and the apparatus described herein may further include operations, features, circuitry, logic, means, or instructions for transmitting the second command concurrently to the first memory die and the second memory die based at least in part on transmitting the first command and the third command, where the second command may be further configured to request the status associated with the status bank from the second memory die and receiving, via a second channel of the data bus determined based at least in part on the assigned second queue slot of the status bank, the status of the second operation based at least in part on transmitting the second command concurrently to the first memory die and the second memory die.

(82) In some examples of the method **700** and the apparatus described herein, and the method, apparatuses, and non-transitory computer-readable medium may include further operations,

features, circuitry, logic, means, or instructions for transmitting a fourth command associated with a third operation to the first memory die of the plurality of memory dice based at least in part on receiving the indication of completion of the first operation, where the fourth command includes an assignment of the third operation to a queue slot of the status bank.

(83) In some examples of the method **700** and the apparatus described herein, the first command may be configured to initiate the first operation on at least one plane of the first memory die and the method, apparatuses, and non-transitory computer-readable medium may include further operations, features, circuitry, logic, means, or instructions for determining that the received status of the first operation may be associated with the at least one plane of the first memory die based at least in part on the assigned queue slot of the status bank.

(84) Some examples of the method **700** and the apparatus described herein may further include operations, features, circuitry, logic, means, or instructions for determining that the received status of the first operation may be associated with the at least one plane of the first memory die by identifying a mapping between the assigned queue slot of the status bank and the first memory die.

(85) Some examples of the method **700** and the apparatus described herein may further include operations, features, circuitry, logic, means, or instructions for transmitting the first command via an address channel or a data channel coupled with the first memory die, where the first command includes an association between the queue slot of the status bank and the first channel of the data bus.

(86) In some examples of the method **700** and the apparatus described herein, the first memory die includes a plurality of queue slots of each of a plurality of status banks, and each queue slot of the plurality of queue slots of each of the plurality of status banks may be associated with a respective channel of the data bus.

(87) FIG. **8** shows a flowchart illustrating a method **800** that supports dynamic status registers array in accordance with examples as disclosed herein. The operations of method **800** may be implemented by a memory device or its components as described herein. For example, the operations of method **800** may be performed by a memory device as described with reference to FIGS. **1** through **4** and **6**. In some examples, a memory device may execute a set of instructions to control the functional elements of the device to perform the described functions. Additionally or alternatively, the memory device may perform aspects of the described functions using special-purpose hardware.

(88) At **805**, the method may include receiving a first command associated with a first operation on data, where the first command includes an assignment of the first operation to a queue slot of a status bank. The operations of **805** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **805** may be performed by a reception component **625** as described with reference to FIG. **6**.

(89) At **810**, the method may include receiving a second command requesting a status of the first operation based at least in part on receiving the first command, where the second command is associated with an output of status for the status bank on a data bus coupled with a plurality of devices, a device of the plurality of devices including the memory array and the controller. The operations of **810** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **810** may be performed by a reception component **625** as described with reference to FIG. **6**.

(90) At **815**, the method may include generating a bit indicating the status of the first operation performed on the memory array based at least in part on receiving the second command. The operations of **815** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **815** may be performed by a bit generation component **630** as described with reference to FIG. **6**.

(91) At **820**, the method may include outputting the bit onto a first channel of the data bus based at least in part on generating the bit and an association between the assigned queue slot of the status

bank and the first channel. The operations of **820** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **820** may be performed by an output component **635** as described with reference to FIG. 6.

(92) In some examples, an apparatus as described herein may perform a method or methods, such as the method **800**. The apparatus may include, features, circuitry, logic, means, or instructions (e.g., a non-transitory computer-readable medium storing instructions executable by a processor) for receiving a first command associated with a first operation on data, where the first command includes an assignment of the first operation to a queue slot of a status bank, receiving a second command requesting a status of the first operation based at least in part on receiving the first command, where the second command is associated with an output of status for the status bank on a data bus coupled with a plurality of devices, a device of the plurality of devices including the memory array and the controller, generating a bit indicating the status of the first operation performed on the memory array based at least in part on receiving the second command, and outputting the bit onto a first channel of the data bus based at least in part on generating the bit and an association between the assigned queue slot of the status bank and the first channel.

(93) Some examples of the method **800** and the apparatus described herein may further include operations, features, circuitry, logic, means, or instructions for assigning the queue slot to the first operation based at least in part on receiving the first command, where the first command may be associated with a first plane of the memory array, where the generated bit indicates the status of the first operation performed on the first plane of the memory array, and the bit may be output onto the first channel of the data bus based at least in part on assigning the queue slot to the first operation.

(94) In some examples of the method **800** and the apparatus described herein, a second channel of the data bus may be associated with a concurrent output of a status associated with a second operation on a second plane of the memory array according to an assignment of the second operation with a second queue slot of the status bank associated with the second channel.

(95) Some examples of the method **800** and the apparatus described herein may further include operations, features, circuitry, logic, means, or instructions for storing a mapping between the assigned queue slot of the status bank and the first plane of the memory array that may be associated with the first operation.

(96) Some examples of the method **800** and the apparatus described herein may further include operations, features, circuitry, logic, means, or instructions for receiving a third command associated with a second operation on the data, where the third command may be associated with a third plane of the memory array, and where the first command includes an assignment of the second operation to a second queue slot of the status bank that may be different than the queue slot.

(97) It should be noted that the methods described above describe possible implementations, and that the operations and the steps may be rearranged or otherwise modified and that other implementations are possible. Further, portions from two or more of the methods may be combined.

(98) Information and signals described herein may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the above description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof. Some drawings may illustrate signals as a single signal; however, the signal may represent a bus of signals, where the bus may have a variety of bit widths.

(99) The terms “electronic communication,” “conductive contact,” “connected,” and “coupled” may refer to a relationship between components that supports the flow of signals between the components. Components are considered in electronic communication with (or in conductive contact with or connected with or coupled with) one another if there is any conductive path between the components that can, at any time, support the flow of signals between the components. At any given time, the conductive path between components that are in electronic communication

with each other (or in conductive contact with or connected with or coupled with) may be an open circuit or a closed circuit based on the operation of the device that includes the connected components. The conductive path between connected components may be a direct conductive path between the components or the conductive path between connected components may be an indirect conductive path that may include intermediate components, such as switches, transistors, or other components. In some examples, the flow of signals between the connected components may be interrupted for a time, for example, using one or more intermediate components such as switches or transistors.

(100) The term “coupling” refers to a condition of moving from an open-circuit relationship between components in which signals are not presently capable of being communicated between the components over a conductive path to a closed-circuit relationship between components in which signals are capable of being communicated between components over the conductive path. If a component, such as a controller, couples other components together, the component initiates a change that allows signals to flow between the other components over a conductive path that previously did not permit signals to flow.

(101) The term “isolated” refers to a relationship between components in which signals are not presently capable of flowing between the components. Components are isolated from each other if there is an open circuit between them. For example, two components separated by a switch that is positioned between the components are isolated from each other if the switch is open. If a controller isolates two components, the controller affects a change that prevents signals from flowing between the components using a conductive path that previously permitted signals to flow.

(102) The terms “if,” “when,” “based on,” or “based at least in part on” may be used interchangeably. In some examples, if the terms “if,” “when,” “based on,” or “based at least in part on” are used to describe a conditional action, a conditional process, or connection between portions of a process, the terms may be interchangeable.

(103) The term “in response to” may refer to one condition or action occurring at least partially, if not fully, as a result of a previous condition or action. For example, a first condition or action may be performed and second condition or action may at least partially occur as a result of the previous condition or action occurring (whether directly after or after one or more other intermediate conditions or actions occurring after the first condition or action).

(104) Additionally, the terms “directly in response to” or “in direct response to” may refer to one condition or action occurring as a direct result of a previous condition or action. In some examples, a first condition or action may be performed and second condition or action may occur directly as a result of the previous condition or action occurring independent of whether other conditions or actions occur. In some examples, a first condition or action may be performed and second condition or action may occur directly as a result of the previous condition or action occurring, such that no other intermediate conditions or actions occur between the earlier condition or action and the second condition or action or a limited quantity of one or more intermediate steps or actions occur between the earlier condition or action and the second condition or action. Any condition or action described herein as being performed “based on,” “based at least in part on,” or “in response to” some other step, action, event, or condition may additionally or alternatively (e.g., in an alternative example) be performed “in direct response to” or “directly in response to” such other condition or action unless otherwise specified.

(105) The devices discussed herein, including a memory array, may be formed on a semiconductor substrate, such as silicon, germanium, silicon-germanium alloy, gallium arsenide, gallium nitride, etc. In some examples, the substrate is a semiconductor wafer. In some other examples, the substrate may be a silicon-on-insulator (SOI) substrate, such as silicon-on-glass (SOG) or silicon-on-sapphire (SOP), or epitaxial layers of semiconductor materials on another substrate. The conductivity of the substrate, or sub-regions of the substrate, may be controlled through doping using various chemical species including, but not limited to, phosphorous, boron, or arsenic.

Doping may be performed during the initial formation or growth of the substrate, by ion-implantation, or by any other doping means.

(106) A switching component or a transistor discussed herein may represent a field-effect transistor (FET) and comprise a three terminal device including a source, drain, and gate. The terminals may be connected to other electronic elements through conductive materials, e.g., metals. The source and drain may be conductive and may comprise a heavily-doped, e.g., degenerate, semiconductor region. The source and drain may be separated by a lightly-doped semiconductor region or channel. If the channel is n-type (i.e., majority carriers are electrons), then the FET may be referred to as an n-type FET. If the channel is p-type (i.e., majority carriers are holes), then the FET may be referred to as a p-type FET. The channel may be capped by an insulating gate oxide. The channel conductivity may be controlled by applying a voltage to the gate. For example, applying a positive voltage or negative voltage to an n-type FET or a p-type FET, respectively, may result in the channel becoming conductive. A transistor may be “on” or “activated” if a voltage greater than or equal to the transistor's threshold voltage is applied to the transistor gate. The transistor may be “off” or “deactivated” if a voltage less than the transistor's threshold voltage is applied to the transistor gate.

(107) The description set forth herein, in connection with the appended drawings, describes example configurations and does not represent all the examples that may be implemented or that are within the scope of the claims. The term “exemplary” used herein means “serving as an example, instance, or illustration” and not “preferred” or “advantageous over other examples.” The detailed description includes specific details to providing an understanding of the described techniques. These techniques, however, may be practiced without these specific details. In some instances, well-known structures and devices are shown in block diagram form to avoid obscuring the concepts of the described examples.

(108) In the appended figures, similar components or features may have the same reference label. Further, various components of the same type may be distinguished by following the reference label by a hyphen and a second label that distinguishes among the similar components. If just the first reference label is used in the specification, the description is applicable to any one of the similar components having the same first reference label irrespective of the second reference label.

(109) The functions described herein may be implemented in hardware, software executed by a processor, firmware, or any combination thereof. If implemented in software executed by a processor, the functions may be stored on or transmitted over, as one or more instructions or code, a computer-readable medium. Other examples and implementations are within the scope of the disclosure and appended claims. For example, due to the nature of software, functions described above can be implemented using software executed by a processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations.

(110) For example, the various illustrative blocks and components described in connection with the disclosure herein may be implemented or performed with a general-purpose processor, a DSP, an ASIC, an FPGA or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor, but in the alternative, the processor may be any processor, controller, microcontroller, or state machine. A processor may be implemented as a combination of computing devices (e.g., a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration).

(111) As used herein, including in the claims, “or” as used in a list of items (for example, a list of items prefaced by a phrase such as “at least one of” or “one or more of”) indicates an inclusive list such that, for example, a list of at least one of A, B, or C means A or B or C or AB or AC or BC or

ABC (i.e., A and B and C). Also, as used herein, the phrase “based on” shall not be construed as a reference to a closed set of conditions. For example, an exemplary step that is described as “based on condition A” may be based on both a condition A and a condition B without departing from the scope of the present disclosure. In other words, as used herein, the phrase “based on” shall be construed in the same manner as the phrase “based at least in part on.”

(112) Computer-readable media includes both non-transitory computer storage media and communication media including any medium that facilitates transfer of a computer program from one place to another. A non-transitory storage medium may be any available medium that can be accessed by a general purpose or special purpose computer. By way of example, and not limitation, non-transitory computer-readable media can comprise RAM, ROM, electrically erasable programmable read-only memory (EEPROM), compact disk (CD) ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other non-transitory medium that can be used to carry or store desired program code means in the form of instructions or data structures and that can be accessed by a general-purpose or special-purpose computer, or a general-purpose or special-purpose processor. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of medium. Disk and disc, as used herein, include CD, laser disc, optical disc, digital versatile disc (DVD), floppy disk, and Blu-ray disc, where disks usually reproduce data magnetically, while discs reproduce data optically with lasers. Combinations of the above are also included within the scope of computer-readable media.

(113) The description herein is provided to enable a person skilled in the art to make or use the disclosure. Various modifications to the disclosure will be apparent to those skilled in the art, and the generic principles defined herein may be applied to other variations without departing from the scope of the disclosure. Thus, the disclosure is not limited to the examples and designs described herein but is to be accorded the broadest scope consistent with the principles and novel features disclosed herein.

Claims

1. A memory system, comprising: a plurality of memory devices; a data bus coupled with each of the plurality of memory devices; and processing circuitry coupled with at least some of the plurality of memory devices via the data bus, the processing circuitry configured to: transmit a first command associated with a first operation to a first memory device of the plurality of memory devices, wherein the first command comprises an assignment of the first operation to a first queue slot of a status bank; transmit a second command concurrently to the first memory device and a second memory device in response to transmitting the first command, wherein the second command requests a first status associated with the status bank from the first memory device and a second status associated with the status bank from the second memory device; receive, from the first memory device via a first channel of the data bus determined in accordance with the assigned first queue slot of the status bank, the first status associated with the first memory device in response to transmitting the first command to the first memory device; and receive, from the second memory device of the plurality of memory devices via a second channel of the data bus determined in accordance with a second queue slot of the status bank different than the first queue slot, the second status associated with the second memory device.

2. The memory system of claim 1, wherein the processing circuitry is further configured to: transmit a third command associated with a second operation to the second memory device subsequent to transmitting the first command, wherein the third command comprises a second

assignment of the second operation to the second queue slot of the status bank.

3. The memory system of claim 1, wherein transmitting the second command concurrently to the first memory device and the second memory device comprises: transmitting a first chip enable signal associated with the first memory device concurrently with a second chip enable signal associated with the second memory device, wherein the first chip enable signal activates the first memory device and the second chip enable signal activates the second memory device.

4. The memory system of claim 1, wherein the first status associated with the first memory device comprises a first value indicating that the first memory device is ready to be serviced and the second status associated with the second memory device comprises a second value indicating that the second memory device is busy.

5. The memory system of claim 1, wherein receiving the first status associated with the first memory device comprises receiving an indication of completion of the first operation, wherein the processing circuitry is further configured to: transmit a fourth command associated with a third operation to the first memory device in response to receiving the indication of the completion of the first operation, wherein the fourth command comprises a second assignment of the third operation to the first queue slot of the status bank.

6. The memory system of claim 1, wherein the first command is configured to initiate the first operation on at least one plane of the first memory device, wherein the processing circuitry is further configured to: determine that the received first status associated with the first memory device is associated with the at least one plane of the first memory device in accordance with the assigned first queue slot of the status bank.

7. The memory system of claim 6, wherein the processing circuitry is further configured to: determine that the received first status associated with the first memory device is associated with the at least one plane of the first memory device by identifying a mapping between the assigned first queue slot of the status bank and the first memory device.

8. The memory system of claim 1, wherein the processing circuitry is further configured to: transmit the first command via an address channel or a data channel coupled with the first memory device, wherein the first command comprises an association between the first queue slot of the status bank and the first channel of the data bus.

9. A memory system, comprising: a plurality of memory devices; a data bus coupled with each of the plurality of memory devices; and processing circuitry coupled with at least some of the plurality of memory devices via the data bus, the processing circuitry configured to: transmit a first command associated with a first operation to a first memory device of the plurality of memory devices, wherein the first command comprises an assignment of the first operation to a first queue slot of a status bank. wherein the first memory device comprises a plurality of queue slots of each of a plurality of status banks, wherein each queue slot of the plurality of queue slots of each of the plurality of status banks is associated with a respective channel of the data bus; receive, from the first memory device via a first channel of the data bus determined in accordance with the assigned first queue slot of the status bank, a first status associated with the first memory device in response to transmitting the first command to the first memory device; and receive, from a second memory device of the plurality of memory devices via a second channel of the data bus determined in accordance with a second queue slot of the status bank different than the first queue slot, a second status associated with the second memory device.

10. A memory system, comprising: one or more memory devices comprising a plurality of planes; a data bus coupled with the one or more memory devices; and processing circuitry coupled with the one or more memory devices via the data bus, the processing circuitry configured to: transmit, to the one or more memory devices, a first command associated with a first operation corresponding to a first plane of the plurality of planes, wherein the first command comprises an assignment of the first operation to a queue slot of a status bank; transmit, to the one or more memory devices, a second command in response to transmitting the first command, wherein the second command

requests a status associated with the status bank; receive, via a first channel of the data bus determined in accordance with the assigned queue slot of the status bank, the status of the first operation in response to transmitting the second command to the one or more memory devices, wherein receiving the status of the first operation comprises receiving an indication of completion of the first operation; and remove the assignment of the first operation to the queue slot of the status bank in response to the indication of the completion of the first operation.

11. The memory system of claim 10, wherein the processing circuitry is further configured to: transmit a third command associated with a second operation corresponding to a second plane of the plurality of planes subsequent to transmitting the first command, wherein the third command comprises a second assignment of the second operation to a second queue slot of the status bank.

12. The memory system of claim 11, wherein the processing circuitry is further configured to: receive, via a second channel of the data bus determined in accordance with the assigned second queue slot of the status bank, the status of the second operation in response to transmitting the second command.

13. The memory system of claim 10, wherein the processing circuitry is further configured to: transmit a fourth command associated with a third operation corresponding to the first plane of the plurality of planes in response to receiving the indication of the completion of the first operation, wherein the fourth command comprises a second assignment of the third operation to the queue slot of the status bank.

14. The memory system of claim 10, wherein the processing circuitry is further configured to: determine that the received status of the first operation corresponds to the first plane in accordance with the assigned queue slot of the status bank.

15. The memory system of claim 10, wherein the one or more memory devices comprises a plurality of queue slots of each of a plurality of status banks, wherein each queue slot of the plurality of queue slots of each of the plurality of status banks is associated with a respective channel of the data bus.

16. A memory system, comprising: one or more memory devices comprising a plurality of planes; a data bus coupled with the one or more memory devices; and processing circuitry coupled with the one or more memory devices via the data bus, the processing circuitry configured to: transmit, to the one or more memory devices, a first command associated with a first operation corresponding to a first plane of the plurality of planes, wherein the first command comprises an assignment of the first operation to a queue slot of a status bank; transmit, to the one or more memory devices, a second command in response to transmitting the first command, wherein the second command requests a status associated with the status bank; receive, via a first channel of the data bus determined in accordance with the assigned queue slot of the status bank, the status of the first operation in response to transmitting the second command to the one or more memory devices; store, at the memory system, a mapping that indicates respective associations between each plane of the plurality of planes and a respective queue slot of the status bank, each queue slot corresponding to a respective channel of the data bus; and determine that the received status of the first operation corresponds to the first plane in accordance with the assigned queue slot of the status bank, wherein determining that the received status of the first operation corresponds to the first plane is in accordance with the stored mapping.

17. The memory system of claim 16, wherein the stored mapping indicates that the first plane corresponds to a first memory die of the one or more memory devices and that a second plane of the plurality of planes corresponds to a second memory die of the one or more memory devices.

18. A non-transitory computer-readable medium storing code comprising instructions which, when executed by a processor of a memory system, cause the memory system to: transmit a first command associated with a first operation to a first memory device of a plurality of memory devices of the memory system, wherein the first command comprises an assignment of the first operation to a first queue slot of a status bank; transmit a second command concurrently to the first

memory device and a second memory device in response to transmitting the first command, wherein the second command requests a first status associated with the status bank from the first memory device and a second status associated with the status bank from the second memory device; receive, from the first memory device via a first channel of a data bus determined in accordance with the assigned first queue slot of the status bank, the first status associated with the first memory device in response to transmitting the first command to the first memory device; and receive, from the second memory device of the plurality of memory devices via a second channel of the data bus determined in accordance with a second queue slot of the status bank different than the first queue slot, the second status associated with the second memory device.
