

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407165
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Khalid; Muhammad

Fault recovery controller for integrated solar PV system

Abstract

A reactive power support system for a radial distribution network includes multiple loads, a radial distribution transmission line (RDTL) connected at a first end to a grid transformer, a point of common coupling (PCC) connected to a second end of the RDTL, a solar power inverter connected in parallel with a photovoltaic module and an inverter controller connected to the inverter. An output terminal of the inverter is connected to the PCC. Each load is connected by a load bus to the RDTL. The inverter controller provides gate control signals which switch a set of transistor gates of the inverter to operate at less than or greater than a unity power factor to inject or to absorb the reactive power, respectively, at the PCC in order to regulate a voltage of the RDTL during a three-phase to ground fault on a load bus connected to one of the loads.

Inventors: Khalid; Muhammad (Dhahran, SA)

Applicant: KING FAHD UNIVERSITY OF PETROLEUM AND MINERALS (Dhahran, SA)

Family ID: 94975966

Assignee: KING FAHD UNIVERSITY OF PETROLEUM AND MINERALS (Dhahran, SA)

Appl. No.: 18/394452

Filed: December 22, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20250096566 A1	Mar. 20, 2025

Related U.S. Application Data

us-provisional-application US 63583075 20230915

Publication Classification

Int. Cl.: H02J3/18 (20060101); H02M7/537 (20060101)

U.S. Cl.:

CPC H02J3/1878 (20130101); H02M7/537 (20130101);

Field of Classification Search

CPC: H02J (3/18); H02J (3/1878); H02M (7/537)

USPC: 307/31

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2018/0115255	12/2017	Jalili	N/A	N/A
2020/0064782	12/2019	Li et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
109713711	12/2021	CN	N/A

OTHER PUBLICATIONS

Molina-Garcia et al.: “Reactive Power flow Control for PV Inverters Voltage Support in LV Distribution Networks”; IEEE Transactions on Smart Grid, vol. 8, No. 1; Jan. 2017; pp. 447-456. (Year: 2017). cited by examiner

El Moursi et al. ; Fault ride through capability for grid interfacing large scale PV power plants ; IET Generation, Transmission & Distribution, vol. 7, Iss. 9 ; Apr. 23, 2013 ; 11 Pages. cited by applicant

Molina-Garcia et al. ; Reactive Power Flow Control for PV Inverters Voltage Support in LV Distribution Networks ; IEEE Transactions on Smart Grid, vol. 8, Issue 1 ; Nov. 4, 2016 ; Abstract Only ; 1 Page. cited by applicant

Primary Examiner: Kaplan; Hal

Attorney, Agent or Firm: Oblon, McClelland, Maier & Neustadt, L.L.P.

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS (1) The present application claims the benefit of priority to U.S. Prov. App. No. 63/583,075, titled “Fault Recovery Controller for Integrated Solar PV System”, filed on Sep. 15, 2023.

STATEMENT REGARDING PRIOR DISCLOSURE BY THE INVENTORS

(1) Aspects of this technology are described in an article “Voltage Recovery Through Active-Reactive Coordination of Solar PV Inverters During Grid Fault”, published by 2022 11th

International Conference on Renewable Energy Research and Application (ICRERA), Istanbul, Turkey, 2022, pp. 395-399, doi: 10.1109/ICRERA55966.2022.9922796, on Oct. 25, 2022, incorporated herein by reference in its entirety.

STATEMENT OF ACKNOWLEDGEMENT

(2) The inventor(s) acknowledge the financial support provided by the King Fahd University of Petroleum and Minerals (KFUPM), Riyadh, Saudi Arabia through Project #INRE2106.

BACKGROUND

Technical Field

(3) The present disclosure is directed to a method for controlling a photovoltaic inverter for the ride-through of a network fault, and more particularly relates to a fault recovery controller for an integrated solar PV system.

Description of Related Art

(4) The “background” description provided herein is for the purpose of generally presenting the context of the disclosure. Work of the presently named inventors, to the extent it is described in this background section, as well as aspects of the description which may not otherwise qualify as prior art at the time of filing, are neither expressly or impliedly admitted as prior art against the present invention.

(5) Establishment of a green and sustainable energy sector highlights the growing acceptance of renewable energy sources. Accommodating variable renewable energy sources becomes increasingly challenging at higher penetration levels. Currently, more reliable energy management strategies and standards need to be formulated to mitigate the impact of variable renewable energy sources (RES) and introduce a more effective form of power system flexibility.

(6) The integration of renewable energy sources, such as solar, wind, or similar sources, with a power grid can be accomplished through various means. Renewable energy sources often include an inverter to convert the DC signal from the renewable source into an AC signal to support the grid in accordance with electricity demand. However, during faults, such as a grid fault, LLL fault, LLLG fault, etc., the assignment of a fixed power factor of the inverter for the integrated renewable energy sources with the grid can help mitigate the aforementioned fault.

(7) Following recommendations by the IEEE-1547 standard regarding the restriction of voltage regulation by distributed generators, most inverters are permitted to operate at a fixed unity power factor with negligible reactive power injection or absorption in both small and large renewable distributed generator interconnections. However, due to renewable intermittency, this active power injection initiates an undesirable trend of steady-state voltage variations during ramped renewable distributed output or light loading periods.

(8) Some utilities have achieved voltage regulation by stipulating a fixed predetermined reactive power compensation capability of inverters. This is accomplished through either “fixed Q” (where Q refers to a reactive power factor) and/or “fixed $\cos \varphi$ ” (where $\cos \varphi$ refers to an angle between the real and apparent power) methods. Although these methodologies do not actively alleviate voltage variations, with thorough study before interconnection, they can, to some extent, establish reactive power flow between the grid and distributed generators (DGs), thereby mitigating voltage fluctuations or any one of faults including L (single line-to-ground fault), LL (double line-to-ground fault), LLL (triple line-to-ground fault), L-G (line-to-ground fault), LL-G (double line-to-ground fault) or LLL-G (triple line-to-ground fault) faults arising from intermittent distributed generator active power output.

(9) Quantifying the reactive power capability of the inverter in a PV system has been proposed. For instance, US20200064782A1 describes a centralized control technique for multiple inverters that were evaluated on a distributed grid system, in contrast to a radial distribution grid where voltage vulnerability and sensitivity are higher. However, US20200064782A1 employs Artificial Neural Network (ANN) techniques to determine the D and Q outputs of the inverter, which are then used to compute the necessary reactive power for grid stabilization. Using an ANN to compute the D

and Q outputs increases the computational cost and complexity.

(10) CN109713711B describes a reactive coordination control strategy for distributed photovoltaic inverters under faults, employing equal reactive power injection from all inverters. However, the document relies on centralized coordination and is designed for coordinated active/reactive power control of distributed inverters. The centralized coordination approach raises the computation cost of the system. Additionally, the method involves a complex procedure to control the inverter controller for reactive power computation.

(11) US20180115255A1 outlines a method for controlling an inverter connected between a photovoltaic generator and a power supply network to facilitate the ride-through of a network fault, focusing on controlling the DC link voltage. However, the methodology does not include generating reactive power from the inverter for grid stability.

(12) A control method can be used to enhance fault ride-through capability for utility-scale photovoltaic power plants. (See: Mohamed Shawky El Moursi, Weidong Xiao, Jim. L. Kirtley Jr, "Fault ride-through capability for grid interfacing large scale PV power plants," WILEY, doi: <https://doi.org/10.1049/iet-gtd.2013.0154>). Disabling maximum power point tracking (MPPT) operation and halting active power injection when the grid voltage, v_g , falls below 0.7 p.u. are included. However, ceasing active power injection may result in undesired curtailment of the active power generated by the PV system.

(13) A reactive power flow control aiming to actively integrate photovoltaic systems into LV distribution networks was proposed (See: Ángel Molina-García, Rosa A. Mastromauro, Tania García-Sánchez, Sante Pugliese, Marco Liserre, Silvio Stasi, "Reactive Power Flow Control for PV Inverters Voltage Support in LV Distribution Networks", IEEE Access, Volume: 8, Issue: 1, Pages 447-456, doi: 10.1109/TSG.2016.2625314). The controller establishes P-w and Q-V parameters using predefined reactive power capability curves for 6 kW inverters. However, injecting reactive power at a bus or grid fault is not described.

(14) Each of the previously mentioned methods or systems has one or more limitations that hinder their widespread adoption. Consequently, there is a need for systems and methods capable of providing reactive power to the grid from a grid-connected PV inverter during LLL or LLLG faults.

SUMMARY

(15) In an exemplary embodiment, a reactive power support system for a radial distribution network is described. The reactive power support system for a radial distribution network comprises a radial distribution transmission line connected at a first end to a grid transformer and a plurality of loads. Each load is connected by a load bus to the radial distribution transmission line. The reactive power support system further comprises a point of common coupling connected to a second end of the radial distribution transmission line, a photovoltaic module and a solar power inverter connected in parallel with the photovoltaic module. The solar power inverter has an output terminal configured to connect to the point of common coupling. The reactive power support system further comprises an inverter controller connected to the solar power inverter. The inverter controller is configured to provide gate control signals which switch a set of transistor gates of the solar power inverter to operate at less than or greater than a unity power factor to provide reactive power or to absorb reactive power respectively at the point of common coupling in order to regulate a voltage of the radial distribution transmission line during a three-phase to ground fault on a load bus connected to one of the loads.

(16) In another exemplary embodiment, a method of providing reactive power support to a radial distribution network is described. The method includes connecting a first end radial distribution transmission line to a grid transformer. The method further includes connecting a plurality of loads in parallel to the radial distribution transmission line. The method further includes installing a photovoltaic module. The method further includes connecting a solar power inverter in parallel with the photovoltaic module. The method further includes connecting an output terminal of the solar power inverter to a point of common coupling at a second end of the radial distribution

transmission line. The method further includes connecting an inverter controller to the solar power inverter. The method further includes measuring, with a voltmeter, a voltage at the point of common coupling. The method further includes receiving, by the inverter controller, the voltage measured at the point of common coupling and a voltage reference value. The method further includes generating, by the inverter controller, gate control signals configured to switch a set of transistor gates of the solar power inverter to operate at less than or greater than a unity power factor to provide reactive power to or to absorb reactive power at the point of common coupling respectively when the voltage measured at the point of common coupling is less than or greater than the voltage reference value due to a three-phase to ground fault on a load bus connected to one of the loads.

(17) In another exemplary embodiment, a method of providing reactive power support by a photovoltaic module to a grid connected radial distribution network connected to a plurality of load buses is described. The method includes installing a photovoltaic module and connecting a solar power inverter in parallel with the photovoltaic module. The method further includes connecting an output terminal of the solar power inverter to a point of common coupling of the radial distribution transmission line and connecting an inverter controller to the solar power inverter. The method further includes measuring, with a voltmeter, a voltage at the point of common coupling. The method further includes receiving, by the inverter controller, the voltage measured at the point of common coupling and a voltage reference value. The method further includes generating, by the inverter controller, gate control signals configured to switch a set of transistor gates of the solar power inverter to operate at less than or greater than a unity power factor to provide reactive power to or to absorb reactive power at the point of common coupling respectively when the voltage measured at the point of common coupling is less than or greater than the voltage reference value due to a three-phase to ground fault on a load bus connected to one of the loads.

(18) The foregoing general description of the illustrative embodiments and the following detailed description thereof are merely exemplary aspects of the teachings of this disclosure, and are not restrictive.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) A more complete appreciation of this disclosure and many of the attendant advantages thereof will be readily obtained as the same becomes better understood by reference to the following detailed description when considered in connection with the accompanying drawings, wherein:

(2) FIG. 1 illustrates a simple two-bus distribution network.

(3) FIG. 2 illustrates a multi-bus distribution network with a distributed generator connected to a bus.

(4) FIG. 3 illustrates a radial distribution network including a reactive power support system, according to certain embodiments.

(5) FIG. 4 illustrates a voltage profile during an LLL-G fault at a first bus, according to certain exemplary embodiments.

(6) FIG. 5A illustrates a voltage profile during the LLL-G fault at a fourth bus, according to certain exemplary embodiments.

(7) FIG. 5B illustrates a voltage profile during the LLL-G fault at a sixth bus, according to certain exemplary embodiments.

(8) FIG. 6 illustrates a flowchart of a method of providing a reactive power support to a radial distribution network, according to certain embodiments.

(9) FIG. 7 illustrates details of the hardware description of the computing environment, according to exemplary embodiments.

(10) FIG. 8 illustrates a schematic diagram of a data processing system, according to certain embodiments, for performing the functions of the exemplary embodiments.

(11) FIG. 9 shows one implementation of a CPU, according to certain embodiments.

(12) FIG. 10 illustrates various distributed components of a system for executing the functions and features as described in the disclosure, according to certain embodiments.

DETAILED DESCRIPTION

(13) In the drawings, like reference numerals designate identical or corresponding parts throughout the several views. Further, as used herein, the words “a”, “an” and the like generally carry a meaning of “one or more”, unless stated otherwise.

(14) Furthermore, the terms “approximately,” “approximate”, “about” and similar terms generally refer to ranges that include the identified value within a margin of 20%, 10%, or preferably 5%, and any values therebetween.

(15) Aspects of this disclosure are directed to a reactive power support system for a radial distribution network, a method of providing reactive power support to a radial distribution network and a method of providing reactive power support by a photovoltaic module to a grid connected radial distribution network connected to a plurality of load buses. The reactive power support system is configured to provide the reactive power by operating a voltage inverter connected to a PV panel at a non-unitary power factor to generate the reactive power to compensate for one or more grid faults. The reactive power support system is configured with a control curve that establishes the relation between the active-reactive power with the bus voltage in the radial distribution network.

(16) FIG. 1 illustrates a conventional simplified two-bus distribution network **100**. The simplified two-bus distribution network **100** may be a radial distribution network, such as, but not limited to, a ring-type radial distribution network, an interconnected type of radial distribution network, or various other types of radial distribution networks. The two-bus distribution network **100** includes an electrical distribution station **102**. The electrical distribution station **102** may refer to, but is not limited to an electrical substation, distribution substations, a radial distribution system or the like. The two-bus distribution network **100** includes an on-load tap changer **104** along with a transformer (indicated by the double circle symbol). The on-load tap changer **104** regulates the output voltage of the transformer (not shown). The regulation is performed by altering the turn ratios of the transformer (not shown) by changing the number of turns in one winding. The regulation ensures the quality of the voltage by increasing the grid voltage through the electrical distribution station **102** when power consumption is high and reducing it when power consumption is low. The on-load tap changer **104** may be a reactance type, resistive type or the like. The two-bus distribution network **100** further includes buses **106** and **110** electrically coupled with the on-load tap changer **104**, and a transmission line **108** with electrical impedance $R+jX$ between the buses **106** and **110**. PL and QL represent a real and reactive power, respectively, of a load (not shown) coupled with the bus **110**. The active and reactive power is represented by P and Q, respectively. The sending end voltage is represented as V_s , and V_r denotes the receiving end voltage in the two-bus distribution network **100**.

(17) Active voltage regulation can be established as a function of a local variable for the two-bus distribution network **100**. The relationship between system variables and parameters can be established. For instance, the power factor of a distributed generator (not shown), such as solar PV or wind system integrated into the two-bus distribution network **100**, may be actively adjusted as a function of the locally measured active power injected into the grid (not shown) by the distributed generator (not shown). This adjustment limits the impact of active power variation and simultaneous mitigation of the voltage regulation through reactive power compensation is achieved. Mathematically, the expression is shown as below:

$$(18) \quad \hat{V}_s = \hat{V}_s + \frac{RP + XQ}{\hat{V}_s^*} + j \frac{XP + RQ}{\hat{V}_s^*}, \quad (1) \quad \hat{V} = \hat{V}_s = \hat{V}_s + \frac{RP + XQ}{\hat{V}_s^*} + j \frac{XP + RQ}{\hat{V}_s^*}, \quad (2)$$

where, {circumflex over (V)}.sub.s denotes a value of a voltage vector at the sending end, that is, the bus **106**; {circumflex over (V)}.sub.R denotes a value of a voltage vector at the receiving end, that is, the bus **110**; and $\Delta\{\text{circumflex over (V)}\}$ denotes a value of a voltage drop between the sending end and the receiving end.

(19) The voltage drop $\Delta\{\text{circumflex over (V)}\}$ can be considered equal to the real part in equation (2) since the phase difference between {circumflex over (V)}.sub.s and {circumflex over (V)}.sub.R is considered to be negligible.

(20) Considering {circumflex over (V)}.sub.s=|V.sub.S|=V.sub.S=absolute value of V.sub.s, equation 2 can be re-written as below:

$$(21) \quad V \approx \frac{RP + XQ}{V_s}. \quad (3)$$

(22) If the sending end voltage at bus **106** is considered as a base voltage or per unit voltage, equation 3 can be re-written as:

$$(23) \quad V \approx RP + XQ. \quad (4)$$

(24) Equation (4) shows the dependency of the voltage drop ΔV on the active component R as well as on the reactive component X.

(25) When a distributed generator (DG) such as a solar PV system is integrated to one of the buses, for example at bus **110** at the receiving end, the power transfer increases the voltage of the respective bus **110** compared to bus **106**. At this condition, the voltage at the receiving end can be written as:

$$(26) \quad V_R \approx XQ + RP + V_S. \quad (5)$$

(27) Therefore, the direction of power flow is likely to reverse as the bus **110** to which the distributed generator is connected would be at higher voltage compared to the voltage at the sending end connected to bus **106**.

(28) This voltage drop can be expressed as:

$$(29) \quad \text{Voltagedrop}(V) = V_{DG} - V_S \approx \frac{XQ + RP}{V_{DG}}, \quad (6)$$

where: V.sub.DG=Voltage at DG terminal; P.sub.G=Generated active power from the distributed generator; Q.sub.G=Generated reactive power from the distributed generator; Q.sub.c=Reactive power of shunt compensators; Q.sub.L=Reactive power consumption due to load; P=P.sub.G–P.sub.L=Difference between the generated power and the load demand; and Q=(±Q.sub.C–Q.sub.L±Q.sub.G)

(30) Inserting values of P, Q into equation (6), and considering the per unit voltage of V.sub.DG, the voltage drop can be re-written as:

$$(31) \quad \text{Voltagedrop}(V) = V_{DG} - V_S \approx R(P_G - P_L) + X(\pm Q_C - Q_L \pm Q_G). \quad (7)$$

(32) The distributed generators are configured to provide a net export of active power and potentially provide or receive a net export or import of reactive power respectively. While the load is responsible for the consumption of active and reactive power, the shunt compensators are responsible for the import or export of reactive power. Due to this fact, the reactive power capacity of distributed generators is determined by the different types of energy supplies. The impact of a high level of penetration of distributed generators in a large distribution network is discussed in FIG. 2.

(33) FIG. 2 illustrates a conventional multi-bus distribution network **200** with an electrical distributed generator **224** connected to bus **214**. The electrical distributed generator **224** may be a solar PV system, for example. Similar to the construction of the two-bus distribution network **100** in FIG. 1, the multi-bus distribution network **200** also includes an electrical distribution station **202**, an on-load tap changer **204** and transformer (indicated by the double circle symbol), a plurality of

buses, that is, **206**, **210**, **212**, **214**, **216**, **218**, a plurality of transmission lines **208**, **220**, **222** with corresponding electrical impedances in $R_{ij} + jX_{ij}$ between each sending end bus (**206**, for example) and receiving end bus (**210**, for example). P_{Lj} and Q_{Li} represent real and reactive power, respectively, of a load (not shown) coupled with a bus, for example, bus **214**. The active and reactive power are represented by P_{ij} and Q_{ij} , respectively, where $i=1$ to $(n-1)$ and $j=1$ to $(2-n)$, where n represents the number of buses in the multi-bus distribution network **200**. (34) Accordingly, equation (3) can be re-written as:

$$(35) \quad V_{ij} \approx \frac{R_{ij}P_{ij} + X_{ij}Q_{ij}}{V_i}, \quad (8)$$

where, ΔV_{ij} =Voltage drop from $i_{sup.th}$ to $j_{sup.th}$ bus; R_{ij} =Resistance between $i_{sup.th}$ and $j_{sup.th}$ bus; X_{ij} =Reactance between $i_{sup.th}$ and $j_{sup.th}$ bus; P_{ij} =Active power flow through $i_{sup.th}$ and $j_{sup.th}$ bus; Q_{ij} =Reactive power flow through $i_{sup.th}$ and $j_{sup.th}$ bus; and V_i =Voltage at the $i_{sup.th}$ bus.

(36) Since the voltage at bus **214** is higher compared to the voltage at bus **212**, the flow of power could be reversed. As such, equation (8) may be re-written as (by swapping the positions of i and j) as:

$$(37) \quad V_{ij} \approx \frac{R_{ij}P_{ij} + X_{ij}Q_{ij}}{V_j} \quad (9)$$

(38) Replacing the value of $P_{ij}=(P_{Gj}-P_{Lj})$ and $Q_{ij}=(\pm Q_{Cj}-Q_{Lj} \pm Q_{Gj})$ from equation (7), equation (9) is re-written as:

$$(39) \quad \text{Voltage variation } V_{ij} \approx \frac{R_{ij}(P_{Gj} - P_{Lj}) + X_{ij}(\pm Q_{Cj} - Q_{Lj} \pm Q_{Gj})}{V_j} \quad (10)$$

where, P_{Gj} =Generated active power from the distributed generator; Q_{Gj} =Generated reactive power by the distributed generator; P_{Lj} =Active power of the load at bus j ; Q_{Lj} =Reactive power of the load at bus j ; Q_{Cj} =Shunt allocated at $j_{sup.th}$ bus of the multi-bus distribution network **200**

(40) To obtain a per unit expression for V_{ij} , equation 10 is re-written as:

$$(41) \quad V_{ij} \approx R_{ij}(P_{Gj} - P_{Lj}) + X_{ij}(\pm Q_{Cj} \pm Q_{Gj} - Q_{Lj}). \quad (11)$$

(42) Equation (11) for ΔV_{ij} is utilized to extract the reactive power capability of the solar PV based inverter system to enable non-unitary power factor operation in terms of the voltage variation in the current invention. Since, the unitary power factor of a PV based inverter system is used for harnessing active power, in non-unitary operations, the potential reactive power capability can be identified using the apparent power. As such, at an interval, an inverter of the PV system is capable of either injecting or absorbing a specified amount of reactive power Q_{in} .

(43) The relationship between the real power P_{Gj} , the reactive power Q_{in} , and the apparent power S_{Gj} is given by:

$$(44) \quad Q_{in} \leq \sqrt{S_{Gj}^2 - P_{Gj}^2}, \quad (12)$$

where S_{Gj} =apparent power from the PV system, P_{Gj} =Real power from the PV system, and Q_{in} =Reactive power from the PV system.

(45) The reactive power (Q_{in}) through the PV system may be mathematically derived in terms of the voltage at bus j , when a distributed generator, in this case the PV system with inverter, is attached at bus j in the multi-bus distribution network **200**, as below:

$$(46) \quad Q_{in} = \begin{cases} \alpha L S(1 - e^{(1-V_j)}), & 1.05 p.u. < V_j < 0.95 p.u. \\ 0, & \text{otherwise} \end{cases}, \quad (13)$$

where, αL =an active loading constant that varies in the range of (1-10), according to the active power curtailment required from the PV inverters for voltage regulation; and V_j =Corresponding bus voltage at the $j_{sup.th}$ bus.

(47) As Q_{in} is computed using equation (13), the expression for reactive power P_{Gj} from

the PV system is derived by re-writing equation (12), as below:

$$(48) \quad P_{Gj} = \begin{cases} \sqrt{S_{Gj}^2 - Q_{in}^2}, & 1.05p.u. < V_j < 0.95p.u. \\ P_{Gjmax}, & \text{otherwise} \end{cases} \quad (14)$$

(49) Using $Q_{sub.in}$ and $P_{sub.Gj}$ from equation (13) and equation (14), the required power factor for either injecting reactive power or absorbing reactive power is given by:

$$(50) \quad \text{Powerfactor} = \frac{(P_{Gj})}{(P_{Gj} + Q_{in})} \quad (15)$$

Accordingly, the reactive power support from the PV inverter is able to regulate the critical bus voltage $V_{sub.j}$ during a system fault occurrence. The aspects described with respect to equation (1) to equation (15) and FIG. 1 and FIG. 2 are used to implement a reactive power support system for a radial distribution network, as described in detail with respect to FIG. 3.

(51) FIG. 3 illustrates a radial distribution network 300 including a reactive power support system 302, according to an embodiment. The reactive power support system 302 is configured to either inject or absorb a reactive power to the radial distribution network 300 during one or more faults or disturbances. The one or more disturbances may include L, LL, LLL, L-G, LL-G, or LLL-G faults that may occur at any bus in the radial distribution network 300 connected to a PV array. The reactive power support system 302 is described in detail later in the description.

(52) The radial distribution network 300 includes a grid transformer 308. The grid transformer 308 may be selected from the group containing dry type transformers, step-down transformers, distribution transformers, polyphase transformers, single-phase transformers, iron core transformers, medium voltage transformers, three-phase transformers or the like. The transformer may be a step-up type or a step-down type of transformer.

(53) The radial distribution network 300 includes a radial distribution transmission line 304 for transmitting electrical power from a substation or a grid network 346 to a customer, end user or load 310. The radial distribution transmission line 304 is connected at a first end 306 to the grid transformer 308.

(54) The radial distribution network 300 includes one or more loads 310, for example loads 310-1, 310-2, 310-3, 310-4, 310-5, and 310-6. Each load 310 is connected by a respective load bus 312 to the radial distribution transmission line 304. The load busses 312 are represented by 312-1, 312-2, 312-3, 312-4, 312-5, and 312-6. The loads may be an industrial load, a residential load or the like.

(55) The radial distribution network 300 includes a point of common coupling (PCC) 314 connected to a second end 316 of the radial distribution transmission line 304. The second end 316 of the radial distribution transmission line 304 is connected to the load bus 312-6.

(56) The radial distribution network 300 further includes the grid network 346. The grid network 346 is coupled with a grid controller 348 for controlling the operation and/or monitoring various parameters related to the grid network 346. The grid controller 348 is also configured to measure the voltage of the grid network 346. The measured voltage of the grid network 346 acts as a reference voltage ($V_{sub.ref}$). The measured reference voltage ($V_{sub.ref}$) is fed as input to the reactive power support system 302. Further, the grid network 346 is connected to the grid transformer 308. The grid network 346 could be a microgrid, a power grid, a wide area synchronous grid, a super grid or the like. In an aspect, the radial distribution network 300 may further include an electrical distribution station (not shown). The electrical distribution station (not shown) is connected to the grid network 346. The electrical distribution station may be similar to the electrical distribution station 102, 202 as discussed earlier in FIG. 1 and FIG. 2. The radial distribution network 300 may also include an on-load tap changer (OLTC) (204, shown in FIG. 2). The on-load tap changer may be electrically connected between the grid network 346 and the grid transformer 308. The OLTC is substantially similar to the OLTC 104, 204 as discussed earlier in FIG. 1 and FIG. 2. The OLTC is configured to adjust the voltage of the grid transformer 308 to

provide a constant voltage at the first end **306** of the radial distribution transmission line **304**.

(57) The radial distribution network **300** further includes the reactive power support system **302**.

The reactive power support system **302** includes at least one photovoltaic module **318**. The photovoltaic module **318** may be a single solar panel or an array of solar panels. The photovoltaic module **318** may be a monocrystalline type, a polycrystalline type, a thin-film type or a passivated emitter and rear contact (PERC) type solar panel.

(58) The reactive power support system **302** of the radial distribution network **300** further includes a solar power inverter **320**. The solar power inverter **320** is connected in parallel with at least one photovoltaic module **318**. A first output terminal of the photovoltaic module **318** is connected with one end of an inductor **350** through which the DC current $I_{sub.DC}$ generated by the PV panel **318** flows. Another end of the inductor **350** is connected with a first input terminal of the solar power inverter **320**. One end of a capacitor **324** is connected with another end of the inductor **350** and thus also connected with the first input terminal of the solar power inverter **320**. A second output terminal of the photovoltaic module **318** is connected with a second input terminal of the solar power inverter **320** and also with another end of the capacitor **324**. As such, the capacitor **324** is in parallel with the photovoltaic module **318** and the solar power inverter **320**. The solar power inverter **320** may be selected from a string inverter, a microinverter, a power optimizer type inverter, a hybrid inverter or the like, known in the art.

(59) The constructional detail of the solar power inverter **320** is further explained herein. A zoomed view of the solar power inverter **320** along with the photovoltaic module **318**, the inductor **350** and the capacitor **324** is also shown in FIG. 3. The solar power inverter **320** includes a set of one or more transistors S . For example, the solar power inverter **320** includes a first transistor $S_{sub.11}$. A collector terminal of the first transistor $S_{sub.11}$ is connected to a positive terminal of the capacitor **324**. The emitter terminal of the first transistor $S_{sub.11}$ is connected to the point of common coupling **314** by a first phase transmission line **326**. The solar power inverter **320** further includes a second transistor $S_{sub.12}$. A collector terminal of the second transistor $S_{sub.12}$ is connected to the first phase transmission line **326**, whereas an emitter of the second transistor $S_{sub.12}$ is connected to a ground terminal or a zero potential terminal or a reference potential terminal **328**. The solar power inverter **320** further includes a third transistor $S_{sub.21}$. A collector terminal of the third transistor $S_{sub.21}$ is connected to the positive terminal of the capacitor **324** whereas an emitter terminal of the third transistor $S_{sub.21}$ is connected to the point of common coupling **314** by a second phase transmission line **330**. The solar power inverter **320** further includes a fourth transistor $S_{sub.22}$. A collector terminal of the fourth transistor $S_{sub.22}$ is connected to the second phase transmission line **330** whereas an emitter terminal of the fourth transistor $S_{sub.22}$ is connected to the ground terminal **328**. The solar power inverter **320** further includes a fifth transistor $S_{sub.31}$. A collector terminal of the fifth transistor $S_{sub.31}$ is connected to the positive terminal of the capacitor **324** whereas an emitter terminal of the fifth transistor $S_{sub.31}$ is connected to the point of common coupling **314** by a third phase transmission line **332**. The solar power inverter **320** further includes a sixth transistor $S_{sub.32}$. A collector terminal of the sixth transistor $S_{sub.32}$ is connected to the third phase transmission line **332** whereas an emitter terminal of the sixth transistor $S_{sub.32}$ is connected to the ground terminal **328**. The first phase transmission line **326**, the second phase transmission line **330** and the third phase transmission line **332** may have a connection of capacitors $C1$, $C2$ and $C3$, respectively to act as a filter circuit.

(60) Each transistor S is paired with a respective reversed biased diode **334**. Each reversed biased diode **334** is connected in parallel with the respective transistor S . For example, a reversed biased diode **334-1** is connected in parallel to the first transistor $S_{sub.11}$, a reversed biased diode **334-2** is connected in parallel to the second transistor $S_{sub.12}$, a reversed biased diode **334-3** is connected in parallel to the third transistor $S_{sub.21}$, a reversed biased diode **334-4** is connected in parallel to the fourth transistor $S_{sub.22}$, a reversed biased diode **334-5** is connected in parallel to the fifth transistor $S_{sub.31}$ and a reversed biased diode **334-6** is connected in parallel to the sixth transistor

S.sub.31. In an aspect, the transistor may be selected from the group including a BJT, a FET, a MOSFET, a JFET, either individually or in combination.

(61) The reactive power support system **302** of the radial distribution network **300** further includes a voltmeter **342**. A first input terminal of the voltmeter **342** is connected from the output terminal of the solar power inverter **320**. A second input terminal of the voltmeter **342** is connected to the point of common coupling **314**. In other words, the output terminal of the solar power inverter **320** is electrically connected to the point of common coupling **314** and the voltmeter **342** is configured to measure the voltage at the point of common coupling **314**.

(62) The reactive power support system **302** of the radial distribution network **300** further includes an inverter controller **322**. The inverter controller **322** includes an adder **336**. The adder **336** includes two inputs. The voltage at the point of point of common coupling **314** is fed as an input to a negative input terminal of the adder **336** through a feedback transmission line **344** connected between the voltmeter **342** and the negative input of the adder **336**. The feedback transmission line **344** is configured to transmit the voltage at the point of common coupling **314** to the negative input of the adder **336**. Thus, the output voltage measured from the voltmeter **342** at the point of the common coupling **314** is used as input to the negative input terminal of the adder **336**. Also, the grid controller **348** is configured to transmit the voltage reference signal (V.sub.ref) to the positive input terminal of the adder **336**. Therefore, the measured reference voltage (V.sub.ref) from the grid controller **348** is fed as input to the positive input terminal of the adder **336** of the inverter controller **322**. Thus, the adder **336** is configured to receive the voltage reference signal (V.sub.ref) at the positive input terminal of the adder **336**, voltage (V.sub.PCC) at the point of common coupling **314** at the negative input terminal of the adder **336**, add the voltage reference signal (V.sub.ref) to the negative point of common coupling voltage (V.sub.PCC) and generate an error signal (E.sub.s) at an output terminal of the adder **336**.

(63) The inverter controller **322** of the reactive power support system **302** further includes a proportional integral controller **338**. The proportional integral controller or a PI controller **338** is connected in series with the adder **336**. The output generated by the adder **336** is fed as input to the proportional integral controller **338**. For example, the proportional integral controller **338** is configured to receive the error signal (E.sub.s) from the output terminal of the adder **336**. The proportional integral controller **338** is further configured to sample the error signal (E.sub.s) during a time window, compute the average of the error signals (E.sub.s) and generate an average error signal at the output of the proportional integral controller **338**.

(64) The inverter controller **322** of the reactive power support system **302** further includes a pulse width modulator **340**. The pulse width modulator **340** is also connected in series with the proportional integral controller **338**. The pulse width modulator **340** is configured to receive the average error signal from the output of the proportional integral controller **338**. The pulse width modulator **340** thus generate a gate control signals G based upon the average error signal. The generated gate control signal G acts as input to the solar power inverter **320**. The gate control signals G may be classified as a combination of six different gate control signals, such as G.sub.11, G.sub.12, G.sub.21, G.sub.22, G.sub.31 and G.sub.32. A gate of each transistor S of the set of transistor gates is configured to connect to a respective one of the gate control signals G. More specifically, each gate control signal G is configured to be supplied as input to the respective gate terminal of the set of the transistors S. For example, G.sub.11 is configured to act as input to the gate terminal of the first transistor S.sub.11, G.sub.12 is configured to act as input to the to the gate terminal of the second transistor S.sub.12, G.sub.21 is configured to act as input to the to the gate terminal of the third transistor S.sub.21, G.sub.22 is configured to act as input to the to the gate terminal of the fourth transistor S.sub.22, G.sub.31 is configured to act as input to the to the gate terminal of the fifth transistor S.sub.31, and G.sub.32 is configured to act as input to the to the gate terminal of the sixth transistor S.sub.32. Thus, each gate control signal G is configured to switch a polarity of the gate of a respective transistor S of the solar power inverter **320** to switch the

respective transistor S ON or OFF.

(65) Now the operation of the reactive power support system **302** is described in detail. The grid network **346** supplies the reference voltage ($V_{sub.ref}$) to the radial distribution transmission line **304**. The buses **312** also receive the reference voltage ($V_{sub.ref}$). The reference voltage ($V_{sub.ref}$) voltage appears at the point of common coupling **314** connected at the bus **312-6**. The grid controller **348** is configured to monitor the reference voltage ($V_{sub.ref}$) provided by the grid network **346** and supplies the reference voltage ($V_{sub.ref}$) to the reactive power support system **302**. The reactive power support system **302** receives the reference voltage ($V_{sub.ref}$) and supplies to the inverter controller **322** of the reactive power support system **302**. The inverter controller **322** receives the reference voltage ($V_{sub.ref}$) and supplies to the positive input terminal of the adder **336**. In an embodiment, the inverter controller **322** may use a per unit reference voltage ($V_{sub.ref}$) (that is, $V_{sub.ref}=1$ p.u.) and supplies it to the positive input terminal of the adder **336**.

Accordingly, the positive input terminal of the adder **336** always receives 1 p.u as the reference voltage ($V_{sub.ref}$). Case I: There is no fault on any load bus **312**.

(66) When there is no fault, for example an L, LL, LLL, L-G, LL-G, or LLL-G fault, on any load bus **312**, the voltage at the point of common coupling **314** is equal to the voltage at the 6.sup.th load bus **312-6** (that is, $V_{sub.j}=6$) at which the photovoltaic module **318** with solar power inverter **320** is connected. At this time,

$V_{sub.j}=6=V_{sub.ref}$.

(67) The reactive power support system **302** receives the measured output voltage $V_{sub.j}=6$ at the point of the common coupling **314** from the voltmeter **342** and supplies to the inverter controller **322** of the reactive power support system **302** through the feedback transmission line **344**. The inverter controller **322** receives the measured output voltage $V_{sub.j}=6$ and supplies to the negative input terminal of the adder **336**. In an aspect, the inverter controller **322** may also use a per unit voltage of the PCC terminal **314** (for example, $V_{sub.j}=6=1$ p.u.) and supplies it to the negative input terminal of the adder **336**. Accordingly, the negative input terminal of the adder **336** receives 1 p.u as the voltage at PCC terminal **314**.

(68) Since, there is no fault, $V_{sub.j}=6=V_{sub.ref}=1$ p.u. The output of the adder **336**=Grid voltage ($V_{sub.ref}$)–Voltage at the point of common coupling ($V_{sub.j}=6$)=0 p.u. This condition indicates a balanced state of the radial distribution transmission line **304**. As such, the output through the adder **336** is zero. The output, that is, zero, is fed as input to the proportional integral controller **338**. As such, the error signal is zero unit. The proportional integral controller **338** sample the zero unit during the time window, averages zero unit and generate an average error signal as zero unit only. The output as average of zero unit is further fed as input to the pulse width modulator **340**. The pulse width modulator **340** receives the zero-unit as average error signal. Mathematically, the reactive power support system **302** is configured to use equation (13) and equation (14) and computes the reactive power value as $Q_{sub.in}=0$ and the active power= $P_{sub.Gj}=P_{sub.Gmax}$. Also, $V_{sub.j}=6=1$ p.u. is within the limits from equation (13).

(69) The reactive power support system **302** is further configured to compute the required power factor using equation 15. At this time,

(70) Powerfactor = $P_{Gj} / (P_{Gj} + Q_{in}) = P_{Gj} / (P_{Gj} + 0) = (P_{Gmax} / P_{Gmax}) = 1$

(71) The power factor=1 corresponds to an average error signal as zero unit as received from the proportional integral controller **338**. Also, the unity power factor indicates that the reactive power at the point of common coupling **314** equals the grid reference value. The average error signal as zero unit corresponding to power factor **1** is further fed as input to the pulse width modulator **340**.

(72) The pulse width modulator **340** receives the average error signal as zero unit and generate gate control signals G corresponding to power factor=1. In an aspect, the G is represented as a gate control signal (in vector form) $(G)=[G_{sub.11}, G_{sub.12}, G_{sub.21}, G_{sub.22}, G_{sub.31}, G_{sub.32}]$, where $G_{sub.ij}$ =Either '0' or '1'. '0' and '1' indicates an OFF condition, the non-conducting state and the ON condition, respectively, of the respective transistor $S_{sub.ij}$ from the set of transistor S.

Moreover, respective gate control signal $G_{sub.ij}$ is to be fed as input to the gate terminal of the respective transistor $S_{sub.ij}$.

(73) Accordingly, the pulse width modulator **340** is configured to generate the gate control signal G . Since, the required power factor is the unity power factor, the pulse width modulator **340** having stored the corresponding gate signal $G=[G_{sub.11}, G_{sub.12}, G_{sub.21}, G_{sub.22}, G_{sub.31}, G_{sub.32}]$ equivalent to unity power factor. At this time, corresponding gate signal $G=[G_{sub.11}, G_{sub.12}, G_{sub.21}, G_{sub.22}, G_{sub.31}, G_{sub.32}]$ refers to generation of active power only when the power factor is unity as $P(\text{active power})=P_{sub.Gmax}$. In an example, for each reactive power value and the corresponding active power value (or the corresponding power factor value based upon the active and reactive power value), the pulse width modulator **340** may store the corresponding gate signal G in vector form. The pulse width modulator **340**, based upon the gate control signal G corresponding to the unity power factor, inputs the gate control signal G corresponding to generation of active power only, to the solar power inverter **320**. The gate control signals G are thus configured to switch the set of transistor gates of the solar power inverter **320** to provide only active power to the point of common coupling **314**. As such, the gate control signals G switches the set of transistor gates S of the solar power inverter **320** to provide only active power to the point of common coupling **314** when the radial distribution transmission line **304** is balanced. This condition also indicates that the grid network **346** is stable and none of the buses **312** have faults of the L, LL, LLL, L-G, LL-G or LLL-G type. Therefore, the voltage measured at the point of common coupling ($V_{sub.j=6}$) **314** is equal to the voltage reference value ($V_{sub.ref}$) transmitted from the grid network **346**.

(74) Case II: The load bus **312** has a fault and $V_{sub.j=6}$ is below 0.95 p.u at any moment. One of the load buses, for example, a third load bus **312-3** has a fault. In an aspect, the fault may be an LLL-G fault. In another example, the fault may be a L, LL, LLL, L-G, or LL-G type fault. Due to the LLL-G fault, the voltage profile $V_{sub.j=6}$ at the point of common coupling **314** also fluctuates. Thus, the voltage $V_{sub.j=6}$ at the point of common coupling **314** is not equal to the grid network voltage ($V_{sub.ref}$) but either less than or greater than grid network voltage ($V_{sub.ref}$). As such, the value of $V_{sub.j=6}$ may rise above 1.05 p.u or fall below 0.95 p.u. as provided in equation 13 earlier and also given below.

$1.05 \text{ p.u} < V_{sub.j}$.

OR

$V_{sub.j} < 0.95 \text{ p.u}$.

(75) This condition would indicate an occurrence of the fault. During occurrence of the fault, the bus voltage of the respective load bus **312-3** needs to be regulated in order to regulate a voltage of the radial distribution transmission line **304** during the LLL-G fault on the load bus **312-3** connected to the load **310-3**. Considering $V_{sub.j=6}$ at any moment is below 0.95 p.u., that is, 0.90 p.u., for example. At this time,
 $V_{sub.j=6} < V_{sub.ref}$.

(76) The reactive power support system **302** receives the measured output voltage $V_{sub.j=6}$ (for example, 0.90) at the point of the common coupling **314** from the voltmeter **342** and supplies (in an example, $V_{sub.j=0.90}$) to the inverter controller **322** of the reactive power support system **302** through the feedback transmission line **344**. The inverter controller **322** receives the measured output voltage $V_{sub.j=6}$ and supplies to the negative input terminal of the adder **336**. In an aspect, the inverter controller **322** uses per unit voltage of PCC terminal **314** (that is, $V_{sub.j=6}=0.90 \text{ p.u.}$) and supplies it to the negative input terminal of the adder **336**. Accordingly, the negative input terminal of the adder **336** receives less than 0.95 p.u. (that is, 0.90 p.u) from the voltage at PCC terminal **314**. The output of the adder **336** is considered as an error signal.

(77) Error signal = Grid voltage ($V_{sub.ref}$) – Voltage at the point of common coupling ($V_{sub.j=6}$). The error signal $> 0 \text{ p.u.}$ since the grid voltage ($V_{sub.ref}$) $> (V_{sub.j=6})$. This condition indicates an unbalanced state of the radial distribution transmission line **304**. As such, the output through the

adder **336** is a non-zero and positive value as the error signal. The error signal as the output of the adder **336**, that is, positive non-zero value, is fed as input to the proportional integral controller **338**. The proportional integral controller **338** samples the positive non-zero value during the time window. Further, the proportional integral controller **338** averages the positive non-zero value and generate an average of the positive non-zero value at the output terminal of the proportional integral controller **338**. The output as average of the positive non-zero value is further fed as input to the pulse width modulator **340**. The inverter controller **322** computes the reactive power value $Q_{sub.in}$ using equation 13, as below:

$$(78) \quad Q_{in} = \begin{cases} S(1-e^{(1-V_j)}), 1.05p.u. < V_j < 0.95p.u. \\ 0, \text{otherwise} \end{cases} \quad (13)$$

(79) This time, the reactive power value as $Q_{sub.in}$ turns out to be ‘Negative’ after putting value of $V_{sub.j} < 0.95$ (that is, $0.90 p.u.$). This indicates that the reactive power $Q_{sub.in}$ at the point of common coupling **314** is less than a grid reference value. As such, greater than a unity power factor is required in order to regulate the voltage of the radial distribution transmission line **304** during the three-phase to ground fault (LLL-G) on the load bus **312-3** connected to the load **310-3**.

(80) The inverter controller **322** of the reactive power support system **302** computes the active power $P_{sub.Gj}$ by using equation (14) and putting the negative value of $Q_{sub.in}$ in the equation (14) as below:

$$(81) \quad P_{Gj} = \begin{cases} \sqrt{S_{Gj}^2 - \text{Math. } Q_{in}^2}, 1.05p.u. < V_j < 0.95p.u. \\ P_{Gjmax}, \text{otherwise} \end{cases} \quad (14)$$

(82) The computed active power $P_{sub.Gj}$ is positive. The inverter controller **322** of the reactive power support system **302** is further configured to use the computed value of the active power $P_{sub.Gj}$ (positive) and the reactive power $Q_{sub.in}$ (negative) in equation (15) to compute the required power factor, as below:

$$(83) \quad \text{Powerfactor} = \frac{(P_{Gj})}{(P_{Gj} + Q_{in})} \quad (15)$$

From equation (15), Power factor = $P_{sub.Gj} / (P_{sub.Gj} + (-Q_{sub.in})) = P_{sub.Gj} / (P_{sub.Gj} - Q_{sub.in}) > 1$

(84) The power factor > 1 corresponds that greater than a unity power factor is required to absorb reactive power at the point of common coupling **314** in order to regulate the voltage of the radial distribution transmission line **304** during the LLL-G fault on the load bus **312-3** connected to the load **310-3**. Accordingly, the average of the positive non-zero value as average error signal corresponding to the necessary power factor grater then 1 (unity) is further fed as input to the pulse width modulator **340**.

(85) The pulse width modulator **340** receives the average of the positive non-zero error signal and generates gate control signals G corresponding to power factor > 1 necessary to absorb the reactive power at the point of common coupling **314** in order to regulate the voltage of the radial distribution transmission line **304** during the LLL-G fault on the load bus **312-3** connected to the loads **310-3**. In an aspect, the G could be represented as a gate control signal (in vector form) $(G) = [G_{sub.11}, G_{sub.12}, G_{sub.21}, G_{sub.22}, G_{sub.31}, G_{sub.32}]$, where $G_{sub.ij}$ = Either ‘0’ or ‘1’. ‘0’ indicates OFF condition or non-conducting state and ‘1’ indicates ON condition, respectively, of the respective transistor $S_{sub.ij}$ from the set of transistor S . Moreover, respective gate control signal $G_{sub.ij}$ is to be fed as input to the gate terminal of the respective transistor $S_{sub.ij}$.

(86) Accordingly, the pulse width modulator **340** of the inverter controller **322** generates the gate control signal G corresponding to power factor greater than unity. Thus, the gate control signal G switches the set of transistor gates of the solar power inverter **320** to operate at greater than the unity power factor.

(87) Since, the required power factor is greater than unity, the pulse width modulator **340** having stored the corresponding gate signal $G=[G_{sub.11}, G_{sub.12}, G_{sub.21}, G_{sub.22}, G_{sub.31}, G_{sub.32}]$ equivalent to greater than unity power factor. At this time, the gate signal $G=[G_{sub.11}, G_{sub.12}, G_{sub.21}, G_{sub.22}, G_{sub.31}, G_{sub.32}]$ refers to generation of corresponding active power as well as reactive power as computed in equation (13) and equation (14) that yields the power factor >1 (unity).

(88) The pulse width modulator **340**, based upon the gate control signal G corresponding to greater than the unity power factor, inputs the gate control signal G corresponding to generation of active power as well as reactive power as computed from equations 13 and 14, to the solar power inverter **320**. The gate control signals G are thus configured to switch the set of transistor gates of the solar power inverter **320** to provide active power as well as a reactive power as computed from equations 13 and 14, corresponding to power factor greater than unity, to the point of common coupling **314**. The point of common coupling **314** absorbs the reactive power. As such, the voltage of the radial distribution transmission line **304** is regulated during the three-phase to ground fault on the load bus **312-3** connected to the load **310-3**. At this point, the gate control signals G switches the set of transistor gates S of the solar power inverter **320** to provide the active power as well as reactive power corresponding to power factor greater than 1 (unity) to the point of common coupling **314** to regulate the voltage of the radial distribution transmission line **304** during the three-phase to ground fault on the load bus **312-3** connected to the load **310-3**. Accordingly, the voltage of the radial distribution transmission line **304** is regulated.

(89) Case III: When one of the load bus **312** has a fault and $V_{sub.j=6}$ is above 1.05 p.u at any moment. One of the load bus **312**, for example, a third load bus **312-3** has a fault. In an aspect, the fault may be again an LLL-G fault. In another example, the fault may be a L, LL, LLL, L-G, or LL-G type fault. Due to the LLL-G fault, the voltage profile $V_{sub.j=6}$ at the point of common coupling **314** also fluctuates. Thus, the voltage $V_{sub.j=6}$ at the point of common coupling **314** is not equal to the grid network voltage ($V_{sub.ref}$) but either less than or greater than grid network voltage ($V_{sub.ref}$). As such, the value of $V_{sub.j=6}$ may rise above 1.05 p.u or fall below 0.95 p.u. as provided in equation 13 earlier and also given below.

$1.05 \text{ p.u} < V_{sub.j}$.

OR

$V_{sub.j} < 0.95 \text{ p.u.}$

(90) This condition indicates an occurrence of the fault. During an occurrence of a fault, the bus voltage of the respective load bus **312-3** must be regulated in order to regulate the voltage of the radial distribution transmission line **304** during the LLL-G fault on the load bus **312-3** connected to the load **310-3**. Considering $V_{sub.j=6}$ at any moment is above 1.05 p.u. (1.10 p.u. for example). At this time,

$V_{sub.j=6} > V_{sub.ref}$.

(91) The reactive power support system **302** receives the measured output voltage $V_{sub.j=6}$ (1.10 p.u. for example) at the point of the common coupling **314** from the voltmeter **342** and supplies (that is, $V_{sub.j}=1.10 \text{ p.u.}$) to the inverter controller **322** of the reactive power support system **302** through the feedback transmission line **344**. The inverter controller **322** receives the measured output voltage $V_{sub.j=6}$ and supplies to the negative input terminal of the adder **336**. In an aspect, the inverter controller **322** uses per unit voltage of PCC terminal **314** (that is, $V_{sub.j=6}=1.10 \text{ p.u.}$) and supplies it to the negative input terminal of the adder **336**. Accordingly, the negative input terminal of the adder **336** receives greater than 1.05 p.u. (for example, 1.10 p.u) from the voltage at PCC terminal **314**. Now, the output of the adder **336** is considered as an error signal.

Error signal = Grid voltage ($V_{sub.ref}$) – Voltage at the point of common coupling ($V_{sub.j=6}$) = $1.00 \text{ p.u.} - 1.10 \text{ p.u.}$

(92) The error signal $< 0 \text{ p.u.}$, since the grid voltage ($V_{sub.ref}$) $<$ ($V_{sub.j=6}$)

(93) This condition indicates an unbalanced state of the radial distribution transmission line **304**.

The output through the adder **336** is a non-zero and a negative value as the error signal. The error signal as the output of the adder **336**, that is, negative non-zero value, is fed as input to the proportional integral controller **338**.

(94) The proportional integral controller **338** samples the negative non-zero value during the time window. Further, the proportional integral controller **338** averages the negative non-zero value and generate an average of the negative non-zero value at the output terminal of the proportional integral controller **338**. The output as average of the negative non-zero value is further fed as input to the pulse width modulator **340**.

(95) Mathematically, the inverter controller **322** of the reactive power support system **302** computes the reactive power value $Q_{\text{sub.in}}$ using equation 13, as below:

$$(96) \quad Q_{\text{in}} = \begin{cases} -S(1-e^{(1-V_j)}), & 1.05p.u. < V_j < 0.95p.u. \\ 0, & \text{otherwise} \end{cases} \quad (13)$$

(97) This time, the reactive power value as $Q_{\text{sub.in}}$ turns out to be 'Positive' after putting value of $V_{\text{sub.j}} > 1.05$ (that is, 1.10 p.u.). This indicates that the reactive power $Q_{\text{sub.in}}$ at the point of common coupling **314** is greater than a grid reference value. As such, less than a unity power factor is required in order to regulate the voltage of the radial distribution transmission line **304** during the three-phase to ground fault (LLL-G) on the load bus **312-3** connected to the load **310-3**.

(98) Mathematically, the inverter controller **322** of the reactive power support system **302** computes the active power $P_{\text{sub.Gj}}$ by using equation (14) and putting the positive value of $Q_{\text{sub.in}}$ in the equation 14 as below:

$$(99) \quad P_{\text{Gj}} = \begin{cases} \sqrt{S_{\text{Gj}}^2 - \text{Math. } Q_{\text{in}} \cdot \text{Math. }^2}, & 1.05p.u. < V_j < 0.95p.u. \\ P_{\text{Gjmax}}, & \text{otherwise} \end{cases} \quad (14)$$

(100) The computed active power $P_{\text{sub.Gj}}$ is positive. The inverter controller **322** of the reactive power support system **302** is further configured to use the computed value of the active power $P_{\text{sub.Gj}}$ (positive) and the reactive power $Q_{\text{sub.in}}$ (positive) in equation 15 to compute the required power factor, as below:

$$(101) \quad \text{Powerfactor} = \frac{(P_{\text{Gj}})}{(P_{\text{Gj}} + Q_{\text{in}})} \quad (15)$$

(102) From equation (15), Power

factor = $P_{\text{sub.Gj}} / (P_{\text{sub.Gj}} + Q_{\text{sub.in}}) = P_{\text{sub.Gj}} / (P_{\text{sub.Gj}} + Q_{\text{sub.in}}) < 1$. The power factor < 1 corresponds that less than a unity power factor is required to provide reactive power at the point of common coupling **314** in order to regulate the voltage of the radial distribution transmission line **304** during the LLL-G fault on the load bus **312-3** connected to the load **310-3**. Accordingly, the average of the negative non-zero value as average error signal corresponding to the necessary power factor less than 1 (unity) is further fed as input to the pulse width modulator **340**.

(103) The pulse width modulator **340** receives the average of the negative non-zero error signal and generates gate control signals G corresponding to power factor < 1 necessary to provide the reactive power at the point of common coupling **314** in order to regulate the voltage of the radial distribution transmission line **304** during the LLL-G fault on the load bus **312-3** connected to the load **310-3**. In an aspect, the G could be represented as a gate control signal (in vector form) (G) = [$G_{\text{sub.11}}$, $G_{\text{sub.12}}$, $G_{\text{sub.21}}$, $G_{\text{sub.22}}$, $G_{\text{sub.31}}$, $G_{\text{sub.32}}$], where $G_{\text{sub.ij}}$ = Either '0' or '1'. '0' indicates OFF condition or non-conducting state and '1' indicates ON condition, respectively, of the respective transistor $S_{\text{sub.ij}}$ from the set of transistor S . Moreover, respective gate control signal $G_{\text{sub.ij}}$ is to be fed as input to the gate terminal of the respective transistor $S_{\text{sub.ij}}$.

(104) Accordingly, the pulse width modulator **340** of the inverter controller **322** generates the gate control signal G corresponding to power factor less than unity. The gate control signal G would switch the set of transistor gates of the solar power inverter **320** to operate at less than the unity

power factor.

(105) Since, the required power factor is less than unity, the pulse width modulator **340** having stored the corresponding gate signal $G=[G_{\text{sub.11}}, G_{\text{sub.12}}, G_{\text{sub.21}}, G_{\text{sub.22}}, G_{\text{sub.31}}, G_{\text{sub.32}}]$ equivalent to less than unity power factor. At this time, the gate signal $G=[G_{\text{sub.11}}, G_{\text{sub.12}}, G_{\text{sub.21}}, G_{\text{sub.22}}, G_{\text{sub.31}}, G_{\text{sub.32}}]$ refers to generation of corresponding active power as well as reactive power as computed in equation 13 and 14 that yields the power factor <1 (unity).

(106) The pulse width modulator **340**, based upon the gate control signal G corresponding to less than the unity power factor, inputs the gate control signal G corresponding to generation of active power as well as reactive power as computed from equations 13 and 14, to the solar power inverter **320**. The gate control signals G are thus configured to switch the set of transistor gates of the solar power inverter **320** to provide active power as well as a reactive power as computed from equations 13 and 14, corresponding to power factor less than unity, to the point of common coupling **314**. This provides additional reactive power at the point of common coupling **314**. As such, the voltage of the radial distribution transmission line **304** is regulated during the three-phase to ground fault on the load bus **312-3** connected to the load **310-3**. The gate control signals G switches the set of transistor gates S of the solar power inverter **320** to provide the active power as well as reactive power corresponding to power factor less than 1 (unity) to the point of common coupling **314** to regulate the voltage of the radial distribution transmission line **304** during the three-phase to ground fault on the load bus **312-3** connected to the load **310-3**. Accordingly, the voltage of the radial distribution transmission line **304** is regulated.

(107) Accordingly, whenever the voltage on the load bus **312** fluctuates due to, for example LLL-G type fault, the reactive power support system **302** immediately provides the momentarily necessary reactive power support by either injecting the reactive power or by absorbing the reactive power to the point of common coupling **314** by the inverter controller **322** connected to the solar power inverter **320**. Based upon the voltage value available at the point of common coupling **314** as compared to the reference voltage of the grid network **346**, the inverter controller **322** is provide gate control signals G which switch the set of transistor gates of the solar power inverter **320** to operate at less than or greater than a unity power factor to provide reactive power or to absorb reactive power respectively at the point of common coupling **314** in order to regulate the voltage of the radial distribution transmission line **304** during a three-phase to ground fault on the load bus **312** connected to one of the loads **310**. In an embodiment, the inverter controller **322** of the reactive power support system **302** may include a relation curve, such as a control curve between active/reactive power/power factor and corresponding value of gate control signals necessary to generate corresponding power factor equivalent to generate corresponding active or reactive power in order to regulate the voltage of the radial distribution transmission line **304** during the three-phase to ground fault on the load bus **312** connected to one of the loads **310**. Also, the generation of more than the unity power factor, equal to unity power factor or less then unity power by the inverter controller **322** by controlling the gate control signals G based upon the reference voltage and the voltage at the point of common coupling **314** is a continuous and an iterative process and the aforementioned process is regularly computed for the necessary reactive power or active power or both, required till the voltage profile on the respective load bus **312** is completely stabilized.

(108) FIG. 4 illustrates a voltage profile **400** during LLL-G fault at a first load bus **312-1**, according to an aspect of the present disclosure. To analyze the efficacy of the solar power inverter **320** under control of the inverter controller **322**, the LLL-G fault was injected at the first load bus **312-1** at time $t=1$ and cleared in 20 msec. A plotline **402** shows observed voltage profile **400** at the point of common coupling ($V_{\text{sub.PCC}}$) when the inverter controller **322** was actively providing grater then unity power factor when the reactive power at the point of common coupling **314** was less than a grid reference value due to LLG-fault at the first load bus **312-1**, and when the inverter controller **322** was actively providing less then then unity power factor when the reactive power at

the point of common coupling **314** was greater than the grid reference value due to LLG-fault at the first load bus **312-1**. The voltage profile **400** incurred a maximum voltage magnitude during the fault condition as the stability was limited due to the isolation of the feeder. However, at $t=2$ sec the voltage was recovered. It was clear from the plotline **402** that the voltage profile was found to be under permissible limits (0.95-1.05 p.u.) while also satisfying the IEEE 1547-2018 distributed energy resource requirement. On the other hand, a plotline **404** shows a voltage profile at the point of common coupling (V.sub.PCC) when the inverter controller **322** was removed or not used with the solar power inverter **320**. From the result of the plotline **404** it was clear that, without the integration of the inverter controller **322** of the reactive power support system **302**, the voltage after fault clearance was not recovered and remains below 0.95 p.u. The result from both plotlines **402**, **404** indicates that the inverter controller **322** of the reactive power support system **302** successfully stabilized the voltage profile at the point of common coupling **314** even when the LLG-fault occurred at first load bus **312-1**.

(109) FIG. 5A illustrates a voltage profile **500-1** during LLG-fault at a fourth load bus **312-4**, according to an aspect. To again analyze the efficacy of the solar power inverter **320** under control of the inverter controller **322**, the LLG-fault was again injected at the fourth load bus **312-4** at time $t=1$ and again cleared in 20 msec. A plotline **502** shows observed voltage profile **500-1** at the point of common coupling (V.sub.PCC) during LLG-fault at a fourth load bus **312-4**. It was clear from the plotline **502** that the fault at the fourth load bus **312-4** experienced a comparatively lower magnitude of overvoltage and undervoltage during the fault occurrence. Also, the voltage profile **500-1** was again found to be under permissible limits (0.95-1.05 p.u.) while also satisfying the IEEE 1547-2018 distributed energy resource requirement. On the other hand, a plotline **504** shows a voltage profile at the point of common coupling (V.sub.PCC) when the inverter controller **322** was removed or not used with the solar power inverter **320**. From the result of the plotline **504** it was clear that, without the integration of the inverter controller **322** of the reactive power support system **302**, the voltage after fault clearance was not recovered and remains below 0.95 p.u. again. The result from both plotlines **502**, **504** indicates that the inverter controller **322** of the reactive power support system **302** successfully stabilized the voltage profile at the point of common coupling **314** even when the LLG-fault occurred at the fourth load bus **312-4**.

(110) FIG. 5B illustrates a voltage profile **500-2** during LLG-fault at the sixth load bus **312-6**, according to an exemplary embodiment. To again analyze the efficacy of the solar power inverter **320** under control of the inverter controller **322**, the LLG-fault was again injected third time at the sixth load bus **312-6** at time $t=1$ and again cleared in 20 msec. A plotline **506** shows observed voltage profile **500-2** at the point of common coupling (V.sub.PCC) during LLG-fault at the sixth load bus **312-6**. It was again clear from the plotline **506** that the fault at the sixth load bus **312-6** also experienced a comparatively lower magnitude of overvoltage and undervoltage during the fault occurrence. Also, the voltage profile **500-2** was again found to be under permissible limits (0.95-1.05 p.u.) while also satisfying the IEEE 1547-2018 distributed energy resource requirement. On the other hand, a plotline **508** shows a voltage profile **500-2** at the point of common coupling (V.sub.PCC) when the inverter controller **322** was removed or not used with the solar power inverter **320**. From the result of the plotline **508** it was clear that, without the integration of the inverter controller **322** of the reactive power support system **302**, the voltage after fault clearance was not recovered and remains below 0.95 p.u. again. The result from both plotlines **506**, **508** indicates that the inverter controller **322** of the reactive power support system **302** again successfully stabilized the voltage profile at the point of common coupling **314** even when the LLG-fault occurred at the sixth load bus **312-6**.

(111) FIG. 6 illustrates a flowchart of a method **600** of providing a reactive power support to a radial distribution network **300**, according to an aspect. The reactive power support is provided by a photovoltaic module to the grid connected radial distribution network **300**. The radial distribution network **300** is connected to a plurality of load buses **312**. The method is performed in the inverter

controller **322** as described in FIG. 3. The method **600** is described in conjunction with FIG. 3 and various experimental observations in FIG. 4, FIG. 5A and FIG. 5B. Various steps of the method **600** are included through blocks in FIG. 6. One or more blocks may be combined or eliminated to achieve the method **600** of providing the reactive power support to the radial distribution network **300**, without departing from the scope of the present disclosure.

(112) At step **602**, the method **600** includes, installing a photovoltaic module. The photovoltaic module includes a photovoltaic module **318**, a capacitor **324** and an inductor **350** connected to the photovoltaic module **318**. A first end **306** of the radial distribution transmission line **304** is also connected to a grid transformer **308**. Moreover, plurality of loads **310** are also connected in parallel the radial distribution transmission line **304**.

(113) At step **604**, the method **600** includes connecting the solar power inverter **320** in parallel with the photovoltaic module.

(114) At step **606**, the method **600** includes connecting an output terminal of the solar power inverter **320** to a point of common coupling **314** of the radial distribution transmission line **304**.

(115) At step **608**, the method **600** includes connecting an inverter controller **322** to the solar power inverter **320**.

(116) At step **610**, the method **600** includes measuring, with a voltmeter **342**, a voltage at the point of common coupling **314**.

(117) At step **612**, the method **600** includes receiving, by the inverter controller **322**, the voltage measured at the point of common coupling **314** and a voltage reference value. The voltage reference value is received from the grid controller **348**. The grid controller **348** is connected with the grid network **346** and configured to receive the voltage from the grid network **346** that acts as the reference voltage. The reference voltage is fed to an adder **336** of the inverter controller **322**.

(118) At step **614**, the method **600** includes generating, by the inverter controller **322**, gate control signals G configured to switch a set of transistor gates of the solar power inverter **320** to operate at less than or greater than a unity power factor to provide reactive power to or to absorb reactive power at the point of common coupling **314**, respectively when the voltage measured at the point of common coupling **314** is less than or greater than the voltage reference value due to a three-phase to ground fault on the load bus **312** connected to one of the loads **310**.

(119) Embodiments of the disclosure is illustrated with respect to FIG. 1 to FIG. 6. A reactive power support system **302** for a radial distribution network **300** is described. The radial distribution network **300** includes a radial distribution transmission line **304** connected at a first end **306** to a grid transformer **308** and a plurality of loads **310**. Each load **310** is connected by a load bus **312** to the radial distribution transmission line **304**. The radial distribution network **300** further includes a point of common coupling **314** connected to a second end **316** of the radial distribution transmission line **304**, a photovoltaic module **318** and a solar power inverter **320** connected in parallel with the photovoltaic module **318**. The solar power inverter **320** has an output terminal configured to connect to the point of common coupling **314**. The reactive power support system **302** for the radial distribution network **300** includes an inverter controller **322** connected to the solar power inverter **320**. The inverter controller **322** is configured to provide gate control signals G which switch a set of transistor gates of the solar power inverter **320** to operate at less than or greater than a unity power factor to provide reactive power or to absorb reactive power respectively at the point of common coupling **314** in order to regulate a voltage of the radial distribution transmission line **304** during a three-phase to ground fault on the load bus **312** connected to one of the loads **310**.

(120) In an aspect, the gate control signals G are configured to switch the set of transistor gates of the solar power inverter **320** to provide active power to the point of common coupling **314** when the radial distribution transmission line **304** is balanced.

(121) In an aspect, the reactive power support system further comprises a capacitor **324** in parallel with the photovoltaic module **318** and the solar power inverter **320**; and an inductor **350** connected

between the photovoltaic module **318** and the solar power inverter **320**.

(122) In an aspect, the set of transistors comprise a first transistor S.sub.11 having its collector connected to a positive terminal of the capacitor **324** and its emitter connected to the point of common coupling **314** by a first phase transmission line **326**; a second transistor S.sub.12 having its collector connected to the first phase transmission line **326** and its emitter connected to a ground terminal **328**, a third transistor S.sub.21 having its collector connected to a positive terminal of the capacitor **324** and its emitter connected to the point of common coupling **314** by a second phase transmission line **330**; a fourth transistor S.sub.22 having its collector connected to the second phase transmission line **330** and its emitter connected to the ground terminal **328**, a fifth transistor S.sub.31 having its collector connected to a positive terminal of the capacitor **324** and its emitter connected to the point of common coupling **314** by a third phase transmission line **332**, a sixth transistor S.sub.32 having its collector connected to the third phase transmission line **332** and its emitter connected to the ground terminal **328**, and a reversed biased diode **334** in parallel with each transistor of the set of transistors. A gate of each transistor of the set of transistor gates is configured to connect to a respective one of the gate control signals G.

(123) In an aspect, the inverter controller **322** is configured to provide gate control signals G that operate the solar power inverter **320** at: greater than a unity power factor when the reactive power at the point of common coupling **314** is less than a grid reference value, unity power factor when the reactive power at the point of common coupling **314** equals the grid reference value, and less than the unity power factor when the reactive power at the point of common coupling **314** is greater than the grid reference value.

(124) In an aspect, the inverter controller **322** comprises an adder **336** configured to receive a voltage reference signal at a positive input terminal, a point of common coupling voltage at a negative input terminal, add the voltage reference signal to the negative point of common coupling voltage and generate an error signal at an output terminal. The inverter controller **322** further comprises a proportional integral controller **338** connected in series with the adder **336**. The proportional integral controller **338** is configured to sample the error signal during a time window, average the error signals and generate an average error signal. The inverter controller **322** further comprises a pulse width modulator **340** connected in series with the proportional integral controller **338**. The pulse width modulator **340** is configured to receive the average error signal and generate gate control signals G. Each gate control signal G is configured to switch a polarity of the gate of a respective transistor of the solar power inverter **320** to switch the respective transistor ON or OFF.

(125) In an aspect, the reactive power support system further comprises a voltmeter **342** connected between the point of common coupling **314** and the output terminal of the solar power inverter **320**. The voltmeter **342** is configured to measure the voltage at the point of common coupling **314**; and a feedback transmission line **344** connected between the voltmeter **342** and the negative input of the adder **336**. The feedback transmission line **344** is configured to transmit the voltage at the point of common coupling **314** to the negative input of the adder **336**.

(126) In an aspect, the reactive power support system further comprises a grid network **346** connected to the grid transformer **308**. The grid network **346** includes a grid controller **348**. The grid controller **348** is configured to transmit the voltage reference signal to the positive input terminal of the adder **336**.

(127) In an aspect, the reactive power support system further comprises an electrical distribution station **102**, **202** connected to the grid network **346**; and an on-load tap changer **104**, **204** connected between the grid network **346** and the grid transformer **308**.

(128) In another aspect, a method of providing reactive power support to a radial distribution network **300** is disclosed. The method includes connecting a first end **306** of the radial distribution transmission line **304** to a grid transformer **308**. The method further includes connecting a plurality of loads **310** in parallel to the radial distribution transmission line **304**. The method further includes installing a photovoltaic module **318**. The method further includes connecting a solar power

inverter **320** in parallel with the photovoltaic module **318**. The method further includes connecting an output terminal of the solar power inverter **320** to a point of common coupling **314** at a second end **316** of the radial distribution transmission line **304**. The method further includes connecting an inverter controller **322** to the solar power inverter **320**. The method further includes measuring, with a voltmeter **342**, a voltage at the point of common coupling **314**. The method further includes receiving, by the inverter controller **322**, the voltage measured at the point of common coupling **314** and a voltage reference value. The method further includes generating, by the inverter controller **322**, gate control signals G configured to switch a set of transistor gates of the solar power inverter **320** to operate at less than or greater than a unity power factor to provide reactive power to or to absorb reactive power at the point of common coupling **314** respectively when the voltage measured at the point of common coupling **314** is less than or greater than the voltage reference value due to a three-phase to ground fault on a load bus **312** connected to one of the loads **310**.

(129) In an aspect, the method further includes generating, by the inverter controller **322**, the gate control signals G and transmitting the gate control signals G to the set of transistor gates of the solar power inverter **320** to provide active power to the point of common coupling **314** when the voltage measured at the point of common coupling **314** is equal to the voltage reference value.

(130) In an aspect, the method further includes connecting a capacitor **324** in parallel with the photovoltaic module **318** and the solar power inverter **320**; and connecting an inductor **350** in series with the photovoltaic module **318** and the solar power inverter **320**.

(131) In an aspect, the method further includes connecting the gate control signals G to the solar power inverter **320**. The solar power inverter **320** includes a first transistor S.sub.11 having its collector connected to a positive terminal of the capacitor **324** and its emitter connected to the point of common coupling **314** by a first phase transmission line **326**. The solar power inverter **320** further includes a second transistor S.sub.12 having its collector connected to the first phase transmission line **326** and its emitter connected to a ground terminal **328**. The solar power inverter **320** further includes a third transistor S.sub.21 having its collector connected to a positive terminal of the capacitor **324** and its emitter connected to the point of common coupling **314** by a second phase transmission line **330**. The solar power inverter **320** further includes a fourth transistor S.sub.22 having its collector connected to the second phase transmission line **330** and its emitter connected to the ground terminal **328**. The solar power inverter **320** further includes a fifth transistor S.sub.31 having its collector connected to the positive terminal of the capacitor **324** and its emitter connected to the point of common coupling **314** by a third phase transmission line **332**. The solar power inverter **320** further includes a sixth transistor S.sub.32 having its collector connected to the third phase transmission line **332** and its emitter connected to the ground terminal **328**. The solar power inverter **320** further includes a reversed biased diode **334** in parallel with each transistor of the set of transistors S. The method further includes connecting the gate control signals G to the set of transistor gates such that a gate of each transistor is connected to a respective gate control signal G.

(132) In an aspect, the method further includes generating, by the inverter controller **322**, the gate control signals G to operate the solar power inverter **320** at greater than a unity power factor when the reactive power at the point of common coupling **314** is less than a grid reference value, unity power factor when the reactive power at the point of common coupling **314** equals the grid reference value, and less than the unity power factor when the reactive power at the point of common coupling **314** is greater than the grid reference value.

(133) In an aspect, the method further includes connecting a feedback transmission line **344** between the voltmeter **342** and the negative input of the adder **336**; and transmitting the voltage at the point of common coupling **314** to the negative input of the adder **336**.

(134) In an aspect, the method further includes receiving, by an adder **336** of the inverter controller **322**, the voltage reference at a positive input terminal and the voltage measured at the point of

common coupling **314** at a negative input terminal. The method further includes subtracting the voltage measured at the point of common coupling **314** from the voltage reference signal. The method further includes generating an error signal at an output terminal of the adder **336**. The method further includes sampling, by a proportional integral controller **338** connected in series with the adder **336**, the error signal during a time window, averaging the error signals and generating an average error signal. The method further includes receiving, by a pulse width modulator **340** connected in series with the proportional integral controller **338**, the average error signal. The method further includes generating, by the pulse width modulator **340**, gate control signals G based on the average error signal. Each gate control signal is configured to switch a polarity of a gate of a respective transistor of the solar power inverter to switch of the respective transistor ON or OFF.

(135) In an aspect, the method further includes connecting a grid network **346** to the grid transformer **308**. The grid network **346** includes a grid controller **348**. The method further includes transmitting, by the grid controller **348**, the voltage reference value to the positive input terminal of the adder **336**.

(136) In an aspect, the method further includes connecting an electrical distribution station **102**, **202** to the grid network **346**; and connecting an on-load tap changer (OLTC) **104**, **204** between the grid network and the grid transformer. The method further includes adjusting the transformer **308**, by the on-load tap changer **104**, **204**, to provide a constant voltage at the first end **306** of the radial distribution transmission line **304**.

(137) In another aspect, a method of providing reactive power support by a photovoltaic module **318** to a grid connected radial distribution network **300** connected to a plurality of load buses **312** is disclosed. The method includes installing the photovoltaic module **318**. The method further includes connecting a solar power inverter **320** in parallel with the photovoltaic module **318**. The method further includes connecting an output terminal of the solar power inverter **320** to a point of common coupling **314** of the radial distribution transmission line **304**. The method further includes connecting an inverter controller **322** to the solar power inverter **320**. The method further includes measuring, with a voltmeter **342**, a voltage at the point of common coupling **314**. The method further includes receiving, by the inverter controller **322**, the voltage measured at the point of common coupling **314** and a voltage reference value. The method further includes generating, by the inverter controller **322**, gate control signals G configured to switch a set of transistor gates S of the solar power inverter **320** to operate at less than or greater than a unity power factor to provide reactive power to or to absorb reactive power at the point of common coupling **314** respectively when the voltage measured at the point of common coupling **314** is less than or greater than the voltage reference value due to a three-phase to ground fault on a load bus **312** connected to one of the loads **310**.

(138) In an aspect, the method further includes generating, by the inverter controller **322**, the gate control signals G to operate the solar power inverter **320** at greater than a unity power factor when the reactive power at the point of common coupling **314** is less than a grid reference value, unity power factor when the reactive power at the point of common coupling **314** equals the grid reference value, and less than the unity power factor when the reactive power at the point of common coupling **314** is greater than the grid reference value.

(139) Next, further details of the hardware description of the computing environment according to exemplary embodiments are described with reference to FIG. 7. In FIG. 7, a controller **700** described is representative of the inverter controller **322** of FIG. 3 in which the controller is a computing device which includes a CPU **701** which performs the processes described above/below. The process data and instructions may be stored in memory **702**. These processes and instructions may also be stored on a storage medium disk **704** such as a hard drive (HDD) or portable storage medium or may be stored remotely.

(140) Further, the claims are not limited by the form of the computer-readable media on which the instructions of the inventive process are stored. For example, the instructions may be stored on

CDs, DVDs, in FLASH memory, RAM, ROM, PROM, EPROM, EEPROM, hard disk or any other information processing device with which the computing device communicates, such as a server or computer.

(141) Further, the claims may be provided as a utility application, background daemon, or component of an operating system, or combination thereof, executing in conjunction with CPU **701**, **703** and an operating system such as Microsoft Windows 7, Microsoft Windows 10, Microsoft Windows 11, UNIX, Solaris, LINUX, Apple MAC-OS and other systems known to those skilled in the art.

(142) The hardware elements in order to achieve the computing device may be realized by various circuitry elements, known to those skilled in the art. For example, CPU **701** or CPU **703** may be a Xenon or Core processor from Intel of America or an Opteron processor from AMD of America, or may be other processor types that would be recognized by one of ordinary skill in the art. Alternatively, the CPU **701**, **703** may be implemented on an FPGA, ASIC, PLD or using discrete logic circuits, as one of ordinary skill in the art would recognize. Further, CPU **701**, **703** may be implemented as multiple processors cooperatively working in parallel to perform the instructions of the inventive processes described above.

(143) The computing device in FIG. **7** also includes a network controller **706**, such as an Intel Ethernet PRO network interface card from Intel Corporation of America, for interfacing with network **760**. As can be appreciated, the network **760** can be a public network, such as the Internet, or a private network such as an LAN or WAN network, or any combination thereof and can also include PSTN or ISDN sub-networks. The network **760** can also be wired, such as an Ethernet network, or can be wireless such as a cellular network including EDGE, 3G, 4G and 5G wireless cellular systems. The wireless network can also be Wi-Fi, Bluetooth, or any other wireless form of communication that is known.

(144) The computing device further includes a display controller **708**, such as a NVIDIA Geforce GTX or Quadro graphics adaptor from NVIDIA Corporation of America for interfacing with display **710**, such as a Hewlett Packard HPL2445w LCD monitor. A general purpose I/O interface **712** interfaces with a keyboard and/or mouse **714** as well as a touch screen panel **716** on or separate from display **710**. General purpose I/O interface also connects to a variety of peripherals **718** including printers and scanners, such as an OfficeJet or DeskJet from Hewlett Packard.

(145) A sound controller **720** is also provided in the computing device such as Sound Blaster X-Fi Titanium from Creative, to interface with speakers/microphone **722** thereby providing sounds and/or music.

(146) The general-purpose storage controller **724** connects the storage medium disk **704** with communication bus **726**, which may be an ISA, EISA, VESA, PCI, or similar, for interconnecting all of the components of the computing device. A description of the general features and functionality of the display **710**, keyboard and/or mouse **714**, as well as the display controller **708**, storage controller **724**, network controller **706**, sound controller **720**, and general purpose I/O interface **712** is omitted herein for brevity as these features are known.

(147) The exemplary circuit elements described in the context of the present disclosure may be replaced with other elements and structured differently than the examples provided herein. Moreover, circuitry configured to perform features described herein may be implemented in multiple circuit units (e.g., chips), or the features may be combined in circuitry on a single chipset, as shown on FIG. **8**.

(148) FIG. **8** shows a schematic diagram of a data processing system, according to certain embodiments, for performing the functions of the exemplary embodiments. The data processing system is an example of a computer in which code or instructions implementing the processes of the illustrative embodiments may be located.

(149) In FIG. **8**, data processing system **800** employs a hub architecture including a north bridge and memory controller hub (NB/MCH) **825** and a south bridge and input/output (I/O) controller

hub (SB/ICH) **820**. The central processing unit (CPU) **830** is connected to NB/MCH **825**. The NB/MCH **825** also connects to the memory **845** via a memory bus, and connects to the graphics processor **850** via an accelerated graphics port (AGP). The NB/MCH **825** also connects to the SB/ICH **820** via an internal bus (e.g., a unified media interface or a direct media interface). The CPU Processing unit **830** may contain one or more processors and even may be implemented using one or more heterogeneous processor systems.

(150) For example, FIG. **9** shows one implementation of CPU **830**, according to an embodiment. In one implementation, the instruction register **938** retrieves instructions from the fast memory **940**. At least part of these instructions are fetched from the instruction register **938** by the control logic **936** and interpreted according to the instruction set architecture of the CPU **830**. Part of the instructions can also be directed to the register **932**. In one implementation the instructions are decoded according to a hardwired method, and in another implementation the instructions are decoded according to a microprogram that translates instructions into sets of CPU configuration signals that are applied sequentially over multiple clock pulses. After fetching and decoding the instructions, the instructions are executed using the arithmetic logic unit (ALU) **934** that loads values from the register **932** and performs logical and mathematical operations on the loaded values according to the instructions. The results from these operations can be feedback into the register and/or stored in the fast memory **940**. According to certain implementations, the instruction set architecture of the CPU **830** can use a reduced instruction set architecture, a complex instruction set architecture, a vector processor architecture, a very large instruction word architecture. Furthermore, the CPU **830** can be based on the Von Neuman model or the Harvard model. The CPU **830** can be a digital signal processor, an FPGA, an ASIC, a PLA, a PLD, or a CPLD. Further, the CPU **830** can be an x86 processor by Intel or by AMD; an ARM processor, a Power architecture processor by, e.g., IBM; a SPARC architecture processor by Sun Microsystems or by Oracle; or other known CPU architecture.

(151) Referring again to FIG. **8**, the data processing system **800** can include that the SB/ICH **820** is coupled through a system bus to an I/O Bus, a read only memory (ROM) **856**, universal serial bus (USB) port **864**, a flash binary input/output system (BIOS) **868**, and a graphics controller **858**. PCI/PCIe devices can also be coupled to SB/ICH **820** through a PCI bus **862**.

(152) The PCI devices may include, for example, Ethernet adapters, add-in cards, and PC cards for notebook computers. The Hard disk drive **860** and CD-ROM **866** can use, for example, an integrated drive electronics (IDE) or serial advanced technology attachment (SATA) interface. In one implementation the I/O bus can include a super I/O (SIO) device.

(153) Further, the hard disk drive (HDD) **860** and optical drive **866** can also be coupled to the SB/ICH **820** through a system bus. In one implementation, a keyboard **870**, a mouse **872**, a parallel port **878**, and a serial port **876** can be connected to the system bus through the I/O bus. Other peripherals and devices that can be connected to the SB/ICH **820** using a mass storage controller such as SATA or PATA, an Ethernet port, an ISA bus, a LPC bridge, SMBus, a DMA controller, and an Audio Codec.

(154) Moreover, the present disclosure is not limited to the specific circuit elements described herein, nor is the present disclosure limited to the specific sizing and classification of these elements. For example, the skilled artisan will appreciate that the circuitry described herein may be adapted based on changes on battery sizing and chemistry or based on the requirements of the intended back-up load to be powered.

(155) The functions and features described herein may also be executed by various distributed components of a system. For example, one or more processors may execute these system functions, wherein the processors are distributed across multiple components communicating in a network. The distributed components may include one or more client and server machines, which may share processing, as shown by FIG. **10**, in addition to various human interface and communication devices (e.g., display monitors, smart phones, tablets, personal digital assistants (PDAs)). The

network may be a private network, such as a LAN or WAN, or may be a public network, such as the Internet. Input to the system may be received via direct user input and received remotely either in real-time or as a batch process. Additionally, some implementations may be performed on modules or hardware not identical to those described. Accordingly, other implementations are within the scope that may be claimed.

(156) The above-described hardware description is a non-limiting example of corresponding structure for performing the functionality described herein.

(157) Numerous modifications and variations of the present disclosure are possible in light of the above teachings. It is therefore to be understood that within the scope of the appended claims, the invention may be practiced otherwise than as specifically described herein.

Claims

1. A reactive power support system for a radial distribution network, comprising: a radial distribution transmission line connected at a first end to a grid transformer; a plurality of loads, wherein each load is connected by a load bus to the radial distribution transmission line; a point of common coupling connected to a second end of the radial distribution transmission line; a photovoltaic module; a solar power inverter connected in parallel with the photovoltaic module, wherein the solar power inverter has an output terminal configured to connect to the point of common coupling; and an inverter controller connected to the solar power inverter, wherein the inverter controller is configured to provide gate control signals which switch a set of transistor gates of the solar power inverter to operate at less than or greater than a unity power factor to provide reactive power or to absorb reactive power respectively at the point of common coupling in order to regulate a voltage of the radial distribution transmission line during a three-phase to ground fault on a load bus connected to one of the loads.
2. The reactive power support system of claim 1, wherein the gate control signals are configured to switch the set of transistor gates of the solar power inverter to provide active power to the point of common coupling when the radial distribution transmission line is balanced.
3. The reactive power support system of claim 1, further comprising: a capacitor in parallel with the photovoltaic module and the solar power inverter; and an inductor connected between the photovoltaic module and the solar power inverter.
4. The reactive power support system of claim 3, wherein the set of transistor gates comprise: a first transistor S.sub.11 having its collector connected to a positive terminal of the capacitor and its emitter connected to the point of common coupling by a first phase transmission line; a second transistor S.sub.12 having its collector connected to the first phase transmission line and its emitter connected to a ground terminal; a third transistor S.sub.21 having its collector connected to a positive terminal of the capacitor and its emitter connected to the point of common coupling by a second phase transmission line; a fourth transistor S.sub.22 having its collector connected to the second phase transmission line and its emitter connected to the ground terminal; a fifth transistor S.sub.31 having its collector connected to a positive terminal of the capacitor and its emitter connected to the point of common coupling by a third phase transmission line; a sixth transistor S.sub.32 having its collector connected to the third phase transmission line and its emitter connected to the ground terminal; and a reversed biased diode in parallel with each transistor of the set of transistors, wherein a gate of each transistor of the set of transistor gates is configured to connect to a respective one of the gate control signals.
5. The reactive power support system of claim 1, wherein the inverter controller is configured to provide gate control signals that operate the solar power inverter at: greater than a unity power factor when the reactive power at the point of common coupling is less than a grid reference value, unity power factor when the reactive power at the point of common coupling equals the grid reference value, and less than the unity power factor when the reactive power at the point of

common coupling is greater than the grid reference value.

6. The reactive power support system of claim 5, wherein the inverter controller comprises: an adder configured to receive a voltage reference signal at a positive input terminal, a point of common coupling voltage at a negative input terminal, add the voltage reference signal to the negative point of common coupling voltage and generate an error signal at an output terminal; a proportional integral controller connected in series with the adder, wherein the proportional integral controller is configured to sample the error signal during a time window, average the error signals and generate an average error signal; and a pulse width modulator connected in series with the proportional integral controller, wherein the pulse width modulator is configured to receive the average error signal and generate gate control signals, wherein each gate control signal is configured to switch a polarity of the gate of a respective transistor of the solar power inverter to switch the respective transistor ON or OFF.

7. The reactive power support system of claim 5, further comprising: a voltmeter connected between the point of common coupling and the output terminal of the solar power inverter, wherein the voltmeter is configured to measure the voltage at the point of common coupling; and a feedback transmission line connected between the voltmeter and the negative input of the adder, wherein the feedback transmission line is configured to transmit the voltage at the point of common coupling to the negative input of the adder.

8. The reactive power support system of claim 5, further comprising: a grid network connected to the grid transformer, wherein the grid network includes a grid controller, wherein the grid controller is configured to transmit the voltage reference signal to the positive input terminal of the adder.

9. The reactive power support system of claim 8, further comprising: an electrical distribution station connected to the grid network; and an on-load tap changer (OLTC) connected between the grid network and the grid transformer.

10. A method of providing reactive power support to a radial distribution network, comprising: connecting a first end of a radial distribution transmission line to a grid transformer; connecting a plurality of loads in parallel to the radial distribution transmission line; installing a photovoltaic module; connecting a solar power inverter in parallel with the photovoltaic module; connecting an output terminal of the solar power inverter to a point of common coupling at a second end of the radial distribution transmission line; connecting an inverter controller to the solar power inverter; measuring, with a voltmeter, a voltage at the point of common coupling; receiving, by the inverter controller, the voltage measured at the point of common coupling and a voltage reference value; and generating, by the inverter controller, gate control signals configured to switch a set of transistor gates of the solar power inverter to operate at less than or greater than a unity power factor to provide reactive power to or to absorb reactive power at the point of common coupling respectively when the voltage measured at the point of common coupling is less than or greater than the voltage reference value due to a three-phase to ground fault on a load bus connected to one of the loads.

11. The method of claim 10, further comprising: generating, by the inverter controller, the gate control signals; transmitting the gate control signals to the set of transistor gates of the solar power inverter to provide active power to the point of common coupling when the voltage measured at the point of common coupling is equal to the voltage reference value.

12. The method of claim 10, further comprising: connecting a capacitor in parallel with the photovoltaic module and the solar power inverter; and connecting an inductor in series with the photovoltaic module and the solar power inverter.

13. The method of claim 12, further comprising: connecting the gate control signals to the solar power inverter, wherein the solar power inverter includes: a first transistor S.sub.11 having its collector connected to a positive terminal of the capacitor and its emitter connected to the point of common coupling by a first phase transmission line; a second transistor S.sub.12 having its

collector connected to the first phase transmission line and its emitter connected to a ground terminal; a third transistor S.sub.21 having its collector connected to a positive terminal of the capacitor and its emitter connected to the point of common coupling by a second phase transmission line; a fourth transistor S.sub.22 having its collector connected to the second phase transmission line and its emitter connected to the ground terminal; a fifth transistor S.sub.31 having its collector connected to a positive terminal of the capacitor and its emitter connected to the point of common coupling by a third phase transmission line; a sixth transistor S.sub.32 having its collector connected to the third phase transmission line and its emitter connected to the ground terminal; a reversed biased diode in parallel with each transistor of the set of transistors; and connecting the gate control signals to the set of transistor gates such that a gate of each transistor is connected to a respective gate control signal.

14. The method of claim 13, further comprising: generating, by the inverter controller, the gate control signals to operate the solar power inverter at: greater than a unity power factor when the reactive power at the point of common coupling is less than a grid reference value, unity power factor when the reactive power at the point of common coupling equals the grid reference value, and less than the unity power factor when the reactive power at the point of common coupling is greater than the grid reference value.

15. The method of claim 14, further comprising: connecting a feedback transmission line between the voltmeter and the negative input of the adder; and transmitting the voltage at the point of common coupling to the negative input of the adder.

16. The method of claim 15, further comprising: receiving, by an adder of the inverter controller, the voltage reference at a positive input terminal and the voltage measured at the point of common coupling at a negative input terminal; subtracting the voltage measured at the point of common coupling from the voltage reference signal; generating an error signal at an output terminal of the adder; sampling, by a proportional integral controller connected in series with the adder, the error signal during a time window, averaging the error signals and generating an average error signal; and receiving, by a pulse width modulator connected in series with the proportional integral controller, the average error signal; generating, by the pulse width modulator, gate control signals based on the average error signal, wherein each gate control signal is configured to switch a polarity of a gate of a respective transistor of the solar power inverter to switch of the respective transistor ON or OFF.

17. The method of claim 16, further comprising: connecting a grid network to the grid transformer, wherein the grid network includes a grid controller; and transmitting, by the grid controller, the voltage reference value to the positive input terminal of the adder.

18. The method of claim 17, further comprising: connecting an electrical distribution station to the grid network; and connecting an on-load tap changer (OLTC) between the grid network and the grid transformer; and adjusting the transformer, by the OLTC, to provide a constant voltage at the first end of the radial distribution transmission line.

19. A method of providing reactive power support by a photovoltaic module to a grid connected radial distribution network connected to a plurality of load buses, comprising: installing a photovoltaic module; connecting a solar power inverter in parallel with the photovoltaic module; connecting an output terminal of the solar power inverter to a point of common coupling of a radial distribution transmission line; connecting an inverter controller to the solar power inverter; measuring, with a voltmeter, a voltage at the point of common coupling; receiving, by the inverter controller, the voltage measured at the point of common coupling and a voltage reference value; and generating, by the inverter controller, gate control signals configured to switch a set of transistor gates of the solar power inverter to operate at less than or greater than a unity power factor to provide reactive power to or to absorb reactive power at the point of common coupling respectively when the voltage measured at the point of common coupling is less than or greater than the voltage reference value due to a three-phase to ground fault on a load bus connected to one

of the loads.

20. The method of claim 19, further comprising: generating, by the inverter controller, the gate control signals to operate the solar power inverter at: greater than a unity power factor when the reactive power at the point of common coupling is less than a grid reference value, unity power factor when the reactive power at the point of common coupling equals the grid reference value, and less than the unity power factor when the reactive power at the point of common coupling is greater than the grid reference value.
