

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12405103
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Rasbornig; Friedrich et al.

Inductive sensor with improved safety

Abstract

An inductive sensor may include a first angle measurement path associated with determining an angular position based on a first set of input signals. The inductive sensor may include a second angle measurement path associated with determining an angular position based on a second set of input signals. The inductive sensor may include an amplitude regulation path associated with regulating amplitudes of a set of output signals. The inductive sensor may include a safety path associated with performing one or more safety checks. Each safety check of the one or more safety checks may be associated with at least one of the first angle measurement path, the second angle measurement path, or the amplitude regulation path.

Inventors: Rasbornig; Friedrich (Klagenfurt, AT), Hammerschmidt; Dirk (Finkenstein, AT), Werth; Tobias (Villach, AT)

Applicant: Infineon Technologies AG (Neubiberg, DE)

Family ID: 83361440

Assignee: Infineon Technologies AG (Neubiberg, DE)

Appl. No.: 18/672162

Filed: May 23, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240310157 A1	Sep. 19, 2024

Related U.S. Application Data

continuation parent-doc US 17301746 20210413 US 11994387 child-doc US 18672162

Publication Classification

Int. Cl.: G01B7/30 (20060101); G01L3/10 (20060101); G01L5/22 (20060101)

U.S. Cl.:

CPC G01B7/30 (20130101); G01L3/105 (20130101); G01L5/221 (20130101)

Field of Classification Search

CPC: G01B (7/30); G01L (3/105); G01L (5/221)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
8453518	12/2012	Diekmann et al.	N/A	N/A
9614478	12/2016	Nero, Jr. et al.	N/A	N/A
9678138	12/2016	Forster	N/A	G01R 31/088
9874609	12/2017	Rasbornig et al.	N/A	N/A
10464597	12/2018	Rasbornig	N/A	G01L 5/221
10605626	12/2019	Hammerschmidt	N/A	N/A
11002567	12/2020	Hammerschmidt	N/A	N/A
11662260	12/2022	Latham et al.	N/A	N/A
11692887	12/2022	Witts et al.	N/A	N/A
11733288	12/2022	Gstoettenbauer et al.	N/A	N/A
11859971	12/2023	Hammerschmidt	N/A	G01D 3/08
11982526	12/2023	Hammerschmidt	N/A	G01D 5/16
11994387	12/2023	Rasbornig	N/A	G01D 5/2046
12163782	12/2023	Rasbornig	N/A	G01B 7/30
2011/0068777	12/2010	Tiemann et al.	N/A	N/A
2020/0284615	12/2019	Hammerschmidt et al.	N/A	N/A
2022/0326002	12/2021	Rasbornig et al.	N/A	N/A
2022/0373318	12/2021	Rasbornig et al.	N/A	N/A
2022/0404135	12/2021	Hammerschmidt	N/A	N/A
2022/0404136	12/2021	Hammerschmidt	N/A	N/A
2023/0041763	12/2022	Park et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
102008017857	12/2008	DE	N/A

Primary Examiner: Hollington; Octavia

Attorney, Agent or Firm: Harrity & Harrity, LLP

Background/Summary

RELATED APPLICATION (1) This application is a continuation of U.S. patent application Ser. No. 17/301,746, filed Apr. 13, 2021, which is incorporated herein by reference in its entirety.

BACKGROUND

(1) An inductive sensor uses the principle of electromagnetic induction to determine a position (e.g., a linear position or an angular position) of an object. A general functioning principle of an inductive sensor is based on an alternating current (AC) signal being applied to an excitation coil which, in turn, induces signals in one or more receiving coils. An inductive coupling between the excitation coil and the one or more receiving coils depends on positions of components of the inductive sensor that move relative to each other—specifically on either the relative positions of the excitation coil and the one or more receiving coils (when the excitation coil or the one or more receiving coils are affixed to the object) or on a position of a rotor (e.g., a metallic or magnetic element that is affixed to the object) that moves relative to the excitation coil and the one or more receiving coils. The inductive coupling between the excitation coil and the one or more receiving coils therefore changes with the position of the object. The inductive sensor detects amplitude values or phase relationships of the signals induced in the one or more receiving coils and determines the position and/or one or more other characteristics of the object, accordingly.

SUMMARY

(2) In some implementations, an inductive sensor includes a first angle measurement path associated with determining an angular position based on a first set of input signals; a second angle measurement path associated with determining an angular position based on a second set of input signals; an amplitude regulation path associated with regulating amplitudes of a set of output signals; and a safety path associated with performing one or more safety checks, wherein each safety check of the one or more safety checks is associated with at least one of the first angle measurement path, the second angle measurement path, or the amplitude regulation path.

(3) In some implementations, a method includes receiving a plurality of signals on a safety path of an inductive sensor, wherein each signal of the plurality of signals is received from a first angle measurement path of the inductive sensor, a second angle measurement path of the inductive sensor, or an amplitude regulation path of the inductive sensor; and performing one or more safety checks on the safety path based on the plurality of signals, wherein each safety check of the one or more safety checks is associated with at least one of the first angle measurement path, the second angle measurement path, or the amplitude regulation path.

(4) In some implementations, an inductive sensor includes a first measurement path associated with determining a position of a first object based on a first set of input signals; a second measurement path associated with determining a position of a second object based on a second set of input signals; an amplitude regulation path associated with regulating amplitudes of a set of output signals; and a safety path associated with assessing functionality of at least one of the first measurement path, the second measurement path, or the amplitude regulation path, wherein the first measurement path, the second measurement path, the amplitude regulation path, and the safety path are integrated on a monolithic semiconductor device.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a block diagram illustrating an example inductive sensor with improved safety, as described herein.

(2) FIG. 2 is a block diagram illustrating a particular example implementation of the inductive sensor with improved safety shown in FIG. 1.

(3) FIG. 3 is a block diagram illustrating another example inductive sensor with improved safety, as

described herein.

(4) FIG. 4 is a flowchart of an example process relating to an inductive sensor performing one or more safety checks, as described herein.

DETAILED DESCRIPTION

(5) The following detailed description of example implementations refers to the accompanying drawings. The same reference numbers in different drawings may identify the same or similar elements.

(6) An inductive sensor may be designed to determine a position of an object and/or one or more other characteristics of the object in a given application. For example, an inductive sensor may be used in an electronic power steering (EPS) application to determine an angular position of a steering column and/or a torque applied to the steering column. In some applications, such as an EPS application, it may be necessary to ensure functional safety of the inductive sensor.

(7) In general, functional safety can be defined as an absence of unreasonable risk (e.g., to a system, to an environment, to people, and/or the like) due to hazards caused by malfunctioning behavior (e.g., a systematic failure, a random failure, or the like) of the inductive sensor. In the automotive context, an Automotive Safety Integrity Level (ASIL) scheme is used to dictate functional safety requirements for an inductive sensor. The ASIL scheme is a risk classification scheme defined by the International Organization for Standardization (ISO) 26262 standard (titled Functional Safety for Road Vehicles), which provides a standard for functional safety of electrical and/or electronic systems in production automobiles. An ASIL classification defines safety requirements necessary to be in line with the ISO 26262 standard. An ASIL is established by performing a risk analysis of a potential hazard by looking at severity, exposure, and controllability of a vehicle operating scenario. A safety goal for that hazard in turn carries the ASIL requirements. There are four ASILs identified by the standard: ASIL A, ASIL B, ASIL C, ASIL D. ASIL D dictates the highest integrity requirements, while ASIL A dictates the lowest. A hazard with a risk that is low (and, therefore, does not require safety measures in accordance with ISO 26262) is identified as quality management (QM). In some cases, it is desirable or required that an inductive sensor achieves a high ASIL. For example, it may be desirable or required that an inductive sensor used in an electronic power steering (EPS) application achieves ASIL C or ASIL D. To ensure functional safety in an inductive sensor, as well as external coils utilized by the inductive sensor (e.g., an excitation coil and one or more receiving coils on an external printed circuit board (PCB)), a safety mechanism that allows malfunctioning behavior to be identified and signaled should be implemented.

(8) Some implementations described herein provide an inductive sensor with improved safety. In some implementations, the inductive sensor includes a first angle measurement path associated with determining an angular position based on a first set of input signals, a second angle measurement path associated with determining an angular position based on a second set of input signals, and an amplitude regulation path associated with regulating amplitudes of a set of output signals. In some implementations, the inductive sensor includes a safety path associated with performing one or more safety checks, where each safety check of the one or more safety checks is associated with the first angle measurement path, the second angle measurement path, and/or the amplitude regulation path. Notably, in some implementations, the first angle measurement path, the second angle measurement path, the amplitude regulation path, and the safety path are integrated on a monolithic semiconductor device (e.g., on a single chip). Additional details are provided below.

(9) FIG. 1 is a block diagram illustrating an example inductive sensor **100** with improved safety. As shown in FIG. 1, the inductive sensor **100** includes an angle measurement path **102a**, an angle measurement path **102b**, an amplitude regulation path **104**, a transmitting (TX) coil excitation component **106**, a safety path **108**, and a digital output signal generation component **110**. In some implementations, the angle measurement path **102a**, the angle measurement path **102b**, the

amplitude regulation path **104**, and the safety path **108** are integrated on a monolithic semiconductor device (e.g., a single chip). In some implementations, integration on the monolithic semiconductor device reduces a size and cost of inductive sensor **100** (e.g., as compared to a solution that utilizes a non-monolithic solution, such as a dual chip).

(10) As shown in FIG. 1, various paths and components of the inductive sensor **100** are electrically connected to coils of a PCB **150** in order to enable the inductive sensor **100** to receive signals from or transmit signals to the coils of the PCB **150**. For example, as shown in FIG. 1, the angle measurement path **102a** and the amplitude regulation path **104** may be connected to a set of receiving (RX) coils **154a** of the PCB **150** (e.g., to enable receipt of a first set of input signals associated with the set of RX coils **154a**). Similarly, the angle measurement path **102b** and the safety path **108** may be connected to a set of RX coils **154b** (e.g., to enable receipt of a second set of receiving coils signals associated with the set of RX coils **154b**). Further, the TX coil excitation component **106** is connected to the TX coil **152** (e.g., to enable the TX coil excitation component **106** to transmit a set of output signals to the TX coil **152**).

(11) As further indicated in FIG. 1, a rotor **180** (e.g., a metallic or magnetic element that is affixed to the object for which an angular position, an applied torque, or the like, is to be determined) may be arranged relative to the TX coil **152** and the sets of RX coils **154**. In some implementations, the rotor **180** is arranged to move (e.g., rotate about an axis) relative to the TX coil **152** and the sets of RX coils **154** such that inductive coupling between the TX coil **152** and the sets of RX coils **154** depends on a position (e.g., an angular position) of the rotor **180**. In some implementations, the inductive sensor **100** may include a single rotor **180**. In some implementations, the inductive sensor **100** may include multiple rotors **180** (e.g., a rotor **180** for each angle measurement path **102**, an example of which is shown in FIG. 2).

(12) An angle measurement path **102** (e.g., the angle measurement path **102a**, the angle measurement path **102b**) includes one or more components associated with determining an angular position of the rotor **180** based on a set of input signals associated with a set of RX coils **154**. For example, the set of input signals may include a signal indicating a sine of the angular position (herein referred to as a sine signal) and a signal indicating a cosine of the angular position (herein referred to a cosine signal). That is, the set of input signals may include a pair of signals with a 90 degree (°) phase offset. Here, the angle measurement path **102** may determine an angular position of the rotor **180** based on the sine signal and the cosine signal (e.g., by calculating an arctangent of the sine signal divided by the cosine signal).

(13) In some implementations, as shown in FIG. 1, the inductive sensor **100** includes two angle measurement paths **102**, each of which processes a different set of input signals. For example, the angle measurement path **102a** may receive a first set of input signals associated with the set of RX coils **154a** and may determine an angular position of the rotor **180** based on the first set of input signals. Similarly, the angle measurement path **102b** may receive a second set of input signals received associated with the set of RX coils **154b** and may determine an angular position of the rotor **180** based on the second set of input signals. In some implementations, the angle measurement path **102a**, the angle measurement path **102b**, and/or another component of the inductive sensor **100** may include a component configured to calculate a torque based on the angular position determined on the angle measurement path **102a** and the angular position determined on the angle measurement path **102b** (e.g., by calculating a difference between the angular position determined on the angle measurement path **102a** and the angular position determined on the angle measurement path **102b**).

(14) The amplitude regulation path **104** includes one or more components associated with regulating an amplitude of a set of output signals transmitted by the TX coil excitation component **106** (e.g., to the TX coil **152**). For example, the amplitude regulation path **104** may receive the first set of input signals associated with the set of RX coils **154a** and may receive the set of output signals associated with the TX coil excitation component **106** (i.e., output signals actually

transmitted by the TX coil excitation component **106**). Here, the amplitude regulation path **104** may determine a target output signal amplitude based on the first set of input signals and amplitudes of the set of output signals. The amplitude regulation path **104** may then provide, to the TX coil excitation component **106**, a signal indicating the target output signal amplitude and, in this way, may regulate the amplitude of the set of output signals transmitted by the TX coil excitation component **106**.

(15) The TX coil excitation component **106** includes one or more components associated with transmitting the set of output signals to the TX coil **152**. For example, the TX coil excitation component **106** may include a coil oscillator that receives, from the amplitude regulation path **104**, a signal indicating a target output signal amplitude, and may transmit a set of output signals based on the target output signal amplitude (e.g., such that the output signals have an amplitude that matches the target output signal amplitude).

(16) The safety path **108** includes one or more components associated with performing one or more safety checks associated with the inductive sensor **100**. In some implementations, each safety check of the one or more safety checks is associated with at least one of the angle measurement path **102a**, the angle measurement path **102b**, or the amplitude regulation path **104**. In some implementations, as shown in FIG. 1, the safety path **108** may be configured to receive the set of output signals transmitted by the TX coil excitation component **106**, the second set of input signals associated with set of RX coils **154b**, and/or one or more other signals in association with performing the one or more safety checks, as described herein. In some implementations, as shown in FIG. 1, the safety path **108** may be configured to provide a safety indication (e.g., a failure indication, an error indication, a deactivation indication, an OK indication, or the like) to the digital output signal generation component **110**. Details regarding examples of the one or more safety checks that can be performed by the safety path **108** are provided following the description of FIG. 2.

(17) The digital output signal generation component **110** includes one or more components associated with generating and transmitting an output signal (e.g., a signal carrying sensor data, a signal carrying a safety indication, or the like). In some implementations, as shown in FIG. 1, the digital output signal generation component **110** may receive one or more signals from the angle measurement path **102a**, the angle measurement path **102b**, and the safety path **108**, and may generate and transmit the output signal accordingly. In some implementations, the digital output signal generation component **110** may transmit the output signal to an electronic control unit (ECU) (not shown) associated with the inductive sensor **100**.

(18) As indicated above, FIG. 1 is provided as an example. Other examples may differ from what is described with regard to FIG. 1. Further, the number and arrangement of components shown in FIG. 1 are provided as an example. In practice, there may be additional components, fewer components, different components, or differently arranged components than those shown in FIG. 1. Furthermore, two or more components shown in FIG. 1 may be implemented within a single component, or a single component shown in FIG. 1 may be implemented as multiple, distributed components. Additionally, or alternatively, a set of components (e.g., one or more components) shown in FIG. 1 may perform one or more functions described as being performed by another set of components shown in FIG. 1.

(19) FIG. 2 is a block diagram illustrating a particular example implementation **200** of the inductive sensor **100** described above.

(20) As shown in FIG. 2, in the example implementation **200**, the angle measurement path **102a** includes a demodulator **202**, an analog-to-digital convertor (ADC) **204**, a digital input state machine **206**, and an angle calculation component **208**. In some implementations, although not indicated in FIG. 2, the angle measurement path **102a** may further include a torque calculation component **218** or a memory **220** (e.g., a non-volatile memory component). In operation, the demodulator **202** receives a first input signal from a first RX coil **154a** (e.g., via a coil input **Ia0**

and a coil input Ia1), and receives a second input signal from a second RX coil 154a (e.g., via a coil input Ia2 and a coil input Ia3). Here, the first input signal is a signal indicating a cosine of an angular position of the rotor 180a, while the second input signal corresponds to a signal indicating a sine of the angular position of the rotor 180a. The first and second input signals on the angle measurement path 102a are referred to collectively as a first set of input signals. The demodulator 202, the ADC 204, and the digital input state machine 206 process the first set of input signals to generate a signal indicating a cosine x1 of the angular position of the rotor 180a and a signal indicating a sine y1 of the angular position of the rotor 180a, which are provided to the angle calculation component 208. The angle calculation component 208 calculates an angular position a1 of the rotor 180a based on the cosine x1 and the sine y1 (e.g., using information from the memory 220). The angle calculation component 208 then provides the angular position a1 to the torque calculation component 218. In some implementations, as shown, the digital input state machine 206 may provide signals indicating the cosine x1 and the sine y1 as determined on the angle measurement path 102a to the safety path 108 (e.g., to a safety digital signal processor (DSP) 242). In some implementations, the angle calculation component 208 may provide a signal indicating the angular position a1 to the safety path 108 (e.g., to the safety DSP 242). In some implementations, the angle calculation component 208 may provide a signal indicating angular position a1 to the digital output signal generation component 110 (e.g., a digital protocol generation component 222) which may generate and provide (e.g., via an analog protocol output stage 224) an output signal carrying an indication of the angular position a1.

(21) As further shown in the example implementation 200, the angle measurement path 102b includes a demodulator 210, an ADC 212, a digital input state machine 214, and an angle calculation component 216. In some implementations, although not indicated in FIG. 2, the angle measurement path 102b may further include the torque calculation component 218 or the memory 220. In operation, the demodulator 210 receives a first input signal from a first RX coil 154b (e.g., via a coil input Ib0 and a coil input Ib1), and receives a second input signal from a second RX coil 154b (e.g., via a coil input Ib2 and a coil input Ib3). Here, the first input signal is a signal indicating a cosine of an angular position of the rotor 180b, while the second input signal is a signal indicating a sine of the angular position of the rotor 180b. The first and second input signals on the angle measurement path 102b are referred to collectively as a second set of input signals. The demodulator 210, the ADC 212, and the digital input state machine 214 process the second set of input signals to generate a signal indicating a cosine x2 of the angular position of the rotor 180b and a signal indicating a sine y2 of the angular position of the rotor 180b, which are provided to the angle calculation component 216. The angle calculation component 216 calculates an angular position a2 of the rotor 180b based on the cosine x2 and the sine y2 (e.g., and using information from the memory 220). The angle calculation component 216 then provides a signal indicating the angular position a2 to the torque calculation component 218 and to the safety path 108 (e.g., to the safety DSP 242). In some implementations, as shown, the digital input state machine 214 may provide signals indicating the cosine x2 and the sine y2 as determined on the angle measurement path 102b to the safety path 108 (e.g., to the safety DSP 242). In some implementations, the angle calculation component 216 may provide the angular position a1 to the safety path 108 (e.g., to the safety DSP 242). In some implementations, the angle calculation component 216 may provide a signal indicating the angular position a2 to the digital output signal generation component 110 (e.g., the digital protocol generation component 222) which may generate and provide (e.g., via the analog protocol output stage 224) an output signal carrying an indication of the angular position a2.

(22) In some implementations, the torque calculation component 218 (e.g., included on the angle measurement path 102a or the angle measurement path 102b) may determine a torque T based on the angular position a1 from the angle measurement path 102a and the angular position a2 from the angle measurement path 102b. In some implementations, the torque calculation component 218 may provide a signal indicating the torque T to the safety path 108 (e.g., to the safety DSP 242). In

some implementations, the torque calculation component **218** may provide a signal indicating the torque T to the digital output signal generation component **110** (e.g., the digital protocol generation component **222**) which may generate and provide (e.g., via the analog protocol output stage **224**) an output signal carrying an indication of the torque T .

(23) As further shown in the example implementation **200**, the amplitude regulation path **104** includes a demultiplexer **226**, an ADC **228**, a digital input state machine **230**, and a digital amplitude generation component **232**. In operation, the demultiplexer **226** receives a set of output signals (e.g., signals provided to a coil output $O1$ and a coil output $O2$ by the TX coil excitation component **106**, such as a coil oscillator component **234**). The demultiplexer **226**, the ADC **228**, and the digital input state machine **230** process the set of output signals to determine a target output signal amplitude $amp1$, and a signal indicating the target output signal amplitude $amp1$ is provided to the digital amplitude generation component **232**. The digital amplitude generation component **232** then provides, to the coil oscillator component **234**, a signal associated with regulating the amplitudes of the set of output signals (e.g., such that the set of output signals have an amplitude that matches the target signal amplitude $amp1$). In some implementations, as shown, the digital input state machine **230** provides a signal indicating the target output signal amplitude $amp1$ to the safety path **108** (e.g., to the safety DSP **242**).

(24) In some implementations, as further shown, the demultiplexer **226** receives the first set of input signals associated with the set of RX coils **154a**. Here, the demultiplexer **226**, the ADC **228**, and the digital input state machine **230** process the first set of input signals and provide signals indicating a cosine $X1S$ and a sine $Y1S$ to the safety path **108** (e.g., to the safety DSP **242**). Here, the signal indicating the cosine $X1S$ corresponds to a cosine signal of the angular position of the rotor **180a** on the amplitude regulation path **104** (e.g., the cosine signal of the angular position after the first set of input signals is processed by the amplitude regulation path **104**), and the signal indicating the sine $Y1S$ corresponds to a sine signal of the angular position of the rotor **180a** on the amplitude regulation path **104** (e.g., the sine signal of the angular position after the first set of input signals is processed by the amplitude regulation path **104**). In some implementations, the signals indicating the cosine $X1S$ and the sine $Y1S$ are used by the safety path **108** in association with performing one or more safety checks, as described below. Thus, by providing the signals indicating the cosine $X1S$ and the sine $Y1S$ in association with performing the one or more safety checks, the amplitude regulation path **104** may serve partially as a safety path associated with performing the one or more safety checks.

(25) As further shown in the example implementation **200**, the safety path **108** includes a demultiplexer **236**, an ADC **238**, a digital input state machine **240**, the safety DSP **242**, and a memory **244** (e.g., a read-only memory (ROM)). In operation, the demultiplexer **236** receives the second set of input signals associated with the set of RX coils **154b** and receives the set of output signals (e.g., signals provided to the coil output $O1$ and the coil output $O2$ by the TX coil excitation component **106**). The demultiplexer **236**, the ADC **238**, and the digital input state machine **240** process the set of output signals to determine a target output signal amplitude $amp2$ (e.g., in a manner similar to that of the amplitude regulation path **104**), and a signal indicating the target output signal amplitude $amp2$ is provided to the safety DSP **242**. In some implementations, the safety path **108** uses the target output signal amplitude $amp2$ to perform one or more safety checks, as described below.

(26) In some implementations, as shown, the digital input state machine **240** provides signals indicating a cosine $X2S$ and a sine $Y2S$ to the safety path **108** (e.g., to the safety DSP **242**). Here, the signal indicating the cosine $X2S$ corresponds to a cosine signal of the angular position of the rotor **180b** on the safety path **108** (e.g., the cosine signal of the angular position after the second set of input signals is processed by the safety path **108**) and the signal indicating the sine $Y2S$ corresponds to a sine signal of the angular position of the rotor **180b** on the safety path **108** (e.g., the sine signal of the angular position after the second set of input signals is processed by the safety

path **108**). In some implementations, the safety path **108** uses the signals indicating the cosine X2S and the sine Y2S to perform one or more safety checks, as described below.

(27) In some implementations, the safety path **108** may perform one or more safety checks associated with the angle measurement path **102a**, the angle measurement path **102b**, the amplitude regulation path **104**, or the TX coil excitation component **106**. For example, the safety DSP **242** (e.g., using information from the memory **244**) may perform a safety check based on the cosine x1, the sine y1, the angular position a1, the cosine x2, the sine y2, the angular position a2, the torque T, the target output signal amplitude amp1, the cosine X1S, the sine Y1S, the target output signal amplitude amp1, the cosine X2S, the sine Y2S, the target output signal amplitude amp2, or the like. Examples of safety checks that can be performed by the safety DSP **242** are provided below. In some implementations, the safety DSP **242** may provide a safety indication (e.g., a failure indication, an error indication, a deactivation indication, an OK indication, or the like) associated with one or more safety checks performed by the safety path **108** to the digital output signal generation component **110** (e.g., the digital protocol generation component **222**) which may generate and provide (e.g., via the analog protocol output stage **224**) an output signal carrying the safety indication.

(28) As indicated above, FIG. 2 is provided as an example. Other examples may differ from what is described with regard to FIG. 2. Further, the number and arrangement of components shown in FIG. 2 are provided as an example. In practice, there may be additional components, fewer components, different components, or differently arranged components than those shown in FIG. 2. Furthermore, two or more components shown in FIG. 2 may be implemented within a single component, or a single component shown in FIG. 2 may be implemented as multiple, distributed components. Additionally, or alternatively, a set of components (e.g., one or more components) shown in FIG. 2 may perform one or more functions described as being performed by another set of components shown in FIG. 2.

(29) As described above, the safety path **108** may perform one or more safety checks associated with the angle measurement path **102a**, the angle measurement path **102b**, the amplitude regulation path **104**, the TX coil excitation component **106**, or the like. Examples of safety checks that can be performed by the safety path **108** are provided as follows.

(30) In some aspects, the one or more safety checks performed by the safety path **108** may include a determination of whether a difference between the angular position determined on the angle measurement path **102a** and the angular position determined on the angle measurement path **102b** satisfies a threshold. For example, the safety path **108** (e.g., the safety DSP **242**) may receive, from the angle measurement path **102a**, the signal indicating the angular position a1 as determined by the angle measurement path **102a**. The safety path **108** may further receive, from the angle measurement path **102b**, the signal indicating the angular position a2 as determined by the angle measurement path **102b**. Here, the safety path **108** may calculate a difference between the angular position a1 and the angular position a2, and may determine whether the difference satisfies an angular position difference threshold (e.g., is less than or equal a maximum allowable difference, such as 2°, 5°, or the like). In this example, if the difference satisfies the threshold, then the safety path **108** may determine that the angular positions a1 and a2 pass the safety check. Conversely, if the difference fails to satisfy the threshold, then the safety path **108** may determine that the angular positions a1 and a2 fail the safety check.

(31) In some implementations, the one or more safety checks performed by the safety path **108** may include a determination of whether an amplitude of an output signal transmitted by the TX coil excitation component **106** matches a target output signal amplitude determined on the amplitude regulation path **104**. For example, the safety path **108** may receive an output signal provided to the coil output O1 by the TX coil excitation component **106** and may receive the signal indicating target output signal amplitude amp1 determined on the amplitude regulation path **104**. Here, the safety path **108** may calculate a difference between an amplitude of the output signal provided to

the coil output O1 and the target output signal amplitude amp1 determined on the amplitude regulation path 104, and may determine whether the difference satisfies an amplitude difference threshold (e.g., is less than or equal a maximum allowable difference). In this example, if the difference satisfies the threshold, then the safety path 108 may determine that the amplitude of the output signal provided to the coil output O1 passes the safety check. Conversely, if the difference fails to satisfy the threshold, then the safety path 108 may determine that the output signal provided to the coil output O1 fails the safety check. In some implementations, the safety path 108 may (separately) perform this safety check for each output signal provided to a coil output by the TX coil excitation component 106 (e.g., the safety path 108 may perform a similar check for an output signal provided to the coil output O2 by the TX coil excitation component 106).

(32) In some implementations, the one or more safety checks performed by the safety path 108 may include a determination of whether a target output signal amplitude determined on the amplitude regulation path 104 matches a target output signal amplitude determined on the safety path 108. For example, the safety path 108 may receive the signal indicating the target output signal amplitude amp1 determined on the amplitude regulation path 104. The safety path 108 may also receive the set of output signals provided to the coil outputs O1 and O2, as described above. Here, the safety path 108 (e.g., the digital input state machine 240) may determine a target output signal amplitude amp2, based on the set of output signals. The safety path 108 (e.g., the safety DSP 242) may then calculate a difference between the target output signal amplitude amp1 determined on the amplitude regulation path 104 and the target output signal amp2 determined on the safety path 108. The safety path 108 may then determine whether the difference satisfies a target output signal amplitude difference threshold (e.g., is less than or equal a maximum allowable difference). In this example, if the difference satisfies the threshold, then the safety path 108 may determine that the target output signal amplitude amp1 determined on the amplitude regulation path 104 passes the safety check. Conversely, if the difference fails to satisfy the threshold, then the safety path 108 may determine that the target output signal amplitude amp1 determined on the amplitude regulation path 104 fails the safety check.

(33) In some implementations, the one or more safety checks performed by the safety path 108 may include a determination of whether a vector length of amplitudes associated with the first set of input signals is within a particular vector length range on the amplitude regulation path 104. For example, the safety path 108 may receive the signals indicating the cosine X1S and the sine Y1S from the amplitude regulation path 104. Here, the safety path 108 may calculate a vector length raS of amplitudes of the signal indicating the cosine X1S and the signal indicating the sine Y1S (e.g., $raS = \sqrt{X1S.^2 + Y1S.^2}$). Next, the safety path 108 may determine whether the vector length raS is within a particular vector length range (e.g., whether $raS.sub.min \leq raS \leq raS.sub.max$). In this example, if the vector length raS is within the particular vector length range, then the safety path 108 may determine that the vector length raS of the amplitudes associated with the first set of input signals on the amplitude regulation path 104 passes the safety check. Conversely, if the vector length raS is outside of the particular vector length range, then the safety path 108 may determine that the vector length raS of the amplitudes associated with the first set of input signals on the amplitude regulation path 104 fails the safety check. Notably, the vector length raS is not impacted by processing on the angle measurement path 102a (e.g., because the signals indicating the cosine X1S and the sine Y1S are provided by the amplitude regulation path 104). Thus, this safety check provides a vector length check associated with the first set of input signals that is independent of the angle measurement path 102a.

(34) In some implementations, the one or more safety checks performed by the safety path 108 may include a determination of whether a vector length of amplitudes associated with the second set of input signals is within a particular vector length range on the safety path 108. For example, the safety path 108 may process the second set of input signals to generate the signals indicating the cosine X2S and the sine Y2S. Here, the safety path 108 may calculate a vector length rbS of

amplitudes of the signal indicating cosine X2S and the signal indicating the sine Y2S (e.g., $rbS = \sqrt{X2S_{sup}^2 + Y2S_{sup}^2}$). Next, the safety path **108** may determine whether the vector length rbS is within a particular vector length range (e.g., whether $rbS_{sub.min} \leq rbS \leq rbS_{sub.max}$). In this example, if the vector length rbS is within the particular vector length range, then the safety path **108** may determine that the vector length rbS of the amplitudes associated with the second set of input signals passes the safety check. Conversely, if the vector length rbS is outside of the particular vector length range, then the safety path **108** may determine that the vector length rbS of the amplitudes associated with the second set of input signals fails the safety check. Notably, the vector length rbS is not impacted by processing on the angle measurement path **102b** (e.g., because the signals indicating the cosine X2S and the sine Y2S are generated by the amplitude regulation path **104**). Thus, this safety check provides a vector length check associated with the second set of input signals that is independent of the angle measurement path **102b**.

(35) In some implementations, the one or more safety checks include a determination of whether an amplitude associated with a subset of the first set of input signals on the angle measurement path **102a** matches an amplitude associated with a corresponding subset of the second set of input signals on the angle measurement path **102b**. For example, the safety path **108** may receive the signal indicating the cosine $x1$ from the angle measurement path **102a**. The safety path **108** may further receive the signal indicating the cosine signal $x2$ from the angle measurement path **102b**. Here, the safety path **108** may determine a difference between an amplitude of the signal indicating the cosine signal $x1$ from the angle measurement path **102a** and an amplitude of the signal indicating the cosine signal $x2$ from the angle measurement path **102b**, and may determine whether the difference satisfies a signal amplitude difference threshold (e.g., is less than or equal a maximum allowable difference). In this example, if the difference satisfies the threshold, then the safety path **108** may determine that amplitudes of the signals indicating the cosine signals $x1$ and $x2$ pass the safety check. Conversely, if the difference fails to satisfy the threshold, then the safety path **108** may determine that the amplitudes of the signal indicating the cosine signals $x1$ and $x2$ fail the safety check. In some implementations, the safety path **108** may perform a similar safety check for the signal indicating the sine $y1$ from the angle measurement path **102a** and the signal indicating the sine $y2$ from the angle measurement path **102b**.

(36) In some implementations, the one or more safety checks include a determination of whether a torque T calculated on an angle measurement path matches a torque calculated on the safety path **108**. For example, the safety path **108** may receive (e.g., from the angle measurement path **102a**, the angle measurement path **102b**, or the like) a signal indicating a torque T calculated the angle measurement path **102**. Further, the safety path **108** may receive the signal indicating the angular position $a1$ determined on the angle measurement path **102a** and may receive the signal indicating the angular position $a2$ determined on the angle measurement path **102b**. Here, the safety path **108** may calculate a torque based on the angular position $a1$ determined on the angle measurement path **102a** and the angular position $a2$ determined on the angle measurement path **102b**. The safety path **108** may then determine whether a difference between the torque T calculated on the angle measurement path **102** and the torque calculated on the safety path **108** satisfies a torque difference threshold (e.g., is less than or equal a maximum allowable difference). In this example, if the difference satisfies the threshold, then the safety path **108** may determine that the torque T from the angle measurement path **102** passes the safety check. Conversely, if the difference fails to satisfy the threshold, then the safety path **108** may determine that the torque T from the angle measurement path **102** fails the safety check.

(37) In some implementations, the one or more safety checks include a determination of whether a resistance at a connection of the inductive sensor **100** to an external coil (e.g., an RX coil **154**, the TX coil **152**) satisfies a resistance threshold. For example, the safety path **108** may receive a signal indicating a resistance at a connection of the inductive sensor **100** to the external coil, and may determine whether the resistance satisfies a resistance threshold (e.g., is less than or equal to a

maximum allowable resistance). In this example, if the resistance at the connection satisfies the threshold, then the safety path **108** may determine that the resistance at the connection passes the safety check. Conversely, if the resistance at the connection fails to satisfy the threshold, then the safety path **108** may determine that the resistance at the connection fails the safety check.

(38) In some implementations, the one or more safety checks include a determination of whether a vector length of amplitudes associated with the first set of input signals is within a particular vector length range on the angle measurement path **102a**. For example, the safety path **108** may receive the signal indicating the cosine x_1 and the signal indicating the sine y_1 . Here, the safety path **108** may calculate a vector length r_a of the amplitudes of the signal indicating the cosine x_1 and the signal indicating the sine y_1 (e.g., $r_a = \sqrt{x_1^2 + y_1^2}$). Next, the safety path **108** may determine whether the vector length r_a is within a particular vector length range (e.g., whether $r_{a.sub.min} \leq r_a \leq r_{a.sub.max}$). In this example, if the vector length r_a is within the particular vector length range, then the safety path **108** may determine that the vector length r_a of the amplitudes associated with the first set of input signals from the angle measurement path **102a** passes the safety check. Conversely, if the vector length r_a is outside of the particular vector length range, then the safety path **108** may determine that the vector length r_a of the amplitudes associated with the first set of input signals from the angle measurement path **102a** fails the safety check.

(39) In some implementations, the one or more safety checks include a determination of whether a vector length of amplitudes associated with the second set of input signals is within a particular vector length range on the angle measurement path **102b**. For example, the safety path **108** may receive the signal indicating the cosine x_2 and the signal indicating the sine y_2 . Here, the safety path **108** may calculate a vector length r_b of the amplitudes of the signal indicating the cosine x_2 and the signal indicating the sine y_2 from the angle measurement path **102b** (e.g., $r_b = \sqrt{x_2^2 + y_2^2}$). Next, the safety path **108** may determine whether the vector length r_b is within a particular vector length range (e.g., whether $r_{b.sub.min} \leq r_b \leq r_{b.sub.max}$). In this example, if the vector length r_b is within the particular vector length range, then the safety path **108** may determine that the vector r_b length of the amplitudes associated with the second set of input signals from the angle measurement path **102b** passes the safety check. Conversely, if the vector length r_b is outside of the particular vector length range, then the safety path **108** may determine that the vector length r_b of the amplitudes associated with the second set of input signals from the angle measurement path **102b** fails the safety check.

(40) In some implementations, the one or more safety checks include a determination of whether a characteristic of a first coil input associated with a first input signal matches a characteristic of a second coil input associated with a second input signal, where the first input signal is included in the first set of input signals and the second input signal is included in the second set of input signals. For example, the safety path **108** may receive a signal corresponding a first coil input I_{a0} (e.g., a coil input at a particular terminal of an RX coil **154a**), and may receive a signal corresponding to a second coil input I_{b0} (e.g., a coil input at a particular terminal of an RX coil **154b**). Here, the safety path **108** may determine whether a difference between a characteristic (e.g., an amplitude) of the signal corresponding to the coil input I_{a0} matches a characteristic of the signal corresponding to the coil input I_{b0} satisfies a coil input characteristic difference threshold (e.g., is less than or equal a maximum allowable difference). In this example, if the difference satisfies the threshold, then the safety path **108** may determine that the characteristic of the coil inputs I_{a0} and I_{b0} pass the safety check. Conversely, if the difference fails to satisfy the threshold, then the safety path **108** may determine that the characteristic of the coil inputs I_{a0} and I_{b0} fail the safety check. In some implementations, the safety path **108** may perform a similar safety check for other pairs of coil inputs at the RX coils **154** (e.g., coil inputs I_{a1} and I_{b1} , coil inputs I_{a2} and I_{b2} , coil inputs I_{a3} and I_{b3} , or the like).

(41) The above described safety checks are provided as examples, and other safety checks are possible (e.g., depending on the design of the inductive sensor **100**). That is, in some

implementations of the inductive sensor **100**, the safety path **108** may perform one or more additional, other, or different safety checks than those described above.

(42) Notably, in inductive sensor **100** in FIG. **1** (e.g., and in the example implementation **200** of the inductive sensor **100**), the angle measurement path **102a**, the angle measurement path **102b**, the amplitude regulation path **104**, and the safety path **108** are illustrated as being implemented in independent hardware. That is, components of the inductive sensor **100** that perform measurement (e.g., angle measurement, output signal amplitude measurement, or the like), control (e.g., output signal amplitude regulation), and safety checking are illustrated as being implemented in independent hardware. However, in some implementations, one or more components of one or more paths of the inductive sensor **100** may be implemented in software or may be implemented in a combination of hardware and software. For example, portions of two or more paths of the inductive sensor **100** may in some implementations be combined on common (e.g., shared) hardware (e.g., a lockstep core). In some implementations, functions of the portions of the two or more paths combined on the common hardware may be diverse (e.g., to improve safety of using the common hardware).

(43) FIG. **3** is a block diagram illustrating an example implementation **300** of an inductive sensor **100** in which components to perform measurement are implemented in hardware, while components configured to perform control and components configured to perform safety checking are implemented in software. In the example shown in FIG. **3**, the angle measurement path **102a** and the angle measurement path **102b** are implemented in independent hardware. However, the amplitude regulation path **104** is implemented in a combination of hardware and software. For example, a portion **104h** of the amplitude regulation path **104** associated with performing a measurement (e.g., a measurement of an amplitude of an output signal provided by the TX coil excitation component **106**) is implemented in independent hardware, while a portion **104s** of the amplitude regulation path **104** associated with performing control and/or safety checking is implemented in an independent software task. Similarly, a portion **108h** of the safety path **108** associated with performing a measurement is implemented in independent hardware, while a portion **108s** of the safety path **108** associated with performing safety checking is implemented in one or more independent software tasks. In some implementations, the example implementation **300** may utilize independent software tasks (e.g., to ensure safety for the example implementation **300**).

(44) As indicated above, FIG. **3** is provided as an example. Other examples may differ from what is described with regard to FIG. **3**. Further, the number and arrangement of components shown in FIG. **3** are provided as an example. In practice, there may be additional components, fewer components, different components, or differently arranged components than those shown in FIG. **3**. Furthermore, two or more components shown in FIG. **3** may be implemented within a single component, or a single component shown in FIG. **3** may be implemented as multiple, distributed components. Additionally, or alternatively, a set of components (e.g., one or more components) shown in FIG. **3** may perform one or more functions described as being performed by another set of components shown in FIG. **3**.

(45) FIG. **4** is a flowchart of an example process relating to an inductive sensor performing one or more safety checks, as described herein. In some implementations, one or more process blocks of FIG. **4** may be performed by an inductive sensor (e.g., inductive sensor **100**).

(46) As shown in FIG. **4**, process **400** may include receiving a plurality of signals on a safety path of an inductive sensor, wherein each signal of the plurality of signals is received from a first angle measurement path of the inductive sensor, a second angle measurement path of the inductive sensor, or an amplitude regulation path of the inductive sensor (block **410**). For example, the inductive sensor may receive a plurality of signals on a safety path (e.g., safety path **108**) of the inductive sensor, wherein each signal of the plurality of signals is received from a first angle measurement path (e.g., angle measurement path **102a**) of the inductive sensor, a second angle

measurement path (e.g., angle measurement path **102b**) of the inductive sensor, or an amplitude regulation path (e.g., amplitude regulation path **104**) of the inductive sensor, as described above.

(47) As further shown in FIG. 4, process **400** may include performing one or more safety checks on the safety path based on the plurality of signals, wherein each safety check of the one or more safety checks is associated with at least one of the first angle measurement path, the second angle measurement path, or the amplitude regulation path (block **420**). For example, the inductive sensor may perform one or more safety checks on the safety path based on the plurality of signals, wherein each safety check of the one or more safety checks is associated with at least one of the first angle measurement path, the second angle measurement path, or the amplitude regulation path, as described above.

(48) Process **400** may include additional implementations, such as any single implementation or any combination of implementations described below and/or in connection with one or more other processes described elsewhere herein.

(49) In a first implementation, the first angle measurement path, the second angle measurement path, the amplitude regulation path, and the safety path are integrated on a monolithic semiconductor device.

(50) In a second implementation, alone or in combination with the first implementation, the amplitude regulation path includes a partial safety path associated with performing a safety check associated with the first set of input signals.

(51) In a third implementation, alone or in combination with one or more of the first and second implementations, the plurality of signals includes a first signal indicating an angular position determined on the first angle measurement path and a second signal indicating an angular position determined on the second angle measurement path, and performing the one or more safety checks comprises determining whether a difference between the angular position determined on the first angle measurement path and the angular position determined on the second angle measurement path satisfies a threshold.

(52) In a fourth implementation, alone or in combination with one or more of the first through third implementations, the plurality of signals includes a first signal indicating an amplitude of an output signal and a second signal indicating a target output signal amplitude determined on the amplitude regulation path, and performing the one or more safety checks comprises determining whether the amplitude of the output signal matches the target output signal amplitude.

(53) In a fifth implementation, alone or in combination with one or more of the first through fourth implementations, the plurality of signals includes a first signal indicating a target output signal amplitude determined on the amplitude regulation path and a second signal indicating a target output signal amplitude determined on the safety path, and performing the one or more safety checks comprises determining whether the target output signal amplitude determined on the amplitude regulation path matches the target output signal amplitude determined on the safety path.

(54) In a sixth implementation, alone or in combination with one or more of the first through fifth implementations, wherein the plurality of signals includes a set of input signals, and performing the one or more safety checks comprises determining whether a vector length of amplitudes associated with the set of input signals is within a particular vector length range on the amplitude regulation path.

(55) In a seventh implementation, alone or in combination with one or more of the first through sixth implementations, wherein the plurality of signals includes a first set of input signals and a second set of input signals, and performing the one or more safety checks includes determining whether an amplitude associated with a subset of the first set of input signals on the first angle measurement path matches an amplitude associated with a corresponding subset of the second set of input signals on the second angle measurement path.

(56) In an eighth implementation, alone or in combination with one or more of the first through seventh implementations, wherein the plurality of signals includes a signal indicating a torque

calculated on an angle measurement path measurement path matches a torque calculated on the safety path, and performing the one or more safety checks includes determining whether the torque calculated on the angle measurement path matches the torque calculated on the safety path.

(57) In a ninth implementation, alone or in combination with one or more of the first through eighth implementations, wherein the plurality of signals includes a signal indicating a resistance at a connection of the inductive sensor to an external coil, and performing the one or more safety checks comprises determining whether the resistance at the connection of the inductive sensor to the external coil satisfies a resistance threshold.

(58) In a tenth implementation, alone or in combination with one or more of the first through ninth implementations, wherein the plurality of signals includes a set of input signals associated with a set of input signals, and performing the one or more safety checks comprises determining whether a vector length of amplitudes associated with the set of input signals is within a particular vector length range on a corresponding angle measurement path.

(59) In an eleventh implementation, alone or in combination with one or more of the first through tenth implementations, wherein the plurality of signals includes a first input signal and a second input signal, and performing the one or more safety checks comprises determining whether a characteristic a first coil input associated with a first input signal matches a characteristic of a second coil input associated with a second input signal, wherein the first input signal is included in the first set of input signals and the second input signal is included in the second set of input signals.

(60) Although FIG. 4 shows example blocks of process 400, in some implementations, process 400 may include additional blocks, fewer blocks, different blocks, or differently arranged blocks than those depicted in FIG. 4. Additionally, or alternatively, two or more of the blocks of process 400 may be performed in parallel.

(61) The foregoing disclosure provides illustration and description, but is not intended to be exhaustive or to limit the implementations to the precise forms disclosed. Modifications and variations may be made in light of the above disclosure or may be acquired from practice of the implementations.

(62) As used herein, the term “component” is intended to be broadly construed as hardware, firmware, and/or a combination of hardware and software. It will be apparent that systems and/or methods described herein may be implemented in different forms of hardware, firmware, or a combination of hardware and software. The actual specialized control hardware or software code used to implement these systems and/or methods is not limiting of the implementations. Thus, the operation and behavior of the systems and/or methods are described herein without reference to specific software code—it being understood that software and hardware can be designed to implement the systems and/or methods based on the description herein.

(63) As used herein, satisfying a threshold may, depending on the context, refer to a value being greater than the threshold, greater than or equal to the threshold, less than the threshold, less than or equal to the threshold, equal to the threshold, not equal to the threshold, or the like.

(64) Even though particular combinations of features are recited in the claims and/or disclosed in the specification, these combinations are not intended to limit the disclosure of various implementations. In fact, many of these features may be combined in ways not specifically recited in the claims and/or disclosed in the specification. Although each dependent claim listed below may directly depend on only one claim, the disclosure of various implementations includes each dependent claim in combination with every other claim in the claim set. As used herein, a phrase referring to “at least one of” a list of items refers to any combination of those items, including single members. As an example, “at least one of: a, b, or c” is intended to cover a, b, c, a-b, a-c, b-c, and a-b-c, as well as any combination with multiple of the same item.

(65) No element, act, or instruction used herein should be construed as critical or essential unless explicitly described as such. Also, as used herein, the articles “a” and “an” are intended to include

one or more items, and may be used interchangeably with “one or more.” Further, as used herein, the article “the” is intended to include one or more items referenced in connection with the article “the” and may be used interchangeably with “the one or more.” Furthermore, as used herein, the term “set” is intended to include one or more items (e.g., related items, unrelated items, or a combination of related and unrelated items), and may be used interchangeably with “one or more.” Where only one item is intended, the phrase “only one” or similar language is used. Also, as used herein, the terms “has,” “have,” “having,” or the like are intended to be open-ended terms. Further, the phrase “based on” is intended to mean “based, at least in part, on” unless explicitly stated otherwise. Also, as used herein, the term “or” is intended to be inclusive when used in a series and may be used interchangeably with “and/or,” unless explicitly stated otherwise (e.g., if used in combination with “either” or “only one of”).

Claims

1. A sensor, comprising: an amplitude regulation path associated with regulating amplitudes of a first signal associated with a first set of receiving (Rx) coils; and a safety path associated with performing one or more safety checks associated with the amplitude regulation path.
2. The sensor of claim 1, further comprising: a transmitting (Tx) coil excitation component, wherein the first signal is associated with the first set of Rx coils and the Tx coil excitation component, and wherein the one or more safety checks are associated with the amplitude regulation path and the Tx coil excitation component.
3. The sensor of claim 2, wherein the first signal is based on: a set of input signals associated with a set of Rx coils, and a set of second output signals associated with the Tx coil excitation component.
4. The sensor of claim 1, wherein the one or more safety checks include at least one of: a determination of whether an amplitude of the first signal matches a target output signal amplitude determined on the amplitude regulation path, or a determination of whether a target output signal amplitude determined on the amplitude regulation path matches a target output signal amplitude determined on the safety path.
5. The sensor of claim 1, further comprising: one or more angle measurement paths associated with angular positions associated with second signals associated with a second set of Rx coils.
6. The sensor of claim 5, wherein the one or more safety checks are associated with the amplitude regulation path and the one or more angle measurement paths.
7. The sensor of claim 1, further comprising: an output component configured to: receive, from the safety path, an input signal, different from the first signal, associated with the one or more safety checks, generate an output signal, different from the first signal, based on the input signal, and transmit the output signal.
8. A sensor, comprising: at least two of: a first position measurement path associated with determining a first angular position based on a first set of input signals associated with a set of receiving (Rx) coils, a second position measurement path associated with determining a second angular position based on a second set of input signals associated with the set of Rx coils, or an amplitude regulation path associated with regulating amplitudes of a set of output signals; and a safety path associated with performing one or more safety checks associated with the at least two of the first position measurement path, the second position measurement path, or the amplitude regulation path.
9. The sensor of claim 8, wherein the first set of input signals or the second set of input signals comprises: a signal indicating a sine of a respective one of the first angular position or the second angular position, and a signal indicating a cosine of the respective one of the first angular position or the second angular position.
10. The sensor of claim 8, wherein the one or more safety checks includes a determination of whether a difference between the first angular position and the second angular position satisfies a

threshold.

11. The sensor of claim 8, wherein the one or more safety checks includes at least one of: a determination of whether a vector length of amplitudes associated with the first set of input signals is within a particular vector length range on the amplitude regulation path, a determination of whether a vector length of amplitudes associated with the second set of input signals is within a particular vector length range on the safety path, or a determination of whether an amplitude associated with a subset of the first set of input signals on the first position measurement path matches an amplitude associated with a corresponding subset of the second set of input signals on the second position measurement path.

12. The sensor of claim 8, wherein the one or more safety checks includes at least one of: a determination of whether a torque based on at least one of the first position measurement path or the second position measurement path matches a torque based on the safety path, or a determination of whether a resistance at a connection of the sensor to an external coil satisfies a resistance threshold.

13. The sensor of claim 8, wherein the one or more safety checks includes at least one of: a determination of whether a vector length of amplitudes associated with the first set of input signals is within a particular vector length range on the first position measurement path, a determination of whether a vector length of amplitudes associated with the second set of input signals is within a particular vector length range on the second position measurement path, or a determination of whether a characteristic of a first coil input associated with a first signal of the first set of input signals matches a characteristic of a second coil input associated with a second input signal of the second set of input signals.

14. The sensor of claim 8, wherein at least one of: the first position measurement path comprises a first angle and linear position measurement path, or the second position measurement path comprises a second angle and linear position measurement path.

15. A method, comprising: receiving one or more first signals, associated with a set of receiving (Rx) coils, on an amplitude regulation path associated with a sensor; receiving one or more second signals on at least one of: a first safety path, of the sensor, from a first angle measurement path of the sensor, or a second safety path, of the sensor, from a second angle measurement path of the sensor; and performing one or more safety checks on the amplitude regulation path and the at least one of: the first angle measurement path or the second angle measurement path.

16. The method of claim 15, wherein the first angle measurement path and the second angle measurement path are integrated on a monolithic semiconductor device.

17. The method of claim 15, wherein the one or more second signals includes: a signal indicating a first angular position associated with the first angle measurement path, and a signal indicating a second angular position associated with the second angle measurement path.

18. The method of claim 17, wherein performing the one or more safety checks comprises at least one of: determining whether a difference between the first angular position and the second angular position satisfies a threshold.

19. The method of claim 15, wherein performing the one or more safety checks comprises: determining whether a torque based on at least one of the first angle measurement path or the second angle measurement path matches a torque based on the at least one of the first safety path or the second safety path.

20. The method of claim 15, wherein performing the one or more safety checks comprises: determining whether a resistance at a connection of the sensor to an external coil satisfies a resistance threshold.
