

(56)

References Cited

U.S. PATENT DOCUMENTS

2015/0162128	A1 *	6/2015	Rosenfeld		H01F 38/14 336/200
2015/0222129	A1 *	8/2015	McCauley		H01F 27/02 307/104
2017/0222483	A1 *	8/2017	Feng		H02J 50/90
2019/0097448	A1 *	3/2019	Partovi		H02J 50/40

OTHER PUBLICATIONS


N. Ha-Van and C. Seo, "Analytical and Experimental Investigations of Omnidirectional Wireless Power Transfer Using a Cubic Transmitter," IEEE Transactions on Industrial Electronics, vol. 65, No. 2, pp. 1358-1366, Feb. 2018.

J. Feng, Q. Li, F. C. Lee and M. Fu, "Transmitter Coils Design for Free-Positioning Omnidirectional Wireless Power Transfer System," in IEEE Transactions on Industrial Informatics, vol. 15, No. 8, pp. 4656-4664, Aug. 2019.


B. H. Choi; E. S. Lee.; Y. H. Sohn, G. C. Jang, C. T. Rim, "Six Degrees of Freedom Mobile Inductive Power Transfer by Crossed Dipole Tx and Rx Coils," IEEE Transactions on Power Electronics, vol. 31, No. 4, pp. 3252-3272, Apr. 2016.

A. Sharma, G. Singh, D. Bhatnagar, I. J. Garcia Zuazola and A. Perallos, "Magnetic field forming Using Planar Multicoil Antenna to Generate Orthogonal H-Field Components," in IEEE Transactions on Antennas and Propagation, vol. 65, No. 6, pp. 2906-2915, Jun. 2017.


* cited by examiner

**FIG. 1**


--Prior Art--

**FIG. 2A**

--Prior Art--

**FIG. 2B**

--Prior Art--

**FIG. 3**




FIG. 4A




FIG. 4B




FIG. 5A




FIG. 5B




FIG. 6A




FIG. 6B

FIG. 7A










FIG. 7B

FIG. 8A














FIG. 9

**FIG. 10****FIG. 11**

**FIG. 12**

**FIG. 13**

**FIG. 14**

**FIG. 15**




FIG. 16A




FIG. 16B




FIG. 16C




FIG. 17











FIG. 18



**FIG. 19**


**FIG. 20**



**FIG. 21**

**FIG. 22**

**FIG. 23**

**FIG. 24**

**FIG. 25**

**FIG. 26**

1

PLANAR OMNIDIRECTIONAL WIRELESS POWER TRANSFER SYSTEM

BACKGROUND

Wireless power or energy transfer is directed to the transmission of electrical energy from a power source to an electrical load without the use of conductors. Wireless power transfer can be achieved using a various power transmission technologies using time-varying electric, magnetic, or electromagnetic fields. Wireless power transfer can be particularly useful in situations where the use of conductors is inconvenient or dangerous, for example, to transfer power.

For near-field wireless power transfer, inductive coupling is widely used and its applications include providing power to charge electric toothbrushes, radio-frequency identification (RFID) tags, smartcards, and implantable medical devices. Recently, more emphasis has been placed on the development of wireless power transfer systems for charging mobile and handheld computing devices.

Overall, wireless power transfer with loosely coupled coils is a promising solution to deliver power to a battery in a variety of applications. Due to its convenience, wireless power transfer technology has become popular in electric vehicles, consumer electronics, and medical devices. Thus far, the majority of these systems are directional power transfer systems, and the magnetic field induced by the transmitter coil is in one direction, meaning that the energy power transfer capability degrades greatly when there is some angle misalignment between the coupled coils.

BRIEF DESCRIPTION OF THE DRAWINGS

Many aspects of the present disclosure can be better understood with reference to the following drawings. The components in the drawings are not necessarily drawn to scale, with emphasis instead being placed upon clearly illustrating the principles of the disclosure. In the drawings, like reference numerals designate corresponding parts throughout the several views.

FIG. 1 illustrates an example wireless power transfer system according to various examples described herein.

FIG. 2A illustrates an example wireless power transfer platform with three orthogonal, symmetric coils according to various examples described herein.

FIG. 2B illustrates example excitation waveforms applied to the orthogonal, symmetric coils X, Y, and Z shown in FIG. 2A, respectively, according to various examples described herein.

FIG. 3 illustrates an example planar omnidirectional wireless power transfer system according to various aspects of the embodiments described herein.

FIG. 4A illustrates a pair of circular coils arranged to provide field directivity between the coils according to various aspects of the embodiments described herein.

FIG. 4B illustrates a pair of rectangular coils arranged to provide field directivity between the coils according to various aspects of the embodiments described herein.

FIG. 5A illustrates a perspective view of the pair of rectangular coils shown in FIG. 4B, arranged to provide field directivity between the coils according to various aspects of the embodiments described herein.

FIG. 5B is an example cross-sectional diagram of fields generated by the pair of rectangular coils shown in FIG. 5A, taken along A'-A' in FIG. 5A, according to various aspects of the embodiments described herein.

2

FIG. 6A illustrates a perspective view of a pair of graduated rectangular coils, arranged to provide field directivity between the coils according to various aspects of the embodiments described herein.

FIG. 6B is an example cross-sectional diagram of fields generated by the pair of rectangular coils shown in FIG. 6A, taken along B'-B' in FIG. 6A, according to various aspects of the embodiments described herein.

FIG. 7A illustrates an example planar coil arrangement including a first pair of graduated coils, a second pair of graduated coils, and a third coil according to various aspects of the embodiments described herein.

FIG. 7B illustrates the first pair of graduated coils, the second pair of graduated coils, and the third coil shown in FIG. 7A according to various aspects of the embodiments described herein.

FIG. 8A illustrates another example planar coil arrangement including a first pair of graduated coils, a second pair of graduated coils, and a third coil according to various aspects of the embodiments described herein.

FIG. 8B illustrates the first pair of graduated coils, the second pair of graduated coils, and the third coil shown in FIG. 7B according to various aspects of the embodiments described herein.

FIG. 8C illustrates the practical application of the planar coil arrangement shown in FIG. 8A according to various aspects of the embodiments described herein.

FIG. 8D illustrates another planar coil arrangement according to various aspects of the embodiments described herein.

FIG. 8E illustrates another planar coil arrangement according to various aspects of the embodiments described herein.

FIG. 9 illustrates other components of the example omnidirectional wireless power transfer system shown in FIG. 3 according to various aspects of the embodiments described herein.

FIG. 10 illustrates four example resonant tank topologies according to various aspects of the embodiments described herein.

FIG. 11 illustrates an example series-series resonant converter topology according to various aspects of the embodiments described herein.

FIG. 12 illustrates an example equivalent circuit of the example series-series resonant converter shown in FIG. 11 according to various aspects of the embodiments described herein.

FIGS. 13 and 14 illustrate voltage gain and phase of input impedance curves for different load resistances and resonant couplings according to various aspects of the embodiments described herein.

FIG. 15 illustrates gain characteristics of a resonant converter having a series resonant frequency between two parallel resonant frequencies according to various aspects of the embodiments described herein.

FIGS. 16A-16C illustrate the general topology forms of resonant converters with coupling independent resonance and zero voltage switching according to various aspects of the embodiments described herein.

FIG. 17 illustrates a resonant converter having a series resonant frequency between two parallel resonant frequencies according to various aspects of the embodiments described herein.

FIG. 18 illustrates an example use of Norton's Theorem and Thevenin's Theorem to transform the resonant tank network shown in FIG. 17 into a simple branch according to various aspects of the embodiments described herein.

FIG. 19 illustrates the simple branch developed using Norton's Theorem and Thevenin's Theorem from the relatively complicated resonant tank network shown in FIG. 18 according to various aspects of the embodiments described herein.

FIGS. 20 and 21 illustrate voltage gain and phase of input impedance curves for different load resistances and resonant couplings of the resonant converter shown in FIG. 16 according to various aspects of the embodiments described herein.

FIGS. 22-26 illustrate other example resonant converter topologies and gain curve characteristics according to various aspects of the embodiments described herein.

DETAILED DESCRIPTION

Near-field wireless power transfer can be relied upon to transfer power in various applications or fields of use, such as in military, medical, consumer device, and automotive fields, among others. One challenge in the design of near-field wireless power transfer systems arises because the level of coupling between transmitter and receiver coils can vary. The level or extent of coupling can vary because there is no predefined physical connection or orientation between the transmitter and receiver coils. For example, in a wireless power transfer system where a user is expected to set or place a device upon a charging plate or base, the position and orientation of the receiver coil (with respect to the transmitter coil) is dependent on the user's placement of the device and can vary. Thus, the coupling coefficient between the transmitter and receiver coils is not fixed as in the conventional case where a transformer is used. At the same time, the load presented by the device can vary, for example, based on different charging stages of the charging profile of the battery, among other reasons.

Many conventional wireless power transfer platforms are designed to be directional, meaning that devices are charged efficiently only when placed in a predetermined orientation (or relatively narrow range of certain orientations). Small portable electronic devices can typically be placed near a wireless charging station in a number of different orientations, however, and some of those orientations may not be suitable for efficient wireless power transfer. Thus, a well-designed omnidirectional wireless power transfer system would be desirable for charging portable electronic devices.

To illustrate the types of problems that can be encountered with conventional wireless power transfer platforms, FIG. 1 illustrates an example wireless power transfer system 1 according to various examples described herein. The wireless power transfer system 1 includes a wireless charging pad 2 among other components not shown in FIG. 1. The wireless charging pad 2 is set on a planar or relatively planar surface 3. The wireless charging pad 2 includes a coil for wireless power transfer to the devices 4 and 5, among possibly others, placed over the wireless charging pad 2. The devices 4 and 5 can be placed or set on the wireless charging pad 2 in nearly any position and orientation.

The wireless charging pad 2 is designed to generate a magnetic field having primary field density in one (or primarily one) direction 6, such as extending up from a center of the wireless charging pad 2 in a direction orthogonal to the planar surface 3. Based on the respective orientations of the devices 4 and 5, coupling between the magnetic field generated by the wireless charging pad 2 and receiver coils in the devices 4 and 5 will vary. For example, the coefficient of coupling between the magnetic field and the receiver coil in the device 4 may be greater than the

coefficient of coupling between the magnetic field and the receiver coil in the device 5. In that case, the wireless charging pad 2 can transfer more power to the device 4 than the device 5. The difference is primarily attributed to the orientation of the devices 4 and 5, and the receiver coils in the devices 4 and 5, over the wireless charging pad 2.

The level or extent of coupling between the wireless charging pad 2 and the devices 4 and 5 can also vary as the devices 4 and 5 are placed and replaced or repositioned on the wireless charging pad 2 over time. The coupling can vary because there is no predefined physical orientation between the wireless charging pad 2 and the receiver coils in the devices 4 and 5. The positions and orientations of the receiver coils in the devices 4 and 5 with respect to the transmitter coil in the wireless charging pad 2 is dependent on a user's placement of the devices 4 and 5 and can vary. Thus, the coupling coefficients are not fixed as in the conventional case where a transformer is used.

The wireless power transfer system 1 is designed to generate a magnetic field having primary field density in one direction, but other wireless power transfer systems have been proposed. Example systems are described in U.S. Pat. No. 10,333,353, titled "OMNIDIRECTIONAL WIRELESS POWER TRANSFER SYSTEM," which is hereby incorporated herein by reference in its entirety. An example coil arrangement for wireless power transfer with three orthogonal, symmetric coils X, Y, and Z, is shown in FIG. 2A. The excitation waveforms applied to coils X, Y, and Z, respectively, are shown in FIG. 2B and in expressions (1)-(3) below. The amplitude of the excitation current of coil Y and coil Z is modulated by relatively low frequency sinusoidal waveforms.

$$I_x = I_m \sin(\omega t) \quad (1)$$

$$I_y = I_m \sin(\omega_2 t) \sin\left(\omega t + \frac{\pi}{2}\right) \quad (2)$$

$$I_z = I_m \sin\left(\omega_2 t + \frac{\pi}{2}\right) \sin\left(\omega t + \frac{\pi}{2}\right) \quad (3)$$

With these excitation currents, magnetic field induced at a center of the three symmetric coils can be expressed as:

$$\vec{B}_x = \frac{\mu_0}{2R} I_x \vec{x}, \vec{B}_y = \frac{\mu_0}{2} I_y \vec{y}, \text{ and } \vec{B}_z = \frac{\mu_0}{2R} I_z \vec{z}, \text{ where} \quad (4)$$

μ_0 is vacuum permeability, $\vec{x}$, $\vec{y}$, $\vec{z}$ are standard basis vectors, and R is the radius of the coils.

The total magnetic field induced at the center by three coils can be calculated as:

$$\vec{B}_t = \vec{B}_x + \vec{B}_y + \vec{B}_z. \quad (5)$$

The total magnetic field at the center of the three symmetric coils is a time-varying vector, and the magnitude is constant according to expression (6) as:

$$|B_t|^2 = |B_x|^2 + |B_y|^2 + |B_z|^2 = \frac{\mu_0^2 I_m^2}{4R^2} \left[\sin^2(\omega t) + \sin^2(\omega_2 t) \sin^2\left(\omega t + \frac{\pi}{2}\right) + \sin^2\left(\omega_2 t + \frac{\pi}{2}\right) \sin^2\left(\omega t + \frac{\pi}{2}\right) \right] = \frac{\mu_0^2 I_m^2}{4R^2}. \quad (6)$$

As such, the field trajectory will be on the surface of a sphere. Thus, with a structure of three symmetric coils and

5

modulated excitation current, omnidirectional field can be induced at the center and magnetic field will rotate in a three-dimensional manner over time.

Other than at the center point O, the magnetic field induced by each coil is not the same and the magnetic field trajectory is not on the surface of a sphere. For example, as for point A in FIG. 2A, which is away from the center, the magnetic field induced by coil X and coil Y is very small and can be neglected compared with the magnetic field induced by coil Z. Therefore, there is no omnidirectional magnetic field at point A. For similar reasons, there is also no omnidirectional magnetic field at any other point other than the center point O. In practice, even with a spherical or semispherical container, devices will fall to the bottom and/or lay on side surfaces of the container, and there is no omnidirectional magnetic field in those areas with the coil structure shown in FIG. 2A.

To improve upon the systems described above with reference to FIGS. 1 and 2A, a number of planar omnidirectional wireless power transfer systems are described herein. According to aspects of the embodiments, an omnidirectional wireless power transfer system includes a high frequency power generator configured to generate a supply of high frequency oscillating power, a number of transmitter-side resonant tank circuits electrically coupled to the high frequency power generator, a planar coil arrangement including a number of coils arranged for omnidirectional power transfer to an electronic device about the planar coil arrangement, and a controller configured to activate individual ones of the transmitter-side resonant tank circuits to wirelessly transmit power to the electronic device through near-field resonant inductive coupling. In one example, the controller can activate individual ones of the transmitter-side resonant tank circuits over time to generate an omnidirectional magnetic field distribution for wireless power transmission. In other aspects, various transmitter-side and receiver-side tank circuits for coupling independent resonance and zero voltage switching (ZVS) operation are described.

FIG. 3 illustrates an example planar omnidirectional wireless power transfer system 10 according to various aspects of the embodiments described herein. The wireless power transfer system 10 is a representative example to convey the concepts described herein. The wireless power transfer system 10 can include additional components that are not shown in the drawings, and one or more of the components illustrated can be omitted in some cases.

The wireless power transfer system 10 includes a power transfer controller 50 and a power transfer platform 60. The platform 60 is set on a planar or relatively planar surface 20 in the example shown. The power transfer controller 50 is electrically coupled to and controls the operations of the platform 60. The platform 60 includes a planar coil arrangement. The planar coil arrangement can include a number of coils arranged for omnidirectional wireless power transfer to the devices 70 and 71, among possibly others, placed over the power transfer platform 60.

The platform 60, under the control of the power transfer controller 50, generates fields that extend in more than one direction, including fields that can change direction over time. For example, the power transfer controller 50 can control the platform 60 to generate fields that extend in the vertical direction 80, which is orthogonal to (or substantially orthogonal to) the planar surface 20. The power transfer controller 50 can also control the platform 60 to generate fields that extend in the horizontal direction 81, which is parallel to (or substantially parallel to) the planar surface

6

20. While having a significant component that runs parallel to the planar surface 20, the horizontal direction 81 can also vary in terms of its rotation. The power transfer controller 50 can also control the platform 60 to vary or shift the direction of generated fields among the vertical direction 80 and the horizontal direction 81 over time. Thus, the wireless power transfer system 10 can generate omnidirectional fields.

The wireless power transfer system 10 can adjust or adapt the extent of inductive coupling between the platform 60 and the devices 70 and 71, even if the devices 70 and 71 are repositioned on the power transfer platform 60 over time. The power transfer controller 50 can adjust or adapt the inductive coupling by powering one or more of the coils in the platform 60 in a certain sequence or manner over time. Thus, the coupling coefficient between the platform 60 and the devices 70 and 71 can be adjusted for the best power transfer, even when the devices 70 and 71 are repositioned over time.

The platform 60 includes a number of coils arranged for omnidirectional power transfer to the devices 70 and 71, among others, through inductive coupling. As described in further detail below with reference to FIGS. 7A and 8A, the coils can be embedded or integrated in or on the platform 60 in a number of different arrangements for the transmission of power. At the same time, the devices 70 and 71 include coils for the receipt of power from the platform 60. Power can be transferred from the power transfer platform 60 to the devices 70 and 71 through inductive coupling. In other aspects of the embodiments, power can be transferred through near-field resonant inductive coupling between magnetically coupled coils that are part of resonant circuits tuned to resonate at a common frequency.

The devices 70 and 71 can include various types of devices, such as cellular phones, watches, gaming devices, fitness trackers, RFID-enabled keys and tags, wireless headphones, tablet computers, e-book readers, and other devices. The positions and orientations of the coils in the platform 60 are known and constant based on design. However, the positions and orientations of the coils in the devices 70 and 71 (i.e., with respect to the platform 60) cannot be known with certainty, because the devices 70 and 71 can be placed in various ways (i.e., positions and orientations) on the platform 60.

In certain aspects of the embodiments, the power transfer controller 50 is configured to activate a number of resonant cell circuits (which include the coils in the platform 60) to provide omnidirectional wireless power transfer to the devices 70 and 71. Due to the omnidirectional nature of the wireless power transfer using the system 10, the transfer of power to the devices 70 and 71 (for charging or other purposes) can be increased as compared to other systems such as those shown in FIGS. 1 and 2A, among others.

Particularly, even though the orientation of the devices 70 and 71 can vary from time to time, the omnidirectional nature of wireless power transfer using the system 10 offers greater power transfer than systems without such omnidirectional characteristics. In the context of the examples described below, the omnidirectional nature of the system 10 is related to the type and arrangement of the coils in the platform 60 and the ability for the power transfer controller 50 to activate those coils, individually or in combination with each other with modulation excitation current. The transfer of power during the activation of individual coils and combinations of coils is evaluated by the power transfer controller 50 to select certain coils which offer better transfer of power. Additionally, the power transfer controller 50 can also modulate the supply of power to individual resonant

cell circuits in the system 10, to search for and find a power supply approach for the highest power transfer to the devices 70 and 71.

In other aspects, the system 10 can incorporate resonant converter gain characteristics in which one series resonance frequency is positioned or centered between two parallel resonant frequencies. Resonant converter topologies with such gain characteristics can achieve the advantages of coupling independent resonance and ZVS operation, which means this converter can always operate efficiently no matter how the electronic devices is positioned. Example resonant converter topologies exhibiting those gain characteristics are described in further detail below. These resonant converter topologies are particularly suitable for applications with variable coupling and variable load, such as encountered during wireless power transfer.

Various examples of the coils for use in the platform 60 are described below with reference to FIGS. 4A, 4B, 5A, 5B, 6A, 6B, 7A, 7B, 8A, and 8B. The coils are illustrated in a representative fashion, as examples for the purpose of discussion. The coils are not illustrated as continuous wires or traces, but instead using concentric shapes for ease of illustration. In practice, each of the coils can be formed using a single, non-overlapping (or non-intersecting) conductive wire or trace. The coils can be formed in one or more layers of printed circuit boards (PCBs), as a wire winding secured to a suitable substrate, or using other suitable approaches. The coils in the platform 60 are designed to be planar in nature, such that the platform 60 can be formed in a relatively planar shape or form itself. Thus, the platform 60 can be easily integrated into many different types of structures, such as in desks, tables, and other furniture, in countertops, in automobiles, and in other structures.

FIG. 4A illustrates a pair of circular coils 200 arranged to provide field directivity in a direction 203 (i.e., from left to right on the page, in the X direction) between the coils 200 according to various aspects of the embodiments described herein. The pair of circular coils 200 includes a first circular coil 201 and a second circular coil 202. The first circular coil 201 is arranged in a side-by-side arrangement next to the second circular coil 202. In the example shown, current flows through the first circular coil 201 in a counter-clockwise direction, such that the field generated by the first circular coil 201 extends out of the page. Current flows through the second circular coil 202 in a clockwise direction, such that the field generated by the second circular coil 202 extends into the page.

Because the coils 201 and 202 are arranged next to each other, a portion of the field that extends out of the page through the center of the coil 201 extends toward the coil 202 in the direction 203 and into the page through the center of the coil 202. Thus, over the circular coils 200, a portion of the field extends horizontally in the X direction 203, from left to right across the page. As such, that portion of the field can inductively couple to another coil (not shown), when arranged in a plane that extends orthogonal to the page and also perpendicular to the direction 203 (i.e., in the Y direction).

FIG. 4B illustrates a pair of rectangular coils 210 arranged to provide field directivity in a direction 213 (i.e., from left to right on the page, in the X direction) between the coils 210 according to various aspects of the embodiments described herein. The pair of rectangular coils 210 includes a first rectangular coil 211 and a second rectangular coil 212. The first rectangular coil 211 is arranged in a side-by-side arrangement next to the second rectangular coil 212. The first rectangular coil 211 extends along the longitudinal axis

214, and the second rectangular coil 212 extends along the longitudinal axis 215 as shown. The longitudinal axis 214 extends parallel or substantially parallel to the longitudinal axis 215. In the example shown, current flows through the first rectangular coil 211 in a counter-clockwise direction, such that the field generated by the first rectangular coil 211 extends out of the page. Current flows through the second rectangular coil 212 in a clockwise direction, such that the field generated by the second rectangular coil 212 extends into the page.

Because the coils 211 and 212 are arranged next to each other, a portion of the field that extends out of the page through the center of the coil 211 extends toward the coil 212 in the direction 213 and into the page through the center of the coil 212. Thus, over the rectangular coils 210, a portion of the field extends horizontally in the X direction 213, from left to right across the page. As such, that portion of the field can inductively couple to another coil (not shown), when arranged in a plane that extends orthogonal to the page and also perpendicular to the direction 213 (i.e., in the Y direction). Another example of the horizontal extension of the field in the X direction is shown in FIG. 5A.

FIG. 5A illustrates a perspective view of the pair of rectangular coils 210 shown in FIG. 4B, arranged to provide field directivity in a direction 213 (i.e., from left to right on the page, in the X direction) between the coils 210 according to various aspects of the embodiments described herein. The pair of rectangular coils 210 includes the first rectangular coil 211 and the second rectangular coil 212. The first rectangular coil 211 is arranged in a side-by-side arrangement next to the second rectangular coil 212. In the example shown, current flows through the first rectangular coil 211 in a counter-clockwise direction. Current flows through the second rectangular coil 212 in a clockwise direction.

Because the coils 211 and 212 are arranged next to each other, a portion of the field that extends out of the page through the center of the coil 211 extends toward the coil 212 in the direction 213 and into the page through the center of the coil 212. Thus, over the rectangular coils 210, a portion of the field extends horizontally in the X direction 213, from left to right across the page, as shown. As such, that portion of the field can inductively couple to another coil (not shown), when arranged in the plane 216 that extends orthogonal to the page and also perpendicular to the direction 213 (i.e., in the Y direction).

FIG. 5B is an example cross-sectional diagram of fields generated by the pair of rectangular coils 210 shown in FIG. 5A, taken along A'-A' in FIG. 5A, according to various aspects of the embodiments described herein. The coils 211 and 212 are shown in the side-by-side arrangement in FIG. 5B, with the portion of the field extending horizontally in the X direction 213. An example length "A" of the extension in the horizontal direction 213 is shown in FIG. 5B.

FIG. 6A illustrates a perspective view of a pair of graduated rectangular coils 220, arranged to provide field directivity in a direction 223 (i.e., from left to right on the page, in the X direction) between the coils 220 according to various aspects of the embodiments described herein. The pair of graduated rectangular coils 220 includes the first graduated rectangular coil 221 and the second graduated rectangular coil 222. The first graduated rectangular coil 221 is arranged in a side-by-side arrangement next to the second graduated rectangular coil 222. The first graduated rectangular coil 221 extends along the longitudinal axis 224, and the second graduated rectangular coil 222 extends along the longitudinal axis 225 as shown. The longitudinal axis 224 extends parallel or substantially parallel to the longitudinal

axis **225**. In the example shown, current flows through the first graduated rectangular coil **221** in a counter-clockwise direction. Current flows through the second graduated rectangular coil **222** in a clockwise direction.

Because the coils **221** and **222** are arranged next to each other, a portion of the field that extends out of the page through the center of the coil **221** extends toward the coil **222** in the direction **223** and into the page through the center of the coil **222**. Thus, over the rectangular coils **220**, a portion of the field extends horizontally in the X direction **223**, from left to right across the page, as shown. As such, that portion of the field can inductively couple to another coil (not shown), when arranged in the plane **226** that extends orthogonal to the page and also perpendicular to the direction **223** (i.e., in the Y direction).

FIG. **6B** is an example cross-sectional diagram of fields generated by the pair of rectangular coils **220** shown in FIG. **6A**, taken along B'-B' in FIG. **6A**, according to various aspects of the embodiments described herein. The coils **221** and **222** are shown in the side-by-side arrangement in FIG. **6B**, with the portion of the field extending in horizontally in the X direction **223**. An example length "B" of the extension in the horizontal direction **223** is shown in FIG. **6B**. The length "B" in FIG. **6B** is longer than the length "A" in FIG. **5B**, because the rectangular coils **221** and **222** in FIG. **6A** are graduated, as compared to the rectangular coils **211** and **212** in FIG. **5A**. Thus, the graduated rectangular coils **221** and **222** can provide a larger area for inductive coupling over the horizontal direction **223** than the rectangular coils **211** and **212**. The magnetic field induced by the graduated rectangular coils **221** is also more uniform as compared with the rectangular coils **211** and **212**. Additional aspects of the graduated rectangular coils **221** and **222** are described in further detail below with reference to FIG. **7**.

FIG. **7A** illustrates an example planar coil arrangement **240** according to various aspects of the embodiments described herein. The platform **60** can incorporate or include the planar coil arrangement **240**. The planar coil arrangement **240** includes a first pair of graduated coils **220A** to provide field directivity in a first "X" direction, a second pair of graduated coils **220B** to provide field directivity in a second "Y" direction, and a third coil **230** to provide field directivity in a third "Z" (i.e., out of the page) direction. The coils **220A**, **220B**, and **230** are centered and can overlap each other in some lengths of windings, although the coils **220A**, **220B**, and **230** are electrically isolated or separated from each other. FIG. **7B** illustrates the first pair of graduated coils **220A**, the second pair of graduated coils **220B**, and the third coil **230** shown in FIG. **7A**, separated from each other.

The planar coil arrangement **240** and the coils **220A**, **220B**, and **230** are illustrated in a representative fashion in FIGS. **7A** and **7B**, as examples for the purpose of discussion. The coils **220A**, **220B**, and **230** are not illustrated as continuous wires or traces, but instead using concentric shapes for ease of illustration. In practice, each of the coils **220A**, **220B**, and **230** can be formed using one or more conductive wires or traces. The coils **220A**, **220B**, and **230** can be formed in one or more layers of PCBs, as windings secured to a suitable substrate, or using other suitable approaches. The coils **220A**, **220B**, and **230** are designed to be planar in nature, such that the planar coil arrangement **240** can be formed in a relatively planar shape or form itself. Thus, the planar coil arrangement **240** can be easily integrated into many different types of structures, such as in desks, tables, and other furniture, in countertops, in automobiles, and in other structures. Currents can be supplied, respectively, to the coils **220A**, **220B**, and **230** of the planar coil arrangement

240 by the power transfer controller **50** (FIG. **3**), to provide omnidirectional wireless power transfer, as described in further detail below with reference to FIG. **9**.

Referring to FIG. **7B**, the first pair of graduated rectangular coils **220A** includes a first graduated rectangular coil **221A** and the second graduated rectangular coil **222A**. The second pair of graduated rectangular coils **220B** includes a first graduated rectangular coil **221B** and the second graduated rectangular coil **222B**. A longitudinal axis of the coils **221A** and **222A** extend in the "X" direction, and the longitudinal axis of the coils **221B** and **222B** extend in the "Y" direction, as shown. Thus, the coils **221A** and **222A** have a longitudinal axis that extends perpendicular to the longitudinal axis of the coils **221B** and **222B**.

The first graduated rectangular coil **221A** includes a number of windings. In the example shown, the windings are graduated in length along the "X" direction, with the outer winding extending a distance "D1," the next inner winding extending the distance "D2," the next inner winding extending the distance "D3," and the next inner winding extending the distance "D4." The distance "D1," is larger than the distance "D2," the distance "D2" is larger than the distance "D3," and the distance "D3" is larger than the distance "D4." The second graduated rectangular coil **222A** includes a similar arrangement of graduated-length windings. The second pair of graduated rectangular coils **220B** is similar to the first pair of graduated rectangular coils **220A**. Thus, the first pair of graduated rectangular coils **220A** can provide a relatively large area for inductive coupling over the direction "X," and the second pair of graduated rectangular coils **220B** can provide a relatively large area for inductive coupling over the direction "Y."

The third coil **230** includes a number of concentric, graduated windings, as shown in FIG. **7B**. The third coil **230** includes only one coil, rather than a pair of coils, as with the coils **220A** and **220B**. The third coil **230** is also square in shape in the example shown in FIG. **7B**, rather than the rectangular shape of the coils **220A** and **220B**. The third coil **230** can thus be relied upon to provide field directivity in a third "Z" (i.e., out of the page) direction.

In various embodiments, the coils **220A**, **220B**, and **230** can include any suitable number of concentric, graduated windings or turns of windings. Although each of the coils **220A**, **220B**, and **230** is shown to include four winding turns, any suitable number of turns can be relied upon. Additionally, the overall dimensions of the coils **220A**, **220B**, and **230** can vary as compared to that shown. The coils **220A**, **220B**, and **230** can be larger or smaller than those shown in FIGS. **7A** and **7B**.

PCB fabrication technology can be relied upon to implement the planar coil arrangement **240**, among others described herein, in a low-cost manner. The coils **220A** (for "X" field directivity), **220B** (for "Y" field directivity), and **230** (for "Z" field directivity) can be printed in different layers of the PCB. For an example four-layer PCB implementation, the coils **220A** can be implemented in layer 1, the coil **230** can be implemented in layer 2, interconnects can be implemented in layer 3, and the coils **220B** can be implemented in layer 4. The distance between layer 1 and layer 2 can be only 0.3 mm, although larger or smaller dimensions can be relied upon.

The small integration can increase the parasitic capacitance between the coils **220A**, **220B**, and **230**. There are two main types parasitic capacitance, including inter-coil capacitance between two different coils and equivalent parallel capacitance (EPC) of single coil. In one example, the EPC of the coil **230** is about 72 pF. Since the self-inductance of

11

the coil **230** is about 3 uH, the self-resonance frequency of coil **230** is about 10.8 MHz. To follow the AirFuel™ wireless charging standard, the operating frequency of the power transfer system **10** can be selected as 6.78 MHz. Therefore, the EPC is so large that the self-resonance will happen near the operating frequency, which means large electric field and extra dielectric loss. In addition, the large inter-coil capacitance leads to unnecessary circulation energy flowing among different transmitter coils and the circulating energy also results in extra loss. Considering this, it can be helpful to reduce the parasitic capacitances between the coils **220A**, **220B**, and **230**.

FIG. **8A** illustrates an example planar coil arrangement **250** according to various aspects of the embodiments described herein. The platform **60** can incorporate or include the planar coil arrangement **250**. The planar coil arrangement **240** includes the first pair of graduated coils **220A** to provide field directivity in a first “X” direction, the second pair of graduated coils **220B** to provide field directivity in a second “Y” direction, and a third coil **260** to provide field directivity in a third “Z” (i.e., out of the page) direction. The coils **220A**, **220B**, and **260** are centered and can overlap each other in some lengths of windings, although the coils **220A**, **220B**, and **260** are electrically isolated or separated from each other. FIG. **8B** illustrates the first pair of graduated coils **220A**, the second pair of graduated coils **220B**, and the third coil **260** shown in FIG. **8A**, separated from each other.

The planar coil arrangement **250** and the coils **220A**, **220B**, and **260** are illustrated in a representative fashion in FIGS. **8A** and **8B**, as examples for the purpose of discussion. The coils **220A**, **220B**, and **260** are not illustrated as continuous wires or traces, but instead using concentric shapes for ease of illustration. In practice, each of the coils **220A**, **220B**, and **260** can be formed using one or more conductive wires or traces. The coils **220A**, **220B**, and **260** can be formed in one or more layers of PCBs, as windings secured to a suitable substrate, or using other suitable approaches. The coils **220A**, **220B**, and **260** are designed to be planar in nature, such that the planar coil arrangement **250** can be formed in a relatively planar shape or form itself. Thus, the planar coil arrangement **250** can be easily integrated into many different types of structures, such as in desks, tables, and other furniture, in countertops, in automobiles, and in other structures. Currents can be supplied, respectively, to the coils **220A**, **220B**, and **260** of the planar coil arrangement **250** by the power transmission controller **50** (FIG. **3**), to provide omnidirectional wireless power transfer, as described in further detail below with reference to FIG. **9**.

The coil **260** includes a number of concentric, graduated windings, as shown in FIG. **8B**. The coil **260** includes only one coil, rather than a pair of coils, as with the coils **220A** and **220B**. The third coil **230** is also round in shape in the example shown in FIG. **8B**, rather than the rectangular shape of the coils **220A** and **220B**. The coil **260** can thus be relied upon to provide field directivity in a third “Z” (i.e., out of the page) direction.

The coil **260** in FIG. **8B** can provide certain advantages for some applications as compared to the coil **230** shown in FIG. **7B**. When arranged in the planar coil arrangement **250** with the coils **220A** and **220B**, the coil **260** does not include as many lengths of windings that extend parallel to lengths of windings of the coils **220A** and **220B**. Thus, the coil **260** is designed to reduce parasitic capacitance among the windings in the planar coil arrangement **250** shown in FIG. **8A** as compared to the planar coil arrangement **240** shown in FIG. **7A**. The circular shape of the coil **260** reduces the overlap or parallel extension with the coils **220A** and **220B**. Based on

12

the circular design of the coil **260**, the parasitic capacitances between the coil **260** and the coils **220A** and **220B** can be reduced by more than 50% in some cases as compared to the parasitic capacitances between the coil **230** and the coils **220A** and **220B**. The self-resonance frequency of the coil **260** can thus be modified, for example, to 20 MHz with the modified design, which is further away from the example operating frequency 6.78 MHz. In other design aspects, the spacings (e.g., laminate layer thickness) between different layers in the PCB board supporting the coils **220A**, **220B**, and **260** can also be increased, and the widths of each winding turn can be decreased to further reduce parasitic capacitances if necessary.

The planar coil arrangements **240** and **250** shown in FIGS. **7A** and **8A** facilitate the generation of magnetic fields in different directions over time. The power transfer controller **50** can activate one or more of the coils **220A**, **220B**, **230**, and **260** in the planar coil arrangements **240** and **250**, over time in various ways, to generate a composite magnetic field having a certain direction and magnitude. The direction and magnitude of the magnetic field will depend, at least in part, upon which of the coils **220A**, **220B**, **230**, and **260** are excited, and the magnitude and phase of the exciting current (s) provided to the coils **220A**, **220B**, **230**, and **260**, respectively, as determined by the power transfer controller **50**. Thus, the power transfer controller **50** can activate or excite one or more of the coils **220A**, **220B**, **230**, and **260** at a particular, potentially modulated, magnitude and/or phase, depending upon where the devices **70** and **71**, among others, are positioned over the power transfer platform **60** (FIG. **3**). The generation of magnetic field at a particular, adjustable direction and magnitude is advantageous because the orientation of the coils in the electronic devices **30-33** can vary depending upon how the electronic devices **30-33** settle into the receptacle **20** as described above.

FIG. **8C** illustrates the practical application of the planar coil arrangement shown in FIG. **8A**, identified as the planar coil arrangement **270**. The platform **60** can incorporate or include the planar coil arrangement **270**. The planar coil arrangement **270** includes a first pair of graduated coils **271A**, **271B** to provide field directivity in a first “X” direction, a second pair of graduated coils **272A**, **272B** to provide field directivity in a second “Y” direction, and a third coil **273** to provide field directivity in a third “Z” (i.e., out of the page) direction. The coils **271A**, **271B**, **272A**, **272B**, and **273** are centered and can overlap each other in some lengths of windings, although the coils are electrically isolated or separated from each other. As compared to the planar coil arrangement **250** shown in FIG. **8A** (which is representative), the planar coil arrangement **270** shows an example of how a single, continuous winding or trace can be used to form graduated coils.

FIG. **8D** illustrates another planar coil arrangement **280** according to various aspects of the embodiments described herein. The platform **60** can incorporate or include the planar coil arrangement **280**. The planar coil arrangement **280** includes a first pair of graduated coils **281A**, **281B** to provide field directivity in a first “X” direction, a second pair of graduated coils **282A**, **282B** to provide field directivity in a second “Y” direction, and a third coil **283** to provide field directivity in a third “Z” (i.e., out of the page) direction. The coils **281A**, **281B**, **282A**, **282B**, and **283** are centered and can overlap each other in some lengths of windings, although the coils are electrically isolated or separated from each other. As compared to the planar coil arrangement **250** shown in FIG. **8A** (which is representative), the coils **281A**, **281B** are graduated oval coils rather than graduated rectan-

13

gular coils. Similarly, the coils **282A**, **282B** are graduated oval coils rather than graduated rectangular coils. The planar coil arrangement **280** is one example to reduce parasitic capacitance between windings according to the concepts described herein.

FIG. **8E** illustrates another planar coil arrangement **290** according to various aspects of the embodiments described herein. The platform **60** can incorporate or include the planar coil arrangement **290**. The planar coil arrangement **290** includes a first pair of graduated coils **291A**, **291B** to provide field directivity in a first “X” direction, a second pair of graduated coils **292A**, **292B** to provide field directivity in a second “Y” direction, and a third coil **293** to provide field directivity in a third “Z” (i.e., out of the page) direction. The coils **291A**, **291B**, **292A**, **292B**, and **293** are centered and can overlap each other in some lengths of windings, although the coils are electrically isolated or separated from each other. As compared to the planar coil arrangement **250** shown in FIG. **8A** (which is representative), the coils **291A**, **291B** are graduated oval coils rather than graduated rectangular coils. Similarly, the coils **292A**, **292B** are graduated oval coils rather than graduated rectangular coils. Additionally, the coil **293** is a graduated square coil rather than a graduated circular coil. The planar coil arrangement **290** is one example to reduce parasitic capacitance between windings according to the concepts described herein.

FIG. **9** illustrates other components of the example omnidirectional wireless power transfer system **10** shown in FIG. **3** according to various aspects of the embodiments described herein. Among other components, the power transfer controller **50** includes the power converter **100**, resonant power converter **110**, controller **120**, and resonant cells **130-134**. FIG. **9** also illustrates a power supply **150** for the power transfer controller **50**. As described herein, the power transfer controller **50** can transfer power to the device **70**, which includes the coil **40** and a power converter **160**. The resonant cells **130-134** are electrically coupled in a closed circuit with the coils **221A**, **222A**, **221B**, **222B**, and **260**, respectively, and the coils **221A**, **222A**, **221B**, **222B**, and **260** can be considered circuit elements in the resonant cells **130-134**.

The power supply **150** can be embodied as any suitable supply of power for the power transfer controller **50**. In that context, the supply of power can be provided from line or bulk power, one or more batteries or other charge stores, or other power supplies. In various cases, the supply of power can be provided in the form of alternating or direct current at suitable level of potential.

The power converter **100** is configured to convert the power provided by the power supply **150** to power suitable for the resonant power converter **110**. In that context, the power converter **100** can be embodied as any suitable topology of power converter, such as a switch mode converter including a buck or boost arrangement of switching power transistors, for example. In one case, the power converter **100** can be embodied as a buck converter to step down power provided by the power supply **150** at a first, higher DC voltage to power for the resonant power converter **110** at a second, lower DC voltage. In some cases, the controller **120** can provide one or more modulated control signals to the power converter **100** to control the duty cycle of its switching power devices and, thus, the supply of power to the resonant power converter **110**, although the power converter **100** can operate in other cases without any external control. In some cases, the function of power converter **100** can also be achieved by controlling the duty cycle of the resonant power converter **110**, and the power converter **100** can be eliminated.

14

As discussed in further detail below with reference to FIG. **10**, the resonant power converter **110** forms, in part, a number of resonant circuits along with the resonant cells **130-134**, the coils **221A**, **222A**, **221B**, **222B**, and **260**, the coil **40** of the device **70**, and the power converter **160** of the device **70**. The resonant power converter **110** can include a number of switching transistors in one or more switch banks. In that context, the resonant power converter **110** is configured to feed charge from the power converter **100** to a transmitter-side resonant tank in each of the resonant cells **130-134**. Various examples of transmitter-side resonant tank circuits that can be used for the resonant cells **130-134** are described below. From the resonant cells **130-134**, power is inductively coupled through one or more of the coils **221A**, **222A**, **221B**, **222B**, and **260**, to the coil **40** of the device **70**, and to a receiver-side resonant tank in the power converter **160** of the device **70**. Examples of receiver-side resonant tank circuits for the power converter **160** are also described below. According to one aspect of the embodiments, the transmitter-side and receiver-side resonant tank circuits can be designed for coupling independent resonance with ZVS operation, although ZVS operation is not a requirement.

As noted above, the resonant power converter **110** includes circuitry to supply RF power (e.g., high frequency sinusoidal alternating current) to drive the resonant tank circuits in the resonant cells **130-134**. In one case, the resonant power converter **110** includes a switch bank of one or more switching transistors for each of the resonant cells **130-134**, and the resonant power converter **110** can supply RF power separately to each of the resonant cells **130-134**. In that case, the resonant power converter **110** is representative of a number of different resonant power converters for each of the resonant cells **130-134**, and modulated RF power can be provided respectively to each of the resonant cells **130-134**. The RF power can be respectively modulated in amplitude and/or phase through transistor switching control, modulation circuitry, or other circuitry directed by one or more control signals provided from the controller **120**.

In another case, the resonant power converter **110** includes a switch bank for one or more pairs of the resonant cells **130-134**, such as for the X, Y, and Z coils. In that case, modulated RF power can be provided to the X1 and X2 resonant cells **130** and **131**, to the Y1 and Y2 resonant cells **132** and **133**, and to the Z resonant cell **134**. The RF power can be modulated respectively in amplitude and/or phase for the X, Y, and Z coils through transistor switching control, modulation circuitry, or other circuitry directed by one or more control signals provided from the controller **120**.

The wireless power transfer system **10** and the resonant cells **130-134** can operate at any suitable frequency for wireless power transfer. The AirFuel™ wireless power transfer standard uses an operating frequency of 6.78 MHz, as one example. The resonant cells **130-134** can operate at 6.78 MHz, but higher and lower frequencies can be relied upon. The Qi standard for wireless charging, as another example, uses a lower frequency of 140 kHz, and the resonant cells **130-134** can operate at 140 kHz. The wireless power transfer system **10** and the resonant cells **130-134** can operate at lower or higher operating frequencies in other cases. Lower frequencies can be relied upon in some cases to charge a larger number of devices over a larger surface area and distance. Thus, the resonant cells **130-134** can operate at any suitable frequency for wireless power transfer. The resonant cells **130-134** can also operate over a range of different operating frequencies over time, to better match mutual inductance and power transfer to various devices over time.

15

In other cases, the resonant power converter **110** can generate RF power for the resonant cells **130-134**, collectively, and include a one or more amplitude and/or phase modulation circuits to generate a number of amplitude and/or phase modulated versions of the RF power for the resonant cells **130-134**. In any case, the resonant power converter **110** includes circuitry to supply power that drives the resonant tank circuits in the resonant cells **130-134** for near-field resonant inductive coupling of power to the coil **40** of the device **70**, among coils of other devices.

The controller **120** can be embodied as one or more processors and related circuitry to support the processors, such as one or more memory devices, crystal oscillators, linear regulators, analog-to-digital converters, digital-to-analog converters, local interfaces, etc. The local interface can include, for example, a data bus with an accompanying address/control bus between memory devices and processors. The processor can include a general- or specific-purpose processor, such as a microprocessor, microcontroller, digital signal processor, or other processing circuitry. The controller **120** can also be embodied, at least in part, as one or more discrete logic circuits, application specific integrated circuits (ASICs), programmable logic devices (e.g., field-programmable gate array (FPGAs), and complex programmable logic devices (CPLDs)).

In some cases, one or more processors of the controller **120** can execute computer-readable software or program instructions embodied in a non-transitory computer-readable medium (e.g., memory device). Through execution of the instructions, the controller **120** can be directed to perform one or more of the operations described herein. In other cases, the controller **120** can be designed to conduct or perform the operations described herein without the execution of software.

The controller **120** is configured to control the overall operation of the power transfer controller **50** and the transmission of power to devices. For example, the controller **120** is configured to control the resonant power converter **110** to activate (e.g., provide RF power to) one or more of the resonant cells **130-134**. In that way, the controller **120** can direct and control the wireless transmission of power to the device **70**. For example, the controller **120** can generate one or more control signals to direct the resonant power converter **110** to generate RF power to induce resonant, inductive power transfer between magnetic-field-coupled coils in the resonant cell **130** and the coil **40** of the device **70**. Similarly, the controller **120** can direct the resonant power converter **110** to induce power transfer between magnetic-field-coupled coils in any combination of one or more of the resonant cells **130-134** and the coil **40** of the device **70**.

Further, the controller **120** can direct the resonant power converter **110** to generate RF power at a certain frequency, amplitude, and/or phase for the resonant cell **130** and the other resonant cells **131-134**, respectively. Thus, the controller **120** can control whether RF power is provided, as well as the frequency, amplitude, and phase of that RF power, to each of the resonant cells **130-134** individually. The manner in which the resonant cells **130-134** can be excited in the power transfer controller **50** is thus flexible, as various combinations of the coils **221A**, **222A**, **221B**, **222B**, and **260** can be selectively excited in various ways through the resonant cells **130-134** to induce a preferred magnitude and direction of the magnetic field over or around the platform **60**. In effect, the magnitude and direction of the magnetic field can be adjusted to account for different positions and orientations the coil **40** of the device **70** and similar coils of other devices over the platform **60**.

16

For example, if the device **70** is placed over and rests flat on the platform **60** near a center of the coil **260**, then the controller **120** can direct the resonant power converter **110** to generate RF power for the resonant cell **134** and the coil **260**. Because of the position and orientation of the coil **40** of the device **70** with respect to the coil **260** in that case, the excitation of the coil **260** is likely to lead to a relatively high power transfer through resonant inductive coupling, at least as compared to an excitation of the other coils **221A**, **222A**, **221B**, **222B**.

When the device **70** is first placed over the platform **60**, however, the power transfer controller **50** may not know the position and orientation at which the device **70** was placed or settled. Thus, the controller **120** is configured to sense a level of power transferred (or that can be transferred) to the device **70** by exciting each of the resonant cells **130-134** (and, hence, the coils **221A**, **222A**, **221B**, **222B**, and **260**) individually over time. For example, the controller **120** can direct the resonant power converter **110** to provide RF power to each of the resonant cells **130-134**, individually, and to measure the amount of power transferred to the device **70** by each one. The power transfer can be measured or sensed using any suitable techniques, such as through the identification of voltage drops or droops, the amount of current supplied, or other approaches. In that way, the controller **120** can identify a coefficient of power transfer or resonant inductive coupling between individual ones of the resonant cells **130-134** (and the coils **221A**, **222A**, **221B**, **222B**, and **260**) and the coil **40** of the device **70**, respectively.

The controller **120** can also sense a level of power transferred to the device **70** by the excitation of one or more combinations of the resonant cells **130-134** over time. In that case, the controller **120** can direct the resonant power converter **110** to provide RF power to various combinations of the resonant cells **130-134** over time and measure the amount of power transferred for each combination. Additionally, the RF power provided to respective ones of the resonant cells **130-134** can be modulated in amplitude and/or phase as compared to each other, and the controller **120** can measure the amount of power transferred for various combinations of that modulated power.

Various combinations of the coils **221A**, **222A**, **221B**, **222B**, and **260** can be excited over time to induce rotating and, as averaged over time, omnidirectional magnetic fields. Thus, rotating magnetic fields in different planes can be induced over the platform **60**. Also, by exciting one or more of the coils **221A**, **222A**, **221B**, **222B**, and **260**, respectively, for different periods of time, using different amplitudes, and/or different phases of high frequency sinusoidal alternating current, omnidirectional magnetic fields can be induced over the platform **60** in an average sense.

Additionally, the coils **221A**, **222A**, **221B**, **222B**, and **260** can be excited simultaneously to induce a three-dimensional rotating magnetic field over the platform **60**. One example of the excitation currents that can be provided to the coils **221A**, **222A**, **221B**, **222B**, and **260** is similar to that shown in FIG. 2B. For that example case, the magnetic field distribution provided over the platform **60** at different time instants was simulated with finite element analysis (FEA) software. The magnetic field distribution was shown to shift over time between upward, downward, right, and left directions, among others.

Thus, the controller **120** can achieve an omnidirectional magnetic field over the platform **60** through controlled excitation of the resonant cells **130-134** and the coils **221A**, **222A**, **221B**, **222B**, and **260**. The excitation examples described herein are not exhaustive, however, and other

17

ways are within the scope of the embodiments. With so many flexible ways of excitation, the proposed arrangement of the coils **221A**, **222A**, **221B**, **222B**, and **260** in the platform **60** can achieve omnidirectional wireless power transfer. Overall, the magnetic field distribution above the platform **60** can vary omnidirectionally over time, and an omnidirectional field distribution is induced in the region above the platform **60**. Therefore, there is no need to align the receiver coil **40** of the device **70** in any particular orientation with respect to the platform **60**. The power transfer controller **50** can transfer energy to the device **70**, among others, in any direction, and the freedom of charging orientation is greatly improved.

Turing to other aspects of the embodiments, one challenge in the design of resonant converters is to design for ZVS operation of the switching devices. A recommended switching frequency of the AirFuel™ wireless power transfer standard is 6.78 MHz. The use of such high switching frequencies can be detrimental to switching devices unless resonant converters are designed for ZVS operation. Without ZVS operation, switching losses can be relatively high and efficiency suffers. Additionally, electromagnetic compatibility of the system can also be a concern for designs that fail to account for ZVS operation.

FIG. **10** illustrates example resonant tank topologies according to various aspects of the embodiments described herein. Particularly, FIG. **10** illustrates a series-series resonant tank at pane (a), a parallel-series resonant tank at pane (b), a series-parallel resonant tank at pane (c), and a parallel-parallel resonant tank at pane (d). Among the four resonant tank topologies shown in FIG. **10**, the series-series resonant converter is widely used. The wireless power transfer system **10** and the planar coil arrangements described above can be used with any suitable resonant circuit technology, at any suitable operating frequency. FIG. **10**, and the other figures described below, illustrate example resonant circuit topologies, but the embodiments are not limited to use with the examples provided.

In the example resonant tank topologies shown in FIG. **10**, k is a coupling metric related to the level of inductive coupling between the transmitter coil and the receiver coil. In practice, the value of k may be based on the position and orientation of the receiver coils in the receiver-side resonant tanks as compared to the transmitter coils of the transmitter-side resonant tanks. In other words, as discussed above, in a wireless power transfer system where a user is expected to set or place an electronic device including a receiver coil into a charging receptacle, the position and orientation of the receiver coil (with respect to the transmitter coil) is dependent on the user's placement of the device and will vary. Thus, the value of k can vary dependent on the user's placement of the device into the charging receptacle.

FIG. **11** illustrates an example resonant converter **300** incorporating series-series resonant tank topology according to various aspects of the embodiments described herein. At the transmitter side of the resonant converter **300**, a power source **310** supplies charge to a switch bank **320**, which is configured to feed charge to a transmitter-side resonant tank **330**. The resonant converter **300** also includes a receiver-side resonant tank **340**, a rectifier bank **350**, a bulk charge store **360**, and a load **370**. The resonant converter **300** is representative and provided for context to describe certain features and advantages of the embodiments. Other circuit elements (and variations of the circuit elements shown) can be relied upon in various embodiments.

In FIG. **11**, the power source **310** is representative of any suitable supply of power for the resonant converter **300**. The

18

switch bank **320** includes an arrangement of switching transistors. Although designs using a single transistor are possible, half bridge and full bridge arrangements of transistors can be used to drive the transmitter-side resonant tank **330** more efficiently, and a half bridge is shown for the switch bank **320** in FIG. **11**. The transmitter-side resonant tank **330** and the receiver-side resonant tank **340** include combinations of capacitive and inductive circuit elements that form a series-series resonant tank topology. The transmitter-side resonant tank **330** in FIG. **11** includes a resonant capacitor C_{tx} and transmitter coil L_{tx} , and the receiver-side resonant tank **340** includes the resonant capacitor C_{rx} and receiver coil L_{rx} . The resonant capacitor C_{tx} , transmitter coil L_{tx} , resonant capacitor C_{rx} , and receiver coil L_{rx} can be selected for use with a resonant operating frequency for near-field resonant inductive coupling.

Other combinations of capacitive and inductive circuit elements for other converter topologies, including those shown in the other figures, can be used. The rectifier bank **350** includes an arrangement of diodes to rectify the flow of power which is inductively coupled from the transmitter-side resonant tank **330** to the receiver-side resonant tank **340** for storage into the bulk charge store **360**. Any suitable arrangement of diodes (e.g., half bridge, full bridge, etc.) can be used in the rectifier bank **350**.

Here, it is noted that the power source **310** is representative of a supply of power, such as the supply of power provided by the power converter **100** shown in FIG. **9**. Further, the resonant power converter **110** shown in FIG. **9** can include a switch bank similar to the switch bank **320** for each of the resonant cells **130-133**, and the switching transistors can be controlled by control signals provided by the controller **120**. Each of the resonant cells **130-133** shown in FIG. **9** can include a transmitter-side resonant tank similar to the transmitter-side resonant tank **330**. Similarly, each of the coils **221A**, **222A**, **221B**, **222B**, and **260** shown in FIG. **9** can include a transmitter coil similar to the transmitter coil L_{tx} . The power converter **160** for the device **70** shown in FIG. **9** can include a receiver-side resonant tank similar to the receiver-side resonant tank **340**, and the coil **40** of the device **70** can include a receiver coil similar to the receiver coil L_{rx} .

FIG. **12** illustrates an example AC equivalent circuit of the series-series resonant converter shown in FIG. **11** with a T model of the transformer. Based on the equivalent circuit, voltage gain and phase of input impedance curves are shown for different load resistances and resonant couplings in FIGS. **13** and **14**. The $k=0.4$ case of coupling is shown in FIG. **13**, and the $k=0.2$ case of coupling is shown in FIG. **14**.

According to the voltage gain curves in FIGS. **13** and **14**, there are three resonant frequencies in the series-series resonant converter topology, including two series resonant frequencies f_{s1} , f_{s2} and one parallel resonant frequency f_p . The expressions for these three resonant frequency are:

$$f_{s1} = \frac{1}{2\pi\sqrt{(1+k)L_{tx}C_{tx}}}, \quad (7)$$

$$f_{s2} = \frac{1}{2\pi\sqrt{(1-k)L_{tx}C_{tx}}}, \text{ and} \quad (8)$$

$$f_p = \frac{1}{2\pi\sqrt{L_{tx}C_{tx}}}. \quad (9)$$

According to the expressions, the two series resonant frequencies (SRFs) are coupling dependent and the parallel

resonant frequency (PRF) is coupling independent. Therefore, the SRFs move and the PRF is fixed when the resonant coupling of the series-series resonant converter changes as shown in FIGS. 13 and 14. Further, for different load conditions, the voltage gain can change dramatically for the PRF. This variable voltage gain can be a challenge for system controllability in voltage output applications. For example, as discussed above, the load presented by electronic devices can vary as the load presented by a battery varies based on the different charging stages in the charging profile of the battery. However, the SRFs exhibit load-independent voltage gain, which is desirable from controllability point of view.

Compatible inductive input impedance is important for ZVS operation of switching devices in half bridges and related switching topologies. The phase of input impedance with different loads is also shown in FIGS. 13 and 14. As shown, the input impedance is resistive at the PRF, which is at the boundary between the ZVS and zero current switching (ZCS) regions. Therefore, ZVS operation can be lost around the PRF due to component tolerances. For the first SRF at f_{s1} , the input impedance is capacitive in most load ranges. Thus, ZVS operation is not available. On the contrary, ZVS operation can be achieved in most load SRF ranges at f_{s2} .

In summary, the resonant frequency characteristics of series-series resonant converters is that, for SRF f_{s1} : moving SRF with variable coupling, and no ZVS operation in most load ranges. For SRF f_{s2} : moving SRF with variable coupling, ZVS operation in most load ranges. For PRF f_p : variable voltage gain with different loads, ZVS operation cannot be guaranteed.

Thus, there is no good operating region with variable coupling and load in series-series resonant converters. At the same time, parallel-series and parallel-parallel resonant converters are most suitable for current source input applications. In real applications, current source input applications are relatively difficult to implement, and those two topologies are not considered here. The series-parallel resonant converter has one moving SRF with variable coupling, which is similar to the series-series resonant converter. Thus, the four basic resonant topologies shown in FIG. 10 are not ideal to solve the challenges of varying coupling and load conditions in wireless power transfer applications.

As described above, the gain characteristics of series-series resonant converters include two coupling dependent SRFs with load independent voltage gains and one coupling independent PRF with load dependent voltage gain, and the PRF is in the center of the SRFs. Therefore, the center resonance is coupling independent. Similarly, gain characteristics with one SRF in the center of two PRFs can achieve coupling and load independent resonance. One example of gain characteristics with one SRF in the center of two PRFs is shown in FIG. 15. With the type of gain characteristics shown in FIG. 15, coupling and load independent resonance can be achieved for near-field wireless power transfer at the center SRF. At the same time, at the left SRF, ZVS can be achieved due to the negative slope of the gain curve. Therefore, a resonant converter with this type of gain characteristics can be used to achieve coupling and load independent resonance with ZVS operation for near-field wireless power transfer.

FIG. 16A illustrates the general topology form of a resonant converter with coupling independent resonance and zero voltage switching. The resonant converter shown in FIG. 16A includes a parallel resonant cell 400, a ZVS branch 410, and a series resonant cell 420. The parallel resonant cell 400 can be implemented in many ways. FIG. 16B illustrates

example parallel resonant cells 300 implemented with two or three passive components. As shown in FIG. 16, one simple form of the ZVS branch 410 can be a capacitor, which can change the input impedance to inductive to make sure zero voltage switching occurs. However, other, more complicated forms of the ZVS branch 410 with more components can also be used to change the input impedance. The series resonant cell 420 can use the self-inductance of the receiver coil as part of resonant cell. Therefore, there is always an inductor in the left side of series resonant cell. FIG. 16C illustrates example series resonant cells 420 implemented with two or three passive components.

One example resonant converter topology, called a CLCL-LC resonant converter, is shown in FIG. 17. To find how the series resonance is formed in the CLCL-LC resonant converter, the use of Norton's Theorem and Thevenin's Theorem is shown in FIG. 18 to transform the relatively complicated resonant tank network into a simple branch in series with a load resistor. Since the input source has no relationship with the resonant frequency of the resonant network, a simple branch with L_{rk} reflected into the primary (transmitter) side, as shown in FIG. 18, has the same SRF as the CLCL-LC resonant converter.

According to FIG. 19, if L_r and C_r are in resonance, power will go through L_m , L_{rk} , and C_{rx} due to the high impedance of the parallel resonance. Further, L_m and L_{rk} in series can be equivalent to the self-inductance of the receiver coil, which is coupling independent. If C_{rx} is designed to resonate with L_{rx} at the resonance frequency of L_r and C_r , then the CLCL-LC resonant converter will have a coupling independent series resonant frequency given by:

$$f_s = \frac{1}{2\pi\sqrt{L_r C_r}} = \frac{1}{2\pi\sqrt{L_{rx} C_{rx}}}. \quad (10)$$

As for the parallel frequency of the CLCL-LC resonant converter, L_m will join the resonance like LLC. The parallel resonance is formed by L_r and C_r in parallel, and will resonate with C_{tx} , L_{tk} , L_m in series. The expression for this calculation is given by:

$$\frac{j\omega L_r \cdot \frac{1}{j\omega C_r}}{j\omega L_r + \frac{1}{j\omega C_r}} + j\omega L_{tk} + j\omega L_m + \frac{1}{j\omega C_{tx}} = 0. \quad (11)$$

There are two solutions of expression (11), which means two PRFs exist in CLCL-LC resonant converter. The solutions of expression (11) are relatively complicated and, thus, not shown here. From the result of the solutions, however, one PRF is present on the left side of the SRF and another PRF is present on the right side of the SRF. Intuitively, in low frequency ranges, the series branch (L_{tk} , L_m , C_{tx}) is capacitive, which can be equivalent to a capacitor C_{eq} . Therefore, the parallel frequency

$$f_{p1} = \frac{1}{2\pi\sqrt{L_r(C_r + C_{eq})}}$$

is in the left side of f_s . In high frequency ranges, the series branch (L_{tk} , L_m , C_{tx}) is inductive, which can be equivalent to an inductor L_{eq} . So the parallel frequency

21

$$f_{p2} = \frac{1}{2\pi\sqrt{(L_r/L_{eq})C_r}}$$

is in the right side of f_s .

The voltage gain and phase of input impedance curves of the CLCL-LC resonant converter shown in FIG. 17 with different loads and for different couplings are shown in FIGS. 20 and 21. The $k=0.4$ case of coupling is shown in FIG. 20, and the $k=0.2$ case of coupling is shown in FIG. 21.

As demonstrated by FIGS. 20 and 21, a coupling independent SRF with ZVS operation is achieved with the CLCL-LC resonant converter topology. The entire shaded region can be selected as the operation region. From the gain curve, there are two PRFs around the fixed SRF, with one PRF on the left side and the other PRF on the right side of the SRF. With this type of gain characteristics, fixed SRF with ZVS operation can be achieved, which is an important concept in the design of coupling independent resonance frequency in variable coupling applications.

In extension to the CLCL-LC resonant converter topology shown in FIG. 17, other topologies of resonant converters with coupling independent resonance and ZVS operation can be found. Some example resonant converter topologies and gain curve characteristics of that type are shown in FIGS. 22-26. FIG. 22 is the CLCL-LC resonant converter topology (similar to that shown in FIG. 17), which is used as a reference for the other topologies.

The other resonant converter topologies shown in FIGS. 23-26 have the same order as the CLCL-LC resonant converter topology in FIG. 22. FIG. 23 is a LCCL-LC resonant converter topology, FIG. 24 is a LC-LCCL resonant converter topology. Further, with the addition of more passive components, there are other resonant converter topologies with coupling independent resonance and ZVS operation. One such resonant converter topology having higher order than the CLCL-LC resonant converter topology is shown in FIG. 25. FIG. 26 is a LCCL-LCL resonant converter topology. In all these resonant converter topologies, a fixed SRF is created in the center of two PRFs in gain characteristics. With this type of gain characteristics, coupling independent operation region with ZVS operation can be obtained.

The above-described examples of the present disclosure are merely possible examples of implementations set forth for a clear understanding of the principles of the disclosure. Many variations and modifications can be made without departing substantially from the spirit and principles of the disclosure. All such modifications and variations are intended to be included herein within the scope of this disclosure and protected by the following claims.

Therefore, the following is claimed:

1. A planar omnidirectional wireless power transfer system, comprising:

a plurality of resonant tank circuits electrically coupled to a power generator;

a planar coil arrangement for omnidirectional wireless power transfer, the planar coil arrangement comprising a plurality of individual planar coils arranged for omnidirectional wireless power transfer to a device placed over the planar coil arrangement, each of the plurality of individual planar coils being electrically coupled to a corresponding one of the plurality of resonant tank circuits, the plurality of individual planar coils comprising:

22

a first pair of planar graduated coils comprising two individual planar coils arranged in a side-by-side arrangement to provide field directivity in a first direction, each planar graduated coil comprising an outer winding extending around inner concentric windings, the inner concentric windings of each planar graduated coil increasingly offset away from another of the first pair of planar graduated coils;

a second pair of planar graduated coils comprising two individual planar coils arranged in a side-by-side arrangement to provide field directivity in a second direction, each planar graduated coil comprising an outer winding extending around inner concentric windings, the inner concentric windings of each planar graduated coil increasingly offset away from another of the second pair of planar graduated coils; and

a third planar coil arranged to provide field directivity in a third direction; and

a controller configured to wirelessly transmit power through one or more of the plurality of individual planar coils by individually activating the corresponding one of the resonant tank circuits with different voltage or current to provide omnidirectional power transfer to the device.

2. The system according to claim 1, wherein:

each of the two individual planar coils of the first pair of planar graduated coils is formed by a separate single conductive wire or trace and each of the two individual planar coils of the second pair of planar graduated coils is formed by a separate single conductive wire or trace.

3. The system according to claim 1, wherein:

separation between the outer winding and an adjacent inner concentric winding of each of the first pair of planar graduated coils is larger on a side adjacent to the other planar graduated coil of the first pair of planar graduated coils than on a side opposite the other planar graduated coil; and

separation between the outer winding and an adjacent inner concentric winding of each of the second pair of planar graduated coils is larger on a side adjacent to the other planar graduated coil of the second pair of planar graduated coils than on a side opposite the other planar graduated coil.

4. The system according to claim 1, wherein the third planar coil comprises a third circular coil, which is different in shape than at least one of the first pair of planar graduated coils or the second pair of planar graduated coils, to reduce parasitic capacitance in the planar coil arrangement.

5. The system according to claim 1, wherein:

the first pair of planar graduated coils comprises a first pair of two individual rectangular coils in a side-by-side arrangement; and

the second pair of planar graduated coils comprises a second pair of two individual rectangular coils in a side-by-side arrangement.

6. The system according to claim 5, wherein a longitudinal axis of the first pair of two individual rectangular coils is perpendicular to a longitudinal axis of the second pair of two individual rectangular coils.

7. The system according to claim 1, wherein:

the first pair of planar graduated coils comprises a first pair of two individual oval coils in a side-by-side arrangement; and

the second pair of planar graduated coils comprises a second pair of two individual oval coils in a side-by-side arrangement.

23

8. The system according to claim 1, wherein the plurality of individual planar coils are arranged to provide a multi-directional magnetic field distribution.

9. The system according to claim 1, wherein the controller is further configured to activate individual ones of the resonant tank circuits with different voltage or current over time to generate an omnidirectional field distribution over the planar coil arrangement.

10. The system according to claim 1, wherein the controller is further configured to sense a level of power transferred to the device by individual ones of the plurality of resonant tank circuits and identify a coefficient of power transfer between individual ones of the plurality of resonant tank circuits and the device.

11. The system according to claim 1, wherein the controller is further configured to modulate a supply of power provided to individual ones of the plurality of resonant tank circuits in at least one of amplitude or phase to generate an omnidirectional field distribution for increased power transfer to the device.

12. The system according to claim 1, wherein the plurality of resonant tank circuits comprise at least one resonant converter topology for coupling independent resonance and zero voltage switching (ZVS).

13. The system according to claim 1, further comprising: the device, the device comprising a receiver-side resonant tank circuit for near-field resonant inductive coupling with one or more of the plurality of resonant tank circuits and one or more of the plurality of individual planar coils.

14. The system according to claim 13, wherein at least one of the plurality of resonant tank circuits and the receiver-side resonant tank circuit comprises a resonant converter topology for coupling independent resonance and zero voltage switching (ZVS).

15. A planar omnidirectional wireless power transfer system, comprising:

a planar coil arrangement for omnidirectional wireless power transfer, the planar coil arrangement comprising a plurality of individual planar coils arranged for omnidirectional wireless power transfer to a device placed over the planar coil arrangement, the plurality of individual planar coils comprising:

a first pair of planar graduated coils comprising two individual planar coils arranged in a side-by-side arrangement to provide field directivity in a first direction, each planar graduated coil comprising an outer winding extending around inner concentric windings, the inner concentric windings of each planar graduated coil increasingly offset away from another of the first pair of planar graduated coils; and

24

a second pair of planar graduated coils comprising two individual planar coils arranged in a side-by-side arrangement to provide field directivity in a second direction, each planar graduated coil comprising an outer winding extending around inner concentric windings, the inner concentric windings of each planar graduated coil increasingly offset away from another of the second pair of planar graduated coils; and

a controller configured to activate individual ones of the plurality of individual planar coils with different voltage or current to wirelessly transmit omnidirectional power to the device.

16. The system according to claim 15, wherein a third coil is arranged to provide field directivity in a third direction; the first direction is perpendicular to the second direction; and the third direction is orthogonal to the first direction and the second direction.

17. The system according to claim 16, wherein the third coil comprises a third circular coil.

18. The system according to claim 16, wherein: the first pair of planar graduated coils comprises a first pair of two individual rectangular coils in a side-by-side arrangement; and

the second pair of planar graduated coils comprises a second pair of two individual rectangular coils in a side-by-side arrangement.

19. The system according to claim 16, wherein: the first pair of planar graduated coils comprises a first pair of two individual oval coils in a side-by-side arrangement; and

the second pair of planar graduated coils comprises a second pair of two individual oval coils in a side-by-side arrangement.

20. The system according to claim 15, wherein: separation between the outer winding and an adjacent inner concentric winding of each of the first pair of planar graduated coils is larger on a side adjacent to the other planar graduated coil of the first pair of planar graduated coils than on a side opposite the other planar graduated coil; and

separation between the outer winding and an adjacent inner concentric winding of each of the second pair of planar graduated coils is larger on a side adjacent to the other planar graduated coil of the second pair of planar graduated coils than on a side opposite the other planar graduated coil.

* * * * *