

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12401135
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Kim; Dongyeon et al.

Electronic device including antenna

Abstract

According to an embodiment of the present disclosure, an electronic device may include: a housing; an antenna structure positioned in the housing and including a printed circuit board, multiple first antenna elements, multiple second antenna elements, and multiple electrical paths; and a wireless communication circuit electrically connected to the multiple first antenna elements through the electrical paths. The antenna structure may include antenna elements arranged for enhancing a communication performance and/or may be capable of securing the quality and the accuracy of the positioning for the signal source even though there are various directions or orientations where the electronic device faces, or various polarization characteristics of a signal transmitted from the signal source.

Inventors:	Kim; Dongyeon (Suwon-si, KR), Kim; Hosaeng (Suwon-si, KR)
Applicant:	SAMSUNG ELECTRONICS CO., LTD. (Suwon-si, KR)
Family ID:	1000008777728
Assignee:	Samsung Electronics Co., Ltd. (Suwon-si, KR)
Appl. No.:	17/846576
Filed:	June 22, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20240332819 A1	Oct. 03, 2024

Foreign Application Priority Data

KR	10-2021-0072081	Jun. 03, 2021
----	-----------------	---------------

Related U.S. Application Data

Publication Classification

Int. Cl.: H01Q1/24 (20060101); H01Q5/25 (20150101); H01Q9/04 (20060101); H01Q21/06 (20060101); H01Q21/24 (20060101)

U.S. Cl.:

CPC H01Q21/065 (20130101); H01Q5/25 (20150115); H01Q9/0428 (20130101); H01Q21/24 (20130101); H01Q1/243 (20130101)

Field of Classification Search

CPC: H01Q (1/243); H01Q (21/065); H01Q (5/25); H01Q (9/0414); H01Q (1/38); H01Q (9/0428); H01Q (21/24); H01Q (9/0407)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
4827271	12/1988	Berneking	343/846	H01Q 5/378
6154176	12/1999	Fathy et al.	N/A	N/A
7427957	12/2007	Zeinolabedin Rafi et al.	N/A	N/A
8717245	12/2013	Krivokapic et al.	N/A	N/A
10734726	12/2019	Fujimoto	N/A	N/A
2009/0058731	12/2008	Geary et al.	N/A	N/A
2010/0007561	12/2009	Bucca et al.	N/A	N/A
2020/0021011	12/2019	Cooper et al.	N/A	N/A
2020/0021019	12/2019	Rajagopalan et al.	N/A	N/A
2023/0299487	12/2022	Hwang	343/702	H01Q 9/0407

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
112751189	12/2020	CN	N/A
2000114859	12/1999	JP	N/A
2001-177314	12/2000	JP	N/A
2019-515536	12/2018	JP	N/A
10-2461630	12/2021	KR	N/A

OTHER PUBLICATIONS

Search Report dated Sep. 6, 2022 issued in International Patent Application No. PCT/KR2022/007891. cited by applicant
Extended European Search Report dated Sep. 19, 2024 for EP Application No. 22816489.3. cited by applicant

Primary Examiner: Lopez Cruz; Dimary S

Assistant Examiner: Hamadyk; Anna N

Attorney, Agent or Firm: Nixon & Vanderhye P.C.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of International Application No. PCT/KR2022/007891 designating the United States, filed on Jun. 3, 2022, in the Korean Intellectual Property Receiving Office and claiming priority to Korean Patent Application No. 10-2021-0072081, filed on Jun. 3, 2021, in the Korean Intellectual Property Office, the disclosures of which are incorporated by reference herein in their entireties.

BACKGROUND

Field

(1) The disclosure relates to an electronic device including an antenna.

Description of Related Art

(2) An electronic device may support an ultra-wide band (UWB). The UWB may correspond to a technology following the international standard IEEE 802.15.4, and may perform communication with a bandwidth of a broadband. The UWB is optimized as a technology in which positioning using a bandwidth of a broadband is performed, rather than increasing a transmission rate or a communication rate using a broadband in the conventional communication.

(3) An antenna supporting a UWB, or an antenna for transmitting and/or receiving a signal in various other frequency bands, may be developed to enhance a communication performance. For example, an electronic device (e.g., an initiator, a receiver, or a receiver (Rx) device) may identify or estimate the location of a signal source (e.g., a responder, a transmitter, or a transmitter (Tx) device) using a phase difference of signals received in two antennas. The electronic device may identify a reception angle (e.g., a signal direction) of a signal for a configured axis of the electronic device, or a distance between the electronic device and a signal source, using a positioning method (e.g., angle of arrival (AOA)). As a response related to the positioning, a signal (e.g., a Tx signal) transmitted from the signal source may have various polarization characteristics according to an antenna type, an antenna location, or the direction (orientation) where the signal source faces. When the electronic device is implemented to receive single polarization, it may be difficult to secure the quality or the accuracy of the positioning to correspond to various polarization characteristic of a signal transmitted from the signal source. In addition, when the electronic device is implemented to receive single polarization, it may be difficult to secure the quality or the accuracy of the positioning for the signal source to correspond to the orientation or various directions (orientations) where the electronic device faces.

SUMMARY

(4) Embodiments of the disclosure may provide an electronic device including an antenna capable of enhancing a communication performance.

(5) Embodiments of the disclosure may provide an electronic device including an antenna capable of securing the quality and the accuracy of the positioning for the signal source even though there are various directions or orientations where the electronic device faces, or various polarization characteristics of a signal transmitted from the signal source.

(6) According to an example embodiment of the disclosure, an electronic device may include: a housing, an antenna structure including at least one antenna positioned in the housing and including a printed circuit board, multiple first antenna elements, multiple second antenna elements, and

multiple electrical paths, and a wireless communication circuit electrically connected to the multiple first antenna elements through the electrical paths, wherein the printed circuit board includes a first surface oriented in a first direction and a second surface oriented in a second direction opposite to the first direction, wherein the multiple first antenna elements are positioned in the printed circuit board on the first surface or to be closer to the first surface than the second surface, are configured to generate circular polarization, and include, when seen from above the first surface, a first border and a third border spaced apart from each other and extending in parallel to each other, a second border and a fourth border spaced apart from each other by a distance between the first border and the third border, extending in parallel to each other, and disposed to be perpendicular to the first border or the third border, and multiple first notches formed on the first border, the second border, the third border, and the fourth border and arranged at a 90-degree angle with reference to a center of each of the multiple first antenna elements, the multiple second antenna elements are positioned in the printed circuit board to be closer to the second surface than the multiple first antenna elements, overlap with, when seen from above the first surface, the multiple first antenna elements one-to-one, are configured to generate circular polarization, and include, when seen from above the first surface, a fifth border and a seventh border spaced apart from each other and extending in parallel to each other, a sixth border and an eighth border spaced apart from each other by a distance between the fifth border and the seventh border, and disposed to be perpendicular to the fifth border or the seventh border, and multiple second notches formed on the fifth border, the sixth border, the seventh border, and the eighth border, arranged at a 90-degree angle with reference to the center, and overlapping with at least some of the multiple first notches one-to-one, and the multiple electrical paths are positioned on the printed circuit board and include multiple conductive vias electrically connected to the multiple first antenna elements, wherein the printed circuit board includes: a first conductive layer including the multiple first antenna elements, a second conductive layer including the multiple second antenna elements, a first dielectric positioned between the first conductive layer and the second conductive layer, a third conductive layer configured to electrically connect the multiple conductive vias to the wireless communication circuit and positioned in the printed circuit board to be closer to the second surface than the second conductive layer, a fourth conductive layer including a ground plane and positioned in the printed circuit board to be closer to the second surface than the third conductive layer, and a second dielectric positioned between the third conductive layer and the fourth conductive layer and having a greater dielectric constant than the first dielectric, each of the multiple second antenna elements includes a hole, each of the multiple conductive vias is positioned to extend through the hole, the multiple second antenna elements are configured to be indirectly fed by the multiple conductive vias, and the multiple first notches have different shapes from the multiple second notches.

(7) According to an example embodiment of the disclosure, an antenna structure may include: a printed circuit board including a first surface oriented in a first direction and a second surface oriented in a second direction opposite to the first direction, a first conductive layer positioned in the printed circuit board on the first surface or to be closer to the first surface than the second surface, and including multiple first antenna elements, configured to generate circular polarization, and including, when seen from above the first surface, a first border and a third border spaced apart from each other and extending in parallel to each other, a second border and a fourth border spaced apart from each other by a distance between the first border and the third border, extending in parallel to each other, and disposed to be perpendicular to the first border or the third border, and multiple first notches formed on the first border, the second border, the third border, and the fourth border, and arranged at a 90-degree angle with reference to a center of each of the multiple first antenna elements, a second conductive layer positioned in the printed circuit board to be closer to the second surface than the multiple first antenna elements, and including multiple second antenna elements overlapping with, when seen from above the first surface, the multiple first antenna

elements one-to-one, configured to generate circular polarization, and including, when seen from above the first surface, a fifth border and a seventh border spaced apart from each other and extending in parallel to each other, a sixth border and an eighth border spaced apart from each other by a distance between the fifth border and the seventh border, and disposed to be perpendicular to the fifth border or the seventh border, and multiple second notches formed on the fifth border, the sixth border, the seventh border, and the eighth border, arranged at a 90-degree angle from the center, and overlapping with at least some of the multiple first notches one-to-one, a third conductive layer positioned in the printed circuit board to be closer to the second surface than the second conductive layer, a fourth conductive layer including a ground plane and positioned in the printed circuit board to be closer to the second surface than the third conductive layer, a first dielectric included in the printed circuit board and positioned between the first conductive layer and the second conductive layer, a second dielectric included in the printed circuit board, positioned between the third conductive layer and the fourth conductive layer, and having a greater dielectric constant than the first dielectric, multiple conductive vias positioned in the printed circuit board and electrically connecting the multiple first antenna elements and the third conductive layer, and a wireless communication circuit electrically connected to the multiple first antenna elements through the third conductive layer, wherein each of the multiple second antenna elements includes a hole, each of the multiple conductive vias is positioned to extend through the hole, the multiple second antenna elements are configured to be indirectly fed by the multiple conductive vias, and the multiple first notches have different shapes from the multiple second notches.

(8) An electronic device including an antenna according to various example embodiments of the disclosure can enhance a communication performance using circular polarization. For example, an electronic device including an antenna of the disclosure can perform positioning for a signal source, and it may be easier to secure the quality and the accuracy of the positioning even though there are various directions or orientations where the electronic device faces, or various polarization characteristics of a signal transmitted from the signal source.

(9) Other effects obtained or predicted by various embodiments of the disclosure will be directly or implicitly described in the detailed description of the embodiments of the disclosure.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) The above and other aspects, features and advantages of certain embodiments of the present disclosure will be more apparent from the following detailed description, taken in conjunction with the accompanying drawings, in which:

(2) FIG. 1 is a block diagram illustrating an example electronic device in a network environment according to various embodiments;

(3) FIG. 2 is a front perspective view illustrating of an electronic device according to various embodiments;

(4) FIG. 3 is a rear perspective view of the electronic device of FIG. 2 according to various embodiments;

(5) FIGS. 4 and 5 are exploded perspective views illustrating the electronic device of FIG. 2 according to various embodiments;

(6) FIG. 6 is a diagram illustrating a part of an electronic device according to various embodiments;

(7) FIG. 7 is a diagram illustrating a second antenna structure according to various embodiments;

(8) FIG. 8 is a diagram illustrating a first antenna including a first antenna element and a second antenna element according to various embodiments;

(9) FIG. 9 is a cross-sectional view of an x-z plane of a second antenna structure for an A-A' line in FIG. 7 according to various embodiments;

- (10) FIG. 10 is a cross-sectional view of an x-z plane of a second antenna structure for a B-B' line in FIG. 7 according to various embodiments;
- (11) FIG. 11 is a graph illustrating a resonance characteristic of a second antenna structure when changing a third width of each of multiple second notches included in multiple second antenna elements according to various embodiments
- (12) FIG. 12 is a graph illustrating a resonance characteristic of a second antenna structure when changing a second width of each of multiple first notches included in multiple first antenna elements according to various embodiments;
- (13) FIG. 13 is a graph illustrating antenna radiation efficiency of multiple first antenna elements when fixing a first width of each of multiple first notches included in the multiple first antenna elements and changing a third width of each of multiple second notches included in multiple second antenna elements according to various embodiments;
- (14) FIG. 14 is a graph illustrating an axis ratio characteristic of a second antenna structure according to an embodiment.
- (15) FIGS. 15 and 16 are graphs illustrating an impedance characteristic of a second antenna structure and an impedance characteristic of an antenna structure using linear polarization in a comparative example according to various embodiments;
- (16) FIG. 17 is a diagram illustrating a first antenna element according to various embodiments;
- (17) FIG. 18 is a diagram illustrating a second antenna element according to various embodiments;
- (18) FIG. 19 is a diagram illustrating a second antenna element according to various embodiments;
- (19) FIG. 20 is a graph illustrating a value obtained by measuring an angle at which a signal transmitted from a second electronic device is received by a first electronic device according to the orientation or the direction in which the first electronic device and the second electronic device face according to various embodiments;
- (20) FIG. 21 is a cross-sectional view on an x-z plane of a part of the electronic device illustrated in FIG. 3, according to various embodiments; and
- (21) FIG. 22 is a diagram illustrating the electronic device illustrated in FIG. 3, according to various embodiments.

DETAILED DESCRIPTION

- (22) Hereinafter, various example embodiments disclosed herein will be described with reference to the accompanying drawings.
- (23) FIG. 1 is a block diagram illustrating an example electronic device **101** in a network environment **100** according to various embodiments.
- (24) Referring to FIG. 1, the electronic device **101** in the network environment **100** may communicate with an external electronic device **102** via a first network **198** (e.g., a short-range wireless communication network), or at least one of an external electronic device **104** or a server **108** via a second network **199** (e.g., a long-range wireless communication network). The electronic device **101** may communicate with the external electronic device **104** via the server **108**. The electronic device **101** may include a processor **120**, memory **130**, an input module **150**, a sound output module **155**, a display module **160**, an audio module **170**, a sensor module **176**, an interface **177**, a connecting terminal **178**, a haptic module **179**, a camera module **180**, a power management module **188**, a battery **189**, a communication module **190**, a subscriber identification module (SIM) **196**, and/or an antenna module **197**. In various embodiments of the disclosure, at least one (e.g., the connection terminal **178**) of the components may be omitted from the electronic device **101**, or one or more other components may be added in the electronic device **101**. In various embodiments of the disclosure, some of the components may be implemented as single integrated circuitry. For example, the sensor module **176**, the camera module **180**, or the antenna module **197** may be implemented as embedded in single component (e.g., the display module **160**).
- (25) The processor **120** may execute, for example, software (e.g., a program **140**) to control at least one other component (e.g., a hardware or software component) of the electronic device **101**

coupled with the processor **120**, and may perform various data processing or computation. As at least part of the data processing or computation, the processor **120** may load a command or data received from another component (e.g., the sensor module **176** or the communication module **190**) in a volatile memory **132**, process the command or the data stored in the volatile memory **132**, and store resulting data in a non-volatile memory **134**. The processor **120** may include a main processor **121** (e.g., a central processing unit (CPU) or an application processor (AP)), or an auxiliary processor **123** (e.g., a graphics processing unit (GPU), a neural processing unit (NPU), an image signal processor (ISP), a sensor hub processor, or a communication processor (CP)) that is operable independently from, or in conjunction with, the main processor **121**. Additionally or alternatively, the auxiliary processor **123** may be adapted to consume less power than the main processor **121**, or to be specific to a specified function. The auxiliary processor **123** may be implemented as separate from, or as part of the main processor **121**.

(26) The auxiliary processor **123** may control, for example, at least some of functions or states related to at least one component (e.g., the display module **160**, the sensor module **176**, or the communication module **190**) among the components of the electronic device **101**, instead of the main processor **121** while the main processor **121** is in an inactive (e.g., a sleep) state, or together with the main processor **121** while the main processor **121** is in an active state (e.g., executing an application). The auxiliary processor **123** (e.g., an ISP or a CP) may be implemented as part of another component (e.g., the camera module **180** or the communication module **190**) functionally related to the auxiliary processor **123**. According to an embodiment of the disclosure, the auxiliary processor **123** (e.g., a neural network processing device) may include a hardware structure specified for processing an artificial intelligence model. The artificial intelligence model may be created through machine learning. Such learning may be performed, for example, in the electronic device **101** itself on which the artificial intelligence model is performed, or may be performed through a separate server (e.g., the server **108**). The learning algorithms may include, for example, supervised learning, unsupervised learning, semi-supervised learning, or reinforcement learning, but is not limited thereto. The artificial intelligence model may include a plurality of artificial neural network layers. The artificial neural network may be any of a deep neural network (DNN), a convolutional neural network (CNN), a recurrent neural network (RNN), a restricted Boltzmann machine (RBM), a deep belief network (DBN), a bidirectional recurrent DNN (BRDNN), a deep Q-network, or a combination of two or more of the above-mentioned networks, but is not limited the above-mentioned examples. In addition to the hardware structure, the artificial intelligence model may additionally or alternatively include a software structure.

(27) The memory **130** may store various data used by at least one component (e.g., the processor **120** or the sensor module **176**) of the electronic device **101**. The various data may include, for example, software (e.g., the program **140**) and input data or output data for a command related thereto. The memory **130** may include the volatile memory **132** and/or the non-volatile memory **134**.

(28) The program **140** may be stored in the memory **130** as software, and may include, for example, an operating system (OS) **142**, middleware **144**, and/or an application **146**.

(29) The input module **150** may receive a command or data to be used by another component (e.g., the processor **120**) of the electronic device **101**, from the outside (e.g., a user) of the electronic device **101**. The input module **150** may include, for example, a microphone, a mouse, a keyboard, a key (e.g., a button), or a digital pen (e.g., a stylus pen).

(30) The sound output module **155** may output sound signals to the outside of the electronic device **101**. The sound output module **155** may include, for example, a speaker or a receiver. The speaker may be used for general purposes, such as playing multimedia or playing record, and the receiver may be used for incoming calls. The receiver may be implemented as separate from, or as part of the speaker.

(31) The display module **160** may visually provide information to the outside (e.g., a user) of the

electronic device **101**. The display module **160** may include, for example, a display, a hologram device, or a projector and control circuitry to control a corresponding one of the display, hologram device, and projector. The display module **160** may include touch circuitry (e.g., a touch sensor) adapted to detect a touch, or sensor circuitry (e.g., a pressure sensor) adapted to measure the intensity of force incurred by the touch.

(32) The audio module **170** may convert a sound into an electrical signal and vice versa. The audio module **170** may obtain the sound via the input module **150**, or output the sound via the sound output module **155** or a headphone of an external electronic device (e.g., the external electronic device **102**) directly (e.g., wiredly) or wirelessly coupled with the electronic device **101**.

(33) The sensor module **176** may detect an operational state (e.g., power or temperature) of the electronic device **101** or an environmental state (e.g., a state of a user) external to the electronic device **101**, and then generate an electrical signal or data value corresponding to the detected state. The sensor module **176** may include, for example, a gesture sensor, a gyro sensor, an atmospheric pressure sensor, a magnetic sensor, an acceleration sensor, a grip sensor, a proximity sensor, a color sensor, an infrared (IR) sensor, a biometric sensor, a temperature sensor, a humidity sensor, or an illuminance sensor.

(34) The interface **177** may support one or more specified protocols to be used for the electronic device **101** to be coupled with the external electronic device (e.g., the external electronic device **102**) directly (e.g., wiredly) or wirelessly. The interface **177** may include, for example, a high-definition multimedia interface (HDMI), a universal serial bus (USB) interface, a secure digital (SD) card interface, and/or an audio interface.

(35) The connecting terminal **178** may include a connector via which the electronic device **101** may be physically connected with the external electronic device (e.g., the external electronic device **102**). The connecting terminal **178** may include, for example, an HDMI connector, a USB connector, an SD card connector, and/or an audio connector (e.g., a headphone connector).

(36) The haptic module **179** may convert an electrical signal into a mechanical stimulus (e.g., a vibration or a movement) or electrical stimulus which may be recognized by a user via his tactile sensation or kinesthetic sensation. The haptic module **179** may include, for example, a motor, a piezoelectric element, or an electric stimulator.

(37) The camera module **180** may capture a still image or moving images. The camera module **180** may include one or more lenses, image sensors, ISPs, or flashes.

(38) The power management module **188** may manage power supplied to or consumed by the electronic device **101**. The power management module **188** may be implemented as at least part of, for example, a power management integrated circuit (PMIC).

(39) The battery **189** may supply power to at least one component of the electronic device **101**. The battery **189** may include, for example, a primary cell which is not rechargeable, a secondary cell which is rechargeable, and/or a fuel cell.

(40) The communication module **190** may support establishing a direct (e.g., wired) communication channel or a wireless communication channel between the electronic device **101** and the external electronic device (e.g., the external electronic device **102**, the external electronic device **104**, or the server **108**) and performing communication via the established communication channel. The communication module **190** may include one or more CPs that are operable independently from the processor **120** (e.g., the AP) and supports a direct (e.g., wired) communication or a wireless communication. The communication module **190** may include a wireless communication module **192** (e.g., a cellular communication module, a short-range wireless communication module, or a global navigation satellite system (GNSS) communication module) or a wired communication module **194** (e.g., a local area network (LAN) communication module or a power line communication (PLC) module). A corresponding one of these communication modules may communicate with the external electronic device via the first network **198** (e.g., a short-range communication network, such as BLUETOOTH, wireless-fidelity (Wi-Fi)

direct, or IR data association (IrDA)) or the second network **199** (e.g., a long-range communication network, such as a legacy cellular network, a 5th generation (5G) network, a next generation communication network, the Internet, or a computer network (e.g., LAN or wide area network (WAN)). These various types of communication modules may be implemented as a single component (e.g., a single chip), or may be implemented as multiple components (e.g., multiple chips) separate from each other. The wireless communication module **192** may identify and authenticate the electronic device **101** in a communication network, such as the first network **198** or the second network **199**, using subscriber information (e.g., international mobile subscriber identity (IMSI)) stored in the SIM **196**.

(41) The wireless communication module **192** may support a 5G network, after a 4th generation (4G) network, and next-generation communication technology, e.g., new radio (NR) access technology. The NR access technology may support high-speed transmission of high-capacity data (i.e., enhanced mobile broadband (eMBB)), minimization of terminal power and connection of multiple terminals (massive machine type communications (mMTC)), or high reliability and low latency (ultra-reliable and low-latency communications (URLLC)). The wireless communication module **192** may support a high-frequency band (e.g., a mmWave band) to achieve, for example, a high data transmission rate. The wireless communication module **192** may support various technologies for securing performance in a high-frequency band, such as beamforming, massive multiple-input and multiple-output (MIMO), full-dimensional MIMO (FD-MIMO), array antenna, analog beam-forming, or large-scale antenna. The wireless communication module **192** may support various requirements specified in the electronic device **101**, an external electronic device (e.g., external the electronic device **104**), or a network system (e.g., the second network **199**). According to an embodiment of the disclosure, the wireless communication module **192** may support a peak data rate for implementing eMBB (e.g., 20 Gbps or more), loss coverage for implementing mMTC (e.g., 164 dB or less), or U-plane latency for realizing URLLC (e.g., 0.5 ms or less for each of downlink (DL) and uplink (UL) or 1 ms or less for round trip).

(42) The antenna module **197** may transmit or receive a signal or power to or from the outside (e.g., the external electronic device) of the electronic device **101**. The antenna module **197** may include an antenna including a radiating element including a conductive material or a conductive pattern formed in or on a substrate (e.g., a printed circuit board (PCB)). The antenna module **197** may include a plurality of antennas (e.g., an antenna array). In such a case, at least one antenna appropriate for a communication scheme used in the communication network, such as the first network **198** or the second network **199**, may be selected, for example, by the communication module **190** (e.g., the wireless communication module **192**) from the plurality of antennas. The signal or the power may then be transmitted or received between the communication module **190** and the external electronic device via the selected at least one antenna. Another component (e.g., a radio frequency integrated circuit (RFIC)) other than the radiating element may be additionally formed as part of the antenna module **197**.

(43) According to various embodiments of the disclosure, the antenna module **197** may form a mmWave antenna module. According to an embodiment of the disclosure, the mmWave antenna module may include a PCB, an RFIC that is disposed on or adjacent to a first surface (e.g., the bottom surface) of the PCB and is capable of supporting a predetermined high-frequency band (e.g., a mmWave band), and a plurality of antennas (e.g., array antennas) that is disposed on or adjacent to a second surface (e.g., the top surface or the side surface) of the PCB and is capable of transmitting or receiving a signal of the predetermined high-frequency band.

(44) At least some of the above-described components may be coupled mutually and communicate signals (e.g., commands or data) therebetween via an inter-peripheral communication scheme (e.g., a bus, general purpose input and output (GPIO), serial peripheral interface (SPI), or mobile industry processor interface (MIPI)).

(45) Commands or data may be transmitted or received between the electronic device **101** and the

external electronic device **104** via the server **108** coupled with the second network **199**. Each of the external electronic devices **102** or **104** may be a device of a same type as, or a different type, from the electronic device **101**. All or some of operations to be executed at the electronic device **101** may be executed at one or more of the external electronic devices **102**, **104**, or **108**. For example, if the electronic device **101** should perform a function or a service automatically, or in response to a request from a user or another device, the electronic device **101**, instead of, or in addition to, executing the function or the service, may request the one or more external electronic devices to perform at least part of the function or the service. The one or more external electronic devices receiving the request may perform the at least part of the function or the service requested, or an additional function or an additional service related to the request, and transfer an outcome of the performing to the electronic device **101**. The electronic device **101** may provide the outcome, with or without further processing of the outcome, as at least part of a reply to the request. To that end, a cloud computing, distributed computing, mobile edge computing (MEC), or client-server computing technology may be used, for example. The electronic device **101** may provide an ultra-low delay service using, for example, distributed computing or MEC. In an embodiment of the disclosure, the external electronic device **104** may include an internet of things (IoT) device. The server **108** may be an intelligent server using machine learning and/or neural networks. According to an embodiment of the disclosure, the external electronic device **104** or the server **108** may be included in the second network **199**. The electronic device **101** may be applied to an intelligent service (e.g., smart home, smart city, smart car, or healthcare) based on 5G communication technology or IoT-related technology.

(46) An electronic device according to an embodiment of the disclosure may be one of various types of electronic devices. The electronic devices may include a portable communication device (e.g., a smartphone), a computer device, a portable multimedia device, a portable medical device, a camera, a wearable device, a home appliance, or the like. However, the electronic device is not limited to any of those described above.

(47) Various embodiments of the disclosure and the terms used herein are not intended to limit the technological features set forth herein to particular embodiments and include various changes, equivalents, or replacements for a corresponding embodiment. With regard to the description of the drawings, similar reference numerals may be used to refer to similar or related elements. It is to be understood that a singular form of a noun corresponding to an item may include one or more of the things, unless the relevant context clearly indicates otherwise. As used herein, each of such phrases as “A or B,” “at least one of A and B,” “at least one of A or B,” “A, B, or C,” “at least one of A, B, and C,” and “at least one of A, B, or C,” may include any one of, or all possible combinations of the items enumerated together in a corresponding one of the phrases. As used herein, such terms as “1st” and “2nd,” or “first” and “second” may be used to simply distinguish a corresponding component from another, and does not limit the components in other aspect (e.g., importance or order). If an element (e.g., a first element) is referred to, with or without the term “operatively” or “communicatively,” as “coupled with,” “coupled to,” “connected with,” or “connected to” another element (e.g., a second element), the element may be coupled with the other element directly (e.g., wiredly), wirelessly, or via a third element.

(48) The term “module” may include a unit implemented in hardware, software, or firmware, or any combination thereof, and may interchangeably be used with other terms, for example, “logic,” “logic block,” “part,” or “circuitry”. A module may be a single integral component, or a minimum unit or part thereof, adapted to perform one or more functions. For example, according to an embodiment of the disclosure, the module may be implemented in a form of an application-specific integrated circuit (ASIC).

(49) Various embodiments as set forth herein may be implemented as software (e.g., the program **140**) including one or more instructions that are stored in a storage medium (e.g., an internal memory **136** or an external memory **138**) that is readable by a machine (e.g., the electronic device

101). For example, a processor (e.g., the processor **120**) of the machine (e.g., the electronic device **101**) may invoke at least one of the one or more instructions stored in the storage medium, and execute it, with or without using one or more other components under the control of the processor. This allows the machine to be operated to perform at least one function according to the at least one instruction invoked. The one or more instructions may include a code generated by a compiler or a code executable by an interpreter. The machine-readable storage medium may be provided in the form of a non-transitory storage medium. Wherein, the “non-transitory” storage medium is a tangible device, and may not include a signal (e.g., an electromagnetic wave), but this term does not differentiate between where data is semi-permanently stored in the storage medium and where the data is temporarily stored in the storage medium.

(50) A method according to an embodiment of the disclosure may be included and provided in a computer program product. The computer program product may be traded as a product between a seller and a buyer. The computer program product may be distributed in the form of a machine-readable storage medium (e.g., compact disc read only memory (CD-ROM)), or be distributed (e.g., downloaded or uploaded) online via an application store (e.g., PLAYSTORE™), or between two user devices (e.g., smart phones) directly. If distributed online, at least part of the computer program product may be temporarily generated or at least temporarily stored in the machine-readable storage medium, such as memory of the manufacturer's server, a server of the application store, or a relay server.

(51) Each component (e.g., a module or a program) of the above-described components may include a single entity or multiple entities. One or more of the above-described components may be omitted, or one or more other components may be added. Alternatively or additionally, a plurality of components (e.g., modules or programs) may be integrated into a single component. In such a case, the integrated component may perform one or more functions of each of the plurality of components in the same or similar manner as they are performed by a corresponding one of the plurality of components before the integration. Operations performed by the module, the program, or another component may be carried out sequentially, in parallel, repeatedly, or heuristically, or one or more of the operations may be executed in a different order or omitted, or one or more other operations may be added.

(52) FIG. 2 is a front perspective view of an electronic device **200** according to various. FIG. 3 is a rear perspective view of an electronic device **200** according to various embodiments.

(53) Referring to FIGS. 2 and 3, in an embodiment, the electronic device **200** (e.g., the electronic device **101** of FIG. 1) may include a housing **300** forming an exterior of the electronic device **200**, and the housing **300** may form, for example, a front surface **300A** of the electronic device **200**, a rear surface **300B** of the electronic device **200**, and a side surface **300C** of the electronic device **200**, which surrounds a space between the front surface **300A** and the rear surface **300B**. In an embodiment, the housing **300** may refer to a structure forming at least a part of the front surface **300A**, the rear surface **300B**, and the side surface **300C**.

(54) According to an embodiment, the housing **300** may include a front plate **310**, a rear plate **320**, and/or a bezel structure **330**. At least a part of the front surface **300A** of the electronic device **200** may be formed by the front plate **310**. The front plate **310** may be substantially transparent, and may include, for example, a polymer plate or a glass plate including various coating layers. At least a part of the rear surface **300B** of the electronic device **200** may be formed by the rear plate **320**. In an embodiment, the rear plate **320** may include a first rear plate **321** forming one part of the rear surface **300B** and a second rear plate **322** forming another part of the rear surface **300B**. The first rear plate **321** and the second rear plate **322** may be substantially opaque. The first rear plate **321** and/or the second rear plate **322** may be formed of, for example, coated or colored glass, ceramic, polymer, metal, or a combination of two or more of the materials above. In another example, the first rear plate **321** and/or the second rear plate **322** may include alloy (e.g., stainless steel) including aluminum, aluminum alloy, magnesium, magnesium alloy, or iron. The bezel structure

330 may surround at least one a part of the space between the front plate **310** and the rear plate **320**. At least a part of the side surface **300C** of the electronic device **200** may be formed by the bezel structure **330**. In an embodiment, the bezel structure **330** may be called a “side bezel structure” or a “side member” as an element substantially forming the side surface **300C** of the electronic device **200**. The bezel structure **330** may include, for example, metal and/or polymer.

(55) According to an embodiment, the front plate **310** may include a first curved part **3001** and a second curved part **3002** curved and seamlessly extending from the front surface **300A** toward the rear surface **300B**. The first curved part **3001** and the second curved part **3002** may be formed to be adjacent to opposite edges of the front plate **310**, which are positioned opposite to each other. For example, the first curved part **3001** and the second curved part **3002** may be arranged to be symmetrical to each other by interposing a plane part (not shown) of the front plate **310** therebetween.

(56) According to an embodiment, the first rear plate **321** may include a third curved part **3003** and a fourth curved part **3004** curved and seamlessly extending from the rear surface **300B** toward the front surface **300A**. The third curved part **3003** may be formed to be adjacent to an edge on one side of the first rear plate **321**, so as to correspond to the first curved part **3001** of the front plate **310**. The fourth curved part **3004** may be formed to be adjacent to an edge on the other side of the first rear plate **321**, so as to correspond to the second curved part **3002** of the front plate **310**. In an embodiment, a part **331** of the bezel structure **330** may include a fifth curved part **3005** seamlessly connected to the fourth curved part **3004** of the first rear plate **321**, so as to correspond to the second curved part **3002** of the front plate **310**. For example, a curved part on one side, which includes the fourth curved part **3004** and the fifth curved part **3005**, may be disposed to be symmetrical to the third curved part **3003** on the other side. In an embodiment, the second rear plate **322** may be positioned to correspond to the fifth curved part **3005**. For example, the part **331** of the bezel structure **330**, which forms the fifth curved part **3005**, may extend along a partial margin (e.g., a margin following a dotted line indicated by a reference numeral “E”) by the second rear plate **322**, among a margin (or an edge or a border) of the rear plate **320**, and may come into contact with the second rear plate **320**. In an embodiment, the fifth curved part **3005** may be formed by the first rear plate **321** or the second rear plate **322**. In an embodiment, the first rear plate **321** and the second rear plate **322** may be integrally formed. In an embodiment, the first rear plate **321** and/or the second rear plate **322** may be integrally formed with the bezel structure **330**, and may include the same material (e.g., a metal material such as aluminum) as the bezel structure **330**. (57) In an embodiment, the housing **300** may be implemented without at least one of a curved part including the first curved part **3001**, the second curved part **3002**, the third curved part **3003**, or the fourth curved part **3004** and the fifth curved part **3005**.

(58) According to an embodiment, the electronic device **200** may include at least one of a display **201**, a first audio module **202**, a second audio module **203**, a third audio module **204**, a fourth audio module **205**, a sensor module **206**, a first camera module **207**, multiple second camera modules **208**, a light emitting module **209**, an input module **210**, a first connection terminal module **211**, or a second connecting terminal module **212**. In an embodiment, the electronic device **200** may omit at least one of the elements above, or may additionally include other elements.

(59) A display area (e.g., a screen display area or an active area) of the display **201** may be visually exposed (e.g., visible) through, for example, the front plate **310**. In an embodiment, in the electronic device **200**, a display area seen through the front plate **310** may be implemented as large as possible (e.g., a large screen or a full screen). For example, the display **201** may be implemented to have an outer periphery having the substantially same shape as the outer peripheral shape of the front plate **310**. In an embodiment, the display **201** may include a touch detection circuit. In an embodiment, the display **201** may include a pressure sensor capable of measuring the intensity (pressure) of a touch. In an embodiment, the display **201** may be coupled to a digitizer (e.g., an electromagnetic induction panel) for detecting a magnetic field-type electronic pen (e.g., a stylus

pen), or may be positioned to be adjacent to the digitizer.

(60) The first audio module **202** may include, for example, a first microphone positioned in the electronic device **200**, and a first microphone hole formed through the side surface **200C** to correspond to the first microphone. The second audio module **203** may include, for example, a second microphone positioned in the electronic device **200**, and a second microphone hole formed through the rear surface **300B** of the second microphone. The second microphone hole may be formed through, for example, the first rear plate **321**. In an embodiment, the second microphone hole may be formed through the second rear plate **322**. The positions and the number of audio modules of a microphone may not be limited to the illustrated examples and there may be various positions and numbers of audio modules. In an embodiment, the electronic device **200** may include multiple microphones used for detection of the direction of sound.

(61) The third audio module **204** may include, for example, a first speaker positioned in the electronic device **200**, and a first speaker hole formed through the side surface **300C** to correspond to the first speaker. The fourth audio module **205** may include, for example, a second speaker positioned in the electronic device **200** and a second speaker hole formed through the front surface **300A** to correspond to the second speaker. In an embodiment, the first speaker may include an external speaker. In an embodiment, the second speaker may include a call receiver, and the second speaker hole may be called a receiver hole. The positions or the number of the third audio modules **204** or the fourth audio modules **205** may not be limited to the illustrated examples and there may be various positions or numbers of the third audio modules or the fourth audio modules. In an embodiment, the microphone hole and the speaker hole may be implemented as a single hole. In an embodiment, the third audio module **204** or the fourth audio module **205** may include a piezo speaker from which a speaker hole is omitted.

(62) The sensor module **206** may generate, for example, an electric signal or a data value corresponding to an internal operational state or an external environment state of the electronic device **200**. In an embodiment, the sensor module **206** may include an optical sensor positioned in the electronic device **200** to correspond to the front surface **300A** of the sensor module **206**. The optical sensor may include, for example, a proximity sensor or an illuminance sensor. The optical sensor may be aligned with an opening formed on the display **201**. External light may be introduced into the optical sensor through the opening of the display **201** and the front plate **310**. In an embodiment, the optical sensor may be disposed under the display **201**, and may perform a related function without visually distinguishing (or exposing) the position of the optical sensor. For example, the optical sensor may be positioned on the rear surface of the display **201**, or may be positioned under (below or beneath) the display **201**. In an embodiment, the optical sensor may be positioned to be aligned with a recess formed on the rear surface of the display **201**. The optical sensor may be disposed to overlap with at least a part of a screen and perform a sensing function without being exposed to the outside. In this case, a partial area of the display **201**, which at least partially overlaps with the optical sensor, may include a different pixel structure and/or wiring structure from other areas. For example, the partial area of the display **201**, which at least partially overlaps with the optical sensor, may have different pixel density from other areas. In an embodiment, multiple pixels may not be arranged in the partial area of the display **201**, which at least partially overlaps the optical sensor. In an embodiment, the electronic device **200** may include a biometric sensor (e.g., a fingerprint sensor) positioned under the display **201**. The biometric sensor may be implemented in an optical type, a captive type, or an ultrasonic type, and there may be various positions and numbers of the biometric sensors. The electronic device **200** may further include other various sensor modules, for example, at least one of a gesture sensor, a gyro sensor, an atmospheric pressure sensor, a magnetic sensor, an acceleration sensor, a grip sensor, a color sensor, an infrared (IR) sensor, a temperature sensor, or a humidity sensor.

(63) The first camera module **207** (e.g., a front camera module) may be positioned, for example, in the electronic device **200** to correspond to the front surface **300A**. The multiple second camera

modules **208** (e.g., rear camera modules) may be positioned, for example, in the electronic device **200** to correspond to the rear surface **300B**. In an embodiment, the multiple second camera modules **208** may be positioned to correspond to the second rear plate **322**. The first camera module **207** and/or the multiple second camera modules **208** may include one or multiple lenses, image sensors, and/or image signal processors. The positions and the number of the first camera modules or the second camera modules may not be limited to the illustrated example and there may be various positions and numbers of the first camera modules or the second camera modules.

(64) According to an embodiment, the display **201** may include an opening aligned with the first camera module **207**. External light may reach the first camera module **207** through the opening of the display **201** and the front plate **310**. In an embodiment, the opening of the display **201** may be formed in a notch shape according to the position of the first camera module **207**. In an embodiment, the first camera module **207** may be disposed under the display **201**, and may perform a related function (e.g., image capturing) without visually distinguishing (or exposing) the position of the first camera module **207**. For example, the first camera module **207** may be positioned on the rear surface of the display **201**, or may be positioned under (below or beneath) the display **201**, and may include a hidden display rear camera (e.g., an under-display camera (UDC)). In an embodiment, the first camera module **207** may be positioned to be aligned with a recess formed on the rear surface of the display **201**. The first camera module **207** may be disposed to overlap with at least a part of a screen, and may acquire an image of an external subject, without being visually exposed to the outside. In this case, a partial area of the display **201**, which at least partially overlaps with the first camera module **207**, may include a different pixel structure and/or wiring structure from other areas. For example, the partial area of the first display **201**, which at least partially overlaps with the first camera module **207**, may have different pixel density from other areas. The pixel structure and/or the wiring structure formed in the partial area of the display **201**, which at least partially overlaps with the first camera module **207**, may reduce an optical loss between the outside and the first camera module **207**. In an embodiment, a pixel may not be disposed in the partial area of the display **201**, which at least partially overlaps with the first camera module **207**. In an embodiment, the electronic device **200** may further include a light emitting module (e.g., a light source) positioned in the electronic device **200** to correspond to the front surface **300A**. For example, the light emitting module may provide state information of the electronic device **200** in an optical type. In an embodiment, the light emitting module may provide a light source linked with an operation of the first camera module **207**. The light emitting module may include, for example, an LED, an IR LED, or a xenon lamp.

(65) According to an embodiment, the multiple second camera modules **208** may have different attributes (e.g., angles of view) or functions, and may include, for example, a dual camera or a triple camera. The multiple second camera modules **208** may include multiple camera modules including a lens having different angles of view, and the electronic device **200** may control a change in an angle of view of a camera module, performed in the electronic device **200**, based on a user selection. The multiple second camera modules **208** may include at least one of a wide-angle camera, a telephoto camera, a color camera, a monochrome camera, or an infrared (IR) camera (e.g., a time of flight (TOF) camera and a structure light camera). In an embodiment, the IR camera may operate as at least a part of a sensor module. The light emitting module **209** (e.g., flash) may include a light source for the multiple second camera modules **208**. The light emitting module **209** may include, for example, an LED or a xenon lamp.

(66) The input module **210** may include, for example, one or more key input devices. The one or more key input devices may be positioned, for example, on an opening formed on the side surface **300C**. In an embodiment, the electronic device **200** may not include some or all of the key input devices, and the key input device that is not included may be implemented as a soft key using the display **201**. There may be various positions and numbers of the input modules **210**, and in an embodiment, the input module **210** may include at least one sensor module.

(67) The first connection terminal module **211** (e.g., a first connector module or a first interface terminal module) may include, for example, a first connector (or a first interface terminal) positioned in the electronic device **200**, and a first connector hole formed through the side surface **300C** to correspond to the first connector. The second connection terminal module **212** (e.g., a second connector module or a second interface terminal module) may include, for example, a second connector (or a second interface terminal) positioned in the electronic device **200**, and a second connector hole formed through the side surface **300c** to correspond to the second connector. The electronic device **200** may transmit and/or receive power and/or data to and/or from an external electronic device electrically connected to the first connector or the second connector. In an embodiment, the first connector may include a universal serial bus (USB) connector or a high-definition multimedia interface (HDMI) connector. In an embodiment, the second connector may include a connector for a memory card (e.g., a secure digital (SD) memory card or a subscriber identity module (SIM) card). In an embodiment, the second connector may include an audio connector (e.g., a headphone connector or an earset connector). The positions or the number of the connection terminal modules may not be limited to the illustrated example and there may be various positions or numbers of the connection terminal modules.

(68) According to an embodiment, the electronic device **200** may include a second antenna structure **5** positioned in the housing **300**. For example, the electronic device **200** may perform a positioning function (e.g., angle of arrival (AOA)) for a signal source (e.g., a responder, a transmitter, or a Tx device) using the second antenna structure **5**. The electronic device **200** may include a wireless communication circuit (e.g., the wireless communication module **192** of FIG. **1**) electrically connected to the second antenna structure **5**, and a processor (e.g., the processor **120** of FIG. **1**) electrically connected to the wireless communication circuit. In an embodiment, the processor may identify (or estimate) a reception angle (e.g., the direction of a signal) of a signal for a configured axis of the electronic device **200**, or the distance from the electronic device or the signal source, using a time difference between signals received through the second antenna structure **5** and a phase difference due to the time difference. The electronic device **200** may support a positioning function using a bandwidth (e.g., UWB) of a broadband. For example, the UWB corresponds to a technology following the international standard of IEEE 802.15.4, and may indicate a technology in which communication is performed with a bandwidth of a broadband.

(69) The electronic device **200** may further include various elements according to a providing form thereof. Such elements may have forms changed in various ways according to the trend toward convergence of the electronic device **200**, but the electronic device **200** may further include having equal levels to those of the abovementioned elements although all of the elements are not listed herein. In various embodiments, the electronic device **200** may omit specific elements of the above-described elements or substitute the same with other elements according to a providing form thereof.

(70) FIGS. **4** and **5** are exploded perspective views of an electronic device **200** of FIG. **2** according to various embodiments. FIG. **6** is a diagram illustrating a part of an electronic device **200** according to various embodiments. FIG. **7** a diagram illustrating a second antenna structure **5** according to various embodiments.

(71) Referring to FIGS. **4**, **5**, **6**, and **7**, in an embodiment, the electronic device **200** may include a front plate **310**, a rear plate **320**, a bezel structure **330**, a first support member **410**, a second support member **420**, a third support member **430**, a display **201**, a first substrate assembly **440**, a second substrate assembly **450**, a battery **460**, a first antenna structure **470**, and/or a second antenna structure **5**. In an embodiment, the electronic device **200** may omit at least one of the elements or may additionally include other elements.

(72) According to an embodiment, the bezel structure **330** (or a side member) may include a first bezel structure **411** (or a first side surface part), a second bezel structure **412** (or a second side surface part), a third bezel part **413** (or a third surface part), or a fourth bezel part **414** (or a fourth

side surface part). The first bezel part **411** and the third bezel part **413** may be spaced apart from each other and extend in parallel to each other. The second bezel part **412** may connect one end of the first bezel part **411** to one end of the third bezel part **413**. The fourth bezel part **414** may connect the other end of the first bezel part **411** to the other end of the third bezel part **413**, and the fourth bezel part **414** and the second bezel part **412** may be spaced apart from each other and extend in parallel to each other. At least a part of a first corner part **415** connecting the first bezel part **411** and the second bezel part **412**, a second corner part **416** connecting the second bezel part **412** and the third bezel part **413**, a third corner part **417** connecting the third bezel part **413** and the fourth bezel part **414**, and/or a fourth corner part **418** connecting the first bezel part **411** and the fourth bezel part **414** may be formed to have a circular shape. Each of the first bezel part **411** and the third bezel part **413** may have a first length extending in the y-axis direction, and each of the second bezel part **412** and the fourth bezel part **414** may have a second length which is shorter than the first length and extends in the x-axis direction. In an embodiment, the first length and the second length may be substantially identical to each other. The first support member **410** may be disposed in the electronic device **200** and connected to the bezel structure **330**, or may be integrally formed with the bezel structure **330**. The first support member **410** may be formed of, for example, a metal material and/or a non-metal material (e.g., polymer). In an embodiment, a conductive part included in the first support member **440** may function as an electromagnetic shield for the display **201**, the first substrate assembly **440**, and/or the second substrate assembly **450**. The first support member **410** and the bezel structure **330** may be called a front case **400**. The first support member **410** corresponds to a part of the front case **400**, in which elements such as the display **201**, the first substrate assembly **440**, the second substrate assembly **450**, and the battery **460** are arranged, and may contribute to durability and rigidity (e.g., torsional rigidity) of the electronic device **200**. In an embodiment, the first support member **410** may be called a “bracket”, a “mounting plate”, or a “support structure”. In an embodiment, the first support member **410** may be defined as a part of the housing **300** (see FIG. 2).

(73) For example, the display **201** may be positioned between the first member **410** and the front plate **310** and disposed on one surface of the first support member **410**. In an embodiment, the front plate **310** and the display **201** may be integrally formed. For example, the first substrate assembly **440** and the second substrate assembly **450** may be positioned between the first support member **410** and the rear plate **320**, and disposed on the other surface of the first support member **410**. For example, the battery **460** may be positioned between the first support member **410** and the rear plate **320**, and disposed on the first support member **410**.

(74) According to an embodiment, the first substrate assembly **440** may include a first printed circuit board **441** (e.g., a printed circuit board (PCB) or a printed circuit board assembly (PBA)). The first substrate assembly **440** may include various electronic components electrically connected to the first printed circuit board **441**. The electronic components may be arranged on the first printed circuit board **441**, and may be electrically connected to the first printed circuit board **441** through an electrical path such as a cable or a flexible printed circuit board (FPCB). Referring to FIGS. 2 and 3, the electronic components may include, for example, a second microphone included in the second audio module **203**, a second speaker included in the fourth audio module **205**, the sensor module **206**, the first camera module **207**, the multiple second camera modules **208**, the light emitting module **209**, or the input module **210**.

(75) According to an embodiment, when seen from above the front plate **310** (e.g., when seen in the -z axis direction), the second substrate assembly **450** and the first substrate assembly **440** may be spaced apart from each other by interposing the battery **460** therebetween. The second substrate assembly **450** may include a second printed circuit board **451** electrically connected to the first printed circuit board **441** of the first printed circuit **440**. The second substrate assembly **450** may include various electronic components electrically connected to the second printed circuit board **451**. The electronic components may be arranged on the second printed circuit board **451**, or may

be electrically connected to the second printed circuit board **451** through an electrical path such as a cable of an FPCB. Referring to FIGS. **2** and **3**, the electronic components may include, for example, a first microphone included in the first audio module **202**, a first speaker included in the third audio module **204**, a first connector included in the first connection terminal module **211**, or a second connector included in the second connection terminal module **212**.

(76) According to an embodiment, the first substrate assembly **440** or the second substrate assembly **450** may include a primary PCB (or a main PCB or a master PCB), a secondary PCB (or a slave PCB) disposed to overlap with the primary PCB, and/or an interposer substrate between the primary PCB and the secondary PCB.

(77) The battery **460** corresponds to a device for supplying power to at least one element of the electronic device **200**, and may include, for example, a primary cell which is not rechargeable, a secondary cell which is rechargeable, or a fuel cell. The battery **460** may be integrally formed in the electronic device **200**, or may be detachably disposed to the electronic device **200**.

(78) According to an embodiment, the second support member **420** may be positioned between the first support member **410** and the rear plate **320**, and may be coupled to the first support member **410** and/or the first substrate assembly **440** using a coupling element such as a bolt. At least a part of the first substrate assembly **440** may be positioned between the first support member **410** and the second support member **420**, and the second support member **420** may cover and protect the first substrate assembly **440**. When seen from above the rear plate **320** (when seen from the +z axis direction), the third support member **430** and the second support member **420** may be at least partially spaced apart from each other by interposing the battery **460** therebetween. The third support member **430** may be positioned between the first support member **410** and the rear plate **320**, and may be coupled to the first support member **410** and/or the second substrate assembly **450** using a coupling element such as a bolt. At least a part of the second substrate assembly **450** may be positioned between the first support member **410** and the third support member **430**, and the third support member **430** may cover and protect the second substrate assembly **450**. The second support member **420** and/or the third support member **430** may be formed of a metal material and/or a non-metal material (e.g., polymer). In an embodiment, the second support member **420** may function as an electromagnetic shield for the first substrate assembly **440**, and the third support member **430** may function as an electromagnetic shield for the second substrate assembly **450**. In an embodiment, the second support member **420** and/or the third support member **430** may be called a rear case. In an embodiment, the second support member **420** and/or the third support member **430** may be defined as a part of the housing **300** (see FIG. **2**).

(79) In an embodiment, an integrated substrate assembly including the first substrate assembly **440** and the second substrate assembly **450** may be implemented. For example, when seen from above the rear plate **320** (e.g., when seen from above +z axis direction), the substrate assembly may include a first part and a second part, which are spaced apart from each other by interposing the battery **460** therebetween, and a third part extending between the battery **460** and the bezel structure **330** and connecting the first part and the second part. The third part may be substantially implemented to be rigid. In an embodiment, the third part may be substantially implemented to be flexible. In an embodiment, an integrated support member including the second support member **420** and the third support member **430** may be implemented.

(80) According to an embodiment, the second support member **420** (e.g., a rear case) may include a non-conductive member **421** formed of a non-metal material (e.g., polymer) and/or multiple conductive patterns **422**, **423**, **424**, and **425** arranged on the non-conductive member. For example, the conductive pattern **422**, **423**, **424**, or **425** may be implemented by laser direct structuring (LDS). The LDS may correspond to, for example, a scheme of designing a pattern on the non-conductive member **421** using a laser and plating a conductive material such as copper or nickel on the pattern, so as to form a conductive pattern. The multiple conductive patterns **422**, **423**, **424**, and **425** may be electrically connected to a wireless communication circuit (e.g., the wireless communication

module **192** of FIG. **1**) included in the first substrate assembly **440** so as to operate as an antenna radiator. In an embodiment, at least a part of a conductive part included in the bezel structure **330** may operate as an antenna radiator electrically connected to the wireless communication circuit. The wireless communication circuit may process a transmission signal or a reception signal in at least one selected or designated frequency band through at least one antenna radiator. The selected or designated frequency band may include at least one of, for example, a low band (LB) (about 600 MHz to about 1 GHz), a middle band (MB) (about 1 GHz to about 2.3 GHz), a high band (HB) (about 2.3 GHz to about 2.7 GHz), or an ultra-high band (UHB) (about 2.7 GHz to about 6 GHz). The designated frequency band may include various other frequency bands.

(81) According to an embodiment, the first antenna structure **470** may be at least partially positioned between the battery **460** and the rear plate **320**. The first antenna structure **470** may be implemented as, for example, a film type such as an FPCB. The first antenna structure **470** may include at least one conductive pattern utilized as a loop-type radiator. For example, the at least one conductive pattern may include a plane-type spiral conductive pattern (e.g., a plane coil or a pattern coil). The first antenna structure **470** may be disposed on, for example, the battery **460**, and may include a first area **471** including a spiral conductive pattern and a second area **472** extending from the first area **471** and electrically connected to the first substrate assembly **440**. The at least one conductive pattern included in the first antenna structure **470** may be electrically connected to a wireless communication circuit (or a wireless communication module) included in the first substrate assembly **440**. For example, the at least one conductive pattern may be utilized for short-distance wireless communication such as a near-field communication (NFC). In another example, the at least one conductive pattern may be utilized for magnetic secure transmission (MST) for transmitting and/or receiving a magnetic signal. In an embodiment, the at least one conductive pattern included in the antenna structure **470** may be electrically connected to a power transmission/reception circuit included in the first substrate assembly **440**. The power transmission/reception circuit may wirelessly receive power from an external electronic device using the at least one conductive pattern, or wireless transmit power to the external electronic device. The power transmission/reception circuit may include a power management module, and may include, for example, a power management integrated circuit (PMIC) or a charger integrated circuit (IC). The power transmission/reception circuit may charge the battery **460** using power wirelessly received using the conductive pattern.

(82) According to an embodiment, the second antenna structure **5** may include a circuit substrate (a circuit board or substrate) **500**, multiple first antenna elements **61**, **62**, and **63**, and multiple second antenna elements **71**, **72**, and **73**. The circuit substrate **500** may indicate an insulation material for allowing the conductive pattern (e.g., a copper clad pattern) such as the multiple first antenna elements **61**, **62**, and **63** and the multiple second elements **71**, **72**, and **73** to be disposed. In an embodiment, the second antenna structure **5** has a shape in which a circuit (e.g., a conductive pattern) is positioned on the circuit substrate **500** (e.g., an insulation substrate), and may include a printed circuit board (PCB) **50**. The printed circuit board **50** of the second antenna structure may include, for example, a rigid printed circuit board (RPCB), a flexible printed circuit board (FPCB), or a rigid flexible printed circuit board (RFPCB).

(83) According to an embodiment, the second antenna structure **5** may be at least partially positioned between the first substrate assembly **440** and the rear plate **320**. In another example, the second antenna structure **5** may be positioned between the second support member **420** and the battery **460** when seen from above the rear plate **320** (when seen in the +2 axis direction). The second antenna structure **5** may be disposed to substantially not to overlap with the second support member **420**, the first antenna structure **470**, the battery **460**, the multiple second camera modules **208**, or the light-emitting module **209** when seen from above the rear plate **320**. For example, the second antenna structure **5** may not substantially overlap with the multiple conductive patterns **422**, **423**, **424**, and **425** of the second support member **420** or the conductive pattern of the first antenna

structure **470** when seen from above the rear plate **320**.

(84) According to an embodiment, the electronic device **200** may include a cover member **480** (or a cover structure or a support structure) positioned between the first substrate assembly **440** and the rear plate **320**. The cover member **480** may include metal and/or polymer, and may be coupled to the first substrate assembly **440** and/or the first support member **410** using a bolt. When seen from above the rear plate **320** (e.g., when seen in the +z direction), a part of the first substrate assembly **440** may overlap with the second support member **420**, and another part of the second substrate assembly **440** may overlap with the cover member **480**. The second support member **420** and the cover member **480** may be arranged not to hide the multiple second camera modules **208** using external light having passed through the rear plate **320** and the light emitting module **209** outputting light passing through the rear plate **320**. In an embodiment, the second antenna structure **5** may be disposed to the cover member **480**. For example, a polymer adhesive material may be positioned between the second antenna structure **5** and the cover member **480**. The printed circuit board **50** of the antenna structure **5** may include a first part **51** including the multiple first antenna elements **61**, **62**, and **63** and the multiple second antenna elements **71**, **72**, and **73**, and a second part **52** extending from the first part **51** and electrically connected to the first substrate assembly **440**. The first part **51** of the printed circuit board **50** may be disposed to the cover member **480**. The second part **52** of the printed circuit board **50** may be electrically connected to the first substrate assembly **440** through, for example, an opening **481** (e.g., a notch-type opening) of the cover member **480**. In an embodiment, the second support member **420** and the cover member **480** may be integrally formed.

(85) According to an embodiment, the printed circuit board **50** of the antenna structure **5** may include multiple conductive layers stacked thereon, the multiple conductive layers including at least one conductive pattern, and a dielectric (or an insulator) may be positioned between the multiple conductive layers. One or more conductive patterns included in the multiple conductive layers may be utilized as antenna radiators. The one or more conductive patterns included in the multiple conductive layers may be utilized as electrical paths (e.g., signal lines). The one or more conductive patterns included in the multiple conductive layers may be utilized as ground planes. A conductive pattern utilized as an antenna radiator may be called an “antenna element” or a “radiation pattern”. A conductive pattern utilized as at least part of an electrical path may be called a “path pattern”. A conductive pattern utilized as at least a part of a ground plane may be called a “ground pattern”. The printed circuit board **50** may include multiple conductive vias. A conductive via may correspond to a conductive hole made to allow a connection wire for electrically connecting conductive patterns in different conductive layers to be disposed. A conductive via may include, for example, a plated through-hole (PTH), a laser via-hole (LVH), a buried via-hole (BVH), or a stacked via.

(86) According to an embodiment, the multiple first antenna elements **61**, **62**, and **63** may include a first conductive layer (not shown) among the multiple conductive layers of the printed circuit board **50**. The multiple second antenna elements **71**, **72**, and **73** may include a second conductive layer (not shown) that is different from the first conductive layer, among the multiple conductive layers of the printed circuit board **50**. For example, when seen from above the rear plate **320** (when seen in the +z axis direction), the multiple first antenna elements **61**, **62**, and **63** may include substantially the same shape. For example, when seen from above the rear plate **320**, the multiple second antenna elements **71**, **72**, and **73** may include substantially the same shape. When seen from above the rear plate **320**, the multiple first antenna elements **61**, **62**, and **63** may be aligned with the multiple second antenna elements **71**, **72**, and **73** one-to-one and overlap with each other.

(87) According to an embodiment, the antenna structure **5** may include a first antenna {circle around (1)} (or a first patch antenna), a second antenna {circle around (2)} (or a second patch antenna), and/or a third antenna {circle around (3)} (or a third patch antenna). For example, the first antenna {circle around (1)} may include the first antenna elements **61** and the second antenna

element **71** aligning and overlapping with each other when seen from above the rear plate **320**. For example, the second antenna {circle around (2)} may include the first antenna elements **62** and the second antenna element **72** aligning and overlapping with each other when seen from above the rear plate **320**. For example, the third antenna {circle around (3)} may include the first antenna elements **63** and the second antenna element **73** aligning and overlapping with each other when seen from above the rear plate **320**. In an embodiment, the first antenna {circle around (1)}, the second antenna {circle around (2)}, and the third antenna {circle around (3)} may be included in and called as an antenna array (AR).

(88) According to an embodiment, when a radiation current (or an electromagnetic signal) is provided to the first antenna {circle around (1)}, the first antenna {circle around (1)} may generate dual-band circular polarization. In an embodiment, the first antenna {circle around (1)} may include a feeding unit corresponding to a part into which the radiation current is fed. For example, a printed communication circuit (e.g., the wireless communication module **192** of FIG. **1**) included in the first substrate assembly **440** may provide the radiation current to the feeding unit of the first antenna {circle around (1)}. The first antenna {circle around (1)} may emit the fed electromagnetic signal (e.g., a UWB signal) to the outside or may receive the electromagnetic signal from the outside. The second antenna {circle around (2)} may be implemented in the substantially same manner as the first antenna {circle around (1)} and operate. The third antenna {circle around (3)} may be implemented in the substantially same manner as the first antenna {circle around (1)} and operate.

(89) According to an embodiment, the electronic device **200** may communicate with a signal source (e.g., a responder, a transmitter, or a Tx device) using an antenna array (AR). For example, the electronic device **200** may perform a positioning function (e.g., AOA) for a signal source (e.g., a responder, a transmitter, or a Tx device) using an antenna array (AR). In an embodiment, the antenna array (AR) may be disposed in an “L” shape. For example, according to the “L”-shaped disposition, the first antenna {circle around (1)} and the second antenna {circle around (2)} among the antenna array (AR) may be arranged to be spaced from each other in the x-axis direction, and the first antenna {circle around (1)} and the third antenna {circle around (3)} among the antenna array (AR) may be arranged to be spaced from each other in the y-axis direction. A processor (e.g., the processor **120** of FIG. **1**) may identify or estimate a first angle (e.g., a first signal reception angle) at which a signal is received with respect to a configured x axis of the electronic device **200**, using a time difference and a phase difference between signals received through the first antenna {circle around (1)} and the second antenna {circle around (2)} arranged in the x-axis direction. For example, the configured x axis of the electronic device **200** may be in a direction in which the second bezel part **412** and the fourth bezel part **414** of FIG. **5** extend in parallel to each other. The processor may identify or estimate a second angle (e.g., a second signal reception angle) at which a signal is received with respect to a configured y axis of the electronic device **200**, using a time difference and a phase difference between signals received through the first antenna {circle around (1)} and the third antenna {circle around (3)} arranged in the y-axis direction. For example, the configured y axis of the electronic device **200** may be in a direction in which the first bezel part **411** and the third bezel part **413** of FIG. **5** extend in parallel to each other. The processor may identify or estimate a direction of a signal source for the electronic device **200** using the first angle and the second angle. The electronic device **200** may identify or estimate a distance between the electronic device **200** and the signal source using a time difference between signals received through the antenna array (AR) and a phase difference due to the time difference. In an embodiment, when the first antenna {circle around (1)} and the second antenna {circle around (2)} are in a misalign state in the x-axis direction, or when the first antenna {circle around (1)} and the third antenna {circle around (3)} are in a misalign state in the y-axis direction, in order to reduce a positioning recognition error, the electronic device **200** may be implemented to perform compensation by applying an offset value based on a misaligned distance between antennas. In an embodiment, the

positions and the number of antennas included in the antenna array (AR) may not be limited to the illustrated example and there may be various positions and numbers of antennas. In an embodiment, the antenna array (AR) may be disposed in various shapes other than the illustrated “L” shape.

(90) In an embodiment, the antenna structure **5** may include multiple antenna arrays which are formed in a manner at least partially similar to or substantially identical to that of the antenna array (AR). For example, the antenna structure **5** may include a printed circuit board (e.g., an RPCB, an FPCB, or an RFPCB) including a first antenna array and a second antenna array. In another example, the antenna structure **5** may include a printed circuit board (e.g., an RPCB, an FPCB, or an RFPCB) including a first antenna array, a second antenna array, and a third antenna array. The first antenna array and the second antenna array may be arranged in a first direction, and the first antenna array and the third antenna array may be arranged in a second direction different from the first direction. In an embodiment, the first direction may correspond to an x-axis direction, and the second direction may correspond to a y-axis direction. In another example, the antenna structure **5** may include a printed circuit board (e.g., an RPCB, an FPCB, or an RFPCB) including three or more antenna arrays.

(91) In an embodiment, the antenna structure **5** may further include another antenna array (not shown) which transmits and/or receives a signal of a frequency band that is at least partially different from that of a signal transmitted and/or received by the antenna array (AR).

(92) According to an embodiment, when a positioning function (e.g., AOA) for a signal source may not be implemented, or a design is made to include an antenna, the antenna structure **5** may be formed to include one antenna.

(93) According to an embodiment, the electronic device **200** may further include at least one another antenna structure that is substantially at least partially identical to the antenna structure **5**. For example, the antenna structure **5** and the at least another antenna structure may be arranged in the x-axis direction or the y-axis direction. For example, the antenna structure **5** and one antenna structure may be arranged in the x-axis direction, and the antenna structure **5** and the other antenna structure may be arranged in the y-axis direction. In an embodiment, the antenna structure **5** and the at least one another antenna structure may be implemented as an integrated printed circuit board (e.g., an RPCB, an FPCB, or an RFPCB). In an embodiment, when the antenna structure **5** and the at least one another antenna structure is implemented as a PCB, one connector **1040** may be formed, or connectors corresponding to the antenna structure **5** and the at least one antenna structure may be formed, respectively.

(94) In an embodiment, a wireless communication circuit (e.g., the wireless communication module **192** of FIG. **1**) may be configured to communicatively transmit and/or receive a signal of at least one selected or designated frequency band through an antenna (e.g., the first antenna {circle around (1)}, the second antenna {circle around (2)}, or the third antenna {circle around (3)}). For example, the wireless communication circuit may be configured to communicatively transmit and/or receive a first signal (or a first frequency signal) of a first frequency and a second signal (or a second frequency signal) of a second frequency different from the first frequency through an antenna (e.g., the first antenna {circle around (1)}), the second antenna {circle around (2)}, or the third antenna {circle around (3)}. In an embodiment, the multiple first antenna elements **61**, **62**, and **63** may have a first resonance frequency corresponding to the first signal, and the multiple second antenna elements **71**, **72**, and **73** may have a second resonance frequency corresponding to the second signal. For example, the frequency of the first signal may be about 8 GHZ, and the frequency of the second signal may be about 6.5 GHZ.

(95) According to an embodiment, the multiple first antenna elements **61**, **62**, and **63** may be formed to have an electrical length (e.g., a length indicated in a wavelength ratio) corresponding to a length of $\frac{1}{2}$ of a wavelength (a half wavelength) of a signal of a first frequency (e.g., about 8 GHZ) transmitted from a signal source. In an embodiment, the multiple second antenna elements

71, 72, and 73 may be formed to have an electrical length corresponding to a length of $\frac{1}{2}$ of a wavelength (a half wavelength) of a signal of a second frequency (e.g., about 6.5 GHz) transmitted from a signal source. In an embodiment, the multiple first antenna elements 61, 62, and 63 or the multiple second antenna elements 71, 72, and 73 may be formed to have an electrical length corresponding to a length of $\frac{1}{4}$ of a wavelength of a signal transmitted from a signal source.

(96) According to an embodiment, the printed circuit board 50 of the second antenna structure 5 may include a first path pattern PP1, a second path pattern PP2, or a third path pattern PP3. The first path pattern PP1, the second path pattern PP2, or the third path pattern PP3 may be included in a first conductive layer (not shown) including the multiple first antenna elements 61, 62, and 63 of multiple conductive layers of the printed circuit board 50, and a third conductive layer (not shown) including the multiple second antenna elements 71, 72, and 73 among the multiple conductive layers of the printed circuit board 50, the third conductive layer being different from a second conductive layer (not shown). The second antenna structure 5 may include a connector 1040 disposed in the second part 52 of the printed circuit board 50. The first path pattern (or a first signal line pattern) PP1 may be electrically connected to the first antenna element 61 of the first antenna {circle around (1)} through a first conductive via V1 of the printed circuit board 50. The first path pattern PP1 may be electrically connected to the connector 1040 through a fourth conductive via V4 of the printed circuit board 50. The second path pattern (or a second signal line pattern) PP2 may be electrically connected to the first antenna element 62 of the second antenna {circle around (2)} through a second conductive via V2 of the printed circuit board 50. The second path pattern PP2 may be electrically connected to the connector 1040 through a fifth conductive via V5 of the printed circuit board 50. The third path pattern (or a third signal line pattern) PP3 may be electrically connected to the first antenna element 63 of the third antenna {circle around (3)} through a third conductive via V3 of the printed circuit board 50. The third path pattern PP3 may be electrically connected to the connector 1040 through a sixth conductive via V6 of the printed circuit board 50. A first electrical path (EP1) including the first path pattern PP1, the first conductive via V1, and the fourth conductive via V4 may form a first signal line which connects the first antenna element 61 of the first antenna {circle around (1)} to the connector 1040. A second electrical path (EP2) including the second path pattern PP2, the second conductive via V2, and the fifth conductive via V5 may form a second signal line which connects the first antenna element 62 of the second antenna {circle around (2)} to the connector 1040. A third electrical path (EP3) including the third path pattern PP3, the third conductive via V3, and the sixth conductive via V6 may form a third signal line which connects the first antenna element 63 of the third antenna {circle around (3)} to the connector 1040. The wireless communication circuit (e.g., the wireless communication module 192 of FIG. 1) included in the first substrate assembly 440 may provide a radiation current (an electromagnetic signal) to the first antenna element 61 of the first antenna {circle around (1)} through the first electrical path (EP1), and the first antenna element 61 may emit a radio wave. The first antenna element 61 of the first antenna {circle around (1)} may emit an electromagnetic signal fed through the first electrical path (EP1) (e.g., a first feeding line) to the outside or receive an electromagnetic signal from the outside. The wireless communication circuit included in the first substrate assembly 440 may provide a radiation current (or an electromagnetic signal) to the first antenna element 62 of the second antenna {circle around (2)} through the second electrical path (EP2), and the first antenna element 62 of the second antenna {circle around (2)} may emit a radio wave. The first antenna element 62 of the second antenna {circle around (2)} may emit an electromagnetic signal fed through the second electrical path (EP2) (e.g., a second feeding line) to the outside, or receive an electromagnetic signal from the outside. The wireless communication circuit included in the first substrate assembly 440 may provide a radiation current (or an electromagnetic signal) to the first antenna element 63 of the third antenna {circle around (3)} through the third electrical path (EP3), and the first antenna element 63 of the third antenna {circle around (3)} may emit a radio wave. The first antenna element 63 of the third antenna {circle around (3)} may emit a radio wave. The first antenna element 63 of the third antenna {circle around (3)} may emit a radio wave.

around (3)} may emit an electromagnetic signal fed through the third electrical path (EP3) (e.g., a third feeding line) to the outside, or may receive an electromagnetic signal from the outside.

(97) According to an embodiment, the second antenna element **72** of the first antenna {circle around (1)} may include a first hole H1 (or a first opening). In an embodiment, the first conductive via V1 may be positioned to extend through the first hole H1. The second conductive layer (not shown) including the second antenna element **71** of the first antenna {circle around (1)}, among the multiple conductive layers of the printed circuit board **50** may include a first coupling conductive pattern CP1 positioned through the first hole H1. The first coupling conductive pattern CP1 may be physically separated from the second antenna element **71** of the first antenna {circle around (1)}. The first conductive via V1 may electrically connect the first antenna element **61** of the first antenna {circle around (1)} included in the first conductive layer, the first coupling conductive pattern CP1 included in the second conductive layer, and the first path pattern PP1 included in the third conductive layer. In an embodiment, due to electromagnetic coupling between the first coupling conductive pattern CP1 and the second antenna element **71** of the first antenna {circle around (1)}, the second antenna element **71** may be indirectly fed. The second antenna element **71** of the first antenna {circle around (1)} may emit an indirectly fed electromagnetic signal to the outside, or receive an electromagnetic signal from the outside. The first coupling conductive pattern CP1 and the second antenna element **71** of the first antenna {circle around (1)} may be positioned to be spaced apart from each other by a corresponding distance so as to be electromagnetically coupled to each other, based on a wavelength corresponding to a resonance frequency of the second antenna element **71**. For example, the first coupling conductive pattern CP1 and the second antenna element **71** of the first antenna {circle around (1)} may be positioned to be spaced apart from each other by a distance of about 0.2 mm to about 0.5 mm. The first coupling conductive pattern CP1 corresponds to an element which allows the second antenna element **71** of the first antenna {circle around (1)}) to be fed in an electromagnetic coupling scheme, and may be called various other terms such as a “feeding conductive pattern”. The first coupling conductive pattern CP1 may be called as a part of the first electrical path EP1, and in an embodiment, due to electromagnetic coupling between the second antenna element **71** of the first antenna {circle around (1)}) and the first electrical path EP1, the second antenna element **71** may be indirectly fed.

(98) According to an embodiment, the second antenna element **72** of the second antenna {circle around (2)} may include a second hole H2 (or a second opening). In an embodiment, the second conductive via V2 may be positioned to extend through the second hole H2. The second conductive layer (not shown) included in the second antenna element **72** of the second antenna {circle around (2)}, among the multiple conductive layers of the printed circuit board **50** may include a second coupling conductive pattern CP2 positioned through the second hole H2. The second coupling conductive pattern CP2 may be physically separated from the second antenna element **72** of the second antenna {circle around (2)}. The second conductive via V2 may be electrically connected to the first antenna element **62** of the second antenna {circle around (2)} included in the first conductive layer, the second coupling conductive pattern CP2 included in the second conductive layer, and the second path pattern PP2 included in the third conductive layer. In an embodiment, due to electromagnetic coupling between the second coupling conductive pattern CP2 and the second antenna element **72** of the second antenna {circle around (2)}, the second antenna element **72** may be indirectly fed. The second antenna element **72** of the second antenna {circle around (2)} may emit an indirectly fed electromagnetic signal to the outside, or receive an electromagnetic signal from the outside. The second coupling conductive pattern CP2 may be called as a part of the second electrical path EP2, and in an embodiment, due to electromagnetic coupling between the second antenna element **72** of the second antenna {circle around (2)} and the second electrical path EP2, the second antenna element **72** may be indirectly fed.

(99) According to an embodiment, the second antenna element **73** of the third antenna {circle

around (3)} may include a third hole H3 (or a third opening). The third conductive via V3 may be positioned to extend through the third hole H3. The second conductive layer (not shown) included in the second antenna element 73 of the third antenna {circle around (3)}, among the multiple conductive layers of the printed circuit board 50, may include a third coupling conductive pattern CP3 positioned through the third hole H3. The third coupling conductive pattern CP3 may be physically separated from the second antenna element 73 of the third antenna {circle around (3)}. The third conductive via V3 may be electrically connected to the first antenna element 63 of the third antenna {circle around (3)} included in the first conductive layer, the third coupling conductive pattern CP3 included in the second conductive layer, and the third path pattern PP3 included in the third conductive layer. In an embodiment, due to electromagnetic coupling between the third coupling conductive pattern CP3 and the second antenna element 73 of the third antenna {circle around (3)}, the second antenna element 73 may be indirectly fed. The second antenna element 73 of the third antenna {circle around (3)} may emit an indirectly fed electromagnetic signal to the outside, or receive an electromagnetic signal from the outside. The third coupling conductive pattern CP3 may be called as a part of the third conductive path EP3, and in an embodiment, due to electromagnetic coupling between the second antenna element 73 of the third antenna {circle around (3)} and the third electrical path EP3, the second antenna element 73 may be indirectly fed.

(100) According to an embodiment, the first hole H1 may be a circle having a radius when seen from above the rear plate 320 (e.g., when seen in the +z axis-direction). For example, the first coupling conductive pattern CP1 may be a circular corresponding to the circular first hole H1 when seen from above the rear plate 320. When seen from above the rear plate 320, a circular slot may be formed between the first coupling conductive pattern CP1 and the second antenna element 71 of the first antenna {circle around (1)}. In an embodiment, the first hole H1 or the first coupling conductive pattern CP1 corresponding to the first hole H1 may not be limited to the illustrated example, and may have various other shapes (e.g., an oval shape or a polygonal shape). For example, the first hole H1 may have a circular shape, an oval shape, or a polygonal shape, and the first coupling conductive pattern CP1 may have a circular shape, an oval shape, or a polygonal shape. The second hole H2 or the third hole H3 may be formed to have substantially the same shape as the first hole H1. The second coupling conductive pattern CP2 or the third coupling conductive pattern CP3 may be formed to have substantially the same shape as the first coupling conductive pattern CP1.

(101) According to an embodiment, the second antenna element 71 of the first antenna {circle around (1)} may be implemented to be indirectly fed by the first conductive via V1 without the first coupling conductive pattern CP1. In the same manner, the second antenna element 72 of second antenna {circle around (2)} may be implemented to be indirectly fed by the second conductive via V2 without the second coupling conductive pattern CP2. In the same manner, the second antenna element 73 of the third antenna {circle around (3)} may be implemented to be indirectly fed by the third conductive via V3 without the third coupling conductive pattern CP3.

(102) According to an embodiment, the first coupling conductive pattern CP1 may be defined as a part of the first conductive via V1 or a part of a first via structure for the first conductive via V1, and in this case, the second antenna element 71 of the first antenna {circle around (1)} may be indirectly fed by the first conductive via V1. In the same manner, the second coupling conductive pattern CP2 may be defined as a part of the second conductive via V2 or a part of a second via structure for the second conductive via V2, and in this case, the second antenna element 72 of the second antenna {circle around (2)} may be indirectly fed by the second conductive via V2. In the same manner, the third coupling conductive pattern CP3 may be defined as a part of the third conductive via V3 or as a part of a third via structure for the third conductive via V3, and in this case, the second antenna element 73 of the third antenna {circle around (3)} may be indirectly fed by the third conductive via V3.

(103) FIG. 8 is a diagram illustrating a first antenna {circle around (1)} including a first antenna element **61** and a second antenna element **71** according to various embodiments.

(104) Referring to FIG. 8, in an embodiment, when seen on an x-y plane (e.g., when seen in the +z axis direction in FIG. 5), the first antenna element **61** of the first antenna {circle around (1)} may include a first border **811**, a second border **812**, a third border **813**, or a fourth border **814**. For example, the first border **811** and the third border **813** may be positioned to be spaced from each other and substantially extend in parallel to each other in the x-axis direction. For example, the second border **812** and the fourth border **814** may be positioned to be spaced from each other and substantially extend in parallel to each other in the y-axis direction. The first border **811** and the third border **813** may be substantially perpendicular to the second border **812** and the fourth border **814**. In an embodiment, the distance between the first border **811** and the third border **813** may be substantially identical to the distance between the second border **812** and the fourth border **814**. In an embodiment, the first antenna element **61** of the first antenna {circle around (1)} may include multiple first notches (or slits) **N11**, **N12**, **N13**, and **N14**. The multiple first notches **N11**, **N12**, **N13**, and **N14** may include a (1-1)th notch **N11** formed on the first border **811**, a (1-2)th notch **N12** formed on the second border **812**, a (1-3)th notch **N13** formed on the third border **813**, and a (1-4)th notch **N14** formed on the fourth border **814**. In an embodiment, the multiple first notches **N11**, **N12**, **N13**, and **N14** may include substantially the same rectangular shape. The (1-1).sup.th notch **N11** formed on the first border **811** corresponds to a recessed opening on the first border **811**, and may have a first width **W1** formed in the y-axis direction and a second width **W2** formed in the x-axis direction. The (1-2).sup.th notch **N12** formed on the second border **812** corresponds to a recessed opening on the second border **812**, and may have a first width **W1** formed in the x-axis direction and a second width **W2** formed in the y-axis direction. The (1-3).sup.th notch **N13** formed on the third border **813** corresponds to a recessed opening on the third border **813**, and may have a first width **W1** formed in the y-axis direction and a second width **W2** formed in the x-axis direction. The (1-4).sup.th notch **N14** formed on the fourth border **814** corresponds to a recessed opening on the fourth border **814**, and may have a first width **W1** formed in the x-axis direction and a second width **W2** formed in the y-axis direction. In an embodiment, the (1-1).sup.th notch **N11** formed on the first border **811** and the (1-3).sup.th notch **N13** formed on the third border **813** may be formed to be substantially symmetrical to each other with reference to the center **C1** of the first antenna element **61** when seen from the x-y plane. The center **C1** may indicate, for example, a point on the first antenna element **61**, which has substantially the same distance from the first border **811**, the second border **812**, the third border **813**, and the fourth border **814**. In an embodiment, the (1-2).sup.th notch **N12** formed on the second border **812** and the (1-4).sup.th notch **N14** formed on the fourth border **814** may be formed to be substantially symmetrical to each other with reference to the center **C1** of the first antenna element **61** when seen from the x-y plane. In an embodiment, the multiple first notches **N11**, **N12**, **N13**, and **N14** may be arranged substantially at a 90-degree angle with reference to the center **C1** of the first antenna element **61** when seen from the x-y plane.

(105) According to an embodiment, when seen on the x-y plane (e.g., when seen in the + % axis direction in FIG. 5), the second antenna element **71** of the first antenna {circle around (1)} may include may include a fifth border **815**, a sixth border **816**, a seventh border **817**, or an eighth border **818**. For example, the fifth border **815** and the seventh border **817** may be positioned to be spaced from each other and substantially extend in parallel to each other in the x-axis direction. For example, the sixth border **816** and the eighth border **818** may be positioned to be spaced from each other and substantially extend in parallel to each other in the y-axis direction. In an embodiment, when seen on the x-y plane, the fifth border **815**, the sixth border **816**, the seventh border **817**, and the eighth border **818** may be positioned to be spaced apart from each other by substantially the same distance with reference to the center **C1** of the first antenna element **61**. For example, the distance between the fifth border **815** and the seventh border **817** may be substantially identical to

the distance between the sixth border **816** and the eighth border **818**. In an embodiment, the second antenna element **71** of the first antenna {circle around (1)} may include multiple second notches (or second slits) **N21**, **N22**, **N23**, and **N24**. The multiple second notches **N21**, **N22**, **N23**, and **N24** may include a (2-1).sup.th notch **N21** formed on the fifth border **815**, a (2-2).sup.th notch **N22** formed on the sixth border **816**, a (2-3).sup.th notch **N23** formed on the seventh border **817**, and a (2-4).sup.th notch **N24** formed on the eighth border **818**. In an embodiment, the multiple second notches **N21**, **N22**, **N23**, and **N24** may include substantially the same rectangular shape. The (2-1).sup.th notch **N21** formed on the fifth border **815** corresponds to a recessed opening on the fifth border **815**, and may have a third width **W3** formed in the y-axis direction and a fourth width **W4** formed in the x-axis direction. The (2-2).sup.th notch **N22** formed on the sixth border **816** corresponds to a recessed opening on the sixth border **816**, and may have a third width **W3** formed in the x-axis direction and a fourth width **W4** formed in the y-axis direction. The (2-3).sup.th notch **N23** formed on the seventh border **817** corresponds to a recessed opening on the seventh border **817**, and may have a third width **W3** formed in the y-axis direction and a fourth width **W4** formed in the x-axis direction. The (2-4).sup.th notch **N24** formed on the eighth border **818** corresponds to a recessed opening on the eighth border **818**, and may have a third width **W3** formed in the x-axis direction and a fourth width **W4** formed in the y-axis direction. In an embodiment, the (2-1).sup.th notch **N21** formed on the fifth border **815** and the (2-3).sup.th notch **N23** formed on the seventh border **817** may be formed to be substantially symmetrical to each other with reference to the center **C1** of the first antenna element **61** when seen from the x-y plane. In an embodiment, the (2-2).sup.th notch **N22** formed on the sixth border **816** and the (2-4).sup.th notch **N24** formed on the eighth border **818** may be formed to be substantially symmetrical to each other with reference to the center **C1** of the first antenna element **61** when seen from the x-y plane. In an embodiment, the multiple second notches **N21**, **N22**, **N23**, and **N24** may be arranged substantially at a 90-degree angle with reference to the center **C1** of the first antenna element **61** when seen from the x-y plane. For example, the center of the second antenna element **71** may substantially overlap with the center **C1** of the first antenna element **61** when seen on the x-y plane.

(106) According to an embodiment, when seen on the x-y plane (e.g., when seen in the + % axis direction in FIG. 5), the first border **811**, the second border **812**, the third border **813**, or the fourth border **814** of the first antenna element **61** included in the first antenna {circle around (1)} may be positioned to be spaced apart from the center **C1** of the first antenna element **61** by a first distance **L1**. When seen on the x-y plane, the fifth border **815**, the sixth border **816**, the seventh border **817**, or the eighth border **818** of the second antenna element **71** included in the first antenna {circle around (1)} may be positioned to be spaced apart from the center **C1** of the first antenna element **61** by a second distance **L2** that is greater than the first distance **L1**. In an embodiment, the first distance **L1** and the second distance **L2** may be implemented to be substantially identical to each other. In an embodiment, the first distance **L1** may be implemented to be greater than the second distance **L2**.

(107) According to an embodiment, when seen on the x-y plane (e.g., when seen in the + % axis direction in FIG. 5), the multiple first notches **N11**, **N12**, **N13**, and **N14** overlap with the multiple second notches **N21**, **N22**, **N23**, and **N24** one-to-one. In an embodiment, a structure in which when seen from the x-y plane, the multiple first notches **N11**, **N12**, **N13**, and **N14** overlap with the multiple second notches **N21**, **N22**, **N23**, and **N24** one-to-one may contribute so that the multiple first antenna elements **61**, **62**, and **63** and the multiple second antenna elements **71**, **72**, and **73** can be divided and used for each use frequency. In an embodiment, a structure in which when seen from the x-y plane, the multiple first notches **N11**, **N12**, **N13**, and **N14** overlap with the multiple second notches **N21**, **N22**, **N23**, and **N24** one-to-one may contribute so that an internal electric field of the second antenna structure **5** forms both a transverse magnetic (TM) **01** mode and a TM₁₀ mode each corresponding to a basic mode of a patch antenna.

(108) According to an embodiment, according to the shapes of the multiple first notches **N11**, **N12**,

N13, and N14, a resonance characteristic (e.g., a response frequency) of the first antenna element 61 included in the first antenna {circle around (1)} may vary. For example, according to the first width W1 or the second width W2, a resonance characteristic (e.g., a response frequency) of the first antenna element 61 included in the first antenna {circle around (1)} may vary. In an embodiment, according to the shapes of the multiple second notches N21, N22, N23, and N24, a resonance characteristic (e.g., a response frequency) of the second antenna element 71 included in the first antenna {circle around (1)} may vary. For example, according to the third width W3 or the fourth width W4, a resonance characteristic (e.g., a response frequency) of the second antenna element 71 included in the first antenna {circle around (1)} may vary.

(109) According to an embodiment, the multiple first notches N11, N12, N13, and N14 may have different shapes from those of the multiple second notches N21, N22, N23, and N24, and accordingly, a resonance frequency of the first antenna element 61 included in the first antenna {circle around (1)} may be different from a resonance frequency of the second antenna element 71 included in the first antenna {circle around (1)}. As shown in FIG. 8, the first width W1 may be different from the third width W3, and the second width W2 may be different from the fourth width W4. In an embodiment, the first width W1 may be smaller than the third width W3, and the second width W2 may be greater than the fourth width W4. For example, the first width W1 may have a value equal to or lower than about 0.5 mm, and the third width W3 may have a value equal to or lower than about 5 mm greater than the first width W1. In an embodiment, the first width W1 and the third width W3 may be substantially identical to each other, and the second width W2 and the fourth width W4 may be different from each other. In an embodiment, the first width W1 and the third width W3 may be different from each other, and the second width W2 and the fourth width W4 may be substantially identical to each other.

(110) According to an embodiment, the shapes of the multiple first notches N11, N12, N13, and N14 or the shapes of the multiple second notches N21, N22, N23, and N24 may not be limited to the illustrated rectangular shape, and may be implemented in various different shapes. In an embodiment, the shapes of the multiple first notches N11, N12, N13, and N14 or the shapes of the multiple second notches N21, N22, N23, and N24 may include a shape in which both sides are symmetrical to each other, for example, an isosceles trapezoid or a circular shape.

(111) According to an embodiment, the first antenna element 61 of the first antenna {circle around (1)} may include, when seen on the x-y plane (e.g., when seen in the +z axis direction in FIG. 5), a first chamfer CH1 formed at a part at which the second border 812 and the third border 813 are connected. The first chamfer CH1 may indicate a diagonal border for connecting the second border 812 and the third border 813. The first antenna element 61 of the first antenna {circle around (1)} may include, when seen on the x-y plane, a second chamfer CH2 formed at a part at which the first border 811 and the fourth border 814 are connected. The second chamfer CH2 may indicate a diagonal border for connecting the first border 811 and the fourth border 814. In an embodiment, the first chamfer CH1 may be called a first truncated corner, and the second chamfer CH2 may be called a second truncated corner. In an embodiment, the first chamfer CH1 and the second chamfer CH2 may be formed to be substantially symmetrical to each other with reference to the center C1 of the first antenna element 61. For example, the first chamfer CH1 may form a first angle of about 45 degrees with respect to the second border 812 or the third border 813, and the second chamfer CH2 may form a second angle of about 45 degrees with respect to the first border 811 or the fourth border 814. In an embodiment, the first antenna element 61 of the first antenna {circle around (1)} may substantially form circular polarization by the first chamfer CH1 and the second chamfer CH2. The first chamfer CH1 and the second chamfer CH2 formed at two corners, respectively, the two corners being positioned at opposite sides in a diagonal direction, may contribute so that the first antenna element 61 of the first antenna {circle around (1)} may form circular polarization. In an embodiment, the first angle and the second angle may be formed as an angle that is different from that in the illustrated example.

(112) According to an embodiment, the second antenna element **71** of the first antenna {circle around (1)} may include, when seen on the x-y plane (e.g., when seen in the +z axis direction in FIG. 5), a third chamfer **CH3** formed at a part at which the sixth border **816** and the seventh border **817** are connected. The third chamfer **CH3** may indicate a diagonal border for connecting the sixth border **816** and the seventh border **817**. The second antenna element **71** of the first antenna {circle around (1)} may include, when seen on the x-y plane, a fourth chamfer **CH4** formed at a part at which the fifth border **815** and the eighth border **818** are connected. The fourth chamfer **CH4** may indicate a diagonal border for connecting the fifth border **815** and the eighth border **818**. In an embodiment, the third chamfer **CH3** may be called a third truncated corner, and the fourth chamfer **CH4** may be called a fourth truncated corner. In an embodiment, the third chamfer **CH3** and the fourth chamfer **CH4** may be formed to be substantially symmetrical to each other with reference to the center **C1** of the first antenna element **61**. In an embodiment, the first chamfer **CH1** and the third chamfer **CH3** may be substantially parallel to each other, and the second chamfer **CH2** and the fourth chamfer **CH4** may be substantially parallel to each other. For example, the third chamfer **CH3** may form a first angle of about 45 degrees with respect to the sixth border **816** or the seventh border **817**, and the fourth chamfer **CH4** may form a second angle of about 45 degrees with respect to the fifth border **815** or the eighth border **818**. When seen on the x-y plane, the third chamfer **CH3** may be formed not to overlap with the first chamfer **CH1**, or in an embodiment, may be formed to overlap with the first chamfer **CH1**. When seen on the x-y plane, the fourth chamfer **CH4** may be formed not to overlap with the second chamfer **CH2**, or in an embodiment, may be formed to overlap with the second chamfer **CH2**. In an embodiment, the second antenna element **71** of the first antenna {circle around (1)} may substantially form circular polarization by the third chamfer **CH3** and the fourth chamfer **CH4**. The third chamfer **CH3** and the fourth chamfer **CH4** formed at two corners, respectively, the two corners being positioned at opposite sides in a diagonal direction, may contribute so that the second antenna element **71** of the first antenna {circle around (1)} may form circular polarization.

(113) According to an embodiment, a first feeding structure **801** including the first hole **H1**, the first coupling conductive pattern **CP1**, and the first conductive via **V1** of the first antenna element **61** included in the first antenna {circle around (1)} may be positioned between the center **C1** of the first antenna element **61** and the (1-1).sup.th notch **N11** formed on the first border **811** when seen from the x-y plane (e.g., when seen in the +z axis direction in FIG. 5). In an embodiment, the first feeding structure **801** may be closer to the (1-1).sup.th notch **N11** than the center **C1** of the first antenna element **61**. When the first feeding structure **801** is formed to be closer to the (1-1).sup.th notch **N11** than the center **C1** of the first antenna element **61**, the second antenna structure **5** may have impedance reducing a power loss in a dual band. In an embodiment, the first conductive via **V1** may be positioned to be spaced apart from the center **C1** of the first antenna element **61** by about 3 mm when seen on the x-y plane. In an embodiment, the (2-1).sup.th notch **N21** formed on the fifth border **815** may not substantially overlap with the first feeding structure **801** when seen on the x-y plane.

(114) According to an embodiment, the first antenna element **62** and the second antenna element **72** of the second antenna {circle around (2)} may be formed in substantially the same manner as the first antenna element **61** and the second antenna element **71** included in the first antenna {circle around (1)} according to an embodiment of FIG. 7, and for example, may be implemented to include the multiple borders **811**, **812**, **813**, **814**, **815**, **816**, **817**, and **818**, the multiple first notches **N11**, **N12**, **N13**, and **N14**, the multiple second notches **N21**, **N22**, **N23**, and **N24**, and the multiple chamfers **CH1**, **CH2**, **CH3**, and **CH4**. In an embodiment (see FIG. 7), when seen on the x-y plane (e.g., when seen in the +z axis direction in FIG. 5), a second feeding structure including the second hole **H2**, the second coupling conductive pattern **CP2**, and the second conductive via **V2** of the first antenna element **62** included in the second antenna {circle around (2)} may be positioned between the center of the first antenna element **62** and the (1-3).sup.th notch **N11** formed on the third border

813. For example, the second feeding structure may be closer to the first notch **N11** formed on the third border **813** than the center of the first antenna element **62** included in the second antenna {circle around (2)}.

(115) According to an embodiment, the first antenna element **63** and the second antenna element **73** included in the third antenna {circle around (3)} may be formed in substantially the same manner as the first antenna element **61** and the second antenna element **71** included in the first antenna {circle around (1)} according to an embodiment of FIG. 7, and for example, may be implemented to include the multiple borders **811**, **812**, **813**, **814**, **815**, **816**, **817**, and **818**, the multiple first notches **N11**, **N12**, **N13**, and **N14**, the multiple second notches **N21**, **N22**, **N23**, and **N24**, and the multiple chamfers **CH1**, **CH2**, **CH3**, and **CH4**. In an embodiment (see FIG. 7), when seen on the x-y plane (e.g., when seen in the +z axis direction in FIG. 5), a third feeding structure including the third hole **H3**, the third coupling conductive pattern **CP3**, and the third conductive via **V3** of the first antenna element **63** included in the third antenna {circle around (3)} may be positioned between the center of the first antenna element **63** and the first notch **N11** formed on the first border **811**. For example, the third feeding structure may be closer to the first notch **N11** formed on the first border **811** than the center of the first antenna element **63** included in the third antenna {circle around (3)}.

(116) According to an embodiment, when seen on the x-y plane (e.g., when seen in the +z axis direction in FIG. 5), the distance between centers of two first antenna elements **61** and **62** (see FIG. 7) arranged in the x-axis direction, or the distance between centers of two first antenna elements **61** and **63** (see FIG. 7) arranged in the y-axis direction may be formed as a $\frac{1}{2}$ length (a half wavelength) or a $\frac{1}{4}$ length of a wavelength of a first frequency signal transmitted from a signal source. In an embodiment, when seen on the x-y plane, the distance between centers of two second antenna elements **71** and **72** (see FIG. 7) arranged in the x-axis direction, or the distance between two second antenna elements **71** and **73** (see FIG. 7) arranged in the y-axis direction may be formed as a $\frac{1}{2}$ length (a half wavelength) or a $\frac{1}{4}$ length of a wavelength of a second frequency signal transmitted from a signal source. For example, when seen on the x-y plane, the distance between centers of two first antenna elements **61** and **62** (see FIG. 7) arranged in the x-axis direction, the distance between centers of two first antenna elements **61** and **63** (see FIG. 7) arranged in the y-axis direction, the distance between centers of two second antenna elements **71** and **72** arranged in the x-axis direction, or the distance between two second antenna elements **71** and **73** (see FIG. 7) arranged in the y-axis direction may be about 12 mm to about 20 mm.

(117) FIG. 9 is a cross-sectional view **900** of an x-z plane of a second antenna structure **5** taken along line A-A' in FIG. 7 according to various embodiments. FIG. 10 is a cross-sectional view **1000** of an x-z plane of a second antenna structure **5** taken along line B-B' in FIG. 7 according to various embodiments.

(118) Referring to FIGS. 7, 9, and 10, in an embodiment, the second part **52** of the printed circuit board **50** may have flexibility greater than that of the first part **51** of the printed circuit board **50**. The second part **52** may have a bending characteristic (e.g., flexibility) which allows bending without damage while reducing occurrence of stress in the same condition, compared to the first part **51**. In an embodiment, the first part **51** and the second part **52** may be substantially flexible, and the second part **52** may have flexibility greater than that of the first part **51**. For example, the second part **52** may have a thinner thickness or a smaller number of laminates than the first part **51**, and accordingly, may be implemented to be more flexible than the first part **51**. In another example, the second part **52** may include materials different from those of the first part **51** and may be implemented to be more rigid than the first part **51**. In an embodiment, the second part **52** may correspond to a substantially flexible part (or a flexible interval) of the printed circuit board **50**, and the first part **51** may correspond to substantially rigid parts (or rigid intervals) of the printed circuit board **50**. The printed circuit board **50** may be formed by including a flexible part and a rigid part or other parts having flexibility using various other structures.

(119) According to an embodiment, the printed circuit board **50** included in the second antenna structure **5** may include a first surface **501** and a second surface **502** oriented in a direction opposite to the first surface **501**. The first surface **501** may face, for example, the rear plate **320** (see FIG. **4** or **5**). In an embodiment, a first thickness between the first surface **501** and the second surface **502** in the first part **51** of the printed circuit board **50** may be greater than the second thickness between the first surface **501** and the second surface **502** in the second part **52** of the printed circuit board **50**. The first part **51** of the printed circuit board **50** may include more laminates than the second part **52** of the printed circuit board **50**, and may have the first thickness that is thicker than the second thickness of the second part **52**. In an embodiment, there may be a height difference between a first area **5011** included in the first part **51** of the first surface **501** and a second area **5012** included in the second part **52** of the first surface **501** due to a thickness difference between the first part **51** and the second part **52**.

(120) According to an embodiment, the printed circuit board **50** may include a first dielectric **D1**, a second dielectric **D2**, a third dielectric **D3**, a fourth dielectric **D4**, a fifth dielectric **D5**, a first conductive layer **910**, a second conductive layer **920**, a third conductive layer **930**, a fourth conductive layer **940**, a first surface protection layer **1010**, a second surface protection layer **1020**, a connector **1040**, or a reinforcing member **1030**.

(121) According to an embodiment, the first dielectric **D1**, the second dielectric **D2**, the third dielectric **D3**, and the fourth dielectric **D4** may be positioned in the first part **51** of the printed circuit board **50**. The fifth dielectric **D5** may extend from the first part **51** to the second part **52**. The fourth dielectric **D4** may be closest to the first surface **501** among the multiple dielectrics **D1**, **D2**, **D3**, **D4**, and **D5**, and the fifth dielectric **D5** may be closest to the second surface **502** among the multiple dielectrics **D1**, **D2**, **D3**, **D4**, and **D5**. The first dielectric **D1** may be positioned between the third dielectric **D3** and the fourth dielectric **D4**. The third dielectric **D3** may be positioned between the first dielectric **D1** and the second dielectric **D2**. The second dielectric **D2** may be positioned between the third dielectric **D3** and the fifth dielectric **D5**. The first dielectric **D1**, the second dielectric **D2**, the third dielectric **D3**, the fourth dielectric **D4**, or the fifth dielectric **D5** may include various insulation materials or a non-conductive material.

(122) According to an embodiment, the first conductive layer **910** may be positioned to be closest to the first surface **501** among conductive layers included in the first part **51** of the printed circuit board **50**. The first conductive layer **910** may be disposed on the fourth dielectric **D4**. For example, the first conductive layer **910** may be positioned on a surface of the fourth dielectric **D4**, the surface being opposite to a surface facing the first dielectric **D1**. The second conductive layer **920** may be positioned between the second dielectric **D2** and the third dielectric **D3**. The third conductive layer **930** may be positioned between the second dielectric **D2** and the fifth dielectric **D5**. The fourth conductive layer **940** may be positioned to be closest to the second surface **502** among conductive layers included in the printed circuit board **50**. The fourth conductive layer **940** may be positioned on the fifth dielectric **D5**. For example, the fourth conductive layer **940** may be disposed on a surface of the fifth dielectric **D5**, the surface being opposite to a surface facing the second dielectric **D2**. In an embodiment, the first conductive layer **910** may include multiple first antenna elements **61**, **62**, and **63**. In an embodiment, the second conductive layer **920** may include the multiple second antenna elements **71**, **72**, and **73**, the first coupling conductive pattern **CP1**, the second coupling conductive pattern **CP2**, and/or the third coupling conductive pattern **CP3**. In an embodiment, the third conductive layer **930** may include the first path pattern **PP1**, the second path pattern **PP2**, and/or the third path pattern **PP3**. The third conductive layer **930** may include, for example, a part of a first signal line between the connector **1040** and the first antenna element **61** of the first antenna {circle around (1)}, a part of a second signal line between the connector **1040** and the first antenna element **62** of the second antenna {circle around (2)}, and/or a part of a third signal line between the connector **1040** and the first antenna element **63** of the third antenna {circle around (3)}. In an embodiment, the third conductive layer **930** and the fourth conductive layer **940**

may form a coplanar waveguide (CPW) for transferring a frequency signal.

(123) According to an embodiment, at least a part of the fourth conductive layer **940** may be utilized as a ground plane G. The ground plane G included in the fourth conductive layer **940** may reduce an electromagnetic effect (e.g., electromagnetic interference (EMI)) to a circuit (or a circuit pattern) of the printed circuit board **50**. For example, the ground plane G included in the fourth conductive layer **940** may reduce an effect on a circuit of the printed circuit board **50**, the effect being exerted by external electromagnetic noise toward the second surface **502**. For example, the ground plane G included in the fourth conductive layer **940** may reduce an effect on an electrical element around the printed circuit board **50**, the effect being exerted by an electromagnetic field generated when a current flows through the circuit of the printed circuit **50**.

(124) According to an embodiment, at least a part of the printed circuit board **50** may be formed using, for example, a flexible copper clad laminate (FCCL). The flexible copper clad laminate corresponds to a laminate used for a printed circuit, and may include a structure in which copper clad is attached to one side or opposite sides of an insulation film (or a dielectric film) having flexibility using an adhesive material (e.g., an acrylic adhesive). The insulation film having flexibility may include, for example, various non-conductive materials such as a polyimide film or a polyester film. For example, a flexible printed circuit board may be processed through a series of processes such as circuit printing, etching, and resist peeling, so that a laminate structure including a dielectric and a conductive layer disposed on one surface and/or the other surface of the dielectric can be formed. In an embodiment, the first conductive layer **910** and the fourth dielectric **D4** may be formed using the flexible copper clad laminate. In an embodiment, the second conductive layer **920** and the third dielectric **D3** may be formed using the flexible copper clad laminate. In an embodiment, the third conductive layer **930**, the fourth conductive layer **940**, and the fifth dielectric **D5** may be formed using the flexible copper clad laminate. In an embodiment, the third dielectric **D3**, the fourth dielectric **D4**, and/or the fifth dielectric **D5** corresponds to an insulation film (a dielectric film) based on the flexible copper clad laminate, and may include, for example, prepreg (pre-impregnated materials) (e.g., an insulation resin layer). The prepreg may be, for example, a material obtained by impregnating liquid synthetic resin into a fabric enhancer (e.g., a reinforcing base material) such as carbon fiber or glass fiber. In an embodiment, the third dielectric **D3**, the fourth dielectric **D4**, and/or the fifth dielectric **D5** may further include a reinforcing base material such as paper or nonwoven glass fabric, and the reinforcing base material may increase intensity (e.g., longitudinal/traverse directional intensity) of a dielectric, which may be insufficient only with resin, or may reduce a temperature dimensional change ratio. In another example, the prepreg may include a thermosetting resin system such as phenol resin or epoxy resin, and a thermoplastic resin system such as polyetherkethone. In an embodiment, the prepreg may include unidirectional prepreg and cloth prepreg.

(125) According to an embodiment, the fifth dielectric **D5** may include a material capable of securing flexibility of the second part **52** of the printed circuit board **50**.

(126) According to an embodiment, the first dielectric **D1** may include a first non-conductive adhesive material for coupling (or bonding) the third dielectric **D3** and the fourth dielectric **D4**. The second dielectric **D2** may include a second non-conductive adhesive material for coupling (or bonding) the third dielectric **D3** and the fifth dielectric **D5**. The first dielectric **D1** or the second dielectric **D2** may include, for example, an acryl-based or an epoxy-based non-conductive adhesive material. The first dielectric **D1** or the second dielectric **D2** may include, for example, a flexible polymer adhesive material.

(127) According to an embodiment, the first surface protection layer **1010** and the second surface protection layer **1020** may play a role of protecting a circuit (or a circuit pattern) of the printed circuit board **50**, and may include, for example, an insulation layer or a non-conductive layer. The first surface protection layer **1010** may form at least a part of the first surface **501** of the printed circuit board **50**, and the second surface protection layer **1020** may form at least a part of the

second surface **502** of the printed circuit board **50**. In an embodiment, the first surface protection layer **1010** or the second surface protection layer **1020** may be called a “coverlay”. The first surface protection layer **1010** or the second surface protection layer **1020** may include, for example, various insulation materials such as epoxy component solder mask insulation ink (e.g., photo-imageable solder resist (PSR) ink (PSR mask ink)). In an embodiment, the first surface protection layer **1010** may include an electromagnetic shield composition (or an electromagnetic wave shield composition), and in this case, may be positioned, when seen in the +z axis direction, not to overlap the multiple first antenna elements **61**, **62**, and **63** and the multiple second antenna elements **71**, **72**, and **73**.

(128) According to an embodiment, the connector **1040** may be disposed at the second part **52** of the printed circuit board **50**. The connector **1040** may be positioned on the second surface **502** of the printed circuit board **50**. The fourth conductive layer **940** may include a third terminal pattern TP electrically connected to the third path pattern PP3 of the first conductive layer **910** through the sixth conductive via V6. The fourth conductive layer **940** may include a first terminal pattern (not shown) electrically connected to the first path pattern PP1 of the first conductive layer **910** through the fourth conductive via V4. The fourth conductive layer **940** may include a second terminal pattern (not shown) electrically connected to the second path pattern PP2 of the first conductive layer **910** through the fifth conductive via V5. The first terminal pattern, the second terminal pattern, and the third terminal pattern (TP) may be arranged to be physically separated from one another. The first terminal pattern, the second terminal pattern, and the third terminal pattern TP may be arranged to be physically separated from the ground plane G included in the fourth conductive layer **940**. The first terminal pattern, the second terminal pattern, and the third terminal pattern TP may be electrically or mechanically connected to the connector **1040** using a conductive adhesive material **1041** such as solder. The first terminal pattern, the second terminal pattern, and the third terminal pattern TP correspond parts for connection to the connector **1040** using a conductive adhesive material, and may be called, in an embodiment, a “conductive pad” or a “land”. In an embodiment, the second part **62** of the printed circuit board **50** may be inserted into a connector included in the first substrate assembly **440**, without the connector **1040**, so as to be electrically connected to the first substrate assembly **440**. In an embodiment, the second part **62** of the printed circuit board **50** may be electrically connected to the first substrate assembly **440** (see FIG. 6) using a conductive adhesive material such as solder, without the connector **1040**.

(129) According to an embodiment, the ground plane G of the fourth conductive layer **940** may be electrically connected to the connector **1040**. The ground plane G of the fourth conductive layer **940** may be electrically connected to a ground structure (e.g., a ground plane) included in the first substrate assembly **440** through the connector **1040**.

(130) According to an embodiment, the reinforcing member **1030** may be disposed in the second part **52** of the printed circuit board **50** to correspond to the connector **1040**. The reinforcing member **1030** may be disposed, when seen from above the first surface **501** of the printed circuit board **50**, on the first surface **502** to at least partially overlap the connector **1040**. The reinforcing member **1030** may be positioned between the second part **52** of the printed circuit board **50** and the rear plate **320** (see FIG. 4 or 5) to press the connector **1040** toward the first substrate assembly **440** so that a connection between the connector **1040** and the first substrate assembly **440** is maintained. In an embodiment, the reinforcing member **1030** may include a non-conductive material (e.g., polymer) or a metal material. In an embodiment, the reinforcing member **1030** may be substantially rigid, and may include, for example, a stiffener such as a reinforcing plate. In an embodiment, the reinforcing member **1030** may have a dielectric constant (e.g., a low dielectric constant) for reducing an electromagnetic effect exerted on the circuit board **50**. In an embodiment, the reinforcing member **1030** may include a flexible material, or may be replaced with a flexible member.

(131) According to an embodiment, the second antenna structure **5** may have directivity which

allows electromagnetic waves to be concentrated in a direction (e.g., -z axis direction) to the rear surface **300B** of the electronic device **200** (see FIG. 3), or allows transmission or reception of waves. The first antenna {circle around (1)}, the second antenna {circle around (2)}, and the third antenna {circle around (3)} illustrated in FIG. 7 may form a beam pattern (or an antenna radiation pattern). The beam pattern may correspond to a valid area in which a signal can be emitted or detected. The beam pattern may include, for example, a main beam (or a main lobe) formed in a maximum radiation direction (boresight). The main beam may indicate a beam through which a relatively large amount of energy is emitted, and the first antenna {circle around (1)}, the second antenna {circle around (2)}, and the third antenna {circle around (3)} may form a main beam substantially in a direction (e.g., -z axis direction) to the rear surface **300B** of the electronic device **200** (see FIG. 3). A ground plane (or a ground layer) included in the fourth conductive layer **940** may contribute so that, in an embodiment, a beam for irradiating a relatively large amount of energy is formed substantially in a direction to the rear surface **300B** of the electronic device **200** (see FIG. 3) through the first antenna {circle around (1)}, the second antenna {circle around (2)}, and the third antenna {circle around (3)}.

(132) According to an embodiment, a dielectric constant, a dielectric loss, and/or a z-axis direction thickness of a dielectric (e.g., the first dielectric **D1**, the third dielectric **D3**, and/or the fourth dielectric **D4**) between the first conductive layer **910** and the second conductive layer **920** may correspond to conditions to be considered when the multiple first antenna elements **61**, **62**, and **63** are implemented. For example, when the multiple first antenna elements **61**, **62**, and **63** are implemented so that a first signal of a selected or designated first frequency band is transmitted and/or received while reducing a loss, or antenna radiation efficiency is secured, a dielectric constant, a dielectric loss, and/or a z-axis direction thickness of the first dielectric **D1**, the third dielectric **D3**, or the fourth dielectric **D4** may be considered. For example, the shapes of the multiple first antenna elements **61**, **62**, and **63** may be implemented in consideration of the dielectric constant, the dielectric loss, and/or the z-axis direction thickness of the first dielectric **D1**, the third dielectric **D3**, or the fourth dielectric **D4**.

(133) According to an embodiment, a dielectric constant, a dielectric loss, and/or a z-axis direction thickness of a dielectric (e.g., the second dielectric **D2** and/or the fifth dielectric **D5**) between the second conductive layer **920** and the fourth conductive layer **940** may correspond to conditions to be considered when the multiple second antenna elements **71**, **72**, and **73** are implemented. For example, when the multiple second antenna elements **71**, **72**, and **73** are implemented so that a second signal of a selected or designated second frequency band is transmitted and/or received while reducing a loss, or antenna radiation efficiency is secured, a dielectric constant, a dielectric loss, and/or a z-axis direction thickness of the second dielectric **D2** or the fifth dielectric **D5** may be considered. For example, the shapes of the multiple second antenna elements **71**, **72**, and **73** may be implemented in consideration of the dielectric constant, the dielectric loss, and/or the z-axis direction thickness of the second dielectric **D2** or the fifth dielectric **D5**.

(134) According to an embodiment, the second dielectric **D2** (e.g., a second non-conductive adhesive material) may have a greater dielectric constant than the first dielectric **D1** (e.g., a first non-conductive adhesive material). When a first dielectric constant of the second dielectric **D2** is greater than a second dielectric constant of the first dielectric **D1**, it may be easy to reduce sizes of the multiple second antenna elements **71**, **72**, and **73** for transmitting and/or receiving signals in lower frequency bands, compared to the multiple first antenna elements **61**, **62**, and **63**. In an embodiment, the first dielectric constant (a relative dielectric constant) of the first dielectric **D1** may be about 1 to 4, and the second dielectric constant (a relative dielectric constant) of the second dielectric **D2** may be about 5 to 10. The first dielectric constant or the second dielectric constant greater than the first dielectric constant may have various other values.

(135) According to an embodiment, a third dielectric constant of the third dielectric **D3**, a fourth dielectric constant of the fourth dielectric **D4**, or a fifth dielectric constant of the fifth dielectric **D5**

may be smaller than the second dielectric constant of the second dielectric D2. In an embodiment, the third dielectric constant, the fourth dielectric constant, or the fifth dielectric constant may be substantially identical to the first dielectric constant of the first dielectric D1, or may be different from the first dielectric constant. In an embodiment, the third dielectric constant, the fourth dielectric constant, or the fifth dielectric constant may be greater than the first dielectric constant of the first dielectric D1. For example, the dielectric constant of the first dielectric D1 may be about 2.8, and a dielectric loss of the first dielectric D1 may be about 0.0025. For example, the dielectric constant of the second dielectric D2 may be about 7.4, and a dielectric loss of the second dielectric D2 may be about 0.06. For example, the dielectric constant of the third dielectric D3, the fourth dielectric D4, or the fifth dielectric D5 may be about 3.3, and a dielectric loss of the dielectric constant of the third dielectric D3, the fourth dielectric D4, or the fifth dielectric D5 may be about 0.0035.

(136) According to an embodiment, the first conductive layer 910 may be formed to have a thickness of about 20 micrometers (μm), but is not limited thereto and there may be various thicknesses. The second conductive layer 920, the third conductive layer 930, or the fourth conductive layer 940 may be formed to have a thickness thinner than that of the first conductive layer 910, and may have, for example, a thickness of about 5 μm , but is not limited thereto and there may be various thicknesses.

(137) According to an embodiment, the fourth dielectric D4 may have a thickness of about 25 μm , but is not limited thereto and there may be various thicknesses. According to an embodiment, the third dielectric D3 may have a thickness of about 25 μm , but is not limited thereto and there may be various thicknesses. According to an embodiment, the fifth dielectric D5 may have a thickness of about 75 μm , but is not limited thereto and there may be various thicknesses.

(138) According to an embodiment, the first dielectric D1 or the second dielectric D2 may have a thickness that is different from or substantially identical to the thickness of the third dielectric D3, the fourth dielectric D4, or the fifth dielectric D5. For example, the first dielectric D1 may have a thickness of about 100 μm , but is not limited thereto and there may be various thicknesses. For example, the second dielectric D2 may have a thickness of about 75 μm , but is not limited thereto and there may be various thicknesses.

(139) According to an embodiment, at least two of the first dielectric D1, the third dielectric D3, and the fourth dielectric D4 may be replaced with one dielectric. In an embodiment, the antenna structure 5 may omit at least one of elements positioned on the printed circuit board 50, or may additionally include other elements.

(140) According to an embodiment, the second antenna structure 5 may individually adjust a resonance frequency of each of the multiple first antenna elements 61, 62, and 63 and the multiple second antenna elements 71, 72, and 73 for each use frequency. A description thereof will be made below with reference to FIGS. 11 and 12.

(141) FIG. 11 is a graph illustrating a resonance characteristic of a second antenna structure 5 when changing a third width W3 of each of multiple second notches N21, N22, N23, and N24 included in multiple second antenna elements 71, 72, and 73 (see FIG. 7) according to various embodiments.

(142) Referring to FIGS. 7, 8, and 11, for example, reference numeral "1101" and reference numeral "1102" indicate resonance characteristics for cases where there are different third widths W3. FIG. 11 shows a parameter sweep according to change in the third width W3 of each of the second notches N21, N22, N23, and N24, and for example, a frequency band in which the second antenna structure 5 can transmit or receive a signal substantially without a power loss may change according to the change in the third width W3. Although not shown, a frequency band in which the second antenna structure 5 can transmit or receive a signal substantially without a power loss may change according to a change in a fourth width W4 of each of the second notches N21, N22, N23, and N24. In an embodiment, a resonance frequency of the second antenna structure 5 may vary according to the change in the third width W3 and/or the change in the fourth width W4 of each of

the multiple second notches N21, N22, N23, and N24. In an embodiment, the second antenna structure 5 may substantially resonate in a second use frequency (e.g., about 6.5 GHZ) through adjustment of the third width W3 and/or the fourth width W4.

(143) According to an embodiment, when at least one of the third width W3 and the fourth width W4 of each of the multiple second notches N21, N22, N23, and N24, a resonance frequency of the second antenna structure 5 may move downward or upward. For example, when at least one of the third width W3 and the fourth width W4 increases, a resonance frequency of the second antenna structure 5 may move upward. For example, when at least one of the third width W3 and the fourth width W4 decreases, a resonance frequency of the second antenna structure 5 may move upward.

(144) According to an embodiment, an effect exerted on consonant frequency movement (e.g., downward movement of a frequency or upward movement of a frequency) of the second antenna structure 5 by the change in in the fourth width W4 may be greater than that exerted by the change in the third width W3.

(145) FIG. 12 is a graph illustrating a resonance characteristic of a second antenna structure 5 when changing a second width W2 of each of multiple first notches N11, N12, N13, and N14 included in multiple first antenna elements 61, 62, and 63 (see FIG. 7) according to various embodiments.

(146) Referring to FIGS. 7, 8, and 12, for example, reference numeral “1201”, reference numeral “1202”, and reference numeral “1203” indicate resonance characteristics for cases where there are different second widths W2. FIG. 12 shows a parameter sweep according to change in the second width W2 of each of the first notches N11, N12, N13, and N14, and for example, a resonance frequency band in which the second antenna structure 5 can transmit or receive a signal may change according to the change in the second width W2. Although not shown, a frequency band in which the second antenna structure 5 can transmit or receive a signal may change according to a change in the first width W1 of each of the first notches N11, N12, N13, and N14. In an embodiment, a resonance frequency of the second antenna structure 5 may vary according to the change in the first width W1 and/or the change in the second width W2 of each of the multiple first notches N11, N12, N13, and N14. In an embodiment, the second antenna structure 5 may substantially resonate in a first use frequency (e.g., about 8 GHZ) through adjustment of the first width W1 and/or the second width W2.

(147) According to an embodiment, when at least one of the first width W1 and the second width W2 of each of the multiple first notches N11, N12, N13, and N14 changes, a resonance frequency of the second antenna structure 5 may move downward or upward. For example, when at least one of the first width W1 and the second width W2 increases, a resonance frequency of the second antenna structure 5 may move upward. For example, when at least one of the first width W1 and the second width W2 decreases, a resonance frequency of the second antenna structure 5 may move upward.

(148) According to an embodiment, an effect exerted on consonant frequency movement (e.g., downward movement of a frequency or upward movement of a frequency) of the second antenna structure 5 by the change in in the second width W2 may be greater than that exerted by the change in the first width W1.

(149) FIG. 13 is a graph illustrating antenna radiation efficiency of multiple first antenna elements 61, 62, and 63 when fixing a first width W1 of each of multiple first notches N11, N12, N13, and N14 included in the multiple first antenna elements 61, 62, and 63 and changing a third width W3 of each of multiple second notches N21, N22, N23, and N24 (see FIG. 8) included in multiple second antenna elements 71, 72, and 73 (see FIG. 7), according to various embodiments.

(150) Referring to FIGS. 7, 8, and 13, for example, reference numeral “1301” indicates antenna radiation efficiency of the multiple first antenna elements 61, 62, and 63 for a case where a first width W1 of each of the multiple first notches N11, N12, N13, and N14 is different from a third width W3 of each of the multiple second notches N21, N22, N23, and N24. For example, the first width W1 may be about 0.2 mm, and the third width W3 may be about 2 mm. Reference numeral

“1302”, as a comparative example, indicates antenna radiation efficiency of the multiple first antenna elements **61**, **62**, and **63** for a case where the third width **W3** of each of the multiple second notches **N21**, **N22**, **N23**, and **N24** is wider, compared to reference numeral “1301”. For example, the first width **W1** may be about 0.2 mm, and the third width **W3** may be about 4 mm. When the first width **W1** of each of the multiple first notches **N11**, **N12**, **N13**, and **N14** is different from the third width **W3** of the multiple second notches **N21**, **N22**, **N23**, and **N24**, antenna radiation efficiency of the multiple first antenna elements **61**, **62**, and **63** may be enhanced in a first use frequency (e.g., 8 GHz), compared to the comparative example.

(151) According to an embodiment, in a first embodiment in which the third width **W3** of each of the multiple second notches **N21**, **N22**, **N23**, and **N24** is substantially identical to the first width **W1** of each of the multiple first notches **N11**, **N12**, **N13**, and **N14**, or greater than the first width **W1**, an antenna radiation performance can be enhanced compared to a first comparative example in which the third width **W3** is smaller than the first width **W1**. In the first embodiment, an electromagnetic effect between the multiple antenna elements **61**, **62**, and **63** and the multiple second antenna elements **71**, **72**, and **73** can be reduced, whereby contribution to securing of the antenna radiation performance can be made, compared to the first comparative example. In an embodiment, in a second embodiment in which the third width **W3** is greater than the first width **W1**, an antenna radiation performance can be enhanced compared to a second comparative example in which the third width **W3** is substantially identical to the first width **W1**, or smaller than the first width **W1**. In the second embodiment, an electromagnetic effect between the multiple antenna elements **61**, **62**, and **63** and the multiple second antenna elements **71**, **72**, and **73** can be reduced, whereby contribution to securing of the antenna radiation performance can be made, compared to the second comparative example.

(152) FIG. 14 is a graph illustrating an axis ratio of a second antenna structure 5 according to various embodiments.

(153) Referring to FIG. 14, the second antenna structure 5 according to an embodiment may have an axis ratio formed closer to 1 in the first use frequency (e.g., about 8 GHz) and a second use frequency (e.g., about 6.5 GHz) and substantially have a circular polarization characteristic.

(154) FIGS. 15 and 16 are graphs illustrating an impedance characteristic of a second antenna structure 5 and an impedance characteristic of an antenna structure using linear polarization in a comparative example according to various embodiments.

(155) Referring to FIGS. 15 and 16, reference numerals “1501” and “1601” indicate impedance characteristics of the second antenna structure 5 according to an embodiment using circular polarization. Reference numerals “1502” and “1602” indicate impedance characteristics of the antenna structure according to the comparative example using linear polarization.

(156) For example, the antenna structure using the linear polarization may have an about 3% bandwidth corresponding to about 8.08 GHz to about 8.38 GHz in the first use frequency (e.g., about 8 GHz). The second antenna structure 5 using circular polarization according to an embodiment may have an about 4.75% enhanced bandwidth corresponding to about 8.05 GHz to about 8.45 GHz in the first use frequency (e.g., about 8 GHz), compared to the antenna structure using linear polarization according to the comparative example.

(157) For example, the antenna structure using linear polarization may have an about 3% bandwidth corresponding to about 6.52 GHz to about 6.72 GHz in the second use frequency (e.g., about 6.5 GHz). The second antenna structure 5 using circular polarization according to an embodiment may have an about 4.3% enhanced bandwidth corresponding to about 6.32 GHz to about 6.6 GHz in the second use frequency (e.g., about 6.5 GHz), compared to the antenna structure using linear polarization according to the comparative example.

(158) The second antenna structure 5 according to an embodiment may divide and use the multiple first antenna elements **61**, **62**, and **63** and the multiple second antenna elements **71**, **72**, and **73** for each use frequency, and use both a **TM01** mode and a **TM10** mode each corresponding to a basic

mode of a patch antenna, and thus, the second antenna structure 5 may be a wider impedance bandwidth compared to the antenna structure using linear polarization according to the comparative example.

(159) FIG. 17 is diagram illustrating a first antenna element according to various embodiments.

(160) Referring to FIG. 17, in an embodiment, a first antenna element 1701 or 1702 may include multiple first notches N11, N12, N13, and N14, a first chamfer CH1, and a second chamfer CH2. In FIG. 17, a conductive via for feeding the first antenna elements 1701 and 1702 is omitted.

Reference numerals “1701” and “1702” illustrate first antenna elements for cases where the first chamfer CH1 and the second chamfer CH2 are arranged at different positions. For example, like the multiple first antenna elements 61, 62, and 63 according to the embodiment of FIG. 8, the first antenna element indicated by reference numeral “1701” may include a first chamfer CH1 formed at a part at which the second border 812 and the third border 813 are connected, and a second chamfer CH2 formed at a part at which the first border 811 and the fourth border 814 are connected. The first antenna element indicated by reference numeral “1702” is another example for replacing the multiple first antenna elements 61, 62, and 63 according to the embodiment of FIG. 8, and may include a first chamfer CH1 formed at a part at which the first border 811 and the second border 812 are connected, and a second chamfer CH2 formed at a part at which the third border 813 and the fourth border 814 are connected. In an embodiment, the first antenna element indicated by reference numeral “1701” may form light-handed circular polarization (LHCP). In an embodiment, the first antenna element indicated by reference numeral “1702” may form right-handed circular polarization (RHCP).

(161) FIG. 18 is a diagram illustrating a second antenna element according various embodiments.

(162) Referring to FIG. 18, in an embodiment, a second antenna element 1801 or 1802 may include multiple second notches N21, N22, N23, and N24, a third chamfer CH3, and a fourth chamfer CH4. In FIG. 18, a hole and a coupling conductive pattern related to feeding of the second antenna elements 1801 and 1802 are omitted. Reference numerals “1801” and “1802” illustrate second antenna elements for cases where the third chamfer CH3 and the fourth chamfer CH4 are arranged at different positions. For example, like the multiple second antenna elements 71, 72, and 73 according to the embodiment of FIG. 8, the second antenna element indicated by reference numeral “1801” may include a third chamfer CH3 formed at a part at which the sixth border 816 and the seventh border 817 are connected, and a fourth chamfer CH4 formed at a part at which the fifth border 815 and the eighth border 818 are connected. The second antenna element indicated by reference numeral “1802” is another example for replacing the multiple second antenna elements 71, 72, and 73 according to the embodiment of FIG. 8, and may include a third chamfer CH3 formed at a part at which the fifth border 815 and the sixth border 816 are connected, and a fourth chamfer CH4 formed at a part at which the seventh border 817 and the eighth border 818 are connected. In an embodiment, the second antenna element indicated by reference numeral “1801” may form LHCP. In an embodiment, the second antenna element indicated by reference numeral “1802” may form RHCP.

(163) FIG. 19 is a diagram illustrating a second antenna element 1900 according to various embodiments.

(164) Referring to FIG. 19, in an embodiment, a second antenna element 1900 is another example for replacing the multiple second antenna elements 71, 72, and 73 according to the embodiment of FIG. 8, and may be implemented without a third chamfer CH3 and a fourth chamfer CH4. The second antenna element 1900 implemented without the third chamfer CH3 and the fourth chamfer CH4 may form linear polarization.

(165) According to an embodiment, a feeding structure, as shown in reference numeral “1901”, formed in substantially the same manner as the first feeding structure 801 according to the embodiment of FIG. 8, may be positioned between the second notch N21 formed on the fifth border 815 and the center C2 (e.g., the center aligned with the center C1 of FIG. 8) of the second

antenna element **1900** and positioned to be closer to the second notch N21 than the center C2, and in this case, the second antenna element **1900** may form horizontal polarization. In an embodiment, as shown in reference numeral “**1903**”, the feeding structure may be positioned between the second notch N23 formed on the seventh border **817** and the center C2 of the second antenna element **1900** and positioned to be closer to the second notch N22 than the center C2, and in this case, the second antenna element **1900** may form horizontal polarization.

(166) According to an embodiment, as shown in reference numeral “**1902**”, a feeding structure formed in substantially the same manner as the first feeding structure **801** according to the embodiment of FIG. **8** may be positioned between the second notch N22 formed on the sixth border **816** and the center C2 of the second antenna element **1900** and positioned to be closer to the second notch N22 than the center C2, and in this case, the second antenna element **1900** may form vertical polarization. In an embodiment, as shown in reference numeral “**1904**”, the feeding structure may be positioned between the second notch N24 formed on the eighth border **818** and the center C2 of the second antenna element **1900** and positioned to be closer to the second notch N24 than the center C2, and in this case, the second antenna element **1900** may form vertical polarization.

(167) FIG. **20** are graphs illustrating a value obtained by measuring an angle at which a signal transmitted from a second electronic device **2002** is received by a first electronic device **2001** according to the orientation or the direction in which the first electronic device **2001** and the second electronic device **2002** face according to various embodiments. In an embodiment, the first electronic device **2001** may be the electronic device **200** of FIG. **2**, and may measure an angle at which a signal transmitted from the second electronic device **2002** is received, using the second antenna structure **5** (see FIG. **7**) which generates circulation polarization. The second electronic device **2002**, as a signal source, may generate linear polarization or circular polarization. For example, the second electronic device **2002** may transmit a signal to the first electronic device **2001** using various types of antennas such as a monopole antenna, a dipole antenna, a planar inverted-F antenna (PIFA), an IFA, or a patch antenna.

(168) Referring to FIG. **20**, according to a first measurement condition indicated by reference numeral “**2010**”, the first electronic device **2001** and the second electronic device **2002** may be arranged in the portrait orientation, and the first electronic device **2001** may rotate with reference to a central axis C3 that is in parallel to a y axis. According to a second measurement condition indicated by reference numeral “**2020**”, the first electronic device **2001** may be disposed in the portrait orientation, the second electronic device **2002** may be disposed in the landscape orientation, and the first electronic device **2001** may rotate with reference to the central axis C3 that is in parallel to a y axis. According to a third measurement condition indicated by reference numeral “**2030**”, the first electronic device **2001** and the second electronic device **2002** may be arranged in the landscape orientation, and the first electronic device **2001** may rotate with reference to the central axis C4 that is in parallel to an x axis. A horizontal axis in each of the graphs indicates a rotation angle of the first electronic device **2001**. A vertical axis in each of the graphs may indicate a value obtained by measuring an angle (e.g., an angle at which a signal is received with respect to an x axis, or an angle at which a signal is received with respect to a y axis) at which a signal transmitted from the second electronic device **2002** (e.g., a signal source) is received according to the rotation angle of the first electronic device **2001**. For example, the graph indicated by reference numeral “**2003**” and the graph indicated by reference numeral “**2004**” may indicate a design range in which reliability of data received from the second electronic device **2002** according to the rotation angle of the first electronic device **2001** can be secured. In an embodiment, the design range may be configured so that the first electronic device **2001** should secure reliability of data received from the second electronic device **2002** at an about -60 degree angle to an about +60 degree angle. In an embodiment, the first electronic device **2001** includes the second antenna structure **5** (see FIG. **7**) which generates circular polarization, and thus, a signal reception angle

having reliability satisfying a design range without a substantial effect on the orientation of the first electronic device **2001** or the orientation of the second electronic device **2002** can be measured. (169) According to an embodiment, Table 1 below indicates a distance recognized (or measured or estimated) by the electronic device **200** (see FIG. 2) including an antenna (hereinafter, referred to as a circular polarization antenna) which generates circular polarization, with respect to a signal source according to a polarization characteristic of a signal transmitted from the signal source. Table 1 below indicates a distance recognized (or measured or estimated), by an electronic device in a comparative example including an antenna (hereinafter, referred to as a linear polarization antenna) which generates linear polarization, with respect to a signal source according to a polarization characteristic of a signal transmitted from the signal source. The electronic device **200** including the circular polarization antenna (e.g., the second antenna structure **5** of FIG. 7) can reduce deviation (or error) of a recognized distance with respect to the signal source, compared to the electronic device in the comparative example.

(170) TABLE-US-00001

TABLE 1	Linear polarization antenna	Portrait	Landscape	Signal orientation
orientation transmitted	Circular polarization antenna	(occurrence of from signal Portrait	Landscape of vertical	horizontal source orientation
orientation polarization)	polarization)	Horizontal	37 m	35 m
		6.5 m	38 m	polarization Vertical
		37 m	33 m	39 m
		7.5 m	polarization 45-degree	35 m
		35 m	25 m	35 m
		polarization	Recognized	4 m
		32.5 m	distance	deviation

(171) In an embodiment, referring to FIG. 13 and Table 1, the electronic device **200** including the circular polarization antenna receives a signal of a bandwidth (e.g., UWB) of a broadband using the circular polarization, and thus, positioning accuracy can be secured without an substantial effect on the orientation of a signal source or a polarization characteristic of a signal transmitted to the signal source. For example, in a case of the electronic device in the comparative example, when the liner polarization generated in the linear polarization antenna does not match with a polarization characteristic of a signal received from the signal source, the strength of the signal received from to the linear polarization antenna deteriorates and phase information may be distorted, whereby it may be difficult to secure the positioning accuracy.

(172) FIG. 21 is a cross-sectional view **2100** taken on an x-z plane of a part of the electronic device **200** illustrated in FIG. 3, according to various embodiments. FIG. 22 is a diagram illustrating the electronic device **200** illustrated in FIG. 3, according to various embodiments.

(173) Referring to FIGS. 21 and 22, in an embodiment, the cross-sectional view **2100** may include a bezel structure **330**, a first support member **410**, a front plate **310**, a rear plate **320**, a display **201**, multiple second camera modules **208**, a first substrate assembly **440**, a cover member **480**, a second antenna structure **5**, or a buffer member **2120**.

(174) According to an embodiment, the display **201** may be positioned between the first support member **410** and the front plate **310**. The multiple second camera modules **208**, the first substrate assembly **440**, the cover member **480**, the second antenna structure **5**, or the buffer member **2120** may be positioned between the first support member **410** and the rear plate **320**. The cover member **480** may be positioned between the first substrate assembly **440** and the rear plate **320**. The second antenna structure **5** may be at least partially positioned on the cover member **480** and the rear plate **320**. The buffer member **2120** may be positioned between the second antenna structure **5** and the rear plate **320**. In an embodiment, the multiple second camera modules **208** may not substantially overlap with the first substrate assembly **440**, the cover member **480**, the second antenna structure **5**, or the buffer member **2120** when seen above from the rear plate **320** (e.g., when seen in the +z axis direction).

(175) According to an embodiment, the first substrate assembly **440** may include a primary PCB **2111**, a secondary PCB **2112**, and an interposer substrate **2113** between the primary PCB **2111** and the secondary PCB **2112**. The primary PCB **2111** may be disposed on the first support member **410**. The secondary PCB **2112** may be disposed to at least partially overlap with the primary PCB **2111**

when seen from above the rear plate **320** (e.g., when seen in the +z axis direction). The interposer substrate **2113** may electrically connect the primary PCB **2111** and the secondary PCB **2112**. The interposer substrate **2113** may include, for example, multiple conductive vias (not shown) for electrically connecting the primary PCB **2111** and the secondary PCB **2112**. At least a part of the multiple conductive vias included in the interposer substrate **2113** may be a part of a signal line through which a signal is transferred between a first electronic component disposed on the primary PCB **2111** and a second electronic component disposed on the secondary PCB **2112**. In an embodiment, a part of the multiple conductive vias included in the interposer substrate **2112** may be a part of a ground path for electrically connecting a first ground plane included in the primary PCB **2111** and a second ground plane included in the secondary PCB **2112**.

(176) According to an embodiment, the cover member **480** may be in contact with the secondary PCB **2112**. The cover member **480** may include, for example, metal and/or polymer. The second antenna structure **5** may be disposed on the cover member **480**.

(177) According to an embodiment, the buffer member **2120** may be disposed in the second antenna structure **5**, or disposed on the rear plate **320**. The buffer member **2120** may be positioned on a gap between the second antenna structure **5** and the rear plate **320**. The buffer member **2120** may be disposed between the second antenna structure **5** and the rear plate **320** to press the second antenna structure **5** toward the first substrate assembly **440**. The buffer member **2120** may reduce an effect (e.g., scratch) between the second antenna structure **5** and the rear plate **320**. In an embodiment, the buffer member **2120** may reduce a frictional joint between the second antenna structure **5** and the rear plate **320**. The buffer member **2120** may include a non-conductive material which can reduce an antenna radiation performance when the second antenna structure **5** transmits or receives a frequency signal toward the rear surface **300B**. The buffer member **2120** may have a dielectric constant (e.g., a low dielectric constant) which can reduce deterioration in the antenna radiation performance of the second antenna structure **5**. For example, the buffer member **2120** may be in a film shape, or include a flexible member such as a sponge.

(178) According to an embodiment, the rear plate **320** may be formed of a non-conductive material such as polymer or glass.

(179) According to an embodiment, the rear plate **320** may include a metal material, and in this case, may include multiple openings **2210**, **2220**, and **2230** positioned to correspond to the multiple first antenna elements **61**, **62**, and **63** of the second antenna structure **5**. In an embodiment, the multiple openings **2210**, **2220**, and **2230** may be formed as a single opening. The multiple openings **2210**, **2220**, and **2230** may overlap with the multiple first antenna elements **61**, **62**, and **63** and the multiple second antenna elements **71**, **72**, and **73** when seen from above the rear plate **320** (e.g., when seen in the +z axis direction). A non-conductive member **2240** may be positioned on the multiple openings **2210**, **2220**, and **2230** to form a part of the rear surface **300B** of the electronic device **200**. In an embodiment, the non-conductive member **2240** positioned on the multiple openings **2210**, **2220**, and **2230** may be a radio frequency (RF) window area (or a radiating aperture area). When the second antenna structure **5** transmits or receives a frequency signal, propagation of the frequency signal may be performed by going through the non-conductive member **2240**. The non-conductive member **2240** may secure coverage while reducing deterioration in the radiation performance of the second antenna structure **5** with respect to the rear plate **320**. In an embodiment, when seen from above the rear plate **320**, the multiple openings **2210**, **2220**, and **2230** may have sizes that are enough to overlap with the whole of the multiple first antenna elements **61**, **62**, and **63**.

(180) According to an embodiment, the electronic device **200** may further include a flexible member **2250** (e.g., a sponge) positioned between the second antenna structure **5** and the rear plate **320**. The flexible member **2250** may be disposed in the second antenna structure **5**, or disposed on the rear plate **320**. The flexible member **2250** may not overlap with the buffer member **2120** when seen from above the rear plate **320**. The flexible member **2250** may be disposed between the

connector **1040** and the rear plate **320** elastically press the connector **1040** toward the first substrate assembly **440** so that the connector **1040** does not separated from the first substrate assembly **440**. In an embodiment, the flexible member **2250** may be positioned between the reinforcing member **1030** (see FIG. **10**) and the rear plate **320**. In an embodiment, the flexible member **2250** may be implemented to be replaced with the reinforcing member **1030**. In an embodiment, the reinforcing member **2120** may be extended to be replaced with the flexible member **2250**.

(181) According to an example embodiment of the disclosure, an electronic device (e.g., the electronic device **200** of FIG. **2**) may include: a housing (e.g., the housing **300** of FIG. **2**). The electronic device may include: an antenna structure (e.g., the second antenna structure **5** of FIG. **3**) positioned in the housing. The antenna structure may include: a printed circuit board (e.g., the printed circuit board **50** of FIG. **9** or **10**). The printed circuit board may include: a first surface (e.g., the first surface **501** of FIG. **9** or **10**) oriented in a first direction and a second surface (e.g., the second surface **502** of FIG. **9** or **10**) oriented in a second direction opposite to the first direction. The antenna structure may include: multiple first antenna elements (e.g., the first antenna elements **61**, **62**, and **63** of FIG. **7**) positioned in the printed circuit board on the first surface or to be closer to the first surface than the second surface. The multiple first antenna elements may be configured to generate circular polarization. The multiple first antenna elements may include, when seen from above the first surface, a first border (e.g., the first border **811** of FIG. **8**) and a third border (e.g., the third border **813** of FIG. **8**) spaced apart from each other and extending in parallel to each other. The multiple first antenna elements may include, when seen from above the first surface, a second border (e.g., the second border **812** of FIG. **8**) and a fourth border (e.g., the fourth border **814** of FIG. **8**) spaced apart from each other by a distance between the first border and the third border and extending in parallel to each other. The second border and the fourth border may be arranged to be perpendicular to the first border or the third border. The multiple first antenna elements may include, when seen from above the first surface, multiple first notches (e.g., the multiple first notches **N11**, **N12**, **N13**, and **N14** of FIG. **8**) formed on the first border, the second border, the third border, and the fourth border. The multiple first notches may be arranged at a 90-degree angle with reference to a center (e.g., the center **C1** of FIG. **8**) of each of the multiple first antenna elements. The antenna structure may include multiple second antenna elements (e.g., the multiple second antenna elements **71**, **72**, and **73** of FIG. **7**) positioned in the printed circuit board to be closer to the second surface than the multiple first antenna elements. The multiple second antenna elements may overlap, when seen from above the first surface, the multiple first antenna elements one-to-one. The multiple second antenna elements may be configured to generate circular polarization. The multiple second antenna elements may include, when seen from above the first surface, a fifth border (e.g., the fifth border **815** of FIG. **8**) and a seventh border (e.g., the seventh border **817** of FIG. **7**) spaced apart from each other and extending in parallel to each other. The multiple second antenna elements may include, when seen from above the first surface, a sixth border (e.g., the sixth border **816** of FIG. **8**) and an eighth border (e.g., the eighth border **818** of FIG. **8**) spaced apart from each other by a distance between the fifth border and the seventh border. The sixth border and the eighth border may be arranged to be perpendicular to the fifth border or the seventh border. The multiple second antenna elements may include, when seen from above the first surface, multiple second notches (e.g., the multiple second notches **N21**, **N22**, **N23**, and **N24** of FIG. **8**) formed on the fifth border, the sixth border, the seventh border, and the eighth border. The multiple second notches are arranged at a 90-degree angle with reference to the center, and may overlap with at least some of the multiple first notches one-to-one. The antenna structure may include multiple electrical paths (e.g., the first electrical path **EP1**, the second electrical path **EP2**, and the third electrical path **EP3** of FIG. **7**) positioned on the printed circuit board. The multiple electrical paths may include multiple conductive vias (e.g., the first conductive via **V1**, the second conductive via **V2**, and the third conductive via **V3** of FIG. **7**). The electronic device may include a wireless communication circuit (e.g., the wireless communication module **192** of FIG. **1**) electrically

connected to the multiple first antenna elements through the electrical paths. The printed circuit board may include a first conductive layer (e.g., the first conductive layer **910** of FIG. **9**) including the multiple first antenna elements. The printed circuit board may include a second conductive layer (e.g., the second conductive layer **920** of FIG. **8**) including the multiple second antenna elements. The printed circuit board may include a first dielectric (e.g., the first dielectric **D1** of FIG. **9**) positioned between the first conductive layer and the second conductive layer. The printed circuit board may include a third conductive layer (e.g., the third conductive layer **930** of FIG. **9**) configured to electrically connect the multiple conductive vias to the wireless communication circuit. The third conductive layer may be positioned in the printed circuit board to be closer to the second surface than the second conductive layer. The printed circuit board may include a fourth conductive layer (e.g., the fourth conductive layer **940** of FIG. **9**) positioned in the printed circuit board to be closer to the second surface than the third conductive layer. The fourth conductive layer may include a ground plane. The printed circuit board may include a second dielectric (e.g., the second dielectric **D2** of FIG. **9**) positioned between the third conductive layer and the fourth conductive layer. The second dielectric may have a greater dielectric constant than the first dielectric. Each of the multiple second antenna elements may include a hole (e.g., the first hole **H1**, the second hole **H2**, or the third hole **H3** of FIG. **7**). Each of the multiple conductive vias may be positioned to extend through the hole. The multiple second antenna elements may be configured to be indirectly fed by the multiple conductive vias. The multiple first notches may have different shapes from the multiple second notches.

(182) According to an example embodiment of the disclosure, each (e.g., the first conductive via **V1**, the second conductive via **V2**, or the third conductive via **V3**) of the conductive vias may be positioned, when seen from above the first surface (e.g., the first surface **501** of FIG. **9**), between two first notches (e.g., two first notches **N11** and **N13** of FIG. **8**) symmetrically positioned with reference to the center, among the multiple first notches, and positioned to be closer to one (e.g., the first notch **N11** of FIG. **8**) of the two first notches.

(183) According to an example embodiment of the disclosure, each of the multiple first antenna elements (e.g., the multiple first antenna elements **61**, **62**, and **63** of FIG. **7**) may include, when seen from above the first surface (e.g., the first surface **501** of FIG. **9**), a first chamfer (e.g., the first chamfer **CH1** of FIG. **8**) formed at a part at which the second border and the third border are connected. Each of the multiple first antenna elements may include, when seen from above the first surface, a second chamfer (e.g., the second chamfer **CH2** of FIG. **8**) formed at a part at which the first border and the fourth border are connected. The first chamfer and the second chamfer may be, when seen from above the first surface, formed to be symmetrical to each other with reference to the center (e.g., the center **C1** of FIG. **8**).

(184) According to an example embodiment of the disclosure, each of the multiple second antennas elements (e.g., the second antenna elements **71**, **72**, and **73** of FIG. **7**) may include, when seen from above the first surface (e.g., the first surface **501** of FIG. **9**), a third chamfer (e.g., the third chamfer **CH3** of FIG. **8**) formed at a part at which the sixth border and the seventh border are connected. Each of the multiple second antennas elements may include, when seen from above the first surface, a fourth chamfer (e.g., the fourth chamfer **CH4** of FIG. **8**) formed at a part at which the fifth border and the eighth border are connected. The third chamfer and the fourth chamfer may be, when seen from above the first surface, formed to be symmetrical to each other with reference to the center (e.g., the center **C1** of FIG. **8**).

(185) According to an example embodiment of the disclosure, the first border (e.g., the first border **811** of FIG. **8**) or the third border (e.g., the third border **813** of FIG. **8**) may be parallel to the fifth border (e.g., the fifth border **815** of FIG. **8**) or the seventh border (e.g., the seventh border **817** of FIG. **8**).

(186) According to an example embodiment of the disclosure, the multiple first notches (e.g., the multiple first notches **N11**, **N12**, **N13**, and **N14** of FIG. **8**) and the multiple second notches (e.g., the

multiple second notches **N21**, **N22**, **N23**, and **N24** of FIG. **8**) may be formed to have different square shapes.

(187) According to an example embodiment of the disclosure, the printed circuit board (e.g., the printed circuit board **50** of FIG. **10**) may include a first part (e.g., the first part **51** of FIG. **10**) including the multiple first antenna elements, the multiple second antenna elements, and the multiple conductive vias. The printed circuit board may include a second part (e.g., the second part **52** of FIG. **10**) extending from the first part. The second part may have a thickness thinner than the first part, and may be electrically connected to the wireless communication circuit.

(188) According to an example embodiment of the disclosure, when seen from above the first surface, two (e.g., two first antenna elements **61** and **62** of FIG. **7**) of the multiple first antenna elements and two (e.g., two second antenna elements **71** and **72** of FIG. **7**) of the multiple second antenna elements may be arranged to be spaced apart from each other in an x-axis direction. When seen from above the first surface, two (e.g., two first antenna elements **61** and **63** of FIG. **7**) of the multiple first antenna elements and two (e.g., two second elements **71** and **73** of FIG. **7**) of the multiple second antenna elements may be arranged to be spaced apart from each other in a y-axis direction.

(189) According to an example embodiment of the disclosure, a distance between centers of two first antenna elements (e.g., two first antenna elements **61** and **62** of FIG. **7**) arranged in the x-axis direction, among the multiple first antenna elements, or a distance between centers of two first antenna elements (e.g., two first antenna elements **61** and **63** of FIG. **7**) arranged in the y-axis direction, among the multiple first antenna elements, have a length of $\frac{1}{2}$ of a wavelength of a first signal transmitted and/or received through the multiple first antenna elements. A distance between centers of two second antenna elements (e.g., two second antenna elements **71** and **72** of FIG. **7**) arranged in the x-axis direction, among the multiple second antenna elements, or a distance between centers of two second antenna elements (e.g., two second antenna elements **71** and **73** of FIG. **7**) arranged in the y-axis direction, among the multiple second antenna elements, may have a length of $\frac{1}{2}$ of a wavelength of a second signal transmitted and/or received through the multiple second antenna elements.

(190) According to an example embodiment of the disclosure, the wireless communication circuit (e.g., the wireless communication module **192** of FIG. **1**) may be configured to transmit and/or receive a first signal of a selected or designated first frequency band through the multiple first antenna elements (e.g., the multiple first antenna elements **61**, **62**, and **63** of FIG. **7**). The wireless communication circuit may be configured to transmit and/or receive a second signal of a selected or designated second frequency band through the multiple second antenna elements (e.g., the multiple second antenna elements **71**, **72** and **73** of FIG. **7**). The first signal may have a frequency higher than that of the second signal.

(191) According to an example embodiment of the disclosure, the first frequency band or the second frequency band may include a frequency band relating to an ultra-wide band (UWB).

(192) According to an example embodiment of the disclosure, the first signal may have an 8 GHz frequency, and the second signal may have a 6.5 GHz frequency.

(193) According to an example embodiment of the disclosure, the electronic device may include a processor (e.g., the processor **120** of FIG. **1**) electrically connected to the wireless communication circuit. The processor may be configured to perform a positioning function for a signal source, based on signals received through the multiple first antenna elements (e.g., the multiple first antenna elements **61**, **62**, and **63** of FIG. **7**) or the multiple second antenna elements (e.g., the multiple second antenna elements **71**, **72**, and **73** of FIG. **7**).

(194) According to an example embodiment of the disclosure, the electronic device may further include at least one another antenna structure which is at least partially identical to the antenna structure (e.g., the antenna structure **5** of FIG. **3**). The antenna structure and the at least one another antenna structure may be integrally formed.

(195) According to an example embodiment of the disclosure, the at least one another antenna structure may be positioned in an x-axis direction or a y-axis direction orthogonal to the first direction with respect to the antenna structure (e.g., the antenna structure **5** of FIG. **3**).

(196) According to an example embodiment, an antenna structure (e.g., the antenna structure **5** of FIG. **3**) may include: a printed circuit board (e.g., the printed circuit board **50** of FIGS. **9** and **10**). The printed circuit board may include a first surface (e.g., the first surface **501** of FIGS. **9** and **10**) oriented in a first direction and a second surface (e.g., the second surface **502** of FIGS. **9** and **10**) oriented in a second direction opposite to the first direction. The antenna structure may include a first conductive layer (e.g., the first conductive layer **910** of FIG. **9**) positioned in the printed circuit board on the first surface or to be closer to the first surface than the second surface. The first conductive layer may include multiple first antenna elements (e.g., the multiple first antenna elements **61**, **62**, and **63** of FIG. **7**) configured to generate circular polarization. The multiple first antenna elements may include, when seen from above the first surface, a first border (e.g., the first border **811** of FIG. **8**) and a third border (e.g., the third border **813** of FIG. **8**) spaced apart from each other and extending in parallel to each other. The multiple first antenna elements may include, when seen from above the first surface, a second border (e.g., the second border **812** of FIG. **8**) and a fourth border (e.g., the fourth border **814** of FIG. **8**) spaced apart from each other by a distance between the first border and the third border and extending in parallel to each other. The second border and the fourth border may be arranged to be perpendicular to the first border or the third border. The multiple first antenna elements may include multiple first notches (e.g., the multiple first notches **N11**, **N12**, **N13**, and **N14**) formed on the first border, the second border, the third border, and the fourth border. The multiple first notches may be arranged at a 90-degree angle with reference to a center (e.g., the center **C1** of FIG. **8**) of each of the multiple first antenna elements. The antenna structure may include a second conductive layer (e.g., the second conductive layer **920** of FIG. **9**) positioned in the printed circuit board to be closer to the second surface than the multiple first antenna elements. The second conductive layer may include multiple second antenna elements (e.g., the multiple second elements **71**, **72**, and **73** of FIG. **7**) configured to generate circular polarization. The second antenna elements may overlap with, when seen from above the first surface, the multiple first antenna elements one-to-one. The multiple second antenna elements may include, when seen from above the first surface, a fifth border (e.g., the fifth border **815** of FIG. **8**) and a seventh border (e.g., the seventh border **817** of FIG. **8**) spaced apart from each other and extending in parallel to each other. The multiple second antenna elements may include, when seen from above the first surface, a sixth border (e.g., the sixth border **816** of FIG. **8**) and an eighth border (e.g., the eighth border **818** of FIG. **8**) spaced apart from each other by a distance between the fifth border and the seventh border. The sixth border and the eighth border may be arranged to be perpendicular to the fifth border or the seventh border. The multiple second antenna elements may include, when seen from above the first surface, the multiple second notches (e.g., the multiple second notches **N21**, **N22**, **N23**, and **N24** of FIG. **8**) formed on the fifth border, the sixth border, the seventh border, and the eighth border. The multiple second notches may be arranged at a 90-degree angle from the center, and overlap with at least some of the multiple first notches one-to-one. The antenna structure may include a third conductive layer (e.g., the third conductive layer **930** of FIG. **9**) positioned in the printed circuit board to be closer to the second surface than the second conductive layer. The antenna structure may include a fourth conductive layer (e.g., the fourth conductive layer **940** of FIG. **9**) positioned in the printed circuit board to be closer to the second surface than the third conductive layer. The fourth conductive layer may include a ground plane. The antenna structure may include a first dielectric (e.g., the first dielectric **D1** of FIG. **9**) included in the printed circuit board. The first dielectric may be positioned between the first conductive layer and the second conductive layer. The antenna structure may include a second dielectric (e.g., the second dielectric **D2** of FIG. **9**) included in the printed circuit board. The second dielectric may be positioned between the third conductive layer and the fourth conductive layer. The second

dielectric may have a greater dielectric constant than the first dielectric. The antenna structure may include multiple conductive vias (e.g., the first conductive via **V1**, the second conductive via **V2**, and the third conductive via **V3** of FIG. 7) positioned in the printed circuit board. The multiple conductive vias may electrically connect the multiple first antenna elements and the third conductive layer. The electronic device may include a wireless communication circuit (e.g., the wireless communication module **192** of FIG. 1) electrically connected to the multiple first antenna elements through the third conductive layer. Each of the multiple second antenna elements may include a hole (e.g., the first hole **H1**, the second hole **H2**, or the third hole **H3** of FIG. 7). Each of the multiple conductive vias may be positioned to extend through the hole. The multiple second antenna elements may be configured to be indirectly fed by the multiple conductive vias. The multiple first notches may have different shapes from the multiple second notches.

(197) According to an example embodiment of the disclosure, each (e.g., the first conductive layer **V1**, the second conductive via **V2**, or the third conductive layer **V3** of FIG. 7) of the conductive vias may be positioned, when seen from above the first surface (e.g., the first surface **501** of FIG. 9), between two first notches (e.g., two first notches **N11** and **N13** of FIG. 8) symmetrically positioned with reference to the center, among the multiple first notches, and positioned to be closer to one (e.g., the first notch **N11** of FIG. 8) of the two first notches.

(198) According to an example embodiment of the disclosure, each of the multiple first antenna elements (e.g., the multiple first antenna elements **61**, **62**, and **63** of FIG. 7) may include, when seen from above the first surface (e.g., the first surface **501** of FIG. 9), a first chamfer (e.g., a first chamfer **CH1** of FIG. 8) formed at a part at which the second border and the third border are connected. Each of the multiple first antenna elements may include, when seen from above the first surface, a second chamfer formed (e.g., the second chamfer **CH2** of FIG. 8) at a part at which the first border and the fourth border are connected. The first chamfer and the second chamfer may be, when seen from above the first surface, formed to be symmetrical to each other with reference to the center (e.g., the center **C1** of FIG. 8).

(199) According to an example embodiment of the disclosure, each of the multiple second antennas elements (e.g., the multiple second antenna elements **71**, **72**, and **73** of FIG. 7) may include, when seen from above the first surface (e.g., the first surface **501** of FIG. 9), a third chamfer (e.g., the third chamfer **CH3** of FIG. 8) formed at a part at which the sixth border and the seventh border are connected. Each of the multiple second antennas elements may include, when seen from above the first surface, a fourth chamfer (e.g., the fourth chamfer **CH4** of FIG. 8) formed at a part at which the fifth border and the eighth border are connected. The third chamfer and the fourth chamfer may be, when seen from above the first surface, formed to be symmetrical to each other with reference to the center (e.g., the center **C1** of FIG. 8).

(200) According to an example embodiment, the multiple first notches (e.g., the multiple first notches **N11**, **N12**, **N13**, and **N14** of FIG. 8) may have different rectangular shapes from the multiple second notches (e.g., the multiple second notches **N21**, **N22**, **N23**, and **N24** of FIG. 8).

(201) According an example embodiment, when seen from above the first surface, two (e.g., two first antenna elements **61** and **62** of FIG. 7) of the multiple first antenna elements and two (e.g., two second antenna elements **71** and **72** of FIG. 7) of the multiple second antenna elements may be arranged to be spaced apart from each other in an x-axis direction. When seen from above the first surface, two (e.g., two first antenna elements **61** and **63** of FIG. 7) of the multiple first antenna elements and two (e.g., two second antenna elements **71** and **73** of FIG. 7) of the multiple second antenna elements may be arranged to be spaced apart from each other in a y-axis direction.

(202) While the disclosure has been illustrated and described with reference to various example embodiments, it will be understood that the various example embodiments are intended to be illustrative, not limiting. It will be further understood by those skilled in the art that various changes in form and detail may be made without departing from the true spirit and full scope of the disclosure, including the appended claims and their equivalents. It will also be understood that any

of the embodiment(s) described herein may be used in conjunction with any other embodiment(s) described herein.

Claims

1. An electronic device comprising: a housing; an antenna structure positioned in the housing and comprising a printed circuit board, multiple first antenna elements, multiple second antenna elements, and multiple electrical paths; and a wireless communication circuit electrically connected to the multiple first antenna elements through the electrical paths, wherein the printed circuit board comprises a first surface oriented in a first direction and a second surface oriented in a second direction opposite to the first direction, wherein the multiple first antenna elements are: positioned in the printed circuit board on the first surface or to be closer to the first surface than the second surface, configured to generate circular polarization, and each comprise, when viewed from above the first surface, a first border and a third border spaced apart from each other and extending in parallel to each other, a second border and a fourth border spaced apart from each other by a distance between the first border and the third border, extending in parallel to each other, and respectively disposed to be perpendicular to the first border or the third border, and multiple first notches with at least one of the first notches formed on each of the first border, the second border, the third border, and the fourth border, and arranged at a 90-degree angle with reference to a center of each of the multiple first antenna elements, wherein the multiple second antenna elements are: positioned in the printed circuit board to be closer to the second surface than the multiple first antenna elements, overlap with, when viewed from above the first surface, the multiple first antenna elements one-to-one, configured to generate circular polarization, and each comprise, when viewed from above the first surface, a fifth border and a seventh border spaced apart from each other and extending in parallel to each other, a sixth border and an eighth border spaced apart from each other by a distance between the fifth border and the seventh border, and respectively disposed to be perpendicular to the fifth border or the seventh border, and multiple second notches with at least one of the second notches formed on each of the fifth border, the sixth border, the seventh border, and the eighth border, arranged at a 90-degree angle with reference to the center, and wherein a portion of each of the second notches overlaps with a corresponding one of the first notches, and wherein the multiple electrical paths are positioned on the printed circuit board and comprise multiple conductive vias electrically connected to the multiple first antenna elements, wherein the printed circuit board comprises: a first conductive layer comprising the multiple first antenna elements; a second conductive layer comprising the multiple second antenna elements; a first dielectric positioned between the first conductive layer and the second conductive layer; a third conductive layer configured to electrically connect the multiple conductive vias to the wireless communication circuit and positioned in the printed circuit board to be closer to the second surface than the second conductive layer; a fourth conductive layer comprising a ground plane and positioned in the printed circuit board to be closer to the second surface than the third conductive layer; and a second dielectric positioned between the third conductive layer and the fourth conductive layer and having a greater dielectric constant than the first dielectric, wherein each of the multiple second antenna elements comprises a hole and each of the multiple conductive vias is positioned to extend through the corresponding hole, wherein the multiple second antenna elements are configured to be indirectly fed by the multiple conductive vias, and wherein the multiple first notches have different shapes from the multiple second notches.
2. The electronic device of claim 1, wherein each of the conductive vias is positioned, when viewed from above the first surface, between two first notches symmetrically positioned with reference to the center, among the multiple first notches, and positioned to be closer to one of the two first notches.
3. The electronic device of claim 1, wherein each of the multiple first antenna elements comprises,

when viewed from above the first surface: a first chamfer formed at a part at which the second border and the third border are connected; and a second chamfer formed at a part at which the first border and the fourth border are connected, wherein the first chamfer and the second chamfer are, when viewed from above the first surface, symmetrical to each other with reference to the center.

4. The electronic device of claim 3, wherein each of the multiple second antennas elements comprises, when viewed from above the first surface: a third chamfer formed at a part at which the sixth border and the seventh border are connected; and a fourth chamfer formed at a part at which the fifth border and the eighth border are connected, wherein the third chamfer and the fourth chamfer are, when viewed from above the first surface, symmetrical to each other with reference to the center.

5. The electronic device of claim 1, wherein the first border or the third border is parallel to the fifth border or the seventh border.

6. The electronic device of claim 1, wherein the multiple first notches and the multiple second notches have rectangular shapes of different dimensions.

7. The electronic device of claim 1, wherein the printed circuit board comprises: a first part comprising the multiple first antenna elements, the multiple second antenna elements, and the multiple conductive vias; and a second part extending from the first part, having a thickness thinner than the first part, and electrically connected to the wireless communication circuit.

8. The electronic device of claim 1, wherein when viewed from above the first surface, two of the multiple first antenna elements and two of the multiple second antenna elements are arranged to be spaced apart from each other in an x-axis direction, and wherein two of the multiple first antenna elements and two of the multiple second antenna elements are arranged to be spaced apart from each other in a y-axis direction.

9. The electronic device of claim 8, wherein a distance between centers of two first antenna elements arranged in the x-axis direction, among the multiple first antenna elements, or a distance between centers of two first antenna elements arranged in the y-axis direction, among the multiple first antenna elements have a length of $\frac{1}{2}$ of a wavelength of a first signal transmitted and/or received through the multiple first antenna elements, and wherein a distance between centers of two second antenna elements arranged in the x-axis direction, among the multiple second antenna elements, or a distance between centers of two second antenna elements arranged in the y-axis direction, among the multiple second antenna elements have a length of $\frac{1}{2}$ of a wavelength of a second signal transmitted and/or received through the multiple second antenna elements.

10. The electronic device of claim 1, wherein the wireless communication circuit is configured to transmit and/or receive a first signal of a selected or designated first frequency band through the multiple first antenna elements, and to transmit and/or receive a second signal of a selected or designated second frequency band through the multiple second antenna elements, wherein the first signal has a frequency higher than a frequency of the second signal.

11. The electronic device of claim 10, wherein the first frequency band or the second frequency band comprises a frequency band relating to an ultra-wide band (UWB).

12. The electronic device of claim 10, wherein the first signal has a frequency of 8 GHz, and the second signal has a frequency of 6.5 GHz.

13. The electronic device of claim 1, further comprising a processor electrically connected to the wireless communication circuit, wherein the processor is configured to perform a positioning function for a signal source, based on signals received through the first antenna elements or the second antenna elements.

14. The electronic device of claim 1, further comprising at least one another antenna structure at least partially identical to the antenna structure, wherein the antenna structure and the at least one another antenna structure are integrally formed.

15. The electronic device of claim 14, wherein the at least one another antenna structure is positioned in an x-axis direction or a y-axis direction orthogonal to the first direction with respect

to the antenna structure.

16. An antenna structure comprising: a printed circuit board comprising a first surface oriented in a first direction and a second surface oriented in a second direction opposite to the first direction; a first conductive layer positioned in the printed circuit board on the first surface or to be closer to the first surface than the second surface, and comprising multiple first antenna elements, configured to generate circular polarization, and each comprising, when viewed from above the first surface, a first border and a third border spaced apart from each other and extending in parallel to each other, a second border and a fourth border spaced apart from each other by a distance between the first border and the third border, extending in parallel to each other, and respectively disposed to be perpendicular to the first border or the third border, and multiple first notches with at least one of the first notches formed on each of the first border, the second border, the third border, and the fourth border, and arranged at a 90-degree angle with reference to a center of each of the multiple first antenna elements; a second conductive layer positioned in the printed circuit board to be closer to the second surface than the multiple first antenna elements, and comprising multiple second antenna elements overlapping with, as viewed from above the first surface, the multiple first antenna elements one-to-one, configured to generate circular polarization, and each comprising, when viewed from above the first surface, a fifth border and a seventh border spaced apart from each other and extending in parallel to each other, a sixth border and an eighth border spaced apart from each other by a distance between the fifth border and the seventh border, and respectively disposed to be perpendicular to the fifth border or the seventh border, and multiple second notches with at least one of the second notches formed on each of the fifth border, the sixth border, the seventh border, and the eighth border, arranged at a 90-degree angle from the center, and wherein a portion of each of the second notches overlaps with a corresponding one of the first notches; a third conductive layer positioned in the printed circuit board to be closer to the second surface than the second conductive layer; a fourth conductive layer comprising a ground plane and positioned in the printed circuit board to be closer to the second surface than the third conductive layer; a first dielectric included in the printed circuit board and positioned between the first conductive layer and the second conductive layer; a second dielectric included in the printed circuit board, positioned between the third conductive layer and the fourth conductive layer, and having a greater dielectric constant than the first dielectric; multiple conductive vias positioned in the printed circuit board and electrically connecting the multiple first antenna elements and the third conductive layer; and a wireless communication circuit electrically connected to the multiple first antenna elements through the third conductive layer, wherein each of the multiple second antenna elements comprises a hole and each of the multiple conductive vias is positioned to extend through the hole, wherein the multiple second antenna elements are configured to be indirectly fed by the multiple conductive vias, and wherein the multiple first notches have different shapes from the multiple second notches.

17. The antenna structure of claim 16, wherein each of the conductive vias is positioned, when viewed from above the first surface, between two first notches symmetrically positioned with reference to the center, among the multiple first notches, and positioned to be closer to one of the two first notches.

18. The antenna structure of claim 16, wherein each of the multiple first antenna elements comprise, when viewed from above the first surface: a first chamfer formed at a part at which the second border and the third border are connected; and a second chamfer formed at a part at which the first border and the fourth border are connected, wherein the first chamfer and the second chamfer are, when viewed from above the first surface, symmetrical to each other with reference to the center, and wherein each of the multiple second antennas elements comprises, when viewed from above the first surface; a third chamfer formed at a part at which the sixth border and the seventh border are connected; and a fourth chamfer formed at a part at which the fifth border and the eighth border are connected, wherein the third chamfer and the fourth chamfer are, when

viewed from above the first surface, symmetrical to each other with reference to the center.

19. The antenna structure of claim 16, wherein the multiple first notches and the multiple second notches have rectangular shapes of different dimensions.

20. The antenna structure of claim 16, wherein when viewed from above the first surface, two of the multiple first antenna elements and two of the multiple second antenna elements are arranged to be spaced apart from each other in an x-axis direction, and wherein two of the multiple first antenna elements and two of the multiple second antenna elements are arranged to be spaced apart from each other in a y-axis direction.
