

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12401557
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Kulkarni; Pushkar Bajirao et al.

Techniques for waveform compression

Abstract

Methods, systems, and devices for wireless communications are described. A user equipment (UE) may generate an input signal including information for transmission over a wireless channel. The UE may perform a first waveform shaping stage on the input signal to increase an in-band emissions ratio and reduce a peak-to-average power ratio (PAPR) of the input signal. The UE may perform a second waveform shaping stage on the output of the first waveform shaping stage to reduce an adjacent channel leakage ratio of the output of the first waveform shaping stage. The UE may then transmit a signal over the wireless channel based on an output of the second waveform shaping stage.

Inventors: Kulkarni; Pushkar Bajirao (San Diego, CA), Burke; Joseph Patrick (San Diego, CA), Mohamed Ibrahim; Abdelrahman Mohamed Ahmed (San Diego, CA), Gutman; Igor (Hod HaSharon, IL), Cezanne; Juergen (Ocean Township, NJ)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 1000008777851

Assignee: QUALCOMM Incorporated (San Diego, CA)

Appl. No.: 17/929072

Filed: September 01, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20240080233 A1	Mar. 07, 2024

Publication Classification

Int. Cl.: H04L27/26 (20060101); H04L5/00 (20060101); H04L27/34 (20060101)

U.S. Cl.:CPC **H04L27/2623** (20130101); **H04L5/0048** (20130101); **H04L27/3494** (20130101);**Field of Classification Search****CPC:** H04L (27/26); H04L (5/00); H04L (27/34); H04L (25/03); H04B (1/04)**References Cited****U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
7873116	12/2010	Okada	375/295	H04L 5/06
7995975	12/2010	Sundstrom	455/308	H04L 27/2624
8145251	12/2011	Love	455/343.1	H04W 52/367
8150338	12/2011	Sundstrom	455/308	H04L 27/2624
8463314	12/2012	Love	455/343.1	H04W 52/367
8467463	12/2012	Hassler	375/260	H04L 27/2623
8478328	12/2012	Love	455/343.1	H04W 52/367
8862649	12/2013	Kang	708/319	H04L 27/2624
9231534	12/2015	Rozenblit	N/A	H03F 1/0227
9246523	12/2015	Stopler	N/A	H04B 1/0458
9622190	12/2016	Goedken	N/A	H04W 52/367
9755669	12/2016	Chen	N/A	H03F 3/245
9762350	12/2016	Stopler	N/A	H04L 25/03343
9973370	12/2017	Langer	N/A	H03F 1/3258
10050817	12/2017	Terry	N/A	H04L 27/26265
10084630	12/2017	Ng	N/A	H03F 3/24
10389308	12/2018	Mao	N/A	H03F 3/21
10469109	12/2018	Gutman	N/A	H03F 3/24
10491443	12/2018	Khan	N/A	H04B 1/04
10680870	12/2019	Levinbook	N/A	H04L 27/2636
10701694	12/2019	Khan	N/A	H04W 72/0453
10841136	12/2019	McCoy	N/A	H04L 25/03261

11108609	12/2020	Levinbook	N/A	H04L 27/2607
11177849	12/2020	Wang	N/A	H04B 1/401
11411794	12/2021	Fehri	N/A	H04L 27/2615
11424897	12/2021	Eger	N/A	H04L 27/2624
11444733	12/2021	Levy	N/A	H04L 25/0224
11516058	12/2021	Mukkavilli	N/A	H04W 76/27
11540230	12/2021	Maleki	N/A	H04L 27/2624
11563614	12/2022	Yunusov	N/A	H04L 27/2615
11677603	12/2022	Sahraei	370/329	H04L 27/2614
11683706	12/2022	Barak	370/252	H04L 5/0048
11689343	12/2022	Eger	370/330	H04L 5/023
11700023	12/2022	Upadhya	375/296	H04B 1/0475
11711120	12/2022	Sverdlov	375/262	H04B 7/0639
11729038	12/2022	Zach	370/328	H04L 27/2623
11777777	12/2022	Ly	370/329	H04W 72/044
11855594	12/2022	Kojima	N/A	H04W 52/00
11888670	12/2023	Meir	N/A	H04B 1/0475
11997036	12/2023	Levy	N/A	H04W 72/541
12057985	12/2023	Sakhnini	N/A	H04L 27/2697
12063600	12/2023	Gutman	N/A	H04W 52/241
12137017	12/2023	Zhang	N/A	H04L 27/2613
12143082	12/2023	Gutman	N/A	H03G 3/3089
2007/0173260	12/2006	Love	455/450	H04W 72/541
2007/0173276	12/2006	Love	455/522	H04W 52/367
2008/0025254	12/2007	Love	370/329	H04W 52/242
2012/0114073	12/2011	Beek	375/296	H04L 25/03834
2012/0172080	12/2011	Love	455/522	H04W 52/367

2012/0172081	12/2011	Love	455/522	H04W 52/367
2012/0219086	12/2011	Beek	375/295	H04L 27/2634
2013/0016765	12/2012	Park	375/295	H04L 27/2626
2013/0165132	12/2012	Goedken	455/450	H04W 52/243
2016/0241359	12/2015	Stopler	N/A	H04L 27/26265
2019/0268202	12/2018	Levinbook	N/A	H04L 27/2614
2020/0068570	12/2019	Khan	N/A	H04B 1/0475
2020/0204421	12/2019	Levinbook	N/A	H04L 27/2607
2021/0099197	12/2020	Wang	N/A	H04B 1/401
2021/0144657	12/2020	Ang	N/A	H04W 52/0261
2021/0176107	12/2020	Hou	N/A	H03F 1/3241
2021/0288854	12/2020	Mukkavilli	N/A	H04L 27/2618
2021/0328751	12/2020	Eger	N/A	H04L 27/2614
2022/0038322	12/2021	Ly	N/A	H04L 27/2614
2022/0255688	12/2021	Radulescu	N/A	H04L 27/2601
2022/0385515	12/2021	Kutz	N/A	H04L 27/2623
2022/0393709	12/2021	Kutz	N/A	H03F 3/24
2023/0091116	12/2022	Kutz	370/329	H03F 1/32
2023/0133797	12/2022	Jiang	370/330	H04L 27/2623
2023/0155617	12/2022	Meir	370/329	H04L 25/0224
2023/0291630	12/2022	Hosseini	N/A	H04L 27/2646
2023/0318636	12/2022	Kulkarni	455/552.1	H03F 3/213
2023/0389005	12/2022	Zhang	N/A	H04W 72/1263
2024/0007971	12/2023	Saggar	N/A	H04W 52/36
2024/0014991	12/2023	Paz	N/A	H04L 5/0048
2024/0040506	12/2023	Uziel	N/A	H04W 52/0229
2024/0080233	12/2023	Kulkarni	N/A	H04L 5/0048
2024/0088848	12/2023	Kojima	N/A	H03F 3/245
2024/0121715	12/2023	Abotabl	N/A	H04W 52/0274
2024/0187290	12/2023	Oved	N/A	H04B 1/12

2024/0357395	12/2023	Shaked	N/A	H04L 5/0051
--------------	---------	--------	-----	-------------

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1695335	12/2004	CN	H04L 27/2614
1702964	12/2004	CN	N/A
1972179	12/2006	CN	N/A
1972263	12/2006	CN	N/A
1972264	12/2006	CN	N/A
2907089	12/2006	CN	N/A
2907090	12/2006	CN	N/A
101048950	12/2006	CN	N/A
101136890	12/2007	CN	N/A
101257481	12/2007	CN	N/A
101483627	12/2008	CN	N/A
100550627	12/2008	CN	N/A
100555891	12/2008	CN	N/A
101601247	12/2008	CN	H04L 27/2618
101645862	12/2009	CN	N/A
101702698	12/2009	CN	H04L 5/06
101986636	12/2010	CN	H04B 1/713
101399792	12/2010	CN	N/A
101483627	12/2010	CN	N/A
1695335	12/2010	CN	H04L 27/2614
102223338	12/2010	CN	N/A
101257481	12/2011	CN	N/A
101601247	12/2012	CN	H04L 27/2618
101702698	12/2012	CN	H04L 5/06
103188199	12/2012	CN	N/A
102223338	12/2012	CN	N/A
101645862	12/2012	CN	N/A
101986636	12/2013	CN	H04B 1/713
104751209	12/2014	CN	N/A
104751209	12/2017	CN	N/A
108462559	12/2017	CN	N/A
109952748	12/2018	CN	G06F 17/141
110945846	12/2019	CN	H04B 1/02
109952748	12/2019	CN	G06F 17/141
110945846	12/2020	CN	H04B 1/02
114189411	12/2021	CN	H04B 1/0064
115244905	12/2021	CN	N/A
116158127	12/2022	CN	N/A
102021106637	12/2020	DE	H04L 1/0003
102021106637	12/2020	DE	H04L 1/0003

1924044	12/2007	EP	H04L 27/2618
2536046	12/2011	EP	N/A
2406904	12/2012	EP	H04L 25/03834
2654226	12/2012	EP	H04L 25/03834
2103067	12/2017	EP	H04L 27/2624
2050200	12/2017	EP	H04W 52/242
1982434	12/2018	EP	H04W 52/367
2654226	12/2018	EP	H04L 25/03834
3529957	12/2020	EP	N/A
3968526	12/2021	EP	H04B 1/0064
2009164754	12/2008	JP	H04L 1/0026
4558741	12/2009	JP	H04L 5/06
2012182840	12/2011	JP	H04L 1/0026
5061892	12/2011	JP	H04L 1/0026
5122564	12/2012	JP	H04W 52/242
5415959	12/2013	JP	H04L 27/2624
5445624	12/2013	JP	H04L 1/0026
20240095185	12/2023	KR	N/A
WO-0309373	12/2001	WO	H04L 25/00
WO-2006049140	12/2005	WO	N/A
WO-2007087482	12/2006	WO	H04W 52/242
WO-2007087483	12/2006	WO	H04W 52/367
WO-2008014118	12/2007	WO	H04W 52/242
WO-2008058840	12/2007	WO	H04L 27/2618
WO-2008074801	12/2007	WO	H04L 27/2624
WO-2011009239	12/2010	WO	H04L 25/03834
WO-2012065451	12/2011	WO	H04B 1/713
WO-2013185698	12/2012	WO	H04L 27/0008
WO-2014088792	12/2013	WO	H04W 52/146
WO-2016042400	12/2015	WO	H04B 1/0458
WO-2018098692	12/2017	WO	N/A
WO-2019042532	12/2018	WO	N/A
WO-2019117888	12/2018	WO	N/A

WO-2020040815	12/2019	WO	N/A
WO-2020188316	12/2019	WO	G06N 3/04
WO-2021096800	12/2020	WO	H04B 1/401
WO-2021183981	12/2020	WO	N/A
WO-2021211461	12/2020	WO	H04L 27/2614
WO-2021222345	12/2020	WO	H04L 27/2614
WO-2022027054	12/2021	WO	H04L 27/2614
WO-2022199793	12/2021	WO	H04L 27/2601
WO-2022240740	12/2021	WO	N/A
WO-2013009522	12/2022	WO	H04L 25/03
WO-2023025397	12/2022	WO	H04L 27/26412
WO-2023075979	12/2022	WO	H04L 27/2614
WO-2023225442	12/2022	WO	H04L 1/0007
WO-2024005710	12/2023	WO	H04L 25/03834
WO-2024006602	12/2023	WO	H04L 27/2607
WO-2024006610	12/2023	WO	N/A
WO-2024006610	12/2023	WO	N/A

OTHER PUBLICATIONS

Pedro F. G. da Silva et al. Design of Crest Factor Reduction Techniques Based on Clipping and Filtering for Wireless Communications Systems, IEEE 2013 (Year: 2013). cited by examiner

An Iterative Method to Restore the Performance of Clipped and Filtered OFDM Signals, by Chen et al. IEEE 2003 (Year: 2003). cited by examiner

Crest Factor Reduction Techniques Based on Clipping and Filtering for Wireless Communications Systems, by Pedro F. G. et al., IEEE 2013 (Year: 2013). cited by examiner

Iterative Clipping and Filtering Technique for PAPR Reduction of OFDM Signals, by Abouty et al., Feb. 2013 (Year: 2013). cited by examiner

J. Armstrong, Peak-to-average power reduction for OFDM by repeated clipping and frequency domain filtering, Electronics Letters, vol. 38, No. 5, Feb. 2002 (Year: 2002). cited by examiner

Sperlich et al. Power_amplifier_linearization_with_digital_pre-distortion_and_crest_factor_reduction, IEEE 2004 (Year: 2004). cited by examiner

Primary Examiner: Tadese; Berhanu

Attorney, Agent or Firm: Holland & Hart LLP

Background/Summary

FIELD OF TECHNOLOGY

(1) The following relates to wireless communications, including improved techniques for

waveform compression.

BACKGROUND

(2) Wireless communications systems are widely deployed to provide various types of communication content such as voice, video, packet data, messaging, broadcast, and so on. These systems may be capable of supporting communication with multiple users by sharing the available system resources (e.g., time, frequency, and power). Examples of such multiple-access systems include fourth generation (4G) systems such as Long Term Evolution (LTE) systems, LTE-Advanced (LTE-A) systems, or LTE-A Pro systems, and fifth generation (5G) systems which may be referred to as New Radio (NR) systems. These systems may employ technologies such as code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal FDMA (OFDMA), or discrete Fourier transform spread orthogonal frequency division multiplexing (DFT-S-OFDM). A wireless multiple-access communications system may include one or more base stations, each supporting wireless communication for communication devices, which may be known as user equipment (UE).

(3) Some wireless communications systems may support wireless communications between network devices. For example, a UE may transmit uplink signaling to a network entity. In some cases, a signal between network devices may be referred to as a waveform. Network devices may perform operations to shape waveforms, which may include compression operations or other signal processing operations. In some cases, waveform shaping operations may reduce signal noise or intermodulation distortion (IMD) associated with the signal. Some wireless devices may include power amplifiers (PAs) for amplifying signals. A range (e.g., a transmission distance) of a signal may be based on a level of amplification at a PA. However, in some cases, increasing an output of a PA may result in undesirable waveform properties.

SUMMARY

(4) The described techniques relate to improved methods, systems, devices, and apparatuses that support improved techniques for waveform compression. For example, the described techniques provide for a network device (e.g., a user equipment (UE) or a network entity) to increase a range of a signal while increasing an in-band emissions (IBE) ratio for the signal, reducing a peak-to-average power ratio (PAPR) for the signal, and reducing an adjacent channel leakage ratio (ACLR) of the signal. The network device may perform a first waveform shaping stage, including an interference cancelling operation and a clipping operation, and a second stage including a frequency selective filtering operation. In some cases, one or both waveform shaping stages may be performed iteratively (e.g., for a quantity of iterations).

(5) A method for wireless communications at a user equipment (UE) is described. The method may include generating an input signal including information for transmission over a wireless channel, performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal, performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage, and transmitting a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage.

(6) An apparatus for wireless communications at a UE is described. The apparatus may include a processor, memory coupled with the processor, and instructions stored in the memory. The instructions may be executable by the processor to cause the apparatus to generate an input signal including information for transmission over a wireless channel, perform a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal, perform a second waveform

shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage, and transmit a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage.

(7) Another apparatus for wireless communications at a UE is described. The apparatus may include means for generating an input signal including information for transmission over a wireless channel, means for performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal, means for performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage, and means for transmitting a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage.

(8) A non-transitory computer-readable medium storing code for wireless communications at a UE is described. The code may include instructions executable by a processor to generate an input signal including information for transmission over a wireless channel, perform a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal, perform a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage, and transmit a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage.

(9) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, performing the first waveform shaping stage of the multistage waveform shaping process may include operations, features, means, or instructions for performing an interference cancellation operation to increase the in-band emissions ratio of the input signal.

(10) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, performing the interference cancellation operation may include operations, features, means, or instructions for performing a state expansion of nonlinear components of the input signal and performing frequency selective filtering on an output of the state expansion.

(11) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, performing the interference cancellation operation may include operations, features, means, or instructions for performing a clipping operation on the input signal and performing frequency selective filtering on an output of the clipping operation.

(12) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, performing the first waveform shaping stage of the multistage waveform shaping process may include operations, features, means, or instructions for performing a clipping operation after increasing the in-band emissions ratio of the input signal to reduce the PAPR of the input signal.

(13) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, performing the clipping operation may include operations, features, means, or instructions for performing a quantity of iterations of the clipping operation, where the output of the first waveform shaping stage includes an output of a final iteration of the quantity of iterations of the clipping operation.

(14) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, performing the second waveform shaping stage of the multistage waveform shaping process may include operations, features, means, or instructions for performing frequency selective filtering on the output of the first waveform shaping stage to reduce the adjacent channel

leakage ratio of the output of the first waveform shaping stage.

(15) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, an in-band emissions ratio of the output of the second waveform shaping stage may be greater than the in-band emissions ratio of the input signal.

(16) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, an adjacent channel leakage ratio of the output of the second waveform shaping stage may be greater than an adjacent channel leakage ratio of the input signal.

(17) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, performing the first waveform shaping stage may include operations, features, means, or instructions for introducing intermodulation distortion to the output of the first waveform shaping stage for processing at a receiver.

(18) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, performing the first waveform shaping stage may include operations, features, means, or instructions for reducing an adjacent channel leakage ratio of the input signal.

(19) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, performing the first waveform shaping stage may include operations, features, means, or instructions for performing a quantity of iterations of the first waveform shaping stage, where the output of the first waveform shaping stage includes an output of a final iteration of the quantity of iterations of the first waveform shaping stage.

(20) A method for wireless communication at a UE is described. The method may include generating an input signal including information for transmission over a wireless channel, performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal, performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage, and transmitting a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage.

(21) An apparatus for wireless communication at a UE is described. The apparatus may include a processor, memory coupled with the processor, and instructions stored in the memory. The instructions may be executable by the processor to cause the apparatus to generate an input signal including information for transmission over a wireless channel, perform a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal, perform a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage, and transmit a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage.

(22) Another apparatus for wireless communication at a UE is described. The apparatus may include means for generating an input signal including information for transmission over a wireless channel, means for performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal, means for performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage, and means for transmitting a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage.

- (23) A non-transitory computer-readable medium storing code for wireless communication at a UE is described. The code may include instructions executable by a processor to generate an input signal including information for transmission over a wireless channel, perform a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal, perform a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage, and transmit a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage.
- (24) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for perform an interference cancellation operation to increase the in-band emissions ratio of the input signal.
- (25) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for perform a state expansion of nonlinear components of the input signal and perform frequency selective filtering on an output of the state expansion.
- (26) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for perform a clipping operation on the input signal and perform frequency selective filtering on an output of the clipping operation.
- (27) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for perform a clipping operation after increasing the in-band emissions ratio of the input signal to reduce the PAPR of the input signal.
- (28) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for perform a quantity of iterations of the clipping operation, where the output of the first waveform shaping stage includes an output of a final iteration of the quantity of iterations of the clipping operation.
-

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 illustrates an example of a wireless communications system that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure.
- (2) FIGS. 2A and 2B illustrate examples of systems that support improved techniques for waveform compression in accordance with one or more aspects of the present disclosure.
- (3) FIGS. 3A and 3B illustrate examples of subsystems that support improved techniques for waveform compression in accordance with one or more aspects of the present disclosure.
- (4) FIG. 4 illustrates an example of a subsystem that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure.
- (5) FIGS. 5 and 6 show block diagrams of devices that support improved techniques for waveform compression in accordance with one or more aspects of the present disclosure.
- (6) FIG. 7 shows a block diagram of a communications manager that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure.
- (7) FIG. 8 shows a diagram of a system including a device that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure.
- (8) FIGS. 9 and 10 show flowcharts illustrating methods that support improved techniques for

waveform compression in accordance with one or more aspects of the present disclosure.

DETAILED DESCRIPTION

(9) A wireless communications system may support wireless communications between network devices. For example, a user equipment (UE) may transmit uplink signaling to a network entity. In some cases, a signal, such as an uplink signal transmitted by the UE, may be referred to as a waveform. The term “waveform” may refer to a shape of the signal taken with respect to time (e.g., an amplitude of the signal with respect to time). In some cases, it may be desirable to increase a range (e.g., transmission distance) of a signal, however, some techniques for increasing the range of the signal may result in undesirable waveform properties. For example, a UE may increase a power output or a gain for a signal, however, as a result of increasing the power output or the gain, a peak-to-average power ratio (PAPR), an adjacent channel leakage ratio (ACLR), an in-band emissions (IBE) ratio, or any combination thereof for the waveform may be negatively affected.

(10) In accordance with aspects of the present disclosure, a network device may perform one or more operations to increase a range of a signal (e.g., a transmitted waveform) without negatively affecting a PAPR, ACLR and IBE for the signal. In some cases, the waveform may include intermodulation distortion (IMD), however, a receiver may be configured to process (e.g., decode) the waveform with IMD. In some cases, the one or more operations performed by the network device may include a first stage and a second stage. The first stage may include performing an interference cancelling operation to increase an IBE ratio of the waveform and performing a clipping operation to reduce a PAPR of the waveform. The second stage may include performing a frequency selective filtering operation to reduce an ACLR of the waveform. As a result of performing the operations for the first stage and the second stage, a range of the waveform may be increased.

(11) Aspects of the disclosure are initially described in the context of wireless communications system with reference to FIG. 1. Features of the disclosure are described in the context of systems and subsystems with reference to FIGS. 2A through 4. Aspects of the disclosure are further illustrated by and described with reference to apparatus diagrams, system diagrams, and flowcharts that relate to improved techniques for waveform compression with reference to FIGS. 5 through 10.

(12) FIG. 1 illustrates an example of a wireless communications system **100** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The wireless communications system **100** may include one or more network entities **105**, one or more UEs **115**, and a core network **130**. In some examples, the wireless communications system **100** may be a Long Term Evolution (LTE) network, an LTE-Advanced (LTE-A) network, an LTE-A Pro network, a New Radio (NR) network, or a network operating in accordance with other systems and radio technologies, including future systems and radio technologies not explicitly mentioned herein.

(13) The network entities **105** may be dispersed throughout a geographic area to form the wireless communications system **100** and may include devices in different forms or having different capabilities. In various examples, a network entity **105** may be referred to as a network element, a mobility element, a radio access network (RAN) node, or network equipment, among other nomenclature. In some examples, network entities **105** and UEs **115** may wirelessly communicate via one or more communication links **125** (e.g., a radio frequency (RF) access link). For example, a network entity **105** may support a coverage area **110** (e.g., a geographic coverage area) over which the UEs **115** and the network entity **105** may establish one or more communication links **125**. The coverage area **110** may be an example of a geographic area over which a network entity **105** and a UE **115** may support the communication of signals according to one or more radio access technologies (RATs).

(14) The UEs **115** may be dispersed throughout a coverage area **110** of the wireless communications system **100**, and each UE **115** may be stationary, or mobile, or both at different times. The UEs **115** may be devices in different forms or having different capabilities. Some

example UEs **115** are illustrated in FIG. 1. The UEs **115** described herein may be capable of supporting communications with various types of devices, such as other UEs **115** or network entities **105**, as shown in FIG. 1.

(15) As described herein, a node of the wireless communications system **100**, which may be referred to as a network node, or a wireless node, may be a network entity **105** (e.g., any network entity described herein), a UE **115** (e.g., any UE described herein), a network controller, an apparatus, a device, a computing system, one or more components, or another suitable processing entity configured to perform any of the techniques described herein. For example, a node may be a UE **115**. As another example, a node may be a network entity **105**. As another example, a first node may be configured to communicate with a second node or a third node. In one aspect of this example, the first node may be a UE **115**, the second node may be a network entity **105**, and the third node may be a UE **115**. In another aspect of this example, the first node may be a UE **115**, the second node may be a network entity **105**, and the third node may be a network entity **105**. In yet other aspects of this example, the first, second, and third nodes may be different relative to these examples. Similarly, reference to a UE **115**, network entity **105**, apparatus, device, computing system, or the like may include disclosure of the UE **115**, network entity **105**, apparatus, device, computing system, or the like being a node. For example, disclosure that a UE **115** is configured to receive information from a network entity **105** also discloses that a first node is configured to receive information from a second node.

(16) In some examples, network entities **105** may communicate with the core network **130**, or with one another, or both. For example, network entities **105** may communicate with the core network **130** via one or more backhaul communication links **120** (e.g., in accordance with an S1, N2, N3, or other interface protocol). In some examples, network entities **105** may communicate with one another via a backhaul communication link **120** (e.g., in accordance with an X2, Xn, or other interface protocol) either directly (e.g., directly between network entities **105**) or indirectly (e.g., via a core network **130**). In some examples, network entities **105** may communicate with one another via a midhaul communication link **162** (e.g., in accordance with a midhaul interface protocol) or a fronthaul communication link **168** (e.g., in accordance with a fronthaul interface protocol), or any combination thereof. The backhaul communication links **120**, midhaul communication links **162**, or fronthaul communication links **168** may be or include one or more wired links (e.g., an electrical link, an optical fiber link), one or more wireless links (e.g., a radio link, a wireless optical link), among other examples or various combinations thereof. A UE **115** may communicate with the core network **130** via a communication link **155**.

(17) One or more of the network entities **105** described herein may include or may be referred to as a base station **140** (e.g., a base transceiver station, a radio base station, an NR base station, an access point, a radio transceiver, a NodeB, an eNodeB (eNB), a next-generation NodeB or a giga-NodeB (either of which may be referred to as a gNB), a 5G NB, a next-generation eNB (ng-eNB), a Home NodeB, a Home eNodeB, or other suitable terminology). In some examples, a network entity **105** (e.g., a base station **140**) may be implemented in an aggregated (e.g., monolithic, standalone) base station architecture, which may be configured to utilize a protocol stack that is physically or logically integrated within a single network entity **105** (e.g., a single RAN node, such as a base station **140**).

(18) In some examples, a network entity **105** may be implemented in a disaggregated architecture (e.g., a disaggregated base station architecture, a disaggregated RAN architecture), which may be configured to utilize a protocol stack that is physically or logically distributed among two or more network entities **105**, such as an integrated access backhaul (IAB) network, an open RAN (O-RAN) (e.g., a network configuration sponsored by the O-RAN Alliance), or a virtualized RAN (vRAN) (e.g., a cloud RAN (C-RAN)). For example, a network entity **105** may include one or more of a central unit (CU) **160**, a distributed unit (DU) **165**, a radio unit (RU) **170**, a RAN Intelligent Controller (RIC) **175** (e.g., a Near-Real Time RIC (Near-RT RIC), a Non-Real Time RIC (Non-RT

RIC)), a Service Management and Orchestration (SMO) **180** system, or any combination thereof. An RU **170** may also be referred to as a radio head, a smart radio head, a remote radio head (RRH), a remote radio unit (RRU), or a transmission reception point (TRP). One or more components of the network entities **105** in a disaggregated RAN architecture may be co-located, or one or more components of the network entities **105** may be located in distributed locations (e.g., separate physical locations). In some examples, one or more network entities **105** of a disaggregated RAN architecture may be implemented as virtual units (e.g., a virtual CU (VCU), a virtual DU (VDU), a virtual RU (VRU)).

(19) The split of functionality between a CU **160**, a DU **165**, and an RU **170** is flexible and may support different functionalities depending upon which functions (e.g., network layer functions, protocol layer functions, baseband functions, RF functions, and any combinations thereof) are performed at a CU **160**, a DU **165**, or an RU **170**. For example, a functional split of a protocol stack may be employed between a CU **160** and a DU **165** such that the CU **160** may support one or more layers of the protocol stack and the DU **165** may support one or more different layers of the protocol stack. In some examples, the CU **160** may host upper protocol layer (e.g., layer 3 (L3), layer 2 (L2)) functionality and signaling (e.g., Radio Resource Control (RRC), service data adaptation protocol (SDAP), Packet Data Convergence Protocol (PDCP)). The CU **160** may be connected to one or more DUs **165** or RUs **170**, and the one or more DUs **165** or RUs **170** may host lower protocol layers, such as layer 1 (L1) (e.g., physical (PHY) layer) or L2 (e.g., radio link control (RLC) layer, medium access control (MAC) layer) functionality and signaling, and may each be at least partially controlled by the CU **160**. Additionally, or alternatively, a functional split of the protocol stack may be employed between a DU **165** and an RU **170** such that the DU **165** may support one or more layers of the protocol stack and the RU **170** may support one or more different layers of the protocol stack. The DU **165** may support one or multiple different cells (e.g., via one or more RUs **170**). In some cases, a functional split between a CU **160** and a DU **165**, or between a DU **165** and an RU **170** may be within a protocol layer (e.g., some functions for a protocol layer may be performed by one of a CU **160**, a DU **165**, or an RU **170**, while other functions of the protocol layer are performed by a different one of the CU **160**, the DU **165**, or the RU **170**). A CU **160** may be functionally split further into CU control plane (CU-CP) and CU user plane (CU-UP) functions. A CU **160** may be connected to one or more DUs **165** via a midhaul communication link **162** (e.g., F1, F1-c, F1-u), and a DU **165** may be connected to one or more RUs **170** via a fronthaul communication link **168** (e.g., open fronthaul (FH) interface). In some examples, a midhaul communication link **162** or a fronthaul communication link **168** may be implemented in accordance with an interface (e.g., a channel) between layers of a protocol stack supported by respective network entities **105** that are in communication via such communication links.

(20) In wireless communications systems (e.g., wireless communications system **100**), infrastructure and spectral resources for radio access may support wireless backhaul link capabilities to supplement wired backhaul connections, providing an IAB network architecture (e.g., to a core network **130**). In some cases, in an IAB network, one or more network entities **105** (e.g., IAB nodes **104**) may be partially controlled by each other. One or more IAB nodes **104** may be referred to as a donor entity or an IAB donor. One or more DUs **165** or one or more RUs **170** may be partially controlled by one or more CUs **160** associated with a donor network entity **105** (e.g., a donor base station **140**). The one or more donor network entities **105** (e.g., IAB donors) may be in communication with one or more additional network entities **105** (e.g., IAB nodes **104**) via supported access and backhaul links (e.g., backhaul communication links **120**). IAB nodes **104** may include an IAB mobile termination (IAB-MT) controlled (e.g., scheduled) by DUs **165** of a coupled IAB donor. An IAB-MT may include an independent set of antennas for relay of communications with UEs **115**, or may share the same antennas (e.g., of an RU **170**) of an IAB node **104** used for access via the DU **165** of the IAB node **104** (e.g., referred to as virtual IAB-MT

(vIAB-MT)). In some examples, the IAB nodes **104** may include DUs **165** that support communication links with additional entities (e.g., IAB nodes **104**, UEs **115**) within the relay chain or configuration of the access network (e.g., downstream). In such cases, one or more components of the disaggregated RAN architecture (e.g., one or more IAB nodes **104** or components of IAB nodes **104**) may be configured to operate according to the techniques described herein.

(21) In the case of the techniques described herein applied in the context of a disaggregated RAN architecture, one or more components of the disaggregated RAN architecture may be configured to support improved techniques for waveform compression as described herein. For example, some operations described as being performed by a UE **115** or a network entity **105** (e.g., a base station **140**) may additionally, or alternatively, be performed by one or more components of the disaggregated RAN architecture (e.g., IAB nodes **104**, DUs **165**, CUs **160**, RUs **170**, RIC **175**, SMO **180**).

(22) A UE **115** may include or may be referred to as a mobile device, a wireless device, a remote device, a handheld device, or a subscriber device, or some other suitable terminology, where the “device” may also be referred to as a unit, a station, a terminal, or a client, among other examples. A UE **115** may also include or may be referred to as a personal electronic device such as a cellular phone, a personal digital assistant (PDA), a tablet computer, a laptop computer, or a personal computer. In some examples, a UE **115** may include or be referred to as a wireless local loop (WLL) station, an Internet of Things (IoT) device, an Internet of Everything (IoE) device, or a machine type communications (MTC) device, among other examples, which may be implemented in various objects such as appliances, or vehicles, meters, among other examples.

(23) The UEs **115** described herein may be able to communicate with various types of devices, such as other UEs **115** that may sometimes act as relays as well as the network entities **105** and the network equipment including macro eNBs or gNBs, small cell eNBs or gNBs, or relay base stations, among other examples, as shown in FIG. 1.

(24) The UEs **115** and the network entities **105** may wirelessly communicate with one another via one or more communication links **125** (e.g., an access link) using resources associated with one or more carriers. The term “carrier” may refer to a set of RF spectrum resources having a defined physical layer structure for supporting the communication links **125**. For example, a carrier used for a communication link **125** may include a portion of a RF spectrum band (e.g., a bandwidth part (BWP)) that is operated according to one or more physical layer channels for a given radio access technology (e.g., LTE, LTE-A, LTE-A Pro, NR). Each physical layer channel may carry acquisition signaling (e.g., synchronization signals, system information), control signaling that coordinates operation for the carrier, user data, or other signaling. The wireless communications system **100** may support communication with a UE **115** using carrier aggregation or multi-carrier operation. A UE **115** may be configured with multiple downlink component carriers and one or more uplink component carriers according to a carrier aggregation configuration. Carrier aggregation may be used with both frequency division duplexing (FDD) and time division duplexing (TDD) component carriers. Communication between a network entity **105** and other devices may refer to communication between the devices and any portion (e.g., entity, sub-entity) of a network entity **105**. For example, the terms “transmitting,” “receiving,” or “communicating,” when referring to a network entity **105**, may refer to any portion of a network entity **105** (e.g., a base station **140**, a CU **160**, a DU **165**, a RU **170**) of a RAN communicating with another device (e.g., directly or via one or more other network entities **105**).

(25) Signal waveforms transmitted via a carrier may be made up of multiple subcarriers (e.g., using multi-carrier modulation (MCM) techniques such as orthogonal frequency division multiplexing (OFDM) or discrete Fourier transform spread OFDM (DFT-S-OFDM)). In a system employing MCM techniques, a resource element may refer to resources of one symbol period (e.g., a duration of one modulation symbol) and one subcarrier, in which case the symbol period and subcarrier spacing may be inversely related. The quantity of bits carried by each resource element may

depend on the modulation scheme (e.g., the order of the modulation scheme, the coding rate of the modulation scheme, or both), such that a relatively higher quantity of resource elements (e.g., in a transmission duration) and a relatively higher order of a modulation scheme may correspond to a relatively higher rate of communication. A wireless communications resource may refer to a combination of an RF spectrum resource, a time resource, and a spatial resource (e.g., a spatial layer, a beam), and the use of multiple spatial resources may increase the data rate or data integrity for communications with a UE **115**.

(26) The time intervals for the network entities **105** or the UEs **115** may be expressed in multiples of a basic time unit which may, for example, refer to a sampling period of $T_{\text{sub}} = 1/(\Delta f_{\text{sub}} \cdot N_{\text{sub}} \cdot f)$ seconds, for which Δf_{sub} may represent a supported subcarrier spacing, and $N_{\text{sub}} \cdot f$ may represent a supported discrete Fourier transform (DFT) size. Time intervals of a communications resource may be organized according to radio frames each having a specified duration (e.g., 10 milliseconds (ms)). Each radio frame may be identified by a system frame number (SFN) (e.g., ranging from 0 to 1023).

(27) Each frame may include multiple consecutively-numbered subframes or slots, and each subframe or slot may have the same duration. In some examples, a frame may be divided (e.g., in the time domain) into subframes, and each subframe may be further divided into a quantity of slots. Alternatively, each frame may include a variable quantity of slots, and the quantity of slots may depend on subcarrier spacing. Each slot may include a quantity of symbol periods (e.g., depending on the length of the cyclic prefix prepended to each symbol period). In some wireless communications systems **100**, a slot may further be divided into multiple mini-slots associated with one or more symbols. Excluding the cyclic prefix, each symbol period may be associated with one or more (e.g., $N_{\text{sub}} \cdot f$) sampling periods. The duration of a symbol period may depend on the subcarrier spacing or frequency band of operation.

(28) A subframe, a slot, a mini-slot, or a symbol may be the smallest scheduling unit (e.g., in the time domain) of the wireless communications system **100** and may be referred to as a transmission time interval (TTI). In some examples, the TTI duration (e.g., a quantity of symbol periods in a TTI) may be variable. Additionally, or alternatively, the smallest scheduling unit of the wireless communications system **100** may be dynamically selected (e.g., in bursts of shortened TTIs (sTTIs)).

(29) Physical channels may be multiplexed for communication using a carrier according to various techniques. A physical control channel and a physical data channel may be multiplexed for signaling via a downlink carrier, for example, using one or more of time division multiplexing (TDM) techniques, frequency division multiplexing (FDM) techniques, or hybrid TDM-FDM techniques. A control region (e.g., a control resource set (CORESET)) for a physical control channel may be defined by a set of symbol periods and may extend across the system bandwidth or a subset of the system bandwidth of the carrier. One or more control regions (e.g., CORESETs) may be configured for a set of the UEs **115**. For example, one or more of the UEs **115** may monitor or search control regions for control information according to one or more search space sets, and each search space set may include one or multiple control channel candidates in one or more aggregation levels arranged in a cascaded manner. An aggregation level for a control channel candidate may refer to an amount of control channel resources (e.g., control channel elements (CCEs)) associated with encoded information for a control information format having a given payload size. Search space sets may include common search space sets configured for sending control information to multiple UEs **115** and UE-specific search space sets for sending control information to a specific UE **115**.

(30) In some examples, a network entity **105** (e.g., a base station **140**, an RU **170**) may be movable and therefore provide communication coverage for a moving coverage area **110**. In some examples, different coverage areas **110** associated with different technologies may overlap, but the different coverage areas **110** may be supported by the same network entity **105**. In some other examples, the

overlapping coverage areas **110** associated with different technologies may be supported by different network entities **105**. The wireless communications system **100** may include, for example, a heterogeneous network in which different types of the network entities **105** provide coverage for various coverage areas **110** using the same or different radio access technologies.

(31) The wireless communications system **100** may be configured to support ultra-reliable communications or low-latency communications, or various combinations thereof. For example, the wireless communications system **100** may be configured to support ultra-reliable low-latency communications (URLLC). The UEs **115** may be designed to support ultra-reliable, low-latency, or critical functions. Ultra-reliable communications may include private communication or group communication and may be supported by one or more services such as push-to-talk, video, or data. Support for ultra-reliable, low-latency functions may include prioritization of services, and such services may be used for public safety or general commercial applications. The terms ultra-reliable, low-latency, and ultra-reliable low-latency may be used interchangeably herein.

(32) In some examples, a UE **115** may be configured to support communicating directly with other UEs **115** via a device-to-device (D2D) communication link **135** (e.g., in accordance with a peer-to-peer (P2P), D2D, or sidelink protocol). In some examples, one or more UEs **115** of a group that are performing D2D communications may be within the coverage area **110** of a network entity **105** (e.g., a base station **140**, an RU **170**), which may support aspects of such D2D communications being configured by (e.g., scheduled by) the network entity **105**. In some examples, one or more UEs **115** of such a group may be outside the coverage area **110** of a network entity **105** or may be otherwise unable to or not configured to receive transmissions from a network entity **105**. In some examples, groups of the UEs **115** communicating via D2D communications may support a one-to-many (1:M) system in which each UE **115** transmits to each of the other UEs **115** in the group. In some examples, a network entity **105** may facilitate the scheduling of resources for D2D communications. In some other examples, D2D communications may be carried out between the UEs **115** without an involvement of a network entity **105**.

(33) The core network **130** may provide user authentication, access authorization, tracking, Internet Protocol (IP) connectivity, and other access, routing, or mobility functions. The core network **130** may be an evolved packet core (EPC) or 5G core (5GC), which may include at least one control plane entity that manages access and mobility (e.g., a mobility management entity (MME), an access and mobility management function (AMF)) and at least one user plane entity that routes packets or interconnects to external networks (e.g., a serving gateway (S-GW), a Packet Data Network (PDN) gateway (P-GW), or a user plane function (UPF)). The control plane entity may manage non-access stratum (NAS) functions such as mobility, authentication, and bearer management for the UEs **115** served by the network entities **105** (e.g., base stations **140**) associated with the core network **130**. User IP packets may be transferred through the user plane entity, which may provide IP address allocation as well as other functions. The user plane entity may be connected to IP services **150** for one or more network operators. The IP services **150** may include access to the Internet, Intranet(s), an IP Multimedia Subsystem (IMS), or a Packet-Switched Streaming Service.

(34) The wireless communications system **100** may operate using one or more frequency bands, which may be in the range of 300 megahertz (MHz) to 300 gigahertz (GHz). Generally, the region from 300 MHz to 3 GHz is known as the ultra-high frequency (UHF) region or decimeter band because the wavelengths range from approximately one decimeter to one meter in length. UHF waves may be blocked or redirected by buildings and environmental features, which may be referred to as clusters, but the waves may penetrate structures sufficiently for a macro cell to provide service to the UEs **115** located indoors. Communications using UHF waves may be associated with smaller antennas and shorter ranges (e.g., less than 100 kilometers) compared to communications using the smaller frequencies and longer waves of the high frequency (HF) or very high frequency (VHF) portion of the spectrum below 300 MHz.

(35) The wireless communications system **100** may utilize both licensed and unlicensed RF spectrum bands. For example, the wireless communications system **100** may employ License Assisted Access (LAA), LTE-Unlicensed (LTE-U) radio access technology, or NR technology using an unlicensed band such as the 5 GHz industrial, scientific, and medical (ISM) band. While operating using unlicensed RF spectrum bands, devices such as the network entities **105** and the UEs **115** may employ carrier sensing for collision detection and avoidance. In some examples, operations using unlicensed bands may be based on a carrier aggregation configuration in conjunction with component carriers operating using a licensed band (e.g., LAA). Operations using unlicensed spectrum may include downlink transmissions, uplink transmissions, P2P transmissions, or D2D transmissions, among other examples.

(36) A network entity **105** (e.g., a base station **140**, an RU **170**) or a UE **115** may be equipped with multiple antennas, which may be used to employ techniques such as transmit diversity, receive diversity, multiple-input multiple-output (MIMO) communications, or beamforming. The antennas of a network entity **105** or a UE **115** may be located within one or more antenna arrays or antenna panels, which may support MIMO operations or transmit or receive beamforming. For example, one or more base station antennas or antenna arrays may be co-located at an antenna assembly, such as an antenna tower. In some examples, antennas or antenna arrays associated with a network entity **105** may be located at diverse geographic locations. A network entity **105** may include an antenna array with a set of rows and columns of antenna ports that the network entity **105** may use to support beamforming of communications with a UE **115**. Likewise, a UE **115** may include one or more antenna arrays that may support various MIMO or beamforming operations. Additionally, or alternatively, an antenna panel may support RF beamforming for a signal transmitted via an antenna port.

(37) Beamforming, which may also be referred to as spatial filtering, directional transmission, or directional reception, is a signal processing technique that may be used at a transmitting device or a receiving device (e.g., a network entity **105**, a UE **115**) to shape or steer an antenna beam (e.g., a transmit beam, a receive beam) along a spatial path between the transmitting device and the receiving device. Beamforming may be achieved by combining the signals communicated via antenna elements of an antenna array such that some signals propagating along particular orientations with respect to an antenna array experience constructive interference while others experience destructive interference. The adjustment of signals communicated via the antenna elements may include a transmitting device or a receiving device applying amplitude offsets, phase offsets, or both to signals carried via the antenna elements associated with the device. The adjustments associated with each of the antenna elements may be defined by a beamforming weight set associated with a particular orientation (e.g., with respect to the antenna array of the transmitting device or receiving device, or with respect to some other orientation).

(38) As described herein, the UE **115**, the network entity **105**, or both, may be configured for high data rate communications. For example, the UE **115** may modulate waveforms for wireless communications using quadrature amplitude modulation (QAM), which may have a higher data rate than quadrature phase shift keying (QPSK) modulation. In some cases, for high data rate communications, a network device (e.g., the UE **115**, the network entity **105**, or both) may reduce a gain of a PA to improve signal quality. However, reducing the gain of the PA may reduce a range of the signal.

(39) In accordance with aspects of the present disclosure, a UE **115**, a network entity **105**, or both may perform waveform shaping operations to increase a quality of a signal. For example, the UE **115** may perform the waveform shaping operations to mitigate negative effects of increasing PA output and meet performance targets for the signal. The waveform shaping operations may include a clipping operation to reduce a PAPR of a waveform, an interference cancelling operation to increase an IBE ratio of the waveform, and an ACLR correction operation to increase ACLR of the waveform. Accordingly, the range of the signal may be increased without reducing a quality of the

signal.

(40) FIG. 2A illustrates an example of a system **200-a** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The system **200-a** may be implemented by aspects of the wireless communications system **100**. For example, the system **200-a** may be implemented by a UE **115** or a network entity **105**, as described with reference to FIG. 1. The system **200-a** may include one or more components (e.g., hardware components) installed at a UE **115** or a network entity **105** for processing wireless communications signals. For example, the system **200-a** may include an input signal generator **210**, an interference canceller **215**, a clipper **220**, an ACLR correction component **225**, and a cyclic prefix (CP) component **230**. These components may be implemented as, for example, a first waveform shaping stage **205-a** and a second waveform shaping stage **205-b**. In some cases, the first waveform shaping stage **205-a** may be performed prior to the second waveform shaping stage **205-b**.

(41) In some cases, a signal may be amplified using a power amplifier (PA). For example, a UE **115** may amplify a signal for wireless communications using a PA. The PA may have an efficiency, which may be referred to as power-added efficiency (PAE). In some cases, the input signal generator **210** may include one or more PAs, which may amplify a signal. In some other cases, a signal may be amplified by a PA that is not included in the input signal generator **210**. For example, the first waveform shaping stage **205-a**, the second waveform shaping stage **205-b**, or both, may include one or more PAs. Additionally or alternatively, a UE **115** may utilize one or more PAs to amplify an output of the CP component **230**. In some cases, a range of the signal may be based on a configuration (e.g., a setting, a parameter) of the PA. For example, increasing a gain of a PA may increase a range of a signal output by the PA. Additionally or alternatively, operation of a PA may be based on a maximum power reduction (MPR), which may be a setting or a parameter of a PA. The MPR may specify an extent to which an output of a PA is reduced (e.g., a reduction of a maximum power level). In some cases, increasing an MPR for a PA may reduce a range of a signal output by the PA.

(42) Amplifying a signal (e.g., via a PA) without performing a multi-stage waveform shaping process may negatively impact one or more signal quality metrics (e.g., non-linearity of the signal may be increased, intermodulation distortion (IMD) of the signal may be increased). For example, amplifying a signal may reduce signal quality if the signal is not effectively compressed. In some cases, amplifying a signal may increase a PAPR, decrease an IBE ratio, decrease an ACLR, and decrease an error vector magnitude (EVM) for the signal. In some cases, amplifying the signal may degrade signal quality to the extent that a receiver (e.g., a network entity **105**) may be unable to decode the signal. For example, a network entity may not be configured to receive or process non-linear signaling. Accordingly, an output of a PA may be reduced to increase signal quality at a transmitter (e.g., increasing MPR may reduce signal power and may increase signal quality). For example, a UE **115** may reduce a gain for a PA to improve signal quality. However, reducing an output of a PA may reduce a range of the signal, which may be undesirable.

(43) In some cases, a network device (e.g., a UE **115** or a network entity **105**) may modulate a signal according to a modulation scheme. In some cases, a data rate for a wireless communications signal may be based on a modulation scheme. For example, a UE **115** may modulate a signal using QPSK, QAM, or any other modulation scheme. In some cases, a data rate for QAM may be higher than a data rate for QPSK. In some cases, a network device may determine a modulation scheme based on operating conditions. For example, if operating conditions are relatively favorable, a UE **115** may determine to use a modulation scheme associated with a relatively high data rate. In some cases, a UE **115** may be unable to communicate high data rate signaling if an SNR is not sufficiently high. Accordingly, for modulation schemes associated with high data rates (e.g., 256QAM), a network device may reduce an output of a PA (e.g., increase MPR) to increase signal quality. However, reducing the output of the PA may decrease the range of the signal.

(44) In accordance with aspects of the present disclosure a network device (e.g., a UE **115** or a

network entity **105**) may increase a range of a signal by increasing an output of a PA and performing one or more waveform shaping operations to meet performance targets for the signal (e.g., to mitigate negative effects of increasing PA output). For example, the UE **115** may modulate the signal according to a modulation scheme (e.g., QAM256), which may traditionally be associated with a relatively high MPR, however, the UE **115** may select a decreased MPR to increase the range of the signal. The UE **115** may then perform one or more waveform shaping operations to minimize nonlinear effects of the increased power output of the PA. For example, the UE **115** may push IMD in-band while meeting out-of-band performance metrics. Accordingly, the range of the signal may be increased without negatively impacting one or more performance metrics. In some cases, the signal may be received by a network entity, which may be capable of receiving non-linear signaling. The network entity (e.g., the non-linear receiver) may perform one or more operations to increase an SNR of the signal.

(45) The system **200-a** may enable a network device (e.g., a UE **115**, a network entity **105**) to improve signal quality. For example, the system **200-a** may enable the network device to improve signal quality for signaling with high data rates and low MPRs. For example, the system **200-a** may improve PAPR, ACLR, and IBE ratio for the signal at higher levels of amplification. A UE **115** may use an input signal generator **210** to generate a waveform (e.g., with an increased power, with an increased range), use an interference canceller **215** and a clipper **220** to reduce a PAPR and increase an IBE ratio of the waveform, and use an ACLR correction component **225** to increase an ACLR of the waveform. That is, the input signal generator **210** may include one or more PAs, which may increase a power of the signal and the waveform shaping stages **205** may improve the signal quality. In some other cases, a power of the signal may be increase using one or more PAs not included in the input signal generator **210**. For example, a UE **115** may utilize one or more PAs to amplify an output of the CP component **230**. In such cases, the one or more PAs may be coupled with an output of the CP component **230**. In some cases, the UE **115** may use a CP component **230** to add a CP to the waveform. As a result of the operations performed during the first waveform shaping stage **205-a** and the second waveform shaping stage **205-b**, the range of the signal may be increased without negatively impacting PAPR, IBE ratio, and ACLR for the signal.

(46) In some cases, a first waveform shaping stage **205-a**, a second waveform shaping stage **205-b**, or both, may be performed iteratively (e.g., for a quantity of iterations). For example, the first waveform shaping stage **205-a** may include a feedback loop where the waveform output by the clipper **220** is fed back to an input of the interference canceller **215**. In some other cases, the feedback loop may not be utilized. For example, an output of the clipper **220** may not be fed back to the input of the interference canceller **215**. In some cases, the clipper **220** may perform a compression operation, which may reduce or clip peaks of a waveform. The clipper **220** may be an example of a hard clipper or a soft clipper. In some cases, the system **200-a** may include electronic couplings. For example, the input signal generator **210** may be electronically coupled with the interference canceller **215**. Similarly, the interference canceller may be electronically coupled with the clipper **220**, the clipper **220** may be electronically coupled with the ACLR correction component **225**, and the ACLR correction component **225** may be electronically coupled with the CP component **230**. In some other cases, the components included in the system **200-a** may be wirelessly coupled. The combination of the first waveform shaping stage **205-a** and the second waveform shaping stage **205-b** may be an example of a multi-stage signal compression technique (MASCOT).

(47) FIG. 2B illustrates an example of a system **200-b** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The system **200-b** may be implemented by aspects of the wireless communications system **100**. For example, the system **200-b** may be implemented by a UE **115** or a network entity **105**, as described with reference to FIG. 1. The system **200-b** may include one or more components (e.g., hardware components) installed at a UE **115** or a network entity **105** for processing wireless communications

signals. The one or more components may include an input signal generator **210**, an interference canceller **215**, a clipper **220**, an ACLR correction component **225**, and a CP component **230**, which may be examples of respective components as described with reference to FIG. 2A. These components may be implemented as, for example, a first waveform shaping stage **205-a** and a second waveform shaping stage **205-b**.

(48) In some cases, the system **200-b** may include a feedback loop that enables the clipper **220** to iteratively perform clipping operations on a waveform output by the interference canceller **215**. For example, the first waveform shaping stage **205-a** may include an electrical coupling between an output of the clipper **220** and an input of the clipper **220**. An output of the clipper **220** may be fed back (e.g., via the electrical coupling) to an input of the clipper **220**. That is, the clipper **220** may perform (e.g., iteratively) a quantity of clipping operations on an output of the interference canceller **215**. In some cases, the feedback loop (e.g., for the clipper **220**) may not be utilized. For example, an output of the clipper **220** may not be fed back to the input of the clipper **220**.

(49) Iteratively performing a quantity of clipping operations on the waveform output by the interference canceller **215** may reduce a PAPR of the waveform. In some cases, each clipping operation (e.g., each iteration of the clipping operation) may further reduce a PAPR of the waveform when compared to a previous iteration of the clipping operation. In some cases, a network device (e.g., a UE **115** or a network entity **105**) may determine a quantity of clipping operations for reducing a PAPR of a waveform such that the PAPR of the waveform is below a threshold PAPR. For example, a network device may activate one or more switching components which may couple an output of the clipper **220** with an input of the clipper **220** for a duration. In some cases, the network device may determine to perform a quantity of clipping operations on an output of the interference canceller **215**, which may reduce a PAPR of the output of the interference canceller **215**.

(50) FIG. 3A illustrates an example of a subsystem **300-a** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The subsystem **300-a** may be implemented by aspects of the wireless communications system **100**. For example, the subsystem **300-a** may be implemented by a UE **115** or a network entity **105**, as described with reference to FIG. 1. The subsystem **300-a** may include one or more components (e.g., hardware components) installed at a UE **115** or a network entity **105** for processing wireless communications signals. For example, the subsystem **300-a** may include a state expander **305**, an FFT component **310-a**, a frequency domain (FD) weighing component **315-a**, an iFFT component **320-a**, a clipper **220**, a multiplier **325**, and a summation block **330-a**.

(51) As described herein, the first waveform shaping stage **205-a** may include a clipper **220** and an interference canceller **215**, as described with reference to FIG. 2. In some cases, the interference canceller **215** may include the state expander **305**, the multiplier **325**, the FFT component **310-a**, the FD weighing component **315-a**, and the iFFT component **320-a**. In some cases, an output of the interference canceller **215** may be received by the summation block **330-a**. The summation block **330-a** may subtract the output of the interference canceller **215** (e.g., an output of the iFFT component **320-a**) from an output of the input signal generator **210** (e.g., a raw waveform).

(52) The interference canceller **215** may serve to increase an IBE ratio of a waveform. For example, the interference canceller **215** may receive an output of the input signal generator **210** and may perform one or more operations to increase the IBE ratio of the output of the input signal generator **210**. In some cases, the one or more operations to increase the IBE ratio may include a state expansion operation, an FFT operation, a FD weighing operation, and an iFFT operation. In some cases, the interference canceller **215** may include the multiplier **325**. The multiplier **325** may perform one or more operations to combine an output of the state expander **305** with one or more clipper kernels (e.g., Volterra memoryless hard clipper kernels normalized to a linear term).

(53) As described herein, the clipper **220** may perform one or more operations to reduce a PAPR of a waveform. For example, the clipper **220** may perform the one or more operations on an output of

the summation block **330-a**. The one or more operations may include one or more compression techniques, such as hard clipping or soft clipping. In some cases, a clipper **220** may flatten a portion of a signal that exceeds a threshold, which may reduce a difference between a maximum amplitude of the signal and an average amplitude of the signal. For example, the clipper **220** may reduce a dynamic range for a portion of a signal that exceeds the threshold. The gain may be reduced based on a parameter for compression. In some cases, the clipper **220** may reduce a gain or an amplitude for a portion of the signal based on a compression ratio. In some cases, a clipping level (e.g., a degree of compression) may be determined based on a type of a receiver that receives the output of the CP component **230** (e.g., a signal, a waveform). For example, a UE may select a clipping level for the clipper **220** based on determining that a receiving device, such as a network entity, is a non-linear receiving device or otherwise capable of receiving non-linear transmissions. (54) In some cases, the subsystem **300-a** may include electronic couplings. For example, the state expander **305** may be electronically coupled with the input signal generator **210**, the multiplier **325**, and the summation block **330-a**. Similarly, the FFT component **310-a** may be electronically coupled with the multiplier **325** and the FD weighing component **315-a**. The iFFT component **320-a** may be electronically coupled with the FD weighing component **315-a** and the summation block **330-a**. Additionally or alternatively, the clipper **220** may be electronically coupled with the summation block **330-a** and the ACLR correction component **225**.

(55) FIG. **3B** illustrates an example of a subsystem **300-b** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The subsystem **300-b** may be implemented by aspects of the wireless communications system **100**. For example, the subsystem **300-b** may be implemented by a UE **115** or a network entity **105**, as described with reference to FIG. **1**. The subsystem **300-b** may include one or more components (e.g., hardware components) installed at a UE **115** or a network entity **105** for processing wireless communications signals. For example, the subsystem **300-b** may include an FFT component **310-a**, a frequency domain (FD) weighing component **315-a**, an iFFT component **320-a**, a clipper **220**, a multiplier **325**, and a summation block **330-a**, which may be examples of respective components as described with reference to FIG. **3A**. Additionally, or alternatively, the subsystem **300-b** may include a clipper **335**. For example, the clipper **335** may be implemented as an alternative to the multiplier **325** and the state expander **305**.

(56) In some cases, the clipper **335** may reduce a complexity of the subsystem **300-b** (e.g., when compared to the subsystem **300-a**). The clipper **335** may reduce a PAPR of a waveform output by the input signal generator **210**, as described with reference to FIGS. **2A** and **2B**. That is, the clipper **335** may reduce the PAPR of the waveform output by the input signal generator **210** prior to being transmitted to the FFT component **310-a**. In some cases, the clipper **335** may be an example of the clipper **220** (e.g., the clipper **335** may not be different from the clipper **220**). In some other cases, the clipper **335** may be different from the clipper **220**. The clipper **335** may reduce a PAPR of a waveform prior to being transmitted to the clipper **220**, which may save power, processing resources, or both.

(57) FIG. **4** illustrates an example of a subsystem **400** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The subsystem **400** may be implemented by aspects of the wireless communications system **100**. For example, the subsystem **400** may be implemented by a UE **115** or a network entity **105**, as described with reference to FIG. **1**. The subsystem **400** may include one or more components (e.g., hardware components) installed at a UE **115** or a network entity **105** for processing wireless communications signals. For example, the subsystem **400** may include an FFT component **310-b**, an FD weighing component **315-b**, an iFFT component **320-b**, and a summation block **330-b**.

(58) As described herein, the second waveform shaping stage **205-b** may include or implement an ACLR correction component **225**, as described with reference to FIG. **2**. In such cases, the ACLR correction component **225** may include the FFT component **310-b**, the FD weighing component

315-b, and the iFFT component **320-b**. In some cases, an output of the ACLR correction component **225** (e.g., an output of the iFFT component **320-b**) may be received by the summation block **330-b**. The summation block **330-b** may combine the output of the ACLR correction component (e.g., an output of the iFFT component **320-b**) with an output of the clipper **220**. In some other cases, the summation block **330-b** may subtract the output of the ACLR correction component **225** from the output of the clipper **220**. In some cases, the second waveform shaping stage **205-b** may not include the summation block **330-b**. For example, an output of the clipper **220** may be transmitted directly to the FFT component **310-b**. Additionally, or alternatively, an output of the FFT component **310-b** may be transmitted directly to the FD weighing component **315-b**, an output of the FD weighing component **315-b** may be transmitted directly to the iFFT component **320-b**, and an output of the iFFT component **320-b** may then be transmitted to the CP component **230** (e.g., without being transmitted to a summation block **330-b**). In some cases, one or more components (e.g., of a UE) may receive an output of the second waveform shaping stage and perform up-conversion or other operations using a digital predistortion block (e.g., prior to the output of the second waveform shaping stage being amplified by a PA).

(59) The ACLR correction component **225** may serve to increase an ACLR of a waveform (e.g., based on an ACLR threshold or specification). For example, the ACLR correction component **225** may receive an output of the clipper **220** and may perform one or more operations to increase the ACLR ratio of the output of the clipper **220**. That is, the ACLR correction component **225** may reduce adjacent channel leakage. In some cases, the one or more operations to increase the ACLR may include an FFT operation, a FD weighing operation, and an iFFT operation. The FD weighing operation (e.g., performed by the FD weighing component **315-b**) may be based on a function including one or more configurable parameters (e.g., the FD weighing operation may be modular). In some cases, the FFT component **310-b** and the summation block **330-b** may receive the output of the clipper **220**.

(60) The one or more operations performed by the ACLR correction component **225** may include one or more compression techniques. In some cases, the subsystem **400** may include electronic couplings, which may be wireless couplings. For example, the FFT component **310-b** may be coupled with the FD weighing component **315-b** and the clipper **220**. Similarly, the iFFT component **320-b** may be electronically coupled with the FD weighing component **315-b** and the summation block **330-b**. In some cases, the summation block **330-b** may be electronically coupled with the clipper **220** and the CP component **230**.

(61) In some cases, the second waveform shaping stage **205-b** may be optional (e.g., the second waveform shaping stage **205-b** may be omitted). For example, it may be desirable under some circumstances to reduce a complexity of a system **200**, as described with reference to FIG. 2. In such cases, one or more components of a system **200** may be omitted or modified. For example, the system **200-b** may include a feedback loop for a clipper **220**. Based on including the feedback loop, the system **200-b** may be modified to omit the second waveform shaping stage **205-b**. Additionally, or alternatively, a subsystem **300-b** may include a clipper **335**. Based on including the clipper **335**, the subsystem **300-b** may be modified to omit the second waveform shaping stage **205-b**. In some cases, omitting the second waveform shaping stage **205-b** may reduce a complexity of a system **200** or a subsystem **300**. In some cases, the second waveform shaping stage **205-b** may be modified to include a finite impulse response (FIR) filter (not shown) (e.g., instead of the FFT component **310-b**, the FD weighing component **315-b**, the iFFT component **320-b**, and the summation block **330-b**).

(62) FIG. 5 shows a block diagram **500** of a device **505** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The device **505** may be an example of aspects of a UE **115** as described herein. The device **505** may include a receiver **510**, a transmitter **515**, and a communications manager **520**. The device **505** may also include a processor. Each of these components may be in communication with one another

(e.g., via one or more buses).

(63) The receiver **510** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to improved techniques for waveform compression). Information may be passed on to other components of the device **505**. The receiver **510** may utilize a single antenna or a set of multiple antennas.

(64) The transmitter **515** may provide a means for transmitting signals generated by other components of the device **505**. For example, the transmitter **515** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to improved techniques for waveform compression). In some examples, the transmitter **515** may be co-located with a receiver **510** in a transceiver module. The transmitter **515** may utilize a single antenna or a set of multiple antennas.

(65) The communications manager **520**, the receiver **510**, the transmitter **515**, or various combinations thereof or various components thereof may be examples of means for performing various aspects of improved techniques for waveform compression as described herein. For example, the communications manager **520**, the receiver **510**, the transmitter **515**, or various combinations or components thereof may support a method for performing one or more of the functions described herein.

(66) In some examples, the communications manager **520**, the receiver **510**, the transmitter **515**, or various combinations or components thereof may be implemented in hardware (e.g., in communications management circuitry). The hardware may include a processor, a digital signal processor (DSP), a central processing unit (CPU), an application-specific integrated circuit (ASIC), a field-programmable gate array (FPGA) or other programmable logic device, a microcontroller, discrete gate or transistor logic, discrete hardware components, or any combination thereof configured as or otherwise supporting a means for performing the functions described in the present disclosure. In some examples, a processor and memory coupled with the processor may be configured to perform one or more of the functions described herein (e.g., by executing, by the processor, instructions stored in the memory).

(67) Additionally, or alternatively, in some examples, the communications manager **520**, the receiver **510**, the transmitter **515**, or various combinations or components thereof may be implemented in code (e.g., as communications management software or firmware) executed by a processor. If implemented in code executed by a processor, the functions of the communications manager **520**, the receiver **510**, the transmitter **515**, or various combinations or components thereof may be performed by a general-purpose processor, a DSP, a CPU, an ASIC, an FPGA, a microcontroller, or any combination of these or other programmable logic devices (e.g., configured as or otherwise supporting a means for performing the functions described in the present disclosure).

(68) In some examples, the communications manager **520** may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **510**, the transmitter **515**, or both. For example, the communications manager **520** may receive information from the receiver **510**, send information to the transmitter **515**, or be integrated in combination with the receiver **510**, the transmitter **515**, or both to obtain information, output information, or perform various other operations as described herein.

(69) The communications manager **520** may support wireless communications at a UE in accordance with examples as disclosed herein. For example, the communications manager **520** may be configured as or otherwise support a means for generating an input signal including information for transmission over a wireless channel. The communications manager **520** may be configured as or otherwise support a means for performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage

includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal. The communications manager **520** may be configured as or otherwise support a means for performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage. The communications manager **520** may be configured as or otherwise support a means for transmitting a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage.

(70) By including or configuring the communications manager **520** in accordance with examples as described herein, the device **505** (e.g., a processor controlling or otherwise coupled with the receiver **510**, the transmitter **515**, the communications manager **520**, or a combination thereof) may support techniques for increasing PAE. For example, the device **505** may support techniques for improving signaling quality, which may enable the device **505** to reduce power consumption of the device. Additionally or alternatively, the device **505** may support techniques for improving signal quality associated with high data rate communications. Accordingly, communication resources may be utilized more efficiently. For example, the device **505** may perform waveform shaping operations to reduce PAPR, increase IBE, and increase ACLR, which may improve signal quality.

(71) FIG. **6** shows a block diagram **600** of a device **605** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The device **605** may be an example of aspects of a device **505** or a UE **115** as described herein. The device **605** may include a receiver **610**, a transmitter **615**, and a communications manager **620**. The device **605** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(72) The receiver **610** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to improved techniques for waveform compression). Information may be passed on to other components of the device **605**. The receiver **610** may utilize a single antenna or a set of multiple antennas.

(73) The transmitter **615** may provide a means for transmitting signals generated by other components of the device **605**. For example, the transmitter **615** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to improved techniques for waveform compression). In some examples, the transmitter **615** may be co-located with a receiver **610** in a transceiver module. The transmitter **615** may utilize a single antenna or a set of multiple antennas.

(74) The device **605**, or various components thereof, may be an example of means for performing various aspects of improved techniques for waveform compression as described herein. For example, the communications manager **620** may include an input signal generator **625**, a first waveform shaping stage component **630**, a second waveform shaping stage component **635**, a signal transmitter **640**, or any combination thereof. The communications manager **620** may be an example of aspects of a communications manager **520** as described herein. In some examples, the communications manager **620**, or various components thereof, may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **610**, the transmitter **615**, or both. For example, the communications manager **620** may receive information from the receiver **610**, send information to the transmitter **615**, or be integrated in combination with the receiver **610**, the transmitter **615**, or both to obtain information, output information, or perform various other operations as described herein.

(75) The communications manager **620** may support wireless communications at a UE in accordance with examples as disclosed herein. The input signal generator **625** may be configured

as or otherwise support a means for generating an input signal including information for transmission over a wireless channel. The first waveform shaping stage component **630** may be configured as or otherwise support a means for performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal. The second waveform shaping stage component **635** may be configured as or otherwise support a means for performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage. The signal transmitter **640** may be configured as or otherwise support a means for transmitting a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage. (76) FIG. 7 shows a block diagram **700** of a communications manager **720** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The communications manager **720** may be an example of aspects of a communications manager **520**, a communications manager **620**, or both, as described herein. The communications manager **720**, or various components thereof, may be an example of means for performing various aspects of improved techniques for waveform compression as described herein. For example, the communications manager **720** may include an input signal generator **725**, a first waveform shaping stage component **730**, a second waveform shaping stage component **735**, a signal transmitter **740**, or any combination thereof. Each of these components may communicate, directly or indirectly, with one another (e.g., via one or more buses).

(77) The communications manager **720** may support wireless communications at a UE in accordance with examples as disclosed herein. The input signal generator **725** may be configured as or otherwise support a means for generating an input signal including information for transmission over a wireless channel. The first waveform shaping stage component **730** may be configured as or otherwise support a means for performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal. The second waveform shaping stage component **735** may be configured as or otherwise support a means for performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage. The signal transmitter **740** may be configured as or otherwise support a means for transmitting a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage. (78) In some examples, to support performing the first waveform shaping stage of the multistage waveform shaping process, the first waveform shaping stage component **730** may be configured as or otherwise support a means for performing an interference cancellation operation to increase the in-band emissions ratio of the input signal.

(79) In some examples, to support performing the interference cancellation operation, the first waveform shaping stage component **730** may be configured as or otherwise support a means for performing a state expansion of nonlinear components of the input signal. In some examples, to support performing the interference cancellation operation, the first waveform shaping stage component **730** may be configured as or otherwise support a means for performing frequency selective filtering on an output of the state expansion.

(80) In some examples, to support performing the first waveform shaping stage of the multistage waveform shaping process, the first waveform shaping stage component **730** may be configured as or otherwise support a means for performing a clipping operation after increasing the in-band emissions ratio of the input signal to reduce the PAPR of the input signal.

(81) In some examples, to support performing the second stage of the multistage waveform shaping process, the second waveform shaping stage component **735** may be configured as or otherwise support a means for performing frequency selective filtering on the output of the first waveform shaping stage to reduce the adjacent channel leakage ratio of the output of the first waveform shaping stage.

(82) In some examples, an in-band emissions ratio of the output of the second waveform shaping stage is greater than an in-band emissions ratio of the input signal.

(83) In some examples, an adjacent channel leakage ratio of the output of the second waveform shaping stage is greater than an adjacent channel leakage ratio of the input signal.

(84) In some examples, to support performing the first waveform shaping stage, the first waveform shaping stage component **730** may be configured as or otherwise support a means for introducing intermodulation distortion to the output of the first waveform shaping stage for processing at a receiver.

(85) In some examples, to support performing the first waveform shaping stage, the first waveform shaping stage component **730** may be configured as or otherwise support a means for reducing an adjacent channel leakage ratio of the input signal.

(86) In some examples, to support performing the first waveform shaping stage, the first waveform shaping stage component **730** may be configured as or otherwise support a means for performing a quantity of iterations of the first waveform shaping stage, where the output of the first waveform shaping stage includes an output of a final iteration of the quantity of iterations of the first waveform shaping stage.

(87) FIG. **8** shows a diagram of a system **800** including a device **805** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The device **805** may be an example of or include the components of a device **505**, a device **605**, or a UE **115** as described herein. The device **805** may communicate (e.g., wirelessly) with one or more network entities **105**, one or more UEs **115**, or any combination thereof. The device **805** may include components for bi-directional voice and data communications including components for transmitting and receiving communications, such as a communications manager **820**, an input/output (I/O) controller **810**, a transceiver **815**, an antenna **825**, a memory **830**, code **835**, and a processor **840**. These components may be in electronic communication or otherwise coupled (e.g., operatively, communicatively, functionally, electronically, electrically) via one or more buses (e.g., a bus **845**).

(88) The I/O controller **810** may manage input and output signals for the device **805**. The I/O controller **810** may also manage peripherals not integrated into the device **805**. In some cases, the I/O controller **810** may represent a physical connection or port to an external peripheral. In some cases, the I/O controller **810** may utilize an operating system such as iOS®, ANDROID®, MS-DOS®, MS-WINDOWS®, OS/2®, UNIX®, LINUX®, or another known operating system. Additionally or alternatively, the I/O controller **810** may represent or interact with a modem, a keyboard, a mouse, a touchscreen, or a similar device. In some cases, the I/O controller **810** may be implemented as part of a processor, such as the processor **840**. In some cases, a user may interact with the device **805** via the I/O controller **810** or via hardware components controlled by the I/O controller **810**.

(89) In some cases, the device **805** may include a single antenna **825**. However, in some other cases, the device **805** may have more than one antenna **825**, which may be capable of concurrently transmitting or receiving multiple wireless transmissions. The transceiver **815** may communicate bi-directionally, via the one or more antennas **825**, wired, or wireless links as described herein. For example, the transceiver **815** may represent a wireless transceiver and may communicate bi-directionally with another wireless transceiver. The transceiver **815** may also include a modem to modulate the packets, to provide the modulated packets to one or more antennas **825** for transmission, and to demodulate packets received from the one or more antennas **825**. The

transceiver **815**, or the transceiver **815** and one or more antennas **825**, may be an example of a transmitter **515**, a transmitter **615**, a receiver **510**, a receiver **610**, or any combination thereof or component thereof, as described herein.

(90) The memory **830** may include random access memory (RAM) and read-only memory (ROM). The memory **830** may store computer-readable, computer-executable code **835** including instructions that, when executed by the processor **840**, cause the device **805** to perform various functions described herein. The code **835** may be stored in a non-transitory computer-readable medium such as system memory or another type of memory. In some cases, the code **835** may not be directly executable by the processor **840** but may cause a computer (e.g., when compiled and executed) to perform functions described herein. In some cases, the memory **830** may contain, among other things, a basic I/O system (BIOS) which may control basic hardware or software operation such as the interaction with peripheral components or devices.

(91) The processor **840** may include an intelligent hardware device (e.g., a general-purpose processor, a DSP, a CPU, a microcontroller, an ASIC, an FPGA, a programmable logic device, a discrete gate or transistor logic component, a discrete hardware component, or any combination thereof). In some cases, the processor **840** may be configured to operate a memory array using a memory controller. In some other cases, a memory controller may be integrated into the processor **840**. The processor **840** may be configured to execute computer-readable instructions stored in a memory (e.g., the memory **830**) to cause the device **805** to perform various functions (e.g., functions or tasks supporting improved techniques for waveform compression). For example, the device **805** or a component of the device **805** may include a processor **840** and memory **830** coupled with or to the processor **840**, the processor **840** and memory **830** configured to perform various functions described herein.

(92) The communications manager **820** may support wireless communications at a UE in accordance with examples as disclosed herein. For example, the communications manager **820** may be configured as or otherwise support a means for generating an input signal including information for transmission over a wireless channel. The communications manager **820** may be configured as or otherwise support a means for performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal. The communications manager **820** may be configured as or otherwise support a means for performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage. The communications manager **820** may be configured as or otherwise support a means for transmitting a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage.

(93) By including or configuring the communications manager **820** in accordance with examples as described herein, the device **805** may support techniques for increasing a range of wireless communications. For example, the device **805** may perform waveform shaping operations, which may enable the device **805** to increase an output of a PA. In some cases, the waveform shaping operations may additionally enable the device **805** to improve PAE, which may reduce power consumption at the device **805**. For example, the device **805** may perform waveform shaping operations to reduce PAPR, increase IBE, and increase ACLR, which may improve signal quality.

(94) In some examples, the communications manager **820** may be configured to perform various operations (e.g., receiving, monitoring, transmitting) using or otherwise in cooperation with the transceiver **815**, the one or more antennas **825**, or any combination thereof. Although the communications manager **820** is illustrated as a separate component, in some examples, one or more functions described with reference to the communications manager **820** may be supported by or performed by the processor **840**, the memory **830**, the code **835**, or any combination thereof. For

example, the code **835** may include instructions executable by the processor **840** to cause the device **805** to perform various aspects of improved techniques for waveform compression as described herein, or the processor **840** and the memory **830** may be otherwise configured to perform or support such operations.

(95) FIG. **9** shows a flowchart illustrating a method **900** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The operations of the method **900** may be implemented by a UE or its components as described herein. For example, the operations of the method **900** may be performed by a UE **115** as described with reference to FIGS. **1** through **8**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

(96) At **905**, the method may include generating an input signal including information for transmission over a wireless channel. The operations of **905** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **905** may be performed by an input signal generator **725** as described with reference to FIG. **7**.

(97) At **910**, the method may include performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal. The operations of **910** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **910** may be performed by a first waveform shaping stage component **730** as described with reference to FIG. **7**.

(98) At **915**, the method may include performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage. The operations of **915** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **915** may be performed by a second waveform shaping stage component **735** as described with reference to FIG. **7**.

(99) At **920**, the method may include transmitting a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage. The operations of **920** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **920** may be performed by a signal transmitter **740** as described with reference to FIG. **7**.

(100) FIG. **10** shows a flowchart illustrating a method **1000** that supports improved techniques for waveform compression in accordance with one or more aspects of the present disclosure. The operations of the method **1000** may be implemented by a UE or its components as described herein. For example, the operations of the method **1000** may be performed by a UE **115** as described with reference to FIGS. **1** through **8**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

(101) At **1005**, the method may include generating an input signal including information for transmission over a wireless channel. The operations of **1005** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1005** may be performed by an input signal generator **725** as described with reference to FIG. **7**.

(102) At **1010**, the method may include performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, where performing the first waveform shaping stage includes increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal. The operations of **1010** may be performed in accordance

with examples as disclosed herein. In some examples, aspects of the operations of **1010** may be performed by a first waveform shaping stage component **730** as described with reference to FIG. 7. (103) At **1015**, the method may include performing an interference cancellation operation to increase the in-band emissions ratio of the input signal. The operations of **1015** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1015** may be performed by a first waveform shaping stage component **730** as described with reference to FIG. 7.

(104) At **1020**, the method may include performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, where performing the second waveform shaping stage includes reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage. The operations of **1020** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1020** may be performed by a second waveform shaping stage component **735** as described with reference to FIG. 7.

(105) At **1025**, the method may include transmitting a signal over the wireless channel, where the signal is based on an output of the second waveform shaping stage. The operations of **1025** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1025** may be performed by a signal transmitter **740** as described with reference to FIG. 7.

(106) The following provides an overview of aspects of the present disclosure:

(107) Aspect 1: A method for wireless communications at a UE, comprising: generating an input signal comprising information for transmission over a wireless channel; performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, wherein performing the first waveform shaping stage comprises increasing an in-band emissions ratio of the input signal and reducing a peak-to-average-power ratio (PAPR) of the input signal; performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, wherein performing the second waveform shaping stage comprises reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage; and transmitting a signal over the wireless channel, wherein the signal is based at least in part on an output of the second waveform shaping stage.

(108) Aspect 2: The method of aspect 1, wherein performing the first waveform shaping stage of the multistage waveform shaping process further comprises: performing an interference cancellation operation to increase the in-band emissions ratio of the input signal.

(109) Aspect 3: The method of aspect 2, wherein performing the interference cancellation operation further comprises: performing a state expansion of nonlinear components of the input signal; and performing frequency selective filtering on an output of the state expansion.

(110) Aspect 4: The method of any of aspects 2 through 3, wherein performing the interference cancellation operation further comprises: performing a clipping operation on the input signal; and performing frequency selective filtering on an output of the clipping operation.

(111) Aspect 5: The method of any of aspects 1 through 4, wherein performing the first waveform shaping stage of the multistage waveform shaping process further comprises: performing a clipping operation after increasing the in-band emissions ratio of the input signal to reduce the PAPR of the input signal.

(112) Aspect 6: The method of aspect 5, wherein performing the clipping operation further comprises: performing a quantity of iterations of the clipping operation, wherein the output of the first waveform shaping stage comprises an output of a final iteration of the quantity of iterations of the clipping operation.

(113) Aspect 7: The method of any of aspects 1 through 6, wherein performing the second waveform shaping stage of the multistage waveform shaping process further comprises: performing frequency selective filtering on the output of the first waveform shaping stage to reduce the

adjacent channel leakage ratio of the output of the first waveform shaping stage.

(114) Aspect 8: The method of any of aspects 1 through 7, wherein an in-band emissions ratio of the output of the second waveform shaping stage is greater than the in-band emissions ratio of the input signal.

(115) Aspect 9: The method of any of aspects 1 through 8, wherein an adjacent channel leakage ratio of the output of the second waveform shaping stage is greater than an adjacent channel leakage ratio of the input signal.

(116) Aspect 10: The method of any of aspects 1 through 9, wherein performing the first waveform shaping stage further comprises: introducing intermodulation distortion to the output of the first waveform shaping stage for processing at a receiver.

(117) Aspect 11: The method of any of aspects 1 through 10, wherein performing the first waveform shaping stage further comprises: reducing an adjacent channel leakage ratio of the input signal.

(118) Aspect 12: The method of any of aspects 1 through 11, wherein performing the first waveform shaping stage further comprises: performing a quantity of iterations of the first waveform shaping stage, wherein the output of the first waveform shaping stage comprises an output of a final iteration of the quantity of iterations of the first waveform shaping stage.

(119) Aspect 13: An apparatus for wireless communications at a UE, comprising a processor; memory coupled with the processor; and instructions stored in the memory and executable by the processor to cause the apparatus to perform a method of any of aspects 1 through 12.

(120) Aspect 14: An apparatus for wireless communications at a UE, comprising at least one means for performing a method of any of aspects 1 through 12.

(121) Aspect 15: A non-transitory computer-readable medium storing code for wireless communications at a UE, the code comprising instructions executable by a processor to perform a method of any of aspects 1 through 12.

(122) It should be noted that the methods described herein describe possible implementations, and that the operations and the steps may be rearranged or otherwise modified and that other implementations are possible. Further, aspects from two or more of the methods may be combined.

(123) Although aspects of an LTE, LTE-A, LTE-A Pro, or NR system may be described for purposes of example, and LTE, LTE-A, LTE-A Pro, or NR terminology may be used in much of the description, the techniques described herein are applicable beyond LTE, LTE-A, LTE-A Pro, or NR networks. For example, the described techniques may be applicable to various other wireless communications systems such as Ultra Mobile Broadband (UMB), Institute of Electrical and Electronics Engineers (IEEE) 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802.20, Flash-OFDM, as well as other systems and radio technologies not explicitly mentioned herein.

(124) Information and signals described herein may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

(125) The various illustrative blocks and components described in connection with the disclosure herein may be implemented or performed using a general-purpose processor, a DSP, an ASIC, a CPU, an FPGA or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor but, in the alternative, the processor may be any processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices (e.g., a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration).

(126) The functions described herein may be implemented using hardware, software executed by a

processor, firmware, or any combination thereof. If implemented using software executed by a processor, the functions may be stored as or transmitted using one or more instructions or code of a computer-readable medium. Other examples and implementations are within the scope of the disclosure and appended claims. For example, due to the nature of software, functions described herein may be implemented using software executed by a processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations.

(127) Computer-readable media includes both non-transitory computer storage media and communication media including any medium that facilitates transfer of a computer program from one location to another. A non-transitory storage medium may be any available medium that may be accessed by a general-purpose or special-purpose computer. By way of example, and not limitation, non-transitory computer-readable media may include RAM, ROM, electrically erasable programmable ROM (EEPROM), flash memory, compact disk (CD) ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other non-transitory medium that may be used to carry or store desired program code means in the form of instructions or data structures and that may be accessed by a general-purpose or special-purpose computer, or a general-purpose or special-purpose processor. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of computer-readable medium. Disk and disc, as used herein, include CD, laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc. Disks may reproduce data magnetically, and discs may reproduce data optically using lasers. Combinations of the above are also included within the scope of computer-readable media.

(128) As used herein, including in the claims, “or” as used in a list of items (e.g., a list of items prefaced by a phrase such as “at least one of” or “one or more of”) indicates an inclusive list such that, for example, a list of at least one of A, B, or C means A or B or C or AB or AC or BC or ABC (i.e., A and B and C). Also, as used herein, the phrase “based on” shall not be construed as a reference to a closed set of conditions. For example, an example step that is described as “based on condition A” may be based on both a condition A and a condition B without departing from the scope of the present disclosure. In other words, as used herein, the phrase “based on” shall be construed in the same manner as the phrase “based at least in part on.”

(129) The term “determine” or “determining” encompasses a variety of actions and, therefore, “determining” can include calculating, computing, processing, deriving, investigating, looking up (such as via looking up in a table, a database or another data structure), ascertaining and the like. Also, “determining” can include receiving (e.g., receiving information), accessing (e.g., accessing data stored in memory) and the like. Also, “determining” can include resolving, obtaining, selecting, choosing, establishing, and other such similar actions.

(130) In the appended figures, similar components or features may have the same reference label. Further, various components of the same type may be distinguished by following the reference label by a dash and a second label that distinguishes among the similar components. If just the first reference label is used in the specification, the description is applicable to any one of the similar components having the same first reference label irrespective of the second reference label, or other subsequent reference label.

(131) The description set forth herein, in connection with the appended drawings, describes example configurations and does not represent all the examples that may be implemented or that are within the scope of the claims. The term “example” used herein means “serving as an example, instance, or illustration,” and not “preferred” or “advantageous over other examples.” The detailed

description includes specific details for the purpose of providing an understanding of the described techniques. These techniques, however, may be practiced without these specific details. In some instances, known structures and devices are shown in block diagram form in order to avoid obscuring the concepts of the described examples.

(132) The description herein is provided to enable a person having ordinary skill in the art to make or use the disclosure. Various modifications to the disclosure will be apparent to a person having ordinary skill in the art, and the generic principles defined herein may be applied to other variations without departing from the scope of the disclosure. Thus, the disclosure is not limited to the examples and designs described herein but is to be accorded the broadest scope consistent with the principles and novel features disclosed herein.

Claims

1. A method for wireless communications at a user equipment (UE), comprising: generating an input signal comprising information for transmission over a wireless channel; performing a first waveform shaping stage of a multistage waveform shaping process on the input signal, wherein performing the first waveform shaping stage comprises a first operation that increases an in-band emissions ratio of the input signal and a second operation, performed after the first operation, that reduces a peak-to-average-power ratio (PAPR) of the input signal; performing a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, wherein performing the second waveform shaping stage comprises reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage after increasing the in-band emissions ratio of the input signal and reducing the PAPR of the input signal; and transmitting a signal over the wireless channel, wherein the signal is based at least in part on an output of the second waveform shaping stage.
2. The method of claim 1, wherein performing the first operation of the first waveform shaping stage of the multistage waveform shaping process further comprises: performing an interference cancellation operation to increase the in-band emissions ratio of the input signal.
3. The method of claim 2, wherein performing the interference cancellation operation further comprises: performing a state expansion of nonlinear components of the input signal; and performing frequency selective filtering on an output of the state expansion.
4. The method of claim 2, wherein performing the interference cancellation operation further comprises: performing a clipping operation on the input signal; and performing frequency selective filtering on an output of the clipping operation.
5. The method of claim 1, wherein performing the second operation of the first waveform shaping stage of the multistage waveform shaping process further comprises: performing a clipping operation after increasing the in-band emissions ratio of the input signal to reduce the PAPR of the input signal.
6. The method of claim 5, wherein performing the clipping operation further comprises: performing a quantity of iterations of the clipping operation, wherein the output of the first waveform shaping stage comprises an output of a final iteration of the quantity of iterations of the clipping operation.
7. The method of claim 1, wherein performing the second waveform shaping stage of the multistage waveform shaping process further comprises: performing frequency selective filtering on the output of the first waveform shaping stage to reduce the adjacent channel leakage ratio of the output of the first waveform shaping stage.
8. The method of claim 1, wherein an in-band emissions ratio of the output of the second waveform shaping stage is greater than the in-band emissions ratio of the input signal.
9. The method of claim 1, wherein an adjacent channel leakage ratio of the output of the second waveform shaping stage is greater than an adjacent channel leakage ratio of the input signal.
10. The method of claim 1, wherein performing the first waveform shaping stage further comprises:

introducing intermodulation distortion to the output of the first waveform shaping stage for processing at a receiver.

11. The method of claim 1, wherein performing the first waveform shaping stage further comprises: reducing an adjacent channel leakage ratio of the input signal.

12. The method of claim 1, wherein performing the first waveform shaping stage further comprises: performing a quantity of iterations of the first waveform shaping stage, wherein the output of the first waveform shaping stage comprises an output of a final iteration of the quantity of iterations of the first waveform shaping stage.

13. An user equipment (UE) for wireless communications, comprising: one or more memories storing processor-executable code; and one or more processors coupled with the one or more memories and operable to execute the code to cause the UE to: generate an input signal comprising information for transmission over a wireless channel; perform a first waveform shaping stage of a multistage waveform shaping process on the input signal, wherein performing the first waveform shaping stage comprises a first operation that increases an in-band emissions ratio of the input signal and a second operation, performed after the first operation, that reduces a peak-to-average-power ratio (PAPR) of the input signal; perform a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, wherein performing the second waveform shaping stage comprises reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage after increasing the in-band emissions ratio of the input signal and reducing the PAPR of the input signal; and transmit a signal over the wireless channel, wherein the signal is based at least in part on an output of the second waveform shaping stage.

14. The UE of claim 13, wherein, to perform the first operation of the first waveform shaping stage of the multistage waveform shaping process, the one or more processors are further operable to execute the code to cause the UE to: perform an interference cancellation operation to increase the in-band emissions ratio of the input signal.

15. The UE of claim 14, wherein, to perform the interference cancellation operation, the one or more processors are further operable to execute the code to cause the UE to: perform a state expansion of nonlinear components of the input signal; and perform frequency selective filtering on an output of the state expansion.

16. The UE of claim 14, wherein, to perform the interference cancellation operation, the one or more processors are further operable to execute the code to cause the UE to: perform a clipping operation on the input signal; and perform frequency selective filtering on an output of the clipping operation.

17. The UE of claim 13, wherein, to perform the second operation of the first waveform shaping stage of the multistage waveform shaping process, the one or more processors are further operable to execute the code to cause the UE to: perform a clipping operation after increasing the in-band emissions ratio of the input signal to reduce the PAPR of the input signal.

18. The UE of claim 17, wherein, to perform the clipping operation, the one or more processors are further operable to execute the code to cause the UE to: perform a quantity of iterations of the clipping operation, wherein the output of the first waveform shaping stage comprises an output of a final iteration of the quantity of iterations of the clipping operation.

19. The UE of claim 13, wherein to perform the second waveform shaping stage of the multistage waveform shaping process, the one or more processors are further operable to execute the code to cause the UE to: perform frequency selective filtering on the output of the first waveform shaping stage to reduce the adjacent channel leakage ratio of the output of the first waveform shaping stage.

20. The UE of claim 13, wherein an in-band emissions ratio of the output of the second waveform shaping stage is greater than the in-band emissions ratio of the input signal.

21. The UE of claim 13, wherein an adjacent channel leakage ratio of the output of the second waveform shaping stage is greater than an adjacent channel leakage ratio of the input signal.

22. The UE of claim 13, wherein to perform the first waveform shaping stage, the one or more

processors are further operable to execute the code to cause the UE to: introduce intermodulation distortion to the output of the first waveform shaping stage for processing at a receiver.

23. The UE of claim 13, wherein to perform the first waveform shaping stage, the one or more processors are further operable to execute the code to cause the UE to: reduce an adjacent channel leakage ratio of the input signal.

24. The UE of claim 13, wherein to perform the first waveform shaping stage, the one or more processors are further operable to execute the code to cause the UE to: perform a quantity of iterations of the first waveform shaping stage, wherein the output of the first waveform shaping stage comprises an output of a final iteration of the quantity of iterations of the first waveform shaping stage.

25. A non-transitory computer-readable medium storing code for wireless communication at a user equipment (UE), the code comprising instructions executable to: generate an input signal comprising information for transmission over a wireless channel; perform a first waveform shaping stage of a multistage waveform shaping process on the input signal, wherein performing the first waveform shaping stage comprises a first operation that increases an in-band emissions ratio of the input signal and a second operation, performed after the first operation, that reduces a peak-to-average-power ratio (PAPR) of the input signal; perform a second waveform shaping stage of the multistage waveform shaping process on an output of the first waveform shaping stage, wherein performing the second waveform shaping stage comprises reducing an adjacent channel leakage ratio of the output of the first waveform shaping stage after increasing the in-band emissions ratio of the input signal and reducing the PAPR of the input signal; and transmit a signal over the wireless channel, wherein the signal is based at least in part on an output of the second waveform shaping stage.

26. The non-transitory computer-readable medium of claim 25, wherein the instructions to perform the first operation of the first waveform shaping stage of the multistage waveform shaping process are further executable to: perform an interference cancellation operation to increase the in-band emissions ratio of the input signal.

27. The non-transitory computer-readable medium of claim 26, wherein the instructions to perform the interference cancellation operation are further executable to: perform a state expansion of nonlinear components of the input signal; and perform frequency selective filtering on an output of the state expansion.

28. The non-transitory computer-readable medium of claim 26, wherein the instructions to perform the interference cancellation operation are further executable to: perform a clipping operation on the input signal; and perform frequency selective filtering on an output of the clipping operation.

29. The non-transitory computer-readable medium of claim 25, wherein the instructions to perform the second operation of the first waveform shaping stage of the multistage waveform shaping process are further executable to: perform a clipping operation after increasing the in-band emissions ratio of the input signal to reduce the PAPR of the input signal.

30. The non-transitory computer-readable medium of claim 29, wherein the instructions to perform the clipping operation are further executable to: perform a quantity of iterations of the clipping operation, wherein the output of the first waveform shaping stage comprises an output of a final iteration of the quantity of iterations of the clipping operation.
