

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent

12401922

Kind Code

B2

Date of Patent

August 26, 2025

Inventor(s)

Sakurabu; Hitoshi et al.

Imaging element, imaging apparatus, operation method of imaging element, and program

Abstract

An imaging element includes a reading circuit that reads out pixel data obtained by imaging a subject at a first frame rate, a memory that stores the read pixel data, and an output circuit that outputs image data based on the stored pixel data at a second frame rate. The first frame rate is a frame rate higher than the second frame rate. The pixel data includes phase difference pixel data and non-phase difference pixel data different from the phase difference pixel data. The reading circuit reads out the pixel data of each of a plurality of frames in parallel within an output period defined by the second frame rate as a period in which the image data of one frame is output, and performs reading of the non-phase difference pixel data and a plurality of reading of the phase difference pixel data within the output period.

Inventors: Sakurabu; Hitoshi (Saitama, JP), Kobayashi; Makoto (Saitama, JP), Hasegawa; Ryo (Saitama, JP), Kawai; Tomoyuki (Saitama, JP)

Applicant: FUJIFILM CORPORATION (Tokyo, JP)

Family ID: 1000008781881

Assignee: FUJIFILM CORPORATION (Tokyo, JP)

Appl. No.: 18/539291

Filed: December 14, 2023

Prior Publication Data

Document Identifier

US 20240114260 A1

Publication Date

Apr. 04, 2024

Foreign Application Priority Data

JP

2019-046435

Mar. 13, 2019

Related U.S. Application Data

continuation parent-doc US 18165229 20230206 US 11882375 child-doc US 18539291
continuation parent-doc US 17400133 20210812 US 11616927 20230328 child-doc US 18165229
continuation parent-doc WO PCT/JP2020/002930 20200128 PENDING child-doc US 17400133

Publication Classification

Int. Cl.: H04N25/75 (20230101); H04N25/704 (20230101); H04N25/71 (20230101);
H04N25/772 (20230101)

U.S. Cl.:

CPC H04N25/75 (20230101); H04N25/704 (20230101); H04N25/71 (20230101);
H04N25/772 (20230101)

Field of Classification Search

USPC: None

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
11509823	12/2021	Kawai et al.	N/A	N/A
11616927	12/2022	Sakurabu et al.	N/A	N/A
11882375	12/2023	Sakurabu	N/A	H04N 23/60
2005/0168610	12/2004	Kobayashi	N/A	N/A
2014/0085512	12/2013	Ikeda et al.	N/A	N/A
2015/0085172	12/2014	Uenishi	N/A	N/A
2016/0353005	12/2015	Kaibara	N/A	N/A
2018/0115729	12/2017	Ise et al.	N/A	N/A
2021/0377479	12/2020	Sakurabu et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1649393	12/2004	CN	N/A
103404126	12/2012	CN	N/A
2014-178603	12/2013	JP	N/A
2018-66928	12/2017	JP	N/A
2018-195892	12/2017	JP	N/A
7481313	12/2023	JP	N/A

OTHER PUBLICATIONS

English language translation of the following: Office action dated Jul. 8, 2024 from the SIPO in a Chinese patent application No. 202310033460.3 corresponding to the instant patent application. This office action translation is submitted now in order to supplement the understanding of the cited references which are being disclosed in the instant Information Disclosure Statement. cited by applicant

International Search Report issued in International Application No. PCT/JP2020/002930 on Apr. 28, 2020. cited by applicant
Written Opinion of the ISA issued in International Application No. PCT/JP2020/002930 on Apr. 28, 2020. cited by applicant
Notice of Allowance issued by USPTO on Dec. 7, 2022, in related U.S. Appl. No. 17/400,133. cited by applicant
Non-Final Office Action issued by USPTO on Jun. 14, 2023, in related U.S. Appl. No. 18/165,229. cited by applicant
Notice of Allowance issued by USPTO on Sep. 20, 2023, in related U.S. Appl. No. 18/165,229. cited by applicant
English language translation of the following: Office action dated Jun. 24, 2025 from the JPO in a Japanese patent application No. 2024-071724 corresponding to the instant patent application. This office action translation is submitted now in order to supplement the understanding of the cited references which are being disclosed in the instant Information Disclosure Statement. cited by applicant

Primary Examiner: Monk; Mark T

Attorney, Agent or Firm: SOLARIS Intellectual Property Group, PLLC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation application of U.S. application Ser. No. 18/165,229, filed on Feb. 6, 2023, which is a continuation of U.S. application Ser. No. 17/400,133, filed on Aug. 12, 2021, which is a continuation application of International Application No. PCT/JP2020/002930, filed on Jan. 28, 2020. Further, this application claims priority from Japanese Patent Application No. 2019-046435, filed on Mar. 13, 2019. The entire disclosure of each of the applications above is incorporated herein by reference.

BACKGROUND

1. Technical Field

(1) The technology of the present disclosure relates to an imaging element, an imaging apparatus, an operation method of an imaging element, and a program.

2. Description of the Related Art

(2) JP2014-178603A discloses an imaging apparatus comprising an imaging unit, a region-of-interest decision unit, a control unit, and a focal point detection unit.

(3) In the imaging apparatus disclosed in JP2014-178603A, the imaging unit has a plurality of imaging regions and generates image signals corresponding to rays incident on the imaging regions. The region-of-interest decision unit decides a region-of-interest of an image indicated by the image signals based on the image signals output from the imaging unit.

(4) The control unit includes a first control portion and a second control portion. The first control portion performs a control such that an imaging region on which an optical image corresponding to the region-of-interest is incident among the plurality of imaging regions is imaged under a first imaging condition. The second control portion performs a control such that an imaging region other than the imaging region on which the optical image corresponding to the region-of-interest is incident among the plurality of imaging regions is imaged under a second imaging condition different from the first imaging condition. The focal point detection unit detects a focal point adjustment state of the region-of-interest. The first control portion performs a control for performing imaging at a higher frame rate than the second control portion.

SUMMARY

(5) An embodiment according to the technology of the present disclosure provides an imaging element, an imaging apparatus, an operation method of an imaging element, and a program capable of increasing accuracy of auto-focus with a simple configuration, compared to a case of reading out pixel data a plurality of number of times from a pixel dedicated to the auto-focus within a reading period in which an image of one frame is read out.

(6) A first aspect according to the technology of the present disclosure is an imaging element that includes a phase difference pixel and comprises a reading portion that reads out pixel data obtained by imaging a subject at a first frame rate and is incorporated in the imaging element, a storage portion that stores the pixel data read out by the reading portion and is incorporated in the imaging element, and an output portion that outputs image data based on the pixel data stored in the storage portion at a second frame rate and is incorporated in the imaging element, in which the first frame rate is a frame rate higher than the second frame rate, the pixel data includes phase difference pixel data and non-phase difference pixel data different from the phase difference pixel data, and the reading portion reads out the pixel data of each of a plurality of frames in parallel within an output period defined by the second frame rate as a period in which the image data of one frame is output, and performs reading of the non-phase difference pixel data and a plurality of reading of the phase difference pixel data within the output period. Accordingly, high accuracy of auto-focus can be achieved with a simpler configuration than in a case where the pixel data is read out a plurality of number of times from a pixel dedicated to the auto-focus within a reading period in which an image of one frame is read out.

(7) A second aspect according to the technology of the present disclosure is the imaging element according to the first aspect, in which the reading portion performs reading of the non-phase difference pixel data and reading of the phase difference pixel data in parallel. Accordingly, more pieces of the phase difference pixel data and the non-phase difference pixel data can be read out within a limited time period, compared to a case where reading of one of the non-phase difference pixel data and the phase difference pixel data is started after reading of the other is completed.

(8) A third aspect according to the technology of the present disclosure is the imaging element according to the first or second aspect, in which the reading portion reads out the pixel data in units of lines. Accordingly, the pixel data can be thinned out in units of lines.

(9) A fourth aspect according to the technology of the present disclosure is the imaging element according to any one of the first to third aspects, in which the phase difference pixel data is pixel data of the phase difference pixel, and the non-phase difference pixel data is pixel data of a non-phase difference pixel that is a pixel different from the phase difference pixel. The phase difference pixel data and the non-phase difference pixel data can be easily obtained, compared to a case of generating the phase difference pixel data from pixel data of a pixel other than the phase difference pixel and generating the non-phase difference pixel data from pixel data of a pixel other than the non-phase difference pixel.

(10) A fifth aspect according to the technology of the present disclosure is the imaging element according to the fourth aspect, in which reading of the non-phase difference pixel data is reading of the non-phase difference pixel data from the non-phase difference pixel, and the plurality of reading of the phase difference pixel data is a plurality of reading of the phase difference pixel data from the phase difference pixel. Accordingly, the non-phase difference pixel data and a plurality of pieces of the phase difference pixel data can be obtained within the output period, compared to a case where reading of the phase difference pixel data from the phase difference pixel and reading of the non-phase difference pixel data from the non-phase difference pixel are alternately performed once for each output period.

(11) A sixth aspect according to the technology of the present disclosure is the imaging element according to the fourth or fifth aspect, further comprising an imaging surface on which a plurality of first lines including the phase difference pixel and a plurality of second lines consisting of only

the non-phase difference pixel are arranged, in which the reading portion includes a first reading portion that reads out the phase difference pixel data from each phase difference pixel included in the plurality of first lines, and a second reading portion that reads out the non-phase difference pixel data from each non-phase difference pixel included in the plurality of second lines. Accordingly, a load exerted on reading of the phase difference pixel data and a load exerted on reading of the non-phase difference pixel data can be distributed.

(12) A seventh aspect according to the technology of the present disclosure is the imaging element according to the sixth aspect, in which reading of the phase difference pixel data from the phase difference pixel by the first reading portion and reading of the non-phase difference pixel data from the non-phase difference pixel by the second reading portion are independently performed. Accordingly, a case where one of reading of the phase difference pixel data and reading of the non-phase difference pixel data affects the other can be avoided.

(13) An eighth aspect according to the technology of the present disclosure is the imaging element according to the seventh aspect, in which in a reading period of one frame, reading of the phase difference pixel data from the phase difference pixel by the first reading portion is performed earlier than reading of the non-phase difference pixel data from the non-phase difference pixel by the second reading portion. Accordingly, the phase difference pixel data can be quickly used for processing of the auto-focus, compared to a case where reading of the non-phase difference pixel data is performed earlier than reading of the phase difference pixel data.

(14) A ninth aspect according to the technology of the present disclosure is the imaging element according to any one of the sixth to eighth aspects, in which the first lines are lines in which the phase difference pixel and the non-phase difference pixel are periodically arranged. Accordingly, accuracy of the auto-focus for a wide area can be increased, compared to a case of using a line in which the phase difference pixels and the non-phase difference pixels are arranged in a locally concentrated manner.

(15) A tenth aspect according to the technology of the present disclosure is the imaging element according to any one of the sixth to ninth aspects, in which on the imaging surface, the first lines and a predetermined number of lines of the second lines are alternately arranged in a direction intersecting with a line direction of the first lines. Accordingly, the accuracy of the auto-focus for the wide area can be increased, compared to a case where the first lines and the second lines are arranged in a locally concentrated manner in the direction intersecting with the line direction of the first lines.

(16) An eleventh aspect according to the technology of the present disclosure is the imaging element according to any one of the first to tenth aspects, in which the reading portion reads out the non-phase difference pixel data of one frame as recording pixel data within a reading period of one frame, and reads out the phase difference pixel data during reading of the non-phase difference pixel data as the recording pixel data. Accordingly, more pieces of the non-phase difference pixel data as the recording pixel data and the phase difference pixel data can be read out within a limited time period, compared to a case where the phase difference pixel data is read out after waiting for reading of the non-phase difference pixel data as the recording pixel data.

(17) A twelfth aspect according to the technology of the present disclosure is the imaging element according to the eleventh aspect, in which the reading portion reads out the non-phase difference pixel data and the phase difference pixel data as display pixel data within the reading period of one frame, and reads out the non-phase difference pixel as the recording pixel data in a case where a predetermined condition is satisfied. Accordingly, general-purpose properties can be increased, compared to a case of reading out non-phase difference pixel data at all times as the recording pixel data.

(18) A thirteenth aspect according to the technology of the present disclosure is the imaging element according to the eleventh aspect, in which the reading portion reads out the non-phase difference pixel data as the recording pixel data in a case of a continuous shooting mode.

Accordingly, in a case of the continuous shooting mode, the non-phase difference pixel data read out as the recording pixel data can be recorded.

(19) A fourteenth aspect according to the technology of the present disclosure is the imaging element according to any one of the first to thirteenth aspects, further comprising a derivation portion that derives a correction coefficient for correcting light reduction characteristics caused by the phase difference pixel based on the phase difference pixel data, in which the output portion outputs the correction coefficient derived by the derivation portion. Accordingly, light reduction characteristics appearing in an image based on the phase difference pixel data can be corrected.

(20) A fifteenth aspect according to the technology of the present disclosure is the imaging element according to any one of the first to fourteenth aspects, in which the image data includes first pixel data based on the non-phase difference pixel data and second pixel data based on the phase difference pixel data obtained by the plurality of reading, and in a case of outputting the image data of one frame, the output portion outputs the first pixel data and the second pixel data at different timings. Accordingly, it is possible to contribute to size reduction of the imaging element, compared to a case of using a dedicated output circuit for each of the phase difference pixel data and the non-phase difference pixel data.

(21) A sixteenth aspect according to the technology of the present disclosure is the imaging element according to the fifteenth aspect, in which the output portion outputs the first pixel data after output of the second pixel data is completed. Accordingly, the phase difference pixel data can be quickly used for processing of the auto-focus, compared to a case where the phase difference pixel data is output after output of the non-phase difference pixel data is completed.

(22) A seventeenth aspect according to the technology of the present disclosure is the imaging element according to any one of the first to sixteenth aspects, in which the image data includes pixel data based on the non-phase difference pixel data and pixel data based on a statistical value of the phase difference pixel data obtained by the plurality of reading. Accordingly, an output data amount from the imaging element can be decreased, compared to a case of outputting a plurality of pieces of the phase difference pixel data obtained for each frame.

(23) An eighteenth aspect according to the technology of the present disclosure is the imaging element according to the seventeenth aspect, in which the statistical value is an arithmetic mean value of the phase difference pixel data. Accordingly, the output data amount from the imaging element can be decreased, compared to a case of outputting the plurality of pieces of phase difference pixel data obtained for each frame.

(24) A nineteenth aspect according to the technology of the present disclosure is the imaging element according to any one of the first to eighteenth aspects, further comprising an A/D converter that is shared for the phase difference pixel data and the non-phase difference pixel data, in which the A/D converter performs A/D conversion on the phase difference pixel data and the non-phase difference pixel data at different timings. Accordingly, it is possible to contribute to size reduction of the imaging element, compared to a case of using a dedicated A/D converter for each of the phase difference pixel data and the non-phase difference pixel data.

(25) A twentieth aspect according to the technology of the present disclosure is the imaging element according to any one of the first to eighteenth aspects, further comprising a plurality of A/D converters, in which the plurality of A/D converters include a first A/D converter used for only the phase difference pixel data and a second A/D converter used for only the non-phase difference pixel data. Accordingly, the A/D conversion of the phase difference pixel data and the A/D conversion of the non-phase difference pixel data can be performed in parallel in the output period.

(26) A twenty-first aspect according to the technology of the present disclosure is the imaging element according to any one of the first to twentieth aspects, in which at least a photoelectric conversion element and the storage portion are formed in one chip. Accordingly, portability of the imaging element is increased, compared to an imaging element in which the photoelectric conversion element and the storage portion are not formed in one chip.

(27) A twenty-second aspect according to the technology of the present disclosure is the imaging element according to the twenty-first aspect, in which the imaging element is a laminated imaging element in which the photoelectric conversion element is laminated with the storage portion. Accordingly, a transfer speed of the image data from the photoelectric conversion element to the storage portion can be increased, compared to a case of not laminating the photoelectric conversion element and the storage portion.

(28) A twenty-third aspect according to the technology of the present disclosure is an imaging apparatus comprising the imaging element according to any one of the first to twenty-second aspects, and a control portion that performs at least one of a control for displaying the image based on the image data output by the output portion on a display portion or a control for storing the image data output by the output portion in a storage device. Accordingly, high accuracy of the auto-focus can be achieved with a simpler configuration than in a case where the pixel data is read out a plurality of number of times from the pixel dedicated to the auto-focus within the reading period in which the image of one frame is read out.

(29) A twenty-fourth aspect according to the technology of the present disclosure is an operation method of an imaging element including a phase difference pixel, a reading portion that reads out pixel data obtained by imaging a subject at a first frame rate, a storage portion that stores the pixel data read out by the reading portion, and an output portion that outputs image data based on the pixel data stored in the storage portion at a second frame rate, the imaging element incorporating the reading portion, the storage portion, and the output portion, in which the first frame rate is a frame rate higher than the second frame rate, the pixel data includes phase difference pixel data and non-phase difference pixel data different from the phase difference pixel data, and the operation method comprises, by the reading portion, reading out the pixel data of each of a plurality of frames in parallel within an output period defined by the second frame rate as a period in which the image data of one frame is output, and performing reading of the non-phase difference pixel data and a plurality of reading of the phase difference pixel data within the output period. Accordingly, high accuracy of the auto-focus can be achieved with a simpler configuration than in a case where the pixel data is read out a plurality of number of times from the pixel dedicated to the auto-focus within the reading period in which the image of one frame is read out.

(30) A twenty-fifth aspect according to the technology of the present disclosure is a program causing a computer to function as a reading portion and an output portion included in an imaging element including a phase difference pixel, the reading portion that reads out pixel data obtained by imaging a subject at a first frame rate, a storage portion that stores the pixel data read out by the reading portion, and the output portion that outputs image data based on the pixel data stored in the storage portion at a second frame rate, the imaging element incorporating the reading portion, the storage portion, and the output portion, in which the first frame rate is a frame rate higher than the second frame rate, the pixel data includes phase difference pixel data and non-phase difference pixel data different from the phase difference pixel data, and the reading portion reads out the pixel data of each of a plurality of frames in parallel within an output period defined by the second frame rate as a period in which the image data of one frame is output, and performs reading of the non-phase difference pixel data and a plurality of reading of the phase difference pixel data within the output period. Accordingly, high accuracy of the auto-focus can be achieved with a simpler configuration than in a case where the pixel data is read out a plurality of number of times from the pixel dedicated to the auto-focus within the reading period in which the image of one frame is read out.

(31) A twenty-sixth aspect according to the technology of the present disclosure is an imaging element including a phase difference pixel and incorporating a processor and a memory, in which the processor is configured to read out pixel data obtained by imaging a subject at a first frame rate, the memory stores the pixel data read out by the processor, image data based on the pixel data stored in the memory is output at a second frame rate, the first frame rate is a frame rate higher than

the second frame rate, the pixel data includes phase difference pixel data and non-phase difference pixel data different from the phase difference pixel data, and the processor is configured to read out the pixel data of each of a plurality of frames in parallel within an output period defined by the second frame rate as a period in which the image data of one frame is output, and perform reading of the non-phase difference pixel data and a plurality of reading of the phase difference pixel data within the output period.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Exemplary embodiments of the technology of the disclosure will be described in detail based on the following figures, wherein:

(2) FIG. 1 is a perspective view illustrating an example of an exterior of an imaging apparatus according to first and second embodiments;

(3) FIG. 2 is a block diagram illustrating an example of a configuration of the imaging apparatus according to the first and second embodiments;

(4) FIG. 3A is a conceptual diagram for describing an imaging frame rate of an imaging element included in the imaging apparatus according to the first and second embodiments;

(5) FIG. 3B is a conceptual diagram for describing an output frame rate of the imaging element included in the imaging apparatus according to the first and second embodiments;

(6) FIG. 4 is a block diagram illustrating an example of a configuration of an electric system of an imaging apparatus main body according to the first and second embodiments;

(7) FIG. 5 is a block diagram illustrating an example of a laminated structure of the imaging element included in the imaging apparatus according to the first and second embodiments, and an example of a connection relationship among the imaging element, a signal processing portion, and a controller;

(8) FIG. 6 is an arrangement diagram illustrating an example of arrangement, on an imaging surface, of each pixel included in a photoelectric conversion element of the imaging element included in the imaging apparatus according to the first and second embodiments;

(9) FIG. 7 is a conceptual diagram illustrating an example of incidence characteristics of subject light with respect to a first phase difference pixel and a second phase difference pixel included in the photoelectric conversion element illustrated in FIG. 6;

(10) FIG. 8 is a schematic configuration diagram illustrating an example of a configuration of a non-phase difference pixel included in the photoelectric conversion element illustrated in FIG. 6;

(11) FIG. 9 is a block diagram illustrating an example of a configuration of an electric system of the imaging element included in the imaging apparatus according to the first embodiment;

(12) FIG. 10 is a time chart illustrating an example of a reading timing of each of analog phase difference pixel data and analog non-phase difference pixel data for each frame by a reading circuit of the imaging element included in the imaging apparatus according to the first embodiment;

(13) FIG. 11 is a time chart illustrating an example of a reading timing of analog pixel data, a timing of A/D conversion, a storage timing into a memory, and an output timing of digital pixel data in the imaging element included in the imaging apparatus according to the first embodiment;

(14) FIG. 12 is a flowchart illustrating an example of a flow of timing control processing according to the first embodiment;

(15) FIG. 13 is a flowchart illustrating an example of a flow of phase difference pixel processing according to the first embodiment;

(16) FIG. 14 is a flowchart illustrating an example of a flow of non-phase difference pixel processing according to the first embodiment;

(17) FIG. 15 is a flowchart illustrating an example of a flow of pixel data processing according to

the first embodiment;

(18) FIG. **16** is a time chart illustrating a first modification example of the reading timing of the analog pixel data, the timing of the A/D conversion, the storage timing in the memory, and the output timing of the digital pixel data in the imaging element included in the imaging apparatus according to the first embodiment;

(19) FIG. **17** is a time chart illustrating a second modification example of the reading timing of the analog pixel data, the timing of the A/D conversion, the storage timing in the memory, and the output timing of the digital pixel data in the imaging element included in the imaging apparatus according to the first embodiment;

(20) FIG. **18** is a time chart illustrating a third modification example of the reading timing of the analog pixel data, the timing of the A/D conversion, the storage timing in the memory, and the output timing of the digital pixel data in the imaging element included in the imaging apparatus according to the first embodiment;

(21) FIG. **19** is a block diagram illustrating an example of a configuration of an electric system of the imaging element included in the imaging apparatus according to the second embodiment;

(22) FIG. **20** is a time chart illustrating an example of a reading timing of analog pixel data for each frame by a reading circuit of the imaging element included in the imaging apparatus according to the second embodiment;

(23) FIG. **21** is a time chart illustrating an example of a reading timing of analog pixel data, a timing of A/D conversion, a storage timing into a memory, and an output timing of digital pixel data in the imaging element included in the imaging apparatus according to the second embodiment;

(24) FIG. **22** is a flowchart illustrating an example of a flow of in-imaging element processing according to the second embodiment;

(25) FIG. **23** is a continuation of the flowchart illustrated in FIG. **22**;

(26) FIG. **24** is a flowchart illustrating an example of a flow of pixel data processing according to the second embodiment;

(27) FIG. **25** is a graph illustrating an example of light reduction characteristics of a first phase difference image based on first phase difference pixel data from a first phase difference pixel and light reduction characteristics of a second phase difference image based on second phase difference pixel data from a second phase difference pixel included in the imaging element according to the second embodiment;

(28) FIG. **26** is a block diagram illustrating an example of a calculation circuit that calculates a correction coefficient for correcting the light reduction characteristics illustrated in FIG. **25**;

(29) FIG. **27** is a conceptual diagram illustrating an example of an aspect before and after correction of the first phase difference image based on the first phase difference pixel data from the first phase difference pixel and the second phase difference image based on the second phase difference pixel data from the second phase difference pixel included in the imaging element according to the second embodiment;

(30) FIG. **28** is a block diagram illustrating a modification example of the configuration of the electric system of the imaging element included in the imaging apparatus according to the first and second embodiments;

(31) FIG. **29** is a conceptual diagram illustrating an example of an aspect in which various programs are installed on a computer in the imaging element from a storage medium storing the various programs; and

(32) FIG. **30** is a block diagram illustrating an example of a schematic configuration of a smart device incorporating the imaging element according to the first and second embodiments.

DETAILED DESCRIPTION

(33) Hereinafter, an example of embodiments of an imaging apparatus according to the embodiments of the technology of the present disclosure will be described in accordance with the

appended drawings.

(34) First, meanings of terms used in the following description will be described.

(35) The abbreviation CPU stands for “Central Processing Unit”. The abbreviation RAM stands for “Random Access Memory”. The abbreviation ROM stands for “Read Only Memory”. The abbreviation DRAM stands for “Dynamic Random Access Memory”. The abbreviation SRAM stands for “Static Random Access Memory”.

(36) The abbreviation LSI stands for “Large-Scale Integration”. The abbreviation ASIC stands for “Application Specific Integrated Circuit”. The abbreviation PLD stands for “Programmable Logic Device”. The abbreviation FPGA stands for “Field-Programmable Gate Array”.

(37) The abbreviation SSD stands for “Solid State Drive”. The abbreviation DVD-ROM stands for “Digital Versatile Disc Read Only Memory”. The abbreviation USB stands for “Universal Serial Bus”. The abbreviation HDD stands for “Hard Disk Drive”. The abbreviation EEPROM stands for “Electrically Erasable and Programmable Read Only Memory”.

(38) The abbreviation CCD stands for “Charge Coupled Device”. The abbreviation CMOS stands for “Complementary Metal Oxide Semiconductor”. The abbreviation EL stands for “Electro-Luminescence”. The abbreviation A/D stands for “Analog/Digital”. The abbreviation OF stands for “Interface”. The abbreviation UI stands for “User Interface”. The abbreviation PC stands for “Personal Computer”. The abbreviation AF stands for “Auto-Focus”. The abbreviation AE stands for “Automatic Exposure”. The abbreviation SoC stands for “System-on-a-chip”.

First Embodiment

(39) As illustrated in FIG. 1 as an example, an imaging apparatus **10** is an interchangeable lens camera. The imaging apparatus **10** comprises an imaging apparatus main body **12** and an interchangeable lens **14** that is interchangeably mounted on the imaging apparatus main body **12**.

(40) An imaging element **44** is disposed in the imaging apparatus main body **12**. In a case where the interchangeable lens **14** is mounted on the imaging apparatus main body **12**, subject light showing a subject is transmitted through the interchangeable lens **14**, and an image of the subject light is formed on an imaging surface **44A** of the imaging element **44**.

(41) A release button **20** and a dial **22** are disposed on an upper surface of the imaging apparatus main body **12**. The dial **22** is operated in a case of setting an operation mode of an imaging system, an operation mode of a playback system, and the like. The release button **20** functions as an imaging preparation instruction portion and an imaging instruction portion, and a push operation of two stages of an imaging preparation instruction state and an imaging instruction state can be detected. For example, the imaging preparation instruction state refers to a state where a push is performed to an intermediate position (half push position) from a standby position, and the imaging instruction state refers to a state where a push is performed to a final push position (full push position) exceeding the intermediate position. Hereinafter, the “state where a push is performed to the half push position from the standby position” will be referred to as a “half push state”, and the “state where a push is performed to the full push position from the standby position” will be referred to as a “full push state”.

(42) In the imaging apparatus **10**, an imaging mode and a playback mode are selectively set as an operation mode in accordance with an instruction of a user. The imaging mode is broadly divided into a display motion picture imaging mode and a recording imaging mode. In each of the display motion picture imaging mode and the recording imaging mode, an AF mode is set in accordance with the instruction of the user.

(43) In the display motion picture imaging mode, in a case where the AF mode is set, imaging for a display motion picture image is performed by setting an exposure state by performing an AE function and performing a focusing control by performing an AF function for each frame. A live view image is generated by performing imaging for the display motion picture image. Generally, the live view image is also referred to as a live preview image.

(44) The recording imaging mode is broadly divided into a motion picture image recording imaging

mode and a still picture image recording imaging mode. The motion picture image recording imaging mode and the still picture image recording imaging mode are selectively set in accordance with the instruction of the user. In the imaging apparatus **10**, in the motion picture image recording imaging mode, in a case where the AF mode is set, imaging for a recording motion picture image is performed by setting the exposure state by performing the AE function and performing the focusing control by performing the AF function for each frame. A motion picture image obtained by performing the imaging for the recording motion picture image is recorded on a predetermined recording medium such as a memory card or a USB memory (hereinafter, simply referred to as the “predetermined recording medium”). The motion picture image obtained by performing the imaging for the recording motion picture image is an example of “recording pixel data” according to the embodiments of the technology of the present disclosure.

(45) In the still picture image recording imaging mode, in a case where the AF mode is set, an imaging condition is adjusted by setting the release button **20** to the half push state. Then, in a case where the full push state is subsequently set, imaging for a still picture image is performed. That is, by setting the release button **20** to the half push state, the exposure state is set by performing the AE function, and then, the focusing control is performed by performing the AF function. In a case where the release button **20** is set to the full push state, imaging for a recording still picture image is performed. A still picture image obtained by performing the imaging for the recording still picture image is recorded on the predetermined recording medium. The still picture image obtained by performing the imaging for the recording still picture image is an example of the “recording pixel data” according to the embodiments of the technology of the present disclosure.

(46) As illustrated in FIG. 2 as an example, the interchangeable lens **14** includes an imaging lens **40**. The imaging lens **40** comprises an objective lens **40A**, a focus lens **40B**, and a stop **40C**. The objective lens **40A**, the focus lens **40B**, and the stop **40C** are arranged in an order of the objective lens **40A**, the focus lens **40B**, and the stop **40C** along an optical axis **L1** from a subject side to an imaging apparatus main body **12** side. The stop **40C** operates by receiving motive power from a driving source (not illustrated) such as a motor. Accordingly, an opening degree of the stop **40C** is changed. By changing the opening degree of the stop **40C**, exposure is adjusted.

(47) The focus lens **40B** is attached to a sliding mechanism **15**. A motor **17** is connected to the sliding mechanism **15**. The motor **17** generates motive power and operates the sliding mechanism **15** by transmitting the generated motive power to the sliding mechanism **15**. The sliding mechanism **15** moves the focus lens **40B** along the optical axis **L1** in response to the motive power provided from the motor **17**.

(48) The motor **17** is connected to a controller **46** of the imaging apparatus main body **12** through a communication line **55**. The motor **17** is controlled by the controller **46**. In the AF mode, by moving the focus lens **40B** along the optical axis **L1** under control of the controller **46**, the image of the subject light is formed on the imaging surface **44A** of the imaging element **44** at a focus position corresponding to a subject distance. The “focus position” here refers to a position of the focus lens **40B** on the optical axis **L1** in a focused state. Hereinafter, for convenience of description, a control for aligning the focus lens **40B** to the focus position will be referred to as an “AF control”.

(49) The imaging apparatus main body **12** comprises a mechanical shutter **42** and the imaging element **44**. The mechanical shutter **42** operates by receiving motive power from a driving source (not illustrated) such as a motor. In a case where the interchangeable lens **14** is mounted on the imaging apparatus main body **12**, the subject light is transmitted through the imaging lens **40**, and the image of the subject light is formed on the imaging surface **44A** of the imaging element **44** through the mechanical shutter **42**.

(50) The imaging apparatus main body **12** comprises the controller **46**, a UI system device **48**, and a signal processing portion **50**. Each of the controller **46** and the signal processing portion **50** is implemented by an LSI. In addition, each of the controller **46** and the signal processing portion **50**

is positioned on a rear stage of the imaging element **44** and thus, is referred to as a rear stage circuit of the imaging element **44**.

(51) The controller **46** controls the entire imaging apparatus **10**. The UI system device **48** is a device that presents information to the user or receives an instruction from the user. The UI system device **48** is connected to the controller **46**. The controller **46** acquires various types of information from the UI system device **48** and controls the UI system device **48**.

(52) The imaging element **44** is connected to the controller **46** through a communication line **57** and generates image data **69** indicating the image of the subject by imaging the subject under control of the controller **46**.

(53) The imaging element **44** is connected to the signal processing portion **50** through a communication line **53**. The signal processing portion **50** is a device including an ASIC. The controller **46** is connected to the signal processing portion **50** through a communication line **60**.

(54) The image data **69** is input into the signal processing portion **50** from the imaging element **44** through the communication line **53**. The signal processing portion **50** performs various types of signal processing on the image data **69** which is input from the imaging element **44** through the communication line **53**. The various types of signal processing include well-known signal processing such as white balance adjustment, sharpness adjustment, gamma correction, color space conversion processing, and color difference correction.

(55) While the device including the ASIC is illustrated as the signal processing portion **50** in the first embodiment, the technology of the present disclosure is not limited thereto. The signal processing portion **50** may be a device including an ASIC, an FPGA, and/or a PLD. In addition, the signal processing portion **50** may be a computer including a CPU, a ROM, and a RAM. The number of CPUs may be singular or plural. In addition, the signal processing portion **50** may be implemented by a combination of a hardware configuration and a software configuration.

(56) The imaging element **44** is an example of a “laminated imaging element” according to the embodiments of the technology of the present disclosure. In the present embodiment, the imaging element **44** is a CMOS image sensor. In addition, while the CMOS image sensor is illustrated here as the imaging element **44**, the technology of the present disclosure is not limited thereto. For example, the technology of the present disclosure is also established in a case where the imaging element **44** is a CCD image sensor.

(57) In the imaging element **44**, as illustrated in FIG. 3A as an example, a plurality of pieces of image data **69** each indicating the image of the subject are generated by imaging the subject at an imaging frame rate. In addition, in the imaging element **44**, the generated plurality of pieces of image data **69** are output at an output frame rate. Any of the imaging frame rate and the output frame rate is a variable frame rate. The imaging frame rate is an example of a “first frame rate” according to the embodiments of the technology of the present disclosure, and the output frame rate is an example of a “second frame rate” according to the embodiments of the technology of the present disclosure.

(58) The imaging frame rate and the output frame rate have a relationship of “imaging frame rate > output frame rate”. That is, the imaging frame rate is a frame rate higher than the output frame rate. For example, the imaging frame rate is a frame rate at which imaging of eight frames is performed within a period T as illustrated in FIG. 3A, and the output frame rate is a frame rate at which two frames are output within the period T as illustrated in FIG. 3B. Specifically, 240 frames per second (fps) is exemplified as an example of the imaging frame rate, and 60 fps is exemplified as an example of the output frame rate.

(59) As illustrated in FIG. 4 as an example, the controller **46** comprises a CPU **46A**, a ROM **46B**, a RAM **46C**, a first communication I/F **46D1**, a second communication I/F **46D2**, and a third communication I/F **46D3**. The CPU **46A**, the ROM **46B**, the RAM **46C**, the first communication I/F **46D1**, the second communication I/F **46D2**, and the third communication I/F **46D3** are connected to each other through a busline **88**.

(60) The ROM **46B** stores various programs. The CPU **46A** reads out the various programs from the ROM **46B** and loads the read various programs into the RAM **46C**. The CPU **46A** controls the entire imaging apparatus **10** in accordance with the various programs loaded in the RAM **46C**.

(61) The various programs stored in the ROM **46B** include a timing control program **46B1** and a pixel data processing program **46B2**. The CPU **46A** executes timing control processing (refer to FIG. **12**), described later, in accordance with the timing control program **46B1**. In addition, the CPU **46A** executes pixel data processing (refer to FIG. **15**), described later, in accordance with the pixel data processing program **46B2**.

(62) Each of the first communication I/F **46D1**, the second communication I/F **46D2**, and the third communication I/F **46D3** is a communication device including an FPGA. The first communication I/F **46D1** is connected to the signal processing portion **50** through the communication line **60**. The image data **69** (refer to FIG. **2**, FIG. **3A**, and FIG. **3B**) on which the various types of signal processing are performed by the signal processing portion **50** is input into the first communication I/F **46D1** through the communication line **60**. The first communication I/F **46D1** transfers the image data **69** input from the signal processing portion **50** to the CPU **46A**.

(63) The second communication I/F **46D2** is connected to the imaging element **44** through the communication line **57**. The CPU **46A** controls the imaging element **44** through the second communication I/F **46D2**.

(64) The third communication I/F **46D3** is connected to the motor **17** through the communication line **55**. The CPU **46A** controls the motor **17** through the third communication I/F **46D3**.

(65) A secondary storage device **80** and an external I/F **82** are connected to the busline **88**. The secondary storage device **80** is a non-volatile memory such as an SSD, an HDD, or an EEPROM. The CPU **46A** reads out and writes various types of information in the secondary storage device **80**.

(66) The external I/F **82** is a communication device including an FPGA. The predetermined recording medium is connected to the external I/F **82**. In addition, an external apparatus (not illustrated) such as a PC or a server is connected to the external I/F **82**. The external I/F **82** exchanges various types of information between the CPU **46A** and the external apparatus.

(67) The UI system device **48** comprises the touch panel display **26** and a reception device **84**. A display **32** is connected to the busline **88**. A liquid crystal display is exemplified as an example of the display **32**. Instead of the liquid crystal display, the display **32** may be a display of other types such as an organic EL display. The display **32** displays various images such as the live view image and the still picture image and also text information under control of the CPU **46A**. The display **32** is an example of a “display portion (display)” according to the embodiments of the technology of the present disclosure. In addition, the CPU **46A** is an example of a “control portion (processor)” according to the embodiments of the technology of the present disclosure.

(68) The reception device **84** comprises a hard key portion **25** and a touch panel **34**. The hard key portion **25** includes a plurality of hard keys including the release button **20** and the dial **22**. The touch panel **34** is a transmissive touch panel and is overlaid on a surface of a display region of the display **32**. The touch panel **34** detects a contact of an instruction object such as a finger or a stylus pen. The hard key portion **25** and the touch panel **34** are connected to the busline **88**, and the CPU **46A** operates in accordance with various instructions received by each of the hard key portion **25** and the touch panel **34**.

(69) As illustrated in FIG. **5** as an example, the imaging element **44** incorporates a photoelectric conversion element **61**, a processing circuit **62**, and a memory **64**. The imaging element **44** is an imaging element in which the photoelectric conversion element **61**, the processing circuit **62**, and the memory **64** are formed in one chip. That is, the photoelectric conversion element **61**, the processing circuit **62**, and the memory **64** are formed in one package. In the imaging element **44**, the photoelectric conversion element **61** is laminated with the processing circuit **62** and the memory **64**. Specifically, the photoelectric conversion element **61** and the processing circuit **62** are electrically connected to each other by a bump (not illustrated) of copper or the like having

conductivity. The processing circuit **62** and the memory **64** are also electrically connected to each other by a bump (not illustrated) of copper or the like having conductivity. While a three-layer structure of the photoelectric conversion element **61**, the processing circuit **62**, and the memory **64** is illustrated here, the technology of the present disclosure is not limited thereto. A two-layer structure of the photoelectric conversion element **61** and a memory layer in which the processing circuit **62** and the memory **64** are formed in one layer may be used. The memory **64** is an example of a “storage portion (memory)” according to the embodiments of the technology of the present disclosure.

(70) The processing circuit **62** is, for example, an LSI, and the memory **64** is, for example, a DRAM. However, the technology of the present disclosure is not limited thereto, and an SRAM may be employed as the memory **64** instead of the DRAM.

(71) The processing circuit **62** is a device including an ASIC and an FPGA and controls the entire imaging element **44** in accordance with an instruction of the controller **46**. While an example of implementing the processing circuit **62** by the device including the ASIC and the FPGA is exemplified here, the technology of the present disclosure is not limited thereto. For example, a device including an ASIC, an FPGA, and/or a PLD may be used. In addition, a computer including a CPU, a ROM, and a RAM may be employed as the processing circuit **62**. The number of CPUs may be singular or plural. In addition, the processing circuit **62** may be implemented by a combination of a hardware configuration and a software configuration.

(72) The photoelectric conversion element **61** includes a plurality of photodiodes arranged in a matrix form. Photodiodes of “4896×3265” pixels are exemplified as an example of the plurality of photodiodes.

(73) Color filters are arranged in each photodiode included in the photoelectric conversion element **61**. The color filters include a G filter corresponding to green (G) that most contributes to obtaining a brightness signal, an R filter corresponding to red (R), and a B filter corresponding to blue (B). The photoelectric conversion element **61** includes R pixels, G pixels, and B pixels (refer to FIG. 6). The R pixels are pixels corresponding to photodiodes in which the R filter is arranged. The G pixels are pixels corresponding to photodiodes in which the G filter is arranged. The B pixels are pixels corresponding to photodiodes in which the B filter is arranged.

(74) The imaging element **44** has a so-called electronic shutter function and controls an electric charge accumulation time period of each photodiode in the photoelectric conversion element **61** by performing the electronic shutter function under control of the controller **46**. The electric charge accumulation time period refers to a so-called shutter speed.

(75) In the imaging apparatus **10**, the imaging for the still picture image and imaging for the motion picture image are performed using a rolling shutter method. In the still picture image recording imaging mode, the imaging for the still picture image is implemented by performing the electronic shutter function and operating the mechanical shutter **42** (refer to FIG. 2). In addition, in the still picture image recording imaging mode, imaging for continuous shooting is implemented by performing the electronic shutter function without operating the mechanical shutter **42**. In addition, in the motion picture image recording imaging mode, the imaging for the motion picture image is implemented by performing the electronic shutter function without operating the mechanical shutter **42**. Furthermore, in the display motion picture imaging mode, imaging for the live view image is also implemented by performing the electronic shutter function without operating the mechanical shutter **42**. While the rolling shutter method is illustrated here, the technology of the present disclosure is not limited thereto. A global shutter method may be applied instead of the rolling shutter method.

(76) The processing circuit **62** reads out the image data **69** obtained by imaging the subject by the photoelectric conversion element **61**. The image data **69** is signal electric charges accumulated in the photoelectric conversion element **61**. The processing circuit **62** performs A/D conversion on the analog image data **69** read out from the photoelectric conversion element **61**. The processing circuit

62 stores the digital image data **69** obtained by performing the A/D conversion on the analog image data **69** in the memory **64**.

(77) The processing circuit **62** is connected to the signal processing portion **50** through the communication line **53**. In addition, the processing circuit **62** is connected to the second communication I/F **46D2** of the controller **46** through the communication line **57**.

(78) The memory **54** comprises a plurality of storage regions including a first storage region **64A**, a second storage region **64B**, a third storage region **64C**, a fourth storage region **64D**, and a fifth storage region **64E**. For example, each of the plurality of storage regions stores the digital image data **69** at addresses corresponding to the pixels of the photoelectric conversion element **61** in units of pixels for each frame. In addition, the plurality of storage regions are randomly accessed by the processing circuit **62**.

(79) As illustrated in FIG. **6** as an example, the R pixels, the G pixels, and the B pixels are arranged on the imaging surface **44A** of the photoelectric conversion element **61** with predetermined periodicity in each of a row direction (horizontal direction) and a column direction (vertical direction). In the first embodiment, the R pixels, the G pixels, and the B pixels are arranged with periodicity corresponding to X-Trans (registered trademark) arrangement. While the X-Trans arrangement is illustrated in the example illustrated in FIG. **6**, the technology of the present disclosure is not limited thereto. Arrangement of the R pixels, the G pixels, and the B pixels may be Bayer arrangement or honeycomb arrangement.

(80) In the example illustrated in FIG. **6**, in a first row, the R pixels, the G pixels, and the B pixels are arranged in circulation in an order of the G pixel, the B pixel, the R pixel, the G pixel, the R pixel, and the B pixel in the row direction. In addition, in a second row, the R pixels, the G pixels, and the B pixels are arranged in circulation in an order of the R pixel, the G pixel, the G pixel, the B pixel, the G pixel, and the G pixel in the row direction. In addition, in a third row, the R pixels, the G pixels, and the B pixels are arranged in circulation in an order of the B pixel, the G pixel, the G pixel, the R pixel, the G pixel, and the G pixel in the row direction. In addition, in a fourth row, the R pixels, the G pixels, and the B pixels are arranged in circulation in an order of the G pixel, the R pixel, the B pixel, the G pixel, the B pixel, and the R pixel in the row direction. In addition, in a fifth row, the R pixels, the G pixels, and the B pixels are arranged in circulation in an order of the B pixel, the G pixel, the G pixel, the R pixel, the G pixel, and the G pixel in the row direction. Furthermore, in a sixth row, the R pixels, the G pixels, and the B pixels are arranged in circulation in an order of the R pixel, the G pixel, the G pixel, the B pixel, the G pixel, and the G pixel in the row direction. An arrangement pattern of the R pixels, the G pixels, and the B pixels of the entire photoelectric conversion element **61** is formed by repetition of an arrangement pattern of the R pixels, the G pixels, and the B pixels of the first row to the sixth row in units of six rows in the column direction.

(81) The photoelectric conversion element **61** is formed by two types of photosensitive pixels of phase difference pixels and non-phase difference pixels N that are pixels different from the phase difference pixels. Generally, the non-phase difference pixels N are also referred to as normal pixels. A plurality of phase difference pixel lines **61A** and a plurality of non-phase difference pixel lines **61B** are arranged on the imaging surface **44A**. The phase difference pixel lines **61A** are horizontal lines including the phase difference pixels. Specifically, the phase difference pixel lines **61A** are horizontal lines in which the phase difference pixels and the non-phase difference pixels N coexist. The non-phase difference pixel lines **61B** are horizontal lines including only a plurality of non-phase difference pixels N, that is, horizontal lines consisting of a plurality of non-phase difference pixels N. The phase difference pixel lines **61A** are an example of a “first line” according to the embodiments of the technology of the present disclosure, and the non-phase difference pixel lines **61B** are an example of a “second line” according to the embodiments of the technology of the present disclosure.

(82) As illustrated in FIG. **6** as an example, the phase difference pixel lines **61A** and a

predetermined number of lines of the non-phase difference pixel lines **61B** are alternately arranged on the imaging surface **44A** in the column direction. For example, the “predetermined number of lines” here refer to two lines. While two lines are illustrated here as the predetermined number of lines, the technology of the present disclosure is not limited thereto. The predetermined number of lines may be a few lines more than or equal to three lines, ten and a few lines, a few tens of lines, a few hundred lines, or the like. In addition, in the example illustrated in FIG. **6**, the row direction is an example of a “line direction of the first line” according to the embodiments of the technology of the present disclosure, and the column direction is an example of a “direction intersecting with the line direction of the first line” according to the embodiments of the technology of the present disclosure.

(83) The phase difference pixel lines **61A** are arranged in the column direction by skipping two lines at a time from the first row to a last row. Pixels of a part of the phase difference pixel lines **61A** are the phase difference pixels. Specifically, the phase difference pixel lines **61A** are horizontal lines in which the phase difference pixels and the non-phase difference pixels **N** are periodically arranged. The phase difference pixels are broadly divided into first phase difference pixels **L** and second phase difference pixels **R**. In the phase difference pixel lines **61A**, the first phase difference pixels **L** and the second phase difference pixels **R** are alternately arranged at intervals of a few pixels in the line direction as the **G** pixels.

(84) The first phase difference pixels **L** and the second phase difference pixels **R** are arranged to alternately appear in the column direction. In the example illustrated in FIG. **6**, in a fourth column, the first phase difference pixel **L**, the second phase difference pixel **R**, the first phase difference pixel **L**, and the second phase difference pixel **R** are arranged in this order in the column direction from the first row. That is, the first phase difference pixels **L** and the second phase difference pixels **R** are alternately arranged in the column direction from the first row. In addition, in the example illustrated in FIG. **6**, in a tenth column, the second phase difference pixel **R**, the first phase difference pixel **L**, the second phase difference pixel **R**, and the first phase difference pixel **L** are arranged in this order in the column direction from the first row. That is, the second phase difference pixels **R** and the first phase difference pixels **L** are alternately arranged in the column direction from the first row.

(85) As illustrated in FIG. **7** as an example, each first phase difference pixel **L** comprises a microlens **19**, a light shielding member **21A**, and a photodiode **PD**. In the first phase difference pixel **L**, the light shielding member **21A** is arranged between the microlens **19** and a light receiving surface of the photodiode **PD**. A left half (left side in a case of facing the subject from the light receiving surface (in other words, a right side in a case of facing the light receiving surface from the subject)) of the light receiving surface of the photodiode **PD** in the row direction is shielded against light by the light shielding member **21A**.

(86) Each second phase difference pixel **R** comprises the microlens **19**, a light shielding member **21B**, and the photodiode **PD**. In the second phase difference pixel **R**, the light shielding member **21B** is arranged between the microlens **19** and the light receiving surface of the photodiode **PD**. A right half (right side in a case of facing the subject from the light receiving surface (in other words, a left side in a case of facing the light receiving surface from the subject)) of the light receiving surface of the photodiode **PD** in the row direction is shielded against light by the light shielding member **21B**.

(87) Luminous flux passing through an exit pupil of the imaging lens **40** is broadly divided into left region passing light **300L** and right region passing light **300R**. The left region passing light **300L** refers to luminous flux of a left half of the luminous flux passing through the exit pupil of the imaging lens **40** in a case of facing a subject side from a phase difference pixel side. The right region passing light **300R** refers to luminous flux of a right half of the luminous flux passing through the exit pupil of the imaging lens **40** in a case of facing the subject side from the phase difference pixel side. The luminous flux passing through the exit pupil of the imaging lens **40** is

divided leftward and rightward by the microlens **19** and the light shielding members **21A** and **21B** functioning as a pupil separation portion. The first phase difference pixel **L** receives the left region passing light **300L** as the subject light, and the second phase difference pixel **R** receives the right region passing light **300R** as the subject light. Consequently, a first phase difference image corresponding to a subject image corresponding to the left region passing light **300L** and a second phase difference image corresponding to a subject image corresponding to the right region passing light **300R** are generated by the imaging element **44**.

(88) Hereinafter, for convenience of description, the first phase difference pixel **L** and the second phase difference pixel **R** will be referred to as the “phase difference pixel” unless otherwise necessary to distinguish therebetween. In addition, hereinafter, for convenience of description, the light shielding members **21A** and **21B** will be referred to as the “light shielding member” without the reference numerals unless otherwise necessary to distinguish therebetween.

(89) As illustrated in FIG. **8** as an example, the non-phase difference pixel is different from the phase difference pixel in that the light shielding member is not included. The photodiode **PD** of the non-phase difference pixel receives the left region passing light **300L** and the right region passing light **300R** as the subject light.

(90) As illustrated in FIG. **9** as an example, the processing circuit **62** comprises a reading circuit **62A**, a digital processing circuit **62B**, an image processing circuit **62C**, an output circuit **62D**, and a control circuit **62E**. The reading circuit **62A** is an example of a “reading portion (reading circuit)” according to the embodiments of the technology of the present disclosure. The output circuit **62D** is an example of an “output portion (output circuit)” according to the embodiments of the technology of the present disclosure.

(91) The reading circuit **62A** comprises a first reading circuit **62A1** and a second reading circuit **62A2**. The first reading circuit **62A1** is an example of a “first reading portion (first reading circuit)” according to the embodiments of the technology of the present disclosure, and the second reading circuit **62A2** is an example of a “second reading portion (second reading circuit)” according to the embodiments of the technology of the present disclosure.

(92) Each of the first reading circuit **62A1** and the second reading circuit **62A2** is connected to the photoelectric conversion element **61**, the digital processing circuit **62B**, and the control circuit **62E**. The memory **64** is connected to the control circuit **62E**. The image processing circuit **62C** is also connected to the control circuit **62E**. The output circuit **62D** is also connected to the control circuit **62E**. The control circuit **62E** is connected to the controller **46** through the communication line **57**. The output circuit **62D** is connected to the signal processing portion **50** through the communication line **53**.

(93) As illustrated in FIG. **9** as an example, the image data **69** is broadly divided into analog pixel data **69A** and digital pixel data **69B**. Hereinafter, for convenience of description, the analog pixel data **69A** and the digital pixel data **69B** will be referred to as the “image data **69**” unless otherwise necessary to distinguish therebetween.

(94) The analog pixel data **69A** is broadly divided into analog phase difference pixel data **69A1** that is analog pixel data of the phase difference pixel, and analog non-phase difference pixel data **69A2** that is analog pixel data of the non-phase difference pixel **N**. The digital pixel data **69B** is broadly divided into digital phase difference pixel data **69B1** and digital non-phase difference pixel data **69B2**. The digital phase difference pixel data **69B1** is pixel data obtained by digitizing the analog phase difference pixel data **69A1**. The digital non-phase difference pixel data **69B2** is pixel data obtained by digitizing the analog non-phase difference pixel data **69A2**.

(95) The analog pixel data **69A** and the digital pixel data **69B** are an example of “pixel data” according to the embodiments of the technology of the present disclosure. The analog phase difference pixel data **69A1** and the digital phase difference pixel data **69B1** are an example of “second pixel data” according to the embodiments of the technology of the present disclosure. The analog non-phase difference pixel data **69A2** and the digital non-phase difference pixel data **69B2**

are an example of “first pixel data” according to the embodiments of the technology of the present disclosure.

(96) The controller **46** supplies a timing control signal to the control circuit **62E** through the communication line **57**. The timing control signal includes an imaging vertical synchronization signal and an output vertical synchronization signal. The output vertical synchronization signal is a synchronization signal for defining an output timing in units of frames. In other words, the output vertical synchronization signal is a synchronization signal for defining the output frame rate. That is, an output period in which the digital pixel data **69B** of one frame is output (hereinafter, simply referred to as the “output period”) is defined by the output vertical synchronization signal. The imaging vertical synchronization signal is a synchronization signal for defining an imaging timing in units of frames. In other words, the imaging vertical synchronization signal is a synchronization signal for defining the imaging frame rate. That is, an interval in which imaging is performed is defined by the imaging vertical synchronization signal.

(97) In the first embodiment, a plurality of imaging vertical synchronization signals are supplied to the control circuit **62E** from the controller **46** within the output period. Accordingly, imaging of a plurality of frames is performed within the output period.

(98) The reading circuit **62A** reads out, in units of horizontal lines, the analog pixel data **69A** that is obtained by imaging the subject at the imaging frame rate. That is, the reading circuit **62A** controls the photoelectric conversion element **61** and reads out the analog pixel data **69A** from the photoelectric conversion element **61** in units of horizontal lines under control of the control circuit **62E**. The reading circuit **62A** is a circuit that can selectively read out the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** for all pixels included in the photoelectric conversion element **61**. As will be described in detail later, selectively reading of the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** is implemented by the first reading circuit **62A1** and the second reading circuit **62A2**. While an example of a form of selectively reading out the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** for all pixels included in the photoelectric conversion element **61** is exemplified here, the technology of the present disclosure is not limited thereto. For example, the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** may be selectively read out for a designated pixel group of a part of all pixels included in the photoelectric conversion element **61**.

(99) Reading of the analog pixel data **69A** of one frame from the photoelectric conversion element **61** is started in accordance with the imaging vertical synchronization signal. The control circuit **62E** transfers the imaging vertical synchronization signal supplied from the controller **46** to the reading circuit **62A**. In a case where the imaging vertical synchronization signal is input from the control circuit **62E**, the reading circuit **62A** starts reading out the analog pixel data **69A** of one frame from the photoelectric conversion element **61**.

(100) Specifically, the control circuit **62E** transfers the imaging vertical synchronization signal supplied from the controller **46** to the first reading circuit **62A1** and the second reading circuit **62A2**. In a case where the imaging vertical synchronization signal is input into each of the first reading circuit **62A1** and the second reading circuit **62A2**, reading of the analog phase difference pixel data **69A1** from the phase difference pixel and reading of the analog non-phase difference pixel data **69A2** from the non-phase difference pixel **N** are independently performed. Reading of the analog phase difference pixel data **69A1** is performed by the first reading circuit **62A1**, and reading of the analog non-phase difference pixel data **69A2** is performed by the second reading circuit **62A2**.

(101) More specifically, in a case where the imaging vertical synchronization signal is input from the control circuit **62E**, the first reading circuit **62A1** reads out the analog phase difference pixel data of one frame from each phase difference pixel of the photoelectric conversion element **61** for each phase difference pixel line **61A**. The second reading circuit **62A2** reads out the analog non-

phase difference pixel data of one frame from each non-phase difference pixel N of the photoelectric conversion element **61** for each non-phase difference pixel line **61B** in a case where a reading start condition (described later) is satisfied. The “reading start condition” here refers to a condition that the imaging vertical synchronization signal is input from the control circuit **62E**, and that reading of the analog phase difference pixel data of one frame by the first reading circuit **62A1** is completed.

(102) The reading circuit **62A** performs analog signal processing on the analog pixel data **69A** read out from the photoelectric conversion element **61**. The analog signal processing includes well-known processing such as noise cancelation processing and analog gain processing. The noise cancelation processing is processing of canceling a noise caused by variations in characteristics between pixels included in the photoelectric conversion element **61**. The analog gain processing is processing of applying a gain to the analog pixel data **69A**. The analog pixel data **69A** on which the analog signal processing is performed in such a manner is output to the digital processing circuit **62B** by the reading circuit **62A**.

(103) The digital processing circuit **62B** comprises an A/D converter **62B1**. The digital processing circuit **62B** performs digital signal processing on the analog pixel data **69A** input from the reading circuit **62A**. For example, the digital signal processing includes correlative double sampling, A/D conversion performed by the A/D converter **62B1**, and digital gain processing.

(104) The correlative double sampling is performed on the analog pixel data **69A** by the digital processing circuit **62B**. The A/D converter **62B1** performs the A/D conversion on the analog pixel data **69A** on which signal processing of the correlative double sampling is performed. Accordingly, the analog pixel data **69A** is digitized, and the digital pixel data **69B** is obtained. The digital gain processing is performed on the digital pixel data **69B** by the digital processing circuit **62B**. The digital gain processing refers to processing of applying a gain to the digital pixel data **69B**.

(105) The control circuit **62E** acquires the digital pixel data **69B**, which is obtained by performing the digital signal processing, from the digital processing circuit **62B** and stores the acquired digital pixel data **69B** in the memory **64**.

(106) The memory **64** is a memory that can store the digital pixel data **69B** of a plurality of frames. The memory **64** has a plurality of storage regions (refer to FIG. 5). The digital pixel data **69B** is stored in a corresponding storage region of the memory **64** in units of pixels by the control circuit **62E**.

(107) The control circuit **62E** can randomly access the memory **64** and acquires the digital non-phase difference pixel data **69B2** from the memory **64**. The control circuit **62E** outputs the digital non-phase difference pixel data **69B2** acquired from the memory **64** to the image processing circuit **62C**. The image processing circuit **62C** performs image processing on the digital non-phase difference pixel data **69B2** input from the control circuit **62E**. Demosaicing, digital thinning processing, digital addition processing, data filling processing, and the like are exemplified as the “image processing” here.

(108) The demosaicing is processing of calculating every color information for each pixel from a mosaic image corresponding to arrangement of the color filters. For example, in a case of an imaging element consisting of color filters of three colors of R, G, and B, color information on all of R, G, and B is calculated from a mosaic image consisting of R, G, and B for each pixel.

(109) The digital thinning processing is processing of thinning out pixels included in the digital non-phase difference pixel data **69B2** in units of lines. For example, the units of lines refer to units of horizontal lines and/or units of vertical lines. The digital addition processing is, for example, processing of calculating an arithmetic mean of pixel values for a plurality of pixels included in the digital non-phase difference pixel data **69B2**. Processing of filling a lower empty bit of the digital non-phase difference pixel data **69B2** with specific data, or the like is exemplified as the data filling processing. For example, information for specifying a method of the digital thinning processing performed on the digital non-phase difference pixel data **69B2**, or a frame number for

specifying a frame is exemplified as the “specific data” here.

(110) The image processing circuit **62C** outputs the digital non-phase difference pixel data **69B2** after the image processing to the control circuit **62E**. The control circuit **62E** stores the digital non-phase difference pixel data **69B2** input from the image processing circuit **62C** in the memory **64**. The digital non-phase difference pixel data **69B2** after the image processing is an example of “image data based on pixel data” and “first pixel data based on phase difference pixel data” according to the embodiments of the technology of the present disclosure.

(111) The control circuit **62E** acquires the digital pixel data **69B** from the memory **64**. The control circuit **62E** outputs the digital pixel data **69B** acquired from the memory **64** to the output circuit **62D**.

(112) Specifically, each time the digital phase difference pixel data **69B1** of one frame is stored in the memory **64**, the control circuit **62E** acquires the digital phase difference pixel data **69B1** of one frame from the memory **64** without waiting for storage of the digital non-phase difference pixel data in the memory **64**. The control circuit **62E** outputs the most recent digital phase difference pixel data **69B1** of one frame acquired from the memory **64** to the output circuit **62D**.

(113) In a case where acquisition of the digital phase difference pixel data **69B1** corresponding to the analog phase difference pixel data **69A1** of one frame read out by the first reading circuit **62A1** within the output period is completed, the control circuit **62E** acquires the digital non-phase difference pixel data **69B2** from the memory **64**. The digital non-phase difference pixel data **69B2** acquired from the memory **64** is the digital non-phase difference pixel data **69B2** corresponding to the analog non-phase difference pixel data **69A2** of one frame read out by the second reading circuit **62A2** within the output period. The control circuit **62E** outputs the digital non-phase difference pixel data **69B2** acquired from the memory **64** to the output circuit **62D**.

(114) In a case of outputting the digital pixel data **69B** of one frame, the output circuit **62D** outputs the digital phase difference pixel data **69B1** and the digital non-phase difference pixel data **69B2** at different timings. Specifically, first, the output circuit **62D** outputs the digital phase difference pixel data **69B1** and then, outputs the digital non-phase difference pixel data **69B2** after output of the digital phase difference pixel data **69B1** is completed.

(115) The digital phase difference pixel data **69B1** of all frames read out within the output period is output to the output circuit **62D** by the control circuit **62E** earlier than the digital non-phase difference pixel data **69B2**. The output circuit **62D** outputs the digital pixel data **69B** input from the control circuit **62E** to the signal processing portion **50** in order of input. First, the output circuit **62D** outputs the digital phase difference pixel data **69B1** of all frames read out within the output period to the signal processing portion **50** and next, outputs the digital non-phase difference pixel data **69B2** of all frames read out within the output period to the signal processing portion **50**.

(116) In the imaging apparatus **10**, imaging using the rolling shutter method is performed. Accordingly, as illustrated in FIG. **10** as an example, a gap occurs between a reading start timing and a reading finish timing. The reading start timing is a timing at which reading of a horizontal line (hereinafter, referred to as a “first horizontal line”) predetermined as a horizontal line in which reading is performed first among all horizontal lines of an imaging region of the imaging element **44** is performed. The reading finish timing is a timing at which reading of a horizontal line (hereinafter, referred to as a “last horizontal line”) predetermined as a horizontal line in which reading is performed last among all horizontal lines of the imaging region of the imaging element **44** is performed. In the rolling shutter method, reading of the analog pixel data **69A** is sequentially performed for each horizontal line in all horizontal lines of the imaging region of the imaging element **44** in accordance with a horizontal synchronization signal. Thus, the reading finish timing is reached later than the reading start timing. Accordingly, a gap occurs between a timing at which exposure is performed on the first horizontal line, and a timing at which the exposure is performed on the last horizontal line.

(117) In FIG. **10**, an example of an aspect of each of a reading timing and a reset timing of four

frames within one output period is illustrated. In the example illustrated in FIG. 10, “F” is the abbreviation for “frame”. In the example illustrated in FIG. 10, imaging of four frames is performed within one output period. That is, reading of a plurality of pieces of analog pixel data 69A is performed in parallel within one output period. For example, in reading of a first frame to a fourth frame within one output period, reading of the first frame and reading of the second frame are performed in parallel. Accordingly, resetting of the first frame and resetting of the second frame are also performed in parallel. That is, a reading period of the first frame and a reading period of the second frame overlap partially, and a reset period of the first frame and a reset period of the second frame overlap partially. The same applies to the second frame and the third frame. In addition, the same applies to the third frame and the fourth frame.

(118) In such a manner, reading of the analog non-phase difference pixel data 69A2 of four frames and reading of the analog phase difference pixel data 69A1 of four frames are performed within one output period. That is, within one output period, plural reading of the analog phase difference pixel data 69A1 are performed in addition to reading of the analog non-phase difference pixel data 69A2. Here, “reading of the analog non-phase difference pixel data 69A2” refers to reading of the analog non-phase difference pixel data 69A2 from the non-phase difference pixel N. In addition, the “plural reading of the analog phase difference pixel data 69A1” refers to plural reading of the analog phase difference pixel data 69A1 from the phase difference pixel. That is, this means that the analog phase difference pixel data 69A1 is read out many times from the same phase difference pixel within one output period.

(119) In addition, as illustrated in FIG. 10 as an example, in each frame, first, the analog phase difference pixel data 69A1 is read out from the photoelectric conversion element 61 by the first reading circuit 62A1. That is, the analog phase difference pixel data 69A1 is read out one line at a time by the first reading circuit 62A1 using all phase difference pixel lines 61A of one frame as a reading target. Each time reading of one phase difference pixel line 61A by the first reading circuit 62A1 is completed, resetting by the first reading circuit 62A1 is performed.

(120) In a case where reading of the analog phase difference pixel data 69A1 for all phase difference pixel lines 61A is completed, next, the analog non-phase difference pixel data 69A2 is read out one line at a time by the second reading circuit 62A2 using all non-phase difference pixel lines 61B as the reading target. Each time reading of one non-phase difference pixel line 61B by the second reading circuit 62A2 is completed, resetting by the second reading circuit 62A2 is performed.

(121) In such a manner, in a reading period of one frame, reading of the analog phase difference pixel data 69A1 from the phase difference pixel by the first reading circuit 62A1 is performed earlier than reading of the analog non-phase difference pixel data 69A2 from the non-phase difference pixel N by the second reading circuit 62A2.

(122) In addition, in the example illustrated in FIG. 10, reading of the analog non-phase difference pixel data 69A2 of the first frame and reading of the analog phase difference pixel data 69A1 of the second frame are performed in parallel. That is, a reading period of the analog non-phase difference pixel data 69A2 of the first frame overlaps with a reading period of the analog phase difference pixel data 69A1 of the second frame. The same applies to the second frame and the third frame. In addition, the same applies to the third frame and the fourth frame.

(123) As illustrated in FIG. 11 as an example, the analog phase difference pixel data 69A1 read out by the first reading circuit 62A1 for each frame within one output period is digitized by the A/D converter 62B1 and converted into the digital phase difference pixel data 69B1. In a case where digitization of all pieces of the analog phase difference pixel data 69A1 read out within one output period is completed, the A/D conversion is performed on the analog non-phase difference pixel data 69A2 read out by the second reading circuit 62A2 for each frame within one output period. That is, the analog non-phase difference pixel data 69A2 read out by the second reading circuit 62A2 for each frame is digitized by the A/D converter 62B1 and converted into the digital non-

phase difference pixel data **69B2**.

(124) In such a manner, the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** are subjected to the A/D conversion at different timings by the A/D converter **62B1**. This is because the A/D converter **62B1** is shared for the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2**.

(125) As illustrated in FIG. **11** as an example, each piece of the digital phase difference pixel data **69B1** obtained by performing the A/D conversion for each frame is stored in a corresponding storage region of the memory **64**. In the example illustrated in FIG. **11**, the digital phase difference pixel data **69B1** of the first frame is stored in the first storage region **64A**. In addition, the digital phase difference pixel data **69B1** of the second frame is stored in the second storage region **64B**. In addition, the digital phase difference pixel data **69B1** of the third frame is stored in the third storage region **64C**. In addition, the digital phase difference pixel data **69B1** of the fourth frame is stored in the fourth storage region **64D**.

(126) The digital non-phase difference pixel data **69B2** obtained by performing the A/D conversion for each frame is combined into one frame and stored in the fifth storage region **64E**. Here, for example, “combining” refers to an arithmetic mean, in units of pixels, of the digital non-phase difference pixel data **69B2** of a plurality of frames (in the example illustrated in FIG. **11**, the first frame to the fourth frame) obtained by performing imaging within one output period. In such a manner, by calculating the arithmetic mean of the digital non-phase difference pixel data **69B2** of the plurality of frames in units of pixels, the digital non-phase difference pixel data **69B2** of one frame is generated.

(127) While an example in which the digital non-phase difference pixel data **69B2** of the plurality of frames is combined into one frame is illustratively described here, the technology of the present disclosure is not limited thereto. For example, all pieces of the digital non-phase difference pixel data **69B2** of the plurality of frames may be stored in the memory **64**. In addition, the analog non-phase difference pixel data **69A2** may be read out by the second reading circuit **62A2** for only one representative frame (for example, the first frame) of the plurality of frames. In this case, as will be described in detail later as a modification example, the analog non-phase difference pixel data **69A2** is not read out by the second reading circuit **62A2** for the other frames (for example, the second frame to the fourth frame) (refer to FIG. **16**). Thus, only the analog non-phase difference pixel data **69A2** of one frame is subjected to the A/D conversion, and the “combining” is not necessary.

(128) In a case where the digital phase difference pixel data **69B1** is stored in the memory **64** in units of frames, the digital phase difference pixel data **69B1** in the memory **64** is transferred to the output circuit **62D** at a timing at which storage of the digital phase difference pixel data **69B1** of one frame in the memory **64** is completed. That is, the digital phase difference pixel data **69B1** in the memory **64** is acquired from the memory **64** and output to the output circuit **62D** by the control circuit **62E**. The output circuit **62D** outputs the digital phase difference pixel data **69B1** input from the control circuit **62E** to the signal processing portion **50**.

(129) After the digital phase difference pixel data **69B1** in the memory **64** is output by the output circuit **62D**, the digital non-phase difference pixel data **69B2** in the memory **64** is acquired from the memory **64** and output to the output circuit **62D** by the control circuit **62E**. The output circuit **62D** outputs the digital non-phase difference pixel data **69B2** input from the control circuit **62E** to the signal processing portion **50**.

(130) Next, an action of the imaging apparatus **10** will be described.

(131) First, the timing control processing executed by the CPU **46A** in accordance with the timing control program **46B1** in a case where a condition under which execution of the timing control processing is started is satisfied will be described with reference to FIG. **12**. For example, a condition that the imaging mode is set is exemplified as the condition under which execution of the timing control processing is started.

(132) In the timing control processing illustrated in FIG. 12, first, in step ST10, the CPU 46A determines whether or not the reading start timing is reached. The reading start timing refers to a timing at which the imaging element 44 is instructed to start reading out the analog pixel data 69A from the photoelectric conversion element 61. In step ST10, in a case where the reading start timing is not reached, a negative determination is made, and the timing control processing transitions to step ST18. In step ST10, in a case where the reading start timing is reached, a positive determination is made, and the timing control processing transitions to step ST12.

(133) In step ST12, the CPU 46A outputs the imaging vertical synchronization signal to the imaging element 44. Then, the timing control processing transitions to step ST14. The imaging vertical synchronization signal output by executing processing of step ST12 is received by the control circuit 62E of the imaging element 44. In the imaging element 44, imaging is performed at the imaging frame rate that is determined in accordance with the imaging vertical synchronization signal received by the control circuit 62E.

(134) In step ST14, the CPU 46A determines whether or not the number of times of output of the imaging vertical synchronization signal reaches a predetermined number of times (for example, four times). In step ST14, in a case where the number of times of output of the imaging vertical synchronization signal does not reach the predetermined number of times, a negative determination is made, and the timing control processing transitions to step ST18. In step ST14, in a case where the number of times of output of the imaging vertical synchronization signal reaches the predetermined number of times, a positive determination is made, and the timing control processing transitions to step ST16.

(135) In step ST16, the CPU 46A outputs the output vertical synchronization signal to the imaging element 44. Then, the timing control processing transitions to step ST18. The output vertical synchronization signal output by executing processing of step ST16 is received by the control circuit 62E of the imaging element 44. In the imaging element 44, the digital pixel data 69B is output by the output circuit 62D at the output frame rate that is determined in accordance with the output vertical synchronization signal received by the control circuit 62E.

(136) In step ST18, the CPU 46A determines whether or not a condition (hereinafter, referred to as a “timing control processing finish condition”) under which the timing control processing is finished is satisfied. For example, a condition that an instruction to finish the timing control processing is received by the reception device 84 (refer to FIG. 4) is exemplified as the timing control processing finish condition. In step ST18, in a case where the timing control processing finish condition is not satisfied, a negative determination is made, and the timing control processing transitions to step ST10. In step ST18, in a case where the timing control processing finish condition is satisfied, a positive determination is made, and the timing control processing is finished.

(137) Next, phase difference pixel processing executed by the processing circuit 62 within the output period will be described with reference to FIG. 13.

(138) In the phase difference pixel processing illustrated in FIG. 13, first, in step ST30, the control circuit 62E determines whether or not the imaging vertical synchronization signal output by executing processing of step ST12 of the timing control processing is received. In step ST30, in a case where the imaging vertical synchronization signal is not received, a negative determination is made, and the phase difference pixel processing transitions to step ST40. In step ST30, in a case where the imaging vertical synchronization signal is received, a positive determination is made, and the phase difference pixel processing transitions to step ST32.

(139) In step ST32, the first reading circuit 62A1 reads out the analog phase difference pixel data 69A1 from the phase difference pixel using all phase difference pixel lines 61A of one frame as a target. Then, the phase difference pixel processing transitions to step ST34.

(140) In step ST34, the digital processing circuit 62B converts the analog phase difference pixel data 69A1 into the digital phase difference pixel data 69B1 by performing the digital signal

processing on the analog phase difference pixel data **69A1** read out by the first reading circuit **62A1**.

(141) In subsequent step **ST36**, the control circuit **62E** acquires the digital phase difference pixel data **69B1** from the digital processing circuit **62B** and stores the acquired digital phase difference pixel data **69B1** in the memory **64**. Then, the phase difference pixel processing transitions to step **ST38**.

(142) In a case where the digital phase difference pixel data **69B1** is stored in the memory **64**, the digital phase difference pixel data **69B1** is acquired from the memory **64** by the control circuit **62E**, and the acquired digital phase difference pixel data **69B1** is transferred to the output circuit **62D**.

(143) In subsequent step **ST38**, the output circuit **62D** outputs the digital phase difference pixel data **69B1** input from the control circuit **62E** to the signal processing portion **50**. Then, the phase difference pixel processing transitions to step **ST40**.

(144) In step **ST40**, the control circuit **62E** determines whether or not a condition (hereinafter, referred to as a “phase difference pixel processing finish condition”) under which the phase difference pixel processing is finished is satisfied. For example, a condition that an instruction to finish the phase difference pixel processing is received by the reception device **84** (refer to FIG. 4) is exemplified as the phase difference pixel processing finish condition. In step **ST40**, in a case where the phase difference pixel processing finish condition is not satisfied, a negative determination is made, and the phase difference pixel processing transitions to step **ST30**. In step **ST40**, in a case where the phase difference pixel processing finish condition is satisfied, a positive determination is made, and the phase difference pixel processing is finished.

(145) Next, non-phase difference pixel processing executed by the processing circuit **62** within the output period will be described with reference to FIG. 14.

(146) In the non-phase difference pixel processing illustrated in FIG. 14, first, in step **ST60**, a determination as to whether or not reading of the analog phase difference pixel data **69A1** of one frame by the first reading circuit **62A1** is finished is performed. In step **ST60**, in a case where reading of the analog phase difference pixel data **69A1** of one frame by the first reading circuit **62A1** is not finished, a negative determination is made, and the non-phase difference pixel processing transitions to step **ST72**. In step **ST60**, in a case where reading of the analog phase difference pixel data **69A1** of one frame by the first reading circuit **62A1** is finished, a positive determination is made, and the non-phase difference pixel processing transitions to step **ST62**.

(147) In step **ST62**, the second reading circuit **62A2** reads out the analog non-phase difference pixel data **69A2** from the non-phase difference pixel N using all non-phase difference pixel lines **61B** of one frame as a target. Then, the non-phase difference pixel processing transitions to step **ST64**.

(148) In step **ST64**, the digital processing circuit **62B** converts the analog non-phase difference pixel data **69A2** into the digital non-phase difference pixel data **69B2** by performing the digital signal processing on the analog non-phase difference pixel data **69A2** read out by the second reading circuit **62A2**.

(149) In subsequent step **ST66**, the control circuit **62E** acquires the digital non-phase difference pixel data **69B2** from the digital processing circuit **62B** and stores the acquired digital non-phase difference pixel data **69B2** in the memory **64**. Then, the non-phase difference pixel processing transitions to step **ST68**. The memory **64** stores the digital non-phase difference pixel data **69B2** on which the image processing is performed by the image processing circuit **62C**.

(150) In step **ST68**, the control circuit **62E** determines whether or not a non-phase difference pixel data output timing is reached. The non-phase difference pixel data output timing refers to a timing at which the digital non-phase difference pixel data **69B2** in the memory **64** is output to the signal processing portion **50**. The non-phase difference pixel data output timing may be a timing that does not overlap with an output timing of the digital phase difference pixel data **69B1** of all frames to the signal processing portion **50** within the same output period. For example, a timing at which

output of the digital phase difference pixel data **69B1** of all frames to the signal processing portion **50** within the same output period is completed is exemplified as the non-phase difference pixel data output timing.

(151) In step **ST68**, in a case where the non-phase difference pixel data output timing is not reached, a negative determination is made, and the determination of step **ST68** is performed again. In step **ST68**, in a case where the non-phase difference pixel data output timing is reached, a positive determination is made, and the non-phase difference pixel processing transitions to step **ST70**.

(152) In step **ST70**, the control circuit **62E** acquires the digital non-phase difference pixel data **69B2** from the memory **64** and transfers the acquired digital non-phase difference pixel data **69B2** to the output circuit **62D**. The output circuit **62D** outputs the digital non-phase difference pixel data **69B2** input from the control circuit **62E** to the signal processing portion **50**. Then, the non-phase difference pixel processing transitions to step **ST72**.

(153) In step **ST72**, the control circuit **62E** determines whether or not a condition (hereinafter, referred to as a “non-phase difference pixel processing finish condition”) under which the non-phase difference pixel processing is finished is satisfied. For example, a condition that an instruction to finish the non-phase difference pixel processing is received by the reception device **84** (refer to FIG. **4**) is exemplified as the non-phase difference pixel processing finish condition. In step **ST72**, in a case where the non-phase difference pixel processing finish condition is not satisfied, a negative determination is made, and the non-phase difference pixel processing transitions to step **ST60**. In step **ST72**, in a case where the non-phase difference pixel processing finish condition is satisfied, a positive determination is made, and the non-phase difference pixel processing is finished.

(154) In the signal processing portion **50**, various types of signal processing are performed on the digital pixel data **69B** input from the imaging element **44**, and the digital pixel data **69B** on which the various types of signal processing are performed is output to the controller **46**.

(155) Next, pixel data processing executed by the CPU **46A** in accordance with the pixel data processing program **46B2** in a case where the digital pixel data **69B** is input into the controller **46** from the signal processing portion **50** will be described with reference to FIG. **15**.

(156) In the pixel data processing illustrated in FIG. **15**, first, in step **ST150**, the CPU **46A** determines whether or not the digital pixel data **69B** input from the signal processing portion **50** is the digital non-phase difference pixel data **69B2**. In step **ST150**, in a case where the digital pixel data **69B** input from the signal processing portion **50** is the digital phase difference pixel data **69B1**, a negative determination is made, and the pixel data processing transitions to step **ST154**. In step **ST150**, in a case where the digital pixel data **69B** input from the signal processing portion **50** is the digital non-phase difference pixel data **69B2**, a positive determination is made, and the pixel data processing transitions to step **ST152**.

(157) In step **ST152**, the CPU **46A** outputs the digital non-phase difference pixel data **69B2** to the display **32**. Then, the pixel data processing transitions to step **ST156**.

(158) In a case where the digital non-phase difference pixel data **69B2** is output to the display **32**, the display **32** displays an image based on the digital non-phase difference pixel data **69B2**.

(159) In step **ST154**, the CPU **46A** executes the AF control using the digital phase difference pixel data **69B1** input from the signal processing portion **50**. Then, the pixel data processing transitions to step **ST156**.

(160) In step **ST156**, the CPU **46A** determines whether or not a condition (hereinafter, referred to as a “pixel data processing finish condition”) under which the pixel data processing is finished is satisfied. For example, a condition that an instruction to finish the pixel data processing is received by the reception device **84** (refer to FIG. **4**) is exemplified as the pixel data processing finish condition. In step **ST156**, in a case where the pixel data processing finish condition is not satisfied, a negative determination is made, and the pixel data processing transitions to step **ST150**. In step

ST156, in a case where the pixel data processing finish condition is satisfied, a positive determination is made, and the pixel data processing is finished.

(161) As described above, in the imaging apparatus **10** according to the first embodiment, the analog pixel data **69A** of each of the plurality of frames is read out in parallel within the output period by the reading circuit **62A**. In addition, reading of the analog non-phase difference pixel data **69A2** and plural reading of the analog phase difference pixel data **69A1** are performed within the output period by the reading circuit **62A**.

(162) In a case where, for example, the pixel data is read out a plurality of number of times from a pixel dedicated to the AF within a reading period in which the analog pixel data **69A** of one frame is read out, mounting of the A/D converter is required for each pixel dedicated to the AF, and a configuration of the imaging element is complicated.

(163) Meanwhile, in a configuration of the imaging element **44** according to the first embodiment, the A/D converter is not mounted for each phase difference pixel. Thus, the configuration of the imaging element **44** is simpler than the configuration of the imaging element in which the A/D converter is mounted for each pixel dedicated to the AF (for example, the phase difference pixel). In addition, within the output period, the analog pixel data **69A** of each of the plurality of frames is read out in parallel, and reading of the analog non-phase difference pixel data **69A2** and plural reading of the analog phase difference pixel data **69A1** are performed.

(164) A plurality of pieces of digital phase difference pixel data **69B1** obtained by digitizing a plurality of pieces of analog phase difference pixel data **69A1** are used for the AF control. Apparently, the plurality of pieces of digital phase difference pixel data **69B1** contribute to achieving high accuracy of the AF more than one piece of digital phase difference pixel data **69B1**. Accordingly, according to the imaging element **44** according to the first embodiment, high accuracy of the AF can be achieved with a simpler configuration than in a case where the pixel data is read out a plurality of number of times from the pixel dedicated to the AF within a reading period in which an image of one frame is read out.

(165) In addition, in the imaging element **44** according to the first embodiment, reading of the analog non-phase difference pixel data **69A2** and reading of the analog phase difference pixel data **69A1** are performed in parallel by the reading circuit **62A**. Accordingly, more pieces of the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** can be read out within a limited time period, compared to a case where reading of one of the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** is started after reading of the other is completed.

(166) In addition, in the imaging element **44** according to the first embodiment, the analog pixel data **69A** is read out in units of horizontal lines by the reading circuit **62A**. Accordingly, thinning in units of horizontal lines can be implemented.

(167) In addition, in the imaging element **44** according to the first embodiment, pixel data of the phase difference pixel is employed as the analog phase difference pixel data **69A1**, and pixel data of the non-phase difference pixel N is employed as the analog non-phase difference pixel data **69A2**. Accordingly, the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** can be more easily obtained than in a case of generating the analog phase difference pixel data **69A1** from pixel data of a pixel other than the phase difference pixel and generating the analog non-phase difference pixel data **69A2** from pixel data of a pixel other than the non-phase difference pixel.

(168) In addition, in the imaging element **44** according to the first embodiment, within the output period, the analog non-phase difference pixel data **69A2** is read out from the non-phase difference pixel N, and the analog phase difference pixel data **69A1** is read out a plurality of number of times from the phase difference pixel. Accordingly, the analog non-phase difference pixel data **69A2** and a plurality of pieces of analog phase difference pixel data **69A1** can be obtained within the output period, compared to a case where reading of the analog non-phase difference pixel data **69A2** from

the non-phase difference pixel N and reading of the analog phase difference pixel data **69A1** from the phase difference pixel are alternately performed once for each output period.

(169) In addition, in the imaging element **44** according to the first embodiment, the analog phase difference pixel data **69A1** is read out from each phase difference pixel included in the plurality of phase difference pixel lines **61A** by the first reading circuit **62A1**. In addition, the analog non-phase difference pixel data **69A2** is read out from each non-phase difference pixel N included in the plurality of non-phase difference pixel lines **61B** by the second reading circuit **62A2**. Accordingly, a load exerted on reading of the analog phase difference pixel data **69A1** and a load exerted on reading of the analog non-phase difference pixel data **69A2** can be distributed.

(170) In addition, in the imaging element **44** according to the first embodiment, reading of the analog phase difference pixel data **69A1** by the first reading circuit **62A1** and reading of the analog non-phase difference pixel data **69A2** by the second reading circuit **62A2** are independently performed. Accordingly, a case where one of reading of the analog phase difference pixel data **69A1** and reading of the analog non-phase difference pixel data **69A2** affects the other can be avoided.

(171) In addition, in the imaging element **44** according to the first embodiment, reading of the analog phase difference pixel data **69A1** from the phase difference pixel by the first reading circuit **62A1** is performed earlier than reading of the analog non-phase difference pixel data **69A2** from the non-phase difference pixel N by the second reading circuit **62A2**. Accordingly, the digital phase difference pixel data **69B1** can be quickly used for the AF control, compared to a case where reading of the analog non-phase difference pixel data **69A2** is performed earlier than reading of the analog phase difference pixel data **69A1**.

(172) In addition, in the imaging element **44** according to the first embodiment, the horizontal line in which the phase difference pixels and the non-phase difference pixels N are periodically arranged is employed as the phase difference pixel line **61A**. Accordingly, accuracy of the AF for a wide area can be increased, compared to a case of using a horizontal line in which the phase difference pixels and the non-phase difference pixels N are arranged in a locally concentrated manner.

(173) In addition, in the imaging element **44** according to the first embodiment, the phase difference pixel lines **61A** and the predetermined number of lines of the non-phase difference pixel lines **61B** are alternately arranged on the imaging surface **44A** in the column direction. Accordingly, the accuracy of the AF for a wide area can be increased, compared to a case where the phase difference pixel lines **61A** and the non-phase difference pixel lines **61B** are arranged in the column direction in a locally concentrated manner.

(174) In addition, in the imaging element **44** according to the first embodiment, in a case where the digital pixel data **69B** of one frame is output by the output circuit **62D**, the digital phase difference pixel data **69B1** and the digital non-phase difference pixel data **69B2** are output at different timings. Accordingly, it is possible to contribute to size reduction of the imaging element **44**, compared to a case of using a dedicated output circuit for each of the digital phase difference pixel data **69B1** and the digital non-phase difference pixel data **69B2**.

(175) In addition, in the imaging element **44** according to the first embodiment, the digital non-phase difference pixel data **69B2** is output after output of the digital phase difference pixel data **69B1** is completed. Accordingly, the digital phase difference pixel data **69B1** can be quickly used for the AF control, compared to a case where the digital phase difference pixel data **69B1** is output after output of the digital non-phase difference pixel data **69B2** is completed.

(176) In addition, in the imaging element **44** according to the first embodiment, the A/D conversion is performed on the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** at different timings. Accordingly, it is possible to contribute to size reduction of the imaging element **44**, compared to a case of using a dedicated A/D converter for each of the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2**.

(177) In addition, the imaging element **44** according to the first embodiment is an imaging element in which the photoelectric conversion element **61**, the processing circuit **62**, and the memory **64** are formed in one chip. Accordingly, portability of the imaging element **44** is increased, compared to an imaging element in which the photoelectric conversion element **61**, the processing circuit **62**, and the memory **64** are not formed in one chip. In addition, a degree of design freedom can be increased, compared to a case of the imaging element in which the photoelectric conversion element **61**, the processing circuit **62**, and the memory **64** are not formed in one chip. Furthermore, it is possible to contribute to size reduction of the imaging apparatus main body **12**, compared to a case of the imaging element in which the photoelectric conversion element **61**, the processing circuit **62**, and the memory **64** are not formed in one chip.

(178) In addition, as illustrated in FIG. 5, the laminated imaging element in which the photoelectric conversion element **61** is laminated with the memory **64** is employed as the imaging element **44**. Accordingly, since a wire that connects the photoelectric conversion element **61** to the memory **64** can be shortened, a wire delay can be reduced. Consequently, a transfer speed of the image data **69** from the photoelectric conversion element **61** to the memory **64** can be increased, compared to a case where the photoelectric conversion element **61** and the memory **64** are not laminated. Improving the transfer speed contributes to high-speed processing in the entire processing circuit **62**. In addition, the degree of design freedom can be increased, compared to a case of not laminating the photoelectric conversion element **61** and the memory **64**. Furthermore, it is possible to contribute to size reduction of the imaging apparatus main body **12**, compared to a case of not laminating the photoelectric conversion element **61** and the memory **64**.

(179) Furthermore, in the imaging apparatus **10**, the live view image or the like based on the digital pixel data **69B** is displayed on the display **32**. In addition, the digital pixel data **69B** is stored in the secondary storage device **80**. Accordingly, general-purpose properties of the digital pixel data **69B** can be increased.

(180) While the imaging element in which the photoelectric conversion element **61**, the processing circuit **62**, and the memory **64** are formed in one chip is illustrated as the imaging element **44** in the first embodiment, the technology of the present disclosure is not limited thereto. For example, at least the photoelectric conversion element **61** and the memory **64** among the photoelectric conversion element **61**, the processing circuit **62**, and the memory **64** may be formed in one chip.

(181) In addition, in the first embodiment, the image processing circuit **62C** performs the image processing on the digital non-phase difference pixel data **69B2** obtained by performing the A/D conversion, and the digital non-phase difference pixel data **69B2** on which the image processing is performed is used as an output target. However, the technology of the present disclosure is not limited thereto. The digital non-phase difference pixel data **69B2** obtained by performing the A/D conversion may be output by the output circuit **62D** without performing the image processing on the digital non-phase difference pixel data **69B2**. In this case, instead of the image processing circuit **62C**, the signal processing portion **50** and/or the controller **46** which is the rear stage circuit of the imaging element **44** may perform the image processing on the digital non-phase difference pixel data **69B2**.

(182) In addition, in the first embodiment, while the image processing is not performed on the digital phase difference pixel data **69B1** by the image processing circuit **62C**, the technology of the present disclosure is not limited thereto. For example, the image processing may be performed on the digital phase difference pixel data **69B1** by the image processing circuit **62C**. In this case, the digital phase difference pixel data **69B1** on which the image processing is performed by the image processing circuit **62C** is output to the signal processing portion **50** by the output circuit **62D**. The digital non-phase difference pixel data **69B2** on which the image processing is performed by the image processing circuit **62C** is an example of the “image data” and “second pixel data based on the phase difference pixel data” according to the embodiments of the technology of the present disclosure.

(183) In addition, in the first embodiment, while an example of a form of performing wired communication between the imaging element **44** and the signal processing portion **50** through the communication line **53** is illustratively described, the technology of the present disclosure is not limited thereto. For example, wireless communication may be performed between the imaging element **44** and the signal processing portion **50**. Similarly, wireless communication may be performed between the imaging element **44** and the controller **46**, and wireless communication may be performed between the signal processing portion **50** and the controller **46**.

(184) In addition, in the first embodiment, while an example of a form of reading out the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** for all frames within the output period is illustratively described, the technology of the present disclosure is not limited thereto. For example, as illustrated in FIG. **16**, the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** may be read out for only one representative frame (in the example illustrated in FIG. **16**, the first frame) of all frames within the output period. In this case, only the analog phase difference pixel data **69A1** may be read out for each of the other frames (in the example illustrated in FIG. **16**, the second frame to the fourth frame). Accordingly, since reading of the analog non-phase difference pixel data **69A2** is not performed for the frames other than the representative frame, power consumption can be reduced, compared to a case where the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** are read out for each of all frames.

(185) In addition, in the first embodiment, while an example of a form in which each time the digital phase difference pixel data **69B1** is stored in the memory **64**, the digital phase difference pixel data **69B1** is output to the signal processing portion **50** without waiting for storage of the digital phase difference pixel data **69B1** of a subsequent frame in the memory **64** is illustratively described, the technology of the present disclosure is not limited thereto. For example, as illustrated in FIG. **17**, the digital phase difference pixel data **69B1** of all frames may be output to the signal processing portion **50** by the output circuit **62D** after waiting for storage of the digital phase difference pixel data **69B1** of all frames in the memory **64** in one output period. In this case, the digital non-phase difference pixel data **69B2** may be output to the signal processing portion **50** by the output circuit **62D** after waiting for completion of output of the digital phase difference pixel data **69B1** of all frames to the signal processing portion **50**. Accordingly, an output timing of the digital phase difference pixel data **69B1** and an output timing of the digital non-phase difference pixel data **69B2** can be differently set.

(186) In addition, in the first embodiment, while an example of a form of outputting the digital phase difference pixel data **69B1** of each frame to the signal processing portion **50** by the output circuit **62D** is illustratively described, the technology of the present disclosure is not limited thereto. For example, pixel data based on a statistical value of a plurality of pieces of digital phase difference pixel data **69B1** obtained for each frame may be output to the signal processing portion **50** by the output circuit **62D**. Accordingly, an output data amount from the imaging element **44** to the signal processing portion **50** can be decreased, compared to a case of outputting the plurality of pieces of digital phase difference pixel data **69B1** obtained for each frame to the signal processing portion **50**.

(187) An arithmetic mean value of a plurality of pieces of digital phase difference pixel data **69B1** obtained for each frame within the output period is exemplified as the statistical value. Here, for example, the digital phase difference pixel data **69B1** of the plurality of frames is combined into the digital phase difference pixel data **69B1** of one frame by calculating the arithmetic mean value between positionally corresponding pixels among the plurality of frames of the digital phase difference pixel data **69B1**. Accordingly, the output data amount from the imaging element **44** to the signal processing portion **50** can be decreased, compared to a case of outputting the plurality of pieces of digital phase difference pixel data **69B1** obtained for each frame to the signal processing portion **50**. Besides the arithmetic mean value, a center value, a mode value, or the like is

exemplified as another example of the statistical value.

Second Embodiment

(188) In the first embodiment, an example of a form of reading out the analog phase difference pixel data **69A1** used for the AF control and the analog non-phase difference pixel data **69A2** used for an application other than the AF control is illustrative described. In a second embodiment, a case where the analog phase difference pixel data **69A1** is also used for the application other than the AF control will be described. In the second embodiment, the same constituents as the first embodiment will be designated by the same reference numerals and will not be described.

Hereinafter, parts different from the first embodiment will be mainly described.

(189) As illustrated in FIG. **4** as an example, the imaging apparatus **10** according to the second embodiment is different from the imaging apparatus **10** according to the first embodiment in that a pixel data processing program **46B3** is stored in the ROM **46B** of the controller **46** instead of the pixel data processing program **46B2**.

(190) As illustrated in FIG. **19** as an example, in the imaging apparatus **10** according to the second embodiment, in a case where an instruction to set the operation mode of the imaging apparatus **10** to a continuous shooting mode is received by the reception device **84** (refer to FIG. **4**), a continuous shooting instruction signal is supplied to the control circuit **62E** from the controller **46** through the communication line **57**. The continuous shooting instruction signal refers to a signal for instructing the imaging element **44** to perform imaging as continuous shooting mode.

(191) In a case where the imaging apparatus **10** is set to the continuous shooting mode, as illustrated in FIG. **20** as an example, all pieces of analog pixel data **69A** are read out by the second reading circuit **62A2** for one representative frame (in the example illustrated in FIG. **20**, the first frame) in each output period as the recording pixel data. In the example illustrated in FIG. **20**, the second reading circuit **62A2** reads out the analog pixel data **69A** for the first frame in order from the first row to the last row of the photoelectric conversion element **61**. That is, reading of the analog pixel data **69A** is performed for all horizontal lines including the phase difference pixel lines **61A** and the non-phase difference pixel lines **61B**.

(192) While an example of a form of performing reading using all horizontal lines as a target is illustratively described here for convenience of description, the analog pixel data **69A** may be read out by performing thinning in units of a few rows and/or units of a few columns using the phase difference pixels and the non-phase difference pixels **N** as a target.

(193) In the example illustrated in FIG. **20**, in one output period, for the second frame or later, the analog phase difference pixel data **69A1** is read out by the first reading circuit **62A1**, and reading of the analog non-phase difference pixel data **69A2** is not performed.

(194) In addition, as illustrated in FIG. **20** as an example, in the imaging element **44**, reading of the analog phase difference pixel data **69A1** for the other frames is performed by the first reading circuit **62A1** in the reading period of the analog pixel data **69A** of one frame. The “analog pixel data **69A** of one frame” here includes the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2**.

(195) In the example illustrated in FIG. **20**, the analog phase difference pixel data **69A1** is read out by the first reading circuit **62A1** for the other plurality of frames during reading of the analog pixel data **69A** as the recording pixel data within a reading period of the first frame. In the example illustrated in FIG. **20**, the other plurality of frames refer to the second frame to the fourth frame.

(196) Here, the analog phase difference pixel data **69A1** is read out by the first reading circuit **62A1** for the other plurality of frames during reading of the analog pixel data **69A** as the recording pixel data within the reading period of one frame. However, the technology of the present disclosure is not limited thereto. For example, the analog phase difference pixel data **69A1** may be read out by the first reading circuit **62A1** for the subsequent one frame during reading of the analog pixel data **69A** as the recording pixel data within the reading period of one frame.

(197) In a case where the analog pixel data **69A** is read out by the second reading circuit **62A2** as

the recording pixel data within the reading period of the first frame, the A/D conversion is performed on the analog pixel data **69A** read out as the recording pixel data as illustrated in FIG. **21** as an example. Accordingly, the analog pixel data **69A** is converted into the digital pixel data **69B** and stored in the memory **64**. The digital pixel data **69B** stored in the memory **64** is output to the signal processing portion **50** by the output circuit **62D**.

(198) Next, an action of the imaging apparatus **10** according to the second embodiment will be described.

(199) First, in-imaging element processing executed by the processing circuit **62** of the imaging element **44** within the output period will be described with reference to FIG. **22** and FIG. **23**.

(200) In the in-imaging element processing illustrated in FIG. **22**, first, in step **ST100**, the control circuit **62E** determines whether or not the imaging vertical synchronization signal output by executing processing of step **ST12** of the timing control processing described in the first embodiment is received. In step **ST100**, in a case where the imaging vertical synchronization signal is not received, a negative determination is made, and the in-imaging element processing transitions to step **ST112**. In step **ST100**, in a case where the imaging vertical synchronization signal is received, a positive determination is made, and the in-imaging element processing transitions to step **ST102**.

(201) In step **ST102**, the control circuit **62E** determines whether or not reading of the analog pixel data **69A** performed by the reading circuit **62A** is reading of the first frame. In step **ST102**, in a case where reading of the analog pixel data **69A** performed by the reading circuit **62A** is reading of the second frame or later, a negative determination is made, and the in-imaging element processing transitions to step **ST114** illustrated in FIG. **23**. In step **ST102**, in a case where reading of the analog pixel data **69A** performed by the reading circuit **62A** is reading of the first frame, a positive determination is made, and the in-imaging element processing transitions to step **ST104**. Here, the read analog pixel data **69A** includes the analog phase difference pixel data **69A1** of one frame and the analog non-phase difference pixel data **69A2** of one frame.

(202) In step **ST104**, the second reading circuit **62A2** reads out the analog pixel data **69A** of one frame from the photoelectric conversion element **61**. Then, the in-imaging element processing transitions to step **ST106**.

(203) In step **ST106**, the digital processing circuit **62B** converts the analog pixel data **69A** into the digital pixel data **69B** by performing the digital signal processing on the analog pixel data **69A** read out by the second reading circuit **62A2**.

(204) In subsequent step **ST107**, the control circuit **62E** acquires the digital pixel data **69B** from the digital processing circuit **62B** and stores the acquired digital pixel data **69B** in the memory **64**. Then, the in-imaging element processing transitions to step **ST110**. The memory **64** stores the digital pixel data **69B** on which the image processing is performed by the image processing circuit **62C**.

(205) In a case where the digital pixel data **69B** is stored in the memory **64**, the digital pixel data **69B** is acquired from the memory **64** by the control circuit **62E**, and the acquired digital pixel data **69B** is transferred to the output circuit **62D**.

(206) In subsequent step **ST110**, the output circuit **62D** outputs the digital pixel data **69B** input from the control circuit **62E** to the signal processing portion **50**. Then, the in-imaging element processing transitions to step **ST112**.

(207) In step **ST114** illustrated in FIG. **23**, the first reading circuit **62A1** reads out the analog phase difference pixel data **69A1** of one frame from the photoelectric conversion element **61**. Then, the in-imaging element processing transitions to step **ST116**.

(208) In step **ST116**, the digital processing circuit **62B** converts the analog phase difference pixel data **69A1** into the digital phase difference pixel data **69B1** by performing the digital signal processing on the analog phase difference pixel data **69A1** read out by the first reading circuit **62A1**.

(209) In subsequent step **ST118**, the control circuit **62E** acquires the digital phase difference pixel data **69B1** from the digital processing circuit **62B** and stores the acquired digital phase difference pixel data **69B1** in the memory **64**. Then, the in-imaging element processing transitions to step **ST120**.

(210) In step **ST120**, the control circuit **62E** determines whether or not a phase difference pixel data output timing is reached. The phase difference pixel data output timing refers to a timing at which the digital phase difference pixel data **69B1** in the memory **64** is output to the signal processing portion **50**. The phase difference pixel data output timing may be a timing that does not overlap with an output timing of the digital pixel data **69B** of the first frame to the signal processing portion **50** within the same output period. For example, a timing at which output of the digital pixel data **69B** of the first frame to the signal processing portion **50** within the same output period is completed is exemplified as the phase difference pixel data output timing.

(211) In step **ST120**, in a case where the phase difference pixel data output timing is not reached, a negative determination is made, and the determination of step **ST120** is performed again. In step **ST120**, in a case where the phase difference pixel data output timing is reached, a positive determination is made, and the in-imaging element processing transitions to step **ST122**.

(212) In step **ST122**, the control circuit **62E** acquires the digital phase difference pixel data **69B1** from the memory **64** and transfers the acquired digital phase difference pixel data **69B1** to the output circuit **62D**. The output circuit **62D** outputs the digital phase difference pixel data **69B1** input from the control circuit **62E** to the signal processing portion **50**. Then, the in-imaging element processing transitions to step **ST112** illustrated in FIG. 22.

(213) In step **ST112**, the control circuit **62E** determines whether or not a condition (hereinafter, referred to as an “in-imaging element processing finish condition”) under which the in-imaging element processing is finished is satisfied. For example, a condition that an instruction to finish the in-imaging element processing is received by the reception device **84** (refer to FIG. 4) is exemplified as the in-imaging element processing finish condition. In step **ST112**, in a case where the in-imaging element processing finish condition is not satisfied, a negative determination is made, and the in-imaging element processing transitions to step **ST100**. In step **ST112**, in a case where the in-imaging element processing finish condition is satisfied, a positive determination is made, and the in-imaging element processing is finished.

(214) In the signal processing portion **50**, various types of signal processing are performed on the digital pixel data **69B** input from the imaging element **44**, and the digital pixel data **69B** on which the various types of signal processing are performed is output to the controller **46**.

(215) Next, pixel data processing executed by the CPU **46A** in accordance with the pixel data processing program **46B3** in a case where the digital pixel data **69B** is input into the controller **46** from the signal processing portion **50** will be described with reference to FIG. 24.

(216) In the pixel data processing illustrated in FIG. 24, first, in step **ST250**, the CPU **46A** determines whether or not the digital pixel data **69B** input from the signal processing portion **50** is the recording pixel data. The “recording pixel data” here refers to pixel data obtained by performing the various types of signal processing on the digital pixel data **69B** (digital pixel data **69B** output in step **ST110**) of the first frame by the signal processing portion **50**. In addition, the “digital pixel data **69B** of the first frame” here refers to the digital pixel data **69B** obtained by digitizing the analog pixel data **69A** (analog pixel data **69A** read out in step **ST104**) of the first frame read out by the second reading circuit **62A2** within the output period.

(217) In step **ST250**, in a case where the digital pixel data **69B** input from the signal processing portion **50** is the digital phase difference pixel data **69B1**, a negative determination is made, and the pixel data processing transitions to step **ST256**. In step **ST250**, in a case where the digital pixel data **69B** input from the signal processing portion **50** is the recording pixel data, a positive determination is made, and the pixel data processing transitions to step **ST252**.

(218) In step **ST252**, the CPU **46A** records the recording pixel data on the predetermined recording

medium. Then, the pixel data processing transitions to step ST254.

(219) In step ST254, the CPU 46A acquires the recording pixel data, which is recorded on the predetermined recording medium in step ST250, from the predetermined recording medium, and thins out and outputs the recording pixel data to the display 32. Then, the pixel data processing transitions to step ST254. For example, a method of thinning out even-numbered lines or odd-numbered lines in the column direction is exemplified as a method of thinning out the recording pixel data. In a case where the recording pixel data is output to the display 32, the display 32 displays an image based on the recording pixel data.

(220) In step ST256, the CPU 46A executes the AF control using the digital phase difference pixel data 69B1 input from the signal processing portion 50. Then, the pixel data processing transitions to step ST260.

(221) In step ST260, the CPU 46A determines whether or not the pixel data processing finish condition described in the first embodiment is satisfied. In step ST260, in a case where the pixel data processing finish condition is not satisfied, a negative determination is made, and the pixel data processing transitions to step ST250. In step ST260, in a case where the pixel data processing finish condition is satisfied, a positive determination is made, and the pixel data processing is finished.

(222) As described above, in the imaging element 44 according to the second embodiment, the analog pixel data 69A including the analog phase difference pixel data 69A1 and the analog non-phase difference pixel data 69A2 of one frame is read out by the second reading circuit 62A2 as the recording pixel data within the reading period of one frame. The analog phase difference pixel data 69A1 of the other frames is read out by the first reading circuit 62A during reading of the analog pixel data 69A as the recording pixel data. Accordingly, more pieces of the analog pixel data 69A as the recording pixel data and the analog phase difference pixel data 69A1 can be read out within a limited time period, compared to a case where the analog phase difference pixel data 69A1 is read out after waiting for reading of the analog pixel data 69A as the recording pixel data.

(223) In addition, in the imaging element 44 according to the second embodiment, the analog non-phase difference pixel data 69A2 is read out as the recording pixel data in a case of the continuous shooting mode. Accordingly, in a case of the continuous shooting mode, the digital non-phase difference pixel data 69B2 obtained by digitizing the analog non-phase difference pixel data 69A2 read out as the recording pixel data can be recorded on the predetermined recording medium.

(224) In the second embodiment, while an example of a form of reading out the analog non-phase difference pixel data 69A2 as the recording pixel data in a case of the continuous shooting mode is illustratively described, the technology of the present disclosure is not limited thereto. For example, the analog non-phase difference pixel data 69A2 may be read out as the recording pixel data in a case where a predetermined condition is satisfied. A condition that the predetermined recording medium is electrically connected to the external FF 82 is exemplified as a first example of the predetermined condition. A condition that the imaging apparatus 10 is set to the motion picture image recording imaging mode is exemplified as a second example of the predetermined condition. A condition that the imaging apparatus 10 is set to the still picture image recording imaging mode is exemplified as a third example of the predetermined condition. A condition that the imaging frame rate is set to a frame rate higher than a first predetermined frame rate (for example, 120 fps) is exemplified as a fourth example of the predetermined condition. A condition that the output frame rate is set to a frame rate higher than a second predetermined frame rate (for example, 30 fps) is exemplified as a fifth example of the predetermined condition. In such a manner, by reading out the analog non-phase difference pixel data 69A2 as the recording pixel data in a case where the predetermined condition is satisfied, general-purpose properties can be increased, compared to a case of reading out the analog non-phase difference pixel data 69A2 at all times as the recording pixel data.

(225) As illustrated in FIG. 7 as an example, the left region passing light 300L that has passed

through the exit pupil of the imaging lens **40** passes through the microlens **19** corresponding to the first phase difference pixel L and is received by the photodiode PD of the first phase difference pixel L. However, in a case where the left region passing light **300L** passes through the microlens **19** corresponding to the second phase difference pixel R, the light shielding member **21B** is shielding against the left region passing light **300L**. Thus, the left region passing light **300L** is not received by the photodiode PD of the second phase difference pixel R.

(226) Meanwhile, the right region passing light **300R** that has passed through the exit pupil of the imaging lens **40** passes through the microlens **19** corresponding to the second phase difference pixel R and is received by the photodiode PD of the second phase difference pixel R. However, in a case where the right region passing light **300R** passes through the microlens **19** corresponding to the first phase difference pixel L, the light shielding member **21A** is shielding against the right region passing light **300R**. Thus, the right region passing light **300R** is not received by the photodiode PD of the first phase difference pixel L.

(227) In such a manner, since the light shielding member is arranged in a half of the pixel, and a center of each of the left region passing light **300L** and the right region passing light **300R** deviates from an optical axis of the imaging lens **40**, light reduction characteristics linearly change in each of the first phase difference pixel L and the second phase difference pixel R in accordance with a pixel position on the horizontal line. For example, in a case where the digital phase difference pixel data **69B1** is employed as the recording pixel data, a change in light reduction characteristics appears as a change in output of the image based on the recording pixel data. For example, as illustrated in FIG. 25, in a first phase difference image based on the digital phase difference pixel data **69B1** obtained from the first phase difference pixel L, brightness is decreased as the pixel position moves in a rightward direction. In addition, in a second phase difference image based on the digital phase difference pixel data **69B1** obtained from the second phase difference pixel R, the brightness is decreased as the pixel position moves in a leftward direction.

(228) Therefore, a correction coefficient for correcting the light reduction characteristics caused by the phase difference pixels may be derived by the control circuit **62E**. In order to derive the correction coefficient, the control circuit **62E** comprises a calculation circuit **62E1** as illustrated in FIG. 26 as an example. The calculation circuit **62E1** is an example of a “derivation portion (derivation circuit)” according to the embodiments of the technology of the present disclosure and calculates the correction coefficient. The correction coefficient is broadly divided into a first phase difference pixel correction coefficient and a second phase difference pixel correction coefficient.

(229) The first phase difference pixel correction coefficient refers to a ratio $A_{\text{sub}.n}$ of the digital phase difference pixel data **69B1** of the first phase difference pixel L to the digital non-phase difference pixel data **69B2** of the non-phase difference pixel N in a case where the non-phase difference pixel N and the first phase difference pixel L adjacent to each other are used as a target. In the example illustrated in FIG. 26, a ratio $A_{\text{sub}.0}$ and a ratio $A_{\text{sub}.1}$ are illustrated as an example of the ratio $A_{\text{sub}.n}$.

(230) The second phase difference pixel correction coefficient refers to a ratio $B_{\text{sub}.n}$ of the digital phase difference pixel data **69B1** of the second phase difference pixel R to the digital non-phase difference pixel data **69B2** of the non-phase difference pixel N in a case where the non-phase difference pixel N and the second phase difference pixel R adjacent to each other are used as a target. In the example illustrated in FIG. 26, a ratio $B_{\text{sub}.0}$ and a ratio $B_{\text{sub}.1}$ are illustrated as an example of the ratio $B_{\text{sub}.n}$.

(231) The correction coefficient calculated by the calculation circuit **62E1** is output to the signal processing portion **50** by the output circuit **62D**. In the signal processing portion **50**, as illustrated in FIG. 27 as an example, the light reduction characteristics are corrected using the correction coefficient. In such a manner, by calculating the correction coefficient for correcting the light reduction characteristics by the calculation circuit **62E1** and outputting the calculated correction coefficient to the signal processing portion **50** by the output circuit **62D**, the light reduction

characteristics appearing in an image based on the digital phase difference pixel data **69B1** can be corrected.

(232) While an example of a form of calculating the correction coefficient is illustratively described here, the technology of the present disclosure is not limited thereto. For example, the control circuit **62E** may derive the correction coefficient using an association table in which the digital non-phase difference pixel data **69B2** of the non-phase difference pixel N and the digital phase difference pixel data **69B1** are associated with the correction coefficient.

(233) In addition, while an example of a form of outputting the correction coefficient to the signal processing portion **50** is illustratively described here, the technology of the present disclosure is not limited thereto. For example, the image processing circuit **62C** and/or the control circuit **62E** may correct the light reduction characteristics appearing in the image based on the digital phase difference pixel data **69B1** using the correction coefficient.

(234) In each of the embodiments, while the A/D converter **62B1** shared for the analog phase difference pixel data **69A1** and the analog non-phase difference pixel data **69A2** is illustrated, the technology of the present disclosure is not limited thereto, and a plurality of A/D converters may be applied. In this case, for example, as illustrated in FIG. **28**, a digital processing circuit **620B** is applied instead of the digital processing circuit **62B** (refer to FIG. **9** and FIG. **19**) described in each of the embodiments. The digital processing circuit **620B** includes a plurality of A/D converters. The “plurality of A/D converters” here include a first A/D converter **620B1** and a second A/D converter **620B2**. The first A/D converter **620B1** is an A/D converter used for only the analog phase difference pixel data **69A1**, and the second A/D converter **620B2** is an A/D converter used for only the analog non-phase difference pixel data **69A2**. The first A/D converter **620B1** and the second A/D converter **620B2** perform the A/D conversion independently of each other. Accordingly, the A/D conversion of the analog phase difference pixel data **69A1** and the A/D conversion of the analog non-phase difference pixel data **69A2** can be performed in parallel in the output period using the first A/D converter **620B1** and the second A/D converter **620B2**.

(235) In each of the embodiments, while an example of a form in which the output circuit **62D** outputs the digital phase difference pixel data **69B1** to the signal processing portion **50** from the imaging element **44** is exemplified, the technology of the present disclosure is not limited thereto. For example, the output circuit **62D** may output correlation data to the signal processing portion **50**. In this case, the control circuit **62E** acquires various types of information such as information indicating characteristics of an incidence angle of the subject light, an F number, and a defocus amount from the controller **46**. The control circuit **62E** corrects brightness of the digital phase difference pixel data **69B1** related to the first phase difference pixel L and brightness of the digital phase difference pixel data **69B1** related to the second phase difference pixel R in accordance with the acquired various types of information. That is, the control circuit **62E** performs sensitivity ratio correction on the digital phase difference pixel data **69B1** related to the first phase difference pixel L and the digital phase difference pixel data **69B1** related to the second phase difference pixel R. The control circuit **62E** performs a correlation operation using the digital phase difference pixel data **69B1** subjected to the sensitivity ratio correction, and the output circuit **62D** outputs the correlation data that is a result of the correlation operation, to the signal processing portion **50**.

(236) In such a manner, by outputting the correlation data to the signal processing portion **50** from the imaging element **44**, an output data amount from the output circuit **62D** to the signal processing portion **50** can be decreased, compared to a case of outputting the digital phase difference pixel data **69B1** from the output circuit **62D**. Consequently, high-speed AF can be achieved.

(237) In the correlation operation, pattern matching is performed. Thus, it is preferable that the brightness of the digital phase difference pixel data **69B1** related to the first phase difference pixel L is the same as or similar to the brightness of the digital phase difference pixel data **69B1** related to the second phase difference pixel R. Thus, the correlation operation performed by the control circuit **62E** may be a normalized cross-correlation operation. In this case, similarity between the

digital phase difference pixel data **69B1** related to the first phase difference pixel L and the digital phase difference pixel data **69B1** related to the second phase difference pixel R can be stably calculated even in a case where brightness of the subject changes.

(238) In each of the embodiments, while a case where the imaging frame rate is fixed is described, the technology of the present disclosure is not limited thereto. For example, the imaging frame rate may be changed in connection with an exposure time period. In addition, the imaging frame rate may be increased as the exposure time period is shortened. In addition, exposure of the photoelectric conversion element **61** may be resumed after reading of the analog pixel data **69A** of at least one pixel by the reading circuit **62A** is completed after exposure is started. In addition, a reading speed of the analog pixel data **69A** by the reading circuit **62A** may be changed in accordance with the number of frames from which the analog pixel data **69A** is read out in parallel. In addition, the reading circuit **62A** may change a data amount of the analog pixel data **69A** in a case of performing the A/D conversion on the analog pixel data **69A**, in accordance with the number of frames from which the analog pixel data **69A** is read out in parallel, and the number of A/D converters performing the A/D conversion on the read analog pixel data **69A**.

(239) In addition, while an example of a form of implementing the processing circuit **62** by the device including the ASIC and the FPGA is illustratively described in each of the embodiments, the technology of the present disclosure is not limited thereto. For example, imaging processing described above may be implemented by a software configuration using a computer.

(240) In this case, for example, as illustrated in FIG. **29**, various programs causing a computer **852** incorporated in the imaging element **44** to execute the phase difference pixel processing, the non-phase difference pixel processing, and the in-imaging element processing are stored in a storage medium **900**.

(241) The various programs refer to a phase difference pixel processing program **902**, a non-phase difference pixel processing program **904**, and an in-imaging element processing program **906**. The phase difference pixel processing program **902** is a program causing the computer **852** to execute the phase difference pixel processing. The non-phase difference pixel processing program **904** is a program causing the computer **852** to execute the non-phase difference pixel processing. The in-imaging element processing program **906** is a program causing the computer **852** to execute the in-imaging element processing.

(242) As illustrated in FIG. **29** as an example, the computer **852** comprises a CPU **852A**, a ROM **852B**, and a RAM **852C**. The various programs stored in the storage medium **900** are installed on the computer **852**. The CPU **852A** executes the phase difference pixel processing in accordance with the phase difference pixel processing program **902**. In addition, the CPU **852A** executes the non-phase difference pixel processing in accordance with the non-phase difference pixel processing program **904**. Furthermore, the CPU **852A** executes the in-imaging element processing in accordance with the in-imaging element processing program **906**.

(243) While a single CPU is illustrated as the CPU **852A** here, the technology of the present disclosure is not limited thereto. A plurality of CPUs may be employed instead of the CPU **852A**. The storage medium is a non-temporary storage medium. Any portable storage medium such as an SSD or a USB memory is exemplified as an example of the storage medium **900**.

(244) While the various programs are stored in the storage medium **900** in the example illustrated in FIG. **29**, the technology of the present disclosure is not limited thereto. For example, the various programs may be stored in advance in the ROM **852B**, and the CPU **852A** may read out the various programs from the ROM **852B**, load the various programs into the RAM **852C**, and execute the loaded various programs.

(245) In addition, the various programs may be stored in a storage portion of another computer, a server apparatus, or the like connected to the computer **852** through a communication network (not illustrated), and the various programs may be downloaded to the computer **852** in response to a request from the imaging apparatus **10**. In this case, the downloaded various programs are executed

by the CPU **852A** of the computer **852**.

(246) In addition, the computer **852** may be disposed on an outside of the imaging element **44**. In this case, the computer **852** may control the processing circuit **62** in accordance with the various programs.

(247) The following various processors can be used as a hardware resource for executing the phase difference pixel processing, the non-phase difference pixel processing, the in-imaging element processing, the timing control processing, and the pixel data processing (hereinafter, referred to as “various types of processing”) described in each of the embodiments. For example, as described above, a CPU that is a general-purpose processor functioning as the hardware resource for executing the various types of processing by executing software, that is, the programs, is exemplified as a processor. In addition, a dedicated electric circuit such as an FPGA, a PLD, or an ASIC that is a processor having a circuit configuration dedicatedly designed to execute a specific type of processing is exemplified as a processor.

(248) The hardware resource for executing the various types of processing may be configured with one of those various processors or may be configured with a combination of two or more processors of the same type or different types (for example, a combination of a plurality of FPGAs or a combination of a CPU and an FPGA). In addition, the hardware resource for executing the various types of processing may be one processor.

(249) As an example of a configuration with one processor, first, as represented by a computer such as a client and a server, a form in which one processor is configured with a combination of one or more CPUs and software, and in which this processor functions as a hardware resource for executing in-imaging apparatus processing is available. Second, as represented by an SoC or the like, a form of using a processor that implements, by one IC chip, a function of the entire system including a plurality of hardware resources for executing the various types of processing is available. In such a manner, the in-imaging apparatus processing is implemented using one or more of the various processors as the hardware resource.

(250) Furthermore, as a hardware structure of those various processors, more specifically, an electric circuit in which circuit elements such as semiconductor elements are combined can be used.

(251) While an interchangeable lens camera is illustrated as the imaging apparatus **10** in each of the embodiments, the technology of the present disclosure is not limited thereto. For example, the technology of the present disclosure may be applied to a smart device **950** illustrated in FIG. **30**.

The smart device **950** illustrated in FIG. **30** as an example is an example of the imaging apparatus according to the embodiments of the technology of the present disclosure. The imaging element **44** described in the embodiments is mounted in the smart device **950**. Even with the smart device **950** configured in such a manner, the same actions and effects as the imaging apparatus **10** described in each of the embodiments are obtained. The technology of the present disclosure can be applied to not only the smart device **950** but also a personal computer or a wearable terminal apparatus.

(252) In addition, while the display **32** is illustrated in each of the embodiments, the technology of the present disclosure is not limited thereto. For example, a separate display that is retrofit into the imaging apparatus main body **12** may be used as the “display portion (display)” according to the embodiments of the technology of the present disclosure.

(253) In addition, the various types of processing are merely an example. Accordingly, unnecessary steps may be deleted, new steps may be added, or a processing order may be rearranged without departing from a gist of the technology of the present disclosure.

(254) Above described contents and illustrated contents are detailed description for parts according to the embodiments of the technology of the present disclosure and are merely an example of the technology of the present disclosure. For example, description related to the above configurations, functions, actions, and effects is description related to an example of configurations, functions, actions, and effects of the parts according to the embodiments of the technology of the present

disclosure. Thus, unnecessary parts may be removed, new elements may be added, or parts may be replaced in the above described contents and the illustrated contents without departing from the gist of the technology of the present disclosure. In addition, particularly, description related to common technical knowledge or the like that does not need to be described in terms of embodying the technology of the present disclosure is omitted in the above described contents and the illustrated contents in order to avoid complication and facilitate understanding of the parts according to the embodiments of the technology of the present disclosure.

(255) In the present specification, “A and/or B” has the same meaning as “at least one of A or B”. This means that “A and/or B” may be only A, only B, or a combination of A and B. In addition, in the present specification, the same approach as “A and/or B” is applied to a case where three or more matters are represented by connecting the matters with “and/or”.

(256) All documents, patent applications, and technical standards disclosed in the present specification are incorporated in the present specification by reference to the same extent as in a case where each of the documents, patent applications, technical standards are specifically and individually indicated to be incorporated by reference.

Claims

1. An imaging element including a focus related pixel, which is a pixel that can acquire data related to a focus state of a subject, the imaging element comprising: a reading circuit that reads out pixel data obtained by imaging the subject at a first frame rate; a memory that stores the pixel data read out by the reading circuit; and an output circuit that outputs image data based on the pixel data stored in the memory at a second frame rate, wherein the first frame rate is a higher frame rate than the second frame rate, wherein the pixel data includes focus related pixel data, which is data related to the focus state, and non-focus related pixel data different from the focus related pixel data, and wherein the reading circuit reads out the pixel data of each of a plurality of frames in parallel within an output period defined by the second frame rate as a period in which the image data of one frame is output, and performs reading of the non-focus related pixel data and a plurality of readings of the focus related pixel data within the output period.
2. The imaging element according to claim 1, wherein the reading circuit performs reading of the non-focus related pixel data and reading of the focus related pixel data in parallel.
3. The imaging element according to claim 1, wherein the reading circuit reads out the pixel data in units of lines.
4. The imaging element according to claim 1, wherein: the focus related pixel data is pixel data of the focus related pixel, and the non-focus related pixel data is pixel data of a non-focus related pixel that is a pixel different from the focus related pixel.
5. The imaging element according to claim 4, wherein: reading of the non-focus related pixel data is reading of the non-focus related pixel data from the non-focus related pixel, and the plurality of readings of the focus related pixel data is a plurality of readings of the focus related pixel data from the focus related pixel.
6. The imaging element according to claim 4, further comprising: an imaging surface on which a plurality of first lines including the focus related pixel and a plurality of second lines consisting of only the non-focus related pixel are arranged, wherein the reading circuit includes a first reading circuit that reads out the focus related pixel data from each focus related pixel included in the plurality of first lines, and a second reading circuit that reads out the non-focus related pixel data from each non-focus related pixel included in the plurality of second lines.
7. The imaging element according to claim 6, wherein reading of the focus related pixel data from the focus related pixel by the first reading circuit and reading of the non-focus related pixel data from the non-focus related pixel by the second reading circuit are independently performed.
8. The imaging element according to claim 7, wherein in a reading period of one frame, reading of

the focus related pixel data from the focus related pixel by the first reading circuit is performed earlier than reading of the non-focus related pixel data from the non-focus related pixel by the second reading circuit.

9. The imaging element according to claim 6, wherein the first lines are lines in which the focus related pixel and the non-focus related pixel are periodically arranged.

10. The imaging element according to claim 6, wherein, on the imaging surface, the first lines and a predetermined number of lines of the second lines are alternately arranged in a direction intersecting with a line direction of the first lines.

11. The imaging element according to claim 1, wherein the reading circuit reads out the non-focus related pixel data of one frame as recording pixel data within a reading period of one frame, and reads out the focus related pixel data during reading of the non-focus related pixel data as the recording pixel data.

12. The imaging element according to claim 11, wherein the reading circuit reads out the non-focus related pixel data and the focus related pixel data as display pixel data within the reading period of one frame, and reads out the non-focus related pixel data as the recording pixel data in a case in which a predetermined condition is satisfied.

13. The imaging element according to claim 11, wherein the reading circuit reads out the non-focus related pixel data as the recording pixel data in a case of a continuous shooting mode.

14. The imaging element according to claim 1, further comprising: a derivation circuit that derives a correction coefficient for correcting light reduction characteristics caused by the focus related pixel based on the focus related pixel data, wherein the output circuit outputs the correction coefficient derived by the derivation circuit.

15. The imaging element according to claim 1, wherein the image data includes first pixel data based on the non-focus related pixel data and second pixel data based on the focus related pixel data obtained by the plurality of reading of the focus related pixel data, and in a case of outputting the image data of one frame, the output circuit outputs the first pixel data and the second pixel data at different timings.

16. The imaging element according to claim 15, wherein the output circuit outputs the first pixel data after output of the second pixel data is completed.

17. The imaging element according to claim 1, wherein the image data includes pixel data based on the non-focus related pixel data and pixel data based on a statistical value of the focus related pixel data obtained by the plurality of reading of the focus related pixel data.

18. The imaging element according to claim 17, wherein the statistical value is an arithmetic mean value of the focus related pixel data.

19. The imaging element according to claim 1, further comprising: an A/D converter that is shared for the focus related pixel data and the non-focus related pixel data, wherein the A/D converter performs A/D conversion on the focus related pixel data and the non-focus related pixel data at different timings.

20. The imaging element according to claim 1, further comprising: a plurality of A/D converters, wherein the plurality of A/D converters include a first A/D converter used for only the focus related pixel data and a second A/D converter used for only the non-focus related pixel data.

21. The imaging element according to claim 1, wherein at least a photoelectric conversion element and the memory are formed in one chip.

22. The imaging element according to claim 21, wherein the imaging element is a laminated imaging element in which the photoelectric conversion element is laminated with the memory.

23. An imaging apparatus comprising: the imaging element according to claim 1; and a processor configured to perform at least one of a control for displaying the image based on the image data output by the output circuit on a display or a control for storing the image data output by the output circuit in a storage device.

24. An operation method of an imaging element that includes a focus related pixel, which is a pixel

that can acquire data related to a focus state of a subject, a reading circuit that reads out pixel data obtained by imaging the subject at a first frame rate, a memory that stores the pixel data read out by the reading circuit, and an output circuit that outputs image data based on the pixel data stored in the memory at a second frame rate, wherein the first frame rate is a higher frame rate than the second frame rate, and wherein the pixel data includes focus related pixel data and non-focus related pixel data different from the focus related pixel data, the operation method comprising, by the reading circuit, reading out the pixel data of each of a plurality of frames in parallel within an output period defined by the second frame rate as a period in which the image data of one frame is output, and performing reading of the non-focus related pixel data and a plurality of readings of the focus related pixel data within the output period.

25. A non-transitory computer-readable storage medium storing a program executable by a computer to function, in an imaging element including a focus related pixel, which is a pixel that can acquire data related to a focus state of a subject, as a reading circuit that reads out pixel data obtained by imaging the subject at a first frame rate, as a memory that stores the pixel data read out by the reading circuit, and as an output circuit that outputs image data based on the pixel data stored in the memory at a second frame rate, wherein the first frame rate is a higher frame rate than the second frame rate, wherein the pixel data includes focus state pixel data that is data related to the focus state and non-focus related pixel data different from the focus state pixel data, and wherein the reading circuit reads out the pixel data of each of a plurality of frames in parallel within an output period defined by the second frame rate as a period in which the image data of one frame is output, and performs reading of the non-focus related pixel data and a plurality of readings of the focus related pixel data within the output period.
