

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12387771
Kind Code	B2
Date of Patent	August 12, 2025
Inventor(s)	Kwon; Youngcheon et al.

Memory device for supporting new command input scheme and method of operating the same

Abstract

A method of operating a memory device including row pins and column pins includes receiving a first active command through the row pins during 1.5 cycles of a clock signal, receiving a first read command or a first write command through the column pins during 1 cycle of the clock signal, receiving a first precharge command through the row pins during a 0.5 cycle of the clock signal corresponding to a rising edge of the clock signal, receiving a second active command through the row pins during the 1.5 cycles of the clock signal, receiving a second read command or a second write command through the column pins during the 1 cycle of the clock signal, and receiving a second precharge command through the row pins during the 0.5 cycle of the clock signal corresponding to a falling edge of the clock signal.

Inventors: Kwon; Youngcheon (Hwaseong-si, KR), Ryu; Jemin (Seoul, KR), Youn; Jaeyoun (Suwon-si, KR), Lee; Haesuk (Seongnam-si, KR), Choi; Jihyun (Daegu, KR)

Applicant: SAMSUNG ELECTRONICS CO., LTD. (Suwon-si, KR)

Family ID: 74187221

Assignee: SAMSUNG ELECTRONICS CO., LTD. (Suwon-si, KR)

Appl. No.: 18/654443

Filed: May 03, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240282353 A1	Aug. 22, 2024

Foreign Application Priority Data

KR	10-2020-0008110	Jan. 21, 2020
KR	10-2020-0103438	Aug. 18, 2020

Related U.S. Application Data

continuation parent-doc US 18299440 20230412 US 12002543 child-doc US 18654443
continuation parent-doc US 17574174 20220112 US 11636885 20230425 child-doc US 18299440
continuation parent-doc US 17145941 20210111 US 11250894 20220215 child-doc US 17574174

Publication Classification

Int. Cl.: G11C7/22 (20060101); G11C7/10 (20060101)

U.S. Cl.:

CPC G11C7/222 (20130101); G11C7/1048 (20130101); G11C7/1057 (20130101);
G11C7/1084 (20130101);

Field of Classification Search

CPC: G11C (7/222); G11C (7/1048); G11C (7/1057); G11C (7/1084); G11C (8/08); G11C (11/4076); G06F (13/382); G06F (13/4291)

USPC: 365/233.1

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6279116	12/2000	Lee	N/A	N/A
6510095	12/2002	Matsuzaki et al.	N/A	N/A
6717884	12/2003	Kim	N/A	N/A
7299329	12/2006	Choi et al.	N/A	N/A
7433258	12/2007	Rao et al.	N/A	N/A
8059484	12/2010	Yoko	N/A	N/A
8497666	12/2012	Nagasawa	N/A	N/A
9064560	12/2014	Qawami et al.	N/A	N/A
10579263	12/2019	Shin et al.	N/A	N/A
11025232	12/2020	Scolari et al.	N/A	N/A
11250894	12/2021	Kwon et al.	N/A	N/A
11386885	12/2021	Chatterjee et al.	N/A	N/A
11636885	12/2022	Kwon	365/233.1	G11C 7/1057
12002543	12/2023	Kwon	N/A	G11C 11/4076
2002/0041536	12/2001	Tomita	N/A	N/A
2002/0064083	12/2001	Ryu et al.	N/A	N/A
2002/0116657	12/2001	Uchida	N/A	N/A
2009/0296514	12/2008	Yeh	N/A	N/A
2013/0238841	12/2012	Kim	N/A	N/A
2013/0254475	12/2012	Perego et al.	N/A	N/A
2015/0187403	12/2014	Kim et al.	N/A	N/A
2016/0086644	12/2015	Hong	365/230.03	G11C 7/1087

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
201145786	12/2010	TW	N/A
201941013	12/2018	TW	N/A

OTHER PUBLICATIONS

Communication dated May 31, 2021, from the European Patent Office in European Application No. 21152630.6. cited by applicant

Communication issued Dec. 27, 2021 by the Taiwanese Patent Office in Taiwanese Patent Application No. 110102104. cited by applicant

Office Action issued on Jun. 11, 2025 by the Chinese Patent Office in corresponding CN Patent Application No. 202110072030.3. cited by applicant

Primary Examiner: Hoang; Huan

Attorney, Agent or Firm: Sughrue Mion, PLLC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This is a Continuation of U.S. application Ser. No. 18/299,440 filed Apr. 12, 2023, which is a Continuation of U.S. application Ser. No. 17/574,174 filed Jan. 12, 2022, which is a Continuation Application of U.S. patent application Ser. No. 17/145,941 filed Jan. 11, 2021, which claims priority under 35 U. S. C. § 119 to Korean Patent Application No. 10-2020-0008110 and Korean Patent Application No. 10-2020-0103438 filed on Jan. 21, 2020, and Aug. 18, 2020, respectively, in the Korean Intellectual Property Office, the disclosures of which are incorporated by reference herein in their entirety.

BACKGROUND

(1) The inventive concept relates to a semiconductor device, and more particularly, to a memory device for supporting a new command input scheme and a method of operating the same.

(2) Electronic devices such as a smart phone, a graphic accelerator, and an artificial intelligence (AI) accelerator process data by using a memory device such as dynamic random access memory (DRAM). As an amount of data to be processed by an electronic device increases, a memory device having high capacity and bandwidth is required. In particular, in order to process data at a high speed, use of a memory device providing high throughput input and output of a multichannel interface method such as a high bandwidth memory (HBM) standard is increasing. As the use of such memory device increases, an efficient input and output interface method is required between a host device (e.g., a memory controller) and the memory device.

SUMMARY

(3) According to an aspect of the inventive concept, there is provided a method of operating a memory device including row pins for receiving row commands and column pins for receiving column commands different from the row commands. The method includes receiving a first active command for one memory bank through the row pins during one and half (1.5) cycles of a clock signal, receiving a first read command or a first write command for the one memory bank through the column pins during one (1) cycle of the clock signal after receiving the first active command, receiving a first precharge command for the one memory bank through the row pins during a half (0.5) cycle of the clock signal corresponding to a rising edge of the clock signal after receiving the first read command or the first write command, receiving a second active command for the one memory bank through the row pins during the 1.5 cycles of the clock signal, receiving a second

read command or a second write command for the one memory bank through the column pins during the 1 cycle of the clock signal after receiving the second active command, and receiving a second precharge command for the one memory bank through the row pins during the 0.5 cycle of the clock signal corresponding to a falling edge of the clock signal after receiving the second read command or the second write command.

(4) According to an aspect of the inventive concept, there is provided a memory device including a clock pin receiving a clock signal, row pins receiving row commands, column pins receiving column commands different from the row commands, and an interface circuit receiving a first active command through the row pins during 1.5 cycles among 2 cycles of the clock signal, receiving a first precharge command during a remaining 0.5 cycle corresponding to a falling edge of the clock signal, receiving a first write command or a first read command through the column pins during 1 cycle among the 2 cycles, and receiving a second write command or a second read command during the remaining 1 cycle.

(5) According to an aspect of the inventive concept, there is provided a memory device including a clock pin receiving a clock signal, row pins receiving row commands, column pins receiving column commands different from the row commands, and an interface circuit receiving a first row command at a first rising edge of the clock signal and a second row command at a first falling edge of the clock signal through the row pins in a first period including the first rising edge and the first falling edge of the clock signal, receiving a first column command through the column pins in the first period, receiving a third row command at a second rising edge of the clock signal and a fourth row command at a second falling edge of the clock signal through the row pins in a second period including the second rising edge and the second falling edge of the clock signal, and receiving a second column command through the column pins in the second period. The second row command and the third row command are specific commands representing the same operation.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) Example embodiments of inventive concepts will be more clearly understood from the following detailed description taken in conjunction with the accompanying drawings in which:
- (2) FIG. 1 is a block diagram illustrating a memory system according to an example embodiment;
- (3) FIG. 2 is a block diagram of the memory device of FIG. 1 according to an example embodiment;
- (4) FIGS. 3A to 3C illustrate examples of a timing diagram in which the memory device of FIG. 1 receives commands according to example embodiment;
- (5) FIGS. 4A and 4B illustrate examples of a timing diagram in which the memory device of FIG. 1 receives commands for one memory bank according to example embodiments;
- (6) FIG. 5 is a flowchart illustrating an operation of the memory device of FIG. 1 according to an example embodiment;
- (7) FIG. 6 is a block diagram of the control logic circuit of FIG. 2 according to an example embodiment;
- (8) FIG. 7 is a block diagram illustrating a stacked memory device according to an example embodiment;
- (9) FIG. 8 is a block diagram of the stacked memory device of FIG. 7 according to an example embodiment;
- (10) FIG. 9 is a block diagram illustrating an example of enlargement of the stacked memory device of FIG. 8 according to an example embodiment;
- (11) FIG. 10 is a block diagram illustrating an example of enlargement of the stacked memory device of FIG. 8 according to an example embodiment;

- (12) FIGS. **11A** and **11B** illustrate examples of a timing diagram in which the stacked memory device of FIG. **7** receives commands according to example embodiments;
- (13) FIG. **12A** is a table illustrating a row command according to an example embodiment;
- (14) FIG. **12B** is a table illustrating an example of a column command according to an example embodiment;
- (15) FIG. **13** is a circuit diagram of a control logic circuit for sensing a precharge command based on the row command of FIG. **12A** according to an example embodiment;
- (16) FIG. **14** is a view illustrating a semiconductor package according to an example embodiment;
- (17) FIG. **15** is a view illustrating an implementation example of a semiconductor package according to an example embodiment;
- (18) FIG. **16** is a view illustrating a semiconductor package according to another example embodiment; and
- (19) FIG. **17** is a block diagram illustrating a computing system according to an example embodiment.

DETAILED DESCRIPTION OF THE EMBODIMENTS

(20) Hereinafter, example embodiments of the inventive concepts will be described so that those skilled in the art may easily perform the inventive concepts.

(21) FIG. **1** is a block diagram illustrating a memory system **10** according to an example embodiment. Referring to FIG. **1**, the memory system **10** may include a memory controller **100** and a memory device **200**. The memory controller **100** may control an overall operation of the memory device **200**. The memory controller **100** may control the memory device **200** so that data is output from or stored in the memory device **200** and may be implemented as a part of a system-on-chip (SoC). However, the example embodiment is not limited thereto.

(22) The memory controller **100** may include a host interface circuit **110** and a clock pin CK_P', a row pin R_P', a column pin C_P', and a data pin D_P'. The host interface circuit **110** may transmit a clock signal CK to the memory device **200** through the clock pin CK_P'. The clock signal CK may periodically toggle between a high level and a low level. For example, the clock signal CK may be a differential signal that is one of a differential pair.

(23) The host interface circuit **110** may transmit a row command CMD_r and/or a row address ADD_r (hereinafter, referred to as a row command/row address CMD_r/ADD_r) to the memory device **200** through the row pin R_P'. For example, the row command CMD_r may include an active command ACT and a precharge command PRE. For example, the row address ADD_r may include a bank address corresponding to the row command CMD_r. The host interface circuit **110** may transmit the row command/row address CMD_r/ADD_r to the memory device **200** based on toggle timings of the clock signal CK.

(24) The host interface circuit **110** may transmit a column command CMD_c and/or a column address ADD_c (hereinafter, referred to as a column command/column address CMD_c/ADD_c) to the memory device **200** through the column pin C_P'. For example, the column command CMD_c may include a read command RD and a write command WR. The row command CMD_r and the column command CMD_c may include different commands. For example, the column address ADD_c may include a bank address corresponding to the column command CMD_c. The host interface circuit **110** may transmit the column command/column address CMD_c/ADD_c to the memory device **200** based on the toggle timings of the clock signal CK.

(25) The host interface circuit **110** may transmit data DATA to the memory device **200** through the data pin D_P'. The host interface circuit **110** may transmit the data DATA to the memory device **200** based on toggle timings of an additional data clock signal (e.g., a write data strobe signal WDQS). The host interface circuit **110** may receive the data DATA from the memory device **200** through the data pin D_P'.

(26) The memory device **200** may operate in accordance with control of the memory controller **100**. For example, the memory device **200** may output the stored data in accordance with the

control of the memory controller **100** or may store the data received from the memory controller **100**.

(27) The memory device **200** may include a memory interface circuit **210** and a memory bank array **220**. The memory device **200** may further include a clock pin CK_P, a row pin R_P, a column pin C_P, and a data pin D_P corresponding to the clock pin CK_P', the row pin R_P', the column pin C_P', and the data pin D_P' of the memory controller **100**. The memory interface circuit **210** may receive the clock signal CK from the memory controller **100** through the clock pin CK_P.

(28) The memory interface circuit **210** may receive the row command/row address CMD_r/ADD_r from the memory controller **100** through the row pin R_P. For example, the memory interface circuit **210** may sample the row command/row address CMD_r/ADD_r based on the toggle timings of the clock signal CK. According to an example embodiment, the row command/row address CMD_r/ADD_r may be transmitted to the memory device **200** through a plurality of signal lines. In this case, the row pin R_P may include a plurality of pins corresponding to the plurality of signal lines. For example, the row pin R_P may include 10 pins. However, the inventive concept is not limited thereto.

(29) The memory interface circuit **210** may receive the column command/column address CMD_c/ADD_c from the memory controller **100** through the column pin C_P. For example, the memory interface circuit **210** may sample the column command/column address CMD_c/ADD_c based on the toggle timings of the clock signal CK. According to an example embodiment, the column command/column address CMD_c/ADD_c may be transmitted to the memory device **200** through the plurality of signal lines. In this case, the column pin C_P may include a plurality of pins corresponding to the plurality of signal lines. For example, the column pin C_P may include 8 pins. However, the inventive concept is not limited thereto.

(30) The memory interface circuit **210** may receive the data DATA from the memory controller **100** through the data pin D_P. The memory interface circuit **210** may sample the data DATA based on the toggle timings of the additional data clock signal (e.g., the write data strobe signal WDQS). The memory interface circuit **210** may transmit the data DATA to the memory controller **100** through the data pin D_P. For example, the memory interface circuit **210** may transmit the data DATA to the memory controller **100** based on the toggle timings of the additional data clock signal (e.g., the write data strobe signal WDQS). According to an example embodiment, the data DATA may be received by or transmitted from the memory device **200** through the plurality of signal lines. In this case, the data pin D_P may include a plurality of pins corresponding to the plurality of signal lines. For example, the data pin D_P may include 64 or 128 pins. However, the inventive concept is not limited thereto.

(31) The memory interface circuit **210** may generate a control signal iCTRL based on the row command CMD_r and the column command CMD_c that are received from the memory controller **100** and may control operations of memory banks of a memory bank array **220** based on the control signal iCTRL.

(32) The memory bank array **220** may include one or more memory banks. The memory bank may include a plurality of memory cells connected to word lines and bit lines. For example, the plurality of memory cells may be dynamic random access memory (DRAM) cells. In this case, the host interface circuit **110** and the memory interface circuit **210** may communicate with input and output signals based on one of the standards such as a double data rate (DDR) standard, a low power double data rate (LPDDR) standard, a graphics double data rate (GDDR) standard, a wide I/O standard, a high bandwidth memory (HBM) standard, and a hybrid memory cube (HMC) standard. However, the inventive concept is not limited thereto. Memory cells may be at least one of various memory cells such as static RAM (SRAM), phase-change RAM (PRAM), magnetic RAM (MRAM), resistive RAM (RRAM), and ferroelectric RAM (FRAM).

(33) The memory banks of the memory bank array **220** may write or read the data DATA in or from the memory cells in response to the control signal iCTRL.

(34) According to an example embodiment, the host interface circuit **110** may transmit a specific command (e.g., a precharge command PRE) of the row command CMD_r at a rising and/or falling edge of the clock signal CK. The host interface circuit **110** may start to transmit the specific command at the timing corresponding to the rising and/or falling edge of the clock signal CK. For example, the host interface circuit **110** may transmit the specific command at a timing corresponding to the rising edge of the clock signal CK in a first time period and may transmit the specific command at a timing corresponding to the falling edge of the clock signal CK in a second time period. The host interface circuit **110** may transmit a remaining command excluding the specific command of the row command CMD_r and the column command CMD_c at the rising edge of the clock signal CK. The host interface circuit **110** may start to transmit the remaining command of the row command CMD_r and the column command CMD_c at a timing corresponding to the rising edge of the clock signal CK.

(35) According to an example embodiment, the memory interface circuit **210** may sense the specific command although the specific command is transmitted from the memory controller **100** at any timing. Although the specific command is received at the timing corresponding to the rising and/or falling edge of the clock signal CK, the memory interface circuit **210** may sense the specific command. For example, the memory interface circuit **210** may sense the specific command transmitted at each of two timings by decoding the row command CMD_r.

(36) Hereinafter, for convenience sake, that the specific command is transmitted or received at the rising and/or falling edge of the clock signal CK may mean that the specific command starts to be transmitted or received at the timing corresponding to the rising and/or falling edge of the clock signal CK.

(37) FIG. 2 is an example block diagram of the memory device **200** of FIG. 1. Referring to FIG. 2, the memory device **200** may include a memory bank array **220**, a control logic circuit **230**, and an input and output circuit **240**. The memory bank array **220** may include a plurality of memory banks **220a** to **220n**. Each of the plurality of memory banks **220a** to **220n** may include a memory cell array **221**, a row decoder **222**, a column decoder **223**, and a sense amplifier/write driver **224**. The control logic circuit **230** and the input and output circuit **240** may be included in the memory interface circuit **210** of FIG. 1. However, the inventive concept is not limited thereto. The control logic circuit **230** and the input and output circuit **240** may be provided as separate circuits.

(38) According to an example embodiment, the plurality of memory banks **220a** to **220n** may be divided into a plurality of bank groups. For example, each bank group may include 4 memory banks. However, the inventive concept is not limited thereto. When the plurality of memory banks **220a** to **220n** are divided into the plurality of bank groups, timing parameters for accessing within the same bank group may be set to be different from timing parameters for accessing to different bank groups.

(39) The memory cell array **221** may include a plurality of memory cells. The plurality of memory cells may be formed at points at which the word lines WL intersect with the bit lines BL.

(40) The row decoder **222** may be connected to the memory cell array **221** through the word lines WL. The row decoder **222** may control voltages of the word lines WL in response to control of the control logic circuit **230**.

(41) The column decoder **223** may be connected to the cell array **221** through the bit lines BL. The column decoder **223** may select at least one of the bit lines BL in response to the control of the control logic circuit **230**. The sense amplifier/write driver **224** may sense or control a voltage or current of the bit line selected by the column decoder **223**.

(42) The control logic circuit **230** may receive the row command/row address CMD_r/ADD_r and the column command/column address CMD_c/ADD_c from the memory controller **100** of FIG. 1. The control logic circuit **230** may decode the row command/row address CMD_r/ADD_r and the column command/column address CMD_c/ADD_c. According to an example embodiment, the control logic circuit **230** may decode the row command CMD_r through a row command decoder

and may decode the column command CMD_c through a column command decoder. For example, the control logic circuit **230** may sense the active command ACT or the precharge command PRE by decoding the row command CMD_r. The control logic circuit **230** may sense the write command WR or the read command RD by decoding the column command CMD_c.

(43) The control logic circuit **230** may generate control signals for controlling the plurality of memory banks **220a** to **220n** based on the decoding result. For example, when the active command ACT is sensed, the control logic circuit **230** may generate a control signal for activating a specific word line of a specific memory bank. In this case, the specific word line of the specific memory bank may be activated in accordance with the row address ADD_r corresponding to the active command ACT. For example, when the precharge command PRE is sensed, the control logic circuit **230** may generate a control signal for precharging at least one memory bank. In this case, in accordance with the row address ADD_r corresponding to the precharge command PRE, the specific memory bank or all memory banks may be precharged. For example, when the write command WR or the read command RD is sensed, the control logic circuit **230** may generate a control signal so as to write or read the data DATA in or from the specific memory bank. In this case, in accordance with the column address ADD_c corresponding to the write command WR or the read command RD, the data DATA may be written in or read from a memory cell corresponding to the column address ADD_c.

(44) According to an example embodiment, the control logic circuit **230** may include a specific command decoding circuit for decoding a specific command (e.g., the precharge command PRE) received at the rising and/or falling edge of the clock signal CK in the row command CMD_r. Accordingly, the control logic circuit **230** may sense the specific command although the row command CMD_r representing the specific command is received at any timing.

(45) The input and output circuit **240** may transmit and receive the data DATA to and from an external device (e.g., the memory controller **100**) through a plurality of data lines. The input and output circuit **240** may include an input and output buffer for temporarily storing read data provided from the plurality of memory banks **220a** to **220n** and write data provided from the external device.

(46) FIGS. 3A to 3C illustrate examples of a timing diagram in which the memory device of FIG. 1 receives commands according to example embodiments. Specifically, FIG. 3A is a timing diagram illustrating that the precharge command PRE is received at the rising edge of the clock signal CK_c and FIG. 3B is a timing diagram illustrating that the precharge command PRE is received at the falling edge of the clock signal CK_c. FIG. 3C is a timing diagram illustrating that the precharge command PRE is received at the rising and falling edge of the clock signal CK_c.

(47) Referring to FIGS. 3A to 3C, clock signals CK_c and CK_t are received through two signal lines as a differential pair. For example, the clock signal CK_c may correspond to the clock signal CK of FIG. 1. The row command CMD_r and the column command CMD_c are received based on toggle timings of the clock signals CK_c and CK_t. The active command ACT and the precharge command PRE are received as the row command CMD_r and the write command WR, and the read command RD are received as the column command CMD_c. The active command ACT is received during 1.5 cycles corresponding to two rising edges and one falling edge of the clock signal CK_c, and the precharge command PRE is received during a 0.5 cycle corresponding to one rising edge or one falling edge of the clock signal CK_c. The write command WR and the read command RD are received during 1 cycle corresponding to one rising edge and one falling edge of the clock signal CK_c.

(48) Referring to FIGS. 1 and 3A, the memory device **200** may receive an active command ACTa and the write command WR at a first point in time t1 corresponding to the rising edge of the clock signal CK_c. The memory device **200** may receive the active command ACTa and the write command WR in parallel at the first point in time t1. In this case, a bank address corresponding to the active command ACTa may be different from a bank address corresponding to the write

command WR. For example, the active command ACTa may correspond to a first bank address BA1, the write command WR may correspond to a second bank address BA2. Because the active command ACTa is received during the 1.5 cycles, the active command ACTa may be received until a second point in time t2.

(49) The memory device **200** may receive the read command RD at the second point in time t2. The memory device **200** may receive the active command ACTa and the read command RD in parallel at the second point in time t2. In this case, the bank address corresponding to the active command ACTa may be different from a bank address corresponding to the read command RD. For example, the active command ACTa may correspond to a first bank address BA1, the read command RD may correspond to a third bank address BA3.

(50) As illustrated in FIG. 3A, when the read command RD is received without delay after the write command WR is completely received (i.e., when a time interval between the write command WR and the read command RD is 1 tCK (i.e., 1 cycle of the clock signal CK_c)), the bank address corresponding to the write command WR may be different from the bank address corresponding to the read command RD. For example, the write command WR may correspond to a second bank address BA2, and the read command RD may correspond to a third bank address BA3. For example, when the memory banks are divided into the plurality of bank groups, a bank group corresponding to the write command WR may be different from a bank group corresponding to the read command RD. Accordingly, the bank addresses corresponding to the active command ACTa, the write command WR, and the read command RD may be different from one another.

(51) The memory device **200** may not receive the row command CMD_r representing a specific operation at a third point in time t3 corresponding to the falling edge of the clock signal CK_c. For example, the memory device **200** may receive a no operation row command (e.g., RNOP of FIG. 12A) representing a no operation at the third point in time t3.

(52) The memory device **200** may receive a precharge command PREb at a fourth point in time t4 corresponding to the rising edge of the clock signal CK_c. After the active command ACTa is completely received, the precharge command PREb may be received with delay of the 0.5 cycle. In this case, the bank address corresponding to the active command ACTa may be different from a bank address corresponding to the precharge command PREb. For example, the active command ACTa may correspond to a first bank address BA1, and the precharge command PREb may correspond to a fourth bank address BA4. However, the inventive concept is not limited thereto. The precharge command PREb may correspond to the second bank address BA2 corresponding to the write command WR received at the first point in time t1 or the third bank address BA3 corresponding to the read command RD received at the second point in time t2.

(53) The memory device **200** may not receive the row command CMD_r representing a specific operation at a fifth point in time t5 corresponding to the falling edge of the clock signal CK_c. For example, the memory device **200** may receive the no operation row command RNOP at the fifth point in time t5. The memory device **200** may receive an active command ACTc at a sixth point in time t6 corresponding to the rising edge of the clock signal CK_c and may receive a precharge command PREd at a seventh point in time t7 corresponding to the rising edge of the clock signal CK_c.

(54) As described above, when the precharge command PRE is received at the rising edge of the clock signal CK_c, the precharge command PRE may be received with delay (e.g. 0.5 cycle) after the active command ACT is completely received.

(55) Referring to FIGS. 1 and 3B, the memory device **200** may receive the active command ACTa and the write command WR at the first point in time t1 corresponding to the rising edge of the clock signal CK_c and may receive the active command ACTa and the read command RD at the second point in time t2.

(56) The memory device **200** may receive the precharge command PREb at the third point in time t3 corresponding to the falling edge of the clock signal CK_c. After the active command ACTa is

completely received, the precharge command PREb may be received without delay. Therefore, at the third point in time t3, the precharge command PREb and the read command RD may be received in parallel.

(57) According to example embodiment of FIG. 3B, the bank address corresponding to the active command ACTa may be different from the bank address corresponding to the write command WR. In addition, the bank address corresponding to the active command ACTa, the bank address corresponding to the precharge command PREb, and the bank address corresponding to the read command RD may be different from one another. For example, the active command ACTa may correspond to the first bank address BA1, the write command WR may correspond to the second bank address BA2, the read command RD may correspond to the third bank address BA3, and the precharge command PREb may correspond to the fourth bank address BA4. However, the inventive concept is not limited thereto. The precharge command PREb may correspond to the second bank address BA2 corresponding to the write command WR received at the first point in time t1.

(58) After the precharge command PREb is completely received, the memory device 200 may receive the active command ACTc at the fourth point in time t4 corresponding to the rising edge of the clock signal CK_c without delay. After the active command ACTc is completely received, the memory device 200 may receive the precharge command PREd at the fifth point in time t5 corresponding to the falling edge of the clock signal CK_c without delay.

(59) As described above, when the precharge command PRE is received at the falling edge of the clock signal CK_c, the precharge command PRE may be received without delay after the active command ACT is completely received.

(60) Referring to FIGS. 1 and 3C, the memory device 200 may receive the active command ACTa from the first point in time t1 corresponding to the rising edge of the clock signal CK_c to the second point in time t2. The memory device 200 may receive the write command WR from the second point in time t2 to the third point in time t3. The memory device 200 may receive the precharge command PREb at the third point in time t3 corresponding to the falling edge of the clock signal CK_c. Accordingly, during the 1 cycle of the clock signal CK_c corresponding to the second point in time t2 and the third point in time t3, the active command ACTa, the precharge command PREb, and the write command WR may be received. In this case, the bank address corresponding to the active command ACTa, the bank address corresponding to the precharge command PREb, and the bank address corresponding to the write command WR may be different from one another. For example, the active command ACTa may correspond to the first bank address BA1, the write command WR may correspond to the second bank address BA2, and the precharge command PREb may correspond to the third bank address BA3.

(61) After the precharge command PREb is completely received, the memory device 200 may receive the active command ACTc at the fourth point in time t4 without delay. After the active command ACTc is completely received, the memory device 200 may receive the no operation row command RNOP at the fifth point in time t5 corresponding to the falling edge of the clock signal CK_c and may receive the precharge command PREd at the sixth point in time t6 corresponding to the rising edge of the clock signal CK_c. After the active command ACTc is completely received, the precharge command PREd may be received with delay of the 0.5 cycle. After the precharge command PREd is completely received, the memory device 200 may receive the no operation row command RNOP at the seventh point in time t7 corresponding to the falling edge of the clock signal CK_c. The memory device 200 may receive the read command RD from the sixth point in time t6 to the seventh point in time t7. Accordingly, during the 1 cycle of the clock signal CK_c corresponding to the sixth point in time t6 and the seventh point in time t7, the precharge command PREd, the no operation row command RNOP, and the read command RD may be received.

(62) As described above, when the precharge command PRE is received at the rising and falling edge of the clock signal CK_c, the precharge command PRE may be received without or with delay

after the active command ACT is completely received.

(63) In FIGS. 3A to 3C, it is illustrated that the precharge command PRE for one memory bank is received. However, the inventive concept is not limited thereto. For example, the memory device **200** may receive the precharge command PRE corresponding to all memory banks at the rising and/or falling edge of the clock signal CK_c.

(64) As described above, when the active command ACT is received during the 1.5 cycles of the clock signal CK_c and the precharge command PRE is received during the 0.5 cycle of the clock signal CK_c, the precharge command PRE may be received at the rising and/or falling edge of the clock signal CK_c. The memory device **200** may receive the precharge command PRE selectively transmitted by the memory controller **100** at a timing between the rising edge and the falling edge of the clock signal CK_c.

(65) As described above, when the precharge command PRE is received at the falling edge of the clock signal CK_c, the precharge command PRE may be received during the 0.5 cycle without delay after the active command ACT is completely received during the 1.5 cycles and the active command ACT may be received without delay after the precharge command PRE is completely received. In addition, at a timing at which the active command ACT or the precharge command PRE is received, the write command WR or the read command RD may be received in parallel. Therefore, commands corresponding to a plurality of banks may be quickly received when memory access is continuously performed by an operation like in bank interleave or bank group interleave. Therefore, an operation speed of the memory device **200** may increase.

(66) FIGS. 4A and 4B illustrate examples of a timing diagram in which the memory device **200** of FIG. 1 receives commands for one memory bank according to example embodiments. Specifically, FIG. 4A is a timing diagram illustrating that a precharge command PRE1 is received at the rising edge of the clock signal CK_c and FIG. 4B is a timing diagram illustrating that a precharge command PRE2 is received at the falling edge of the clock signal CK_c.

(67) Referring to FIG. 4A, the memory device **200** may receive an active command ACT1 during the 1.5 cycles of the clock signal CK_c from the first point in time t1 to the second point in time t2. The memory device **200** may receive a read command RD1 or a write command WR1 in accordance with the active command ACT1 at the third point in time t3. After the read command RD1 or the write command WR1 is completely received, the memory device **200** may receive the precharge command PRE1 during the 0.5 cycle at the fourth point in time t4 corresponding to the rising edge of the clock signal CK_c. In this case, a minimum time interval tRASa between the active command ACT1 and the precharge command PRE1 (i.e., a minimum time interval for transmitting the precharge command PRE1 after the active command ACT1 is transmitted) may correspond to a time interval between the second point in time t2 corresponding to the rising edge of the clock signal CK_c and the fourth point in time t4 corresponding to the rising edge of the clock signal CK_c. For example, the minimum time interval tRASa may be determined by a standard.

(68) After the precharge command PRE1 is completely received, the memory device **200** may receive the active command ACTa from the fifth point in time t5 to the sixth point in time t6. In this case, a minimum time interval tRPa between the precharge command PRE1 and the active command ACTa (i.e., a minimum time interval for transmitting the active command ACTa after the precharge command PRE1 is transmitted) may correspond to a time interval between the fourth point in time t4 corresponding to the rising edge of the clock signal CK_c and the sixth point in time t6 corresponding to the rising edge of the clock signal CK_c. For example, the minimum time interval tRPa may be determined by a standard.

(69) As described above, when the two active commands ACT1 and ACTa are received for the same memory bank, a minimum time interval tRCa between the active command ACT1 and the active command ACTa (i.e., a minimum time interval for transmitting the active command ACTa after the active command ACT1 is transmitted) may correspond to a time interval between the

second point in time **t2** and the sixth point in time **t6**. For example, the minimum time interval **tRCa** may be determined by a standard.

(70) Referring to FIG. 4B, the memory device **200** may receive an active command **ACT2** during the 1.5 cycles of the clock signal **CK_c** from the seventh point in time **t7** to an eighth point in time **t8**. The memory device **200** may receive a read command **RD2** or a write command **WR2** in accordance with the active command **ACT2** at a ninth point in time **t9**. After the read command **RD2** or the write command **WR2** is completely received, the memory device **200** may receive a precharge command **PRE2** for the 0.5 cycle at a tenth point in time **t10** corresponding to the falling edge of the clock signal **CK_c**. In this case, a minimum time interval **tRASb** between the active command **ACT2** and the precharge command **PRE2** (i.e., a minimum time interval for transmitting the precharge command **PRE2** after the active command **ACT2** is transmitted) may correspond to a time interval between the eighth point in time **t8** corresponding to the rising edge of the clock signal **CK_c** and the tenth point in time **t10** corresponding to the falling edge of the clock signal **CK_c**. For example, the minimum time interval **tRASb** may be determined by a standard. In this case, the minimum time interval **tRASa** of FIG. 4A may be different from the minimum time interval **tRASb** of FIG. 4B. For example, the minimum time interval **tRASa** may be greater than the minimum time interval **tRASb** by the 0.5 cycle of the clock signal **CK_c**.

(71) After the precharge command **PRE2** is completely received, the memory device **200** may receive an active command **ACTb** from an 11.sup.th point in time **t11** to a 13.sup.th point in time **t13**. In this case, a minimum time interval **tRPb** between the precharge command **PRE2** and the active command **ACTb** (i.e., a minimum time interval for transmitting the active command **ACTb** after the precharge command **PRE2** is transmitted) may correspond to a time interval between the tenth point in time **t10** corresponding to the falling edge of the clock signal **CK_c** and the 12.sup.th point in time **t12** corresponding to the falling edge of the clock signal **CK_c**. For example, the minimum time interval **tRPb** may be determined by a standard. In this case, the minimum time interval **tRPa** of FIG. 4A may be equal to the minimum time interval **tRPb** of FIG. 4B.

(72) As described above, when the two active commands **ACT2** and **ACTb** are received for the same memory bank, a minimum time interval **tRCb** between the active command **ACT2** and the active command **ACTb** (i.e., a minimum time interval for transmitting the active command **ACTb** after the active command **ACT2** is transmitted) may correspond to a time interval between the eighth point in time **t8** and the 13.sup.th point in time **t13**. For example, the minimum time interval **tRCb** may be determined by a standard. In this case, the minimum time interval **tRCa** of FIG. 4A may be equal to the minimum time interval **tRCb** of FIG. 4B. However, the inventive concept is not limited thereto.

(73) FIG. 5 is a flowchart illustrating an example operation of the memory device of FIG. 1. Specifically, FIG. 5 illustrates a memory access operation for one memory bank of the memory device **200** as described with reference to FIGS. 4A and 4B. Referring to FIGS. 1 and 5, in operation **S201**, the memory device **200** may receive the active command **ACT** through the row pin **R_P**. In this case, the memory device **200** may further receive the row address **ADD_r** including the specific memory bank address together with the active command **ACT**. The memory device **200** may activate the specific word line of the specific memory bank in response to the active command **ACT**.

(74) In operation **S202**, the memory device **200** may receive the read command **RD** or the write command **WR** through the column pin **C_P**. In this case, the memory device **200** may further receive the column address **ADD_c** including the specific memory bank address together with the read command **RD** or the write command **WR**. The memory device **200** may read or write the data **DATA** from or in the memory cell of the specific memory bank in response to the read command **RD** or the write command **WR**.

(75) In operation **S203**, the memory device **200** may receive the precharge command **PRE** at the rising or falling edge of the clock signal **CK** through the row pin **R_P**. The memory device **200** may

further receive the row address ADD_r including the specific memory bank address together with the precharge command PRE. The memory device **200** may precharge the memory cells of the specific memory bank in response to the precharge command PRE. For example, as illustrated in FIGS. 3A to 4B, when the precharge command PRE is received during the 0.5 cycle of the clock signal CK, the memory device **200** may completely receive the precharge command PRE at the rising or falling edge of the clock signal CK. For another example, when the precharge command PRE is received during the cycle of the clock signal CK greater than the 0.5 cycle, the memory device **200** may start to receive the precharge command PRE at the rising or falling edge of the clock signal CK.

(76) FIG. 6 is a block diagram of the control logic circuit **230** of FIG. 2. Referring to FIG. 6, the control logic circuit **230** may include a row command decoder **230a** and a column command decoder **230b**. The row command decoder **230a** may decode the row command CMD_r received through the row pin R_P based on the clock signal CK received through the clock pin CK_P. The column command decoder **230b** may decode the column command CMD_c received through the column pin C_P based on the clock signal CK received through the clock pin CK_P.

(77) The row command decoder **230a** may decode the specific command (e.g., the precharge command PRE) received at the rising and/or falling edge of the clock signal CK in the row command CMD_r. The row command decoder **230a** may include a first specific command decoder **231**, a second specific command decoder **232**, a comparator **233**, and an inverter **234** in order to decode the specific command.

(78) The first specific command decoder **231** may receive the clock signal CK and the row command CMD_r and may output a first decoding result DR1 representing whether the row command CMD_r is the specific command based on the rising edge of the clock signal CK.

(79) The second specific command decoder **232** may receive a signal obtained by inverting the clock signal CK through the inverter **234** and the row command CMD_r. Therefore, the second specific command decoder **232** may output a second decoding result DR2 representing whether the row command CMD_r is the specific command based on the falling edge of the clock signal CK. In FIG. 6, the clock signal CK is illustrated as being input to the second specific command decoder **232** through the inverter **234**. However, the inventive concept is not limited thereto. For example, as described with reference to FIGS. 3A to 3C, when the clock signal CK is formed of a differential pair, the clock signal CK_c may be input to the first specific command decoder **231** and a clock signal CK_t may be input to the second specific command decoder **232**.

(80) The comparator **233** may generate an internal command iCMD by comparing the first decoding result DR1 with the second decoding result DR2. For example, when the first decoding result DR1 or the second decoding result DR2 represents that the row command CMD_r is the specific command, the comparator **233** may generate the internal command iCMD corresponding to the specific command. Therefore, the memory device **200** may perform a corresponding operation in response to the internal command iCMD. For example, when the internal command iCMD represents the precharge command PRE, the memory device **200** may perform a precharge operation.

(81) As described above, the control logic circuit **230** may sense the specific command received at the rising edge of the clock signal CK and the specific command received at the falling edge of the clock signal CK through a specific command decoder. In addition, as described with reference to FIGS. 3A to 3C, although the row command CMD_r and the column command CMD_c are received in parallel, the control logic circuit **230** may decode the row command CMD_r and the column command CMD_c in parallel through the row command decoder **230a** and the column command decoder **230b**.

(82) FIG. 7 is a block diagram illustrating a stacked memory device **300** according to example embodiments. Referring to FIG. 7, the stacked memory device **300** may correspond to the memory device **200** of FIG. 1. The stacked memory device **300** may include a buffer die **310** and first to

fourth core dies **320** to **350**. For example, the buffer die **310** may be referred to as an interface die, a base die, a logic die, or a master die and each of the first to fourth core dies **320** to **350** may be referred to as a memory die or a slave die. In FIG. 7, the stacked memory device **300** is illustrated as including four core dies, that is, the first to fourth core dies **320** to **350**. However, the number of core dies may vary. For example, the stacked memory device **300** may include 8, 12, or 16 core dies.

(83) The buffer die **310** and the first to fourth core dies **320** to **350** may be stacked through silicon vias (TSV) and may be electrically connected to each other. Therefore, the stacked memory device **300** may have a three-dimensional memory structure in which the plurality of dies, that is, the first to fourth core dies **320** to **350**, are stacked. For example, the stacked memory device **300** may be implemented based on the HBM standard or the HMC standard.

(84) The stacked memory device **300** may support a plurality of functionally independent channels (or vaults). For example, as illustrated in FIG. 7, the stacked memory device **300** may support first to 16.sup.th channels CH0 to CH15. When each of the first to 16.sup.th channels CH0 to CH15 supports 64 data passages (that is, when 64 data pins are provided for each of the first to 16.sup.th channels CH0 to CH15), the stacked memory device **300** including the first to 16.sup.th channels CH0 to CH15 may support 1,024 data passages. However, the inventive concept is not limited thereto. The stacked memory device **300** may support no less than 1,024 data passages and various numbers of channels (e.g., eight channels). For example, when the stacked memory device **300** supports eight channels and each of the eight channels supports 128 data passages, the stacked memory device **300** may support 1,024 data passages.

(85) Each of the first to fourth core dies **320** to **350** may support at least one channel. For example, as illustrated in FIG. 7, each of the first to fourth core dies **320** to **350** may support four channels CH0 to CH3, CH4 to CH7, CH8 to CH11, or CH12 to CH15. In this case, the first to fourth core dies **320** to **350** may support different channels. However, the inventive concept is not limited thereto. At least two of the first to fourth core dies may support the same channel. For example, when the stacked memory device **300** includes eight core dies, one of four core dies forming one stack and one of four core dies forming another stack may support the same channel. In this case, the core dies supporting the same channel may be distinguished by stack IDs SID.

(86) Each of the channels may consist of an independent command and a data interface. For example, the channels may be independently clocked based on independent timing requirements and may not be synchronized with each other.

(87) Each of the channels may include a plurality of memory banks **301**. For example, the memory banks **301** included in one channel may correspond to the memory bank array **220** of FIG. 1. Each of the plurality of memory banks **301** may include memory cells connected to word lines and bit lines, a row decoder, a column decoder, and a sense amplifier. For example, each of the first to 16.sup.th channels CH0 to CH15 may include 32 memory banks **301**. However, the inventive concept is not limited thereto. Each of the first to 16.sup.th channels CH0 to CH15 may include no less than eight memory banks **301**. In FIG. 7, it is illustrated that the memory banks **301** included in one channel are included in one core die. However, the memory banks **301** included in one channel may be distributed among multiple core dies. For example, when the two of the first to fourth core dies support the first channel CH0, the memory banks **301** included in the first channel CH0 may be distributed between two core dies.

(88) According to an example embodiment, the memory banks **301** included in one channel may be divided into a plurality of bank groups. For example, each of the plurality of bank groups may include four memory banks. However, the inventive concept is not limited thereto.

(89) According to an example embodiment, one channel may be divided into two independently operating pseudo channels. For example, the pseudo channels may share a command and clock inputs (e.g., the clock signal CK and/or a clock enable signal CKE) of a channel, however, may independently decode and execute commands. For example, when one channel supports 64 data

passages, each of the pseudo channels may support 32 data passages. For example, when one channel includes 32 memory banks **301**, each of the pseudo channels may include 16 memory banks **301**.

(90) The buffer die **310** and the first to fourth core dies **320** to **350** may include a TSV area **302**. TSVs formed to pass through the first to fourth core dies **320** to **350** may be arranged in the TSV area **302**. The buffer die **310** may transmit and receive various signals to and from the first to fourth core dies **320** to **350** through the TSVs. The first to fourth core dies **320** to **350** may transmit and receive signals to and from the buffer die **310** and another core die through the TSVs. In this case, the signals may be independently transmitted and received through the corresponding TSVs by channel. For example, when an external host device (e.g., the memory controller **100** of FIG. **1**) transmits a data signal to the first channel CH0 in order to store data in the memory cell of the first channel CH0, the buffer die **310** may store the data in the memory cell of the first channel CH0 by transmitting the data signal to the first core die **320** through the TSVs corresponding to the first channel CH0.

(91) According to an example embodiment, in order to transmit the signals through the TSVs, a power supply voltage VDDQL may be used. The power supply voltage VDDQL may be less than a power supply voltage VDDQ used for an overall operation of the buffer die **310**. For example, the power supply voltage VDDQ may be 1.1 V and the power supply voltage VDDQL may be 0.4 V.

(92) The buffer die **310** may include a physical layer **311**. The physical layer **311** may include interface circuits communicating with the external host device. According to an example embodiment, the physical layer **311** may include an interface circuit corresponding to each of the first to 16.sup.th channels CH0 to CH15. For example, an interface circuit corresponding to one channel may correspond to the memory interface circuit **210** of FIG. **1**. The signals received from the external host device through the physical layer **311** may be transmitted to the first to fourth core dies **320** to **350** through the TSVs.

(93) According to an example embodiment, the buffer die **310** may include a channel controller corresponding to each of the channels. The channel controller may manage memory reference operations of a corresponding channel and may determine a timing requirement of the corresponding channel.

(94) According to an example embodiment, the buffer die **310** may include a plurality of pins for receiving the signals from the external host device. The buffer die **310** may receive the clock signal CK, a command/address signal C/A, a write data strobe signal WDQS, and a data signal DQ through the plurality of pins and may transmit a read data strobe signal RDQS and the data signal DQ. For example, the buffer die **310** may include two pins (e.g., the clock pin CK_P of FIG. **1**) for receiving the clock signal CK, 18 pins (e.g., the row pin R_P and the column pin C_P of FIG. **1**) for receiving the command/address signal C/A, four pins for receiving the write data strobe signal WDQS, four pins for transmitting the read data strobe signal RDQS, and 64 pins (e.g., the data pin D_P of FIG. **1**) for transmitting and receiving the data signal DQ.

(95) According to an example embodiment, the stacked memory device **300** may further include an error correction code (ECC) circuit for detecting and correcting an error of data. For example, in a write operation, the ECC circuit may generate parity bits for the data transmitted from the host device. In a read operation, the ECC circuit may detect and correct the error of the data transmitted from one of the first to fourth core dies **320** to **350** by using the parity bits and may transmit the error corrected data to the external host device.

(96) According to an example embodiment, the stacked memory device **300** may receive the row command CMD_r through the row pin R_P and may receive the column command CMD_c through the column pin C_P as described with reference to FIGS. **1** to **6**. The stacked memory device **300** may receive the specific command of the row command CMD_r at the rising and/or falling edge of the clock signal CK. The stacked memory device **300** may sense the specific command from the row command CMD_r transmitted at one of the rising and falling edges of the

clock signal CK. For example, the specific command may be the precharge command PRE.

(97) According to an example embodiment, the stacked memory device **300** may include the specific command decoder for sensing the specific command by decoding the row command CMD_r at the rising edge of the clock signal CK and sensing the specific command by decoding the row command CMD_r at the falling edge of the clock signal CK as illustrated in FIG. 6.

(98) FIG. 8 is an example block diagram of the stacked memory device **300** of FIG. 7. Referring to FIG. 8, the stacked memory device **400** may include a buffer die **410** and a core die **420**. The core die **420** may support a channel CHa among a plurality of channels. The buffer die **410** and the core die **420** may communicate through TSVs **401** to **404** positioned in the TSV area. The TSVs **401** to **404** may be positioned in the TSV area corresponding to the channel CHa. For example, the buffer die **410** may transmit the clock signal CK to the core die **420** through the TSV **401**, may transmit the row command/row address CMD_r/ADD_r to the core die **420** through the TSV **402**, may transmit the column command/column address CMD_c/ADD_c to the core die **420** through the TSV **403**, and may transmit and receive the data DATA to and from the core die **420** through the TSV **404**. In FIG. 8, each of the TSVs **401** to **404** is implemented by one TSV. However, each of the TSVs **401** to **404** may be implemented by various numbers of TSVs.

(99) The buffer die **410** may include a memory interface circuit **411** corresponding to the channel CHa. The memory interface circuit **411** may correspond to the memory interface circuit **210** of FIG. 1. The memory interface circuit **411** may receive the clock signal CK, the row command/row address CMD_r/ADD_r, the column command/column address CMD_c/ADD_c, and the data DATA that are transmitted to the channel CHa through the clock pin CK_P, the row pin R_P, the column pin C_P, and the data pin D_P corresponding to the channel CHa. The memory interface circuit **411** may transmit the clock signal CK, the row command/row address CMD_r/ADD_r, the column command/column address CMD_c/ADD_c, and the data DATA to the core die **420** through the TSVs **401** to **404**. According to an example embodiment, the memory interface circuit **411** may transmit the signal processed clock signal CK, the row command/row address CMD_r/ADD_r, the column command/column address CMD_c/ADD_c, and the data DATA to the core die **420**. The memory interface circuit **411** may transmit the data DATA transmitted from the core die **420** through the TSV **404** to the external host device (e.g., the memory controller **100** of FIG. 1).

(100) The core die **420** may include a control logic circuit **421**, a data input and output circuit **422**, and a memory cell array **423**. The control logic circuit **421**, the data input and output circuit **422**, and the memory cell array **423** may support the channel CHa. The memory cell array **423** may be included in one of the memory banks included in the channel CHa. The control logic circuit **421**, the data input and output circuit **422**, and the memory cell array **423** may respectively correspond to the control logic circuit **230**, the input and output circuit **240**, and the memory cell array **221** of FIG. 2. Therefore, previously given description may be omitted.

(101) The control logic circuit **421** may receive the clock signal CK, the row command/row address CMD_r/ADD_r, and the column command/column address CMD_c/ADD_c that are transmitted from the buffer die **410** through the TSVs **401** to **403**. The control logic circuit **421** may decode the row command/row address CMD_r/ADD_r and the column command/column address CMD_c/ADD_c. According to an example embodiment, the control logic circuit **421** may sense the specific command (e.g., the precharge command PRE) by decoding the row command CMD_r received at the rising edge of the clock signal CK and may sense the specific command by decoding the row command CMD_r received at the falling edge of the clock signal CK as described with reference to FIG. 6. The control logic circuit **421** may control the data input and output circuit **422** and the memory cell array **423** based on the decoding result.

(102) The data input and output circuit **422** may transmit and receive the data DATA to and from the buffer die **410** through the TSV **404**. In a write operation, the data input and output circuit **422** may transmit the data DATA transmitted from the buffer die **410** through the TSV **404** to the memory cell array **423**. Therefore, the memory cell array **423** may store the data DATA. In a read

operation, the data input and output circuit **422** may transmit the data DATA output from the memory cell array **423** to the buffer die **410** through the TSV **404**.

(103) In FIG. **8**, it is illustrated that the row command CMD_r and the column command CMD_c are decoded by the core die **420** through the control logic circuit **421** of the core die **420**. However, the inventive concept is not limited thereto. For example, the row command CMD_r and the column command CMD_c may be decoded through the command decoder included in the memory interface circuit **411** of the buffer die **410**.

(104) FIG. **9** is a block diagram illustrating an example of enlargement of the stacked memory device **400** of FIG. **8**. Referring to FIG. **9**, the stacked memory device **400a** may include a buffer die **410** and a core die **420a**. The core die **420a** may support the channel CHa divided into a first pseudo channel PC0 and a second pseudo channel PC1. The core die **420a** may include the control logic circuit **421**, the data input and output circuit **422**, and the memory cell array **423** supporting the first pseudo channel PC0 and a control logic circuit **424**, a data input and output circuit **425**, and a memory cell array **426** supporting the second pseudo channel PC1. Because the control logic circuit **424**, the data input and output circuit **425**, and the memory cell array **426** respectively correspond to the control logic circuit **421**, the data input and output circuit **422**, and the memory cell array **423**, detailed description thereof will not be given.

(105) The control logic circuit **421** may receive the clock signal CK, the row command/row address CMD_r/ADD_r, and the column command/column address CMD_c/ADD_c from the buffer die **410** through the TSVs **401** to **403**. When the row address ADD_r represents the first pseudo channel PC0, the control logic circuit **421** may decode the row command CMD_r. When the column address ADD_c represents the first pseudo channel PC0, the control logic circuit **421** may decode the column command CMD_c. That is, the control logic circuit **421** may decode the row command CMD_r and the column command CMD_c corresponding to the first pseudo channel PC0 and may control the data input and output circuit **422** and the memory cell array **423** in accordance with the decoding result.

(106) The control logic circuit **424** may receive the clock signal CK, the row command/row address CMD_r/ADD_r, and the column command/column address CMD_c/ADD_c transmitted from the buffer die **410** through the TSVs **401** to **403**. When the row address ADD_r represents the second pseudo channel PC1, the control logic circuit **424** may decode the row command CMD_r. When the column address ADD_c represents the second pseudo channel PC1, the control logic circuit **424** may decode the column command CMD_c. That is, the control logic circuit **424** may decode the row command CMD_r and the column command CMD_c corresponding to the second pseudo channel PC1 and may control the data input and output circuit **425** and the memory cell array **426** in accordance with the decoding result.

(107) FIG. **10** is a block diagram illustrating an example of enlargement of the stacked memory device **400a** of FIG. **8**. Referring to FIG. **10**, the stacked memory device **400b** may include a buffer die **410**, a first core die **420**, and a second core die **430**. The first core die **420** and the second core die **430** may support the same channel CHa among a plurality of channels. The first core die **420** may be included in one stack including a plurality of core dies, and the second core die **430** may be included in another stack including the plurality of core dies. In this case, the first and second core dies **420** and **430** may be distinguished by stack IDs SID. For example, the first core die **420** may correspond to a first stack ID SID0 and the second core die **430** may correspond to a second stack ID SID1. In FIG. **10**, it is illustrated that another core die is not positioned between the first core die **420** and the second core die **430**. However, another core die may be positioned between the first core die **420** and the second core die **430**.

(108) The buffer die **410** and the first and second core dies **420** and **430** may communicate through the TSVs **401** to **404** positioned in the TSV area. For example, the buffer die **410** may transmit the clock signal CK to the first and second core dies **420** and **430** through the TSV **401**, may transmit the row command/row address CMD_r/ADD_r to the first and second core dies **420** and **430**

through the TSV **402**, may transmit the column command/column address CMD_c/ADD_c to the first and second core dies **420** and **430** through the TSV **403**, and may transmit and receive the data DATA to and from the first and second core dies **420** and **430** through the TSV **404**. In FIG. **10**, it is illustrated that the buffer die **410** communicates with the first and second core dies **420** and **430** by using the TSVs **401** to **404**. However, the buffer die **410** may communicate with the first and second core dies **420** and **430** by using separate TSVs corresponding to the first and second core dies **420** and **430**.

(109) The first core die **420** may include the control logic circuit **421**, the data input and output circuit **422**, and the memory cell array **423** supporting the channel CHa, and the second core die **430** may include a control logic circuit **431**, a data input and output circuit **432**, and a memory cell array **433** supporting the channel CHa. Because the control logic circuit **431**, the data input and output circuit **432**, and the memory cell array **433** respectively correspond to the control logic circuit **421**, the data input and output circuit **422**, and the memory cell array **423**, detailed description thereof will be omitted.

(110) The control logic circuit **421** may receive the clock signal CK, the row command/row address CMD_r/ADD_r, and the column command/column address CMD_c/ADD_c from the buffer die **410** through the TSVs **401** to **403**. When the row address ADD_r represents the first stack ID SID0, the control logic circuit **421** may decode the row command CMD_r. When the column address ADD_c represents the first stack ID SID0, the control logic circuit **421** may decode the column command CMD_c. That is, the control logic circuit **421** may decode the row command CMD_r and the column command CMD_c corresponding to the first stack ID SID0 and may control the data input and output circuit **422** and the memory cell array **423** in accordance with the decoding result.

(111) The control logic circuit **431** may receive the clock signal CK, the row command/row address CMD_r/ADD_r, and the column command/column address CMD_c/ADD_c from the buffer die **410** through the TSVs **401** to **403**. When the row address ADD_r represents the second stack ID SID1, the control logic circuit **431** may decode the row command CMD_r. When the column address ADD_c represents the second stack ID SID1, the control logic circuit **431** may decode the column command CMD_c. That is, the control logic circuit **431** may decode the row command CMD_r and the column command CMD_c corresponding to the second stack ID SID1 and may control the data input and output circuit **432** and the memory cell array **433** in accordance with the decoding result.

(112) FIGS. **11A** and **11B** illustrate examples of a timing diagram in which the stacked memory device **300** of FIG. **7** receives commands according to example embodiments. Specifically, FIG. **11A** illustrates an example in which a write command WR for first to third bank groups BG1 to BG3 is received. FIG. **11B** illustrates an example in which a write command WR for different pseudo channels PC0 and PC1 is received.

(113) Referring to FIGS. **11A** and **11B**, the stacked memory device **300** may receive the active command ACT for the 1.5 cycles, may receive the precharge command PRE for the 0.5 cycle, and may receive the write command WR for the 1 cycle. The stacked memory device **300** may receive the precharge command PRE at the rising and falling edge of the clock signal CK_c. For example, as illustrated in FIGS. **11A** and **11B**, after the active command ACTa is completely received, without delay, the stacked memory device **300** may receive the precharge command PREb at the falling edge of the clock signal CK_c. After the precharge command PREb is completely received, the stacked memory device **300** may receive the active command ACTc without delay. After the active command ACTc is completely received, the stacked memory device **300** may receive the precharge command PREd at the rising edge of the clock signal CK_c with delay of the 0.5 cycle. In this case, because examples of the row command CMD_c of FIGS. **11A** and **11B** correspond to the example of the row command CMD_c of FIG. **3C**, detailed description thereof will be omitted. In FIGS. **11A** and **11B**, examples in which the write commands WR are received are described. However, the inventive concept is not limited thereto. For example, the write commands WR may

be changed into read commands RD.

(114) Referring to FIGS. 7 and 11A, the stacked memory device 300 may receive the active command ACTa and the first write command WR1 at the first point in time t1. In this case, the first write command WR1 may correspond to one of memory banks of the first bank group BG1. After the first write command WR1 is completely received, the stacked memory device 300 may receive the active command ACTc and the second write command WR2 at the second point in time t2. In this case, the second write command WR2 may correspond to one of memory banks of the second bank group BG2. After the second write command WR2 is completely received, the stacked memory device 300 may receive the precharge command PREd and the third write command WR3 at the third point in time t3. In this case, the third write command WR3 may correspond to one of memory banks of the third bank group BG3. For example, as illustrated in FIG. 11A, a time interval for receiving different write commands may be 2 tCK (i.e., the 2 cycles of the clock signal CK_c).

(115) As described above, when the write commands WR or the read commands RD are continuously received for the different bank groups, after one write command WR or one read command RD is completely received, the stacked memory device 300 may receive another write command WR or another read command RD with delay.

(116) Referring to FIGS. 7 and 11B, the stacked memory device 300 may sequentially receive the first to fifth write commands WR1 to WR5 from the first point in time t1 to the fifth point in time t5. A time interval for receiving the different write commands may be 1 tCK (i.e., the 1 cycle of the clock signal CK_c). For example, as illustrated in FIG. 11B, after one write command is completely received, another write command may be immediately received. In this case, the continuously received two write commands may correspond to different pseudo channels. For example, the first write command WR1, the third write command WR3, and the fifth write command WR5 may correspond to one of memory banks of the first pseudo channel PC0 and the second write command WR2 and the fourth write command WR4 may correspond to one of memory banks of the second pseudo channel PC1.

(117) As described above, when the write commands WR or the read commands RD are continuously received for the different pseudo channels, after one write command WR or one read command RD is completely received, the stacked memory device 300 may receive another write command WR or another read command RD without delay. Therefore, the stacked memory device 300 may quickly receive commands when memory access is continuously performed by an operation like in pseudo channel interleave.

(118) FIG. 12A is a table illustrating an example of a row command according to an example embodiment, and FIG. 12B is a table illustrating an example of a column command according to an example embodiment.

(119) Referring to FIG. 12A, the row command may include a no operation row command RNOP, an active command ACT, a precharge command PREpb for a specific bank, a precharge command PREab for all banks, a refresh command REFpb for a specific bank, a refresh command REFab for all banks, a refresh management command RFMpb for a specific bank, a refresh management command RFMab for all banks, a power-down entry command PDE, a self refresh entry command SRE, a power-down exit command PDX, and a self refresh exit command SRX.

(120) The no operation row command RNOP, the precharge commands PREpb and PREab, the refresh commands REFpb and REFab, the refresh management commands RFMpb and RFMab, the power-down exit command PDX, and the self refresh exit command SRX may be received for the 0.5 cycle of the clock signal CK. In this case, the no operation row command RNOP and the precharge commands PREpb and PREab may be received at the rising edge R or the falling edge F of the clock signal CK as described with reference to FIGS. 3A to 3C. The refresh management commands RFMpb and RFMab, the power-down exit command PDX, and the self refresh exit command SRX may be received at the rising edge R of the clock signal CK.

(121) The active command ACT may be received for the 1.5 cycles of the clock signal CK. For example, the active command ACT may be received to correspond to two rising edges R and falling edges F of the clock signal CK. The power-down entry command PDE and the self refresh entry command SRE may be received for the 1 cycle of the clock signal CK. For example, the power-down entry command PDE and the self refresh entry command SRE may be received to correspond to one rising edge R and one falling edge F of the clock signal CK.

(122) The respective commands may be distinguished based on signal values received through first to tenth row pins R_P0 to R_P9. For example, when signal values corresponding to high levels H are received through the first to fourth row pins R_P0 to R_P3 at the rising edge R or the falling edge F of the clock signal CK, the row command may be sensed as the no operation row command RNOP. In this case, through the fifth to tenth row pins R_P4 to R_P9, signal values corresponding to a valid value V (e.g., a high level H or a low level L) may be received.

(123) For example, when a signal value corresponding to the low level L is received through a first row pin R_P0 and signal values corresponding to the high level H are received through second and third row pins R_P1 and R_P2 at a first rising edge R of the clock signal CK, the row command may be sensed as the active command ACT. In this case, a pseudo channel PC may be received through a fourth row pin R_P3, a stack ID SID may be received through fifth and sixth row pins R_P4 and R_P5, and a bank address BA may be received through seventh to tenth row pins R_P6 to R_P9. For example, when the stacked memory device **300** is implemented by one stack, valid values V may be received through the fifth and sixth row pins R_P4 and R_P5 instead of the stack ID SID. While the active command ACT is received after the first rising edge R of the clock signal CK (i.e., at a first falling edge F and a second rising edge R of the clock signal CK), the signal values corresponding to the high level H may be received through the first and second row pins R_P0 and R_P1 and a row address RA may be received through the third to tenth row pins R_P2 to R_P9.

(124) For example, when a signal value corresponding to the high level H is received through the first row pin R_P0 and signal values corresponding to the low level L are received through the second and third row pins R_P1 and R_P2 at the rising edge R or the falling edge F of the clock signal CK, the row command may be sensed as the precharge command PREpb. In this case, the pseudo channel PC may be received through the fourth row pin R_P3, the stack ID SID may be received through fifth and sixth row pins R_P4 and R_P5, and the bank address BA may be received through the seventh to tenth row pins R_P6 to R_P9. For example, when the stacked memory device **300** is implemented by one stack, the valid values V may be received through the fifth and sixth row pins R_P4 and R_P5 instead of the stack ID SID.

(125) For example, when the signal values corresponding to the high level H are received through the first and third row pins R_P0 and R_P2 and the signal value corresponding to the low level L is received through the second row pin R_P1 at the rising edge R or the falling edge F of the clock signal CK, the row command may be sensed as the precharge command PREab. In this case, the pseudo channel PC may be received through the fourth row pin R_P3 and the valid value V may be received through the fifth to tenth row pins R_P4 to R_P9.

(126) Based on the signal values received through the first to tenth row pins R_P0 to R_P9, the row command may be sensed as one of the refresh commands REFpb and REFab, the refresh management commands RFMpb and RFMab, the power-down entry command PDE, the self refresh entry command SRE, the power-down exit command PDX, and the self refresh exit command SRX.

(127) Referring to FIG. **12B**, column commands may include a no operation column command CNOP, read commands RD and RDA, write commands WR and WRA, a mode register set command MRS, and a mode register read command MRR. Here, the read command RDA and the write command WRA instruct an auto precharge operation together with a read operation and a write operation. The respective commands may be received for the 1 cycle corresponding to the

rising edge R and the falling edge F of the clock signal CK.

(128) The respective commands may be distinguished based on signal values received through first to eighth column pins C_P0 to C_P7. For example, when the signal values corresponding to the high level H are received through the first and third column pins C_P0 and C_P2 and the signal values corresponding to the low level L are received through the second and fourth row pins C_P1 and C_P3 at the rising edge R of the clock signal CK, the column command may be sensed as the read command RD. For example, when the signal value corresponding to the high level H is received through the first column pin C_P0 and the signal values corresponding to the low level L are received through the second to fourth column pins C_P1 to C_P3 at the rising edge R of the clock signal CK, the column command may be sensed as the write command WR.

(129) When the read command RD or the write command WR is sensed through the first to fourth column pins C_P0 to C_P3, the pseudo channel PC may be received through the fifth column pin C_P4, the stack ID SID may be received through the sixth and seventh column pins C_P5 and C_P6, and a part of the bank address BA may be received through the eighth column pin C_P7. For example, when the stacked memory device 300 is implemented by one stack, the valid values V may be received through the sixth and seventh column pins C_P5 and C_P6 instead of the stack ID SID. While the read command RD or the write command WR is received after the rising edge R of the clock signal CK (that is, at the falling edge F of the clock signal CK), the remaining of the bank address BA may be received through the first to third column pins C_P0 to C_P2 and a column address CA may be received through the fourth to eighth column pins C_P3 to C_P7.

(130) Based on signal values received through the first to eighth column pins C_P0 to C_P7, the column command may be sensed as one of the no operation column command CNOP, the read command RDA, the write command WRA, the mode register set command MRS, and the mode register read command MRR. Here, a mode register address MA and set information OP may be received together as the mode register set command MRS is received and the mode register address MA may be received together as the mode register read command MRR is received.

(131) FIG. 13 is an example circuit diagram of a control logic circuit 440 for sensing a precharge command according to the row command of FIG. 12A. Specifically, FIG. 13 is an example circuit diagram of a specific command decoder for sensing the precharge command PREpb for a specific bank. Referring to FIG. 13, the control logic circuit 440 may correspond to at least one of the control logic circuits 421, 424, and 431 of FIGS. 8 to 10. The control logic circuit 440 may include inverters 441 to 447, NAND gates 448 and 449, flipflops 451 and 452, and an OR gate 453. The inverters 441, 442, and 446, the NAND gate 448, and the flipflop 451 may correspond to the first specific command decoder 231 of FIG. 6, the inverters 443, 444, and 447, the NAND gate 449, and the flipflop 452 may correspond to the second specific command decoder 232 of FIG. 6, and the OR gate 453 may correspond to the comparator 233 of FIG. 6.

(132) When the precharge command PREpb representing the row command is received, as described with reference to FIG. 12A, the signal values respectively corresponding to the high level H, the low level L, and the low level L may be received through the first to third row pins R_P0 to R_P2. The signal value received through the first row pin R_P0 may be input to each of the NAND gates 448 and 449 and the signal values received through the second and third row pins R_P1 and R_P2 may be inverted by the inverters 441 to 444 and may be respectively input to the NAND gates 448 and 449. Therefore, the signal values corresponding to the high level H may be input to each of the NAND gates 448 and 449 and the signal value corresponding to the low level L may be output from each of the NAND gates 448 and 449. The signal values output from the NAND gates 448 and 449 may be inverted by the inverters 446 and 447 and may be input to input terminals D of the flipflops 451 and 452.

(133) The flipflop 451 may output the signal value input to the input terminal D based on the rising edge R of the clock signal CK received through the clock pin CK_P to an output terminal Q as a first decoding result DR1. For example, when the row command representing the precharge

command PREpb is received at the rising edge R of the clock signal CK, the flipflop **451** may output the first decoding result DR1 corresponding to the high level H. For example, when the row command representing the precharge command PREpb is not received at the rising edge R of the clock signal CK, the flipflop **451** may output the first decoding result DR1 corresponding to a low level L.

(134) The flipflop **452** may receive a signal obtained by inverting the clock signal CK by the inverter **445**. That is, the flipflop **452** may output the signal value input to the input terminal D based on the falling edge F of the clock signal CK to the output terminal Q as the second decoding result DR2. For example, when the row command representing the precharge command PREpb is received at the falling edge F of the clock signal CK, the flipflop **452** may output the second decoding result DR2 corresponding to a high level H. For example, when the row command representing the precharge command PREpb is not received at the falling edge F of the clock signal CK, the flipflop **452** may output the second decoding result DR2 corresponding to a low level L.

(135) The OR gate **453** may output an internal command iCMD representing the precharge command PREpb by comparing the first decoding result DR1 or the second decoding result DR2. For example, when the first decoding result DR1 or the second decoding result DR2 is at a high level H (that is, when the row command represents the precharge command PREpb), the OR gate **453** may output the internal command iCMD at a high level H, which indicates that the precharge command PREpb is sensed.

(136) The control logic circuit **440** illustrated in FIG. **13** is only an example. The inventive concept is not limited thereto. For example, the control logic circuit **440** may include a plurality of logic gates capable of performing a first logical operation (e.g., a logical AND operation) instead of the NAND gate **448** or **449** or a plurality of logic gates capable of performing a second logical operation (e.g., a logical OR operation) instead of the OR gate **453**.

(137) FIG. **14** is a view illustrating a semiconductor package **1000** according to an example embodiment of the inventive concept. Referring to FIG. **14**, the semiconductor package **1000** may include a stacked memory device **1100**, a system on chip (SoC) **1200**, an interposer **1300**, and a package substrate **1400**. The stacked memory device **1100** may include a buffer die **1110** and core dies **1120** to **1150**. The stacked memory device **1100** may correspond to stacked memory devices **300**, **400**, **400a**, and **400b** described with reference to FIGS. **7** to **13**.

(138) Each of the core dies **1120** to **1150** may include memory cells for storing data. The buffer die **1110** may include a physical layer **1111** and direct access areas DAB and **1112**. The physical layer **1111** may be electrically connected to a physical layer **1210** of the SoC **1200** through the interposer **1300**. The stacked memory device **1100** may receive or transmit signals from or to the SoC **1200** through the physical layer **1111**. The physical layer **1111** may include the memory interface circuit **411** of the buffer die **410** described with reference to FIGS. **8** to **10**.

(139) The direct access area **1112** may provide an access route capable of testing the stacked memory device **1100** without through the SoC **1200**. The direct access area **1112** may include a conductive unit (e.g., a port or a pin) capable of directly communicating with an external test device. A test signal received through the direct access area **1112** may be transmitted to the core dies **1120** to **1150** through TSVs **1101**. The data read from the core dies **1120** to **1150** for testing the core dies **1120** to **1150** may be transmitted to the external test device through the TSVs **1101** and the direct access area **1112**. Therefore, a direct access test for the core dies **1120** to **1150** may be performed.

(140) The buffer die **1110** and the core dies **1120** to **1150** may be electrically connected to each other through the TSVs **1101** and bumps **1102**. The buffer die **1110** may receive the signals respectively provided from the SoC **1200** to channels through the bumps **1102** assigned to the channels or may transmit the signals to the SoC **1200** through the bumps **1102**. For example, the bumps **1102** may be microbumps.

(141) The SoC **1200** may execute applications supported by the semiconductor package **1000** by

using the stacked memory device **1100**. For example, the SoC **1200** may execute specialized operations including at least one processor among a central processing unit (CPU), an application processor (AP), a graphics processing unit (GPU), a neural processing unit (NPU), a tensor processing unit (TPU), a vision processing unit (VPU), an image signal processor (ISP), and a digital signal processor (DSP).

(142) The SoC **1200** may control an overall operation of the stacked memory device **1100**. The SoC **1200** may correspond to the memory controller **100** of FIG. **1**. The SoC **1200** may include a physical layer **1210**. The physical layer **1210** may include an interface circuit for transmitting and receiving the signals to and from the physical layer **1111** of the stacked memory device **1100**. For example, the physical layer **1210** may include the host interface circuit **110** of FIG. **1**. The SoC **1200** may provide various signals to the physical layer **1111** through the physical layer **1210**. The signals provided to the physical layer **1111** may also be transmitted to the core dies **1120** to **1150** through an interface circuit of the physical layer **1111** and the TSVs **1101**.

(143) The interposer **1300** may connect the stacked memory device **1100** to the SoC **1200**. The interposer **1300** may connect the physical layer **1111** of the stacked memory device **1100** to the physical layer **1210** of the SoC **1200** and may provide physical routes formed by using conductive materials. Therefore, the stacked memory device **1100** and the SoC **1200** may be stacked on the interposer **1300** and may transmit and receive the signals to and from each other.

(144) Bumps **1103** may be attached onto the package substrate **1400**, and solder balls **1104** may be attached under the package substrate **1400**. For example, the bumps **1103** may be flipchip bumps. The interposer **1300** may be stacked on the package substrate **1400** through the bumps **1103**. The semiconductor package **1000** may transmit and receive the signals to and from another external package or semiconductor devices through the solder balls **1104**. For example, the package substrate **1400** may be a printed circuit board (PCB).

(145) According to an example embodiment, the physical layer **1111** of the buffer die **1110** may receive the row commands and the column commands from the SoC **1200** through the bumps **1102** as described with reference to FIGS. **1** to **13**. The physical layer **1111** may receive a specific command (e.g., the precharge command PRE) among the row commands at the rising edge R or the falling edge F of the clock signal CK.

(146) FIG. **15** is a view illustrating an implementation example of a semiconductor package **2000** according to an example embodiment. Referring to FIG. **15**, the semiconductor package **2000** may include a plurality of stacked memory devices **2100** and an SoC **2200**. Each of the plurality of stacked memory devices **2100** may correspond to the stacked memory device **1100** of FIG. **14** and the SoC **2200** may correspond to the SoC **1200** of FIG. **14**. The plurality of stacked memory devices **2100** and the SoC **2200** may be stacked on an interposer **2300**, and the interposer **2300** may be stacked on a package substrate **2400**. The semiconductor package **2000** may transmit and receive signals to and from another external package or semiconductor devices through solder balls **2001** attached under the package substrate **2400**.

(147) Each of the plurality of stacked memory devices **2100** may be implemented based on the HBM standard. However, the inventive concept is not limited thereto. Each of the plurality of stacked memory devices **2100** may be implemented based on the GDDR standard, the HMC standard, or the wide I/O standard.

(148) The SoC **2200** may include at least one processor such as a CPU, an AP, a GPU, or an NPU and a plurality of memory controllers for controlling the plurality of stacked memory devices **2100**. The SoC **2200** may transmit and receive the signals to and from a corresponding stacked memory device through a memory controller.

(149) FIG. **16** is a view illustrating a semiconductor package **3000** according to another example embodiment. Referring to FIG. **16**, the semiconductor package **3000** may include a stacked memory device **3100**, a host die **3200**, and a package substrate **3300**. The stacked memory device **3100** may include a buffer die **3110** and core dies **3120** to **3150**. The buffer die **3110** may include a

physical layer **3111** for communicating with the host die **3200**, and each of the core dies **3120** to **3150** may include memory cells for storing data. The stacked memory device **3100** may correspond to the stacked memory devices **300**, **400**, **400a**, and **400b** described with reference to FIGS. 7 to 13. (150) The host die **3200** may include a physical layer **3210** for communicating with the stacked memory device **3100**. The physical layer **3111** and the physical layer **3210** may communicate with each other through TSVs **3001**. The host die **3200** may correspond to the memory controller **100** of FIG. 1, and the physical layer **3111** may correspond to the host interface circuit **110** of FIG. 1. The host die **3200** may include a processor for controlling an overall operation of the semiconductor package **3000** and executing an application supported by the semiconductor package **3000**. For example, the host die **3200** may include at least one processor such as a CPU, an AP, a GPU, or an NPU.

(151) The stacked memory device **3100** may be arranged on the host die **3200** based on the TSVs **3001** and may be vertically stacked on the host die **3200**. Therefore, the buffer die **3110**, the core dies **3120** to **3150**, and the host die **3200** may be electrically connected to each other through the TSVs **3001** and bumps **3002** without an interposer. For example, the bumps **3002** may be microbumps.

(152) Bumps **3003** may be attached onto the package substrate **3300** and solder balls **3004** may be attached under the package substrate **3300**. For example, the bumps **3003** may be flipchip bumps. The host die **3200** may be stacked on the package substrate **3300** through the bumps **3003**. The semiconductor package **3000** may transmit and receive signals to and from another external package or semiconductor devices through the solder balls **3004**.

(153) According to an example embodiment, the physical layer **3111** of the buffer die **3110** may receive the row commands and the column commands from the host die **3200** through the TSVs **3001** as described with reference to FIGS. 1 to 13. The physical layer **3111** may receive a specific command (e.g., the precharge command PRE) among the row commands at the rising edge R or the falling edge F of the clock signal CK.

(154) According to another embodiment, the stacked memory device **3100** may be implemented only by the core dies **3120** to **3150** without the buffer die **3110**. In this case, each of the core dies **3120** to **3150** may further include interface circuits for communicating with the host die **3200**. In this case, each of the core dies **3120** to **3150** may transmit and receive signals to and from the physical layer **3210** of the host die **3200** through the TSVs **3001**.

(155) FIG. 17 is a block diagram illustrating a computing system **4000** according to an example embodiment. The computing system **4000** may be implemented by one electronic device or may be dispersed into two or more electronic devices. For example, the computing system **4000** may be implemented by at least one of various electronic devices such as a desktop computer, a laptop computer, a tablet computer, a smart phone, a self-driving car, a digital camera, a wearable device, a healthcare device, a server system, a data center, a drone, a handheld game console, an Internet of Things (IoT) device, a graphics accelerator, and an artificial intelligence (AI) accelerator.

(156) Referring to FIG. 17, the computing system **4000** may include a host **4100**, an accelerator subsystem **4200**, and an interconnect **4300**. The host **4100** may control an overall operation of the accelerator subsystem **4200** and the accelerator subsystem **4200** may operate in accordance with control of the host **4100**. The host **4100** and the accelerator subsystem **4200** may be connected through the interconnect **4300**. Various signals and data may be transmitted and received between the host **4100** and the accelerator subsystem **4200** through the interconnect **4300**.

(157) The host **4100** may include a host processor **4110**, a host memory controller **4120**, host memory **4130**, and an interface circuit **4140**. The host processor **4110** may control an overall operation of the computing system **4000**. The host processor **4110** may control the host memory **4130** through the host memory controller **4120**. The host processor **4110** may control the accelerator subsystem **4200** connected through the interconnect **4300**. For example, the host processor **4110** may assign a work to the accelerator subsystem **4200** by transmitting a command to

the accelerator subsystem **4200**.

(158) The host processor **4110** may be a general purpose processor or a main processor performing general operations related to various operations of the computing system **4000**. For example, the host processor **4110** may be a CPU or an AP.

(159) The host memory **4130** may be main memory of the computing system **4000**. The host memory **4130** may store data processed by the host processor **4110** or data received from the accelerator subsystem **4200**. For example, the host memory **4130** may be implemented by DRAM. However, the inventive concept is not limited thereto. The host memory **4130** may include at least one of volatile memory such as SRAM and non-volatile memory such as flash memory, PRAM, RRAM, or MRAM.

(160) The interface circuit **4140** may be formed so that the host **4100** communicates with the accelerator subsystem **4200**. The host processor **4110** may transmit and receive control signals and data to and from the accelerator subsystem **4200** through the interface circuit **4140**. According to an example embodiment, the host processor **4110**, the host memory controller **4120**, and the interface circuit **4140** may be implemented by one chip.

(161) The accelerator subsystem **4200** may perform a specific function in accordance with control of the host **4100**. For example, the accelerator subsystem **4200** may perform operations specialized to a specific application in accordance with the control of the host **4100**. The accelerator subsystem **4200** may be physically or electrically connected to the hosts **4100** or may be implemented in various forms such as a module, a card, a package, a chip, and a device to be wired or wirelessly connected. For example, the accelerator subsystem **4200** may be implemented by a graphics card or an accelerator card. For example, the accelerator subsystem **4200** may be implemented based on a field programmable gate array (FPGA) or an application specific integrated circuit (ASIC).

(162) According to an example embodiment, the accelerator subsystem **4200** may be implemented based on at least one of various packaging techniques. For example, the accelerator subsystem **4200** may be implemented by a packaging technique such as ball grid arrays (BGAs), a multichip package (MCP), a system on package (SOP), a system in package (SIP), a package on package (POP), chip scale packages (CSPs), a wafer level package (WLP), or a panel level package (PLP). For example, partial or all components of the accelerator subsystem **4200** may be connected through copper-to-copper bonding. For example, partial or all components of the accelerator subsystem **4200** may be connected through an interposer such as a silicon interposer, an organic interposer, a glass interposer, or an active interposer. For example, partial or all components of the accelerator subsystem **4200** may be stacked based on a through silicon via (TSV). For example, partial or all components of the accelerator subsystem **4200** may be connected through a high speed linkage (e.g., a silicon bridge).

(163) The accelerator subsystem **4200** may include a dedicated processor **4210**, a local memory controller **4220**, local memory **4230**, and a host interface circuit **4240**. The dedicated processor **4210** may operate in accordance with control of the host processor **4110**. For example, the dedicated processor **4210** may read data from the local memory **4230** through the local memory controller **4220** in response to a command of the host processor **4110**. The dedicated processor **4210** may process data by performing an operation based on the read data. The dedicated processor **4210** may transmit the processed data to the host processor **4110** or may write the processed data in the local memory **4230**.

(164) The dedicated processor **4210** may perform operations specialized to a specific application based on a value stored in the local memory **4230**. For example, the dedicated processor **4210** may perform operations specialized to applications such as an AI, a streaming analysis, video transcoding, data indexing, data encoding/decoding, and data encryption. Therefore, the dedicated processor **4210** may process various forms of data such as image data, audio data, motion data, biometric data, and a key value. For example, the dedicated processor **4210** may include at least one of the GPU, the NPU, the TPU, the VPU, the ISP, and the DSP.

(165) The dedicated processor **4210** may include a processor core or a plurality of processor cores such as a dual core, a quad core, and a hexa core. According to an example embodiment, the dedicated processor **4210** may include a greater number of cores than the host processor **4110** for an operation specialized to parallelism. For example, the dedicated processor **4210** may include 1,000 or more cores.

(166) The local memory controller **4220** may control an overall operation of the local memory **4230**. According to an example embodiment, the local memory controller **4220** may perform error correction code (ECC) encoding and ECC decoding, may perform data verification by a cyclic redundancy check (CRC) method, or may perform data encryption and data decryption. The local memory controller **4220** may correspond to the memory controller **100** of FIG. **1**.

(167) The local memory **4230** may be exclusively used by the dedicated processor **4210**. The local memory **4230** may be implemented by DRAM. However, the inventive concept is not limited thereto. For example, the local memory **4230** may be implemented by at least one of the volatile memory such as the SRAM and the non-volatile memory such as the flash memory, the PRAM, the RRAM, or the MRAM. According to an example embodiment, the local memory **4230** may be mounted on a substrate together with the dedicated processor **4210** or may be implemented in various forms such as the chip, the package, the module, the card, and the device to be connected to the dedicated processor **4210** based on a separate connector. The local memory **4230** may correspond to the memory device **200** or the stacked memory device **300** or **400** described with reference to FIGS. **1** to **13**.

(168) According to an example embodiment, the local memory **4230** may include a logic circuit capable of performing some operations. The logic circuit may perform a linear operation, a comparison operation, a compression operation, a data conversion operation, and an arithmetic operation for data read from or to be written in the local memory **4230**. Therefore, a size of the data processed by the logic circuit may be reduced. When the size of the data is reduced, bandwidth efficiency between the local memory **4230** and the local memory controller **4220** may improve.

(169) The host interface circuit **4240** may be formed so that the accelerator subsystem **4200** communicates with the host **4100**. The accelerator subsystem **4200** may transmit and receive a control signal and data to and from the host **4100** through the host interface circuit **4240**. According to an example embodiment, the dedicated processor **4210**, the local memory controller **4220**, and the host interface circuit **4240** may be implemented by one chip.

(170) The interconnect **4300** may provide a data transmission path between the host **4100** and the accelerator subsystem **4200** and may function as a data bus or a data link. The data transmission path may be wired or wirelessly formed. The interface circuit **4140** and the host interface circuit **4240** may communicate through the interconnect **4300** based on a predetermined code. For example, the interface circuit **4140** and the host interface circuit **4240** may communicate based on one of various standards such as an advanced technology attachment (ATA), a serial ATA (SATA), an external SATA (e-SATA), a small computer small interface (SCSI), a serial attached SCSI (SAS), a peripheral component interconnection (PCI), a PCI express (PCIe), an NVM express (NVMe), an advanced extensible interface (AXI), an ARM microcontroller bus architecture (AMBA), an IEEE 1394, a universal 8 serial bus (USB), a secure digital (SD) card, a multi-media card (MMC), an embedded multi-media card (eMMC), a universal flash storage (UFS), a compact flash (CF), and a Gen-Z. Alternatively, the interface circuit **4140** and the host interface circuit **4240** may communicate based on a communication link among devices such as a coherent accelerator processor interface (openCAPI), cache coherent interconnect for accelerators (CCIX), a compute express link (CXL), and a NVLINK. Alternatively, the interface circuit **4140** and the host interface circuit **4240** may communicate based on a wireless communication technology such as a long term evolution (LTE), a 5G, an LTE-M, an NB-IoT, a LPWAN, a Bluetooth, a near field communication (NFC), a Zigbee, a Z-wave, or a WLAN.

(171) According to an example embodiment, the accelerator subsystem **4200** may further include a

sensor capable of sensing image data, audio data, motion data, biometric data, and peripheral environment information. According to an example embodiment, when the sensor is included in the accelerator subsystem **4200**, the sensor may be connected to other components (e.g., the dedicated processor **4210** and the local memory **4230**) based on the above-described packaging technique. The accelerator subsystem **4200** may process data sensed by the sensor based on specific operations.

(172) In FIG. **17**, it is illustrated that the dedicated processor **4210** uses one local memory **4230** through one local memory controller **4220**. However, the inventive concept is not limited thereto. For example, the dedicated processor **4210** may use a plurality of local memory components through one local memory controller **4220**. As another example, the dedicated processor **4210** may use local memory corresponding to each of a plurality of local memory controllers through the plurality of local memory controllers.

(173) While the inventive concept has been particularly shown and described with reference to embodiments thereof, it will be understood that various changes in form and details may be made therein without departing from the spirit and scope of the following claims.

Claims

1. A memory device comprising: a clock pin configured to receive a clock signal; row pins configured to receive a first active command and a first precharge command during a first time period, and receive a second active command and a second precharge command during a second time period; and column pins configured to receive a first column command during the first time period, and receive a second column command during the second time period, wherein during the first time period, the row pins are configured to receive the first active command during a first sub-period and receive the first precharge command during a second sub-period which starts at a timing corresponding to a rising edge of the clock signal after receiving the first active command, and the column pins are configured to receive the first column command during a third sub-period, wherein during the second time period, the row pins are configured to receive the second active command during a fourth sub-period and receive the second precharge command during a fifth sub-period which starts at a timing corresponding to a falling edge of the clock signal after receiving the second active command, and the column pins are configured to receive the second column command during a sixth sub-period, and wherein each of the first sub-period and the fourth sub-period corresponds to a first number of rising edges of the clock signal and a second number of falling edges of the clock signal, and the second number is different from the first number.
2. The memory device of claim 1, wherein the first number is 2 and the second number is 1.
3. The memory device of claim 1, wherein a first minimum time interval between the first active command and the first precharge command is different from a second minimum time interval between the second active command and the second precharge command.
4. The memory device of claim 3, wherein the first minimum time interval is greater than the second minimum time interval by a half (0.5) cycle of the clock signal.
5. The memory device of claim 1, wherein a number of row pins is 10 and a number of column pins is 8.
6. The memory device of claim 1, wherein the memory device is configured to communicate with an external host device based on a high bandwidth memory (HBM) interface.
7. The memory device of claim 1, wherein each of the first column command and the second column command is a read command or a write command.
8. The memory device of claim 1, wherein a length of each of the second sub-period and the fifth sub-period is a half (0.5) cycle of the clock signal.
9. A memory controller comprising: a clock pin configured to transmit a clock signal to a memory device; row pins configured to transmit a first active command for the memory device and a first

precharge command for the memory device during a first time period, and transmit a second active command for the memory device and a second precharge command for the memory device during a second time period; and column pins configured to transmit a first column command for the memory device during the first time period, and transmit a second column command for the memory device during the second time period, wherein during the first time period, the row pins are configured to transmit the first active command to the memory device during a first sub-period and transmit the first precharge command to the memory device during a second sub-period which starts at a timing corresponding to a rising edge of the clock signal after transmitting the first active command, and the column pins are configured to transmit the first column command to the memory device during a third sub-period, and wherein during the second time period, the row pins are configured to transmit the second active command to the memory device during a fourth sub-period and transmit the second precharge command to the memory device during a fifth sub-period which starts at a timing corresponding to a falling edge of the clock signal after transmitting the second active command, and the column pins are configured to transmit the second column command to the memory device during a sixth sub-period, and wherein each of the first sub-period and the fourth sub-period corresponds to a first number of rising edges of the clock signal and a second number of falling edges of the clock signal, and the second number is different from the first number.

10. The memory controller of claim 9, wherein the first number is 2 and the second number is 1.

11. The memory controller of claim 9, wherein a first minimum time interval between the first active command and the first precharge command is different from a second minimum time interval between the second active command and the second precharge command.

12. The memory controller of claim 11, wherein the first minimum time interval is greater than the second minimum time interval by a half (0.5) cycle of the clock signal.

13. The memory controller of claim 9, wherein each of the first column command and the second column command is a read command or a write command.

14. The memory controller of claim 9, wherein a length of each of the second sub-period and the fifth sub-period is a half (0.5) cycle of the clock signal.

15. A memory system comprising: a package substrate; an interposer stacked on the package substrate; a memory device stacked on the interposer, the memory device including a clock pin, row pins and column pins; and a memory controller stacked on the interposer, the memory controller configured to transmit a first row command to the memory device during a first time period, transmit a second row command to the memory device during a second time period, and transmit a clock signal to the memory device, wherein the interposer is configured to connect the memory device to the memory controller, wherein the memory device is configured to decode the first row command received through the row pins during the first time period, and decode the second row command received through the row pins during the second time period, wherein the first row command is transmitted during a first sub-period which starts at a timing corresponding to a rising edge of the clock signal, wherein the second row command is transmitted during a second sub-period which starts at a timing corresponding to a falling edge of the clock signal, and wherein the first row command corresponds to a first precharge command and the second row command corresponds to a second precharge command.

16. The memory system of claim 15, wherein during the first time period, the memory device is configured to receive a first active command through the row pins during a third sub-period, and receive the first precharge command during the first sub-period after receiving the first active command, and wherein during the second time period, the memory device is configured to receive a second active command through the row pins during a fourth sub-period, and receive the second precharge command during the second sub-period after receiving the second active command, wherein each of the third sub-period and the fourth sub-period corresponds to a first number of rising edges of the clock signal and a second number of falling edges of the clock signal, and the

second number is different from the first number.

17. The memory system of claim 16, wherein during the first time period, the memory device is further configured to receive a first column command through the column pins during a fifth sub-period, and wherein during the second time period, the memory device is further configured to receive a second column command through the column pins during a sixth sub-period.

18. The memory system of claim 16, wherein the first number is 2 and the second number is 1.

19. The memory system of claim 17, wherein each of the first column command and the second column command is a read command or a write command.

20. The memory system of claim 15, wherein a length of each of the first sub-period and the second sub-period is a half (0.5) cycle of the clock signal.
