

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12387695
Kind Code	B2
Date of Patent	August 12, 2025
Inventor(s)	Hu; Chonglin

Display panel and electronic device

Abstract

A display panel and an electronic device are provided by the present application. In the image display period of at least one frames under the first preset refresh mode, during the display period, the data line is configured to output display voltage to the pixel unit, during the vertical blanking stage, the data line is configured to output compensation voltage to the pixel unit. When the display voltage is a positive polarity voltage, a voltage value of the display voltage is less than a voltage value of the compensation voltage, when the display voltage is a negative polarity voltage, the voltage value of the display voltage is greater than the voltage value of the compensation voltage.

Inventors:	Hu; Chonglin (Guangdong, CN)
Applicant:	SHENZHEN CHINA STAR OPTOELECTRONICS SEMICONDUCTOR DISPLAY TECHNOLOGY CO., LTD. (Guangdong, CN)
Family ID:	78493234
Assignee:	Shenzhen China Star Optoelectronics Semiconductor Ltd. (Shenzhen, CN)
Appl. No.:	17/600444
Filed (or PCT Filed):	September 06, 2021
PCT No.:	PCT/CN2021/116583
PCT Pub. No.:	WO2023/029020
PCT Pub. Date:	March 09, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240331655 A1	Oct. 03, 2024

Foreign Application Priority Data

CN202111004841.6Aug. 30, 2021

Publication Classification

Int. Cl.: G09G3/36 (20060101)

U.S. Cl.:

CPC G09G3/3696 (20130101); G09G3/3607 (20130101); G09G3/3614 (20130101); G09G3/3648 (20130101); G09G2310/061 (20130101); G09G2320/0247 (20130101); G09G2320/045 (20130101); G09G2340/0435 (20130101)

Field of Classification Search

CPC: G09G (3/3648); G09G (3/3614); G09G (3/36)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5798740	12/1997	Bitzakidis et al.	N/A	N/A
7477223	12/2008	Sekiguchi et al.	N/A	N/A
10535287	12/2019	Wang	N/A	G09G 3/20
10777140	12/2019	Kim et al.	N/A	N/A
2003/0112213	12/2002	Noguchi	345/96	G09G 3/3614
2013/0106824	12/2012	Yamauchi	345/92	G09G 5/00
2015/0138249	12/2014	Miyata et al.	N/A	N/A
2018/0074569	12/2017	An et al.	N/A	N/A
2019/0335553	12/2018	Ahmed	N/A	G09G 3/32
2023/0267865	12/2022	Ying	345/212	G09G 3/20
2024/0363084	12/2023	Tian	N/A	G09G 3/3648

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
111341258	12/2015	CN	N/A
107464540	12/2016	CN	N/A
107871474	12/2017	CN	N/A
110164350	12/2018	CN	N/A
110570828	12/2018	CN	N/A
110827756	12/2019	CN	N/A
111061085	12/2019	CN	N/A
111243480	12/2019	CN	N/A
112365856	12/2020	CN	N/A
112530351	12/2020	CN	N/A
112767867	12/2020	CN	N/A
113178157	12/2020	CN	N/A
4487024	12/2009	JP	N/A

OTHER PUBLICATIONS

CN113178157A Display device with variable refresh frequency, display method thereof and clock control board Apr. 8, 2021 Zhang Weiwei; Jin Yikun; Chen Yongquan (Year: 2021). cited by examiner

International Search Report and the Written Opinion Dated Jan. 19, 2024 From the International Searching Authority Re. Application No. PCT/CN2021/116583 and Its Translation Into English. (13 Pages). cited by applicant

Notification of Decision of Rejection Dated Dec. 5, 2022 From The State Intellectual Property Office of the People's Republic of China Re. Application No. 202111004841.6 and Its Translation Into English. (18 Pages). cited by applicant

Notification of Office Action and Search Report Dated Mar. 9, 2022 From The State Intellectual Property Office of the People's Republic of China Re. Application No. 202111004841.6 and Its Translation Into English. (18 Pages). cited by applicant

Notification of Office Action Dated Aug. 29, 2022 From The State Intellectual Property Office of the People's Republic of China Re. Application No. 202111004841.6 and Its Translation Into English. (18 Pages). cited by applicant

Primary Examiner: Chow; Van N

Background/Summary**CROSS-REFERENCE TO RELATED APPLICATIONS**

(1) This application is a National Phase of PCT Patent Application No. PCT/CN2021/116583 having International filing date of Sep. 6, 2021, which claims the benefit of priority of Chinese Patent Application No. 202111004841.6 filed on Aug. 30, 2021. The contents of the above applications are all incorporated by reference as if fully set forth herein in their entirety.

TECHNICAL FIELD

(2) The present application relates to display technical field, and particularly to a display panel and an electronic device.

BACKGROUND

(3) Most existing Timer Control Registers (TCONs) support a Variable Refresh Rate (VRR) function, which means that refresh rate of display panels is dynamically adjusted by changing the duration of Vertical Blanking (VBlank) period in a frame period of the display panels to match the refresh rate of graphics cards, so as to solve the problems of tearing and fluctuation of images displayed by the display panels and improve smoothness of images.

(4) However, when refresh frequency is relatively low, vertical blanking stage of the frame cycle will maintain a certain duration, during which the display panels generate leakage current, which affects display quality.

SUMMARY

(5) A display panel and an electronic device are provided by the present application, which can compensate leakage current generated by display panels during vertical blanking stage.

(6) A display panel is provided, including: a data line; a pixel unit connected to the data line, wherein the data line is configured to output a data voltage to the pixel unit during an image display period of each frame, the image display period includes a display period and a vertical blanking stage; under a first preset refresh mode, during the image display period of at least one frames, the data voltage includes a display voltage and a compensation voltage; during the display period, the

data line outputs the display voltage to the pixel unit, during the vertical blanking stage, the data line outputs the compensation voltage to the pixel unit; when the display voltage is a positive polarity voltage, a voltage value of the display voltage is less than a voltage value of the compensation voltage, when the display voltage is a negative polarity voltage, the voltage value of the display voltage is greater than the voltage value of the compensation voltage.

(7) Optionally, in some embodiments of the present application, when the display voltage is a positive polarity voltage, the compensation voltage is a positive polarity voltage corresponding to the maximum display gray scale of the display panel; when the display voltage is a negative polarity voltage, the compensation voltage is a negative polarity voltage corresponding to the maximum display gray scale of the display panel;

(8) Optionally, in some embodiments of the present application, the voltage value of the compensation voltage is adjusted in real time according to the voltage value of the display voltage.

(9) Optionally, in some embodiments of the present application, a common voltage of the display panel is zero, an absolute value of the display voltage is less than an absolute value of the compensation voltage.

(10) Optionally, in some embodiments of the present application, the first preset refresh mode includes a first refresh mode and a second refresh mode, a refresh frequency of the first refresh mode is lower than a refresh frequency of the second refresh mode; under the first refresh mode, the data voltage includes a first display voltage and a first compensation voltage, during the display period, the data line outputs the first display voltage to the pixel unit, during the vertical blanking stage, the data line outputs the first compensation voltage to the pixel unit; when the display voltage is a positive polarity voltage, a voltage value of the first display voltage is less than a voltage value of the first compensation voltage, when the first display voltage is a negative polarity voltage, the voltage value of the first display voltage is greater than the voltage value of the first compensation voltage; under the second refresh mode, the data voltage includes a second display voltage and a second compensation voltage, during the display period, the data line outputs the second display voltage to the pixel unit, during the vertical blanking stage, the data line outputs the second compensation voltage to the pixel unit; when the display voltage is a positive polarity voltage, a voltage value of the second display voltage is less than a voltage value of the second compensation voltage, when the second display voltage is a negative polarity voltage, the voltage value of the second display voltage is greater than the voltage value of the second compensation voltage; wherein a voltage difference between the first compensation voltage and the first display voltage is greater a voltage difference between the second compensation voltage and the second display voltage.

(11) Optionally, in some embodiments of the present application, the display panel has a second preset refresh mode, a refresh frequency of the second preset refresh mode is higher than a refresh frequency of the first preset refresh mode; under the first preset refresh mode, each of the vertical blanking stage includes a first period and a second period, a duration of the second period is equal to a duration of the vertical blanking stage in the second preset refresh mode; during the first period, the data line outputs the compensation voltage to the pixel unit.

(12) Optionally, in some embodiments of the present application, the display panel has a second preset refresh mode, a refresh frequency of the second preset refresh mode is higher than a refresh frequency of the first preset refresh mode; under the second preset refresh mode, the data voltage includes a third display voltage and a third compensation voltage, during the display period, the data lines outputs the third display voltage to the pixel unit, during the vertical blanking stage, the data voltage outputs the third compensation voltage to the pixel unit; when the third display voltage is a positive polarity voltage, a voltage value of the third display voltage is greater than a positive polarity voltage corresponding to a minimum display gray scale, when the third display voltage is a negative polarity voltage, a voltage value of the third compensation voltage is less than a negative polarity voltage corresponding to the minimum display gray scale.

(13) Optionally, in some embodiments of the present application, the display panel includes a scanning line, the scanning line is configured to cross with the data line; during the vertical blanking stage, the scanning line is configured to output a reference low level voltage, and a voltage value of the reference low level voltage is greater than or less than a voltage value of a preset reference low level voltage.

(14) Optionally, in some embodiments of the present application, the first preset refresh mode includes a first refresh mode and a second refresh mode, a refresh frequency of the first refresh mode is lower than a refresh frequency of the second refresh mode; under the first refresh mode, during the vertical blanking stage, the scanning line is configured to output a first reference low level voltage, under the second refresh mode, during the vertical blanking stage, the scanning line is configured to output a second reference low level voltage; both a voltage value of the first reference low level voltage and a voltage value of the second reference low level voltage are greater or less than the voltage value of the preset reference low level voltage.

(15) Optionally, in some embodiments of the present application, the voltage value of the first reference low level voltage is equal to the voltage value of the second reference low level voltage.

(16) Optionally, in some embodiments of the present application, when both the voltage value of the first reference low level voltage and the voltage value of the second reference low level voltage are less than the voltage value of the preset reference low level voltage, the voltage value of the first reference low level voltage is less than the voltage value of the second reference low level voltage; when both the voltage value of the first reference low level voltage and the voltage value of the second reference low level voltage are greater than the voltage value of the preset reference low level voltage, the voltage value of the first reference low level voltage is greater than the voltage value of the second reference low level voltage.

(17) Correspondingly, an electronic device is also provided by the present application, including the display panel and a driving device, the driving device is configured to provide a data voltage to the display panel, wherein the display panel includes a data line; a pixel unit connected to the data line, wherein the data line is configured to output a data voltage to the pixel unit during an image display period of each frame, the image display period includes a display period and a vertical blanking stage; under a first preset refresh mode, during the image display period of at least one frame, the data voltage includes a display voltage and a compensation voltage; during the display period, the data line outputs the display voltage to the pixel unit, during the vertical blanking stage, the data line outputs the compensation voltage to the pixel unit; when the display voltage is a positive polarity voltage, a voltage value of the display voltage is less than a voltage value of the compensation voltage, when the display voltage is a negative polarity voltage, the voltage value of the display voltage is greater than the voltage value of the compensation voltage.

(18) Optionally, in some embodiments of the present application, when the display voltage is a positive polarity voltage, the compensation voltage is a positive polarity voltage corresponding to the maximum display gray scale of the display panel; when the display voltage is a negative polarity voltage, the compensation voltage is a negative polarity voltage corresponding to the maximum display gray scale of the display panel;

(19) Optionally, in some embodiments of the present application, the voltage value of the compensation voltage is adjusted in real time according to the voltage value of the display voltage.

(20) Optionally, in some embodiments of the present application, a common voltage of the display panel is zero, an absolute value of the display voltage is less than an absolute value of the compensation voltage.

(21) Optionally, in some embodiments of the present application, the first preset refresh mode includes a first refresh mode and a second refresh mode, a refresh frequency of the first refresh mode is lower than a refresh frequency of the second refresh mode; under the first refresh mode, the data voltage includes a first display voltage and a first compensation voltage, during the display period, the data line outputs the first display voltage to the pixel unit, during the vertical blanking

stage, the data line outputs the first compensation voltage to the pixel unit; when the display voltage is a positive polarity voltage, a voltage value of the first display voltage is less than a voltage value of the first compensation voltage, when the first display voltage is a negative polarity voltage, the voltage value of the first display voltage is greater than the voltage value of the first compensation voltage; under the second refresh mode, the data voltage includes a second display voltage and a second compensation voltage, during the display period, the data line outputs the second display voltage to the pixel unit, during the vertical blanking stage, the data line outputs the second compensation voltage to the pixel unit; when the display voltage is a positive polarity voltage, a voltage value of the second display voltage is less than a voltage value of the second compensation voltage, when the second display voltage is a negative polarity voltage, the voltage value of the second display voltage is greater than the voltage value of the second compensation voltage; wherein a voltage difference between the first compensation voltage and the first display voltage is greater a voltage difference between the second compensation voltage and the second display voltage.

(22) Optionally, in some embodiments of the present application, the display panel has a second preset refresh mode, a refresh frequency of the second preset refresh mode is higher than a refresh frequency of the first preset refresh mode; under the first preset refresh mode, each of the vertical blanking stage includes a first period and a second period, a duration of the second period is equal to a duration of the vertical blanking stage in the second preset refresh mode; during the first period, the data line outputs the compensation voltage to the pixel unit.

(23) Optionally, in some embodiments of the present application, the display panel has a second preset refresh mode, a refresh frequency of the second preset refresh mode is higher than a refresh frequency of the first preset refresh mode; under the second preset refresh mode, the data voltage includes a third display voltage and a third compensation voltage, during the display period, the data lines outputs the third display voltage to the pixel unit, during the vertical blanking stage, the data voltage outputs the third compensation voltage to the pixel unit; when the third display voltage is a positive polarity voltage, a voltage value of the third display voltage is greater than a positive polarity voltage corresponding to a minimum display gray scale, when the third display voltage is a negative polarity voltage, a voltage value of the third compensation voltage is less than a negative polarity voltage corresponding to the minimum display gray scale.

(24) Optionally, in some embodiments of the present application, the display panel includes a scanning line, the scanning line is configured to cross with the data line; during the vertical blanking stage, the scanning line is configured to output a reference low level voltage, and a voltage value of the reference low level voltage is greater than or less than a voltage value of a preset reference low level voltage.

(25) Optionally, in some embodiments of the present application, the first preset refresh mode includes a first refresh mode and a second refresh mode, a refresh frequency of the first refresh mode is lower than a refresh frequency of the second refresh mode; under the first refresh mode, during the vertical blanking stage, the scanning line is configured to output a first reference low level voltage, under the second refresh mode, during the vertical blanking stage, the scanning line is configured to output a second reference low level voltage; both a voltage value of the first reference low level voltage and a voltage value of the second reference low level voltage are greater or less than the voltage value of the preset reference low level voltage.

(26) A display panel and an electronic device are provided by the present application. The display panel includes a data line and a pixel unit connected to the data line. Wherein, the data line is configured to output data voltage to the pixel unit during the image display period of each frame. The image display period includes a display period and a vertical blanking stage. In the image display period of at least one frames under the first preset refresh mode, during the display period, the data line is configured to output display voltage to the pixel unit, and during the vertical blanking stage, the data line is configured to output compensation voltage to the pixel unit. And

when the display voltage is a positive polarity voltage, a voltage value of the display voltage is less than a voltage value of the compensation voltage, when the display voltage is a negative polarity voltage, the voltage value of the display voltage is greater than the voltage value of the compensation voltage. Thus, compensation for leakage generated by the display panel during the vertical blanking stage is provided by means of micro charging, improving the display effect of the display panel.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) In order to more clearly illustrate the technical solution of this disclosure, a brief description of the drawings that are necessary for the illustration of the embodiments will be given as follows. Obviously, the drawings described below show only some embodiments of this disclosure, and a person having ordinary skill in the art may also obtain other drawings based on the drawings described without making any creative effort.
- (2) FIG. 1 is a structural schematic diagram of a display panel provided by the present application.
- (3) FIG. 2 is a structural schematic diagram of an image display period of the display panel provided by the present application.
- (4) FIG. 3 is a first sequence diagram of a driving signal of the display panel provided by the present application.
- (5) FIG. 4 is a second sequence diagram of the driving signal of the display panel provided by the present application.
- (6) FIG. 5 is a third sequence diagram of the driving signal of the display panel provided by the present application.
- (7) FIG. 6 is a fourth sequence diagram of the driving signal of the display panel provided by the present application.
- (8) FIG. 7 is a fifth sequence diagram of the driving signal of the display panel provided by the present application.
- (9) FIG. 8 is a schematic diagram of a leakage current curve of an N-type transistor provided by the present application.
- (10) FIG. 9 is a sixth sequence diagram of the driving signal of the display panel provided by the present application.
- (11) FIG. 10 is a seventh sequence diagram of the driving signal of the display panel provided by the present application.
- (12) FIG. 11 is a structural schematic diagram of an electronic device provided by the present application.

DETAILED DESCRIPTION

(13) The present disclosure is further described in detail below with reference to the accompanying drawings and embodiments. A person having ordinary skill in the art may obtain other embodiments based on the embodiments provided in the present application without making any creative effort, which all belong to the scope of the present application. In addition, it should be understood that the specific embodiments described herein are only used to illustrate and explain the present application and are not used to limit the present application. In addition, the terms “first” and “second” are only used for descriptive purposes and cannot be understood as indicating or implying relative importance or implicitly indicating the number of indicated technical features. Thus, the features defining “first” and “second” may explicitly or implicitly include one or more of the features.

(14) A display panel and an electronic device are provided by the present application, which are described in detail. It should be noted that the order of description of the following embodiments is

not a limitation of the preferred order of the embodiments of the present application.

(15) Please refer to FIG. 1 to FIG. 3, FIG. 1 is a structural schematic diagram of a display panel provided by the present application. FIG. 2 is a structural schematic diagram of an image display period of the display panel provided by the present application. FIG. 3 is a first sequence diagram of a driving signal of the display panel provided by the present application.

(16) Wherein, a display panel **100** includes a data line **11** and a pixel unit **20**. The pixel unit **20** is connected to the data line **11**. The data line **11** is configured to output data voltage to the pixel unit **20** during an image display period of each frame. The image display period includes a display period AA and a vertical blanking stage VB. Under a first preset refresh mode, during the image display period of at least one frames, the data voltage includes a display voltage D and a compensation voltage V. During the display period AA, the data line **11** outputs the display voltage D to the pixel unit **20**. During the vertical blanking stage VB, the data line **11** outputs the compensation voltage V to the pixel unit **20**. When the display voltage D is a positive polarity voltage, a voltage value of the display voltage D is less than a voltage value of the compensation voltage V. When the display voltage D is a negative polarity voltage, the voltage value of the display voltage D is greater than the voltage value of the compensation voltage V.

(17) Specifically, the display panel **100** further includes a scanning line **12**. The pixel unit **20** is defined by the crossed data line **11** and scanning line **12**. The pixel unit **20** includes a transistor **21** and a pixel electrode **22**. A control terminal of the transistor **21** is connected to the scanning line **12**. An input terminal of the transistor **21** is connected to the data line **11**. An output terminal of the transistor **21** is connected to the pixel electrode **22**. This is a well-known technology to those skilled in the art and will not be described here.

(18) Wherein, during the image displaying of the display panel **100**, refresh speed of display images is decided by refresh rate. Wherein, the higher the refresh rate, the higher the refresh speed of display image is, namely, the more frequently the display images are switched.

(19) Wherein, numbers of the data lines **11**, the scanning lines **12** and the pixel units **20** can be designed according to size and resolution of the display panel **100**. The data line **11** and the scanning line **12** can cross to each other vertically, or only cross to each other but not vertically. The accompanying drawings are only examples and cannot be understood as limitation to the present application. Besides, 1G1D (one gate one data, one gate line with one data line) driving architecture can be applied in the display panel **100** provided by the present application, but the present application is not limited to this. For example, HG2D (half gate two data, half gate electrode with two data lines) driving architecture can also be applied in the display panel **100** of the present application, which is no longer described in detail herein.

(20) Wherein, during the display period AA of each frame, the scanning line **12** is configured to output scanning signal. The scanning signal turns on the transistor **21**, so as to turn on the pixel unit **20** row-by-row. The data line **11** is configured to output data voltage to charge the corresponding pixel unit **20**. During the vertical blanking stage VB of each frame, all of the transistor **21** are turned off. The pixel unit **20** maintains the display image of current frame.

(21) Specifically, each frame of the display panel **100** includes the display period AA and the vertical blanking stage VB. During the display period AA of each frame, a plurality of data lines **11** are configured to output display data corresponding to each row of the pixel units **20** respectively, for example, red, green and blue (RGB) display voltage, so as to light all of the pixel units **20** within one frame. During the vertical blanking stage VB, the plurality of data lines **11** are configured to output blanking data corresponding to each row of the pixel units **20** respectively, for example, the blanking data corresponding to each row of the pixel units **20** are 0th gray scale signal (the minimum grayscale signal), namely, the black scale signal. Only when display data of the pixel units **20** in a same row of next frame comes, content of the pixel units **20** in right this row of last frame is overwritten. Therefore, in ideal conditions, during the vertical blanking stage VB, the potential of the pixel electrode **22** of each of the pixel units **20** maintains the potential of the display

voltage of current frame.

(22) However, due to the switching characteristics of the transistor **21**, the transistor **21** cannot be completely turned off during the vertical blanking stage VB of each frame, there will be certain leakage current. It can be understood that the display panel **100** is a liquid crystal display panel. When the liquid crystal display panel displays, brightness is determined by voltage difference applied to both sides of the liquid crystals. Voltage of one side of the liquid crystals is constant, which is a common voltage VCOM. Voltage of another side is the voltage of the pixel electrode **22**. When there is leakage current at the pixel electrode **22**, the voltage difference between the pixel electrode **22** and the common voltage VCOM will decrease, leading to a decrease in brightness of the pixel unit **20**. Besides, due to the characteristics of the liquid crystals, it is necessary to continuously and alternately provide positive and negative polarity voltages to the pixel unit **20**. Wherein, a voltage with a voltage value greater than the common voltage VCOM is defined as a positive polarity voltage, and a voltage with a voltage value less than the common voltage VCOM is defined as a negative polarity voltage.

(23) Thus, under the first preset refresh mode, during the image display period of at least one frames, when the display voltage D is a positive polarity voltage, a voltage value of the display voltage D is less than a voltage value of the compensation voltage V. A voltage of the input terminal of the transistor **21** is greater than a voltage of the output terminal of the transistor **21**, leakage current occurs from the input terminal of the transistor **21** to the output terminal. Potential of the pixel electrode **22** is increased by means of micro charging, the voltage difference between two sides of the liquid crystals is increased, and brightness of the pixel electrode **20** is increased. When the display voltage D is a negative polarity voltage, the voltage value of the display voltage D is configured to be greater than the voltage value of the compensation voltage V. The voltage of the input terminal of the transistor **21** is less than the voltage of the output terminal of the transistor **21**, leakage current occurs from the output terminal of the transistor **21** to the input terminal. Potential of the pixel electrode **22** is decreased, the voltage difference between two sides of the liquid crystals is increased similarly, and brightness of the pixel electrode **20** is increased. Thus, compensation is provided to the leakage current of the pixel electrode **22** during the vertical blanking stage VB, to improve display effect of the display panel **100**.

(24) It should be noted that as the source electrode and the drain electrode of the transistor are symmetric, the source electrode and the drain electrode can be interchangeable. In the present application, in order to distinguish the two electrodes of the transistor except the gate electrode, one of them is called the source electrode and the other one is called the drain electrode. In the present application, the control terminal of the transistor **21** is the gate electrode, the input terminal of the transistor **21** is the source electrode, and the output terminal of the transistor **21** is the drain electrode.

(25) Besides, the transistors applied in the present application can include P-type transistor and/or N-type transistor, wherein the P-type transistor is turned on when the gate electrode is low level, and is turned off when the gate electrode is high level, the N-type transistor is turned on when the gate electrode is high level, and is turned off when the gate electrode is low level. It should be noted that the transistors in the following embodiments of the present application are described by taking N-type transistors as examples, but they cannot be understood as limitations on the present application.

(26) It can be understood that the voltage value of the common voltage VCOM of the display panel **100** need to be designed according to display requirements to the display panel **100**. When the common voltage COM of the display panel **100** is 0, the absolute value of the display voltage D is less than the absolute value of the compensation voltage V.

(27) Certainly, the common voltage COM of the display panel **100** cannot be configured to be 0. For example, in some of the embodiments, the common voltage VCOM of the display panel **100** is configured to be 7V or other numbers, which needs to meet the requirement that when the display

voltage D is a positive polarity voltage, the voltage value of the display voltage D is less than the voltage value of the compensation voltage V. When the display voltage D is a negative polarity voltage, the voltage value of the display voltage D is greater than the voltage value of the compensation voltage V.

(28) In the present application, under the first preset frequency mode, compensation to leakage is only provided to the image display period of at least one frames to reduce the power consumption of the display panel **100**. Under the first preset frequency mode, compensation to leakage is provide to the image display period of all frames to ensure display brightness of the display panel **100** to the greatest extent under the first preset frequency mode. The following embodiments of the present application take that compensation to leakage is provided the pixel electrode **22** during the vertical blanking stage VB of the image display period of each frame as an example, but it cannot be understood as a limitation to the present application.

(29) In the present application, when the display voltage D is a positive polarity voltage, the compensation voltage V is a positive polarity voltage corresponding to the maximum display gray scale of the display panel **100**. When the display voltage D is a negative polarity voltage, the compensation voltage V is a negative polarity voltage corresponding to the maximum display gray scale of the display panel **100**.

(30) For example, if an image display data input to the display panel **100** is written binary 8 bit, eighth power of 2 brightness gray scales from the darkest to the brightest will be generated. Which is different brightness gray scales of 256 level (for example, it can be written as 0th gray scale to 255th gray scale). Wherein, it is assumed that the display brightness corresponding to the 255th gray scale is the maximum brightness, that is, the voltage value corresponding to the 255th gray scale is the greatest. Certainly, the image display data received by the display panel **100** of the present application can be written in binary 6 bit, binary 10 bit, etc. It should be noted that the present application are described by taking binary 8 bit as examples, but they cannot be understood as limitations to the present application.

(31) It can be understood that during the image display period of each frame under the first preset frequency mode, each of the pixel units **20** is corresponding to each of the display voltage D. The display voltage D can be any gray scale voltage from 0th gray scale to 255th gray scale. In the present application, the compensation voltage V is configured according to the maximum gray scale of the display panel **100**. For example, when the display voltage D is a positive polarity voltage, the compensation voltage V is configured as the positive polarity voltage corresponding to the maximum display gray scale of the display panel **100**, to ensure the voltage of the input terminal of each of the transistors **21** is greater than or equal to the voltage of the output terminal. Thus, leakage current is generated from the input terminal of the transistor **21** to the output terminal, so as to micro charge the pixel electrode **22**, and to increase potential of the pixel electrode **22**, so as to provide a compensation to the leakage of the pixel electrode **22** during the vertical blanking stage VB under the first refresh mode. Which is same when the display voltage D is a negative polarity voltage, which is no longer described in detail herein.

(32) In addition, taking the positive polarity voltage as an example, in the driving device of the display panel **100**, it is usually necessary to design a logic circuit to estimate and output the compensation voltage V corresponding to each of the pixel units **20**, so as to ensure that the voltage value of the compensation voltage V corresponding to each of the pixel units **20** is greater than the voltage value of corresponding display voltage D. In the present application, all of the compensation voltage V is configured as the positive polarity voltage corresponding to the maximum display gray scale of the display panel **100**. On one hand, the logic circuit can be simplified and the complexity of signals of the display panel **100** can be reduced. On the other hand, it is ensured that the voltage value of the compensation voltage V corresponding to each of the pixel units **20** is greater than the voltage value of corresponding display voltage D to achieve the compensation effect.

(33) Certainly, in other embodiments of the present application, the voltage value of the compensation voltage **V** can be real-time adjusted according to the voltage value of the display voltage **D**. Namely, the compensation voltage **V** can be configured against display voltage **D** corresponding to each of the pixel units **20**, as long as it is ensured that the voltage value of the compensation voltage **V** is greater than the voltage value of the display voltage **D** to lower the power consumption of the display panel **100**.

(34) In the present application, the first preset frequency mode can only include one refresh mode. Under the refresh mode, a compensation to leakage of the display panel **100** is provided by means of micro charge to improve the display brightness of the display panel **100**.

(35) Certainly, the first preset frequency mode can include a plurality of refresh mode. It can be understood that under different refresh frequency, the duration of the vertical blanking stage of image display period are different, which causes leakage current of different levels. Leakage current of different levels may induce different brightness in display image of the display panel. Therefore, when the frequency of the display panel changes, flickers will occur in the display panel.

(36) Hereto, please refer to FIG. 1 and FIG. 4, FIG. 4 is a second sequence diagram of the driving signal of the display panel provided by the present application. Difference between the display panel **100** of FIG. 4 and the display panel **100** of the FIG. 3 is that: in the embodiment, the first preset refresh mode includes a first refresh mode and a second refresh mode. A refresh frequency of the first refresh mode is lower than a refresh frequency of the second refresh mode.

(37) Wherein, under the first refresh mode, the data voltage includes a first data voltage **D1** and a first compensation voltage **V1**. During the display period **AA**, the data line **11** outputs the first display voltage **D1** to the pixel unit **20**. During the vertical blanking stage **VB**, the data line **11** outputs the first compensation voltage **V1** to the pixel unit **20**. When the first display voltage **D1** is a positive polarity voltage, a voltage value of the first display voltage **D1** is less than a voltage value of the first compensation voltage **V1**. When the first display voltage **D1** is a negative polarity voltage, the voltage value of the first display voltage **D1** is greater than the voltage value of the first compensation voltage **V1**.

(38) Wherein, under the second refresh mode, the data voltage includes a second data voltage **D2** and a second compensation voltage **V2**. During the display period **AA**, the data line **11** outputs the second display voltage **D2** to the pixel unit **20**. During the vertical blanking stage **VB**, the data line **11** outputs the second compensation voltage **V2** to the pixel unit **20**. When the second display voltage **D2** is a positive polarity voltage, a voltage value of the second display voltage **D2** is less than a voltage value of the second compensation voltage **V2**. When the second display voltage **D1** is a negative polarity voltage, the voltage value of the second display voltage **D2** is greater than the voltage value of the second compensation voltage **V2**.

(39) As the refresh frequency of the first refresh mode is lower than the refresh frequency of the second refresh mode, a duration of each vertical blanking stage **VB** of the first refresh mode is longer than a duration of each vertical blanking stage **VB** of the second refresh mode. The longer the duration of the vertical blanking stage, the longer the duration of the present display image of the display panel **100** is. And the longer the duration of which the voltage applied on the pixel electrode **22** is. At the same time, the worse the leakage current of the transistor **21** is. That is, the brightness of the pixel electrode **22** decreases more in the first refresh mode than in the second refresh mode.

(40) In addition, in addition to the leakage caused by incomplete close of the transistor **21**, there are other factors causing leakage in the display panel **100**, for example, light will also induce leakage, etc. Similarly, since the duration of the vertical blanking period **VB** of the first refresh mode is longer, compared to the second refresh mode, the pixel electrode **22** in the first refresh mode will also generate more leakage in the vertical blanking period **VB**.

(41) Therefore, compensation to leakage of the pixel electrode **22** is provide by means of micro

charge both in the first refresh mode and the second refresh mode in this embodiment, the potential difference of the pixel electrodes **22** under the first refresh mode and the second refresh mode induced by leakage of the transistor **21** can be reduced. At the same moment, compensation is provided to the pixel electrode **22** under the first refresh mode and the second refresh mode to achieve the balance between compensation and leakage, so as to improve the overall display effect of the display panel **100**.

(42) Furthermore, in some embodiments of the present application, a voltage difference between the first compensation voltage **V1** and the first display voltage **D1** is greater than a voltage difference between the second compensation voltage **V2** and the second display voltage **D2**.

(43) It can be understood that micro current compensation can be provided to the pixel electrode **22** according to the leakage characteristic of the transistor **21**. The greater the voltage difference between the input terminal and the output terminal of the transistor **21**, the greater the leakage current is, the better the compensation effect on the pixel electrode **22** is. Since the duration of each vertical blanking stage **VB** under the first refresh mode is longer, the leakage of the pixel electrode **22** under the first refresh mode is worse than the leakage of the pixel electrode **22** under the second refresh mode. Therefore, the voltage difference between the first compensation voltage **V1** and the first display voltage **D1** is configured to be greater than the voltage difference between the second compensation voltage **V2** and the second display voltage **D2**, charging to the pixel electrode **22** under the first refresh mode can be increased to improve the compensation to the pixel electrode **22** under the first refresh mode, so as to further reduce the brightness difference between display images of the display panel **100** under various refresh frequency.

(44) Certainly, in other embodiments of the present application, when there is a great brightness difference between the first refresh mode and the second refresh mode, the compensation can be provided to the pixel unit **20** only under the first refresh mode, to avoid flickers in images while switching images.

(45) In the present application, the duration of the display period **AA** under the first refresh mode and the second refresh mode are identical. Namely, the charging time to the pixel unit **20** under the first refresh mode and the second refresh mode are identical. Thus, the refresh frequency of the display panel **100** is dynamically adjusted by only changing the duration of the vertical blanking period **VB** in the frame cycle of the display panel **100**.

(46) Please refer to FIG. 1 and FIG. 5, FIG. 5 is a third sequence diagram of the driving signal of the display panel provided by the present application. Difference between the display panel **100** of FIG. 5 and the display panel **100** of the FIG. 3 is that: in the embodiment, the display panel has a second preset refresh mode. A refresh frequency of the second preset refresh mode is higher than the refresh frequency of the first preset refresh mode.

(47) Only in the vertical blanking stage **VB** of at least one frames under the first preset refresh mode, the compensation voltage **V** is provided to the pixel unit **20** in the present application, compensation to leakage of the pixel electrode **22** during the vertical blanking stage **VB** are provided by means of micro charge to decrease the brightness difference of the display panel **100** under the first preset refresh mode and the second preset refresh mode, to avoid flickers in images while switching images.

(48) Furthermore, please refer to FIG. 1 and FIG. 6, FIG. 6 is a fourth sequence diagram of the driving signal of the display panel provided by the present application. Difference between the display panel **100** of FIG. 6 and the display panel **100** of the FIG. 5 is that: in the embodiment, in the first preset refresh mode, each of the vertical blanking stage **VB** includes a first time period **T1** and a second time period **T2**. A duration of the second time period **T2** is equal to the duration of the vertical blanking stage **VB** under the second preset refresh mode. During the first time period **T1**, the data line **11** outputs the compensation voltage **V** to the pixel unit **20**.

(49) It can be understood that the leakage of the pixel electrode **22** under the first refresh mode and the second refresh mode are different, mainly because the duration of each of the vertical blanking

stage VB of the first refresh mode is longer than the duration of each of the vertical blanking stage VB of the second refresh mode. Therefore, a first compensation voltage V1 is configured for the data line 11 during the first time period T1 in this embodiment, and the duration of the second time period T2 is configured to be equal to the duration of each of the vertical blanking stage VB under the second refresh mode. On one hand, the duration of leakage of the pixel electrode 22 induced by the transistor 21 under the first preset refresh mode and the second preset refresh mode are identical, so as to reduce leakage difference caused by the transistor 21. On the other hand, micro charge compensation can be provided to the pixel electrode 22 during the first time period T1 to compensate the leakage of the pixel electrode 22 caused by other factors under the first refresh mode to further reduce leakage difference between the pixel electrode 22 under the preset first refresh mode and the second preset refresh mode, so as to reduce brightness difference of display images of the display panel 100 under different refresh frequency.

(50) Please refer to FIG. 1 and FIG. 7, FIG. 7 is a fifth sequence diagram of the driving signal of the display panel provided by the present application. Difference between the display panel 100 of FIG. 7 and the display panel 100 of the FIG. 5 is that: in the embodiment, under the second preset refresh mode, the data voltage includes a third display voltage D3 and a third compensation voltage V3. During the display period AA, the data line 11 outputs the third display voltage D3 to the pixel unit 20. In the vertical blanking stage VB, the data line 11 outputs the third compensation voltage V3 to the pixel unit 20.

(51) When the third display voltage D3 is a positive polarity voltage, a voltage value of the third compensation voltage V3 is greater than the positive polarity voltage corresponding to the minimum display gray scale of the display panel 100. When the third display voltage D3 is a negative polarity voltage, a voltage value of the third compensation voltage V3 is less than the negative polarity voltage corresponding to the minimum display gray scale of the display panel 100.

(52) It can be understood that, in the vertical blanking stage VB, the data lines are configured to output black gray scale signal to the pixel unit 20, namely, the minimum display gray scale of the display panel 100. Therefore, when the third display voltage D3 is a positive polarity voltage, the voltage value of the third compensation voltage V3 is configured to be greater than the positive polarity voltage corresponding to the minimum display gray scale of the display panel 100, which aggravates the leakage of the pixel electrode 22 during the vertical blanking stage VB. That is, by improving the leakage of the display panel 100 under the second preset refresh mode, the leakage difference of the pixel electrode 22 between the first preset refresh mode and the second preset refresh mode is reduced. Similarly, when the third display voltage D3 is a negative polarity voltage, the voltage value of the third compensation voltage V3 is configured to be less than the negative polarity voltage corresponding to the minimum display gray scale of the display panel 100, which aggravates the leakage of the pixel electrode 22 during the vertical blanking stage VB.

(53) Certainly, in other embodiments of the present application, in order to decrease power consumption of the display panel 100, when the brightness difference between the first refresh mode and the second refresh mode is relatively small, further compensation to leakage can only be provided to the pixel unit 20 under the second refresh mode, to reduce the leakage difference between the pixel electrode 22 under the first refresh mode and the second refresh mode.

(54) Furthermore, in the present application, during the vertical blanking stage VB of the image display period of each frame, the scanning line 12 outputs corresponding reference low level voltage to turn off the transistor 21. The potential of the reference low level voltage can be designed according to the switching characteristics of the transistor 21.

(55) Specifically, please refer to FIG. 8, FIG. 8 is a schematic diagram of a leakage current curve of an N-type transistor provided by the present application. Wherein, the abscissa is a voltage value of the reference low level voltage, in volts (V). The ordinate is the leakage current of the transistor 21, in ampere (I). As shown in FIG. 6, when the transistor 21 is turned off, it is not in a completely off

state, certain off state leakage current will still be generated. However, as to the transistor **21**, under the control of the preset reference low level voltage **V0**, the transistor **21** has a minimum leakage current.

(56) Hereto, please refer to FIG. **1** and FIG. **9**, FIG. **9** is a fourth sequence diagram of the driving signal of the display panel provided by the present application. Difference between the display panel **100** of FIG. **9** and the display panel **100** of the FIG. **6** is that: in the embodiment, during the vertical blanking stage VB of one frame, the data line **12** is configured to output the reference low level voltage **VSSG**. The voltage value of the reference low level voltage **VSSG** is greater than or less than a voltage value of a preset reference low level voltage **V0**.

(57) In this regard, it can be understood that the leakage of the transistor **21** is taken advantage, and micro charging compensation is provide to the pixel electrode **22** within the vertical blanking stage VB in the embodiment. As the preset reference low level voltage **V0** is corresponding to the minimum leakage current of the transistor **21**, the voltage value of the reference low level voltage **VSSG** is configured to be greater or less than the voltage value of the preset reference low level voltage **V0**, which improves the leakage of the transistor **21**, by improving the compensation to the potential of the pixel electrode **22**, the brightness of the display panel **100** is prevented from decreasing.

(58) It should be noted that the leakage current curve of a P-type transistor is similar to the leakage current curve of the N-type transistor, which will not be repeated here.

(59) Please refer to FIG. **1** and FIG. **10**, FIG. **10** is a fifth sequence diagram of the driving signal of the display panel provided by the present application. Difference between the display panel **100** of FIG. **10** and the display panel **100** of the FIG. **9** is that: in the embodiment, under the first preset refresh mode, during the vertical blanking stage VB of each frame, the data line **12** is configured to output the first reference low level voltage **VSSQ1**. Under the second preset refresh mode, during the vertical blanking stage VB of each frame, the data line **12** is configured to output the second reference low level voltage **VSSQ2**.

(60) Wherein, a voltage value of the first reference low level voltage **VSSQ1** is greater than or less than a voltage value of the preset reference low level voltage **V0**. A voltage value of the second reference low level voltage **VSSQ2** is greater than or less than the voltage value of the preset reference low level voltage **V0**.

(61) It can be known from the above analysis that under the driving of the preset reference low level voltage **V0**, the leakage current of the transistor **21** in the off state can be minimized.

Therefore, the voltage value of the first reference low level voltage **VSSQ1** is configured to be greater than or less than the voltage value of the preset reference low level voltage **V0** to improve the leakage of the transistor **21** during the vertical blanking stage VB under the first refresh mode. Similarly, the voltage value of the second reference low level voltage **VSSQ2** is configured to be greater than or less than the voltage value of the preset reference low level voltage **V0** to improve the leakage of the transistor **21** during the vertical blanking stage VB under the second refresh mode.

(62) Furthermore, in some embodiments of the present application, the voltage value of the first reference low level voltage **VSSQ1** and the voltage value of the second reference low level voltage **VSSQ2** are identical.

(63) It can be understood that in the driving device of the display panel **100**, it is usually necessary to design a logic circuit to output the corresponding reference low level voltage **VSSQ1** and reference low level voltage **VSSQ2**. The voltage value of the reference low level voltage **VSSQ1** and the voltage value of the reference low level voltage **VSSQ2** can be configured to be identical, so that the logic circuit can be simplified and the complexity of signals in the display panel **100** can be reduced.

(64) In some embodiments of the present application, both the voltage value of the first reference low level voltage **VSSQ1** and the voltage value of the second reference low level voltage **VSSQ2**

are less than the voltage value of the reference low level voltage VSSQ, and the voltage value of the first reference low level voltage VSSQ1 is less than the voltage value of the second reference low level voltage VSSQ2.

(65) It can be known from the analysis, when both the voltage value of the first reference low level voltage VSSQ1 and the voltage value of the second reference low level voltage VSSQ2 are less than the voltage value of the reference low level voltage V0, the voltage value of the first reference low level voltage VSSQ1 is configured to be less than the voltage value of the second reference low level voltage VSSQ2, the leakage current of the transistor 21 under the control of first reference low level voltage VSSQ1 is greater than the leakage current of the transistor 21 under the control of the second reference low level voltage VSSQ2.

(66) It can be understood that micro charging compensation can be provided to the pixel electrode 22 through the leakage of the transistor 21. The greater the leakage current of the transistor 21, the better the compensation effect is. As the leakage of the pixel electrode 22 under the first refresh mode is greater than the leakage of the pixel electrode 22 under the second refresh mode, the voltage value of the first reference low level voltage VSSQ1 is configured to be less than the voltage value of the second reference low level voltage VSSQ2, the charging to the pixel electrode 22 under the first refresh mode can be increased to improve the compensation to the pixel electrode 22 under the first refresh mode, so as to further reduce the brightness difference between display images of the display panel 100 under various refresh frequency.

(67) In some embodiments of the present application, both the voltage value of the first reference low level voltage VSSQ1 and the voltage value of the second reference low level voltage VSSQ2 are greater than the voltage value of the reference low level voltage V0, and the voltage value of the first reference low level voltage VSSQ1 is greater than the voltage value of the second reference low level voltage VSSQ2.

(68) It can be known from the analysis, when both the voltage value of the first reference low level voltage VSSQ1 and the voltage value of the second reference low level voltage VSSQ2 are greater than the voltage value of the reference low level voltage V0, the voltage value of the first reference low level voltage VSSQ1 is configured to be greater than the voltage value of the second reference low level voltage VSSQ2, the leakage current of the transistor 21 under the control of first reference low level voltage VSSQ1 is greater than the leakage current of the transistor 21 under the control of the second reference low level voltage VSSQ2.

(69) It can be understood that micro charging compensation can be provided to the pixel electrode 22 through the leakage of the transistor 21. The greater the leakage current of the transistor 21, the better the compensation effect is. As the leakage of the pixel electrode 22 under the first refresh mode is greater than the leakage of the pixel electrode 22 under the second refresh mode. Therefore, the voltage value of the first reference low level voltage VSSQ1 is configured to be greater than the voltage value of the second reference low level voltage VSSQ2, the charging to the pixel electrode 22 under the first refresh mode can be improved to increase the compensation to the pixel electrode 22 under the first refresh mode, so as to further reduce the brightness difference between display images of the display panel 100 under various refresh frequency.

(70) Correspondingly, an electric device is also provided by the present application, including a display panel and a driving device. The driving device is configured to provide driving signals to the display panel. The driving signals can be the reference low level voltage, the first display voltage, the first compensation voltage, the second display voltage, and the second compensation voltage, etc. The display panel is the display panel described in anyone of the above embodiments, which is no longer described in detail herein.

(71) The electronic device in the present application can be smart phone, tablet computer, video player, personal computer (PC), etc., which is not limited in the present application.

(72) Specifically, please refer to FIG. 11, FIG. 11 is a structural schematic diagram of an electric device provided by the present application. Wherein, the electronic device 1000 includes a display

panel **100** and a driving device **200**. The driving device **200** is configured to provide driving signals to the display panel.

(73) The driving device **200** includes, but is not limited to a timing controller **201**, a data driving circuit **202**, and a gate driving circuit **203**. Specifically, the timing controller **201** is configured to provide display data to the data driving circuit **202**. The data driving circuit **202** is configured to output the data voltage to the pixel unit **20** through the data line **11** during the display period of each frame. The data driving circuit **202** is also configured to output the compensation voltage to the pixel unit **20** through the data line **11** in the vertical blanking stage of each frame. The gate driving circuit **203** is used to output a scanning signal such as reference low level voltage to the scanning line **12**.

(74) Certainly, in other embodiments, an array substrate gate driver on array (GOA) can be integrated in the display panel **100** to replace the gate driver **203**, so as to realize a narrow frame.

(75) An electric device is also provided by the present application, including a display panel **100**. The display panel **100** includes a data line **11** and a pixel unit **20** connected to the data line **11**. Wherein, the data line **11** is configured to output data voltage to the pixel unit **20** during the image display period of each frame. The image display period includes a display period and a vertical blanking stage. In the image display period of at least one frames under the first preset refresh mode, during the display period, the data line **11** is configured to output display voltage to the pixel unit **20**, during the vertical blanking stage, the data line **11** is configured to output compensation voltage to the pixel unit **20**. And when the display voltage is a positive polarity voltage, a voltage value of the display voltage is less than a voltage value of the compensation voltage, when the display voltage is a negative polarity voltage, the voltage value of the display voltage is greater than the voltage value of the compensation voltage. Thus, compensation to the leakage generated by the display panel **100** in the vertical blanking stage is provided by means of micro charging, improving the display effect of the display panel. When the display panel **100** includes a plurality of refresh modes, the brightness difference in the display images of the display panel **100** under different refresh frequency is reduced to avoid image flickers while switching images.

(76) The display panel and electronic device provided by the present application are described in detail above. In this application, specific examples are applied to explain the principle and implementation mode of the application. The description of the above embodiments is only used to help understand the method and core idea of the application. At the same time, for those skilled in the art, according to the thought of the present disclosure, there will be changes in the specific embodiments and application scope. In conclusion, the content of the specification should not be understood as the limitation of the application.

Claims

1. A display panel, having a first preset refresh mode and a second preset refresh mode, and comprising: a data line; and a pixel unit connected to the data line, wherein the data line is configured to output a data voltage to the pixel unit during an image display period of each frame, the image display period comprises a display period and a vertical blanking stage; a refresh frequency of the second preset refresh mode is higher than a refresh frequency of the first preset refresh mode; under the first preset refresh mode, the vertical blanking stage comprises a first period and a second period, and a duration of the second period is equal to a duration of the vertical blanking stage under the second preset refresh mode; under the first preset refresh mode, during the image display period of at least one frames, the data voltage comprises a display voltage and a compensation voltage; during the display period, the data line outputs the display voltage to the pixel unit, during the first period of the vertical blanking stage, the data line outputs the compensation voltage to the pixel unit, and during the second period of the vertical blanking stage, the data line does not output the compensation voltage to the pixel unit; under the second preset

refresh mode, during the vertical blanking stage, the data line does not output the compensation voltage to the pixel unit; and when the display voltage is a positive polarity voltage, a voltage value of the display voltage is less than a voltage value of the compensation voltage, and when the display voltage is a negative polarity voltage, the voltage value of the display voltage is greater than the voltage value of the compensation voltage.

2. The display panel according to claim 1, wherein when the display voltage is a positive polarity voltage, the compensation voltage is a positive polarity voltage corresponding to a maximum display gray scale of the display panel; and when the display voltage is a negative polarity voltage, the compensation voltage is a negative polarity voltage corresponding to the maximum display gray scale of the display panel.

3. The display panel according to claim 1, wherein the voltage value of the compensation voltage is adjusted in real time according to the voltage value of the display voltage.

4. The display panel according to claim 1, wherein a common voltage of the display panel is zero, an absolute value of the display voltage is less than an absolute value of the compensation voltage.

5. The display panel according to claim 1, wherein the display panel comprises a scanning line, the scanning line is configured to cross with the data line; during the vertical blanking stage, the scanning line is configured to output a reference low level voltage, and a voltage value of the reference low level voltage is greater than or less than a voltage value of a preset reference low level voltage.

6. The display panel according to claim 5, wherein under the first preset refresh mode, during the vertical blanking stage, the scanning line is configured to output a first reference low level voltage, and under the second preset refresh mode, during the vertical blanking stage, the scanning line is configured to output a second reference low level voltage; both a voltage value of the first reference low level voltage and a voltage value of the second reference low level voltage are greater or less than the voltage value of the preset reference low level voltage.

7. The display panel according to claim 6, wherein the voltage value of the first reference low level voltage is equal to the voltage value of the second reference low level voltage.

8. The display panel according to claim 6, when both the voltage value of the first reference low level voltage and the voltage value of the second reference low level voltage are less than the voltage value of the preset reference low level voltage, the voltage value of the first reference low level voltage is less than the voltage value of the second reference low level voltage; when both the voltage value of the first reference low level voltage and the voltage value of the second reference low level voltage are greater than the voltage value of the preset reference low level voltage, the voltage value of the first reference low level voltage is greater than the voltage value of the second reference low level voltage.

9. An electronic device, comprising the display panel and a driving device, the driving device is configured to provide a data voltage to the display panel, wherein the display panel has a first preset refresh mode and a second preset refresh mode, and comprises: a data line; and a pixel unit connected to the data line, wherein the data line is configured to output a data voltage to the pixel unit during an image display period of each frame, the image display period comprises a display period and a vertical blanking stage; a refresh frequency of the second preset refresh mode is higher than a refresh frequency of the first preset refresh mode; under the first preset refresh mode, the vertical blanking stage comprises a first period and a second period, and a duration of the second period is equal to a duration of the vertical blanking stage under the second preset refresh mode; under the first preset refresh mode, during the image display period of at least one frames, the data voltage comprises a display voltage and a compensation voltage; during the display period, the data line outputs the display voltage to the pixel unit, during the first period of the vertical blanking stage, the data line outputs the compensation voltage to the pixel unit, and during the second period of the vertical blanking stage, the data line does not output the compensation voltage to the pixel unit; under the second preset refresh mode, during the vertical blanking stage, the data line does not

output the compensation voltage to the pixel unit; and when the display voltage is a positive polarity voltage, a voltage value of the display voltage is less than a voltage value of the compensation voltage, and when the display voltage is a negative polarity voltage, the voltage value of the display voltage is greater than the voltage value of the compensation voltage.

10. The electronic device according to claim 9, wherein when the display voltage is a positive polarity voltage, the compensation voltage is a positive polarity voltage corresponding to a maximum display gray scale of the display panel; and when the display voltage is a negative polarity voltage, the compensation voltage is a negative polarity voltage corresponding to the maximum display gray scale of the display panel.

11. The electronic device according to claim 9, wherein the voltage value of the compensation voltage is adjusted in real time according to the voltage value of the display voltage.

12. The electronic device according to claim 9, wherein a common voltage of the display panel is zero, an absolute value of the display voltage is less than an absolute value of the compensation voltage.

13. The electronic device according to claim 9, wherein the display panel comprises a scanning line, the scanning line is configured to cross with the data line; during the vertical blanking stage, the scanning line is configured to output a reference low level voltage, and a voltage value of the reference low level voltage is greater than or less than a voltage value of a preset reference low level voltage.

14. The electronic device according to claim 13, wherein under the first preset refresh mode, during the vertical blanking stage, the scanning line is configured to output a first reference low level voltage, and under the second preset refresh mode, during the vertical blanking stage, the scanning line is configured to output a second reference low level voltage; both a voltage value of the first reference low level voltage and a voltage value of the second reference low level voltage are greater or less than the voltage value of the preset reference low level voltage.

15. The electronic device according to claim 14, wherein the voltage value of the first reference low level voltage is equal to the voltage value of the second reference low level voltage.

16. The electronic device according to claim 14, when both the voltage value of the first reference low level voltage and the voltage value of the second reference low level voltage are less than the voltage value of the preset reference low level voltage, the voltage value of the first reference low level voltage is less than the voltage value of the second reference low level voltage; when both the voltage value of the first reference low level voltage and the voltage value of the second reference low level voltage are greater than the voltage value of the preset reference low level voltage, the voltage value of the first reference low level voltage is greater than the voltage value of the second reference low level voltage.

17. A display panel, having a first preset refresh mode, and comprising: a data line; a scanning line crossing with the data line; and a pixel unit connected to the data line and the scanning line, wherein the data line is configured to output a data voltage to the pixel unit during an image display period of each frame, the image display period comprises a display period and a vertical blanking stage; during the vertical blanking stage, the scanning line is configured to output a reference low level voltage, and a voltage value of the reference low level voltage is greater than or less than a voltage value of a preset reference low level voltage; under the first preset refresh mode, during the image display period of at least one frames, the data voltage comprises a display voltage and a compensation voltage, during the display period, the data line outputs the display voltage to the pixel unit, and during the vertical blanking stage, the data line outputs the compensation voltage to the pixel unit; when the display voltage is a positive polarity voltage, a voltage value of the display voltage is less than a voltage value of the compensation voltage, and when the display voltage is a negative polarity voltage, the voltage value of the display voltage is greater than the voltage value of the compensation voltage; the first preset refresh mode comprises a first refresh mode and a second refresh mode, a refresh frequency of the first refresh mode is lower than a refresh frequency

of the second refresh mode; under the first refresh mode, during the vertical blanking stage, the scanning line is configured to output a first reference low level voltage, under the second refresh mode, during the vertical blanking stage, the scanning line is configured to output a second reference low level voltage; both a voltage value of the first reference low level voltage and a voltage value of the second reference low level voltage are greater or less than the voltage value of the preset reference low level voltage.

18. The display panel according to claim 17, wherein the voltage value of the first reference low level voltage is equal to the voltage value of the second reference low level voltage.

19. The display panel according to claim 17, when both the voltage value of the first reference low level voltage and the voltage value of the second reference low level voltage are less than the voltage value of the preset reference low level voltage, the voltage value of the first reference low level voltage is less than the voltage value of the second reference low level voltage; when both the voltage value of the first reference low level voltage and the voltage value of the second reference low level voltage are greater than the voltage value of the preset reference low level voltage, the voltage value of the first reference low level voltage is greater than the voltage value of the second reference low level voltage.

20. The display panel according to claim 17, wherein under the first refresh mode, the data voltage comprises a first display voltage and a first compensation voltage, during the display period, the data line outputs the first display voltage to the pixel unit, during the vertical blanking stage, the data line outputs the first compensation voltage to the pixel unit; when the display voltage is a positive polarity voltage, a voltage value of the first display voltage is less than a voltage value of the first compensation voltage, when the first display voltage is a negative polarity voltage, the voltage value of the first display voltage is greater than the voltage value of the first compensation voltage; wherein under the second refresh mode, the data voltage comprises a second display voltage and a second compensation voltage, during the display period, the data line outputs the second display voltage to the pixel unit, during the vertical blanking stage, the data line outputs the second compensation voltage to the pixel unit; when the display voltage is a positive polarity voltage, a voltage value of the second display voltage is less than a voltage value of the second compensation voltage, when the second display voltage is a negative polarity voltage, the voltage value of the second display voltage is greater than the voltage value of the second compensation voltage; and wherein a voltage difference between the first compensation voltage and the first display voltage is greater a voltage difference between the second compensation voltage and the second display voltage.
