

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12388162
Kind Code	B2
Date of Patent	August 12, 2025
Inventor(s)	Sato; Takuya

Marchand balun formed in a laminated substrate and including a main line and sub-lines, where a parallel line is connected to a sub-line

Abstract

A balun includes an unbalanced terminal; first and second balanced terminals; first and second main lines; first and second sub-lines; and a parallel line. The first main line has an end connected to the unbalanced terminal. The second main line has an end connected to another end of the first and second end that is open. The first sub-line is connected between the first and a reference potential, and is coupled to the first main line. The second sub-line is connected between the second balanced terminal and the reference potential, and is coupled to the second main line. The parallel line is connected in parallel with a part of the first sub-line. The line length of a specific portion of the first sub-line that is connected in parallel with the parallel line is different from the line length of the parallel line.

Inventors:	Sato; Takuya (Kyoto, JP)
Applicant:	Murata Manufacturing Co., Ltd. (Kyoto, JP)
Family ID:	78525629
Assignee:	MURATA MANUFACTURING CO., LTD. (Kyoto, JP)
Appl. No.:	17/938160
Filed:	October 05, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230027154 A1	Jan. 26, 2023

Foreign Application Priority Data

JP	2020-084219	May. 13, 2020
----	-------------	---------------

Related U.S. Application Data

continuation parent-doc WO PCT/JP2021/016435 20210423 PENDING child-doc US 17938160

Publication Classification

Int. Cl.: H01P5/10 (20060101); H03H7/42 (20060101)

U.S. Cl.:

CPC H01P5/10 (20130101); H03H7/42 (20130101);

Field of Classification Search

CPC: H01P (5/10); H03H (7/42)

USPC: 333/26

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6133806	12/1999	Sheen	N/A	N/A
2006/0071738	12/2005	Yasuda et al.	N/A	N/A
2011/0102096	12/2010	Jeong et al.	N/A	N/A
2020/0220516	12/2019	Lin et al.	N/A	H03F 3/26

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1755978	12/2005	CN	N/A
2000-188218	12/1999	JP	N/A
2002-217670	12/2001	JP	N/A
2002-280221	12/2001	JP	N/A
2003-110314	12/2002	JP	N/A
2011-101341	12/2010	JP	N/A

OTHER PUBLICATIONS

International Search Report for PCT/JP2021/016435 dated Jul. 13, 2021. cited by applicant

Primary Examiner: Lee; Benny T

Attorney, Agent or Firm: McDonald Hopkins LLC

Background/Summary

CROSS REFERENCE TO RELATED APPLICATION (1) This is a continuation of International Application No. PCT/JP2021/016435 filed on Apr. 23, 2021 which claims priority from Japanese

BACKGROUND ART

Technical Field

(1) The present disclosure relates to baluns that convert signals between an unbalanced line and a balanced line, and more particularly to a structure for improving the characteristics of a laminated-type balun.

(2) Baluns are converters used for interconversion between an unbalanced signal and a balanced signal. A balanced signal includes a pair of signals having equal amplitude and phases that are inverted from each other, and is generally used in differential amplifier circuits in ICs in communication systems. In contrast, an unbalanced signal is a signal used in a transmission method that transmits changes in electric potential relative to ground potential, and input/output signals of a microstrip line or an antenna correspond to an unbalanced signal.

(3) For example, Japanese Unexamined Patent Application Publication No. 2002-280221 (Patent Document 1) discloses a so-called “Marchand balun” in which two lines having a length of $2/4$ and connected to a balanced line are coupled to a line connected to an unbalanced line and having a length of $\lambda/2$, which is $1/2$ of wavelength λ . Patent Document 1: Japanese Unexamined Patent Application Publication No. 2002-280221

BRIEF SUMMARY

(4) In a portable radio communication device represented by a smartphone, a mobile phone, or the like, a balun is used in a front-end circuit for connecting an unbalanced line of an antenna and a balanced line of an IC circuit that processes radio-frequency (RF) signals. In recent years, the frequency band of RF signals used for communication has been expanding, and individual components that form the device, such as a balun, are also required to handle a wider bandwidth. In addition, it is desirable to reduce power consumption by reducing losses in components forming each device, and to enable long-term operation with a certain amount of charge.

(5) The present disclosure improves the bandpass characteristic of a balun used in a communication device.

(6) A balun according to a first aspect of the present embodiment includes: an unbalanced terminal; a first balanced terminal and a second balanced terminal; a first main line and a second main line; a first sub-line and a second sub-line; and a parallel line. The first main line has a first end connected to the unbalanced terminal. The second main line has a first end connected to a second end of the first main line, and a second end that is open. The first sub-line is connected between the first balanced terminal and a reference potential, and is coupled to the first main line. The second sub-line is connected between the second balanced terminal and the reference potential, and is coupled to the second main line. The parallel line is connected in parallel with a part of the first sub-line. A line length of a specific portion of the first sub-line that is connected in parallel with the parallel line is different from a line length of the parallel line.

(7) A balun according to a second aspect of the present embodiment includes: a dielectric substrate in which a plurality of dielectric layers are laminated; an unbalanced terminal, a first balanced terminal, a second balanced terminal, and a reference potential terminal provided on the dielectric substrate; a first main line and a second main line; a first sub-line and a second sub-line; and a parallel line. The first main line has a first end connected to the unbalanced terminal. The second main line has a first end connected to a second end of the first main line, and a second end that is open. The first sub-line is connected between the first balanced terminal and a reference potential. The second sub-line is connected between the second balanced terminal and the reference potential. The parallel line is connected in parallel with a part of the first sub-line. In the dielectric substrate, the lines are arranged in an order of the first main line, the first sub-line, the parallel line, the second sub-line, and the second main line in a laminating direction. A line length of a specific

portion of the first sub-line that is connected in parallel with the parallel line is different from a line length of the parallel line.

(8) According to the balun according to the present disclosure, a parallel line connected in parallel with a part of the first sub-line coupled to the first main line connected to the unbalanced terminal is arranged. The line length of the parallel line is different from the line length of a specific portion of the first sub-line that is connected in parallel with the parallel line. By adopting such a configuration, the phase difference in the passband may be adjusted. Therefore, the improvement of bandpass characteristics of the balun may be realized.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a block diagram of a communication device provided with a front-end circuit to which a balun according to an embodiment is applied.

(2) FIG. 2 is an example of a circuit diagram of the balun in FIG. 1.

(3) FIG. 3 is a diagram describing the relationship between the line length of a first sub-line and the line length of a second line in FIG. 2.

(4) FIG. 4 is an external perspective view of the balun in FIG. 2.

(5) FIG. 5 is an exploded perspective view of the balun in FIG. 2.

(6) FIG. 6 is a circuit diagram of a balun of a first comparative example.

(7) FIG. 7 is a characteristic diagram for describing the comparison between the balun of the embodiment and the balun of the first comparative example.

(8) FIG. 8 is a circuit diagram of a balun of a second comparative example.

(9) FIG. 9 is a characteristic diagram for describing the comparison between the balun of the embodiment and the balun of the second comparative example.

(10) FIG. 10 is a circuit diagram of a balun of a third comparative example.

(11) FIG. 11 is a characteristic diagram for describing the comparison between the balun of the embodiment and the balun of the third comparative example.

(12) FIG. 12 is a circuit diagram of a balun of a fourth comparative example.

(13) FIG. 13 is a characteristic diagram for describing the comparison between the balun of the embodiment and the balun of the fourth comparative example.

(14) FIG. 14 is a circuit diagram of a balun of a fifth comparative example.

(15) FIG. 15 is a characteristic diagram for describing the comparison between the balun of the embodiment and the balun of the fifth comparative example.

(16) FIG. 16 is a circuit diagram of a balun of a sixth comparative example.

(17) FIG. 17 is a characteristic diagram for describing the comparison between the balun of the embodiment and the balun of the sixth comparative example.

DETAILED DESCRIPTION

(18) Hereinafter, an embodiment of the present disclosure will be described in detail with reference to the drawings. Note that the same or corresponding portions in the drawings will be given the same reference sign and the description thereof is not repeated.

(19) [Outline of Communication Device]

(20) FIG. 1 is a block diagram of a communication device 1 provided with a front-end circuit 10 to which a balun 100 according to the embodiment is applied. Referring to FIG. 1, the communication device 1 includes, in addition to the front-end circuit 10, an antenna ANT and an RFIC 20, which is a signal processing circuit.

(21) The RFIC 20 outputs a radio-frequency (RF) signal that is a transmission signal to a transmission-side line TX, and the output RF signal is emitted as radio waves from the antenna ANT via the front-end circuit 10. The RFIC 20 also receives radio waves received at the antenna

ANT as an RF signal that is a reception signal from a reception-side line RX, processes the reception signal, and transmits the processed reception signal to a subsequent circuit.

(22) The front-end circuit **10** includes, in addition to the balun **100**, a switch SW, filters FLT1 and FLT2, a power amplifier PA, and a low-noise amplifier LNA. The switch SW is used for switching between transmission and reception of radio waves at the antenna ANT. The switch SW includes a common terminal TC and two selection terminals TA and TB. The common terminal TC is connected to the antenna ANT. The selection terminal TA is connected to the transmission-side line TX with the filter FLT1 and the power amplifier PA interposed therebetween. The selection terminal TB is connected to the reception-side line RX with the filter FLT2, the low noise amplifier LNA, and the balun **100** interposed therebetween.

(23) To emit radio waves from the antenna ANT, the common terminal TC of the switch SW is connected to the selection terminal TA. In contrast, to receive radio waves at the antenna ANT, the common terminal TC of the switch SW is connected to the selection terminal TB.

(24) The power amplifier PA amplifies an RF signal that is a transmission signal transmitted from the RFIC **20**, and outputs the amplified RF signal to the filter FLT1. The filter FLT1 is composed of a low-pass filter, a high-pass filter, or a bandpass filter, and passes a signal in a desired frequency band of the RF signal amplified by the power amplifier PA. The RF signal that has passed through the filter FLT1 is emitted as radio waves from the antenna ANT via the switch SW.

(25) Like the above-mentioned filter FLT1, the filter FLT2 is composed of a low-pass filter, a high-pass filter, or a bandpass filter, and passes a signal in a desired frequency band of an RF signal that is a reception signal received at the antenna ANT. The RF signal that has passed through the filter FLT2 is amplified with low noise by the low-noise amplifier LNA and is transmitted to the balun **100**.

(26) The balun **100** is a converter for converting an unbalanced signal to a balanced signal. A balanced signal includes a pair of signals with equal amplitude and phases that are inverted from each other, and an unbalanced signal is a signal used in a transmission method that transmits changes in electric potential relative to ground potential. In general, a line connected to an antenna is an unbalanced line. In contrast, processing is performed using a balanced signal in an IC circuit such as the RFIC **20**. Therefore, a reception signal from the antenna ANT, which is transmitted as an unbalanced signal, is converted, using the balun **100**, to a balanced signal suitable for processing in the RFIC **20**.

(27) [Configuration of Balun]

(28) FIG. 2 is an example of a circuit diagram of the balun **100** in FIG. 1. Referring to FIG. 2, the balun **100** includes an unbalanced terminal T1, two balanced terminals (a first balanced terminal T2 and a second balanced terminal T3), and four lines **110**, **120**, **210**, and **220**. When λ is the wavelength of an RF signal to pass, basically each of the above lines has an electrical length of $\lambda/4$.

(29) In the following description, the case of converting an unbalanced signal to a balanced signal using the unbalanced terminal T1 as an input terminal IN and the first balanced terminal T2 and the second balanced terminal T3 as output terminals OUT1 and OUT2, respectively, will be described by way of example. Note that the balun **100** may also be used in the case of converting a balanced signal input to the first balanced terminal T2 and the second balanced terminal T3 to an unbalanced signal and outputting the unbalanced signal from the unbalanced terminal T1.

(30) The balun **100** is a so-called “Marchand balun” in which two lines having a length of $\lambda/4$ and connected to a balanced line are coupled to a line connected to an unbalanced line and having a length of $\lambda/2$, which is $1/2$ of the wavelength λ . More specifically, the unbalanced line connected to the unbalanced terminal T1 includes two lines (the first main line **110** and the second main line **120**) connected in series. The first main line **110** has a first end connected to the unbalanced terminal T1, and a second end connected to a first end of the second main line **120**. A second end of the second main line is open.

(31) The first main line **110** includes a first portion **111** connected to the unbalanced terminal T1

and a second portion **112** connected in series to the first portion **111**. In addition, the second main line **120** includes a third portion **121** connected to the second portion **112** of the first main line **110** and a fourth portion **122** connected in series to the third portion **121**.

(32) The first sub-line **210** is connected between the first balanced terminal **T2** and a reference potential (ground potential). The first sub-line **210** is electromagnetic-field coupled to the first main line **110** of the unbalanced line. The first sub-line **210** includes a fifth portion **211** connected to the first balanced terminal **T2**, and a sixth portion **212** connected between the fifth portion **211** and the reference potential. In the first sub-line **210**, the first portion **111** and the sixth portion **212** are coupled, and the second portion **112** and the fifth portion **211** are coupled.

(33) Similarly, the second sub-line **220** is connected between the second balanced terminal **T3** and the reference potential. The second sub-line **220** is electromagnetic-field coupled to the second main line **120** of the unbalanced line. The second sub-line **220** includes a seventh portion **221** connected to the second balanced terminal **T3**, and an eighth portion **222** connected between the seventh portion **221** and the reference potential. In the second sub-line **220**, the third portion **121** and the seventh portion **221** are coupled, and the fourth portion **122** and the eighth portion **222** are coupled.

(34) A capacitor **C2** is connected between the first balanced terminal **T2** and the reference potential. In addition, a capacitor **C3** is connected between the second balanced terminal **T3** and the reference potential. The capacitors **C2** and **C3** are provided for adjusting the impedance. Note that the capacitors **C2** and **C3** are optional configurations, and, if the impedance is adjustable using the configuration of other elements, one or both of the capacitors **C2** and **C3** might not be provided. Note that the “capacitor **C2**” and the “capacitor **C3**” in the embodiment correspond to a “first capacitor” and a “second capacitor”, respectively, in the present disclosure.

(35) With such a configuration, an RF signal input to the unbalanced terminal **T1** (input terminal **IN**) is transmitted to two balanced lines by electromagnetic field coupling, and is output as a balanced signal from the first balanced terminal **T2** (output terminal **OUT1**) and the second balanced terminal **T3** (output terminal **OUT2**).

(36) In the balun **100** of the present embodiment, the balanced line connected to the first balanced terminal **T2** is provided with, in addition to the first sub-line **210** described above, a first line **230** and a second line **240**. The first line **230** has a first end connected to a midpoint **MP** (the node between the fifth portion **211** and the sixth portion **212**) of the first sub-line **210**, and a second end that is open. The first line **230** is electromagnetic-field coupled to the first portion **111** of the first main line **110** and the sixth portion **212** of the first sub-line. As will be described later, because a pole is generated in the high frequency domain of the passband due to the first line **230**, the return loss is reduced.

(37) The second line **240** is connected in parallel with the sixth portion **212** of the first sub-line **210**. Here, in the balun **100** of the present embodiment, as illustrated in FIG. 3, a line length **LNG2** of the second line **240** is shorter than a line length **LNG1** of the sixth portion **212** of the first sub-line **210**. Accordingly, the phase of a signal output from the first balanced terminal **T2** is delayed. In contrast, if the line length **LNG2** of the second line **240** is longer than the line length **LNG1** of the sixth portion **212**, the phase of a signal output from the first balanced terminal **T2** is advanced. As mentioned above, depending on the line length of the second line **240**, the phase difference between a signal output from the first balanced terminal **T2** and a signal output from the second balanced terminal **T3** may be adjusted.

(38) Moreover, in the balun **100** of the present embodiment, the second sub-line **220** has a portion that is strongly coupled to the second main line **120** and a portion that is weakly coupled to the second main line **120**. The strength of coupling between the seventh portion **221** of the second sub-line **220** and the third portion **121** of the second main line **120** is stronger than the strength of coupling between the eighth portion **222** of the second sub-line **220** and the fourth portion **122** of the second main line **120**. More specifically, the distance between the seventh portion **221** of the

second sub-line **220** and the third portion **121** of the second main line **120** is shorter than the distance between the eighth portion **222** of the second sub-line **220** and the fourth portion **122** of the second main line **120**.

(39) As mentioned above, in the second sub-line **220** coupled to the second main line **120**, the impedance of the eighth portion **222** close to the reference potential is larger than the impedance of the seventh portion **221**, thereby realizing a wide bandwidth of the bandpass characteristics.

(40) Note that the “second line **240**” in the embodiment corresponds to a “parallel line” in the present disclosure. In addition, the “sixth portion **212**” in the embodiment corresponds to a “specific portion” in the present disclosure.

(41) Next, the structure of the balun illustrated in FIG. 2 will be described in detail using FIGS. 4 and 5. FIG. 4 is an external perspective view of the balun **100**. In addition, FIG. 5 is an exploded perspective view of the balun **100**. As illustrated in FIG. 4, the balun **100** includes a dielectric substrate **150** having a substantially cuboid shape. In FIGS. 4 and 5, the laminating direction of the dielectric substrate **150** serves as the Z axis, a direction along the long side of the dielectric substrate **150** as the X axis, and a direction along the short side as the Y axis. In the following description, a face of the dielectric substrate **150** in the positive direction of the Z axis may also be referred to as an upper face **151**, and a face in the negative direction of the Z axis as a lower face **152**. Moreover, a face of the dielectric substrate **150** in the negative direction of the Y axis may also be referred to as a side face **153**, and a face in the positive direction of the Y axis also as a side face **154**.

(42) Referring to FIGS. 4 and 5, the balun **100** includes the dielectric substrate **150** in which a plurality of dielectric layers LY1 to LY14 are laminated, and which has a substantially cuboid outer shape. On the outer surface of the dielectric substrate **150**, a plurality of substantially-C-shaped outer electrodes, extending across the upper face **151**, the side faces **153** and **154**, and the lower face **152**, are provided. The outer electrodes are used for connection with an external device and are also used for connection between the wiring patterns of the individual layers of the dielectric substrate **150**. The outer electrodes include the unbalanced terminal T1, the balanced terminals T2 and T3, a ground terminal GND (reference potential terminal) for connecting to the reference potential, and a connection terminal T0 for interlayer connection. The upper face **151** of the dielectric substrate **150** is marked with a directional mark DM representing the direction.

(43) As illustrated in FIG. 5, the lines **110**, **120**, **220** (**221** and **222**), **230**, and **240** included in the balun **100** are coils whose winding direction is the Z axis direction. In addition, in the case where the dielectric substrate **150** is viewed in plan from the laminating direction (Z axis direction), the openings of the coils of the individual lines at least partially overlap with one another. Note that the openings of the coils represent, in the case where the dielectric substrate is viewed in plan from the Z axis direction, internal portions surrounded by the coils formed in the lines in a ring shape around the winding axis. In addition, as illustrated in FIG. 5, the lines may be wound around a common winding axis.

(44) In the dielectric substrate **150**, the lines **110**, **120**, **220** (**221** and **222**), **230**, and **240** are arranged from the upper face **151** toward the lower face **152** in the laminating direction, and are arranged in the order of the first main line **110**, the first line **230**, the first sub-line **210**, the second line **240**, the second sub-line **220**, and the second main line **120**. Each line is provided on one dielectric layer or over two adjacent dielectric layers. The dielectric layers are connected by vias provided inside the dielectric substrate **150** or by outer electrodes provided on the outer surface of the dielectric substrate **150**.

(45) More specifically, the first main line **110** is wound on the third layer LY3 in the counterclockwise (CCW) direction from the inner circumference toward the outer circumference of the coil when viewed in plan from the positive direction of the Z axis. An inner circumference end of the first main line **110** is connected to the unbalanced terminal T1 (input terminal IN) provided on the outer surface of the dielectric substrate **150** with a via V1, and a line L1 provided on the

second layer LY2 interposed therebetween. In addition, an outer circumference end of the first main line **110** is connected in the third layer LY3 to the connection terminal T0 provided on the outer surface of the dielectric substrate **150**.

(46) The second main line **120** is wound on the fourteenth layer LY14, which is the lowest layer, in the clockwise (CW) direction from the inner circumference toward the outer circumference of the coil when viewed in plan from the positive direction of the Z axis. An inner circumference end of the second main line **120** is connected to nowhere and is an open end. An outer circumference end of the second main line **120** is connected in the fourteenth layer LY14 to the connection terminal T0 provided on the outer surface of the dielectric substrate **150**. By the connection terminal T0, the second main line **120** is connected in series to the first main line **110**.

(47) The first sub-line **210** is wound on the fifth layer LY5 in the CCW direction from the inner circumference toward the outer circumference of the coil when viewed in plan from the positive direction of the Z axis. An inner circumference end of the first sub-line **210** is connected to a line L2 provided in the eighth layer LY8 with a via V3 interposed therebetween. The line L2 is connected in the eighth layer LY8 to the ground terminal GND provided on the outer surface of the dielectric substrate **150**. An outer circumference end of the first sub-line **210** is connected in the fifth layer LY5 to the first balanced terminal T2 (output terminal OUT1) provided on the outer surface of the dielectric substrate **150**.

(48) The first line **230** is provided on the fourth layer LY4, which is between the third layer LY3 where the first main line **110** is provided and the fifth layer LY5 where the first sub-line **210** is provided. The first line **230** is wound in the CCW direction from the inner circumference toward the outer circumference of the coil when viewed in plan from the positive direction of the Z axis. An inner circumference end of the first line **230** is an open end. An outer circumference end of the first line **230** is connected to a midpoint MP1 of the first sub-line **210** with a via V2 interposed therebetween. The midpoint MP1 is at a position that includes neither the outer circumference end nor the inner circumference end of the first sub-line **210**. Note that the line length from the midpoint MP1 to the inner circumference end of the first line **230** is different from the line length from the midpoint MP1 to the ground terminal GND by way of the inner circumference end of the first sub-line **210** and the line L2 on the eighth layer LY8.

(49) Because the first line **230** is provided on the dielectric layer between the dielectric layer where the first main line **110** is provided and the dielectric layer where the first sub-line **210** is provided, the first line **230** is electromagnetic-field coupled to both the first main line **110** and the first sub-line **210**. Furthermore, the coupling between the first line **230** and the first main line **110** is stronger than the coupling between the first sub-line **210** and the first main line **110**.

(50) A second line **240** is provided on the seventh layer LY7. The second line **240** is wound in the CCW direction from the inner circumference toward the outer circumference of the coil when viewed in plan from the positive direction of the Z axis. An inner circumference end of the second line **240** is connected to a via V3, and is connected to the inner circumference end of the first sub-line **210** and to the ground terminal GND with the via V3 interposed therebetween. In addition, an outer circumference end of the second line **240** is connected to a midpoint MP2 of the first sub-line **210** with a via V4 interposed therebetween. That is, the second line **240** is connected in parallel with a part of the first sub-line **210** by the via V3 and the via V4. Although the midpoint MP1 to which the via V2 is connected and the midpoint MP2 to which the via V4 is connected are at different positions in the first sub-line **210** in FIG. 5, the midpoint MP1 and the midpoint MP2 may be at the same position in the first sub-line **210**.

(51) The second sub-line **220** is provided over two layers, the twelfth layer LY12 and the thirteenth layer LY13. The eighth portion **222** of the second sub-line **220** is provided on the twelfth layer LY12, and the seventh portion **221** of the second sub-line **220** is provided on the thirteenth layer LY13.

(52) The eighth portion **222** of the second sub-line **220** is wound on the twelfth layer LY12 in the

CW direction from the inner circumference toward the outer circumference of the coil when viewed in plan from the positive direction of the Z axis. An inner circumference end of the eighth portion **222** is connected to a line **L3** provided on the eleventh layer **LY11** with a via **V5** interposed therebetween. The line **L3** is connected in the eleventh layer **LY11** to the ground terminal **GND** provided on the outer surface of the dielectric substrate **150**. In contrast, an outer circumference end of the eighth portion **222** is connected, with a via **V7** interposed therebetween, to an inner circumference end of the seventh portion **221** of the second sub-line **220** provided on the thirteenth layer **LY13**.

(53) The seventh portion **221** of the second sub-line **220** is wound on the thirteenth layer **LY13** in the CW direction from the inner circumference toward the outer circumference of the coil when viewed in plan from the positive direction of the Z axis. As described above, the inner circumference end of the seventh portion **221** of the second sub-line **220** is connected to the outer circumference end of the eighth portion **222** on the twelfth layer **LY12** with the via **V7** interposed therebetween. An outer circumference end of the seventh portion **221** is connected to a line **L4** provided on the eleventh layer **LY11** with a via **V6** interposed therebetween. The line **L4** is connected in the eleventh layer **LY11** to the second balanced terminal **T3** (output terminal **OUT2**) provided on the outer surface of the dielectric substrate **150**. That is, with such connections, the seventh portion **221** and the eighth portion **222** of the second sub-line **220** are connected in series between the second balanced terminal **T3** and the ground terminal **GND**.

(54) In the second sub-line **220**, because signals are output from the second balanced terminal **T3**, the signal transmission direction is a direction from the ground terminal **GND** toward the second balanced terminal **T3**. That is, when viewed in the signal transmission direction, the second sub-line **220** is wound on the CW direction from the ground terminal **GND** toward the second balanced terminal **T3**. In contrast, the second main line **120** transmits signals from the connection terminal **T0** (in other words, the unbalanced terminal **T1**) to the open end. Therefore, when viewed in the signal transmission direction, the second main line **120** is wound in the CCW direction from the unbalanced terminal **T1** toward the open end of the second main line **120**. That is, the second main line **120** and the second sub-line **220** are coupled in the reverse winding direction when viewed in the signal transmission direction.

(55) The seventh portion **221** and the eighth portion **222** of the second sub-line **220** are arranged so as not to overlap with each other except for a portion where the seventh portion **221** and the eighth portion **222** are connected to each other by the via **V7** when viewed in plan from the positive direction of the Z axis. In addition, the entire second sub-line **220** (seventh portion **221**+eighth portion **222**) when viewed in plan from the positive direction of the Z axis overlaps with the second main line **120** provided on the fourteenth layer **LY14**. The line width of the second main line **120** is wider than the line width of the second sub-line **220**. Since the line width of one line is wider than the line width of the other line, the influence of misalignment of the lines is reduced.

(56) Each of the seventh portion **221** and the eighth portion **222** of the second sub-line **220** is electromagnetic-field coupled to the second main line **120**. Here, since the seventh portion **221** is provided on the dielectric layer between the dielectric layer where the eighth portion **222** is provided and the dielectric layer where the second sub-line **220** is provided, the distance between the second sub-line **220** and the seventh portion **221** is shorter than the distance between the second sub-line **220** and the eighth portion **222**. Therefore, the coupling between the second sub-line **220** and the seventh portion **221** is stronger than the coupling between the second sub-line **220** and the eighth portion **222**.

(57) On the ninth layer **LY9**, a flat plate electrode **C21** connected to the first balanced terminal **T2** and a flat plate electrode **C31** connected to the second balanced terminal **T3** are provided. Moreover, on the tenth layer **LY10**, a flat plate electrode (ground electrode) **C10** connected to the ground terminal **GND** is provided, and each of the flat plate electrode **C21** and the flat plate electrode **C31** on the ninth layer **LY9** faces the ground electrode **C10** on the tenth layer **LY10**. The

flat plate electrode C21 and the ground electrode C10 constitute the capacitor C2 in FIG. 2. The flat plate electrode C31 and the ground electrode C10 constitute the capacitor C3 in FIG. 2.

(58) The ground electrode C10 is provided with an opening OP1 in a part of a portion where the first sub-line 210 and the second sub-line 220 overlap when the dielectric substrate 150 is viewed in plan from the Z axis direction. By the opening OP1, the first sub-line 210 and the second sub-line 220 are electromagnetic-field coupled.

(59) Such a balun is used in a front-end circuit for connecting an unbalanced line of an antenna and a balanced line of an IC circuit that processes RF signals in a portable radio communication device represented by a smartphone, a mobile phone, or the like. In recent years, the frequency band of RF signals used for communication has been expanding, and a balun is also required to improve its bandpass characteristics by handling a wider bandwidth and/or reducing losses.

(60) In the balun 100 of the present embodiment, in addition to the configuration of a general “Marchand balun”, a sub-line (first sub-line 210) that is coupled to a main line (first main line 110) on the unbalanced terminal side of the unbalanced line is provided with the first line 230 whose first end is an open end and the second line 240 connected in parallel. Furthermore, in the balun 100, of a sub-line (second sub-line 220) coupled to a main line (second main line 120) on the open end side of the unbalanced line, the anterior portion (seventh portion 221) is arranged closer to the main line than the posterior portion (eighth portion 222). By adopting such a configuration, a wide bandwidth and low losses of the bandpass characteristics may be realized.

(61) Hereinafter, the signal bandpass characteristics of the balun 100 of the present embodiment will be described using comparative examples.

(62) [Characteristics of Balun]

(63) (1) Effects of First Line

(64) First, the influence of the first line 230 provided on the first sub-line 210 on the bandpass characteristics will be described using a first comparative example and a second comparative example. FIG. 6 illustrates a circuit diagram of a balun 300 of the first comparative example, and FIG. 7 illustrates the bandpass characteristics of the balun 100 of the embodiment and the balun 300 of the first comparative example. Moreover, FIG. 8 illustrates a circuit diagram of a balun 300A of the second comparative example, and FIG. 9 illustrates the bandpass characteristics of the balun 100 of the embodiment and the balun 300A of the second comparative example.

(65) The balun 300 of the first comparative example has a configuration in which the first line 230 of the balun 100 of the embodiment illustrated in FIG. 2 has been removed. Also, the balun 300A of the second comparative example has a configuration in which the first line 230 of the balun 100 of the embodiment has been replaced by a first line 230A. The first line 230A has a configuration in which the open end of the first line 230 is connected to the reference potential. Since configurations in the baluns 300 and 300A other than those described above are the same as the balun 100, the description of overlapping elements is not repeated.

(66) In FIGS. 7 and 9 and FIGS. 11, 13, 15 and 17 described later, the results of simulating the characteristics of the balun 100 of the embodiment and the comparative examples, including insertion loss (IL), return loss (RL), amplitude balance (AB), and phase difference (PD), are indicated. In FIGS. 7 and 9, solid lines LN10 to LN13 and LN20 to LN23 indicate the case of the balun 100 of the embodiment, and dashed lines LN10X to LN13X and LN20X to LN23X indicate the cases of the comparative examples. Note that the passband specification in the simulation examples is in the range of 1450 MHz to 5800 MHz inclusive.

First Comparative Example

(67) With reference to FIG. 7, the influence of the presence or absence of the first line 230 on the bandpass characteristics will be described.

(68) First, with regard to insertion loss, both of the balun 100 of the embodiment (solid line LN10) and the balun 300 of the first comparative example (dashed line LN10X) satisfy the specification range of 3.0 dB or less over the entire passband. However, in the high frequency domain (around

4000 MHz to 5800 MHz) of the passband, the balun **100** of the embodiment has a smaller insertion loss than the balun **300** of the first comparative example.

(69) With regard to return loss, the balun **300** of the first comparative example (dashed line LN11X) has a return loss larger than the specification range of 12 dB in the high frequency domain of 4400 MHz and above, whereas the balun **100** of the embodiment (solid line LN11) has a return loss smaller than the specification range over the entire passband. As indicated by solid line LN11, in comparison with the balun **300**, the balun **100** has a new pole generated in the vicinity of 6000 MHz, and this pole contributes to the reduction of return loss in the high frequency domain. That is, the provision of the first line **230** causes the first line **230** to act as an LC resonance circuit, and the pole is newly generated.

(70) With regard to amplitude balance and phase difference, both of the balun **100** of the embodiment (solid lines LN12 and LN13) and the balun **300** of the first comparative example (dashed lines LN12X and LN13X) have achieved the respective specification ranges (AB: within ± 0.5 dB, PD: within $\pm 7^\circ$) over the entire passband. However, as compared with the case of the balun **300**, the balun **100** of the embodiment has an amplitude balance and a phase difference that are close to zero in a domain slightly higher than the passband (around 6500 MHz to 7000 MHz), and this realizes the homogenization of both characteristics over the passband.

Second Comparative Example

(71) Next, the influence of having the first end of the first line **230** as an open end on the bandpass characteristics will be described using the second comparative example.

(72) Referring to FIG. 9, the insertion loss, return loss, amplitude balance, and phase difference of the balun **300A** of the second comparative example are all within their respective specification ranges in the passband. However, especially in a domain above 4800 MHz, the return loss of the balun **300** of the second comparative example is larger than the return loss of the balun **100** of the embodiment. That is, since one of the two ends of the first line **230** is an open end, the return loss in the high frequency domain is small.

(73) A new resonance path is formed by coupling of one of the two ends of the first lines **230**, as an open end, with the first portion **111** of the first main line **110**. Therefore, by adjusting this coupling, a new resonance point is generated in the passband. This new resonance point reduces the return loss.

(74) As described above, since the first line whose first end is open and which is coupled to the first main line and the first sub-line is added to the first sub-line in the “Marchand balun”, the insertion loss and return loss in the passband are reduced, thereby improving the bandpass characteristics of the balun.

(75) (2) Effects of Second Line

Third Comparative Example

(76) Next, the influence of the second line **240** partially connected in parallel with the first sub-line **210** on the bandpass characteristics will be described using a third comparative example. FIG. 10 illustrates a circuit diagram of a balun **300B** of the third comparative example, and FIG. 11 indicates the bandpass characteristics of the balun **100** of the embodiment (solid lines LN30 to LN33) and the bandpass characteristics of the balun **300B** of the third comparative example (dashed lines LN30X to LN33X).

(77) As illustrated in FIG. 10, the balun **300B** of the third comparative example has a configuration in which the second line **240** of the balun **100** of the embodiment has been removed. Since configurations in the balun **300B** other than the portion of the second line **240** are the same as the balun **100**, the description of overlapping elements is not repeated.

(78) Referring to FIG. 11, in the balun **300B** of the third comparative example, although the return loss (dashed line LN31X) is larger than the balun **100** of the embodiment by about 2 dB in the domain of 3000 MHz and above, the insertion loss, return loss, and amplitude balance (dashed lines LN30X to LN32X) satisfy the respective specification ranges over the entire passband. In

contrast, the phase difference (dashed line LN33X) is much greater than the specification range of 7° in the domain of 4000 MHz and below. In other words, the phase difference is improved by providing the first sub-line **210** with the second line **240**.

(79) In the case where the second line **240** is connected in parallel with the first sub-line **210**, the phase change of signals passing through these lines is influenced by the shorter line out of the first sub-line **210** and the second line **240**. In contrast, because the first sub-line **210** is closer to the first main line **110** than the second line **240**, the first sub-line **210** is more dominant in terms of coupling to the first main line **110**. That is, the influence of the second line **240** on changes in the amount of coupling between the first main line **110** and the balanced line connected to the first balanced terminal T2 is small, and as a result, a change in amplitude is small. Therefore, by providing the second line **240**, the phase difference may be adjusted while suppressing changes in amplitude balance.

(80) As described above, since the second line, which is partially connected in parallel with the first sub-line, is provided in the “Marchand balun”, the phase difference in the passband is reduced, and the bandpass characteristics of the balun are improved.

(81) (3) Effects of Arrangement of Second Sub-Line

(82) Next, the influence of the arrangement of the seventh portion **221** and the eighth portion **222** of the second sub-line **220** on the bandpass characteristics will be described using a fourth comparative example to a sixth comparative example.

Fourth Comparative Example

(83) FIG. **12** is a circuit diagram of a balun **300C** of the fourth comparative example. The balun **300C** of the fourth comparative example has a configuration in which the second sub-line **220** of the balun **100** illustrated in FIG. **2** has been replaced by a second sub-line **220A**. In the second sub-line **220A**, both the seventh portion **221** and the eighth portion **222** are arranged in close proximity to the second main line **120**. More specifically, in the exploded perspective view of FIG. **5**, this corresponds to a configuration where the seventh portion **221** and the eighth portion **222** are formed on the thirteenth layer LY13. Since other configurations in the balun **300C** are the same as the balun **100** of the embodiment, the description of overlapping elements is not repeated.

(84) FIG. **13** is a diagram for describing the comparison of the bandpass characteristics of the balun **100** of the embodiment and the balun **300C** of the fourth comparative example. FIG. **13** illustrates the bandpass characteristics of the balun **100** of the embodiment (solid lines LN40 to LN43) and the bandpass characteristics of the balun **300C** of the fourth comparative example (dashed lines LN40X to LN43X).

(85) Referring to FIG. **13**, with regard to insertion loss, although outside the passband, the balun **100** of the embodiment (solid line LN40) has an insertion loss smaller than the balun **300C** of the fourth comparative example (dashed line LN40X) in the high frequency domain, thereby realizing a wide bandwidth. Accordingly, even in the passband, the insertion loss is improved in the domain of 5500 MHz and above.

(86) With regard to return loss, in the domain of 3000 MHz and above, the balun **300C** of the fourth comparative example (dashed line LN41X) has a return loss lower than the balun **100** of the embodiment (solid line LN41) by 2 dB or more over the entire passband; however, with regard to amplitude balance and phase difference, the balun **100** of the embodiment (solid lines LN42 and LN43) is improved in the high frequency domain of the passband, as compared with the balun **300C** of the fourth comparative example (dashed lines LN42X and LN43X).

(87) Therefore, in view of the overall characteristics, it may be said that the balun **100** of the embodiment realizes better bandpass characteristics than the balun **300C** of the fourth comparative example.

Fifth Comparative Example

(88) FIG. **14** is a circuit diagram of a balun **300D** of the fifth comparative example. The balun **300D** of the fifth comparative example has a configuration in which the second sub-line **220** of the

balun **100** illustrated in FIG. 2 has been replaced by a second sub-line **220B**. In the second sub-line **220B**, both the seventh portion **221** and the eighth portion **222** are arranged away from the second main line **120**. More specifically, in the exploded perspective view of FIG. 5, this corresponds to a configuration where the seventh portion **221** and the eighth portion **222** are provided on the twelfth layer **LY12**. Since other configurations in the balun **300D** are the same as the balun **100** of the embodiment, the description of overlapping elements is not repeated.

(89) FIG. 15 is a diagram for describing the comparison of the bandpass characteristics of the balun **100** of the embodiment and the balun **300D** of the fifth comparative example. FIG. 15 illustrates the bandpass characteristics of the balun **100** of the embodiment (solid lines **LN50** to **LN53**) and the bandpass characteristics of the balun **300D** of the fifth comparative example (dashed lines **LN50X** to **LN53X**).

(90) Referring to FIG. 15, with regard to insertion loss, like the case of the fourth comparative example, the balun **100** of the embodiment (solid line **LN50**) has an insertion loss lower than the balun **300D** of the fifth comparative example (dashed line **LN50X**) over a wide frequency band. Moreover, with regard to return loss, in the low frequency domain of the passband, the balun **300D** of the fifth comparative example (dashed line **LN51X**) has a return loss that is partially lower than the balun **100** of the embodiment (solid line **LN51**), but the baluns **300D** and **100** have return losses that are at about the same level in the passband as a whole.

(91) In contrast, with regard to amplitude balance, the balun **300D** of the fifth comparative example (dashed line **LN52X**) has an amplitude difference larger than the balun **100** of the embodiment (solid line **LN52**), which greatly deviates from the specification range at around 2300 MHz to 5200 MHz. Moreover, with regard to phase difference, the balun **300D** of the fifth comparative example (dashed line **LN53X**) has a large phase difference in the high frequency domain in the vicinity of 6000 MHz to 7500 MHz.

(92) As described above, the balun **100** of the embodiment realizes better bandpass characteristics than the balun **300D** of the fifth comparative example.

Sixth Comparative Example

(93) FIG. 16 is a circuit diagram of a balun **300E** of the sixth comparative example. The balun **300E** of the sixth comparative example has a configuration in which the second sub-line **220** of the balun **100** illustrated in FIG. 2 has been replaced by a second sub-line **220C**. In the second sub-line **220C**, contrary to the balun **100** of the embodiment, the seventh portion **221** of the second sub-line **220** is arranged farther away than the eighth portion **222**. More specifically, in the exploded perspective view of FIG. 5, this corresponds to a configuration where the seventh portion **221** is provided on the twelfth layer **LY12**, and the eighth portion **222** is provided on the thirteenth layer **LY13**. Since other configurations in the balun **300E** are the same as the balun **100** of the embodiment, the description of overlapping elements is not repeated.

(94) FIG. 17 is a diagram for describing the comparison of the bandpass characteristics of the balun **100** of the embodiment and the balun **300E** of the sixth comparative example. FIG. 17 illustrates the bandpass characteristics of the balun **100** of the embodiment (solid lines **LN60** to **LN63**) and the bandpass characteristics of the balun **300E** of the sixth comparative example (dashed lines **LN60X** to **LN63X**).

(95) Referring to FIG. 17, with regard to insertion loss, like the case of the fourth comparative example and the fifth comparative example, the balun **100** of the embodiment (solid line **LN60**) has an insertion loss lower than the balun **300E** of the sixth comparative example (dashed line **LN60X**) over a wide frequency band. In contrast, with regard to return loss, although the balun **100** and the balun **300E** satisfy the specification range, the balun **300E** of the sixth comparative example (dashed line **LN62X**) has a low return loss overall, as compared with the balun **100** of the embodiment (solid line **LN61**).

(96) With regard to amplitude balance, the balun **300D** of the sixth comparative example (dashed line **LN62X**) has large fluctuations of amplitude difference, which greatly deviates from the

specification range in the intermediate frequency domain (around 2200 MHz to 4200 MHz) and the high frequency domain (around 5200 MHz to 5800 MHz) of the passband. Moreover, with regard to phase difference, the phase difference of the balun **300E** of the sixth comparative example (dashed line LN**53X**) is large and is outside the specification range in the high frequency domain around 5300 MHz to 7200 MHz.

(97) As described above, the balun **100** of the embodiment realizes better bandpass characteristics than the balun **300E** of the sixth comparative example.

(98) In general, it is known that the characteristics of the coupling of the main line and the sub-line on the posterior side of the “Marchand balun” are improved by weakening the coupling on the open end side. For example, such a configuration may be realized by narrowing the line width of the main line toward the open end, and narrowing the line width of the sub-line toward the reference potential. In the balun **100** of the embodiment, since the seventh portion **221** of the second sub-line **220** is arranged closer to the second main line **120** than the eighth portion **222**, the coupling of the main line and the sub-line on the open end side is weaker than the coupling of the main line and the sub-line on the first main line **110** side. Therefore, by adopting an arrangement such as the balun **100** of the embodiment, bandpass characteristics that are better than those achieved by the arrangement of the baluns **300C** to **300E** of the fourth to sixth comparative examples may be realized.

(99) The embodiments disclosed here should be considered illustrative in all respects and not restrictive. The scope of the present disclosure is indicated by the scope of claims rather than the description of the above embodiments and is intended to include all changes within the meaning and scope equivalent to the scope of the claims.

REFERENCE SIGNS LIST

(100) **1** communication device **10** front-end circuit **100**, **300**, and **300A** to **300E** baluns **110** to **112**, **120** to **122**, **210** to **212**, **220**, **220A** to **220C**, **221**, **222**, **230**, **230A**, **240**, **L1**, **L2**, **L3**, and **L4** lines **150** dielectric substrate **151** upper face **152** lower face **153** and **154** side faces **ANT** antenna **C2** and **C3** capacitors **C10** ground electrode **C21** and **C31** flat plate electrodes **DM** directional mark **FLT1** and **FLT2** filters **GND** ground terminal **IN** input terminal **LNA** low noise amplifier **LY1** to **LY14** dielectric layers **MP**, **MP1**, and **MP2** midpoints **OP1** opening **OUT1** and **OUT2** output terminals **PA** power amplifier **RX** reception-side line **SW** switch **T0** connection terminal **T1** unbalanced terminal **T2** and **T3** balanced terminals **TA** selection terminal **TC** common terminal **TX** transmission-side line **V1** to **V7** vias

Claims

1. A balun comprising: a dielectric substrate in which a plurality of dielectric layers are laminated; an unbalanced terminal, a first balanced terminal, a second balanced terminal, and a reference potential terminal on the dielectric substrate; a first main line having a first end that is connected to the unbalanced terminal; a second main line having a first end that is connected to a second end of the first main line, and having a second end that is open; a first sub-line connected between the first balanced terminal and the reference potential terminal; a second sub-line connected between the second balanced terminal and the reference potential terminal; and a parallel line connected in parallel with a part of the first sub-line, wherein in a laminating direction of the dielectric substrate, the first sub-line is between the first main line and the parallel line, the parallel line is between the first sub-line and the second sub-line, and the second sub-line is between the parallel line and the second main line, and a line length of a portion of the first sub-line that is connected in parallel with the parallel line is different from a line length of the parallel line.
 2. The balun according to claim 1, wherein the line length of the parallel line is shorter than the line length of the portion of the first sub-line that is connected in parallel with the parallel line.
-

