

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12388361
Kind Code	B2
Date of Patent	August 12, 2025
Inventor(s)	Guo; Guoyong et al.

Battery charging circuit and methods for trickle charging and precharging a dead multi-cell-in-series battery

Abstract

Methods and apparatus for trickle charging and precharging a dead multi-cell-in-series battery. One battery charging circuit generally includes a charge pump circuit comprising a plurality of switches, being coupled to first and second power supply nodes, and being configured to multiply (or divide) a first voltage at the first power supply node to generate a second voltage at the second power supply node; a driver circuit configured to drive the plurality of switches in the charge pump circuit; and an arbiter having a first input coupled to the first power supply node, a second input coupled to the second power supply node, a third input coupled to a third power supply node having a third voltage, and an output coupled to a power supply terminal of the driver circuit. The arbiter is configured to select between the first, second, and third voltages to power the driver circuit.

Inventors: Guo; Guoyong (San Jose, CA), Kun; Cheong (San Diego, CA), Song; Chunping (Palo Alto, CA)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 78704960

Assignee: QUALCOMM Incorporated (San Diego, CA)

Appl. No.: 17/336075

Filed: June 01, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20210376622 A1	Dec. 02, 2021

Related U.S. Application Data

Publication Classification

Int. Cl.: **H02M3/07** (20060101); **H01M10/44** (20060101); **H02J7/00** (20060101); H02M1/00 (20060101); H02M3/158 (20060101)

U.S. Cl.:

CPC **H02M3/07** (20130101); **H01M10/441** (20130101); **H02J7/007182** (20200101); **H02M3/072** (20210501); H02J7/0024 (20130101); H02J2207/20 (20200101); H02M1/0095 (20210501); H02M3/071 (20210501); H02M3/073 (20130101); H02M3/1582 (20130101)

Field of Classification Search

CPC: H02M (3/07); H02M (3/072); H01M (10/441); H02J (7/007182)

USPC: 320/117

References Cited**U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
3590358	12/1970	Ruben	320/141	H02J 7/007182
4016473	12/1976	Newman	N/A	N/A
4061956	12/1976	Brown	320/160	H02J 7/0047
4785226	12/1987	Fujisawa	320/DIG.11	H02J 7/35
5225763	12/1992	Krohn	320/155	H02J 7/0045
5684384	12/1996	Barkat et al.	N/A	N/A
5717318	12/1997	Matsuda	323/273	H02M 3/07
5818201	12/1997	Stockstad et al.	N/A	N/A
5832303	12/1997	Murase	710/36	H04L 49/254
6081096	12/1999	Barkat	320/124	H02J 9/061
6304068	12/2000	Hui	323/225	H02M 3/07
6304467	12/2000	Nebrigic	363/49	H02M 3/07
6310789	12/2000	Nebrigic	363/60	H02M 3/07
6359797	12/2001	Bayer	363/59	H02M 1/146
6369619	12/2001	Kawa	327/108	H03K 19/00315
6370046	12/2001	Nebrigic	363/59	H02M 3/07
6538907	12/2002	Hoshino	363/60	H02M 3/07
6559492	12/2002	Hazucha	257/691	H02M 3/07
6643151	12/2002	Nebrigic	363/124	H02M 3/07
6661683	12/2002	Botker	363/60	H02M 3/07
6703891	12/2003	Tanaka	327/536	G11C 5/145
6819573	12/2003	Hazucha	363/56.02	H02M 3/07
7129774	12/2005	Bosnyak	327/539	G11C 29/028
7176654	12/2006	Meyer et al.	N/A	N/A
7260732	12/2006	Bittner, Jr.	713/323	G06F 1/28

7262580	12/2006	Meyer	320/141	H02J 7/0031
7321219	12/2007	Meyer	320/125	H02J 7/00047
7323847	12/2007	Meyer	320/110	H02J 7/0031
7474141	12/2008	Huang	363/59	H02M 3/07
7508094	12/2008	Johnson, Jr.	307/64	H02J 9/062
7508167	12/2008	Meyer	320/135	H02J 7/0014
7612603	12/2008	Petricek	327/306	H02M 3/07
7675262	12/2009	Broughton	323/299	G05F 1/573
7737658	12/2009	Sennami	320/112	H02J 7/0068
7925906	12/2010	Ranganathan	713/320	G06F 1/26
7969233	12/2010	Matano	327/536	H02M 3/073
8018198	12/2010	Meyer	320/136	H02J 7/0069
8040701	12/2010	Oyama	363/60	H02M 3/07
8106708	12/2011	Vasani	330/261	H03F 1/0244
8258857	12/2011	Adkins	327/536	H02M 3/07
8270189	12/2011	Walters	363/59	H02M 3/073
8305011	12/2011	Kitagawa	315/297	H05B 45/38
8427113	12/2012	Xing	320/140	H02J 7/007182
8519788	12/2012	Khlat	330/297	H03F 3/24
8525479	12/2012	Meyer	320/135	H02J 7/0013
8564918	12/2012	Gagne	361/91.1	H03K 17/063
8576523	12/2012	Srivastava	361/118	H02M 1/32
8582336	12/2012	Tanaka	363/142	H02M 1/4208
8723490	12/2013	Moussaoui	323/284	H02M 3/1588
8941327	12/2014	Ryu	315/307	H05B 45/46
8981839	12/2014	Kay	307/43	G06F 1/263
9013229	12/2014	Rahman	327/536	H02M 3/073
9118189	12/2014	Meyer	N/A	H02J 7/00047
9136756	12/2014	Liu	N/A	H02M 3/07
9143032	12/2014	Le	N/A	H02M 3/07
9252666	12/2015	Sakita	N/A	H02M 3/1584
9325237	12/2015	Ren	N/A	H02M 3/07
9350243	12/2015	Chen	N/A	H02M 3/158
9379604	12/2015	Zhong	N/A	H02M 3/07
9401622	12/2015	Carobolante	N/A	H02J 50/90
9413232	12/2015	Torres	N/A	H02M 3/07
9820354	12/2016	Kang	N/A	H05B 45/60
9836071	12/2016	Atkinson	N/A	H02J 7/0063
9858841	12/2017	Nishimura	N/A	G09G 3/006
9871403	12/2017	Sotani	N/A	H01L 31/02021
9917510	12/2017	Ahmed	N/A	H02M 3/07
9964986	12/2017	Rueger	N/A	G05F 3/262
10008864	12/2017	Meyer	N/A	H02J 7/00711
10050522	12/2017	Scheel	N/A	H02M 3/073
10063139	12/2017	Le	N/A	H02M 3/07
10250057	12/2018	Zhao	N/A	H02J 7/0068
10361581	12/2018	Maalouf	N/A	H02J 7/007182
10374443	12/2018	Meyer	N/A	H02J 7/0048
10389235	12/2018	Giuliano	N/A	H02M 3/1582
10404086	12/2018	Wu	N/A	H02J 7/02

10404175	12/2018	Chakraborty	N/A	H02M 3/158
10424956	12/2018	Ghabra	N/A	H02J 7/0048
10424957	12/2018	Ghabra	N/A	H02J 7/342
10447152	12/2018	Zhang	N/A	H02M 7/4837
10468898	12/2018	Crosby, II	N/A	H02M 3/158
10516284	12/2018	Maalouf et al.	N/A	N/A
10523115	12/2018	Scheel	N/A	H02M 3/073
10560017	12/2019	Muramatsu	N/A	G05F 1/10
10615697	12/2019	Ferrari	N/A	H02M 3/1584
10714948	12/2019	Meyer	N/A	H02J 7/007194
10734826	12/2019	Zhao	N/A	H02J 7/02
10734891	12/2019	Oporta	N/A	H02J 7/02
10749218	12/2019	Hawley	N/A	H02M 3/1584
10763754	12/2019	Oouchi	N/A	H02J 7/0013
10790672	12/2019	Jury	N/A	H02J 1/108
10790689	12/2019	Krishna	N/A	H02J 7/00714
10802523	12/2019	Londak	N/A	G05F 1/565
10868429	12/2019	Li	N/A	H02M 3/07
10903738	12/2020	Zhang	N/A	H02M 3/07
11018582	12/2020	Bandyopadhyay	N/A	H02M 3/158
11063446	12/2020	Meyer	N/A	H02J 7/00036
11101674	12/2020	Walley	N/A	H02J 7/00
11112844	12/2020	Sporck	N/A	G06F 13/4022
11171493	12/2020	Kun	N/A	H02M 3/158
11290027	12/2021	Han	N/A	H02J 7/02
11309716	12/2021	Li	N/A	H02M 7/219
11316424	12/2021	Giuliano	N/A	H02M 3/07
11424629	12/2021	Han	N/A	H01M 10/441
11435769	12/2021	Londak	N/A	G05F 1/565
11502535	12/2021	Tian	N/A	H02M 3/07
11502599	12/2021	Yen	N/A	H02M 3/07
11522466	12/2021	Li	N/A	H02M 7/4837
11527951	12/2021	Jing	N/A	H02M 3/07
11532987	12/2021	Han	N/A	H02M 1/0058
11545897	12/2022	Yen	N/A	H02J 7/007
11557964	12/2022	Pullen	N/A	H02M 1/15
11563337	12/2022	Yuan	N/A	H02J 50/12
11601051	12/2022	Yu	N/A	H02M 7/483
11606032	12/2022	Song	N/A	H02M 3/1582
11621638	12/2022	Zhang	323/271	H02M 3/07
11650644	12/2022	Sporck	710/313	G06F 13/4282
11677260	12/2022	Li	320/116	H02J 7/342
11695334	12/2022	Liu	363/60	H02M 3/072
11705812	12/2022	Yen	323/282	H02M 1/15
11742756	12/2022	Kumar	323/282	H02M 3/07
11777396	12/2022	Liu	363/13	H02M 3/1582
11791721	12/2022	Chen	713/300	H02J 7/007
11791723	12/2022	Giuliano	363/60	H02M 3/07
11831241	12/2022	Jung	N/A	H02M 1/0032
11837887	12/2022	Cho	N/A	H02M 3/158

11855536	12/2022	Giuliano	N/A	H02M 3/07
11923715	12/2023	Song	N/A	H02M 3/33584
12021402	12/2023	Liu	N/A	H02J 7/0016
12051972	12/2023	Ausseresse	N/A	H02M 3/33571
12101020	12/2023	Huang	N/A	H02M 3/1582
2001/0033501	12/2000	Nebrigic	363/49	H02M 3/1588
2002/0014908	12/2001	Lauterbach	327/536	G11C 5/145
2002/0051372	12/2001	Hoshino	363/60	H02M 3/07
2003/0085418	12/2002	Hazucha	257/299	H02M 3/07
2003/0174003	12/2002	Nogami	327/156	H03K 5/04
2003/0174524	12/2002	Botker	363/60	H02M 3/07
2004/0145919	12/2003	Hazucha	363/17	H02M 3/07
2004/0227490	12/2003	MacNair, Jr.	320/132	H02J 7/0069
2004/0263119	12/2003	Meyer	320/116	H02J 7/0042
2005/0162131	12/2004	Sennami	320/128	H01M 50/269
2006/0108975	12/2005	Meyer	320/107	H02J 7/00038
2006/0108983	12/2005	Meyer	320/128	H02J 7/0014
2006/0250122	12/2005	Broughton	323/299	G05F 1/573
2007/0103109	12/2006	Meyer	320/103	H02J 7/0036
2007/0216228	12/2006	Johnson, Jr.	307/64	H02J 9/062
2007/0273334	12/2006	Meyer	320/145	H02J 7/0048
2008/0036432	12/2007	Takada	320/137	H02J 7/34
2008/0042729	12/2007	Huang	327/536	H02M 3/07
2008/0054855	12/2007	Hussain	320/162	H02J 7/0068
2008/0303584	12/2007	Walters	327/536	H02M 3/073
2009/0027022	12/2008	Oyama	327/536	H02M 3/07
2009/0033289	12/2008	Xing	320/140	H02J 7/007182
2009/0033293	12/2008	Xing	323/284	H02J 7/00712
2009/0153101	12/2008	Meyer	320/119	H02J 7/00038
2009/0323378	12/2008	Melse	363/60	H02M 3/07
2009/0326624	12/2008	Melse	607/116	A61N 1/378
2010/0073077	12/2009	Matano	327/536	H02M 3/073
2010/0194294	12/2009	Kitagawa	315/161	H05B 45/38
2010/0321193	12/2009	Liao	340/657	H02J 7/0048
2011/0316634	12/2010	Vasani	330/296	H03F 1/0244
2012/0001596	12/2011	Meyer	320/125	H02J 7/00306
2012/0001599	12/2011	Tanaka	323/205	H02M 1/4208
2012/0049772	12/2011	Moussaoui	318/376	H02M 3/1588
2012/0049936	12/2011	Adkins	327/536	H02M 3/07
2012/0206845	12/2011	Gagne	361/86	H03K 17/063
2012/0212141	12/2011	Ryu	315/186	H05B 45/347
2012/0212293	12/2011	Khlat	330/127	H03F 3/24
2012/0235730	12/2011	Quan	327/536	H02M 3/07
2012/0236444	12/2011	Srivastava	361/56	H03F 1/52
2012/0274394	12/2011	Chan	327/536	H02M 3/07
2012/0313701	12/2011	Khlat	330/127	H02M 3/07
2013/0020960	12/2012	Ren	327/536	H02M 3/07
2013/0113430	12/2012	Kim	320/136	H02J 7/0032
2013/0162230	12/2012	Miyamae	323/271	H02M 3/158
2013/0300385	12/2012	Li	323/271	H02M 3/07

2013/0328613	12/2012	Kay	327/427	G06F 1/263
2013/0335012	12/2012	Meyer	320/107	H02J 7/0013
2014/0210402	12/2013	Sakita	320/107	H02M 3/1584
2014/0210436	12/2013	Zhong	323/271	H02M 3/07
2014/0268946	12/2013	Liu	363/60	H02M 3/07
2014/0306648	12/2013	Le	323/266	H02M 3/07
2014/0306673	12/2013	Le	323/266	H02M 3/158
2015/0015323	12/2014	Rahman	327/536	H02M 3/073
2015/0028801	12/2014	Carobolante	320/108	H02J 50/60
2015/0028803	12/2014	Shevde	320/108	H02J 50/90
2015/0145497	12/2014	Torres	323/283	H02M 3/07
2015/0207401	12/2014	Zhang	323/271	H02M 3/07
2015/0303803	12/2014	Chen	323/271	H02M 3/158
2015/0311720	12/2014	Zhao	307/43	H02J 7/0068
2015/0340887	12/2014	Meyer	320/112	H02J 7/0045
2015/0381035	12/2014	Torres	327/536	H02M 3/16
2015/0381053	12/2014	Mittermaier	323/271	H02J 7/345
2016/0094084	12/2015	Sotani	320/101	H01L 31/02021
2016/0240130	12/2015	Nishimura	N/A	G09G 3/006
2016/0241142	12/2015	Scheel	N/A	H02M 3/073
2017/0055327	12/2016	Kang	N/A	F21V 29/745
2017/0126041	12/2016	Sato	N/A	H02J 7/02
2017/0179715	12/2016	Huang	N/A	H02M 3/155
2017/0185094	12/2016	Atkinson	N/A	G06F 1/3243
2017/0185096	12/2016	Rueger	N/A	G05F 3/262
2017/0237274	12/2016	Lazarev	320/166	H02J 3/28
2017/0244318	12/2016	Giuliano	N/A	H02M 3/07
2017/0256956	12/2016	Irish	N/A	H02M 7/217
2017/0256958	12/2016	Irish	N/A	H02M 7/483
2017/0352403	12/2016	Lee	N/A	G11C 13/0004
2017/0358987	12/2016	Oouchi	N/A	B60L 53/22
2018/0013303	12/2017	Wu	N/A	H02J 7/02
2018/0019665	12/2017	Zhang	N/A	H02M 7/483
2018/0026526	12/2017	Ahmed	323/271	H02M 3/07
2018/0034289	12/2017	Meyer	N/A	H02J 7/0013
2018/0041060	12/2017	Walley	N/A	H02J 7/0045
2018/0076635	12/2017	Maalouf	N/A	H02J 7/02
2018/0091044	12/2017	Salem	N/A	H02M 3/07
2018/0138735	12/2017	Maalouf	N/A	H02J 50/12
2018/0145517	12/2017	Krishna	N/A	H02J 7/007182
2018/0205231	12/2017	Jury	N/A	H02J 3/38
2018/0234011	12/2017	Muramatsu	N/A	H02M 3/073
2018/0278549	12/2017	Mula	N/A	H04L 47/39
2018/0309304	12/2017	Meyer	N/A	H02J 7/0036
2018/0337545	12/2017	Crosby, II	N/A	H02J 7/00712
2018/0341309	12/2017	Sporck	N/A	G06F 13/4295
2018/0366965	12/2017	Ghabra	N/A	B60R 25/406
2019/0089244	12/2018	Koski	N/A	H02M 3/07
2019/0115765	12/2018	Lai	N/A	H02J 7/00712
2019/0115829	12/2018	Oporta	N/A	H02J 7/02

2019/0140537	12/2018	Scheel	N/A	H02M 3/073
2019/0148795	12/2018	Hawley	320/134	H01M 10/441
2019/0173307	12/2018	Zhao	N/A	H02J 7/00
2019/0190284	12/2018	Pinto	N/A	H02J 7/00
2019/0207519	12/2018	Chakraborty	N/A	H02M 1/36
2019/0237982	12/2018	Ghabra	N/A	B60R 25/406
2019/0348849	12/2018	Kun	N/A	H02M 3/158
2019/0348913	12/2018	Zhang	N/A	H02M 3/07
2019/0356142	12/2018	Meyer	N/A	H02J 7/00038
2019/0356149	12/2018	Li	N/A	H02M 3/33576
2019/0386481	12/2018	Cho	N/A	G01R 19/16571
2019/0393777	12/2018	Giuliano	N/A	H02M 3/1582
2020/0036218	12/2019	Maalouf	N/A	H02J 50/10
2020/0127467	12/2019	Li	N/A	H02J 7/342
2020/0136508	12/2019	Bandyopadhyay	N/A	H03K 5/24
2020/0161976	12/2019	Song	N/A	H02M 3/158
2020/0185923	12/2019	Yang	N/A	H02J 3/381
2020/0228006	12/2019	Scheel	N/A	H02M 3/073
2020/0266634	12/2019	Lai	N/A	H02J 7/02
2020/0285260	12/2019	Londak	N/A	G05F 1/575
2020/0303927	12/2019	Tian	N/A	H02M 3/07
2020/0343740	12/2019	Meyer	N/A	H02J 7/0048
2020/0366120	12/2019	Yuan	N/A	H02J 50/12
2020/0373844	12/2019	Ausseresse	N/A	H02M 3/07
2020/0403514	12/2019	Yu	N/A	H02M 3/07
2020/0409403	12/2019	Londak	N/A	G05F 1/575
2021/0067041	12/2020	Cho	N/A	H02M 3/156
2021/0075223	12/2020	Li	N/A	H02M 3/1588
2021/0083572	12/2020	Yen	N/A	H02J 7/06
2021/0083573	12/2020	Yen	N/A	H02M 3/07
2021/0111570	12/2020	Cho	N/A	H02J 7/007192
2021/0194266	12/2020	Song	N/A	H02J 7/007192
2021/0194358	12/2020	Jing	N/A	H02M 1/36
2021/0242771	12/2020	Chen	N/A	H02J 7/0068
2021/0336450	12/2020	Meyer	N/A	H02J 7/00309
2021/0359606	12/2020	Han	N/A	H02M 1/0054
2021/0376719	12/2020	Pullen	N/A	G06F 1/3206
2021/0382535	12/2020	Sporck	N/A	G06F 13/385
2021/0408818	12/2020	Yang	N/A	H02J 50/12
2022/0094277	12/2021	Han	N/A	H02J 7/02
2022/0181907	12/2021	Kasper	N/A	H02M 3/33584
2022/0190714	12/2021	Ye	N/A	H02M 1/007
2022/0224123	12/2021	Li	N/A	H02J 7/02
2022/0224229	12/2021	Giuliano	N/A	H02M 3/1582
2022/0231518	12/2021	Kun	N/A	H02M 1/0054
2022/0255433	12/2021	Wen	N/A	H02M 3/158
2022/0311339	12/2021	Yen	N/A	H02M 3/158
2022/0337078	12/2021	Shao	N/A	H02M 3/07
2022/0396167	12/2021	Sharifipour	N/A	B60L 53/51
2023/0006555	12/2022	Jung	N/A	H02M 3/07

2023/0013025	12/2022	Kumar	N/A	H02M 1/0095
2023/0024417	12/2022	Yamaguchi	N/A	H02J 7/00714
2023/0026736	12/2022	Liu	N/A	H02M 1/0095
2023/0047446	12/2022	Liu	N/A	H02M 1/007
2023/0066436	12/2022	Rutkowski	N/A	H02J 1/08
2023/0088177	12/2022	Giuliano	363/60	H02M 1/0058
2023/0089638	12/2022	Liu	320/106	H02M 3/072
2023/0097692	12/2022	Liu	363/60	H02M 3/158
2023/0102466	12/2022	Huang	323/282	H02M 3/1582
2023/0283096	12/2022	Kun	320/140	H02J 50/10
2023/0318340	12/2022	Shao	307/23	H02M 3/07
2023/0387800	12/2022	Govindarajulu	N/A	H02M 3/1582
2023/0387801	12/2022	Govindarajulu	N/A	H02M 3/158
2023/0412074	12/2022	Giuliano	N/A	H02M 1/42
2024/0055992	12/2023	Jung	N/A	H02M 1/0032
2024/0079883	12/2023	Cho	N/A	H02J 50/80
2024/0088789	12/2023	Giuliano	N/A	H02M 3/07

Primary Examiner: Trischler; John T

Attorney, Agent or Firm: Patterson + Sheridan, L.L.P.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S) (1) This application claims the benefit of priority to U.S. Provisional Application No. 63/033,356, entitled “Trickle Charging a Multi-Cell-in-Series Dead Battery” and filed Jun. 2, 2020, which is expressly incorporated by reference herein in its entirety as if fully set forth below and for all applicable purposes.

TECHNICAL FIELD

(1) Certain aspects of the present disclosure generally relate to electronic circuits and, more particularly, to methods and apparatus for charging a dead multi-cell-in-series battery.

BACKGROUND

(2) A voltage regulator ideally provides a constant direct current (DC) output voltage regardless of changes in load current or input voltage. Voltage regulators may be classified as linear regulators or switching regulators. While linear regulators tend to be relatively compact, many applications may benefit from the increased efficiency of a switching regulator. A linear regulator may be implemented by a low-dropout (LDO) regulator, for example. A switching regulator (also known as a “switching converter” or “switcher”) may be implemented, for example, by a switched-mode power supply (SMPS), such as a buck converter, a boost converter, a buck-boost converter, or a charge pump.

(3) For example, a buck converter is a type of SMPS typically comprising: (1) a high-side switch coupled between a relatively higher voltage rail and a switching node, (2) a low-side switch coupled between the switching node and a relatively lower voltage rail, (3) and an inductor coupled between the switching node and a load (e.g., represented by a shunt capacitive element). The high-side and low-side switches are typically implemented with transistors, although the low-side switch may alternatively be implemented with a diode.

(4) A charge pump is a type of SMPS typically comprising at least one switching device to control the connection of a supply voltage across a load through a capacitor. In a voltage doubler (also

referred to as a “multiply-by-two (X2) charge pump”), for example, the capacitor of the charge pump circuit may initially be connected across the supply, charging the capacitor to the supply voltage. The charge pump circuit may then be reconfigured to connect the capacitor in series with the supply and the load, doubling the voltage across the load. This two-stage cycle is repeated at the switching frequency for the charge pump. Charge pumps may be used to multiply or divide voltages by integer or fractional amounts, depending on the circuit topology.

(5) Power management integrated circuits (power management ICs or PMICs) are used for managing the power scheme of a host system and may include and/or control one or more voltage regulators (e.g., buck converters and/or charge pumps). A PMIC may be used in battery-operated devices, such as mobile phones, tablets, laptops, wearables, etc., to control the flow and direction of electrical power in the devices. The PMIC may perform a variety of functions for the device such as DC-to-DC conversion (e.g., using a voltage regulator as described above), battery charging, power-source selection, voltage scaling, power sequencing, etc.

SUMMARY

(6) The systems, methods, and devices of the disclosure each have several aspects, no single one of which is solely responsible for its desirable attributes. Without limiting the scope of this disclosure as expressed by the claims that follow, some features are discussed briefly below. After considering this discussion, and particularly after reading the section entitled “Detailed Description,” one will understand how the features of this disclosure provide the advantages described herein.

(7) Certain aspects of the present disclosure generally relate to methods and apparatus for charging a dead multi-cell-in-series battery, such as trickle charging such a battery using a charge pump.

(8) Certain aspects of the present disclosure are directed to a battery charging circuit. The battery charging circuit generally includes a charge pump circuit comprising a plurality of switches and a capacitive element, being coupled to a first power supply node and a second power supply node, and being configured to at least one of: multiply a first voltage at the first power supply node to generate a second voltage at the second power supply node; or divide the second voltage at the second power supply node to generate the first voltage at the first power supply node; a driver circuit coupled to the charge pump circuit and configured to drive the plurality of switches in the charge pump circuit; and an arbiter having a first input coupled to the first power supply node, a second input coupled to the second power supply node, a third input coupled to a third power supply node having a third voltage, and an output coupled to a power supply terminal of the driver circuit, the arbiter being configured to select between the first voltage, the second voltage, and the third voltage to power the driver circuit.

(9) Certain aspects of the present disclosure are directed to a power supply system comprising the battery charging circuit described herein. The power supply system further includes a power management circuit, the power management circuit having a switched-mode power supply circuit with an output coupled to the first power supply node of the battery charging circuit.

(10) Certain aspects of the present disclosure are directed to a wireless device comprising the battery charging circuit described herein. The wireless device further includes a multi-cell battery coupled to the second power supply node of the battery charging circuit.

(11) Certain aspects of the present disclosure are directed to a method of supplying power. The method generally includes selecting between a first voltage at a first power supply node, a second voltage at a second power supply node, and a third voltage at a third power supply node to power a driver circuit coupled to a charge pump circuit; and operating at least a portion of the driver circuit powered using the selected first, second, or third voltage.

(12) To the accomplishment of the foregoing and related ends, the one or more aspects comprise the features hereinafter fully described and particularly pointed out in the claims. The following description and the appended drawings set forth in detail certain illustrative features of the one or more aspects. These features are indicative, however, of but a few of the various ways in which the principles of various aspects may be employed.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) So that the manner in which the above-recited features of the present disclosure can be understood in detail, a more particular description, briefly summarized above, may be had by reference to aspects, some of which are illustrated in the appended drawings. It is to be noted, however, that the appended drawings illustrate only certain typical aspects of this disclosure and are therefore not to be considered limiting of its scope, for the description may admit to other equally effective aspects.
 - (2) FIG. 1 is a block diagram of an example device comprising a power management system that includes a power supply circuit and a battery charging circuit, in accordance with certain aspects of the present disclosure.
 - (3) FIG. 2A is a schematic diagram of an example power supply system capable of trickle charging a dead battery using a battery charging circuit with a trickle charger, a battery switch, and two alternative power supply rails.
 - (4) FIG. 2B is a timing diagram illustrating trickle charging the dead battery using the power supply system of FIG. 2A.
 - (5) FIG. 3A is a schematic diagram of an example power supply system capable of trickle charging a dead battery using a battery charging circuit with three alternative power supply rails and without a trickle charger or a battery switch, in accordance with certain aspects of the present disclosure.
 - (6) FIG. 3B is a timing diagram illustrating trickle charging the dead battery using the power supply system of FIG. 3A, in accordance with certain aspects of the present disclosure.
 - (7) FIG. 4 is a flow diagram of example operations for supplying power, in accordance with certain aspects of the present disclosure.
 - (8) FIG. 5 is a flow diagram of example operations for supplying power, in accordance with certain aspects of the present disclosure.
 - (9) To facilitate understanding, identical reference numerals have been used, where possible, to designate identical elements that are common to the figures. It is contemplated that elements disclosed in one aspect may be beneficially utilized on other aspects without specific recitation.
- ### DETAILED DESCRIPTION

- (10) Certain aspects of the present disclosure provide techniques and apparatus for charging a dead multi-cell-in-series battery, such as trickle charging such a battery using a charge pump.
- (11) Various aspects of the disclosure are described more fully hereinafter with reference to the accompanying drawings. This disclosure may, however, be embodied in many different forms and should not be construed as limited to any specific structure or function presented throughout this disclosure. Rather, these aspects are provided so that this disclosure will be thorough and complete, and will fully convey the scope of the disclosure to those skilled in the art. Based on the teachings herein one skilled in the art should appreciate that the scope of the disclosure is intended to cover any aspect of the disclosure disclosed herein, whether implemented independently of or combined with any other aspect of the disclosure. For example, an apparatus may be implemented or a method may be practiced using any number of the aspects set forth herein. In addition, the scope of the disclosure is intended to cover such an apparatus or method which is practiced using other structure, functionality, or structure and functionality in addition to or other than the various aspects of the disclosure set forth herein. It should be understood that any aspect of the disclosure disclosed herein may be embodied by one or more elements of a claim.
- (12) The word “exemplary” is used herein to mean “serving as an example, instance, or illustration.” Any aspect described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other aspects.
- (13) As used herein, the term “connected with” in the various tenses of the verb “connect” may

mean that element A is directly connected to element B or that other elements may be connected between elements A and B (i.e., that element A is indirectly connected with element B). In the case of electrical components, the term “connected with” may also be used herein to mean that a wire, trace, or other electrically conductive material is used to electrically connect elements A and B (and any components electrically connected therebetween).

Example Device

(14) It should be understood that aspects of the present disclosure may be used in a variety of applications. Although the present disclosure is not limited in this respect, the circuits disclosed herein may be used in any of various suitable apparatus, such as in the power supply, battery charging circuit, or power management circuit of a communication system, a video codec, audio equipment such as music players and microphones, a television, camera equipment, and test equipment such as an oscilloscope. Communication systems intended to be included within the scope of the present disclosure include, by way of example only, cellular radiotelephone communication systems, satellite communication systems, two-way radio communication systems, one-way pagers, two-way pagers, personal communication systems (PCS), personal digital assistants (PDAs), and the like.

(15) FIG. 1 illustrates an example device **100** in which aspects of the present disclosure may be implemented. The device **100** may be a battery-operated device such as a cellular phone, a PDA, a handheld device, a wireless device, a laptop computer, a tablet, a smartphone, a wearable device, etc.

(16) The device **100** may include a processor **104** that controls operation of the device **100**. The processor **104** may also be referred to as a central processing unit (CPU). Memory **106**, which may include both read-only memory (ROM) and random access memory (RAM), provides instructions and data to the processor **104**. A portion of the memory **106** may also include non-volatile random access memory (NVRAM). The processor **104** typically performs logical and arithmetic operations based on program instructions stored within the memory **106**.

(17) In certain aspects, the device **100** may also include a housing **108** that may include a transmitter **110** and a receiver **112** to allow transmission and reception of data between the device **100** and a remote location. For certain aspects, the transmitter **110** and receiver **112** may be combined into a transceiver **114**. One or more antennas **116** may be attached or otherwise coupled to the housing **108** and electrically connected to the transceiver **114**. The device **100** may also include (not shown) multiple transmitters, multiple receivers, and/or multiple transceivers.

(18) The device **100** may also include a signal detector **118** that may be used in an effort to detect and quantify the level of signals received by the transceiver **114**. The signal detector **118** may detect such signal parameters as total energy, energy per subcarrier per symbol, and power spectral density, among others. The device **100** may also include a digital signal processor (DSP) **120** for use in processing signals.

(19) The device **100** may further include a battery **122**, which may be used to power the various components of the device **100** (e.g., when another power source—such as a wall adapter or a wireless power charger—is unavailable). The battery **122** may comprise a single cell or multiple cells connected in series. The device **100** may also include a power management system **123** for managing the power from the battery **122**, a wall adapter, and/or a wireless power charger to the various components of the device **100**. The power management system **123** may perform a variety of functions for the device such as DC-to-DC conversion, battery charging, power-source selection, voltage scaling, power sequencing, etc. In certain aspects, the power management system **123** may include a power management integrated circuit (power management IC or PMIC) **124** and one or more power supply circuits, such as a battery charger **125**, which may be controlled by the PMIC. For certain aspects, at least a portion of one or more of the power supply circuits may be integrated in the PMIC **124**. The PMIC **124** and the one or more power supply circuits may include at least a portion of a switched-mode power supply (SMPS) circuit, which may be implemented by any of

various suitable SMPS circuit topologies, such as a buck converter, a buck-boost converter, a three-level buck converter, or a charge pump, such as a multiply-by-two (X2) or multiply-by-three (X3) charge pump.

(20) The various components of the device **100** may be coupled together by a bus system **126**, which may include a power bus, a control signal bus, and/or a status signal bus in addition to a data bus.

Example Trickle Charging Schemes

(21) Battery charging systems (e.g., the battery charger **125** of FIG. **1**) are trending towards higher charging current, which leads to the desire for higher efficiency converters that can operate over a wider battery voltage range. To reduce thermal issues and/or conserve power, it may be desirable to operate such battery charging systems with higher efficiency.

(22) In one example parallel charging solution, the master charger is implemented based on a buck converter topology. The master charger is capable of charging the battery (e.g., the battery **122**) and providing power by itself or may be paralleled with one or more slave chargers. Each of the slave chargers may be implemented, for example, as a switched-capacitor converter (e.g., a divide-by-two (Div2) charge pump) or a switched-mode power supply (SMPS) topology using an inductor (e.g., a buck converter). Charge pump converters may provide a more efficient alternative than buck converters.

(23) Compared with single-cell (1S) battery charging, charging a two-cell-in-series (2S) battery stores two times the power in the battery with the same charging current, thereby offering double the charging rate. A power supply system for charging a 2S battery may include, for example, a buck charger followed by a boost charger, or a buck charger followed by a charge pump capable of voltage multiplying by two (X2). Such a X2 charge pump may also be capable of dividing by two (Div2) when discharging the 2S battery in the opposite direction (i.e., in reverse). Hence, a battery charging circuit with this multiply-by-two and divide-by-two charge pump capability may be referred to as an “X2/D2” circuit or chip. The power source for the X2/D2 circuit may come from a first power supply node, which may come from a buck converter in a power management circuit (e.g., the PMIC **124**), or from a second power supply node, which may come from the 2S battery.

(24) When the 2S battery is dead, the battery may be recharged. However, trying to fast charge a dead battery may introduce a high current that may damage the battery and/or shorten the life of the battery. Therefore, trickle charging may be used to more slowly charge a dead battery. Trickle charging typically involves applying a continuous constant-current charge at a low rate.

(25) FIG. **2A** is a schematic diagram of an example power supply system **200** capable of trickle charging a dead multi-cell battery **201** (e.g., a 2S battery). The power supply system **200** includes a power management circuit **202** (e.g., a PMIC **124**) and a battery charging circuit **204** (e.g., battery charger **125**, such as an X2/D2 chip).

(26) The power management circuit **202** may include a switched-mode power supply (SMPS) **214**, gate drivers **216**, a first battery switch **220** (e.g., transistor QBAT1), a reverse blocking transistor **222**, and control logic **224**. For certain aspects, the SMPS **214** may also include an optional trickle charger **218** in parallel with the first battery switch **220**. The SMPS **214** may be implemented by any of various suitable switching regulators, such as a two-level buck converter (as illustrated in FIG. **2A**) or a three-level buck converter. The control logic **224** may control the gate drivers **216**, which may provide level-shifted outputs to the gates of the power transistors implementing the SMPS **214**. The control logic **224** may also control the reverse blocking transistor **222** and/or the first battery switch **220**. The SMPS **214** may receive power at an input power node **225** (labeled “USB_IN”) from one of multiple potential power sources, such as a wall adapter or other power cable (e.g., a Universal Serial Bus (USB) adapter) connected via USB port **226** or a wireless power charger (not shown). The output of the SMPS **214** at system power node **227** (labeled “VPH,” but also referred to as “VPH_PWR”) may provide power to one or more core PMICs **228** and/or other circuits within a device (e.g., device **100**). The first battery switch **220** may be coupled between the

system power node **227** and a first power supply node **213** (labeled “VBAT1,” but also referred to as “VBAT_PWR”) for the battery charging circuit **204**.

(27) The battery charging circuit **204** in FIG. 2A may include a charge pump circuit **206**, a driver circuit **207**, a trickle charger **208**, a second battery switch **210** (e.g., transistor QBAT2), and an arbiter **212**. The second battery switch **210** and the trickle charger **208** may be coupled in parallel between the charge pump circuit **206** and a second power supply node **215** (labeled “VBAT2”) for the battery charging circuit **204**. The second power supply node **214** may be coupled to the battery **201**. The arbiter **212** may be configured to select between two alternative power supply rails (e.g., VBAT1 and VBAT2) for powering gate drivers in the driver circuit **207**, as described below.

(28) While the charge pump circuit **206** is generally described herein with the example of an X2/D2 charge pump, it is to be understood that the charge pump circuit **206** may be implemented with other configurations, such as an X3/D3 charge pump. The charge pump circuit **206** may include a plurality of switches (which may be implemented by a first transistor Q1, a second transistor Q2, a third transistor Q3, and a fourth transistor Q4 as shown) and a flying capacitive element Cfly. Transistor Q2 may be coupled to transistor Q1 via a first node (labeled “CFH”), transistor Q3 may be coupled to transistor Q2 via a second node (which may also be or be coupled to the first power supply node **213** having voltage VBAT1), and transistor Q4 may be coupled to transistor Q3 via a third node (labeled “CFL”). For certain aspects, the transistors Q1-Q4 may be implemented as n-type metal-oxide-semiconductor (NMOS) transistors, as illustrated in FIG. 2A. In this case, the drain of transistor Q2 may be coupled to the source of transistor Q1, the drain of transistor Q3 may be coupled to the source of transistor Q2, and the drain of transistor Q4 may be coupled to the source of transistor Q3. The source of transistor Q4 may be coupled to a reference potential node (e.g., electrical ground, labeled “PGND”) for the circuit. The flying capacitive element Cfly may have a first terminal coupled to the first node (CFH) and have a second terminal coupled to the third node (CFL).

(29) Control logic (not shown) may control operation of the charge pump circuit **206** in the battery charger. For example, the control logic may control operation of transistors Q1-Q4 via output signals to the inputs of respective gate drivers in the driver circuit **207**. The outputs of the gate drivers are coupled to respective gates of transistors Q1-Q4. The gate drivers may each receive power at a power supply terminal coupled to a common power supply node **217** (labeled “VDD”). Inputs to the arbiter **212** may be coupled to the first power supply node **213** (VBAT1) and to the second power supply node **215** (VBAT2), and the control logic may control the arbiter **212** to select which power level to output at the common power supply node **217**.

(30) The control logic may control operation of the charge pump circuit **206** to cycle through different phases $\Phi 1$ and $\Phi 2$, with various combinations of transistors Q1-Q4 in different open and closed states. During $\Phi 1$, transistors Q2 and Q4 are closed, while transistor Q1 and Q3 are open, thereby charging flying capacitive element Cfly to VBAT1 from CFH to CFL. During $\Phi 2$, transistors Q1 and Q3 are closed, while transistors Q2 and Q4 are open, thereby bootstrapping VBAT2 at the second power supply node **215** to $2 \times \text{VBAT1}$ by adding the voltage across the flying capacitive element Cfly to the voltage at the first power supply node **213**. In this manner, the charge pump circuit **206** acts as an X2 charge pump.

(31) FIG. 2B is a timing diagram **250** illustrating trickle charging a dead multi-cell battery **201** (e.g., a dead 2S battery) using the power supply system **200** of FIG. 2A. Initially, VBAT1 and VBAT2=0 V (dead battery), and then at time $t_{\text{sub.0}}$, a power source capable of charging the multi-cell battery **201** is provided. For example, a user may plug in a wall adapter or other power cable (e.g., USB)). At time $t_{\text{sub.1}}$, the power management circuit **202** may bring up VPH_PWR to boot the system, using the buck converter illustrated in FIG. 2A, for example. For certain aspects, the power management circuit **202** trickle charges up VBAT_PWR (VBAT1 for the battery charger) starting at time $t_{\text{sub.2}}$ using the trickle charger **218** in the power management circuit. For other aspects, the power management circuit **202** may quickly bring up VBAT_PWR (VBAT1) (e.g.,

without using the trickle charger **218** or when the trickle charger is not present).

(32) The battery charging circuit **204** may have an undervoltage lockout (UVLO) threshold voltage. At time t.sub.3 when VBAT1 is greater than the UVLO threshold, the power management circuit **202** may enable the battery charging circuit **204** (via transition of an enable signal, such as SMB_EN, at time t.sub.4) to soft start and bring up an intermediate voltage (e.g., MID_MB) at node **211**, with the second battery switch **210** open (e.g., with transistor QBAT2 off). For certain aspects, the battery charging circuit **204** may most likely not directly soft-start into the dead multi-cell battery **201**. Rather, trickle charging the multi-cell battery **201** may utilize a well-controlled low current. After the intermediate voltage (e.g., MID_SMB) reaches $2 \times \text{VBAT1}$ for a 2S battery (or $N \times \text{VBAT1}$ for a battery with N cells) at time t.sub.5, the trickle charger **208** may be turned on at time t.sub.6 to trickle charge the multi-cell battery **201** and bring up VBAT2 (i.e., increase the voltage of VBAT2). After VBAT2 reaches $2 \times \text{VBAT1}$ for a 2S battery (or $N \times \text{VBAT1}$ for battery with N cells), the battery charging circuit **204** may close the second battery switch (e.g., turn on transistor QBAT2) at time t.sub.7 and may notify the power management circuit **202** to start normal charging (e.g., fast charging). Therefore, trickle charging in this manner involves four states: power management circuit trickle charging between times t.sub.2 and t.sub.3, battery charger soft start between times t.sub.4 and t.sub.5, battery charger trickle charging between times t.sub.6 and t.sub.7, and normal charging (e.g., fast charging) after time t.sub.7.

(33) Trickle charging using the power supply system **200** may not be as ideal as possible. For example, the battery charging circuit **204** in FIG. 2A has a second battery switch **210** (e.g., transistor QBAT2), which occupies extra area. Furthermore, the on-resistance of transistor QBAT2 may be associated with power loss during discharging of the multi-cell battery **201**. In other words, when the multi-cell battery **201** is powering the device (providing power to the system power node **227** (VPH_PWR)) instead of a wall adapter, USB, or other external source), the on-resistance of transistor QBAT2 dissipates some power. Furthermore, the battery charging circuit **204** in FIG. 2A has a trickle charger **208**, which occupies semiconductor space and adds costs to the battery charging circuit. Moreover, this trickle-charging scheme may be considered to be complicated, involving back-and-forth handshaking between the power management circuit **202** and the battery charging circuit **204**.

(34) Accordingly, certain aspects of the present disclosure provide techniques and apparatus for trickle charging a multi-cell-in-series battery with a battery charger that lacks a trickle charger and a battery switch (e.g., transistor QBAT2). Instead, the battery charger may be provided with three alternative power supply rails.

(35) FIG. 3A is a schematic diagram of an example power supply system **300**, in accordance with certain aspects of the present disclosure. As shown, the example power supply system **300** is capable of trickle charging a dead two-cell-in-series (2S) battery, although it is to be understood that the scope of the present disclosure includes batteries with more than two cells (e.g., three-cell-in-series (3S), four-cell-in-series (4S) batteries, or n-cell-in-series, where n is any integer greater than 1) and a battery charging circuit (e.g., X3D3, X4D4, or XnDn) capable of charging and/or discharging such an n-cell-in-series battery.

(36) In the power supply system **300**, the battery charging circuit **304** is provided with a third power supply voltage node **310** (labeled "VDD5"), which may be used during trickle charging of the dead battery **201**. When both the first power supply voltage (e.g., VBAT1) and the second power supply voltage (e.g., VBAT2) are low, this third power supply voltage (VDD5) can supply the analog and digital circuits of the battery charging circuit **304** to allow operation thereof. This third power supply voltage may be provided from the power management circuit **202** (e.g., the PMIC **124**) or may be provided from a power source (e.g., an LDO or SMPS (buck, boost, etc.) outside of the power management circuit. As an example, the third power supply voltage may be the same as the driver power supply for the power management circuit's own SMPS (e.g., VDD5 may be used to power the gate drivers **216**).

(37) The battery charging circuit **304** in FIG. **3A** may include an arbiter **312** configured to select between three alternative power supply rails (e.g., VBAT1, VBAT2, and VDD5). Control logic (not shown) may control the arbiter **312** to select which power level to output at the common power supply node **217**. However, the battery charging circuit **304** in FIG. **3A** may not include a trickle charger (e.g., trickle charger **208**) or a battery switch (e.g., transistor QBAT2). Rather, the drain of transistor Q1 may be coupled to the second power supply node **215** (VBAT2).

(38) FIG. **3B** is a timing diagram **350** illustrating trickle charging a dead multi-cell battery **201** (e.g., a dead 2S battery) using the power supply system **300** of FIG. **3A**, in accordance with certain aspects of the present disclosure. Initially, VBAT1 and VBAT2=0 V (dead battery), and then at time t.sub.0, a power source capable of charging the multi-cell battery **201** is provided. For example, a user may plug in a wall adapter or other power cable (e.g., USB). The third power supply voltage (e.g., VDD5) may be generated at time t.sub.1. For certain aspects, the power management circuit **202** generates the third power supply voltage, while in other aspects, the third power supply voltage is supplied by another circuit. At time t.sub.2 (which may occur before or after time t.sub.1), the power management circuit **202** may bring up VPH_PWR to boot the system, using the buck converter of FIG. **3A**, for example. At time t.sub.3, the power management circuit **202** may also enable the battery charging circuit **304** with the transition of an enable signal (e.g., SMB_EN changing from logic low to logic high). The power management circuit **202** trickle charges up VBAT_PWR (VBAT1 for the battery charger) starting at time t.sub.4 using the trickle charger **218**, with a trickle charge current I.sub.TRKL. Concurrently with VBAT_PWR (VBAT1) being trickle charged, the battery charging circuit **304** operates with the third supply voltage (VDD5) and trickle charges the multi-cell battery **201** with half the trickle charge current ($I_{\text{sub.TRKL}}/2$), which also slowly brings up VBAT2. When the second power supply voltage (e.g., VBAT2) reaches the fast-charge threshold (e.g., $2 \times \text{VBAT1}$) at time t.sub.5, fast charging may begin. Therefore, trickle charging in this manner involves two states: power management circuit trickle charging simultaneously with battery charging circuit trickle charging between times t.sub.4 and t.sub.5, followed by normal charging (e.g., fast charging) after time t.sub.5.

(39) Trickle charging using the power supply system **300** of FIG. **3A** may provide some advantages over trickle charging using the power supply system **200** of FIG. **2A**. For example, no battery switch (e.g., transistor QBAT2) is used in the battery charging circuit **304**, thereby saving the area consumption and power loss during discharging of the battery **201**. Furthermore, no trickle charger is used in the battery charging circuit **304**, thus reducing the occupied semiconductor area and cost. Moreover, this trickle-charging scheme in power supply system **300** may be considered to be simpler and more straightforward, without the back-and-forth handshaking between the power management circuit and the battery charging circuit.

Example Operations

(40) FIG. **4** is a flow diagram of example operations **400** for supplying power, in accordance with certain aspects of the present disclosure. The operations **400** may be performed by a power supply system (e.g., the power supply system **300** of FIG. **3A**). FIG. **5** is a flow diagram of example operations **500** for supplying power, in accordance with certain aspects of the present disclosure.

(41) The operations **400** may begin, at block **402**, with the power supply system selecting between a first voltage (e.g., VBAT1) at a first power supply node (e.g., first power supply node **213**), a second voltage (e.g., VBAT2) at a second power supply node (e.g., second power supply node **215**), and a third voltage (e.g., VDD5) at a third power supply node (e.g., third power supply voltage node **310**) to power a driver circuit (e.g., driver circuit **207**) coupled to a charge pump circuit (e.g., charge pump circuit **206**). At block **404**, the power supply system may operate at least a portion of the driver circuit (e.g., gate drivers for transistors Q1 and Q2), which may be powered using the selected first, second, or third voltage.

(42) According to certain aspects, the selecting at block **402** includes selecting the third voltage when the third voltage is higher than the first voltage and the second voltage (e.g., block **502**).

(43) According to certain aspects, the selecting at block **402** includes selecting the third voltage when the first voltage and the second voltage are indicative of a dead battery (e.g., multi-cell battery **201**) coupled to the second power supply node (e.g., block **504**).

(44) According to certain aspects, the operations further involve at least one of: the charge pump circuit multiplying the first voltage at the first power supply node to generate the second voltage at the second power supply node (e.g., block **506**); or the charge pump circuit dividing the second voltage at the second power supply node to generate the first voltage at the first power supply node (e.g., block **508**).

(45) According to certain aspects, the operations **400** further include generating the third voltage at the third power supply node with a voltage regulator (e.g., an LDO, block **510**).

(46) According to certain aspects (e.g., block **512**), a multi-cell battery (e.g., multi-cell battery **201**) coupled to the second power supply node is dead. In this case, the first, second, and third voltages may be zero at a first moment (e.g., at a time before time $t_{sub.0}$). The operations **400** may further involve receiving power at a second moment (e.g., at time $t_{sub.0}$) after the first moment and bringing up the third voltage at a third moment (e.g., at time $t_{sub.1}$) after the second moment. For certain aspects, the operations **400** further include receiving an enablement signal (e.g., `SMB_EN`). In this case, the selecting at block **402** may involve selecting the third voltage in response to the enablement signal. For certain aspects (e.g., block **514**), the operations **400** may further include trickle charging the first power supply node and trickle charging the battery via the second power supply node by powering at least a portion of the driver circuit using the third voltage. For certain aspects (e.g., block **516**), the operations **400** may further include normally charging (e.g., fast charging, as opposed to trickle charging) the battery via the second power supply node after the second voltage reaches a threshold voltage (e.g., $2 \times V_{BAT1}$).

Example Aspects

(47) In addition to the various aspects described above, specific combinations of aspects are within the scope of the disclosure, some of which are detailed below:

(48) Aspect 1: A battery charging circuit comprising: a charge pump circuit comprising a plurality of switches and a capacitive element, being coupled to a first power supply node and a second power supply node, and being configured to at least one of: multiply a first voltage at the first power supply node to generate a second voltage at the second power supply node; or divide the second voltage at the second power supply node to generate the first voltage at the first power supply node; a driver circuit coupled to the charge pump circuit and configured to drive the plurality of switches in the charge pump circuit; and an arbiter having a first input coupled to the first power supply node, a second input coupled to the second power supply node, a third input coupled to a third power supply node having a third voltage, and an output coupled to a power supply terminal of the driver circuit, the arbiter being configured to select between the first voltage, the second voltage, and the third voltage to power the driver circuit.

(49) Aspect 2: The battery charging circuit of Aspect 1, wherein the arbiter is configured to select the third voltage when the third voltage is higher than the first voltage and the second voltage.

(50) Aspect 3: The battery charging circuit of Aspect 1 or 2, wherein the arbiter is configured to select the third voltage when the first voltage and the second voltage are indicative of a dead battery coupled to the second power supply node.

(51) Aspect 4: The battery charging circuit of any preceding Aspect, wherein the plurality of switches in the charge pump circuit comprises: a first switch coupled between the second power supply node and a first terminal of the capacitive element; a second switch coupled in series with the first switch and coupled between the first terminal of the capacitive element and the first power supply node; a third switch coupled in series with the second switch and coupled between the first power supply node and a second terminal of the capacitive element; and a fourth switch coupled in series with the third switch and coupled between the second terminal of the capacitive element and a reference potential node.

- (52) Aspect 5: The battery charging circuit of Aspect 4, wherein the first switch is connected to the second power supply node.
- (53) Aspect 6: The battery charging circuit of Aspect 4 or 5, wherein the battery charging circuit lacks a trickle charger between the first switch and the second power supply node.
- (54) Aspect 7: The battery charging circuit of any of Aspects 4-6, wherein the battery charging circuit lacks a fifth switch between the first switch and the second power supply node.
- (55) Aspect 8: The battery charging circuit of any of Aspects 4-7, wherein: the first, second, third, and fourth switches are implemented by first, second, third, and fourth transistors, respectively; a drain of the second transistor is coupled to a source of the first transistor; a drain of the third transistor is coupled to a source of the second transistor; and a drain of the fourth transistor is coupled to a source of the third transistor.
- (56) Aspect 9: The battery charging circuit of Aspect 8, wherein the first, second, third, and fourth transistors comprise n-type metal-oxide-semiconductor (NMOS) transistors.
- (57) Aspect 10: The battery charging circuit of any preceding Aspect, wherein the second power supply node is configured to couple to a terminal of a multi-cell battery.
- (58) Aspect 11: The battery charging circuit of any preceding Aspect, wherein the first power supply node is configured to couple to an output of a switched-mode power supply circuit.
- (59) Aspect 12: The battery charging circuit of any preceding Aspect, wherein the charge pump circuit is configured to at least one of: double the first voltage at the first power supply node to generate the second voltage at the second power supply node; or half the second voltage at the second power supply node to generate the first voltage at the first power supply node.
- (60) Aspect 13: A power supply system comprising the battery charging circuit of any of Aspects 1-10 and 12, the power supply system further comprising a power management circuit, the power management circuit having a switched-mode power supply circuit with an output coupled to the first power supply node of the battery charging circuit.
- (61) Aspect 14: The power supply system of Aspect 13, further comprising a voltage regulator having an output coupled to the third power supply node and configured to generate the third voltage.
- (62) Aspect 15: The power supply system of Aspect 13, wherein the power management circuit is configured to generate the third voltage.
- (63) Aspect 16: The power supply system of any of Aspects 13-15, further comprising a switch coupled between the output of the switched-mode power supply circuit and the first power supply node.
- (64) Aspect 17: The power supply system of Aspect 16, further comprising a trickle charger coupled in parallel with the switch and coupled between the output of the switched-mode power supply circuit and the first power supply node.
- (65) Aspect 18: A wireless device comprising the battery charging circuit of any of Aspects 1-9, 11, and 12, the wireless device further comprising a multi-cell battery coupled to the second power supply node of the battery charging circuit.
- (66) Aspect 19: A method of supplying power, comprising: selecting between a first voltage at a first power supply node, a second voltage at a second power supply node, and a third voltage at a third power supply node to power a driver circuit coupled to a charge pump circuit; and operating at least a portion of the driver circuit powered using the selected first, second, or third voltage.
- (67) Aspect 20: The method of Aspect 19, wherein the selecting comprises selecting the third voltage when the third voltage is higher than the first voltage and the second voltage.
- (68) Aspect 21: The method of Aspect 19 or 20, wherein the selecting comprises selecting the third voltage when the first voltage and the second voltage are indicative of a dead battery coupled to the second power supply node.
- (69) Aspect 22: The method of any of Aspects 19-21, further comprising multiplying, with the charge pump circuit, the first voltage at the first power supply node to generate the second voltage

at the second power supply node.

(70) Aspect 23: The method of any of Aspects 19-21, further comprising dividing, with the charge pump circuit, the second voltage at the second power supply node to generate the first voltage at the first power supply node.

(71) Aspect 24: The method of any of Aspects 19-23, further comprising generating the third voltage at the third power supply node with a low dropout voltage regulator.

(72) Aspect 25: The method of any of Aspects 19, 20, and 22-24, wherein a multi-cell battery coupled to the second power supply node is dead, wherein the first, second, and third voltages are zero at a first moment, and wherein the method further comprises: receiving power at a second moment after the first moment; and bringing up the third voltage at a third moment after the second moment.

(73) Aspect 26: The method of Aspect 25, further comprising: receiving an enablement signal, wherein the selecting comprises selecting the third voltage in response to the enablement signal; trickle charging the first power supply node; and trickle charging the battery via the second power supply node by powering at least a portion of the driver circuit using the third voltage.

(74) Aspect 27: The method of Aspect 26, further comprising normally charging the battery via the second power supply node after the second voltage reaches a threshold voltage.

(75) The various operations of methods described above may be performed by any suitable means capable of performing the corresponding functions. The means may include various hardware and/or software component(s) and/or module(s), including, but not limited to a circuit, an application-specific integrated circuit (ASIC), or processor. Generally, where there are operations illustrated in figures, those operations may have corresponding counterpart means-plus-function components with similar numbering.

(76) As used herein, the term “determining” encompasses a wide variety of actions. For example, “determining” may include calculating, computing, processing, deriving, investigating, looking up (e.g., looking up in a table, a database, or another data structure), ascertaining, and the like. Also, “determining” may include receiving (e.g., receiving information), accessing (e.g., accessing data in a memory), and the like. Also, “determining” may include resolving, selecting, choosing, establishing, and the like.

(77) As used herein, a phrase referring to “at least one of” a list of items refers to any combination of those items, including single members. As an example, “at least one of: a, b, or c” is intended to cover: a, b, c, a-b, a-c, b-c, and a-b-c, as well as any combination with multiples of the same element (e.g., a-a, a-a-a, a-a-b, a-a-c, a-b-b, a-c-c, b-b, b-b-b, b-b-c, c-c, and c-c-c or any other ordering of a, b, and c).

(78) The methods disclosed herein comprise one or more steps or actions for achieving the described method. The method steps and/or actions may be interchanged with one another without departing from the scope of the claims. In other words, unless a specific order of steps or actions is specified, the order and/or use of specific steps and/or actions may be modified without departing from the scope of the claims.

(79) It is to be understood that the claims are not limited to the precise configuration and components illustrated above. Various modifications, changes and variations may be made in the arrangement, operation, and details of the methods and apparatus described above without departing from the scope of the claims.

Claims

1. A battery charging circuit comprising: a charge pump circuit comprising a plurality of switches and a capacitive element, being coupled to a first power supply node and a second power supply node, and being configured to at least one of: multiply a first voltage at the first power supply node to generate a second voltage at the second power supply node; or divide the second voltage at the

second power supply node to generate the first voltage at the first power supply node; a driver circuit coupled to the charge pump circuit and configured to drive the plurality of switches in the charge pump circuit; and an arbiter having a first input coupled to the first power supply node, a second input coupled to the second power supply node, a third input coupled to a third power supply node having a third voltage, and an output coupled to a power supply terminal of the driver circuit, the arbiter being configured to select between the first voltage, the second voltage, and the third voltage to power the driver circuit, wherein the second power supply node is configured to couple to a terminal of a battery, and wherein the plurality of switches in the charge pump circuit comprises: a first switch coupled between the second power supply node and a first terminal of the capacitive element; a second switch coupled in series with the first switch and coupled between the first terminal of the capacitive element and the first power supply node; a third switch coupled in series with the second switch and coupled between the first power supply node and a second terminal of the capacitive element; and a fourth switch coupled in series with the third switch and coupled between the second terminal of the capacitive element and a reference potential node.

2. The battery charging circuit of claim 1, wherein the arbiter is configured to select the third voltage when the third voltage is higher than the first voltage and the second voltage.
3. The battery charging circuit of claim 1, wherein the arbiter is configured to select the third voltage when the first voltage and the second voltage are indicative of a dead battery coupled to the second power supply node.
4. The battery charging circuit of claim 1, wherein the first switch is connected to the second power supply node and wherein the second power supply node is connected to the terminal of the battery.
5. The battery charging circuit of claim 1, wherein the battery charging circuit lacks a trickle charger between the first switch and the second power supply node.
6. The battery charging circuit of claim 1, wherein the battery charging circuit lacks a fifth switch between the first switch and the second power supply node.
7. The battery charging circuit of claim 1, wherein the second power supply node is configured to couple to a terminal of a multi-cell battery.
8. The battery charging circuit of claim 1, wherein the first power supply node is configured to couple to an output of a switched-mode power supply circuit.
9. The battery charging circuit of claim 1, wherein the charge pump circuit is configured to at least one of: double the first voltage at the first power supply node to generate the second voltage at the second power supply node; or half the second voltage at the second power supply node to generate the first voltage at the first power supply node.
10. A wireless device comprising the battery charging circuit of claim 1, the wireless device further comprising a multi-cell battery coupled to the second power supply node of the battery charging circuit.
11. The battery charging circuit of claim 1, wherein: the first, second, third, and fourth switches are implemented by first, second, third, and fourth transistors, respectively; a drain of the first transistor is coupled to the second power supply node; a drain of the second transistor is coupled to a source of the first transistor; a drain of the third transistor is coupled to a source of the second transistor; and a drain of the fourth transistor is coupled to a source of the third transistor.
12. The battery charging circuit of claim 11, wherein the first, second, third, and fourth transistors comprise n-type metal-oxide-semiconductor (NMOS) transistors.
13. A power supply system comprising the battery charging circuit of claim 1, the power supply system further comprising a power management circuit, the power management circuit having a switched-mode power supply circuit with an output coupled to the first power supply node of the battery charging circuit.
14. The power supply system of claim 13, further comprising a voltage regulator having an output coupled to the third power supply node and configured to generate the third voltage.
15. The power supply system of claim 13, wherein the power management circuit is configured to

generate the third voltage.

16. The power supply system of claim 13, further comprising a switch coupled between the output of the switched-mode power supply circuit and the first power supply node.

17. The power supply system of claim 16, further comprising a trickle charger coupled in parallel with the switch and coupled between the output of the switched-mode power supply circuit and the first power supply node.

18. A method of supplying power, comprising: selecting between a first voltage at a first power supply node, a second voltage at a second power supply node for coupling to a terminal of a battery, and a third voltage at a third power supply node to power a driver circuit coupled to a charge pump circuit, wherein the charge pump circuit includes a plurality of switches and a capacitive element and wherein the plurality of switches comprise: a first switch coupled between the second power supply node and a first terminal of the capacitive element; a second switch coupled in series with the first switch and coupled between the first terminal of the capacitive element and the first power supply node; a third switch coupled in series with the second switch and coupled between the first power supply node and a second terminal of the capacitive element; and a fourth switch coupled in series with the third switch and coupled between the second terminal of the capacitive element and a reference potential node; and operating at least a portion of the driver circuit powered using the selected first, second, or third voltage.

19. The method of claim 18, wherein the selecting comprises selecting the third voltage when the third voltage is higher than the first voltage and the second voltage.

20. The method of claim 18, wherein the selecting comprises selecting the third voltage when the first voltage and the second voltage are indicative of a dead battery coupled to the second power supply node.

21. The method of claim 18, further comprising multiplying, with the charge pump circuit, the first voltage at the first power supply node to generate the second voltage at the second power supply node.

22. The method of claim 18, further comprising dividing, with the charge pump circuit, the second voltage at the second power supply node to generate the first voltage at the first power supply node.

23. The method of claim 18, further comprising generating the third voltage at the third power supply node with a low dropout voltage regulator.

24. The method of claim 18, wherein the battery comprises a multi-cell battery that is coupled to the second power supply node and is dead, wherein the first voltage, the second voltage, and the third voltage are at a voltage level at a first moment, and wherein the method further comprises: receiving power at a second moment after the first moment; and bringing up the third voltage at a third moment after the second moment.

25. The method of claim 24, further comprising: receiving an enablement signal, wherein the selecting comprises selecting the third voltage in response to the enablement signal; trickle charging the first power supply node; and trickle charging the multi-cell battery via the second power supply node by powering at least a portion of the driver circuit using the third voltage.

26. The method of claim 25, further comprising normally charging the multi-cell battery via the second power supply node after the second voltage reaches a threshold voltage.
