

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12411161
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Lee; Ungryeol et al.

Chamber for measuring performance of antenna, system including the same, and operating method thereof

Abstract

An anechoic antenna chamber includes: a holder on which a device under test (DUT) is configured to be mounted, at least one first antenna configured to radiate a first test signal of a first frequency band, a second antenna provided at an inner side of the antenna chamber and configured to radiate a second test signal of a second frequency, at least one driver configured to rotate the DUT, and a control circuit operatively connected with the at least one first antenna, the second antenna, and the at least one driving part. The control circuit is configured to control the driver to rotate the DUT and control the at least one first antenna to radiate the first test signal having an intensity of a specified range and control the second antenna to radiate the second test signal, while rotating the DUT.

Inventors: Lee; Ungryeol (Suwon-si, KR), Kim; Myeonggeun (Suwon-si, KR), Park; Nohwan (Suwon-si, KR), Park; Jongseo (Suwon-si, KR), Lee; Jaeyup (Suwon-si, KR), Choi; Yungil (Suwon-si, KR)

Applicant: SAMSUNG ELECTRONICS CO., LTD. (Suwon-si, KR)

Family ID: 85572461

Assignee: Samsung Electronics Co., Ltd. (Suwon-si, KR)

Appl. No.: 17/903382

Filed: September 06, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230089785 A1	Mar. 23, 2023

Foreign Application Priority Data

KR	10-2021-0123254	Sep. 15, 2021
----	-----------------	---------------

Related U.S. Application Data

continuation parent-doc WO PCT/KR2022/012820 20220826 PENDING child-doc US 17903382

Publication Classification

Int. Cl.: G01R29/10 (20060101); G01R29/08 (20060101); H04B17/11 (20150101); H04B17/15 (20150101); H04B17/21 (20150101)

U.S. Cl.:

CPC G01R29/0821 (20130101); H04B17/11 (20150115); H04B17/21 (20150115);

Field of Classification Search

CPC: H01Q (1/12); H01Q (1/27); H01Q (3/00); H01Q (3/08); H01Q (3/12); G01R (29/0821); G01R (29/10); G01R (29/105); H04B (17/00); H04B (17/0085); H04B (17/11); H04B (17/15); H04B (17/21); H04B (17/29)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
7873339	12/2010	Qi	455/425	H04B 17/29
11047894	12/2020	Kvarnstrand et al.	N/A	N/A
11515952	12/2021	Hsieh	N/A	H04W 52/50
2010/0109957	12/2009	Moon et al.	N/A	N/A
2013/0271317	12/2012	Goel et al.	N/A	N/A
2014/0087668	12/2013	Mow	455/67.14	H04W 24/08
2014/0256267	12/2013	Chien	455/67.12	H04B 17/15
2017/0223559	12/2016	Kong	N/A	H04B 7/0413
2020/0244377	12/2019	Maruo	N/A	H04B 5/20
2020/0341044	12/2019	Kvarnstrand	N/A	H04B 17/309
2021/0399811	12/2020	Endo	N/A	H04B 17/15
2023/0033833	12/2022	Maruo	N/A	G01R 29/105

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
------------	------------------	---------	-----

OTHER PUBLICATIONS

Search Report and Written Opinion dated Dec. 20, 2022 issued in International Patent Application No. PCT/KR2022/012820. cited by applicant

Primary Examiner: Pham; Thai

Attorney, Agent or Firm: Nixon & Vanderhye P.C.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of International Application No. PCT/KR2022/012820 designating the United States, filed on Aug. 26, 2022, in the Korean Intellectual Property Receiving Office and claiming priority to Korean Patent Application No. 10-2021-0123254, filed on Sep. 15, 2021, in the Korean Intellectual Property Office, the disclosures of which are incorporated by reference herein in their entireties.

BACKGROUND

Field

(1) The disclosure relates to a chamber for measuring the performance of an antenna, a system including the same, and an operating method thereof.

Description of Related Art

(2) With the development of information technology (IT), various types of electronic devices such as smartphones, tablet personal computers (PCs) have been spread widely. The electronic device may transmit and receive a wireless signal with another electronic device or a base station using an antenna. The electronic device may perform various functions (e.g., wireless communication and positioning) based on information included in the wireless signal.

(3) An anechoic antenna chamber may be used to measure antenna performance of the electronic device. The antenna chamber may be a small room surrounded by a wall having an anechoic characteristic, which may at least one antenna for radiating a test signal and a device under test (DUT) for receiving the test signal.

(4) The antenna chamber may be designed to measure communication performance of the DUT for the test signal in various use environments. For example, to measure a receive sensitivity of the test signal received by the DUT at various angles, the antenna chamber may rotate the DUT while radiating the test signal using the at least one antenna. For example, when the DUT is used in the city center, an obstacle, which obstructs movement of a signal, may be disposed in the antenna chamber to measure communication performance of the DUT.

(5) A test signal may include a plurality of test signals (e.g., a first test signal and a second test signal), each of which has a different frequency. The measurement of a receive sensitivity of a test signal (e.g., the second test signal) to be measured among the plurality of test signals may be based on another test signal (e.g., the first test signal). For example, a DUT may measure a receive sensitivity of the second test signal in response to that the first test signal is received.

(6) An intensity of the first test signal received by the DUT may be a weak electric field, at a specific angle. Alternatively, the DUT may fail to receive the first test signal at the specific angle. In this case, the measurement of a receive sensitivity for the second test signal, which is performed in the antenna chamber, may be inaccurate. A method for improving the accuracy of measuring a receive sensitivity of the second test signal is needed.

SUMMARY

- (7) In accordance with an example embodiment of the disclosure, an anechoic antenna chamber is provided. The anechoic antenna chamber may include: a holder configured to provide a mount on which a device under test (DUT) is mounted, at least one first antenna configured to radiate a first test signal of a first frequency band, a second antenna provided at an inner side of the antenna chamber and configured to radiate a second test signal of a second frequency, at least one driver configured to rotate the DUT, and a control circuit operatively connected with the at least one first antenna, the second antenna, and the at least one driver. The control circuit may be configured to rotate the DUT using the at least one driver and control the first antenna to radiate the first test signal having an intensity of a specified range and control the second antenna to radiate the second test signal, while rotating the DUT.
- (8) According to various example embodiments of the disclosure, the antenna chamber may maintain some (e.g., a first test signal) of test signals received by a DUT at a specified level, thus improving the accuracy of measuring a receive sensitivity of a test signal (e.g., a second test signal) to be measured.
- (9) In addition, various effects ascertained directly or indirectly through the disclosure may be provided.
- (10) The effects that are achieved through various example embodiments of the disclosure may not be limited to what has been particularly described herein, and other advantages not described herein may be more clearly understood from the following detailed description by persons skilled in the art.
-

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) The above and other aspects, features and advantages of certain embodiments of the present disclosure will be more apparent from the following detailed description, taken in conjunction with the accompanying drawings, in which:
- (2) FIG. 1 is a block diagram illustrating an example electronic device in a network environment according to various embodiments;
- (3) FIG. 2 is a block diagram illustrating an example configuration of an antenna chamber, according to various embodiments;
- (4) FIG. 3 is a diagram illustrating an example antenna chamber, according to various embodiments;
- (5) FIG. 4A is a diagram illustrating an example radiation pattern formed by a test signal according to various embodiments;
- (6) FIG. 4B is a diagram illustrating an example radiation pattern formed by a test signal according to various embodiments;
- (7) FIG. 5 is a diagram illustrating an example antenna chamber structure for improving the accuracy of measuring a receive sensitivity, according to various embodiments;
- (8) FIG. 6 is a diagram illustrating an example radiation pattern formed by a test signal according to various embodiments;
- (9) FIG. 7A is a graph illustrating a CN0 value of a test signal measured in an antenna chamber, according to various embodiments;
- (10) FIG. 7B is a graph illustrating a CN0 value of a test signal measured in an antenna chamber, according to various embodiments;
- (11) FIG. 7C is a table illustrating a sensitivity and a TIS of a test signal, according to various embodiments;
- (12) FIG. 8 is a flowchart illustrating an example operation of an antenna chamber, according to

various embodiments; and

(13) FIG. 9 is a diagram illustrating an example antenna chamber structure for improving the accuracy of measuring a receive sensitivity, according to various embodiments.

(14) With regard to description of drawings, the same or similar components will be marked by the same or similar reference signs.

DETAILED DESCRIPTION

(15) FIG. 1 is a block diagram illustrating an example electronic device **101** in a network environment **100** according to various embodiments. Referring to FIG. 1, the electronic device **101** in the network environment **100** may communicate with an electronic device **102** via a first network **198** (e.g., a short-range wireless communication network), or at least one of an electronic device **104** or a server **108** via a second network **199** (e.g., a long-range wireless communication network). According to an embodiment, the electronic device **101** may communicate with the electronic device **104** via the server **108**. According to an embodiment, the electronic device **101** may include a processor **120**, memory **130**, an input module **150**, a sound output module **155**, a display module **160**, an audio module **170**, a sensor module **176**, an interface **177**, a connecting terminal **178**, a haptic module **179**, a camera module **180**, a power management module **188**, a battery **189**, a communication module **190**, a subscriber identification module (SIM) **196**, or an antenna module **197**. In various embodiments, at least one of the components (e.g., the connecting terminal **178**) may be omitted from the electronic device **101**, or one or more other components may be added in the electronic device **101**. In various embodiments, some of the components (e.g., the sensor module **176**, the camera module **180**, or the antenna module **197**) may be implemented as a single component (e.g., the display module **160**).

(16) The processor **120** may execute, for example, software (e.g., a program **140**) to control at least one other component (e.g., a hardware or software component) of the electronic device **101** coupled with the processor **120**, and may perform various data processing or computation. According to an embodiment, as at least part of the data processing or computation, the processor **120** may store a command or data received from another component (e.g., the sensor module **176** or the communication module **190**) in volatile memory **132**, process the command or the data stored in the volatile memory **132**, and store resulting data in non-volatile memory **134**. According to an embodiment, the processor **120** may include a main processor **121** (e.g., a central processing unit (CPU) or an application processor (AP)), or an auxiliary processor **123** (e.g., a graphics processing unit (GPU), a neural processing unit (NPU), an image signal processor (ISP), a sensor hub processor, or a communication processor (CP)) that is operable independently from, or in conjunction with, the main processor **121**. For example, when the electronic device **101** includes the main processor **121** and the auxiliary processor **123**, the auxiliary processor **123** may be adapted to consume less power than the main processor **121**, or to be specific to a specified function. The auxiliary processor **123** may be implemented as separate from, or as part of the main processor **121**.

(17) The auxiliary processor **123** may control at least some of functions or states related to at least one component (e.g., the display module **160**, the sensor module **176**, or the communication module **190**) among the components of the electronic device **101**, instead of the main processor **121** while the main processor **121** is in an inactive (e.g., sleep) state, or together with the main processor **121** while the main processor **121** is in an active state (e.g., executing an application). According to an embodiment, the auxiliary processor **123** (e.g., an image signal processor or a communication processor) may be implemented as part of another component (e.g., the camera module **180** or the communication module **190**) functionally related to the auxiliary processor **123**. According to an embodiment, the auxiliary processor **123** (e.g., the neural processing unit) may include a hardware structure specified for artificial intelligence model processing. An artificial intelligence model may be generated by machine learning. Such learning may be performed, e.g., by the electronic device **101** where the artificial intelligence is performed or via a separate server

(e.g., the server **108**). Learning algorithms may include, but are not limited to, e.g., supervised learning, unsupervised learning, semi-supervised learning, or reinforcement learning. The artificial intelligence model may include a plurality of artificial neural network layers. The artificial neural network may be a deep neural network (DNN), a convolutional neural network (CNN), a recurrent neural network (RNN), a restricted boltzmann machine (RBM), a deep belief network (DBN), a bidirectional recurrent deep neural network (BRDNN), deep Q-network or a combination of two or more thereof but is not limited thereto. The artificial intelligence model may, additionally or alternatively, include a software structure other than the hardware structure.

(18) The memory **130** may store various data used by at least one component (e.g., the processor **120** or the sensor module **176**) of the electronic device **101**. The various data may include, for example, software (e.g., the program **140**) and input data or output data for a command related thereto. The memory **130** may include the volatile memory **132** or the non-volatile memory **134**.

(19) The program **140** may be stored in the memory **130** as software, and may include, for example, an operating system (OS) **142**, middleware **144**, or an application **146**.

(20) The input module **150** may receive a command or data to be used by another component (e.g., the processor **120**) of the electronic device **101**, from the outside (e.g., a user) of the electronic device **101**. The input module **150** may include, for example, a microphone, a mouse, a keyboard, a key (e.g., a button), or a digital pen (e.g., a stylus pen).

(21) The sound output module **155** may output sound signals to the outside of the electronic device **101**. The sound output module **155** may include, for example, a speaker or a receiver. The speaker may be used for general purposes, such as playing multimedia or playing record. The receiver may be used for receiving incoming calls. According to an embodiment, the receiver may be implemented as separate from, or as part of the speaker.

(22) The display module **160** may visually provide information to the outside (e.g., a user) of the electronic device **101**. The display module **160** may include, for example, a display, a hologram device, or a projector and control circuitry to control a corresponding one of the display, hologram device, and projector. According to an embodiment, the display module **160** may include a touch sensor adapted to detect a touch, or a pressure sensor adapted to measure the intensity of force incurred by the touch.

(23) The audio module **170** may convert a sound into an electrical signal and vice versa. According to an embodiment, the audio module **170** may obtain the sound via the input module **150**, or output the sound via the sound output module **155** or a headphone of an external electronic device (e.g., an electronic device **102**) directly (e.g., wiredly) or wirelessly coupled with the electronic device **101**.

(24) The sensor module **176** may detect an operational state (e.g., power or temperature) of the electronic device **101** or an environmental state (e.g., a state of a user) external to the electronic device **101**, and then generate an electrical signal or data value corresponding to the detected state. According to an embodiment, the sensor module **176** may include, for example, a gesture sensor, a gyro sensor, an atmospheric pressure sensor, a magnetic sensor, an acceleration sensor, a grip sensor, a proximity sensor, a color sensor, an infrared (IR) sensor, a biometric sensor, a temperature sensor, a humidity sensor, or an illuminance sensor.

(25) The interface **177** may support one or more specified protocols to be used for the electronic device **101** to be coupled with the external electronic device (e.g., the electronic device **102**) directly (e.g., wiredly) or wirelessly. According to an embodiment, the interface **177** may include, for example, a high definition multimedia interface (HDMI), a universal serial bus (USB) interface, a secure digital (SD) card interface, or an audio interface.

(26) A connecting terminal **178** may include a connector via which the electronic device **101** may be physically connected with the external electronic device (e.g., the electronic device **102**). According to an embodiment, the connecting terminal **178** may include, for example, a HDMI connector, a USB connector, a SD card connector, or an audio connector (e.g., a headphone connector).

(27) The haptic module **179** may convert an electrical signal into a mechanical stimulus (e.g., a vibration or a movement) or electrical stimulus which may be recognized by a user via his tactile sensation or kinesthetic sensation. According to an embodiment, the haptic module **179** may include, for example, a motor, a piezoelectric element, or an electric stimulator.

(28) The camera module **180** may capture a still image or moving images. According to an embodiment, the camera module **180** may include one or more lenses, image sensors, image signal processors, or flashes.

(29) The power management module **188** may manage power supplied to the electronic device **101**. According to an embodiment, the power management module **188** may be implemented as at least part of, for example, a power management integrated circuit (PMIC).

(30) The battery **189** may supply power to at least one component of the electronic device **101**. According to an embodiment, the battery **189** may include, for example, a primary cell which is not rechargeable, a secondary cell which is rechargeable, or a fuel cell.

(31) The communication module **190** may support establishing a direct (e.g., wired) communication channel or a wireless communication channel between the electronic device **101** and the external electronic device (e.g., the electronic device **102**, the electronic device **104**, or the server **108**) and performing communication via the established communication channel. The communication module **190** may include one or more communication processors that are operable independently from the processor **120** (e.g., the application processor (AP)) and supports a direct (e.g., wired) communication or a wireless communication. According to an embodiment, the communication module **190** may include a wireless communication module **192** (e.g., a cellular communication module, a short-range wireless communication module, or a global navigation satellite system (GNSS) communication module) or a wired communication module **194** (e.g., a local area network (LAN) communication module or a power line communication (PLC) module). A corresponding one of these communication modules may communicate with the external electronic device via the first network **198** (e.g., a short-range communication network, such as Bluetooth™, wireless-fidelity (Wi-Fi) direct, or infrared data association (IrDA)) or the second network **199** (e.g., a long-range communication network, such as a legacy cellular network, a 5G network, a next-generation communication network, the Internet, or a computer network (e.g., LAN or wide area network (WAN))). These various types of communication modules may be implemented as a single component (e.g., a single chip), or may be implemented as multi components (e.g., multi chips) separate from each other. The wireless communication module **192** may identify and authenticate the electronic device **101** in a communication network, such as the first network **198** or the second network **199**, using subscriber information (e.g., international mobile subscriber identity (IMSI)) stored in the subscriber identification module **196**.

(32) The wireless communication module **192** may support a 5G network, after a 4G network, and next-generation communication technology, e.g., new radio (NR) access technology. The NR access technology may support enhanced mobile broadband (eMBB), massive machine type communications (mMTC), or ultra-reliable and low-latency communications (URLLC). The wireless communication module **192** may support a high-frequency band (e.g., the mmWave band) to achieve, e.g., a high data transmission rate. The wireless communication module **192** may support various technologies for securing performance on a high-frequency band, such as, e.g., beamforming, massive multiple-input and multiple-output (massive MIMO), full dimensional MIMO (FD-MIMO), array antenna, analog beam-forming, or large scale antenna. The wireless communication module **192** may support various requirements specified in the electronic device **101**, an external electronic device (e.g., the electronic device **104**), or a network system (e.g., the second network **199**). According to an embodiment, the wireless communication module **192** may support a peak data rate (e.g., 20 Gbps or more) for implementing eMBB, loss coverage (e.g., 164 dB or less) for implementing mMTC, or U-plane latency (e.g., 0.5 ms or less for each of downlink (DL) and uplink (UL), or a round trip of 1 ms or less) for implementing URLLC.

(33) The antenna module **197** may transmit or receive a signal or power to or from the outside (e.g., the external electronic device) of the electronic device **101**. According to an embodiment, the antenna module **197** may include an antenna including a radiating element including a conductive material or a conductive pattern formed in or on a substrate (e.g., a printed circuit board (PCB)). According to an embodiment, the antenna module **197** may include a plurality of antennas (e.g., array antennas). In such a case, at least one antenna appropriate for a communication scheme used in the communication network, such as the first network **198** or the second network **199**, may be selected, for example, by the communication module **190** (e.g., the wireless communication module **192**) from the plurality of antennas. The signal or the power may then be transmitted or received between the communication module **190** and the external electronic device via the selected at least one antenna. According to an embodiment, another component (e.g., a radio frequency integrated circuit (RFIC)) other than the radiating element may be additionally formed as part of the antenna module **197**.

(34) According to various embodiments, the antenna module **197** may form a mmWave antenna module. According to an embodiment, the mmWave antenna module may include a printed circuit board, a RFIC disposed on a first surface (e.g., the bottom surface) of the printed circuit board, or adjacent to the first surface and capable of supporting a designated high-frequency band (e.g., the mmWave band), and a plurality of antennas (e.g., array antennas) disposed on a second surface (e.g., the top or a side surface) of the printed circuit board, or adjacent to the second surface and capable of transmitting or receiving signals of the designated high-frequency band.

(35) At least some of the above-described components may be coupled mutually and communicate signals (e.g., commands or data) therebetween via an inter-peripheral communication scheme (e.g., a bus, general purpose input and output (GPIO), serial peripheral interface (SPI), or mobile industry processor interface (MIPI)).

(36) According to an embodiment, commands or data may be transmitted or received between the electronic device **101** and the external electronic device **104** via the server **108** coupled with the second network **199**. Each of the electronic devices **102** or **104** may be a device of a same type as, or a different type, from the electronic device **101**. According to an embodiment, all or some of operations to be executed at the electronic device **101** may be executed at one or more of the external electronic devices **102**, **104**, or **108**. For example, if the electronic device **101** should perform a function or a service automatically, or in response to a request from a user or another device, the electronic device **101**, instead of, or in addition to, executing the function or the service, may request the one or more external electronic devices to perform at least part of the function or the service. The one or more external electronic devices receiving the request may perform the at least part of the function or the service requested, or an additional function or an additional service related to the request, and transfer an outcome of the performing to the electronic device **101**. The electronic device **101** may provide the outcome, with or without further processing of the outcome, as at least part of a reply to the request. To that end, a cloud computing, distributed computing, mobile edge computing (MEC), or client-server computing technology may be used, for example. The electronic device **101** may provide ultra low-latency services using, e.g., distributed computing or mobile edge computing. In an embodiment, the external electronic device **104** may include an internet-of-things (IoT) device. The server **108** may be an intelligent server using machine learning and/or a neural network. According to an embodiment, the external electronic device **104** or the server **108** may be included in the second network **199**. The electronic device **101** may be applied to intelligent services (e.g., smart home, smart city, smart car, or healthcare) based on 5G communication technology or IoT-related technology.

(37) The electronic device according to various embodiments may be one of various types of electronic devices. The electronic devices may include, for example, a portable communication device (e.g., a smartphone), a computer device, a portable multimedia device, a portable medical device, a camera, a wearable device, a home appliance, or the like. According to an embodiment of

the disclosure, the electronic devices are not limited to those described above.

(38) It should be appreciated that various embodiments of the present disclosure and the terms used therein are not intended to limit the technological features set forth herein to particular embodiments and include various changes, equivalents, or replacements for a corresponding embodiment. With regard to the description of the drawings, similar reference numerals may be used to refer to similar or related elements. It is to be understood that a singular form of a noun corresponding to an item may include one or more of the things, unless the relevant context clearly indicates otherwise. As used herein, each of such phrases as “A or B,” “at least one of A and B,” “at least one of A or B,” “A, B, or C,” “at least one of A, B, and C,” and “at least one of A, B, or C,” may include any one of, or all possible combinations of the items enumerated together in a corresponding one of the phrases. As used herein, such terms as “1st” and “2nd,” or “first” and “second” may be used to simply distinguish a corresponding component from another, and does not limit the components in other aspect (e.g., importance or order). It is to be understood that if an element (e.g., a first element) is referred to, with or without the term “operatively” or “communicatively”, as “coupled with,” “coupled to,” “connected with,” or “connected to” another element (e.g., a second element), the element may be coupled with the other element directly (e.g., wiredly), wirelessly, or via a third element.

(39) As used in connection with various embodiments of the disclosure, the term “module” may include a unit implemented in hardware, software, or firmware, or any combination thereof, and may interchangeably be used with other terms, for example, “logic,” “logic block,” “part,” or “circuitry”. A module may be a single integral component, or a minimum unit or part thereof, adapted to perform one or more functions. For example, according to an embodiment, the module may be implemented in a form of an application-specific integrated circuit (ASIC).

(40) Various embodiments as set forth herein may be implemented as software (e.g., the program **140**) including one or more instructions that are stored in a storage medium (e.g., internal memory **136** or external memory **138**) that is readable by a machine (e.g., the electronic device **101**). For example, a processor (e.g., the processor **120**) of the machine (e.g., the electronic device **101**) may invoke at least one of the one or more instructions stored in the storage medium, and execute it, with or without using one or more other components under the control of the processor. This allows the machine to be operated to perform at least one function according to the at least one instruction invoked. The one or more instructions may include a code generated by a compiler or a code executable by an interpreter. The machine-readable storage medium may be provided in the form of a non-transitory storage medium. Wherein, the “non-transitory” storage medium is a tangible device, and may not include a signal (e.g., an electromagnetic wave), but this term does not differentiate between where data is semi-permanently stored in the storage medium and where the data is temporarily stored in the storage medium.

(41) According to an embodiment, a method according to various embodiments of the disclosure may be included and provided in a computer program product. The computer program product may be traded as a product between a seller and a buyer. The computer program product may be distributed in the form of a machine-readable storage medium (e.g., compact disc read only memory (CD-ROM)), or be distributed (e.g., downloaded or uploaded) online via an application store (e.g., PlayStore™), or between two user devices (e.g., smart phones) directly. If distributed online, at least part of the computer program product may be temporarily generated or at least temporarily stored in the machine-readable storage medium, such as memory of the manufacturer's server, a server of the application store, or a relay server.

(42) According to various embodiments, each component (e.g., a module or a program) of the above-described components may include a single entity or multiple entities, and some of the multiple entities may be separately disposed in different components. According to various embodiments, one or more of the above-described components may be omitted, or one or more other components may be added. Alternatively or additionally, a plurality of components (e.g.,

modules or programs) may be integrated into a single component. In such a case, according to various embodiments, the integrated component may still perform one or more functions of each of the plurality of components in the same or similar manner as they are performed by a corresponding one of the plurality of components before the integration. According to various embodiments, operations performed by the module, the program, or another component may be carried out sequentially, in parallel, repeatedly, or heuristically, or one or more of the operations may be executed in a different order or omitted, or one or more other operations may be added.

(43) FIG. 2 is a block diagram illustrating an example configuration of an antenna chamber, according to various embodiments. FIG. 3 is a diagram illustrating an example antenna chamber, according to various embodiments. FIG. 4A is a diagram illustrating an example radiation pattern formed by a test signal according to various embodiments. FIG. 4B is a diagram illustrating an example radiation pattern formed by a test signal according to various embodiments.

(44) In an embodiment, an antenna chamber **200** may include a control circuit **210**, at least one antenna **230**, a holder **240**, and/or a wireless communication circuit **260**. A DUT **220** (e.g., an electronic device **101** of FIG. 1) may be disposed in the antenna chamber **200**. For example, the DUT **220** may be mounted on a mounting part **255** of the holder **240** in the antenna chamber **200**.

(45) The control circuit **210** may be operatively connected with the at least one antenna **230**, the holder **240**, and/or the wireless communication circuit **260**. The control circuit **210** may include a simulator and/or a measurement device or may be implemented as a part thereof. For example, the control circuit **210** may include a network emulator, a global navigation satellite system (GNSS) simulator, and/or a positioning controller or may be implemented as a part thereof.

(46) The control circuit **210** may control operations of components included in the antenna chamber **200**. For example, the control circuit **210** may radiate a test signal (e.g., a global positioning system (GPS) signal) using the at least one antenna **230**. For example, the control circuit **210** may rotate some of the at least one antenna **230** in a clockwise direction or a counterclockwise direction. For example, the control circuit **210** may control such that the at least one antenna **230** radiates a test signal, in a state where it rotates some of the at least one antenna **230** 90 degrees in a clockwise direction. For example, the control circuit **210** may control at least one driving part **250** to rotate the mounting part **255**. For example, the control circuit **210** may transmit and receive information associated with the test signal with the DUT **220** through the wireless communication circuit **260**.

(47) The at least one antenna **230** may be disposed at a specified position in the antenna chamber **200**. For example, some of the at least one antenna **230** may be arranged at an inner side of the antenna chamber **200**. For example, some (e.g., at least one first antenna) of the at least one antenna **230** may be mounted on the mounting part **255** of the holder **240**. For example, some (e.g., the at least one first antenna) of the at least one antenna **230** may be arranged on an inner wall of the antenna chamber **200**.

(48) The at least one antenna **230** may radiate a test signal. For example, the test signal may be a signal based on a wireless communication (e.g., long term evolution (LTE) communication or new radio (NR) communication) protocol and/or a signal based on a global navigation satellite system (GNSS) protocol.

(49) In an embodiment, the test signal may include a plurality of test signals of different frequency bands. For example, the plurality of test signals may be global positioning system (GPS) signals. For example, the plurality of test signals may include at least one of an L1 signal or an L5 signal. The L1 signal may be, for example, a signal of the 1575.42 MHz band, which may be a signal used for positioning. The L5 signal may be, for example, a signal of the 1176.45 MHz band, which may be a signal used for positioning.

(50) The holder **240** may be disposed at a specified position in the antenna chamber **200**. For example, the holder **240** may be disposed spaced apart from the at least one antenna **230** at a specified interval. The specified interval may be an interval suitable for measuring a receive

sensitivity of the test signal radiated from the at least one antenna **230** at the DUT **220** mounted on the mounting part **255**.

(51) The holder **240** may include the at least one driving part (e.g., including, for example, a driver, a motor, etc.) **250** and/or the mounting part **255**.

(52) The mounting part **255** may receive other components associated with the antenna chamber **200**. For example, the mounting part **255** may receive the DUT **220**. For another example, the mounting part **255** may receive some (e.g., the at least one first antenna) among the at least one antenna **230**.

(53) The at least one driving part **250** may rotate at least one joint (e.g., a bearing structure) of the holder **240** to rotate and/or move the mounting part **255**. The components mounted on the mounting part **255** may rotate and/or move together with the mounting part **255**. For example, the DUT **220** may rotate together with the rotation of the mounting part **255**. When the DUT **220** rotates, a main antenna **222** of the DUT **220** may rotate at a fixed position in the antenna chamber **200**. In this case, the main antenna **222** may be understood as being located on a rotary axis of the mounting part **255**.

(54) The wireless communication circuit **260** may include an antenna for assisting in test. For example, the wireless communication circuit **260** may include an antenna for assisting in communication (e.g., LTE, WCDMA, CDMA, or Wi-Fi communication) between the DUT **220** and the control circuit **210**. The control circuit **210** may transmit and receive information associated with the test signal with the DUT **220** through the wireless communication circuit **260**.

(55) The DUT **220** may include the main antenna **222** (e.g., an antenna module **197** of FIG. 1) and/or a wireless communication circuit **224** (e.g., a communication module **190** of FIG. 1).

(56) The main antenna **222** may receive the test signal radiated by the at least one antenna **230**.

(57) The wireless communication circuit **224** may transmit information associated with the test signal to the control circuit **210** or may receive the information associated with the test signal from the control circuit **210**. For example, the wireless communication circuit **224** may include an auxiliary antenna for assisting in communication (e.g., LTE, WCDMA, CDMA, or Wi-Fi communication) between the DUT **220** and the control circuit **210**. The wireless communication circuit **224** may transmit and receive the information associated with the test signal with the control circuit **210** through the auxiliary antenna.

(58) Referring to FIG. 3, the antenna chamber **200** may, for example, be an anechoic chamber. The antenna chamber **200** may have a plurality of embossing structures at its inner side. For example, a test signal which arrives at a wall surface of the antenna chamber **200** among test signals radiated from the at least one antenna **230** may be absorbed by the antenna chamber **200**.

(59) In an embodiment, an antenna **300** (e.g., the at least one antenna **230**) and the holder **240** may be arranged spaced apart from each other at a specified interval d in the antenna chamber **200**. The control circuit **210** may be operatively connected with the antenna **300** and/or the holder **240**. It is shown that the control circuit **210** is disposed outside the antenna chamber **200**, but the control circuit **210** may be disposed inside of the antenna chamber **200**. Hereinafter, operations of the respective components of the antenna chamber **200** may be understood as being substantially performed by the control circuit **210**. FIG. 3 is illustrative, and the antenna chamber **200** may further include various components (e.g., the wireless communication circuit **260**) which are not shown in FIG. 3.

(60) The holder **240** may be implemented with a turn table **320**, a support column **322**, and/or an arm **324**. The mounting part **255** may be implemented as a part of the arm **324**. The turn table **320**, the support column **322**, and/or the arm **324** may be connected with each other by at least one joint and may be adjusted (or rotated) by the at least one driving part **250**. For example, the control circuit **210** may adjust each component of the holder **240** using the at least one driving part **250** to rotate the mounting part **255**. The structure of the holder **240** of FIG. 3 is illustrative, and the holder **240** may be implemented as another structure capable of rotating the mounting part **255**.

- (61) In an embodiment, the control circuit **210** may radiate a test signal using the antenna **300**. The control circuit **210** may rotate the antenna **300** in a clockwise direction or a counterclockwise direction.
- (62) In an embodiment, the DUT **220** may receive the test signal radiated from the antenna **300** using the main antenna **222**. A signal which arrives at a wall surface of the antenna chamber **200** among test signals radiated from the antenna **300** may be absorbed by a wall surface of the antenna chamber **200**. Thus, the test signal received by the DUT **220** may be a signal moved through a line of sight (LoS) path. The LoS path may be a straight path between the antenna **300** and the DUT **220**.
- (63) The DUT **220** may transmit the information associated with the test signal to the control circuit **210** through the wireless communication circuit **224**. The control circuit **210** may measure a receive sensitivity of the test signal based on the received information. Hereinafter, a description will be given of a method for measuring a receive sensitivity of the test signal, which is performed in the antenna chamber **200**. The receive sensitivity in disclosure may be referred to as total isotropic sensitivity (TIS).
- (64) In an embodiment, the control circuit **210** may radiate a test signal (e.g., an L1 signal or an L5 signal) of a specified intensity using the antenna **300**.
- (65) For example, an intensity of the test signal radiated by the antenna **300** may be -130 dBm. -130 dBm may be understood as an intensity of a GPS signal received from a satellite in a general atmospheric environment.
- (66) In an embodiment, the control circuit **210** may radiate a test signal at various angles. For example, the control circuit **210** may radiate the test signal in a state where it rotates the antenna **300** 90 degrees in a clockwise direction or a counterclockwise direction.
- (67) The control circuit **210** may move and/or rotate the mounting part **255** using at least one driving part **250**.
- (68) For example, the control circuit **210** may rotate the turn table **320** in a rotation direction 1 using the at least one driving part **250**. The rotation direction 1 is shown as a counterclockwise direction, or vice versa. θ may be a rotation angle which is previously defined on a rotation plane of the rotation direction 1. The mounting part **255** and the DUT **220** may rotate together along rotation of the turn table **320**. The main antenna **222** of the DUT **220** may be located on a rotary axis x of the turn table **320**. In this case, the main antenna **222** may rotate at a fixed position.
- (69) For example, the control circuit **210** may rotate the arm **324** in a rotation direction 2 using the at least one driving part **250**. The rotation direction 2 is shown as a counterclockwise direction, or vice versa. ϕ may be a rotation angle which is previously defined on a rotation plane of the rotation direction 2. The mounting part **255** and the DUT **220** may rotate together along rotation of the arm **324**. The main antenna **222** of the DUT **220** may be located on a rotary axis y of the arm **324** orthogonal to the rotary axis x. In this case, the main antenna **222** may rotate at a fixed position.
- (70) In an embodiment, the control circuit **220** may receive a test signal at a plurality of specified angles. The plurality of specified angles may be defined as a combination of the rotary axes θ and ϕ and the angle of the antenna **300**. For example, it may be referred to as 0 when the angle of the antenna **300** among the plurality of specified angles is 0 degree, and it may be referred to as 1 when the angle of the antenna **300** is 90 degrees. For example, the specified angles may be (30 degrees, 60 degrees, 1). In this case, the DUT **220** may be in a state where it rotates 30 degrees in the rotation direction 1 and a state where it rotates 60 degrees in the rotation direction 2, and the angle of the antenna **300** may be 90 degrees.
- (71) The DUT **220** may measure a carrier to noise ratio (CN0) for the test signal received at the plurality of specified angles. The number of the plurality of specified angles may be previously determined. The DUT **220** may transmit the information associated with the test signal to the control circuit **210**. For example, the DUT **220** may transmit a CN0 value of the test signal to the control circuit **210**. For another example, the DUT **220** may transmit information associated with

positioning to the control circuit **210**. For another example, the DUT **220** may transmit a positioning result (e.g., the measured latitude and/or longitude of the DUT **220**) to the control circuit **210**.

(72) In an embodiment, the control circuit **210** may identify a radiation pattern of the test signal based on the received information. For example, the control circuit **210** may identify the radiation pattern of the test signal based on a CN0 value measured by the DUT **220** at the plurality of specified angles.

(73) Referring to FIG. **4A**, reference numeral **410** may be understood as a radiation pattern formed by a test signal (e.g., an L1 signal). The radiation pattern **410** may indicate reception performance of the main antenna **222** for the test signal. For example, reception performance for a direction **400** of the main antenna **220** may be higher than reception performance for a direction **405**. The direction **400** may be understood as a direction corresponding to an angle where the CN0 value is maximum.

(74) The control circuit **210** may control such that the antenna **300** radiates the test signal while decreasing an intensity of the test signal by a specified intensity (e.g., 1 dBm) at an angle where the DUT **220** has a maximum CN0 value. The DUT **220** may measure a CN0 for the test signal and may transmit the measured CN0 value to the control circuit **210**. The control circuit **210** may identify linearity of reception performance of the main antenna **222** based on the received CN0 value. In this manner, the control circuit **210** may identify that a CN0 value on the radiation pattern represents reception performance of the DUT **220** at the corresponding angle.

(75) The control circuit **210** may measure a sensitivity of the test signal at an angle where the CN0 value is maximum. For example, the control circuit **210** may receive information about the test signal from the DUT **220** at an angle where the DUT **220** has the maximum CN0 value. The control circuit **210** may perform positioning based on the received information. The control circuit **210** may compare the positioning result with a position of the DUT **220** in the antenna chamber **200** to identify an error rate.

(76) The control circuit **210** may repeat positioning while reducing an intensity of the test signal radiated by the antenna **300** at the angle where the DUT **220** has the maximum CN0 value. The control circuit **210** may repeat positioning to a point where the error rate of the positioning is greater than or equal to a threshold. The control circuit **210** may identify an electric field, measured at a minimum intensity of the test signal where positioning is normally possible, as sensitivity at the corresponding angle. For example, when the error rate of the positioning is less than the threshold, the positioning at the corresponding angle may be understood as being normally possible.

(77) The control circuit **210** may calculate a receive sensitivity (TIS) based on the CN0 value and the sensitivity. The TIS may be a minimum signal level where the DUT **220** may normally perform positioning, when the DUT **220** receives the same signal in all directions. The TIS may be used as an indicator indicating a receive sensitivity of the DUT **220**. The TIS may be calculated using Equation 1.

$$(78) \quad TIS = \frac{2N * M * CN0(\text{peak}) * \text{sensitivity}(\text{peak})}{\text{.Math.}_{i=1}^{N-1} \cdot \text{.Math.}_{j=0}^{M-1} [CN0_{\Theta}(\Theta_i, \varnothing_j) + CN0_{\varnothing}(\Theta_i, \varnothing_j)] \sin(\Theta_1)} \quad [\text{Equation1}]$$

(79) CN0 (peak) may be a maximum CN0 value measured by the DUT **220**. Sensitivity (peak) may be a sensitivity of the test signal identified at an angle where the CN0 value is maximum. N and M are random integers greater than 1. N may be the number of specified angles which is previously defined on a rotation plane corresponding to the rotation direction 1. M may be the number of specified angles which is previously defined on a rotation plane corresponding to the rotation direction 2.

(80) Hereinafter, a description will be given of an example method for measuring a TIS, which is performed in the antenna chamber, when the test signal includes a plurality of different tests signals

(an L1 signal and an L5 signal) and when measurement of a receive sensitivity for a test signal (e.g., the L5 signal) to be measured is based on another test signal (e.g., the L1 signal).

(81) In an embodiment, the antenna **300** may radiate the L1 signal and the L5 signal. The DUT **220** may measure CN0 of the L5 signal, in response to receiving the L1 signal. The DUT **220** may transmit a CN0 value of the L5 signal to the control circuit **210**. The control circuit **210** may form a radiation pattern for the L5 signal based on the CN0 value.

(82) Referring to FIG. **4B**, reference numeral **410** may be a radiation pattern formed by the L1 signal. Reference numeral **420** may be a radiation pattern formed by the L5 signal. The radiation patterns formed by the L1 signal and the L5 signal may be different from each other. In an embodiment, the control circuit **210** may only identify the radiation pattern of the L5 signal based on the information received from the DUT **220** and may fail to identify the radiation pattern of the L1 signal. Thus, the radiation pattern **410** may be understood as a virtual radiation pattern.

(83) The DUT **220** may have high reception performance at different angles for the L1 signal and the L5 signal. For example, in the main antenna **222**, reception performance for a direction **440** may be higher than reception performance for a direction **445**, in conjunction with the L1 signal. For example, in the main antenna **222**, the reception performance for the direction **445** may be higher than the reception performance for the direction **440**, in conjunction with the L5 signal. The direction **445** may be a direction corresponding to an angle where the DUT **220** has a maximum CN0 value with respect to the L5 signal.

(84) In an embodiment, intensity of the L1 signal for a certain range **430** may be a weak electric field. For example, an intensity of the L1 signal received by the DUT **220** may be a weak electric field with respect to the direction **445**.

(85) Referring again to FIG. **3**, the control circuit **210** may reduce an intensity of a test signal radiated by the antenna **300** to measure sensitivity at an angle (corresponding to the direction **445**) where the DUT **220** has the maximum CN0 with respect to the L5 signal. For example, the antenna **300** may reduce an intensity of the L1 signal and an intensity of the L5 signal.

(86) In an embodiment, as the intensity of the L1 signal is reduced, the DUT **220** may fail to receive the L1 signal or the intensity of the L1 signal received by the DUT **220** may be a weak electric field. In this case, irrespective of the intensity of the L5 signal, the intensity of the L5 signal identified at the corresponding angle may be inaccurate. TIS calculation based on inaccurate sensitivity may be inaccurate.

(87) Hereinafter, an example method for enhancing inaccurate TIS measurement is described in greater detail.

(88) FIG. **5** is a diagram illustrating an example antenna chamber structure for improving the accuracy of measuring a receive sensitivity, according to various embodiments. FIG. **6** is a diagram illustrating an example radiation pattern formed by a test signal according to various embodiments. The description of components of FIG. **2** or **3** may be referenced to describe FIGS. **5** and **6**.

(89) Reference numeral **500** illustrates a part of a holder **240**. The other components of an antenna chamber **200** except for the holder **240** may be the same as or similar to those shown in FIG. **3**.

(90) The antenna chamber **200** may further include at least one first antenna **520**. In an embodiment, the at least one first antenna **520** may be disposed on a first region **510** of the holder **240**. For example, the first region **510** may be one region of an arm **324**. In an embodiment, the at least one first antenna **520** may be disposed on another region (e.g., a second region **515**) of the holder **240**. For example, the first region **510** may be one region of the arm **324**. For example, the second region **515** may be one region of a support column **322**.

(91) The at least one first antenna **520** may be disposed on at least one of the first region **510** or the second region **515** to form a fixed angle with a DUT **220**. The position of the at least one first antenna **520** shown in FIG. **5** is illustrative, and the at least one first antenna **520** may be disposed on another position of the holder **240** to form a fixed angle with the DUT **220**.

(92) A plurality of test signals, each of which has a different frequency, in FIG. **5** may be radiated

by different antennas. For example, the at least one first antenna **520** may radiate a first test signal (e.g., an L1 signal). For example, an antenna **300** may radiate a second test signal (e.g., an L5 signal). Hereinafter, the antenna **300** may be a second antenna.

(93) The control circuit **210** may rotate the DUT **220** using at least one driving part **250**. For example, the DUT **220** may rotate in a rotation direction 1 or a rotation direction 2. A main antenna **222** of the DUT **220** may be located on a rotary axis of the rotation direction 1 or the rotation direction 2. In this case, the main antenna **222** may rotate at a fixed position.

(94) When the DUT **220** rotates, the at least one first antenna **520** may rotate together. For example, the at least one first antenna **520** may rotate while maintaining a fixed angle and/or interval with the DUT **220**.

(95) In an embodiment, the control circuit **210** may radiate a test signal, while rotating the DUT **220**. For example, the control circuit **210** may radiate the L1 signal using the at least one first antenna **520**. For example, the control circuit **210** may radiate the L5 signal using the second antenna.

(96) Because the at least one first antenna **520** rotates together with the DUT **220** while maintaining the fixed angle and/or interval with the DUT **220**, an intensity of the L1 signal received from the at least one first antenna **520** by the DUT **220** may be constant or an intensity within a specified range.

(97) Referring to FIG. 6, reference numeral **610** may be a radiation pattern formed by the L1 signal. The radiation pattern **610** may be a virtual radiation pattern. For example, reference numeral **620** may be a radiation pattern formed by the L5 signal. For example, the DUT **220** may have reception performance of a similar level to the L1 signal at all angles. The DUT **220** may perform normal positioning based on the L5 signal irrespective of an intensity of the L1 signal in a direction **530**.

(98) The radiation pattern is shown as a globular shape in FIG. 6. However, the radiation pattern **610** may have any shape. Although the radiation pattern **610** has the any shape, the DUT **220** may perform normal positioning based on the L5 signal irrespective of the L1 signal. For example, when the radiation pattern **610** has any shape, the intensity of the L1 signal at all angles of the DUT **220** may be greater than or equal to a minimum intensity capable of performing normal positioning based on the L1 signal. For another example, when the radiation pattern **610** has any shape, the control circuit **210** may control an intensity of the L1 signal at a specific angle in software. For example, the control circuit **210** may control the at least one first antenna **520** to increase the intensity of the L1 signal at a specific angle. In this case, at the specific angle, the intensity of the L1 signal may be greater than or equal to the minimum intensity capable of performing the normal positioning based on the L1 signal.

(99) Referring again to FIG. 5, when identifying the sensitivity of the L5 signal, the control circuit **210** may decrease the intensity of the L5 signal radiated by the second antenna at a plurality of specified angles. When the intensity of the L5 signal decreases, the intensity of the L1 signal received by the DUT **220** may be constant or may be maintained at an intensity within a specified range. In an embodiment, the control circuit **210** may identify an electric field measured at a minimum intensity of the L5 signal capable of normally performing positioning as a sensitivity of the corresponding angle (e.g., an angle corresponding to the direction **530**).

(100) The sensitivity of the L5 signal measured in an embodiment according to FIG. 5 may be more accurate than sensitivity identified in an embodiment according to FIG. 3. The antenna chamber **200** may calculate an accurate TIS based on the identified sensitivity.

(101) FIG. 5 is only one example for enhancing accuracy of the TIS, and the antenna chamber **200** may be designed in various methods to accomplish the same purpose. For example, the at least one first antenna **520** may be disposed on an inner wall of the antenna chamber **200**.

(102) In an embodiment, an anechoic antenna chamber **200** may include a holder **240** on which a DUT **220** is able to be mounted, at least one first antenna configured to radiate a first test signal of a first frequency band, a second antenna configured to be provided at an inner side of the antenna

chamber **200** and radiate a second test signal of a second frequency, at least one driving part **250** configured to rotate the DUT **220**, and a control circuit **210** operatively connected with the at least one first antenna, the second antenna, and the at least one driving part **250**. The control circuit **210** may be configured to rotate the DUT **220** using the at least one driving part **250** and radiate the first test signal having an intensity of a specified range through the at least one first antenna and radiate the second test signal through the second antenna, while rotating the DUT **220**.

(103) In an embodiment, the at least one first antenna may be mounted on a mounting part **255** to form a fixed angle with the DUT **220**, when the DUT **220** is mounted on the mounting part **255**. The control circuit **210** may be configured to rotate the at least one first antenna together with the DUT **220** using the at least one driving part **250**.

(104) In an embodiment, the at least one first antenna may be provided on an inner wall of the antenna chamber **200**. The control circuit **210** may be configured to radiate the first test signal through some of the at least one first antenna. The control circuit **210** may be configured to, when the DUT **220** rotates, radiate the first test signal based on a switching operation of the at least one first antenna.

(105) In an embodiment, the first test signal and the second test signal may be signals based on a global navigation satellite system (GNSS). The first test signal may include an L1 signal, and the second test signal may include an L5 signal.

(106) In an embodiment, the control circuit **210** may be configured to correct an error of positioning based on the first test signal using the second test signal. The control circuit **210** may be configured to measure a receive sensitivity of the second test signal based on the first test signal received through the DUT **220**.

(107) In an embodiment, the at least one driving part **250** may include a bearing structure.

(108) In an embodiment, the at least one driving part **250** may include a first driving part (e.g., including a driver, motor, etc.) for rotating the at least one mounting part **255** about a first rotary axis and a second driving part for rotating the at least one mounting part **255** about a second rotary axis perpendicular to the first rotary axis. In an embodiment, the control circuit **210** may be configured to rotate the DUT **220** on at least one plane using the at least one driving part **250**. In an embodiment, a main antenna **222** included in the DUT **220** may be disposed at a fixed position on the first rotary axis and the second rotary axis.

(109) In an embodiment, the control circuit **210** may be configured to identify a radiation pattern of the second test signal received by the DUT **220** at a specified angle, while the DUT **220** rotates about the first rotary axis or the second rotary axis. The control circuit **210** may be configured to radiate the second test signal at a specified intensity, when identifying the radiation pattern of the second test signal.

(110) In an embodiment, the control circuit **210** may be configured to linearize the identified radiation pattern. In an embodiment, the control circuit **210** may be configured to measure a sensitivity of the second test signal while adjusting an intensity of the second test signal, based on the radiation pattern.

(111) In an embodiment, the control circuit **210** may be configured to calculate a total isotropic sensitivity (TIS) of the second test signal based on the radiation pattern and the sensitivity.

(112) In an embodiment, the antenna chamber **200** may further include at least one of a network emulator, a global navigation satellite system (GNSS) simulator, or a positioning controller. The control circuit **210** may be implemented as a part of at least one of the network emulator, the GNSS simulator, or the positioning controller.

(113) In an embodiment, the antenna chamber **200** may further include an embossing structure. The embossing structure may be provided on an inner wall of the antenna chamber **200**. In an embodiment, the antenna chamber **200** may further include a wireless communication circuit **260**. The control circuit **210** may be configured to receive information associated with the second test signal from the DUT **220** through the wireless communication circuit **260**.

(114) FIG. 7A is a graph illustrating a CN0 value of a test signal measured in an antenna chamber, according to various embodiments. FIG. 7B is a graph illustrating a CN0 value of a test signal measured in an antenna chamber, according to various embodiments. Components of FIGS. 2 to 6 may be referenced to describe FIGS. 7A and 7B.

(115) In FIGS. 7A and 7B, the vertical axis of graphs 700 and 750 indicates a CN0 value of a test signal (e.g., an L1 signal and an L5 signal) received by a DUT 220. The horizontal axis of the graphs 700 and 750 may indicate an angle (e.g., a plurality of specified angles) of the DUT 220. Referring to the graphs 700 and 750, reference numeral 720 may indicate a second test signal (e.g., an L5 signal) and reference numeral 725 may indicate a first test signal (e.g., an L1 signal).

(116) The graph 700 of FIG. 7A illustrates a CN0 value of a test signal measured in an antenna chamber structure according to FIG. 3.

(117) In an embodiment, a CN0 value of the L1 signal received by the DUT 220 at a specific angle (e.g., (0, 240), (60, 0)) may be 0 (or null). In this case, it may be impossible for the DUT 220 to perform normal positioning using the L1 signal at the corresponding angle. In an embodiment, a sensitivity of the L5 signal measured at an angle (e.g., (0, 240), (60, 0)) where the CN0 value of the L1 signal is 0 (or null) may be inaccurate.

(118) In an embodiment, an intensity of the L1 signal received by the DUT 220 at a specific angle (e.g., (0, 120)) may be less than a minimum electric field required to normally perform positioning based on the L5 signal. When the intensity of the L1 signal is less than the minimum electric field, a receive sensitivity of the L5 signal, which is calculated for the corresponding angle, may be inaccurate.

(119) The graph 750 of FIG. 7B illustrates a CN0 value of a test signal measured in an antenna chamber structure according to FIG. 5. A CN0 value of the L1 signal may be constant or a value within a specified range at all angles of the DUT 220, except for a certain interval (e.g., (0,0)~(30,0)). The certain interval may be understood as an angle where the CN0 of the L1 signal is not measured. For example, the CN0 value of the L1 signal may be maintained between 50 and 60. In this case, the DUT 220 may perform normal positioning based on the L5 signal.

(120) FIG. 7C is a table illustrating examples of a sensitivity and a TIS of a test signal, according to various embodiments. Components of FIGS. 2 to 6 may be referenced to describe FIG. 7C.

(121) A table 770 may indicate a sensitivity and a TIS of an L5 signal, which are calculated in an existing antenna chamber (e.g., an antenna chamber according to FIG. 3) and an improved antenna chamber (e.g., an antenna chamber according to FIG. 5) with respect to a specified angle.

(122) When the CN0 and the sensitivity of the L5 signal are proportional to each other and when the TIS calculated at a plurality of specified angles is uniform, the reliability (or accuracy) of measuring the receive sensitivity may be understood as being high.

(123) In the table 770, it may be understood that the CN0 of the L5 signal and a sensitivity measured in an existing antenna chamber are not proportional to each other, while the CN0 of the L5 signal and a sensitivity measured in an improved antenna chamber are generally proportional to each other.

(124) In the table 770, because a deviation between a maximum value and a minimum value of a TIS calculated in the improved antenna chamber is 2, it may be understood as being less than a deviation (12.6) of the existing antenna chamber. The TIS calculated in the improved antenna chamber may be more uniform than that in the existing antenna chamber.

(125) Thus, a TIS of the L5 signal with high reliability (or accuracy) may be obtained by the improved antenna chamber.

(126) FIG. 8 is a flowchart illustrating an example operation of an antenna chamber, according to various embodiments.

(127) Components of FIGS. 2 to 6 may be referenced to describe FIG. 8.

(128) In operation 802, a control circuit 210 may rotate a DUT 220 using at least one driving part 250. The DUT 220 may rotate along a rotation direction 1 or a rotation direction 2. A main antenna

222 of the DUT **220** may be located on a rotary axis x or a rotary axis y to rotate at a fixed position. (129) In operation **804**, the control circuit **210** may radiate a first test signal and/or a second test signal. For example, the control circuit **210** may radiate the first test signal (e.g., an L1 signal) using at least one first antenna (e.g., at least one first antenna **520**). For example, the control circuit **210** may radiate a second test signal (e.g., an L5 signal) using a second antenna (e.g., an antenna **300**).

(130) In an embodiment, the at least one first antenna may be mounted on a mounting part **255** of the holder **240** at a fixed angle and/or interval with the DUT **220**. A CN0 value of the first test signal received by the DUT **220** from the at least one first antenna may be constant or a value within a specified range.

(131) In an embodiment, the at least one first antenna may be disposed on an inner wall of the antenna chamber **200**. For example, the at least one first antenna may be disposed at a different position on the inner wall of the antenna chamber **200** to radiate the first test signal. The at least one first antenna may perform a switching operation depending to rotation of the DUT **220** such that the CN0 value of the first test signal received by the DUT **220** is constant or a value within a specified range.

(132) In an embodiment, the control circuit **210** may calculate a receive sensitivity (a TIS) based on a CN0 value and a sensitivity of the L5 signal identified at a plurality of specified angle.

(133) In an embodiment, the DUT **220** may measure both of a CN0 of the L1 signal and a CN0 of the L5 signal. The control circuit **210** may compare the CN0 value of the L1 signal with the CN0 value of the L5 signal to identify a specific angle where the CN0 value of the L1 signal is higher than the CN0 value of the L5 signal. In this case, the position of the at least one antenna may be irrelevant. The control circuit **210** may increase an intensity of the L1 signal to a specified level at the corresponding angle. The specified level may be an intensity of the L1 signal where the DUT **220** is able to perform normal positioning based on the L5 signal irrespective of the L1 signal at the corresponding angle. In this case, normal positioning based on the L1 signal at all angles of the DUT **220** may be impossible. However, the control circuit **210** may calculate a TIS with high accuracy based on a CN0 value and/or a sensitivity at a specific angle.

(134) FIG. **9** is a diagram illustrating an example antenna chamber structure for improving the accuracy of measuring a receive sensitivity, according to various embodiments.

(135) Components of FIGS. **2** to **6** may be referenced to describe FIG. **9**.

(136) In an embodiment, an antenna chamber **200** may be implemented as a room structure having a cube shape. The antenna chamber **200** may include an inner wall corresponding to each direction (e.g., a +X-axis direction, a -X-axis direction, a +Y-axis direction, a -Y-axis direction, a +Z-axis direction, or a -Z-axis direction).

(137) At least one first antenna **900**, **902**, and **904** may be disposed on the inner wall of the antenna chamber **200**. For example, the at least one first antenna **900**, **902**, and **904** may be disposed at a different position on the inner wall of the antenna chamber **200**. For example, the 1-1st antenna **900** may be disposed on the inner wall corresponding to the +X-axis direction. For example, the 1-2nd antenna **902** may be disposed on the inner wall corresponding to the +Z-axis direction. For example, the 1-3rd antenna **904** may be disposed on the inner wall corresponding to the -X-axis direction.

(138) A holder **240** and an antenna **300** (e.g., a second antenna) may be arranged in the antenna chamber **200**. The holder **240** and the antenna **300** may be arranged spaced apart from each other at a specified interval. A DUT **220** may be disposed on a mounting part **255** of the holder **240**. The antenna **300** may be referred to as the second antenna.

(139) The control circuit **210** may rotate the DUT **220** using at least one driving part **250**. The control circuit **210** may radiate a first test signal (e.g., an L1 signal) through the at least one first antenna **900**, **902**, and **904**. The control circuit **210** may radiate a second test signal (e.g., an L5 signal) through the antenna **300**. For example, the antenna **300** may be an antenna which radiates a

signal to be tested.

(140) The control circuit **210** may control the at least one first antenna **900**, **902**, and **904** such that a CN0 value of the first test signal received by the DUT **220** is constant or a value within a specified range.

(141) In an embodiment, the at least one first antenna **900**, **902**, and **904** may be controlled to perform a switching operation. For example, the control circuit **210** may radiate the first test signal using some (e.g., the 1-1st antenna **900**) of the at least one first antenna **900**, **902**, and **904**. When the first test signal received by the DUT **220** is a weak electric field as the DUT **220** rotates, the control circuit **210** may switch the 1-1st antenna to some (e.g., the 1-2nd antenna) of the at least one first antenna **900**, **902**, and **904** to radiate the first test signal using the 1-2nd antenna.

(142) While the disclosure has been illustrated and described with reference to various example embodiments, it will be understood that the various example embodiments are intended to be illustrative, not limiting. It will be further understood by those skilled in the art that various changes in form and detail may be made without departing from the true spirit and full scope of the disclosure, including the appended claims and their equivalents. It will also be understood that any of the embodiment(s) described herein may be used in conjunction with any other embodiment(s) described herein.

Claims

1. An anechoic antenna chamber, comprising: a holder on which a device under test (DUT) is configured to be mounted; at least one first antenna configured to radiate a first test signal of a first frequency band; a second antenna provided at an inner side of the antenna chamber and configured to radiate a second test signal of a second frequency; at least one driver configured to rotate the DUT; and a control circuit operatively connected with the at least one first antenna, the second antenna, and the at least one driving part, wherein the control circuit is configured to: control the at least one driver to rotate the DUT; and control the at least one first antenna to radiate the first test signal having an intensity of a specified range and control the second antenna to radiate the second test signal, while rotating the DUT, and wherein the at least one driver includes: a first driver configured to rotate at least one mounting part about a first rotary axis; and a second driver configured to rotate the at least one mounting part about a second rotary axis perpendicular to the first rotary axis.
2. The anechoic antenna chamber of claim 1, wherein the at least one first antenna is mounted on a mounting part of the holder to form a fixed angle with the DUT, based on the DUT being mounted on the mounting part of the holder.
3. The anechoic antenna chamber of claim 2, wherein the control circuit is configured to: rotate the at least one first antenna together with the DUT using the at least one driver.
4. The anechoic antenna chamber of claim 1, wherein the at least one first antenna is provided on an inner wall of the antenna chamber, and wherein the control circuit is configured to: radiate the first test signal through some of the at least one first antenna.
5. The anechoic antenna chamber of claim 4, wherein the control circuit is configured to: based on the DUT rotating, radiate the first test signal based on a switching operation of the at least one first antenna.
6. The anechoic antenna chamber of claim 1, wherein the first test signal and the second test signal are signals based on a global navigation satellite system (GNSS), wherein the first test signal includes a signal of the 1575.42 MHz band, and wherein the second test signal includes a signal of the 1176.45 MHz band.
7. The anechoic antenna chamber of claim 6, wherein the control circuit is configured to: correct an error of positioning based on the first test signal using the second test signal.
8. The anechoic antenna chamber of claim 6, wherein the control circuit is configured to: measure a

receive sensitivity of the second test signal based on the first test signal received through the DUT.

9. The anechoic antenna chamber of claim 1, wherein the at least one driver includes a bearing.
10. The anechoic antenna chamber of claim 1, wherein the control circuit is configured to: rotate the DUT on at least one plane using the at least one driver.
11. The anechoic antenna chamber of claim 1, wherein a main antenna included in the DUT is disposed at a fixed position on the first rotary axis and the second rotary axis.
12. The anechoic antenna chamber of claim 1, wherein the control circuit is configured to: identify a radiation pattern of the second test signal received by the DUT at a specified angle, while the DUT rotates about the first rotary axis or the second rotary axis.
13. The anechoic antenna chamber of claim 12, wherein the control circuit is configured to: radiate the second test signal at a specified intensity, based on identifying the radiation pattern of the second test signal.
14. The anechoic antenna chamber of claim 13, wherein the control circuit is configured to: linearize the identified radiation pattern.
15. The anechoic antenna chamber of claim 13, wherein the control circuit is configured to: measure a sensitivity of the second test signal while adjusting an intensity of the second test signal, based on the radiation pattern.
16. The anechoic antenna chamber of claim 15, wherein the control circuit is configured to: calculate a total isotropic sensitivity (TIS) of the second test signal based on the radiation pattern and the sensitivity.
17. The anechoic antenna chamber of claim 1, further comprising: at least one of a network emulator, a global navigation satellite system (GNSS) simulator, or a positioning controller, wherein the control circuit is included as a part of at least one of the network emulator, the GNSS simulator, or the positioning controller.
18. The anechoic antenna chamber of claim 1, further comprising: an embossing structure comprising an embossing material configured to absorb a signal radiated from at least one antenna, wherein the embossing structure is provided on an inner wall of the antenna chamber.
19. The anechoic antenna chamber of claim 1, further comprising: a wireless communication circuit, wherein the control circuit is configured to: receive information associated with the second test signal from the DUT through the wireless communication circuit.
