

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12408206
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Zander; Olof et al.

Beam management during initial access

Abstract

A method of operating a wireless communication device (**102**) configured to connect to a communications network (**100**) includes: monitoring for multiple downlink reference signals (**411**) transmitted by at least one access node of the communications network (**100**) using multiple downlink transmit beams (**361-364**), each one of the multiple downlink reference signals (**411**) being associated with a respective at least one of multiple random-access occasions (**415-418**); and accessing at least two random-access occasions (**415, 418**) of the multiple random-access occasions (**415-418**), the at least two random-access occasions (**415, 418**) being associated with at least two downlink reference signals (**411**) selected from the multiple downlink reference signals (**411**) based on said monitoring and establishing a multibeam operation between the wireless communication device (**102**) and the communications network (**100**), wherein the multi-beam operation is established based on at least two downlink transmit beams (**361,364**) used for transmitting the selected at least two downlink reference signals (**411**).

Inventors:	Zander; Olof (Sodra Sandby, SE), Rusek; Fredrik (Eslov, SE), Bengtsson; Erik (Eslov, SE), Zhao; Kun (Malmo, SE), Flordelis; Jose (Lund, SE)
Applicant:	Sony Group Corporation (Tokyo, JP)
Family ID:	74191728
Assignee:	Sony Group Corporation (Tokyo, JP)
Appl. No.:	17/790714
Filed (or PCT Filed):	January 14, 2021
PCT No.:	PCT/EP2021/050665
PCT Pub. No.:	WO2021/144351
PCT Pub. Date:	July 22, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20230060540 A1	Mar. 02, 2023

Foreign Application Priority Data

SE	2030011-7	Jan. 14, 2020
----	-----------	---------------

Publication Classification

Int. Cl.: H04B7/06 (20060101); H04W74/00 (20090101); H04W74/08 (20240101); H04W74/0833 (20240101)

U.S. Cl.:

CPC H04B7/0695 (20130101); H04W74/006 (20130101); H04W74/0833 (20130101);

Field of Classification Search

CPC: H04B (7/0695); H04B (7/0404); H04W (74/006); H04W (74/0833); H04L (5/0048)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2017/0181132	12/2016	Xiao	N/A	H04L 5/005
2018/0331794	12/2017	Nagaraja	N/A	H04W 74/0833
2019/0029049	12/2018	Akkarakaran et al.	N/A	N/A
2019/0075014	12/2018	Zhou et al.	N/A	N/A
2019/0158345	12/2018	Lincoln	N/A	H04W 52/0251
2019/0215220	12/2018	Islam	N/A	H04W 74/085
2019/0254079	12/2018	Akoum et al.	N/A	N/A
2019/0357264	12/2018	Yi	N/A	H04W 74/002
2020/0008188	12/2019	Nam	N/A	H04W 72/0446
2020/0068484	12/2019	da Silva	N/A	H04W 24/10
2021/0176789	12/2020	Takahashi	N/A	H04B 7/088

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
109076543	12/2017	CN	N/A
109644494	12/2018	CN	N/A

2018084800	12/2017	WO	N/A
2018089265	12/2017	WO	N/A
2018171802	12/2017	WO	N/A
2019139730	12/2018	WO	N/A
2019139844	12/2018	WO	N/A
WO-2019192610	12/2018	WO	N/A
2019215012	12/2018	WO	N/A

OTHER PUBLICATIONS

International Search Report and Written Opinion from corresponding International Application No. PCT/EP/2021/050665, Mar. 25, 2021, 15 pages. cited by applicant

Office Action and Search Report from corresponding Swedish Application No. 2030011-7, Dec. 4, 2020, 9 pages. cited by applicant

Yu-Ngok Ruyue Li et al., “Beam Management in Millimeter-Wave Communications for 5G and Beyond,” IEEE Access, vol. 8, Jan. 1, 2020, vol. 8, 12 pages. cited by applicant

Nokia et al., “Beam Management in Initial Access,” 3rd Generation Partnership Project (3GPP) TSG-RAN WG1#86bis, R1-1610288, Oct. 10-14, 2016, 4 pages. cited by applicant

Nokia et al., “Beam Management Procedures in Beam Based Access,” 3rd Generation Partnership Project (3GPP) TSG-RAN WG1#86, R1-167286, Aug. 22-26, 2016, 5 pages. cited by applicant

J. Flordelis et al., “Massive MIMO Performance—TDD versus FDD: What do Measurements Say?”, IEEE Transactions on Wireless Communications, vol. 17, No. 4, Apr. 2018, 15 pages. cited by applicant

Primary Examiner: Salad; Abdullahi E

Attorney, Agent or Firm: Tucker Ellis LLP

Background/Summary

TECHNICAL FIELD

(1) Various examples relate to beam management for a multi-beam operation in a communication system. More specifically, various examples relate to beam management during initial access of a wireless communication device to a cellular network.

BACKGROUND

(2) Multiple-input multiple-output (MIMO) techniques are sometimes used to enhance reliability and/or throughput of communication on a wireless link. Here, the transmitter node and the receiver node both include multiple antennas that can be operated in a phase-coherent manner. Thereby, a signal can be transmitted redundantly (diversity multi-antenna mode) along multiple spatial data streams, or multiple signals can be transmitted on multiple spatial data streams (spatial multiplexing multi-antenna operational mode). Spatial data streams can be defined by focusing the transmission energy for transmitting (transmit beam, TX beam) and/or the receive sensitivity for receiving (receive beam, RX beam) to a particular spatial direction. Here, the process of identifying the appropriate beams is often referred to as beam establishment or beam management.

(3) Beam management typically requires control signaling between the nodes of the MIMO communication system. For example, where a MIMO communication system is implemented by a base station of a cellular network and a wireless communication device attachable to the cellular network, initial access of the wireless communication device to the cellular network may impose a framework of control signaling that, according to reference implementations, makes it difficult to

implement beam management at this early stage.

SUMMARY

(4) Accordingly, there is a need for advanced techniques of beam management during initial access. This need is met by the features of the independent claims. The features of the dependent claims define embodiments.

(5) A method of operating a UE is provided. The UE is configured to connect to a communications NW. The method includes monitoring for multiple downlink reference signals. The multiple downlink reference signals are transmitted by at least one access node of the communications network. The multiple downlink reference signals are transmitted using multiple downlink transmit beams. Each one of the multiple downlink reference signals is associated with a respective at least one of multiple random-access occasions. The method also includes accessing at least two RA occasions of the multiple RA occasions. The at least two RA occasions are associated with at least two downlink reference signals. The at least two downlink reference signals are selected from the multiple downlink reference signals. Said selecting is based on said monitoring. The method further includes establishing a multi-beam operation between the UE and the communications network. The multi-beam operation is established based on the at least two downlink transmit beams used for transmitting the selected at least two downlink reference signals.

(6) A computer program or a computer-program product or a computer-readable storage medium includes program code. The program code can be executed by at least one processor. Executing the program code causes the at least one processor to perform a method of operating a UE. The UE is configured to connect to a communications NW. The method includes monitoring for multiple downlink reference signals. The multiple downlink reference signals are transmitted by at least one access node of the communications network. The multiple downlink reference signals are transmitted using multiple downlink transmit beams. Each one of the multiple downlink reference signals is associated with a respective at least one of multiple random-access occasions. The method also includes accessing at least two RA occasions of the multiple RA occasions. The at least two RA occasions are associated with at least two downlink reference signals. The at least two downlink reference signals are selected from the multiple downlink reference signals. Said selecting is based on said monitoring. The method further includes establishing a multi-beam operation between the UE and the communications network. The multi-beam operation is established based on the at least two downlink transmit beams used for transmitting the selected at least two downlink reference signals.

(7) A wireless communication device is configured to connect to a communications network. The wireless communication device includes control circuitry configured to monitor for multiple downlink reference signals transmitted by at least one access node of the communications network using multiple downlink transmit beams, each one of the multiple downlink reference signals being associated with a respective at least one of multiple random-access occasions. The control circuitry is further configured to access at least two random-access occasions of the multiple random-access occasions, the at least two random-access occasions being associated with at least two downlink reference signals selected from the multiple downlink reference signals based on said monitoring. The control circuitry is further configured to establish a multi-beam operation between the wireless communication device and the communications network, wherein the multi-beam operation is established based on at least two downlink transmit beams used for transmitting the selected at least two downlink reference signals.

(8) A method of operating at least one access node of a communications network is provided. The method includes transmitting multiple downlink reference signals. The multiple downlink reference signals are transmitted using multiple downlink transmit beams. Each one of the multiple downlink reference signals is associated with a respective at least one of multiple RA occasions. The method also includes monitoring an access of the UE to at least two RA occasions associated with at least two downlink reference signals of the multiple downlink reference signals.

The method also includes establishing a multi-beam operation based on said monitoring of the access. The multi-beam operation is between the EU and the communications network. The multi-beam operation is established based on at least two downlink transmit beams of the multiple downlink transmit beams that are used for transmitting the at least two downlink reference signals.

(9) A computer program or a computer-program product or a computer-readable storage medium includes program code. The program code can be executed by at least one processor. Executing the program code causes the at least one processor to perform a method of operating at least one access node of a communications network. The method includes transmitting multiple downlink reference signals. The multiple downlink reference signals are transmitted using multiple downlink transmit beams. Each one of the multiple downlink reference signals is associated with a respective at least one of multiple RA occasions. The method also includes monitoring an access of the UE to at least two RA occasions associated with at least two downlink reference signals of the multiple downlink reference signals. The method also includes establishing a multi-beam operation based on said monitoring of the access. The multi-beam operation is between the EU and the communications network. The multi-beam operation is established based on at least two downlink transmit beams of the multiple downlink transmit beams that are used for transmitting the at least two downlink reference signals.

(10) At least one access node of a communications network includes control circuitry. The control circuitry is configured to transmit multiple downlink reference signals using multiple downlink transmit beams, each one of the multiple downlink reference signals being associated with a respective at least one of multiple random-access occasions. The control circuitry is also configured to monitor an access of the wireless communication device to at least two random-access occasions associated with at least two downlink reference signals of the multiple downlink reference signals. Further, the control circuitry is further configured to, establish a multi-beam operation between the wireless communication device and the communications network based on said monitoring of the access, wherein the multi-beam operation is established based on at least two downlink transmit beams of the multiple downlink transmit beams used for transmitting the at least two downlink reference signals.

(11) It is to be understood that the features mentioned above and those yet to be explained below may be used not only in the respective combinations indicated, but also in other combinations or in isolation without departing from the scope of the invention.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 schematically illustrates a communication system according to various examples.
- (2) FIG. 2 schematically illustrates MIMO operation of the communication system of FIG. 1 according to various examples.
- (3) FIG. 3 schematically illustrates a transmit beam sweep of a base station of the communication system according to various examples.
- (4) FIG. 4 schematically illustrates a receive beam sweep of a wireless communication device of the communication system according to various examples.
- (5) FIG. 5 schematically illustrates multi-beam operation of the wireless communication system according to various examples.
- (6) FIG. 6 schematically illustrates a cellular network according to various examples.
- (7) FIG. 7 schematically illustrates multiple connection modes in which the wireless communication device can be operated according to various examples.
- (8) FIG. 8 schematically illustrates multiple random-access occasions for initial access of the wireless communication device to the cellular network according to various examples.

(9) FIG. 9 is a signaling diagram of communicating between the wireless communication device and the cellular network according to various examples.

(10) FIG. 10 is a flowchart of a method according to various examples.

(11) FIG. 11 is a flowchart of a method according to various examples.

DETAILED DESCRIPTION OF EMBODIMENTS

(12) Some examples of the present disclosure generally provide for a plurality of circuits or other electrical devices. All references to the circuits and other electrical devices and the functionality provided by each are not intended to be limited to encompassing only what is illustrated and described herein. While particular labels may be assigned to the various circuits or other electrical devices disclosed, such labels are not intended to limit the scope of operation for the circuits and the other electrical devices. Such circuits and other electrical devices may be combined with each other and/or separated in any manner based on the particular type of electrical implementation that is desired. It is recognized that any circuit or other electrical device disclosed herein may include any number of microcontrollers, a graphics processor unit (GPU), integrated circuits, memory devices (e.g., FLASH, random access memory (RAM), read only memory (ROM), electrically programmable read only memory (EPROM), electrically erasable programmable read only memory (EEPROM), or other suitable variants thereof), and software which co-act with one another to perform operation(s) disclosed herein. In addition, any one or more of the electrical devices may be configured to execute a program code that is embodied in a non-transitory computer readable medium programmed to perform any number of the functions as disclosed.

(13) In the following, embodiments of the invention will be described in detail with reference to the accompanying drawings. It is to be understood that the following description of embodiments is not to be taken in a limiting sense. The scope of the invention is not intended to be limited by the embodiments described hereinafter or by the drawings, which are taken to be illustrative only.

(14) The drawings are to be regarded as being schematic representations and elements illustrated in the drawings are not necessarily shown to scale. Rather, the various elements are represented such that their function and general purpose become apparent to a person skilled in the art. Any connection or coupling between functional blocks, devices, components, or other physical or functional units shown in the drawings or described herein may also be implemented by an indirect connection or coupling. A coupling between components may also be established over a wireless connection. Functional blocks may be implemented in hardware, firmware, software, or a combination thereof.

(15) Techniques are described that facilitate initial access of a UE to a communications network, e.g., to a cellular network. In particular, techniques are described that facilitate initial access using MIMO operation. In particular, the techniques described herein facilitate beam management during the initial access of a wireless communication device (UE) to a cellular network (NW). The techniques described herein can be used to reliably determine one or more downlink (DL) transmit (TX) beams at a base station (BS) of the cellular NW to be used for transmitting data to the UE. The one or more DL TX beams can then be used for subsequent communication of data, e.g., application data and/or higher-layer control data. Alternatively or additionally, using the techniques described herein, it is possible to determine one or more uplink (UL) receive (RX) beams at the BS. DL TX beams and UL RX beams are so-called BS beams, because they are employed by the BS.

(16) In some examples, it is also possible to determine UE beams, i.e., UL TX beams and/or DL RX beams. RX beams can be defined by a RX spatial filter. Alternatively or additionally, TX beams can be defined by a TX spatial filter. More generally speaking, a transmission using a spatial filter results in a certain beam or beam pattern.

(17) Once a beam has been determined, this beam can be used for subsequent communication of data, e.g., application data and/or higher-layer control data.

(18) According to various examples, it is possible for the UE to access multiple random-access (RA) occasions, the RA occasions (ROs) being associated with different BS beams. Based on this

multi-RO access, it is then possible to establish a multi-beam operation. I.e., information conveyed by or determined based on the multi-RO access can be used to appropriately configure the multi-beam operation. For example, the BS can acquire information on multiple high-quality beam pairs between the BS and the UE already during initial access and at low delay. The overall control signaling overhead can be reduced. The capacity of the wireless link between the UE and the BS can be estimated. The multiple beam pairs determined from the multi-RO access can be used for the multi-beam operation.

(19) For example, the UE may monitor for multiple DL reference signals (RSs). The DL RSs can be transmitted by the BS using multiple DL TX beams. Then, based on a comparison of RX properties of the multiple DL RSs—e.g., a RX amplitude—the UE can determine two or more strongest DL TX beams. The DL RSs can be associated with different ROs. The UE can accordingly select those ROs that are associated with the DL RSs having been transmitted using the two or more strongest DL TX beams. Then, the multi-beam operation—e.g., UL and/or DL multi-beam operation—can be established based on the two or more strongest DL TX beams and/or UL RX beams corresponding to those DL TX beams (e.g., having the same antenna weights). For example, the two or more strongest DL TX beams and/or the corresponding two or more UL RX beams may be used for the transmission in accordance with the multi-beam operation, e.g., for a subsequent data communication during a connected mode. It would also be possible to refine the two or more strongest DL TX beams and/or the corresponding two or more strongest UL RX beams: such beam refinement can include determining sub-beams, e.g., having a narrower beam width.

(20) FIG. 1 schematically illustrates a communication system. The communication system includes two nodes **101**, **102** that are configured to communicate with each other via a wireless link **114**. In the example of FIG. 1, the node **101** is implemented by an access node, more specifically a BS, and the node **102** is implemented by a UE. The BS **101** can be part of a cellular NW (not shown in FIG. 1). As a general rule, the techniques described herein could be used for various types of communication systems, e.g., also for peer-to-peer communication, etc. For sake of simplicity, however, hereinafter, various techniques will be described in the context of a communication system that is implemented by a BS of a cellular NW and a UE.

(21) Communication on the wireless link **114** can employ time-division duplex (TDD) and/or frequency-division duplex (FDD). Using TDD, communication in the DL and in the UL takes place at different points in time using the same frequency. Using FDD, communication in the DL and in the UL takes place at the same point in time, using different frequencies.

(22) FIG. 2 illustrates details with respect to the BS **101**. The BS **101** includes control circuitry that is implemented by a processor **1011** and a non-volatile memory **1015**. The processor **1011** can load program code that is stored in the memory **1015**. The processor **1011** can then execute the program code. Executing the program code causes the processor to perform techniques as described herein, e.g.: communicating on a wireless link using MIMO; performing beamsweeps; transmitting signals such as RSs; scheduling signals for transmission on the wireless link; participating in initial access of the UE **102**; monitoring for the UE **102** accessing ROs; participating in establishment of a MIMO operation; participating in data transmission in accordance with the MIMO operation; etc.

(23) FIG. 2 also illustrates details with respect to the UE **102**. The UE **102** includes control circuitry that is implemented by a processor **1021** and a nonvolatile memory **1025**. The processor **1021** can load program code that is stored in the memory **1025**. The processor can execute the program code. Executing the program code causes the processor to perform techniques as described herein, e.g.: communicating on a wireless link using MIMO and/or FDD; performing beamsweeps; participating in an initial access of the UE **102** to the cellular NW of the BS **101**; monitoring for RSs, i.e., attempting to receive RSs; selecting one or more ROs; participating in establishment of a MIMO operation; participating in data transmission in accordance with the MIMO operation; etc.

(24) FIG. 2 also illustrates details with respect to communication between the BS **101** and the UE

102 on the wireless link **114**. The BS **101** includes an interface **1012** that can access and control multiple antennas **1014**. Likewise, the UE **102** includes an interface **1022** that can access and control multiple antennas **1024**.

(25) While the scenario of FIG. 2 illustrates the antennas **1014** being coupled to the BS **101**, as a general rule, it would be possible to employ transmit-receive points (TRPs) that are spaced apart from the BS.

(26) The interfaces **1012**, **1022** can each include one or more TX chains and or more receiver chains. For instance, such RX chains can include low noise amplifiers, analogue to digital converters, mixers, etc. Analogue and/or digital beamforming would be possible.

(27) Thereby, phase-coherent transmitting and/or receiving (communicating) can be implemented across the multiple antennas **1014**, **1024**. Thereby, the BS **101** and the UE **102** implement a MIMO communication system.

(28) As a general rule, the receiver of the MIMO communication system receives a signal y that is obtained from an input signal x multiplied by the transmission matrix H . FIG. 2 includes two example labels for the components $h_{sub.11}$ and $h_{sub.13}$ of the transmission matrix H .

(29) The transmission matrix H defines the channel impulse response of the wireless link **114**. The rank of the transmission matrix corresponds to the number of linearly independent rows or columns and, as such, indicates how many independent data streams can be used simultaneously; this is sometimes referred to as the number of layers. The rank can be set in different MIMO transmission modes. For MIMO transmission modes, the amplitude and/or phase (antenna weights) of each one of the antennas **1014**, **1024** is appropriately controlled by the interfaces **1012**, **1022**.

(30) For instance, a diversity MIMO transmission mode relies on transmitting the same data redundantly using multiple TX antennas. Thus, multiple data streams carry the same data. Thereby, the signal-to-noise ratio can be increased. The redundant signals can be generated using different encoding, e.g., Alamouti encoding.

(31) Another MIMO transmission mode is spatial multiplexing. Spatial multiplexing allows to increase the data rate: The data is divided into different data streams and these different data streams can be transmitted contemporaneously over the wireless link **114**.

(32) The diversity MIMO transmission mode and the spatial multiplexing multi-antenna transmission mode can be described as using multiple beams, the beams defining the spatial data streams. These modes are, therefore, also referred to as multi-beam operation. By using a beam, the direction of the wavefront of signals transmitted by a transmitter of the communication system is controlled. Energy is focused into a respective direction, by phase-coherent superposition of the individual signals originating from each antenna **1014**, **1024**. Thereby, the spatial data stream can be directed. The spatial data streams transmitted on multiple beams can be independent, resulting in spatial multiplexing multi-antenna transmission; or dependent on each other, e.g., redundant, resulting in diversity MIMO transmission.

(33) As a general rule, alternatively or additionally to such TX beams, it is possible to employ RX beams.

(34) The concept of beams can be used in so-called beamsweeps. Details with respect to beamsweeping are explained next in connection with FIG. 3 and FIG. 4.

(35) FIG. 3 illustrates DL TX beams **301-309** used by the BS **101**. In some examples, the BS **101** can employ a beamsweep **300**. Here, the BS **101** activates the beams **301-309** on different resources (e.g., different time-frequency resources, and/or using orthogonal codes) such that the UE **102** can monitor for respective signals transmitted on the DL TX beams **301-309**. As a general rule, monitoring for signals can pertain to attempting to receive signals. This can include blind decoding, etc. The UE **102** may then select the best DL TX beam **301-309**—e.g., based on a RX property of the received signal, such as amplitude and/or phase and/or angle-of-arrival, etc.—and provide a respective indication to the BS **101**. As a general rule, the best DL TX beam **301-309** could be the strongest beam. Also, other quality metrics may be taken into account, e.g., signal-to-noise. Then,

subsequent data can be communicated on the selected DL TX beam **301-309**. Such beam management can, in particular, be facilitated by using RSs, i.e., signals having a well-defined transmit property such as sequence, amplitude, phase, and/or precoding, etc.. RSs are sometimes also referred to as pilot signals.

(36) It would be possible that such DL TX beamsweep **300** implemented by the BS **101** is coordinated with a DL RX beamsweep **310** implemented by the UE **102**. A DL RX beamsweep **310** is illustrated in FIG. **4**. The DL RX beamsweep **310** includes multiple DL RX beams **311*-313*** (for sake of simplicity, throughout this text, RX beams are denoted with “*”). The DL RX beamsweep **310** does not necessarily have to be coordinated with a DL TX beamsweep **300**.

(37) FIG. **5** schematically illustrates aspects with respect to the diversity MIMO transmission mode. Here, the multiple transmit antennas are used to define multiple spatial data streams that carry the same data; this can also be viewed as a coherent combination of multiple DL TX beams **301-303** with optimized phase shifts.

(38) FIG. **6** schematically illustrates a cellular NW **100**. The example of FIG. **6** illustrates the cellular NW **100** according to the 3GPP NR/5G architecture. Details of the 3GPP 5G architecture are described in 3GPP TS 23.501, version 15.3.0 (**2017-09**). While FIG. **1** and further parts of the following description illustrate techniques in the 3GPP 5G framework of a cellular NW, similar techniques may be readily applied to other communication protocols. Examples include 3GPP LTE 4G—e.g., in the MTC or NB-IOT framework—and even non-cellular wireless systems, e.g., an IEEE Wi-Fi technology.

(39) In the scenario of FIG. **1**, a UE **102** is connectable to the cellular NW **100** via a data connection. For example, the UE **102** may be one of the following: a cellular phone; a smart phone; an IOT device; an MTC device; a sensor; an actuator; etc.

(40) The UE **102** is connectable to a core NW (CN) **115** of the cellular NW **100** via a RAN **111**, typically formed by one or more BSs **101** (only a single BS **101** is illustrated in FIG. **1** for sake of simplicity). A wireless link **114** is established between the RAN **111**—specifically between one or more of the BSs **112** of the RAN **111**—and the UE **102**.

(41) The wireless link **114** implements a time-frequency resource grid. Typically, OFDM is used: here, a carrier includes multiple subcarriers. The subcarriers (in frequency domain) and the symbols (in time domain) then define time-frequency resource elements of the time-frequency resource grid. Thereby, a protocol time base is defined, e.g., by the duration of frames and subframes including multiple symbols and the start and stop positions of the frames and subframes. Different time-frequency resource elements can be allocated to different logical channels or RSs of the wireless link **114**.

(42) Examples include: Physical DL Shared Channel (PDSCH); Physical DL Control Channel (PDCCH); Physical UL Shared Channel (PUSCH); Physical UL Control Channel (PUCCH); channels for random access; etc.. For FDD, the PUCCH and PUSCH are communicated on the wireless link **114** in the UL frequency band **601** and the PDCCH and the PDSCH are in the DL frequency band **602** (hence, the names “UL frequency band” and “DL frequency band”).

(43) The CN **115** includes a user plane (UP) **191** and a control plane (CP) **192**. Application data—e.g., of a data service—is typically routed via the UP **191**. For this, there is provided a UP function (UPF) **121**. The UPF **121** may implement router functionality. Application data may pass through one or more UPFs **121**. In the scenario of FIG. **1**, the UPF **121** acts as a gateway towards a data NW (DN) **180**, e.g., the Internet or a Local Area NW. Application data can be communicated between the UE **102** and one or more servers **181** of the data NW **180**. The server **181** can execute an application that provides a service associated with the application data.

(44) The cellular NW **100** also includes a mobility-control node, here implemented by an Access and Mobility Management Function (AMF) **131**. The cellular NW **100** also includes a session-control node, here implemented by a Session Management Function (SMF) **132**. The cellular NW **100** further includes a Policy Control Function (PCF) **133**; a NW Slice Selection Function (NSSF)

135; an Authentication Server Function (AUSF) **136**; and a Unified Data Management (UDM) **137**. (45) FIG. 6 also illustrates the protocol reference points N1-N22 between these nodes.

(46) The AMF **131** provides one or more of the following functionalities: connection management sometimes also referred to as registration management; NAS termination for communication between the CN **115** and the UE **102**; connection management; reachability management; mobility management; connection authentication; and connection authorization. After UE registration to the NW, the AMF **131** creates a UE context **459** and keeps this UE context, at least as long as the UE **102** is registered to the cellular NW **100**. The UE context **459** can hold one or more identities of the UE **102** (UE ID), e.g., temporary identities.

(47) The SMF **132** supports a data connection **189**. The data connection **189** is established by the SMF **132** if the respective UE **102** operates in a connected connection mode. The data connection **189** is established on the wireless link **114**. The wireless link **114** can pertain to the underlying physical medium and the data connection **189** can include a set of logical channels, scheduling rules, etc. The data connection **189** may include one or more data flows or bearers such as a dedicated data flow/bearer or a default data flow/bearer. The state of the data connection is also defined on the RRC layer, e.g., generally Layer 3 of the OSI model. The SMF **132** provides one or more of the following functionalities: session management including session establishment, modify and release, including data flow/bearer set up of UP data flows/bearers between the RAN **111** and the UPF **121**; selection and control of UPFs; configuring of traffic steering; etc.

(48) FIG. 7 illustrates aspects with respect to different connection modes **401-402** in which the UE **102** can operate according to various examples. When operating in the connected connection mode **401**, the data connection **189** between the UE **102** and the cellular NW **100** is established. Application data can be communicated to and from the UE **102**. A transition into the connected connection mode **401** is referred to as initial access.

(49) When operating the UE **102** in the idle connection mode **402**, the data connection **189** is released. It would be possible that the AMF **131** maintains the UE context **459**. The UE **102** can use a discontinuous reception cycle (DRX) cycle that alternately switches the interface **1022** between an inactive state and an active state. The interface **1022**—when operating in the inactive state—may not be able to RX any signals. E.g., an amplifier or an analogue to digital converter or parts of the digital front end may be switched off. On the other hand, the interface **1022**—when operating in the active state—may be able to RX signals, e.g., paging signals.

(50) To transition from the idle connection mode **402** to the connected connection mode **401**, a RA procedure may be performed. The RA procedure includes transmitting a RA preamble at a RO. Details with respect to the ROs are illustrated in FIG. 8.

(51) FIG. 8 schematically illustrates aspects with respect to synchronization signal blocks (SSBs). FIG. 8 illustrates that the BS **101** transmits multiple SSBs **411** at different resources, e.g., time-frequency and/or code resources.

(52) The SSBs **411** can facilitate a cell search for the UE **102** during initial access. An SSB **411** can, e.g., include a primary synchronization signal (SS) and a secondary SS. The primary SS and the secondary SS implement RSs. The SSBs **411** can include a physical broadcast channel (PBCH). The PBCH carries a master information block and uses a specific modulation, typically quadrature phase shift keying, for reliable reception.

(53) Within an SSB **411**, the primary SS and the secondary SS are for the UE **102** to lock in to the correct frequency and time. There is also some identity of the transmitting BS **101** encoded into the combined SS. When in sync, the UE **102** can extract information about the associated RA channel allocation from the PBCH.

(54) The SSBs **411** can be repeatedly or periodically transmitted by the BS **101**, e.g., on predefined time-frequency resources of the time-frequency resource grid.

(55) It is possible that a burst **410** of SSBs **411** is transmitted, employing a beamsweep **360** including the DL TX beams **361-364**. Thereby, spatial coverage can be increased. Typically, the

burst may have a duration of, e.g., up to 5 ms. The periodicity with which the bursts are transmitted may be 20 ms to 160 ms.

(56) The SSBs **411** transmitted on different DL TX beams **361-364** can have a different SSB time index. Thus, different SSBs **411**—i.e., having different SSB time indices—are associated with different ROs **415-418**.

(57) FIG. **8** also illustrates aspects with respect to the ROs **415-418**. As illustrated in FIG. **8**, there is an association **419** between SSBs **411** of the burst **410** having different SSB time indices, and multiple ROs **415-418**. The different ROs **415-418** are arranged at different times, frequencies or employ different—e.g., orthogonal—codes for the RA preamble.

(58) The association **419** between the SSBs **411** and the ROs **415-418** is typically implemented by pre-defining a number of SSB time indices per RO. This number can be larger than one which corresponds to multiple SSBs being associated with a single RO. The number can also be smaller than one which corresponds to a single SSB corresponding to multiple ROs. The SSBs (e.g., in ascending order of the time index) are then associated with the ROs, firstly, in frequency domain; secondly, in time domain within a slot; and thirdly in time domain between RA slots.

(59) By selecting the appropriate RO **415-418**, the UE **102** can indicate—according to reference implementations—which DL TX beam **361-364** was best. This enables to establish an appropriate beam pair during initial access.

(60) The general framework of beam management during initial access has been described above. This framework of beam management during initial access can be enhanced by inventive concepts pertaining to multi-RO access. Such examples will be described next.

(61) In the example of FIG. **8**, the UE **102** accesses two ROs **415, 418**, to establish multiple beam pairs. As a general rule, in the various examples described herein, it is possible that the UE **102** accesses two or more ROs. Then, multi-beam operation can be established on the wireless link **114** using the BS beams associated with the selected ROs: for DL transmission, this would include the DL TX beams **361, 364**; and for UL transmission this would include the UL RX beams **351*** and **354***. The UL RX beam **351*** corresponds to the DL TX beam **361** in that it has a similar spatial characteristic and/or assumed beam correspondence. For example, the same antenna weights may be used for the BS beams **351*** and **361**.

(62) FIG. **8** also illustrates aspects with respect to beam management at the UE **102** for UL TX beams to be used by the UE **102** to access the multiple ROs. There are various options available for implementing the access to the multiple ROs at the UE **102**. Two of these options are illustrated in FIG. **8**: in a first option (option I), it would be possible that the UE **102** uses the same UL TX beam—here, UL TX beam **381**—for accessing both the ROs **415, 418**. In a second option (option II), it would be possible that the UE **102** uses different UL TX beams—here, UL TX beams **381** and **384**—for accessing the ROs **415, 418**. It would also be possible that for some ROs different UL TX beams are used, while for other ROs the same UL TX beams are used.

(63) In option I, the BS **101** can coherently combine signals received using multiple UL RX beams with optimized phase shift and/or amplitude, thereby obtaining a higher multi-antenna gain for rank-1 transmissions. The UL TX beam **381** used in option I to access, both, the RO **415**, as well as the RO **418** is determined in accordance with the DL TX beam **361**. For example, it would be possible that the UE **102** determines an angle of arrival of the SSB **411** transmitted using the DL TX beam **361**, e.g., based on a receive property of a corresponding RS included in the SSB **411**, e.g., the amplitude and/or phase at the various antennas **1024** of the UE **102**. Then, the UE **102** could determine the appropriate antenna weights so as to transmit UL signals with the same spatial characteristics, i.e., to invert the direction of the spatial data stream. This can be helpful under the assumption of channel reciprocity.

(64) On the other hand, the UL TX beams **381, 384** used in option II to access the RO **415** and the RO **418**, respectively, is determined in accordance with the DL TX beams **361** and **364**, respectively. The DL TX beam **361** is used to transmit the SSB **411** that is associated with the RO

415 which is accessed using the UL TX beam **381**. The DL TX beam **364** is used to transmit the SSB **411** that is associated with the RO **418** which is accessed using the UL TX beam **384**.

(65) Thereby, according to option I, it is possible to configure a spatial diversity multi-antenna mode in which a single DL RX beam—i.e., DL RX beams **381*** corresponding to the UL TX beam **381**—is used at the UE **102** (cf. FIG. 5). The BS **101** can use the DL TX beams **361**, **364** to generate two dependent spatial data streams. The UE **102** can indicate, in a respective device parameter of the multi-beam operation that it prefers the diversity multi-antenna mode, and/or that it has coherent decoding/encoding capability, and/or whether the diversity multi-antenna mode is for UL transmission and/or DL transmission.

(66) According to option II, spatial diversity or spatial multiplexing multi-antenna operational modes can be used, relying on the multiple DL RX beams **381*** and **384***. Multiple beam pairs between UE **102** and BS **101** can be established, already during initial access; these beam pairs can be used after initial access, when communicating payload data. The UE can indicate, in a respective device parameter of the multi-beam operation, that it prefers spatial-multiplexing or diversity multi-antenna mode, and/or has coherent or non-coherent operation, and/or whether the respective multi-antenna mode is for UL transmission and/or DL transmission.

(67) FIG. 9 is a signaling diagram of communication between the BS **101** and the UE **102**. FIG. 9, in particular, illustrates aspects with respect to beam management during initial access, in accordance with FIG. 8. This is one illustrative example; other signal flows are possible.

(68) FIG. 9 illustrates aspects with respect to communicating a configuration regarding access to multiple ROs. The configuration can be communicated from the communications NW **100** to the UE **102**—cf. NW configuration **6011**—and/or from the UE **102** to the communications NW **100**—cf. device configuration at **6506**. The multi-RO access then is in accordance with such configuration. For example, such configuration can impose certain constraints on the multi-RO access, e.g., in terms of the number of ROs accessed and/or in terms of the UL TX beams used by the UE for accessing the ROs. The multi-beam operation can be set in accordance with the configuration. Specifically, by communicating the configuration, it is possible for the communications NW **100** to appropriately configure the multi-beam operation. For instance, the UE **102** could indicate that it will use the same UL TX beam for accessing multiple ROs; then, the cellular NW can configure a diversity multi-antenna mode using multiple spatial streams that rely on a single UE beam. The rank of the multi-beam operation may be set in accordance with the indicated number of UL TX beams used by the UE for accessing the ROs.

(69) Initially, at **6501**, the UE **102** receives a network configuration **6011** transmitted by the BS **101** of the cellular network **100**. The network configuration **6011** is indicative of a network support of the UE **102** accessing multiple ROs **415-418**. Thus, the access to more than a single RO **415-418** can be conditional on the respective network support as indicated by the network configuration **6011**. If the cellular NW **100** does not support multi-RO access, the UE **102** may only access a single RO **415-418** (e.g., except for escalation strategies where access on a given RO **415-418** fails).

(70) There are various options available of providing the NW configuration to the UE **102**. For instance, the NW configuration **6011** could be received on the PDCCH or as a control message on the PDSCH, e.g., as a RRC Layer 3 control message, while operating the UE **102** in the connected connection mode **401**. It would also be possible that the NW configuration **6011** is included in a system information block that is broadcasted by the BS **101**. In yet another option, it would be possible that the NW configuration **6011** is received during a RA procedure as early data **6012**, e.g., at **6507** (as will be explained in detail below).

(71) It would be possible that the NW configuration **6011** is indicative of a maximum number of ROs **415-418** to be accessed by the UE **102**. For example, the NW configuration **6011** could be indicative of the UE **102** being allowed to access four or fewer ROs **415-418**. Then, the UE **102** may determine the appropriate number of ROs **415-418** to be accessed based on, e.g., its multi-

beam operation configuration, a receive property of the RSs included in the SSBs **411** that are transmitted using the multiple beams **361-364**, etc., as well as in accordance with the maximum number of ROs.

(72) The NW configuration **6011** can be indicative of a minimum number of UL TX beams to be used by the UE **102** when accessing the ROs **415-418**. For example, the NW configuration **6011** could be indicative of the number of UL TX beams expressed in terms of the number of ROs **415-418** to be used. For example, the NW configuration **6011** could be indicative of the UE **102** to use M UL TX beams when accessing N ROs **415-418**. M could be equal or smaller than N. M could be a function of N, i.e., M(N).

(73) The NW configuration **6011** could also be indicative of a set number of UL TX beams to be used by the UE **102** when accessing the ROs **415-418**. I.e., the NW may set the number of UL TX beams to a certain value. The UE **102** may not have any choice regarding the selection of the number of UL TX beams to be used when accessing the ROs **415-418**.

(74) Prior to initiating the RA procedure **600**, the UE **102** monitors for SSBs **411** transmitted by the BS **101**. This transmission is implemented using a beamsweep, e.g., the beamsweep **360** (cf. FIG. **8**). The SSBs **411** transmitted at **6502** thus form a burst **410**. Based on the SSBs **411**, the UE **102** can synchronize with the BS **101**.

(75) The UE **102** can then monitor for paging indicators and paging messages (paging signals) **6000**. Blind decoding of the PDCCH for receiving the paging indicator can be implemented.

(76) Upon receiving the paging signal **6000** at **6503**, initial access is triggered, in this example using RA procedure **600**.

(77) As a general rule, there are other trigger criteria for initial access, e.g., UE power up or UE-originating UL data. As such, the paging signal **6000** is optional.

(78) At **6504**, based on the SSBs **411**, the UE **102** transmits a RA preamble to the BS **101**, in a respective RAm_{sg}1 **6001**. Thereby, the UE **102** accesses RO **415**. This RAm_{sg}1 **6001** may be indicative of a temporary identity of the UE **102** (UE-ID).

(79) In response to transmitting the RAm_{sg}1 **6001**, the UE **102** receives, at **6505**, a RA response message, the RAm_{sg}2 **6002**. The RAm_{sg}2 includes a new temporary identity for the UE **102**, timing adjustment information, and an UL scheduling grant for time-frequency resources. The UL scheduling grant may be addressed to the UEs **102** RA Radio NW Temporary Identity (RA-RNTI). Using these UL resources indicated by the UL scheduling grant included in the RAm_{sg}2 **6002**, the UE **102** sends, at **6506**, a RRC connection request RAm_{sg}3 **6003**. In response to the RRC connection request **6003**, the UE **102** receives, at **6507**, a contention resolution message RAm_{sg}4 **6004** to ensure the right UE is addressed. This finalizes or aborts establishment of the data connection **189**. The UE **102** is then transitioned into operation into the connected connection mode **401**.

(80) Early data (ED) **6012**—e.g., application data or RRC control data—can be included in the RAm_{sg}3 **6003** and/or the RAm_{sg}4 **6004**. Thus, generally UL ED and/or DL ED is possible to be included in the RA procedure. The ED **6012** can be piggybacked to the RAm_{sg}3 **6003** and/or the RAm_{sg}4 **6004**, e.g., in a NAS field. ED **6012** could also be included in RAm_{sg}2, or even in RAm_{sg}1, e.g., by using preamble partitioning. For a 2-step RA procedure, ED can be included in the RAm_{sg}A and RAm_{sg}B (corresponding to RAm_{sg}1 and RAm_{sg}3, and RAm_{sg}2 and RAm_{sg}4, respectively).

(81) At **6508**, a further RA preamble **6001** is transmitted by the UE **102**, thereby accessing the RO **418**. As will be appreciated, the ROs **415** and **418** can be accessed based on the same measurements of the burst **410** of the SSBs **411** transmitted by the BS **101** at **6502** (in other examples, further bursts **410** of SSBs **411** may be monitored). Further, the RO **418** is accessed even though the access to the RO **415** has been successful, i.e., the multi-RO access is not due to an escalation strategy in case of failed RO access.

(82) The UL ED **6012** can be used to provide a device configuration associated with the UE **102**

accessing multiple ROs **415-418** to the cellular NW **100**. The UE **102** can access the multiple ROs **415-418** in accordance with the device configuration and the BS **101** can monitor the access of the ROs **415-418** in accordance with the device configuration.

(83) For example, the device configuration could be indicative of the UE accessing multiple ROs. For instance, the device configuration could be indicative of the RO **418** that is later on accessed, i.e., of the to-be-accessed ROs. For example, the device configuration could be indicative of whether the same or different UL TX beams are used for accessing the multiple ROs **415-418** (cf. FIG. **8** where two options I and II have been explained, using the same UL TX beam **381** or using different UL TX beams **381**, **384**). It would be possible that the device configuration is indicative of the number of UL TX beams that are used by the UE **102** for accessing the multiple ROs **415-418**. Alternatively or additionally, the device configuration could be indicative of a number of ROs **415-418** that are accessed by the UE **102**.

(84) While FIG. **9** illustrates an example in which the device configuration is transmitted in the RA procedure **600** associated with the RO **415**, in other examples, it would also be possible that the device configuration is provided otherwise to the cellular NW **100** (e.g., after transitioning to the connected connection mode **401**).

(85) The device configuration can be determined in accordance with the NW configuration **6011** received at **6501**. For example, the number of ROs **415-418** that are accessed by the UE **102** could be selected to be equal or smaller than the maximum number of ROs to be accessed as indicated by the NW configuration **6011**.

(86) Alternatively or additionally to transmitting the device configuration of said accessing of the multiple ROs **415**, **418**, the ED **6012** can also be used to provide a device parameter of the multi-beam operation to the cellular NW **100**. Then, the multi-beam operation can later be established in accordance with the device parameter. The device parameter can be indicative of one or more UE capability limitations in connection with the multi-beam operation. For instance, the UE capability limitation could specify the inability of the UE **102** to coherently receive and/or transmit on multiple beams. The UE capability limitation could specify the inability of the UE **102** to communicate bi-directionally on some of the beams, e.g., single UL, single DL, bidirectional. For instance, the device parameter could indicate a preferred multi-beam operation mode such as diversity or spatial multiplexing or beamsweep. It would be possible that the device parameter includes an analog and/or digital front end capability of the interface **1022** of the UE **102**, e.g., whether the UE **102** supports digital beamforming, number of receive chains, a number of transmit chains, etc., to give just a few examples. Alternatively or additionally, it would be possible that the device parameter includes a beam priority order of the DL TX beams **361**, **364** used by the BS **101** to transmit the SSB **411** associated with the selected ROs **415**, **418** (cf. FIG. **8**). The beam priority order could be set, e.g., in accordance with a receive quality of the respective RSs included in the SSB **411**. For instance, the receive quality could be determined depending on a receive amplitude. To give an example, in a scenario in which a RS included in the SSB **411** transmitted using the DL TX beam **361** is received at the higher signal-to-noise level than a RS included in the SSB **411** transmitted using the DL TX beam **364**, the beam priority order could indicate that the DL TX beam **361** has priority over the DL TX beam **364**. This can be considered when establishing, e.g., spatial multiplexing multi-antenna operation so that data is routed at a lower data rate via the spatial data stream associated with the DL TX beam **364**, if compared to the spatial data stream associated with the DL TX beam **361**. The device parameter may be indicative of whether or not the UE **102** uses multiple beams for accessing the multiple ROs. The device parameter could be indicative of a number of beams that the UE **102** uses for accessing the multiple ROs.

(87) While FIG. **9** illustrates an example in which the device parameter is transmitted in the RA procedure **600** associated with the RO **415**, in other examples, it would also be possible that the device parameter is provided otherwise to the cellular NW **100** (e.g., after transitioning to the connected connection mode **401**).

(88) For example, the beam priority order as described above could also be implicitly the indicated to the cellular NW **100** based on the sequence with which the ROs **415-418** are being accessed. For example, the scenario FIG. **8** and FIG. **9**, the RO **415** is accessed before accessing the RO **418**. This indicates the DL TX beam **361** having higher priority if compared to the DL TX beam **364**, because the DL TX beam **361** is used for transmitting the SSB **411** that is associated with the RO **415** and the DL TX beam **364** is used for transmitting the SSB **411** that is associated with the RO **418**.

(89) In the example of FIG. **9**, the DL ED 6012 could be used in order to indicate which RA preamble **6001** is to be used by the UE **102** for accessing the RO **418** at **6508**. Accordingly, the further RA preamble **6001** transmitted at **6508** can be contention free. The contention-free RA preamble could be provided as part of the DL ED 6012. Differently, the RA preamble **6001** transmitted at **6504** when accessing the RO **415** could be contention-based.

(90) As a general rule, it would be possible that multiple ROs **415-418** are accessed with (i) contention-based random-access preambles only, (ii) contention free RA preambles only, or (iii) a mixture of contention-based and contention free RA preambles, as illustrated in FIG. **9**. Details with respect to (i)-(iii) are explained in Table 1.

(91) TABLE-US-00001 TABLE 1 Options for choice of RA preamble when accessing multiple ROs

Choice of RA preamble	Explanation
(i) Multiple contention-based preambles are used in multiple ROs.	For example, different or the same contention-based preamble may be used. ED transmitted in the first RA procedure can include device configuration of multi-RO access and/or device parameter of multi- beam operation.
(ii) Multiple contention-free preambles are used.	NW configuration of multi-RO access, UE-ID can be provided prior to initial access to the UE 102.
(iii) UE-ID acquired from first-accessed RO that is accessed using contention-based RA preamble.	Subsequent ROs are accessed using contention-free RA preambles. This enables to identify the UE instantaneously and establish the multi-beam operation. NW configuration of multi-RO access can be provided as ED in RAmgs2 or RAmgs4 or RAmgsB. ED transmitted in the first RA procedure can include device configuration of multi-RO access and/or device parameter of multi-beam operation.

(92) While FIG. **9** illustrates an example of a 4-step RA procedure **600**, similar techniques may be readily employed for a 2-step RA procedure.

(93) FIG. **10** is a flowchart of a method according to various examples. The method of FIG. **10** may be executed by a UE connectable to a cellular NW. For instance, the method of FIG. **10** could be executed by the UE **102**. More specifically, the method of FIG. **10** could be executed by the processor **1021** of the UE **102**, upon loading program code from the memory **1025**.

(94) Optional boxes are indicated with dashed lines in FIG. **10**.

(95) At box **3001**, the UE receives a NW configuration from the cellular NW. The NW configuration is indicative of a NW support of the UE accessing multiple ROs for the purpose of configuring a multi-beam operation. In particular, the NW configuration can be received from a BS of a cell of the cellular NW that thereby indicates its support of the UE accessing multiple ROs. Alternatively or additionally, it would also be possible that the NW configuration is received from an anchoring node associated with the UE, e.g., a mobility control node such as the AMF **131** (cf. FIG. **6**).

(96) Next, at box **3002**, the UE checks whether it is to perform an initial access. If yes, the method proceeds to box **3003**.

(97) At box **3003**, the UE monitors for SSBs. The UE receives one or more SSBs that can have different time indices. Different SSBs within a burst are transmitted using different DL TX beams. The SSBs include DL RSs. Each SSB is associated with a respective ROs.

(98) The UE can then select, at box **3004**, at least two of these ROs. The selected at least two ROs are associated with at least two DL RSs included in the received SSBs that are selected by the UE based on the monitoring at box **3003**. For instance, the N strongest DL RSs (i.e., being received with the highest signal-to-noise ratio) could be selected.

(99) At box **3005**, the selected at least two ROs are accessed. I.e., RA preambles are transmitted at the selected at least two ROs. Contention free and/or contention-based RA preambles may be used.

(100) At box **3006**, it is optionally possible to transmit a device configuration of said accessing of the at least two ROs and/or a device parameter for the subsequent multi-beam operation to the cellular NW. For instance, this can be done using ED piggybacked to the RAm_{sg3} or RAm_{sgA}.

(101) Note that box **3006** can be executed before the access to the multiple ROs at box **3005** is completed.

(102) At box **3007**, multi-beam operation of a wireless link between the UE and the cellular NW is established. The multi-beam operation is established in accordance with the access to the multiple ROs at box **3005**. For example, it would be possible that multiple DL TX beams are used for the multi-beam operation, wherein the multiple DL TX beams are associated with the ROs that are accessed at box **3005**. More specifically, the multiple DL TX beams that are used for the multi-beam operation that is established at box **3007** can be used for transmitting the SSBs associated with the selected at least two ROs of box **3004**. It would also be possible to refine these beams, e.g., use sub-beams.

(103) The multi-beam operation may be used after the RA procedure has concluded.

(104) For example, a selection could be made between a diversity multi-antenna mode or a spatial multiplexing multi-antenna operation mode, in accordance with the access to the multiple ROs at box **3005**.

(105) At box **3008**, it is then possible to establish the wireless link between the UE and the cellular NW, e.g., by completing a RA procedure triggered by the access to one of the ROs that are accessed at box **3005**. The RA procedure can be completed using the multi-beam operation that is established at box **3007**. Further, subsequent communication on the then established wireless link can be implemented using the multi-beam operation that is established at box **3007**.

(106) The order of boxes **3001-3008** is an example only. For example, it would be possible that the NW configuration is received as part of a RA procedure that is triggered by the RO access of box **3005** (as such, box **3001** can be executed after box **3005**).

(107) FIG. **11** is a flowchart of a method according to various examples. The method of FIG. **11** can be executed by an access node of a communications NW. For instance, the method of FIG. **11** could be executed by a BS of a cellular NW, e.g., the BS **101** of the cellular NW **100**. More specifically, it would be possible that the method of FIG. **11** is executed by the processor **1011** of the BS **101**, upon loading program code from the memory **1015**.

(108) The method of FIG. **11** is interrelated with the method of FIG. **10**. I.e., the BS **101** and the UE **102** interact when executing the methods of FIG. **10** and FIG. **11**.

(109) Optional boxes are illustrated with dashed lines in FIG. **11**.

(110) The method starts with box **3101**. Here, a NW configuration is transmitted to a UE that is in communication with the access node. Box **3101** is interrelated with box **3001**. The NW configuration can indicate whether the access node supports the UE accessing multiple ROs, in order to establish a multi-beam operation during initial access. Box **3101** is interrelated with box **3001**.

(111) At box **3103**, SSBs are transmitted using multiple beams. In particular, a burst of SSBs can be transmitted using a beam sweep. The SSBs include RSs. The UE can sound the channel based on the RSs. Each SSB is associated with a respective RO. Box **3103** is interrelated with box **3003**.

(112) At box **3105**, the ROs are monitored. I.e., the access node attempts to receive a RA message on the ROs. For example, a BS of a cellular NW can attempt to receive RAm_{sg1} or RAm_{sgA} on the ROs. Box **3105** is interrelated with box **3005**.

(113) By receiving RAm_{sg1} or RAm_{sgA} on multiple ROs the BS can determine that the same UE has accessed both RAs.

(114) In some examples, it would be possible that based on a receive property—i.e., amplitude and/or phase—of a RS associated with the RA message the BS acquires channel state information.

The subsequent multi-beam operation can be configured based on such channel sounding.

(115) At box **3106**, it would be possible to receive a device configuration for the multi-RO access of the UE and/or a device parameter of the subsequent multi-beam operation. Box **3106** is interrelated with box **3006**.

(116) Then, at box **3107**, the multi-beam operation is established. For instance, a diversity multi-antenna mode or a spatial multiplexing multi-antenna operation mode may be activated. The beams used for the multi-beam operation can be determined based on the ROs that are accessed by the UE at box **3105**. For instance, each RO can be associated with the respective DL TX beam that has been used to transmit the corresponding SSB. Then, these DL TX beams can be used for the multi-beam operation, or be further refined. For example, the multi-beam operation pertains to UL transmission, then UL RX beams can be used that are corresponding to these DL TX beams, e.g., use the same antenna weights and/or having corresponding spatial characteristics.

(117) The multi-beam operation that is established at box **3107** can be used for completing RA on further accessed ROs, as part of box **3105**. The multi-beam operation can also be used for communicating data on the wireless link that is subsequently established at box **3108**. Box **3107** corresponds to box **3007**. Box **3108** corresponds to box **3008**.

(118) Summarizing, above techniques have been described that facilitate multi-beam operation, e.g., using diversity multi-antenna and/or spatial multiplexing multi-antenna operation. Techniques have been described that facilitate a UE accessing multiple ROs. The cellular NW can indicate whether it support such multi-RO access. For example, such NW configuration can be signaled as part of a broadcasted system information.

(119) The UE can access a first RO and report its intention to access one or more further ROs, e.g., using ED transmitted as part of the RA procedure associated with the access of the first RO. as a general rule, the UE can provide a device configuration for the multi-RO access and/or a device parameter for the multi-beam operation to the cellular NW, e.g., as ED. The UE could indicate the expected number of ROs to be accessed and/or the number of UL TX beams used for this. For instance, the UE may use the same UL TX beam for accessing two or more of multiple ROs.

(120) The BS may assign RA preambles for the one or more further ROs as part of DL ED transmitted to the UE as part of the RA procedure associated with the access of the first random access occasion. Then, contention-free access is possible in the at least one further RA procedure associated with the one or more further ROs.

(121) By means of such techniques, low delay to spatial diversity and/or multiplexing is possible already during initial access. The overall control signaling overhead can be limited.

(122) Although the invention has been shown and described with respect to certain preferred embodiments, equivalents and modifications will occur to others skilled in the art upon the reading and understanding of the specification. The present invention includes all such equivalents and modifications and is limited only by the scope of the appended claims.

(123) For illustration, above, various techniques have been described in which a 4-step RA procedure is used. Similar techniques may also be applied for a 2-step RA procedure. As a general rule, the 2-step RA procedure relies on a combination of RAm_{sg1} and RAm_{sg3} into RAm_{sgA}, and on a combination of RAm_{sg2} and RAm_{sg4} into RAm_{sgB}.

(124) For further illustration, various examples have been described in which UL ED is piggybacked to RAm_{sg3}. It is possible that at least parts of this information is provided via the RAm_{sg1}, e.g., using preamble partitioning.

(125) For further illustration, various examples have been described in which a DL RS is implemented by SSB. In other examples, other kinds and types of DL RS may be used.

(126) For still further illustration, various examples have been described in which the UE selects the strongest DL TX beams. In other examples, other and/or further quality metrics could be taken into account, e.g., signal-to-noise ratio.

(127) For still further illustration, above, various scenarios have been described in which a single

BS receives RAm1 or RAmA on multiple ROs accessed by a UE and monitored by that single BS. Similar techniques may be applicable to scenarios in which multiple ROs associated with SSBs of a burst and accessed by a UE are monitored by different BSs, e.g., through TRPs.

Claims

1. A method of operating a wireless communication device configured to connect to a communications network, the method comprising: monitoring for multiple downlink reference signals transmitted by at least one access node of the communications network using multiple downlink transmit beams, each one of the multiple downlink reference signals being associated with a respective at least one of multiple random-access occasions, accessing at least two random-access occasions of the multiple random-access occasions, the at least two random-access occasions being associated with at least two downlink reference signals selected from the multiple downlink reference signals based on said monitoring, and establishing a multi-beam operation between the wireless communication device and the communications network, wherein the multi-beam operation is established based on at least two downlink transmit beams used for transmitting the selected at least two downlink reference signals.
2. The method of claim 1, wherein said accessing of the at least two random-access occasions is in accordance with at least one configuration communicated between the wireless communication device and the communications network.
3. The method of claim 1, further comprising: receiving a network configuration from the communications network, wherein the at least two random-access occasions are accessed in accordance with the network configuration.
4. The method of claim 3, wherein the network configuration is indicative of a maximum number of random-access occasions to be accessed by the wireless communication device.
5. The method of claim 3, wherein the network configuration is indicative of whether the wireless communication device is to use the same or different uplink transmit beams are used for said accessing of the at least two random-access occasions.
6. The method of claim 3, wherein the network configuration is indicative of a minimum number of uplink transmit beams to be used by the wireless communication device for said accessing of the at least two random-access occasions, wherein the minimum number of uplink transmit beams optionally depends on a number of the at least two random-access occasions.
7. The method of claim 3, wherein the network configuration is indicative of a network support of access to multiple random-access occasions.
8. The method of claim 1, further comprising: transmitting a device configuration of said accessing of the at least two random-access occasions to the communications network, wherein said accessing of the at least two random-access occasions is in accordance with the device configuration.
9. The method of claim 8, wherein the device configuration is indicative of whether the same or different uplink transmit beams are used for said accessing of the at least two random-access occasions.
10. The method of claim 8, wherein the device configuration is indicative of a number of random-access occasions accessed by the wireless communication device.
11. The method of claim 8, wherein the device configuration is transmitted in a random-access procedure associated with at least one of the at least two random-access occasions.
12. The method of claim 8, wherein the device configuration is indicative of a number of uplink transmit beams that are used for said accessing of the at least two random-access occasions.
13. The method of claim 8, further comprising: receiving a network configuration from the communications network, and wherein the at least two random-access occasions are accessed in accordance with the network configuration; and wherein the device configuration is determined

based on the network configuration.

14. The method of claim 1, further comprising: transmitting a device parameter of the multi-beam operation to the communications network, wherein the multi-beam operation is established in accordance with the device parameter.

15. The method of claim 14, wherein the device parameter comprises a mode of the multi-beam operation selected from: diversity, and spatial multiplexing.

16. The method of claim 14, wherein the device parameter comprises a frontend capability of a wireless interface of the wireless communication device.

17. The method of claim 14, wherein the device parameter comprises a beam priority order of the at least two downlink transmit beams, the beam priority order depending on a receive property of the at least two downlink reference signals.

18. The method of claim 14, wherein the device parameter is transmitted in a random-access procedure associated with said accessing of the at least two random-access occasions.

19. The method of claim 1, wherein the at least two random-access occasions are accessed using the same uplink transmit beam.

20. A method of operating at least one access node of a communications network, the method comprising: transmitting multiple downlink reference signals using multiple downlink transmit beams, each one of the multiple downlink reference signals being associated with a respective at least one of multiple random-access occasions, monitoring an access of the wireless communication device to at least two random-access occasions associated with at least two downlink reference signals of the multiple downlink reference signals, and based on said monitoring of the access, establishing a multi-beam operation between the wireless communication device and the communications network, wherein the multi-beam operation is established based on at least two downlink transmit beams of the multiple downlink transmit beams used for transmitting the at least two downlink reference signals.
