

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication
Kind Code
Publication Date
Inventor(s)

20250278666
A1
September 04, 2025
BONDERSON; Parsa et al.

TRACKING AND MITIGATION OF QUASIPARTICLE POISONING ERRORS IN MAJORANA QUANTUM COMPUTING SYSTEMS

Abstract

A computing system including a quantum computing device that includes Majorana islands at which Majorana zero modes (MZMs) are instantiated. The computing system further includes a controller configured to control the quantum computing device to perform a joint parity measurement at two or more MZMs. The controller is further configured to control the quantum computing device to perform quasiparticle poisoning (QPP) detection at the one or more Majorana islands to thereby generate error data. The error data includes one or more QPP indications associated with the one or more Majorana islands. The controller is further configured to receive the error data from the quantum computing device. The controller is further configured to update an accumulated error state of the one or more Majorana islands based at least in part on the error data, and to perform an update operation based at least in part on the accumulated error state.

Inventors: BONDERSON; Parsa (Santa Barbara, CA), AASEN; David Alexander (Santa Barbara, CA), KNAPP; Christina Paulsen (Goleta, CA)

Applicant: Microsoft Technology Licensing, LLC (Redmond, WA)

Family ID: 93380174

Assignee: Microsoft Technology Licensing, LLC (Redmond, WA)

Appl. No.: 19/207214

Filed: May 13, 2025

Related U.S. Application Data

parent US continuation 18313243 20230505 parent-grant-document US 12333388 child US 19207214

Publication Classification

Int. Cl.: G06N10/70 (20220101); G06N10/40 (20220101)

U.S. Cl.:

CPC G06N10/70 (20220101); G06N10/40 (20220101);

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS [0001] This application is a continuation of U.S. patent application Ser. No. 18/313,243, filed May 5, 2023, the entirety of which is hereby incorporated herein by reference for all purposes.

BACKGROUND

[0002] Majorana-based quantum computing is an approach to quantum computing that utilizes Majorana zero modes (MZMs). The MZMs are instantiated at floating superconducting regions of a quantum computing device. When two or more MZMs are formed at a floating superconducting region, that superconducting region is known as a Majorana island. The parities of the MZMs included in the Majorana island may be used to store qubits and classical bits that are used in quantum computations.

SUMMARY

[0003] According to one aspect of the present disclosure, a computing system is provided, including a quantum computing device. The quantum computing device includes a plurality of Majorana islands at which a plurality of Majorana zero modes (MZMs) are instantiated. The quantum computing device further includes a plurality of quantum dots located proximate to the plurality of Majorana islands. The quantum computing device further includes a plurality of capacitance sensors. The computing system further includes a controller configured to, for an island-dot system including one or more Majorana islands of the plurality of Majorana islands and one or more quantum dots of the plurality of quantum dots, control the quantum computing device to perform a joint parity measurement of two or more MZMs of the plurality of MZMs located in the one or more Majorana islands. Performing the joint parity measurement includes, at each of a plurality of candidate resonance regions corresponding to a plurality of values of a change in a fermion number of the island-dot system, setting one or more corresponding Majorana island gate voltages of the one or more Majorana islands and one or more corresponding quantum dot gate voltages of the one or more quantum dots to respective candidate resonance values located within the candidate resonance region. Performing the joint parity measurement further includes, at each of the plurality of candidate resonance regions, via a capacitance sensor of the plurality of capacitance sensors, detecting a microwave response signal measured at the island-dot

system. Performing the joint parity measurement further includes outputting a joint parity value of the two or more MZMs based at least in part on the microwave response signal.

[0004] According to another aspect of the present disclosure, a computing system is provided, including a quantum computing device. The quantum computing device includes a plurality of Majorana islands at which a plurality of Majorana zero modes (MZMs) are instantiated. The computing system further includes a controller configured to control the quantum computing device to perform a joint parity measurement at two or more MZMs of the plurality of MZMs. The two or more MZMs are located in one or more Majorana islands of the plurality of Majorana islands. The controller is further configured to control the quantum computing device to perform quasiparticle poisoning (QPP) detection at the one or more Majorana islands to thereby generate error data. The error data includes one or more QPP indications associated with the one or more Majorana islands. The controller is further configured to receive the error data from the quantum computing device. The controller is further configured to update an accumulated error state of the one or more Majorana islands based at least in part on the error data. The controller is further configured to perform an update operation based at least in part on the accumulated error state.

[0005] This Summary is provided to introduce a selection of concepts in a simplified form that are further described below in the Detailed Description. This Summary is not intended to identify key features or essential features of the claimed subject matter, nor is it intended to be used to limit the scope of the claimed subject matter. Furthermore, the claimed subject matter is not limited to implementations that solve any or all disadvantages noted in any part of this disclosure.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0006] FIG. 1 schematically shows a computing system including a quantum computing device that includes a plurality of island-dot systems and a controller that includes a processor and memory, according to one example embodiment.

[0007] FIG. 2 shows an example configuration of the island-dot system in which a Majorana island included in the island-dot system is a coherent link, according to the example of FIG. 1.

[0008] FIG. 3 schematically shows an island-dot system including a first Majorana island and a second Majorana island provided as Majorana tetrons, according to the example of FIG. 1.

[0009] FIGS. 4A-4B show the island-dot system of FIG. 3 when the controller controls the quantum computing device to perform a joint parity measurement and to perform quasiparticle poisoning detection.

[0010] FIG. 5 schematically shows the island-dot system and the controller when a joint parity measurement is performed at a plurality of candidate resonance regions, according to the example of FIG. 1.

[0011] FIG. 6A schematically shows plots of the energy of the island-dot system as a function of a detuning energy for a plurality of different interference phase values when the change in the fermion number equals zero, according to the example of FIG. 3.

[0012] FIG. 6B schematically shows plots of the energy of the island-dot system as a function of a detuning energy for a plurality of different interference phase values when the change in the fermion number equals one, according to the example of FIG. 3.

[0013] FIG. 7A schematically shows the computing system when quasiparticle poisoning detection is performed at the quantum computing device, according to the example of FIG. 1.

[0014] FIG. 7B schematically shows the computing system when the controller is configured to perform an update operation, according to the example of FIG. 7A.

[0015] FIG. 7C schematically shows the computing system when the controller is configured to transmit, to the quantum computing device, instructions to perform quantum error correction, according to the example of FIG. 7A.

[0016] FIG. 8 schematically shows a plurality of logical computing timesteps that each include a respective plurality of physical computing timesteps, according to the example of FIG. 7A.

[0017] FIGS. 9A-9B show examples of quasiparticle poisoning between Majorana zero modes of the Majorana islands included in the island-dot system, according to the example of FIG. 3.

[0018] FIGS. 10A-10C show examples of quasiparticle poisoning between Majorana zero modes of the Majorana islands included in another island-dot system, according to the example of FIG. 1.

[0019] FIGS. 11A-11D show examples of quasiparticle poisoning between Majorana zero modes and quantum dots of included in the island-dot system of FIGS. 10A-10C.

[0020] FIG. 12A schematically shows the computing system when the controller is configured to compute a plurality of estimated fermion number probabilities of different values of the change in the fermion number, according to the example of FIG. 1.

[0021] FIG. 12B schematically shows computation of a plurality of candidate resonance regions corresponding to a plurality of joint parity measurement types, according to the example of FIG. 12A.

[0022] FIG. 13A schematically shows the computing system during a calibration phase in which the controller is configured to estimate the plurality of candidate resonance regions, according to the example of FIG. 5.

[0023] FIGS. 13B-13D schematically show the island-dot system during the calibration phase, according to the example of FIG. 13A.

[0024] FIG. 14A shows a flowchart of a method for use with a computing system that includes a quantum computing device and a controller in order to perform a joint parity measurement, according to the example of FIG. 1.

[0025] FIG. 14B shows additional steps of the method of FIG. 14A that may be performed in some examples to select a number of the plurality of candidate resonance regions.

[0026] FIG. 14C shows additional steps of the method of FIG. 14A that may be performed in some examples during a calibration phase.

[0027] FIG. 15A shows a flowchart of a method that may be used with the computing system to correct for a quasiparticle poisoning error that occurs during a joint parity measurement, according to the example of FIG. 1.

[0028] FIG. 15B shows additional steps of the method of FIG. 15A that may be performed in examples in which a plurality of physical computing timesteps are performed during a logical computing timestep.

[0029] FIG. 15C shows additional steps of the method of FIG. 15A that may be performed in examples in which a quantum-computing-device-side update operation is performed.

[0030] FIG. 16 shows a schematic view of an example computing environment in which the computing system of FIG. 1 may be instantiated.

DETAILED DESCRIPTION

[0031] Each Majorana island included in a Majorana-based quantum computing device may be a coherent link that includes two MZMs, a tetron that includes four MZMs, or a hexon that includes six MZMs. A classical bit may be encoded at a coherent link, and a qubit may be encoded at a tetron or a hexon. The ground states of a Majorana island that includes $2n$ MZMs exhibits 2^{n-1} -fold degeneracy, which allows quantum information to be stored in the ground states of the Majorana island. Measurement-based operations may be performed on a qubit instantiated at a Majorana-based quantum computing device to perform quantum computations. The measurement-based operations may be performed by coupling pairs of MZMs included in the same or different Majorana islands using quantum dots (QDs) adjacent to the Majorana islands. The pairs of MZMs, when coupled, define non-self-intersecting loops that allow coherent single-electron transport between the pairs. The total energy of the linked system of MZMs depends upon the collective fermion parity of the MZMs. This parity may be measured by connecting an MZM or a QD to a readout circuit.

[0032] Topological protection is a property of Majorana-based qubits that is promoted interest in using Majorana-based qubits in quantum computing platforms. Topological protection refers to the exponential suppression of errors as a function of the macroscopic energy ratios of a Majorana-based qubit system. This exponential suppression applies to three sources of errors that may occur at the Majorana island: residual energy splitting between MZMs; intrinsic quasiparticle poisoning of the Majorana island; and addition or removal of electrons to or from a Majorana island tuned to a Coulomb valley. The suppression of residual energy splitting is given by a factor of $e^{-L/\xi}$, where L is a distance separating the MZMs and ξ is a topological correlation length. Intrinsic quasiparticle poisoning occurs when quasiparticles are excited above a superconducting gap Δ of the superconductor. The suppression of intrinsic quasiparticle poisoning is given by a factor of $e^{-\Delta/k_B T}$, where k_B is the Boltzmann constant and T is temperature. The suppression of addition or removal of electrons is given by a factor of $e^{-E_c/k_B T}$, where E_c is a charging energy. Thus, errors may be less likely to occur at Majorana-based qubits than at other types of qubits.

[0033] Quasiparticle poisoning (QPP) is discussed in additional detail below. QPP is a type of error that changes the fermion parity of the MZMs used to encode information in a Majorana island and may thereby produce errors in a quantum computation. There are three types of QPP that occur at Majorana-based quantum computing devices: intrinsic QPP, extrinsic QPP, and intercomponent QPP.

[0034] Intrinsic QPP is QPP that occurs when the fermion number of a Majorana island remains constant, but the state of the Majorana island is thermally excited above the superconducting gap. In a hard gap superconductor, intrinsic QPP occurs when an above-gap quasiparticle is excited from an MZM. This quasiparticle is typically absorbed by an MZM, resulting in a relaxation of the Majorana island back to the ground state subspace. The emitter MZM and the absorber MZM may be different MZMs. Thus, the ground state of the Majorana island may change when the quasiparticle is emitted and absorbed. This change in the ground state may lead to an error in a quantum computation due to the transfer of fermions between the emitter and absorber MZMs.

[0035] Extrinsic QPP is QPP that occurs when the Majorana island exchanges fermions with a fermion source outside the system of Majorana qubits and qubit-measurement components (QDs and coherent links). Extrinsic QPP may, for example, occur as a result of quasiparticle leakage from neighboring electrostatic gates or transport leads included in the quantum computing device. The lowest-energy process that changes the fermion number on the Majorana island is the absorption or emission of a fermion at the island via an MZM. Thus, quasiparticle leakage from components outside the system of Majorana qubits and measurement components typically affects the information encoded in a qubit, thereby resulting in an error in a quantum computation.

[0036] Intercomponent QPP occurs when a Majorana island exchanges one or more fermions with another component of the qubit system, which may be another Majorana island or a QD. Similar to extrinsic QPP, intercomponent QPP typically occurs when a fermion enters or leaves the Majorana island via an MZM. Accordingly, intercomponent QPP also typically results in an error. Intercomponent QPP may, for example, occur during a decoupling step of a measurement when a Majorana island is disconnected from one or more other components of the qubit system.

[0037] As discussed above, intercomponent QPP may be suppressed by increasing the charging energy E_c of the Majorana island or lowering the temperature T . However, high ratios of E_c/T may be difficult to reach. In addition, subsequently to intercomponent QPP occurring, the poisoning quasiparticle may have a high probability of moving to other Majorana islands during subsequent measurements, thereby resulting in correlated errors. This probability approaches $(n-1)/n$ for a measurement performed on n Majorana islands that have the same dimensions. In such an n -island measurement, the additional fermion has the same energy cost to move to each of the Majorana islands that are linked during the measurement. When the distribution of fermions across the linked Majorana islands is imbalanced, the fermions have a high probability of moving into a state that equalizes the fermion numbers of the Majorana islands. The charging energies of the QDs included in the qubit system are typically much higher than the charging energies of the Majorana islands. Thus, intercomponent QPP between Majorana islands is typically the highest-probability form of intercomponent QPP.

[0038] Using the devices and methods discussed below, correction for intercomponent QPP may be performed at a Majorana-based quantum computing device. FIG. 1 schematically shows a computing system 1 including a quantum computing device 10 and a controller 20. The quantum computing device 10 and the controller 20 are communicatively coupled such that the controller 20 is configured to receive inputs from, and transmit output instructions to, the quantum computing device 10. The controller 20 may, for example, be a classical computing device that includes a processor 22 and memory 24, as shown in the example of FIG. 1.

[0039] The quantum computing device 10 includes one or more island-dot systems 11. Each of the island-dot systems 11 includes a Majorana island 12 at which a plurality of Majorana zero modes (MZMs) 14 are instantiated. The Majorana island 12 may be a coherent link, a Majorana tetron, or a Majorana hexon. The island-dot system 11 further includes a measurement circuit 15, which includes a quantum dot 16 electrically connectable to an MZM 14 of the plurality of MZMs 14. In addition, the QD 16 is configured to be electrically connectable to another MZM 14 located in the same Majorana island 12 or another Majorana island 12. The Majorana island 12 and a QD 16 located proximate to the Majorana island 12 form the island-dot system 11. The quantum dot 16 may be coupled to and decoupled from the MZM 14 by closing and opening a switch 17 included in the measurement circuit 15.

[0040] The measurement circuit 15 further includes a capacitance sensor 18 capacitively coupled to the quantum dot 16. At the island-dot system 11, a Majorana island gate voltage $N_{sub,g}$ and a quantum dot gate voltage $n_{sub,g}$ are respectively applied to the Majorana island 12 and the quantum dot 16. Depending upon the values of the Majorana island gate voltage $N_{sub,g}$ and the quantum dot gate voltage $n_{sub,g}$, the capacitance sensor 18 measures different capacitance values for the island-dot system 11. The values obtained during capacitance measurements are used to detect QPP at the Majorana island 12, as discussed below. In addition, as discussed in further detail below, the capacitance sensor 18 is used to perform joint parity measurements when the corresponding QD 16 is electrically coupled to a plurality of MZMs 14.

[0041] The term “island-dot system,” as used herein, refers to a system of one or more Majorana islands 12 and one or more QDs 16 at which a joint parity measurement 32 or a QPP detection 36 is performed, as discussed in further detail below. Island-dot systems 11 are formed by electrically coupling the one or more QDs 16 to the one or more Majorana islands 12. The one or more QDs 16 included in the island-dot system 11 may differ from one or more QDs 16 used to perform the joint fermion parity measurement in some examples. During different joint parity measurements 32 and QPP detections 36 performed at the quantum computing device 10, different combinations of Majorana islands 12 and QDs 16 selected from among the sets of Majorana islands 12 and QDs 16 included in the quantum computing device 10 may be used to form different island-dot systems 11 depending on the specific measurements that the controller 20 instructs the quantum computing device 10 to perform.

[0042] FIG. 2 shows an example island-dot system 11A in which the Majorana island 12 is a coherent link. The coherent link includes a first MZM 14A and a second MZM 14B that form at respective ends of a topological superconducting nanowire 50. In the example of FIG. 2, the QD 16 is electrically connectable to the second MZM 14B. The QD 16 is located within a semiconductor 51. The capacitance sensor 18 in the example of FIG. 2 is configured to measure the quantum capacitance between the QD 16 and a cutter gate 19 coupled to an alternating current (AC) voltage source 52. When the QD 16 is electrically coupled to the Majorana island 12, the quantum capacitance changes.

[0043] In the example of FIG. 2, the Majorana island gate voltage $N_{sub,g}$ and the quantum dot gate voltage $n_{sub,g}$ may be set via respective plunger gates 53A and 53B. The plunger gates 53A and 53B may be located proximate to the Majorana island 12 and the QD 16 above a surface of the island-dot system 11 in a thickness direction. In other examples, the plunger gates 53A and 53B may be located below the Majorana island 12 and the QD 16 or in a plane of the island-dot system 11. The plunger gates 53A and 53B may be electrostatic gates.

[0044] In the example of FIG. 2, the capacitance sensor 18 includes a microwave readout circuit 56 that is electrically coupled to the AC voltage source 52 and capacitively coupled to the QD 16. The microwave readout circuit 56 is configured to generate a microwave response signal 57 based at least in part on a quantum capacitance of the island-dot system 11A. For example, the microwave readout circuit 56 may be an LC circuit at which

the quantum capacitance of the QD 16 and the Majorana island 12 affect a resonant frequency of the microwave readout circuit 56. Thus, a value of the quantum capacitance may be determined from the microwave response signal 57. The microwave response signal 57, in the example of FIG. 2, is output to the controller 20 as a quantum capacitance measurement.

[0045] In the example of FIG. 2, the quantum dot 16 that is used to perform QPP detection measurements is also used to perform joint parity measurements 32 included in quantum computations. Via the quantum dot 16, the quantum computing device 10 is further configured to perform a joint parity measurement 32 of a plurality of MZMs 14 that includes the MZM 14B to which the quantum dot 16 is electrically coupled. Since each joint parity measurement 32 is of an even number of MZMs 14, the joint parity measurement 32 is also performed on at least one other MZM 14. The QD 16 may accordingly serve a dual purpose, thereby allowing QPP to be detected without increasing the number of QDs 16 used in the island-dot system 11. Increases in the size and manufacturing complexity of the quantum computing device 10 may consequently be avoided by using the same QD 16 for QPP detection 36 and joint parity measurements 32.

[0046] FIG. 2 further shows a fermion reservoir 58 that is electrically connectable to the Majorana island 12 and the QD 16. The Majorana island 12 or the QD 16 may be electrically coupled to the fermion reservoir 58 in order to set the fermion number of Majorana island 12 or the QD 16, for example, to reset the fermion number to zero. As depicted in the example of FIG. 2, the fermion reservoir 58 may be an additional QD. The fermion reservoir 58 may be coupled to the MZM 14B, as shown in FIG. 2, and may additionally or alternatively be coupled to the MZM 14A.

[0047] Returning to the example of FIG. 1, the controller 20 is configured to transmit joint parity measurement instructions 30 to the quantum computing device 10. The joint parity measurement instructions 30 include one or more joint parity measurements 32 encoding a quantum computation that the controller 20 instructs the quantum computing device 10 to perform. Each joint parity measurement 32 indicated in the joint parity measurement instructions 30 is an instruction to measure a parity operator of an even number of MZMs 14. The MZMs 14 may be included in the same Majorana island 12 or in different Majorana islands 12. For example, a single-qubit Pauli measurement of a Majorana-based qubit may correspond to measuring the fermion parity associated with a pair of MZMs 14. The map between MZMs 14 and Pauli operators depends on a choice of encoding.

[0048] As shown in the example of FIG. 1, the controller 20 is further configured to transmit QPP detection instructions 34 to the quantum computing device 10. The QPP detection instructions 34 specify one or more QPP detections 36 configured to be performed at respective island-dot systems 11.

[0049] The controller 20 is configured to receive a plurality of quantum capacitance measurements 38 from the capacitance sensors 18 subsequently to transmitting the joint parity measurement instructions 30 and the QPP detection instructions 34 to the quantum computing device 10. When the controller 20 performs a quantum capacitance measurement 38, the controller 20 receives a microwave response signal 57 measured at the island-dot system 11. The controller 20 is further configured to determine, based at least in part on the microwave response signal 57, a joint parity value 39 of the two or more MZMs 14. The joint parity value 39 is an indication of positive parity, negative parity, or an ambiguous parity value.

[0050] As discussed in further detail below, when performing the joint parity measurement 32, the controller 20 is configured to perform quantum capacitance measurement 38 for different values of the Majorana island gate voltage $N_{\text{sub.g}}$ and the quantum dot gate voltage $n_{\text{sub.g}}$. The controller 20 may, in some examples, be further configured to adjust one or more cutter gate voltages $n_{\text{sub.cg}}$ applied to one or more of the cutter gates 19 in order to increase measurement visibility for different values of the Majorana island gate voltage $N_{\text{sub.g}}$ and the quantum dot gate voltage $n_{\text{sub.g}}$. The difference in response signal for positive parity and negative parity is approximately maximized when the island-dot system 11 is tuned to resonance. Away from the resonance region, the visibility of the measurement signal that distinguishes between parities is significantly reduced, which may lead to ambiguous or faulty measurement outcomes. The quantum capacitance measurements 38 are also used when performing both joint parity measurement 32 and QPP detection 36.

[0051] The quantum computing device 10 is configured to perform two-qubit joint parity measurements in addition to one-qubit joint parity measurements. As shown in the example of FIG. 3, a two-qubit measurement is configured to be performed at an island-dot system 11B including a first Majorana island 12A and a second Majorana island 12B. In the example island-dot system 11B of FIG. 3, the first Majorana island 12A and the second Majorana island 12B are Majorana tetrons. At each of the Majorana tetrons, four MZMs 14 are instantiated. The four MZMs 14 instantiated at each Majorana tetron are formed at respective ends of a pair of topological superconducting nanowires 50. The topological superconducting nanowires 50 included in each Majorana tetron are coupled by a trivial superconducting nanowire 54. The measurement circuits 15 and fermion reservoirs 58 of the Majorana tetrons are omitted from FIG. 3 in the interest of clarity.

[0052] The island-dot system 11B of FIG. 3 further includes a first QD 16A and a second QD 16B positioned between respective ends of the topological superconducting nanowires 50 included in the first Majorana island 12A and the second Majorana island 12B. Accordingly, via the first QD 16A and the second QD 16B, two of the MZMs 14 included in the first Majorana island 12A are configured to be electrically coupled to two of the MZMs 14 included in the second Majorana island 12B. This electrical coupling forms an interference loop 55 that passes through the QDs 16A and 16B, the trivial superconducting nanowires 54 of the Majorana islands 12A and 12B, and the MZMs labeled $\gamma_{\text{sub.j.sub.A}}$, $\gamma_{\text{sub.j.sub.B}}$, $\gamma_{\text{sub.k.sub.A}}$, and $\gamma_{\text{sub.k.sub.B}}$.

[0053] FIGS. 4A-4B show the island-dot system 11B of FIG. 3 when the controller 20 controls the quantum computing device 10 to perform a joint parity measurement 32 and perform quasiparticle poisoning detection 36. In the example of FIGS. 4A-4B, the first Majorana island 12A and the second Majorana island 12B are Majorana tetrons. The first Majorana island 12A includes a first MZM 14A, a second MZM 14B, a third MZM 14C, and a fourth MZM 14D. The second Majorana island 12B includes a fifth MZM 14E, a sixth MZM 14F, a seventh MZM 14G, and an eighth MZM 14H. The first step shown in FIG. 4A may sample over the plurality of candidate resonance regions during a joint parity measurement 32. The first step shown in FIG. 4B may sample over the plurality of candidate resonance regions for a QPP detection 36.

[0054] The joint parity measurement 32 is performed on two or more MZMs 14 of the plurality of MZMs 14. As shown in the example of FIG. 4A, when the controller 20 controls the quantum computing device 10 to perform the joint parity measurement 32, the quantum computing device 10 is configured to electrically couple two or more MZMs 14 via one or more quantum dots 16 of the plurality of quantum dots 16. In the example of FIG. 4A, the joint parity measurement 32 is a four-MZM measurement in which two MZMs 14 included in each of the first Majorana island 12A and the second Majorana island 12B are coupled via a first quantum dot 16A and a second quantum dot 16B. In this example, the second MZM 14B is coupled to the fifth MZM 14E via the first quantum dot 16A, and the fourth MZM 14D is coupled to the seventh MZM 14G via the second quantum dot 16B. Thus, an interference loop 55 is formed between the first Majorana island 12A, the first QD 16A, the second Majorana island 12B, and the second QD 16B.

[0055] When the joint parity measurement 32 is performed in the example of FIG. 4A, the controller 20 may be configured to tune the voltages of the plunger gates 53A and 53B to set the Majorana island gate voltage $N_{\text{sub.g}}$ and the quantum dot gate voltage $n_{\text{sub.g}}$. The controller 20 may be configured to iteratively set the Majorana island gate voltage $N_{\text{sub.g}}$ and the quantum dot gate voltage $n_{\text{sub.g}}$ to values within each of a plurality of candidate resonance regions, as discussed in further detail below.

[0056] Subsequently to performing the joint parity measurement 32, the controller 20 is further configured to control the quantum computing device 10 to decouple the two or more MZMs 14 from the one or more quantum dots 16. Decoupling the MZMs 14 from the quantum dots 16 electrically isolates the Majorana islands 12 from the quantum dots 16 and from each other.

[0057] Subsequently to decoupling the two or more MZMs 14 from the one or more quantum dots 16, the controller 20 is further configured to control the quantum computing device 10 to perform quasiparticle poisoning detection 36 at each of the Majorana islands 12 in which the two or more MZMs 14 are located. The quasiparticle poisoning detection is performed via respective capacitance sensors 18 of the plurality of capacitance sensors 18 located proximate to the MZMs 14. When performing the quasiparticle poisoning detection, each capacitance sensor 18 of the plurality of

capacitance sensors **18** measures a quantum capacitance of a respective island-dot system **11** that includes a Majorana island **12** of the plurality of Majorana islands **12** and a quantum dot **16** of the plurality of quantum dots **16**.

[0058] In the example of FIGS. **4A-4B**, the first quantum dot **16A** and the second quantum dot **16B** are respectively included in a first capacitance sensor **18A** and a second capacitance sensor **18B**. The first capacitance sensor **18A** and the second capacitance sensor **18B** may each be structured as shown in FIG. **2**. In this example, each QD **16** used in the QPP detection **36** is also included among the one or more QDs **16** via which the two or more MZMs **14** are electrically coupled during the joint parity measurement **32**. Accordingly, the same QDs **16** are used for both the joint parity measurement **32** and the quasiparticle poisoning detection **36**, thereby reducing the size and complexity of the quantum computing device **10**. In other examples, separate QDs **16** may be used to perform the joint parity measurements **32** and the QPP detection **36**.

[0059] In the example of FIG. **4B**, when the QPP detection **36** is performed, the controller **20** is configured to control the quantum computing device **10** to electrically couple the first QD **16A** to the second MZM **14B** and to electrically couple the second QD **16B** to the seventh MZM **14G**. The first Majorana island **12A** and the first QD **16A** form a first island-dot pair **59A**, and the second Majorana island **12B** and the second QD **16B** form a second island-dot pair **59B**. Accordingly, quantum capacitance is measured for each of the Majorana islands **12**. In other examples, the first QD **16A** may instead be electrically coupled to the fifth MZM **14E**, and the second QD **16B** may instead be electrically coupled to the fourth MZM **14D**.

[0060] The controller **20** may be further configured to control the quantum computing device **10** to electrically decouple the QDs **16** from the Majorana islands **12** subsequently to measuring the quantum capacitance. Thus, the island-dot system **11B** may be prepared for a later joint parity measurement **32**.

[0061] FIG. **5** schematically shows an island-dot system **11** and the controller **20** when the joint parity measurement **32** is performed. For each of a plurality of candidate resonance regions **40**, the Majorana island gate voltage $N_{\text{sub.g}}$ and the quantum dot gate voltage $n_{\text{sub.g}}$ are respectively set to a candidate resonance Majorana island gate voltage **42A** and a candidate resonance quantum dot gate voltage **42B** located within that candidate resonance region **40**. In some examples, a cutter gate voltage $n_{\text{sub.cg}}$ on one or more cutter gates **19** may also be set to a candidate resonance cutter gate voltage **42C**. Each candidate resonance region **40** is a region of a parameter space of values of the Majorana island gate voltage $N_{\text{sub.g}}$ and the quantum dot gate voltage $n_{\text{sub.g}}$. The controller **20** may be configured to set each of the Majorana island gate voltages $N_{\text{sub.g}}$ of the one or more Majorana islands **12** included in the island-dot system **11** to the candidate resonance Majorana island gate voltage **42A** and set each of the quantum dot gate voltages $n_{\text{sub.g}}$ of the one or more quantum dots **16** included in the island-dot system **11** to the candidate resonance quantum dot gate voltage **42B**. The respective cutter gate voltages $n_{\text{sub.cg}}$ of each cutter gate **19** included in the island-dot system **11** may also each be set to the candidate resonance cutter gate voltage **42C**.

[0062] As discussed above, the controller **20** is further configured to receive quantum capacitance measurements **38** from the capacitance sensor **18** located proximate to the Majorana island **12**. The quantum capacitance measurements **38** include respective microwave response signals **57** measured at the candidate resonance regions **40**. When the controller **20** controls the quantum computing device **10** to perform a quantum capacitance measurement **38** at a candidate resonance region **40**, the capacitance sensor **18** measures the quantum capacitance at respective ranges of values of the Majorana island gate voltage $N_{\text{sub.g}}$ and the quantum dot gate voltage $n_{\text{sub.g}}$ located within the candidate resonance region **40**, proximate to the candidate resonance Majorana island gate voltage **42A**, the candidate resonance quantum dot gate voltage **42B**, and the candidate resonance cutter gate voltage **42C**.

[0063] The candidate resonance regions **40** each correspond to a respective value of a total fermion number $N_{\text{sub.tot}}$ of the island-dot system **11**. The total fermion number $N_{\text{sub.tot}}$ is the number of fermions located at the island-dot system **11** relative to a reference value. The change in the fermion number $N_{\text{sub.tot}}$ for a single Majorana island **12** coupled to a single quantum dot **16** is given by $N+n$, where N is the change in the fermion number of the Majorana island **12** and n is the change in the fermion number of the QD **16**. By measuring the capacitance at a plurality of different candidate resonance regions **40**, the capacitance sensor **18** is configured to measure the joint parity of a plurality of MZMs **14** even under conditions in which QPP has occurred at the one or more Majorana islands **12**. In some examples, the one or more candidate resonance regions **40** may correspond to a set of values of the change in the fermion number $N_{\text{sub.tot}}$ of the island-dot system **11** given by $\{-3, -2, -1, 0, 1, 2, 3\}$. In other examples, the candidate resonance regions **40** may correspond to values of the change in the fermion number $N_{\text{sub.tot}}$ given by $\{-2, -1, 0, 1, 2\}$ or $\{-1, 0, 1\}$.

[0064] When the controller **20** performs the joint parity measurement **32**, the controller **20** is further configured to determine the joint parity value **39** of the two or more MZMs **14** at least in part by classifying the microwave response signal **57** as a positive parity response signal **41A**, a negative parity response signal **41B**, or an ambiguous measurement outcome **41C**. The difference between the positive parity response signal **41A** and the negative parity response signal **41B** depends on the Majorana island gate voltage $N_{\text{sub.g}}$, the quantum dot gate voltage $n_{\text{sub.g}}$, and the change in fermion number $N_{\text{sub.tot}}$. The measurement visibility is increased when the island-dot system exhibits resonance. Some candidate resonance regions **40** may have low measurement visibility for certain values of the change in fermion number $N_{\text{sub.tot}}$, thereby resulting in ambiguous measurement outcomes **41C**.

[0065] The controller **20** may be configured to control the quantum computing device **10** to measure the microwave response signal **57** at ranges of values of the Majorana island gate voltage $N_{\text{sub.g}}$ and the quantum dot gate voltage $n_{\text{sub.g}}$ in a candidate resonance region **40**. The controller **20** may be further configured to classify the measured microwave response signal **57** as a positive parity response signal **41A**, a negative parity response signal **41B**, or an ambiguous measurement outcome **41C** determined for that value of $N_{\text{sub.tot}}$ during a calibration phase to thereby distinguish between positive and negative joint parity values **39** for the two or more MZMs **14**. The controller **20** is further configured to output the joint parity value **39** of the two or more MZMs **14**.

[0066] As shown in the example of FIG. **1**, the controller **20** is further configured to control the quantum computing device **10** to perform a QPP detection **36** subsequently to the joint parity measurement **32**. The QPP detection **36**, similarly to the joint parity measurement **32**, may be performed using the capacitance sensor **18** by performing a plurality of quantum capacitance measurements **38**.

[0067] Formalism describing a one-qubit joint parity measurement **32** followed by a QPP detection **36** is provided below. A single-island measurement of MZMs j and k included in the same Majorana island **12** may be modeled using the following Hamiltonian:

$$[00001] H^{(jk)} = H_C + H_t^{(jk)}$$

In the above Hamiltonian, $H_{\text{sub.C}}$ is a charging energy Hamiltonian of the island-dot system **11** when decoupled from other Majorana islands **12** and quantum dots **16**. $H_{\text{sub.C}}$ may be expressed as:

$$[00002] H_C = E_C (\hat{N} - N_g)^2 + \text{Math.C} (\hat{n} - n_g)^2$$

In the above equation, $E_{\text{sub.C}}$ and $\epsilon_{\text{sub.C}}$ are respective geometric charging energies of the Majorana island **12** and the QD **16**, $\{\text{circumflex over } (N)\}$ and $\{\text{circumflex over } (n)\} = f_{\text{sup.tf}}$ are the respective number operators of the Majorana island **12** and the QD **16**, and $N_{\text{sub.g}}$ and $n_{\text{sub.g}}$ are respective dimensionless gate voltages of the Majorana island **12** and the QD **16**. $H_{\text{sub.t.sup.}}(jk)$ is a tunnel coupling of the island-dot system **11** and may be expressed as:

$$[00003] H_t^{(jk)} = t_j e^{i\phi_j/2} f_d + t_k e^{i\phi_k/2} f_d + h.c.$$

In the above equation, $t_{\text{sub.j}}$ and $t_{\text{sub.k}}$ are tunnel coupling strengths associated with the MZMs j and k , $\{\text{circumflex over } (\phi)\}$ is a phase operator of the topological superconducting nanowire **50**, $\gamma_{\text{sub.j}}$ and $\gamma_{\text{sub.k}}$ are MZM operators, and $f_{\text{sub.d}}$ is a fermionic annihilation operator of the quantum dot **16**. The single-qubit Pauli measurement is a measurement of the operator $i\gamma_{\text{sub.j}}\gamma_{\text{sub.k}}$.

[0068] When $E_{\text{sub.C}} \neq \epsilon_{\text{sub.C}}$, for any fixed charge sector (the value of the change in the fermion number of the island-dot system **11**), there are values of the Majorana island gate voltage $N_{\text{sub.g}}$ and the quantum dot gate voltage $n_{\text{sub.g}}$ at which the low-energy sector may be described by the

following Hamiltonian:

$$[00004] H^{(jk)} = -\frac{N_{\text{tot}}}{2} z + t_{C,p_{jk}} x$$

In the above equation, $\sigma_{\text{sub.z}}$ and $\sigma_{\text{sub.x}}$ are the Pauli Z operator and the Pauli X operator. $\delta_{\text{sub.N.sub.tot}}$ is the difference in decoupled charging energy between the two lowest-energy configurations, where the energy sector is expressed as $N_{\text{sub.tot}}=N+n$. $\delta_{\text{sub.N.sub.tot}}$ is given by the following:

$$[00005] N_{\text{tot}} = -2E_C(N_g - \frac{1}{2}) + 2\text{Math.C}(n_g + \frac{1}{2}) + 2E_C N_{\text{tot}}$$

In addition, $t_{\text{sub.C,p.sub.jk}}$ is given by the following:

$$[00006]$$

$$t_{C,p_{jk}} = \sqrt{\text{Math. } t_j \cdot \text{Math. }^2 + \text{Math. } t_k \cdot \text{Math. }^2 + 2p_{jk} \text{Im}(t_j t_k^*)} = \sqrt{\text{Math. } t_j \cdot \text{Math. }^2 + \text{Math. } t_k \cdot \text{Math. }^2 + 2p_{jk} \cdot \text{Math. } t_j t_k \cdot \text{Math. } \sin}$$

In the above equation, the joint parity values $p_{\text{sub.jk}}=\pm 1$ are the eigenvalues corresponding to the two eigenspaces of $i y_{\text{sub.jy.sub.k}}$. A baseline energy has been subtracted from the diagonal terms of $H_{\text{sup.(jk)}}$ in the expression of $H_{\text{sup.(jk)}}$ in terms of the Pauli matrices. The basis of $H_{\text{sup.(jk)}}$ is chosen such that the off-diagonal terms of $H_{\text{sup.(jk)}}$ are represented as proportional to $\sigma_{\text{sub.x}}$. A total flux of the interference loop **55** formed by the QD **16** and the MZMs **14** contributes to relative phase between $t_{\text{sub.j}}$ and $t_{\text{sub.k}}$, such that the factor $\text{Im}(t_{\text{sub.jt}^*} \cdot \text{sub.k})=|t_{\text{sub.jt.sub.k}}|\sin \theta$ depends on the flux as a function of θ . Thus, the size of the interference term in the equation for $t_{\text{sub.C,p.sub.jk}}$ may be modulated by controlling the enclosed flux of the corresponding interference loop **55**.

[0069] The energy and capacitance measured at the quantum dot **16** are respectively given by:

$$[00007] \text{Math.}_{\pm}(p_{jk}) = \pm \frac{1}{2} \sqrt{\frac{2}{N_{\text{tot}}} + 4t_{C,p_{jk}}^2} \text{ and } C_Q(E) = -(\frac{C_g}{e})^2 \frac{\partial^2 E}{\partial n_g^2} \cdot \text{Math. } C_Q(\text{Math.}_{-}(p_{jk})) = \frac{2e^2 \cdot t_{C,p_{jk}}^2}{(\frac{2}{N_{\text{tot}}} + 4t_{C,p_{jk}}^2)^{3/2}}$$

In the above equations, $\alpha=C_{\text{sub.g}}/C_{\text{sub.}\Sigma}$ is a lever arm position of the plunger gate **53B**, where $C_{\text{sub.g}}$ is a capacitance between the plunger gate **53B** and the QD **16** and where $C_{\text{sub.}\Sigma}$ is a total capacitance of the QD **16** and all the gates located proximate to the QD **16**. In addition, $\epsilon_{\text{sub.C}}=e_{\text{sup.}2}/2C_{\text{sub.}\Sigma}$ in the above equation. The above equations for $\epsilon_{\text{sub.}\pm}(p_{\text{sub.jk}})$ and $C_{\text{sub.Q}}(E)$ utilize the equation for $\delta_{\text{sub.N.sub.tot}}$ with lowest-energy configurations $|N_{\text{sub.tot}}+1, -1\rangle_{\text{custom-character}}$ and $|N_{\text{sub.tot}}, 0\rangle_{\text{custom-character}}$, such that $\delta_{\text{sub.N.sub.tot}}(n_{\text{sub.g}})=2\epsilon_{\text{sub.C}}n_{\text{sub.g}}+\text{const}$. The measurement visibility of the single-qubit measurement is accordingly given by the following, where $C_{\text{sub.Q}}(p_{\text{sub.jk}})$ is the quantum capacitance of the ground state energy:

$$[00008] C_Q = C_Q(p_{jk} = +1) - C_Q(p_{jk} = -1) = 2e^2 \cdot \frac{\text{Math. } t_j \cdot \text{Math. }^2 + \text{Math. } t_k \cdot \text{Math. }^2 + 2 \cdot \text{Math. } t_j t_k \cdot \text{Math. } \sin}{[\frac{2}{N_{\text{tot}}} + 4(\text{Math. } t_j \cdot \text{Math. }^2 + \text{Math. } t_k \cdot \text{Math. }^2 + 2 \cdot \text{Math. } t_j t_k \cdot \text{Math. } \sin)]^{3/2}} - \frac{\text{Math. } t_j \cdot \text{Math. }^2 + \text{Math. } t_k \cdot \text{Math. }^2 - 2 \cdot \text{Math. } t_j t_k \cdot \text{Math. } \sin}{[\frac{2}{N_{\text{tot}}} + 4(\text{Math. } t_j \cdot \text{Math. }^2 + \text{Math. } t_k \cdot \text{Math. }^2 - 2 \cdot \text{Math. } t_j t_k \cdot \text{Math. } \sin)]^{3/2}}$$

[0070] The measurement visibility $\Delta C_{\text{sub.Q}}$ is maximized when the capacitance sensor **18** exhibits resonance, such that $\delta_{\text{sub.N.sub.tot}}=0$. The measurement visibility at the resonance point is given by:

$$[00009] C_Q^{(0)} = \frac{e^2}{4} (\frac{1}{t_{C,+1}} - \frac{1}{t_{C,-1}})$$

In examples in which the tunnel coupling strengths are equal, $|t_{\text{sub.j}}|=|t_{\text{sub.k}}|=t$. In such examples, the maximum measurement visibility is given by:

$$[00010] C_Q^{(0)} = \frac{e^2}{4\sqrt{2t}} \frac{\sqrt{1-\sin} - \sqrt{1+\sin}}{\text{Math. } \cos \cdot \text{Math.}}$$

[0071] The location of the resonance point depends on the charge sector of the island-dot system **11**. In the $N_{\text{sub.tot}}=N+n=0$ sector, the lowest-energy states are $|0,0\rangle_{\text{custom-character}}$ and $|-1,1\rangle_{\text{custom-character}}$, and resonance occurs at $N_{\text{sub.g}}=1/2$, $n_{\text{sub.g}}=-1/2$, corresponding to

$$[00011] N_{\text{tot}} = 0$$

In the $N_{\text{sub.tot}}=1$ sector, the lowest-energy states are $|1,0\rangle_{\text{custom-character}}$ and $|2, -1\rangle_{\text{custom-character}}$, and setting the gate voltages to $N_{\text{sub.g}}=1/2$ and $n_{\text{sub.g}}=-1/2$ instead results in a decoupled charging energy difference of $\delta_{\text{sub.N.sub.tot}}=2E_{\text{sub.C}}$. The measurement visibility at such a point is given by:

$$[00012] C_Q^{(1)} = 2e^2 \cdot \frac{t_{C,+1}^2}{(4E_C^2 + 4t_{C,+1}^2)^{3/2}} - \frac{t_{C,-1}^2}{(4E_C^2 + 4t_{C,-1}^2)^{3/2}}$$

When $t_{\text{sub.C,p.sub.jk}}k_{\text{sub.BT}}$ and $\beta E_{\text{sub.C}} \in [3,10]$, the above equation for $\Delta C_{\text{sub.Q.sub.(1)}}$ implies that the measurement visibility drops significantly when QPP has occurred, compared to the unpoisoned state, when $N_{\text{sub.g}}=1/2$ and $n_{\text{sub.g}}=-1/2$.

[0072] When the measurement circuit **15** achieves a sufficient signal-to-noise ratio to distinguish between the two parity states of an unpoisoned qubit, measuring the quantum capacitance of a poisoned qubit results in an ambiguous quantum capacitance measurement **38**. The ambiguity of the measurement in the poisoned state occurs as a result of the quantum capacitance relationship $|C_{\text{sub.Q.sub.(0)}}(\pm 1)| > |C_{\text{sub.Q.sub.(1)}}(\pm 1)| \approx 0$. Since $C_{\text{sub.Q.sub.(1)}}$ is close to zero, as shown in the above inequality, positive and negative parity measurements may result in approximately equal quantum capacitance values when QPP occurs, thereby preventing reliable differentiation between positive and negative parity response signals **41A** and **41B**. When an ambiguous measurement occurs, the state of the qubit after the joint parity measurement **32** may be decohered or partially projected onto an eigenstate of $i y_{\text{sub.jy.sub.k}}$ rather than fully projected.

[0073] Quasiparticle poisoning during a two-qubit measurement is discussed below. A two-qubit measurement performed at the first Majorana island **12A** and the second Majorana island **12B** of FIG. **3** may be modeled using the following Hamiltonian:

$$[00013] H_{\text{sub.C}}^{(j_A k_A; j_B k_B)} = H_C + H_t^{(j_A k_A; j_B k_B)}$$

In this equation, the charging energy Hamiltonian $H_{\text{sub.C}}$ is given by:

$$[00014] H_C = E_C (\hat{N}_A - N_{g,A})^2 + E_C (\hat{N}_B - N_{g,B})^2 + \text{Math.C}(\hat{n}_1 - n_{g,1})^2 + \text{Math.C}(\hat{n}_2 - n_{g,2})^2$$

The tunnel coupling is given by:

$$[00015] H_t^{(j_A k_A; j_B k_B)} = t_{j_A} e^{-i \hat{A}} \frac{1}{j_A} f_1^\dagger + t_{k_A} e^{-i \hat{A}} \frac{1}{k_A} f_2^\dagger + t_{j_B} e^{-i \hat{B}} \frac{1}{j_B} f_1^\dagger + t_{k_B} e^{-i \hat{B}} \frac{1}{k_B} f_2^\dagger + h.c.$$

The two-qubit operator $-\gamma_{\text{sub.j.sub.Ay.sub.k.sub.Ay.sub.j.sub.By.sub.k.sub.B}}$ is measured in the example of FIG. **3**.

[0074] The ground state degeneracy of the charging energy Hamiltonian at the point $N_{\text{sub.g,A}}=N_{\text{sub.g,B}}=1/2$, $n_{\text{sub.g,1}}=n_{\text{sub.g,2}}=-1/2$ in parameter space is discussed below. The total charge sector in this example is $N_{\text{sub.tot}}=N_{\text{sub.A}}+N_{\text{sub.B}}+n_{\text{sub.1}}+n_{\text{sub.2}}$, and the charge configuration states are written as $|N_{\text{sub.A}}, N_{\text{sub.B}}; n_{\text{sub.1}}, n_{\text{sub.2}}\rangle_{\text{custom-character}}$. The two qubits have the following ground states for values of $N_{\text{sub.tot}} \in \{-2, -1, 0, 1, 2\}$:

[0075] $N_{\text{sub.tot}}=-2$: unique ground state $|0,0;-1,-1\rangle_{\text{custom-character}}$.

[0076] $N_{\text{sub.tot}}=-1$: four degenerate ground states $|0,0;-1,0\rangle_{\text{custom-character}}$, $|0,0;0,-1\rangle_{\text{custom-character}}$, $|1,0;-1,-1\rangle_{\text{custom-character}}$, and $|0,1;-1,-1\rangle_{\text{custom-character}}$.

[0077] $N_{\text{sub.tot}}=0$: six degenerate ground states $|0,0;0,0\rangle_{\text{custom-character}}$, $|1,0;-1,0\rangle_{\text{custom-character}}$, $|1,0;0,-1\rangle_{\text{custom-character}}$, $|0,1;-1,0\rangle_{\text{custom-character}}$, $|0,1;0,-1\rangle_{\text{custom-character}}$, and $|1,1;-1,-1\rangle_{\text{custom-character}}$.

[0078] $N_{\text{sub.tot}}=1$: four degenerate ground states $|1,0;0,0\rangle_{\text{custom-character}}$, $|0,1;0,0\rangle_{\text{custom-character}}$, $|1,1;-1,0\rangle_{\text{custom-character}}$, and $|1,1;0,-1\rangle_{\text{custom-character}}$.

[0079] $N_{\text{sub.tot}}=2$: unique ground state $|1,1;0,0\rangle_{\text{custom-character}}$.

[0080] The curvature of the ground state energy with respect to $N_{\text{sub.g,A}}$, $N_{\text{sub.g,B}}$, $n_{\text{sub.g,1}}$, and $n_{\text{sub.g,2}}$ changes between the different charge

sectors. However, since the charge sectors $N_{\text{sub.tot}} \in \{-1, 0, 1\}$ still have degeneracies at the point $N_{\text{sub.g,A}} = N_{\text{sub.g,B}} = \frac{1}{2}$, $n_{\text{sub.g,1}} = n_{\text{sub.g,2}} = -\frac{1}{2}$ in the state space of gate voltages, these charge sectors may also exhibit resonance during the quantum capacitance measurement. This resonance may provide visibility and distinguishability between positive and negative joint parity values **39**.

[0081] In the charge sector $N_{\text{sub.tot}}=0$, the effective Hamiltonian in the low-energy state space (with basis states ordered as listed above) may be written as follows:

$$[00016] H_{N_{\text{tot}}=0}^{(j_A k_A; j_B k_B)} = \begin{pmatrix} \text{Math}_0 & t_{j_A} & i p_{j_A k_A} t_{k_A} & t_{j_B} & i p_{j_B k_B} t_{k_B} & 0 \\ t_{j_A}^* & \text{Math}_{A1} & 0 & 0 & 0 & i p_{j_B k_B} t_{k_B} \\ -i p_{j_A k_A} t_{k_A}^* & 0 & \text{Math}_{A2} & 0 & 0 & t_{j_B} \\ t_{j_B}^* & 0 & 0 & \text{Math}_{B1} & 0 & i p_{j_A k_A} t_{k_A} \\ -i p_{j_B k_B} t_{k_B}^* & 0 & 0 & 0 & \text{Math}_{B2} & t_{j_A} \\ 0 & -i p_{j_B k_B} t_{k_B}^* & t_{j_B}^* & -i p_{j_A k_A} t_{k_A}^* & t_{j_A}^* & \text{Math}_{AB12} \end{pmatrix} \text{ where } \text{Math}_0 = 0$$

$$\text{Math}_{A1} = -2E_{C,A}(N_{g,A} - \frac{1}{2}) + 2\text{Math}_{C,1}(n_{g,1} + \frac{1}{2}), \text{Math}_{A2} = -2E_{C,A}(N_{g,A} - \frac{1}{2}) + 2\text{Math}_{C,2}(n_{g,1} + \frac{1}{2})$$

$$\text{Math}_{B1} = -2E_{C,B}(N_{g,B} - \frac{1}{2}) + 2\text{Math}_{C,1}(n_{g,1} + \frac{1}{2}), \text{Math}_{B2} = -2E_{C,B}(N_{g,B} - \frac{1}{2}) + 2\text{Math}_{C,2}(n_{g,2} + \frac{1}{2})$$

$$\text{Math}_{AB12} = -2E_{C,A}(N_{g,A} - \frac{1}{2}) + 2E_{C,B}(N_{g,B} - \frac{1}{2}) + 2\text{Math}_{C,1}(n_{g,1} + \frac{1}{2}) + 2\text{Math}_{C,2}(n_{g,2} + \frac{1}{2})$$

A baseline energy of $E_{\text{sub.0}} = E_{\text{sub.C,A}} + N_{\text{sub.g,A}} + 2 + E_{\text{sub.C,B}} + N_{\text{sub.g,B}} + 2 + \epsilon_{\text{sub.C,1}} + n_{\text{sub.g,1}} + 2 + \epsilon_{\text{sub.C,2}} + n_{\text{sub.g,2}} + 2$ has been subtracted from the diagonal of $H_{\text{sub.N.sub.tot.sub.0}}^{\text{sup.}(j_{\text{sup.A}} k_{\text{sup.A}} \text{sup.}(j_{\text{sup.B}} k_{\text{sup.B}} \text{sup.})}$. The above Hamiltonian may be derived using the following relationship for a Majorana island J:

$$e^{i \hat{J} / 2} |N_J = 0, p_{j_j k_j}\rangle \text{Math.}$$

$$[00017] = -ie^{i \hat{J} / 2} (i |j_j k_j\rangle_{k_j} |N_J, p_{j_j k_j}\rangle \text{Math.}$$

$$= i p_{j_j k_j} e^{i \hat{J} / 2} |N_J, p_{j_j k_j}\rangle \text{Math.}$$

In the above equation, $p_{\text{sub.j.sub.J.sub.k.sub.J}}$ is an eigenvalue of $i y_{\text{sub.j.sub.Jy.sub.k.sub.J}}$.

[0082] Analytic expressions for energy bands in the two-qubit measurement example may be written by setting $E_{\text{sub.C,A}} = E_{\text{sub.C,B}} = E_{\text{sub.C}}$, $\epsilon_{\text{sub.C,1}} = \epsilon_{\text{sub.C,2}} = \epsilon_{\text{sub.C}}$, $N_{\text{sub.g,A}} = N_{\text{sub.g,B}} = N_{\text{sub.g}}$, and $n_{\text{sub.g,1}} = n_{\text{sub.g,2}} = n_{\text{sub.g}}$. A detuning energy

$$[00018] \text{ }_0 = -2E_C(N_g - \frac{1}{2}) + 2\text{Math}_C(n_g + \frac{1}{2})$$

of the island-dot system **11** may also be subtracted from the diagonal. The resulting energies are given by:

$$[00019] E = \frac{\sqrt{B + \sqrt{B^2 - 4C}}}{2}, \frac{\sqrt{B - \sqrt{B^2 - 4C}}}{2}, 0, \frac{\sqrt{B + \sqrt{B^2 - 4C}}}{2}, \frac{\sqrt{B - \sqrt{B^2 - 4C}}}{2}$$

In the above equation,

$$[00020] B = \text{ }_0 + 2(\text{Math}_{t_{j_A}} \text{Math}_{t_{j_A}}^2 + \text{Math}_{t_{k_A}} \text{Math}_{t_{k_A}}^2 + \text{Math}_{t_{j_B}} \text{Math}_{t_{j_B}}^2 + \text{Math}_{t_{k_B}} \text{Math}_{t_{k_B}}^2) \text{ and}$$

$$C = \text{Math}_{t_{j_A}} \text{Math}_{t_{j_A}}^4 + \text{Math}_{t_{k_A}} \text{Math}_{t_{k_A}}^4 + \text{Math}_{t_{j_B}} \text{Math}_{t_{j_B}}^4 + \text{Math}_{t_{k_B}} \text{Math}_{t_{k_B}}^4 + 2 \text{Math}_{t_{j_A}} \text{Math}_{t_{k_A}} \text{Math}_{t_{j_A}}^2 \text{Math}_{t_{k_A}}^2 + 2 \text{Math}_{t_{j_B}} \text{Math}_{t_{k_B}} \text{Math}_{t_{j_B}}^2 \text{Math}_{t_{k_B}}^2$$

In the equation for C, $p_{\text{sub.j.sub.A.sub.k.sub.A.sub.j.sub.B.sub.k.sub.B}} = p_{\text{sub.j.sub.A.sub.k.sub.A.sub.j.sub.B.sub.k.sub.B}} = \pm 1$ is an eigenvalue of the operator $-y_{\text{sub.j.sub.Ay.sub.k.sub.Ay.sub.j.sub.By.sub.k.sub.B}}$ that is measured for the two-tetron system in the decoupled state. In addition, θ is the phase of $t_{\text{sub.j.sub.A}}^* t_{\text{sub.k.sub.A}}^* t_{\text{sub.j.sub.B}} t_{\text{sub.k.sub.B}} = |t_{\text{sub.j.sub.A}} t_{\text{sub.k.sub.A}} t_{\text{sub.j.sub.B}} t_{\text{sub.k.sub.B}}| e^{i\theta}$. By modifying the flux enclosed in the interference loop **55**, θ may be modulated to adjust the interference term

$$-8 p_{\text{sub.j.sub.A.sub.k.sub.A.sub.j.sub.B.sub.k.sub.B}} |t_{\text{sub.j.sub.A}} t_{\text{sub.k.sub.A}} t_{\text{sub.j.sub.B}} t_{\text{sub.k.sub.B}}| \cos \theta.$$

[0083] FIG. 6A shows plots of the energy E of the island-dot system **11** of FIG. 3 as a function of the detuning energy $\delta_{\text{sub.0}}$ for different values of θ when $N_{\text{sub.tot}}=0$. In the plots shown in FIG. 6A, $|t_{\text{sub.j.sub.A}}| = |t_{\text{sub.k.sub.A}}| = |t_{\text{sub.j.sub.B}}| = |t_{\text{sub.k.sub.B}}| = t$, which simplifies the expressions for B and C to $B = \delta_{\text{sub.0}} \text{sup.} 2 + 8t \text{sup.} 2$ and $C = 8t \text{sup.} 4 (1 - p_{\text{sub.j.sub.A.sub.k.sub.A.sub.j.sub.B.sub.k.sub.B}} \cos \theta)$. The energy E and the detuning energy $\delta_{\text{sub.0}}$ are both divided by t in the plots shown in FIG. 6A. A first plot **60** shows the energy bands when $\theta=0$, a second plot **62** shows the energy bands when $\theta=\pi/8$, a third plot **64** shows the energy bands when $\theta=\pi/4$, and a fourth plot **66** shows the energy bands when $\theta=\pi/2$. The plots **60**, **62**, **64**, and **66** each show a plurality of positive parity response signals **41A** and a plurality of negative parity response signals **41B**. The positive parity response signals **41A** correspond to the parity $p_{\text{sub.j.sub.A.sub.k.sub.A.sub.j.sub.B.sub.k.sub.B}} = +1$ and the negative parity response signals **41B** correspond to the parity $p_{\text{sub.j.sub.A.sub.k.sub.A.sub.j.sub.B.sub.k.sub.B}} = -1$. In each of the plots shown in FIG. 6A, two additional energy bands at $E=0$ are omitted in order to avoid congestion.

[0084] Since the value of the detuning energy $\delta_{\text{sub.0}}$ is determined by the Majorana island gate voltage $N_{\text{sub.g}}$ and the quantum dot gate voltage $n_{\text{sub.g}}$, the controller **20** may be configured to change the measured location on a curve by modifying the values of the Majorana island gate voltage $N_{\text{sub.g}}$ and the quantum dot gate voltage $n_{\text{sub.g}}$. When a quantum capacitance measurement **38** is performed, the microwave response signal **57** is obtained from a thermally averaged combination of the different energy levels associated with positive parity or negative parity.

[0085] In examples in which $N_{\text{sub.g,A}} = N_{\text{sub.g,B}} = \frac{1}{2}$, $n_{\text{sub.g,1}} = n_{\text{sub.g,2}} = -\frac{1}{2}$, and $N_{\text{sub.tot}}=1$, the first Majorana island **12A** and the second Majorana island **12B** have the following effective Hamiltonian:

$$[00021] H_{N_{\text{tot}}=1}^{(j_A k_A; j_B k_B)} = \begin{pmatrix} \text{Math}_A & 0 & t_{j_B} & i p_{j_B k_B} t_{k_B} \\ 0 & \text{Math}_B & t_{j_A} & i p_{j_A k_A} t_{k_A} \\ t_{j_B}^* & t_{j_A}^* & \text{Math}_{AB1} & 0 \\ -i p_{j_B k_B} t_{k_B}^* & -i p_{j_A k_A} t_{k_A}^* & 0 & \text{Math}_{AB2} \end{pmatrix}$$

In this effective Hamiltonian, the baseline energy $E_{\text{sub.0}}$ discussed above is subtracted from the diagonal entries. The diagonal entries have the following values:

$$[00022] \text{Math}_A = -2E_{C,A}(N_{g,A} - \frac{1}{2}), \text{Math}_B = -2E_{C,B}(N_{g,B} - \frac{1}{2}), \text{Math}_{AB1} = -2E_{C,A}(N_{g,A} - \frac{1}{2}) - 2E_{C,B}(N_{g,B} - \frac{1}{2}) + 2\text{Math}_{C,1}(n_{g,1} + \frac{1}{2})$$

$$\text{Math}_{AB2} = -2E_{C,A}(N_{g,A} - \frac{1}{2}) - 2E_{C,B}(N_{g,B} - \frac{1}{2}) + 2\text{Math}_{C,2}(n_{g,2} + \frac{1}{2}) - 3E_C(N_g - \frac{1}{2}) + \text{Math}_C(n_g + \frac{1}{2})$$

When the parameter symmetrization $E_{\text{sub.C,A}} = E_{\text{sub.C,B}} = E_{\text{sub.C}}$, $\epsilon_{\text{sub.C,1}} = \epsilon_{\text{sub.C,2}} = \epsilon_{\text{sub.C}}$, $N_{\text{sub.g,A}} = N_{\text{sub.g,B}} = N_{\text{sub.g}}$, and

$n_{\text{sub.g,1}} = n_{\text{sub.g,2}} = n_{\text{sub.g}}$ is applied in the $N_{\text{sub.tot}}=1$, as was applied above in the $N_{\text{sub.tot}}=0$ case, the following energies are obtained:

$$[00023] E = -\sqrt{\left(\frac{\delta}{2}\right)^2 + \frac{b + \sqrt{b^2 - 4c}}{2}}, -\sqrt{\left(\frac{\delta}{2}\right)^2 + \frac{b - \sqrt{b^2 - 4c}}{2}}, \sqrt{\left(\frac{\delta}{2}\right)^2 + \frac{b + \sqrt{b^2 - 4c}}{2}}, \sqrt{\left(\frac{\delta}{2}\right)^2 + \frac{b - \sqrt{b^2 - 4c}}{2}} \text{ where}$$

$$b = \text{Math}_{t_{j_A}} \text{Math}_{t_{j_A}}^2 + \text{Math}_{t_{k_A}} \text{Math}_{t_{k_A}}^2 + \text{Math}_{t_{j_B}} \text{Math}_{t_{j_B}}^2 + \text{Math}_{t_{k_B}} \text{Math}_{t_{k_B}}^2$$

[0086] FIG. 6B shows plots of the energy E of the island-dot system **11B** of FIG. 3 as a function of the detuning energy $\delta_{\text{sub},0}$ for different values of θ when $N_{\text{sub,tot}}=1$. In the plots shown in FIG. 6B, $|t_{\text{sub},j,\text{sub},A}|=|t_{\text{sub},k,\text{sub},A}|=|t_{\text{sub},j,\text{sub},B}|=|t_{\text{sub},k,\text{sub},B}|=t$, which simplifies the expressions for b and c to $b=4t_{\text{sup},2}$ and $c=2t_{\text{sup},4}(1-p_{\text{sub},j,\text{sub},A} \cdot p_{\text{sub},k,\text{sub},A} \cdot p_{\text{sub},j,\text{sub},B} \cdot p_{\text{sub},k,\text{sub},B} \cos \theta)$. The energy E and the detuning energy $\delta_{\text{sub},0}$ are both divided by t in the plots shown in FIG. 6B. A first plot **70** shows the energy bands when $\theta=0$, a second plot **72** shows the energy bands when $\theta=\pi/8$, a third plot **74** shows the energy bands when $\theta=\pi/4$, and a fourth plot **76** shows the energy bands when $\theta=\pi/2$. The positive parity response signals **41A** in each of the first plot **70**, the second plot **72**, the third plot **74**, and the fourth plot **76** correspond to the parity $p_{\text{sub},j,\text{sub},A} \cdot p_{\text{sub},k,\text{sub},A} \cdot p_{\text{sub},j,\text{sub},B} \cdot p_{\text{sub},k,\text{sub},B}=+1$ and the negative parity response signals **41B** correspond to the parity $p_{\text{sub},j,\text{sub},A} \cdot p_{\text{sub},k,\text{sub},A} \cdot p_{\text{sub},j,\text{sub},B} \cdot p_{\text{sub},k,\text{sub},B}=-1$. As shown in the example of FIG. 6B, QPP changes the positive parity response signals **41A** and the negative parity response signals **41B** relative to those in FIG. 6A. As such, even though there is still a resonance at $N_{\text{sub},g,A}=N_{\text{sub},g,B}=N_{\text{sub},g}$ and $n_{\text{sub},g,1}=n_{\text{sub},g,2}=n_{\text{sub},g}$ for $N_{\text{sub,tot}}=1$, the microwave response signal **57** may be weaker and provide reduced distinguishability between the different parity values, as compared to those of $N_{\text{sub,tot}}=0$ at the same point in parameter space.

[0088] In addition to the one or more QPP indications **82**, the error data **80** may further include one or more indications of the one or more joint parity measurements **32** performed prior to the QPP detection **36**. The error data **80** may further include indications of which MZMs **14** were used in the one or more joint parity measurements **32**. The QPP indications **82** may, in some examples, be expressed in terms of the respective fermion numbers of the one or more Majorana islands **12** before and after each of the joint parity measurements **32**.

[0090] Based at least in part on the error data **80** the controller **20** is further configured to update an accumulated error state **86** of the one or more Majorana islands **12** at which the joint parity measurement **32** is performed. The accumulated error state **86** is configured to store respective error data **80**, or information computed by further processing the error data **80**, for a plurality of joint parity measurements **32**. Thus, the accumulated error state **86** tracks intercomponent QPP errors over a plurality of joint parity measurements **32** included in a quantum computation or error correction code.

[0092] FIG. 7C shows another example of an update operation **90**. In the example of FIG. 7C, the update operation **90** includes transmitting instructions **98** to perform quantum error correction to the quantum computing device **10**. The controller **20** is configured to generate the instructions **98** based at least in part on the accumulated error state **86**. As shown the example of FIG. 7C, the quantum computing device **10** is configured to implement a quantum code **100** that maps a plurality of sets of physical-level operations **102** performed on physical qubits to respective logical-level operations **104** performed on logical qubits. The controller **20** may be configured to generate the instructions **98** based at least in part on the quantum code **100**, such that the quantum error correction accurately maps a modification of the state of the physical qubits to a correction performed on the logical qubits.

[0094] During each of the physical computing timesteps **108**, the controller **20** may be further configured to control the quantum computing device **10** to perform a plurality of joint parity measurements **32** in parallel. In addition, the controller **20** may be further configured to control the quantum computing device **10** to perform a corresponding plurality of QPP detections **36** in parallel. Thus, the joint parity measurements **32** and QPP detections **36** may be performed in a time-efficient manner at the ensemble of physical qubits that forms the one or more logical qubits.

[0096] Formalism is provided below that describes the effects of QPP on the quantum states of the Majorana islands **12** and further describes the

[0097] The joint parity measurement **32** on the MZMs $j.\text{sub}.A$, $k.\text{sub}.A$, $j.\text{sub}.B$, and $k.\text{sub}.B$ is performed by measuring the joint fermion parity operator $-\gamma.\text{sub}.j.\text{sub}.A.\gamma.\text{sub}.j.\text{sub}.B.\gamma.\text{sub}.k.\text{sub}.A.\gamma.\text{sub}.k.\text{sub}.B$ associated with the MZMs **14**. The joint fermion parity operator $-\gamma.\text{sub}.j.\text{sub}.A.\gamma.\text{sub}.j.\text{sub}.B.\gamma.\text{sub}.k.\text{sub}.A.\gamma.\text{sub}.k.\text{sub}.B$ corresponds to a two-qubit Pauli operator $Q.\text{sub}.(j.\text{sub}.A.\text{sub}.k.\text{sub}.A.\text{sub}.j.\text{sub}.B.\text{sub}.k.\text{sub}.B.\text{sub}.)$ on the pair of qubits encoded by the MZMs. In order to perform the measurement of the joint fermion parity operator $-\gamma.\text{sub}.j.\text{sub}.A.\gamma.\text{sub}.j.\text{sub}.B.\gamma.\text{sub}.k.\text{sub}.A.\gamma.\text{sub}.k.\text{sub}.B$, the MZMs **14** of the Majorana islands are coupled pairwise in a manner that forms the interference loop **55** as a closed, non-self-intersecting measurement loop. The MZMs $\gamma.\text{sub}.j.\text{sub}.A$ and $\gamma.\text{sub}.j.\text{sub}.B$ are coupled to each other through a first coupling path, and $\gamma.\text{sub}.k.\text{sub}.A$ and $\gamma.\text{sub}.k.\text{sub}.B$ are coupled to each other through a second coupling path included in the interference loop **55**.

$$[00024]' = \frac{s \rho \Pi_s}{\text{Tr}(\begin{smallmatrix} & s \\ s & \end{smallmatrix})}$$
$$[00025] \begin{pmatrix} j_A k_A; j_B k_B \\ s_A k_A; j_B k_B \end{pmatrix} = \frac{1}{2}(1 - s_{j_A k_A} s_{j_B k_B}) = \frac{1}{2}(1 + sQ_{(j_A k_A)} Q_{(j_B k_B)})$$

[0103] When a fermion enters or leaves a tetron island through the j th MZM, the corresponding Majorana operator $\gamma_{\text{sub},j}$ is applied to the two-tetron state. This Majorana operator $\gamma_{\text{sub},j}$ flips the total parity of the tetron island and applies a Pauli operator **84** to the encoded qubit according to $\gamma_{\text{sub},j}$ custom-characterP.sub.j. The Pauli operators **84** are indicated here as $P_{\text{sub},1}=X$, $P_{\text{sub},2}=Y$, $P_{\text{sub},3}=Z$, and $P_{\text{sub},4}=I$. A process that transfers a fermion between MZMs $j_{\text{sub},A}$ and $j_{\text{sub},B}$ therefore applies the operator $\gamma_{\text{sub},j_{\text{sub},A}}\gamma_{\text{sub},j_{\text{sub},B}}$ to the two-tetron state, as shown in the example of FIG. 9A. Similarly, a process that transfers a fermion between MZMs $k_{\text{sub},A}$ and $k_{\text{sub},B}$ applies the operator $\gamma_{\text{sub},k_{\text{sub},A}}\gamma_{\text{sub},k_{\text{sub},B}}$, as shown in the example of FIG. 9B. The post-measurement and post-decoupling state of the two-tetron system is accordingly given by:

$$\text{where } \rho_0 = \frac{1}{I_0 + I_{jk,jk} + 2 \operatorname{Re}(I_{jk,jk})} \operatorname{Tr} \left(\begin{pmatrix} I_{jk,jk} & I_{jk,jk} \\ I_{jk,jk} & I_{jk,jk} \end{pmatrix} \right) = \frac{1}{I_0 + I_{jk,jk} + 2 \operatorname{Re}(I_{jk,jk})} \operatorname{Tr} \left(\begin{pmatrix} I_{jk,jk} & I_{jk,jk} \\ I_{jk,jk} & I_{jk,jk} \end{pmatrix} \right)$$

[0106] The rewritten equation for ρ'' may be simplified by utilizing the fact that ρ' is a post-measurement state. Thus, the following properties are satisfied:

$$[00029] \quad \begin{aligned} j_A \quad j_B \quad k_A \quad k_B \quad (j_A k_A : j_B k_B) &= s \Pi_S^{(j_A k_A : j_B k_B)} \quad j_A \quad j_B \quad [S(\quad j_A \quad j_B \quad k_A \quad k_B \quad)] \quad (j_A k_A : j_B k_B) \\ &= -S \quad k_A \quad k_B \quad (j_A k_A : j_B k_B) \end{aligned}$$

The post-measurement, post-decoupling state ρ'' has the above properties when the joint parity measurement **32** successfully returns a joint parity value **39** and hence applies the projector to the quantum state. In examples in which the joint parity measurement **32** is a failed or ambiguous measurement, the above properties may not be satisfied. The above properties allow $\lambda.\text{sub}.0$ and $\lambda.\text{sub}.1$ to be simplified as follows:

$$[00030] \quad 0 = I, I + j_k, j_k + 2s\text{Re}(I, j_k) \quad 1 = j, j + k, k + 2s\text{Re}(j, k)$$

In the above equations for $\lambda.\text{sub}.0$ and $\lambda.\text{sub}.1$, the contributions of the interference terms depend on the measurement outcome s . In addition, the above equations for $\lambda.\text{sub}.0$ and $\lambda.\text{sub}.1$ allow for $p.\text{sub}.1=0$ when $|\lambda.\text{sub}.jj|=|\lambda.\text{sub}.kk|=|\lambda.\text{sub}.jk|$. This result of $p.\text{sub}.1=0$ depends on the measurement outcome, and the opposite measurement outcome maximizes the value of $p.\text{sub}.1$ for such parameter values. The post-measurement, post-decoupling state is given as follows in terms of the encoded qubits $p.\text{sub}.q$ and the island parities $[N.\text{sub}.A].\text{sub}.2$ and $[N.\text{sub}.B].\text{sub}.2$ prior to measurement (where $[N].\text{sub}.2=N \bmod 2$):

$$[00031] \quad \rho'' = \frac{p_0}{\text{Tr}(s)} \quad (j_A k_A : j_B k_B) \quad q \quad (j_A k_A : j_B k_B) \quad \text{Math.} \quad \text{Math.} \quad [N_A]_2, [N_B]_2 \quad \text{Math.} \quad \text{Math.} \quad [N_A]_2, [N_B]_2 \quad \text{Math.} \quad + \frac{p_1}{\text{Tr}(s)} P_{j_A}^{(A)} P_{j_B}^{(B)} \quad (j_A k_A : j_B k_B) \quad q \quad (j_A k_A : j_B k_B) \quad P_{j_A}^{(A)} P_{j_B}^{(B)}$$

[0107] As seen from the above equation, for ρ'' , when the fermion parities of the tetron islands are measured after performing the two-tetron measurement, the QPP error does not decohere the encoded computational state. Since the QPP error does not decohere the qubit state, the error in the qubit state may be tracked and corrected. Specifically, a measurement of the fermion parities of the tetron islands after the two-tetron measurement has potential outcomes corresponding to even and odd changes in fermion number, respectively. When the change in the fermion number is even, the tetron islands have the following state:

$$[00032] \quad \rho''' = \frac{1}{\text{Tr}(s)} \quad (j_A k_A : j_B k_B) \quad q \quad (j_A k_A : j_B k_B) \quad \text{Math.} \quad \text{Math.} \quad [N_A]_2, [N_B]_2 \quad \text{Math.} \quad \text{Math.} \quad [N_A]_2, [N_B]_2 \quad \text{Math.}$$

The fermion parity of the tetron islands does not change in such examples. When the change in the fermion number is odd, the tetron islands instead have the following state:

$$[00033] \quad \rho''' = \frac{1}{\text{Tr}(s)} P_{j_A}^{(A)} P_{j_B}^{(B)} \quad (j_A k_A : j_B k_B) \quad q \quad (j_A k_A : j_B k_B) \quad P_{j_B}^{(B)} P_{j_A}^{(A)} \quad \text{Math.} \quad \text{Math.} \quad [N_A + 1]_2, [N_B + 1]_2 \quad \text{Math.} \quad \text{Math.} \quad [N_A + 1]_2, [N_B + 1]_2 \quad \text{Math.}$$

In examples in which the change in the fermion number is odd, the fermion parity of the tetron islands changes.

[0108] The above formalism describing the post-measurement, post-decoupling state may be further modified to distinguish between changes in the fermion numbers of the tetron islands even when the parities of the tetron islands do not change. In the following discussion, the total number of fermions transferred from tetron B to tetron A is denoted as v . The post-measurement, post-decoupling state is accordingly given by:

$$[00034] \quad \rho''' = \frac{p_v}{v_{\text{even}} \text{Tr}(s)} \quad (j_A k_A : j_B k_B) \quad q \quad (j_A k_A : j_B k_B) \quad \text{Math.} \quad \text{Math.} \quad N_A + v, N_B - v \quad \text{Math.} \quad \text{Math.} \quad N_A + v, N_B - v \quad \text{Math.} \quad + \frac{p_v}{v_{\text{odd}} \text{Tr}(s)} P_{j_A}^{(A)} P_{j_B}^{(B)} \quad (j_A k_A : j_B k_B) \quad q \quad (j_A k_A : j_B k_B) \quad P_{j_B}^{(B)} P_{j_A}^{(A)}$$

Measuring the fermion number of the tetron islands accordingly results in the following state:

$$[00035] \quad \rho''' = \frac{1}{\text{Tr}(s)} \quad (j_A k_A : j_B k_B) \quad q \quad (j_A k_A : j_B k_B) \quad \text{Math.} \quad \text{Math.} \quad N_A + v, N_B - v \quad \text{Math.} \quad \text{Math.} \quad N_A + v, N_B - v \quad \text{Math.}$$

when v is even, and

$$[00036] \quad \rho''' = \frac{1}{\text{Tr}(s)} P_{j_A}^{(A)} P_{j_B}^{(B)} \quad (j_A k_A : j_B k_B) \quad q \quad (j_A k_A : j_B k_B) \quad P_{j_B}^{(B)} P_{j_A}^{(A)} \quad \text{Math.} \quad \text{Math.} \quad N_A + v, N_B - v \quad \text{Math.} \quad \text{Math.} \quad N_A + v, N_B - v \quad \text{Math.}$$

when v is odd.

[0109] In examples in which the fermion parity does not change when the tetron islands are decoupled, the resulting state is the ideal post-measurement state, as shown in the above equations for $\rho'''.\text{sub}.v$. When the fermion parity changes, the resulting state of the two-tetron system is equal to the ideal state modified by a known Pauli operator **84**. The value of the Pauli operator **84** is determined by the specific two-tetron measurement that was performed, as discussed in further detail below. In either case, the fermion numbers of the tetron islands are given by $N'.\text{sub}.A=N.\text{sub}.A+v$ and $N'.\text{sub}.B=N.\text{sub}.B+v$. Thus, the QPP error to the encoded computational state may be corrected by applying the inverse of the Pauli operator **84**.

[0110] In some examples, as discussed above with reference to FIG. **8**, the accumulated error state **86** is tracked over a plurality of physical computing timesteps **108**, and the update operation **90** is applied subsequently to a plurality of joint parity measurements **32**. In such examples, as shown in FIG. **8**, the controller **20** is further configured to control the quantum computing device **10** to perform QPP detection **36** subsequently to each of the plurality of joint parity measurements **32**. The controller **20** is further configured to generate the Pauli operator sequence **88** based at least in part on the respective values of the changes in the fermion numbers $N.\text{sub}.tot$ measured during the QPP detections **36**. Accordingly, the controller **20** is configured to iteratively construct the Pauli operator sequence **88** over the plurality of physical computing timesteps **108**.

[0111] The plurality of QPP detections **36** may be performed without the controller **20** transmitting active feedback instructions to the quantum computing device **10** subsequently to each of the joint parity measurements **32**. By not requiring active feedback to track and correct QPP errors, the computing system **1** may utilize a simpler control architecture to control the quantum computing device **10**.

[0112] When performing the Pauli operator tracking in examples in which the update operation **90** is delayed until after a plurality of physical computing timesteps **108**, the controller **20** is configured to utilize the fact that a Pauli operator P may be passed through a Pauli projector

$$[00037] \quad \rho_s^{(Q)} = \frac{1}{2}(1 + sQ).$$

The projector label in the above equation is flipped when the Pauli operators P and Q anti-commute. Accordingly, the following equation holds:

$$\Pi.\text{sub}.s.\text{sup}.(Q)P = \Pi.\text{sub}.\pm s.\text{sup}.(Q)$$

As discussed above, the update operation **90** may be delayed until a physical computing timestep **108** immediately prior to a non-Clifford logical operation.

[0113] A generalization of the above discussion of two-tetron measurements to measurements of N -Majorana-island systems is provided below. The N -Majorana-island measurement is performed on two MZMs **14** from each of the Majorana islands **12** at which the measurement is performed. The N Majorana islands **12** are labeled herein as $J \in \text{custom-character}$, and the N junctions between the Majorana islands **12** are labeled as $j \in \text{custom-character}$. The $2N$ MZMs **14** on which the measurement is performed are labeled as $j.\text{sub}.J$, such that a pair of MZMs **14** linked by the j th coupling path are labeled $j.\text{sub}.J$ and $j.\text{sub}.J+1$. With the above conventions, the following joint fermion parity operator is measured:

$$[00038] \quad \prod_{j=1}^N i \quad j_j \quad j_{j+1}$$

As in the example of the two-tetron measurement discussed above, in the N -Majorana-island measurement, the MZMs **14** included in different Majorana islands **12** are coupled pairwise in a manner that forms a non-self-intersecting interference loop **55** using coupling paths that include quantum dots **16**.

[0114] FIG. **10A** shows an example island-dot system **111** that includes a Majorana tetron **112A**, a Majorana hexon **112B**, and a coherent link **112C**. The island-dot system **111** of FIG. **10A** is shown when a three-Majorana-island measurement of an operator $y.\text{sub}.j.\text{sub}.Ay.\text{sub}.j.\text{sub}.By.\text{sub}.j+1.\text{sub}.By.\text{sub}.j+1.\text{sub}.Cy.\text{sub}.j+2.\text{sub}.Cy.\text{sub}.j+2.\text{sub}.A$ is performed. In the example of FIG. **10A**, the Majorana

tetron **112A** is coupled to the Majorana tetron **112B** via a first QD **116A**, the Majorana hexon **112B** is coupled to the coherent link **112C** via a second QD **116B**, and the coherent link **112C** is coupled to the Majorana tetron via a third QD **116C** to thereby form the interference loop **55**.

[0115] In the N-Majorana-island measurement example, the projection operator is given by:

$$[00039] \quad s = \frac{1}{2}(1 - s) \cdot \text{Math.} \left(\prod_{j=1}^N i^{j_j - j_{j+1}} \right)$$

A fermion transfer between a Majorana island J and a Majorana island J+V applies one of the following operators:

$$[00040] \quad i^{j_j - j_{j+1}} i^{j+1_{j+1} - j+1_{j+2}} \cdot \text{Math.} \left(i^{j+v-1_{j+V-1} - j+v-1_{j+V}} \text{ or } i^{j-1_j - j-1_{j-1}} i^{j-2_{j-1} - j-2_{j-2}} \right) \cdot \text{Math.} \left(i^{j+V_{j+V+1} - j+V_{j+V}} \right)$$

The path along which the fermion travels from the Majorana island J to the Majorana island J+V determines which of the above operators is applied by the QPP event. The fermion transfer also updates classical integer values that track the fermion numbers of the Majorana island J and the Majorana island J+V, as discussed in further detail below. The above operators are equivalent, up to a difference of sign, after the projection operator is applied to the state of the N-Majorana-island system.

[0116] FIGS. **10B-10C** show the island-dot system **111** of FIG. **10A** in examples in which QPP occurs. In the example of FIG. **10B**, QPP occurs between the MZMs $\gamma_{\text{sub.j.sub.A}}$ and $\gamma_{\text{sub.j.sub.B}}$, which applies the operator $\gamma_{\text{sub.j.sub.A}} \gamma_{\text{sub.j.sub.B}}$. In the example of FIG. **10C**, QPP occurs between the MZMs $\gamma_{\text{sub.j+2.sub.C}}$ and $\gamma_{\text{sub.j+2.sub.A}}$ and between the MZMs $\gamma_{\text{sub.j+1.sub.B}}$ and $\gamma_{\text{sub.j+1.sub.C}}$. These two QPP events apply the operator $\gamma_{\text{sub.j+2.sub.A}} \gamma_{\text{sub.j+2.sub.C}} \gamma_{\text{sub.j+1.sub.B}} \gamma_{\text{sub.j+1.sub.C}}$ to the island-dot system **111**.

[0117] The post-measurement, post-decoupling state of an N-Majorana-island system is given by:

$$[00041] \quad p = p_0 + p_1 \cdot \text{Math.} \left(i^{j+v-1_{j+V-1} - j+v-1_{j+V}} i^{j+V_{j+V} - j+v-1_{j+V-1}} \right) \cdot \text{Math.} \left(i^{j_{j+1} - j_j} \right)$$

As in the two-tetron QPP example, $p_{\text{sub.0}}$ is the probability that an even number of fermions are transferred between islands J and J+V, and $p_{\text{sub.1}}$ is the probability that an odd number of fermions are transferred.

[0118] The following discussion extends the above description of the effects of QPP to examples in which QD poisoning occurs. In such examples, the Majorana operator corresponding to intercomponent QPP is no longer guaranteed to involve an even number of MZMs **14**. Fermion transfer may occur between a Majorana island **12** and a QD **16**, or between a pair of QDs **16**. In examples in which fermion transfer occurs between a Majorana island J and a QD k that forms the kth coupling junction between Majorana islands K and K+1, the fermion transfer applies one of the following operators:

$$[00042] \quad i^{j_j - j_{j+1}} i^{j+1_{j+1} - j+1_{j+2}} \cdot \text{Math.} \left(k_K \text{ or } i^{j-1_j - j-1_{j-1}} i^{j-2_{j-1} - j-2_{j-2}} \right) \cdot \text{Math.} \left(k_{K+1} \right)$$

The above operators are equivalent, up to a difference of sign, after the projection operator is applied to the state of the N-Majorana-island system.

The path along which the fermion travels during the QPP event determines which of the above operators the QPP event applies.

[0119] QPP may also result in a fermion transfer between QDs k and k+V that form the kth and k+Vth coupling junctions between Majorana islands K and K+V. In such examples, the corresponding operator applied by the fermion transfer is one of the following operators:

$$[00043] \quad k_{K+1} k_{K+1} k_{K+1} \cdot \text{Math.} \left(k_{K+V} \text{ or } k_K k_{K-1_K} k_{K-1_K-1} \right) \cdot \text{Math.} \left(k_{K+V+1} \right)$$

The above operators are equivalent, up to a difference of sign, after the projection operator is applied to the state of the N-Majorana-island system.

[0120] FIGS. **11A-11B** show examples of QPP between QDs **16** at the island-dot system **111** of FIG. **10A**. In these examples, a fermion is transferred from the first QD **116A** to the second QD **116B**. In the example of FIG. **11A**, QPP occurs between the first QD **116A** and the MZM $\gamma_{\text{sub.j.sub.B}}$, as well as between the MZM $\gamma_{\text{sub.j+1.sub.B}}$ and the second QD **116B**. This QPP applies the operator $\gamma_{\text{sub.j.sub.B}} \gamma_{\text{sub.j+1.sub.B}}$ to the quantum state of the island-dot system **111**. In the example of FIG. **11B**, QPP occurs between the MZM $\gamma_{\text{sub.j.sub.A}}$ and the first QD **116A**, between the second QD **116B** and the MZM $\gamma_{\text{sub.j+1.sub.C}}$, and between the MZM $\gamma_{\text{sub.j+2.sub.A}}$ and the MZM $\gamma_{\text{sub.j+2.sub.C}}$. This QPP applies the operator $\gamma_{\text{sub.j.sub.A}} \gamma_{\text{sub.j+2.sub.A}} \gamma_{\text{sub.j+2.sub.C}} \gamma_{\text{sub.j+1.sub.C}}$.

[0121] FIGS. **11C-11D** show examples of QPP between a Majorana island **12** and a QD **16** at the island-dot system **111** of FIG. **10A**. A fermion is transferred from the Majorana tetron **112A** to the second QD **116B** in the examples of FIGS. **11C-11D**. In the example of FIG. **11C**, QPP occurs between the MZM $\gamma_{\text{sub.j.sub.A}}$ and the MZM $\gamma_{\text{sub.j.sub.B}}$, as well as between the MZM $\gamma_{\text{sub.j+1.sub.B}}$ and the second QD **116B**. This QPP applies the operator $\gamma_{\text{sub.j.sub.A}} \gamma_{\text{sub.j.sub.B}} \gamma_{\text{sub.j+1.sub.B}}$. In the example of FIG. **11D**, QPP occurs between the MZM $\gamma_{\text{sub.j+2.sub.A}}$ and the MZM $\gamma_{\text{sub.j+2.sub.C}}$, as well as between the MZM $\gamma_{\text{sub.j+1.sub.C}}$ and the second QD **116B**. This QPP applies the operator $\gamma_{\text{sub.j+2.sub.A}} \gamma_{\text{sub.j+2.sub.C}} \gamma_{\text{sub.j+1.sub.C}}$.

[0122] Mappings between the Majorana operators associated with the MZMs **14** of a Majorana tetron to the Pauli operators **84** are provided below. These mappings are as follows when the fermion parity of the Majorana island **12** is a qubit degree of freedom:

$$[00044] \quad i_1 = -X_q X_p \quad i_2 = Y_q X_p \quad i_3 = -Z_q X_p \quad i_4 = I_q Y_p$$

In the above equations, the label q corresponds to an encoded topological qubit and the label p corresponds to the island fermion parity.

[0123] When the Majorana island **12** is in an idle configuration, interactions between the Majorana island **12** and its environment quickly decohere the even and odd fermion parity subspaces (the +1 and -1 eigenspaces of $Z_{\text{sub.p}}$). Thus, the Majorana island **12** typically does not exhibit coherent superpositions of states with different island parities. The eigenvalue of $Z_{\text{sub.p}}$ may therefore be treated as a classical variable. The $X_{\text{sub.p}}$ and $Y_{\text{sub.p}}$ operators may be treated as island parity flipping operators with no significant distinction between them.

[0124] The joint fermion parity operator $-\gamma_{\text{sub.1}} \gamma_{\text{sub.2}} \gamma_{\text{sub.3}} \gamma_{\text{sub.4}}$ may be expressed in terms of Pauli operators **84** as follows:

$$[00045] \quad -i_1 i_2 i_3 i_4 = (-X_q X_p)(Y_q X_p)(-Z_q X_p)(I_q Y_p) = I_q Z_p$$

Pairs of Majorana operators map to Pauli operators **84** of the encoded qubit according to:

$$[00046] \quad i_1 i_2 = i(-X_q X_p)(Y_q X_p) = Z_q I_p \quad i_1 i_3 = i(-X_q X_p)(-Z_q X_p) = Y_q I_p \quad i_1 i_4 = i(-X_q X_p)(I_q Y_p) = X_q Z_p$$

$$i_2 i_3 = i(Y_q X_p)(-Z_q X_p) = X_q I_p \quad i_2 i_4 = i(Y_q X_p)(I_q Y_p) = -Y_q Z_p \quad i_3 i_4 = i(-Z_q X_p)(I_q Y_p) = Z_q Z_p$$

Accordingly, when the fermion parity of the Majorana island **12** is even:

$$[00047] \quad X_q = i_2 i_3 = i_1 i_4 \quad Y_q = i_1 i_3 = -i_2 i_4 \quad Z_q = i_1 i_2 = i_3 i_4$$

When the fermion parity of the Majorana island **12** is odd:

$$[00048] \quad X_q = i_2 i_3 = -i_1 i_4 \quad Y_q = i_1 i_3 = i_2 i_4 \quad Z_q = i_1 i_2 = -i_3 i_4$$

[0125] In examples in which Majorana operators of a multi-tetron system are mapped to Pauli operators **84**, Jordan-Wigner strings may be used to ensure that the Majorana operators anticommute with each other. For an arbitrary labeling of the Majorana tetrons with integers $n=1, \dots, N$, the Majorana operators of the nth tetron may be written as follows:

$$[00049] \quad i_1^{(n)} = -X_q^{(n)} X_p^{(n)} \quad \text{Math.} \left(Z_p^{(m)} \right)_{m < n} \quad i_2^{(n)} = Y_q^{(n)} X_p^{(n)} \quad \text{Math.} \left(Z_p^{(m)} \right)_{m < n} \quad i_3^{(n)} = -Z_q^{(n)} X_p^{(n)} \quad \text{Math.} \left(Z_p^{(m)} \right)_{m < n} \quad i_4^{(n)} = I_q^{(n)} Y_p^{(n)} \quad \text{Math.} \left(Z_p^{(m)} \right)_{m < n}$$

Since the Jordan-Wigner operators have the form $\Pi_{\text{sub.m} < n} Z_{\text{sub.p.sup.(m)}}$, and since the p qubits are treated as classical variables, the Jordan-Wigner operators only change the signs of the Majorana operators.

[0126] Using the above relationships between QPP events and joint parity measurements **32**, and between joint parity measurements **32** and Pauli operators **84**, the controller **20** is configured to compute the Pauli operator sequence **88**. Thus, the controller **20** is configured to determine the update operation **90** based at least in part on whatever changes in the fermion numbers are detected as having occurred after each of the joint parity measurements **32**.

[0127] FIG. **12A** schematically shows the computing system **1** in an example in which the controller **20** is further configured to compute a plurality of estimated fermion number probabilities **120** corresponding to the plurality of candidate values of the change in the fermion number $N_{\text{sub.tot}}$. In

addition, the controller **20** may be further configured to determine a probability threshold **122** of an ambiguous measurement or a failed measurement. An ambiguous measurement is a measurement for which the joint parity value **39** of the two or more MZMs **14** is ambiguous at each of the candidate resonance regions **40**. For example, the controller **20** may be configured to determine that a joint parity measurement **32** is an ambiguous measurement when the values of the microwave response signal **57** received at each of the candidate resonance regions **40** are within predetermined confidence intervals associated with both the positive parity response curve **41A** and the negative parity response curve **41B**. A failed measurement is a measurement that is either an ambiguous measurement or a measurement of an island-dot system **11** at which QD poisoning has occurred. The probability threshold **122** may, for example, be a parameter set via user input.

[0128] The controller **20**, in the example of FIG. **12A**, is further configured to select the number of candidate resonance regions **40** based at least in part on the estimated fermion number probabilities **120** and the probability threshold **122**. For example, the controller **20** may be configured to select a fermion number sampling range endpoint N.sub.max, and the controller **20** may be further configured to test for changes in the fermion number included in the set $\{-N_{\text{sub.max}}, -N_{\text{sub.max}}+1, \dots, N_{\text{sub.max}}\}$. Thus, the number of candidate resonance regions **40** may be equal to $2N_{\text{sub.max}}+1$.

[0129] In some examples, as shown in FIG. **12B**, the controller **20** may be further configured to compute a plurality of numbers $2N_{\text{sub.max}}+1$ of candidate resonance regions **40** corresponding to a respective plurality of joint parity measurement types **130**. Accordingly, the different joint parity measurement types **130** may have different values of N.sub.max. For example, the plurality of joint parity measurement types **130** may include a one-qubit measurement that does not utilize a coherent link, a one-qubit measurement that utilizes a coherent link, a two-qubit measurement that does not utilize a coherent link, a two-qubit measurement that utilizes a coherent link, a two-qubit measurement that utilizes two coherent links, a three-qubit measurement that does not utilize a coherent link, a three-qubit measurement that utilizes a coherent link, and a four-qubit measurement that does not utilize a coherent link. Each of the values of N.sub.max may be computed based at least in part on the estimated fermion number probabilities **120** and the probability threshold **122** of an ambiguous or failed measurement.

[0130] When a joint parity measurement **32** is performed subsequently to computing the value of N.sub.max for the different joint parity measurement types **130**, the controller **20** may be further configured to select the number of candidate resonance regions **40** searched during the joint parity measurement **32**. The controller **20** selects the number of candidate resonance regions **40** from among the plurality of numbers $2N_{\text{sub.max}}+1$ computed for the different joint parity measurement types **130** as specified by the joint parity measurement type **130** of the joint parity measurement **32**.

[0131] Computation of the estimated fermion number probabilities **120**, as well as probabilities of an ambiguous measurement or a failed measurement, is discussed in additional detail below. Using these probabilities, the processor **22** may be configured to select the value of N.sub.max such that the probability of an ambiguous measurement or a failed measurement is below the probability threshold **122**. The probability of an ambiguous measurement is given by:

$$[00050] p_{\text{amb}} = 1 - p_{N_{\text{tot}}}$$

In the above equation, p.sub.N.sub.tot is the probability of the occurrence of a specific integer value of N.sub.tot, and = $\{-N_{\text{sub.max}}, -N_{\text{sub.max}}+1, \dots, N_{\text{sub.max}}\}$.

[0132] In examples in which the joint parity measurement **32** is a two-MZM measurement that utilizes one Majorana island **12** and one QD **16**, a regime with $\epsilon_{\text{sub.C}} \gg E_{\text{sub.C}}$ is first considered. In this regime, the probability of QD poisoning is treated as negligible. The probability p.sub.N of the Majorana island **12** having a given value of the change in fermion number N may be modeled as a Gibbs distribution:

$$[00051] p_N = \frac{e^{-E_C(N-N_g)^2}}{\text{Math}_{M=-\infty}^{\infty} e^{-E_C(M-N_g)^2}}$$

In the above equation, $\beta=1/k_{\text{sub.BT}}$. The above Gibbs distribution may, for example, provide an accurate model of the probabilities p.sub.N for a plurality of Majorana tetrons implementing a quantum error correction code or quantum computation over a long duration without the use of active feedback to correct for QPP.

[0133] The joint parity measurements **32** may be modeled as starting with the Majorana island **12** in an unpoisoned state. In such examples, each of the two-qubit measurements ends with the two Majorana islands **12** used in the measurement having an N-poisoned state. The probability of the two Majorana islands **12** ending the measurement in the N-poisoned state may be approximated as:

$$[00052] p_N \approx \frac{e^{-2E_C(N-N_g)^2}}{\text{Math}_{M=-\infty}^{\infty} e^{-2E_C(M-N_g)^2}}$$

The above equation for p.sub.N is equivalent to the equation for p.sub.N in the one-qubit case, except with β replaced by 2β .

[0134] The following table shows values of p.sub.amb computed for various values of N.sub.max and $\beta E_{\text{sub.C}}$ in the one-qubit case when N.sub.g=0.

TABLE-US-00001 log.sub.10(p.sub.amb) $\beta E_{\text{sub.C}} = 3$ $\beta E_{\text{sub.C}} = 4$ $\beta E_{\text{sub.C}} = 5$ $\beta E_{\text{sub.C}} = 6$ $\beta E_{\text{sub.C}} = 7$ N.sub.max = 0 -1.04 -1.45 -1.88 -2.31 -2.74 N.sub.max = 1 -4.95 -6.66 -8.39 -10.1 -11.9 N.sub.max = 2 -11.5 -15.3 -19.2 -23.2 -27.1 N.sub.max = 3 -20.6 -27.5 -34.4 -41.4 -48.3 N.sub.max = 4 -32.3 -43.1 -54.0 -64.8 -75.7

[0135] The probability of a failed measurement is considered below in an example in which the probability of QD poisoning is non-negligible. In this example, the following Hamiltonian may be used to model the Majorana island **12** and the QD **16**:

$$[00053] H(N, n) = E_C(N - N_g)^2 + E_C(n - n_g)^2$$

The probability p.sub.N.sub.tot of measuring a change in fermion number N.sub.tot is given by the following Gibbs distribution:

$$[00054] p_{N_{\text{tot}}} = \frac{e^{-H(N_{\text{tot}}, n)}}{\sum_n e^{-H(N, n)}}$$

Using the above equation for p.sub.N.sub.tot, the ambiguous measurement probability p.sub.amb may be computed as in the case in which the QD poisoning probability is negligible.

[0136] To compute the probability p.sub.fail of a failed measurement that may be either an ambiguous measurement or a measurement in which QD poisoning occurs, the additional constraint n=0 may be used. Thus, when QD poisoning occurs, resulting in n $\neq$ 0, the measurement is treated as a failed measurement. The equation for p.sub.N.sub.tot may accordingly be modified as follows:

$$[00055] p_{N_{\text{tot}}} = \frac{e^{-H(N_{\text{tot}}, 0)}}{\sum_n e^{-H(N, n)}}$$

Accordingly, p.sub.fail may be computed as:

$$[00056] p_{\text{fail}} = 1 - p_{N_{\text{tot}}}$$

[0137] The probability of an ambiguous measurement at a two-Majorana-island system is considered below in an example in which the probability of QD poisoning is negligible. In this example, Majorana islands labeled A and B may be modeled with the following Hamiltonian:

$$[00057] H = E_{C,A}(N_A - N_{g,A})^2 + E_{C,B}(N_B - N_{g,B})^2$$

A Gibbs distribution may be used to approximate the probabilities of configurations of the Majorana islands **12** with different fermion numbers when the Majorana islands **12** are decoupled. When the Majorana islands **12** are decoupled, N.sub.g,A and N.sub.g,B have idle values of approximately zero. The partition function for a fixed value of N.sub.tot is given by:

$$[00058] Z_{N_{\text{tot}}} = N_A + N_B = N_{\text{tot}} e^{-H(N_A, N_B)}$$

The total partition function is given by:

$$[00059] Z = Z_{N_{\text{tot}}} = e^{-(E_{C,A}N_{g,A}^2 + E_{C,B}N_{g,B}^2)} (i_A, -i_A N_{g,A}) (i_B, -i_B N_{g,B})$$

In the above equation,

$$[00060] A = E_{C,A} / B = E_{C,B} /$$

and ϑ is the Jacobi theta function,

$$[00061] (z,) = e^{i n^2 + i 2 n z}$$

[0138] From the above Gibbs distribution, the estimated probabilities p.sub.N.sub.tot may be computed as:

$$[00062] p_{N_{tot}} = \frac{Z_{N_{tot}}}{Z}$$

When N.sub.g,A=N.sub.g,B=0, corresponding to the idle configuration of the Majorana islands **12**, the probability p.sub.amb of an ambiguous measurement outcome may be computed. The following table lists values of p.sub.amb corresponding to various values of N.sub.max when E.sub.C,A=E.sub.C,B=E.sub.C. These values of E.sub.C,A and E.sub.C,B correspond to a two-qubit Pauli measurement performed on two Majorana tetrons and no coherent links.

TABLE-US-00002 log.sub.10(p.sub.amb) β E.sub.C = 3 β E.sub.C = 4 β E.sub.C = 5 β E.sub.C = 6 β E.sub.C = 7 N.sub.max = 0 -0.773 -1.16 -1.58 -2.01 -2.44 N.sub.max = 1 -2.38 -3.20 -4.05 -4.91 -5.78 N.sub.max = 2 -5.99 -8.12 -10.3 -12.4 -14.6 N.sub.max = 3 -10.2 -13.6 -17.1 -20.5 -24.0 N.sub.max = 4 -16.4 -22.0 -27.6 -33.3 -38.9 N.sub.max = 5 -23.2 -31.0 -38.8 -46.6 -54.4

[0139] The following table lists values of p.sub.amb corresponding to various values of N.sub.max when

$$[00063] E_{C,A} = \frac{1}{2} E_{C,B} = E_C$$

These values of E.sub.C,A and E.sub.C,B correspond to a single-qubit Pauli measurement of one Majorana tetron and one coherent link.

TABLE-US-00003 log.sub.10(p.sub.amb) β E.sub.C = 3 β E.sub.C = 4 β E.sub.C = 5 β E.sub.C = 6 β E.sub.C = 7 N.sub.max = 0 -1.02 -1.44 -1.87 -2.31 -2.74 N.sub.max = 1 -3.63 -4.92 -6.22 -7.52 -8.82 N.sub.max = 2 -7.56 -10.1 -12.7 -15.3 -17.9 N.sub.max = 3 -14.1 -18.8 -23.6 -28.4 -33.1 N.sub.max = 4 -21.9 -29.2 -36.6 -44.0 -51.4 N.sub.max = 5 -31.0 -41.4 -51.8 -62.2 -72.7

[0140] The probability of a failed measurement is considered below for a two-Majorana-island system in an example in which the probability of QD poisoning is non-negligible. In this example, the two-Majorana-island system may be modeled with the following Hamiltonian:

$$[00064] H = E_{C,A} (N_A - N_{g,A})^2 + E_{C,B} (N_B - N_{g,B})^2 + c_{1,1} (n_1 - n_{g,1})^2 + c_{2,2} (n_2 - n_{g,2})^2$$

The partition function for a fixed value of N.sub.tot is given by:

$$[00065] Z_{N_{tot}} = N_A + N_B + n_1 + n_2 = N_{tot} e^{-H(N_A, N_B, n_1, n_2)}$$

In addition, the total partition function is given by:

$$[00066] Z = \sum_{N_{tot} \in \mathbb{Z}} \text{Math. } Z_{N_{tot}}$$

The probabilities p.sub.N.sub.tot may be computed as in the case in which the QD poisoning probability is negligible. In addition, the ambiguous measurement probability p.sub.amb may be computed from the probabilities p.sub.N.sub.tot as discussed above.

[0141] In order to compute a more general probability of measurement failure p.sub.fail, the additional constraint n.sub.1=n.sub.2=0 may be introduced, corresponding to no change in the fermion numbers of the QDs **16**. The resulting partition function for a fixed value of N.sub.tot is given by:

$$[00067] Z_{N_{tot}, n_1, n_2} = N_A + N_B + n_1 + n_2 = N_{tot} e^{-H(N_A, N_B, n_1, n_2)}$$

The total partition function is accordingly given by:

$$[00068] Z = Z_{N_{tot}, n_1, n_2}$$

In addition, the equation for p.sub.N.sub.tot may be modified as follows:

$$[00069] p_{N_{tot}} = \frac{Z_{N_{tot}, 0, 0}}{Z}$$

The failure probability p.sub.fail may be computed from p'.sub.N.sub.tot as discussed above in the one-Majorana-island example.

[0142] FIG. **13A** schematically shows the computing system **1** during a calibration phase for a given joint parity measurement **32** in which the controller **20** is configured to estimate the plurality of candidate resonance regions **40** and calibrate a classifier **150** to classify parity response signals. The calibration phase may include a first stage and a second stage. In the first stage, the controller **20** may be configured to locate each candidate resonance region **40** for N.sub.tot $\in \{-N_{max}, \dots, N_{max}\}$ at least in part by tuning the quantum dot gate voltages n.sub.g and Majorana island gate voltages N.sub.g of the one or more QDs **16** and the one or more Majorana islands **12** used in the joint parity measurement **32**. The controller **20** may be configured to tune the Majorana island gate voltages N.sub.g, the quantum dot gate voltages n.sub.g, and the cutter gate voltages n.sub.cg to values located within a Majorana island gate voltage range **140A**, a quantum dot gate voltage range **140B**, and a cutter gate voltage range **140C**, which are the ranges of voltages over which the controller **20** searches for the candidate resonance regions **40**.

[0143] The second stage may include, for each value of the total fermion number N.sub.tot $\in \{-N_{sub.max}, N_{sub.max}\}$, extracting the positive parity response curve **41A** and the negative parity response curve **41B** at each candidate resonance region **40**. The positive parity response curve **41A** and the negative parity response curve **41B** may then be used as the expected response signals with which the classifier of the joint parity measurement **32** is calibrated. Extracting these response signals may further include tuning cutter gate voltages to increase the measurement visibility.

[0144] FIGS. **13B-13D** show the island-dot system **11** during the calibration phase in additional detail, according to one example. The calibration steps shown in FIGS. **13B-13D** may be performed for each of the plurality of values of the changes in the fermion number N.sub.tot $\in \{-N_{sub.max}, N_{sub.max}\}$ such that the classifier **150** is configured to determine a positive parity response signal **41A** and a negative parity response signal **41B** at each candidate resonance region **40**. As shown in FIG. **13B**, the controller **20** may be configured to control the quantum computing device **10** to initialize the one or more Majorana island gate voltages N.sub.g and the one or more quantum dot gate voltages n.sub.g at respective Coulomb valley voltages. The one or more Majorana island gate voltages N.sub.g are each set to a Coulomb valley Majorana island gate voltage **144A** and the one or more quantum dot gate voltages n.sub.g are each set to a Coulomb valley quantum dot gate voltage **144B**.

[0145] The calibration phase may further include setting the change in the fermion number N.sub.tot of the island-dot system **11** to the value for which the controller **20** is currently configured to identify the candidate resonance region **40**. The change in the fermion number N.sub.tot may be set by transferring fermions onto or off the Majorana island **12** via the fermion reservoir **58**. The controller **20** may be further configured to electrically couple the two or more MZMs **14** and the one or more QDs **16**. In the example of FIG. **13B**, the two or more MZMs **14** and the one or more QDs **16** are electrically coupled by closing the switch **17**.

[0146] As depicted in FIG. **13C**, the controller **20** may be further configured to control the quantum computing device **10** to search over the Majorana island gate voltage range **140A**, the quantum dot gate voltage range **140B**, and the cutter gate voltage range **140C**. The search may be performed using the capacitance sensor **18** by iteratively adjusting the Majorana island gate voltage N.sub.g of the one or more Majorana islands **12**, the quantum dot gate voltage n.sub.g of the one or more QDs **16**, and the cutter gate voltage n.sub.cg of the one or more cutter gates **19** based at least in part on quantum capacitance measurements **38**. For example, the controller **20** may be configured to use a hill-climbing search algorithm with respect to the Majorana island gate voltage N.sub.g, the quantum dot gate voltage n.sub.g, and the cutter gate voltage n.sub.cg to approximate a parameter-space location of the candidate resonance region **40**. During the search, the one or more Majorana islands **12** may each be set to the same Majorana island gate voltage N.sub.g, the one or more QDs **16** may each be set to the same quantum dot gate voltage n.sub.g, and the one or more cutter gates **19** may each be set to the same cutter gate voltage n.sub.cg. The controller **20** may be further configured to control the quantum computing device **10** to output a plurality of quantum capacitance measurements **38** of the island-dot system **11** in ranges that include the candidate resonance gate voltages **42A**, **42B**, and **42C**. The controller **20** may be further configured to compute the positive parity response signal **41A**, the negative parity

response signal **41B**, and the ambiguous measurement outcome **41C** from the plurality of quantum capacitance measurements **38** to thereby calibrate the classifier **150**.

[0147] As shown in FIG. **13D**, subsequently to identifying the candidate resonance region **40** and outputting the quantum capacitance measurements **38** at the candidate resonance region **40**, the controller **20** may be further configured to control the quantum computing device **10** to reset the one or more Majorana island gate voltages $N_{\text{sub},g}$ and the one or more quantum dot gate voltages $n_{\text{sub},g}$ to the respective Coulomb valley voltages **144A** and **144B**. In addition, the controller **20** may be further configured to control the quantum computing device **10** to electrically decouple the two or more MZMs **14** and the one or more QDs **16**. Accordingly, the controller **20** may prepare the island-dot system **11** for identification of one or more additional candidate resonance regions **40**.

[0148] The calibration phase may include identifying respective candidate resonance regions **40** for each of a plurality of $N_{\text{sub},\text{tot}}$ values, as discussed above. At each of the values of the change in the fermion number $N_{\text{sub},\text{tot}}$, the controller **20** may be further configured to control the quantum computing device **10** to output a respective plurality of quantum capacitance measurements **38** of the island-dot system **11** at each of the candidate resonance values **42A**, **42B**, and **42C** of the Majorana island gate voltage $N_{\text{sub},g}$, the quantum dot gate voltage $n_{\text{sub},g}$, and the cutter gate voltage $n_{\text{sub},cg}$, including values of the gate voltages $N_{\text{sub},g}$ and $n_{\text{sub},g}$ that correspond to other candidate resonance regions **40**. Thus, the controller **20** may be configured to identify a plurality of off-resonance values of the quantum capacitance for each of the (parity, $N_{\text{sub},\text{tot}}$) pairs.

[0149] FIG. **14A** shows a flowchart of a method **200** for use with a computing system that includes a quantum computing device and a controller. The quantum computing device is a topological quantum computing device that includes a plurality of Majorana islands at which a plurality of MZMs are instantiated. Each Majorana island of the plurality of Majorana islands may be a coherent link, a Majorana tetron, or a Majorana hexon. The quantum computing device further includes a plurality of quantum dots located proximate to the plurality of Majorana islands, as well as a plurality of capacitance sensors configured to perform quantum capacitance measurements of the Majorana islands and quantum dots. The controller is a classical computing device including a processor and memory. Using the method **200** of FIG. **14A**, joint parity measurements of MZMs may be performed even in the presence of QPP.

[0150] At step **202**, the method **200** includes controlling the quantum computing device to perform a joint parity measurement of two or more MZMs of the plurality of MZMs located in the one or more Majorana islands. Step **202** is performed at the controller for an island-dot system that includes one or more Majorana islands of the plurality of Majorana islands and one or more quantum dots of the plurality of quantum dots.

[0151] The flowchart depicted in FIG. **14A** further shows additional steps that are performed at the controller when the joint parity measurement is performed. At step **204**, step **202** includes electrically coupling the two or more MZMs via the one or more quantum dots. Accordingly, a measurement loop that includes the two or more MZMs and the one or more quantum dots may be formed.

[0152] Steps **206** and **208** are performed at each of a plurality of candidate resonance regions corresponding to a plurality of values of a change in a fermion number of the island-dot system. The candidate resonance regions are regions of a parameter space defined in terms of Majorana island gate voltage and QD gate voltage. The candidate resonance regions may further include adjusting one or more cutter gate voltages identified during calibration to increase the measurement visibility. The change in the fermion number is a total number of fermions (e.g., electrons) that move between Majorana islands and/or QDs included in the island-dot system during the QPP event. For example, the one or more candidate resonance regions may correspond to a set of values of the change in the fermion number of the island-dot system selected from the group consisting of $\{-3, -2, -1, 0, 1, 2, 3\}$, $\{-2, -1, 0, 1, 2\}$, and $\{-1, 0, 1\}$.

[0153] At step **206**, step **202** further includes setting one or more corresponding Majorana island gate voltages of the one or more Majorana islands and one or more corresponding quantum dot gate voltages of the one or more QDs to respective candidate resonance values. The candidate resonance values are values of the Majorana island gate voltage and QD gate voltage located within the candidate resonance region.

[0154] At step **208**, step **202** further includes, via a capacitance sensor of the plurality of capacitance sensors, detecting a microwave response signal measured at the island-dot system. The response signal is measured at step **208** by collecting one or more quantum capacitance measurements of the island-dot system via a capacitance sensor of the plurality of capacitance sensors that is located proximate to the island-dot system. In some examples, the quantum capacitance may be measured at ranges of values of the Majorana island gate voltage and the quantum dot gate voltage located within the candidate resonance region.

[0155] At step **210**, the step **202** further includes decoupling the two or more MZMs from the one or more quantum dots subsequently to detecting whether resonance occurs. After the microwave response signal is measured at each of the plurality of candidate resonance regions, step **202** further includes, at step **212**, outputting a joint parity value of the two or more MZMs based at least in part on the microwave response signal. The joint parity value is a positive parity value, a negative parity value, or an ambiguous measurement outcome. Step **212** may include, at step **214**, classifying the microwave response signal as a positive parity response signal, a negative parity response signal, or an ambiguous measurement outcome. The positive parity response signal and the negative parity response signal may be estimated during a calibration phase for different values of the change in the fermion number. By measuring the joint fermion parity of the one or more Majorana islands, the quantum computing device performs a step of a quantum computation or error correction code.

[0156] FIG. **14B** shows additional steps that may be performed in some examples in which the method **200** of FIG. **14A** is performed. The steps of FIG. **14B** may be performed prior to step **202**. At step **216**, the method **200** may further include receiving a probability threshold of an ambiguous measurement or a failed measurement. For example, the controller may receive the probability threshold via user input. At step **218**, the method **200** may further include selecting a number of the plurality of candidate resonance regions. The number of candidate resonance regions may be selected such that the joint parity measurement has a probability of an ambiguous measurement or a failed measurement below the probability threshold when the joint parity measurement is performed at each of the plurality of candidate resonance regions.

[0157] When performing step **218**, the method **200** may further include, at step **220**, computing a plurality of numbers of candidate resonance regions corresponding to a respective plurality of joint parity measurement types. At step **222**, step **218** may further include selecting the number of candidate resonance regions from among the plurality of numbers according to the joint parity measurement type of the joint parity measurement. The plurality of joint parity measurement types may, for example, include a one-qubit measurement that does not utilize a coherent link, a one-qubit measurement that utilizes a coherent link, a two-qubit measurement that does not utilize a coherent link, a two-qubit measurement that utilizes a coherent link, a two-qubit measurement that utilizes two coherent links, a three-qubit measurement that does not utilize a coherent link, a three-qubit measurement that utilizes a coherent link, and a four-qubit measurement that does not utilize a coherent link. Respective numbers of candidate resonance regions may also be computed for other measurement types in some examples.

[0158] FIG. **14C** shows additional steps of the method **200** that may be performed in some examples during a calibration phase. The calibration phase may be performed prior to step **202**. At step **224**, as shown in FIG. **14C**, the method **200** may further include estimating the plurality of candidate resonance regions for each of the plurality of values of the change in the fermion number of the island-dot system. In addition, the calibration phase may further include identifying a positive parity response signal and a negative parity response signal that correspond to a positive fermionic parity and a negative fermionic parity, respectively.

[0159] At step **226**, step **224** may include initializing the one or more Majorana island gate voltages of the one or more Majorana islands and the one or more QD gate voltages of the one or more QDs at respective Coulomb valley voltages. Subsequently to setting the one or more Majorana island gate voltages and the one or more QD gate voltages to the Coulomb valley voltages, step **224** may further include, at step **228**, setting the change in the fermion number of the island-dot system to the value of the change in the fermion number for which the controller is identifying the candidate resonance region. At step **230**, step **224** may further include electrically coupling the two or more MZMs and the one or more QDs.

[0160] At step **232**, the method **200** may further include approximating, as the candidate resonance values corresponding to the value of the change in

the fermion number, respective values of the one or more Majorana island gate voltages and the one or more quantum dot gate voltages at which resonance occurs. The candidate resonance Majorana island gate voltage and the candidate resonance QD gate voltage may be approximated at least in part by searching over respective ranges of the values of the gate voltages using the capacitance sensor.

[0161] At step **234**, step **224** may further include outputting a quantum capacitance measurement of the island-dot system at the candidate resonance values. In some examples, step **234** may include outputting a plurality of quantum capacitance measurements in ranges of the Majorana island gate voltage and the quantum dot gate voltage that are located in the candidate resonance region.

[0162] At step **236**, step **224** may further include resetting the one or more Majorana island gate voltages and the one or more QD gate voltages to the respective Coulomb valley voltages. At step **238**, step **224** may further include electrically decoupling the two or more MZMs and the one or more QDs. Thus, the island-dot system may be prepared for calibration at another combination of a parity value and a change in fermion number.

[0163] At step **240**, step **224** may further include calibrating a classifier that distinguishes between a positive parity response signal, a negative parity response signal, and an ambiguous measurement outcome. The classifier may be calibrated based at least in part on the quantum capacitance measurement obtained for a respective candidate resonance region. Thus, the classifier may be calibrated to identify joint fermionic parities at each of the candidate resonance regions.

[0164] FIG. **15A** shows a flowchart of another method **300** that may be used with the computing system that includes the quantum computing device and the controller. Steps **302** and **304**, as shown in the example of FIG. **15A**, are performed at the quantum computing device. At step **302**, the method **300** includes performing a joint parity measurement at two or more MZMs of the plurality of MZMs instantiated at the plurality of Majorana islands included in the quantum computing device. The two or more MZMs are located in one or more Majorana islands of the plurality of Majorana islands. In some examples, the steps of the method **200** of FIG. **14A** may be performed when performing step **302**.

[0165] At step **304**, the method **300** may further include performing QPP detection at the one or more Majorana islands to thereby generate error data. Similarly to the joint parity measurement, the QPP detection may be performed using a QD and a capacitance sensor located proximate to the Majorana island. The error data includes one or more QPP indications associated with the one or more Majorana islands, with each of the QPP indications specifying whether QPP occurred at that Majorana island during the joint parity measurement. Each QPP indication may further include a change in one or more respective fermion parities of the one or more Majorana islands at which the joint parity measurement is performed.

[0166] Steps **306**, **308**, **310**, and **312** are performed at the controller. At step **306**, the method **300** further includes receiving the error data from the quantum computing device. At step **308**, the method **300** further includes updating an accumulated error state of the one or more Majorana islands based at least in part on the error data. The accumulated error state may track QPP errors over the plurality of physical timesteps.

[0167] In some examples, step **308** may include, at step **310**, computing Pauli operator error data based at least in part on the error data. The Pauli operator error data may specify a Pauli operator applied to a qubit encoded in the one or more Majorana islands by a QPP event indicated in the QPP indication. In such examples, the accumulated error state may include a Pauli operator sequence of a plurality of Pauli operators respectively associated with a plurality of joint parity measurements.

[0168] At step **312**, the method **300** further includes performing an update operation based at least in part on the accumulated error state. As discussed below, the update operation may be a controller-side update operation or a quantum-computing-device-side update operation or an error state tracking operation. The computing system is accordingly configured to adjust for the effects of QPP on a quantum computation or error correction code.

[0169] FIG. **15B** shows additional steps of the method **300** that may be performed in some examples. At step **314**, the method **300** may further include performing a plurality of physical computing timesteps at the quantum computing device during a logical computing timestep. The logical computing timestep may be specified by a quantum code that maps sets of physical-level operations performed on physical qubits to corresponding logical operations performed on logical qubits. The physical computing timesteps may each include a respective joint parity measurement and a respective quasiparticle poisoning detection. By performing the plurality of physical computing timesteps, the quantum computing device may implement a logical-qubit-level gate using a plurality of physical-qubit-level operations.

[0170] At step **316**, the method **300** may further include performing the update operation at the controller during the logical computing timestep subsequently to the plurality of physical computing timesteps. Accordingly, in the example of FIG. **15B**, the update operation is a controller-side update operation. At step **318**, step **316** may include, at the controller, receiving a quantum computation output from the quantum computing device subsequently to the plurality of physical computing timesteps. In examples in which step **318** is performed, step **316** may further include, at step **320**, correcting the quantum computation output based at least in part on the accumulated error state when performing the update operation. Thus, the update operation may be performed at the end of the logical computing timestep.

[0171] FIG. **15C** shows additional steps of the method **300** that may be performed in examples in which the update operation is a quantum-computing-device-side update operation. At step **322**, the method **300** may further include, at the controller, generating instructions to perform quantum error correction based at least in part on the accumulated error state. At step **324**, the method **300** may further include transmitting the instructions to the quantum computing device.

[0172] At step **326**, the method **300** may further include receiving the instructions at the quantum computing device. The method may further include, at step **328**, performing quantum error correction at the one or more Majorana islands based at least in part on the instructions. In some examples, the quantum error correction may be performed subsequently to a physical computing timestep of the plurality of physical computing timesteps that is immediately prior to a non-Clifford logical operation. In such examples, the quantum computing device may avoid having to perform multiple Pauli error correction operations in examples in which multiple QPP events occur during a logical computing timestep.

[0173] In some embodiments, the methods and processes described herein may be tied to a computing system of one or more computing devices. In particular, such methods and processes may be implemented as a computer-application program or service, an application-programming interface (API), a library, and/or other computer-program product.

[0174] FIG. **16** schematically shows a non-limiting embodiment of a computing system **400** that can enact one or more of the methods and processes described above. Computing system **400** is shown in simplified form. Computing system **400** may embody the computing system **1** described above and illustrated in FIG. **1**. Components of computing system **400** may be included in one or more personal computers, server computers, tablet computers, home-entertainment computers, network computing devices, video game devices, mobile computing devices, mobile communication devices (e.g., smart phone), and/or other computing devices, and wearable computing devices such as smart wristwatches and head mounted augmented reality devices.

[0175] Computing system **400** includes a logic processor **402** volatile memory **404**, and a non-volatile storage device **406**. Computing system **400** may optionally include a display subsystem **408**, input subsystem **410**, communication subsystem **412**, and/or other components not shown in FIG. **16**.

[0176] Logic processor **402** includes one or more physical devices configured to execute instructions. For example, the logic processor may be configured to execute instructions that are part of one or more applications, programs, routines, libraries, objects, components, data structures, or other logical constructs. Such instructions may be implemented to perform a task, implement a data type, transform the state of one or more components, achieve a technical effect, or otherwise arrive at a desired result.

[0177] The logic processor may include one or more physical processors (hardware) configured to execute software instructions. Additionally or alternatively, the logic processor may include one or more hardware logic circuits or firmware devices configured to execute hardware-implemented logic or firmware instructions. Processors of the logic processor **402** may be single-core or multi-core, and the instructions executed thereon may be configured for sequential, parallel, and/or distributed processing. Individual components of the logic processor optionally may be distributed among

two or more separate devices, which may be remotely located and/or configured for coordinated processing. Aspects of the logic processor may be virtualized and executed by remotely accessible, networked computing devices configured in a cloud-computing configuration. In such a case, these virtualized aspects are run on different physical logic processors of various different machines, it will be understood.

[0178] Non-volatile storage device **406** includes one or more physical devices configured to hold instructions executable by the logic processors to implement the methods and processes described herein. When such methods and processes are implemented, the state of non-volatile storage device **406** may be transformed—e.g., to hold different data.

[0179] Non-volatile storage device **406** may include physical devices that are removable and/or built-in. Non-volatile storage device **406** may include optical memory, semiconductor memory, and/or magnetic memory, or other mass storage device technology. Non-volatile storage device **406** may include nonvolatile, dynamic, static, read/write, read-only, sequential-access, location-addressable, file-addressable, and/or content-addressable devices. It will be appreciated that non-volatile storage device **406** is configured to hold instructions even when power is cut to the non-volatile storage device **406**.

[0180] Volatile memory **404** may include physical devices that include random access memory. Volatile memory **404** is typically utilized by logic processor **402** to temporarily store information during processing of software instructions. It will be appreciated that volatile memory **404** typically does not continue to store instructions when power is cut to the volatile memory **404**.

[0181] Aspects of logic processor **402**, volatile memory **404**, and non-volatile storage device **406** may be integrated together into one or more hardware-logic components. Such hardware-logic components may include field-programmable gate arrays (FPGAs), program-and application-specific integrated circuits (ASICs), program-and application-specific standard products (PSSP/ASSPs), system-on-a-chip (SOC), and complex programmable logic devices (CPLDs), for example.

[0182] The terms “module,” “program,” and “engine” may be used to describe an aspect of computing system **400** typically implemented in software by a processor to perform a particular function using portions of volatile memory, which function involves transformative processing that specially configures the processor to perform the function. Thus, a module, program, or engine may be instantiated via logic processor **402** executing instructions held by non-volatile storage device **406**, using portions of volatile memory **404**. It will be understood that different modules, programs, and/or engines may be instantiated from the same application, service, code block, object, library, routine, API, function, etc. Likewise, the same module, program, and/or engine may be instantiated by different applications, services, code blocks, objects, routines, APIs, functions, etc. The terms “module,” “program,” and “engine” may encompass individual or groups of executable files, data files, libraries, drivers, scripts, database records, etc.

[0183] When included, display subsystem **408** may be used to present a visual representation of data held by non-volatile storage device **406**. The visual representation may take the form of a graphical user interface (GUI). As the herein described methods and processes change the data held by the non-volatile storage device, and thus transform the state of the non-volatile storage device, the state of display subsystem **408** may likewise be transformed to visually represent changes in the underlying data. Display subsystem **408** may include one or more display devices utilizing virtually any type of technology. Such display devices may be combined with logic processor **402**, volatile memory **404**, and/or non-volatile storage device **406** in a shared enclosure, or such display devices may be peripheral display devices.

[0184] When included, input subsystem **410** may comprise or interface with one or more user-input devices such as a keyboard, mouse, touch screen, or game controller. In some embodiments, the input subsystem may comprise or interface with selected natural user input (NUI) componentry. Such componentry may be integrated or peripheral, and the transduction and/or processing of input actions may be handled on-or off-board. Example NUI componentry may include a microphone for speech and/or voice recognition; an infrared, color, stereoscopic, and/or depth camera for machine vision and/or gesture recognition; a head tracker, eye tracker, accelerometer, and/or gyroscope for motion detection and/or intent recognition; as well as electric-field sensing componentry for assessing brain activity; and/or any other suitable sensor.

[0185] When included, communication subsystem **412** may be configured to communicatively couple various computing devices described herein with each other, and with other devices. Communication subsystem **412** may include wired and/or wireless communication devices compatible with one or more different communication protocols. As non-limiting examples, the communication subsystem may be configured for communication via a wireless telephone network, or a wired or wireless local-or wide-area network. In some embodiments, the communication subsystem may allow computing system **400** to send and/or receive messages to and/or from other devices via a network such as the Internet.

[0186] The following paragraphs discuss several aspects of the present disclosure. According to one aspect of the present disclosure, a computing system is provided, including a quantum computing device that includes a plurality of Majorana islands at which a plurality of Majorana zero modes (MZMs) are instantiated. The quantum computing device further includes a plurality of quantum dots located proximate to the plurality of Majorana islands. The quantum computing device further includes a plurality of capacitance sensors. The computing system further includes a controller configured to, for an island-dot system including one or more Majorana islands of the plurality of Majorana islands and one or more quantum dots of the plurality of quantum dots, control the quantum computing device to perform a joint parity measurement of two or more MZMs of the plurality of MZMs located in the one or more Majorana islands. Performing the joint parity measurement includes, at each of a plurality of candidate resonance regions corresponding to a plurality of values of a change in a fermion number of the island-dot system, setting one or more corresponding Majorana island gate voltages of the one or more Majorana islands and one or more corresponding quantum dot gate voltages of the one or more quantum dots to respective candidate resonance values located within the candidate resonance region. Performing the joint parity measurement further includes, at each of the candidate resonance regions, via a capacitance sensor of the plurality of capacitance sensors, detecting a microwave response signal measured at the island-dot system. Performing the joint parity measurement further includes, based at least in part on the microwave response signal, outputting a joint parity value of the two or more MZMs. The above features may have the technical effect of performing a joint parity measurement that has sufficient measurement visibility even in the presence of quasiparticle poisoning.

[0187] According to this aspect, each Majorana island of the plurality of Majorana islands may be a coherent link, a Majorana tetron, or a Majorana hexon. The above features may have the technical effect of allowing a classical bit or a qubit to be instantiated at each Majorana island.

[0188] According to this aspect, performing the joint parity measurement may further include, at each of the plurality of candidate resonance regions, electrically coupling the two or more MZMs via the one or more quantum dots. Subsequently to detecting the microwave response signal, performing the joint parity measurement may further include decoupling the two or more MZMs from the one or more quantum dots. The above features may have the technical effect of electrically isolating the MZMs from the quantum dots subsequently to the joint parity measurement.

[0189] According to this aspect, the controller may be configured to determine the joint parity value of the two or more MZMs at least in part by classifying the microwave response signal to a positive parity response signal, a negative parity response, signal or an ambiguous response signal. The above features may have the technical effect of indicating, in the output, the joint parity value and whether sufficient measurement visibility was attained.

[0190] According to this aspect, the one or more candidate resonance regions may correspond to a set of values of the change in the fermion number of the island-dot system selected from the group consisting of: $\{-3, -2, -1, 0, 1, 2, 3\}$; $\{-2, -1, 0, 1, 2\}$; and $\{-1, 0, 1\}$. The above features may have the technical effect of checking for distinguishable parity values at the candidate resonance regions that correspond to the highest-probability fermion numbers.

[0191] According to this aspect, the controller is further configured to receive a probability threshold of an ambiguous measurement or a failed measurement. The controller may be further configured to select a number of the plurality of candidate resonance regions for which the joint parity measurement has a probability of an ambiguous measurement or a failed measurement below the probability threshold when the joint parity measurement is performed at each of the plurality of candidate resonance regions. The above features may have the technical effect of allowing a

user to set the number of candidate resonance regions according to a target rate of ambiguous or failed measurements.

[0192] According to this aspect, the controller may be further configured to compute a plurality of numbers of candidate resonance regions corresponding to a respective plurality of joint parity measurement types. The controller may be further configured to select the number of candidate resonance regions from among the plurality of numbers according to the joint parity measurement type of the joint parity measurement. The above features may have the technical effect of allowing the quantum computing device to check for sufficient measurement visibility at different numbers of candidate resonance regions for types of joint parity measurements that have different failed or ambiguous measurement probabilities.

[0193] According to this aspect, the plurality of joint parity measurement types may include a one-qubit measurement that does not utilize a coherent link, a one-qubit measurement that utilizes a coherent link, a two-qubit measurement that does not utilize a coherent link, a two-qubit measurement that utilizes a coherent link, a two-qubit measurement that utilizes two coherent links, a three-qubit measurement that does not utilize a coherent link, a three-qubit measurement that utilizes a coherent link, and a four-qubit measurement that does not utilize a coherent link. The above features may have the technical effect of allowing the quantum computing device to check for sufficient measurement visibility at different numbers of candidate resonance regions for types of joint parity measurements that have different failed or ambiguous measurement probabilities.

[0194] According to this aspect, the controller may be further configured to estimate the plurality of candidate resonance regions during a calibration phase at least in part by, for each of the plurality of values of the change in the fermion number of the island-dot system, controlling the quantum computing device to set the change in the fermion number of the island-dot system and electrically couple the two or more MZMs and the one or more quantum dots. For each of the values of the change in the fermion number, the controller may be further configured to control the quantum computing device to approximate, as the candidate resonance values corresponding to the value of the change in the fermion number, respective values of the one or more Majorana island gate voltages and the one or more quantum dot gate voltages at which resonance occurs at least in part by searching over respective ranges of the values of the gate voltages using the capacitance sensor. For each of the values of the change in the fermion number, the controller may be further configured to control the quantum computing device to output a quantum capacitance measurement of the island-dot system at the candidate resonance values. The above features may have the technical effect of calibrating the quantum capacitance measurements by identifying the candidate resonance regions.

[0195] According to this aspect, for each of the plurality of values of the change in the fermion number, the controller may be further configured to estimate the plurality of candidate resonance regions at least in part by controlling the quantum computing device to initialize the one or more Majorana island gate voltages and the one or more quantum dot gate voltages at respective Coulomb valley voltages prior to setting the change in the fermion number to the value. Subsequently to outputting the quantum capacitance measurement, the controller may be further configured to control the quantum computing device to reset the one or more Majorana island gate voltages and the one or more quantum dot gate voltages to the respective Coulomb valley voltages. The controller may be further configured to control the quantum computing device to electrically decouple the two or more MZMs and the one or more quantum dots. The above features may have the technical effect of preparing the quantum computing device for calibration at another candidate resonance region.

[0196] According to this aspect, at each of the values of the change in the fermion number, the controller may be further configured to control the quantum computing device to output a respective quantum capacitance measurement of the island-dot system at each of the candidate resonance values of the Majorana island gate voltage and the quantum dot gate voltage. The above features may have the technical effect of obtaining quantum capacitance measurements at each candidate resonance region for each of the values of the change in the fermion number during the calibration phase.

[0197] According to another aspect of the present disclosure, a method for use with a computing system including a quantum computing device and a controller is provided. The quantum computing device includes a plurality of Majorana islands. A plurality of Majorana zero modes (MZMs) are instantiated at each of the Majorana islands. The quantum computing device further includes a plurality of quantum dots located proximate to the plurality of Majorana islands and further includes a plurality of capacitance sensors. The method comprises, at the controller, for an island-dot system including one or more Majorana islands of the plurality of Majorana islands and one or more quantum dots of the plurality of quantum dots, controlling the quantum computing device to perform a joint parity measurement of two or more MZMs of the plurality of MZMs located in the one or more Majorana islands. Performing the joint parity measurement includes, at each of a plurality of candidate resonance regions corresponding to a plurality of values of a change in a fermion number of the island-dot system, setting one or more corresponding Majorana island gate voltages of the one or more Majorana islands and one or more corresponding quantum dot gate voltages of the one or more quantum dots to respective candidate resonance values located within the candidate resonance region. At each of the plurality of candidate resonance regions, performing the joint parity measurement further includes, via a capacitance sensor of the plurality of capacitance sensors, detecting a microwave response signal measured at the island-dot system. Performing the joint parity measurement further includes, based at least in part on the microwave response signal, outputting a joint parity value of the two or more MZMs. The above features may have the technical effect of performing a joint parity measurement that has sufficient measurement visibility even in the presence of quasiparticle poisoning.

[0198] According to this aspect, each Majorana island of the plurality of Majorana islands may be a coherent link, a Majorana tetron, or a Majorana hexon. The above features may have the technical effect of allowing a classical bit or a qubit to be instantiated at each Majorana island.

[0199] According to this aspect, performing the joint parity measurement may further include, at each of the plurality of candidate resonance regions, electrically coupling the two or more MZMs via the one or more quantum dots. Subsequently to detecting the microwave response signal, performing the joint parity measurement may further include decoupling the two or more MZMs from the one or more quantum dots. The above features may have the technical effect of electrically isolating the MZMs from the quantum dots subsequently to the joint parity measurement.

[0200] According to this aspect, performing the joint parity measurement may further include classifying the microwave response signal to a positive parity response signal, a negative parity response signal, or an ambiguous response signal. The above features may have the technical effect of indicating, in the output, the joint parity value and whether sufficient measurement visibility was attained.

[0201] According to this aspect, the one or more candidate resonance regions correspond to a set of values of the change in the fermion number of the island-dot system selected from the group consisting of: $\{-3, -2, -1, 0, 1, 2, 3\}$; $\{-2, -1, 0, 1, 2\}$; and $\{-1, 0, 1\}$. The above features may have the technical effect of checking for distinguishable parity values at the candidate resonance regions that correspond to the highest-probability fermion numbers.

[0202] According to this aspect, the method may further include receiving a probability threshold of an ambiguous measurement or a failed measurement. The method may further include selecting a number of the plurality of candidate resonance regions for which the joint parity measurement has a probability of an ambiguous measurement or a failed measurement below the probability threshold when the joint parity measurement is performed at each of the plurality of candidate resonance regions. The above features may have the technical effect of allowing a user to set the number of candidate resonance regions according to a target rate of ambiguous or failed measurements.

[0203] According to this aspect, the method may further include, at the controller, computing a plurality of numbers of candidate resonance regions corresponding to a respective plurality of joint parity measurement types. The method may further include selecting the number of candidate resonance regions from among the plurality of numbers according to the joint parity measurement type of the joint parity measurement. The plurality of joint parity measurement types may include a one-qubit measurement that does not utilize a coherent link, a one-qubit measurement that utilizes a coherent link, a two-qubit measurement that does not utilize a coherent link, a two-qubit measurement that utilizes a coherent link, a two-qubit measurement that utilizes two coherent links, a three-qubit measurement that does not utilize a coherent link, a three-qubit measurement that utilizes a coherent link, and a four-qubit measurement that does not utilize a coherent link.

[0204] According to this aspect, the method may further include estimating the plurality of candidate resonance regions during a calibration phase at

least in part by, for each of the plurality of values of the change in the fermion number of the island-dot system. The calibration phase may further include, for each of the values of the change in the fermion number, electrically coupling the two or more MZMs and the one or more quantum dots. The calibration phase may further include approximating, as the candidate resonance values corresponding to the value of the change in the fermion number, respective values of the one or more Majorana island gate voltages and the one or more quantum dot gate voltages at which resonance occurs at least in part by searching over respective ranges of the values of the gate voltages using the capacitance sensor. The calibration phase may further include, for each of the values of the change in the fermion number, outputting a quantum capacitance measurement of the island-dot system at the candidate resonance values.

[0205] According to another aspect of the present disclosure, a computing system is provided, including a quantum computing device. The quantum computing device includes a plurality of Majorana islands at which a plurality of Majorana zero modes (MZMs) are instantiated. The quantum computing device further includes a plurality of quantum dots located proximate to the plurality of Majorana islands and further includes a plurality of capacitance sensors. The computing system further includes a controller configured to, for an island-dot system including one or more Majorana islands of the plurality of Majorana islands and one or more quantum dots of the plurality of quantum dots, control the quantum computing device to perform a joint parity measurement of two or more MZMs of the plurality of MZMs located in the one or more Majorana islands. Performing the joint parity measurement includes, at each of a plurality of candidate resonance regions corresponding to a plurality of values of a change in a fermion number of the island-dot system and further corresponding to a respective plurality of joint parity measurement types, electrically coupling the two or more MZMs via the one or more quantum dots. Performing the joint parity measurement further includes setting one or more corresponding Majorana island gate voltages of the one or more Majorana islands and one or more corresponding quantum dot gate voltages of the one or more quantum dots to respective candidate resonance values located within the candidate resonance region. Via a capacitance sensor of the plurality of capacitance sensors, performing the joint parity measurement further includes detecting a microwave response signal measured at the island-dot system. Subsequently to detecting the microwave response signal, performing the joint parity measurement further includes decoupling the two or more MZMs from the one or more quantum dots. Based at least in part on the microwave response signal, performing the joint parity measurement further includes outputting a joint parity value of the two or more MZMs. The above features may have the technical effect of performing a joint parity measurement that has sufficient measurement visibility even in the presence of quasiparticle poisoning.

[0206] According to another aspect of the present disclosure, a computing system is provided, including a quantum computing device. The quantum computing device includes a plurality of Majorana islands at which a plurality of Majorana zero modes (MZMs) are instantiated. The computing system further includes a controller configured to control the quantum computing device to perform a joint parity measurement at two or more MZMs of the plurality of MZMs. The two or more MZMs are located in one or more Majorana islands of the plurality of Majorana islands. The controller is further configured to control the quantum computing device to perform quasiparticle poisoning (QPP) detection at the one or more Majorana islands to thereby generate error data. The error data includes one or more QPP indications associated with the one or more Majorana islands. The controller is further configured to receive the error data from the quantum computing device and update an accumulated error state of the one or more Majorana islands based at least in part on the error data. The controller is further configured to perform an update operation based at least in part on the accumulated error state. The above features may have the technical effect of tracking and/or correcting a QPP error that occurs during a joint parity measurement.

[0207] According to this aspect, during a logical computing timestep of a quantum code, the controller may be configured to control the quantum computing device to perform a plurality of physical computing timesteps that include respective joint parity measurements and quasiparticle poisoning detections. The above features may have the technical effect of constructing a logical qubit from a plurality of physical qubits that are controlled using joint parity measurements.

[0208] According to this aspect, during the logical computing timestep, the controller may be further configured to perform the update operation subsequently to the plurality of physical computing timesteps. The above features may have the technical effect of reducing the number of update operations by delaying an update operation until the error state has been accumulated for multiple physical computing timesteps.

[0209] According to this aspect, the controller may be further configured to receive a quantum computation output from the quantum computing device subsequently to a plurality of physical computing timesteps. The update operation may include correcting the quantum computation output at the controller based at least in part on the accumulated error state. The above features may have the technical effect of allowing errors due to QPP to be corrected in classical computation instead of at the quantum computing device.

[0210] According to this aspect, the update operation may include transmitting, to the quantum computing device, instructions to perform quantum error correction. The controller may be configured to generate the instructions based at least in part on the accumulated error state. The above features may have the technical effect of correcting the QPP error at the quantum computing device.

[0211] According to this aspect, the instructions may include instructions to perform the quantum error correction subsequently to a physical computing timestep of the plurality of physical computing timesteps that is immediately prior to a non-Clifford logical operation. The above features may have the technical effect of performing the quantum error correction immediately prior to a logical operation that does not commute with the operations applied to the quantum state by QPP.

[0212] According to this aspect, during each of the physical computing timesteps, the controller may be further configured to control the quantum computing device to perform a plurality of joint parity measurements and a corresponding plurality of quasiparticle poisoning detections in parallel. The above features may have the technical effect of increasing the speed of the quantum computation by concurrently performing joint parity measurements at a plurality of island-dot systems and further performing a plurality of QPP detections at those island-dot systems.

[0213] According to this aspect, based at least in part on the error data, the controller may be further configured to compute Pauli operator error data. The Pauli operator error data may specify a Pauli operator applied to a qubit encoded in the one or more Majorana islands by a QPP event indicated in the QPP indication. The above features may have the technical effect of tracking a Pauli operator error applied to the qubit by the QPP event.

[0214] According to this aspect, the accumulated error state may include a Pauli operator sequence of a plurality of Pauli operators respectively associated with a plurality of joint parity measurements. The above features may have the technical effect of tracking a Pauli operator error applied to the qubit by the QPP event.

[0215] According to this aspect, the QPP indication is an indication of a change in one or more respective fermion parities of the one or more Majorana islands at which the joint parity measurement is performed. The above features may have the technical effect of tracking the change in the fermion parities.

[0216] According to another aspect of the present disclosure, a method for use with a computing system including a quantum computing device and a controller is provided. The method includes, at the quantum computing device, performing a joint parity measurement at two or more Majorana zero modes (MZMs) of a plurality of MZMs instantiated at a plurality of Majorana islands included in the quantum computing device. The two or more MZMs are located in one or more Majorana islands of the plurality of Majorana islands. The method further includes performing quasiparticle poisoning (QPP) detection at the one or more Majorana islands to thereby generate error data. The error data includes one or more QPP indications associated with the one or more Majorana islands. The method further includes, at the controller, receiving the error data from the quantum computing device and updating an accumulated error state of the one or more Majorana islands based at least in part on the error data. The method further includes performing an update operation based at least in part on the accumulated error state. The above features may have the technical effect of tracking and/or correcting a QPP error that occurs during a joint parity measurement.

[0217] According to this aspect, the method may further include, at the quantum computing device, performing a plurality of physical computing timesteps during a logical computing timestep of a quantum code. The physical computing timesteps may each include a respective joint parity

measurement and a respective fermion parities may have the technical effect of constructing a logical qubit from a plurality of physical qubits that are controlled using joint parity measurements.

[0218] According to this aspect, the method may further include, at the controller, performing the update operation during the logical computing timestep subsequently to the plurality of physical computing timesteps. The above features may have the technical effect of reducing the number of update operations by delaying an update operation until the error state has been accumulated for multiple physical computing timesteps.

[0219] According to this aspect, the method may further include, at the controller, receiving a quantum computation output from the quantum computing device subsequently to a plurality of physical computing timesteps. When performing the update operation, the method may further include correcting the quantum computation output based at least in part on the accumulated error state. The above features may have the technical effect of allowing errors due to QPP to be corrected in classical computation instead of at the quantum computing device.

[0220] According to this aspect, the method may further include, at the controller, generating instructions to perform quantum error correction based at least in part on the accumulated error state. The method may further include transmitting the instructions to the quantum computing device. At the quantum computing device, the method may further include receiving the instructions. The method may further include performing quantum error correction at the one or more Majorana islands based at least in part on the instructions. The above features may have the technical effect of correcting the QPP error at the quantum computing device.

[0221] According to this aspect, the quantum error correction may be performed subsequently to a physical computing timestep of the plurality of physical computing timesteps that is immediately prior to a non-Clifford logical operation. The above features may have the technical effect of performing the quantum error correction immediately prior to a logical operation that does not commute with the operations applied to the quantum state by QPP.

[0222] According to this aspect, the method may further include computing Pauli operator error data based at least in part on the error data. The Pauli operator error data may specify a Pauli operator applied to a qubit encoded in the one or more Majorana islands by a QPP event indicated in the QPP indication. The above features may have the technical effect of tracking a Pauli operator error applied to the qubit by the QPP event.

[0223] According to this aspect, the accumulated error state may include a Pauli operator sequence of a plurality of Pauli operators respectively associated with a plurality of joint parity measurements. The above features may have the technical effect of tracking a Pauli operator error applied to the qubit by the QPP event.

[0224] According to this aspect, the QPP indication may be an indication of a change in one or more respective fermion parities of the one or more Majorana islands at which the joint parity measurement is performed. The above features may have the technical effect of tracking the change in the fermion parities.

[0225] According to another aspect of the present disclosure, a computing system is provided, including a controller configured to, in each of a plurality of physical computing timesteps included in a logical computing timestep of a quantum code, receive error data from a quantum computing device. The error data includes a plurality of quasiparticle poisoning (QPP) indications associated with a respective plurality of physical qubits instantiated at the quantum computing device. In each of the physical computing timesteps, the controller is further configured to update an accumulated error state of the plurality of physical qubits based at least in part on the error data. Subsequently to the plurality of physical computing timesteps, the controller is further configured to perform an update operation based at least in part on the accumulated error state. The above features may have the technical effect of tracking and/or correcting a QPP error that occurs during a joint parity measurement.

[0226] “And/or” as used herein is defined as the inclusive or $\vee$, as specified by the following truth table:

TABLE-US-00004														
A	B	$A \vee B$	True	True	True	True	False	True	False	True	True	False	False	False
True	True	True	True	True	True	True	True	True	True	True	True	True	True	True
True	False	True	True	True	True	True	True	True	True	True	True	True	True	True
False	True	True	True	True	True	True	True	True	True	True	True	True	True	True
False	False	False	False	False	False	False	False	False	False	False	False	False	False	False

[0227] It will be understood that the configurations and/or approaches described herein are exemplary in nature, and that these specific embodiments or examples are not to be considered in a limiting sense, because numerous variations are possible. The specific routines or methods described herein may represent one or more of any number of processing strategies. As such, various acts illustrated and/or described may be performed in the sequence illustrated and/or described, in other sequences, in parallel, or omitted. Likewise, the order of the above-described processes may be changed.

[0228] The subject matter of the present disclosure includes all novel and non-obvious combinations and sub-combinations of the various processes, systems and configurations, and other features, functions, acts, and/or properties disclosed herein, as well as any and all equivalents thereof.

Claims

1. A method for use with a computing system that includes a quantum computing device, the method comprising: controlling the quantum computing device to perform a quantum computation including a plurality of logical computing timesteps that implement respective logical-level operations specified by a quantum code, wherein each of the logical computing timesteps includes: performing a plurality of physical computing timesteps at a plurality of physical qubits, wherein each of the physical computing timesteps includes: performing a plurality of joint parity measurements at a set of physical qubits included among the plurality of physical qubits; and performing a plurality of quasiparticle poisoning (QPP) detections on the set of physical qubits to thereby obtain error data; and subsequently to the plurality of physical computing timesteps, performing an update operation on the plurality of physical qubits based at least in part on respective results of the QPP detections included in the error data; and outputting a quantum computation output obtained by performing the plurality of logical computing timesteps included in the quantum computation.
2. The method of claim 1, further comprising, during each of the logical computing timesteps: controlling the quantum computing device to transmit the error data to the controller; at the controller, compute update instructions based at least in part on the error data; and controlling the quantum computing device to perform the update operation according to the update instructions.
3. The method of claim 2, wherein: the update operation is a quantum error correction operation; and the method further comprises computing the update instructions based at least in part on the quantum code.
4. The method of claim 3, wherein the quantum error correction operation is performed subsequently to a physical computing timestep of the plurality of physical computing timesteps that is immediately prior to a non-Clifford logical operation.
5. The method of claim 3, wherein the quantum error correction operation includes a Clifford logical operation that is performed subsequently to a non-Clifford logical operation.
6. The method of claim 2, wherein the accumulated error state includes a Pauli operator sequence of two or more Pauli operators respectively associated with two or more of the joint parity measurements.
7. The method of claim 1, further comprising controlling the quantum computing device to perform the QPP detections subsequently to each of the joint parity measurements included in the logical computing timestep.
8. The method of claim 1, further comprising controlling the quantum computing device to perform two or more of the joint parity measurements in parallel.
9. The method of claim 1, further comprising controlling the quantum computing device to perform two or more of the QPP detections in parallel.
10. The method of claim 1, wherein: the quantum computing device includes a plurality of Majorana islands at which a plurality of Majorana zero modes (MZMs) are instantiated; the joint parity measurements are performed at one or more of the Majorana islands; and the error data indicates a change in one or more respective fermion parities of the one or more of the Majorana islands.
11. A computing system comprising: a quantum computing device; and a controller configured to: control the quantum computing device to perform a quantum computation including a plurality of logical computing timesteps that implement respective logical-level operations specified by a

quantum code, wherein each of the logical computing timesteps includes: performing a plurality of physical computing timesteps at a plurality of physical qubits, wherein each of the physical computing timesteps includes: performing a plurality of joint parity measurements at a set of physical qubits included among the plurality of physical qubits; and performing a plurality of quasiparticle poisoning (QPP) detections on the set of physical qubits to thereby obtain error data; and subsequently to the plurality of physical computing timesteps, performing an update operation on the plurality of physical qubits based at least in part on respective results of the QPP detections included in the error data; and output a quantum computation output obtained by performing the plurality of logical computing timesteps included in the quantum computation.

12. The computing system of claim 11, wherein, during each of the logical computing timesteps, the controller is further configured to: control the quantum computing device to transmit the error data to the controller; compute update instructions based at least in part on the error data; and control the quantum computing device to perform the update operation according to the update instructions.

13. The computing system of claim 12, wherein: the update operation is a quantum error correction operation; and the controller is further configured to compute the update instructions based at least in part on the quantum code.

14. The computing system of claim 13, wherein the quantum error correction operation is performed subsequently to a physical computing timestep of the plurality of physical computing timesteps that is immediately prior to a non-Clifford logical operation.

15. The computing system of claim 13, wherein the quantum error correction operation includes a Clifford logical operation that is performed subsequently to a non-Clifford logical operation.

16. The computing system of claim 12, wherein the accumulated error state includes a Pauli operator sequence of two or more Pauli operators respectively associated with two or more of the joint parity measurements.

17. The computing system of claim 11, wherein the controller is configured to control the quantum computing device to perform the QPP detections subsequently to each of the joint parity measurements included in the logical computing timestep.

18. The computing system of claim 11, wherein the controller is configured to control the quantum computing device to perform two or more of the joint parity measurements in parallel.

19. The computing system of claim 11, wherein the controller is configured to control the quantum computing device to perform two or more of the QPP detections in parallel.

20. A computing system comprising: a quantum computing device; and a controller configured to: control the quantum computing device to perform a quantum computation including a plurality of logical computing timesteps that implement respective logical-level operations specified by a quantum code, wherein each of the logical computing timesteps includes: performing a plurality of physical computing timesteps at a plurality of physical qubits, wherein each of the physical computing timesteps includes: performing a plurality of joint parity measurements in parallel at respective sets of physical qubits included among the plurality of physical qubits; and subsequently to performing the joint parity measurements, performing a plurality of quasiparticle poisoning (QPP) detections in parallel on the sets of physical qubits to thereby obtain error data; and subsequently to the plurality of physical computing timesteps, performing a quantum error correction operation on the plurality of physical qubits based at least in part on respective results of the QPP detections included in the error data; and output a quantum computation output obtained by performing the plurality of logical computing timesteps included in the quantum computation.
