

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12400832
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Nagami; Koichi

Plasma processing apparatus and plasma processing method

Abstract

The disclosed plasma processing apparatus is provided with a chamber, a substrate support, and a power source system. The substrate support has an electrode and configured to support a substrate in the chamber. The power source system is electrically connected to the electrode and configured to apply a bias voltage to the electrode to draw ions from a plasma in the chamber into the substrate on the substrate support. The power source system is configured to output a first pulse to the electrode in a first period and output a second pulse to the electrode in a second period after the first period, as the bias voltage. Each of the first pulse and the second pulse is a pulse of a voltage. A voltage level of the first pulse is different from a voltage level of the second pulse.

Inventors:	Nagami; Koichi (Miyagi, JP)
Applicant:	Tokyo Electron Limited (Tokyo, JP)
Family ID:	1000008781662
Assignee:	Tokyo Electron Limited (Tokyo, JP)
Appl. No.:	18/397941
Filed:	December 27, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240145218 A1	May. 02, 2024

Foreign Application Priority Data

JP	2020-079517	Apr. 28, 2020
JP	2021-035192	Mar. 05, 2021

Related U.S. Application Data

Publication Classification

Int. Cl.: H01J37/32 (20060101)

U.S. Cl.:

CPC H01J37/32422 (20130101); H01J37/32137 (20130101); H01J37/32266 (20130101); H01J37/32715 (20130101); H01J2237/334 (20130101)

Field of Classification Search

CPC: H01J (37/32422)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2003/0215570	12/2002	Seutter	427/255.394	C23C 16/345
2008/0210973	12/2007	Chen et al.	N/A	N/A
2009/0001890	12/2008	Singh et al.	N/A	N/A
2009/0194508	12/2008	Ui et al.	N/A	N/A
2009/0289300	12/2008	Sasaki	257/E27.062	H01L 29/66803
2010/0025821	12/2009	Ohmi et al.	N/A	N/A
2010/0285237	12/2009	Ditizio et al.	N/A	N/A
2011/0014778	12/2010	Klepper et al.	N/A	N/A
2012/0145918	12/2011	Radovanov et al.	N/A	N/A
2013/0052833	12/2012	Ranjan et al.	N/A	N/A
2014/0106571	12/2013	Koo et al.	N/A	N/A
2014/0272182	12/2013	Koo et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2009-187975	12/2008	JP	N/A
2012-104382	12/2011	JP	N/A

Primary Examiner: Chen; Keath T

Attorney, Agent or Firm: Studebaker Brackett PLLC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a Continuation of U.S. patent application Ser. No. 17/232,231 filed Apr. 16, 2021, which is based on and claims the benefit of priority from Japanese Patent Application Nos. 2021-035192, filed on Mar. 5, 2021 and 2020-079517, filed on Apr. 28, 2020, the entire contents of which are incorporated herein by reference.

FIELD

(1) Exemplary embodiments of the present disclosure relate to a plasma processing apparatus and a plasma processing method.

BACKGROUND

(2) A plasma processing apparatus is used in plasma processing on a substrate. The plasma processing apparatus is provided with a chamber and a substrate holding electrode. The substrate holding electrode is provided in the chamber. The substrate holding electrode holds the substrate placed on the principal surface thereof. A type of such plasma processing apparatus is disclosed in Japanese Unexamined Patent Publication No. 2009-187975.

(3) The plasma processing apparatus disclosed in Japanese Unexamined Patent Publication No. 2009-187975 is further provided with a radio frequency generation device and a DC negative pulse generation device. The radio frequency generation device applies a radio frequency voltage to the substrate holding electrode. In the plasma processing apparatus disclosed in Japanese Unexamined Patent Publication No. 2009-187975, the radio frequency voltage is switched on and off alternately. Further, in the plasma processing apparatus disclosed in Japanese Unexamined Patent Publication No. 2009-187975, a DC negative pulse voltage is applied from the DC negative pulse generation device to the substrate holding electrode according to an on/off timing of the radio frequency voltage.

SUMMARY

(4) In an exemplary embodiment, a plasma processing apparatus is provided. The plasma processing apparatus is provided with a chamber, a substrate support, and a power source system. The substrate support has an electrode and configured to support a substrate in the chamber. The power source system is electrically connected to the electrode and configured to apply a bias voltage to the electrode to draw ions from a plasma in the chamber into the substrate on the substrate support. The power source system is configured to output a first pulse to the electrode in a first period and output a second pulse to the electrode in a second period after the first period, as the bias voltage. Each of the first pulse and the second pulse is a pulse of a voltage. A voltage level of the first pulse is different from a voltage level of the second pulse.

(5) The foregoing summary is illustrative only and is not intended to be in any way limiting. In addition to the illustrative aspects, exemplary embodiments, and features described above, further aspects, exemplary embodiments, and features will become apparent by reference to the drawings and the following detailed description.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 schematically illustrates a plasma processing apparatus according to an exemplary embodiment.

(2) FIG. 2 is a timing chart of a bias voltage of a first example.

(3) FIG. 3 is a timing chart of a bias voltage of a second example.

(4) FIG. 4 is a timing chart of a bias voltage of a third example.

(5) FIG. 5 is a timing chart of a bias voltage of a fourth example.

(6) FIG. 6 is a timing chart of a bias voltage of a fifth example.

(7) FIG. 7 illustrates a power source system according to an exemplary embodiment.

(8) FIG. 8 illustrates a power source system according to another exemplary embodiment.

(9) FIG. 9 illustrates a configuration of a substrate support according to another exemplary embodiment.

DETAILED DESCRIPTION

(10) Hereinafter, various exemplary embodiments will be described.

(11) In an exemplary embodiment, a plasma processing apparatus is provided. The plasma processing apparatus is provided with a chamber, a substrate support, and a power source system. The substrate support has an electrode and configured to support a substrate in the chamber. The power source system is electrically connected to the electrode and configured to apply a bias voltage to the electrode to draw ions from a plasma in the chamber into the substrate on the substrate support. The power source system is configured to output a first pulse to the electrode in a first period and output a second pulse to the electrode in a second period after the first period, as the bias voltage. Each of the first pulse and the second pulse is a pulse of a voltage. A voltage level of the first pulse is different from a voltage level of the second pulse.

(12) In the aforementioned embodiment, the voltage level of the first pulse is different from the voltage level of the second pulse. Therefore, energy of ions supplied from the plasma to the substrate in the first period is different from energy of ions supplied from the plasma to the substrate in the second period. Hence, according to the aforementioned embodiment, it is possible to supply ions having different energies to the substrate.

(13) In an exemplary embodiment, the second period may be continuous with the first period. Each of the first pulse and the second pulse may be a pulse of a negative voltage. An absolute value of the voltage level of the first pulse may be smaller than an absolute value of the voltage level of the second pulse.

(14) In an exemplary embodiment, each of the first pulse and the second pulse may be a pulse of a negative voltage. An absolute value of the voltage level of the first pulse may be larger than an absolute value of the voltage level of the second pulse. The power source system may be configured such that an output voltage to the electrode is 0 V in a period between the first period and the second period.

(15) In an exemplary embodiment, the second period may be continuous with the first period. Each of the first pulse and the second pulse may be a pulse of a negative voltage. An absolute value of the voltage level of the first pulse may be larger than an absolute value of the voltage level of the second pulse.

(16) In an exemplary embodiment, the power source system may be configured to output a third pulse to the electrode in a third period after the second period. The third pulse may be a pulse of a negative voltage. An absolute value of a voltage level of the third pulse may be larger than the absolute value of the voltage level of the second pulse.

(17) In an exemplary embodiment, each of the first pulse and the second pulse may be a pulse of a negative voltage. The power source system may be configured to output a pulse of a positive voltage to the electrode before start of the first period within a subsequent cycle of two cycles, each of which includes the first period and the second period. According to the embodiment, electrons are supplied to the substrate when the pulse of the positive voltage is supplied to the electrode of the substrate support. As a result, the amount of positive charges of the substrate is reduced.

(18) In an exemplary embodiment, the power source system may be configured to intermittently output the first pulse to the electrode in the first period. The power source system may be configured to intermittently output the second pulse to the electrode in the second period.

(19) In an exemplary embodiment, each of the first pulse and the second pulse may be a pulse of a negative voltage. The power source system may be configured to alternately output the first pulse and a pulse of a positive voltage to the electrode in the first period. The power source system may be configured to alternately output the second pulse and a pulse of a positive voltage to the electrode in the second period. According to the embodiment, electrons are supplied to the substrate when the pulse of the positive voltage is supplied to the electrode of the substrate support. As a result, the amount of positive charges of the substrate is reduced.

(20) In an exemplary embodiment, the power source system may be configured to output a pulse of a positive voltage to the electrode in a period between the first period and the second period. According to the embodiment, electrons are supplied to the substrate when the pulse of the positive

voltage is supplied to the electrode of the substrate support. As a result, the amount of positive charges of the substrate is reduced.

(21) In another exemplary embodiment, a plasma processing method is provided. The plasma processing method includes preparing a substrate on a substrate support provided in a chamber of a plasma processing apparatus. The substrate support further includes an electrode. The plasma processing method includes outputting a first pulse from a power source system to the electrode in a first period as a bias voltage to draw ions from plasma in the chamber into the substrate. The plasma processing method further includes outputting a second pulse as the bias voltage from the power source system to the electrode in a second period. Each of the first pulse and the second pulse is a pulse of a voltage. A voltage level of the first pulse is different from a voltage level of the second pulse.

(22) In an exemplary embodiment, the second period may be continuous with the first period. Each of the first pulse and the second pulse may be a pulse of a negative voltage. An absolute value of the voltage level of the first pulse may be smaller than an absolute value of the voltage level of the second pulse.

(23) In an exemplary embodiment, each of the first pulse and the second pulse may be a pulse of a negative voltage. An absolute value of the voltage level of the first pulse may be larger than an absolute value of the voltage level of the second pulse. The plasma processing method may further include setting an output voltage from the power source system to the electrode to 0 V in a period between the first period and the second period.

(24) In an exemplary embodiment, the second period may be continuous with the first period. Each of the first pulse and the second pulse may be a pulse of a negative voltage. An absolute value of the voltage level of the first pulse may be larger than an absolute value of the voltage level of the second pulse.

(25) In an exemplary embodiment, the plasma processing method may further include outputting a third pulse from the power source system to the electrode in a third period after the second period. The third pulse may be a pulse of a negative voltage. An absolute value of a voltage level of the third pulse may be larger than the absolute value of the voltage level of the second pulse.

(26) In an exemplary embodiment, the plasma processing method may further include outputting a pulse of a positive voltage from the power source system to the electrode before start of the first period within a subsequent cycle of two cycles, each of which includes the first period and the second period.

(27) In an exemplary embodiment, the first pulse may be intermittently output from the power source system to the electrode in the first period. The second pulse may be intermittently output from the power source system to the electrode in the second period.

(28) In an exemplary embodiment, each of the first pulse and the second pulse may be a pulse of a negative voltage. The plasma processing method may further include intermittently outputting a pulse of a positive voltage from the power source system to the electrode in the first period. The pulse of the positive voltage may be output alternately with the first pulse. The plasma processing method may further include intermittently outputting a pulse of a positive voltage from the power source system to the electrode in the second period. The pulse of the positive voltage may be output alternately with the second pulse.

(29) In an exemplary embodiment, the plasma processing method may further include outputting a pulse of a positive voltage from the power source system to the electrode in a period between the first period and the second period.

(30) Hereinafter, various exemplary embodiments will be described in detail with reference to the drawings. In the drawings, the same or equivalent portions are denoted by the same reference symbols.

(31) FIG. 1 is a diagram schematically showing a plasma processing apparatus according to an exemplary embodiment. A plasma processing apparatus 1 shown in FIG. 1 is a capacitively coupled

plasma processing apparatus. The plasma processing apparatus **1** is provided with a chamber **10**. The chamber **10** provides an internal space **10s** therein. The central axis of the chamber **10** is an axis AX and extends in a vertical direction.

(32) In an embodiment, the chamber **10** may include a chamber body **12**. The chamber body **12** has a substantially cylindrical shape. The internal space **10s** is provided in the chamber body **12**. The chamber body **12** is formed of, for example, aluminum. The chamber body **12** is electrically grounded. A film having plasma resistance is formed on the inner wall surface of the chamber body **12**, that is, a wall surface defining the internal space **10s**. This film may be a film formed by anodization or a ceramic film such as a film formed of yttrium oxide.

(33) A passage **12p** is formed in a side wall of the chamber body **12**. A substrate W passes through the passage **12p** when it is transferred between the internal space **10s** and the outside of the chamber **10**. A gate valve **12g** is provided along the side wall of the chamber body **12** for opening and closing of the passage **12p**.

(34) The plasma processing apparatus **1** is further provided with a substrate support **16**. The substrate support **16** is configured to support the substrate W placed thereon in the chamber **10**. The substrate W has a substantially disk shape. The substrate support **16** is supported by a support **15**. The support **15** extends upward from a bottom portion of the chamber body **12**. The support **15** has a substantially cylindrical shape. The support **15** is formed of an insulating material such as quartz.

(35) The substrate support **16** has a lower electrode **18**. The substrate support **16** may further have an electrostatic chuck **20**. The substrate support **16** may further have an electrode plate **19**. The electrode plate **19** is formed of a conductive material such as aluminum and has a substantially disk shape. The lower electrode **18** is provided on the electrode plate **19**. The lower electrode **18** is formed of a conductive material such as aluminum and has a substantially disk shape. The lower electrode **18** is electrically connected to the electrode plate **19**. The central axes of the lower electrode **18** and the electrode plate **19** substantially coincide with the axis AX.

(36) A flow path **18f** is provided in the lower electrode **18**. The flow path **18f** is a flow path for a heat exchange medium. As the heat exchange medium, for example, a refrigerant is used. A circulation device for the heat exchange medium (for example, a chiller unit) is connected to the flow path **18f**. The circulation device is provided outside the chamber **10**. The heat exchange medium from the circulation device is supplied to the flow path **18f** through a pipe **23a**. The heat exchange medium supplied to the flow path **18f** is returned to the circulation device through a pipe **23b**.

(37) The electrostatic chuck **20** is provided on the lower electrode **18**. When the substrate W is processed in the internal space **10s**, the substrate W is placed on the electrostatic chuck **20** such that the center thereof is located on the axis AX. The electrostatic chuck **20** is configured to hold the substrate. The electrostatic chuck **20** has a main body and an electrode. The main body of the electrostatic chuck **20** is formed of a dielectric such as aluminum oxide or aluminum nitride. The main body of the electrostatic chuck **20** has a substantially disk shape. The central axis of the electrostatic chuck **20** substantially coincides with the axis AX.

(38) The electrode of the electrostatic chuck **20** is provided in the main body of the electrostatic chuck **20**. The electrode of the electrostatic chuck **20** has a film formed of a conductor. A direct-current power source is electrically connected to the electrode of the electrostatic chuck **20**. When a direct-current voltage is applied from the direct-current power source to the electrode of the electrostatic chuck **20**, an electrostatic attraction force is generated between the electrostatic chuck **20** and the substrate W. Due to the generated electrostatic attraction force, the substrate W is attracted to the electrostatic chuck **20** and held by the electrostatic chuck **20**.

(39) The substrate support **16** may further support an edge ring ER that is mounted thereon. The edge ring ER has a ring shape and is formed of, for example, silicon or silicon carbide. The edge ring ER is mounted on the substrate support **16** such that the central axis thereof is located on the axis AX. In an embodiment, the edge ring ER may be partially mounted on the electrostatic chuck

20. The substrate **W** is disposed on the electrostatic chuck **20** and in a region surrounded by the edge ring **ER**.

(40) The plasma processing apparatus **1** may be further provided with a gas supply line **25**. The gas supply line **25** supplies a heat transfer gas, for example, a He gas, from a gas supply mechanism to a gap between the upper surface of the electrostatic chuck **20** and the rear surface (lower surface) of the substrate **W**.

(41) The plasma processing apparatus **1** may be further provided with a tubular part **28** and an insulating part **29**. The tubular part **28** extends upward from the bottom portion of the chamber body **12**. The tubular part **28** extends along the outer periphery of the support **15**. The tubular part **28** is formed of a conductive material and has a substantially cylindrical shape. The tubular part **28** is electrically grounded. The insulating part **29** is provided on the tubular part **28**. The insulating part **29** is formed of an insulating material. The insulating part **29** is formed of ceramic such as quartz, for example. The insulating part **29** has a substantially cylindrical shape. The insulating part **29** extends along the outer periphery of the electrode plate **19**, the outer periphery of the lower electrode **18**, and the outer periphery of the electrostatic chuck **20**.

(42) The plasma processing apparatus **1** is further provided with an upper electrode **30**. The upper electrode **30** is provided above the substrate support **16**. The upper electrode **30** closes an upper opening of the chamber body **12** together with a member **32**. The member **32** is formed of an insulating material. The upper electrode **30** is supported on an upper portion of the chamber body **12** through the member **32**.

(43) The upper electrode **30** may include a ceiling plate **34** and a support **36**. The lower surface of the ceiling plate **34** defines the internal space **10s**. A plurality of gas discharge holes **34a** are formed in the ceiling plate **34**. The plurality of gas discharge holes **34a** penetrate the ceiling plate **34** in a plate thickness direction (the vertical direction). The ceiling plate **34** is formed of, for example, silicon. Alternatively, the ceiling plate **34** may have a structure in which a plasma-resistant film is provided on the surface of a member made of aluminum. This film may be a film formed by anodization or a ceramic film such as a film formed of yttrium oxide.

(44) The support **36** detachably supports the ceiling plate **34**. The support **36** is formed of a conductive material such as aluminum. A gas diffusion chamber **36a** is provided in the interior of the support **36**. A plurality of gas holes **36b** extend downward from the gas diffusion chamber **36a**. The plurality of gas holes **36b** communicate with the plurality of gas discharge holes **34a**, respectively. The support **36** has a gas introduction port **36c** formed therein. The gas introduction port **36c** is connected to the gas diffusion chamber **36a**. A gas supply pipe **38** is connected to the gas introduction port **36c**.

(45) A gas source group **40** is connected to the gas supply pipe **38** through a valve group **41**, a flow rate controller group **42**, and a valve group **43**. The gas source group **40**, the valve group **41**, the flow rate controller group **42**, and the valve group **43** configure a gas supply unit. The gas source group **40** includes a plurality of gas sources. Each of the valve group **41** and the valve group **43** includes a plurality of valves (for example, on-off valves). The flow rate controller group **42** includes a plurality of flow rate controllers. Each of the plurality of flow rate controllers of the flow rate controller group **42** is a mass flow controller or a pressure control type flow rate controller. Each of the plurality of gas sources of the gas source group **40** is connected to the gas supply pipe **38** through a corresponding valve of the valve group **41**, a corresponding flow rate controller of the flow rate controller group **42**, and a corresponding valve of the valve group **43**. The plasma processing apparatus **1** can supply gases from one or more gas sources selected from the plurality of gas sources of the gas source group **40** to the internal space **10s** at individually adjusted flow rates.

(46) A baffle member **48** is provided between the tubular part **28** and the side wall of the chamber body **12**. The baffle member **48** may be a plate-shaped member. The baffle member **48** may be configured, for example, by coating a plate member made of aluminum with ceramic such as

yttrium oxide. A plurality of through-holes are formed in the baffle member **48**. An exhaust pipe **52** is connected to the bottom portion of the chamber body **12** below the baffle member **48**. An exhaust device **50** is connected to the exhaust pipe **52**. The exhaust device **50** has a pressure controller such as an automatic pressure control valve, and a vacuum pump such as a turbo molecular pump, and is capable of reducing the pressure in the internal space **10s**.

(47) The plasma processing apparatus **1** is further provided with a radio frequency power source **61**. The radio frequency power source **61** is a power source that generates first radio frequency power for plasma generation. The frequency of the first radio frequency power is a frequency within the range of 27 to 100 MHz, for example, a frequency of 40 MHz or 60 MHz. The radio frequency power source **61** is connected to the lower electrode **18** through a matcher **61m** and the electrode plate **19**. The matcher **61m** has a matching circuit for matching the impedance on the load side (the lower electrode **18** side) of the radio frequency power source **61** with the output impedance of the radio frequency power source **61**. The radio frequency power source **61** does not need to be electrically connected to the lower electrode **18**, and may be connected to the upper electrode **30** through the matcher **61m**.

(48) The plasma processing apparatus **1** may be further provided with a radio frequency power source **62**. The radio frequency power source **62** is a power source that generates second radio frequency power. The frequency of the second radio frequency power is lower than the frequency of the first radio frequency power. The radio frequency power source **62** is connected to the lower electrode **18** through a matcher **62m** and the electrode plate **19**. The matcher **62m** has a matching circuit for matching the impedance on the load side (the lower electrode **18** side) of the radio frequency power source **62** with the output impedance of the radio frequency power source **62**. The plasma processing apparatus **1** does not need to include the radio frequency power source **62** and the matcher **62m**.

(49) In the plasma processing apparatus **1**, a gas is supplied from the gas supply unit to the internal space **10s**. Then, the radio frequency power is supplied, whereby the gas is excited in the internal space **10s**. As a result, plasma is generated in the internal space **10s**. The substrate **W** is processed with chemical species such as ions and/or radicals from the plasma.

(50) The plasma processing apparatus **1** is further provided with a power source system **70**. The power source system **70** is electrically connected to the lower electrode **18**. The power source system **70** is configured to apply a bias voltage to the lower electrode **18** to draw ions from the plasma into the substrate on the substrate support **16**. The power source system **70** may be connected to the lower electrode **18** through a filter **70f**. The filter **70f** includes a filter circuit that cuts off or reduces the radio frequency power toward the power source system **70**. The details of the power source system **70** will be described later.

(51) The plasma processing apparatus **1** may be further provided with a controller **MC**. The controller **MC** is a computer which includes a processor, a storage device, an input device, a display device, and the like, and controls each part of the plasma processing apparatus **1**. Specifically, the controller **MC** executes a control program stored in the storage device and controls each part of the plasma processing apparatus **1**, based on recipe data stored in the storage device. A process designated by the recipe data is executed in the plasma processing apparatus **1** under the control by the controller **MC**. Plasma processing methods according to various embodiments may be performed in the plasma processing apparatus **1** under the control of each part of the plasma processing apparatus **1** by the controller **MC**.

(52) Hereinafter, the bias voltage that is generated by the power source system **70** will be described with reference to FIGS. **2** to **6**. FIGS. **2** to **6** are timing charts of the bias voltages of first to fifth examples, respectively. Further, the plasma processing methods according to various exemplary embodiments will also be described below.

(53) In various exemplary embodiments, the plasma processing method includes a step of preparing the substrate **W** on the substrate support **16**. The plasma processing method is performed in a state

where the substrate W is placed on the substrate support **16**.

(54) The plasma processing method includes a step of generating plasma in the chamber **10**. A processing gas is supplied from the gas supply unit into the chamber **10** in order to generate plasma. Further, the pressure of the gas in the chamber **10** is adjusted by the exhaust device **50** to a designated pressure. Further, the first radio frequency power is supplied from the radio frequency power source **61**. As a result, plasma is generated from the processing gas in the chamber **10**. The second radio frequency power from the radio frequency power source **62** may be supplied to the lower electrode **18** during the generation of the plasma. The steps of the plasma processing method that are described below are executed in a period in which the plasma is being generated in the chamber **10**.

(55) The plasma processing method includes a step of outputting a first pulse PL1 as the bias voltage from the power source system **70** to the lower electrode **18** in a first period P1, as shown in FIGS. 2 to 6. The first pulse PL1 is a pulse of a voltage. The first pulse PL1 may be a pulse of a direct-current voltage. The first pulse PL1 may have a waveform other than a rectangular wave such as a triangular wave or an impulse wave. The first pulse may have a waveform whose voltage value changes at the leading and trailing edges thereof.

(56) The plasma processing method includes a step of outputting a second pulse PL2 as the bias voltage from the power source system **70** to the lower electrode **18** in a second period P2, as shown in FIGS. 2 to 6. The second period P2 is a period after the first period P1. The second pulse PL2 is a pulse of a voltage. The voltage level of the first pulse PL1 is different from the voltage level of the second pulse PL2. The second pulse PL2 may be a pulse of a direct-current voltage. The second pulse PL2 may have a waveform other than a rectangular wave such as a triangular wave or an impulse wave. The second pulse may have a waveform whose voltage value changes at the leading and trailing edges thereof.

(57) In each of the examples shown in FIGS. 2 to 6, each of the first pulse PL1 and the second pulse PL2 is a pulse of a negative voltage (for example, a negative direct-current voltage). The difference between the voltage level of one (hereinafter referred to as an “H-level pulse”) of the first pulse PL1 and the second pulse PL2 and the reference level (for example, 0 V) may be 6 kV or more. The difference between the voltage level of the H-level pulse and the reference level may be 10 kV or 20 kV or more. The difference between the voltage level of the other (hereinafter referred to as an “L-level pulse”) of the first pulse PL1 and the second pulse PL2 and the reference level (for example, 0 V) may be 5 kV or less.

(58) In the plasma processing method, as shown in FIGS. 2 to 6, a cycle CY may be repeated. The cycle CY includes the first period P1 and the second period P2. In the first to third examples shown in FIGS. 2 to 4, the frequency defining the cycle CY may be a frequency of 100 kHz or more and 1 MHz or less. In the fourth and fifth examples shown in FIGS. 5 and 6, the frequency defining the cycle CY may be 0.2 Hz or more and 1 Hz or less.

(59) In an embodiment, as in the first example shown in FIG. 2, the second period P2 may be continuous with the first period P1. In this embodiment, the absolute value of the voltage level of the first pulse PL1 may be smaller than the absolute value of the voltage level of the second pulse PL2.

(60) In the first example shown in FIG. 2, the reference level of the bias voltage is 0 V. This reference level may have a positive or negative value. In the first example, each of the voltage level of the first pulse PL1 and the voltage level of the second pulse PL2 may have any value, as long as the difference between the reference level and the voltage level of the first pulse PL1 is smaller than the difference between the reference level and the voltage level of the second pulse PL2. That is, in the first example, each of the voltage level of the first pulse PL1 and the voltage level of the second pulse PL2 may have any value, as long as the voltage level of the second pulse PL2 is lower than the voltage level of the first pulse PL1.

(61) In another embodiment, as in the second example shown in FIG. 3, the absolute value of the

voltage level of the first pulse PL1 may be larger than the absolute value of the voltage level of the second pulse PL2. In this embodiment, the plasma processing method may further include a step of setting the output voltage from the power source system 70 to the lower electrode 18 to 0 V in a period PG1 between the first period P1 and the second period P2.

(62) Also in the second example shown in FIG. 3, the reference level of the bias voltage is 0 V. This reference level may have a positive or negative value. In the second example, each of the voltage level of the first pulse PL1 and the voltage level of the second pulse PL2 may have any value, as long as the difference between the reference level and the voltage level of the first pulse PL1 is larger than the difference between the reference level and the voltage level of the second pulse PL2. That is, in the second example, each of the voltage level of the first pulse PL1 and the voltage level of the second pulse PL2 may have any value, as long as the voltage level of the first pulse PL1 is lower than the voltage level of the second pulse PL2.

(63) In still another embodiment, as in the third example shown in FIG. 4, the second period P2 may be continuous with the first period P1. In this embodiment, the absolute value of the voltage level of the first pulse PL1 may be larger than the absolute value of the voltage level of the second pulse PL2.

(64) In still another embodiment, as in the third example shown in FIG. 4, the plasma processing method may further include a step of outputting a third pulse PL3 from the power source system 70 to the lower electrode 18 in a third period P3 after the second period P2. The third pulse PL3 may be a pulse of a negative voltage, and the absolute value of the voltage level of the third pulse PL3 may be larger than the absolute value of the voltage level of the second pulse PL2. The absolute value of the voltage level of the third pulse PL3 may be the same as the absolute value of the voltage level of the first pulse PL1. That is, the third pulse PL3 may be an H-level pulse. The difference between the voltage level of the third pulse PL3 and the reference level (for example, 0 V) may be 6 kV or more. The difference between the voltage level of the third pulse PL3 and the reference level may be 10 kV or 20 kV or more.

(65) Also in the third example shown in FIG. 4, the reference level of the bias voltage is 0 V. This reference level may have a positive or negative value. In the third example, each of the voltage level of the first pulse PL1 and the voltage level of the second pulse PL2 may have any value, as long as the difference between the reference level and the voltage level of the first pulse PL1 is larger than the difference between the reference level and the voltage level of the second pulse PL2. That is, in the third example, each of the voltage level of the first pulse PL1 and the voltage level of the second pulse PL2 may have any value, as long as the voltage level of the first pulse PL1 is lower than the voltage level of the second pulse PL2. Further, in the third example, each of the voltage level of the third pulse PL3 and the voltage level of the second pulse PL2 may have any value, as long as the difference between the reference level and the voltage level of the third pulse PL3 is larger than the difference between the reference level and the voltage level of the second pulse PL2. That is, in the third example, each of the voltage level of the third pulse PL3 and the voltage level of the second pulse PL2 may have any value, as long as the voltage level of the third pulse PL3 is lower than the voltage level of the second pulse PL2.

(66) In still another embodiment, the plasma processing method may further include a step of outputting a pulse PPL of a positive voltage, as in the first to third examples shown in FIGS. 2 to 4. The voltage level of the pulse PPL of the voltage is higher than the reference level (for example, 0 V). The pulse PPL of the voltage may be a pulse of a positive direct-current voltage. The pulse PPL is output in a period PP. The period PP is a period before the start of the first period P1 in the subsequent cycle CY of any two consecutive cycles CY. The period PP may be a period immediately before the subsequent first period P1. In this case, it becomes possible to supply ions having high energy to the substrate W in the subsequent first period P1.

(67) In the first example shown in FIG. 2, the period PP is a period after a period PG. In the first example shown in FIG. 2, the period PG is a period after the second period P2. In the first example

shown in FIG. 2, in the period PG, the output voltage from the power source system 70 to the lower electrode 18 is set to 0 V (that is, the reference level).

(68) In the second example shown in FIG. 3, the period PP is a period after a period PG2. In the second example shown in FIG. 3, the period PG2 is a period after the second period P2. In the second example shown in FIG. 3, in the period PG2, the output voltage from the power source system 70 to the lower electrode 18 is set to 0 V.

(69) In the third example shown in FIG. 4, the period PP is a period after the period PG. In the third example shown in FIG. 4, the period PG is a period after the third period P3. In the third example shown in FIG. 4, in the period PG, the output voltage from the power source system 70 to the lower electrode 18 is set to 0 V (for example, the reference level).

(70) In still another embodiment, as in the fourth example shown in FIG. 5 and the fifth example shown in FIG. 6, the first pulse PL1 may be intermittently output from the power source system 70 to the lower electrode 18 in the first period P1. The first pulse PL1 may be periodically output from the power source system 70 to the lower electrode 18 in the first period P1. The first pulse PL1 is output in sub-periods SP1 within the first period P1. The first pulse PL1 may be periodically output at a frequency of 100 kHz or more and 1 MHz or less.

(71) In still another embodiment, as in the fourth example shown in FIG. 5 and the fifth example shown in FIG. 6, the second pulse PL2 may be intermittently output from the power source system 70 to the lower electrode 18 in the second period P2. The second pulse PL2 may be periodically output from the power source system 70 to the lower electrode 18 in the second period P2. The second pulse PL2 is output in sub-periods SP2 within the second period P2. The second pulse PL2 may be periodically output at a frequency of 100 kHz or more and 1 MHz or less.

(72) In the fourth example shown in FIG. 5 and the fifth example shown in FIG. 6, the absolute value of the voltage level of the first pulse PL1 is larger than the absolute value of the voltage level of the second pulse PL2. The absolute value of the voltage level of the first pulse PL1 may be smaller than the absolute value of the voltage level of the second pulse PL2.

(73) Also in the fourth example shown in FIG. 5, the reference level of the bias voltage is 0 V. This reference level may have a positive or negative value. In the fourth example, each of the voltage level of the first pulse PL1 and the voltage level of the second pulse PL2 may have any value, as long as the difference between the reference level and the voltage level of the first pulse PL1 is different from the difference between the reference level and the voltage level of the second pulse PL2.

(74) In still another embodiment, the plasma processing method may further include a step of intermittently outputting a pulse PPL1 of a positive voltage from the power source system 70 to the lower electrode 18 in the first period P1, as in the fourth example shown in FIG. 5. The voltage level of the pulse PPL1 of the voltage is higher than the reference level (for example, 0 V). The pulse PPL1 of the voltage may be a pulse of a positive direct-current voltage. In this embodiment, the pulse PPL1 of the positive voltage may be output alternately with the first pulse PL1. The pulse PPL1 of the positive voltage is output in periods SPP1. The periods SPP1 may be periods after the respective periods SPG1. The periods SPG1 are periods after the respective sub-periods SP1. In the periods SPG1, the output voltage from the power source system 70 to the lower electrode 18 may be set to 0 V (that is, the reference level). The periods SPP1 may be periods immediately before the respective subsequent sub-periods SP1. In this case, it becomes possible to supply ions having high energy to the substrate W in the subsequent sub-periods SP1.

(75) In still another embodiment, the plasma processing method may further include a step of intermittently outputting a pulse PPL2 of a positive voltage from the power source system 70 to the lower electrode 18 in the second period P2, as in the fourth example shown in FIG. 5. The voltage level of the pulse PPL2 of the voltage is higher than the reference level (for example, 0 V). The pulse PPL2 of the voltage may be a pulse of a positive direct-current voltage. In this embodiment, the pulse PPL2 of the positive voltage may be output alternately with the second pulse PL2. The

pulse PPL2 of the positive voltage is output in periods SPP2. The periods SPP2 may be periods after the respective periods SPG2. The periods SPG2 is periods after the respective sub-periods SP2. In the periods SPG2, the output voltage from the power source system 70 to the lower electrode 18 may be set to 0 V (that is, the reference level). The periods SPP2 may be periods immediately before the respective subsequent sub-periods SP2. In this case, it becomes possible to supply ions having high energy to the substrate W in the subsequent sub-period SP2.

(76) In still another embodiment, the plasma processing method may further include a step of outputting the pulse PPL1 of the positive voltage from the power source system 70 to the lower electrode 18 in the period SPP1 between the first period P1 and the second period P2, as in the fifth example shown in FIG. 6. The voltage level of the pulse PPL1 of the voltage is higher than the reference level (for example, 0 V). The pulse PPL1 of the voltage may be a pulse of a positive direct-current voltage. The period SPP1 may be a period immediately before the subsequent sub-period SP2. In this case, it becomes possible to supply ions having high energy to the substrate W in the subsequent sub-period SP2.

(77) In still another embodiment, the plasma processing method may further include a step of outputting the pulse PPL2 of the positive voltage from the power source system 70 to the lower electrode 18 in the period SPP2, as in the fifth example shown in FIG. 6. The voltage level of the pulse PPL2 of the voltage is higher than the reference level (for example, 0 V). The pulse PPL2 of the voltage may be a pulse of a positive direct-current voltage. The period SPP2 may be a period between the second period P2 and the subsequent first period P1. The period SPP2 may be a period immediately before the subsequent sub-period SP1. In this case, it becomes possible to supply ions having high energy to the substrate W in the subsequent sub-period SP1.

(78) Also in the fifth example shown in FIG. 6, the reference level of the bias voltage is 0 V. This reference level may have a positive or negative value. In the fifth example, each of the voltage level of the first pulse PL1 and the voltage level of the second pulse PL2 may have any value, as long as the difference between the reference level and the voltage level of the first pulse PL1 is different from the difference between the reference level and the voltage level of the second pulse PL2.

(79) In the various exemplary embodiments described above, the energy of the ions that are supplied from the plasma to the substrate W in the first period P1 and the energy of the ions that are supplied from the plasma to the substrate W in the second period P2 are different. Therefore, it becomes possible to supply ions having different energies to the substrate W.

(80) Further, in some exemplary embodiments, the pulse of the positive direct-current voltage is supplied to the lower electrode 18. The pulse of the positive direct-current voltage is supplied to the lower electrode 18, whereby electrons are supplied to the substrate W. As a result, the amount of positive charges of the substrate W is reduced.

(81) In a case of forming an opening in the substrate W by etching a film of the substrate W by using the bias voltage of each of the first to third examples, in the period in which the L-level pulse is supplied, deposits on the substrate W are removed, so that the shape of the opening can be adjusted. Further, in this case, ions can be supplied to the bottom of a deep opening in the period in which the H-level pulse is supplied.

(82) The bias voltages of the fourth and fifth examples can be used for etching of a multilayer film having different types of films. The bias voltages of the fourth and fifth examples can be used for etching in the manufacture of a NAND device, for example. In the manufacture of the NAND device, a multilayer film including alternately laminated layers of a silicon oxide film and a silicon nitride film or a polycrystalline silicon film are etched. The silicon oxide film can be etched with ions having relatively high energy, and the silicon nitride film or the polycrystalline silicon film can be etched with ions having relatively low energy. In a case of using the bias voltages of the fourth and fifth examples, the silicon oxide film may be etched in the first period P1 and the silicon nitride film or the polycrystalline silicon film may be etched in the second period P2.

(83) Hereinafter, power source systems according to some exemplary embodiments that can be adopted as the power source system **70** of the plasma processing apparatus **1** will be described.

(84) FIG. **7** is a diagram showing a power source system according to an exemplary embodiment. A power source system **70A** shown in FIG. **7** can be adopted as the power source system **70** of the plasma processing apparatus **1**. The power source system **70A** can output the bias voltages of the first to fifth examples described above. The power source system **70A** may include a direct-current power source **71**, a pulse unit **72**, and a pulse controller PC.

(85) The direct-current power source **71** is a power source that generates a negative direct-current voltage. The positive terminal of the direct-current power source **71** is connected to the ground. The direct-current power source **71** may be a variable direct-current power source.

(86) The pulse unit **72** is configured to generate a pulse of a voltage from the negative direct-current voltage from the direct-current power source **71**. In an embodiment, the pulse unit **72** may include one or more switching transistors **72a**, one or more switching transistors **72b**, a diode **72c**, and a diode **72d**.

(87) The one or more switching transistors **72a** are connected between the positive terminal of the direct-current power source **71** and a node **721**. In a case where the pulse unit **72** includes a plurality of switching transistors **72a**, these switching transistors **72a** are connected in series between the positive terminal of the direct-current power source **71** and the node **721**.

(88) The one or more switching transistors **72b** are connected between the negative terminal of the direct-current power source **71** and the node **721**. In a case where the pulse unit **72** includes a plurality of switching transistors **72b**, these switching transistors **72b** are connected in series between the negative terminal of the direct-current power source **71** and the node **721**.

(89) The diode **72c** is connected in parallel with the one or more switching transistors **72a**. The diode **72c** is connected between the positive terminal of the direct-current power source **71** and a node **722**. The cathode of the diode **72c** is connected to the positive terminal of the direct-current power source **71**, and the anode of the diode **72c** is connected to the node **722**. The node **722** is connected to the node **721**.

(90) The diode **72d** is connected in parallel with the one or more switching transistors **72b**. The diode **72d** is connected between the negative terminal of the direct-current power source **71** and the node **722**. The anode of the diode **72d** is connected to the negative terminal of the direct-current power source **71**, and the cathode of the diode **72d** is connected to the node **722**.

(91) The pulse controller PC is configured to set an output period of the pulse of the voltage from the pulse unit **72** by supplying a control signal to the pulse unit **72**. In an embodiment, the pulse controller PC supplies a pulse control signal as the control signal to the control terminals of the one or more switching transistors **72a** and the control terminals of the one or more switching transistors **72b**.

(92) When the one or more switching transistors **72a** enter a closed state and the one or more switching transistors **72b** enter an open state by the pulse control signal from the pulse controller PC, the node **722** is connected to the ground. As a result, the output voltage of the power source system **70A** becomes 0 V (that is, the reference level).

(93) When the one or more switching transistors **72a** enter an open state and the one or more switching transistors **72b** enter a closed state by the pulse control signal from the pulse controller PC, the node **722** is connected to the negative terminal of the direct-current power source **71**. As a result, a pulse of a negative voltage (for example, a negative direct-current voltage) is output from the power source system **70A**. Each of the first pulse, the second pulse, and the third pulse described above is generated by adjusting the voltage level of the pulse that is output from the node **722** by adjusting the output voltage level of the direct-current power source **71**.

(94) In an embodiment, the power source system **70A** may further include a direct-current power source **73** and a pulse unit **74**. The direct-current power source **73** is a power source that generates a positive direct-current voltage. The negative terminal of the direct-current power source **73** is

connected to the ground. The direct-current power source **73** may be a variable direct-current power source.

(95) The pulse unit **74** is configured to generate a pulse of a voltage from the positive direct-current voltage from the direct-current power source **73**. In an embodiment, the pulse unit **74** may include one or more switching transistors **74a**, one or more switching transistors **74b**, a diode **74c**, and a diode **74d**.

(96) The one or more switching transistors **74a** are connected between the positive terminal of the direct-current power source **73** and a node **741**. In a case where the pulse unit **74** includes a plurality of switching transistors **74a**, these switching transistors **74a** are connected in series between the positive terminal of the direct-current power source **73** and the node **741**.

(97) The one or more switching transistors **74b** are connected between the negative terminal of the direct-current power source **73** and the node **741**. In a case where the pulse unit **74** includes a plurality of switching transistors **74b**, these switching transistors **74b** are connected in series between the negative terminal of the direct-current power source **73** and the node **741**.

(98) The diode **74c** is connected in parallel with the one or more switching transistors **74a**. The diode **74c** is connected between the positive terminal of the direct-current power source **73** and a node **742**. The cathode of the diode **74c** is connected to the positive terminal of the direct-current power source **73**, and the anode of the diode **74c** is connected to the node **742**. The node **742** is connected to the node **741**.

(99) The diode **74d** is connected in parallel with the one or more switching transistors **74b**. The diode **74d** is connected between the negative terminal of the direct-current power source **73** and the node **742**. The anode of the diode **74d** is connected to the negative terminal of the direct-current power source **73**, and the cathode of the diode **74d** is connected to the node **742**.

(100) The pulse controller PC is configured to set an output period of the pulse of the voltage from the pulse unit **74** by supplying a control signal to the pulse unit **74**. In an embodiment, the pulse controller PC supplies a pulse control signal as the control signal to the control terminals of the one or more switching transistors **74a** and the control terminals of the one or more switching transistors **74b**.

(101) When the one or more switching transistors **74a** enter an open state and the one or more switching transistors **74b** enter a closed state by the pulse control signal from the pulse controller PC, the node **742** is connected to the ground. As a result, the output voltage of the power source system **70A** becomes 0 V (that is, the reference level).

(102) When the one or more switching transistors **74a** enter a closed state and the one or more switching transistors **74b** enter an open state by the pulse control signal from the pulse controller PC, the node **742** is connected to the positive terminal of the direct-current power source **73**. As a result, a pulse of a positive voltage (for example, a positive direct-current voltage) is output from the power source system **70A**.

(103) When the pulse of the negative voltage is output from the power source system **70A**, the one or more switching transistors **74a** and the one or more switching transistors **74b** may be set to an open state. Further, when the pulse of the positive voltage is output from the power source system **70A**, the one or more switching transistors **72a** and the one or more switching transistors **72b** may be set to an open state.

(104) In an embodiment, the pulse controller PC may supply the pulse control signal to the radio frequency power source **61** and/or the radio frequency power source **62**. The radio frequency power source **61** may output the pulse of the first radio frequency power according to the pulse control signal. The pulse of the first radio frequency power may be output in the same phase as, or may be output in a different phase from, the pulse of the direct-current voltage that is output from the power source system **70A**. The radio frequency power source **62** may output the pulse of the second radio frequency power according to the pulse control signal. The pulse of the second radio frequency power may be output in the same phase as, or may be output in a different phase from,

the pulse of the direct-current voltage that is output from the power source system **70A**. The radio frequency power source **61** may output a continuous wave of the first radio frequency power. Further, the radio frequency power source **62** may output a continuous wave of the second radio frequency power.

(105) Hereinafter, FIG. **8** will be referred to. FIG. **8** is a diagram showing a power source system according to another exemplary embodiment. A power source system **70B** shown in FIG. **8** can be adopted as the power source system **70** of the plasma processing apparatus **1**. The power source system **70B** can output the bias voltages of the first to fifth examples described above. Hereinafter, the differences between the power source system **70B** and the power source system **70A** will be described.

(106) The pulse unit **72** of the power source system **70B** further includes a switching transistor **72e**. The switching transistor **72e** is connected between the node **722** and a node **701**. The node **701** is connected to the lower electrode **18**.

(107) The switching transistor **72e** switches between an open state and a closed state according to the control signal (pulse control signal) that is supplied from the pulse controller PC to the control terminal thereof. When the switching transistor **72e** is in an open state, the pulse unit **72** is electrically separated from the node **701** and the lower electrode **18**. When the switching transistor **72e** is in a closed state, the pulse unit **72** is connected to the node **701** and the lower electrode **18**, and a pulse of a negative voltage is output from the pulse unit **72** to the lower electrode **18**. The pulse of the negative voltage that is output from the pulse unit **72** to the lower electrode **18** is used as one of the first pulse PL**1** and the second pulse PL**2**. In a case where the pulse unit **72** outputs the first pulse PL**1**, the pulse unit **72** may further output the third pulse PL**3**.

(108) The power source system **70B** further includes a direct-current power source **75** and a pulse unit **76**. The direct-current power source **75** is a power source that generates a negative direct-current voltage. The positive terminal of the direct-current power source **75** is connected to the ground. The direct-current power source **75** may be a variable direct-current power source. The level of the negative direct-current voltage that is generated by the direct-current power source **75** is different from the level of the negative direct-current voltage that is generated by the direct-current power source **71**.

(109) The pulse unit **76** is configured to generate a pulse of a voltage from the negative direct-current voltage from the direct-current power source **75**. In an embodiment, the pulse unit **76** may include one or more switching transistors **76a**, one or more switching transistors **76b**, a diode **76c**, a diode **76d**, and a switching transistors **76e**.

(110) The one or more switching transistors **76a** are connected between the positive terminal of the direct-current power source **75** and a node **761**. In a case where the pulse unit **76** includes a plurality of switching transistors **76a**, these switching transistors **76a** are connected in series between the positive terminal of the direct-current power source **75** and the node **761**.

(111) The one or more switching transistors **76b** are connected between the negative terminal of the direct-current power source **75** and the node **761**. In a case where the pulse unit **76** includes a plurality of switching transistors **76b**, these switching transistors **76b** are connected in series between the negative terminal of the direct-current power source **75** and the node **761**.

(112) The diode **76c** is connected in parallel with the one or more switching transistors **76a**. The diode **76c** is connected between the positive terminal of the direct-current power source **75** and a node **762**. The cathode of the diode **76c** is connected to the positive terminal of the direct-current power source **75**, and the anode of the diode **76c** is connected to the node **762**. The node **762** is connected to the node **761**. The node **762** is connected to the node **701** through the switching transistor **76e**. That is, the switching transistor **76e** is connected between the node **762** and the node **701**.

(113) The diode **76d** is connected in parallel with the one or more switching transistors **76b**. The diode **76d** is connected between the negative terminal of the direct-current power source **75** and the

node **762**. The anode of the diode **76d** is connected to the negative terminal of the direct-current power source **75**, and the cathode of the diode **76d** is connected to the node **762**.

(114) In the power source system **70B**, the pulse controller PC is configured to set an output period of the pulse of the voltage from the pulse unit **76** by supplying a control signal to the pulse unit **76**. In an embodiment, the pulse controller PC supplies a pulse control signal as the control signal to the control terminals of the one or more switching transistors **76a** and the control terminals of the one or more switching transistors **76b**.

(115) Further, in the power source system **70B**, the pulse controller PC is configured to supply the pulse control signal to the control terminal of the switching transistor **76e**. The switching transistor **76e** switches between an open state and a closed state according to the pulse control signal that is supplied from the pulse controller PC to the control terminal thereof.

(116) When the switching transistor **76e** is in an open state, the pulse unit **76** is electrically separated from the node **701** and the lower electrode **18**. When the switching transistor **76e** is in a closed state, the pulse unit **76** is connected to the node **701** and the lower electrode **18**.

(117) When the one or more switching transistors **76a** enter a closed state and the one or more switching transistors **76b** enter an open state by the pulse control signal from the pulse controller PC, the node **762** is connected to the ground. As a result, the voltage in the node **762** becomes 0 V (that is, the reference level).

(118) When the one or more switching transistors **76a** enter an open state and the one or more switching transistors **76b** enter a closed state by the pulse control signal from the pulse controller PC, the node **762** is connected to the negative terminal of the direct-current power source **75**.

(119) When the pulse unit **76** is connected to the node **701** and the node **762** is connected to the negative terminal of the direct-current power source **75**, a pulse of a negative voltage (for example, a negative direct-current voltage) is output from the pulse unit **76**. The pulse of the negative voltage that is output from the pulse unit **76** to the lower electrode **18** is used as the other of the first pulse PL1 and the second pulse PL2. In a case where the pulse unit **76** outputs the first pulse PL1, the pulse unit **76** may further output the third pulse PL3.

(120) Hereinafter, FIG. **9** will be referred to. FIG. **9** is a diagram showing a configuration of a substrate support according to another exemplary embodiment. A substrate support **16A** shown in FIG. **9** can be adopted in place of the substrate support **16** in the plasma processing apparatus **1**.

(121) The substrate support **16A** has a lower electrode **18A** and an electrostatic chuck **20A**. The lower electrode **18A** is formed of a conductive material such as aluminum and has a substantially disk shape. The radio frequency power source **61** may be connected to the lower electrode **18A** through the matcher **61m**. As described above, the radio frequency power source **61** may be connected to the upper electrode **30** through the matcher **61m**.

(122) The electrostatic chuck **20A** is provided on the lower electrode **18A**. The electrostatic chuck **20A** has a dielectric portion **20d** and an electrode **21a**. The electrostatic chuck **20A** may further have an electrode **22a** and an electrode **22b**. When the substrate W is processed in the internal space **10s**, the substrate W is placed on the electrostatic chuck **20A** and held by the electrostatic chuck **20A**. Further, the edge ring ER is mounted on the substrate support **16A**. The edge ring ER is mounted on the substrate support **16A** such that the central axis thereof coincides with the axis AX. The substrate W accommodated in the chamber **10** is disposed on the electrostatic chuck **20A** and in the region surrounded by the edge ring ER.

(123) The substrate support **16A** has a first region **21** and a second region **22**. In FIG. **9**, the boundary between the first region **21** and the second region **22** is shown by a broken line. The first region **21** is a central region of the substrate support **16A**. The first region **21** includes a central region of the electrostatic chuck **20A** and a central region of the lower electrode **18A**. The second region **22** extends in a circumferential direction on the outside in a radial direction with respect to the first region **21**. The second region **22** includes a peripheral region of the electrostatic chuck **20A** and a peripheral region of the lower electrode **18A**. The electrostatic chuck of the first region **21**

and the electrostatic chuck of the second region **22** may be provided by a single electrostatic chuck. That is, the electrostatic chuck of the first region **21** and the electrostatic chuck of the second region **22** may be integrated. In another embodiment, the electrostatic chuck of the first region **21** and the electrostatic chuck of the second region **22** may be separate electrostatic chucks.

(124) The first region **21** is configured to support the substrate **W** that is placed thereon (that is, on the upper surface thereof). The first region **21** is a region having a disk shape. The central axis of the first region **21** substantially coincides with the axis **AX**. The first region **21** shares the dielectric portion **20d** with the second region **22**. The dielectric portion **20d** is formed of a dielectric such as aluminum nitride or aluminum oxide. The dielectric portion **20d** has a substantially disk shape. In an embodiment, the thickness of the dielectric portion **20d** in the second region **22** is smaller than the thickness of the dielectric portion **20d** in the first region **21**. The position in the vertical direction of the upper surface of the dielectric portion **20d** in the second region **22** may be lower than the position in the vertical direction of the upper surface of the dielectric portion **20d** in the first region **21**.

(125) The first region **21** has the electrode **21a** (a chuck electrode). The electrode **21a** is an electrode having a shape of a film and is provided in the dielectric portion **20d** within the first region **21**. A direct-current power source **101p** is connected to the electrode **21a** through a switch **101s**. When the direct-current voltage from the direct-current power source **101p** is applied to the electrode **21a**, an electrostatic attraction force is generated between the first region **21** and the substrate **W**. Due to the generated electrostatic attraction force, the substrate **W** is attracted to the first region **21** and held by the first region **21**.

(126) The first region **21** further has a first electrode **21c**. The first electrode **21c** is an electrode having a shape of a film and is provided in the dielectric portion **20d** within the first region **21**. The electrode **21a** may extend closer to the upper surface of the first region **21** than the first electrode **21c** in the vertical direction.

(127) A power source system **81** is connected to the first electrode **21c** through a filter **81f**. The power source system **81** has the same configuration as the power source system **70** and is configured to apply the bias voltage described above to the first electrode **21c**. The filter **81f** has the same configuration as the filter **70f**.

(128) The second region **22** extends to surround the first region **21**. The second region **22** is a substantially annular region. The central axis of the second region **22** substantially coincides with the axis **AX**. The second region **22** is configured to support the edge ring **ER** that is placed thereon (that is, on the upper surface thereof). The second region **22** shares the dielectric portion **20d** with the first region **21**.

(129) In an embodiment, the second region **22** may hold the edge ring **ER** by an electrostatic attraction force. In this embodiment, the second region **22** may have one or more electrodes (chuck electrodes). In the example shown in FIG. 9, the second region **22** has a pair of electrodes, that is, the electrodes **22a** and **22b**. The electrodes **22a** and **22b** are provided in the dielectric portion **20d** within the second region **22**. The electrodes **22a** and **22b** configure a bipolar electrode. Each of the electrodes **22a** and **22b** is an electrode having a shape of a film. The electrodes **22a** and **22b** may extend at substantially the same height position in the vertical direction.

(130) A direct-current power source **102p** is connected to the electrode **22a** through a switch **102s** and a filter **102f**. The filter **102f** is configured to cut off or attenuate radio frequency power. A direct-current power source **103p** is connected to the electrode **22b** through a switch **103s** and a filter **103f**. The filter **103f** is configured to cut off or reduce radio frequency power.

(131) The direct-current power source **102p** and the direct-current power source **103p** apply a direct-current voltage to the electrode **22a** and the electrode **22b**, respectively, in order to generate an electrostatic attraction force that attracts the edge ring **ER** to the second region **22**. The set potential of each of the electrodes **22a** and **22b** may be any of a positive potential, a negative potential, and 0 V. For example, the potential of the electrode **22a** may be set to a positive potential,

and the potential of the electrode **22b** may be set to a negative potential. Further, the potential difference between the electrodes **22a** and **22b** may be formed by using a single direct-current power source, instead of two direct-current power sources.

(132) When direct-current voltages are applied to the electrodes **22a** and **22b**, an electrostatic attraction force is generated between the second region **22** and the edge ring ER. The edge ring ER is attracted to the second region **22** by the generated electrostatic attraction force and is held by the second region **22**.

(133) The second region **22** further has a second electrode **22c**. The second electrode **22c** is an electrode having a shape of a film. The second electrode **22c** is provided in the dielectric portion **20d** within the second region **22**. The second electrode **22c** is separated from the first electrode **21c**. The electrodes **22a** and **22b** may extend closer to the upper surface of the second region **22** than the second electrode **22c** in the vertical direction. The second electrode **22c** may be disposed outside the second region **22**. For example, the second electrode **22c** may be provided below the edge ring ER and in the insulating part **29**.

(134) A power source system **82** is connected to the second electrode **22c** through a filter **82f**. The power source system **82** has the same configuration as the power source system **70** and is configured to apply the bias voltage described above to the second electrode **22c**. The filter **82f** has the same configuration as the filter **70f**. A bias voltage that is applied to the second electrode **22c** by the power source system **82** may be synchronized with a bias voltage that is applied to the first electrode **21c** by the power source system **81**. The phase of the bias voltage that is applied to the second electrode **22c** by the power source system **82** may coincide with the phase of the bias voltage that is applied to the first electrode **21c** by the power source system **81**. The bias voltage that is applied to the second electrode **22c** by the power source system **82** may have a phase difference with respect to the bias voltage that is applied to the first electrode **21c** by the power source system **81**.

(135) The second region **22** may further have a gas line **22g**. The gas line **22g** is a gas line provided to supply a heat transfer gas, for example, a He gas, to the gap between the second region **22** and the edge ring ER. The gas line **22g** is connected to a gas supply mechanism **104** which is a source for the heat transfer gas.

(136) The power source system **81** may be connected to the electrode **21a**. In this case, the substrate support **16A** does not need to have the first electrode **21c**. Further, the power source system **82** may be connected to at least one of the electrode **22a** and the electrode **22b**. In this case, the substrate support **16A** does not need to have the second electrode **22c**. Further, the second region **22** does not need to have the electrode **22a** and the electrode **22b**. Further, the power source system **81** may apply a bias voltage to the first electrode **21c** and the second electrode **22c**. In this case, the plasma processing apparatus **1** does not need to be provided with the power source system **82**.

(137) Further, the electrostatic chuck **20A** may have a source electrode to which the radio frequency power from the radio frequency power source **61** is supplied. The source electrode is provided in the dielectric portions **20d** of at least one of the first region **21** and the second region **22**. In a case where the source electrode is provided in the dielectric portion **20d** of the first region **21**, the source electrode may be provided below the first electrode **21c**, and the first electrode **21c** may be provided below the electrode **21a**. Alternatively, the source electrode may be provided above the first electrode **21c** and below the electrode **21a**. In a case where the source electrode is provided in the dielectric portion **20d** of the second region **22**, the source electrode may be provided below the second electrode **22c**, and the second electrode **22c** may be provided below the electrodes **22a** and **22b**. Alternatively, the source electrode may be provided above the second electrode **22c** and below the electrodes **22a** and **22b**.

(138) While various exemplary embodiments have been described above, various additions, omissions, substitutions and changes may be made without being limited to the exemplary

embodiments described above. Elements of the different embodiments may be combined to form another embodiment.

(139) For example, each of the power source systems **70**, **81**, and **82** may have one or more power sources (for example, direct-current power sources) capable of outputting a pulse of a voltage (for example, a direct-current voltage), instead of the configurations shown in FIGS. **7** and **8**. Each of the one or more power sources may be a variable direct-current power source. The bias voltages of various examples described above can be generated by such one or more power sources.

(140) Further, the pulse controller PC may be a configuration associated with the radio frequency power source **61** or the radio frequency power source **62**, instead of the configurations of the power source systems **70**, **81**, and **82**.

(141) Further, in the second example shown in FIG. **3**, the second pulse PL2 may be generated by connecting the node **722** to the ground after the point in time of end of the first period P1, and electrically separating the node **722** from the direct-current power source **71** before the potential of the node **722** becomes 0 V. In order to connect the node **722** to the ground, the one or more switching transistors **72a** are set to a closed state and the one or more switching transistors **72b** are set to an open state. In order to electrically separate the node **722** from the direct-current power source **71**, the one or more switching transistors **72a** and the one or more switching transistors **72b** are set to an open state.

(142) Further, in another embodiment, the plasma processing apparatus may be another type of plasma processing apparatus, instead of the capacitively coupled plasma processing apparatus. The other type of plasma processing apparatus may be an inductively coupled plasma processing apparatus, an electron cyclotron resonance (ECR) plasma processing apparatus, or a plasma processing apparatus that generates plasma by using surface waves such as microwaves. In the plasma processing methods according to various exemplary embodiments, such other types of plasma processing apparatuses may be used.

(143) From the foregoing description, it will be appreciated that various embodiments of the present disclosure have been described herein for purposes of illustration, and that various modifications may be made without departing from the scope and spirit of the present disclosure. Accordingly, the various embodiments disclosed herein are not intended to be limiting, with the true scope and spirit being indicated by the following claims.

Claims

1. A plasma processing apparatus comprising: a chamber; a substrate support having an electrode and disposed in the chamber; and a power source system configured to apply a pulsed voltage signal to the electrode in cycles, wherein each cycle consists of a sequence of first voltage pulses, each of which has a first voltage level and a negative polarity, in a first period in each cycle, a sequence of second voltage pulses, each of which has a second voltage level different from the first voltage level and a negative polarity, in a second period, a third voltage pulse having a positive polarity in a third period between the first period and the second period, the third period being a single period between the first period and the second period, and the third voltage pulse being a single voltage pulse in the third period, and a fourth voltage pulse having a positive polarity in a fourth period after the second period, the fourth voltage pulse being a single voltage pulse in the fourth period.
2. The plasma processing apparatus according to claim 1, wherein the power source system is configured to periodically output the first voltage pulses at a frequency which is not lower than 100 kHz and not higher than 1 MHz in the first period, and periodically output the second voltage pulses at a frequency which is not lower than 100 kHz and not higher than 1 MHz in the second period.
3. The plasma processing apparatus according to claim 1, wherein a frequency which is a reciprocal

of a time length of the cycle is not lower than 0.2 Hz and not higher than 1 Hz.

4. The plasma processing apparatus according to claim 1, wherein the power source system is configured to set an absolute value of the first voltage level to be larger than an absolute value of the second voltage level.

5. The plasma processing apparatus according to claim 1, wherein the power source system is configured to set an absolute value of the first voltage level to be smaller than an absolute value of the second voltage level.

6. The plasma processing apparatus according to claim 1, wherein the substrate support is configured to support a substrate, and the power source system is configured to apply the pulsed voltage signal to the electrode to draw ions from a plasma in the chamber into the substrate on the substrate support.

7. A plasma processing method comprising: preparing a substrate on a substrate support provided in a chamber of a plasma processing apparatus, wherein the substrate support includes an electrode; and outputting a pulsed voltage signal from a power source system to the electrode in cycles, wherein each cycle consists of a sequence of first voltage pulses, each of which has a first voltage level and a negative polarity, in a first period, a sequence of second voltage pulses, each of which has a second voltage level different from the first voltage level and a negative polarity, in a second period, a third voltage pulse having a positive polarity in a third period between the first period and the second period, the third period being a single period between the first period and the second period, and the third voltage pulse being a single voltage pulse in the third period, and a fourth voltage pulse having a positive polarity in a fourth period after the second period, the fourth voltage pulse being a single voltage pulse in the fourth period.

8. The plasma processing method according to claim 7, wherein the first voltage pulses are periodically output at a frequency which is not lower than 100 kHz and not higher than 1 MHz in the first period, and the second voltage pulses are periodically output at a frequency which is not lower than 100 kHz and not higher than 1 MHz in the second period.

9. The plasma processing method according to claim 7, wherein a frequency which is a reciprocal of a time length of the cycle is not lower than 0.2 Hz and not higher than 1 Hz.

10. The plasma processing method according to claim 7, wherein an absolute value of the first voltage level is set to be larger than an absolute value of the second voltage level.

11. The plasma processing method according to claim 7, wherein an absolute value of the first voltage level is set to be smaller than an absolute value of the second voltage level.

12. The plasma processing method according to claim 7, wherein the substrate support is configured to support a substrate, and the pulsed voltage signal is applied to the electrode to draw ions from a plasma in the chamber into the substrate on the substrate support.
