

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413070
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Tsuno; Katsuhiko et al.

Direct-current bus control system

Abstract

A direct-current bus control system is provided for controlling power variation in a DC bus connecting an input power source and a load, including: a main stabilizer including a first charge/discharge element and a first power converter; and a plurality of sub-stabilizers each including a second charge/discharge element, a charge element, or a discharge element, and a second power converter. The plurality of sub-stabilizers include a first sub-stabilizer and a second sub-stabilizer including the charge element. When the voltage of the DC bus is higher than a first charge threshold, the second power converter of the first sub-stabilizer supplies a current equal to a current target value obtained by the second power converter of the first sub-stabilizer from the DC bus to the charge element of the first sub-stabilizer.

Inventors: Tsuno; Katsuhiko (Saitama, JP), Fujii; Katsushi (Saitama, JP), Koike; Kayo (Saitama, JP), Wada; Satoshi (Saitama, JP)

Applicant: RIKEN (Saitama, JP)

Family ID: 86730524

Assignee: RIKEN (Saitama, JP)

Appl. No.: 18/737050

Filed: June 07, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240322564 A1	Sep. 26, 2024

Foreign Application Priority Data

JP	2021-201141	Dec. 10, 2021
----	-------------	---------------

Related U.S. Application Data

continuation parent-doc WO PCT/JP2022/045490 20221209 PENDING child-doc US 18737050

Publication Classification

Int. Cl.: H02J1/04 (20060101); H02J1/12 (20060101); H02J7/35 (20060101)

U.S. Cl.:

CPC H02J1/12 (20130101); H02J1/04 (20130101); H02J7/35 (20130101); H02J2207/20 (20200101); H02J2300/24 (20200101); H02J2300/28 (20200101); H02J2300/30 (20200101)

Field of Classification Search

CPC: H02J (1/04); H02J (1/00); H02J (1/10); H02J (1/12); H02J (7/00); H02J (7/007); H02J (7/00714); H02J (7/34); H02J (7/35)

USPC: 307/44; 307/45; 307/46; 307/82

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
11133673	12/2020	Yamashita	N/A	H02J 1/102
2020/0280183	12/2019	Yamashita et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2012/057032	12/2011	WO	N/A
2019/103059	12/2018	WO	N/A
2021/200902	12/2020	WO	N/A

OTHER PUBLICATIONS

International Search Report for PCT/JP2022/045490 mailed on Feb. 21, 2023. cited by applicant

Primary Examiner: Nguyen; Hai L

Attorney, Agent or Firm: IPUSA, PLLC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation application of International Application No. PCT/JP2022/045490, filed on Dec. 9, 2022, and designating the U.S., which is based upon and claims priority to Japanese Patent Application No. 2021-201141, filed on Dec. 10, 2021, the entire contents of which are incorporated herein by reference.

BACKGROUND

Technical Field

(1) The present disclosure relates to a Direct-Current (DC) bus control system.

Background Art

(2) Recently, as alternative power sources to replace fossil energy and nuclear energy, power source systems utilizing renewable energy such as solar light, wind force, wave force, and the like have been attracting attention. Some power source systems utilizing renewable energy such as solar light, wind force, wave force, and the like have already been put into practical use.

(3) Power generated by power source systems utilizing renewable energy such as solar light, wind force, wave force, and the like greatly varies depending on weather, season, location, and the like. Therefore, in order to maintain the voltage of the DC bus to which the power source system is connected within a predetermined allowable range, it is desirable to connect a power source such as a solar cell or a wind-force power generator to the DC bus via a power converter having a wide input range and a large capacity. However, in the case of connection to the DC bus via a power converter having a large capacity, the large capacity of the power converter may increase the size, complexity, and cost of the entire system.

(4) International Publication No. WO 2019/103059 discloses a DC bus control system configured to efficiently control power variation in the DC bus caused due to variations in the input power source and the load.

SUMMARY

(5) In the DC bus control system disclosed in International Publication No. WO 2019/103059, it is desirable that a sub-stabilizer is charged or discharged efficiently in order to bring efficiency to power variation in the DC bus.

(6) The present disclosure provides a direct-current bus control system for bringing efficiency to charging from the DC bus or discharging to the DC bus.

(7) The present disclosure is a direct-current bus control system for controlling power variation in a DC bus connecting an input power source and a load, the direct-current bus control system including: a main stabilizer including a first charge/discharge element and a first power converter; and a plurality of sub-stabilizers each including a second charge/discharge element, a charge element, or a discharge element, and a second power converter, wherein the first power converter is configured to obtain a bus voltage target value corresponding to a power storage quantity index of the first charge/discharge element, and to cause the first charge/discharge element and the DC bus to bidirectionally transmit or receive a DC power to or from each other such that a voltage of the DC bus becomes equal to the bus voltage target value, the second power converter is configured to obtain a current target value in accordance with a difference between the voltage of the DC bus and a threshold regarding charging or discharging of the second charge/discharge element, the charge element, or the discharge element, and to cause the second charge/discharge element, the charge element, or the discharge element, and the DC bus to transmit or receive a DC power to or from each other such that a current equal to the current target value flows through the second charge/discharge element, the charge element, or the discharge element, the plurality of sub-stabilizers include a first sub-stabilizer and a second sub-stabilizer including the charge element, the second power converter of the first sub-stabilizer is configured to supply the current equal to the current target value obtained by the second power converter of the first sub-stabilizer from the DC bus to the charge element of the first sub-stabilizer when the voltage of the DC bus is higher than a first charge threshold, and the second power converter of the second sub-stabilizer is configured to stop supplying a current from the DC bus to the charge element of the second sub-stabilizer or to supply a constant current from the DC bus to the charge element of the second sub-stabilizer regardless of the voltage of the DC bus when the voltage of the DC bus is higher than the first charge threshold and lower than a second charge threshold that is higher than the first charge

threshold, and to supply the current equal to the current target value obtained by the second power converter of the second sub-stabilizer from the DC bus to the charge element of the second sub-stabilizer when the voltage of the DC bus is higher than the second charge threshold.

(8) The direct-current bus control system according to the present disclosure can bring efficiency to charging from the DC bus or discharging to the DC bus.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a configuration diagram of the entirety of a Direct-Current (DC) bus control system according to the present embodiment;
- (2) FIG. 2 is a configuration diagram illustrating another example of a sub-stabilizer of a DC bus control system according to the present embodiment;
- (3) FIG. 3 is a block diagram illustrating an example of a configuration of a power converter of a solar power generation system;
- (4) FIG. 4 is a block diagram illustrating an example of a configuration of a power converter of a main stabilizer;
- (5) FIG. 5 is a block diagram illustrating an example of a configuration of a power converter of an auxiliary device;
- (6) FIG. 6 is a block diagram illustrating an example of a configuration of a power converter of a sub-stabilizer;
- (7) FIG. 7 is a block diagram illustrating an example of a configuration of a power converter of a sub-stabilizer;
- (8) FIG. 8 is a diagram illustrating an operation of the DC bus control system according to the present embodiment;
- (9) FIG. 9 is a diagram illustrating an operation of the DC bus control system according to the present embodiment;
- (10) FIG. 10 is a diagram illustrating the power generation efficiency of a fuel cell;
- (11) FIG. 11 is a diagram illustrating characteristics of a water electrolysis cell with respect to temperature;
- (12) FIG. 12 is a diagram illustrating a modified example of the operation of the DC bus control system according to the present embodiment;
- (13) FIG. 13 is a diagram illustrating a modified example of the operation of the DC bus control system according to the present embodiment;
- (14) FIG. 14 is a diagram illustrating a modified example of the operation of the DC bus control system according to the present embodiment;
- (15) FIG. 15 is a diagram illustrating a modified example of the operation of the DC bus control system according to the present embodiment; and
- (16) FIG. 16 is a diagram illustrating the operation of the DC bus control system according to the present embodiment.

DETAILED DESCRIPTION OF THE INVENTION

(17) Hereinafter, a Direct-Current (DC) bus control system according to the present embodiment will be described in detail with reference to the drawings. The contents of International Publication No. WO 2019/103059 are hereby incorporated in its entirety by reference.

(18) FIG. 1 is a configuration diagram of the entirety of a Direct-Current (DC) bus control system 1 according to the present embodiment. The DC bus control system 1 controls power variation in a DC bus connecting an input power source and a load. A solar power generation system 10 and a wind-force power generation system 20, which are renewable energy power source systems, are connected to the DC bus control system 1 as input power sources. The solar power generation

system **10** and the wind-force power generation system **20** are connected in parallel to a DC bus **70** of the DC bus control system **1**. The solar power generation system **10** includes a solar cell **11** and a power converter **12**. The wind-force power generation system **20** includes a wind-force power generator **21** and a power converter **22**.

(19) The input power source connected to the DC bus control system **1** may be any desirably selected power source. In a case where the input power source is a renewable energy power source system, it may be not only the power source system described above, but also a power source system utilizing such energy as wave force or geothermal heat, and may be a power source system for hydraulic (low head hydraulic) power generation, tidal power generation, tidal current power generation, temperature-difference power generation, and the like. It may also be a combination of the power source systems described above. Furthermore, the number of power source systems connected in parallel with each other is not particularly limited.

(20) A load **90** is connected to the output of the DC bus control system **1**. The load **90** includes, for example, household or business equipment, devices, and the like. The load **90** also includes a parallel arrangement of a plurality of household or business equipment, devices, and the like. The load **90** may be a DC load such as a DC electric motor, or a Direct Current/Alternate Current (DC/AC) converter configured to convert a DC power into an AC power and its AC load. Moreover, as the load **90**, an AC power system may be connected to the DC bus **70** via a DC/AC converter.

(21) The DC bus control system **1** may include an input power source or may include a load. The DC bus control system **1** may include both an input power source and a load.

(22) The DC bus control system **1** includes a main stabilizer **30** and an auxiliary device **35** that assists the main stabilizer **30**. The DC bus control system **1** also includes a sub-stabilizer **40** and a sub-stabilizer **45** having the same configuration as that of the sub-stabilizer **40**. Further, the DC bus control system **1** includes a sub-stabilizer **50** and a sub-stabilizer **55** having the same configuration as that of the sub-stabilizer **50**, and a sub-stabilizer **60** and a sub-stabilizer **65** having the same configuration as that of the sub-stabilizer **60**. Further, the DC bus control system **1** includes a monitor/instruction device **80**.

(23) Each of the main stabilizer **30**, the auxiliary device **35**, the sub-stabilizer **40**, the sub-stabilizer **45**, the sub-stabilizer **50**, the sub-stabilizer **55**, the sub-stabilizer **60**, and the sub-stabilizer **65** is connected to the DC bus **70**.

(24) The main stabilizer **30** includes a power storage device **31** and a power converter **32**. The main stabilizer **30** sets a variable bus voltage target value within a predetermined allowable range centered on a reference bus voltage (i.e., the reference voltage of the DC bus **70**), operates the power converter **32** such that an output voltage to the DC bus **70** side becomes equal to the bus voltage target value, and controls the charge/discharge of the power storage device **31**.

(25) The auxiliary device **35** includes a power storage device **36** and a power converter **37**. The auxiliary device **35** charges or discharges the power storage device **36** with or by a current having a current value corresponding to the current value of a current that is charged in or discharged from the main stabilizer **30**. The power converter **37** of the auxiliary device **35** controls charge or discharge of the power storage device **36** by operating the power storage device **36** to flow a current having a current value corresponding to the current value of the current with or by which the power converter **32** charges or discharges the power storage device **31**. The auxiliary device **35** apparently amplifies the power that is charged in or discharged from the main stabilizer **30** by charging or discharging the power storage device **36** based on the charge or discharge current of the main stabilizer **30**.

(26) The sub-stabilizer **40** includes a power storage device **41** and a power converter **42**. The sub-stabilizer **45** includes a power storage device **46** and a power converter **47**. The sub-stabilizer **45** has the same configuration as that of the sub-stabilizer **40**. That is, the power storage device **46** has the same specifications as those of the power storage device **41**. The power converter **47** has the

same specifications as those of the power converter **42**. Although the sub-stabilizer **45** will be described here as having the same configuration as that of the sub-stabilizer **40**, the sub-stabilizer **45** is not limited to having the same configuration as that of the sub-stabilizer **40**. For example, the sub-stabilizer **45** needs only to include a charge/discharge element as does the sub-stabilizer **40**.

(27) The sub-stabilizer **40** calculates an input/output current target value based on the difference between a charge/discharge threshold and the voltage of the DC bus **70**, and operates its own power converter **42** such that an input/output current becomes equal to the input/output current target value, to control the charge/discharge of the power storage device **41**. The sub-stabilizer **45** calculates an input/output current target value based on the difference between a charge/discharge threshold and the voltage of the DC bus, and operates the power converter **47** such that an input/output current becomes equal to the input/output current target value, to control the charge/discharge of the power storage device **46**.

(28) Each of the power storage device **31**, the power storage device **36**, the power storage device **41**, and the power storage device **46** is, for example, a battery (secondary battery), an electric double layer capacitor, a capacitor, a flywheel, a redox flow battery, or the like. Each of the power converter **32**, the power converter **37**, the power converter **42**, and the power converter **47** is, for example, an insulated DC/DC converter or a chopper, and is capable of transmitting or receiving a DC power bidirectionally as indicated by the arrows in FIG. **1**.

(29) The sub-stabilizer **50** includes a water electrolysis cell **51** and a power converter **52**. The sub-stabilizer **55** includes a water electrolysis cell **56** and a power converter **57**. The sub-stabilizer **55** has the same configuration as that of the sub-stabilizer **50**. That is, the water electrolysis cell **56** has the same specifications as those of the water electrolysis cell **51**. The power converter **57** has the same specifications as those of the power converter **52**. Although the sub-stabilizer **55** will be described here as having the same configuration as that of the sub-stabilizer **50**, the sub-stabilizer **55** is not limited to having the same configuration as that of the sub-stabilizer **50**. For example, the sub-stabilizer **55** needs only to include a charge element as does the sub-stabilizer **50**.

(30) In the sub-stabilizer **50**, the power converter **52** performs DC/DC conversion such that an input current becomes equal to an input current target value calculated based on the difference between a charge threshold and the voltage of the DC bus **70** and a DC power is supplied to the water electrolysis cell **51** (this is a type of a charging operation). The water electrolysis cell **51** electrolyzes water to produce hydrogen gas and oxygen gas. Similarly, in the sub-stabilizer **55**, the power converter **57** performs DC/DC conversion such that an input current becomes equal to an input current target value calculated based on the difference between a charge threshold and the voltage of the DC bus **70** and a DC power is supplied to the water electrolysis cell **56** (a type of a charging operation). The water electrolysis cell **56** electrolyzes water to produce hydrogen gas and oxygen gas.

(31) The sub-stabilizer **60** includes a fuel cell **61** and a power converter **62**. The sub-stabilizer **65** includes a fuel cell **66** and a power converter **67**. The sub-stabilizer **65** has the same configuration as that of the sub-stabilizer **60**. That is, the fuel cell **66** has the same specifications as those of the fuel cell **61**. The power converter **67** has the same specifications as those of the power converter **62**. Although the sub-stabilizer **65** will be described here as having the same configuration as that of the sub-stabilizer **60**, the sub-stabilizer **65** is not limited to having the same configuration as that of the sub-stabilizer **60**. For example, the sub-stabilizer **65** needs only to include a discharge element as does the sub-stabilizer **60**.

(32) The sub-stabilizer **60** supplies a DC power generated by an electrochemical reaction of the fuel cell **61** to the DC bus **70** via the power converter **62** (this is a type of a discharge operation). In the sub-stabilizer **60**, the power converter **62** performs DC/DC conversion such that an output current becomes equal to an output current target value calculated based on the difference between a discharge threshold and the voltage of the DC bus **70**. Similarly, the sub-stabilizer **65** supplies a DC power generated by an electrochemical reaction of the fuel cell **66** to the DC bus **70** via the

power converter **67** (a type of discharge operation). In the sub-stabilizer **65**, the power converter **67** performs DC/DC conversion such that an output current becomes equal to an output current target value calculated based on the difference between a discharge threshold and the voltage of the DC bus **70**.

(33) The configurations of the sub-stabilizer **50** and the sub-stabilizer **60** described above are merely exemplary. An alternative to the water electrolysis cell **51** may be, for example, a means for electrochemically reducing carbon dioxide to produce C—H-based bonds (CH₄, C₂H₄, and the like.) or alcohols, or a means for reducing nitrogen to produce ammonia. An alternative to the fuel cell **61** may be, for example, a fuel cell utilizing alcohols or the like, or a means for generating electricity by burning a chemical substance (hydrogen, C—H bases, alcohols, ammonia, and the like) to rotate a turbine or the like. The same applies to the sub-stabilizer **55** and the sub-stabilizer **65**.

(34) FIG. 2 is a configuration diagram illustrating a sub-stabilizer **50A**, which is another example of the sub-stabilizer of the DC bus control system **1** according to the present embodiment. The sub-stabilizer **50A** includes a power converter **52** and a power converter **62**, a water electrolysis cell **51**, a fuel cell **61**, and a hydrogen storage device **53**. The sub-stabilizer **50A** has an integrated structure in which the sub-stabilizer **50** and the sub-stabilizer **60** described above share the hydrogen storage device **53**.

(35) In FIG. 1, each of the power storage device **31**, the power storage device **36**, the power storage device **41**, and the power storage device **46** is capable of absorbing (being charged with) and discharging (releasing) a DC power. Each of the water electrolysis cell **51** and the water electrolysis cell **56** can convert a DC power into a gas and store it to absorb (be charged with) the DC power. Each of the fuel cell **61** and the fuel cell **66** can generate power by converting a gas into a DC power. The hydrogen storage device **53** illustrated in FIG. 2 can also absorb (be charged with) and discharge (release) a DC power by storing a gas. The power storage device **36**, the power storage device **41**, and the power storage device **46** each constitute a charge/discharge element. The water electrolysis cell **51** and the water electrolysis cell **56** each constitute a charge element. The fuel cell **61** and the fuel cell **66** each constitute a discharge element. The hydrogen storage device **53** constitutes a charge/discharge element.

(36) Each stabilizer (each of the main stabilizer **30**, the auxiliary device **35**, the sub-stabilizer **40**, the sub-stabilizer **45**, the sub-stabilizer **50**, the sub-stabilizer **55**, the sub-stabilizer **60**, and the sub-stabilizer **65**) serves as a power buffer that transmits or receives a DC power to or from the DC bus **70**. Each of the main stabilizer **30**, the auxiliary device **35**, the sub-stabilizer **40**, and the sub-stabilizer **45** is a power buffer having a charge/discharge function. Each of the sub-stabilizer **50** and the sub-stabilizer **55** is a power buffer having a charge function. Each of the sub-stabilizer **60** and the sub-stabilizer **65** is a power buffer having a discharge function.

(37) It is desirable that there is only one main stabilizer **30** that has a function for setting the bus voltage target value. It is only necessary to provide a required number of sub-stabilizers in accordance with the number of parallel power source systems and the required power of the load **90**.

(38) The monitor/instruction device **80** collects state information regarding a state of each of the main stabilizer **30**, the auxiliary device **35**, the sub-stabilizer **40**, the sub-stabilizer **45**, the sub-stabilizer **50**, the sub-stabilizer **55**, the sub-stabilizer **60**, and the sub-stabilizer **65** (hereinafter referred to as “main stabilizer and the like”), and performs state monitoring and operation monitoring. The state information includes, for example, voltage, current, temperature, and the like. Further, the monitor/instruction device **80** generates an operation command and a charge/discharge threshold command based on the result of monitoring the main stabilizer and the like. Wired or wireless transmission/reception is possible between the monitor/instruction device **80** and the main stabilizer and the like.

(39) Next, the configuration of each part of the DC bus control system **1** according to the present

embodiment will be described. The solar power generation system **10** and the wind-force power generation system **20** are connected as input power sources to the DC bus control system **1** according to the present embodiment.

(40) The solar power generation system **10** and the wind-force power generation system **20** have a common function in that they convert power generated using renewable energy into a DC power via the power converter **12** and the power converter **22**, respectively, and supply it to the DC bus **70**. In the following description, the solar power generation system **10** will be described as an example, and description of the wind-force power generation system **20** will be omitted.

(41) FIG. **3** is a block diagram illustrating a configuration example of the power converter **12** of the solar power generation system **10**. The power converter **12** includes a DC/DC converter **12A** and a control circuit **12B**.

(42) The DC/DC converter **12A** converts a DC output voltage of the solar cell **11** into a DC voltage of a predetermined magnitude through an operation of a semiconductor switching element and outputs it to the DC bus **70**. Part of the DC/DC converter **12A** is constituted by, for example, a step-up chopper.

(43) The control circuit **12B** controls the DC/DC converter **12A**. The control circuit **12B** includes a voltage detector **12a**, a current detector **12b**, an MPPT controller **12c**, a voltage/current controller **12d**, and a drive circuit **12e**. The voltage detector **12a** detects the output voltage of the solar cell **11**. The current detector **12b** detects the output current of the solar cell **11**.

(44) The MPPT controller **12c** performs maximum power point tracking (MPPT). The output voltage of the solar cell **11** detected by the voltage detector **12a** and the output current of the solar cell **11** detected by the current detector **12b** are input into the MPPT controller **12c**. The MPPT controller **12c** searches for the maximum output point of the solar cell **11** by a hill-climbing method or the like and outputs the result to the voltage/current controller **12d**.

(45) The voltage/current controller **12d** generates a drive pulse by Pulse Width Modulation (PWM) control or the like based on the input from the MPPT controller **12c**. The voltage/current controller **12d** outputs the generated drive pulse to the drive circuit **12e**. The drive circuit **12e** turns ON or OFF the semiconductor switching element of the DC/DC converter **12A** based on the drive pulse that is output from the voltage/current controller **12d**.

(46) FIG. **4** is a block diagram illustrating a configuration example of the power converter **32** of the main stabilizer **30**. The power converter **32** includes a DC/DC converter **32A**, a control circuit **32B**, and a current detector **32C**.

(47) The DC/DC converter **32A** has a function of causing the DC bus **70** and the power storage device **31** to bidirectionally transmit or receive a DC power to or from each other to control charge or discharge of the power storage device **31**. Part of the DC/DC converter **32A** is constituted by an insulated DC/DC converter, a chopper, or the like including a semiconductor switching element. The power storage device **31** includes a sensor **31s** configured to detect voltage/current, and temperature.

(48) The control circuit **32B** includes a voltage detector **32a**, a bus voltage target value calculator **32b**, a subtractor **32c**, a charge/discharge controller **32d**, and a drive circuit **32e**.

(49) The voltage detector **32a** detects the voltage of the DC bus **70**. The bus voltage target value calculator **32b** calculates a bus voltage target value in accordance with a power storage quantity index of the power storage device **31**. For example, the bus voltage target value is calculated based on: an estimated power storage quantity index that is obtained by measuring a charge/discharge current of the power storage device **31**; a reference power storage quantity index; and a reference bus voltage. For example, the bus voltage target value is set to be higher as the power storage quantity index (e.g., a charge rate) is higher and to be lower as the power storage quantity index is lower within an allowable range of the voltage of the DC bus **70**.

(50) As the power storage quantity index of the power storage device **31**, for example, a charge rate (State of Charge (SOC)) obtained by integrating the charge/discharge current of the power storage

device **31** detected by the sensor **31s** can be used.

(51) The subtractor **32c** calculates the deviation between the bus voltage target value and a detected bus voltage value. The subtractor **32c** outputs the calculated deviation to the charge/discharge controller **32d**.

(52) The charge/discharge controller **32d** performs PWM control or the like to generate a drive pulse such that a detected bus voltage value becomes equal to the bus voltage target value. A voltage/current, a temperature, and a charge/discharge threshold of the power storage device **31** are input into the charge/discharge controller **32d**. Based on the input information of the power storage device **31** such as voltage/current, temperature, and charge/discharge threshold, the charge/discharge controller **32d** performs PWM control or the like to generate a drive pulse such that a detected bus voltage value becomes equal to the bus voltage target value.

(53) The drive circuit **32e** turns ON and OFF the semiconductor switching element of the DC/DC converter **32A** in accordance with the drive pulse generated by the charge/discharge controller **32d**. As described above, the DC/DC converter **32A** controls the charge/discharge of the power storage device **31** such that a detected bus voltage value becomes equal to the bus voltage target value.

(54) The current detector **32C** detects the current value of the current with or by which the power storage device **31** is charged or discharged. The current detector **32C** outputs the current value thus detected (detected current value) to the power converter **37** of the auxiliary device **35**.

(55) The charge/discharge threshold of the power storage device **31** may be set by the control circuit **32B** itself or received as a command from the monitor/instruction device **80**.

(56) FIG. 5 is a block diagram illustrating a configuration example of the power converter **37** of the auxiliary device **35**. The power converter **37** includes a DC/DC converter **37A**, a control circuit **37B**, and a current detector **37C**.

(57) The DC/DC converter **37A** has a function of causing the DC bus **70** and the power storage device **36** to bidirectionally transmit or receive a DC power to and from each other to control charge or discharge of the power storage device **36**. Part of the DC/DC converter **37A** is constituted by an insulated DC/DC converter, a chopper, or the like including a semiconductor switching element. The power storage device **36** includes a sensor **36s** configured to detect voltage/current, and temperature.

(58) The control circuit **37B** includes an amplifier **37a**, a subtractor **37c**, a charge/discharge controller **37d**, and a drive circuit **37e**. The current detector **37C** measures the current value of the current with or by which the power storage device **36** is charged or discharged. The current detector **37C** outputs the measured current value (detected current value) to the amplifier **37a** of the auxiliary device **35**.

(59) The amplifier **37a** amplifies the detected current value detected by the current detector **37C** with a predetermined amplification factor. Then, the subtractor **37c** calculates the deviation between the detected current value that is input from the current detector **32C** of the main stabilizer **30** and the detected current value that is output by the amplifier **37a**. The subtractor **37c** outputs the calculated deviation to the charge/discharge controller **37d**.

(60) The charge/discharge controller **37d** performs PWM control or the like to generate a drive pulse such that the detected current value that is output by the amplifier **37a** becomes equal to the detected current value that is input from the current detector **32C** of the main stabilizer **30**.

(61) The drive circuit **37e** turns ON and OFF the semiconductor switching element of the DC/DC converter **37A** in accordance with the drive pulse generated by the charge/discharge controller **37d**. The DC/DC converter **37A** controls the charge/discharge of the power storage device **36** as described above, such that the detected current value that is output by the amplifier **37a** becomes equal to the detected current value that is input from the current detector **32C** of the main stabilizer **30**.

(62) By the control circuit **37B** performing control as described above, the power converter **37** performs charge/discharge control such that the power storage device **36** is charged with or

discharged by a current having a current value corresponding to the current value of the current charged in or discharged from the main stabilizer **30**.

(63) In a case where the current value of the current charged in or discharged from the main stabilizer **30** is assumed as a current value I_m , the current value of the current with or by which the power converter **37** charges or discharges the power storage device **36** is assumed as a current value I_s , and a function that monotonically increases with respect to a variable x is assumed as $F(x)$, for example, the control circuit **37B** controls charge or discharge such that the current value I_s becomes a value that is in accordance with the current value I_m so as to satisfy the equation below. The signs of the current value I_m and the current value I_s are, for example, positive when they are a charge current.

$$I_s = F(I_m)$$

(64) The function $F(x)$ may be a linear function or a nonlinear function as long as it increases monotonically with respect to the variable x . For example, the current value I_s may be made equal to the current value I_m , or the current value I_s may be made proportional to the current value I_m . Further, the rate (slope) of the increase of the current value I_s with respect to the increase of the current value I_m is not limited to being constant, and the current value I_s may be changed with respect to the current value I_m such that, for example, the increase of the current value I_s becomes gentler as the current value I_m is greater.

(65) The number of auxiliary devices **35** is not limited to one. For example, the DC bus control system **1** may include a plurality of auxiliary devices **35**.

(66) For example, in a case where a plurality of main stabilizers **30** are provided in order to increase the capacity of the main stabilizer **30**, the plurality of main stabilizers **30**, each of which controls the bus voltage of the DC bus **70**, may conflict with each other in the control of the bus voltage and make the system unstable.

(67) According to the DC bus control system **1** of the present embodiment, the bus voltage of the DC bus **70** is controlled by one main stabilizer **30**, and it is possible to increase the charge/discharge capacity by copying the current, with or by which the power storage device **31** is charged or discharged, to the power storage device **36** of the auxiliary device **35**. According to the DC bus control system **1** of the present embodiment, the bus voltage of the DC bus **70** is controlled by one main stabilizer **30**, making it possible to control the bus voltage of the DC bus **70** stably.

(68) FIG. **6** is a block diagram illustrating a configuration example of the power converter **42** of the sub-stabilizer **40**. The power converter **47** of the sub-stabilizer **45** has the same configuration as that of the power converter **42**. The power converter **42** includes a DC/DC converter **42A** and a control circuit **42B**. The power converter **42** has the same function as that of the power converter **32** of the main stabilizer **30** in that it causes the DC bus **70** and the power storage device **41** to bidirectionally transmit or receive a DC power to or from each other. Like the power storage device **31**, the power storage device **41** includes a sensor **41s** configured to detect voltage/current, and temperature.

(69) The control circuit **42B** includes a voltage detector **42a**, a comparator **42b**, a subtractor **42c**, a charge/discharge controller **42d**, and a drive circuit **42e**.

(70) The power converter **42** differs from the power converter **32** of the main stabilizer **30** in the following points. The charge/discharge controller **42d** of the control circuit **42B** calculates an input/output current target value based on the deviation between a charge/discharge threshold and a detected bus voltage value. The charge/discharge controller **42d** further performs charge/discharge control of the power storage device **41** such that the input/output current of the DC/DC converter **42A** becomes equal to the input/output current target value. The charge/discharge threshold may be a threshold (charge threshold and discharge threshold) relating to charge or discharge of the power storage device **41**, and the input/output current target value may be determined in accordance with the difference between the charge/discharge threshold and the voltage of the DC bus **70**.

(71) The comparator **42b** provided in the control circuit **42B** compares the charge/discharge

threshold of the power storage device **41** with the detected bus voltage value, and outputs a charge command or a discharge command in accordance with the relationship in magnitude between the charge threshold or discharge threshold and the detected bus voltage value to control the operation of the charge/discharge controller **42d**. The charge/discharge threshold may be set by the control circuit **42B** itself or received as a command from the monitor/instruction device **80**.

(72) FIG. 7 is a block diagram illustrating an example of a configuration of the power converter **52** of the sub-stabilizer **50**. The power converter **57** of the sub-stabilizer **55** has the same configuration as that of the power converter **52**. The power converter **52** includes a DC/DC converter **52A** and a control circuit **52B**.

(73) The DC/DC converter **52A** has a function of converting the DC power of the DC bus **70** to a predetermined level and supplying it to the water electrolysis cell **51**. Part of the DC/DC converter **52A** is constituted by an insulated DC/DC converter, a chopper, or the like including a semiconductor switching element.

(74) The water electrolysis cell **51** electrolyzes water using a DC power supplied from the DC/DC converter **52A**. Hydrogen gas generated by the water electrolysis cell **51** is stored in an external storage device (not illustrated). The water electrolysis cell **51** performs an operation of converting a DC power into hydrogen gas and storing it, in other words, a type of a charging operation.

(75) The control circuit **52B** configured to control the DC/DC converter **52A** has the same configuration as that of the control circuit **42B**. The control circuit **52B** includes a voltage detector **52a**, a comparator **52b**, a subtractor **52c**, a charge controller **52d**, and a drive circuit **52e**.

(76) In the control circuit **52B**, the voltage of the DC bus **70** is detected by the voltage detector **52a**. The deviation between a charge threshold and the detected bus voltage value is calculated by the subtractor **52c**. The deviation between the charge threshold and the detected bus voltage value is input into the charge controller **52d**. Moreover, the detected bus voltage value is input into the comparator **52b** together with the charge threshold. When the detected bus voltage value exceeds the charge threshold, the comparator **52b** outputs a charge command to the charge controller **52d**. The charge threshold corresponds to the voltage at which the water electrolysis cell **51** starts electrolysis. That is, the charge threshold is the threshold relating to charge of the water electrolysis cell **51**.

(77) The charge controller **52d** calculates an input/output current target value based on the deviation between the charge threshold and the detected bus voltage value, which is input from the subtractor **52c**. Then, the charge controller **52d** generates a drive pulse as a charge command such that an input/output current of the DC/DC converter **52A** becomes equal to the input/output current target value, and outputs the drive pulse to the drive circuit **52e**. The drive circuit **52e** turns ON or OFF the semiconductor switching element of the DC/DC converter **52A** in accordance with the drive pulse generated by the charge controller **52d**. The DC/DC converter **52A** supplies a DC power to the water electrolysis cell **51** to electrolyze water.

(78) The DC/DC converter **52A** controls the DC power supplied to the water electrolysis cell **51** through the operation described above while also operating such that the input/output current becomes equal to the input/output current target value.

(79) In regard to the sub-stabilizer **60**, when seeing a power generation operation of the fuel cell **61** as a discharge operation, configuring the sub-stabilizer **60** only requires the water electrolysis cell **51**, the charge threshold, and the charge controller **52d** of the sub-stabilizer **50** to be replaced with the fuel cell **61**, a discharge threshold, and a discharge controller, respectively. The discharge threshold corresponds to the voltage at which the fuel cell **61** starts power generation. The power converter **57** of the sub-stabilizer **55** has the same configuration as that of the power converter **52**.

(80) When a detected bus voltage value falls below the discharge threshold, the sub-stabilizer **60** outputs a drive pulse corresponding to a discharge command to the discharge controller to operate the DC/DC converter. By operating the DC/DC converter, the sub-stabilizer **60** supplies a power generated by the fuel cell **61** to the DC bus **70** via the DC/DC converter.

(81) The DC/DC converter controls the power to be generated by the fuel cell **61** through the operation described above while also operating such that an input/output current becomes equal to an input/output current target value.

(82) Each of the water electrolysis cell **51**, the water electrolysis cell **56**, the fuel cell **61**, and the fuel cell **66** is provided with a sensor configured to detect voltage/current, temperature, and the like, and values detected by the sensor are input into the charge controller **52d** and the discharge controller. However, the sensors are not illustrated in the drawings.

(83) Further, the charge threshold and the discharge threshold may be set by each control circuit itself or received as a command from the monitor/instruction device **80**.

(84) The configurations and operations of the power converter **12**, the power converter **32**, the power converter **37**, the power converter **42**, and the power converter **52** illustrated in FIGS. **3** to **7**, in particular, the control circuit **12B**, the control circuit **32B**, the control circuit **37B**, the control circuit **42B**, and the control circuit **52B**, are only exemplary and do not limit the technical scope of the present invention in any way. Naturally, it is possible to employ configurations different from those above.

(85) Next, input power into the water electrolysis cell **51** of the sub-stabilizer **50** and the water electrolysis cell **56** of the sub-stabilizer **55**, and output power from the fuel cell **61** of the sub-stabilizer **60** and the fuel cell **66** of the sub-stabilizer **65** with respect to the voltage of the DC bus **70** will be described. FIG. **8** is a conceptual diagram exemplarily illustrating the input power into the water electrolysis cell **51** of the sub-stabilizer **50** and the water electrolysis cell **56** of the sub-stabilizer **55**, and the output power from the fuel cell **61** of the sub-stabilizer **60** and the fuel cell **66** of the sub-stabilizer **65** with respect to the voltage of the DC bus **70**. The abscissa-direction width of triangular symbols and trapezoidal symbols in FIG. **8** indicates the magnitude of each power, and the wider the width, the larger the power value.

(86) In FIG. **8**, each symbol comes with an abscissa indicating power. On the abscissa indicating power, a power (current) supply from the DC bus, i.e., a charge, is positive. On the abscissa indicating power, a power (current) supply to the DC bus, i.e., a discharge, is negative. The abscissa of each symbol indicates power. However, when power is read as current, the same meaning will also be conveyed. The same applies to the drawings to follow.

(87) FIG. **8** illustrates a case where the input power source is a renewable energy power system, which includes, for example, either or both of the solar power generation system **10** and the wind-force power generation system **20** illustrated in FIG. **1**. Operations for the water electrolysis cell **51** and the water electrolysis cell **56** to be charged, and operations for the fuel cell **61** and the fuel cell **66** to be discharged are controlled in accordance with the voltage of the DC bus **70** to which the power generated by the renewable energy power system is supplied. Operations for the respective parts to be charged or discharged are controlled in accordance with the voltage of the DC bus **70** to which the powers generated by the solar power generation system **10** and the wind-force power generation system **20** are supplied, the charge thresholds of the water electrolysis cell **51** and the water electrolysis cell **56**, the discharge thresholds of the fuel cell **61** and the fuel cell **66**, and the like.

(88) By controlling charge and discharge operations by changing the charge thresholds of the water electrolysis cell **51** and the water electrolysis cell **56** and the discharge thresholds of the fuel cell **61** and the fuel cell **66**, it is possible to individually adjust the DC power which the DC bus **70** and each of the sub-stabilizer **50**, the sub-stabilizer **55**, the sub-stabilizer **60**, and the sub-stabilizer **65** transmit to or receive from each other. In other words, it is possible to minutely control the operation of each power buffer.

(89) The water electrolysis cell **51**, the water electrolysis cell **56**, the fuel cell **61**, and the fuel cell **66** have been described with reference to FIG. **8**. However, the same applies to the power storage device **41** and the power storage device **46**. By controlling the charge and discharge operations by changing the charge/discharge thresholds of the power storage device **41** and the power storage

device **46**, it is possible to individually adjust the DC power which the DC bus **70** and each of the sub-stabilizer **40** and the sub-stabilizer **45** transmit to or receive from each other. In other words, it is possible to minutely control the operation of each power buffer.

(90) Further, the power storage device **41**, the power storage device **46**, the water electrolysis cell **51**, the water electrolysis cell **56**, the fuel cell **61**, and the fuel cell **66** may be combined. That is, the DC power transferred between the DC bus **70** and the sub-stabilizer **40**, the sub-stabilizer **45**, the sub-stabilizer **50**, the sub-stabilizer **55**, the sub-stabilizer **60**, and the sub-stabilizer **65** may be individually adjusted.

(91) The charge threshold and the discharge threshold may be changed based on instructions from the monitor/instruction device **80**, or the power converter **42**, the power converter **47**, the power converter **52**, the power converter **57**, the power converter **62**, and the power converter **67** may each change the thresholds themselves.

(92) First, the fuel cell **61** and the fuel cell **66** will be described. As illustrated in FIG. **8**, the discharge threshold **1** of the fuel cell **61** of the sub-stabilizer **60** is higher than the discharge threshold **2** of the fuel cell **66** of the sub-stabilizer **65**.

(93) Regarding the fuel cell **61**, when the bus voltage decreases from the reference bus voltage to become equal to or lower than the discharge threshold **1**, a power (output power) is supplied from the fuel cell **61** to the DC/DC converter of the power converter **62**. The power (output power) from the fuel cell **61** to the DC/DC converter of the power converter **62** is higher as the bus voltage is lower. When the bus voltage becomes equal to or lower than the discharge threshold **2**, the power (output power) from the fuel cell **61** to the DC/DC converter of the power converter **62** becomes constant.

(94) Regarding the fuel cell **66**, when the bus voltage decreases from the reference bus voltage to become equal to or lower than the discharge threshold **2**, a power (output power) is supplied from the fuel cell **66** to the DC/DC converter of the power converter **67**. The power (output power) from the fuel cell **66** to the DC/DC converter of the power converter **67** is higher as the bus voltage is lower.

(95) When the bus voltage is between the discharge threshold **1** and the discharge threshold **2**, power is supplied from the fuel cell **61** to the DC bus **70**, but no power is supplied from the fuel cell **66**.

(96) Next, the water electrolysis cell **51** and the water electrolysis cell **56** will be described. As illustrated in FIG. **8**, the charge threshold **1** of the water electrolysis cell **51** of the sub-stabilizer **50** is lower than the charge threshold **2** of the water electrolysis cell **56** of the sub-stabilizer **55**.

(97) Regarding the water electrolysis cell **51**, when the bus voltage increases from the reference bus voltage to become equal to or higher than the charge threshold **1**, a power (input power) is supplied from the DC/DC converter **52A** of the power converter **52** to the water electrolysis cell **51**. The power (input power) from the DC/DC converter **52A** of the power converter **52** into the water electrolysis cell **51** is higher as the bus voltage is higher. When the bus voltage becomes equal to or higher than the charge threshold **2**, the power (input power) from the DC/DC converter of the power converter **52** into the water electrolysis cell **51** becomes constant.

(98) Regarding the water electrolysis cell **56**, when the bus voltage further increases from the reference bus voltage to become equal to or higher than the charge threshold **2**, a power (input power) is supplied from the DC/DC converter of the power converter **57** to the water electrolysis cell **56**. The power (input power) from the DC/DC converter of the power converter **57** into the water electrolysis cell **56** is higher as the bus voltage is higher.

(99) When the bus voltage is between the charge threshold **1** and the charge threshold **2**, power is supplied to the water electrolysis cell **51** from the DC bus **70**, but the no power is supplied to the water electrolysis cell **56** from the DC bus **70**.

(100) Next, the operation of the DC bus control system **1** according to the present embodiment will be described. FIG. **9** is a diagram illustrating the operation of the DC bus control system **1**

according to the present embodiment. The abscissa of each graph indicates the time. The ordinate of each graph indicates voltage or power.

(101) From top to bottom, the graphs illustrate the bus voltage of the DC bus **70**, the external power relating to the solar power generation system **10** and the wind-force power generation system **20** (input power sources) and the load **90**, and powers of the main stabilizers, the water electrolysis cell **51**, the water electrolysis cell **56**, the fuel cell **61**, and the fuel cell **66**. Regarding the external power, the solid line denotes the power relating to the input power sources (the solar power generation system **10** and the wind-force power generation system **20**), and the dotted line denotes the power relating to the load. The main stabilizers are the main stabilizer **30** and the auxiliary device **35**. The power supplied from the DC bus **70** is positive, and the power supplied to the DC bus **70** is negative.

(102) Regarding the bus voltage, V_0 indicates the reference bus voltage, V_{th1} indicates the charge threshold **1**, V_{th2} indicates the charge threshold **2**, V_{dth1} indicates the discharge threshold **1**, and V_{dth2} indicates the discharge threshold **2**.

(103) The bus voltage when the DC bus control system **1** starts to operate is assumed to be the reference bus voltage V_0 . When the DC bus control system **1** just starts to operate, it is assumed that the external power, i.e., the power from the input power sources and the power to the load **90**, are not supplied, and that the main stabilizers, the water electrolysis cell **51**, the water electrolysis cell **56**, the fuel cell **61**, and the fuel cell **66** are not operating.

(104) At the timing t_1 , the input power sources (the solar power generation system **10** and the wind-force power generation system **20**) start to operate. At the timing t_1 at which the input power sources start to operate, because the bus voltage is higher than the discharge threshold **1** V_{dth1} and lower than the charge threshold **1** V_{th1} , the water electrolysis cell **51** and the water electrolysis cell **56** are not being charged, and the fuel cell **61** and the fuel cell **66** are not being discharged. Therefore, the main stabilizers are charged with power from the DC bus **70**. In response to the main stabilizers being supplied with power from the DC bus **70**, the bus voltage increases in accordance with the charge rate of the main stabilizers.

(105) When the bus voltage becomes equal to or higher than the charge threshold **1** V_{th1} at the timing t_2 , the water electrolysis cell **51** starts to be charged from the DC bus **70**. In the meantime, because the bus voltage is lower than the charge threshold **2** V_{th2} , the water electrolysis cell **56** does not start to be charged. The power to the main stabilizers decreases in accordance with the power to the water electrolysis cell **51**. The bus voltage continues to increase in accordance with the charge rate of the main stabilizers.

(106) When the bus voltage becomes equal to or higher than the charge threshold **2** V_{th2} at the timing t_3 , the water electrolysis cell **56** starts to be charged from the DC bus **70**. The water electrolysis cell **51** is charged with a constant power (current). The power to the main stabilizers decreases in accordance with the power to the water electrolysis cell **51** and the water electrolysis cell **56**. The bus voltage continues to increase in accordance with the charge rate of the main stabilizers.

(107) At the timing t_4 , the power to the main stabilizers becomes zero. Therefore, the bus voltage becomes a constant voltage.

(108) Next, at the timing t_5 , the load **90** starts to operate. It is assumed that the power from the input power sources and the power to the load **90** are equal. Upon starting to operate, the load **90** is supplied with power from the main stabilizers. In response to power being supplied from the main stabilizers, their charge rate decreases, and the bus voltage decreases. In response to the decrease in the bus voltage, the power charged in the water electrolysis cell **56** decreases.

(109) When the bus voltage becomes lower than the charge threshold **2** V_{th2} at the timing t_6 , the water electrolysis cell **56** stops being charged from the DC bus **70**. Due to power being supplied from the main stabilizers, their charge rate decreases, and the bus voltage decreases. Due to the decrease in the bus voltage, charge into the water electrolysis cell **51** gradually decreases.

(110) When the bus voltage becomes lower than the charge threshold $1 V_{ch1}$ at the timing $t7$, the water electrolysis cell **51** stops being charged from the DC bus **70**. Since the main stabilizers are not being discharged and charged, the bus voltage is constant.

(111) Next, at the timing $t8$, the external power sources stop. When the external power sources stop, the main stabilizers start to be discharged to the DC bus **70**. Since the bus voltage is higher than the discharge threshold $1 V_{dth1}$ and lower than the charge threshold $1 V_{ch1}$, the water electrolysis cell **51** and the water electrolysis cell **56** are not being charged, and the fuel cell **61** and the fuel cell **66** are not being discharged. Therefore, the main stabilizers are discharged to the DC bus **70**. By the main stabilizers supplying power to the DC bus **70**, the bus voltage decreases in accordance with the charge rate of the main stabilizers.

(112) At the timing $t9$, the bus voltage becomes equal to the reference bus voltage $V0$ and further decreases.

(113) When the bus voltage becomes equal to or lower than the discharge threshold $1 V_{dth1}$ at the timing $t10$, the fuel cell **61** is discharged to the DC bus **70**. In the meantime, since the bus voltage is higher than the discharge threshold $2 V_{dth2}$, the fuel cell **66** is not discharged to the DC bus **70**. The power from the main stabilizers decreases proportionately to the power from the fuel cell **61**. The bus voltage continues to decrease in accordance with the charge rate of the main stabilizers.

(114) When the bus voltage becomes equal to or lower than the discharge threshold $2 V_{dth2}$ at the timing $t11$, the fuel cell **66** is discharged to the DC bus **70**, and the DC bus is charged from the fuel cell **61** with a constant power (current). The power from the main stabilizers decreases proportionately to the power to the fuel cell **61** and the fuel cell **66**. The bus voltage continues to decrease in accordance with the charge rate of the main stabilizers.

(115) At the timing $t12$, the power to the main stabilizers becomes 0. Therefore, the bus voltage becomes a constant voltage.

(116) Next, at the timing $t13$, the load **90** stops operating. In response to the load **90** stopping operating, power is supplied to the main stabilizers. In response to power being supplied to the main stabilizers, the charge rate increases and the bus voltage increases. In response to the increase in the bus voltage, the power to be discharged from the fuel cell **66** decreases.

(117) When the bus voltage becomes higher than the discharge threshold $2 V_{dth2}$ at the timing $t14$, the fuel cell **66** stops being discharged to the DC bus **70**. Because power is being supplied to the main stabilizers, the charge rate increases and the bus voltage increases. Due to the increase in the bus voltage, discharge from the fuel cell **61** gradually decreases.

(118) When the bus voltage becomes higher than the discharge threshold $1 V_{dth1}$ at the timing $t15$, the fuel cell **61** stops being discharged to the DC bus **70**. Since the main stabilizers are not being discharged and charged, the bus voltage becomes constant.

(119) At the timing $t16$, the input power sources start to operate. At the timing $t16$ at which the input power sources start to operate, because the bus voltage is higher than the discharge threshold $1 V_{dth1}$ and lower than the charge threshold $1 V_{ch1}$, the water electrolysis cell **51** and the water electrolysis cell **56** are not being charged, and the fuel cell **61** and the fuel cell **66** are not being discharged. Therefore, power is supplied to the main stabilizers from the DC bus **70**. In response to power being supplied to the main stabilizers from the DC bus **70**, the bus voltage increases in accordance with the charge rate of the main stabilizers. The following operation will be performed in the same manner.

(120) FIG. **10** is a conceptual diagram illustrating the power generation efficiency of a fuel cell. In FIG. **10**, the abscissa represents the current flowing in the fuel cell, and the ordinate represents the power generation efficiency of the fuel cell. The line Le conceptually represents the power generation efficiency of the fuel cell. The power generation efficiency of the fuel cell is higher as the current is higher. Since the voltage from the fuel cell is approximately constant in a use range, the power generation efficiency is higher as the current is higher, i.e., as the power is higher. Therefore, it is desirable to use approximately the range A of the fuel cell as illustrated in FIG. **10**

in terms of the power generation efficiency.

(121) Therefore, the DC bus control system **1** according to the present embodiment operates only the fuel cell **61** when the bus voltage is high, specifically, when the bus voltage is equal to or lower than the discharge threshold **1** and higher than the discharge threshold **2**. The DC bus control system **1** according to the present embodiment operates both the fuel cell **61** and the fuel cell **66** when the bus voltage becomes lower, specifically, when the bus voltage becomes equal to or lower than the discharge threshold **2**. In particular, when the bus voltage is equal to or lower than the discharge threshold **2**, the fuel cell **61** can be operated in a range in which it has a high power generation efficiency.

(122) For example, operating the fuel cell **61** and the fuel cell **66** simultaneously when the discharge threshold becomes equal to or lower than the discharge threshold **1** means operating the fuel cell **61** and the fuel cell **66** in ranges in which they have a low power generation efficiency, resulting in a low efficiency of the entire DC bus control system.

(123) The DC bus control system **1** according to the present embodiment can operate the fuel cell **61** in a range in which it has a high power generation efficiency, by operating only the fuel cell **61** when the bus voltage is high. Therefore, the DC bus control system **1** according to the present embodiment can efficiently supply power to the DC bus **70**.

(124) In addition, it is possible to realize the DC bus control system **1** according to the present embodiment, by using the sub-stabilizer **60** and the sub-stabilizer **65** having the same configuration but by varying the discharge threshold between them. Therefore, it is possible to realize the DC bus control system **1** according to the present embodiment, by increasing the number of sub-stabilizers to be installed while not varying them in type but varying the conditions, making it possible to save the manufacturing cost and the installation cost.

(125) FIG. **11** is a conceptual diagram illustrating the characteristics of a water electrolysis cell with respect to temperature. In FIG. **11**, the abscissa indicates the voltage supplied to the water electrolysis cell, and the ordinate indicates the current flowing through the water electrolysis cell. The line Lw**1**, the line Lw**2**, the line Lw**3**, the line Lw**4**, the line Lw**5**, and the line Lw**6** conceptually indicate the relationship between voltage and current when the operating temperature of the water electrolysis cell is 24° C., 40° C., 50° C., 60° C., 70° C., and 80° C., respectively.

(126) As the operating temperature of the water electrolysis cell increases, the current flowing through the water electrolysis cell increases. As the current flowing through the water electrolysis cell increases, the hydrogen production proportional to the current increases. Therefore, in a case of operating water electrolysis cells, operating fewer cells at higher cell temperatures enables an efficient water electrolysis.

(127) Therefore, the DC bus control system **1** according to the present embodiment operates only the water electrolysis cell **51** when the bus voltage is low, specifically, when the bus voltage is equal to or higher than the charge threshold **1** and lower than the charge threshold **2**. The DC bus control system **1** according to the present embodiment operates both the water electrolysis cell **51** and the water electrolysis cell **56** when the bus voltage is higher, specifically, when the bus voltage is equal to or higher than the charge threshold **2**. In particular, when the bus voltage is equal to or higher than the charge threshold **2**, the water electrolysis cell **51** can be operated in a range in which it has a high water electrolysis efficiency.

(128) For example, operating the water electrolysis cell **51** and the water electrolysis cell **56** simultaneously when the charge threshold becomes equal to or higher than the charge threshold **1** means operating the water electrolysis cell **51** and the water electrolysis cell **56** in ranges in which they have a low water electrolysis efficiency, resulting in a low efficiency of the entire DC bus control system.

(129) The DC bus control system **1** according to the present embodiment can operate the water electrolysis cell **51** in a range in which it has a high efficiency, by operating only the water electrolysis cell **51** when the bus voltage is low. Therefore, the DC bus control system **1** according

to the present embodiment can be efficiently charged with power from the DC bus **70**.

(130) In addition, it is possible to realize the DC bus control system **1** according to the present embodiment by using the sub-stabilizer **50** and the sub-stabilizer **55** having the same configuration, but by varying the charge threshold between them. Therefore, it is possible to realize the DC bus control system **1** according to the present embodiment by increasing the number of sub-stabilizer to be installed while not varying them in type but varying the conditions, making it possible to save the manufacturing cost and the installation cost.

(131) Although the foregoing descriptions have illustrated the cases in which two sub-stabilizers are provided, the same control may be performed on three or more sub-stabilizers. For example, when the number of sub-stabilizers is three, the thresholds may be set such that the number of sub-stabilizers to be operated becomes greater in an order of one, two, and three as the bus voltage becomes more deviated from the reference bus voltage.

(132) In addition, the threshold relationship may be reversed for the sub-stabilizer **50** and the sub-stabilizer **55**, and for the sub-stabilizer **60** and the sub-stabilizer **65**. For example, the sub-stabilizer **55** may be operated when the bus voltage is close to the reference bus voltage, and the sub-stabilizer **50** may be operated after the bus voltage becomes more deviated from the reference bus voltage. While the DC bus control system **1** is being operated, the threshold relationship may be reversed for the sub-stabilizer **50** and the sub-stabilizer **55**, and for the sub-stabilizer **60** and the sub-stabilizer **65**. For example, in a given period, the sub-stabilizer **50** may be operated when the bus voltage is close to the reference bus voltage, and in another period, the sub-stabilizer **55** may be operated when the bus voltage is close to the reference bus voltage.

Modified Example of the Operation of the DC Bus Control System **1**

Modified Example 1

(133) In the DC bus control system **1** according to the present embodiment, the input power into the water electrolysis cell **56** when the bus voltage is at the charge threshold **2** is 0. In the DC bus control system **1** according to the present embodiment, the output power from the fuel cell **66** when the bus voltage is at the discharge threshold **2** is 0.

(134) In the modified example 1, the input power into the water electrolysis cell **56** when the bus voltage is at the charge threshold **2** is offset from 0. In the modified example 1, the output power from the fuel cell **66** when the bus voltage is at the discharge threshold **2** is offset from 0. FIG. **12** is a diagram illustrating the modified example 1 of the operation of the DC bus control system **1** according to the present embodiment.

(135) In the modified example 1, it is possible to operate the water electrolysis cell **56** in a range in which it has a higher water electrolysis efficiency, by offsetting from 0, the input power into the water electrolysis cell **56** when the bus voltage is at the charge threshold **2**. In the modified example 1, it is possible to operate the fuel cell **66** in a range in which it has a higher power generation efficiency, by offsetting from 0, the output power from the fuel cell **66** when the bus voltage is at the discharge threshold **2**.

(136) The input/output voltage of the water electrolysis cell **51** and the fuel cell **61** at the discharge threshold **1** or the charge threshold **1** may also be offset from 0.

Modified Example 2

(137) In the DC bus control system **1** according to the present embodiment, the input power into the water electrolysis cell **56** when the bus voltage is between the charge threshold **1** and the charge threshold **2** is 0. In the DC bus control system **1** according to the present embodiment, the output power from the fuel cell **66** when the bus voltage is between the discharge threshold **1** and the discharge threshold **2** is 0.

(138) In the modified example 2, the input power into the water electrolysis cell **56** when the bus voltage is between the charge threshold **1** and the charge threshold **2** is offset from 0. In the modified example 2, the output power from the fuel cell **66** when the bus voltage is between the discharge threshold **1** and the discharge threshold **2** is offset from 0. FIG. **13** is a diagram

illustrating the modified example 2 of the operation of the DC bus control system **1** according to the present embodiment.

(139) In the modified example 2, it is possible to run the water electrolysis cell **56** idle and shorten its start-up time, by offsetting from 0, the input power into the water electrolysis cell **56** when the bus voltage is between the charge threshold **1** and the charge threshold **2**. In the modified example 2, it is possible to run the fuel cell **66** idle and shorten its start-up time, by offsetting from 0, the output power from the fuel cell **66** when the bus voltage is between the discharge threshold **1** and the discharge threshold **2**.

(140) The input/output voltage of the water electrolysis cell **51** and the fuel cell **61** at equal to or lower than the charge threshold **1** or at equal to or higher than the discharge threshold **1** may also be offset from 0.

Modified Example 3

(141) In the DC bus control system **1** according to the present embodiment, while the bus voltage is equal to or higher than the charge threshold **2**, the input power into the water electrolysis cell **56** is proportional to the bus voltage. In the DC bus control system **1** according to the present embodiment, while the bus voltage is equal to or lower than the discharge threshold **2**, the output power from the fuel cell **66** is proportional to the bus voltage.

(142) In the modified example 3, while the bus voltage is equal to or higher than the charge threshold **2**, the input power into the water electrolysis cell **56** changes nonlinearly with the bus voltage. In the modified example 3, while the bus voltage is equal to or lower than the discharge threshold **2**, the output power from the fuel cell **66** changes nonlinearly with respect to the bus voltage. FIG. **14** is a diagram illustrating the modified example 3 of the operation of the DC bus control system **1** according to the present embodiment.

(143) In the modified example 3, by changing the input power into the water electrolysis cell **56** nonlinearly with respect to the bus voltage while the bus voltage is equal to or higher than the charge threshold **2**, it is possible to ease the constraints on the device type and the control method, and to expand the selection and application of the device. In the modified example 3, by changing the output power from the fuel cell **66** nonlinearly with respect to the bus voltage while the bus voltage is equal to or lower than the discharge threshold **2**, it is possible to ease the constraints on the device type and the control method, and to expand the selection and application of the device.

(144) The input/output voltage of the water electrolysis cell **51** and the fuel cell **61** may also be changed nonlinearly.

Modified Example 4

(145) In the DC bus control system **1** according to the present embodiment, while the bus voltage is equal to or higher than the charge threshold **2**, the input power into the water electrolysis cell **51** is constant with respect to the bus voltage. In the DC bus control system **1** according to the present embodiment, while the bus voltage is equal to or lower than the discharge threshold **2**, the output power from the fuel cell **61** is constant with respect to the bus voltage.

(146) In the modified example 4, while the bus voltage is equal to or higher than the charge threshold **2** and lower than a charge threshold **3** that is higher than the charge threshold **2**, the input power into the water electrolysis cell **51** is changed with respect to the bus voltage. In the modified example 4, while the bus voltage is equal to or higher than the charge threshold **3**, the input voltage into the water electrolysis cell **51** is kept constant with respect to the bus voltage. In the modified example 4, while the bus voltage is equal to or lower than the discharge threshold **2** and higher than a discharge threshold **3** that is lower than the discharge threshold **2**, the output power from the fuel cell **61** is changed with respect to the bus voltage. In the modified example 4, while the bus voltage is equal to or lower than the discharge threshold **3**, the output voltage from the fuel cell **61** is kept constant with respect to the bus voltage. FIG. **15** is a diagram illustrating the modified example 4 of the operation of the DC bus control system **1** according to the present embodiment.

(147) In the modified example 4, by keeping the input voltage into the water electrolysis cell **51**

constant with respect to the bus voltage while the bus voltage is equal to or higher than the charge threshold **3**, it is possible to ease the constraints on the control method. In the modified example **4**, by keeping the output voltage from the fuel cell **61** constant with respect to the bus voltage while the bus voltage is equal to or lower than the discharge threshold **3**, it is possible to ease the constraints on the control method.

Modified Example 5

(148) In the foregoing description, the sub-stabilizer **50**, the sub-stabilizer **55**, the sub-stabilizer **60**, and the sub-stabilizer **65** of the DC bus control system **1** according to the present embodiment have been described. The sub-stabilizer **40** and the sub-stabilizer **45** may be operated in the same manner. For example, regarding the sub-stabilizer **40** and the sub-stabilizer **45**, it is possible to control the sub-stabilizer **40** and the sub-stabilizer **45** by using a charge threshold **1** and a discharge threshold **1** for the sub-stabilizer **40**, and using a charge threshold **2** and a discharge threshold **2** for the sub-stabilizer **45**. FIG. **16** is a diagram illustrating the modified example 5 of the operation of the DC bus control system **1** according to the present embodiment.

(149) As illustrated in FIG. **16**, the charge threshold **1** for the power storage device **41** of the sub-stabilizer **40** is lower than the charge threshold **2** for the power storage device **46** of the sub-stabilizer **45**. The discharge threshold **1** for the power storage device **41** of the sub-stabilizer **40** is higher than the discharge threshold **2** for the power storage device **46** of the sub-stabilizer **45**.

(150) Regarding the power storage device **41**, when the bus voltage increases from the reference bus voltage to become equal to or higher than the charge threshold **1**, power (input power) is supplied from the DC/DC converter **42A** of the power converter **42** into the power storage device **41**. The power (input power) from the DC/DC converter **42A** of the power converter **42** into the power storage device **41** is higher as the bus voltage is higher. When the bus voltage becomes equal to or higher than the charge threshold **2**, the power (input power) from the DC/DC converter **42A** of the power converter **42** into the power storage device **41** becomes constant.

(151) Regarding the power storage device **46**, when the bus voltage further increases from the reference bus voltage to become equal to or higher than the charge threshold **2**, power (input power) is supplied from the DC/DC converter of the power converter **47** into the power storage device **46**. The power (input power) from the DC/DC converter of the power converter **47** into the power storage device **46** is higher as the bus voltage is higher.

(152) When the bus voltage is between the charge threshold **1** and the charge threshold **2**, power is supplied into the power storage device **41** from the DC bus **70**, but no power is supplied into the power storage device **46**.

(153) Regarding the power storage device **41**, when the bus voltage decreases from the reference bus voltage to become equal to or lower than the discharge threshold **1**, power (output power) is supplied from the power storage device **41** to the DC/DC converter of the power converter **42**. The power (output power) from the power storage device **41** to the DC/DC converter of the power converter **42** is higher as the bus voltage is lower. When the bus voltage becomes equal to or lower than the discharge threshold **2**, the power (output power) from the power storage device **41** to the DC/DC converter of the power converter **42** becomes constant.

(154) Regarding the power storage device **46**, when the bus voltage decreases from the reference bus voltage to become equal to or lower than the discharge threshold **2**, power (output power) is supplied from the power storage device **46** to the DC/DC converter of the power converter **47**. The power (output power) from the power storage device **46** to the DC/DC converter of the power converter **47** is higher as the bus voltage is lower.

(155) When the bus voltage is between the discharge threshold **1** and the discharge threshold **2**, power is supplied from the power storage device **41** to the DC bus **70**, but no power is supplied from the power storage device **46**.

(156) The modified examples set forth above may be combined appropriately.

(157) The power storage device **31** is an example of the first charge/discharge element, and the

power converter **32** is an example of the first power converter. One selected from the sub-stabilizer **40**, the sub-stabilizer **50**, and the sub-stabilizer **60** is an example of the first sub-stabilizer, and the corresponding one selected from the sub-stabilizer **45**, the sub-stabilizer **55**, and the sub-stabilizer **65** is an example of the second sub-stabilizer. The power storage device **41** and the power storage device **46** are examples of the second charge/discharge element, the water electrolysis cell **51** and the water electrolysis cell **56** are examples of the charge element, and the fuel cell **61** and the fuel cell **66** are examples of the discharge element. The power converter **42**, the power converter **52**, the power converter **62**, the power converter **47**, the power converter **57**, and the power converter **67** are examples of the second power converter. The charge threshold **1** is an example of the first charge threshold, the charge threshold **2** is an example of the second charge threshold, the discharge threshold **1** is an example of the first discharge threshold, and the discharge threshold **2** is an example of the second discharge threshold.

(158) <Stability of the DC Bus Control System **1**>

(159) The stability of the DC bus control system **1** according to the present embodiment will be described below. In the following description, the main stabilizer **30** and the auxiliary device **35** are collectively referred to as the main stabilizers (Main Voltage Controllers (MVC)), the sub-stabilizer **40**, the sub-stabilizer **45**, the sub-stabilizer **50**, the sub-stabilizer **55**, the sub-stabilizer **60**, and the sub-stabilizer **65** are collectively referred to as the sub-stabilizers (Sub Voltage Controllers (SVC)).

(160) [Main Stabilizer]

(161) The main stabilizer controls the bus voltage V.sub.B. The bus voltage V.sub.B is determined by the main stabilizer in accordance with Equation 1. That is, the DC/DC converter of the main stabilizer is a bidirectional converter with a constant voltage output.

$$(162) \quad V_B = \frac{1}{C_{MVC}} \int_0^t I_{MVC} dt + V_{B0} = \frac{Q_{MVC}}{C_{MVC}} + V_{B0} \quad \text{Equation 1}$$

(163) C.sub.MVC represents the capacity of the power storage device of the main stabilizer, I.sub.MVC represents the current flowing through the power storage device of the main stabilizer (a charge current is assumed to be positive), V.sub.B0 represents a bias voltage, and Q.sub.MVC represents the quantity of charges charged in the power storage device of the main stabilizer.

(164) When the maximum suppliable/absorbable power is to be exceeded, the main stabilizer shifts to constant current control at the maximum suppliable/absorbable power of the power storage device, even while aiming at the above-defined V.sub.B as the control target voltage. In the constant current control, since all devices, including the sub-stabilizers, are in constant current mode, the bus voltage is automatically determined such that the sub-stabilizers absorb or discharge any surplus or deficit. Therefore, the bus voltage is controlled to be V.sub.B, and the maximum suppliable power is supplied from the main stabilizer in the constant current mode. That is, the DC bus control system **1** can control power exceeding the power that can be handled by the main stabilizer. However, when power exceeding the power that can be handled by the main stabilizer is supplied, the quantity of charges charged in the power storage device of the main stabilizer has a large absolute value and falls out of the stable control range of a typical sub-stabilizer.

(165) As described above, the DC bus control system **1** does not stop even when there is a power input/output that exceeds the handling capacity of the main stabilizer. However, the DC bus control system **1** does not respond to this in the normal linear responding manner. Moreover, the time for the DC bus control system **1** to recover is the time taken to discharge and absorb charges integrated for this time. The recovery time is approximately as long as the overload time.

(166) The DC bus control system **1** can realize as quick a recovery to the linear control as possible upon disappearance of the overload condition, by restricting Q.sub.MVC of Equation 1 such that the absolute value of Q.sub.MVC falls within the linear control range or becomes a value slightly larger than the linear control range. However, even if the DC bus control system **1** recovers to the linear control, the physical Q.sub.MVC will be offset. That is, the charge rate of the power storage device will be offset.

(167) [Sub-Stabilizer]

(168) A sub-stabilizer generates or absorbs a current (or may be defined by power) that is determined by the bus voltage. A sub-stabilizer has an interface to a constant-current source and to a constant-current load in order for power to be input therein or output therefrom regardless of the value of the bus voltage $V_{sub.B}$. The current $I_{sub.SVC}$ to be generated or absorbed is typically expressed as Equation 2.

(169) $I_{SVC} = I_{SVC}(V_B)$ Equation 2

(170) Among sub-stabilizers, a bidirectional device capable of generation and absorption, a device only capable of generation, and a device only capable of absorption can be expressed as differences in the function system of the function $I_{sub.SVC}()$. Here, the direction from the DC bus, in which the sub-stabilizer absorbs power, is indicated by the positive sign. The definition of the sign may be reversed.

(171) For example, a device only capable of absorption is expressed by the following expressions.

(172)
$$\begin{aligned} I_{SVC} &= a(V_B - b); & a, b > 0, V_B - b > 0 \\ I_{SVC} &= 0; & V_B - b > 0 \end{aligned}$$

(173) For example, a device only capable of generation is expressed by the following expressions.

(174)
$$\begin{aligned} I_{SVC} &= -a(V_B - b); & a, b > 0, V_B - b > 0 \\ I_{SVC} &= 0; & V_B - b < 0 \end{aligned}$$

(175) In the above example, “a” has the conductance dimension. Also, in a case where control is based on power, similar formulation can be achieved by change in the dimension of the coefficient.

(176) [External Devices]

(177) External devices such as a power-consuming device and a power generation device are connected to the DC bus as the current mode (for example, as a constant-current source). The total current consumption Text of the external devices is expressed by Equation 3. Power consumption is indicated by the positive sign.

(178) $I_{ext} = I_{ext}(t)$ Equation 3

[Control Characteristics]

(179) Considering the conversion efficiency and the bias current, the current $I_{sub.MVC}$ in Equation 1 may be the actual charge/discharge current of the power storage device or may be the current on the DC bus side. Here, the current $I_{sub.MVC}$ is assumed to be the current of the power storage device. The power balance on the DC bus is expressed by Equation 4. B represents an offset current.

(180) $kI_{MVC} + I_{SVC} + I_{ext} + B = 0$ Equation 4

(181) From Equations 1 and 2, the following relationship can be obtained.

(182)
$$\begin{aligned} \frac{dV_B}{dt} &= \frac{I_{MVC}}{C_{MVC}} \\ \frac{dI_{SVC}}{dt} &= \frac{\partial I_{SVC}}{\partial V_B} \frac{dV_B}{dt} \end{aligned}$$

(183) Therefore, using the above relationship, the following relationship can be derived.

(184) $kC_{MVC} \frac{d^2 V_B}{dt^2} + \frac{\partial I_{SVC}}{\partial V_B} \frac{dV_B}{dt} + \frac{dI_{ext}}{dt} = 0$

(185) Here, if the power consumption of the external devices is constant, the following relationship will be exhibited.

(186) $\frac{dI_{ext}}{dt} = 0$

(187) Therefore, as shown in Equation 5, the DC bus control system 1 exhibits the response of the primary delay system.

$$(188) \quad \frac{kC_{MVC}}{\frac{\partial I_{SVC}}{\partial V_B}} \frac{dV_B}{dt} + V_B - V_0 = 0 \quad \text{Equation 5}$$

$$V_B = V_0 + \exp(-t / \frac{kC_{MVC}}{\frac{\partial I_{SVC}}{\partial V_B}})$$

(189) When the external power consumption is constant, the bus voltage converges to a constant value at a predetermined time constant. At this time, the I.sub.MVC becomes zero. Therefore, the DC bus control system 1 according to the present embodiment can operate stably without oscillation.

(190) Even in a case of not taking measures against overloading, charging efficiency control is at least necessary, in order to enable a long-time operation. The efficiency of the power storage device used in the main stabilizer is finite, and it is impossible to estimate the efficiency accurately. The efficiency varies depending on the temperature of the device and various parameters. Moreover, in the control, the power storage device is continuously charged or discharged. Even if a calculated Q.sub.MVC is constant in the control, it may be deviated from the Q.sub.MVC of the actual device, and the power storage device may be depleted or saturated in a relatively short time.

(191) The charging efficiency of the power storage device can be estimated from the terminal voltage. However, since the terminal voltage depends on the charge/discharge current, it is necessary to measure the terminal voltage by bringing the charge/discharge current to be zero. By utilizing a nature that the charge/discharge current being zero is automatically achieved when the external devices are stable, it is possible to incorporate the charging efficiency control by using the following equation.

$$(192) \quad V_B = \frac{1}{C_{MVC}} \left\{ \int_0^t I_{MVC} dt - \frac{1}{T_{SoC}} \int_{\text{.Math. } I_{MVC} \text{ .Math. } < I_{th}} (V_{SoC} - V_T) dt \right\} + V_{B0}$$

(193) Note that V.sub.SoC represents the terminal voltage of the power storage device, and V.sub.T represents the control target value of the terminal voltage of the power storage device. The integration of the second term is meant to be performed only when the absolute value of I.sub.MVC is smaller than a threshold I.sub.th. The threshold I.sub.th is a threshold current value that is set as an empirical value. Practically, the above equation is calculated and controlled by discretization.

(194) Moreover, in addition to the above-described operating method of leveling the operations of the plurality of sub-stabilizers, an operating method of taking into consideration the reaction responsiveness, the charging capacity, and the like of each sub-stabilizer and prioritizing the charge power and the discharge power is also conceivable. For example, some sub-stabilizers may be operated in a state close to a fully charged state, while other sub-stabilizers may be operated in a state of being almost completely discharged.

(195) Although the present invention has been described based on the above embodiments, the present invention is not limited to the above embodiments, and various modifications are applicable within the scope of the claims.

Claims

1. A direct-current bus control system for controlling power variation in a DC bus connecting an input power source and a load, the direct-current bus control system comprising: a main stabilizer including a first charge/discharge element and a first power converter; and a plurality of sub-stabilizers each including a second charge/discharge element, a charge element, or a discharge element, and a second power converter, wherein the first power converter is configured to obtain a bus voltage target value corresponding to a power storage quantity index of the first charge/discharge element, and to cause the first charge/discharge element and the DC bus to bidirectionally transmit or receive a DC power to or from each other such that a voltage of the DC bus becomes equal to the bus voltage target value, the second power converter is configured to

obtain a current target value in accordance with a difference between the voltage of the DC bus and a threshold regarding charging or discharging of the second charge/discharge element, the charge element, or the discharge element, and to cause the second charge/discharge element, the charge element, or the discharge element and the DC bus to transmit or receive a DC power to or from each other such that a current equal to the current target value flows through the second charge/discharge element, the charge element, or the discharge element, the plurality of sub-stabilizers include a first sub-stabilizer and a second sub-stabilizer including the charge element, the second power converter of the first sub-stabilizer is configured to supply the current equal to the current target value obtained by the second power converter of the first sub-stabilizer from the DC bus to the charge element of the first metal-stabilizer when the voltage of the DC bus is higher than a first charge threshold, and the second power converter of the second sub-stabilizer is configured to stop supplying a current from the DC bus to the charge element of the second sub-stabilizer or to supply a constant current from the DC bus to the charge element of the second sub-stabilizer regardless of the voltage of the DC bus when the voltage of the DC bus is higher than the first charge threshold and lower than a second charge threshold that is higher than the first charge threshold, and to supply the current equal to the current target value obtained by the second power converter of the second sub-stabilizer from the DC bus to the charge element of the second sub-stabilizer when the voltage of the DC bus is higher than the second charge threshold.

2. The direct-current bus control system according to claim 1, wherein when the voltage of the DC bus is higher than the second charge threshold, the second power converter of the first sub-stabilizer supplies a constant current from the DC bus to the charge element of the first sub-stabilizer regardless of the voltage of the DC bus.

3. The direct-current bus control system according to claim 1, wherein the charge element of each of the first sub-stabilizer and the second sub-stabilizers is a water electrolysis cell.

4. The direct-current bus control system according to claim 1, further comprising: a renewable energy power source system as the input power source.

5. The direct-current bus control system according to claim 1, further comprising: the load.

6. A direct-current bus control system for controlling power variation in a DC bus connecting an input power source and a load, the direct-current bus control system comprising: a main stabilizer including a first charge/discharge element and a first power converter; and a plurality of sub-stabilizers each including a second charge/discharge element, a charge element, or a discharge element, and a second power converter, wherein the first power converter is configured to obtain a bus voltage target value corresponding to a power storage quantity index of the first charge/discharge element, and to cause the first charge/discharge element and the DC bus to bidirectionally transmit or receive a DC power to or from each other such that a voltage of the DC bus becomes equal to the bus voltage target value, the second power converter is configured to obtain a current target value in accordance with a difference between the voltage of the DC bus and a threshold regarding charging or discharging of the second charge/discharge element, the charge element, or the discharge element, and to cause the second charge/discharge element, the charge element, or the discharge element and the DC bus to transmit or receive a DC power to or from each other such that a current equal to the current target value flows through the second charge/discharge element, the charge element, or the discharge element, the plurality of sub-stabilizers include a first sub-stabilizer and a second sub-stabilizer including the discharge element, the second power converter of the first sub-stabilizer is configured to supply the current equal to the current target value obtained by the second power converter of the first sub-stabilizer to the DC bus from the discharge element of the first sub-stabilizer when the voltage of the DC bus is lower than a first discharge threshold, and the second power converter of the second sub-stabilizer is configured to stop supplying a current to the DC bus from the discharge element of the second sub-stabilizer or to supply a constant current to the DC bus from the discharge element of the second sub-stabilizer regardless of the voltage of the DC bus when the voltage of the DC bus is lower than

the first discharge threshold and higher than a second discharge threshold that is lower than the first discharge threshold, and to supply the current equal to the current target value obtained by the second power converter of the second sub-stabilizer to the DC bus from the discharge element of the second sub-stabilizer when the voltage of the DC bus is lower than the second discharge threshold.

7. The direct-current bus control system according to claim 6, wherein when the voltage of the DC bus is lower than the second discharge threshold, the second power converter of the first sub-stabilizer supplies a constant current to the DC bus from the discharge element of the first sub-stabilizer regardless of the voltage of the DC bus.

8. The direct-current bus control system according to claim 6, wherein the discharge element of each of the first sub-stabilizer and the second sub-stabilizers is a fuel cell.

9. A direct-current bus control system for controlling power variation in a DC bus connecting an input power source and a load, the direct-current bus control system comprising: a main stabilizer including a first charge/discharge element and a first power converter; and a plurality of sub-stabilizers each including a second charge/discharge element, a charge element, or a discharge element, and a second power converter, wherein the first power converter is configured to obtain a bus voltage target value corresponding to a power storage quantity index of the first charge/discharge element, and to cause the first charge/discharge element and the DC bus to bidirectionally transmit or receive a DC power to or from each other such that a voltage of the DC bus becomes equal to the bus voltage target value, the second power converter is configured to obtain a current target value in accordance with a difference between the voltage of the DC bus and a threshold regarding charging or discharging of the second charge/discharge element, the charge element, or the discharge element, and to cause the second charge/discharge element, the charge element, or the discharge element and the DC bus to transmit or receive a DC power to or from each other such that a current equal to the current target value flows through the second charge/discharge element, the charge element, or the discharge element, the plurality of sub-stabilizers include a first sub-stabilizer and a second sub-stabilizer including the second charge/discharge element, the second power converter of the first sub-stabilizer is configured to supply the current equal to the current target value obtained by the second power converter of the first sub-stabilizer from the DC bus to the second charge/discharge element of the first sub-stabilizer when the voltage of the DC bus is higher than a first charge threshold, the second power converter of the second sub-stabilizer is configured to stop supplying a current from the DC bus to the second charge/discharge element of the second sub-stabilizer or to supply a constant current from the DC bus to the second charge/discharge element of the second sub-stabilizer regardless of the voltage of the DC bus when the voltage of the DC bus is higher than the first charge threshold and lower than a second charge threshold that is higher than the first charge threshold, and to supply the current equal to the current target value obtained by the second power converter of the second sub-stabilizer from the DC bus to the second charge/discharge element of the second sub-stabilizer when the voltage of the DC bus is higher than the second charge threshold, the second power converter of the first sub-stabilizer is configured to supply the current equal to the current target value obtained by the second power converter of the first sub-stabilizer from the second charge/discharge element of the first sub-stabilizer to the DC bus when the voltage of the DC bus is lower than a first discharge threshold, and the second power converter of the second sub-stabilizer is configured to stop supplying a current from the second charge/discharge element of the second sub-stabilizer to the DC bus or to supply a constant current from the second charge/discharge element of the second sub-stabilizer to the DC bus regardless of the voltage of the DC bus when the voltage of the DC bus is lower than the first discharge threshold and higher than a second discharge threshold that is lower than the first discharge threshold, and to supply the current equal to the current target value obtained by the second power converter of the second sub-stabilizer from the second charge/discharge element of the second sub-stabilizer to the DC bus when the voltage of the

DC bus is lower than the second discharge threshold.

10. The direct-current bus control system according to claim 9, wherein when the voltage of the DC bus is higher than the second charge threshold, the second power converter of the first sub-stabilizer supplies a constant current from the DC bus to the second charge/discharge element of the first sub-stabilizer regardless of the voltage of the DC bus, and when the voltage of the DC bus is lower than the second discharge threshold, the second power converter of the first sub-stabilizer supplies a constant current from the second charge/discharge element of the second sub-stabilizer to the DC bus regardless of the voltage of the DC bus.
