

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12408009
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Cordes; Kevin et al.

Adaptive push to talk switch detection

Abstract

Systems and methods for detecting a state of at least one button are disclosed herein. The method detects a first signal of a headset of a user. The first signal is indicative of the headset being coupled to a device. The headset has a microphone and at least one button. The method determines, based on the detected first headset signal, a first voltage of the microphone, and sets, based on the first voltage of the microphone, a threshold voltage for detecting a state of the at least one button. The method stores the threshold voltage and determines a second voltage of the microphone. The method compares the second voltage of the microphone and the stored threshold voltage, and generates, based on the comparison, a signal indicative of a state of the at least one button.

Inventors: Cordes; Kevin (Miller Place, NY), Chang; Tong-Hsiao (Manhasset, NY)

Applicant: ZEBRA TECHNOLOGIES CORPORATION (Lincolnshire, IL)

Family ID: 88192798

Assignee: Zebra Technologies Corporation (Lincolnshire, IL)

Appl. No.: 18/121897

Filed: March 15, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20230319516 A1	Oct. 05, 2023

Related U.S. Application Data

us-provisional-application US 63325773 20220331

Publication Classification

Int. Cl.: H04W4/10 (20090101); G06F3/16 (20060101)

U.S. Cl.:

CPC H04W4/10 (20130101); G06F3/165 (20130101);

Field of Classification Search

CPC: H04B (1/3827); H04B (1/385); H04B (1/46); H04M (1/6041); H04M (1/6058); H04M (1/6066); H04M (1/72409); H04R (3/00); H04R (2499/11); H04R (1/1041); H04R (5/033); H04R (2201/107); H04R (2420/07); H04R (2420/09); H04W (4/10); H04W (4/16)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5555533	12/1995	Peck	367/901	H04B 11/00
2009/0296952	12/2008	Pantfoerder	381/74	H04R 1/1041
2012/0238237	12/2011	Crestol	455/41.3	H04W 4/10
2014/0315502	12/2013	Lassally	455/90.2	H04B 1/005
2015/0105117	12/2014	Larson	455/518	H04M 1/6066
2015/0244406	12/2014	Abdullah	455/90.2	H04M 1/6041
2016/0309251	12/2015	Poulsen	N/A	H04M 1/6058

Primary Examiner: Trandai; Cindy

Background/Summary

BACKGROUND

(1) A wired analog headset with a 3.5 mm connector (e.g., a phone connector) can connect to a device (e.g., a laptop, tablet, smartphone, etc.) and can support various functions via a plurality of headset buttons (e.g., volume up, volume down, play, stop, etc.). Each button, when pressed by a user, positions a shunt resistor across the microphone connection. These shunt resistors are low value resistors and can sway the resulting voltage level away from the nominal microphone audio signal level to avoid false button press detection. A headset can implement a push to talk (PTT) application via a PTT button which requires a user to press and hold the PTT button when speaking and to release the PTT button when listening. The PTT button, when pressed, positions a resistor across a microphone connection to the device to indicate that PTT is active. A PTT button is not well suited for use with a low value resistor because it can attenuate the microphone audio signal.

Description

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWINGS

(1) The accompanying figures, where like reference numerals refer to identical or functionally similar elements throughout the separate views, together with the detailed description below, are incorporated in and form part of the specification, and serve to further illustrate embodiments of

concepts that include the claimed invention, and explain various principles and advantages of those embodiments.

(2) FIG. 1 is a diagram of a wired analog headset.

(3) FIG. 2 is a circuit diagram illustrating a PTT application of the wired analog headset of FIG. 1.

(4) FIG. 3 is a table illustrating current consumption of a microphone.

(5) FIG. 4A is a circuit diagram of a microphone illustrating a PTT application when a PTT button is open.

(6) FIG. 4B is a circuit diagram of a microphone illustrating a PTT application when a PTT button is closed.

(7) FIG. 5 is a circuit diagram illustrating an embodiment of the system of the present disclosure.

(8) FIG. 6 is a flowchart illustrating processing steps carried out by the system of FIG. 5.

(9) FIG. 7 is a circuit diagram illustrating another embodiment of the system of the present disclosure.

(10) FIG. 8 is a flowchart illustrating processing steps carried out by the system of FIG. 7 for determining and setting a PTT reference voltage.

(11) FIG. 9 is a flowchart illustrating processing steps carried out by the system of FIG. 7 for determining a valid PTT activation.

(12) FIG. 10 is a flowchart illustrating processing steps carried out by the system of FIG. 7 for determining a valid PTT deactivation.

(13) Skilled artisans will appreciate that elements in the figures are illustrated for simplicity and clarity and have not necessarily been drawn to scale. For example, the dimensions of some of the elements in the figures may be exaggerated relative to other elements to help to improve understanding of embodiments of the present invention.

(14) The system and method components have been represented where appropriate by conventional symbols in the drawings, showing only those specific details that are pertinent to understanding the embodiments of the present invention so as not to obscure the disclosure with details that will be readily apparent to those of ordinary skill in the art having the benefit of the description herein.

DETAILED DESCRIPTION

(15) Examples disclosed herein are directed to a method for detecting a state of at least one button, comprising: detecting a first signal of a headset of a user, the first signal being indicative of the headset being coupled to a device, and the headset having a microphone and at least one button; determining, based on the detected first headset signal, a first voltage of the microphone; setting, based on the first voltage of the microphone, a threshold voltage for detecting a state of the at least one button; storing the threshold voltage; determining a second voltage of the microphone; comparing the second voltage of the microphone and the stored threshold voltage; and generating, based on the comparison, a signal indicative of a state of the at least one button.

(16) Additional examples disclosed herein are directed to a system for detecting a state of at least one button comprising a memory configured to store computer executable instructions; and a processor configured to interface with the memory and execute the computer executable instructions to cause the processor to: detect a first signal of a headset of a user, the first signal being indicative of the headset being coupled to a device, and the headset having a microphone and at least one button, determine, based on the detected first headset signal, a first voltage of the microphone, set, based on the first voltage of the microphone, a threshold voltage for detecting a state of the at least one button, store the threshold voltage in the memory, determine a second voltage of the microphone, compare the second voltage of the microphone and the stored threshold voltage, and generate, based on the comparison, a signal indicative of a state of the at least one button.

(17) Additional examples disclosed herein are directed to a tangible machine-readable medium comprising instructions for detecting a state of at least one button that, when executed, cause a machine to at least: detect a first signal of a headset of a user, the first signal being indicative of the

headset being coupled to a device, and the headset having a microphone and at least one button; determine, based on the detected first headset signal, a first voltage of the microphone; set, based on the first voltage of the microphone, a threshold voltage for detecting a state of the at least one button; store the threshold voltage; determine a second voltage of the microphone; compare the second voltage of the microphone and the stored threshold voltage; and generate, based on the comparison, a signal indicative of a state of the at least one button.

(18) As mentioned above, a headset can implement a PTT application via a PTT button which requires a user to press and hold a PTT button when speaking and release the PTT button when listening. The PTT button, when pressed, positions a resistor across a microphone connection to the device to indicate that PTT is active. A PTT button is not well suited for use with a low value resistor because it can attenuate the microphone audio signal.

(19) A known approach includes positioning a higher value resistor (e.g., 8.66K Ω) across the PTT button to minimize attenuation on the microphone audio signal. A device can be interrupted when a resistor is connected in parallel with the microphone. This interrupt is generated by a comparison of the microphone signal to a fixed threshold. For example, when the resistor is connected or disconnected across the microphone (e.g., a PTT button is pressed or released), the threshold is crossed, thus creating an interrupt signal (e.g., via a comparator). However, this approach can make PTT button detection challenging because microphone current can vary greatly from headset to headset. Therefore, setting a fixed universal threshold for all headsets is implausible.

(20) Accordingly, it would be highly beneficial to develop a system and method that can determine and utilize a threshold that is adaptable for different headsets where the threshold is determined when the headset is connected to a device. The systems and methods of the present disclosure address these and other needs.

(21) FIG. 1 is a diagram of a wired analog headset **10** and components thereof. The headset **10** comprises a connector **12** (e.g., a phone connector), a PTT button **14** having a clip **16** and a cord wrap **18**, a rotatable earpiece **20** and a cord **22** that couples the connector **12**, PTT button **14** and rotatable earpiece **20**. The clip **16** allows a user to attach the PTT button **14** to clothing of the user and the cord wrap **18** is an annular recess along a periphery of the PTT button **14** that allows for wrapping the cord **22** when storing the headset **10**.

(22) FIG. 2 is a circuit diagram **50** illustrating a PTT application of the wired analog headset **10** of FIG. 1. As shown in FIG. 2, a connector **12** is coupled to several components including electrostatic discharge suppressors **58a**, **58b** and **58c**; capacitors **60a**, **60b**, and **60c**; a potentiometer **62**; a resistor **64** (e.g., 8.66K Ω); a PTT switch **66** (e.g., a PTT button **14**); a microphone **68**; and a speaker **70**. The connector **12** is coupled to these components via a microphone signal **52**, ground signals **54** and a left audio signal **56**. The headset **10** can include a PTT feature that allows a user to communicate. Built into the headset is a switch **66** (e.g., a PTT button **14**) that the user can press when he/she wishes to speak. As shown in FIG. 2, the switch **66** positions a resistor **64** (e.g., 8.66K Ω) across the microphone connection **52** to a mobile device to indicate PTT has been activated.

(23) FIG. 3 is a table **80** illustrating current consumption of a microphone. Microphone current can vary greatly from headset to headset. When a resistor is connected in parallel with the microphone, a host device is interrupted. This interrupt is generated by a comparison of the microphone signal to a fixed threshold. For example, when the resistor is connected or disconnected across the microphone (e.g., a PTT button is pressed or released), the threshold is crossed, thus creating an interrupt signal (e.g., via a comparator). Since microphone current can vary greatly from headset to headset, setting a fixed universal threshold for all headsets is implausible.

(24) FIGS. 4A and 4B are circuit diagrams of a commonly used headset microphone respectively illustrating a PTT application when a PTT button is open and when the PTT button is closed. As shown in FIG. 4A, the circuit diagram **100** illustrates a PTT application when a PTT button **104** is open (e.g., released). The circuit diagram **100** includes several signals and components including microphone voltage **102** (e.g., V.sub.mic); PTT button **104**; microphone bias voltage **106** (e.g.,

Mic_Bias); resistors **108a** (e.g., source resistor R.sub.s), **108b** (e.g., bias resistor R.sub.b), and **108c** (e.g., gate resistor R.sub.g); junction-gate field-effect transistor (JFET) **110**; microphone **112**; and ground **114**. The microphone **112** generates internal current I.sub.dc when the Mic_Bias voltage **106** is applied externally via the bias resistor R.sub.b **108b**. This current induces microphone current I.sub.mic through the JFET **110** converter. Since microphone current I.sub.mic is the only current through the bias resistor R.sub.b **108b**, the voltage across V.sub.mic **102** can be given by Equation 1 below:

$$V_{\text{sub.mic}} = \text{Mic_Bias} - I_{\text{sub.mic}} * R_{\text{sub.b}} \quad \text{Equation 1}$$

(25) As shown in FIG. 4B, the circuit diagram **150** illustrates a PTT application when a PTT button **104** is closed (e.g., pressed). Microphone current I.sub.mic and a button current I.sub.button run through the bias resistor R.sub.b **108b** when the PTT button **104** is closed. This results in a voltage change of $R_{\text{sub.b}} * I_{\text{sub.button}}$ across V.sub.mic **102**. As such, two distinctive voltages can be detected. These two voltages can vary from headset to headset when internal current I.sub.dc or direct current (DC) I.sub.mic is not well specified by a microphone manufacturer (e.g., Electret). Thus, there is no defined voltage range for V.sub.mic **102** when a Mic_Bias voltage **106** is applied. Therefore, a PTT detector must account for varying biased voltages and voltage differentials. Accordingly, it would be highly beneficial to develop a system and method that can determine an adaptable voltage threshold for different headsets, upon the insertion of a headset into a device, to facilitate PTT detection. The systems and methods of the present disclosure address these and other needs.

(26) The systems and methods of the present disclosure can determine, at the insertion of a headset into a device, a voltage threshold adaptable to the headset. Upon insertion of a headset, a host is notified by a HEADSET_DETECT signal. Once detected, the host can utilize an analog to digital converter (ADC) to measure a microphone voltage (e.g., V.sub.mic). As mentioned above, this voltage can vary from headset to headset and has a direct relationship to the microphone current. The microphone voltage is scaled to an appropriate threshold (e.g., $0.87 * V_{\text{sub.mic}}$). This scaling is dependent on a PTT resistor and a Mic_Bias voltage, which are fixed and have a tighter tolerance than the microphone current. When a user presses the PTT button, the PTT resistor pulls down on the V.sub.mic node thereby reducing its voltage. This change in voltage thus crosses the threshold. Crossing the threshold interrupts the host and, in response, the host executes actions required for PTT. The threshold is reset upon the removal of the headset.

(27) FIG. 5 is a circuit diagram **200** illustrating an embodiment of the system of the present disclosure. The circuit diagram **200** includes several signals and components including a headset **202**, a microphone bias voltage **212** (e.g., Mic_Bias); resistors **214**, **216**, and **232**; a capacitor **218**; an insertion detection **222**; a microcontroller **224**, a 3.3 voltage source **230**; a metal oxide semiconductor field effect transistor (MOSFET) **234**; grounds **210**, **220** and **236**; and a coder-decoder (CODEC) **238**. The headset **202** is directly or indirectly coupled to these components via signal lines, the microcontroller **224**, and the CODEC **238**. The headset **202** includes a microphone **204**, a resistor **206** (e.g., 8.66K Ω), and a switch **208** (e.g., single-pole single-throw), the microcontroller **224** includes an ADC **226** and general-purpose input/output (GPIO) pins **228a** and **228b**, and the CODEC **238** includes a jack detection (JD) pin **240**, a microphone audio (e.g., MIC2-R) pin **242**; and a GPIO pin **244**.

(28) As shown in FIG. 5, on insertion of the headset **202**, the system measures a voltage of a headset microphone **204** using the ADC **226** of the microcontroller **224**. The system determines a voltage threshold and sets the threshold in the system memory. The system monitors a microphone signal to determine when the microphone signal crosses the threshold. When the microphone signal crosses the threshold (e.g., in either direction), the GPIO pin **228a** is triggered to indicate PTT detection (e.g., activation or deactivation) to the CODEC **238**. In response, the CODEC **238** transmits a signal **240** indicative of PTT detection via a universal serial bus (USB) human interface device (HID) to the host system. The system resets the threshold when the headset **202** is

disconnected.

(29) FIG. 6 is a flowchart 250 illustrating processing steps carried out by the system of FIG. 5. Beginning in step 252, the system enters a boot up state. In step 254, the system determines whether a headset 202 is detected. For example, the system determines whether the headset 202 is coupled to a device. If the system detects a headset 202, then the process proceeds to step 256. Alternatively, if the system does not detect a headset 202, the process returns to step 254. Then, in step 256, the system measures a first voltage of the microphone 204 (e.g., $V_{\text{sub.mic1}}$). In step 258, the system sets a threshold (e.g., $0.87 \cdot V_{\text{sub.mic1}}$) for PTT and, in step 260, the system measures a second voltage of the microphone 204 (e.g., $V_{\text{sub.mic2}}$). In step 262, the system determines whether a headset 202 is detected. For example, the system determines whether the headset 202 remains coupled to a device. If the system detects a headset 202, then the process proceeds to step 266. Alternatively, if the system does not detect a headset 202, the process proceeds to step 264 and, in step 264, the system resets the threshold for PTT before returning to step 254. In step 266, the system determines whether the second microphone voltage $V_{\text{sub.mic2}}$ is less than the threshold. If the system determines the second microphone voltage $V_{\text{sub.mic2}}$ is less than the threshold, then the process proceeds to step 270. In step 270, the system generates an enable PTT indication (e.g., a signal). The process then returns to step 260. Alternatively, if the system determines the second microphone voltage $V_{\text{sub.mic2}}$ is not less than the threshold, then the process proceeds to step 268. In step 268, the system generates a disable PTT indication (e.g., a signal). The process then returns to step 260.

(30) FIG. 7 is a circuit diagram 300 illustrating another embodiment of the system of the present disclosure. The circuit diagram 300 includes several signals and components including a headset microphone 302, a microphone bias voltage 304 (e.g., Mic_Bias_1); a bias resistor 306; a microphone bias voltage 312 (e.g., Mic_Bias_1) and voltage at collector 314 (e.g., $V_{\text{CC_1}}$) of a potentiometer 310 (e.g., a digital trimming potentiometer or Digi Trimpot); a low pass filter (LPF) 320; an ADC 322; a supply voltage 326 (e.g., $V_{\text{CC_2}}$) of a voltage comparator 324; and grounds 308, 316 and 326. The system can be implemented via hardware components and software. The system captures a voltage level of the headset microphone 302 when the headset is inserted and utilizes the voltage level of the headset microphone 302 as a baseline to accurately detect subsequent voltage changes based on PTT button press and release. As shown in FIG. 7, the system filters a signal of the headset microphone 302 (e.g., MIC Signal) via an LPF 320 before transmitting the MIC Signal to each of a voltage comparator 324 and an ADC 322. For example, the LPF 320 transmits a first microphone voltage signal (e.g., Voltage_MIC_1) to the voltage comparator 324 and a second microphone voltage signal (e.g., Voltage_MIC_2) to the ADC 322. The ADC 322 senses the Voltage_MIC_2 signal when a headset is inserted. Subsequently, the system generates a PTT button voltage detection reference and stores it in a potentiometer 310 (e.g., a digital trimming potentiometer or Digi Trimpot) via an integrated circuit (I2C) interface. The system compares the Voltage_MIC_1 signal with the detection reference via the voltage comparator 324 and transmits a PTT interrupt signal when the Voltage_MIC_1 signal crosses the detection reference. Additionally, the system measures, via a central processing unit (CPU), the Voltage_MIC_2 signal to validate a PTT button status.

(31) FIG. 8 is a flowchart 330 illustrating processing steps carried out by the system of FIG. 7 for determining and setting a PTT reference voltage. Beginning in step 332, the system detects an insertion of a headset. In step 334, the system detects a voltage level of a PTT signal via an ADC. Then, in step 336, the system determines whether the detected voltage level of the PTT signal is greater than 1.9 volts. If the system determines the detected voltage level of the PTT signal is not greater than 1.9 volts, then the process proceeds to step 330. In step 330, the system effects a predetermined delay (e.g., 10 ms) before returning to step 334. Alternatively, if the system determines the detected voltage level of the PTT signal is greater than 1.9 volts, then the process proceeds to step 340. In step 340, the system determines a threshold for PTT and sets a trigger

threshold. In step **342**, the system determines a PTT button press based on a High and Low interrupt detection range of the ADC.

(32) FIG. **9** is a flowchart **350** illustrating processing steps carried out by the system of FIG. **7** for determining a PTT activation. Beginning in step **352**, the system detects a PTT low trigger interrupt signal. In step **354**, the system effects a predetermined delay (e.g., 10 ms). In step **356**, the system determines whether a voltage level of the detected PTT low trigger interrupt signal is within a PTT range. If the system determines the voltage level of the detected PTT low trigger interrupt signal is within a PTT range, then the process proceeds to step **358**. In step **358**, the system determines that a PTT button is pressed (e.g., by a user) and the process ends. Alternatively, if the system determines the voltage level of the detected PTT low trigger interrupt signal is not within a PTT range, then the process proceeds to step **360**. In step **360**, the system determines whether the voltage level of the detected PTT low trigger interrupt signal is less than a minimum of the PTT range. If the system determines the voltage level of the detected PTT low trigger interrupt signal is less than a minimum of the PTT range, then the process proceeds to step **362**. Then, in step **362**, the system determines that a PTT button is not pressed (e.g., by a user) and the process ends. Alternatively, if the system determines the voltage level of the detected PTT low trigger interrupt signal is not less than a minimum of the PTT range, then the process proceeds to step **364**. In step **364**, the system determines whether the number of retry attempts is greater than a predetermined threshold (e.g., an integer value such as 3). If the system determines the number of retry attempts is greater than a predetermined threshold, then the process proceeds to step **362**. Then, in step **362**, the system determines that a PTT button is not pressed (e.g., by a user) and the process ends. Alternatively, if the system determines the number of retry attempts is not greater than a predetermined threshold, then the process returns to step **354**.

(33) FIG. **10** is a flowchart **380** illustrating processing steps carried out by the system of FIG. **7** for determining a PTT deactivation. Beginning in step **382**, the system detects a PTT high trigger interrupt signal. In step **384**, the system effects a predetermined delay (e.g., 10 ms). In step **386**, the system determines whether a voltage level of the detected PTT high trigger interrupt signal is within a PTT range. If the system determines the voltage level of the detected PTT high trigger interrupt signal is within a PTT range, then the process proceeds to step **388**. In step **388**, the system determines that a PTT button is not released (e.g., by a user) and the process ends. Alternatively, if the system determines the voltage level of the detected PTT high trigger interrupt signal is not within a PTT range, then the process proceeds to step **390**. In step **390**, the system determines that a PTT button is released (e.g., by a user) and the process ends.

(34) In the foregoing specification, specific embodiments have been described. However, one of ordinary skill in the art appreciates that various modifications and changes can be made without departing from the scope of the invention as set forth in the claims below. Accordingly, the specification and figures are to be regarded in an illustrative rather than a restrictive sense, and all such modifications are intended to be included within the scope of present teachings.

(35) The benefits, advantages, solutions to problems, and any element(s) that may cause any benefit, advantage, or solution to occur or become more pronounced are not to be construed as a critical, required, or essential features or elements of any or all the claims. The invention is defined solely by the appended claims including any amendments made during the pendency of this application and all equivalents of those claims as issued.

(36) Moreover in this document, relational terms such as first and second, top and bottom, and the like may be used solely to distinguish one entity or action from another entity or action without necessarily requiring or implying any actual such relationship or order between such entities or actions. The terms “comprises,” “comprising,” “has,” “having,” “includes,” “including,” “contains,” “containing” or any other variation thereof, are intended to cover a non-exclusive inclusion, such that a process, method, article, or apparatus that comprises, has, includes, contains a list of elements does not include only those elements but may include other elements not expressly

listed or inherent to such process, method, article, or apparatus. An element preceded by “comprises . . . a”, “has . . . a”, “includes . . . a”, “contains . . . a” does not, without more constraints, preclude the existence of additional identical elements in the process, method, article, or apparatus that comprises, has, includes, contains the element. The terms “a” and “an” are defined as one or more unless explicitly stated otherwise herein. The terms “substantially”, “essentially”, “approximately”, “about” or any other version thereof, are defined as being close to as understood by one of ordinary skill in the art, and in one non-limiting embodiment the term is defined to be within 10%, in another embodiment within 5%, in another embodiment within 1% and in another embodiment within 0.5%. The term “coupled” as used herein is defined as connected, although not necessarily directly and not necessarily mechanically. A device or structure that is “configured” in a certain way is configured in at least that way, but may also be configured in ways that are not listed.

(37) Certain expressions may be employed herein to list combinations of elements. Examples of such expressions include: “at least one of A, B, and C”; “one or more of A, B, and C”; “at least one of A, B, or C”; “one or more of A, B, or C”. Unless expressly indicated otherwise, the above expressions encompass any combination of A and/or B and/or C.

(38) It will be appreciated that some embodiments may be comprised of one or more specialized processors (or “processing devices”) such as microprocessors, digital signal processors, customized processors and field programmable gate arrays (FPGAs) and unique stored program instructions (including both software and firmware) that control the one or more processors to implement, in conjunction with certain non-processor circuits, some, most, or all of the functions of the method and/or apparatus described herein. Alternatively, some or all functions could be implemented by a state machine that has no stored program instructions, or in one or more application specific integrated circuits (ASICs), in which each function or some combinations of certain of the functions are implemented as custom logic. Of course, a combination of the two approaches could be used.

(39) Moreover, an embodiment can be implemented as a computer-readable storage medium having computer readable code stored thereon for programming a computer (e.g., comprising a processor) to perform a method as described and claimed herein. Examples of such computer-readable storage mediums include, but are not limited to, a hard disk, a CD-ROM, an optical storage device, a magnetic storage device, a ROM (Read Only Memory), a PROM (Programmable Read Only Memory), an EPROM (Erasable Programmable Read Only Memory), an EEPROM (Electrically Erasable Programmable Read Only Memory) and a Flash memory. Further, it is expected that one of ordinary skill, notwithstanding possibly significant effort and many design choices motivated by, for example, available time, current technology, and economic considerations, when guided by the concepts and principles disclosed herein will be readily capable of generating such software instructions and programs and ICs with minimal experimentation.

(40) The Abstract of the Disclosure is provided to allow the reader to quickly ascertain the nature of the technical disclosure. It is submitted with the understanding that it will not be used to interpret or limit the scope or meaning of the claims. In addition, in the foregoing Detailed Description, it can be seen that various features are grouped together in various embodiments for the purpose of streamlining the disclosure. This method of disclosure is not to be interpreted as reflecting an intention that the claimed embodiments require more features than are expressly recited in each claim. Rather, as the following claims reflect, inventive subject matter lies in less than all features of a single disclosed embodiment. Thus the following claims are hereby incorporated into the Detailed Description, with each claim standing on its own as a separately claimed subject matter.

Claims

1. A method for detecting a state of at least one button, comprising: detecting a first signal of a headset of a user, the first signal being indicative of the headset being coupled to a device, and the headset having a microphone and the at least one button; determining, based on the detected first headset signal, a first voltage of the microphone; setting, based on the first voltage of the microphone, a threshold voltage for detecting a state of the at least one button; storing the threshold voltage; determining a second voltage of the microphone; comparing the second voltage of the microphone and the stored threshold voltage; and generating, based on the comparison, a signal indicative of a state of the at least one button.
2. The method of claim 1, further comprising: determining whether a second signal of the headset is detected, the second signal being indicative of the headset remaining coupled to the device; and comparing the second voltage of the microphone and the stored threshold voltage when the second signal of the headset is detected.
3. The method of claim 1, further comprising: determining whether a second signal of the headset is detected, the second signal being indicative of the headset remaining coupled to the device; and clearing the set threshold voltage when the second signal of the headset is not detected.
4. The method of claim 1, further comprising: generating, based on the comparison, a signal indicative of an enable state of the at least one button when the second voltage of the microphone is less than the stored threshold voltage, wherein the enable state is indicative of the at least one button being pressed by the user.
5. The method of claim 1, further comprising: generating, based on the comparison, a signal indicative of a disable state of the at least one button when the second voltage of the microphone is greater than the stored threshold voltage, wherein the disable state is indicative of the at least one button being released by the user.
6. The method of claim 1, wherein the at least one button is a push to talk (PTT) button, and the device is at least one of a smart phone, a tablet, and a mobile computer.
7. A system for detecting a state of at least one button comprising: a memory configured to store computer executable instructions; and a processor configured to interface with the memory and execute the computer executable instructions to cause the processor to: detect a first signal of a headset of a user, the first signal being indicative of the headset being coupled to a device, and the headset having a microphone and the at least one button, determine, based on the detected first headset signal, a first voltage of the microphone, set, based on the first voltage of the microphone, a threshold voltage for detecting a state of the at least one button, store the threshold voltage in the memory, determine a second voltage of the microphone, compare the second voltage of the microphone and the stored threshold voltage, and generate, based on the comparison, a signal indicative of a state of the at least one button.
8. The system of claim 7, wherein the processor is further configured to: determine whether a second signal of the headset is detected, the second signal being indicative of the headset remaining coupled to the device, and compare the second voltage of the microphone and the stored threshold voltage when the second signal of the headset is detected.
9. The system of claim 7, wherein the processor is further configured to: determine whether a second signal of the headset is detected, the second signal being indicative of the headset remaining coupled to the device, and clear the set threshold voltage when the second signal of the headset is not detected.
10. The system of claim 7, wherein the processor is further configured to: generate, based on the comparison, a signal indicative of an enable state of the at least one button when the second voltage of the microphone is less than the stored threshold voltage, wherein the enable state is indicative of the at least one button being pressed by the user.
11. The system of claim 7, wherein the processor is further configured to: generate, based on the comparison, a signal indicative of a disable state of the at least one button when the second voltage

of the microphone is greater than the stored threshold voltage, wherein the disable state is indicative of the at least one button being released by the user.

12. The system of claim 7, wherein the at least one button is a push to talk (PTT) button, and the device is at least one of a smart phone, a tablet, and a mobile computer.

13. A non-transitory tangible machine-readable medium comprising instructions for detecting a state of at least one button that, when executed, cause a machine to at least: detect a first signal of a headset of a user, the first signal being indicative of the headset being coupled to a device, and the headset having a microphone and the at least one button; determine, based on the detected first headset signal, a first voltage of the microphone; set, based on the first voltage of the microphone, a threshold voltage for detecting a state of the at least one button; store the threshold voltage; determine a second voltage of the microphone; compare the second voltage of the microphone and the stored threshold voltage; and generate, based on the comparison, a signal indicative of a state of the at least one button.

14. The non-transitory tangible machine-readable medium of claim 13, wherein the instructions, when executed, further cause the machine to: determine whether a second signal of the headset is detected, the second signal being indicative of the headset remaining coupled to the device; and compare the second voltage of the microphone and the stored threshold voltage when the second signal of the headset is detected.

15. The non-transitory tangible machine-readable medium of claim 13, wherein the instructions, when executed, further cause the machine to: determine whether a second signal of the headset is detected, the second signal being indicative of the headset remaining coupled to the device, and clear the set threshold voltage when the second signal of the headset is not detected.

16. The non-transitory tangible machine-readable medium of claim 13, wherein the instructions, when executed, further cause the machine to: generate, based on the comparison, a signal indicative of an enable state of the at least one button when the second voltage of the microphone is less than the stored threshold voltage, wherein the enable state is indicative of the at least one button being pressed by the user.

17. The non-transitory tangible machine-readable medium of claim 13, wherein the instructions, when executed, further cause the machine to: generate, based on the comparison, a signal indicative of a disable state of the at least one button when the second voltage of the microphone is greater than the stored threshold voltage, wherein the disable state is indicative of the at least one button being released by the user.

18. The non-transitory tangible machine-readable medium of claim 13, wherein the at least one button is a push to talk (PTT) button, and the device is at least one of a smart phone, a tablet, and a mobile computer.
