

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250279403

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

LEI; Jie et al.

ARRAY SUBSTRATE, LIGHT-EMITTING SUBSTRATE AND DISPLAY DEVICE

Abstract

The present disclosure relates to the field of display, and provides an array substrate, a light-emitting substrate, and a display device. The array substrate includes: a base substrate; a first conductive layer and a second conductive layer, stacked on the base substrate and insulated from each other; a plurality of groups of light-emitting element terminals, arranged in an array on the second conductive layer for coupling with light-emitting elements; a plurality of groups of sensor terminals, arranged on the second conductive layer for coupling with sensors.

Inventors: LEI; Jie (Beijing, CN), XU; Zouming (Beijing, CN), TIAN; Jian (Beijing, CN), LIU; Chunjian (Beijing, CN), WU; Xintao (Beijing, CN), ZENG; Qin (Beijing, CN), WANG; Jie (Beijing, CN), ZHANG; Jianying (Beijing, CN)

Applicant: Hefei Xinsheng Optoelectronics Technology co., Ltd. (Anhui, CN); BOE Technology Group Co., Ltd. (Beijing, CN)

Family ID: 83226188

Appl. No.: 19/212934

Filed: May 20, 2025

Related U.S. Application Data

parent US continuation 17641836 20220310 PENDING WO continuation PCT/CN2021/080054 20210310 child US 19212934

Publication Classification

Int. Cl.: H01L25/16 (20230101); H10H20/857 (20250101); H10H29/14 (20250101)

U.S. Cl.:

Background/Summary

CROSS REFERENCE TO RELATED APPLICATION [0001] The present application is Continuation Application of U.S. application Ser. No. 17/641,836, which is a 35 U.S.C. 371 national phase application of PCT International Application No. PCT/CN2021/080054 filed on Mar. 10, 2021, the entire contents of both are incorporated herein by reference in their entireties.

TECHNICAL FIELD

[0002] The present disclosure relates to the field of display technology, and in particular, to an array substrate, a light-emitting substrate and a display device.

BACKGROUND

[0003] MiniLEDs, also known as sub-millimeter light-emitting diodes, have die sizes of about 100 to 300 μm . While for MicroLEDs, the die size is less than 100 μm . At present, the research and development of MiniLEDs and MicroLEDs in the field of backlight and display is continuously deepening, in order to achieve products of better quality.

[0004] It should be noted that the information disclosed in the Background section is only for enhancement of understanding of the background of the present disclosure, and therefore may contain information that does not form the prior art that is already known to a person of ordinary skill in the art.

SUMMARY

[0005] The purpose of the present disclosure is to overcome the above-mentioned deficiencies of the prior art, and provide an array substrate, a light-emitting substrate, and a display device.

[0006] According to an aspect of the present disclosure, an array substrate is provided, including:

[0007] a base substrate; [0008] a first conductive layer and a second conductive layer, stacked on the base substrate and insulated from each other; [0009] a plurality of groups of light-emitting element terminals, arranged in an array on the second conductive layer for coupling with light-emitting elements; [0010] a plurality of groups of sensor terminals, arranged on the second conductive layer for coupling with sensors, where no overlap exists between an orthographic projection of the groups of sensor terminals on the base substrate and an orthographic projection of the groups of light-emitting element terminals on the base substrate, where the group of sensor terminals includes an input terminal and an output terminal, where the sensor includes an input pin and an output pin, and where the input terminal is configured for electrical connection with the input pin, and the output terminal is configured for electrical connection with the output pin; [0011] a first group of signal lines, disposed on the first conductive layer and electrically connected to the groups of sensor terminals for driving the sensors to sense; [0012] a second group of signal lines, disposed on the first conductive layer and electrically connected to the group of light-emitting element terminals for driving the light-emitting elements to emit light; and [0013] a plurality of first leads, where among two adjacent groups of sensor terminals, the first lead is connected to the output terminal of one group of sensor terminals and the input terminal of the other group of sensor terminals.

[0014] In an exemplary embodiment of the present disclosure, the first leads include first column leads extending along a column direction and first row leads extending along a row direction, where each of the first column leads is provided on the first conductive layer, each of the first row leads is provided on the second conductive layer, and the first column lead and the first row lead are electrically connected through a via hole.

[0015] In an exemplary embodiment of the present disclosure, at least one of the first leads includes one of the first column leads and two of the first row leads, the two of the first row leads

extend laterally out from the output terminals and the input terminals of two adjacent groups of sensor terminals respectively, and the two of the first row leads are electrically connected to the first column lead at the same time through via holes.

[0016] In an exemplary embodiment of the present disclosure, the first column leads connected to the groups of sensor terminals located in the same column are arranged along the column direction.

[0017] In an exemplary embodiment of the present disclosure, the group of sensor terminals further includes a power terminal, the sensor further includes a power pin, and the power terminal is configured for electrical connection with the power pin; the first group of signal lines includes a power signal line, and the power terminal is electrically connected to the power signal line; and the power signal line and the first column lead are arranged side by side and at intervals.

[0018] In an exemplary embodiment of the present disclosure, $m \times n$ sensors are sequentially connected in series in an S-shape column by column and row by row, where m and n are both integers, m is a number of rows of the sensors connected in series, and n is a number of columns of the sensors connected in series.

[0019] In an exemplary embodiment of the present disclosure, among two adjacent sensors in the $m \times n$ sensors sequentially connected in series in the S-shape column by column and row by row, the output pin of one sensor is electrically connected with the input pin of the other sensor through the first lead.

[0020] In an exemplary embodiment of the present disclosure the first group of signal lines includes an input signal line and an output signal line; among all the sensors connected in series, the input terminal of the group of sensor terminals corresponding to the sensor at one end is connected to the input signal line, and the output terminal of the group of sensor terminals corresponding to the sensor at the other end is connected to the output signal line.

[0021] According to another aspect of the present disclosure, a light-emitting substrate is provided, including: [0022] the array substrate as described above; [0023] light-emitting elements, coupled to the groups of light-emitting element terminals of the array substrate; and [0024] sensors, coupled to the groups of sensor terminals of the array substrate.

[0025] According to another aspect of the present disclosure, a display device is provided, including the light-emitting substrate described above.

[0026] It is to be understood that the foregoing general description and the following detailed description are exemplary and explanatory only, and are not restrictive of the present disclosure.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0027] The accompanying drawings, which are incorporated in and constitute a part of the present specification, illustrate embodiments consistent with the present disclosure and together with the present description serve to explain the principle of the present disclosure. Obviously, the drawings in the following description are only some embodiments of the present disclosure, and for those of ordinary skill in the art, other drawings may also be obtained from these drawings without creative efforts.

[0028] FIG. 1 is a schematic partial structure diagram of an array substrate of a mini LED according to an embodiment of the present disclosure;

[0029] FIG. 2 is a partial enlarged schematic diagram of the M area in FIG. 1;

[0030] FIG. 3 is a schematic arrangement diagram of light-emitting units;

[0031] FIG. 4 is a schematic structural diagram of the group of sensor terminals;

[0032] FIG. 5 is a cross-sectional schematic diagram along A-A in FIG. 4;

[0033] FIG. 6 is a schematic arrangement diagram of the group of sensor terminals and the signal lines;

[0034] FIG. 7 shows a schematic structural diagram of the first conductive layer in FIG. 6;
[0035] FIG. 8 shows an arrangement of the signal lines of the group of sensor terminals according to an embodiment of the present disclosure;
[0036] FIG. 9 shows a schematic partial structural diagram of the array substrate in FIG. 8;
[0037] FIG. 10 is a partial enlarged schematic diagram of the M area in FIG. 9;
[0038] FIG. 11 is a schematic structural diagram of a group of sensor terminals in FIG. 9;
[0039] FIG. 12 shows a schematic wiring diagram of the first conductive layer in FIG. 9;
[0040] FIG. 13 shows a schematic structural diagram of the first leads;
[0041] FIG. 14 shows the arrangement of the signal lines of the group of sensor terminals according to still another embodiment of the present disclosure;
[0042] FIG. 15 shows a schematic partial structural diagram of the array substrate in FIG. 14;
[0043] FIG. 16 is a schematic structural diagram of a group of sensor terminals in FIG. 14;
[0044] FIG. 17 shows the wiring of the first conductive layer in FIG. 14;
[0045] FIG. 18 shows a schematic diagram of the transmission path for the input signal and the output signal in FIG. 14;
[0046] FIG. 19 shows a schematic partial structural diagram of an array substrate according to yet another embodiment of the present disclosure;
[0047] FIG. 20 is a partial enlarged schematic diagram of M area in FIG. 19;
[0048] FIG. 21 is a schematic structural diagram of a group of sensor terminals in FIG. 19;
[0049] FIG. 22 is a partial enlarged schematic view of the M area including the group of capacitor terminals in FIG. 19;
[0050] FIG. 23 is a schematic structural diagram of the group of capacitor terminals.

LIST OF REFERENCE NUMBERS

[0051] **100**, first conductive layer; **200**, second conductive layer; **300**, insulation layer; **400**, insulation layer; **900**, base substrate; **10**, group of light-emitting element terminals; **11**, anode terminal; **12**, cathode terminal; **101**, light-emitting unit; **20**, group of drive circuit terminals; **21**, input terminal; **22**, power terminal; **23**, output terminal; **24**, first common voltage terminal; **30**, group of sensor terminals; **31**, input terminal; **32**, output terminal; **33**, power terminal; **34**, second common voltage terminal; **40**, group of capacitor terminals; **41**, first capacitor terminal; **42**, second capacitor terminal; **101**, input signal line; **102**, output signal line; **103**, power signal line; **104**, first common voltage signal line; **105**, first lead; **1051**, first column lead; **1052**, first row lead; **106**, second lead; **107**, third lead; **108**, fourth lead; **201**, second common voltage signal line; **202**, drive voltage signal line; **203**, power line; **204**, source address line; **205**, common voltage signal auxiliary line; **5**, slot.

DETAILED DESCRIPTION OF THE EMBODIMENTS

[0052] Example embodiments will now be described more fully with reference to the accompanying drawings. Example embodiments, however, may be embodied in various forms and should not be construed as limited to embodiments set forth herein. Rather, these embodiments are provided so that the present disclosure will be thorough and complete, and will fully convey the concept of example embodiments to those skilled in the art. The same reference numerals in the drawings denote the same or similar structures, and thus their detailed descriptions will be omitted. Furthermore, the drawings are merely schematic illustrations of embodiments of the present disclosure provided, and are not necessarily drawn to scale.

[0053] Although relative terms such as “upper” and “lower” are used in the present specification to describe the relative relationship between one component represented by an icon and another component, these terms are used in the present specification only for convenience, such as based on the direction in the example as described. It will be appreciated that if the device represented by the icon is turned upside down, the component described as being “on” the device will become a component being “beneath” the device. When a particular structure is “on” another structure, it may mean that the particular structure is integrally formed on the other structure, or that the

particular structure is “directly” arranged on the other structure, or that the particular structure is “indirectly” arranged on the other structure through a third structure.

[0054] The terms “a”, “an”, “the”, “said” and “at least one” are used to indicate the presence of one or more elements or components, etc. The terms “include” and “have” are used to indicate an open inclusion, and means that additional elements or components, etc may be present in addition to the listed elements or components, etc. The terms “first”, “second” and “third” etc. are only used as a marker, not as a limit on the number of the relevant objects.

[0055] Embodiments of the present disclosure provide an array substrate, on which light-emitting elements may be bound, thereby serving as a backlight source for a Mini-LED display device. Sensors may also be bound on the array substrate to sense the light-emitting performance of the light-emitting elements, so as to monitor the light-emitting conditions of the backlight source.

[0056] In an embodiment of the present disclosure, FIG. 1 is a schematic partial structure diagram of an array substrate of a mini LED according to an embodiment of the present disclosure, FIG. 2 is a partial enlarged schematic diagram of the M area in FIG. 1, FIG. 3 is a structural schematic diagram of the group of sensor terminals, and FIG. 4 is a schematic cross-sectional view along the AA direction in FIG. 3. Referring to FIGS. 1-4, the Mini-LED array substrate includes a base substrate **900**, a first conductive layer **100** and a second conductive layer **200**. The first conductive layer **100** is provided at one side of the base substrate **900**, and the second conductive layer **200** is provided at the side of the first conductive layer **100** away from the base substrate **900**. An insulation layer **300** is provided between the first conductive layer **100** and the second conductive layer **200**. An insulation layer **400** is provided above the second conductive layer, and an opening area is provided on the insulation layer **400** to expose terminals.

[0057] In an embodiment of the present disclosure, the first conductive layer **100** is used to arrange various signal lines, including a first group of signal lines for driving the sensors, and a second group of signal lines for driving the light-emitting elements to emit light. In some embodiments, a layered structure containing MoNb/Cu/MoNb may be sequentially formed by a sputtering process, where the bottom layer of MoNb is used to improve adhesion, the top layer of MoNb is used to prevent oxidation, and the middle layer of Cu is used as the main part of the signal line. The material has characteristics such as low resistivity. At the same time, the width and the thickness of the signal line may be increased to further reduce the resistance of the signal line. In other embodiments, the intermediate layer of Cu may be formed by an electroplating process. In this case, the bottom layer may be made of MoNiTi through a sputtering process as a seed layer, so as to increase the nucleation density of metal Cu grains during electroplating. Finally, an anti-oxidation layer of MoNiTi or MoNb may be formed through a sputtering process.

[0058] The second conductive layer **200** is provided with a plurality of groups of light-emitting element terminals **10** coupled with the light-emitting elements. The second conductive layer **200** is further provided with several groups of sensor terminals **30** connected with the sensors. The groups of sensor terminals **30** are arranged among the groups of light-emitting element terminals **10**. The orthographic projection of the groups of sensor terminals **30** on the base substrate does not overlap with the orthographic projection of the groups of light-emitting element terminals **10** on the base substrate. The second conductive layer **200** may form a layered structure of MoNb/Cu/CuNi through a sputtering process in sequence, where the bottom layer of MoNb is used to improve adhesion, and the top surface adopts CuNi for both anti-oxidation and solid crystal solidity.

[0059] It should be noted that the groups of light-emitting element terminals **10** according to an embodiment of the present disclosure are used to electrically connect the light-emitting elements to the second group of signal lines on the base substrate. The light-emitting elements may be bound on the array substrate by welding. Thus, the groups of light-emitting element terminals **10** may be a group of pads. The light-emitting elements may also be directly fabricated on the base substrate through a film forming process. Thus, the groups of light-emitting element terminals **10** may also be a group of electrodes that plays a conductive role. Similarly, the groups of sensor terminals **30**

according to an embodiment of the present disclosure may also be a group of pads or a group of electrodes.

[0060] Providing sensors on the array substrate helps to quickly and effectively monitor the light-emitting conditions of the surrounding light-emitting elements, so as to adjust the current, voltage, brightness and other parameters of the light-emitting elements in a timely and finer way, thereby ensuring the stable performance of each light-emitting element.

[0061] Sensors may be of various types according to their functions. For example, the sensor may be a temperature sensor for detecting the temperature of the surrounding light-emitting elements, and adjusting parameters such as voltage and current in time, so as to avoid system insensitivity caused by overheating, or broken lines caused by excessive voltage and current, etc. The sensor may also be a photosensitive sensor for detecting the brightness of the surrounding light-emitting elements, adjusting the brightness of each light-emitting element in time, and keeping the light-emitting brightness of each light-emitting element consistent and stable. In an embodiment, the sensor may be an integrated sensor integrated on a chip, which is bound on the array substrate through the group of sensor terminals **30**.

[0062] The array substrate in some embodiments of the present disclosure will be further described in detail below.

[0063] With reference to FIGS. **1** and **2**, a plurality of light-emitting elements are arranged in an array, and one light-emitting unit **101** includes four light-emitting elements connected in series. The light-emitting element electrically connected to the drive voltage signal line **202** is used as the start point of the four light-emitting elements connected in series, and the light-emitting element electrically connected to the control circuit is used as the end point of the four light-emitting elements connected in series. The four light-emitting elements are driven by one control circuit. Therefore, a fourth lead **108** is further provided in the second conductive layer **200** of the array substrate. The fourth lead **108** connects the four groups of light-emitting element terminals **10** in sequence, so that the four light-emitting elements are connected in series to form a light-emitting unit **101**. It should be noted that, in an example provided by an embodiment of the present disclosure, the number of light-emitting elements in each light-emitting unit is not limited, and may be any number such as **5**, **6**, **7**, and **8**, but not limited only to **4**. Meanwhile, the light-emitting element may be an LED or any other light-emitting element.

[0064] In some examples, according to a specific implementation, with reference to FIG. **1**, the light-emitting elements in the same light-emitting unit **101** are sequentially connected to form a polygon. For example, when the light-emitting unit **101** includes four light-emitting elements, the four light-emitting elements may be sequentially connected to form a quadrangle. Two sides of the quadrilateral may be parallel to the row direction, and the other two sides of the quadrilateral may be parallel to the column direction. Alternatively, two sides of the quadrilateral may also have an included angle with respect to the row direction, and the other two sides of the quadrilateral may also have an included angle with respect to the column direction. Therefore, the four groups of light-emitting element terminals **10** in each light-emitting unit **101** are also arranged in the respective shapes.

[0065] Accordingly, positions of the groups of light-emitting element terminals **10** corresponding to the four light-emitting elements in one light-emitting unit **101** may be connected to each other to obtain a polygon (indicated by the dotted box X in the figures). Specifically, it may be a parallelogram. It can be understood that the vertex of the quadrilateral may be the geometric center of each group of light-emitting element terminals **10**. Herein, attention should be paid to the difference between the dotted box X in FIG. **2** and the dotted box in FIG. **1**. The dotted box X in FIG. **2** represents the position of the group of light-emitting element terminals **10**, and the dotted box in FIG. **1** only roughly depicts the division of the light-emitting unit **101**. In some examples, according to an implementation, among the adjacent light-emitting units **101** in the row direction, the light-emitting elements located at the same position in each light-emitting unit **101** may be

approximately arranged on the same straight line along the row direction. Further, among the adjacent light-emitting units in the column direction, the light-emitting elements located at the same position in each light-emitting unit **101** may be roughly arranged on the same straight line along the column direction. Therefore, the groups of light-emitting element terminals **10** in the row direction and the column direction are also arranged according to the respective ways.

[0066] Further, among the four groups of light-emitting element terminals **10** connected in series, the fourth lead **108** between any two groups of light-emitting element terminals **10** connected in series through the fourth lead **108** includes a plurality of sub-segments extending in the row direction and/or the column direction. The fourth lead is composed of a plurality of sub-segments along the row and column directions, which is convenient to manufacture. Besides, it may reduce the probability of short circuit between two terminals in the same group of light-emitting element terminals, and also reduce the occurrence of short circuit of the fourth lead due to the gap between the signal line in the first conductive layer and its adjacent signal line. Referring specifically to FIG. 2, the fourth lead **108** of the upper left group of light-emitting element terminals **10** extends to the lower left group of light-emitting element terminals **10** along the column direction, row direction, and column direction in sequence.

[0067] Referring to FIG. 2, in an embodiment, the group of light-emitting element terminals **10** includes two terminals, one being the anode terminal **11** and the other being the cathode terminal **12**. The anode terminal **11** is connected to an anode pin of the light-emitting element, and the cathode terminal **12** is connected to the other cathode pin of the light-emitting element.

[0068] The light-emitting element according to an embodiment of the present disclosure is driven to emit light by a control circuit. Therefore, the array substrate according to an embodiment of the present disclosure may be further provided with a group of drive circuit terminals **20**. Similar to the light-emitting element and the sensor, the drive circuit may also be integrated in the chip and bound to the array substrate by welding. Thus, the group of drive circuit terminals **20** may be a group of pads, and may also be directly prepared on the base substrate through a film forming process. Therefore, the group of drive circuit terminals **20** may also be a group of electrodes that plays a conductive role. It can be understood that the orthographic projection of the group of drive circuit terminals **20** on the base substrate does not overlap with the orthographic projections of the group of light-emitting element terminals **10** and the group of sensor terminals **30** on the base substrate.

[0069] In an embodiment, the control circuit for driving the light-emitting element to emit light may be a microchip. The size (e.g., length) of the microchip may be in the order of tens or hundreds of microns. The chip area may be about tens of thousands of square microns or hundreds of square micrometers or even smaller. This is similar in size to Mini-LEDs, has miniaturization features, and is easy to integrate into the array substrate **10** (e.g., bound and coupled to the surface of the array substrate **10**), thereby simplifying the overall structure and facilitating the realization of a light and thin product. Each control circuit directly drives one light-emitting unit **101**, which avoids problems such as complicated operation and easy flickering in the line scan control mode. In addition, the drive circuit **110** has a small number of terminals, a small number of required signals, a simple control method, a simple wiring method, and low cost.

[0070] FIG. 1 and FIG. 2 also show the structure of the group of drive circuit terminals **20** coupled with the drive circuit. The group of drive circuit terminals **20** includes four terminals, which are respectively the input terminal **21** for connecting with the Di pin of the drive circuit, a power terminal **22** for connecting with the Pwr pin of the drive circuit, an output terminal **23** for connecting with the Out pin of the drive circuit, and a common voltage terminal **24** for connecting with the Gnd pin of the drive circuit.

[0071] Referring to FIG. 1 and FIG. 2, the first conductive layer **100** is provided with a second group of signal lines for driving the light-emitting elements to emit light. The second group of signal lines includes a second common voltage signal line **201**, a drive voltage signal line **202**, a power line **203**, and a source address line **204**. The above-mentioned input terminal **21** is

configured to receive a first input signal, such as an address signal, for gating a drive circuit at a corresponding address. For example, the first input signal may be 8-bit start address information transmitted from the source address line **204**. The address of the first drive circuit corresponding to the address signal may be obtained by analyzing the address signal. The power terminal **22** is configured to receive a second input signal, e.g., a power line carrier communication signal from the power line **203**. The second input signal not only provides power for the drive circuit, but also transmits communication data to the drive circuit. The communication data may be used to determine the light-emitting duration of the respective light-emitting unit, thereby controlling the visual light-emitting brightness thereof. The output terminal **23** is configured to output, in the first period of time, a relay signal to the next stage of drive circuit with a cascade relationship thereof. The relay signal includes address information. The address of the corresponding drive circuit may be obtained by analyzing the address signal. The output terminal **23** is further configured to form a signal loop for the respective light-emitting unit within the second period, so that the light-emitting unit may emit with the respective brightness. The common voltage terminal **24** is configured to receive a common voltage signal, such as a ground signal from the second common voltage signal line **201**. In an embodiment of the present disclosure, the second common voltage signal line **201**, the drive voltage signal line **202**, the power line **203**, and the source address line **204** all extend in the column direction and are arranged at intervals in the row direction.

[0072] As shown in FIG. **1**, the arrangement having four light-emitting elements and drive circuits in one light-emitting unit **101** is considered as a repeating unit, the array substrate may include a plurality of repeating units, and adjacent repeating units are arranged at intervals, particularly arranged periodically along the row and column directions. In this way, one group of light-emitting units may be used as a repeating unit for repeating arrangement. For example, in a plurality of light-emitting units arranged in the column direction, the relative positions among the plurality of light-emitting elements and the drive circuits in each light-emitting unit may be substantially the same. In the light-emitting units arranged along the row direction, the relative positions among the plurality of light-emitting elements and the drive circuits in two adjacent light-emitting units may be arranged in a center symmetrical way.

[0073] As shown in FIG. **2**, the group of drive circuit terminals **20** is located outside of the quadrangle (shown by the dotted box X in the figures) obtained by sequentially connecting positions of the four groups of light-emitting element terminals **10** connected in series, so as to facilitate wiring of the fourth lead **108**. In the meanwhile, this helps to minimize influences of the drive circuit on the light output of the light-emitting element. It can be understood that when each light-emitting unit includes $n \times m$ groups of light-emitting element terminals, positions of the plurality of groups of light-emitting element terminals located at the outermost side in the light-emitting unit may be sequentially connected to obtain a polygon, and the group of drive circuit terminals **20** is located outside of the polygon. Herein, positions of the outermost groups of light-emitting element terminals in the light-emitting unit refer to the geometric centers of the above-mentioned groups of light-emitting element terminals. The non-outermost groups of light-emitting element terminals in the light-emitting unit are located inside the aforementioned polygon.

[0074] For the convenience of description, the light-emitting units **101** in the array substrate are marked with coordinates according to the arrangement of rows and columns. For example, there are P rows and Q columns of light-emitting units **101** on the array substrate, and the light-emitting unit **101** in the a-th row and the b-th column may correspond to the coordinate of (a, b), where $1 \leq a \leq P$, $1 \leq b \leq Q$, and P, Q, a, and b are all positive integers. FIG. **3** shows the arrangement structure and coordinates of some light-emitting units **101**.

[0075] In an embodiment, positions of the groups of drive circuit terminals corresponding to the four light-emitting units **101** having coordinates of (a, b), (a+1, b), (a, b+1), and (a+1, b+1) are connected in sequence to obtain a convex quadrilateral, for example, a parallelogram. Specifically, it may be a rectangle or a square. Obviously, each convex quadrilateral is composed of two

triangles, and the two triangles are each composed of positions of three groups of drive circuit terminals **20** in the four light-emitting units **101**.

[0076] In some embodiments, each parallelogram may be composed of two isosceles triangles or equilateral triangles, and each isosceles triangle or equilateral triangle is composed of positions of three groups of drive circuit terminals **20** in the four light-emitting units **101**. When each parallelogram is composed of two equilateral triangles, distances between the respective groups of drive circuit terminals **20** may be close. It should be noted that the terms of “isosceles triangle” and “equilateral triangle” as described here are idealized descriptions. In actual products, due to influences by process and equipment accuracies, the general shape thereof may be the isosceles triangle and the equilateral triangle.

[0077] In some embodiments, referring to FIGS. 1-3, the group of drive circuit terminals **20** in the light-emitting unit (1, 1), the group of drive circuit terminals **20** in the light-emitting unit (1, 2), and the group of drive circuit terminals **20** in the light-emitting unit (2, 1) are respectively located at the three vertices of the triangle, for example, the three vertices of the first triangle. The group of drive circuit terminals **20** in the light-emitting unit (2, 1), the group of drive circuit terminals **20** in the light-emitting unit (1, 2), and the group of drive circuit terminals **20** in the light-emitting unit (2, 2) may be located at the three vertices of the triangle respectively, for example, the three vertices of the second triangle.

[0078] The group of drive circuit terminals **20** in the light-emitting unit (2, 1), the group of drive circuit terminals **20** in the light-emitting unit (2, 2), and the group of drive circuit terminals **20** in the light-emitting unit (3, 1) may be located at the three vertices of the triangle respectively, such as the three vertices of the third triangle. The group of drive circuit terminals **20** in the light-emitting unit (3, 1), the group of drive circuit terminals **20** in the light-emitting unit (2, 2), and the group of drive circuit terminals **20** in the light-emitting unit (3, 2) may be located at the three vertices of the triangle respectively, for example, at the three vertices of the fourth triangle. The group of drive circuit terminals **20** in the light-emitting unit (1, 2), the group of drive circuit terminals **20** in the light-emitting unit (1, 3), and the group of drive circuit terminals **20** in the light-emitting unit (2, 3) may be located at the three vertices of the triangle respectively, for example at the three vertexes of the fifth triangle. The group of drive circuit terminals **20** in the light-emitting unit (2, 3), the group of drive circuit terminals **20** in the light-emitting unit (1, 2), and the group of drive circuit terminals **20** in the light-emitting unit (2, 3) may be respectively located at the three vertices of the triangle, for example at the three vertices of the sixth triangle. The group of drive circuit terminals **20** in the light-emitting unit (1, 3), the group of drive circuit terminals **20** in the light-emitting unit (1, 4), and the group of drive circuit terminals **20** in the light-emitting units (2, 3) may be located at the three vertices of the triangle, for example at the three vertices of the seventh triangle.

[0079] The line connecting the centers of gravity of two adjacent triangles in the row direction or the column direction is parallel to the row direction or the column direction. For example, the line connecting the center of gravity of the first triangle and the center of gravity of the third triangle is parallel to the column direction. The line connecting the center of gravity of the second triangle and the center of gravity of the fourth triangle is also parallel to the column direction. The line connecting the center of gravity of the first triangle, the center of gravity of the fifth triangle, and the center of gravity of the seventh triangle is parallel to the row direction. The line connecting the center of gravity of the second triangle and the center of gravity of the sixth triangle is parallel to the row direction.

[0080] The arrangements for other groups of drive circuit terminals **20** are the same as above, which will not be repeated herein.

[0081] The arrangement of the groups of drive circuit terminals **20** corresponding to the plurality of light-emitting units **101** on the array substrate may be designed according to the above ways, and details are not described herein. In some examples, according to a specific implementation, along the row direction, the arrangement including the group of light-emitting element terminals **10** and

the group of drive circuit terminals **20** corresponding to one light-emitting unit is used as a repeating unit, and the array substrate may include a plurality of repeating units. The adjacent repeating units are arranged at intervals and are periodically arranged along the row direction. In this way, one light-emitting unit may be used as a repeating unit for repeated arrangement, so as to form an array substrate. In this case, in the light-emitting units arranged along the row and column directions, the relative positions among the plurality of groups of light-emitting element terminals **10** and the groups of driving circuit terminals **20** in each light-emitting unit may be substantially the same.

[0082] Referring to FIG. 4, it is a schematic structural diagram of the group of sensor terminals **30**. The group of sensor terminals **30** includes an input terminal **31** for connecting with the R.sub.x pin of the sensor, an output terminal **32** for connecting with the T.sub.x pin of the sensor, a power terminal **33** for connecting to the V.sub.+ pin of the sensor, and a common voltage terminal **34** for connecting to the Gnd pin of the sensor.

[0083] FIG. 5 is a schematic cross-sectional view along the direction A-A in FIG. 4. The first conductive layer **100** is provided with a first group of signal lines for driving the sensors to perform sensing. The first group of signal lines includes an input signal line **101**, an output signal line **102**, a power line **103**, and a first common voltage signal line **104**. Each of the signal lines described above extends in the column direction and is arranged in the row direction. The input terminal **31** is electrically connected to the input signal line **101**, the output terminal **32** is electrically connected to the output signal line **102**, the power terminal **33** is electrically connected to the power signal line **103**, and the common voltage terminal **34** is electrically connected to the first common voltage signal line **104**.

[0084] The first common voltage signal line **104** and the second common voltage signal line **201** are used to provide the ground voltage. Therefore, the second common voltage signal line **201** and the first common voltage signal line **104** may be combined into one signal line. In this case, a common voltage signal may be provided for the sensor and the drive circuit at the same time, without increasing the number of signal lines.

[0085] The sensor provided by embodiments of the present disclosure may be used to sense temperature. For example, the sensor includes a thermal triode, which uses the voltage change between the base and the emitter to sense the temperature change. It may further include an analog-to-digital conversion unit to convert the analog signal indicative of the voltage change into a digital signal. Further, a signal processor such as for denoising and filtering may also be included to further process the digital signal, so that the measurement value of the corresponding temperature change obtained by converting the digital signal is more accurate. By comparing the measurement value of the temperature change with a standard value, the cause of the temperature change may be determined. For example, the cause may be a circuit problem due to the current in the area for temperature measurement, or a packaging problem in the area for temperature measurement. With adjustment or repair directed to different problems, the effect of temperature monitoring is achieved and the product yield is improved.

[0086] The group of sensor terminals **30** may be located at a gap between two adjacent light-emitting units, as shown in FIG. 2. In other embodiments, the group of sensor terminals **30** may also be located between the groups of light-emitting element terminals **10** in the light-emitting unit, as long as the area where the light-emitting unit is located can be sensed. Regardless of the arrangement, a plurality of groups of sensor terminals **30** may be arrayed on the array substrate along the row direction and the column direction, so that the sensors can monitor the temperature of the light-emitting units in different areas.

[0087] The number of the sensors is chosen according to the requirement about the sensing accuracy of the array substrate, and it may be multiple or only one. Accordingly, the number of the groups of sensor terminals **30** may be also one or more.

[0088] In an embodiment of the present disclosure, in order to achieve more accurate inspection

and regulation, the number of the groups of sensor terminals **30** is multiple, and the groups of sensor terminals **30** are arranged in the gap between the light-emitting units. Taking FIG. **6** as an example, it is a schematic arrangement diagram of the group of sensor terminals **30** and signal lines. The figure schematically shows that 15 groups of sensor terminals **30** are arranged evenly on the array substrate in 3 rows and 5 columns.

[0089] It can be understood that the number and arrangement of the groups of sensor terminals **30** are not unique. Each sensor may sense the surrounding light-emitting elements. In order to ensure that the sensing data is helpful for monitoring the actual performance of the light-emitting elements, the number and positions of the sensors may be adjusted according to the number and range of the light-emitting elements that can be sensed by each sensor, so that the full sensing range of the sensors can cover exactly all the light-emitting elements without any repeated sensing. The groups of sensor terminals in FIG. **6** are arranged in the row and column directions. The groups of sensor terminals in each row or each column are located on the same straight line, and the interval between two adjacent groups of sensor terminals is the same, so as to make the test more accurate. In other embodiments, according to the testing requirements, the sensors in each row or each column may also be arranged in other forms. For example, the sensors in each row or each column may be not located on the same straight line, as long as the sensing purpose can be achieved.

[0090] The connection relationship among the sensors will be described below. The array substrate may have N sensors, where N is greater than or equal to 1 and is an integer.

[0091] In some cases, N sensors are cascaded with each other. That is, the T.sub.x pin of the n-th stage of sensor is connected to the R.sub.x pin of the (n+1)-th stage of sensor, the R.sub.x pin of the 1-st stage of sensor is connected to the input signal line **101**, and the T.sub.x pin of the N-th stage of sensor is connected to the output signal line **102**, where n is an integer greater than 1 and less than N-1. The R.sub.x pin of the 1-st stage of sensor is connected to the input signal line **101** through the input terminal **31** in the group of sensor terminals corresponding to the sensor, for receiving the input signal. The output pin T.sub.x of the N-th stage of sensor is connected to the output signal line **102** through the output terminal **32** of the corresponding group of sensor terminals, for transmitting the signal sensed by the sensor to the external circuit. The input signal is generated based on a communication protocol, for performing a series of configurations and settings for various stages of sensors. In the power-on phase, the input signal is configured to sequentially assign address information for the 1-st stage of sensor to the N-th stage of sensor. At the initial configuration phase, the input signal is configured to sequentially specify the sensing accuracy and the sensing range of the 1-st stage of sensor to the N-th stage of sensor with respect to a physical quantity (such as temperature). In the sensing phase, the input signal is configured to specify the x-th stage of sensor for performing the sensing function, and output the corresponding sensing signal. It can be understood that in the sensing phase, only one sensor performs the sensing function at a time, and the other stages of sensors may be equivalent to the (N-1) resistors connected in series with the sensor performing the sensing function. In this way, sensing is achieved at specific locations on the array substrate. Therefore, in the sensing phase, the input signal may be configured to sequentially designate the sensor at each stage to perform the sensing function, so that the sensing signals at various positions on the array substrate can be obtained.

[0092] In some cases, the N sensors may also be independent of each other. In order to avoid too many signal lines and complex overall wiring, sensors located in the same column may be connected to the same power signal line **103**, the same input signal line **101**, and the same output signal line **102**. The R.sub.x pin of each sensor is connected to the input signal line **101** through the input terminal **31** in the group of sensor terminals corresponding to the sensor, for receiving the input signal. The output pin T.sub.x of each sensor is connected to the output signal line **102** through the output terminal **32** in the corresponding group of sensor terminals, for transmitting the signal sensed by the sensor to the external circuit. Each sensor is preset with address information, and the address information of each sensor is different. The input signal is generated based on a

communication protocol for configuring and setting each sensor. In the initial configuration phase, the input signal containing address information is configured to specify the sensing accuracy and the sensing range of the corresponding sensor with respect to a physical quantity (such as temperature). In the sensing phase, the input signal containing address information is configured to specify a certain sensor for performing the sensing function and output a corresponding sensing signal. It can be understood that, in the sensing phase, only one sensor performs the sensing function at a time, and other sensors connected to the same input signal line **101** and the same output signal line **102** as the sensor performing the sensing function do not work, so that sensing at specific locations on the array substrate can be achieved. Therefore, in the sensing phase, the input signal may be configured to sequentially designate the sensors at different positions to perform the sensing function, so that the sensing signals at various positions on the array substrate can be obtained.

[0093] In an embodiment, referring to FIGS. **1-7**, FIG. **6** corresponds to the arrangement of the group of sensor terminals **30** and the signal lines in the array substrate of FIG. **1**, and FIG. **7** shows the structure of the first conductive layer **100** of FIG. **6**. As shown, the number of the input signal lines **101** is equal to the number of the groups of sensor terminals **30** in the row direction, and the number of the output signal lines **102** is also equal to the number of the groups of sensor terminals **30** in the row direction. In the column direction, the input terminal **31** of each group of sensor terminals **30** located in the same column is connected to the same input signal line **101**, and the output terminal **32** of each group of sensor terminal **30** located in the same column is connected to the same output signal line **102**. That is to say, only one input signal line **101** and one output signal line **102** are provided in each column, thereby reducing the number of the input signal lines **101** and the number of the output signal lines **102**.

[0094] In another embodiment, referring to FIGS. **8-12**, FIG. **8** shows the signal line arrangement of the group of sensor terminals **30** in an embodiment, FIG. **9** shows a partial structural schematic diagram of the array substrate in an embodiment, FIG. **10** is a partial enlarged schematic diagram of the M area in FIG. **9**, FIG. **11** is a schematic structural diagram of a group of sensor terminals **30** in FIG. **9**, and FIG. **12** shows the wiring of the first conductive layer **100** in FIG. **8**. As shown in the figures, the number of the input signal lines **101** is equal to the number of the sensor terminals in the row direction, and the number of the output signal lines **102** is equal to the number of the sensor terminals in the row direction. In the column direction, among two adjacent groups of sensor terminals **30** located in the same column, the output terminal **32** of one group of sensor terminals **30** is electrically connected to the input terminal **31** of the other group of sensor terminals **30**; and among various groups of sensor terminals **30** located in the same column, the input terminal **31** of the first group of sensor terminals **30** is connected to one input signal line **101**, and the output terminal **32** of the last group of sensor terminals **30** is connected to one output signal line **102**, so that all the sensors in each column are connected in series, and the signal used to configure the sensors can be transmitted to each sensor in the same column.

[0095] For example, in the structure shown in the figures, the input terminal **31** of the group of sensor terminals **30** in the bottom row and the first column is connected to the input signal line **101**, and the output sub-terminal **32** thereof is connected with the input terminal **31** of the group of sensor terminals **30** in the penultimate row and the first column. The input terminal **31** of the group of sensor terminals **30** in the penultimate row and the first column is connected to the input terminal **31** of the group of sensor terminals **30** in the penultimate row and the first column. In a similar way, the output terminal **32** of the group of sensor terminals **30** in the uppermost row and the first column is connected to the output signal lines **102**, so that the sensors in the first column can be connected in series. In a similar way, the groups of sensor terminals **30** in each column are connected, so that the sensors in each column can be connected in series. Based on such series connection, only one input signal line **101** and one output signal line **102** are arranged in each column. Besides, the input signal line **101** and the output signal line **102** only need to be arranged

above and below the array substrate respectively, and can be routed through edge wirings to the binding area of the array substrate, without the need to penetrate the entire array substrate up and down. Compared with the wiring way shown in FIG. 5, the space occupied by the lines is further reduced.

[0096] In an embodiment, since in the two adjacent groups of sensor terminals **30**, the output terminal **32** of one group of sensor terminals **30** is electrically connected to the input terminal **31** of the other group of sensor terminals **30**, the second conductive layer **200** can be provided with leads for connecting the two input terminals.

[0097] In an embodiment, referring to FIG. **13**, the array substrate further includes a plurality of first leads **105**. The first leads **105** connect the output terminals and the input terminals of two adjacent groups of sensor terminals **30**. The first leads **105** include first column leads **1051** extending in the column direction and first row leads **1052** extending in the row direction. Each of the first column leads **1051** is provided on the first conductive layer **100**, and each of the first row leads **1052** is provided on the second conductive layer **200**. The first column leads **1051** and the first row leads **1052** are electrically connected through via holes. Taking the first leads **105** as shown in the figure as an example, the first leads **105** include one first column lead **1051** and two first row leads **1052**. The two first row leads **1052** extend laterally out from the output terminal and the input terminal respectively. The two first row leads **1052** are electrically connected to the longitudinal first column lead **1051** at the same time through via holes, so that the output terminals and the input terminals of two adjacent groups of sensor terminals **30** are electrically connected. FIG. **13(a)** shows a case where the first column lead **1051** does not intersect with the first row leads **1052**, and FIG. **13(b)** shows a case where the first column lead **1051** intersects with the first row leads **1052**.

[0098] In an embodiment, the first column leads **1051** connected to the groups of sensor terminals **30** located in the same column are arranged along the column direction, so that all the first column leads **1051** occupy the least space in the column direction.

[0099] In yet another embodiment, referring to FIGS. **14-17**, FIG. **14** shows the signal line arrangement of the group of sensor terminals **30** in an embodiment, and FIG. **15** shows a schematic partial structural diagram of the array substrate in an embodiment. The schematic partial enlarged diagram in FIG. **15** is the same as that in FIG. **10**. Besides, FIG. **16** is a schematic structural diagram of a group of sensor terminals **30** in FIG. **14**, and FIG. **17** shows the wiring of the first conductive layer **100** in FIG. **14**. As shown in the figures, the number of the input signal lines **101** and the number of the output signal lines **102** are both one. In the column direction, among two adjacent groups of sensor terminals **30** located in the same column, the output terminal **32** of one group of sensor terminals **30** is electrically connected to the input terminal **31** of the other group of sensor terminals **30**. That is, all the sensors in each column are connected in series. Further, among the groups of sensor terminals **30** in two adjacent columns, the output terminal **32** of the group of sensor terminals **30** located in one column and the first row or the last row is electrically connected to the input terminal **31** of the group of sensor terminals **30** located in the other column and the first row or the last row, so that all the sensors are connected in series. Among all the groups of sensor terminals **30** connected in series, the input terminal **31** of the first group of sensor terminals **30** is connected to the input signal line **101**, and the output terminal **32** of the last group of sensor terminals **30** is connected to the output signal line **102**, so that the signal used to configure the sensors is transmitted to all the sensors on the array substrate.

[0100] FIG. **17** shows a schematic diagram of the transmission paths of the input signals and the output signals according to an embodiment of the present disclosure, and FIG. **18** schematically shows a structure where **15** groups of sensor terminals **30** are arranged in an array on the array substrate in 3 rows and 5 columns. The 15 points A, B, C, . . . , M, N, O represent 15 sensors respectively.

[0101] Each small square in the figures represents a light-emitting unit, each small square on the

abscissa represents a column of light-emitting units, and each small square on the ordinate represents a row of light-emitting units. All the light-emitting units are arranged in an array in rows and columns. The orthographic projections of the group of sensor terminals **30** and the light-emitting units on the base substrate do not overlap. The coordinate values next to each letter in FIG. **18** are used to indicate the positions of the terminal sensors on the array substrate. For example, A (**8.5, 38.5**) indicates that the sensor terminal A is located between the 8-th and 9-th columns of light-emitting units, and is further located between the 38-th and 39-th rows of light-emitting units.

[0102] In some embodiments, the $m \times n$ sensors are sequentially connected in series in an S-shape column by column and row by row. Alternatively, the $m \times n$ sensors are sequentially numbered column by column and row by row in a Z-shape. For example, as shown in FIG. **18**, when $m=3$ and $n=5$, sensor A is connected to the input signal line **101** through the input terminal **31** of the corresponding group of sensor terminals **30**. Then, sensor A and the sensors located in the same column are sequentially connected in series. For example, sensor A, sensor B, and sensor C are connected sequentially in series. After that, sensor C is connected in series with the most adjacent sensor D in the same row. Sensor D is connected sequentially in series with each sensor in the same column. For example, sensor D, sensor E, and sensor F are connected sequentially in series, and so on. Sensor O is connected to the output signal line **102** through the output terminal **32** of the corresponding group of sensor terminals **30**, so as to realize the series connection of the 15 groups of sensors **30**. Based on such series connection, a minimum of one input signal line **101** and one output signal line **102** need to be arranged on the array substrate. Besides, the input signal line **101** and the output signal line **102** only need to be respectively connected with the first and last sensors among various sensors with a series connection relationship, without the need to penetrate through the entire array substrate up and down. Compared with the connection between the groups of sensor terminals corresponding to multiple sensors and the signal lines as shown in FIG. **6**, the series connection can greatly reduce the number of the signal lines, thereby saving the wiring space of the array substrate. In an embodiment, since in two adjacent groups of sensor terminals **30**, the output terminal **32** of one group of sensor terminals **30** is electrically connected to the input terminal **31** of the other group of sensor terminals **30**, the second conductive layer **200** can be provided with lead for connecting the two terminals.

[0103] In an embodiment, referring to FIG. **16**, the array substrate further includes a plurality of first leads **105**. The first leads **105** connect the output sub-terminals and the input sub-terminals of two adjacent groups of sensor terminals **30**. The first leads **105** include first column leads **1051** extending in the column direction and first row leads **1052** extending in the row direction. Each of the first column leads **1051** is provided on the first conductive layer **100**, and each of the first row leads **1052** is provided on the second conductive layer **200**. The first column leads **1051** and the first row leads **1052** are electrically connected through via holes. Taking the first leads **105** as shown in the figures as an example, the first leads **105** include one first column lead **1051** and two first row leads **1052**. The two first row leads **1052** are respectively extend out from the output sub-terminal and the input sub-terminal laterally. The two first row leads **1052** are electrically connected to the longitudinal first column lead **1051** at the same time through via holes, so that the output terminals **32** and the input terminals **31** of two adjacent groups of sensor terminals **30** are electrically connected. FIG. **16(a)** shows a case where the first column lead **1051** does not intersect with the first row leads **1052**, and FIG. **16(b)** shows a case where the first column lead **1051** intersects with the first row leads **1052**.

[0104] In an embodiment, the first column leads **1051** connected to the groups of sensor terminals **30** located in the same column are arranged along the column direction, so that all the first column leads **1051** occupy the least space in the column direction.

[0105] Referring to FIGS. **6**, **8** and **14**, in some embodiments of the present disclosure, the number of the power signal lines **103** is equal to the number of the sensor terminals in the row direction;

and in the column direction, the power terminal of each group of sensor terminals **30** located in the same column **33** is connected to the same power signal line **103**, thereby reducing the number of the power signal lines **103**. Since the power signal lines **103** extend in the column direction, the power terminals **33** and the power signal lines **103** may be connected by providing lateral leads on the second conductive layer **200**. In the structures shown by FIG. 7, FIG. 12 and FIG. 17, the power signal lines **103** and the first column leads **1051** are arranged side by side, and a sufficient distance may be reserved between them, so as to avoid mutual signal interference.

[0106] Similarly, referring to FIG. 6, FIG. 8, and FIG. 14, in some embodiments of the present disclosure, the number of the first common voltage signal lines **104** is equal to the number of the groups of sensor terminals **30** in the row direction; and in the column direction, the common voltage terminal **34** of each group of sensor terminals **30** located in the same column is connected to the same first common voltage signal line **104** (i.e., the second common voltage signal line **201**), thereby reducing the number of the common voltage signal lines.

[0107] In an embodiment, the array substrate further includes a common voltage signal auxiliary line **205** disposed on the second conductive layer **200**. The common voltage signal auxiliary line **205** is electrically connected to the first common voltage signal line through a via hole, so as to increase the signal transmission path by two layers of wiring and improves the signal transmission strength. Referring to FIGS. 19-21, FIG. 19 shows a schematic partial structural diagram of the array substrate in an embodiment, FIG. 20 is a partial enlarged schematic diagram of the M area in FIG. 19, and FIG. 21 is a schematic structural diagram of a group of sensor terminals **30** in an embodiment. The figures exemplarily show a wiring way of the common voltage signal auxiliary line **205**. The common voltage signal line is in a grid shape and covers the gap between adjacent light-emitting units. In the thickness direction of the array substrate, the common voltage signal auxiliary line **205** according to an embodiment is located above the drive voltage signal line **202**. Since both the sensor terminal and the common voltage signal auxiliary line **205** are located on the second conductive layer **200**, the common voltage sub-terminal **34** may be directly connected to the common voltage signal auxiliary line **205**. In other embodiments, the common voltage signal auxiliary line **205** may also have other shapes, which are not specifically limited in embodiments of the present disclosure.

[0108] The groups of terminals **30** having the above structures and the signal lines connected thereto need to occupy the wiring space of the array substrate. In an embodiment, the orthographic projections of the group of sensor terminals **30**, the group of light-emitting element terminals **10**, and the group of drive circuit terminals **20** on the base substrate at least partially overlap with the orthographic projection of the second group of signal lines on the base substrate, so as to save the wiring space. Further, the orthographic projection of the group of sensor terminals **30** on the base substrate, and the orthographic projection of the group of light-emitting element terminals **10** and the group of drive circuit terminals **20** on the base substrate, are respectively located in the orthographic projections on the base substrate of different signal lines in the second group of signal lines. Specifically, according to embodiments shown in FIG. 1, FIG. 9, and FIG. 15, the orthographic projection on the base substrate **900** of the group of light-emitting element terminals **10** occupying most of the space overlaps with the orthographic projection on the base substrate **900** of the wider second common voltage signal line **201**; the orthographic projection on the base substrate **900** of the group of drive circuit terminals **20** also overlaps with the orthographic projection on the base substrate **900** of the second common voltage signal line **201**; and the orthographic projection on the base substrate **900** of the group of sensor terminals **30** overlaps with the orthographic projection on the base substrate **900** of the drive voltage signal line **202**. As a result, the wiring space can be saved.

[0109] For the above-mentioned input signal line **101**, output signal line **102**, power signal line **103**, and first lead **105**, each signal line corresponding to the groups of sensor terminals **30** in each column is located between a second common voltage signal line **201** and a drive voltage signal line

202. In order to utilize the existing space for wiring as much as possible, the edge of the second common voltage signal line **201** or the drive voltage signal line **202** may be properly slotted. If there are at least two signal lines extending in the column direction and being adjacent in the column direction, and their orthographic projections on any line parallel to the column direction share an overlapping area, the position of the slot may correspond to the overlapping area. Therefore, a larger wiring space can be obtained for the at least two adjacent signal lines, thereby improving the utilization rate of the substrate. Referring to FIG. **16(b)**, it can be understood that since the orthographic projections of the two adjacent first column leads **1051** extending longitudinally on any line parallel to the column direction share an overlapping area, the two first column leads **1051** have a wider dimension (including the line width of a single first column lead **1051** and the spacing in the row direction between adjacent first column leads **1051**) in the row direction occupied by the portion corresponding to the overlapping area. The groove **5** is provided on the left side of the second common voltage signal line **201** (i.e., the position corresponding to the above-mentioned overlapping area), so that the portion corresponding to the overlapping area of the two first column leads **1051** can correspond to a larger space in the row direction. The shape of the groove **5** includes but is not limited to the rectangle as in the figures. The size or position of the groove **5** may be chosen according to the size or wiring of each signal line or lead, which is not specifically limited in the present application.

[0110] In an embodiment, referring to FIG. **23**, the array substrate further includes a plurality of groups of capacitor terminals **40**. The groups of capacitor terminals **40** are disposed on the second conductive layer **200** for binding capacitors. The groups of capacitor terminals **40** includes a first capacitor terminal **41** and a second capacitor terminal **42**. The first capacitor terminal **41** and the power terminal **33** are connected to each other. The second capacitor terminal **42** and the common voltage terminal **34** are connected to each other, thereby reducing the noise generated by the sensor and making the overall electrical performance of the array substrate to be more stable.

[0111] FIG. **22** is a partial enlarged schematic view of the M area including the group of capacitor terminals **40** in FIG. **18**, and FIG. **23** is a schematic structural diagram of the group of capacitor terminals **40**. The array substrate further includes a second lead **106** and a third lead **107** disposed on the second conductive layer **200**. One end of the second lead **106** is connected to the first capacitor terminal **41**, and the other end of the second lead **106** is connected to the power signal line **103** through a via hole. One end of the third lead **107** is connected to the first capacitor terminal **41**, and the other end of the third lead **107** is connected to the power terminal **33** of the group of sensor terminals **30**.

[0112] As shown in FIG. **23**, in an embodiment, since the common voltage signal auxiliary line **205** is disposed on the second conductive layer **200**, the common voltage terminal **34** is directly connected to the common voltage signal auxiliary line **205**. Therefore, the second capacitor terminal **42** in the group of capacitor terminals **40** is also connected to the common voltage signal auxiliary line **205**, that is, electrically connected to the first common voltage signal line **104**. Thus, the static electricity generated near the capacitor can be transmitted to the common voltage signal line, so as to avoid electrostatic discharge damage to the array substrate. It should be noted that the common voltage terminal **34**, the second capacitor terminal **42**, and the common voltage signal auxiliary line are all arranged on the second conductive layer **200**. It can be understood that the common voltage signal auxiliary line **25** and other signal lines provided on the second conductive layer **200** need to be covered by an insulation layer, for preventing the lines from oxidizing and affecting the electrical performance. Besides, the upper surfaces of the terminals on the second conductive layer need to be electrically connected to peripheral components, so they are exposed. Therefore, the common voltage terminal **34** and the second capacitor terminal **42** may also be regarded as part of the common voltage signal auxiliary line **205**.

[0113] It should be noted that “extending along the row direction” and “extending along the column direction” in the present disclosure both refer to the overall direction of the signal line

along the row direction or the column direction, which may allow local bending or inclination within the processing error range for the purpose of avoiding other circuit structures, and is not limited to a standard straight line.

[0114] The array substrate provided by an embodiment of the present disclosure may be used as a substrate with a light-emitting function by mounting a light-emitting device thereon, and may be further applied into a display device as a backlight unit.

[0115] After the light-emitting elements, sensor, and drive chips are mounted on the array substrate according to an embodiment of the present disclosure, hemispherical microstructures may be fabricated on the light-emitting elements, sensors, and drive chips, so as to protect the above-mentioned structures and prevent them from being scratched during production and transportation. Specifically, the microstructure above the light-emitting elements is a light-transmissive material, which may further have optical shaping effects on the output light from the light-emitting elements such as improving the light efficiency or increasing the light output from the front view. Besides, the microstructure above the sensors and the drive chips may adopt the transparent materials or a material with a light absorbing effect, which is not limited herein.

[0116] Embodiments of the present disclosure further provide a display device including the array substrate in any of the above-mentioned embodiments. Since the display device includes the above-mentioned array substrate, it has the same beneficial effects, and details are not described herein again in the present disclosure.

[0117] The present disclosure does not specifically limit applications of the display device, which may be products or components with the flexible display function, such as TVs, notebook computers, tablet computers, wearable display devices, mobile phones, vehicle-mounted displays, navigation devices, e-books, digital photo frames, advertising light boxes, etc.

[0118] Other implementations provided by the disclosed examples will readily occur to those skilled in the art upon consideration of the present specification and practice of the content disclosed herein. The present application is intended to cover any modifications, uses or adaptations provided by embodiments of the present disclosure that follow the general principle provided by embodiments of the present disclosure and include those common knowledge or conventional technical means in the technical field not disclosed by the present disclosure. The specification and examples are to be regarded as exemplary only, with the true scope and spirit of embodiments of the present disclosure being indicated by the appended claims.

Claims

1. An array substrate, comprising: a base substrate; a first conductive layer and a second conductive layer, stacked on the base substrate and insulated from each other; a plurality of groups of light-emitting element terminals, arranged in an array on the second conductive layer for coupling with light-emitting elements; a plurality of groups of sensor terminals, arranged on the second conductive layer for coupling with sensors, wherein no overlap exists between an orthographic projection of the groups of sensor terminals on the base substrate and an orthographic projection of the groups of light-emitting element terminals on the base substrate, wherein the group of sensor terminals comprises an input terminal and an output terminal, wherein the sensor comprises an input pin and an output pin, and wherein the input terminal is configured for electrical connection with the input pin, and the output terminal is configured for electrical connection with the output pin; a first group of signal lines, disposed on the first conductive layer and electrically connected to the groups of sensor terminals for driving the sensors to sense; a second group of signal lines, disposed on the first conductive layer and electrically connected to the group of light-emitting element terminals for driving the light-emitting elements to emit light; and a plurality of first leads, wherein among two adjacent groups of sensor terminals, the first lead is connected to the output terminal of one group of sensor terminals and the input terminal of the other group of sensor

terminals.

2. The array substrate according to claim 1, wherein the first leads comprises first column leads extending along a column direction and first row leads extending along a row direction, wherein each of the first column leads is provided on the first conductive layer, each of the first row leads is provided on the second conductive layer, and the first column lead and the first row lead are electrically connected through a via hole.

3. The array substrate according to claim 2, wherein at least one of the first leads comprises one of the first column leads and two of the first row leads, the two of the first row leads extend laterally out from the output terminals and the input terminals of two adjacent groups of sensor terminals respectively, and the two of the first row leads are electrically connected to the first column lead at the same time through via holes.

4. The array substrate according to claim 2, wherein the first column leads connected to the groups of sensor terminals located in the same column are arranged along the column direction.

5. The array substrate according to claim 2, wherein the group of sensor terminals further comprises a power terminal, the sensor further comprises a power pin, and the power terminal is configured for electrical connection with the power pin; the first group of signal lines comprises a power signal line, and the power terminal is electrically connected to the power signal line; and the power signal line and the first column lead are arranged side by side and at intervals.

6. The array substrate according to claim 1, wherein $m \times n$ sensors are sequentially connected in series in an S-shape column by column and row by row, where m and n are both integers, m is a number of rows of the sensors connected in series, and n is a number of columns of the sensors connected in series.

7. The array substrate according to claim 6, wherein among two adjacent sensors in the $m \times n$ sensors sequentially connected in series in the S-shape column by column and row by row, the output pin of one sensor is electrically connected with the input pin of the other sensor through the first lead.

8. The array substrate according to claim 6, wherein the first group of signal lines comprises an input signal line and an output signal line; among all the sensors connected in series, the input terminal of the group of sensor terminals corresponding to the sensor at one end is connected to the input signal line, and the output terminal of the group of sensor terminals corresponding to the sensor at the other end is connected to the output signal line.

9. A light-emitting substrate, comprising: an array substrate; light-emitting elements, coupled to the groups of light-emitting element terminals of the array substrate; and sensors, coupled to the groups of sensor terminals of the array substrate, wherein the array substrate comprises: a base substrate; a first conductive layer and a second conductive layer, stacked on the base substrate and insulated from each other; a plurality of groups of light-emitting element terminals, arranged in an array on the second conductive layer for coupling with light-emitting elements; a plurality of groups of sensor terminals, arranged on the second conductive layer for coupling with sensors, wherein no overlap exists between an orthographic projection of the groups of sensor terminals on the base substrate and an orthographic projection of the groups of light-emitting element terminals on the base substrate, wherein the group of sensor terminals comprises an input terminal and an output terminal, wherein the sensor comprises an input pin and an output pin, and wherein the input terminal is configured for electrical connection with the input pin, and the output terminal is configured for electrical connection with the output pin; a first group of signal lines, disposed on the first conductive layer and electrically connected to the groups of sensor terminals for driving the sensors to sense; a second group of signal lines, disposed on the first conductive layer and electrically connected to the group of light-emitting element terminals for driving the light-emitting elements to emit light; and a plurality of first leads, wherein among two adjacent groups of sensor terminals, the first lead is connected to the output terminal of one group of sensor terminals and the input terminal of the other group of sensor terminals.

- 10.** The light-emitting substrate according to claim 9, wherein the first leads comprises first column leads extending along a column direction and first row leads extending along a row direction, wherein each of the first column leads is provided on the first conductive layer, each of the first row leads is provided on the second conductive layer, and the first column lead and the first row lead are electrically connected through a via hole.
- 11.** The light-emitting substrate according to claim 10, wherein at least one of the first leads comprises one of the first column leads and two of the first row leads, the two of the first row leads extend laterally out from the output terminals and the input terminals of two adjacent groups of sensor terminals respectively, and the two of the first row leads are electrically connected to the first column lead at the same time through via holes.
- 12.** The light-emitting substrate according to claim 10, wherein the first column leads connected to the groups of sensor terminals located in the same column are arranged along the column direction.
- 13.** The light-emitting substrate according to claim 10, wherein the group of sensor terminals further comprises a power terminal, the sensor further comprises a power pin, and the power terminal is configured for electrical connection with the power pin; the first group of signal lines comprises a power signal line, and the power terminal is electrically connected to the power signal line; and the power signal line and the first column lead are arranged side by side and at intervals.
- 14.** The light-emitting substrate according to claim 9, wherein $m \times n$ sensors are sequentially connected in series in an S-shape column by column and row by row, where m and n are both integers, m is a number of rows of the sensors connected in series, and n is a number of columns of the sensors connected in series.
- 15.** The light-emitting substrate according to claim 14, wherein among two adjacent sensors in the $m \times n$ sensors sequentially connected in series in the S-shape column by column and row by row, the output pin of one sensor is electrically connected with the input pin of the other sensor through the first lead.
- 16.** The light-emitting substrate according to claim 14, wherein the first group of signal lines comprises an input signal line and an output signal line; among all the sensors connected in series, the input terminal of the group of sensor terminals corresponding to the sensor at one end is connected to the input signal line, and the output terminal of the group of sensor terminals corresponding to the sensor at the other end is connected to the output signal line.
- 17.** A display device, comprising a light-emitting substrate, wherein the light-emitting substrate comprises: an array substrate; light-emitting elements, coupled to the groups of light-emitting element terminals of the array substrate; and sensors, coupled to the groups of sensor terminals of the array substrate, wherein the array substrate comprises: a base substrate; a first conductive layer and a second conductive layer, stacked on the base substrate and insulated from each other; a plurality of groups of light-emitting element terminals, arranged in an array on the second conductive layer for coupling with light-emitting elements; a plurality of groups of sensor terminals, arranged on the second conductive layer for coupling with sensors, wherein no overlap exists between an orthographic projection of the groups of sensor terminals on the base substrate and an orthographic projection of the groups of light-emitting element terminals on the base substrate, wherein the group of sensor terminals comprises an input terminal and an output terminal, wherein the sensor comprises an input pin and an output pin, and wherein the input terminal is configured for electrical connection with the input pin, and the output terminal is configured for electrical connection with the output pin; a first group of signal lines, disposed on the first conductive layer and electrically connected to the groups of sensor terminals for driving the sensors to sense; a second group of signal lines, disposed on the first conductive layer and electrically connected to the group of light-emitting element terminals for driving the light-emitting elements to emit light; and a plurality of first leads, wherein among two adjacent groups of sensor terminals, the first lead is connected to the output terminal of one group of sensor terminals and the input terminal of the other group of sensor terminals.

- 18.** The display device according to claim 17, wherein the first leads comprises first column leads extending along a column direction and first row leads extending along a row direction, wherein each of the first column leads is provided on the first conductive layer, each of the first row leads is provided on the second conductive layer, and the first column lead and the first row lead are electrically connected through a via hole.
- 19.** The display device according to claim 18, wherein at least one of the first leads comprises one of the first column leads and two of the first row leads, the two of the first row leads extend laterally out from the output terminals and the input terminals of two adjacent groups of sensor terminals respectively, and the two of the first row leads are electrically connected to the first column lead at the same time through via holes.
- 20.** The display device according to claim 18, wherein the first column leads connected to the groups of sensor terminals located in the same column are arranged along the column direction.
-