

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250279614

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

Okano; Yoshinobu et al.

SHOE APPARATUS, ACCESSORY, ACCESSORY SHOE APPARATUS, AND ELECTRONIC APPARATUS

Abstract

A shoe apparatus attachable to and detachable from an accessory shoe apparatus of an electronic apparatus in a first direction includes a plurality of connection terminals arranged in a second direction orthogonal to the first direction, a shoe engagement portion engageable with the accessory shoe apparatus, and a terminal protecting portion configured to project from the shoe engagement portion toward a tip side in the first direction and to protect the plurality of connection terminals. The plurality of connection terminals are exposed in a direction orthogonal to the first and second directions from the terminal protecting portion, and include slopes that tilt in an exposed direction from inside to outside in the second direction on both sides in the second direction of the terminal protecting portion.

Inventors: Okano; Yoshinobu (Saitama, JP), Ishii; Kenji (Kanagawa, JP), Sakamoto; Hiromichi (Tokyo, JP), Shu; Takayuki (Kanagawa, JP), Hayasaki; Hiromi (Kanagawa, JP), Ikeda; Kouji (Tokyo, JP), Hattori; Yuhei (Tokyo, JP), Tohyama; Kei (Kanagawa, JP)

Applicant: CANON KABUSHIKI KAISHA (Tokyo, JP)

Family ID: 83706657

Appl. No.: 19/210636

Filed: May 16, 2025

Foreign Application Priority Data

JP	2021-094031	Jun. 04, 2021
----	-------------	---------------

Related U.S. Application Data

Publication Classification

Int. Cl.: H01R13/631 (20060101); G03B15/02 (20210101)

U.S. Cl.:

CPC H01R13/631 (20130101); G03B15/02 (20130101); G03B2215/056 (20130101)

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION [0001] This application is a continuation of application Ser. No. 17/749,348, filed May 20, 2022, the entire disclosure of which is hereby incorporated by reference.

BACKGROUND OF THE INVENTION

Field of the Invention

[0002] The present invention relates to a shoe apparatus provided to an accessory to make the accessory attachable to and detachable from an electronic apparatus, and an accessory shoe apparatus provided to the electronic apparatus.

Description of the Related Art

[0003] An image pickup apparatus (electronic apparatus), such as a digital camera, includes an accessory shoe apparatus attachable to and detachable from a shoe apparatus of an accessory such as an illumination apparatus (flash unit). The accessory shoe apparatus includes an engagement member engageable with and configured to hold the shoe apparatus, and each of the accessory shoe apparatus and the shoe apparatus includes connection terminals for enabling bidirectional communication between the image pickup apparatus and the accessory. Conventionally, the number of connection terminals is often five.

[0004] Japanese Patent Laid-Open No. (“JP”) 2018-084681 discloses an electronic viewfinder having a shoe apparatus attachable to and detachable from an accessory shoe apparatus of an image pickup apparatus, and the accessory shoe apparatus and the shoe apparatus maintain the compatibility with the five conventional connection terminals (communication pins) and increase the number of connection terminals within the shape of the engagement member.

[0005] However, if the shoe apparatus having a large number of connection terminals as disclosed in JP 2018-084681 gives priority to securing an area necessary to arrange those connection terminals, an area for a shape for protecting those communication terminals and a positioning area between components are limited. In addition, in the case where the shoe apparatus includes a terminal protecting portion for protecting the connection terminal separately from a portion engageable with the engagement member of the accessory shoe apparatus and an external force is applied to the accessory while the terminal protecting portion alone contacts the engagement member of the accessory shoe apparatus, the terminal protecting portion may get damaged.

SUMMARY OF THE INVENTION

[0006] The present invention provides a compact shoe apparatus etc., each of which can secure an area for arranging many communication terminals, an area for a shape for protecting them, and a positioning area between components, and suppress damages of a terminal protecting portion.

[0007] A shoe apparatus according to one aspect of the present invention is attachable to and detachable from an accessory shoe apparatus of an electronic apparatus in a first direction. The

shoe apparatus includes a plurality of connection terminals arranged in a second direction orthogonal to the first direction, a shoe engagement portion engageable with the accessory shoe apparatus, and a terminal protecting portion configured to project from the shoe engagement portion toward a tip side in the first direction and to protect the plurality of connection terminals. The plurality of connection terminals are exposed in a direction orthogonal to the first and second directions from the terminal protecting portion, and include slopes that tilt in an exposed direction from inside to outside in the second direction on both sides in the second direction of the terminal protecting portion.

[0008] An accessory according to another aspect of the present invention includes the above shoe apparatus. An accessory shoe apparatus according to another aspect of the present invention is attachable to and detachable to the above shoe apparatus. An electronic apparatus according to another aspect of the present invention includes the above accessory shoe apparatus.

[0009] Further features of the present invention will become apparent from the following description of exemplary embodiments with reference to the attached drawings.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0010] FIG. 1 illustrates configurations of a camera and an accessory according to a first embodiment of the present invention.

[0011] FIGS. 2A to 2C illustrate an example of the camera to which the accessory is attached and their contact arrangements according to the first embodiment.

[0012] FIGS. 3A and 3B illustrate how an external force is applied to the accessory attached to the camera according to the first embodiment.

[0013] FIG. 4A illustrates a configuration for determining a connection state of a grounded contact according to the first embodiment.

[0014] FIG. 4B is a flowchart illustrating processing executed by the camera according to the first embodiment.

[0015] FIGS. 5A and 5B illustrate a flowchart of processing executed by the camera according to the first embodiment.

[0016] FIGS. 6A, 6B, and 6C are timing charts illustrating signal changes when a contact adjacent to a power supply contact is short-circuited according to the first embodiment.

[0017] FIG. 7 illustrates an assignment example of a functional signal to an accessory type according to the first embodiment.

[0018] FIGS. 8A, 8B, and 8C illustrate a connection destination configuration of the functional signal according to the first embodiment.

[0019] FIG. 9 illustrates a configuration example of the camera and the accessory according to the first embodiment.

[0020] FIG. 10 illustrates another configuration example of the camera and accessories according to the first embodiment.

[0021] FIG. 11 illustrates still another configuration example of the camera and accessories according to the first embodiment.

[0022] FIG. 12 illustrates a configuration example of the accessory according to the first embodiment.

[0023] FIG. 13 illustrates a configuration example of the camera, the accessory, and an intermediate accessory according to the first embodiment.

[0024] FIG. 14 illustrates another configuration example of the camera, the accessory, and the intermediate accessory according to the first embodiment.

[0025] FIGS. 15A and 15B are timing charts in the case where the accessory is a strobe device

according to the first embodiment.

[0026] FIGS. **16A**, **16B**, and **16C** are perspective views of the camera and an external flash unit as the accessory according to the first embodiment.

[0027] FIGS. **17A** and **17B** are an exploded view and a perspective view of an accessory shoe according to the first embodiment.

[0028] FIGS. **18A**, **18B**, and **18C** illustrate a structure of an engagement member and a connection terminal connector of the accessory shoe according to the first embodiment.

[0029] FIGS. **19A** and **19B** are a perspective view and a sectional view of the external flash unit according to the first embodiment.

[0030] FIGS. **20A**, **20B**, and **20C** are a perspective view and a front view illustrating an internal structure of a camera connector according to the first embodiment.

[0031] FIGS. **21A** and **21B** are a top view and a sectional view of the camera connector according to the first embodiment.

[0032] FIGS. **22A** and **22B** are a perspective view and a sectional view of the external flash unit according to a variation.

[0033] FIGS. **23A** and **23B** are a perspective view and a front view illustrating the internal structure of the connector according to the variation.

[0034] FIG. **24** is a front view of the accessory shoe according to the first embodiment.

[0035] FIG. **25** is a partially enlarged view of a connection plug according to the first embodiment.

[0036] FIG. **26** is a front sectional view illustrating a state in which the camera connector is attached to the accessory shoe according to the first embodiment.

[0037] FIGS. **27A** and **27B** are a perspective view and a sectional view of the external flash unit according to the first embodiment.

[0038] FIGS. **28A** and **28B** are a perspective view and a front view illustrating the internal structure of the camera connector according to the first embodiment.

[0039] FIGS. **29A** to **29C** are perspective and sectional views of the digital camera and the external flash unit according to the first embodiment.

[0040] FIG. **30** illustrates a top cover accessory shoe according to the first embodiment.

[0041] FIGS. **31A** to **31C** illustrate a drip-proof structure according to the first embodiment.

[0042] FIG. **32** is a front view illustrating a state in which a camera connector is attached to an accessory shoe according to a second embodiment.

[0043] FIG. **33** illustrates a perspective view of the accessory shoe according to the second embodiment.

[0044] FIGS. **34A** and **34B** are a perspective view and a front view illustrating the internal structure of the camera connector according to the second embodiment.

[0045] FIG. **35** is a front view illustrating a state in which the camera connector is attached to the accessory shoe according to the second embodiment.

[0046] FIGS. **36A** and **36B** are top views of the accessory shoe and the camera connector according to the second embodiment.

[0047] FIG. **37** is a front view illustrating a state in which the camera connector is attached to the accessory shoe according to the second embodiment.

[0048] FIGS. **38A** and **38B** illustrate a positional relationship between a slope of the camera connector and connection terminals according to the second embodiment.

DESCRIPTION OF THE EMBODIMENTS

[0049] Referring now to the accompanying drawings, a description will be given of embodiments according to the present invention.

FIRST EMBODIMENT

[0050] FIG. **1** illustrates an electrical configuration of a camera **100** as an electronic apparatus according to a first embodiment of the present invention and an accessory **200** detachably attached to the camera **100**. In the camera **100** and the accessory **200**, a plurality of contacts (terminals)

TC01 to TC21 of a camera connector **141** provided in the camera **100** and a plurality of contacts TA01 to TA21 of an accessory connector **211** provided in the accessory **200** are connected to each other in a one-to-one correspondence, respectively and thereby they are electrically connected with each other.

[0051] The camera **100** is supplied with the electric power from a battery **111**. The battery **111** is attachable to and detachable from the camera **100**. A camera control circuit **101** as a control means of the camera **100** is a circuit that controls the entire camera **100**, and includes a microcomputer having a built-in CPU or the like.

[0052] A system power supply circuit **112** is a circuit that generates a power supply for supplying the power to each circuit in the camera **100**, and includes a DC/DC converter circuit, an LDO (Low Drop Out), a charge pump circuit, and the like. A voltage of 1.8V generated by the system power supply circuit **112** is constantly supplied as a camera microcomputer power supply VMCU_C from the battery **111** to the camera control circuit **101**. The camera control circuit **101** controls the system power supply circuit **112** and thereby controls turning on and off of the power supply to each circuit of the camera **100**.

[0053] An optical lens **121** is attachable to and detachable from the camera **100**. Light from an object incident through the optical lens **121** is imaged on an image sensor **122** including a CMOS sensor, a CCD sensor, or the like. The object image formed on the image sensor **122** is encoded into a digital imaging signal. An image processing circuit **123** performs image processing such as noise reduction processing and white balance processing for the digital imaging signal to generate image data, and converts it into an image file, such as a JPEG format, in order to record the image data in a recording memory **126**. The image processing circuit **123** generates from the image data VRAM image data for display on a display circuit **127**.

[0054] A memory control circuit **124** controls a transmission and reception of the image data and other data generated by the image processing circuit **123** and the like. A volatile memory **125** is a memory capable of high-speed reading and writing such as DDR3 SDRAM, and is used for a workspace or the like of the image processing performed by the image processing circuit **123**. The recording memory **126** is a readable and writable recording medium such as an SD card or CFexpress card that is attachable to and detachable from the camera **100** via an unillustrated connector. The display circuit **127** is a display located on the back surface of the camera **100**, and includes an LCD panel, an organic EL display panel, and the like. A backlight circuit **128** adjusts the brightness of the display circuit **127** by changing a light amount of the backlight of the display circuit **127**.

[0055] Each of an accessory-use power supply circuit A**131** and an accessory-use power supply circuit B**132** as the power supply means is a voltage conversion circuit that converts the voltage supplied from the system power supply circuit **112** into a predetermined voltage, and generates 3.3 V as an accessory power supply VACC in this embodiment.

[0056] The accessory-use power supply circuit A**131** is a power supply circuit including an LDO or the like and having a low self-consumption power. The accessory-use power supply circuit B**132** is a circuit that includes a DC/DC converter circuit or the like and can flow a larger current than that of the accessory-use power supply circuit A**131**. The self-consumption power of the accessory-use power supply circuit B**132** is larger than that of the accessory-use power supply circuit A**131**. Therefore, when the load current is small, the accessory-use power supply circuit A**131** is more efficient than the accessory-use power supply circuit B**132**, and when the load current is large, the accessory-use power supply circuit B**132** is more efficient than the accessory-use power supply circuit A**131**. The camera control circuit **101** controls turning on and off of the voltage outputs of the accessory-use power supply circuits A**131** and B**132** according to the operating state of the accessory **200**.

[0057] A protection circuit **133** as a protection means includes a current fuse element, a poly-switching element, an electronic fuse circuit that combines a resistor, an amplifier, and a switching

element, and the like, and outputs an overcurrent detection signal DET_OVC when the power supply current values from the accessory-use power supply circuits A131 and B132 to the accessory 200 become excessive (abnormal) beyond a predetermined value. In this embodiment, the protection circuit 133 includes an electronic fuse circuit, and notifies the camera control circuit 101 through the overcurrent detection signal DET_OVC in the case where the current of 1 A or higher flows. The overcurrent detection signal DET_OVC indicates the overcurrent through the Hi level.

[0058] The camera connector 141 is a connector for an electrical connection with the accessory 200 via 21 contacts TC01 to TC21 arranged in a row. The contacts TC01 to TC21 are arranged in this order from one end to the other end in the arrangement direction thereof.

[0059] TC01 is connected to the ground (GND) and serves not only as a contact for the reference potential (GND potential) but also as a contact for controlling the wiring impedance of differential signals DIN and DIP described below. TC01 corresponds to a third grounded contact.

[0060] The differential signal DIN connected to TC02 and the differential signal DIP connected to TC03 are paired differential data communication signals that perform a data communication, and connected to the camera control circuit 101. TC02, TC03, TC07 to TC17, TC19, and TC20, which will be described later, are communication contacts.

[0061] TC04 as a first grounded contact is connected to GND and serves as a reference potential contact between the camera 100 and the accessory 200. TC04 is disposed outside TC05 described below in the contact arrangement direction.

[0062] The accessory power supply VACC generated by the accessory-use power supply circuits A131 and B132 is connected to TC05 as the power supply contact via the protection circuit 133.

[0063] An accessory attachment detection signal/ACC_DET is connected to TC06 as an attachment detection contact. The accessory attachment detection signal/ACC_DET is pulled up to the camera microcomputer power supply VMCU_C via a resistor element Rp134 (10 kΩ). The camera control circuit 101 can detect whether or not the accessory 200 is attached, by reading the signal level of the accessory attachment detection signal/ACC_DET. If the accessory attachment detection signal/ACC_DET signal level (potential) is a Hi level (predetermined potential), the accessory 200 is detected as being non-attached, and if it is a Lo level (GND potential as described later), the accessory 200 is detected as being attached.

[0064] When the camera 100 is powered on and the signal level (potential) of the accessory attachment detection signal/ACC_DET changes from the Hi level to the Lo level, various transmissions are performed between the camera 100 and the accessory 200 via the contacts.

[0065] The camera control circuit 101 supplies the power to the accessory 200 via TC05 as a power supply contact when the attachment state of the accessory 200 is detected.

[0066] SCLK connected to TC07, MOSI connected to TC08, MISO connected to TC09, and CS connected to TC10 are signals to be used by the camera control circuit 101 as a communication master to perform a SPI (Serial Peripheral Interface) communication. In this embodiment, the communication clock frequency of the SPI communication is 1 MHz.

[0067] A communication request signal/WAKE for requesting a communication from the accessory 200 to the camera control circuit 101 is connected to TC11. The communication request signal/WAKE is pulled up to the camera microcomputer power supply VMCU_C via a resistor. The camera control circuit 101 can receive the communication request from the accessory 200 by detecting a trailing edge of the communication request signal/WAKE.

[0068] SDA connected to TC12 and SCL connected to the TC13 are signals for the camera control circuit 101 to act as a communication master and perform an I2C (Inter-Integrated Circuit) communication. SDA and SCL are signals for an open drain communication (referred to as an open drain communication hereinafter) pulled up to the camera microcomputer power supply VMCU_C, and the communication frequency is 100 kbps in this embodiment.

[0069] In the I2C communication, both the data transmission from the camera 100 and the data

transmission from the accessory **200** are performed via the SDA. When the SPI communication and the I2C communication are compared with each other, the I2C communication has a lower communication speed than that of the SPI communication, and can achieve a lower power consumption. The SPI communication has a higher communication speed than the I2C communication, and is therefore suitable for a communication of information having a large data amount. Therefore, in the communication between the camera **100** and the accessory **200** according to this embodiment, information having a large data amount is communicated in the SPI communication, and information having a small data amount is communicated in the I2C communication. For example, data is first communicated in the I2C communication, and a control is made so that the SPI communication is further executed in the case where the SPI communication can be executed or the SPI communication needs to be executed based on this data.

[0070] An FNC1 signal connected to TC14 (synchronous contact), an FNC2 signal connected to TC15, an FNC3 signal connected to TC16, and an FNC4 signal connected to TC17 are signals that can change the function according to the type of the attached accessory **200**. For example, in the case where the accessory **200** is a microphone device, the signal communicated via TC 15 is an audio data signal. In the case where the accessory **200** is an illumination (strobe or flash) unit, the signal communicated via TC14 is a signal for controlling the light emission timing. Depending on the type of the attached accessory, a signal that realizes a different function may be communicated via the same contact. For example, in the case where the accessory **200** is an accessory other than the illumination unit, a synchronization signal for controlling a timing different from the light emission timing may be communicated via TC14. TC14 to TC17 correspond to functional signal contacts. A communication using at least one of the functional signal contacts is also referred to as a functional signal communication.

[0071] The functional signal communication can execute a communication at a timing that does not depend on the I2C communication or the SPI communication in parallel with the I2C communication and the SPI communication.

[0072] The type of the accessory, as used herein, means the above-mentioned microphone device, illumination unit, and the like. Accessories that achieve the same purpose, such as illuminations with different performances, belong to the same type. Accessories that achieve different purposes, such as a microphone device and an illumination unit, belong to different types.

[0073] The functional signal communication is executed based on the information acquired by the I2C communication or the SPI communication.

[0074] TC18 as a second grounded contact (reference potential contact) is also connected to GND, and is a contact that serves as a reference potential between the camera **100** and the accessory **200**, similar to TC04.

[0075] A differential signal D2N connected to TC19 (first differential signal contact) and a differential signal D2P connected to TC20 (second differential signal contact) are paired data communication signals that perform a data communication and connected to the camera control circuit **101**. For example, the USB communication can be performed via TC19 and TC20.

[0076] TC21 is connected to GND and can be used not only as a contact for a reference potential but also as a contact for controlling the wiring impedance of the differential signals D2N and D2P. TC21 corresponds to a fourth grounded contact.

[0077] The contacts TC01, TC04, TC06, TC18, and TC21 are connected, for example, to a GND portion of a flexible substrate **158** illustrated in FIGS. 17A and 17B, which will be described later, and the GND portion of the flexible substrate **158** is fixed with a metallic member having a GND level of the camera **100** by a screw **157** or the like. The metallic member having the GND level includes, for example, an engagement member **151**, an unillustrated base plate inside the camera **100**, and the like.

[0078] This embodiment disposes the attachment detection contact TC06 to which the accessory attachment detection signal/ACC_DET is connected is arranged, next to the contact (first clock

contact) TC07 that transmits SCLK (first clock signal) as a clock signal. In general, a noise (clock noise) due to the potential fluctuation of the clock signal is transmitted to a contact adjacent to the contact of the clock signal, which may cause a malfunction. In particular, in a configuration having a large number of contacts and a short distance between contacts as in this embodiment, the influence is more significant. Accordingly, disposing the attachment detection contact TC06 next to the SCLK contact TC07 can suppress the influence of the clock noise.

[0079] The accessory attachment detection signal/ACC_DET is pulled up before the accessory is attached, but is set to the GND potential after the accessory is attached. On the other hand, the SCLK contact TC07 that transmits the clock signal does not transmit the clock signal before the accessory is attached, and thus the potential does not fluctuate. The potential fluctuates because the clock signal is transmitted only after the accessory is attached.

[0080] When the SCLK contact TC07 transmits the clock signal, the attachment detection contact TC06 is at the GND potential. Therefore, even if the attachment detection contact TC06 receives the clock noises, the potential of the control circuit of the camera 100 or the accessory 200 is less likely to fluctuate, so that the malfunction can be prevented. In addition, the clock noise can be restrained from transmitting to a position distant farther than the attachment detection contact TC06. As a result, since it is unnecessary to dispose the GND terminal, the influence of the clock noises can be suppressed without increasing the number of contacts.

[0081] SCL (second clock signal) as a clock signal is also transmitted to the contact (second clock contact) TC13. However, the frequency of SCLK transmitted to the SCLK contact TC07 is higher than that of SCL, and the SCLK contact TC07 generates more clock noises than the SCL contact TC13. Therefore, disposing the attachment detection contact TC06 next to the SCLK contact TC07 rather than next to the SCL contact TC13 can provide a greater effect of preventing the malfunction due to the clock noises.

[0082] In addition to the difference in frequency, SCL transmitted by the SCL contact TC13 is a clock signal of the I2C communication standard, and the voltage fluctuation of the signal line is driven by the open drain connection. On the other hand, SCLK transmitted by the SCLK contact TC07 is a clock signal pursuant to the SPI communication standard, and the voltage fluctuation of the signal line is driven by the CMOS output. Therefore, the SCL contact TC13 tends to have a gentler edge of the voltage fluctuation than the SCLK contact TC07, and the clock noises are less likely to occur. Thus, disposing the attachment detection contact TC06 next to the SCLK contact TC07 rather than next to the SCL contact TC13 is more effective in preventing the malfunction caused by the clock noises.

[0083] The differential signals DIN and DIP may be transmitted in pairs to the first and second differential signal contacts TC19 and TC20 to transmit the clock signal. At that time, a clock signal (third clock signal) having a frequency higher than that of the SCLK contact TC07 or the SCL contact TC13 may be transmitted. Since the differential signals DIN and DIP are paired signals, the emission of the clock noise is smaller than that of the SCLK contact TC07 or the SCL contact TC13 that transmits a single-ended signal. Therefore, disposing the attachment detection contact TC06 next to the SCLK contact TC07 rather than next to the first and second differential signal contacts TC19 and TC20 can more effectively prevent the malfunction caused by the clock noise.

[0084] The contact (first data contact) TC08 disposed on an opposite side of the attachment detection contact TC06 with respect to the SCLK contact TC07 transmits MOSI (first data signal). Since MOSI is a data signal, it appears to be susceptible to clock noises. Since MOSI is a data signal of the same SPI communication standard as the clock signal transmitted by the SCLK contact TC07, the fluctuation timing of the potential is synchronized with the clock signal and is less affected by the clock noise. Therefore, the contact TC08 does not have to be fixed to the GND potential and can be used as a MOSI contact.

[0085] The accessory 200 has a battery 205 and receives the power supply from the battery 205 and also receives the power supply from the camera 100 via the camera connector 141 and the

accessory connector **211**. An accessory control circuit **201** as a control means of the accessory **200** is a circuit that controls the entire accessory **200**, and is a microcomputer having a built-in CPU and the like.

[0086] An accessory power supply circuit **202** is a circuit that generates a power supply to be supplied to each circuit of the accessory **200**, and includes a DC/DC converter circuit, an LDO, a charge pump circuit, and the like. The voltage 1.8 V generated by the accessory power supply circuit **202** is constantly supplied as an accessory microcomputer power supply VMCU_A to the accessory control circuit **201**. Turning on and off of the power supply to each circuit of the accessory **200** is controlled by controlling the accessory power supply circuit **202**.

[0087] A charging circuit **204** is a circuit for charging the battery **205** using the power supplied from the camera **100**. In the case where it can be determined that the sufficient power is supplied from the camera **100** to perform the charging operation, the accessory control circuit **201** controls the charging circuit **204** to charge the battery **205**. Although the battery **205** attached to the accessory **200** has been described in this embodiment, the accessory **200** may operate only with the power supply from the camera **100** without the battery **205**. In this case, no charging circuit **204** is necessary.

[0088] A differential communication circuit **207** is a circuit for performing a differential communication with the camera **100**, and can transmit and receive data to and from the camera **100**. An external communication IF circuit **208** is an IF circuit for performing a data communication with an unillustrated external device, such as an Ethernet communication IF, a wireless LAN communication IF, and a public network communication IF.

[0089] The accessory control circuit **201** controls the differential communication circuit **207** and the external communication IF circuit **208** and thereby can transmit the data received from the camera **100** to the external device or the data received from the external device to the camera **100**. A functional circuit **206** is a circuit having a different function depending on the type of the accessory **200**. A configuration example of the functional circuit **206** will be described later.

[0090] An external connection terminal **209** is a connector terminal connectable to an external device, and is a USB TYPE-C connector in this embodiment. A connection detecting circuit **210** is a circuit for detecting that an external device is connected to the external connection terminal **209**, and the accessory control circuit **201** can detect that the external device has been connected to the external connection terminal **209** by receiving the output signal of the connection detecting circuit **210**.

[0091] A power switch **203** is a switch for turning on and off the operation of the accessory **200**, and the accessory control circuit **201** can detect the ON position and the OFF position by reading the signal level of the terminal to which the power switch **203** is connected.

[0092] The accessory connector **211** is a connector electrically connectable to the camera **100** via the **21** contacts TA01 to TA21 that are arranged in a row. The contacts TA01 to TA21 are arranged in this order from one end to the other end in the arrangement direction.

[0093] TA01 is connected to GND and serves not only as a contact of the reference potential but also as a contact for controlling the wiring impedance of the differential signals DIN and DIP. TA01 corresponds to a third grounded contact.

[0094] The differential signal DIN connected to TA02 and the differential signal DIP connected to TA03 are paired data communication signals for the data communication, and are connected to the differential communication circuit **207**. TA02, TA03, TA07 to TA17, TA19, and TA20 described later are communication contacts.

[0095] TA04 as the first grounded contact is connected to GND and serves as a reference potential contact between the camera **100** and the accessory **200**. TA04 is located outside TA05 described below in the contact arrangement direction.

[0096] The accessory power supply circuit **202** and the charging circuit **204** are connected to TA05 as the power supply contact, and the accessory power supply VACC supplied from the camera **100**

is connected to it.

[0097] TA**06** as an attachment detection contact is directly connected to GND, and turns the accessory attachment detection signal/ACC_DET described above into the GND level as the Lo level when the accessory **200** is attached to the camera **100**. Thereby, it becomes it serves as a contact for causing the camera **100** to detect the attachment of the accessory **200**.

[0098] SCLK connected to TA**07**, MOSI connected to TA**08**, MISO connected to TA**09**, and CS connected to TA**10** are signals for the accessory control circuit **201** to act as a communication slave and perform the SPI communication.

[0099] The communication request signal/WAKE for requesting the communication from the accessory control circuit **201** to the camera **100** is connected to TA**11**. When the accessory control circuit **201** outputs the communication request signal/WAKE at the Lo level and requests the camera **100** for the communication in the case where the accessory control circuit **201** determines that the communication with the camera **100** is necessary.

[0100] When the power is supplied from the camera control circuit **101** to the accessory **200** via TC**5** in response to detecting that the accessory **200** is in the attached state, the accessory control circuit **201** notifies the camera control circuit **101** of the reception of the power supply by changing the signal level (potential) of the communication request signal/WAKE from the Hi level to the Lo level.

[0101] The accessory control circuit **201** notifies that the accessory **200** has a cause of the communication with the camera **100** by changing the signal level (potential) of the communication request signal/WAKE from the Hi level to the Lo level even without any requests from the camera. With this configuration, the camera control circuit **101** can omit the operation of periodically checking whether or not the accessory **200** has a cause of the communication through polling. In addition, in the case where the accessory **200** has the cause of the communication, the accessory **200** can communicate the fact to the camera **100** on a real-time basis.

[0102] SDA connected to TA**12** and SCL connected to TA**13** are signals for the accessory control circuit **201** to act as a communication slave and perform the I2C communication.

[0103] The FNC**1** signal connected to TA**14** (synchronous contact), the FNC**2** signal connected to TA**15**, the FNC**3** signal connected to TA**16**, and the FNC**4** signal connected to TA**17** are signals whose functions can be changed according to the type of the accessory **200**. For example, in the case where the accessory **200** is a microphone device, it is an audio data signal, and in the case where the accessory **200** is a strobe device, it is a signal for controlling the light emission timing. TA**14** to TA**17** correspond to functional signal contacts.

[0104] TA**18** as the second grounded contact (reference potential contact) is also connected to GND, and serves as a reference potential contact between the camera **100** and the accessory **200**, similar to TA**04**.

[0105] The differential signal D2N connected to TA**19** (first differential signal contact) and the differential signal D2P connected to TA**20** (second differential signal contact) are paired data communication signals for the data communication and connected to the external connection terminal **209**.

[0106] TA**21** is connected to GND and serves not only as a contact for a reference potential but also as a terminal for controlling the wiring impedance of the differential signals D2N and D2P. TA**21** corresponds to a fourth grounded contact. The contacts TA**01**, TA**04**, TA**06**, TA**18**, and TA**21** are connected, for example, to the GND portion of the flexible substrate **259** illustrated in FIGS. **19A** and **19B**, which will be described later, and the GND portion of the flexible substrate **259** is fixed to a metallic member having a GND level of the accessory **200** with an unillustrated screw etc. The metallic member having the GND level includes, for example, a shoe attachment leg **251** and an unillustrated base plate inside the accessory **200**.

[0107] FIG. **2A** illustrates that the accessory connector **211** disposed on the shoe provided on the lower part of the accessory (strobe device) **200** is connected to the camera connector **141** disposed

on the accessory shoe provided at the top of the camera **100**. FIG. 2B illustrates an arrangement example of the **21** contacts TC**01** to TC**21** in the camera connector **141**. TC**01** is disposed at the right end viewed from the object side, and the **21** contacts up to TC**21** are arranged in a row. The accessory shoe is attached by sliding it from the top side to the bottom side in FIG. 2B relative to the accessory shoe having the camera connector **141**.

[0108] FIG. 2C illustrates an arrangement example of the **21** contacts TA**01** to TA**21** in the accessory connector **211**. Similar to the camera connector **141**, TA**01** is disposed at the right end viewed from the object side, and the **21** contacts up to TA**21** are arranged in a row. Usually, the contacts TA**01** to TA**21** and the corresponding contacts TC**01** to TC**21** are connected to each other. However, if an excessive static pressure or impact is applied to the accessory **200**, the contacts may be disconnected. In particular, when a force in the rotational direction acts on the direction in which the contacts are arranged in the accessory **200**, the disconnection is likely to occur at the end contacts.

[0109] FIG. 3A exaggerates the appearance of the excessive static pressure applied to the accessory **200** from the left side viewed from the object side. At this time, a force acts on the contacts TC**21** and TA**21** and the neighboring contacts of the camera connector **141** and the accessory connector **211** in the disconnecting direction, and a poor connection is likely to occur. On the other hand, a stronger force acts on the contacts TC**01** and TA**01** and the neighboring contacts in the connecting direction than that in the normal state.

[0110] FIG. 3B exaggerates the appearance of the excessive static pressure applied to the accessory **200** from the right side viewed from the object side. At this time, a force acts on the contacts TC**01** and TA**01** and the neighboring contacts of the camera connector **141** and the accessory connector **211** in the disconnecting direction, and a poor connection is likely to occur. On the other hand, a stronger force acts on the contacts TC**21** and TA**21** and the neighboring contacts in the connecting directions than that in the normal state.

[0111] This embodiment connects to GND the contacts TC**01** and TA**01** and TC**21** and TA**21** at both ends of the camera connector **141** and the accessory connector **211**. Thereby, even if a poor connection temporarily occurs at the contact at one end due to the excessive static pressure, the GND connection can be secured at the contact at the other end. Therefore, this configuration can restrain each circuit and electric element from getting damaged as a result of that the reference potential of the accessory **200** becomes unstable due to the poor GND connection.

[0112] In the case where the accessory **200** in which part of the GND contacts is missing is attached due to a defect and breakdown of the accessory connector **211** or the like, the camera control circuit **101** cannot detect that the part of the GND contacts is missing. In such a case, the operating current concentrates on the remaining GND contacts, and the accessory **200** may malfunction in some cases.

[0113] FIG. 4A is a configuration example for allowing the camera **100** to detect the connection state of the GND contact of the accessory **200**, and illustrates extracted part relating to the grounded contact from the configuration illustrated in FIGS. 1.

[0114] TC**01**, TC**04**, TC**18**, and TC**21** are connected to input terminals P**1**, P**2**, P**3**, and P**4** of the camera control circuit **101**, respectively, and pulled to the camera microcomputer power supply VMCU_C via resistors **1011Rp_g1**, **1021Rp_g2**, **1031Rp_g3**, and **1041Rp_g4**, respectively. An SW circuit **1**, an SW circuit **2**, an SW circuit **3**, and an SW circuit **4** are connected to TC**01**, TC**04**, TC**18**, and TC**21**, respectively.

[0115] The SW circuit **1** is a switching circuit driven by the control signal of the camera control circuit **101**, and when it is turned on by the control signal, TC**01** is connected to GND. It is desirable that the SW circuit **1** includes, for example, an FET, or a circuit that has impedance that is as small as possible when the operation is turned on, and the impedance that is as large as possible when the operation is turned off. Each of the SW circuits **2**, **3**, and **4** also has the same configuration as that of the SW circuit **1** as illustrated in FIG. 4A.

[0116] A flowchart of FIG. 4B illustrates a sequence for determining the connection state of the grounded terminal in the configuration illustrated in FIG. 4A. The camera control circuit **101** executes this processing and other processing described later according to a computer program. S means the step.

[0117] In **S1001**, the camera control circuit **101** monitors the signal level of the accessory attachment detection signal/ACC_DET and determines whether or not the accessory **200** is attached. If the signal level is Hi, the camera control circuit **101** returns to **S1001** and performs the detection again, assuming that the accessory **200** is not attached, and if the signal level is Lo, it proceeds to **S1002** assuming that the accessory **200** is attached.

[0118] In **S1002**, the camera control circuit **101** makes such a control that the SW circuit **1** is turned on and the SW circuits **2**, **3**, and **4** are turned off, respectively.

[0119] In **S1003**, the camera control circuit **101** confirms the voltage level of the input terminal P1, and determines that TC01 is connected to the grounded contact if it is a Lo level, and that TC01 is not connected to the grounded contact if it is a Hi level.

[0120] Next, in **S1004**, the camera control circuit **101** makes such a control that the SW circuit **2** is turned on and the SW circuits **1**, **3**, and **4** are turned off, respectively.

[0121] In **S1005**, the camera control circuit **101** confirms the voltage level of the input terminal P2, and determines that TC04 is connected to the grounded contact if it is a Lo level, and that TC04 is not connected to the grounded contact if it is a Hi level.

[0122] Next, in **S1006**, the camera control circuit **101** makes such a control that the SW circuit **3** is turned on and the SW circuits **1**, **2**, and **4** are turned off, respectively.

[0123] In **S1007**, the camera control circuit **101** confirms the voltage level of the input terminal P3, and determines that TC18 is connected to the grounded contact if it is a Lo level, and that TC18 is not connected to the grounded contact if it is a Hi level.

[0124] Next, in **S1008**, the camera control circuit **101** makes such a control that the SW circuit **4** is turned on and the SW circuits **1**, **2**, and **3** are turned off, respectively. In **S1009**, the camera control circuit **101** confirms the voltage level of the input terminal P4, and determines that TC18 is connected to the grounded contact if it is a Lo level, and that it is not connected to the grounded contact if it is a Hi level.

[0125] In **S1010**, the camera control circuit **101** makes such a control that the SW circuits **1**, **2**, **3**, and **4** are turned on, respectively.

[0126] Such a control enables the camera control circuit **101** to confirm the attachment state of the grounded contact with the attached accessory **200**, and to determine whether or not to supply to the accessory power supply circuit **202** and the like based on the ground connection state.

[0127] In the meanwhile, if the accessory **200** is tilted to the camera **100** or the like when the accessory **200** is attached to the camera **100**, only some of the plurality of contacts TC01 to TC21 and TA01 to TA21 can be connected with each other. As illustrated in FIGS. 16A, 16B, and 16C, where a Z direction is the attachment direction of the accessory **200** to the camera **100**, an X direction is a direction in which the plurality of contacts TC01 to TC21 and TA01 to TA21 are aligned, and a Y direction is a direction orthogonal to the X direction and the Z direction, only some of the contacts may be connected in the following cases.

[0128] First, as illustrated in FIGS. 3A and 3B, when the accessory **200** is tilted to the camera **100** around an axis parallel to the Z direction, some of the plurality of contacts may be connected with each other on one side where the camera **100** and the accessory **200** are close to each other but some of the plurality of contacts are disconnected from each other on the other side where the camera **100** and the accessory **200** are separated from each other. Although not illustrated, when the accessory **200** is tilted (twisted) to the camera **100** around an axis parallel to the Y direction, some contacts on an opposite side of the plurality of contacts that are connected with each other are separated from each other.

[0129] As detailed later with reference to FIGS. 5A and 5B, in the camera **100** and the accessory

200 according to this embodiment, the attachment detection processing is executed prior to various communications while the accessory **200** is attached to the camera **100**. At this time, if the attachment detection contacts **TC06** and **TA06** are connected, the attachment detection processing can be executed. After the attachment detection processing via the contacts **TC06** and **TA06** is executed, the communication request signal/WAKE is output from the accessory **200** to the camera **100** via the contacts (also referred to as communication request contacts hereinafter) **TC11** and **TA11**. By detecting this communication request signal/WAKE, the camera **100** performs various communications, determining that the accessory **200** is in a communicable state. However, in the case where the camera **100** cannot detect the communication request signal/WAKE even though the attachment of the accessory **200** to the camera **100** is detected, the camera **100** determines that there is a communication error with the accessory **200**. If the accessory **200** is tilted or twisted while the accessory **200** is being attached to the camera **100**, only some of the contacts are temporarily connected, it is determined that there is a communication error, and error processing, such as an alarm, is performed, the user may misunderstand that the accessory **200** breaks down. [0130] Therefore, this embodiment adopts the contact arrangement so as to reduce the occurrence of a situation in which the camera **100** cannot detect the communication request signal/WAKE even though the attachment of the accessory **200** to the camera **100** is detected.

[0131] As described above, when the accessory **200** is tilted to the camera **100** around an axis parallel to the Z direction, the contacts **TC01** and **TA01** and the neighboring contacts are connected as illustrated in FIG. 3A, and the contacts **TC21** and **TA21** and the neighboring contacts are disconnected, or the contacts **TC21** and **TA21** and the neighboring contacts are connected and the contacts **TC01** and **TA01** and the neighboring contacts are disconnected as illustrated in FIG. 3B.

[0132] This embodiment uses the contacts **TC06** and **TA06** to detect the attachment of the accessory **200** to the camera **100**. As illustrated in FIG. 3A, when the contacts **TC01** and **TA01** are connected with each other, the neighboring contacts **TC06** and **TA06** are often connected with each other. At this time, if the communication request contacts **TC11** and **TA11** are located near the distant contacts **TC21** and **TA21**, the camera **100** is unlikely to detect the communication request signal/WAKE even though the attachment of the accessory **200** to the camera **100** is detected.

[0133] On the other hand, as illustrated in FIG. 3B, the contacts **TC06** and **TA06** may be connected with each other while the contacts **TC21** and **TA21** are connected with each other. In this case, if the contacts **TC11** and **TA11** are arranged on a side of the contacts **TC01** and **TA01** distant from the contacts **TC06** and **TA06**, the camera **100** is unlikely to detect the communication request signal/WAKE even though the attachment of the accessory **200** to the camera **100** is detected.

[0134] On the other hand, this embodiment adopts the following contact arrangement. As illustrated in FIG. 1, the attachment detection contacts **TC06** and **TA06** and the communication request contacts **TC11** and **TA11** are disposed between the contacts **TC01** and **TA01** closest to one end and the contacts **TC21** and **TA21** closest to the other end in the direction in which a plurality of contacts **TC01** to **TC21** and **TA01** to **TA21** are arranged (referred to as a contact arrangement direction hereinafter). This arrangement relationship will be referred to as a first arrangement relationship. The attachment detection contacts **TC06** and **TA06** are disposed between the communication request contacts **TC11** and **TA11** and the contacts **TC01** and **TA01**. This arrangement relationship will be referred to as a second arrangement relationship. Then, in the contact arrangement direction, distances between the attachment detection contacts **TC06** and **TA06** and the communication request contacts **TC11** and **TA11** are made shorter than distances between the communication request contacts **TC11** and **TA11** and the contacts **TC21** and **TA21**. This arrangement relationship will be referred to as a third arrangement relationship. In this embodiment, the contacts **TC01** to **TC21** and **TA01** to **TA21** are arranged at regular pitches, so that the distance between the contacts herein can be rephrased as the number of other contacts arranged between these contacts, and a short (or long) distance can be rephrased as a small (or large) number of other contacts.

[0135] In this embodiment, the distances between the communication request contacts **TC11** and **TA11** and the contacts **TC01** and **TA01** are set to be equal to or less than the distance between the communication request contacts **TC11** and **TA11** and the contacts **TC21** and **TA21** in the contact arrangement direction. This arrangement relationship will be referred to as a fourth arrangement relationship. In particular, this embodiment disposes the communication request contacts **TC11** and **TA11** at the centers between the contacts **TC01** to **TC21** and **TC01** to **TC21**, and makes equal to each other the distances between the communication request contacts **TC11** and **TA11** and the contacts **TC01** and **TA01**, and the distances between the communication request contacts **TC11** and **TA11** and the contacts **TC21** and **TA21**. The communication request contacts **TC11** and **TA11** do not necessarily have to be disposed at the centers between the contacts **TC01** to **TC21** and **TC01** to **TC21**, but they are preferably disposed near the centers.

[0136] This embodiment makes the distances between the attachment detection contacts **TC06** and **TA06** and the contacts **TC01** and **TA01** equal to or greater than the distances between the attachment detection contacts **TC06** and **TA06** and the communication request contacts **TC11** and **TA11** in the contact arrangement direction. This arrangement relationship will be referred to as a fifth arrangement relationship. In particular, this embodiment disposes the attachment detection contacts **TC06** and **TA06** at the centers between the communication request contacts **TC11** and **TA11** and the contacts **TC01** and **TA01**, and makes the distances between the attachment detection contacts **TC06** and **TA06** and the contacts **TC01** and **TA01** and the distances between the attachment detection contacts **TC06** and **TA06** and the communication request contacts **TC11** and **TA11** equal to each other. The attachment detection contacts **TC06** and **TA06** do not necessarily have to be disposed at the centers between the communication request contacts **TC11** and **TA11** and the contacts **TC01** and **TA01**, but it is preferable to dispose them near the centers.

[0137] With the above contact arrangement, the communication request contacts **TC11** and **TA11** are highly likely to be connected with each other if the attachment detection contacts **TC06** and **TA06** are connected with each other in the tilted state illustrated in FIG. 3A, and in the tilted state illustrated in FIG. 3B, even if the communication request contacts **TC11** and **TA11** are connected with each other, the attachment detection contacts **TC06** and **TA06** are highly likely to be disconnected with each other. As a result, whichever state the accessory **200** is tilted in, the occurrence of a situation in which the camera **100** cannot detect the communication request signal/WAKE can be reduced even though the attachment of the accessory **200** to the camera **100** is detected.

[0138] A description will now be given as a comparative example of a case where the positions of the contacts **TC06** and **TA06** and the contacts **TC11** and **TA11** are exchanged. That is, a description will be given of a case where the contacts **TC11** and **TA11** are used to detect the attachment and the contacts **TC06** and **TA06** are used to detect the communication request signal/WAKE. In this configuration, when the accessory **200** is tilted to the camera **100** and the contacts **TC01** and **TA01** and the neighboring contacts are disconnected from each other, the contacts **TC11** and **TA11** for the attachment detection may be connected with each other but the contacts **TC06** and **TA06** for the communication request signal/WAKE may be disconnected from each other, resulting in a communication error.

[0139] Therefore, in order to avoid the communication error, it is preferable to dispose the attachment detection contact on one end side in the contact arrangement direction rather than the contacts for the communication request signal/WAKE as in this embodiment.

[0140] As illustrated in FIGS. 20A to 20C and 23 A and 23B, which will be described later, in a configuration where the accessory **200** holds a plurality of contacts with a connection plug **256** as a holding member made of a nonconductive material such as a resin material, the connection plug **256** may have a convex shape toward the lower side (contact direction with the camera connector **141**) in the drawing. In such a case, the contact on one end side in the contact arrangement direction of the plurality of contacts is likely to be connected but the contact on the other end side

is likely to be disconnected. However, the contact arrangement illustrated in this embodiment can reduce an occurrence of a communication error even if some of the contacts are disconnected when the accessory **200** is attached to the camera **100**.

[0141] As described above, when the accessory **200** is twisted relative to the camera **100** around the axis parallel to the Y direction, some contacts on one end side in the contact arrangement direction of the plurality of contacts may be connected, but the other contacts on the other end side may be disconnected. When such a state occurs in the process of attaching the accessory **200** to the camera **100**, the connection timings shift among the plurality of contacts. If the contact timing significantly shifts, a time lag from the attachment detection of the accessory **200** to the camera **100** to the detection of WAKE becomes long, and consequently a communication error may be determined. At this time, depending on the twisting direction of the accessory **200**, the side of the contacts TC**01** and TA**01** or the side of the contacts TC**21** and TA**21** starts to be connected first.

[0142] In the case where the side of the contacts TC**01** and TA**01** starts to be connected, the closer the communication request contacts TC**11** and TA**11** are to the contacts TC**21** and TA**21**, the longer the time lag becomes from the attachment detection of the accessory **200** to the detection of the communication request signal/WAKE. The longer the time lag is, the more easily a communication error is determined. On the other hand, in the case where the side of the contacts TC**21** and TA**21** starts to be connected and the communication request contacts TC**11** and TA**11** are disposed on the side of the contacts TC**01** and TA**01** of the attachment detection contacts TC**06** and TA**06**, a time lag occurs from the attachment detection of the accessory **200** to the detection of the communication request signal/WAKE.

[0143] On the other hand, this embodiment adopts the above contact arrangement, and shortens a time lag from the attachment detection of the accessory **200** to the detection of the communication request signal/WAKE, regardless of which side of the contacts starts to be connected.

[0144] This embodiment disposes at positions between the attachment detection contacts TC**06** and TA**06** and the communication request contacts TC**11** and TA**11** the contacts TC**07** and TA**07** to TC**10** and TA**10** for the SPI communication (communication in the second communication method) between the camera **100** and the accessory **200**. The contacts TC**12**, TA**12**, TC**13**, and TA**13** used for the I2C communication (communication in the first communication method) between the camera **100** and the accessory **200** are disposed at positions close to the communication request contacts TC**11** and TA**11** on the opposite side of the attachment detection contacts TC**06** and TA**06**.

[0145] The communication between the camera **100** and the accessory **200** is executed after the camera **100** detects the communication request signal/WAKE. Therefore, until the communication between the camera **100** and the accessory **200** is executed, the connection of the contacts for the communication is not confirmed. On the other hand, in this embodiment, if the attachment detection contacts TC**06** and TA**06** and the communication request contacts TC**11** and TA**11** are connected with each other, the communication contacts TC**07**, TA**07** to TC**10**, TA**10**, TC**12**, TA**12**, TC**13**, and TA**13** arranged near and between them, respectively, can be considered to be connected.

[0146] Since it can be considered that the positions between the attachment detection contacts TC**06** and TA**06** and the communication request contacts TC**11** and TA**11** are more reliably connected, the contacts used for the SPI communication executed after the I2C communication are preferably disposed at positions between the attachment detection contacts TC**06** and TA**06** and the communication request contacts TC**11** and TA**11**.

[0147] As illustrated in FIGS. 4A, 4B, and FIGS. 12 and 20 which will be used later for the explanation, a configuration in which the number of contacts is smaller than that of the camera **100** is conceivable as the configuration of the accessory **200**. Even in this configuration, the attachment detection contact and the communication request contact are necessary contacts, and the attachment detection contact and the communication request contact may be arranged under an idea similar to the configuration in which the number of contacts is equal to that of the camera **100**. However, a part of the above-mentioned first to fifth arrangement relationships may not be satisfied.

[0148] For example, assume a configuration having no contact TA21 as illustrated in FIGS. 4A and 4B. In this configuration, a distance between the communication request contact TA11 and the contact TA01 is longer than a distance between the communication request contact TA11 and the contact TA20 in the contact arrangement direction. That is, the fourth arrangement relationship is not satisfied. In addition, for example, assume a configuration having no contacts TA01 to TA03 and TA19 to 21 as illustrated in FIG. 12. In this configuration, a distance between the attachment detection contact TA06 and the contact TA04 in the contact arrangement direction is shorter than a distance between the attachment detection contact TA06 and the communication request contact TA11. That is, the fifth arrangement relationship is not satisfied.

[0149] As described above, in a configuration in which the position of the contact position at the end of the accessory 200 is different from the contact position at the end of the camera 100, part of the first to fifth arrangement relationships may not be satisfied. In such a case, it is assumed that the position facing the contact at the end of the camera 100 in the attached state is the position of the contact at the end of the accessory 200, and the attachment detection contact and the communication request contact may be arranged so as to satisfy the first to fifth arrangement relationships. Alternatively, as in the protrusion portion 256a illustrated in FIGS. 20A, 20B, and 20C, the attachment detection contact and the communication request contact may be arranged so as to satisfy the first to fifth arrangement relationships in consideration of the distance from the protrusion portion 256a instead of the distance from the contact at the end. A flowchart of FIG. 5A illustrates processing executed by the camera control circuit 101 when the accessory 200 is attached to the camera 100.

[0150] In S401, the camera control circuit 101 as an attachment detection means monitors the signal level of the accessory attachment detection signal/ACC_DET and determines whether or not the accessory 200 is attached. If the signal level is Hi, the camera control circuit 101 returns to S401 and performs the detection again, assuming that the accessory 200 is not attached, and if the signal level is Lo, proceeds to S402 assuming that the accessory 200 is attached.

[0151] In S402, the camera control circuit 101 sets a power supply control signal CNT_VACC1 to the Hi level in order to turn on the output of the accessory-use power supply circuit A131, and proceeds to S403. The accessory-use power supply circuit A131 outputs the accessory power supply VACC in response to the power supply control signal CNT_VACC1 becoming Hi.

[0152] In S403, the camera control circuit 101 monitors the signal level of the overcurrent detection signal DET_OVC and determines whether or not the overcurrent is flowing. If the signal level is Lo, the camera control circuit 101 proceeds to S404 assuming that no overcurrent flows, and if the signal level is Hi, proceeds to S405 assuming that the overcurrent flows to perform error processing.

[0153] FIG. 6A schematically illustrates a change in the signal in the case where the flow proceeds to S404 in the processing of FIG. 5A. IACC is the current of the accessory power supply VACC. Since the accessory power supply VACC normally leads up after the power supply control signal CNT_VACC1 is set to Hi in S402, the overcurrent detection signal DET_OVC remains at a Lo level.

[0154] FIG. 6B schematically illustrates a change in the above signal in the case where the flow proceeds to S405 in the processing of FIG. 5A. Since the overcurrent flows through IACC after the power supply control signal CNT_VACC1 is set to Hi in S402, the overcurrent detection signal DET_OVC changes to the Hi level and notifies the camera control circuit 101. Upon receiving the notification of the overcurrent detection signal DET_OVC, the camera control circuit 101 turns off the outputs of the accessory-use power supply circuits A131 and B132 as error processing to stop the power supply to the accessory 200. Thus, even in the case where the overcurrent flows through the accessory power supply VACC, the camera control circuit 101 can detect the overcurrent and safely stop the system.

[0155] Usually, in a case where an abnormal current flows through the accessory power supply

VACC, it is presumed that the camera **100** and the accessory **200** are out of order, but since the camera connector **141** and the accessory connector **211** are exposed to the outside, and thus the neighboring contacts may be short-circuited due to an adhesion of a foreign matter such as a metal piece.

[0156] In this embodiment, the accessory power supply VACC has a voltage of 3.3 V, whereas the camera microcomputer power supply VMCU_C and the accessory microcomputer power supply VMCU_A have a voltage of 1.8 V. Thus, if a voltage of 3.3 V is applied to an electric element operating at a voltage of 1.8 V, the electric element may get damaged. Since the post-short-circuiting behavior depends on the characteristic of the electric element, the camera control circuit **101** may not always be able to detect the short-circuiting between the terminals. For example, since the I2C communication signal is at the Hi level in the communication standby state, even if it is short-circuited with the voltage of 3.3 V equal to and higher than the voltage of 1.8V, the abnormality cannot be detected depending on the characteristic of the electric element of the connection destination.

[0157] On the other hand, this embodiment disposes the GND contacts TC**04** and TA**04** on one of the two sides of the accessory power supply VACC contacts TC**05** and TA**05**, and the contacts TC**06** and TA**06** of the accessory attachment detection signal/ACC_DET on the other side. As described above, the accessory attachment detection signal/ACC_DET is connected to GND in the accessory **200**. Thus, even in the case where short-circuiting occurs between the contacts, the overcurrent can be detected and the system can be safely stopped without applying 3.3 V to the element operating at 1.8 V.

[0158] As described above, if the accessory power supply VACC is supplied when the GND contact is not connected, the reference potential of the accessory **200** becomes unstable, and consequently each circuit and the electric element may get damaged. In operating the device, an external force may be applied that makes unstable the connection of the connector terminals. On the other hand, by arranging the accessory power supply VACC contact and the GND contact adjacent to each other as in this embodiment, the connection of only the accessory power supply VACC contact can be more effectively prevented than a case where the accessory power supply VACC contact and the GND contact are separate terminals.

[0159] This embodiment connects the accessory attachment detection signal/ACC_DET to GND in the accessory **200**, but may connect it to GND via a resistor element Rd**231** as in the accessory **200** illustrated in FIG. **9**. The short-circuiting current can be reduced by the connection to GND via the resistor element Rd**231**.

[0160] In this case, it is necessary to select the resistor element Rd**231** having such a resistance value that a voltage of $(R_d/(R_p+R_d)) \times 1.8 \text{ V}$ obtained by dividing the voltage of 1.8 V of the camera microcomputer power supply VMCU_C by the resistor elements Rp**134** and Rd**231** satisfies the Lo level threshold (Vi**1**) of the camera control circuit **101**. For example, in the case where a Low level detection threshold value (Vi**1**) of the camera control circuit **101** is 0.33 times the power supply voltage, the resistance value of the resistor element Rd**231** needs to be half or less of the resistor element Rp**134** (10 kΩ). In the example of FIG. **9**, the resistance value of the resistor element Rd**231** is set to 5 kΩ.

[0161] FIG. **5B** illustrates processing executed by the camera control circuit **101** when the accessory **200** having the configuration illustrated in FIG. **9** is attached to the camera **100**. Since S**411** to S**413** are the same as S**401** to S**403** illustrated in FIG. **5A**, a description thereof will be omitted.

[0162] In S**414** after S**413**, the camera control circuit **101** monitors the signal level of the accessory attachment detection signal/ACC_DET, and determines whether or not the accessory attachment detection signal/ACC_DET contacts TC**06** and TA**06** are short-circuited with the accessory power supply VACC contacts TC**05** and TA**05**. If the signal level is Lo, the camera control circuit **101** proceeds to S**415** assuming that it is not short-circuited, and if the signal level is Hi, proceeds to

S416 assuming that it is short-circuited to performs the error processing.

[0163] FIG. **6C** schematically illustrates the state of the above signal in the case where the accessory power supply VACC and the accessory attachment detection signal/ACC_DET are short-circuited in the accessory **200** having the configuration of FIG. **9** to which the resistor element Rd**231** (5 k Ω) is added. After the power supply control signal CNT_VACC**1** is set to Hi in **S402**, no overcurrent flows in IACC because the current is limited by the resistor element Rd**231**.

[0164] On the other hand, the voltage of the accessory power supply VACC is applied to the accessory attachment detection signal/ACC_DET. As soon as the signal level of the accessory attachment detection signal/ACC_DET becomes Hi due to interrupt processing or the like, the camera control circuit **101** sets the power control signal CNT_VACC**1** to Lo in the error processing and stops outputting the accessory power supply VACC (power supply to the accessory **200**). Thereby, the system can be safely stopped without continuously applying 3.3 V to the terminal of the element operating at 1.8 V.

[0165] As illustrated in FIG. **10**, the accessory **200** may be controlled so that the accessory attachment detection signal/ACC_DET becomes a Lo level (GND potential) by the accessory control circuit **201** via an NPN transistor **212** as a switching means. If the accessory **200** is attached to the camera **100** in the configuration illustrated in FIG. **1**, the camera control circuit **101** can always detect the accessory **200**, but in the configuration illustrated in FIG. **10**, the accessory control circuit **201** can notify the attachment of the accessory **200** to the camera **100** at an arbitrary timing.

[0166] As illustrated in FIG. **11**, the accessory **200** may be configured so as to connect the resistor element Rd**231** in series with the NPN transistor **212**. In this case, the resistance value needs to be half or less of the resistor element Rp**134** (10 k Ω) as in the configuration of FIG. **1**.

[0167] As described above, even if the power supply contact and the adjacent contact are short-circuited, this embodiment can maintain the safety of the system including the camera **100** and the accessory **200**, and restrain them from getting damaged.

[0168] FIG. **7** illustrates an example of the functions of the FNC**1** signal to the FNC**4** signal as the functional signals connected to the contacts TC**14** to TC**17** and the contacts TA**14** to TA**17** for each type of the accessory **200** (here, the microphone device and the strobe device).

[0169] In the microphone device, the FNC**2** signal to the FNC**4** signal are used as a digital audio (I2S: Inter-IC Sound standard) data bus to transfer audio data. FIG. **8A** illustrates a configuration example of the functional circuit **206** in the case where the accessory **200** is a microphone device.

[0170] An audio processing circuit **206A1** in the functional circuit **206** is a codec circuit that converts an audio signal input from a microphone **206A2** into a digital audio (I2S) data format, and is controlled by the accessory control circuit **201**. The accessory control circuit **201** can set the sampling frequency and the resolution by controlling the audio processing circuit **206A1**. In this embodiment, the sampling frequency is 48 KHz and the resolution is 32 bits. The microphone **206A2** is, for example, a MEMS-IC microphone or an electret condenser microphone.

[0171] TA**14** is the FNC**1** signal that is not used as an I2S data bus and is connected to GND. In this embodiment, the unused functional signal is connected to GND, but the present invention is not limited to this embodiment, and a connection to a reference potential may be made as the stable potential other than the GND potential (0V) such as the power supply potential and the L level (low potential) or H level (high potential) of the signal.

[0172] The FNC**2** signal connected to TA**15** (DATA contact) is an audio data signal (DATA), which is a signal output from the accessory **200** to the camera **100**.

[0173] The FNC**3** signal connected to TA**16** (LRCLK contact) is an audio channel clock signal (LRCLK), which is a signal output from the accessory **200** to the camera **100**.

[0174] The FNC**4** signal connected to TA**17** (BCLK contact) is an audio bit clock signal (BCLK), which is a signal output from the camera **100** to the accessory **200**.

[0175] In this embodiment, since the sampling frequency is 48 KHz and the resolution is 32 bits as

described above, the LRCLK frequency is 48 kHz and the BCLK frequency is 3.072 MHz. DATA has a maximum frequency of 1.536 MHz, which is half a cycle of CLK.

[0176] In the contact arrangement according to this embodiment, the reference potential contacts TA18 and TC18 connected to the GND potential as the reference potential are disposed next to the contacts TA17 and TC17 to which the FNC4 signal (BCLK) having the highest frequency is connected among the functional signal contacts to which the functional signals are connected. The signal wiring to the accessory shoe interface is generally configured with a flexible substrate. In order to reduce the product cost, the flexible substrate may have a single-sided specification, and the substrate wiring is made in the same arrangement as the contact arrangement. This embodiment disposes the GND contact as the reference potential contact next to the functional signal contact connected to the signal having the highest frequency among the functional signals. This configuration can suppress radiation noises (EMI) from the functional signal contact, interference with signals connected to other contacts, and crosstalk with signals other than the I2S data bus.

[0177] This embodiment connects to the GND potential as the reference potential the contacts TA18 and TC18 next to the contacts TA17 and TC17 connected to the FNC4 signal (BCLK) having the highest frequency, but the present invention is not limited to this example and the same effect can be obtained even if the connection is made to a stable reference potential other than the GND potential.

[0178] FIG. 8B is an example illustrating a configuration in which audio data is increased relative to FIG. 8A. The purpose of increasing the audio data is to increase the number of channels and the resolution.

[0179] The FNC4 signal connected to TA17 is an audio bit clock signal (BCLK), which is the same as that illustrated in FIG. 8A.

[0180] On the other hand, the FNC3 signal connected to TA14 is an audio channel clock signal (LRCLK), which is a signal output from the accessory 200 to the camera 100.

[0181] The FNC2 signal connected to TA15 is an audio data signal (DATA2), which is a signal output from the accessory 200 to the camera 100.

[0182] The FNC1 signal connected to TA16 operates as an audio data signal (DATA2), which is a signal output from the accessory 200 to the camera 100.

[0183] In this way, in the case where an audio data signal is added to increase the audio data amount and two signals are used, arranging signals in such order that a higher frequency is disposed closer to the GND terminal can provide a configuration that is relatively highly effective in preventing crosstalk.

[0184] FIG. 8C illustrates a configuration example of the functional circuit 206 in the case where the accessory 200 is a strobe device. A light emitting circuit 206B1 in the functional circuit 206 is a strobe light emitting circuit including an IGBT, a trigger coil, and the like, and controls a light emission of the light emitter 206B2. The light emitter 206B2 includes a xenon tube or the like and emits illumination light to illuminate the object. A charging circuit 206B3 includes a transformer, a switching FET, a capacitor, and the like, and accumulates electric charges for causing the light emitter 206B2 to emit light.

[0185] The FNC1 signal connected to TA14 is a light emission synchronization signal (STARTX) for controlling the light emission timing of the light emitter 206B2, and is a signal output from the camera 100 to the accessory 200. The FNC2 signal to the FNC4 signal are not used in the strobe device, and no signal is connected to these contacts.

[0186] This embodiment makes unused functional signal contacts disconnected (OPEN), but the present invention is not limited to this embodiment, and a connection to a stable reference potential, such as the power supply potential and the L or H level of the signal, may be made according to the contacts TC15 to TC17 as connection destinations of the contacts TA15 to TA17.

[0187] In the strobe device, only the FNC1 signal is used among the functional signals. Although the light emission synchronization signal (STARTX) is not a periodically generated signal, the

camera **100** allocates GND to the FNC1 signal when the microphone device is connected so as to prevent the configuration of the camera control circuit **101** from being complicated.

[0188] A description will now be given of further features of the contact arrangement according to this embodiment. SDA (first signal) connected to the contacts TC12 and TA12 as the first signal contacts and SCL (second signal) connected to the contacts TC13 and TA13 as the second signal contacts are both signals for the I2C communication. These signals are transmitted by the open drain communication. Since both SDA and SCL are pulled up to the camera microcomputer power supply VMCU_C, they are the signal having a relatively high impedance during the communication standby, and easily subject to crosstalk.

[0189] Therefore, this embodiment assigns the communication request signal (fourth signal)/WAKE to the contacts TC11 and TA11 as the fourth signal contacts next to the SDA contacts TC12 and TA12. As described above, the communication request signal/WAKE is a signal for making a communication request from the accessory **200** to the camera **100**.

[0190] FIG. 15A illustrates the timing at which the accessory **200** makes a communication request to the camera **100** and performs the I2C communication. As illustrated in FIG. 15A, the signal level of the communication request signal/WAKE changes from the Hi level to the Lo level prior to the I2C communication by SCL and SDA. This is because the I2C communication is performed in response to this change. Accordingly, disposing the contacts TC11 and TA11 of the communication request signal/WAKE at and near the SDA contact for the I2C communication can keep SDA of the communication request signal/WAKE from crosstalk.

[0191] As illustrated in FIG. 15A, a control to change the signal level of the communication request signal/WAKE from the Lo level to the Hi level after the I2C communication can keep SDA of the communication request signal/WAKE from crosstalk.

[0192] The FNC1 signal is assigned to the contacts TC14 and TA14 as the third signal contacts next to the SCL contacts TC13 and TA13. As described above, since GND is assigned to the FNC1 signal in the microphone device, SCL can be kept from crosstalk.

[0193] In the strobe device, the light emission synchronization signal (STARTX: third signal) as the FNC1 signal is assigned to the contacts TC14 and TA14 next to the SCL contacts TC13 and TA13. FIG. 15B illustrates the timing at which the accessory **200** makes a communication request to the camera **100**, and performs the I2C communication and the strobe light emission. As illustrated in FIG. 15B, at the timing (period) when the light emission synchronization signal is output, no I2C communication is performed between the camera **100** and the accessory **200** in order to process the control of the strobe light emission with the highest priority. In other words, the light emission synchronization signal is a signal whose signal level changes before (or after) the I2C communication, but does not change during the I2C communication. This configuration can keep SCL of the light emission synchronization signal from crosstalk.

[0194] Thus, this embodiment disposes the STARTX contact on one of both sides of the SDA contact and the SCL contact, and disposes the/WAKE contact on the other side, thereby achieving a good I2C communication.

[0195] This embodiment sets to an open drain signal, similar to SDA, the communication request signal/WAKE connected to the contacts TC11 and TA11 next to the SDA contacts TC12 and TA12. In comparison with a push-pull type communication request signal/WAKE is a push-pull system, crosstalk to SDA can be suppressed when the signal level of the communication request signal/WAKE changes.

[0196] SCLK connected to the SCLK contacts TC07 and TA07 is a clock signal for the SPI communication, and operates at a driving frequency of 1 MHz in this embodiment. In this embodiment, the attachment detection contacts TC06 and TA06 next to the SCLK contacts TC07 and TA07 are used to transmit the accessory attachment detection signal/ACC_DET. As described above, the accessory attachment detection signal/ACC_DET is a signal that has a potential equivalent to GND when the accessory **200** is attached to the camera **100**. Therefore, this contact

arrangement can prevent crosstalk between SCLK and a signal other than the SPI bus.

[0197] MOSI connected to the other contacts TC**08** and TA**08** next to the SCLK contacts TC**07** and TA**07** is a data signal transmitted from the camera control circuit **101** to the accessory control circuit **201** by the SPI communication. Generally, the timing at which the MOSI output level in the SPI communication changes is synchronized with the timing at which the SCLK output level changes. Therefore, crosstalk can be suppressed between SCLK and MOSI by disposing the MOSI contacts TC**08** and TA**08** next to the SCLK contacts TC**07** and TA**07**.

[0198] MISO connected to the other contacts TC**09** and TA**09** next to the MOSI contacts TC**08** and TA**08** is a data signal transmitted from the accessory control circuit **201** to the camera control circuit **101** in the SPI communication. Generally, the timing at which the MISO output level changes in the SPI communication is synchronized with the timing at which the SCLK output level changes, similar to MOSI. Therefore, by disposing the MISO contacts TC**09** and TA**09** next to the MOSI contacts TC**08** and TA**08**, crosstalk between the MOSI and the MISO can be suppressed.

[0199] CS connected to the other contacts TC**10** and TA**10** next to the MISO contacts TC**09** and TA**09** is a communication request signal transmitted from the camera control circuit **101** to the accessory control circuit **201** in the SPI communication. Generally, CS in the SPI communication maintains a constant output level from a communication request to a communication completion. Therefore, by disposing the CS contacts TC**10** and TA**10** next to the MISO contacts TC**09** and TA**09**, crosstalk to MISO can be suppressed.

[0200] The communication request signal/WAKE connected to the contacts TC**11** and TA**11** adjacent to the CS contacts TC**10** and TA**10** is a signal for making a communication request from the accessory control circuit **201** to the camera control circuit **101**. As described above, the communication request signal/WAKE is an open drain signal, and thus is relatively susceptible to crosstalk. Therefore, this embodiment disposes the contacts TC**10** and TA**10** for CS whose signal level changes relatively infrequently, next to the contacts TC**11** and TA**11** for the communication request signal/WAKE, and can suppress crosstalk to the communication request signal/WAKE.

[0201] A differential signal that requires an impedance control is connected to the contacts TC**01** to TC**03** and TA**01** to TA**03** and the contacts TC**19** to TC**21** and TA**19** to TA**21** located at and near both ends of the camera connector **141** and the accessory connector **211** (these will be collectively referred to as both end sides hereinafter). The signal wiring to the accessory shoe interface is generally configured with a flexible substrate. In order to achieve the desired wiring impedance on the flexible board, it is necessary to keep a distance between the lines of the differential signal and with GND to be wired in parallel. In a board in which both sides are used, it is common to form a mesh GND wiring on the backside of the differential signal. Thus, the signal wiring that requires the impedance control has relatively large restrictions on the wiring design in comparison with a general single-ended signal.

[0202] On the other hand, this embodiment connects the differential signal that requires an impedance control to the contacts located on both ends of the camera connector **141** and the accessory connector **211**, thereby relatively reducing a relationship with other signals and improving the degree of freedom in wiring design.

[0203] The differential signal can be transferred at a high speed of about several hundred Mbps to several Gbps such as USB and PCIe, and is suitable to transfer a large data amount between devices. On the other hand, no differential signal may be used depending on the type of the accessory **200**. The accessory that uses no differential signal needs no contacts assigned to the differential signal, so the accessory cost can be reduced by deleting the contact.

[0204] FIG. **12** illustrates a configuration variation of the accessory **200** illustrated in FIG. **1**. More specifically, it has such a configuration that the contacts TA**01** to TA**03** and TA**19** to TA**21** and signals and circuits connected to them are omitted. That is, the accessory **200** in FIG. **12** has **15** contacts. In the configuration in FIG. **12**, a differential signal is assigned to the contacts TC**01** to TC**03** and TC**19** to TC**21** located at both ends of the camera connector **141**. On the other hand, the

accessory **200** that needs no differential signal adopts a contact arrangement that eliminates a contact for the differential signal from the accessory connector **211**, and includes only the contact necessary for the accessory **200**.

[0205] The accessory **200** in FIG. **12** sets to the GND contacts the contacts TC**04** and TA**04** and the contacts TC**18** and TA**18** near both ends of the camera connector **141** and the accessory connector **211**. With such a contact arrangement, even in the accessory **200** connected to a part of the contacts of the camera connector **141**, the contacts at both ends of the accessory connector **211** can be set to the GND contacts. This configuration can prevent the GND contacts from being disconnected even in the case where an excessive static pressure or impact is applied to the accessory **200**.

[0206] A direct attachment of the accessory **200** to the camera **100** has been described. Referring now to FIG. **13**, a description will be given of an intermediate accessory **300** attached between the camera **100** and the accessory **200**. The camera **100** and the accessory **200** have the above-described configurations. The intermediate accessory **300** includes an extension cable for extending a distance between the camera **100** and the accessory **200**, an adapter used to simultaneously attach a plurality of accessories to the camera **100**, and the like. This embodiment will describe the intermediate accessory **300** as an extension cable. In the configuration in FIG. **13**, the intermediate accessory **300** corresponds to an accessory, and the accessory **200** corresponds to another accessory.

[0207] The intermediate accessory **300** has a camera shoe and an accessory shoe that are attachable to the camera **100** and the accessory **200**, respectively, and each is provided with a camera-side intermediate connector **311** and an accessory-side intermediate connector **312**. The camera-side intermediate connector **311** has **21** contacts TM**01** to TM**21** arranged in a row, and is a connector for making an electrical connection with the camera **100**. The contacts TM**01** to TM**21** each make a one-to-one contact with the contacts TC**01** to TC**21** in the camera connector **141**.

[0208] On the other hand, the accessory-side intermediate connector **312** has **21** contacts TN**01** to TN**21** arranged in a row, and is a connector for making an electrical connection with the accessory **200**. The contacts TN**01** to TN**21** each make a one-to-one contact with the contacts TA**01** to TA**21** in the accessory connector **211**.

[0209] The intermediate accessory **300** having this contact arrangement can provide the power supply and the communication in the same manner as those when the accessory **200** is directly attached to the camera **100**. At this time, the intermediate accessory **300** may receive the power supply from the camera **100**, or the power supply from the camera **100** may be directly transmitted to the accessory **200**. The power supply in this embodiment includes a case where the power supply from the camera **100** is transmitted to the accessory **200** as it is and no power is supplied to the accessory **300**. In FIG. **13**, the number of contacts of the camera-side intermediate connector **311** is the same as the number of contacts of the camera connector **141**, and the number of contacts of the accessory-side intermediate connector **312** is the same as the number of contacts of the accessory connector **211**, but they may not necessarily be equal to each other.

[0210] FIG. **14** illustrates a variation of the configuration of FIG. **13** about the accessory **200** and the intermediate accessory **300**. Although differential signals are connected to the contacts TC**01** to TC**03** and TC**19** to TC**21** on both ends of the camera connector **141**, the differential signal may not be required depending on the function of the accessory **200**. The configuration of FIG. **14** eliminates the contact to which the differential signal is connected, from the camera-side intermediate connector **311** and the accessory-side intermediate connector **312** and the accessory connector **211**. That is, the intermediate accessory **300** and the accessory **200** in FIG. **14** each have **15** contacts. Thereby, a contact arrangement including only the contacts required for the intermediate accessory **300** and the accessory **200** is adopted.

[0211] A detailed description will now be given of the connection configuration between the camera **100** and the external flash unit **120**, which is an example of the accessory **200**.

[0212] FIG. **16A** illustrates the camera **100** viewed from the diagonally rear side. FIG. **16B**

illustrates how to attach the external flash unit **120** to the accessory shoe **1123** of the camera **100**. FIG. **16C** illustrates the external flash unit **120** attached to the camera **100** viewed from the oblique rear side.

[0213] The imaging optical system is provided on the front side (field side) of the camera **100**, and the image display unit **107** is provided on the rear side of the camera **100**. A top cover **150** as an exterior member is provided on the top surface of the camera **100**, and an accessory shoe **1123** is provided to the top cover **150**. On the other hand, in the external flash unit **120**, a camera connector **1206** is provided at the bottom of the external flash unit **120**.

[0214] As illustrated in FIG. **16B**, the external flash unit **120** is slid in a direction parallel to the front side in the Z direction (attachment side in the first direction) relative to the camera **100** to engage the camera connector **1206** and the accessory shoe **1123** with each other. Thereby, the external flash unit **120** can be attached to the camera **100**. The front side in the Z direction is a direction from the rear side to the front side of the camera **100**, that is, a direction from the image display unit **107** side toward the imaging optical system side. An X direction (second direction), a Y direction (third direction), and the Z direction (front-back direction) illustrated in FIGS. **16A**, **16B**, and **16C** and subsequent figures are commonly used. The X direction is a direction orthogonal to the Z direction in the horizontal plane when the Z direction is parallel to the horizontal direction, and is the width direction of the camera **100**. The Y direction is a direction orthogonal to the Z direction and the X direction, and is the height direction of the camera **100**.

[0215] A detailed description will now be given of the accessory shoe **1123** of the camera **100**. FIG. **17A** illustrates the top cover **150** and the exploded accessory shoe **1123**. FIG. **17B** illustrates the assembled accessory shoe **1123**. The assembly direction of the accessory shoe **1123** onto the top cover **150** is the Y direction.

[0216] The accessory shoe **1123** includes the engagement member **151**, a connection terminal connector **152**, a shoe stage **153**, and an accessory shoe spring **154**. The engagement member **151** is a member for holding the external flash unit **120** through an engagement with the external flash unit **120**. The connection terminal connector **152** includes a plurality of connection terminals **152a** arranged at regular pitches in the X direction on a connector base member **152e** as a holding member made of a resin material or the like and held by the connector base member **152e**. The connection terminals **152a** correspond to the contacts TC01 to TC21 in the camera connector **141** illustrated in FIG. **1**.

[0217] In the connection terminal connector **152**, the connection terminals **152a** are arranged on the front side in the Z direction as the attachment direction of the external flash unit **120** (on the front side of the camera **100**) as illustrated in FIG. **17B**. An engagement hole portion **156** to be engaged with a lock pin **252** of the external flash unit **120** illustrated in FIG. **19A** is provided behind the connection terminal connector **152** in the Z direction (on the rear side of the digital camera **100**).

[0218] While the external flash unit **120** is attached to the accessory shoe **1123**, the connection terminals **152a** are electrically connected to the external flash unit **120**. Each of the plurality of connection terminals **152a** is electrically connected to a flexible substrate **158** disposed on the lower side of the top cover **150** in the Y direction. The flexible substrate **158** is connected to an unillustrated main substrate of the camera **100**. Thus, when the external flash unit **120** is attached to the accessory shoe **1123**, a communication is available between the external flash unit **120** and the camera **100**.

[0219] The shoe stage **153** is a housing member that encloses the engagement member **151** and the connection terminal connector **152**. An accessory shoe holding member **155** is a structural skeleton that holds the engagement member **151**. As illustrated in FIG. **17A**, the accessory shoe holding member **155**, the flexible substrate **158**, the top cover **150**, the shoe stage **153**, and the connection terminal connector **152** are fastened to the engagement member **151** by four screws **157** that are inserted into them. Thereby, these members are mutually positioned and fixed. By arranging the four screws **157** one by one in four areas equally divided in the X direction and the Z direction, the

above components can be connected in a well-balanced manner.

[0220] FIG. **18A** illustrates the structure on the top surface side of the engagement member **151**, and FIG. **18B** illustrates the structure on the bottom surface side of the engagement member **151**. FIG. **18C** illustrates the structure of the connection terminal connector **152** on the top surface side. FIG. **24** illustrates the accessory shoe **1123** viewed from the insertion direction (attachment direction) of the external flash unit **120**.

[0221] The engagement member **151** is formed by bending a metal plate in a loop shape so that the end surfaces of the bent ends face and contact each other at a seam **151a**. The engagement member **151** has a pair of engagement portions **151b**, and a coupler **151c** that couples the pair of engagement portions **151b** together. The engagement member **151** has a pair of first screw hole portions **151d** for fastening the screws **157** and a pair of second screw hole portions **151e**. The engagement member **151** has engagement hole portions **156** to be engaged with the lock pins **252** of the external flash unit **120**.

[0222] As illustrated in FIGS. **18A** and **12**, the pair of engagement portions **151b** are separated by a first width (referred to as engagement portion interval hereinafter) **151aa** in the X direction. A holding member **254** of the external flash unit **120**, which will be described later, illustrated in FIG. **19B** is inserted into the engagement portion interval **151aa**. The pair of first screw hole portions **151d** are provided at a predetermined interval in the X direction, and serve as a pair of first fastening hole portions provided apart from each other in the X direction at the back (on the rear side) in the Z direction. The pair of second screw hole portions **151e** are provided at a predetermined interval in the X direction, and serve as a pair of second fastening hole portions provided apart from each other in the X direction at the front in the Z direction. The engagement hole portion **156** is formed at a position engageable with the lock pin **252** of the external flash unit **120** in an area sandwiched between the pair of first screw hole portions **151d**.

[0223] In the connection terminal connector **152**, as illustrated in FIGS. **17B** and **18C**, a plurality of connection terminals **152a** are exposed. In the pitch direction (X direction) in which the plurality of connection terminals **152a** are aligned, the position of the camera connector **1206** is determined by the engagement portion interval **151aa** of the engagement member **151**. Therefore, the holding member **254** of the external flash unit **120** is positioned relative to the connection terminal connector **152** by the engagement member **151**.

[0224] A contact surface and a groove portion illustrated in FIG. **24** are formed on both sides of the connection terminal connector **152** (connector base member **152e**) as one example of the camera connector **141** illustrated in FIG. **1** sandwiching the plurality of connection terminals **152a** in the X direction on the front side in the Z direction. That is, there are formed contact surfaces **152b** that contact and position the accessory shoe **1123** in the Z direction when the external flash unit **120** is attached, and groove portions **152c** into which the accessory shoe **1123** is inserted. Each groove portion **152c** is formed so as to extend from the contact surface **152b** to the front side (attachment side) in the Z direction, and has a slope portion **152d** so as to face inward and diagonally upward (so as to have a tilt to the X direction). Part of the groove portion **152c** above the slope portion **152d** extends outward in the X direction from the position of the top end of the slope portion **152d**. This is to prevent a dent (sink) from being generated in the slope portion **152d** during resin molding if the slope portion **152d** is formed up to the top end of the groove portion **152c**.

[0225] As illustrated in FIG. **24**, in the X direction, an outermost inner surface **152ccc** of the groove portion **152c** in the connector base member **152e** of the accessory shoe **1123** is located outside of the inner end surfaces of the pair of engagement portions **151b** of the engagement member **151** (engagement portion interval **151aa**) and is located inside of the outermost inner surface **151bb** of the engagement member **151**.

[0226] A slope start position **152cc**, which is the end (lower end) of the slope portion **152d** on the bottom surface side of the groove portion **152c**, is provided inside the engagement portion interval **151aa**. Thereby, it is possible to secure an area for providing the contact surface **152b** that comes

into contact with a contact portion **251b** described later of the camera connector **1206** and positions it in the Z direction. Providing the slope shape starting from the slope start position **152cc** can expand a space into which the shoe apparatus (camera connector **1206** described later) of the external flash unit **120** is inserted, and can secure the degree of freedom in the shape of the shoe apparatus. As a result, the shoe apparatus of the external flash unit **120** can be sufficiently formed with a shape that protects the connection terminals.

[0227] A description will now be given of the external flash unit **120**. FIG. **19A** illustrates the external flash unit **120** viewed from the camera connector **1206** side (bottom side in the Y direction). FIG. **19B** is a section taken along a line A-A in FIG. **19A** and illustrates the internal structure of the camera connector **1206**. FIG. **20A** illustrates the camera connector **1206**. However, a base portion **250** and a lock lever **253**, which will be described later, are omitted. FIG. **20B** illustrates the camera connector **1206** viewed from the front in the Z direction.

[0228] The camera connector **1206** is provided on the bottom side in the Y direction (top side in FIG. **19A**) of the base portion **250** of the external flash unit **120** as illustrated in FIG. **19B** when it is attached to the accessory shoe **1123** of the camera **100**. The camera connector **1206** includes a shoe attachment leg (engagement member, shoe plate) **251**, the lock pins **252**, the lock lever **253**, the holding member **254**, a connection plug **256**, and a Y-direction holding member **258**.

[0229] The shoe attachment leg **251** as a shoe engagement member is an engagement member engaged with the accessory shoe **1123** of the camera **100** and held. That is, the shoe attachment leg **251** is an engagement member on the external flash unit **120** side attachable to and detachable from the engagement member **151** of the accessory shoe **1123**.

[0230] A large stress is applied to the accessory shoe **1123** and the camera connector **1206** due to the pressure for maintaining the attachment state and the external force (impact, etc.) acting on the external flash unit **120**. The shoe attachment leg **251** is manufactured by processing a metal plate (sheet metal) in order to secure a high mechanical strength against such a large stress.

[0231] The lock pin **252** is a member for preventing the external flash unit **120** from falling off while the camera connector **1206** (shoe attachment leg **251**) is attached to the accessory shoe **1123**, and is held on the shoe attachment leg **251** movable in the Y direction. More specifically, the lock pin **252** is slidably held in the Y direction by the Y-direction holding member **258**. The lock lever **253** and the Y-direction holding member **258** are held by the holding member **254**.

[0232] When the external flash unit **120** is attached to the accessory shoe **1123** and the lock lever **253** is rotated, the Y-direction holding member **258** is moved downward in the Y-direction in FIG. **19B** by an unillustrated cam portion. At that time, the lock pin **252** also moves downward in the Y direction in FIG. **19B** together with the Y-direction holding member **258**. Thereby, the lock pin **252** projects from the shoe attachment leg **251** and is engaged with the engagement hole portion **156** provided in the engagement member **151** of the accessory shoe **1123**. The lock pin **252** and the engagement hole portion **156** serve as a positioning member in the Z direction for ensuring an electrical connection between the external flash unit **120** and the camera **100**.

[0233] The connection plug **256** as one example of an accessory connector **211** illustrated in FIG. **1** is provided on the front side in the Z direction of the camera connector **1206**, made of a nonconductive material (dielectric material) such as a resin material, and integrated with the holding member **254**. An outermost width T of the connection plug **256** in the X direction is narrower than a width W of the shoe attachment leg **251** in the X direction. Thereby, an area for providing the contact portion **251b** on the shoe attachment leg **251** is secured. The connection plug **256** has a plurality of connection terminals **257** for contacting and communicating with the plurality of connection terminals **152a** of the accessory shoe **1123** illustrated in FIG. **18C**. The connection terminals **257** correspond to the contacts TA01 to TA21 of the accessory connector **211** illustrated in FIG. **1**.

[0234] The plurality of connection terminals **257** are provided so as to have a one-to-one correspondence with the plurality of connection terminals **152a**, and held by the holding member

254 so as to extend in the Z direction and to line up in the X direction. Each connection terminal **257** has a tip portion **257a** that comes into contact with the corresponding connection terminal **152a**. The tip portion **257a** is exposed to the lower side in the Y direction ($-Y$ direction) and the tip side in the Z direction ($+Z$ direction) from the connection plug **256**. Each connection terminal **257** has a shape extending backward in the Z direction from a tip portion **257a**, and has an extension portion **257b** that displaces the tip portion **257a** upward in the Y direction in FIG. **19B** by an elastic deformation when the tip portion **257a** comes into contact with the connection terminal **152a**. A vertical extension portion **257c** extending upward in the Y direction is formed at the back end of the extension portion **257b** in the Z direction. Provided at the upper end of the vertical extension portion **257c** is a flexible substrate connector **257d** to be connected to an unillustrated main substrate of the external flash unit **120** and connected to a flexible substrate **259** inserted into the holding member **254** from the top side in the Y direction.

[0235] The extension portion **257b** has a step portion **257e** having a step in the Y direction in the middle of the Z direction. As described above, the extension portion **257b** can be elastically deformed in the Y direction. However, in the case where the distance L in the Z direction of the extension portion **257b** is short, a sufficient deformation amount cannot be obtained, and the durability is lowered. As a result, the connection terminal **152a** and the tip portion **257a** are repeatedly attached and detached, and the extension portion **257b** may easily get damaged. Accordingly, providing the step portion **257e** to the extension portion **257b** can secure a sufficient distance L without causing the extension portion **257b** to interfere with the shoe attachment leg **251**.

[0236] As illustrated in FIGS. **20A** and **20B**, there are a pair of protrusion portions **256a** that project downward in the Y direction (third direction) so as to sandwich a plurality of connection terminals **257** at both ends of the connection plug **256** in the X direction. That is, a pair of protrusion portions **256a** are provided on both outer sides of the plurality of connection terminals **257**. As illustrated in FIG. **20B**, a lower tip portion **256d** of each protrusion portion **256a** protrudes below a line made by connecting the lower ends of the tip portions **257a** of the connection terminals **257** in order to protect the connection terminals **257** from external forces such as the pressure and the impact. That is, the tip portions **257a** of the connection terminals **257** is provided above (inside) a line made by connecting the lower tip portions **256d** of the pair of protrusion portions **256a**.

[0237] There is a slope portion **256b** on the outer side (outer surface) of each protrusion portion **256a** in the X direction, which serves as an outer surface that extends diagonally upward from the lower tip portion **256d** and faces diagonally downward, that is, has a tilt to the X direction. In other words, each protrusion portion **256a** is provided with the slope portion **256b** on a side not facing the plurality of connection terminals **257** so that the width of each protrusion portion **256a** in the X direction at a position close to the tip in the Y direction is smaller than that at a position distant from the tip. Since each protrusion portion **256a** has such a shape, the connection plug **256** can be inserted into the groove portion **152c** having the slope portion **152d** in the connection terminal connector **152**.

[0238] The slope portion **256b** has a role of releasing an external force, such as the pressure and impact, from the connection plug **256** to prevent the connection plug from getting damaged. For example, FIG. **20C** illustrates a case where an external force is applied to the connection plug **256** from the X direction. FIG. **20C** illustrates the connection plug **256** viewed from the front in the Z direction.

[0239] An external force from the X direction is defined as F_i as a vector. The external force $F_{\text{sub.1}}$ acting on the slope portion **256b** is decomposed according to the addition theorem in the vector space into a component force $F_{\text{sub.2}}$ in a direction along the slope portion **256b** and a component force $F_{\text{sub.3}}$ in a direction perpendicular to the slope portion **256b**. Where θ is an angle formed by the external force $F_{\text{sub.1}}$ and the slope portion **256b**, the component force $F_{\text{sub.2}}$ and the component force $F_{\text{sub.3}}$ can be calculated by the following expression (1).

$$F_{\text{sub.2}} = F_{\text{sub.1}} \cos \theta$$

$$F_{\text{sub.3}} = F_{\text{sub.1}} \sin \theta \quad (1)$$

[0240] In the case where the slope portion **256b** is provided, θ is $0^\circ < \theta < 90^\circ$. In this range, the following is established:

$$F_{\text{sub.2}} < F_{\text{sub.1}}$$

$$F_{\text{sub.3}} < F_{\text{sub.1}} \quad (2)$$

[0241] Since the component force $F_{\text{sub.2}}$ escapes in the direction along the slope portion **256b**, the component force $F_{\text{sub.3}}$ is the only force that affects the connection plug **256**. As described above, since the component force $F_{\text{sub.3}}$ is smaller than the component force $F_{\text{sub.1}}$, the connection plug **256** can be prevented from getting damaged even if an external force that is large to some extent is applied.

[0242] By forming the slope portions **256b** on both sides in the X direction so that its width in the X direction becomes narrower toward the lower side in the Y direction, not only the external force from the X direction but also the external force from the bottom side in the Y direction can be partially released.

[0243] FIG. **25** illustrates the partially enlarged connection plug **256** viewed from the Z direction. In the Y direction, assume that B is a height from the lower tip portion **256d** of the protrusion portion **256a** to the top surface of the connection plug **256** (a height of the connection plug including the protrusion portion), and A is a height of the slope portion **256b** from the lower tip portion **256d** (slope start position **256c**) to the upper end of the slope portion **256b**. At this time, A is preferably one-fifth or more of B, more preferably one-fourth or more, one-third or more, or half or more as illustrated in FIG. **13**. That is, the slope portion **256b** is formed to have a significant size for the function of releasing the external force from the X direction, and is different from a chamfered shape generally provided at the corner of the protrusion portion. The tilt angle θ of the slope portion **256b** to the X direction is preferably set in a range of $45^\circ + 20^\circ$ for the above function of releasing the external force.

[0244] In order to secure a sufficient area for the contact portion **251b** on the shoe attachment leg **251** relative to the contact surface **152b** of the accessory shoe **1123** as the positioning portion in the Z direction, the width in the X direction may be set as short as possible between slope start positions **256c** at the lower tip portions **256d** of the slope portions **256b** on both sides. This embodiment sets the width between the slope start positions **256c** in the X direction inside the width V of the holding member **254** in the X direction. In other words, in this embodiment, the contact portion, which is a portion that contacts the contact surface **152b** of the accessory shoe **1123** and is provided between the shoe engagement portion **251a** and the protrusion portion **256a** in the X direction, has a variable width in the area in contact with the contact surfaces **152b** in the X direction depending on the position in the Y direction. In this embodiment, as the position is closer to the tip of the protrusion portion **256a** in the Y direction, the width of the area in contact with the contact surface **152b** becomes wider in the X direction. In addition, in other words, in this embodiment, the lower tip portion **256d**, which is a lower end in the Y direction of the tip portion in the Z direction, is not located below the plurality of connection terminals **257** in the Y direction and outside the ends on the side of the plurality of connection terminals **257** of the shoe engagement portion **251a** in the X direction. In this embodiment, the lower tip portion **256d** is located below the plurality of connection terminals **257** in the Y direction. In this embodiment, the lower tip portion **256d** is provided at a position inside the ends on the side of the plurality of connection terminals **257** of the shoe engagement portion **251a** in the X direction. This structure secures a sufficient area for the contact portion **251b**.

[0245] The camera connector **1206** has such a structure that the shoe attachment leg **251** and the holding member **254** are fastened. The details of this fastening structure will be described later.

[0246] The holding member **254** can be inserted into the engagement portion interval **151aa** of the engagement member **151** of the accessory shoe **1123** illustrated in FIG. **18A**, and has a coupler **254a** having a width **V** shorter than the width **W** of the shoe attachment leg **251** in the **X** direction. The widths **W** and **V** are defined by the Japanese Industrial Standards (JIS) B7101-1975 “camera accessory attachment seat and attachment foot.” When the coupler **254a** is engaged with the engagement member **151**, the position of the external flash unit **120** relative to the camera **100** is determined in the **X** direction. The shoe attachment leg **251** is urged upward in the **Y** direction when it comes into contact with an elastically deformable portion **154a** of the accessory shoe spring **154** as the urging member illustrated in FIGS. **17A** and **17B**. Thereby, the top surface of the shoe engagement portion **251a** is brought into contact (pressure contact) with the bottom surface of the engagement member **151**, and the position of the external flash unit **120** relative to the camera **100** is determined in the **Y** direction.

[0247] When the contact portion **251b** of the shoe attachment leg **251** contacts the contact surface **152b** on the front side in the **Z** direction of the connection terminal connector **152**, the position of the external flash unit **120** relative to the camera **100** is determined in the **Z** direction.

[0248] The holding member **254** is also a structure for coupling the shoe attachment leg **251** and the base portion **250**, and the lock pins **252** and the connection terminals **257** are arranged inside the coupler **254a**.

[0249] Next follows a description of the fastening structure between the holding member **254** and the shoe attachment leg **251**. FIG. **21A** illustrates the camera connector **1206** viewed from the upper side in the **Y** direction, and FIG. **21B** illustrates a section taken along a line B-B in FIG. **21A**.

[0250] A pair of first screw **260a** and a pair of second screws **260b**, which are fastening members for fastening the shoe attachment leg **251** to the holding member **254**, penetrate the holding member **254** and are fastened to the shoe attachment leg **251**. At this time, by disposing one screw in each of the four areas that are substantially equally divided in the **X** direction and the **Z** direction in a well-balanced manner, the shoe attachment leg **251** is stably held by the holding member **254**. As described above, the shoe attachment leg **251** is a component to which a large stress is applicable. Therefore, a required mechanical strength can be ensured by fastening the metal shoe attachment legs **251** to the holding member **254** with a pair of first screws **260a** and a pair of second screws **260b** arranged in a well-balanced manner.

[0251] As illustrated in FIG. **21B**, a plurality of connection terminals **257** are arranged in an area **S** sandwiched by the pair of first screws **260a** and the pair of second screws **260b**. The widths between the pair of first screws **260a** and between the pair of second screws **260b** are narrower than the width between the lower tip portions **256d** of the protrusion portions **256a** of the connection plug **256**, the width **V** of the holding member **254**, the outermost width **T** of the connection plug **256**, and the width **W** of the shoe attachment leg **251**.

[0252] FIG. **26** illustrates a section of the accessory shoe **1123** viewed from the **Z** direction while the camera connector **1206** is attached to the accessory shoe **1123**. This figure illustrates the sizes **T** and **V** of the camera connector **1206** and the positional relationship between each component of the camera connector **1206** and each component of the accessory shoe **1123**.

[0253] In FIG. **26**, as described above, the top surface of the shoe engagement portion **251a** of the camera connector **1206** contacts the bottom (ceiling surface) of the engagement member **151** of the accessory shoe **1123** for positioning in the **Y** direction.

[0254] On the other hand, none of the lower tip portion **256d** and the slope portion **256b** of the protrusion portion **256a** of the connection plug **256** in the camera connector **1206** contact the bottom surface and the slope portion **152d** of the groove portion **152c** of the accessory shoe **1123**, respectively. A gap between the lower tip portion **256d** of the protrusion portion **256a** and the bottom surface of the groove portion **152c** of the accessory shoe **1123** is set as small as possible.

Thereby, when an external force in the X direction is applied to the external flash unit **120**, the lower tip portion **256d** of the protrusion portion **256a** can come into contact with the bottom surface of the groove portion **152c** of the accessory shoe **1123**, and a floating amount of the connection plug **256** (a tilt to the accessory shoe **1123**) can be reduced.

[0255] Each of a gap between the slope portions **256b** and **152d** and a gap between the inner end surface **152ccc** of the groove portion **152c** and the outer end surface of the connection plug **256** is set to be large to some extent. Thereby, when an external force in the X direction is applied to the external flash unit **120**, the connection terminals **257** and **152a** can be prevented from getting loaded.

[0256] In the groove portion **152c** of the accessory shoe **1123**, a relationship between a height of the groove portion **152c** in the Y direction (a height from the bottom surface of the groove portion **152c** to a ceiling surface of the engagement member **151**) and a height of the slope portion **152d** in the Y direction is similar to a relationship between the height B of the connection plug **256** and the height A of the slope portion **256b** in the camera connector **1206**. It is also preferable that the tilt angle of the slope portion **256b** to the X direction is also set in the range of $45^{\circ}+20^{\circ}$, similarly to the tilt angle θ of the slope portion **256b** in the camera connector **1206**.

[0257] Each embodiment described above has described a surface shape of the slope portion **256b** provided on the protrusion portion **256a** being flat, but the slope portion **256b** may be a curved surface having a curvature. That is, the slope portion **256b** may have a surface with a tilt to the X direction.

[0258] This embodiment can secure an area for providing a larger number of connection terminals than ever and a shape for protecting them and an area for positioning between components, in the compact camera connector **1206** and accessory shoe **1123**.

[0259] A description will now be given of a variation of an external flash unit **120**. FIG. 22A illustrates the external flash unit **120** viewed from the camera connector **1206** side (lower side in the Y direction). FIG. 22B illustrates a section taken along a line A-A in FIG. 22A and illustrates the internal structure of the camera connector **1206**. FIG. 23A illustrates the camera connector **1206**. However, the base portion **250** and the lock lever **253** are omitted. FIG. 23B illustrates the camera connector **1206** viewed from the front in the Z direction.

[0260] The camera connector **1206** is provided on the lower side in the Y direction (upper side in FIG. 22A) of the base portion **250** of the external flash unit **120** as illustrated in FIG. 22B while it is attached to the accessory shoe **1123** of the camera **100**. The camera connector **1206** has a shoe attachment leg **300a**, lock pins **252**, the lock lever **253**, the holding member **254**, a connection plug **300b**, a Y-direction holding member **258**, and a shoe cover **301**.

[0261] The shoe attachment leg **300a** is an engagement member for engaging the external flash unit **120** with the accessory shoe **1123** of the camera **100**, similar to the shoe attachment leg **251** of the above-described embodiment. That is, the shoe attachment leg **300a** is an engagement member on the external flash unit **120** side attachable to and detachable from the engagement member **151** of the accessory shoe **1123**.

[0262] In the above-described embodiment, the shoe attachment leg **251** as a metal shoe plate and the resin holding member **254** are formed as separate members in order to give priority to the mechanical strength. On the other hand, in this variation, the shoe attachment leg **300a** and the holding member **254** are formed as an integrated member by a resin material (nonconductive material). Thereby, the pair of first screws **260a** and the pair of second screws **260b** described in the previous embodiment are not required, a space for arranging the connection terminals **257** becomes wider, and thus a larger number of connection terminals **257** can be arranged. As a result, the external flash unit **120** can communicate more information with the camera **100** via the camera connector **1206** and the accessory shoe **1123**.

[0263] The connection plug **300b** is provided on the front side in the Z direction of the camera connector **1206**, and formed as an integrated member with the holding member **254** made of a

nonconductive resin material in this embodiment. Similar to the above-described embodiment, the outermost width T of the connection plug **300b** in the X direction is made narrower than the width W of the shoe attachment leg **300a** in the X direction, so that the area for providing the contact portion **300e** is secured in the shoe attachment leg **300a**. The connection plug **300b** has a plurality of connection terminals **257** for contacting and communicating with the plurality of connection terminals **152a** of the accessory shoe **1123** illustrated in FIG. **18C**.

[0264] The shoe cover **301** is an enclosure attached to the holding member **254**, and is a member that protects a plurality of connection terminals **257**. The shape of the connection terminal **257** is similar to that of the above embodiment, and the step portion **257e** is provided to secure a sufficient distance L in the Z direction of the extension portion **257b** without interfering with the shoe cover **301**.

[0265] The shape of the connection plug **300b** is also similar to that of the connection plug **256** of the previous embodiment, and a pair of protrusion portions **300c** that project downward in the Y direction are provided so as to sandwich the plurality of connection terminals **257** at both ends of the connection plug **300b** in the X direction. As illustrated in FIG. **23B**, a lower tip portion **300k** of each protrusion portion **300c** projects below a line made by connecting the lower ends of the tip portions **257a** of the connection terminals **257** in order to protect the connection terminal **257** from the external force such as the pressure and the impact. That is, the tip portion **257a** of the connection terminal **257** is provided above (inside) a line made by connecting the lower tip portions **300k** of the pair of protrusion portions **300c**.

[0266] Even in this embodiment, provided on the outer side of each protrusion portion **300c** in the X direction is a slope portion **300f** that extends diagonally upward from the lower tip portion **300k** and faces diagonally downward. Each protrusion portion **300c** having such a shape enables the connection plug **300b** to be inserted into the groove portion **152c** having the slope portion **152d** in the connection terminal connector **152** described in the previous embodiment. As described in the previous embodiment, the slope portion **300f** has a role of releasing the external force such as the pressure and the impact on the connection plug **300b** to prevent the connection plug from getting damaged.

[0267] Similar to the previous embodiment, it is desirable to make as short as possible a distance in the X direction between the slope start positions **300g** at the lower tip portion **300k** of the slope portions **300f** on both sides. Therefore, the slope start positions **300g** on both sides are provided inside the width V of the holding member **254** in the X direction to sufficiently secure the area of the contact portion **300e** of the shoe attachment leg **300a**.

[0268] The holding member **254** is formed so that it can be inserted into and engaged with the engagement portion interval **151aa** of the engagement member **151** illustrated in FIG. **18A**, and has a coupler **300h** having a width V shorter than the width W of the shoe attachment leg **300a** in the X direction. The width W and the width V are defined by the JIS B7101-1975 “camera accessory attachment seat and attachment foot” as in the previous embodiment. When the coupler **300h** is engaged with the engagement member **151**, the position of the external flash unit **120** relative to the camera **100** is determined in the X direction. The shoe attachment leg **300a** is urged upward in the Y direction when it contacts the elastically deformable portion **154a** of the accessory shoe spring **154** illustrated in FIGS. **17A** and **17B**, and thereby the top surface of the shoe engagement portion **300d** contacts the bottom surface (ceiling surface) of the engagement member **151**. Thereby, the position of the external flash unit **120** relative to the camera **100** is determined in the Y direction.

[0269] When the contact portion **300e** of the shoe attachment leg **300a** contacts the contact surface **152b** on the front side in the Z direction of the connection terminal connector **152**, the position of the external flash unit **120** relative to the camera **100** is determined in the Z direction. The holding member **254** is also a structure for coupling the shoe attachment legs **300a** and the base portion **250**, and the lock pin **252** and the connection terminal **257** are arranged inside the coupler **300h**.

[0270] In this embodiment, the case where the camera **100**, the accessory **200**, and the intermediate

accessory **300** have **21** or **15** contacts has been described, but the number of contacts may be other numbers.

[0271] In this embodiment, the microphone device and the strobe device have been described as the accessory **200**, but the accessory according to the present invention includes various devices, such as the electronic viewfinder unit, other than the microphone device and the strobe device. This embodiment has described the camera as an electronic apparatus, but the electronic apparatus according to the present invention also includes various electronic apparatuses other than the camera.

[0272] Next follows another embodiment of the external flash unit **120**.

[0273] FIG. **27A** illustrates the external flash unit **120** viewed from the camera connector **1206** side (lower side in the Y direction). FIG. **27B** illustrates a section taken along a line A-A in FIG. **27A**, which shows the internal structure of the camera connector **1206**. FIG. **28A** illustrates the camera connector **1206**, but omits the base portion **250** and the lock lever **253**. FIG. **28B** illustrates the camera connector **1206** viewed from the front in the Z direction.

[0274] FIG. **29A** illustrates the camera **100** to the external flash unit **120** is attached when the camera **100** is viewed from the diagonally rear side. FIG. **29B** illustrates a section taken along a line B-B in FIG. **29A**, in which the camera connector **1206** (shoe attachment leg **400a**) of the external flash unit **120** is being inserted into the accessory shoe **1123** (engagement member **151**) of the camera **100**. FIG. **29C** illustrates the same section as that of FIG. **29B**, and illustrates the shoe attachment leg **400a** held by the accessory shoe **1123** after the insertion of the shoe attachment leg **400a** into the accessory shoe **1123** is completed.

[0275] The shoe attachment leg **400a** is an engagement member for engaging the external flash unit **120** with the accessory shoe **1123** of the camera **100**. That is, the shoe attachment leg **400a** is an engagement member for the external flash unit **120** that is attachable to and detachable from the engagement member **151** of the accessory shoe **1123**.

[0276] The shoe attachment leg **400a** and a holding member **400** are formed as an integrated member by a resin material (non-conductive material). This configuration eliminates the need for the pair of first screws **260a** and the pair of second screws **260b**, and increases the space for arranging the connection terminals **257**, so that a large number of connection terminals **257** can be arranged. As a result, the external flash unit **120** can communicate more information with the camera **100** via the camera connector **1206** and the accessory shoe **1123**.

[0277] A connection plug **400b** is provided on the front side in the Z direction of the camera connector **1206**, and is formed as a member integrated with the holding member **400** made of a non-conductive resin material. Making the outermost width T of the connection plug **400b** in the X direction narrower than the width W of the shoe attachment leg **400a** in the X direction can secure an area for providing a contact portion **400e** in the shoe attachment leg **400a**. The connection plug **400b** has a plurality of connection terminals **257** that are to contact and communicate with the plurality of connection terminals **152a** of the accessory shoe **1123** illustrated in FIGS. **17A** and **17B**. The shoe cover **301** is an enclosure to be attached to the holding member **400** and serves as a member that protects the plurality of connection terminals **257**. Each connection terminal **257** has the same shape as that of the other embodiment, and the step portion **257e** is provided to secure a sufficient distance L in the Z direction of the extension portion **257b** without interfering with the shoe cover **301**.

[0278] The connection plug **400b** also has the same shape as that of the connection plug **256** of other embodiments, and a pair of protrusion portions **400c** protruding downward in the Y direction so as to sandwich a plurality of connection terminals **257** at both ends of the connection plug **400b** in the X direction. As illustrated in FIG. **28B**, a lower tip portion **400k** of each protrusion portion **400c** protrudes to a position below a line connecting the lower ends of tip portions **257a** of the connection terminals **257** in order to protect the connection terminal **257** from external forces such as pressure and impact. That is, the tip portions **257a** of the connection terminals **257** are provided

above (inside) the line connecting the lower tip portions **400k** of the pair of protrusion portions **400c**.

[0279] Even in this embodiment, slope portions **400f** extending diagonally upward from the lower tip portions **400k** and facing diagonally downward side are provided on the outer side of each protrusion portion **400c** in the X direction. Since each protrusion portion **400c** has such a shape, the connection plug **400b** can be inserted into the groove portion **152c** having the slope portion **152d** in the connection terminal connector **152** described in the first embodiment. As described in other embodiments, the slope portion **400f** has a role of releasing external forces such as pressure and impact from the connection plug **400b** and of preventing the connection plug **400b** from getting damaged.

[0280] A distance in the X direction between slope starting positions **400g** at the lower tip portions **400k** of the slope portions **400f** on both sides may be set as short as possible. Thus, the slope starting positions **400g** on both sides are provided inside a width V of the holding member **254** in the X direction to sufficiently secure the area for the contact portion **400e** of the shoe attachment legs **400a**.

[0281] The holding member **400** has a connector **400h** insertable into the engagement portion interval **151aa** of the engagement member **151** illustrated in FIG. **18A**, engageable with the engagement member **151**, and having the width V shorter than the width W in the X direction of the shoe attachment leg **400a**. The dimensions of the width W and the width V are specified in JIS B7101-1975 "Camera accessories mounting seat and mounting foot." When the connector **400h** is engaged with the engagement member **151**, the external flash unit **120** with respect to the camera **100** is positioned in the X direction.

[0282] The holding member **400** also has a structure for connecting the shoe attachment leg **400a** and the base portion **250** to each other, and the lock pin **252** and the connection terminal **257** are arranged inside the connector **400h**.

[0283] As illustrated in FIGS. **29A** to **29C**, the shoe attachment leg **400a** has a contact range (first range) **400j** that contacts the elastically deformable portion **154a** of the accessory shoe spring **154** illustrated in FIGS. **17A** and **17B**. When the contact range **400j** contacts the elastically deformable portion **154a** of the accessory shoe spring **154**, the shoe attachment leg **400a** is biased upward in the Y direction and a top surface of the shoe engagement portion **400d** contacts a bottom surface of the engagement member **151**. An arrow F in FIGS. **29B** and **29C** represents a biasing force by the accessory shoe spring **154**. Thereby, the external flash unit **120** is positioned relative to the camera **100** in the Y direction. The contact range **400j** corresponds to a biasing range biased by the elastically deformable portion **154a** of the accessory shoe spring **154** while the external flash unit **120** is being attached to the accessory shoe **1123** and when the attachment of the external flash unit **120** to the accessory shoe **1123** is completed. The contact range **400j** is disposed on both sides of the plurality of connection terminals **152a** on the front side (front side of the camera **100**) in the Z direction as the attachment direction.

[0284] The shoe attachment leg **400a** has a non-contact range (second range) **400i** that does not contact the elastically deformable portion **154a** of the accessory shoe spring **154**. This non-contact range **400i** corresponds to a non-biased range that is not biased by the elastically deformable portion **154a** of the accessory shoe spring **154** while the external flash unit **120** is being attached to the accessory shoe **1123** and when the attachment of the external flash unit **120** to the accessory shoe **1123** is completed. In FIG. **16C**, since there is a gap between the accessory shoe spring **154** and the non-contact range **400i**, the biasing force of the accessory shoe spring **154** against the non-contact range **400i** is 0.

[0285] In this embodiment, the thickness of the non-contact range **400i** in the Y direction is set to be larger than the thickness of the contact range **400j** in the same direction. The thickness of the contact range **400j** is set to be the same as that of the first and second embodiments. The thickness of the non-contact range **400i** in the Y direction is set to be larger than that of the contact range

400j for the following reasons.

[0286] A resin shoe according to this embodiment is inferior in strength to a metal shoe where they have the same shape. Thus, the strength can be ensured by increasing the thickness of the shoe attachment leg **400a** in the non-contact range **400i** in the Y direction. Since the strength calculated by the moment of inertia of area increases in proportion to the square of the thickness, it is possible to efficiently increase the strength by increasing the thickness in the Y direction. By making the length of the non-contact range **400i** in the Z direction longer than the length of the contact range **400j** in the Z direction, more strength can be secured.

[0287] By making the thickness of the contact range **400j** equal to that of the other embodiments, the shoe attachment legs **400a** can become versatile according to the JIS, and the elastically deformable portion **154a** of the accessory shoe spring **154** can be prevented from plastically deforming beyond a yield point. When the external flash unit **120** is attached to the accessory shoe **1123**, the thickness of the contact range **400j** in the Y direction is made equal to that of the other embodiments in order to make the attachment load equal to that of the other embodiments.

[0288] Since the non-contact range **400i** is provided on the attachment side of the contact range **400j** in the Z direction, the elastically deformable portion **154a** can be prevented from elastically deforming beyond a yield point even while the external flash unit **120** is being attached to the accessory shoe **1123**.

[0289] In this embodiment, the non-contact range **400i** is a non-biased range that is not biased by the elastically deformable portion **154a** of the accessory shoe spring **154** while the external flash unit **120** is being attached to the accessory shoe **1123** and when the attachment of the external flash unit **120** is completed. Alternatively, the non-contact range **400i** may be biased by the accessory shoe spring **154** while the external flash unit **120** is being attached to the accessory shoe **1123** and when the attachment of the external flash unit **120** is completed. In that case, in the state where the external flash unit **120** is held by the accessory shoe **1123**, the range in which the biasing force of the accessory shoe spring **154** is smaller than the contact range **400j** may be set to a range corresponding to the non-contact range **400i**. That is, the second range of the shoe attachment leg **400a** may be thicker than the first range and may have a biasing force (including 0) applied by the accessory shoe spring **154**, which is smaller than that of the first range.

[0290] When the contact portion **400e** of the shoe attachment leg **400a** comes into contact with the contact surface **152b** on the front side in the Z direction of the connection terminal connector **152**, the external flash unit **120** is positioned in the Z direction relative to the camera **100**.

[0291] Next follows another embodiment of an accessory shoe **423**. FIG. 30 illustrates a top cover **450** separated from the camera **100**, and the disassembled accessory shoe **423**.

[0292] The accessory shoe **423** includes an engagement member **451**, a connection terminal connector **452**, a shoe stage **453**, and the accessory shoe spring **154**. The engagement member **451** is a member that is to be engaged with the external flash unit **120** and thereby hold the external flash unit **120**. The connection terminal connector **452** includes a plurality of connection terminals **452a**. The shoe stage **453** is a housing member that encloses the engagement member **451** and the connection terminal connector **452**. The accessory shoe holding member **155** is a structural skeleton that holds the engagement member **451**.

[0293] The accessory shoe holding member **155**, flexible printed circuits (FPC, flexible substrate) **458**, the top cover **450**, the shoe stage **453**, and the connection terminal connector **452** are fastened to the engagement member **451** by four screws **157** inserted into the holes formed in them.

Thereby, these members are positioned and fixed to each other.

[0294] When the external flash unit **120** is attached to the accessory shoe **423**, the connection terminals **452a** are electrically connected to the external flash unit **120**.

[0295] Each of the plurality of connection terminals **452a** is electrically connected to the FPC **458** disposed on the lower side in the Y direction of the top cover **450**.

[0296] The FPC **458** is connected to an unillustrated main substrate of the camera **100**. Hence,

when the external flash unit **120** is attached to the accessory shoe **423**, communication between the external flash unit **120** and the camera **100** becomes available. In order to connect the FPC **458** to the internal electronics of the camera **100**, the shoe stage **453** has an opening **453a**, and the top cover **450** has an opening **450a**.

[0297] Referring now to FIGS. **31A** to **31C**, a description will be given of a drip-proof structure. FIG. **31A** illustrates the accessory shoe **423** incorporated in the shoe stage **453** viewed from below ($-Y$ direction). FIG. **31B** illustrates only the shoe stage **453** viewed from the $-Y$ direction. FIG. **31C** illustrates a section taken along a line A-A in FIG. **31A**.

[0298] Provided at the back of the connection terminal connector **452** in the Z direction (on the back side of the camera **100**) are engagement hole portions **452b** that are engageable with the lock pin **252** of the external flash unit **120** illustrated in FIG. **19A**. The engagement member **451** has screw hole portions **451a** to which the screws **157** are fastened. The shoe stage **453** is provided with through-hole portions **453c** through which the screws **157** penetrate.

[0299] A rectangular frame-shaped drip-proof member **453b** is provided around the opening **453a** provided to the shoe stage **453**. The drip-proof member **453b** is an elastic member such as an elastomer, and is integrated with the shoe stage **453**. In this embodiment, the drip-proof member **453b** is integrated with the shoe stage **453** by two-color injection molding.

[0300] As illustrated in FIG. **31C**, the drip-proof member **453b** interferes with (contacts) the connection terminal connector **452** and is compressed so as to prevent water from entering the camera **100** through the opening **453a** in the shoe stage **453** and the opening **450a** in the top cover **450**. The drip-proof member **453b** may be made of an elastic member such as sponge or silicon as a member separate from the shoe stage **453**.

[0301] The drip-proof member **453b** is disposed in the projection plane (in the XZ projection plane) from the $+Y$ direction of the connection terminal connector **452**. The screw hole portions **451a** and the through-hole portions **453c** described above are arranged inside the drip-proof member **453b**. This structure can also prevent water from entering through the screw hole portions **451a** and the through-hole portions **453c**.

[0302] Thus, the drip-proof member **453b** provided around the opening **453a** of the shoe stage **453** and the connection terminal connector **452** interfere with each other to prevent water from entering the inside of the camera **100**.

[0303] This embodiment can secure an area for a larger number of connection terminals than ever and a shape for protecting them, and a positioning area between components in a small shoe apparatus and an accessory shoe apparatus.

SECOND EMBODIMENT

[0304] Next follows a description of an accessory shoe of the camera **100** and a shoe apparatus of the external flash unit **120** according to a second embodiment of the present invention. In the case where the camera connector **1206** illustrated in FIGS. **20A** to **20C** is attached to the accessory shoe **1123** illustrated in FIG. **17A** and **17B**, the following problems may occur.

[0305] FIG. **32** illustrates that the camera connector **1206** biased in the X direction is about to be attached to the accessory shoe **1123** when they are viewed from the $+Y$ direction. In this state, the contact portion **251b** of the shoe attachment leg **251** of the camera connector **1206** contacts the tip of the accessory shoe **1123**, and the camera connector **1206** cannot be further inserted into the accessory shoe **1123** in the Z direction. In addition, the shoe attachment leg **251** is not engaged with the engagement member **151**, but part of the connection plug **256** is engaged with the engagement member **151**. In this state, when an external force is applied to the camera connector **1206** in a tilt direction ($+Y$ direction corresponding to a counterclockwise direction about the X axis), the load tends to concentrate on part of the connection plug **256**. Thus, if the external force in the tilt direction is applied to the camera connector **1206** in this state, the connection plug **256** partially engaged with the engagement member **151** may get damaged. Accordingly, this embodiment alleviates the above problems using the following shape.

[0306] FIG. 33 illustrates an accessory shoe 523 of the camera 100 according to this embodiment. The accessory shoe 523 includes an engagement member 551, the connection terminal connector 152, the shoe stage 153, and the accessory shoe spring 154. The engagement member 551 is a member engageable with the external flash unit 120 and configured to hold the external flash unit 120, and has oblique (bevel) portions (second diagonal portions) 551a on both sides thereof in the X direction. Each oblique portion 551a is a portion that tilts outward in the X direction toward the tip in the -Z direction.

[0307] The connection terminal connector 152 includes a plurality of connection terminals 152a. The shoe stage 153 is a housing member that encloses the engagement member 551 and the connection terminal connector 152.

[0308] FIG. 34A illustrates a camera connector 2206 provided to the external flash unit 120 according to this embodiment, but omits the base portion 250 and the lock lever 253. FIG. 34B illustrates the camera connector 2206 viewed from the front side in the Z direction.

[0309] The holding member 500 of the camera connector 2206 includes a shoe attachment leg 500a as an engagement member (shoe engagement portion) engageable with an engagement member 551 of the accessory shoe 523, and a connection plug 500b that protrudes on the tip side in the Z direction of the shoe attachment leg 500a. The connection plug 500b corresponds to a terminal protecting unit that protects a plurality of connection terminals 257. The shoe attachment leg 500a engaged with the engagement member 551 is positioned in the Y direction when its top surface contacts a ceiling surface of the engagement member 551 in the +Y direction (third direction).

[0310] Side (chamfered) slopes 500c are provided on both sides in the X direction on the top surface of the root side of the connection plug 500b, and tip oblique (chamfered) portions 500d as first oblique portions are provided on both sides in the X direction on the tip side of the connection plug 500b. In this embodiment, each of the shoe attachment legs 500a and the connection plug 500b is made of a non-conductive resin material and is formed as one component. Alternatively, only the shoe attachment legs 500a may be made of a metal material.

[0311] FIG. 35 illustrates that the camera connector 2206 biased to one side (-X direction) in the X direction is about to be attached to the accessory shoe 523 when they are viewed from the +Y direction in this embodiment. In this state, the shoe attachment leg 500a of the camera connector 2206 contacts the engagement member 551 of the accessory shoe 523, and the camera connector 2206 cannot be further inserted into the accessory shoe 523 in the Z direction. In addition, the shoe attachment leg 500a is not engaged with the engagement member 551, but part of the connection plug 500b is engaged with the engagement member 551.

[0312] At this time, the side slopes 500c are provided at portions of the connection plug 500b that is engaged with the engagement member 551. Each side slope 500c is a slope that tilts so that the connection plug 500b descends in the -Y direction (direction opposite to the third direction) in an area from the inside to the outside in the X direction. Thus, when an external force is applied to the camera connector 2206 in the tilt direction, the side slopes 500c contact the engagement member 551 and slide, guiding the connection plug 500b to move to the other side (+X direction) in the X direction. This structure can prevent the connection plug 500b from getting damaged. The side slope 500c may be a flat slope having a flat surface or a curved slope having a curved surface. In this embodiment, a slope connected to the side slope 500c is also formed at the tip oblique portion 500d and the outermost tip portion of the connection plug 500b.

[0313] That is, the connection plug 500b has a slope that continuously tilts (inclines) from the tip portion in the X direction to the tip portion in the Z direction. The term "continuously tilts" herein means that the tilt parts are connected, and includes a slope having different tilt angles between a slope facing the X direction and a slope facing the Z direction, and a slope that is bent between the slope facing the X direction and the slope facing the Z direction.

[0314] FIGS. 36A, 36B, and 37 illustrate the tip oblique portion 500d of the connection plug 500b and an oblique portion 551a of the engagement member 551 when they are viewed from the +Y

direction. As illustrated in FIG. 36A, the tip oblique portion **500d** is tilted inward in the X direction by a first angle θ_1 toward the tip in the +Z direction, which is the insertion direction (attachment direction) of the camera connector **2206** into the accessory shoe **523**. On the other hand, as illustrated in FIG. 36B, the oblique portion **551a** has a shape that is tilted outward in the X direction by a second angle θ_2 toward the tip in the -Z direction.

[0315] This embodiment sets the first angle θ_1 to the second angle θ_2 or larger ($\theta_1 \geq \theta_2$). The first angle θ_1 may be set to be larger than the second angle θ_2 ($\theta_1 > \theta_2$).

[0316] FIG. 37 illustrates that the camera connector **2206** tilted by an angle θ around the Y-axis relative to the Z direction is about to be inserted into the accessory shoe **523**. θ is an angle of θ_2 or larger.

[0317] Due to the above relationship between θ_1 and θ_2 , in such a state, the connection plug **500b** alone does not contact the engagement member **551** in the +Y direction before the shoe attachment leg **500a** is engaged with the engagement member **551** of the accessory shoe **523**. Thereby, even if an external force is applied to the camera connector **2206** in the tilt direction in this state, the connection plug **500b** can be prevented from getting damaged.

[0318] Thereafter, when the connection plug **500b** and the shoe attachment leg **500a** advance in the +Z direction towards the engagement member **551** while reducing the tilt angle θ from the Z direction, the shoe attachment leg **500a** alone or the shoe attachment leg **500a** and the connection plug **500b** simultaneously can contact the engagement member **551** in the +Y direction.

[0319] FIGS. 38A and 38B illustrate a positional relationship between the position (tilt starting position) as a starting point of the slope provided at the tip of the connection plug **500b** and the plurality of connection terminals **257**. FIG. 38A illustrates a camera connector **2206** viewed from the +Y direction so as to visualize the positions of the plurality of connection terminals **257** that overlap the connection plug **500b** and cannot be seen. FIG. 38B illustrates a section taken along a line A-A in FIG. 38A. Each of the plurality of connection terminals **257** is partially exposed from the connection plug **256** on the lower side in the Y direction (-Y direction) and on the tip side in the Z direction (+Z direction).

[0320] As illustrated in FIG. 38A, a width of the side slope **500c** in the X direction is wider than a width between adjacent connection terminals in the plurality of connection terminals **257**. Where L is the width of the side slope **500c** in the X direction and l is the width between adjacent connection terminals included in the plurality of connection terminals **257**, a relationship of $L > 3l$ is established, for example. As illustrated in FIG. 38A, in the X direction, a position (tilt starting position) of a starting point of the side slope **500c** is farther from the center of the holding member **500** than the connection terminals located at both ends of the plurality of connection terminals **257**. This structure can form the side slope **500c** while maintaining the strength of the connection plug **500b** so that the connection plug **500b** is prevented from getting damaged even if an external force in the X direction is applied to the connection plug **500b**.

[0321] As illustrated in FIG. 38B, the tips of the plurality of connection terminals **257** are located on the +Z direction side of the position (tilt starting position) as the starting point of the slope at the tip of the connection plug **500b**. When the slope becomes wider in the +Z direction, it becomes easier for the connection plug **500b** to move when an external force is applied to the camera connector **2206** in the tilt direction, so that the connection plug **500b** can be easily prevented from getting damaged. On the other hand, in an attempt to widen the slope in the +Z direction, the connection plug **500b** may become large in the Z direction. Accordingly, adopting the above configuration can form the slope having a predetermined width or more at the outermost tip portion while suppressing the size of the connection plug **500b** in the Z direction.

[0322] Thus, in the above structure, the tip of the connection plug **500b** is tilted so that the connection plug **500b** does not easily get damaged when an external force is applied to the camera connector **2206** in the tilt direction. Even when the shoe attachment legs **500a** provided on both sides of the connection plug **500b** are engaged with the engagement member **551**, the shoe

attachment legs **500a** may get damaged when a strong external force is applied to the camera connector **2206** in the tilt direction. Thus, the tip of each shoe attachment leg **500a** may be tilted. If the tip of the shoe attachment leg **500a** is tilted, the shoe attachment legs **500a** become less likely to get damaged and each tilted portion serves as a guide for inserting and ejecting the camera connector **2206** to and from the accessory shoe **523** and facilitates the insertion and ejection. [0323] On the other hand, the shoe attachment leg **500a** engaged with the engagement member **551** is positioned in the Y direction when its top surface contacts the ceiling surface of the engagement member **551** in the +Y direction, so that the tip of the shoe attachment leg **500a** may not be tilted based on the positioning accuracy in the Y direction. In consideration of both positioning in the Y direction and preventing the shoe attachment leg **500a** from getting damaged, an area of the tilted portion may be limited (so as to be smaller than the area of the tilted portion of the connection plug **500b**) while the tilting structure is employed. In this embodiment, each of the camera **100**, the accessory **200**, and the intermediate accessory **300** has 21 or 15 contacts, but the number of contacts is not limited.

[0324] In this embodiment, the microphone device and the strobe device serve as the accessory **200**, but the accessory according to the present invention includes various devices other than the microphone device and the strobe device such as the electronic viewfinder unit. In this embodiment, the camera serves as an electronic apparatus, but the electronic apparatus according to the present invention also includes various electronic apparatuses other than the camera.

[0325] The above embodiment can provide a small shoe apparatus that can secure an area for many connection terminals and a shape for protecting them, and a positioning area between components, and restrain the terminal protecting portion from getting damaged.

OTHER EMBODIMENTS

[0326] Embodiment(s) of the present invention can also be realized by a computer of a system or apparatus that reads out and executes computer executable instructions (e.g., one or more programs) recorded on a storage medium (which may also be referred to more fully as a ‘non-transitory computer-readable storage medium’) to perform the functions of one or more of the above-described embodiment(s) and/or that includes one or more circuits (e.g., application specific integrated circuit (ASIC)) for performing the functions of one or more of the above-described embodiment(s), and by a method performed by the computer of the system or apparatus by, for example, reading out and executing the computer executable instructions from the storage medium to perform the functions of one or more of the above-described embodiment(s) and/or controlling the one or more circuits to perform the functions of one or more of the above-described embodiment(s). The computer may comprise one or more processors (e.g., central processor (CPU), microprocessor (MPU)) and may include a network of separate computers or separate processors to read out and execute the computer executable instructions. The computer executable instructions may be provided to the computer, for example, from a network or the storage medium. The storage medium may include, for example, one or more of a hard disk, a random-access memory (RAM), a read only memory (ROM), a storage of distributed computing systems, an optical disk (such as a compact disc (CD), digital versatile disc (DVD), or Blu-ray Disc (BD)TM), a flash memory device, a memory card, and the like.

[0327] While the present invention has been described with reference to exemplary embodiments, it is to be understood that the invention is not limited to the disclosed exemplary embodiments. The scope of the following claims is to be accorded the broadest interpretation so as to encompass all such modifications and equivalent structures and functions.

[0328] This application claims the benefit of Japanese Patent Application No. 2021-094031, filed on Jun. 4, 2021, which is hereby incorporated by reference herein in its entirety.

Claims

1. A shoe apparatus attachable to and detachable from an accessory shoe apparatus of an electronic apparatus in a first direction, the shoe apparatus comprising: a plurality of connection terminals arranged in a second direction orthogonal to the first direction; and a terminal protecting portion configured to protect the plurality of connection terminals, wherein the plurality of connection terminals are exposed in a direction orthogonal to the first and second directions from the terminal protecting portion, and the terminal protecting portion includes slopes that tilt in an exposed direction from inside to outside in the second direction on both sides in the second direction.
 2. An accessory comprising a shoe apparatus attachable to and detachable from an accessory shoe apparatus of an electronic apparatus in a first direction, wherein the shoe apparatus includes: a plurality of connection terminals arranged in a second direction orthogonal to the first direction; and a terminal protecting portion configured to protect the plurality of connection terminals, wherein the plurality of connection terminals are exposed in a direction orthogonal to the first and second directions from the terminal protecting portion, and the terminal protecting portion includes slopes that tilt in an exposed direction from inside to outside in the second direction on both sides in the second direction.
-