

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250280736

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

Phung; Timothy et al.

TRIMMABLE INDUCTORS FOR QUBIT FREQUENCY TUNING

Abstract

Systems and techniques that facilitate trimmable inductors for qubit frequency tuning are provided. In various embodiments, a device can comprise a Josephson junction. In various aspects, the Josephson junction can be shunted by a capacitor, and a trimmable inductor can couple the Josephson junction to a pad of the capacitor. In various cases, the trimmable inductor can comprise a first conductive path that includes a severable and/or weldable superconducting bridge and a second conductive path that is in parallel with the first conductive path. In various aspects, severing and/or welding the severable and/or weldable superconducting bridge can controllably change an inductance of the trimmable inductor, which can commensurately change a resonant frequency of a qubit formed by the Josephson junction and the capacitor.

Inventors: Phung; Timothy (Milpitas, CA), Rettner; Charles (San Jose, CA), Mamin; Harry Jonathon (Palo Alto, CA), Adiga; Vivekananda P. (Ossining, NY), Budd; Russell A. (North Salem, NY)

Applicant: International Business Machines Corporation (Armonk, NY)

Family ID: 83195155

Appl. No.: 18/822704

Filed: September 03, 2024

Related U.S. Application Data

parent US division 17200487 20210312 parent-grant-document US 12108689 child US 18822704

Publication Classification

Int. Cl.: H10N60/12 (20230101); H10D1/20 (20250101); H10D1/68 (20250101); H10N60/01 (20230101); H10N69/00 (20230101)

Background/Summary

BACKGROUND

[0001] The subject disclosure relates to qubit frequency tuning, and more specifically to trimmable inductors for qubit frequency tuning.

SUMMARY

[0002] The following presents a summary to provide a basic understanding of one or more embodiments of the invention. This summary is not intended to identify key or critical elements, or delineate any scope of the particular embodiments or any scope of the claims. Its sole purpose is to present concepts in a simplified form as a prelude to the more detailed description that is presented later. In one or more embodiments described herein, devices, systems, computer-implemented methods, apparatus and/or computer program products that facilitate trimmable inductors for qubit frequency tuning are described.

[0003] According to one or more embodiments, a device is provided. In various embodiments, the device can comprise a Josephson junction. In various aspects, the Josephson junction can be shunted by a capacitor. In various instances, a trimmable inductor can couple the Josephson junction to a pad of the capacitor. In various cases, the trimmable inductor can comprise a first conductive path that includes a severable superconducting bridge and a second conductive path that is in parallel with the first conductive path. In various aspects, severing the severable superconducting bridge can increase an inductance of the trimmable inductor, which can decrease a resonant frequency of a qubit formed by the Josephson junction and the capacitor. In various cases, the trimmable inductor can comprise a first conductive path that includes a weldable superconducting bridge and a second conductive path that is in parallel with the first conductive path. In various aspects, welding the weldable superconducting bridge can decrease an inductance of the trimmable inductor, which can increase a resonant frequency of a qubit formed by the Josephson junction and the capacitor.

[0004] According to one or more embodiments, manufacturing and/or fabrication processes can be implemented to create one or more of the above devices.

Description

DESCRIPTION OF THE DRAWINGS

[0005] FIG. 1 illustrates a block diagram of an example, non-limiting device that facilitates trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein.

[0006] FIG. 2 illustrates example, non-limiting circuit diagrams of a trimmable inductor in accordance with one or more embodiments described herein.

[0007] FIG. 3 illustrates block diagrams of an example, non-limiting severable superconducting air bridge that facilitates trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein.

[0008] FIG. 4 illustrates block diagrams of severing an example, non-limiting severable superconducting air bridge that facilitates trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein.

[0009] FIG. 5 illustrates block diagrams of an example, non-limiting weldable superconducting air bridge that facilitates trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein.

[0010] FIG. 6 illustrates block diagrams of welding an example, non-limiting weldable superconducting air bridge that facilitates trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein.

[0011] FIG. 7 illustrates a block diagram of an example, non-limiting device including an internally-meandering trimmable inductor in accordance with one or more embodiments described herein.

[0012] FIG. 8 illustrates a block diagram of an example, non-limiting device including a stepwise-trimmable inductor in accordance with one or more embodiments described herein.

[0013] FIG. 9 illustrates an example, non-limiting circuit diagram of a stepwise-trimmable inductor in accordance with one or more embodiments described herein.

[0014] FIG. 10 illustrates example, non-limiting simulation results showing how one or more embodiments described herein influence resonant frequencies of superconducting qubits.

[0015] FIGS. 11-19b illustrate block diagrams of an example, non-limiting stepwise-trimmable inductor including diffusion-based antifuses in accordance with one or more embodiments described herein.

[0016] FIGS. 20-23 illustrate flow diagrams of example, non-limiting manufacturing and/or fabrication processes that facilitate trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein.

[0017] FIG. 24 illustrates a block diagram of an example, non-limiting operating environment in which one or more embodiments described herein can be facilitated.

DETAILED DESCRIPTION

[0018] The following detailed description is merely illustrative and is not intended to limit embodiments and/or application or uses of embodiments. Furthermore, there is no intention to be bound by any expressed or implied information presented in the preceding Background or Summary sections, or in the Detailed Description section.

[0019] One or more embodiments are now described with reference to the drawings, wherein like referenced numerals are used to refer to like elements throughout. In the following description, for purposes of explanation, numerous specific details are set forth in order to provide a more thorough understanding of the one or more embodiments. It is evident, however, in various cases, that the one or more embodiments can be practiced without these specific details.

[0020] A superconducting quantum computing system can comprise one or more superconducting qubits (e.g., transmon qubits, charge qubits, flux qubits) that are fabricated/manufactured on quantum chips/wafers. The overall operation/performance of the superconducting quantum computing system can depend upon the resonant frequencies (e.g., operational frequencies) of the one or more superconducting qubits. In other words, if the actual resonant frequencies differ from desired/target values by more than a threshold margin, frequency collisions between neighboring qubits on the quantum chips/wafers can result, which can impede proper operation of the superconducting quantum computing system. Thus, systems and/or techniques for facilitating quick and/or accurate post-fabrication tuning of the resonant frequency of a superconducting qubit can be desirable.

[0021] Various embodiments of the invention can address one or more of these technical problems. Specifically, various embodiments of the invention can provide for trimmable superconducting inductors that can be readily trimmed during post-fabrication processing. As described herein, such trimming can alter (e.g., increase and/or decrease) the resonant frequency of an associated superconducting qubit. Thus, in various aspects, the resonant frequency of an already-fabricated superconducting qubit can be tuned to a desired/target value by selectively and/or controllably trimming a trimmable superconducting inductor that is associated with the superconducting qubit.

[0022] In various embodiments, a superconducting qubit can comprise a Josephson junction (e.g., and/or multiple Josephson junctions) shunted by a planar capacitor (e.g., and/or multiple planar capacitors), such as a transmon qubit (e.g., in some cases, a transmon qubit can be a planar qubit with a ratio of Josephson energy to charging energy that is greater than 30). In various aspects, the superconducting qubit can have a resonant frequency (also referred to as “operational frequency”) that is a function of the resistance of the Josephson junction, the overall and/or equivalent capacitance shunted by the Josephson junction, and/or the overall and/or equivalent inductance in series with the Josephson junction. Thus, in various aspects, the resonant frequency of the superconducting qubit can be altered by altering the overall and/or equivalent inductance of the superconducting qubit.

[0023] In various instances, the overall and/or equivalent inductance of the superconducting qubit can be a function of an inductance associated with the superconducting wires that couple the Josephson junction to the planar capacitor. Specifically, in various cases, the planar capacitor can comprise two or more pads that are connected, coupled, and/or bridged by Josephson junctions. In various aspects, the Josephson junctions can be coupled/connected to the two or more pads via any suitable superconducting wires. In various cases, the inductance of the superconducting wires can be a function of the geometry (e.g., size, shape, dimensions, layout) of the superconducting wires and/or of the topology of the superconducting wires (e.g., whether the superconducting wires are coiled/spiraled, whether the superconducting wires are structured in series and/or in parallel). Thus, in various aspects, controllably altering the geometry and/or topology of the superconducting wires can controllably alter the resonant frequency of the superconducting qubit. In various cases, trimmable inductors as described herein can be implemented so as to controllably alter the inductance of the superconducting wires, thereby controllably altering the resonant frequency of the superconducting qubit.

[0024] In various embodiments, a trimmable inductor can be coupled in series between the Josephson junction and a pad of the planar capacitor. That is, the planar capacitor can comprise two or more pads (e.g., metal plates), and a trimmable inductor as described herein can physically and/or electrically link the Josephson junction to at least one of the two or more pads.

[0025] In various aspects, the trimmable inductor can comprise a first conductive path and a second conductive path that is in parallel with the first conductive path. In various cases, the first conductive path can be formed by any suitable superconducting wire which includes a severable and/or weldable superconducting bridge. In various instances, the second conductive path can be formed by any suitable superconducting wire which is coiled, spiraled, and/or meandered so as to exhibit some non-negligible inductance (e.g., an inductance value that is above any suitable threshold/margin). In some cases, the superconducting wire of the first conductive path can be not coiled, not spiraled, and/or not meandered (e.g., and/or less coiled, less spiraled, less meandered), such that the first conductive path exhibits an inductance that is lower than the inductance of the second conductive path. In other cases, however, the first conductive path can be more coiled, more spiraled, and/or more meandered than the second conductive path, such that the first conductive path exhibits an inductance that is higher than the inductance of the second conductive path. In various instances, the second conductive path can lack a severable and/or weldable superconducting bridge.

[0026] In some cases, if the first conductive path comprises a severable superconducting bridge, the Josephson junction can be electrically coupled/connected to the at least one pad by both the first conductive path and the second conductive path when the severable superconducting bridge is unsevered. In other words, because the first conductive path and the second conductive path can be in parallel, both the first conductive path and the second conductive path can be considered as closed electrical connections between Josephson junction and the at least one pad when the first conductive path comprises a severable superconducting bridge that has not yet been severed. In such case, the overall/equivalent inductance of the trimmable inductor can be considered as equal

to the reciprocal of the sum of the reciprocals of the inductance of the first conductive path and the inductance of the second conductive path (e.g., inductances in series add together, inductances in parallel add via reciprocating the sum of their reciprocals). Accordingly, the overall/equivalent inductance of the trimmable inductor can be less than both the inductances of first conductive path and the second conductive path when the severable superconducting bridge is unsevered.

[0027] In various aspects, severing (e.g., via laser melting/ablating, via etching, via scribing, via heating) the severable superconducting bridge can cause the first conductive path to switch from an electrically-closed state (e.g., allowing the flow of current) to an electrically-open state (e.g., not allowing the flow of current). Accordingly, after severing, the Josephson junction can be electrically coupled/connected to the at least one pad by the second conductive path but not by the first conductive path. In such case, the overall/equivalent inductance of the trimmable inductor can now be considered as equal to the inductance of the second conductive path (e.g., if the severable superconducting bridge of the first conductive path is severed/trimmed, the first conductive path can no longer inductively affect the Josephson junction). Moreover, the inductance of the second conductive path can be greater than the reciprocal of the sum of the reciprocals of the inductances of the first conductive path (pre-severing) and the second conductive path. So, severing the severable superconducting bridge of the first conductive path can be considered as increasing the overall/equivalent inductance of the trimmable inductor. This can correspondingly decrease the resonant frequency of the superconducting qubit formed by the Josephson junction and the planar capacitor. In various instances, the magnitude of the decrease in the resonant frequency can depend upon the sizes, shapes, dimensions, layouts, materials, and/or coils/spirals of the superconducting wires that make up the first conductive path and the second conductive path.

[0028] In some cases, if the first conductive path comprises a weldable superconducting bridge, the Josephson junction can be electrically coupled/connected to the at least one pad by the second conductive path and not by the first conductive path when the weldable superconducting bridge is unwelded. In other words, although the first conductive path and the second conductive path can be in parallel, the first conductive path can be considered being in an electrically-open state when the weldable superconducting bridge has not yet been welded. In such case, the overall/equivalent inductance of the trimmable inductor can be considered as equal to the inductance of the second conductive path alone.

[0029] In various aspects, welding (e.g., via laser melting/ablating, via etching, via scribing, via heating) the weldable superconducting bridge can cause the first conductive path to switch from an electrically-open state to an electrically-closed state. Accordingly, after welding, the Josephson junction can be electrically coupled/connected to the at least one pad by both the first conductive path and the second conductive path. In such case, the overall/equivalent inductance of the trimmable inductor can now be considered as equal to the reciprocal of the sum of the reciprocals of the inductance of the first conductive path and the inductance of the second conductive path, such that the overall/equivalent inductance is now less than the individual inductances of the first conductive path and the second conductive path. So, welding the weldable superconducting bridge of the first conductive path can be considered as decreasing the overall/equivalent inductance of the trimmable inductor. This can correspondingly increase the resonant frequency of the superconducting qubit formed by the Josephson junction and the planar capacitor. In various instances, the magnitude of the increase in the resonant frequency can depend upon the sizes, shapes, dimensions, materials, and/or coils/spirals of the superconducting wires that make up the first conductive path and the second conductive path.

[0030] In other words, various embodiments of the invention can include superconducting qubit devices that are pre-fabricated and/or pre-manufactured with trimmable inductors, and such trimmable inductors can be easily trimmed during post-fabrication processing to control resonant frequencies as desired. That is, various embodiments of the invention constitute novel quantum chip structures/architectures that allow for the easy post-fabrication modulation of inductances of

superconducting qubits, thereby allowing commensurately easy post-fabrication tuning of resonant frequencies.

[0031] Various embodiments of the invention can be employed to use hardware and/or software to solve problems that are highly technical in nature (e.g., to facilitate trimmable inductors for qubit frequency tuning), that are not abstract and that cannot be performed as a set of mental acts by a human. Indeed, various embodiments of the invention can constitute real-world, physical quantum structures/devices (e.g., superconducting inductor architectures) that can be fabricated on a real-world substrate (e.g., silicon chip/wafer) in order to facilitate easy tuning of resonant frequencies during post-fabrication processing (e.g., in some cases, embodiments of the invention can be implemented post flip-chip bonding and/or post full chip packaging, without requiring debonding). Such real-world, physical quantum devices/architectures certainly are not abstract, are not laws of nature, and are not natural phenomena.

[0032] Moreover, various embodiments of the invention can integrate into a practical application the teachings disclosed herein. Indeed, in various embodiments, the disclosed teachings can facilitate the fabrication of a quantum device having superconducting inductors, where such superconducting inductors are readily trimmable during post-fabrication processing, and where controllably trimming (e.g., severing and/or welding) such superconducting inductors can correspondingly control a resonant frequency of an associated superconducting qubit on the quantum device without adversely affecting coherence and/or performance of the quantum device. Conventional techniques simply cannot facilitate such tuning of quantum resonant frequencies in a post-fabrication setting. Thus, embodiments of the invention constitute a concrete and tangible technical improvement in the field of quantum frequency tuning.

[0033] It should be appreciated that the figures and/or drawings accompanying this disclosure are non-limiting examples and are not necessarily drawn to scale.

[0034] FIG. 1 illustrates a block diagram of an example, non-limiting device **100** that can facilitate trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein.

[0035] As shown, the device **100** can comprise a substrate **102**. In various aspects, the substrate **102** can comprise any suitable chip/wafer material that can be used in quantum computing (e.g., silicon substrate). In various cases, the substrate **102** can comprise any suitable size, shape, and/or dimensions. In various aspects, a Josephson junction **104** can be formed on the substrate **102**. In various aspects, the Josephson junction **104** can comprise any suitable construction and/or composition (e.g., two or more superconducting layers that sandwich a weak link, such as an oxide layer). In various aspects, the Josephson junction **104** can comprise any suitable size, shape, and/or dimensions. In various instances, the Josephson junction **104** can be coupled to a pad **106** and to a pad **108**. In various aspects, the pad **106** and the pad **108** can comprise any suitable superconducting materials (e.g., can comprise the same and/or different materials as each other), and/or can comprise any suitable sizes, shapes, and/or dimensions (e.g., can comprise the same and/or different dimensions as each other). In various embodiments, the pad **106** and the pad **108** can be considered as collectively forming a planar capacitor that shunts the Josephson junction **104**. Thus, in various aspects, the Josephson junction **104**, the pad **106**, and the pad **108** can together be considered as a transmon qubit.

[0036] In various embodiments, as shown, the Josephson junction **104** can be coupled and/or connected to the pad **108** by a trimmable inductor **110**. As mentioned above, the trimmable inductor **110** can be easily trimmed and/or altered during post-fabrication processing to tune the resonant frequency of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108**.

[0037] In various aspects, the trimmable inductor **110** can comprise a first conductive path **112** and a second conductive path **114**. As shown, the first conductive path **112** can be in parallel with the second conductive path **114**. In other words, the Josephson junction **104** can be coupled/connected

to the pad **108** by both the first conductive path **112** and the second conductive path **114**. In various cases, as depicted, the second conductive path **114** can be formed by any suitable superconducting wire (e.g., niobium wire) that is coiled, spiraled, and/or meandered in any suitable fashion, and/or the first conductive path **112** can be formed by any suitable superconducting wire (e.g., same as and/or different from the material of the second conductive path **114**) that is not coiled, not spiraled, and/or not meandered. In various instances, this can cause an inductance of the first conductive path **112** to be lower than an inductance of the second conductive path **114**. However, those having ordinary skill in the art will appreciate that this is a mere non-limiting example. In various cases, the first conductive path **112** can be coiled, spiraled, and/or meandered and/or the second conductive path **114** can be not coiled, not spiraled, and/or not meandered, such that the inductance of the first conductive path **112** is higher than the inductance of the second conductive path **114**. In any case, the first conductive path **112** and/or the second conductive path **114** can be structured so as to exhibit any suitable inductance values.

[0038] In various embodiments, the first conductive path **112** can comprise a superconducting bridge **116**. In various aspects, the superconducting bridge **116** can be a severable superconducting bridge (e.g., a superconducting fuse) and/or can be a weldable superconducting bridge (e.g., a superconducting antifuse).

[0039] Suppose that the superconducting bridge **116** is severable. In such case, the superconducting bridge **116** can be structured so that the first conductive path **112** is initially in an electrically-closed state. In other words, if the superconducting bridge **116** is severable, electric current can flow across the first conductive path **112** when the superconducting bridge **116** is unsevered. Thus, severing (e.g., via laser melting/ablating, via etching, via scribing, via heating) the superconducting bridge **116** can cause the first conductive path **112** to switch from an electrically-closed state to an electrically-open state. That is, if the superconducting bridge **116** is severable, electric current cannot flow across the first conductive path **112** when the superconducting bridge **116** is severed. In various cases, because the second conductive path **114** can lack superconducting bridges, the second conductive path **114** can be considered as being in a permanently electrically-closed state (e.g., electric current can flow across the second conductive path **114** both before and after severing the superconducting bridge **116**). Thus, when the superconducting bridge **116** is severable, the trimmable inductor **110** can provide two electrical paths (e.g., **112** and **114**) between the Josephson junction **104** and the pad **108** prior to severing of the superconducting bridge **116**, and the trimmable inductor **110** can provide one electrical path (e.g., **114**) between the Josephson junction **104** and the pad **108** after severing of the superconducting bridge **116**. In various cases, such severing can cause the trimmable inductor **110** to switch from providing two inductances in parallel between the Josephson junction **104** and the pad **108** to providing only one inductance between the Josephson junction **104** and the pad **108**. This can increase the overall and/or equivalent inductance of the trimmable inductor **110** (e.g., inductances in parallel can diminish each other by the rule of reciprocating the sum of the reciprocals), which can correspondingly decrease the resonant frequency of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108**.

[0040] Suppose that the superconducting bridge **116** is instead weldable. In such case, the superconducting bridge **116** can be structured so that the first conductive path **112** is initially in an electrically-open state. In other words, if the superconducting bridge **116** is weldable, electric current cannot flow across the first conductive path **112** when the superconducting bridge **116** is unwelded. Thus, welding (e.g., via laser melting/ablating, via etching, via scribing, via heating) the superconducting bridge **116** can cause the first conductive path **112** to switch from an electrically-open state to an electrically-closed state. That is, if the superconducting bridge **116** is weldable, electric current can flow across the first conductive path **112** when the superconducting bridge **116** is welded. As mentioned above, because the second conductive path **114** can lack superconducting bridges, the second conductive path **114** can be considered as being in a permanently electrically-

closed state (e.g., electric current can flow across the second conductive path **114** both before and after welding the superconducting bridge **116**). Thus, when the superconducting bridge **116** is weldable, the trimmable inductor **110** can provide one electrical path (e.g., **114**) between the Josephson junction **104** and the pad **108** prior to welding of the superconducting bridge **116**, and the trimmable inductor **110** can provide two electrical paths (e.g., **112** and **114**) between the Josephson junction **104** and the pad **108** after welding of the superconducting bridge **116**. In various cases, such welding can cause the trimmable inductor **110** to switch from providing only one inductance between the Josephson junction **104** and the pad **108** to providing two inductances in parallel between the Josephson junction **104** and the pad **108**. This can decrease the overall and/or equivalent inductance of the trimmable inductor **110** (e.g., inductances in parallel can diminish each other by the rule of reciprocating the sum of the reciprocals), which can correspondingly increase the resonant frequency of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108**.

[0041] In this way, the inductance of the trimmable inductor **110** (and thus the resonant frequency of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108**) can be controlled by severing and/or welding the superconducting bridge **116** during post-fabrication processing. In various cases, the inductance can be increased (and the resonant frequency can thus be decreased) by severing the superconducting bridge **116**. In various cases, the inductance can be decreased (and the resonant frequency can thus be increased) by welding the superconducting bridge **116**. In various aspects, the magnitude of the change in resonant frequency can depend upon the sizes, shapes, layouts, and/or materials of the first conductive path **112** and/or the second conductive path **114**. Therefore, in various aspects, selective/controlled trimming of the trimmable inductor **110** as described herein allows for selective/controlled modulation of the resonant frequency of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108**.

[0042] The inventors of various embodiments of the invention utilized computer-aided design software to perform computational simulations of a superconducting qubit structure that is topologically equivalent to that depicted in FIG. **1**. Some simulations were conducted in situations where the superconducting bridge **116** is severable, and other simulations were conducted in situations where the superconducting bridge **116** is weldable. Such simulations demonstrated how the surface current density distributions of the trimmable inductor **110** can change in response to severing and/or welding of the superconducting bridge **116**.

[0043] The former simulations showed that, when the superconducting bridge **116** is unsevered, the surface current density in the first conductive path **112** is relatively high and the surface current density in the second conductive path **114** is relatively low. The former simulations also showed that, when the superconducting bridge **116** is severed, the surface current density in the first conductive path **112** becomes relatively low and the surface current density in the second conductive path **114** becomes relatively high. In other words, the first conductive path **112** is primarily electrically active and the second conductive path **114** is primarily electrically inactive when the superconducting bridge **116** is unsevered, and the first conductive path **112** becomes primarily electrically inactive and the second conductive path **114** becomes primarily electrically active when the superconducting bridge **116** is severed.

[0044] The latter simulations showed analogous results. Specifically, the latter simulations showed that, when the superconducting bridge **116** is unwelded, the surface current density in the first conductive path **112** is relatively low and the surface current density in the second conductive path **114** is relatively high. The latter simulations also showed that, when the superconducting bridge **116** is welded, the surface current density in the first conductive path **112** becomes relatively high and the surface current density in the second conductive path **114** becomes relatively low. In other words, the first conductive path **112** is primarily electrically inactive and the second conductive path **114** is primarily electrically active when the superconducting bridge **116** is unwelded, and the

first conductive path **112** becomes primarily electrically active and the second conductive path **114** becomes primarily electrically inactive when the superconducting bridge **116** is welded.

[0045] These simulation results demonstrate how the electrical characteristics of the trimmable inductor **110** can be controlled via severing/welding of the superconducting bridge **116**. Controlling the electrical characteristics of the trimmable inductor **110** in this way thus allows for commensurate controlling of the resonant frequency of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108**.

[0046] Those having ordinary skill in the art will appreciate that the Josephson junction **104**, the pad **106**, the pad **108**, and/or the trimmable inductor **110** can be manufactured on the substrate **102** via any suitable microfabrication and/or nanofabrication techniques (e.g., deposition, etching, angled evaporation, photolithography, patterning).

[0047] FIG. 2 illustrates example, non-limiting circuit diagrams **200** of a trimmable inductor in accordance with one or more embodiments described herein. As shown, FIG. 2 depicts a circuit diagram **202** and a circuit diagram **204**.

[0048] Suppose that the superconducting bridge **116** is severable. In such case, the circuit diagram **202** can be considered as representing the electrical characteristics of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and/or the pad **108** prior to severing of the superconducting bridge **116**, and the circuit diagram **204** can be considered as representing the electrical characteristics of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and/or the pad **108** after severing of the superconducting bridge **116**.

[0049] As shown in the circuit diagram **202**, the Josephson junction **104** can be shunted by a capacitance **206**. In various cases, the capacitance **206** can be the capacitance exhibited by the planar capacitor formed by the pad **106** and the pad **108**. Also as shown in the circuit diagram **202**, an equivalent inductance **208** can be coupled in series between the Josephson junction **104** and the capacitance **206**. In various aspects, the equivalent inductance **208** can be the overall and/or equivalent inductance exhibited by the trimmable inductor **110** before severing of the superconducting bridge **116**. As shown, the equivalent inductance **208** can comprise two sub-inductances that are coupled together in parallel: a sub-inductance **210** and a sub-inductance **212**. In various instances, the sub-inductance **210** can be the inductance exhibited by the first conductive path **112** when the first conductive path **112** is in an electrically-closed state, and the sub-inductance **212** can be the inductance exhibited by the second conductive path **114**. Because the sub-inductance **210** and the sub-inductance **212** are in parallel with each other, the equivalent inductance **208** can be equal to the reciprocal of the sum of the reciprocals of the sub-inductance **210** and the sub-inductance **212**. Accordingly, the equivalent inductance **208** can be lesser than each of the sub-inductance **210** and the sub-inductance **212**.

[0050] As shown in the circuit diagram **204**, the Josephson junction **104** can be shunted by the capacitance **206**, as described above. Also as shown in the circuit diagram **204**, an equivalent inductance **214** can be coupled in series between the Josephson junction **104** and the capacitance **206**. In various aspects, the equivalent inductance **214** can be the overall and/or equivalent inductance exhibited by the trimmable inductor **110** after severing of the superconducting bridge **116**. As shown, the equivalent inductance **214** can comprise one sub-inductance: the sub-inductance **212** which can be exhibited by the second conductive path **114**. In other words, after severing of the superconducting bridge **116**, electric current can no longer flow across the first conductive path **112**, which means that the sub-inductance **210** no longer electrically interacts with the Josephson junction **104**. Accordingly, the sub-inductance **210** is not depicted in the circuit diagram **204**. Thus, the equivalent inductance **214** can be equal to the sub-inductance **212**, which can be greater than the equivalent inductance **208**.

[0051] Therefore, when the superconducting bridge **116** is severable, severing the superconducting bridge **116** can increase the overall and/or equivalent inductance of the trimmable inductor **110** from the equivalent inductance **208** to the equivalent inductance **214**. This can correspondingly

cause a decrease in the resonant frequency of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108**.

[0052] On the other hand, if the superconducting bridge **116** is weldable instead of severable, the circuit diagram **204** can be considered as representing the electrical characteristics of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108** prior to welding of the superconducting bridge **116**, and the circuit diagram **202** can be considered as representing the electrical characteristics of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108** after welding of the superconducting bridge **116**. Therefore, when the superconducting bridge **116** is weldable, welding the superconducting bridge **116** can decrease the overall and/or equivalent inductance of the trimmable inductor **110** from the equivalent inductance **214** to the equivalent inductance **208**. This can correspondingly cause an increase in the resonant frequency of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108**.

[0053] As explained above, severable superconducting bridges can be used to create a trimmable inductor that can be easily modulated during post-fabrication processing to tune the resonant frequency of a superconducting qubit. When one or more of such severable superconducting bridges are severed, the inductance of the trimmable inductor can be increased by a known amount (e.g., which can be a function of the materials, geometry, and/or topology of the trimmable inductor), which can cause a corresponding decrease in resonant frequency. In some embodiments, a severable superconducting bridge can be considered as a superconducting fuse that can transition from a superconducting state (e.g., an electrically-closed state) to a non- superconducting state (e.g., an electrically-open state) in response to any suitable external stimuli (e.g., thermal stimulation, electrical stimulation, optical stimulation). As also explained above, weldable superconducting bridges can be used to create a trimmable inductor that can be easily modulated during post-fabrication processing to tune the resonant frequency of a superconducting qubit. When one or more of such weldable superconducting bridges are welded, the inductance of the trimmable inductor can be decreased by a known amount (e.g., which can be a function of the materials, geometry, and/or topology of the trimmable inductor), which can cause a corresponding increase in resonant frequency. In some embodiments, a weldable superconducting bridge can be considered as a superconducting antifuse that can transition from a non-superconducting state (e.g., an electrically-open state) to a superconducting state (e.g., an electrically-closed state) in response to any suitable external stimuli (e.g., thermal stimulation, electrical stimulation, optical stimulation). Thus, in some cases, a trimmable inductor can be structured so as to have one or more severable superconducting bridges and/or one or more weldable superconducting bridges, thereby allowing the resonant frequency to be controllably shifted up or down as needed/desired.

[0054] In various aspects, FIGS. **3-6** and accompanying text explain how to fabricate various example embodiments of severable and/or weldable superconducting bridges.

[0055] In various embodiments, a severable superconducting bridge can be a superconducting air bridge that is suspended over an underlying substrate surface. FIGS. **3-4** depict example, non-limiting illustrations of such severable superconducting air bridges.

[0056] FIG. **3** illustrates block diagrams of an example, non-limiting severable superconducting air bridge that can facilitate trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein. More specifically, FIG. **3** depicts how such a severable superconducting air bridge can be fabricated/manufactured.

[0057] FIG. **3** depicts a first cross-sectional view **302** and a second cross-sectional view **304**. As shown in the first cross-sectional view **302**, a sacrificial layer **308** can be formed and/or deposited via any suitable patterning and/or lithographic technique (e.g., oxidation, angled evaporation) on a substrate **306** (e.g., a silicon substrate). In various aspects, the sacrificial layer **308** can be an oxide layer and/or any other suitable sacrificial material used in microfabrication and/or nanofabrication. As also shown in the first cross-sectional view **302**, a superconducting layer **310** (e.g., niobium,

aluminum, and/or any other suitable superconducting material) can be deposited via any suitable patterning and/or lithographic technique over and/or across the sacrificial layer **308**. As shown, the result can be that some portions of the superconducting layer **310** are formed on the substrate **306** while another portion of the superconducting layer **310** is formed on top of the sacrificial layer **308**. In other words, the sacrificial layer **308** can be sandwiched between the superconducting layer **310** and the substrate **306**. As shown in the second cross-sectional view **304**, the sacrificial layer **308** can be removed via any suitable technique (e.g., wet etching, ion milling), thereby leaving an open space **312** where the sacrificial layer **308** previously was located. In various aspects, as shown, this can cause a portion of the superconducting layer **310** to be suspended over the substrate **306** (e.g., a part of the superconducting layer **310** is separated from the substrate **306** by the open space **312**). In various aspects, this structure can be considered as a severable superconducting air bridge **314**.

[0058] Although not explicitly shown in FIG. **3**, the severable superconducting air bridge **314** can be fabricated to have any suitable number and/or shapes of perforations and/or any suitable number and/or shapes of tapers. As those having ordinary skill in the art will appreciate, such perforations and/or tapers can reduce an amount of heat needed to melt, ablate, and/or otherwise sever the severable superconducting air bridge **314**.

[0059] FIG. **4** illustrates block diagrams of severing an example, non-limiting severable superconducting air bridge that can facilitate trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein. In other words, FIG. **4** shows how the severable superconducting air bridge **314** of FIG. **3** can be severed.

[0060] As shown, FIG. **4** includes a first cross-sectional view **402** and a second cross-sectional view **404**. In various aspects, the first cross-sectional view **402** depicts a laser **406** addressing the severable superconducting air bridge **314** from above. In various cases, the laser **406** can be controlled so as to melt and/or ablate the severable superconducting air bridge **314** (e.g., so as to melt and/or ablate the portion of the superconducting layer **310** that is separated from the substrate **306** by the open space **312**). As shown in the second cross-sectional view **404**, such melting/ablating can create a severed/trimmed portion **408** in the severable superconducting air bridge **314** (e.g., can severe/trim the suspended portion of the superconducting layer **310**).

[0061] In various aspects, the laser **406** can be aimed and/or directed along any suitable angle/direction. Although not explicitly shown in FIG. **4**, the laser **406** can, in some embodiments, address the severable superconducting air bridge **314** from below (e.g., from below the substrate **306**). Indeed, in various aspects, the substrate **306** can be transparent and/or substantially transparent to various ranges of laser wavelengths. Thus, a laser whose wavelength is within such various ranges can pass through the substrate **306** without melting/ablating the substrate **306**. For example, a silicon substrate can be substantially transparent at laser wavelengths above 1.3 μm .

[0062] In various instances, the open space **312** can serve as a thermal barrier that protects the substrate **306** during melting/ablating of the severable superconducting air bridge **314**. For instance, consider a severable niobium air bridge on a silicon substrate. In various cases, niobium can melt at 2,477 degrees Celsius and silicon can melt at 1,414 degrees Celsius. In various aspects, the laser **406** can be a continuous wave, long-pulsed and/or short-pulsed laser. In such case, the laser **406** can be used to heat the severable niobium air bridge to beyond its melting point, thereby severing the severable niobium air bridge, while leaving the silicon substrate undamaged. Thus, in various aspects, the laser **406** can sever the severable superconducting air bridge **314** without damaging and/or contaminating the substrate **306**. In this way, coherence and/or performance of the superconducting qubit can be not adversely affected.

[0063] Although not explicitly shown in FIG. **4**, any other suitable severing/trimming technique can be implemented other than the laser **406** (e.g., etching, scribing, heating, etc.).

[0064] Although not explicitly shown in FIG. **4**, any other suitable severable/trimmable superconducting couplings can be implemented instead of the severable superconducting air bridge **314** (e.g., in some cases, superconducting lines that run along the substrate **306** and/or that are not

suspended over the substrate **306** can be implemented). Such other severable/trimmable superconducting couplings can be severed/trimmed in similar fashions.

[0065] The above discussion pertains to severable superconducting air bridges. Now, consider weldable superconducting air bridges. In various embodiments, a weldable superconducting bridge can be a superconducting air bridge that is suspended over an underlying superconducting line that runs along a substrate surface. FIGS. **5-6** depict example, non-limiting illustrations of such weldable superconducting air bridges.

[0066] FIG. **5** illustrates block diagrams of an example, non-limiting weldable superconducting air bridge that can facilitate trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein. More specifically, FIG. **5** depicts how such a weldable superconducting air bridge can be fabricated/manufactured.

[0067] FIG. **5** depicts a first cross-sectional view **502** and a second cross-sectional view **504**. As shown in the first cross-sectional view **502**, a first superconducting layer **508** (e.g., niobium, aluminum) can be deposited via any suitable patterning and/or lithographical technique (e.g., angled evaporation) on a substrate **506**. Similarly, a sacrificial layer **510** (e.g., oxide) can be formed and/or deposited via any suitable patterning and/or lithographic technique (e.g., oxidation, angled evaporation) on and/or over top of the first superconducting layer **508**. As also shown in the first cross-sectional view **502**, a second superconducting layer **512** (e.g., niobium, aluminum) can be deposited via any suitable patterning and/or lithographic technique over and/or across the sacrificial layer **510**. As shown, the result can be that some portions of the second superconducting layer **512** are formed on the substrate **506** while another portion of the second superconducting layer **512** is formed on top of the sacrificial layer **510**. In other words, the sacrificial layer **510** can be sandwiched between the second superconducting layer **512** and the first superconducting layer **508**. As shown in the second cross-sectional view **504**, the sacrificial layer **510** can be removed via any suitable technique (e.g., wet etching, ion milling), thereby leaving an open space **514** where the sacrificial layer **510** previously was located. In various aspects, as shown, this can cause a portion of the second superconducting layer **512** to be suspended over both the substrate **506** and the first superconducting layer **508** (e.g., a part of the second superconducting layer **512** is separated from the substrate **506** and/or from the first superconducting layer **508** by the open space **514**). In various aspects, this structure can be considered as a weldable superconducting air bridge **516**. [0068] In various aspects, the weldable superconducting air bridge **516** can include perforations and/or tapered notches, as described above.

[0069] FIG. **6** illustrates block diagrams of welding an example, non-limiting weldable superconducting air bridge that can facilitate trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein. In other words, FIG. **6** shows how the weldable superconducting air bridge **516** of FIG. **6** can be welded.

[0070] As shown, FIG. **6** includes a first cross-sectional view **602** and a second cross-sectional view **604**. In various aspects, the first cross-sectional view **602** depicts a laser **606** addressing the weldable superconducting air bridge **516** from above. Just as described above with respect to FIG. **4**, in various cases, the laser **606** can be controlled so as to melt and/or ablate the weldable superconducting air bridge **516** (e.g., so as to melt and/or ablate the portion of the second superconducting layer **512** that is separated from the substrate **506** and the first superconducting layer **508** by the open space **514**). As shown in the second cross-sectional view **604**, such melting/ablating can create a welded portion **608** in the weldable superconducting air bridge **516** (e.g., can weld and/or fuse the suspended portion of the second superconducting layer **512** to the first superconducting layer **508**).

[0071] In various aspects, the laser **606** can be aimed and/or directed along any suitable angle/direction. Although not explicitly shown in FIG. **6**, the laser **606** can, in some embodiments, address the weldable superconducting air bridge **516** from below (e.g., from below the substrate **506**), as described above with respect to FIG. **4** (e.g., in various aspects, the substrate **506** can be

transparent and/or substantially transparent to various ranges of laser wavelengths).

[0072] Although not explicitly shown in FIG. 6, any other suitable welding technique can be implemented other than the laser 606 (e.g., any suitable localized heating technique). For instance, in some cases, any suitable micromanipulations can be implemented so as to weld a weldable superconducting air bridge. As a non-limiting example, any suitable microtool integrated into a translatable stage, platform, and/or end effector can be implemented so as to physically press and/or deform the suspended portion of the second superconducting layer 512, such that the suspended portion of the second superconducting layer 512 is now in physical contact with the first superconducting layer 508. In various cases, such physical deformation can cause the weldable superconducting air bridge 516 to be in a welded state.

[0073] Those having ordinary skill in the art will appreciate that FIGS. 5-6 depict a mere non-limiting example of a weldable superconducting antifuse. In various cases, any other suitable weldable superconducting antifuses can be implemented in various embodiments of the invention. For example, in some cases, a diffusion-based superconducting antifuse can be implemented. In such case, a dielectric material (e.g., silicon) can be sandwiched between two superconducting materials (e.g., niobium and/or aluminum). Accordingly, the two superconducting materials can be electrically isolated from each other initially. In various aspects, application of heat (e.g., via a laser) to such structure can cause one of the superconducting materials to diffuse into the dielectric layer (e.g., aluminum can diffuse into silicon at temperatures greater than and/or equal to 500 degrees Celsius). Thus, after application of such heat, the two superconducting materials can now be no longer electrically isolated from each other (e.g., the diffused region in the dielectric layer can conduct electricity). As another example, a flow-based superconducting antifuse can be implemented in various embodiments of the invention. In such case, two or more abutting superconducting materials can be separated by a spatial gap (e.g., the spatial gap can be on the order of nanometers and/or micrometers wide). Accordingly, the two superconducting materials can be electrically isolated from each other initially. In various aspects, application of heat to the portions of the superconducting materials that are adjacent to the spatial gap can cause such portions of the superconducting materials to melt and laterally flow together across the spatial gap. Thus, after application of such heat, the two superconducting materials can now be no longer electrically isolated from each other (e.g., because they flowed across the gap, they can be in contact with each other).

[0074] As described above, a superconducting qubit can comprise a planar capacitor, a Josephson junction, and a trimmable superconducting inductor that couples the Josephson junction to at least one pad of the planar capacitor. In various cases, the trimmable inductor can comprise a first conductive path having a severable and/or weldable superconducting bridge (e.g., superconducting fuse and/or antifuse) and a second conductive path that is in parallel with the first conductive path. When a severable superconducting bridge is implemented, it can be severed by laser heating so as to increase the inductance of the trimmable inductor by a discrete amount corresponding to size, shape, dimensions, layout, and/or materials of the trimmable inductor, thereby decreasing the superconducting qubit's resonant frequency. Similarly, when a weldable superconducting bridge is implemented, it can be welded/fused by laser heating so as to decrease the inductance of the trimmable inductor by a discrete amount corresponding to the size, shape, dimensions, layout, and/or materials of the trimmable inductor, thereby increasing the superconducting qubit's resonant frequency. In this way, both severable and/or weldable superconducting bridges can be implemented in a superconducting qubit's trimmable inductor design so that the superconducting qubit's resonant frequency can be tuned up or down as desired.

[0075] As shown in FIG. 1, in various embodiments, the trimmable inductor 110 can be located externally of the pad 108. In other words, the first conductive path 112 and/or the second conductive path 114 can coil, spiral, and/or meander on the surface of the substrate 102 without being surrounded by the pad 108. In other cases, however, the trimmable inductor 110 can be

located internally of the pad **108**, as shown in FIG. 7.

[0076] FIG. 7 illustrates a block diagram of an example, non-limiting device **700** including an internally-meandering trimmable inductor in accordance with one or more embodiments described herein.

[0077] For purposes of visual clarity, the first conductive path **112** and the second conductive path **114** are not indicated by call-out numerals in FIG. 7 (e.g., otherwise, FIG. 7 would become too cluttered). However, the superconducting bridge **116** is called-out in FIG. 7.

[0078] As shown in FIG. 7, in various embodiments, the pad **108** can be fabricated on the substrate **102** so as to have a portion that is cut-out and/or removed as compared to the design of the pad **108** shown in FIG. 1. As illustrated, in various instances, the trimmable inductor **110** can be formed on the surface of the substrate **102** in this cut-out region of the pad **108**. In such case, the trimmable inductor **110** can be considered as being located internally of the pad **108**. In other words, the coils, spirals, and/or meandering portions of the trimmable inductor **110** (e.g., the first conductive path **112** and the second conductive path **114**) can be positioned on the substrate **102** such that they are surrounded by the pad **108**. In various aspects, fabricating the trimmable inductor **110** such that it is located internally of the pad **108** can help to save space (e.g., chip real estate) on the surface of the substrate **102** (e.g., can reduce a surface area footprint of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108**).

[0079] Those having ordinary skill in the art will appreciate that the circuit diagrams depicted in FIG. 2 can be applicable to the internally-meandering inductor design shown in FIG. 7. That is, regardless of whether the trimmable inductor **110** is located externally to the pad **108** (e.g., as in FIG. 1) or internally to the pad **108** (e.g., as in FIG. 7), the trimmable inductor **110** can nevertheless comprise two conductive paths (e.g., **112** and **114**) arranged in parallel, one of which includes a severable and/or weldable superconducting bridge (e.g., **116**), such that the inductance of the trimmable inductor **110** can be controllably modulated during post-fabrication processing by severing and/or welding the superconducting bridge.

[0080] Although FIG. 7 depicts the cut-out and/or removed region of the pad **108** as being rectangular in shape, those having ordinary skill in the art will appreciate that this is a mere non-limiting example. In various cases, the cut-out and/or removed region of the pad **108** can have any suitable size, shape, and/or dimensions. Furthermore, those having ordinary skill in the art will appreciate that any suitable microfabrication and/or nanofabrication techniques can be implemented to create such a cut-out and/or removed region of the pad **108** (e.g., deposition, etching, angled evaporation, photolithography, patterning).

[0081] Although not shown in figures, those having ordinary skill in the art will appreciate that the trimmable inductor **110** can be designed and/or fabricated so as to be both externally and internally located to the pad **108**. In other words, some portion of the trimmable inductor **110** can be internally located to the pad **108** while some other portion of the trimmable inductor **110** can be externally located to the pad **108**. Indeed, in various embodiments, the trimmable inductor **110** can have any suitable layout on the surface of the substrate **102**.

[0082] Thus far, the above discussion mainly describes embodiments of a trimmable inductor that comprises two parallel conductive paths, one path of which includes a severable and/or weldable superconducting bridge. In various aspects, however, a trimmable inductor can comprise any suitable number of parallel conductive paths and any suitable number of severable and/or weldable superconducting bridges. Such embodiments are more fully described with respect to FIG. 8.

[0083] FIG. 8 illustrates a block diagram of an example, non-limiting device **800** including a stepwise-trimmable inductor in accordance with one or more embodiments described herein.

[0084] As shown in FIG. 8, the substrate **102**, the Josephson junction **104**, the pad **106**, and the pad **108** can be as described above, and the trimmable inductor **110** can be internally-located to the pad **108**, as described with respect to FIG. 7. However, as shown, the trimmable inductor **110** can comprise more than just the superconducting bridge **116**. For instance, in the non-limiting example

shown, the trimmable inductor **110** can comprise three other superconducting bridges **802**, **804**, and **806**, each of which can be severable and/or weldable. Accordingly, as shown in FIG. **8**, the trimmable inductor **110** can provide five parallel conductive paths between the Josephson junction **104** and the pad **108**: a first conductive path that includes the superconducting bridge **116**, a second conductive path that includes the superconducting bridge **802**, a third conductive path that includes the superconducting bridge **804**, a fourth conductive path that includes the superconducting bridge **806**, and a fifth conductive path that includes none of the superconducting bridges **116** or **802-806**. [0085] As described above, when the trimmable inductor **110** has only two conductive paths, one of which includes the superconducting bridge **116**, the trimmable inductor **110** can be modulated during post-fabrication processing once by severing and/or welding the superconducting bridge **116**.

[0086] In contrast, in the non-limiting example shown in FIG. **8**, the trimmable inductor **110** can be modulated during post-fabrication processing four times by individually severing and/or welding the four superconducting bridges **116** and/or **802-806**. In other words, a first overall/equivalent inductance value of the trimmable inductor **110** can be achieved by severing/welding none of the superconducting bridges **116** and **802-806**; a second overall/equivalent inductance value of the trimmable inductor **110** can be achieved by severing/welding the superconducting bridge **116**; a third overall/equivalent inductance value of the trimmable inductor **110** can be achieved by severing/welding the superconducting bridge **116** and the superconducting bridge **802**; a fourth overall/equivalent inductance value of the trimmable inductor **110** can be achieved by severing/welding the superconducting bridge **116**, the superconducting bridge **802**, and the superconducting bridge **804**; and a fifth overall/equivalent inductance value of the trimmable inductor **110** can be achieved by severing/welding all of the superconducting bridges **116** and **802-806**. For example, if it is desired to increase the inductance of the trimmable inductor **110**, the superconducting bridge **116** can be severed. Then, if it is desired to further decrease the inductance of the trimmable inductor **110**, the superconducting bridge **802** can be severed (e.g., after the superconducting bridge **116** was severed). Accordingly, in various cases, the superconducting bridges **116** and/or **802-806** can be progressively trimmed (e.g., severed and/or welded, as applicable) in order to alter the inductance of the trimmable inductor **110** as desired. In other words, the trimmable inductor **110**, when structured as shown in FIG. **8**, can be tuned during post-fabrication processing to one of a range of at least five discrete inductance values. In some cases, more than five discrete inductance values can be achieved (e.g., by severing and/or welding different combinations/permutations of the superconducting bridges **116** and/or **802-806**).

[0087] In general, the trimmable inductor **110** can, in various embodiments, comprise n conductive paths for any suitable positive integer n , where the n conductive paths are in parallel with each other, and the trimmable inductor **110** can accordingly include $n-1$ superconducting bridges (e.g., no bridge in one of the conductive paths, and one bridge in each of the remaining conductive paths). In such case, the overall/equivalent inductance of the trimmable inductor **110** can be controllably tuned to at least n discrete values by controllably severing and/or welding the $n-1$ superconducting bridges. Thus, finer and/or more granular changes in inductance of the trimmable inductor **110** can be achieved when more superconducting bridges are implemented as compared to when fewer superconducting bridge are implemented, which can mean that finer and/or more granular changes in resonant frequency can be achieved.

[0088] FIG. **9** illustrates an example, non-limiting circuit diagram **900** of a stepwise-trimmable inductor in accordance with one or more embodiments described herein. That is, the circuit diagram **900** can represent the electrical characteristics of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108** shown in FIG. **8**, either prior to severing of any of the superconducting bridges **116** and **802-806** and/or after welding all of the superconducting bridges **116** and **802-806**.

[0089] As shown in the circuit diagram **900**, the Josephson junction **104** can be shunted by the

capacitance **206**, which can be the capacitance exhibited by the planar capacitor formed by the pad **106** and the pad **108**. Also as shown in the circuit diagram **900**, an equivalent inductance **902** can be coupled in series between the Josephson junction **104** and the capacitance **206**. In various aspects, the equivalent inductance **902** can be the overall and/or equivalent inductance exhibited by the trimmable inductor **110** when all of the superconducting bridges **116** and **802-806** are in electrically-closed states (e.g., such as prior to severing and/or after welding). As shown, the equivalent inductance **902** can comprise five sub-inductances that are coupled together in parallel: sub-inductances **904-912**. In various instances, the sub-inductance **904** can be the inductance exhibited by the conductive path that includes the superconducting bridge **116** when the superconducting bridge **116** is in an electrically-closed state (e.g., unsevered and/or welded); the sub-inductance **906** can be the inductance exhibited by the conductive path that includes the superconducting bridge **802** when the superconducting bridge **802** is in an electrically-closed state (e.g., unsevered and/or welded); the sub-inductance **908** can be the inductance exhibited by the conductive path that includes the superconducting bridge **804** when the superconducting bridge **804** is in an electrically-closed state (e.g., unsevered and/or welded); the sub-inductance **910** can be the inductance exhibited by the conductive path that includes the superconducting bridge **806** when the superconducting bridge **806** is in an electrically-closed state (e.g., unsevered and/or welded); and the sub-inductance **912** can be the inductance exhibited by the conductive path that includes none of the superconducting bridges **116** and **802-806**. Because the sub-inductances **904-912** are in parallel with each other, the equivalent inductance **902** can be equal to the reciprocal of the sum of the reciprocals of the sub-inductances **904-912**. Accordingly, the equivalent inductance **902** can be lesser than each of the sub-inductances **904-912**. Thus, as described herein, the equivalent inductance **902** can be controllably increased in stepwise-fashion by progressively severing the superconducting bridges **116** and **802-806**, where such severing would progressively eliminate respective ones of the sub-inductances **904-912**.

[0090] If the superconducting bridges **116** and **802-806** are severable, those having ordinary skill in the art will appreciate that the circuit diagram **900** can represent the trimmable inductor **110** shown in FIG. **8** before any of the superconducting bridges **116** and **802-806** have been severed. On the other hand, if the superconducting bridges **116** and **802-806** are weldable, those having ordinary skill in the art will appreciate that the circuit diagram **900** can represent the trimmable inductor **110** shown in FIG. **8** after all of the superconducting bridges **116** and **802-806** have been welded. In any case, the circuit diagram **900** illustrates that the overall and/or equivalent inductance **902** exhibited by the trimmable inductor **110** can be stepwise-controlled by severing and/or welding the superconducting bridges **116** and **802-806** one at a time. Accordingly, the resonant frequency of the transmon qubit formed by the Josephson junction **104**, the pad **106**, and the pad **108** can be commensurately stepwise-controlled.

[0091] Although the herein discussion mainly describes embodiments where all of the superconducting bridges **116** and **802-806** are severable or where all of the superconducting bridges **116** and **802-806** are weldable, this is a mere non-limiting example. Those having ordinary skill in the art will appreciate that when multiple superconducting bridges are implemented, they can be any suitable combination of severable and/or weldable (e.g., some of the superconducting bridges can be severable while others can be weldable).

[0092] FIG. **10** illustrates example, non-limiting simulation results **1000** showing how one or more embodiments described herein influence resonant frequencies of superconducting qubits. More specifically, the inventors of various embodiments of the invention used computer-aided design software to simulate how the resonant frequency of a transmon qubit would change based on severing the superconducting bridges (e.g., superconducting fuses) of a stepwise-trimmable inductor as described herein. These results indicate that the inductance of a stepwise-trimmable inductor can be finely controlled by progressively trimming severable superconducting bridges of the stepwise-trimmable inductor.

[0093] Those having ordinary skill in the art will appreciate that the results shown in FIG. 10 are merely non-limiting example results. In practice, the magnitudes of the discrete changes in inductance of the trimmable inductor **110** can depend upon the size, shape, dimensions, layout, and/or materials of the trimmable inductor **110**. In other words, the total tunable range of a superconducting qubit's resonant frequency can depend upon the size, shape, dimensions, layout, and/or materials of the trimmable inductor **110** as well as the number of superconducting bridges of the trimmable inductor **110**. Thus, in various cases, the trimmable inductor **110** can be fabricated to have any suitable size, shape, dimensions, layout, and/or materials as well as any suitable number of superconducting bridges (e.g., any suitable number of conductive paths), so as to span a desired/target frequency range with a desired/target tuning resolution.

[0094] In various aspects, those having ordinary skill in the art will appreciate that analogous results as those shown in FIG. 10 can be obtained for stepwise-trimmable inductors that comprise weldable superconducting bridges (e.g., antifuses).

[0095] FIGS. 11-19b illustrate block diagrams of an example, non-limiting stepwise-trimmable inductor including diffusion-based antifuses in accordance with one or more embodiments described herein. In various aspects, as illustrated in FIG. 11, for example, a planar capacitor pad **1104** can be fabricated (e.g., via any suitable microfabrication and/or nanofabrication technique) on a substrate **1102** (e.g., silicon substrate). In various instances, as shown, the planar capacitor pad **1104** can be fabricated so as to have a cut-out region. In various cases, a spiraled superconducting wire **1106** can be fabricated (e.g., via any suitable microfabrication and/or nanofabrication technique) on the substrate **1102** within the cut-out region of the planar capacitor pad **1104**. In various aspects, the planar capacitor pad **1104** can have any suitable size, shape, and/or dimensions, and can be comprised of any suitable superconducting material (e.g., niobium). Similarly, in various instances, the spiraled superconducting wire **1106** can have any suitable size, shape, and/or dimensions, and can be comprised of any suitable superconducting material (e.g., niobium). As explained below, the spiraled superconducting wire **1106** can be used to create a stepwise-trimmable inductor.

[0096] FIG. 12 illustrates a cross-sectional view **1200** of the quantum structure shown in FIG. 11, where the cross-sectional view **1200** is taken along axis **1108**. As shown in the non-limiting example of FIG. 11, the spiraled superconducting wire **1106** can, in various cases, intersect with the axis **1108** in four locations. In various aspects, these four locations are labeled in FIG. 12: location A, location B, location C, and location D. In various other cases, however, the spiraled superconducting wire **1106** can be structured so as to intersect with the axis **1108** any suitable number of times (e.g., fewer than and/or more than four times).

[0097] As shown in FIG. 13, in various embodiments, a dielectric layer **1302** can be deposited over some portions of the spiraled superconducting wire **1106**. In various cases, the dielectric layer **1302** can have any suitable size, shape, dimensions, and/or can be comprised of any suitable dielectric material (e.g., poly silicon). In various cases, the dielectric layer **1302** can be fabricated via any suitable microfabrication and/or nanofabrication technique. In various instances, the dielectric layer **1302** can be deposited along the axis **1108** such that the dielectric layer **1302** covers all but one of the four locations at which the spiraled superconducting wire **1106** intersects the axis **1108**.

[0098] FIG. 14 illustrates a cross-sectional view **1400** of the quantum structure shown in FIG. 13, where the cross-sectional view **1400** is taken along axis **1108**. In the non-limiting example shown in FIGS. 13-14, the location A, the location B, and the location D are covered by the dielectric layer **1302**, while the location C is not covered by the dielectric layer **1302**. This is a mere non-limiting example. In various other cases, the location C can be covered by the dielectric layer **1302**, and any other location at which the spiraled superconducting wire **1106** intersects the axis **1108** can be left uncovered by the dielectric layer **1302**.

[0099] As shown in FIG. 15, in various embodiments, a top superconducting layer **1502** can be deposited over the dielectric layer **1302** and/or over the portion of the spiraled superconducting

wire **1106** that intersects the axis **1108** but that is not covered by the dielectric layer **1302**. In various cases, the top superconducting layer **1502** can have any suitable size, shape, dimensions, and/or can be comprised of any suitable superconducting material (e.g., aluminum). In various cases, the top superconducting layer **1502** can be fabricated via any suitable microfabrication and/or nanofabrication technique. As shown in the non-limiting example of FIG. **15**, in various instances, the top superconducting layer **1502** can be deposited along the axis **1108** such that the top superconducting layer **1502** covers the dielectric layer **1302** as well as the previously-uncovered portion of the spiraled superconducting wire **1106** that intersects the axis **1108**.

[0100] FIG. **16** illustrates a cross-sectional view **1600** of the quantum structure shown in FIG. **15**, where the cross-sectional view **1600** is taken along axis **1108**. As shown, the top superconducting layer **1502** can be deposited over location A, location B, location C, and location D. Accordingly, this can cause the top superconducting layer **1502** to be in direct contact with the spiraled superconducting wire **1106** at location C, and can cause the top superconducting layer **1502** to be not in direct contact with the spiraled superconducting wire **1106** at location A, location B, and location D. In other words, as shown in FIGS. **15-16**, there exists a single conductive path (e.g., through location C) from the top superconducting layer **1502** to the spiraled superconducting wire **1106**, and ultimately to the planar capacitor pad **1104**.

[0101] In various cases, the structure collectively formed by the spiraled superconducting wire **1106**, the dielectric layer **1302**, and the top superconducting layer **1502** can be considered as a stepwise-trimmable inductor that includes three diffusion-based superconducting antifuses. Specifically, the sandwiched structures (e.g., **1502** on top of **1302** on top of **1106**) at location A, location B, and location D can function as diffused-based superconducting antifuses. This is explained with respect to FIGS. **17a-19b**.

[0102] As shown in FIG. **17a**, a laser **1702** can be aimed at the location B. In various cases, the laser **1702** can cause the sandwiched structure at the location B to heat up. When the location B heats to a sufficiently high temperature, some of the top superconducting layer **1502** can diffuse into the dielectric layer **1302** at the location B. For example, aluminum can diffuse into silicon at temperatures greater than or equal to 500 degrees Celsius. Accordingly, if the top superconducting layer **1502** is comprised of aluminum and if the dielectric layer **1302** is comprised of silicon, the laser **1702** can result in the formation of a diffused portion **1704** in the dielectric layer **1302** at the location B, as shown in FIG. **17b**. This diffused portion **1704** can facilitate the flow of electric current. In other words, because of the diffused portion **1704**, the top superconducting layer **1502** and the spiraled superconducting wire **1106** can be in electrical contact at the location B. In still other words, the laser **1702** can be considered as causing the location B to switch from a non-superconducting state (e.g., an electrically-open state) to a superconducting state (e.g., an electrically-closed state).

[0103] Now, there can be two conductive paths in parallel from the top superconducting layer **1502** to the spiraled superconducting wire **1106** (and thus to the planar capacitor pad **1104**): a first path through the location C and a second path through the location B. As explained above, this can cause an inductance associated with the stepwise-trimmable inductor (e.g., collectively **1106**, **1302**, and **1502**) to be decreased (e.g., adding inductors in parallel decreases overall/equivalent inductance) as compared to the inductance of the stepwise-trimmable inductor shown in FIGS. **15-17**.

[0104] FIGS. **18a-18b** are analogous to FIGS. **17a-17b**, and they show how the inductance of the stepwise-trimmable inductor (e.g., collectively **1106**, **1302**, **1502**) can be further decreased by a discrete amount via aiming a laser **1802** at the location D. Just as explained above, the laser **1802** can result in the formation of a diffused portion **1804** at the location D, which can cause the top superconducting layer **1502** and the spiraled superconducting wire **1106** to be in electrical contact at the location D. Now, there can be three conductive paths in parallel from the top superconducting layer **1502** to the spiraled superconducting wire **1106** (and thus to the planar capacitor pad **1104**): a

first path through the location C, a second path through the location B, and a third path through the location D. As explained above, this can cause an inductance associated with the stepwise-trimmable inductor (e.g., collectively **1106**, **1302**, and **1502**) to be decreased as compared to the inductance of the stepwise-trimmable capacitor as shown in FIG. **17b**.

[0105] FIGS. **19a-19b** are analogous to FIGS. **18a-18b**, and they show how the inductance of the stepwise-trimmable inductor (e.g., collectively **1106**, **1302**, **1502**) can be further decreased by a discrete amount via aiming a laser **1902** at the location A. Just as explained above, the laser **1902** can result in the formation of a diffused portion **1904** at the location A, which can cause the top superconducting layer **1502** and the spiraled superconducting wire **1106** to be in electrical contact at the location A. Now, there can be four conductive paths in parallel from the top superconducting layer **1502** to the spiraled superconducting wire **1106** (and thus to the planar capacitor pad **1104**): a first path through the location C, a second path through the location B, a third path through the location D, and a fourth path through the location A. As explained above, this can cause an inductance associated with the stepwise-trimmable inductor (e.g., collectively **1106**, **1302**, and **1502**) to be even further decreased as compared to the inductance of the stepwise-trimmable inductor as shown in FIG. **18b**.

[0106] Although the herein disclosure discusses various example and non-limiting embodiments of the invention as applied to transmon qubits (e.g., a Josephson junction shunted by a planar capacitor comprising two pads), various embodiments of the invention can be applied to any suitable superconducting qubit whose construction includes capacitive pads and/or Josephson junctions. In other words, a superconducting qubit which can be tuned according to various embodiments of the invention can include one or more Josephson junctions and one or more capacitor pads arranged in any suitable fashion (e.g., regardless of the particular number, arrangement, and/or construction of the Josephson junctions and the capacitor pads of a given superconducting qubit, a Josephson junction can be coupled to a capacitor pad and/or to another Josephson junction via a trimmable inductor as described herein, where such trimmable inductor can be easily altered in order to facilitate resonant frequency tuning of the superconducting qubit).

[0107] Although the herein disclosure mainly discusses embodiments in which only one trimmable inductor is added to a superconducting qubit, it should be appreciated that this is a mere non-limiting example. In various aspects, any suitable number of trimmable inductors can be incorporated into a superconducting qubit.

[0108] In superconducting quantum computing systems, systems and/or techniques that can facilitate post-fabrication resonant frequency tuning can be desirable. Various embodiments of the invention can address this problem. In some embodiments, a superconducting qubit can include a planar capacitor and a Josephson junction. In various cases, a trimmable inductor can provide one or more conductive paths between the Josephson junction and a pad of the planar capacitor. In other embodiments, a superconducting qubit can include two Josephson junctions. In various cases, a trimmable inductor can provide one or more conductive paths between the two Josephson junctions (e.g., the trimmable inductor can chain together a plurality of Josephson junctions). In any case, the trimmable inductor can comprise at least a first conductive path that includes a severable and/or weldable superconducting bridge and at least a second conductive path that is in parallel with the first conductive path. When the superconducting bridge is severed and/or welded (as applicable), an inductance of the trimmable inductor can be altered, and the resonant frequency of the superconducting qubit can correspondingly change.

[0109] In various aspects, embodiments of the invention can enable resonant frequency tuning in post-fabrication environments without negatively/adversely affecting the performance/efficacy of the superconducting qubits (e.g., without requiring debonding and/or de-packaging, without deteriorating coherence times).

[0110] In various embodiments, a trimmable inductor as described herein can be fabricated from any suitable superconducting materials that have sufficiently high kinetic inductances. In various

cases, a superconducting material can be considered to have a sufficiently high kinetic inductance if the ratio of the kinetic inductance to the geometric inductance of that superconducting material is greater than 1. In various cases, some non-limiting limiting examples of such a superconducting material can include niobium nitride and/or niobium titanium nitride. In various instances, when the conductive paths of a trimmable inductor are constructed from superconducting materials having sufficiently high kinetic inductances, severing and/or welding of superconducting bridges of the trimmable inductor can cause greater changes in inductance (and thus greater changes in resonant frequency) as compared to a comparably-sized trimmable inductor whose conductive paths are constructed from superconducting materials having low kinetic inductances. Conversely, when the conductive paths of a trimmable inductor are constructed from superconducting materials having sufficiently high kinetic inductances, severing and/or welding of superconducting bridges of the trimmable inductor can cause comparable changes in inductance (and thus comparable changes in resonant frequency) as compared to a larger (e.g., more coiled, more spiraled, more meandering) trimmable inductor whose conductive paths are constructed from superconducting materials having low kinetic inductances.

[0111] In various embodiments, high inductances can also be achieved by having a series array of Josephson junctions. In such cases, the meandered, coiled, and/or spiraled wires depicted in the figures can be replaced by (and/or in some cases supplemented with) a chain of Josephson junctions, thereby creating a linear superinductance.

[0112] FIGS. **20-23** illustrate flow diagrams of example, non-limiting manufacturing and/or fabrication processes **2000-2300** that can facilitate trimmable inductors for qubit frequency tuning in accordance with one or more embodiments described herein.

[0113] First, consider the manufacturing and/or fabrication process **2000**. In various embodiments, act **2002** can include fabricating a Josephson junction (e.g., **104**) shunted by a capacitor (e.g., collectively **106** and **108**).

[0114] In various aspects, act **2004** can include fabricating a trimmable inductor (e.g., **110**) that couples the Josephson junction to a pad (e.g., **108**) of the capacitor. In various instances, the trimmable inductor can comprise a first conductive path (e.g., **112**) that includes a severable superconducting bridge (e.g., **116**) and a second conductive path (e.g., **114**) that is in parallel with the first conductive path. In various cases, severing the severable superconducting bridge can increase an inductance of the trimmable inductor and can decrease a resonant frequency of a qubit formed by the Josephson junction and the capacitor.

[0115] Next, consider the manufacturing and/or fabrication process **2100**. In various embodiments, act **2102** can include fabricating a Josephson junction (e.g., **104**) shunted by a capacitor (e.g., collectively **106** and **108**).

[0116] In various aspects, act **2104** can include fabricating a trimmable inductor (e.g., **110**) that couples the Josephson junction to a pad (e.g., **108**) of the capacitor. In various instances, the trimmable inductor can comprise a first conductive path (e.g., **112**) that includes a weldable superconducting bridge (e.g., **116**) and a second conductive path (e.g., **114**) that is in parallel with the first conductive path. In various cases, welding the weldable superconducting bridge can decrease an inductance of the trimmable inductor and can increase a resonant frequency of a qubit formed by the Josephson junction and the capacitor.

[0117] Now, consider the manufacturing and/or fabrication process **2200**. In various embodiments, act **2202** can include fabricating a qubit device (e.g., collectively **104**, **106**, and **108**) that includes a Josephson junction (e.g., **104**).

[0118] In various aspects, act **2204** can include fabricating a stepwise-trimmable inductor (e.g., **110** as shown in FIG. **8**) that couples the Josephson junction to a planar capacitor pad (e.g., **108**) of the qubit device or to another Josephson junction of the qubit device. In various instances, the stepwise-trimmable inductor can comprise a first conductive path and a plurality of second conductive paths (e.g., as shown/explained with respect to FIGS. **8-9**) that are in parallel with the

first conductive path. In various aspects, the plurality of second conductive paths can respectively include a plurality of superconducting fuses (e.g., **116, 902, 804, 806**). In various cases, severing any of the plurality of superconducting fuses can increase an inductance of the stepwise-trimmable inductor and can decrease a resonant frequency of the qubit device.

[0119] Finally, consider the manufacturing and/or fabrication process **2300**. In various embodiments, act **2302** can include fabricating a qubit device (e.g., collectively **104, 106, and 108**) that includes a Josephson junction (e.g., **104**).

[0120] In various aspects, act **2304** can include fabricating a stepwise-trimmable inductor (e.g., **110** as shown in FIG. **8**) that couples the Josephson junction to a planar capacitor pad (e.g., **108**) of the qubit device or to another Josephson junction of the qubit device. In various instances, the stepwise-trimmable inductor can comprise a first conductive path and a plurality of second conductive paths (e.g., as shown/explained with respect to FIGS. **8-9**) that are in parallel with the first conductive path. In various aspects, the plurality of second conductive paths can respectively include a plurality of superconducting antifuses (e.g., **116, 802, 804, 806**; and/or location A, location B, and location D of FIG. **16**). In various cases, welding any of the plurality of superconducting antifuses can decrease an inductance of the stepwise-trimmable inductor and can increase a resonant frequency of the qubit device.

[0121] In order to provide additional context for various embodiments described herein, FIG. **24** and the following discussion are intended to provide a brief, general description of a suitable computing environment **2400** in which the various embodiments of the embodiment described herein can be implemented. While the embodiments have been described above in the general context of computer-executable instructions that can run on one or more computers, those skilled in the art will recognize that the embodiments can be also implemented in combination with other program modules and/or as a combination of hardware and software.

[0122] Generally, program modules include routines, programs, components, data structures, etc., that perform particular tasks or implement particular abstract data types. Moreover, those skilled in the art will appreciate that the inventive methods can be practiced with other computer system configurations, including single-processor or multiprocessor computer systems, minicomputers, mainframe computers, Internet of Things (IoT) devices, distributed computing systems, as well as personal computers, hand-held computing devices, microprocessor-based or programmable consumer electronics, and the like, each of which can be operatively coupled to one or more associated devices.

[0123] The illustrated embodiments of the embodiments herein can be also practiced in distributed computing environments where certain tasks are performed by remote processing devices that are linked through a communications network. In a distributed computing environment, program modules can be located in both local and remote memory storage devices.

[0124] Computing devices typically include a variety of media, which can include computer-readable storage media, machine-readable storage media, and/or communications media, which two terms are used herein differently from one another as follows. Computer-readable storage media or machine-readable storage media can be any available storage media that can be accessed by the computer and includes both volatile and nonvolatile media, removable and non-removable media. By way of example, and not limitation, computer-readable storage media or machine-readable storage media can be implemented in connection with any method or technology for storage of information such as computer-readable or machine-readable instructions, program modules, structured data or unstructured data.

[0125] Computer-readable storage media can include, but are not limited to, random access memory (RAM), read only memory (ROM), electrically erasable programmable read only memory (EEPROM), flash memory or other memory technology, compact disk read only memory (CD ROM), digital versatile disk (DVD), Blu-ray disc (BD) or other optical disk storage, magnetic cassettes, magnetic tape, magnetic disk storage or other magnetic storage devices, solid state drives

or other solid state storage devices, or other tangible and/or non-transitory media which can be used to store desired information. In this regard, the terms “tangible” or “non-transitory” herein as applied to storage, memory or computer-readable media, are to be understood to exclude only propagating transitory signals per se as modifiers and do not relinquish rights to all standard storage, memory or computer-readable media that are not only propagating transitory signals per se.

[0126] Computer-readable storage media can be accessed by one or more local or remote computing devices, e.g., via access requests, queries or other data retrieval protocols, for a variety of operations with respect to the information stored by the medium.

[0127] Communications media typically embody computer-readable instructions, data structures, program modules or other structured or unstructured data in a data signal such as a modulated data signal, e.g., a carrier wave or other transport mechanism, and includes any information delivery or transport media. The term “modulated data signal” or signals refers to a signal that has one or more of its characteristics set or changed in such a manner as to encode information in one or more signals. By way of example, and not limitation, communication media include wired media, such as a wired network or direct-wired connection, and wireless media such as acoustic, RF, infrared and other wireless media.

[0128] With reference again to FIG. 24, the example environment **2400** for implementing various embodiments of the aspects described herein includes a computer **2402**, the computer **2402** including a processing unit **2404**, a system memory **2406** and a system bus **2408**. The system bus **2408** couples system components including, but not limited to, the system memory **2406** to the processing unit **2404**. The processing unit **2404** can be any of various commercially available processors. Dual microprocessors and other multi processor architectures can also be employed as the processing unit **2404**.

[0129] The system bus **2408** can be any of several types of bus structure that can further interconnect to a memory bus (with or without a memory controller), a peripheral bus, and a local bus using any of a variety of commercially available bus architectures. The system memory **2406** includes ROM **2410** and RAM **2412**. A basic input/output system (BIOS) can be stored in a non-volatile memory such as ROM, erasable programmable read only memory (EPROM), EEPROM, which BIOS contains the basic routines that help to transfer information between elements within the computer **2402**, such as during startup. The RAM **2412** can also include a high-speed RAM such as static RAM for caching data.

[0130] The computer **2402** further includes an internal hard disk drive (HDD) **2414** (e.g., EIDE, SATA), one or more external storage devices **2416** (e.g., a magnetic floppy disk drive (FDD) **2416**, a memory stick or flash drive reader, a memory card reader, etc.) and a drive **2420**, e.g., such as a solid state drive, an optical disk drive, which can read or write from a disk **2422**, such as a CD-ROM disc, a DVD, a BD, etc. Alternatively, where a solid state drive is involved, disk **2422** would not be included, unless separate. While the internal HDD **2414** is illustrated as located within the computer **2402**, the internal HDD **2414** can also be configured for external use in a suitable chassis (not shown). Additionally, while not shown in environment **2400**, a solid state drive (SSD) could be used in addition to, or in place of, an HDD **2414**. The HDD **2414**, external storage device(s) **2416** and drive **2420** can be connected to the system bus **2408** by an HDD interface **2424**, an external storage interface **2426** and a drive interface **2428**, respectively. The interface **2424** for external drive implementations can include at least one or both of Universal Serial Bus (USB) and Institute of Electrical and Electronics Engineers (IEEE) 1394 interface technologies. Other external drive connection technologies are within contemplation of the embodiments described herein.

[0131] The drives and their associated computer-readable storage media provide nonvolatile storage of data, data structures, computer-executable instructions, and so forth. For the computer **2402**, the drives and storage media accommodate the storage of any data in a suitable digital format. Although the description of computer-readable storage media above refers to respective

types of storage devices, it should be appreciated by those skilled in the art that other types of storage media which are readable by a computer, whether presently existing or developed in the future, could also be used in the example operating environment, and further, that any such storage media can contain computer-executable instructions for performing the methods described herein.

[0132] A number of program modules can be stored in the drives and RAM **2412**, including an operating system **2430**, one or more application programs **2432**, other program modules **2434** and program data **2436**. All or portions of the operating system, applications, modules, and/or data can also be cached in the RAM **2412**. The systems and methods described herein can be implemented utilizing various commercially available operating systems or combinations of operating systems.

[0133] Computer **2402** can optionally comprise emulation technologies. For example, a hypervisor (not shown) or other intermediary can emulate a hardware environment for operating system **2430**, and the emulated hardware can optionally be different from the hardware illustrated in FIG. **24**. In such an embodiment, operating system **2430** can comprise one virtual machine (VM) of multiple VMs hosted at computer **2402**. Furthermore, operating system **2430** can provide runtime environments, such as the Java runtime environment or the .NET framework, for applications **2432**. Runtime environments are consistent execution environments that allow applications **2432** to run on any operating system that includes the runtime environment. Similarly, operating system **2430** can support containers, and applications **2432** can be in the form of containers, which are lightweight, standalone, executable packages of software that include, e.g., code, runtime, system tools, system libraries and settings for an application.

[0134] Further, computer **2402** can be enable with a security module, such as a trusted processing module (TPM). For instance with a TPM, boot components hash next in time boot components, and wait for a match of results to secured values, before loading a next boot component. This process can take place at any layer in the code execution stack of computer **2402**, e.g., applied at the application execution level or at the operating system (OS) kernel level, thereby enabling security at any level of code execution.

[0135] A user can enter commands and information into the computer **2402** through one or more wired/wireless input devices, e.g., a keyboard **2438**, a touch screen **2440**, and a pointing device, such as a mouse **2442**. Other input devices (not shown) can include a microphone, an infrared (IR) remote control, a radio frequency (RF) remote control, or other remote control, a joystick, a virtual reality controller and/or virtual reality headset, a game pad, a stylus pen, an image input device, e.g., camera(s), a gesture sensor input device, a vision movement sensor input device, an emotion or facial detection device, a biometric input device, e.g., fingerprint or iris scanner, or the like. These and other input devices are often connected to the processing unit **2404** through an input device interface **2444** that can be coupled to the system bus **2408**, but can be connected by other interfaces, such as a parallel port, an IEEE 1394 serial port, a game port, a USB port, an IR interface, a BLUETOOTH® interface, etc.

[0136] A monitor **2446** or other type of display device can be also connected to the system bus **2408** via an interface, such as a video adapter **2448**. In addition to the monitor **2446**, a computer typically includes other peripheral output devices (not shown), such as speakers, printers, etc.

[0137] The computer **2402** can operate in a networked environment using logical connections via wired and/or wireless communications to one or more remote computers, such as a remote computer(s) **2450**. The remote computer(s) **2450** can be a workstation, a server computer, a router, a personal computer, portable computer, microprocessor-based entertainment appliance, a peer device or other common network node, and typically includes many or all of the elements described relative to the computer **2402**, although, for purposes of brevity, only a memory/storage device **2452** is illustrated. The logical connections depicted include wired/wireless connectivity to a local area network (LAN) **2454** and/or larger networks, e.g., a wide area network (WAN) **2456**. Such LAN and WAN networking environments are commonplace in offices and companies, and facilitate enterprise-wide computer networks, such as intranets, all of which can connect to a global

communications network, e.g., the Internet.

[0138] When used in a LAN networking environment, the computer **2402** can be connected to the local network **2454** through a wired and/or wireless communication network interface or adapter **2458**. The adapter **2458** can facilitate wired or wireless communication to the LAN **2454**, which can also include a wireless access point (AP) disposed thereon for communicating with the adapter **2458** in a wireless mode.

[0139] When used in a WAN networking environment, the computer **2402** can include a modem **2460** or can be connected to a communications server on the WAN **2456** via other means for establishing communications over the WAN **2456**, such as by way of the Internet. The modem **2460**, which can be internal or external and a wired or wireless device, can be connected to the system bus **2408** via the input device interface **2444**. In a networked environment, program modules depicted relative to the computer **2402** or portions thereof, can be stored in the remote memory/storage device **2452**. It will be appreciated that the network connections shown are example and other means of establishing a communications link between the computers can be used.

[0140] When used in either a LAN or WAN networking environment, the computer **2402** can access cloud storage systems or other network-based storage systems in addition to, or in place of, external storage devices **2416** as described above, such as but not limited to a network virtual machine providing one or more aspects of storage or processing of information. Generally, a connection between the computer **2402** and a cloud storage system can be established over a LAN **2454** or WAN **2456** e.g., by the adapter **2458** or modem **2460**, respectively. Upon connecting the computer **2402** to an associated cloud storage system, the external storage interface **2426** can, with the aid of the adapter **2458** and/or modem **2460**, manage storage provided by the cloud storage system as it would other types of external storage. For instance, the external storage interface **2426** can be configured to provide access to cloud storage sources as if those sources were physically connected to the computer **2402**.

[0141] The computer **2402** can be operable to communicate with any wireless devices or entities operatively disposed in wireless communication, e.g., a printer, scanner, desktop and/or portable computer, portable data assistant, communications satellite, any piece of equipment or location associated with a wirelessly detectable tag (e.g., a kiosk, news stand, store shelf, etc.), and telephone. This can include Wireless Fidelity (Wi-Fi) and BLUETOOTH® wireless technologies. Thus, the communication can be a predefined structure as with a conventional network or simply an ad hoc communication between at least two devices.

[0142] The present invention may be a system, a method, an apparatus and/or a computer program product at any possible technical detail level of integration. The computer program product can include a computer readable storage medium (or media) having computer readable program instructions thereon for causing a processor to carry out aspects of the present invention. The computer readable storage medium can be a tangible device that can retain and store instructions for use by an instruction execution device. The computer readable storage medium can be, for example, but is not limited to, an electronic storage device, a magnetic storage device, an optical storage device, an electromagnetic storage device, a semiconductor storage device, or any suitable combination of the foregoing. A non-exhaustive list of more specific examples of the computer readable storage medium can also include the following: a portable computer diskette, a hard disk, a random access memory (RAM), a read-only memory (ROM), an erasable programmable read-only memory (EPROM or Flash memory), a static random access memory (SRAM), a portable compact disc read-only memory (CD-ROM), a digital versatile disk (DVD), a memory stick, a floppy disk, a mechanically encoded device such as punch-cards or raised structures in a groove having instructions recorded thereon, and any suitable combination of the foregoing. A computer readable storage medium, as used herein, is not to be construed as being transitory signals per se, such as radio waves or other freely propagating electromagnetic waves, electromagnetic waves

propagating through a waveguide or other transmission media (e.g., light pulses passing through a fiber-optic cable), or electrical signals transmitted through a wire.

[0143] Computer readable program instructions described herein can be downloaded to respective computing/processing devices from a computer readable storage medium or to an external computer or external storage device via a network, for example, the Internet, a local area network, a wide area network and/or a wireless network. The network can comprise copper transmission cables, optical transmission fibers, wireless transmission, routers, firewalls, switches, gateway computers and/or edge servers. A network adaptor card or network interface in each computing/processing device receives computer readable program instructions from the network and forwards the computer readable program instructions for storage in a computer readable storage medium within the respective computing/processing device. Computer readable program instructions for carrying out operations of the present invention can be assembler instructions, instruction-set-architecture (ISA) instructions, machine instructions, machine dependent instructions, microcode, firmware instructions, state-setting data, configuration data for integrated circuitry, or either source code or object code written in any combination of one or more programming languages, including an object oriented programming language such as Smalltalk, C++, or the like, and procedural programming languages, such as the “C” programming language or similar programming languages. The computer readable program instructions can execute entirely on the user's computer, partly on the user's computer, as a stand-alone software package, partly on the user's computer and partly on a remote computer or entirely on the remote computer or server. In the latter scenario, the remote computer can be connected to the user's computer through any type of network, including a local area network (LAN) or a wide area network (WAN), or the connection can be made to an external computer (for example, through the Internet using an Internet Service Provider). In some embodiments, electronic circuitry including, for example, programmable logic circuitry, field-programmable gate arrays (FPGA), or programmable logic arrays (PLA) can execute the computer readable program instructions by utilizing state information of the computer readable program instructions to personalize the electronic circuitry, in order to perform aspects of the present invention.

[0144] Aspects of the present invention are described herein with reference to flowchart illustrations and/or block diagrams of methods, apparatus (systems), and computer program products according to embodiments of the invention. It will be understood that each block of the flowchart illustrations and/or block diagrams, and combinations of blocks in the flowchart illustrations and/or block diagrams, can be implemented by computer readable program instructions. These computer readable program instructions can be provided to a processor of a general purpose computer, special purpose computer, or other programmable data processing apparatus to produce a machine, such that the instructions, which execute via the processor of the computer or other programmable data processing apparatus, create means for implementing the functions/acts specified in the flowchart and/or block diagram block or blocks. These computer readable program instructions can also be stored in a computer readable storage medium that can direct a computer, a programmable data processing apparatus, and/or other devices to function in a particular manner, such that the computer readable storage medium having instructions stored therein comprises an article of manufacture including instructions which implement aspects of the function/act specified in the flowchart and/or block diagram block or blocks. The computer readable program instructions can also be loaded onto a computer, other programmable data processing apparatus, or other device to cause a series of operational acts to be performed on the computer, other programmable apparatus or other device to produce a computer implemented process, such that the instructions which execute on the computer, other programmable apparatus, or other device implement the functions/acts specified in the flowchart and/or block diagram block or blocks.

[0145] The flowcharts and block diagrams in the Figures illustrate the architecture, functionality,

and operation of possible implementations of systems, methods, and computer program products according to various embodiments of the present invention. In this regard, each block in the flowchart or block diagrams can represent a module, segment, or portion of instructions, which comprises one or more executable instructions for implementing the specified logical function(s). In some alternative implementations, the functions noted in the blocks can occur out of the order noted in the Figures. For example, two blocks shown in succession can, in fact, be executed substantially concurrently, or the blocks can sometimes be executed in the reverse order, depending upon the functionality involved. It will also be noted that each block of the block diagrams and/or flowchart illustration, and combinations of blocks in the block diagrams and/or flowchart illustration, can be implemented by special purpose hardware-based systems that perform the specified functions or acts or carry out combinations of special purpose hardware and computer instructions.

[0146] While the subject matter has been described above in the general context of computer-executable instructions of a computer program product that runs on a computer and/or computers, those skilled in the art will recognize that this disclosure also can or can be implemented in combination with other program modules. Generally, program modules include routines, programs, components, data structures, etc. that perform particular tasks and/or implement particular abstract data types. Moreover, those skilled in the art will appreciate that the inventive computer-implemented methods can be practiced with other computer system configurations, including single-processor or multiprocessor computer systems, mini-computing devices, mainframe computers, as well as computers, hand-held computing devices (e.g., PDA, phone), microprocessor-based or programmable consumer or industrial electronics, and the like. The illustrated aspects can also be practiced in distributed computing environments in which tasks are performed by remote processing devices that are linked through a communications network. However, some, if not all aspects of this disclosure can be practiced on stand-alone computers. In a distributed computing environment, program modules can be located in both local and remote memory storage devices.

[0147] As used in this application, the terms “component,” “system,” “platform,” “interface,” and the like, can refer to and/or can include a computer-related entity or an entity related to an operational machine with one or more specific functionalities. The entities disclosed herein can be either hardware, a combination of hardware and software, software, or software in execution. For example, a component can be, but is not limited to being, a process running on a processor, a processor, an object, an executable, a thread of execution, a program, and/or a computer. By way of illustration, both an application running on a server and the server can be a component. One or more components can reside within a process and/or thread of execution and a component can be localized on one computer and/or distributed between two or more computers. In another example, respective components can execute from various computer readable media having various data structures stored thereon. The components can communicate via local and/or remote processes such as in accordance with a signal having one or more data packets (e.g., data from one component interacting with another component in a local system, distributed system, and/or across a network such as the Internet with other systems via the signal). As another example, a component can be an apparatus with specific functionality provided by mechanical parts operated by electric or electronic circuitry, which is operated by a software or firmware application executed by a processor. In such a case, the processor can be internal or external to the apparatus and can execute at least a part of the software or firmware application. As yet another example, a component can be an apparatus that provides specific functionality through electronic components without mechanical parts, wherein the electronic components can include a processor or other means to execute software or firmware that confers at least in part the functionality of the electronic components. In an aspect, a component can emulate an electronic component via a virtual machine, e.g., within a cloud computing system.

[0148] In addition, the term “or” is intended to mean an inclusive “or” rather than an exclusive “or.” That is, unless specified otherwise, or clear from context, “X employs A or B” is intended to mean any of the natural inclusive permutations. That is, if X employs A; X employs B; or X employs both A and B, then “X employs A or B” is satisfied under any of the foregoing instances. Moreover, articles “a” and “an” as used in the subject specification and annexed drawings should generally be construed to mean “one or more” unless specified otherwise or clear from context to be directed to a singular form. As used herein, the terms “example” and/or “exemplary” are utilized to mean serving as an example, instance, or illustration. For the avoidance of doubt, the subject matter disclosed herein is not limited by such examples. In addition, any aspect or design described herein as an “example” and/or “exemplary” is not necessarily to be construed as preferred or advantageous over other aspects or designs, nor is it meant to preclude equivalent exemplary structures and techniques known to those of ordinary skill in the art.

[0149] As it is employed in the subject specification, the term “processor” can refer to substantially any computing processing unit or device comprising, but not limited to, single-core processors; single-processors with software multithread execution capability; multi-core processors; multi-core processors with software multithread execution capability; multi-core processors with hardware multithread technology; parallel platforms; and parallel platforms with distributed shared memory. Additionally, a processor can refer to an integrated circuit, an application specific integrated circuit (ASIC), a digital signal processor (DSP), a field programmable gate array (FPGA), a programmable logic controller (PLC), a complex programmable logic device (CPLD), a discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. Further, processors can exploit nano-scale architectures such as, but not limited to, molecular and quantum-dot based transistors, switches and gates, in order to optimize space usage or enhance performance of user equipment. A processor can also be implemented as a combination of computing processing units. In this disclosure, terms such as “store,” “storage,” “data store,” “data storage,” “database,” and substantially any other information storage component relevant to operation and functionality of a component are utilized to refer to “memory components,” entities embodied in a “memory,” or components comprising a memory. It is to be appreciated that memory and/or memory components described herein can be either volatile memory or nonvolatile memory, or can include both volatile and nonvolatile memory. By way of illustration, and not limitation, nonvolatile memory can include read only memory (ROM), programmable ROM (PROM), electrically programmable ROM (EPROM), electrically erasable ROM (EEPROM), flash memory, or nonvolatile random access memory (RAM) (e.g., ferroelectric RAM (FeRAM)). Volatile memory can include RAM, which can act as external cache memory, for example. By way of illustration and not limitation, RAM is available in many forms such as synchronous RAM (SRAM), dynamic RAM (DRAM), synchronous DRAM (SDRAM), double data rate SDRAM (DDR SDRAM), enhanced SDRAM (ESDRAM), Synchlink DRAM (SLDRAM), direct Rambus RAM (DRRAM), direct Rambus dynamic RAM (DRDRAM), and Rambus dynamic RAM (RDRAM). Additionally, the disclosed memory components of systems or computer-implemented methods herein are intended to include, without being limited to including, these and any other suitable types of memory.

[0150] What has been described above include mere examples of systems and computer-implemented methods. It is, of course, not possible to describe every conceivable combination of components or computer-implemented methods for purposes of describing this disclosure, but one of ordinary skill in the art can recognize that many further combinations and permutations of this disclosure are possible. Furthermore, to the extent that the terms “includes,” “has,” “possesses,” and the like are used in the detailed description, claims, appendices and drawings such terms are intended to be inclusive in a manner similar to the term “comprising” as “comprising” is interpreted when employed as a transitional word in a claim.

[0151] The descriptions of the various embodiments have been presented for purposes of

illustration, but are not intended to be exhaustive or limited to the embodiments disclosed. Many modifications and variations will be apparent to those of ordinary skill in the art without departing from the scope and spirit of the described embodiments. The terminology used herein was chosen to best explain the principles of the embodiments, the practical application or technical improvement over technologies found in the marketplace, or to enable others of ordinary skill in the art to understand the embodiments disclosed herein.

Claims

1. A device, comprising: a Josephson junction shunted by a capacitor; and a trimmable inductor that couples the Josephson junction to a pad of the capacitor, wherein the trimmable inductor comprises a first conductive path and a second conductive path that is in parallel with the first conductive path, and wherein the first conductive path includes a welded superconducting bridge.
2. The device of claim 1, wherein welding the welded superconducting bridge decreases inductance of the trimmable inductor and increases resonant frequency of a qubit formed by the Josephson junction and the capacitor.
3. The device of claim 1, wherein the trimmable inductor is located external to the pad of the capacitor.
4. The device of claim 1, wherein the trimmable inductor is located internal to the pad of the capacitor.
5. The device of claim 1, further comprising a plurality of conductive paths.
6. The device of claim 5, wherein a subset of the plurality of conductive paths further comprise a plurality of superconducting anti-fuses.
7. The device of claim 1, wherein at least one of the first and the second conductive paths comprise superconducting materials having low kinetic inductance.
8. A method, comprising: fabricating a Josephson junction shunted by a capacitor; and fabricating a trimmable inductor that couples the Josephson junction to a pad of the capacitor, wherein the trimmable inductor comprises a first conductive path and a second conductive path that is in parallel with the first conductive path, and wherein the first conductive path includes the weldable superconducting bridge.
9. The method of claim 8, wherein welding the weldable superconducting bridge decreases an inductance of the trimmable inductor and increases a resonant frequency of a qubit formed by the Josephson junction and the capacitor.
10. The method of claim 8, wherein the trimmable inductor is located externally of the pad of the capacitor.
11. The method of claim 8, wherein the trimmable inductor is located internally of the pad of the capacitor.
12. The method of claim 8, further comprising a plurality of second conductive paths.
13. The method of claim 12, wherein the plurality of second conductive paths further comprises a plurality of superconducting antifuses.
14. The method of claim 8, wherein the conductive paths are constructed from superconducting materials having low kinetic inductances.
15. The method of claim 8, further comprising fabricating a plurality of Josephson junctions coupled to a pad of the capacitor by the trimmable inductor.
16. The method of claim 15, wherein the trimmable inductor provides one or more conductive paths between the plurality of Josephson junctions.
17. The method of claim 8, further comprising welding the weldable superconducting bridge.
18. The method of claim 17, wherein the welding of the weldable superconducting bridge alters an inductance of the trimmable inductor.
19. The method of claim 18, wherein the altering of the inductance of the trimmable inductor

changes a resonate frequency of a qubit formed by the Josephson junction and the capacitor.

20. A device, comprising: a trimmable inductor that couples a Josephson junction to a pad of a capacitor, wherein the trimmable inductor comprises a first conductive path and a second conductive path that is in parallel with the first conductive path, and wherein the first conductive path includes a superconducting bridge.
