

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12405324
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Nebuya; Satoru

Measurement apparatus and measurement method

Abstract

A measurement apparatus including: a static magnetic field applying part that applies a static magnetic field having a constant magnitude in a first direction to a measurement target; a plurality of current applying parts applying a plurality of AC currents oriented in a plurality of directions toward a portion of the measurement target via an electrode pair; a magnetic field detecting element that detects a magnitude of a magnetic field generated from the portion of the measurement target in response to the static magnetic field having the constant magnitude in the first direction and the plurality of AC currents; a calculating part for calculating impedance of the portion of the measurement target; and an internal information output part for generating information including an internal component of the measurement target.

Inventors:	Nebuya; Satoru (Tokyo, JP)
Applicant:	ASAHI INTECC CO., LTD. (Seto, JP)
Family ID:	81600861
Assignee:	ASAHI INTECC CO., LTD. (Seto, JP)
Appl. No.:	18/143939
Filed:	May 05, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20230305084 A1	Sep. 28, 2023

Related U.S. Application Data

continuation parent-doc WO PCT/JP2020/042112 20201111 PENDING child-doc US 18143939

Publication Classification

Int. Cl.: **G01R33/24** (20060101); **A61B5/0536** (20210101); **A61B5/055** (20060101); **G01R33/44** (20060101); **G01R33/54** (20060101)

U.S. Cl.:

CPC **G01R33/24** (20130101); **A61B5/0536** (20130101); **A61B5/055** (20130101); **G01R33/443** (20130101); **G01R33/543** (20130101);

Field of Classification Search

USPC: None

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
3932805	12/1975	Abe	324/309	G01R 33/3808
5421345	12/1994	Lekholm	600/506	A61B 5/0535
6397095	12/2001	Eyuboglu	324/309	G01R 33/54
2014/0031901	12/2013	Zhu	607/60	A61N 1/36128
2014/0239951	12/2013	Van Lier	324/309	A61B 5/055
2017/0071499	12/2016	Nebuya	N/A	A61B 5/0536
2020/0359898	12/2019	Gleich	N/A	A61B 5/0035

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
H06-225860	12/1993	JP	N/A
2006-502809	12/2005	JP	N/A
2009-119204	12/2008	JP	N/A
5839527	12/2015	JP	N/A
6506466	12/2018	JP	N/A
2020-531150	12/2019	JP	N/A
2015-129756	12/2014	WO	N/A
2019/038083	12/2018	WO	N/A

Primary Examiner: Fuller; Rodney E

Attorney, Agent or Firm: Oliff PLC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) The present application is a bypass continuation application of International Application number PCT/JP2020/042112, filed on Nov. 11, 2020. The contents of the prior application are incorporated herein by reference in their entirety.

BACKGROUND OF THE INVENTION

(1) The present disclosure relates to a measurement apparatus and a measurement method for

measuring information inside a measurement target. A magnetic resonance imaging (MRI) method of outputting information about the inside of a living body as a tomographic image by using a nuclear magnetic resonance phenomenon is known. Also, small and highly sensitive magnetic sensors are known (see Japanese Patent No. 6506466 and Japanese Patent No. 5839527, for example).

(2) With MRI, a static magnetic field is applied from the outside to a living body that is a measurement target, and the living body is macroscopically magnetized. Due to this, since atoms constituting a living body experience precession, when a pulse of an electromagnetic wave having a frequency corresponding to the Larmor frequency of this precession is radiated, resonance occurs, and the rotation speed of the precession changes (nuclear magnetic resonance phenomenon). When the pulse radiation of the electromagnetic wave is stopped, the precession of the atoms returns to a steady state. Since the process (relaxation phenomenon) until returning to such a steady state varies depending on the atoms, MRI generates such a difference in the relaxation phenomenon as an image, and outputs this image as a tomographic image of a living body.

(3) As described above, since MRI includes observing the relaxation phenomenon until the precession of the atoms returns to the steady state, the measurement result cannot be output unless at least a relaxation time has elapsed. On the other hand, in order to detect an abnormality in a living body, it is desirable to acquire and determine a plurality of tomographic images at different positions in the living body, and even if a part of the living body is determined to be normal or abnormal, a measurement time from tens of minutes to one hour or more might be taken.

BRIEF SUMMARY OF THE INVENTION

(4) The present disclosure has been made in view of the above circumstances, and it is an object of the present disclosure to obtain information about the inside of a living body at high speed with a simple configuration.

(5) According to a first aspect of the present disclosure, provided is a measurement apparatus including: a static magnetic field applying part that applies a static magnetic field having a constant magnitude in a first direction to a measurement target; a plurality of current applying parts that apply a plurality of AC currents oriented in a plurality of directions toward a portion of the measurement target, via a pair of electrodes; a magnetic field detecting element that detects a magnitude of a magnetic field of an electromagnetic wave generated due to nuclear magnetic resonance in the portion of the measurement target generated in response to (i) the static magnetic field having the constant magnitude in the first direction and (ii) the plurality of AC currents; a calculating part that calculates impedance of the portion of the measurement target based on a detection result of the magnetic field detecting element; and an internal information output part that generates information including an internal component of the measurement target, based on the calculated impedance.

(6) A second aspect of the present disclosure is a measurement apparatus including: in a state in which a measurement target is magnetized by geomagnetism, a plurality of current applying parts that apply a plurality of AC currents oriented in a plurality of directions, which are different from a direction of a magnetic field of the geomagnetism, toward a portion of the measurement target via a pair of electrodes; a magnetic field detecting element that detects a magnitude of a magnetic field of an electromagnetic wave generated due to nuclear magnetic resonance in the portion of the measurement target generated in response to (i) a static magnetic field caused by the geomagnetism and (ii) the plurality of AC currents; a calculating part that calculates impedance of the portion of the measurement target based on a detection result of the magnetic field detecting element; and an internal information output part that generates information including an internal component of the measurement target, based on the calculated impedance.

(7) A third aspect of the present disclosure is a measurement method including: applying a plurality of AC currents oriented in a plurality of directions toward a portion of the measurement target, through a pair of electrodes; detecting a magnitude of a magnetic field generated from the portion

of the measurement target in response to the plurality of AC currents; calculating impedance of the portion of the measurement target based on a detection result of the magnetic field; and generating and outputting information indicating an internal component of the measurement target, based on the calculated impedance.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 shows a first configuration example of a measurement apparatus **100** according to the present embodiment, together with a measurement target **10**.
- (2) FIG. 2 shows a configuration example of a mounting part **140** and a control part **160** according to the present embodiment, together with the measurement target **10**.
- (3) FIG. 3 shows a modified example of the measurement apparatus **100** according to the present embodiment together with the measurement target **10**.
- (4) FIG. 4 shows an example of an operation flow of the measurement apparatus **100** of the present modification shown in FIG. 3.
- (5) FIG. 5 shows a configuration example of a detection apparatus **400** according to the present embodiment, together with an MR image measurement apparatus **300**.
- (6) FIG. 6 shows a second configuration example of the measurement apparatus **100** according to the present embodiment, together with the measurement target **10**.
- (7) FIG. 7 shows a modified example of the measurement apparatus **100** of the second configuration example according to the present embodiment, together with the measurement target **10**.
- (8) FIG. 8 shows an example of an operation flow of the measurement apparatus **100** of the present modification shown in FIG. 7.
- (9) FIG. 9 shows a configuration example of a detection apparatus **600** according to the present embodiment, together with the MR image measurement apparatus **300**.
- (10) FIG. 10 shows a third configuration example of the measurement apparatus **100** according to the present embodiment, together with the measurement target **10**.
- (11) FIG. 11 shows an example of an operation flow of the measurement apparatus **100** of the third configuration example.
- (12) FIG. 12 shows a fourth configuration example of the measurement apparatus **100** according to the present embodiment, together with the measurement target **10**.

DETAILED DESCRIPTION OF THE INVENTION

(13) Hereinafter, the present disclosure will be described through exemplary embodiments, but the following exemplary embodiments do not limit the scope of the claims, and not all of the combinations of features described in the exemplary embodiments are necessarily essential to the solution means of the disclosure.

(14) <First Configuration Example of a Measurement Apparatus **100**>

(15) FIG. 1 shows a first configuration example of a measurement apparatus **100** according to the present embodiment, together with a measurement target **10**. The measurement apparatus **100** of the first configuration example outputs information about the inside of the measurement target **10** as a tomographic image. The measurement apparatus **100** applies a deflection magnetic field to a measurement target **10** to which a static magnetic field is applied, and acquires information about the inside of the measurement target **10** based on electromagnetic waves generated in response to the application of the deflection magnetic field. The measurement target **10** is, for example, a living body such as a human body. In the present embodiment, an example in which the measurement target **10** is a human body will be described. The measurement apparatus **100** includes a static magnetic field applying part **110**, a deflection magnetic field applying part **120**, a magnetic field

detecting element **130**, a mounting part **140**, a moving part **150**, a control part **160**, and a display part **170**.

(16) The static magnetic field applying part **110** applies a static magnetic field having a constant magnitude in a first direction to the measurement target **10**. FIG. **1** shows an example in which a human body serving as a measurement target **10** stands upright on a ground surface parallel to an XY plane. In FIG. **1**, the first direction is shown as a direction substantially parallel to a Z direction. Here, the Z direction is a direction perpendicular to the ground surface, which is the height direction of the human body. The static magnetic field applying part **110** applies a static magnetic field having a magnitude of several T (tesla), for example, which is the same as the magnitude of the static magnetic field used in the MRI or the like, to the entire measurement target **10**. The static magnetic field applying part **110** may apply a static magnetic field having a magnitude less than several T. For example, the static magnetic field applying part **110** applies a static magnetic field having a magnitude of 100 μ T or more, which is larger than the magnitude of geomagnetism, to the measurement target **10**. The static magnetic field applying part **110** includes a Helmholtz coil, for example.

(17) The deflection magnetic field applying part **120** applies a deflection magnetic field that has a predetermined frequency and is oriented in a second direction, which is different from the first direction, to a part of the measurement target **10** via a coil. Here, the predetermined frequency is determined based on the magnitude of the static magnetic field output from the static magnetic field applying part **110**, and is a frequency of about several kilohertz to hundreds of kilohertz, for example.

(18) The second direction is determined based on a region to be observed in the measurement target **10**, and is one or more directions different from the first direction. For example, the deflection magnetic field applying part **120** applies one or more deflection magnetic fields oriented in one or more directions different from the first direction toward a part of the measurement target **10**.

(19) The deflection magnetic field applying part **120** includes one or more magnetic field generating coils. The magnetic field generating coil is a Helmholtz coil, for example. It is desirable that the deflection magnetic field applying part **120** can apply a deflection magnetic field in various directions to the measurement target **10**. At least six deflection magnetic field applying parts **120** are provided so as to apply the deflection magnetic field in six directions including the $\pm X$ direction, the $\pm Y$ direction, and the $\pm Z$ direction, for example.

(20) In this case, it is desirable that the six deflection magnetic field applying parts **120** are arranged so that deflection magnetic fields of various sizes and directions can be applied to arbitrary portions of the measurement target **10** by controlling the magnitudes of the deflection magnetic fields output from the six deflection magnetic field applying parts **120**. Further, each of the deflection magnetic field applying parts **120** may be movable so that the deflection magnetic field can be applied to various portions of the measurement target **10**.

(21) The magnetic field detecting element **130** is disposed around the measurement target **10**, and detects the magnitude of each magnetic field based on electromagnetic waves generated and propagated in a part of the measurement target **10** caused by the application of a deflection magnetic field. It is desirable for a plurality of magnetic field detecting elements **130** to be disposed to surround the measurement target **10**. The magnetic field detecting element **130** is a highly sensitive magnetic sensor capable of detecting weak magnetic fields in units of nT (nanoteslas), pT (picoteslas), and fT (femtoteslas), for example.

(22) The mounting part **140** has at least some of the deflection magnetic field applying parts **120** mounted thereon. The mounting part **140** has a ring shape or partial ring shape surrounding the measurement target **10**, for example, and has a plurality of deflection magnetic field applying parts **120** mounted thereon. The mounting part **140** has at least some of the plurality of magnetic field detecting elements **130** mounted thereon. FIG. **1** shows an example in which the mounting part **140** has some of the deflection magnetic field applying parts **120** and all the magnetic field detecting

elements **130** mounted thereon.

(23) With such a mounting part **140**, the deflection magnetic field applying parts **120** can apply a plurality of deflection magnetic fields oriented in a plurality of directions, different from the first direction, from the plurality of deflection magnetic field applying parts **120** toward a part of the measurement target **10**. The plurality of magnetic field detecting elements **130** can detect magnetic fields generated in a plurality of directions caused by applying a plurality of deflection magnetic fields.

(24) The moving part **150** moves the mounting part **140** in a predetermined direction while maintaining the directions of the deflection magnetic fields generated by the plurality of deflection magnetic field applying parts **120** with respect to the measurement target **10**. The moving part **150** moves the mounting part **140** in a direction parallel to or perpendicular to the measurement target **10**. FIG. **1** shows an example in which the moving part **150** moves the mounting part **140** in the first direction. It is desirable that the moving part **150** can move the mounting part **140** in such a manner that deflection magnetic fields can be applied to a designated portion from the feet to the head of the human body. Further, the moving part **150** may move the mounting part **140** so as to rotate around the measurement target **10**.

(25) The mounting part **140** may have a cylindrical shape surrounding the measurement target **10**. The mounting part **140** has a cylindrical shape extending in the first direction, for example. In this case, the deflection magnetic field applying parts **120** and the magnetic field detecting elements **130** may be provided at a plurality of different locations on the mounting part **140**. For example, when the mounting part **140** has a size that covers the measurement target **10**, it is desirable that a plurality of deflection magnetic field applying parts **120** are arranged to apply deflection magnetic fields to a designated portion from the feet to the head of the human body. For example, the cylindrical mounting part **140** has a ring shape or a shape having a plurality of ring shapes, surrounding the measurement target **10**. In this case, since the deflection magnetic field can be applied to an arbitrary portion of the measurement target **10** without moving the mounting part **140**, the moving part **150** need not be provided.

(26) The control part **160** controls operations of the static magnetic field applying part **110**, the deflection magnetic field applying part **120**, the magnetic field detecting element **130**, the mounting part **140**, and the moving part **150**. The control part **160** controls the application timing of the static magnetic field by the static magnetic field applying part **110** and the application timing of the deflection magnetic field by the deflection magnetic field applying part **120**, for example. The control part **160** controls the detection timing of the magnetic field detecting element **130**. The control part **160** controls the moving part **150** to move the mounting part **140**. The control part **160** acquires the detection result detected by the magnetic field detecting element **130**. The control part **160** generates a tomographic image of the measurement target **10** based on the obtained detection result. The control part **160** is a computer such as a server, for example.

(27) <Configuration Example of the Mounting Part **140** and Control Part **160**>

(28) FIG. **2** shows a configuration example of the mounting part **140** and the control part **160** according to the present embodiment, together with the measurement target **10**. FIG. **2** shows a configuration example of the mounting part **140** and the measurement target **10** in a cross section of the measurement apparatus **100** in a plane parallel to the XY plane shown in FIG. **1**. As described with reference to FIG. **1**, the mounting part **140** includes a plurality of deflection magnetic field applying parts **120** and a plurality of magnetic field detecting elements **130**.

(29) In the mounting part **140**, the deflection magnetic field applying parts **120** and the magnetic field detecting elements **130** are provided at predetermined intervals along the circumferential direction of the ring shape, for example. The deflection magnetic field applying parts **120** are disposed so as to be able to apply a deflection magnetic field in a predetermined direction. The magnetic field detecting elements **130** are disposed so as to be able to detect the magnetic field generated from the measurement target **10**.

(30) The control part **160** applies the deflection magnetic field from the deflection magnetic field applying parts **120** to the measurement target **10** during a period in which the static magnetic field applying part **110** applies the static magnetic field to the measurement target **10**. Due to this, the deflection magnetic field is applied in a state in which the measurement target **10** is macroscopically magnetized. Accordingly, in the same manner as in the MRI operation, when the frequency of the deflection magnetic field matches the Larmor frequency of the precession of the atoms forming the measurement target **10**, a nuclear magnetic resonance phenomenon occurs. That is, the rotational speed of the precession of the atoms irradiated with the deflection magnetic field, among the atoms forming the measurement target **10**, changes. Due to such a change in precession, an electromagnetic wave in a state different from the steady state is generated from the atoms irradiated with the deflection magnetic field.

(31) Such nuclear magnetic resonance of the atoms is determined depending on the type of atom, the density of the atoms, the magnitude of the static magnetic field, the frequency of the deflection magnetic field, and the like. For example, if the magnitude of the static magnetic field is about 0.1 T to about 2 T, which is similar to the magnetic strength used in the MRI, nuclear magnetic resonance of hydrogen atoms in the human body can be caused by setting the frequency of the deflection magnetic field to about hundreds of kilohertz. If the magnitude of the static magnetic field is about tens of microteslas, which is similar to the magnitude of geomagnetism, nuclear magnetic resonance of hydrogen atoms in the human body can be caused by setting the frequency of the deflection magnetic field to about several kilohertz.

(32) The magnetic field detecting element **130** detects a magnetic field component of an electromagnetic wave generated in response to such nuclear magnetic resonance. The deflection magnetic field applying part **120** applies a deflection magnetic field to a localized portion of the measurement target **10**, for example. An eddy current corresponding to the deflection magnetic field is generated in a localized portion of the measurement target **10**. The eddy current is a current having a magnitude corresponding to the impedance of the localized portion. Then, a magnetic field corresponding to the generated eddy current is generated. The magnetic field detecting element **130** detects the magnitude of the magnetic field generated in this manner. In this way, the magnitude of the magnetic field detected by the magnetic field detecting element **130** is a value based on the electromagnetic wave propagated under the influence of the electric characteristics of the path from the portion to which the deflection magnetic field is applied to the magnetic field detecting element **130**. Here, the electrical characteristics of the path from the portion to which the deflection magnetic field is applied to the magnetic field detecting element **130** are the impedances of organs and the like in the human body, for example.

(33) That is, the magnitude of the magnetic field detected by the magnetic field detecting element **130** corresponds to information about the inside of the human body through which the electromagnetic wave has passed. Therefore, the control part **160** controls the magnitude of the magnetic field output from the deflection magnetic field applying part **120** to apply the deflection magnetic field to a plurality of portions of the measurement target **10**, and acquires the detection result of the magnetic field detecting element **130** for each portion to which the deflection magnetic field is applied. Due to this, the control part **160** can acquire the detection result of the magnetic field corresponding to the impedance distribution inside the measurement target **10**. By analyzing such a detection result, the control part **160** can generate information about the inside of the measurement target **10** as an image. The control part **160** described above includes a storage part **162**, a calculating part **164**, and an image information output part **166**, for example.

(34) The storage part **162** stores the detection result detected by the magnetic field detecting element **130**. The storage part **162** may store intermediate data, calculation results, threshold values, parameters, and the like generated (or used) during the operation of the measurement apparatus **100**. The storage part **162** may supply the stored data to the request source in response to a request from each part in the measurement apparatus **100**.

(35) The storage part **162** may store an OS (Operating System) in which a server or the like functions as the control part **160**, and information such as a program. The storage part **162** may store various types of information including a database referred to at the time of execution of the program. For example, a computer such as a server functions as at least a part of the storage part **162**, the calculating part **164**, and the image information output part **166** by executing a program stored in the storage part **162**.

(36) The storage part **162** includes a ROM (Read Only Memory) for storing a BIOS (Basic Input Output System) and the like of a computer or the like, and a RAM (Random Access Memory) serving as a work area, for example. The storage part **162** may include a large-capacity storage part such as an HDD (Hard Disk Drive) and/or an SSD (Solid State Drive). The computer may further include a GPU (Graphics Processing Unit) or the like.

(37) Based on the detection results of the plurality of magnetic field detecting elements **130**, the calculating part **164** calculates the impedance distribution of at least a portion of the region where the electromagnetic wave propagates in the measurement target **10**. For example, the calculating part **164** compares and analyzes the magnitudes of the magnetic fields of the electromagnetic waves propagated from the plurality of portions, to calculate impedances between the plurality of portions. For example, the calculating part **164** calculates an impedance distribution inside the human body using a two-dimensional Fourier transform or the like.

(38) The image information output part **166** generates and outputs an image showing information about the inside of the measurement target **10**, based on the impedance distribution. The calculating part **164** and the image information output part **166** generate a tomographic image of the inside of the human body using an image reconstruction method known as computer tomography. Since the image reconstruction method is a well-known technique, a detailed description thereof is omitted here. The image information output part **166** may generate a three-dimensional image based on the two-dimensional tomographic image. The image information output part **166** displays the generated image on a display part or the like. The image information output part **166** may store the generated image in the storage part **162**. Further, the image information output part **166** may store the generated image in an external database or the like, via a network or the like.

(39) The display part **170** displays one or more images generated by the image information output part **166**. As described above, the measurement apparatus **100** according to the present embodiment can output an impedance distribution of the inside of a living body such as a human body, as a tomographic image. Since the impedance of the inside of the human body varies depending on the organ or the like, the state of the inside of the human body and the like can be easily confirmed using the tomographic image output from the measurement apparatus **100**.

(40) The measurement apparatus **100** described above applies a static magnetic field and a deflection magnetic field to the measurement target **10** to generate a nuclear magnetic resonance phenomenon, and detects an electromagnetic wave based on the generation of the nuclear magnetic resonance phenomenon. Since the measurement apparatus **100** calculates the impedance distribution without observing the relaxation phenomenon occurring until the nuclear magnetic resonance phenomenon returns to the steady state, such as in MRI, it is possible to output the tomographic image of the inside of the measurement target **10** at a higher speed. In addition, a tumor such as cancer occurring in an organ or the like may change to an impedance different from the impedance of the organ. Accordingly, by using the measurement apparatus **100**, the normal state, the abnormal state, and the like of the organ, which have been difficult to observe by MRI, can be easily observed and distinguished.

(41) As described above, the measurement apparatus **100** detects the electromagnetic wave propagating in response to the nuclear magnetic resonance phenomenon generated inside the measurement target **10**, thereby outputting information about the inside of the measurement target **10** as an image. Accordingly, as long as the electromagnetic wave can be detected, the magnitude of the static magnetic field applied to the measurement target **10** by the static magnetic field

applying part **110** may be smaller than the magnitude of the static magnetic field up to several teslas used in MRI or the like.

(42) In this case, the magnitude of the magnetic field to be detected by the magnetic field detecting element **130** decreases in proportion to the magnitude of the static magnetic field. However, since a magnetic sensor with high sensitivity is known as exemplified in Patent Documents 1 and 2, the magnitude of the static magnetic field output from the static magnetic field applying part **110** can be reduced from milliteslas to approximately several hundred microteslas. Due to this, the measurement apparatus **100** with a compact size can output a tomographic image of the inside of the measurement target **10** inexpensively, without using an expensive and large-sized magnetic field generating apparatus that generates strong magnetic fields of several teslas, for example.

(43) It is also known that, as examples of a highly sensitive magnetic sensor, there are an optical pumping magnetometer, a superconducting quantum interference device SQUID, and the like that have a high sensitivity in units of approximately femtoteslas or less. In this way, when a high-sensitivity magnetic sensor capable of detecting weak magnetic fields in units of picoteslas or less is used as the magnetic field detecting element **130**, the magnitude of the static magnetic field output from the static magnetic field applying part **110** can be made smaller.

(44) For example, the static magnetic field applying part **110** may reduce the magnitude of the static magnetic field to be output to approximately the same magnitude as geomagnetism. In this case, the measurement apparatus **100** may use geomagnetism as a static magnetic field having a certain magnitude in the first direction. Then, the deflection magnetic field applying part **120** applies a deflection magnetic field in a second direction different from the first direction, which is the direction of the magnetic field of the geomagnetism, to a portion of the measurement target **10** magnetized by the geomagnetism.

(45) In such a measurement apparatus **100**, the static magnetic field applying part **110** may be omitted, and the scale of the apparatus may be further reduced. The measurement apparatus **100** may further include a fixed portion that can move the measurement target **10** while the measurement target **10** is fixed so that the first direction, which is the direction of the geomagnetism, and the predetermined direction of the measurement target **10** match each other. Further, such a fixing portion may have a bed or the like so that a human body can be fixed in a reclined state.

(46) In the measurement apparatus **100** according to the present embodiment described above, the static magnetic field applying part **110** applies a static magnetic field with a constant magnitude to the measurement target **10**, but it is not limited to this. In addition, the static magnetic field applying part **110** may be provided so that the magnitude of the static magnetic field applied to the measurement target **10** can be changed.

(47) As described above, the resonance frequency at which nuclear magnetic resonance occurs in the measurement target **10** varies depending on the type of atoms, the magnitude of the static magnetic field, and the like. Therefore, when the static magnetic field applying part **110** changes the magnitude of the static magnetic field applied to the measurement target **10**, the resonance frequency for the atoms contained in the measurement target **10** can be changed. Therefore, the control part **160** acquires the detection result from the magnetic field detecting element **130** for each magnitude of the static magnetic field output from the static magnetic field applying part **110**. Due to this, the calculating part **164** calculates the impedance distribution for each magnitude of the static magnetic field.

(48) In this way, the measurement apparatus **100** can measure the frequency characteristic of the impedance distribution by sweeping the magnitude of the static magnetic field within a predetermined range. The frequency characteristic of the impedance distribution can be expressed with the horizontal axis representing the frequency and the vertical axis representing the value of the impedance at one or more locations. Further, a tomographic image of the impedance distribution may be generated for each of a plurality of resonance frequencies to obtain the

frequency characteristic of the impedance distribution. By measuring the frequency characteristic of the impedance distribution, the occurrence of nuclear magnetic resonance for a plurality of different atoms can be determined and more detailed information about the inside of the measurement target **10** can be acquired, for example.

(49) In the measurement apparatus **100** according to the present embodiment, an example of detecting an electromagnetic wave based on the occurrence of a nuclear magnetic resonance phenomenon has been described, but the present disclosure is not limited thereto. Since the measurement apparatus **100** can generate the nuclear magnetic resonance phenomenon in the measurement target **10**, a relaxation phenomenon occurring until the nuclear magnetic resonance phenomenon returns to a steady state, such as in MRI, can be observed. The following describes such a measurement apparatus **100**.

(50) <Modified Example of the Measurement Apparatus **100** of the First Configuration Example.>

(51) FIG. **3** shows a modified example of the measurement apparatus **100** of the first configuration example according to the present embodiment, together with the measurement target **10**. In the measurement apparatus **100** of the present modification, components that are substantially the same as those of the measurement apparatus **100** according to the present embodiment shown in FIGS. **1** and **2** are denoted by the same reference numerals, and description thereof is omitted. The measurement apparatus **100** of this modification includes a relaxation detecting element **210**, an MR image generating part **220**, and a determining part **230**.

(52) The relaxation detecting element **210** detects a relaxation phenomenon of an electromagnetic wave generated by application of a deflection magnetic field in a portion of the measurement target **10**. The relaxation detecting element **210** is a detecting element similar to the magnetic field detecting element **130**, for example. Further, among the plurality of magnetic field detecting elements **130**, one or more magnetic field detecting elements **130** may further function as a relaxation detecting element **210** and detect a process occurring from the detection of the magnetic field to when the magnitude of the magnetic field returns to a steady state. Since the relaxation phenomenon of an electromagnetic wave is known in MRI measurement, description thereof is omitted here. The control part **160** acquires such a relaxation phenomenon detection result from the magnetic field detecting element **130**.

(53) The MR image generating part **220** generates and outputs a magnetic resonance image, which is a tomographic image of the inside of the measurement target **10**, based on the detection result of the relaxation detecting element **210**. The MR image generating part **220** generates a magnetic resonance image of the inside of the human body using, for example, an image reconstruction method known as computer tomography. Since the image reconstruction method is a well-known technique, a detailed description thereof is omitted here. Due to the above, the measurement apparatus **100** can output a magnetic resonance image by reducing the scale of the measurement apparatus **100** to be smaller than that of a conventional MRI, without generating a strong magnetic field of several teslas.

(54) In this way, the measurement apparatus **100** is configured to be able to measure a tomographic image of the impedance distribution of the measurement target **10** and a magnetic resonance image. In this case, it is desirable that the measurement apparatus **100** is configured to be capable of performing measurement by switching the tomographic image and the magnetic resonance image of the impedance distribution of the measurement target **10**. Further, it is more preferable that the measurement location of the magnetic resonance image can be specified based on the measurement result of the tomographic image of the impedance distribution. In this case, the control part **160** includes a determining part **230**.

(55) The determining part **230** determines a location inside of the measurement target **10** at which to acquire the magnetic resonance image, based on one or more images indicating information about the inside of the measurement target **10** generated by the image information output part **166**. Since the tomographic image of the impedance distribution of the measurement target **10** can be

measured at high speed as described above, the tomographic image can be used to determine a measurement location for the magnetic resonance image, for example. In this case, the determining part **230** may use the measurement results of a plurality of tomographic images to determine the location in the measurement target **10** at which the magnetic resonance image is to be acquired. (56) The determining part **230** determines a location where an abnormality is estimated to be in the tomographic image as a measurement location of the magnetic resonance image, based on image processing such as image comparison, for example. Alternatively, after the image information output part **166** displays the measurement results of the plurality of tomographic images on the display part **170**, the determining part **230** may receive an input of a location to be measured in the magnetic resonance image from a user or the like. The following describes such an operation of the measurement apparatus **100**.

(57) <First Example of the Operation Flow of the Measurement Apparatus **100**>

(58) FIG. **4** shows an example of an operation flow of the measurement apparatus **100** of the present modification shown in FIG. **3**. The measurement apparatus **100** outputs a magnetic resonance image of the measurement target **10** by executing the operation flow from **S410** to **S490**.

(59) First, the control part **160** receives a measurement start instruction for the measurement target **10** from a user or the like (**S410**). Here, it is assumed that the measurement target **10** is disposed so as to have a predetermined positional relationship with respect to the static magnetic field applying part **110**, the deflection magnetic field applying part **120**, and the magnetic field detecting element **130**. The control part **160** further receives information concerning the measurement range for the measurement target **10**. For example, the control part **160** receives an instruction of a measurement range such as a head, a neck, a chest, an abdomen, a waist, a leg, the whole body, or the like. In accordance with the received information, the control part **160** controls the moving part **150** to move the mounting part **140** to a measurement start point of the measurement range.

(60) Next, the static magnetic field applying part **110** applies a static magnetic field having a constant magnitude in the first direction to the measurement target **10** (**S420**). The static magnetic field applying part **110** applies a static magnetic field having a predetermined intensity level to the measurement target **10**.

(61) Next, the deflection magnetic field applying part **120** applies a deflection magnetic field that has a predetermined frequency and is oriented in a second direction, which is different from the first direction, to a portion of the measurement target **10** (**S430**). The deflection magnetic field applying part **120** applies a deflection magnetic field to a portion of the measurement target **10** corresponding to the received measurement range. Then, the plurality of magnetic field detecting elements **130** detect magnitudes of the magnetic fields, around the measurement target **10**, based on electromagnetic waves generated and propagated in the portion of the measurement target **10** due to the application of the deflection magnetic field (**S440**).

(62) Next, the calculating part **164** calculates the impedance distribution of at least a portion of the region where the electromagnetic waves propagate inside the measurement target **10**, based on the detection results of the propagated electromagnetic waves (**S450**). The control part **160** repeats the operations of **S430** to **S450** until the impedance distribution of the measurement range can be calculated (**S460**: NO). Here, as an example, the control part **160** changes the location at which the deflection magnetic field is applied, and calculates the impedance distribution for each location at which the deflection magnetic field is applied. The control part **160** may control the moving part **150** to move the mounting part **140** in order to change the location at which the deflection magnetic field is applied.

(63) If the impedance distribution of the measurement range can be calculated (**S460**: Yes), the image information output part **166** generates and outputs an image indicating information about the inside of the measurement target **10** based on the impedance distribution (**S470**). For example, the image information output part **166** generates one or more tomographic images corresponding to one or more impedance distributions. Alternatively or in addition to this, the image information

output part **166** may generate a 3D image of the inside of the measurement target **10**. For example, the image information output part **166** displays one or more generated images on the display part **170**.

(64) Next, the determining part **230** determines a location inside the measurement target **10** for a magnetic resonance image is to be acquired, based on one or more generated images indicating the information about the inside of the measurement target **10** (**S480**). The determining part **230** receives an input of a location where a magnetic resonance image is to be acquired from the user of the measurement apparatus **100** who has confirmed the image of the measurement target **10** displayed on the display part **170**, for example.

(65) Next, the control part **160** acquires and outputs the determined magnetic resonance image of the location in the measurement target **10** (**S490**). The magnetic resonance image may be acquired using a known method. For example, the static magnetic field applying part **110** applies a static magnetic field having a constant magnitude in the first direction to the measurement target **10**. Then, the deflection magnetic field applying part **120** applies a deflection magnetic field that has a predetermined frequency and is oriented in a direction different from the first direction toward the determined location in the measurement target **10**. The control part **160** may control the moving part **150** to move the mounting part **140** in order to apply the deflected magnetic field to the determined location in the measurement target **10**.

(66) The relaxation detecting element **210** detects an electromagnetic wave generated by the application of the deflection magnetic field and a relaxation phenomenon of the generated electromagnetic wave, at a location in the measurement target **10**. The MR image generating part **220** generates and outputs a magnetic resonance image, which is a tomographic image of the inside of the measurement target, based on the detected results of the generated electromagnetic wave and the relaxation phenomenon of the electromagnetic wave. The MR image generating part **220** displays the generated magnetic resonance image on the display part **170**, for example. The MR image generating part **220** may display the magnetic resonance image together with the image of the inside of the measurement target **10** displayed by the image information output part **166**.

(67) As described above, the measurement apparatus **100** according to the present modification can determine the location in the measurement target **10** at which the magnetic resonance image is to be acquired, based on the tomographic image of the impedance distribution, and can measure this magnetic resonance image. Therefore, the measurement apparatus **100** can measure and output a magnetic resonance image quickly by appropriately determining a location to be observed in the measurement target **10** with a simple configuration.

(68) The operation flow described with reference to FIG. **4** is an example of the operation flow of the measurement apparatus **100** provided with the static magnetic field applying part **110**, but the operation flow is not limited thereto. The measurement apparatus **100** may measure a tomographic image of the impedance distribution after measuring the magnetic resonance image. In a case where the measurement apparatus **100** measures an image and a magnetic resonance image of the inside of the measurement target **10** using geomagnetism, it is needless to say that the same operation can be performed by, for example, omitting the operation of **S420** by the static magnetic field applying part **110** and applying a deflection magnetic field in a direction different from the first direction, which is the direction of the magnetic field of geomagnetism, to a portion of the measurement target **10**.

(69) In the measurement apparatus **100** according to the present embodiment, an example in which an image of the inside of the measurement target **10** can be quickly measured has been described. An example has been described in which the measurement apparatus **100** capable of measuring two images, namely the tomographic image and the magnetic resonance image, of the impedance distribution of the measurement target **10** can switch between executing these two measurements. Alternatively, the measurement apparatus **100** may be configured to be capable of measuring only the magnetic resonance image of the measurement target **10**.

(70) Further, in the measurement apparatus **100** according to the present embodiment described above, an example has been described in which the moving part **150** moves the mounting part **140** while the measurement target **10** is fixed, but the present disclosure is not limited thereto. For example, the mounting part **140** may be fixed, and the moving part **150** may move the measurement target **10**. In this case, it is desirable that the human body serving as the measurement target **10** is fixed to a bed or the like, and the moving part **150** moves the bed.

(71) <Configuration Example of the Detection Apparatus **400**>

(72) Although an example in which the measurement apparatus **100** according to the present embodiment is an independent apparatus has been described, the present disclosure is not limited thereto. The measurement apparatus **100** may be an apparatus that functions by being added to an existing MR image measurement apparatus that outputs a magnetic resonance image. FIG. 5 shows a configuration example of the detection apparatus **400** according to the present embodiment, together with the MR image measurement apparatus **300**.

(73) The MR image measurement apparatus **300** includes at least a configuration that operates in the same manner as the static magnetic field applying part **110**, the deflection magnetic field applying part **120**, the mounting part **140**, the moving part **150**, the display part **170**, and the relaxation detecting element **210**, and the MR image generating part **220** according to the present embodiment. The MR image measurement apparatus **300** includes a control part **310** that controls each part in order to measure a magnetic resonance image. Since the measurement of the magnetic resonance image by the MR image measurement apparatus **300** is substantially the same as the operation described above, description thereof is omitted here.

(74) The detection apparatus **400** is provided in such an MR image measurement apparatus **300**. In this case, a combination of the MR image measurement apparatus **300** and the detecting apparatus **400** functions as at least a portion of the measurement apparatus **100** according to the present embodiment. The detection apparatus **400** includes a plurality of the magnetic field detecting elements **130**, and the control part **160** including the storage part **162**, the calculating part **164**, the image information output part **166**, and the determining part **230**.

(75) The detection apparatus **400** transmits and receives a control signal or the like to and from the MR image measurement apparatus **300** to generate and output an image indicating information about the inside of the measurement target **10**. Further, the detection apparatus **400** may supply a control signal instructing the measurement of the magnetic resonance image to the MR image measurement apparatus **300** based on the image of the inside of the measurement target **10**. Thus, it is possible to configure the measurement apparatus **100** to be capable of acquiring information about the inside of the measurement target **10** at high speed while utilizing existing equipment or the like.

(76) By using the impedance distribution, the measurement apparatus **100** according to the present embodiment can observe a normal state, an abnormal state, and the like of an organ which has been difficult to observe with MRI. In such observation of the internal state of the human body, it is desirable to be able to more accurately measure a minute portion. Therefore, the measurement apparatus **100** may be configured such that a current can be directly supplied to the measurement target **10** by using an electrode pair instead of indirectly supplying a current to the measurement target **10** by using a coil. Due to this, the positional accuracy of the location where the measurement apparatus **100** supplies the current can be improved. The following describes such a measurement apparatus **100**.

(77) <Second Configuration Example of the Measurement Apparatus **100**, and Measurement of Whether the Measurement Target is Normal or Abnormal>

(78) FIG. 6 shows a second configuration example of the measurement apparatus **100** according to the present embodiment, together with the measurement target **10**. In the measurement apparatus **100** of the second configuration example, components that are substantially the same as those of the measurement apparatus **100** of the first configuration example shown in FIG. 1 are denoted by

the same reference numerals, and description thereof is omitted. The measurement apparatus **100** of the second configuration example outputs information about the state of the inside of the measurement target **10**. For example, the measurement apparatus **100** applies a current to a human body to which a static magnetic field is applied, and acquires information such as a normal state and an abnormal state of an organ of the human body based on a magnetic field generated in response to the application of the current.

(79) The measurement apparatus **100** includes the static magnetic field applying part **110**, a current applying part **510**, the magnetic field detecting element **130**, the mounting part **140**, the moving part **150**, the control part **160**, and the display part **170**. In other words, the measurement apparatus **100** of the second configuration example includes the current applying part **510** instead of the deflection magnetic field applying part **120** of the measurement apparatus **100** of the first configuration example. Since the operation of the static magnetic field applying part **110** is the same as that described with reference to FIG. **1**, the description thereof is omitted here.

(80) The current applying part **510** applies an AC current to the human body serving as the measurement target **10**, via the electrode pair. The electrode pair is connected to an AC power source, for example, and generates an electric field corresponding to the AC power supplied from the AC power source. The operation of the AC power source is desirably controlled by the control part **160**. The electrode pair has a positive electrode and a negative electrode formed separated from each other by a predetermined distance. The shapes of the positive electrode and the negative electrode may be such that an AC current can be supplied to a location to be observed in the measurement target **10**. The positive electrode and the negative electrode are preferably disposed in the vicinity of the measurement target **10** so that an AC current can be supplied to the location to be observed in the measurement target **10**, and may be disposed in contact with the measurement target **10**.

(81) The current applying part **510** includes one or more electrode pairs. It is desirable that the current applying part **510** can apply a plurality of AC currents corresponding to eddy currents generated by a plurality of deflection magnetic fields oriented in a plurality of directions different from the first direction to a portion of the measurement target **10**. At least six current applying parts **510** are provided so that AC current can be applied in six directions, which are the +X direction, the +Y direction, and the +Z direction, for example. The current applying part **510** is desirably disposed so as to be able to apply AC currents of various magnitudes and directions to arbitrary locations in the measurement target **10**. Further, each of the current applying parts **510** may be movable so as to apply an AC current to various locations in the measurement target **10**.

(82) The AC current applied by the current applying part **510** is a current corresponding to an eddy current generated by a deflection magnetic field in a second direction different from the first direction in a portion of the measurement target **10**. In other words, the current applying part **510** applies a current similar to the eddy current generated by the deflection magnetic field applied by the deflection magnetic field applying part **120** shown in FIG. **1** to the localized portion of the measurement target **10**. Due to this, a magnetic field corresponding to the AC current corresponding to the impedance of the localized portion is generated in the localized portion of the measurement target **10**. The waveform of the AC current may be a sine wave, a triangular wave, a rectangular wave, or the like, or may be a pulse wave, an attenuated wave, a burst wave, or the like.

(83) The magnetic field detecting element **130** detects the magnitude of the magnetic field generated in this manner. The magnetic field detecting element **130** of the second configuration example detects the magnitude of the magnetic field generated from a portion of the measurement target **10** in accordance with the AC current supplied from the current applying part **510**. One or more magnetic field detecting elements **130** are provided in the vicinity of the measurement target **10**. For example, as described above, it is desirable that a plurality of magnetic field detecting elements **130** are disposed around the measurement target **10** to surround the measurement target **10**. It is desirable that a plurality of magnetic field detecting elements **130** are provided so as to be

able to detect magnetic fields in a plurality of directions. Due to this, the magnetic field detecting elements **130** can detect the magnitude of the magnetic field corresponding to the impedance of the organ or the like in the human body, which is the measurement target **10**, for example.

(84) The mounting part **140** has a plurality of current applying parts **510** mounted thereon. As described above, the mounting part **140** has a ring shape or a partial ring shape surrounding the measurement target **10**. Further, at least some of the plurality of magnetic field detecting elements **130** may be mounted on the mounting part **140**. The moving part **150** moves the mounting part **140** in a predetermined direction while maintaining the direction of the AC current generated by the one or more current applying parts **510** with respect to the measurement target **10**. The other operations of the mounting part **140** and the moving part **150** are the same as those already described with reference to FIG. 1, and so description thereof is omitted here.

(85) The control part **160** controls operations of the static magnetic field applying part **110**, the current applying part **510**, the magnetic field detecting element **130**, the mounting part **140**, and the moving part **150**. The control part **160** controls the application timing of the static magnetic field by the static magnetic field applying part **110** and the application timing of the AC current by the current applying part **510**, for example. Further, the control part **160** may control the application direction of the AC current.

(86) During a period in which the static magnetic field is applied from the static magnetic field applying part **110** to the measurement target **10**, the control part **160** applies an AC current from the current applying part **510** to the measurement target **10**. Due to this, the AC current is applied in a state in which the measurement target **10** is macroscopically magnetized. Therefore, in the same manner as in the MRI operation, the rotational speed of the precession of the atoms to which the AC current is applied among the atoms forming the measurement target **10** changes. Due to such a change in the precession, an electromagnetic wave in a state differing from the steady state is generated from the atoms to which the AC current is applied.

(87) As an example, the control part **160** applies an AC current to a location in the measurement target **10**, and acquires a detection result of the magnetic field detecting element **130** corresponding to the location at which the AC current is applied. In this way, the control part **160** can acquire the detection result of the magnetic field corresponding to the impedance of the location at which the AC current is applied in the measurement target **10**. Further, the control part **160** applies an AC current to a plurality of locations in the measurement target **10**, and acquires the detection result of the magnetic field detecting element **130** for each location at which the AC current is applied, for example. In this way, the control part **160** can acquire the detection result of the magnetic field corresponding to the impedance, the impedance distribution, and the like inside the measurement target **10**.

(88) By analyzing such a detection result, the control part **160** can generate information about the state of the inside of the measurement target **10**. The control part **160** includes the storage part **162**, the calculating part **164**, and an internal information output part **566**, for example. Since the operations of the storage part **162** and the operation of the calculating part **164** are the same as those already described with reference to FIG. 1, the description thereof is omitted here. The calculating part **164** may calculate the impedance inside the measurement target **10** based on the detection result of the magnetic field detecting element **130** at one location inside the measurement target **10**.

(89) The internal information output part **566** generates and outputs information indicating the state of the inside of the measurement target **10** based on the impedance and/or the impedance distribution calculated by the calculating part **164**. The internal information output part **566** can generate information indicating a state of a wider area by using the impedance distribution. In this case, the internal information output part **566** may generate and output an image based on the impedance distribution. The internal information output part **566** generates information such as an abnormal state caused by a tumor such as cancer occurring in an organ or the like. Further, the

internal information output part **566** generates information in which an organ or the like is in a normal state in response to being unable to detect an abnormal state. The display part **170** displays information indicating the state of the inside of the measurement target **10** generated by the internal information output part **566**.

(90) As described above, the measurement apparatus **100** of the second configuration example can efficiently measure the state of the inside of the living body such as a human body by supplying the AC current to the location to be observed. Here, in the measurement apparatus **100** of the second configuration example, similarly to the measurement apparatus **100** of the first configuration example, the static magnetic field applying part **110** may change the magnitude of the static magnetic field applied to the measurement target **10**, and the impedance may be calculated for each magnitude of the static magnetic field.

(91) Similarly to the measurement apparatus **100** of the first configuration example, the measurement apparatus **100** of the second configuration example described above can calculate the impedance without observing the relaxation phenomenon occurring until the nuclear magnetic resonance phenomenon returns to the steady state, and can therefore output the measurement result at high speed. Further, the magnetic field detecting element **130** can measure the state of the inside of the measurement target **10** while being small-scale and inexpensive, by using the highly sensitive magnetic sensor listed in Patent Document 1 or 2.

(92) Also in the measurement apparatus **100** of the second configuration example, when a highly sensitive magnetic sensor capable of detecting weak magnetic fields in units of picoteslas or less is used as the magnetic field detecting element **130**, the magnitude of the static magnetic field output from the static magnetic field applying part **110** can be made smaller. For example, even if the magnitude of the static magnetic field output from the static magnetic field applying part **110** is reduced to a magnitude of several hundred times the magnitude of geomagnetism, the state inside the measurement target **10** can be measured.

(93) In the measurement apparatus **100** of the second configuration example described above, an example of detecting the magnetic field based on the application of the AC current has been described, but the present disclosure is not limited thereto. The measurement apparatus **100** may cause a nuclear magnetic resonance phenomenon in the measurement target **10** and observe the relaxation phenomenon occurring until the nuclear magnetic resonance phenomenon returns to a steady state, such as in MRI. For example, the measurement apparatus **100** is configured to directly supply a current to the measurement target **10** by using the electrode pair, and can therefore generate the nuclear magnetic resonance phenomenon.

(94) In this case, a plurality of current applying parts **510** are provided around the measurement target **10** and apply a plurality of AC currents oriented in a plurality of directions, toward a portion of the measurement target **10**. The magnetic field detecting element **130** detects the relaxation phenomenon of the magnetic field based on the plurality of AC currents generated by the plurality of current applying parts **510** in a portion of the measurement target **10**. The calculating part **164** calculates the impedance inside the measurement target **10** in time series. Due to this, the internal information output part **566** can generate and output an image corresponding to the magnetic resonance image indicating information about the inside of the measurement target **10** based on the calculated change in impedance.

(95) In this case, the internal information output part **566** can generate an image corresponding to the magnetic resonance image of the measurement target **10** by performing known signal processing on the change in impedance, for example. If the detection sensitivity of the magnetic field detecting element **130** is sufficiently high, the internal information output part **566** can output an image, corresponding to the magnetic resonance image, that is approximately equal to the magnetic resonance image. The display part **170** may display an image corresponding to the magnetic resonance image generated by the internal information output part **566**, and may display information indicating the internal state together with the image.

(96) Alternatively or in addition to this, the measurement apparatus **100** may further include a member for capturing a magnetic resonance image. The following describes such a measurement apparatus **100**.

(97) <Modified Example of the Measurement Apparatus **100** of the Second Configuration Example, Generation of an MR Image, and Measurement Apparatus of the First Configuration Example>

(98) FIG. 7 shows a modified example of the measurement apparatus **100** of the second configuration example according to the present embodiment, together with the measurement target **10**. In the measurement apparatus **100** according to the present modification, components that are substantially the same as those of the measurement apparatus **100** according to the second configuration example shown in FIG. 6 are denoted by the same reference numerals, and description thereof is omitted. The measurement apparatus **100** of this modification includes the deflection magnetic field applying part **120**, the relaxation detecting element **210**, the MR image generating part **220**, and the determining part **230**.

(99) The deflection magnetic field applying part **120** has a predetermined frequency and applies a deflection magnetic field in a second direction, which is different from the first direction, toward a portion of the measurement target **10** via a coil. The deflection magnetic field applying part **120** includes a plurality of magnetic field generating coils, and applies a plurality of deflection magnetic fields oriented in a plurality of directions that are different from the first direction toward a portion of the measurement target **10**. Since the operations of the deflection magnetic field applying part **120**, the relaxation detecting element **210**, and the MR image generating part **220** are the same as the operations of these parts described in the modified example of the measurement apparatus **100** of the first configuration example, description thereof is omitted here.

(100) In this way, the measurement apparatus **100** is configured to be capable of measuring the internal information of the measurement target **10** using the AC current and of measuring the magnetic resonance image. In this case, the measurement apparatus **100** is desirably configured to be capable of switching between the measurement of the internal information of the measurement target **10** and the measurement of the magnetic resonance image. Further, it is more preferable that the measurement location of the internal information in the measurement target **10** can be specified based on the measurement result of the magnetic resonance image. In this case, the control part **160** includes the determining part **230**.

(101) Based on the magnetic resonance image generated by the MR image generating part **220**, the determining part **230** determines a location in the measurement target **10** at which the AC current is to be applied by the current applying part **510**. The magnetic resonance image can display information of a position inside the measurement target **10** with high spatial resolution. Therefore, the determining part **230** can easily determine the location of an organ in the body to be observed, for example.

(102) The determining part **230** determines a location where an abnormality is estimated to be in the magnetic resonance image as a location at which an AC current is to be applied, based on image processing such as image analysis and image comparison. Alternatively, after the magnetic resonance image is displayed on the display part **170**, the determining part **230** may receive an input of a location at which the AC current is to be applied from a user or the like. The following describes such an operation of the measurement apparatus **100**.

(103) <Second Example of the Operation Flow of the Measurement Apparatus **100**>

(104) FIG. 8 shows an example of an operation flow of the measurement apparatus **100** of the present modification shown in FIG. 7. The measurement apparatus **100** outputs information on the internal state of the measurement target **10** by executing the operation flow from S810 to S890.

(105) First, the control part **160** receives a measurement start instruction for the measurement target **10** from a user or the like (S810). Here, it is assumed that the measurement target **10** is disposed so as to have a predetermined positional relationship with respect to the static magnetic field applying

part **110**, the deflection magnetic field applying part **120**, the magnetic field detecting element **130**, and the current applying part **510**. The control part **160** further receives information concerning the measurement range of the measurement target **10**. The control part **160** receives an instruction of a measurement range such as a head, a neck, a chest, an abdomen, a waist, a leg, the whole body, or the like. In accordance with the received information, the control part **160** controls the moving part **150** to move the mounting part **140** to the measurement start point of the measurement range.

(106) Next, the static magnetic field applying part **110** applies a static magnetic field having a constant magnitude in the first direction to the measurement target **10** (S820). The static magnetic field applying part **110** applies a static magnetic field having a predetermined intensity level to the measurement target **10**.

(107) Next, the deflection magnetic field applying part **120** applies a deflection magnetic field that has a predetermined frequency and is oriented in a second direction, which is different from the first direction, to a location in the measurement target **10** to be observed (S830). The deflection magnetic field applying part **120** applies a deflection magnetic field to a portion of the measurement target **10** corresponding to the received measurement range.

(108) Next, the control part **160** acquires and outputs a magnetic resonance image of the measurement range of the measurement target **10** (S840). The relaxation detecting element **210** detects the electromagnetic wave generated by the application of the deflection magnetic field and the relaxation phenomenon of the generated electromagnetic wave in the measurement range of the measurement target **10**. The MR image generating part **220** generates and outputs a magnetic resonance image, which is a tomographic image of the inside of the measurement target, based on the detection results of the generated electromagnetic wave and the relaxation phenomenon of the electromagnetic wave. The MR image generating part **220** displays the generated magnetic resonance image on the display part **170**, for example.

(109) Next, based on the magnetic resonance image, the determining part **230** determines the internal position in the measurement target **10** to be observed (S850). The determining part **230** receives an input of a location to be observed from a user of the measurement apparatus **100** who has confirmed the magnetic resonance image of the measurement target **10** displayed on the display part **170**, for example. Further, the determining part **230** may determine a location where the state is to be observed by image analysis.

(110) Next, the current applying part **510** applies an AC current toward the determined position inside the measurement target **10** (S860). Then, the plurality of magnetic field detecting elements **130** respectively detect magnitudes of magnetic fields generated in a portion of the measurement target **10** due to the application of the AC current, around the measurement target **10** (S870).

(111) Next, the calculating part **164** calculates the impedance inside the measurement target **10** based on the detection result of the magnetic field (S880). The internal information output part **566** generates and outputs information about the internal state of the measurement target **10** based on the impedance (S890). The internal information output part **566** generates information such as whether an organ is normal, abnormal, or suspected to be abnormal. The internal information output part **566** displays the generated information on the display part **170**. For example, the display part **170** displays the internal state at a position corresponding to the measured organ in the magnetic resonance image.

(112) As described above, the measurement apparatus **100** according to the present modified example determines the location where the internal state of the measurement target **10** is to be acquired, based on the magnetic resonance image. Due to this, the measurement apparatus **100** can appropriately determine the location to be observed using the positional information of the measurement target **10** measured with high spatial resolution, and can quickly measure the internal state.

(113) The operation flow described with reference to FIG. **8** is an example of the operation flow of the measurement apparatus **100** provided with the static magnetic field applying part **110**, but is not

limited thereto. When the measurement apparatus **100** measures an image inside the measurement target **10** and a magnetic resonance image using geomagnetism, for example, the operation of **S820** by the static magnetic field applying part **110** may be omitted. Further, the measurement apparatus **100** may measure the magnetic resonance image after measuring the internal state.

(114) Further, instead of the deflection magnetic field, the measurement apparatus **100** may generate an image corresponding to the magnetic resonance image by applying an AC current to the measurement target **10** as described above. In this case, the operation of **S830** is, for example, an operation in which the plurality of current applying parts **510** apply a plurality of AC currents oriented in a plurality of directions, from a plurality of positions around the measurement target **10**, toward a portion of the measurement target **10**.

(115) In the operation of **S840**, the relaxation detecting element **210** detects a relaxation phenomenon of a magnetic field generated based on the plurality of AC currents in a portion of the measurement target **10**. Then, the internal information output part **566** generates and outputs an image corresponding to a magnetic resonance image indicating information about the inside of the measurement target **10** based on the change in impedance calculated by the calculating part **164**.

(116) In the operation of **S850**, the determining part **230** determines a location in the measurement target **10** to which the AC current corresponding to the eddy current generated by the deflection magnetic field in the second direction is to be applied, based on the image corresponding to the magnetic resonance image. In this way, the determining part **230** may determine a location in the measurement target **10** where the state is to be measured by applying the AC current, based on the image corresponding to the magnetic resonance image.

(117) <Combination of the First Configuration Example and Second Configuration Example>

(118) Further, the measurement apparatus **100** may be configured to be capable of quickly measuring an image of the inside of the measurement target **10** as described with the measurement apparatus **100** of the first configuration example. In this case, the control part **160** is further provided with the image information output part **166** that generates and outputs an image indicating information about the inside of the measurement target **10**. Then, the plurality of magnetic field detecting elements **130** respectively detect the magnitudes of magnetic fields based on electromagnetic waves generated and propagated in a portion of the measurement target **10** due to the application of the deflection magnetic field by the deflection magnetic field applying part **120**.

(119) Then, based on the detection results of the plurality of magnetic field detecting elements **130**, the calculating part **164** calculates the impedance distribution of at least a portion of the region where the electromagnetic wave propagates inside the measurement target **10**. Thus, the image information output part **166** generates an image indicating information about the inside of the measurement target **10**, based on the impedance distribution calculated by the calculating part **164**.

(120) As described in steps **S410** to **S480** of FIG. 4, the measurement apparatus **100** can quickly measure a tomographic image of the impedance distribution of the measurement target **10** and determine a measurement range in which the magnetic resonance image is to be observed. Then, as described in steps **S830** to **S850** of FIG. 8, the measurement apparatus **100** can determine a location where an internal state is to be observed by observing a magnetic resonance image. As a result, the measurement apparatus **100** can appropriately determine the internal position in the measurement target **10** to be observed and quickly measure the internal state, as described in **S860** to **S890** of FIG. 8.

(121) If the measurement apparatus **100** does not require a spatial resolution high enough to use a magnetic resonance image, the determining part **230** may determine the internal position to be observed based on the tomographic image of the impedance distribution of the measurement target **10**. The measurement apparatus **100** can measure the internal state of the measurement target **10** at a higher speed without using a magnetic resonance image. The measurement apparatus **100** may be configured for such purposes, and in this case, the relaxation detecting element **210** and the MR image generating part **220** need not be provided. In this case, the measurement apparatus **100** has

the function of the first configuration example described in FIG. 1 and the function of the second configuration example described in FIG. 6.

(122) <Configuration Example of the Detection Apparatus **600** and Configuration Added to the MR Image Measurement Apparatus>

(123) Although the measurement apparatus **100** of the second configuration example has been described as an independent apparatus, the present disclosure is not limited thereto. The measurement apparatus **100** may be an apparatus that functions by being added to an existing MR image measurement apparatus that outputs a magnetic resonance image, similarly to the detecting apparatus **400** described with reference to FIG. 5. FIG. 9 shows a configuration example of the detection apparatus **600** according to the present embodiment, together with the MR image measurement apparatus **300**.

(124) The MR image measurement apparatus **300** includes at least a configuration that operates in the same manner as the static magnetic field applying part **110**, the deflection magnetic field applying part **120**, the mounting part **140**, the moving part **150**, the display part **170**, the relaxation detecting element **210**, and the MR image generating part **220** according to the present embodiment. The MR image measurement apparatus **300** includes the control part **310** that controls each part in order to measure a magnetic resonance image. Since the measurement of the magnetic resonance image by the MR image measurement apparatus **300** is substantially the same as the operation described above, description thereof is omitted here.

(125) The detection apparatus **600** is provided in such an MR image measurement apparatus **300**. In this case, a combination of the MR image measurement apparatus **300** and the detecting apparatus **600** functions as at least a portion of the measurement apparatus **100** according to the present embodiment. The detection apparatus **600** includes the current applying part **510**, a plurality of the magnetic field detecting elements **130**, and the control part **160** including the storage part **162**, the calculating part **164**, the determining part **230**, and the internal information output part **566**.

(126) The detection apparatus **600** transmits and receives a control signal or the like to and from the MR image measurement apparatus **300** to generate and output information indicating the internal state of the measurement target **10**. Further, the detection apparatus **600** receives the magnetic resonance image generated by the MR image measurement apparatus **300**, and determines a position at which the internal state of the measurement target **10** is to be observed. Then, the detection apparatus **600** supplies a control signal instructing application of the AC current to the MR image measurement apparatus **300** based on the determined observation position for the internal state. Due to this, it is possible to configure the measurement apparatus **100** to be capable of acquiring the internal state of the measurement target **10** at high speed while utilizing existing equipment or the like.

(127) In the measurement apparatus **100** of the second configuration example, an example has been described in which the abnormal state and the normal state of the measurement target **10** can be determined by applying the AC current to the measurement target **10** to which the static magnetic field is applied. It has been described that the location measured by the measurement apparatus **100** may be determined based on an image generated by the measurement apparatus **100** or the MR image measurement apparatus **300** of the first configuration example, but the present disclosure is not limited to this. If the apparatus is capable of outputting the inside of the measurement target **10** as an image, the measurement apparatus **100** can determine the location to be measured.

(128) For example, the measurement apparatus **100** may be combined with a device that outputs the inside of the measurement target **10** as an image by applying AC current oriented in a plurality of directions. Further, since the measurement apparatus **100** may be configured to include the current applying part **510** for applying the AC current to the measurement apparatus **100**, the measurement apparatus **100** can have such a function. The following describes an apparatus having such a function.

(129) <Third Configuration Example of the Measurement Apparatus **100**, and Measurement of an Internal Image of the Measurement Target by Applying a Current>

(130) FIG. **10** shows a third configuration example of the measurement apparatus **100** according to the present embodiment, together with the measurement target **10**. The measurement apparatus **100** of the third configuration example applies an AC current to the measurement target **10** without applying a static magnetic field to the measurement target **10**, and outputs the inside of the measurement target **10** as an image. As described above, the measurement apparatus **100** determines the abnormal state and the normal state of the measurement target **10** by applying the static magnetic field and the AC current to the measurement target **10**.

(131) The measurement apparatus **100** includes the static magnetic field applying part **110**, the magnetic field detecting element **130**, the mounting part **140**, the moving part **150**, the control part **160**, the display part **170**, the determining part **230**, and the current applying part **510**. In other words, the measurement apparatus **100** of the third configuration example has substantially the same configuration as the measurement apparatus **100** of the second configuration example, and components that are substantially the same as those of the measurement apparatus **100** of the second configuration example shown in FIG. **6** are denoted by the same reference numerals and description thereof is omitted.

(132) A plurality of current applying parts **510** are provided around the measurement target. The current applying parts **510** apply a plurality of AC currents oriented in a plurality of directions, toward a portion of the measurement target **10**. A plurality of the magnetic field detecting elements **130** are disposed around the measurement target **10**, and each of the magnetic field detecting elements **130** detects the magnitude of a magnetic field generated from a portion of the measurement target **10** according to the plurality of applied AC currents. In this case, the calculating part **164** calculates the impedance distribution inside the measurement target based on the detection results of the plurality of magnetic field detecting elements **130**.

(133) When the static magnetic field is not being applied to the measurement target **10**, the impedance distribution calculated by the calculating part **164** is an impedance distribution corresponding to a line of electric force generated by the application of the AC current to the inside of the measurement target **10**. When the calculating part **164** calculates the impedance distribution by applying the AC currents to the inside of the measurement target **10** from a plurality of directions, the impedance distribution corresponding to the internal structure of the measurement target **10** can be acquired.

(134) Accordingly, the internal information output part **566** can generate and output an image indicating the information about the inside of the measurement target **10**, based on the calculated impedance distribution. The internal information output part **566** generates a tomographic image of a portion of the measurement target **10** by processing the impedance distribution using a known numerical analysis or the like, for example. In this way, the measurement apparatus **100** of the third configuration example can output a tomographic image of the measurement target **10** at a higher speed and more simply than an MR measurement apparatus or the like.

(135) At least some of the current applying parts **510** may sweep the frequency of the AC current applied to the measurement target **10**. In this case, the calculating part **164** can calculate the frequency characteristic of the impedance corresponding to the frequency of the AC current. The internal information output part **566** can then generate the internal state of the measurement target **10** based on the frequency characteristic of the impedance.

(136) Inside the measurement target **10**, an induction magnetic field is generated in response to the applied AC current. The frequency of the generated induction magnetic field corresponds to the frequency of the applied AC current. Therefore, when the frequency of the AC current is swept while the location at which the AC current is applied is fixed, a spectrum distribution of the induction magnetic field generated can be acquired. The spectrum distribution of the induction magnetic field is a spectrum distribution corresponding to an organ or the like of the human body,

for example.

(137) Therefore, by analyzing the spectrum distribution of the induction magnetic field, the organ at the location where the AC current is applied can be distinguished. The spectrum distribution of the induction magnetic field can be different between normal cells and abnormal cells, even in the same organ. Accordingly, based on the spectrum distribution of the induction magnetic field, it is possible to determine whether or not the organ at the location where the AC current is applied is normal. As an example, the internal information output part **566** compares the acquired spectrum distribution with the spectrum distribution of a normal organ measured in the past, to determine whether or not the location where the AC current is applied is normal.

(138) The determining part **230** determines a location in the measurement target **10** at which the state is to be detected by applying the AC current with the current applying part **510**, based on the image indicating the internal information of the measurement target **10** generated by the internal information output part **566**. For example, the determining part **230** receives information of a location to be detected from a user of the measurement apparatus **100**. Here, the user can determine the location to be detected from an image inside the measurement target **10** including information of the organ. Then, the measurement apparatus **100** measures the state at the determined location by applying the static magnetic field and the AC current to the determined location as described with reference to FIG. **6**, for example.

(139) <Example of an Operation Flow of the Measurement Apparatus **100** of the Third Configuration Example>

(140) FIG. **11** shows an example of an operation flow of the measurement apparatus **100** of the third configuration example. The measurement apparatus **100** outputs information about the internal state of the measurement target **10** by executing the operation flow from **S1110** to **S1180**.

(141) First, the control part **160** receives a measurement start instruction for the measurement target **10** from a user or the like (**S1110**). Here, it is assumed that the measurement target **10** is disposed so as to have a predetermined positional relationship with respect to the static magnetic field applying part **110**, the magnetic field detecting element **130**, and the current applying part **510**. The control part **160** further receives information about the measurement range of the measurement target **10**. The control part **160** receives an instruction for a measurement range such as a head, a neck, a chest, an abdomen, a waist, a leg, the whole body, or the like. In accordance with the received information, the control part **160** controls the moving part **150** to move the mounting part **140** to the measurement start point of the measurement range.

(142) Next, the plurality of current applying parts **510** apply AC currents in a plurality of directions toward the determined position inside the measurement target **10** (**S1120**). The plurality of magnetic field detecting elements **130** detect the magnitudes of magnetic fields generated in a portion of the measurement target **10** due to the application of the AC currents, around the measurement target **10** (**S1130**). The plurality of current applying parts **510** apply the plurality of AC currents one by one to the measurement target **10** in a predetermined order, for example. In this case, the application of the current in **S1120** and the detection of the magnetic field in **S1130** may be repeated. Further, at least some of the current applying parts **510** among the plurality of current applying parts **510** may sweep the frequency of the AC current applied to the measurement target **10**.

(143) Next, the calculating part **164** calculates the impedance distribution inside the measurement target **10** based on the detection result of the magnetic field (**S1140**). The internal information output part **566** generates and outputs an image indicating information about the inside of the measurement target **10**, based on the impedance distribution (**S1150**). By executing the operation flow from **S1110** to **S1150** a plurality of times, images of a plurality of locations may be acquired.

(144) Next, the determining part **230** determines a location in the measurement target **10** at which the state is to be observed by applying the AC current with the current applying part **510**, based on the image of the inside of the measurement target **10** generated by the internal information output

part **566** (S1160). For example, the determining part **230** receives an input of a location to be observed from a user of the measurement apparatus **100** who has confirmed an image of the inside of the measurement target **10** displayed on the display part **170**. Further, the determining part **230** may determine a location where the state is to be observed, by using image analysis.

(145) Next, the static magnetic field applying part **110** applies a static magnetic field having a constant magnitude in the first direction to the measurement target **10** (S1170). The static magnetic field applying part **110** applies a static magnetic field having a predetermined intensity level to the measurement target **10**. Then, the measurement apparatus **100** generates and outputs information about the internal state of the measurement target **10** (S1180). Note that since the operation of S1180 is the same as the operations of S860 to S890 described with reference to FIG. 8, description thereof is omitted here.

(146) In the manner described above, the measurement apparatus **100** according to the third configuration example determines the location where the internal state of the measurement target **10** is to be measured, based on the image of the inside of the measurement target **10** acquired by applying the AC current in a plurality of directions. Thus, the measurement apparatus **100** can appropriately determine the location to be observed using the positional information of the measurement target **10** measured with high spatial resolution, and can quickly measure the internal state.

(147) The measurement apparatus **100** of the third configuration example may measure the internal state of the measurement target **10** by sweeping the frequency of the AC current applied to the measurement target **10** by the current applying part **510**. In this case, the measurement apparatus **100** does not perform the operation of S1170, and applies the AC current from the current applying part **510** to the position inside of the measurement target **10** where the state is to be observed, as determined by the determining part **230**, thereby sweeping the frequency of the AC current. Then, the calculating part **164** calculates the frequency characteristic of the impedance corresponding to the frequency of the AC current, and the internal information output part **566** generates and outputs the internal state of the measurement target **10** based on the frequency characteristic of the impedance (S1180). In such a measurement apparatus **100**, the static magnetic field applying part **110** may be omitted.

(148) As described above, the measurement apparatus **100** can acquire a tomographic image of the inside of the measurement target **10** with a simple configuration in which AC current is applied to the measurement target **10** from a plurality of directions and the generated magnetic field is detected. Thus, the measurement apparatus **100** can determine a location at which the internal state is to be measured in the measurement target **10** based on the acquired tomographic image and measure the state at this location, with a simpler configuration. Further, since the measurement apparatus **100** can acquire the tomographic image of the measurement target **10** and measure the internal state using the common current applying part **510** and magnetic field detecting element **130**, the configuration of the apparatus can be simplified and the cost of the apparatus can be reduced.

(149) <Modified example of the Measurement Apparatus **100** of the Third Configuration Example>

(150) The measurement apparatus **100** of the third configuration example described above may be combined with the other configurations described in the measurement apparatus **100** of the first configuration example and the measurement apparatus **100** of the second configuration example. For example, as described with reference to FIG. 7, the measurement apparatus **100** of the third configuration example may further include the deflection magnetic field applying part **120**, the relaxation detecting element **210**, and the MR image generating part **220**, and may have a function of measuring a magnetic resonance image. In this case, the determining part **230** determines a location in the measurement target **10** where the magnetic resonance image is to be measured, based on the internal image of the measurement target **10** generated by the internal information output part **566**. Then, based on the magnetic resonance image generated by the MR image

generating part **220**, the determining part **230** determines a location in the measurement target **10** at which the state is to be detected by applying an AC current with the current applying part **510**.

(151) In this case, for example, the measurement apparatus **100** acquires a tomographic image of one or more regions of the measurement target **10** by executing one or more operation flows from **S1110** to **S1150** in FIG. **11**. As an example, the measurement apparatus **100** generates tomographic images at a plurality of different locations in the human body.

(152) Then, the determining part **230** determines a location where a sharper magnetic resonance image is to be measured. As an example, one location where a sharper image is to be obtained is determined from the plurality of tomographic images of the human body. Next, the magnetic resonance image is measured by executing the operation flow from **S820** to **S840** in FIG. **8**. Also, by further executing the operation flow from **S850** to **S890** in FIG. **8**, the state at the location determined from the magnetic resonance image may be measured. Instead of the operations from **S860** to **S890**, the current applying part **510** may sweep the frequency of the AC current applied to the measurement target **10** to measure the state at the location determined from the magnetic resonance image.

(153) As described above, the measurement apparatus **100** can determine the location where the magnetic resonance image is to be measured by easily obtaining more tomographic images at high speed. Then, the measurement apparatus **100** can determine the location at which the state is to be measured, by using a sharp magnetic resonance image.

(154) Further, the measurement apparatus **100** of the third configuration example may be an apparatus that functions by being added to an existing MR image measurement apparatus that outputs a magnetic resonance image, similarly to the detecting apparatus **400** described in FIG. **5** and the detecting apparatus **600** described in FIG. **9**. Such a measurement apparatus **100** of the third configuration example has substantially the same configuration as the configuration of FIG. **9**. In addition, as described with reference to FIG. **10**, such an apparatus applies a plurality of AC currents to output an image of the inside of the measurement target **10**.

(155) For example, a plurality of current applying parts **510** are provided around the measurement target **10**, and apply a plurality of AC currents oriented in a plurality of directions toward a portion of the measurement target **10**. A plurality of magnetic field detecting elements **130** are disposed around the measurement target **10**, and detect magnetic fields generated by the application of the plurality of AC currents. The calculating part **164** calculates the impedance distribution inside the measurement target **10** based on the detection results of the plurality of magnetic field detecting elements **130**. Then, the internal information output part **566** generates and outputs an image indicating information about the inside of the measurement target **10**, based on the calculated impedance distribution.

(156) Further, at least a part of the plurality of current applying parts **510** may sweep the frequency of the AC current applied to the measurement target **10**. In this case, the calculating part **164** calculates the frequency characteristic of the impedance corresponding to the frequency of the AC current, and the internal information output part **566** generates information indicating the internal state of the measurement target **10** based on the calculated frequency characteristic of the impedance.

(157) The measurement apparatus **100** of the third configuration example functions as an apparatus combined with the MR image measurement apparatus **300**, as described above. Thus, the measurement apparatus **100** can apply a plurality of AC currents to the measurement target **10** to generate an image indicating information about the inside of the measurement target **10**. Further, the determining part **230** can determine a location in the measurement target **10** at which the MR image measurement apparatus **300** is to measure the magnetic resonance image, based on the image of the inside of the measurement target **10** generated by the internal information output part **566**.

(158) Then, based on the magnetic resonance image generated by the MR image measurement apparatus **300**, the determining part **230** can determine the location in the measurement target **10** to

be measured by applying the AC current with the current applying part **510**. The measurement apparatus **100** can measure the internal state by applying the AC current to the determined position. In this way, it is possible to configure the measurement apparatus **100** to be capable of acquiring an image and a state of the inside of the measurement target **10** at high speed, while utilizing existing equipment or the like.

(159) In the measurement apparatus **100** of the third configuration described above, an example is described in which the measurement apparatus **100** is combined with an apparatus that outputs a sharper MR image, but the present disclosure is not limited thereto. The measurement apparatus **100** may be configured as an independent apparatus for obtaining a tomographic image. For example, the measurement apparatus **100** may be an apparatus including a plurality of the current applying parts **510**, a plurality of the magnetic field detecting elements **130**, the calculating part **164**, and the internal information output part **566**.

(160) In this case, a plurality of the magnetic field detecting elements **130** are provided around the measurement target **10**, and at least some of the plurality of current applying parts **510** sweep the frequency of the AC current applied to the measurement target **10**, for example. Then, the calculating part **164** calculates the impedance of a portion of the measurement target **10** and the frequency characteristic of the impedance corresponding to the frequency of the AC current, based on the detection results of the plurality of magnetic field detecting elements **130**. Thus, the internal information output part **566** can generate an image based on the calculated impedance distribution, and an internal state of the measurement target **10** based on the frequency characteristic of the impedance.

(161) In other words, the measurement apparatus **100** of the third configuration example can measure an image of the inside of the measurement target **10** and an internal state, by applying an AC current to the measurement target **10** without applying a magnetic field. The measurement apparatus **100** may further include the mounting part **140** and the moving part **150** described above.

(162) In the measurement apparatus **100** according to the present embodiment described above, an example has been described in which an AC current or the like is applied to a living body serving as the measurement target **10** in order to acquire information about the inside of the living body, but the present disclosure is not limited thereto. The measurement apparatus **100** may be used for searching for living bodies, or may be used for measuring vital activity of a living body, for example. The following describes such a measurement apparatus **100**.

(163) <Fourth Configuration Example of the Measurement Apparatus **100**>

(164) FIG. **12** shows a fourth configuration example of the measurement apparatus **100** according to the present embodiment, together with the measurement target **10**. The measurement apparatus **100** of the fourth configuration example includes a plurality of the current applying parts **510**, the magnetic field detecting element **130**, the calculating part **164**, and the internal information output part **566**. As described above, the measurement apparatus **100** is desirably configured as an apparatus independent of the apparatus for outputting the MR image. The measurement apparatus **100** searches for a living body that is trapped in the measurement target **10**, with the measurement target **10** being the ground, rubble, a building, or the like.

(165) The plurality of current applying parts **510** apply a plurality of AC currents oriented in a plurality of directions, from a plurality of positions in the measurement target **10** toward portions of the measurement target **10**, through the pair of electrodes. The magnetic field detecting element **130** detects the magnitude of the magnetic field generated from the portions of the measurement target **10** according to the plurality of AC currents. A plurality of the magnetic field detecting elements **130** may be provided. Even though the portion of the measurement target **10** to which the AC current is applied is not a living body, if a magnetic field is generated by electromagnetic induction, the magnetic field detecting element **130** detects the magnitude of the generated magnetic field. If a magnetic field hardly occurs in the portion to which the AC current is applied, the detection amount of the magnetic field by the magnetic field detecting element **130** becomes

zero.

(166) The calculating part **164** calculates the impedance of the portion of the measurement target **10** based on the detection result of the magnetic field detecting element **130**. The internal information output part **566** generates information including internal components of the measurement target **10**, based on the calculated impedance. For example, the value of the impedance varies depending on the component of the portion to which the AC current is applied, such as a living body, soil, concrete, stone, or wood. Accordingly, it is possible to determine whether or not a living body exists in the measurement target **10** even in a state where a person is trapped in the ground, under rubble, in a building, or the like due to a natural disaster or the like and where the living body cannot be visually recognized from outside the measurement target **10**.

(167) In the measurement apparatus **100** of the fourth configuration example, it is desirable to apply AC current to a plurality of portions of the measurement target **10** to measure whether or not a living body exists in the plurality of portions. In this case, it is desirable that the measurement apparatus **100** measures the impedance distribution of a predetermined region of the measurement target **10** and measures the range of impedance corresponding to a living body. Thus, since the measurement apparatus **100** can generate an image of a predetermined region corresponding to the impedance distribution, the user or the like can determine whether a person exists or some other animal or the like exists inside the measurement target **10**, by visually recognizing the size, the schematic shape, and the like of the living body.

(168) Further, the measurement apparatus **100** may measure the impedance inside the measurement target **10** while comparing the impedance of each portion. For example, the current applying part **510** applies a plurality of AC currents to a first portion and a second portion of the measurement target **10**. Then, the calculating part **164** calculates a first impedance based on the detection result of the magnetic field generated from the first portion of the measurement target **10** according to the plurality of AC currents, and a second impedance based on the detection result of the magnetic field generated from the second portion of the measurement target **10** according to the plurality of AC currents. The internal information output part **566** generates information including at least one component of the first portion and the second portion by comparing the calculated first impedance and the second impedance.

(169) In this case, the calculating part **164** may calculate the absolute value of the impedance of a part of the measurement target **10**, or may calculate the relative value of the impedance, instead of or in addition to the absolute value. Thus, even when the calculating part **164** calculates the relative value of the impedance, if the measurement apparatus **100** measures the second portion after measuring the first portion, for example, it is possible to confirm whether or not the second portion is the same component as the first portion. Further, the user of the measurement apparatus **100** can determine a third portion to be measured next, by referring to the comparison result between the second portion and the first portion.

(170) At least some of the plurality of current applying parts **510** may sweep the frequency of the AC current applied to the measurement target **10**. The calculating part **164** calculates a frequency characteristic of a portion of the impedance of the measurement target **10** based on the detection result of the magnetic field detecting element **130**. Due to this, the internal information output part **566** can acquire the spectrum distribution of the induction magnetic field generated in a portion of the measurement target **10**, so that the information of the components in this portion of the measurement target **10** can be generated more accurately.

(171) Further, the measurement apparatus **100** of the fourth configuration example may measure a change over time of the impedance in a portion of the measurement target **10**. In this case, the current applying part **510** continuously applies a plurality of AC currents for a predetermined period to at least a portion of the measurement target **10**. The magnetic field detecting element **130** detects a change over time of the magnitude of the magnetic field generated in a portion of the measurement target **10**. The calculating part **164** calculates the impedance of a portion of the

measurement target **10** a plurality of times in a predetermined period, and outputs the change over time of the impedance.

(172) For example, a person trapped in the ground, under rubble, in a building, or the like, performs vital activity such as breathing as long as the person survives, even in a situation where the person cannot move freely. Therefore, the change over time of the impedance of the measurement target **10** corresponds to a change accompanying such vital activity. For example, when a change in the position of an organ due to breathing, a change in the position of a person due to movement of the person, a change in the position of rubble or the like due to movement of the person, or the like occurs in a portion where AC current is being applied, the impedance changes over time.

(173) The internal information output part **566** generates information including internal components of the measurement target **10** based on such a change over time of the impedance of a portion of the measurement target **10**. For example, the internal information output part **566** outputs information that a living body is moving, in response to a change over time of the impedance. The internal information output part **566** may output information indicating that a component corresponding to the impedance has changed over time.

(174) Further, when the AC current is applied to a plurality of portions of the measurement target **10** to measure a change over time of the impedance of the plurality of portions, the internal information output part **566** may convert the change of the impedance of the plurality of portions into an image or the like and output the image. Thus, the user of the measurement apparatus **100** can determine that a person, an animal, or the like is performing vital activity inside the measurement target **10**.

(175) The measurement apparatus **100** of the fourth configuration example described above may be formed as an apparatus housed in a single chassis. In this case, the measurement apparatus **100** may further be provided with wheels or the like so as to be movable on the ground, for example. In this case, the measurement apparatus **100** may be formed so as to be self-propelled. In the measurement apparatus **100**, at least a portion including the current applying part **510** and the magnetic field detecting element **130** may be formed separately from the apparatus body. As described above, it is desirable that the measurement apparatus **100** of the fourth configuration example is formed so as to be able to perform measurement while moving to a plurality of positions on the ground of a field, on rubble, or the like.

(176) The present disclosure has been described above on the basis of the exemplary embodiments. The technical scope of the present disclosure is not limited to the scope explained in the above embodiments, and it is obvious to those skilled in the art that various changes and modifications within the scope of the disclosure may be made. An aspect to which such changes and modifications are added can be included in the technical scope of the present disclosure is obvious from the description of the claims.

Claims

1. A measurement apparatus comprising: a static magnetic field applying part that applies a static magnetic field having a constant magnitude in a first direction to a measurement target; a plurality of current applying parts that apply a plurality of AC currents oriented in a plurality of directions toward a portion of the measurement target, via a pair of electrodes; a magnetic field detecting element that detects a magnitude of a magnetic field of an electromagnetic wave generated due to nuclear magnetic resonance in the portion of the measurement target generated in response to (i) the static magnetic field having the constant magnitude in the first direction and (ii) the plurality of AC currents; a calculating part that calculates impedance of the portion of the measurement target based on a detection result of the magnetic field detecting element; and an internal information output part that generates information including an internal component of the measurement target, based on the calculated impedance, wherein the current applying parts apply the plurality of AC

currents to a first portion and a second portion of the measurement target; the calculating part calculates a first impedance based on a detection result of a magnetic field generated from the first portion of the measurement target according to the plurality of AC currents, and a second impedance based on a detection result of a magnetic field generated from the second portion of the measurement target according to the plurality of AC currents; and the internal information output part generates information including at least one component of the first portion and the second portion, by comparing the calculated first impedance and the calculated second impedance.

2. The measurement apparatus according to claim 1, further comprising: a mounting part which has a ring shape or a partial ring shape surrounding the measurement target, and on which one or more of the plurality of the current applying parts are mounted; and a moving part that moves the mounting part in a predetermined direction while maintaining a direction of the AC currents generated by the one or more current applying parts with respect to the measurement target.

3. The measurement apparatus according to claim 2, wherein a plurality of the magnetic field detecting elements are provided around the measurement target; and the mounting part has one or more of the magnetic field detecting elements mounted thereon.

4. A measurement apparatus comprising: a static magnetic field applying part that applies a static magnetic field having a constant magnitude in a first direction to a measurement target; a plurality of current applying parts that apply a plurality of AC currents oriented in a plurality of directions toward a portion of the measurement target, via a pair of electrodes; a magnetic field detecting element that detects a magnitude of a magnetic field of an electromagnetic wave generated due to nuclear magnetic resonance in the portion of the measurement target generated in response to (i) the static magnetic field having the constant magnitude in the first direction and (ii) the plurality of AC currents; a calculating part that calculates impedance of the portion of the measurement target based on a detection result of the magnetic field detecting element; and an internal information output part that generates information including an internal component of the measurement target, based on the calculated impedance, wherein the current applying parts apply the plurality of AC currents continuously for a predetermined period in at least the portion of the measurement target; the calculating part calculates the impedance of the portion of the measurement target a plurality of times in the predetermined period; and the internal information output part generates the information including the internal component of the measurement target, based on a change over time of the impedance of the portion of the measurement target.

5. The measurement apparatus according to claim 4, further comprising: a mounting part which has a ring shape or a partial ring shape surrounding the measurement target, and on which one or more of the plurality of the current applying parts are mounted; and a moving part that moves the mounting part in a predetermined direction while maintaining a direction of the AC currents generated by the one or more current applying parts with respect to the measurement target.

6. The measurement apparatus according to claim 5, wherein a plurality of the magnetic field detecting elements are provided around the measurement target; and the mounting part has one or more of the magnetic field detecting elements mounted thereon.

7. A measurement apparatus comprising: a static magnetic field applying part that applies a static magnetic field having a constant magnitude in a first direction to a measurement target; a plurality of current applying parts that apply a plurality of AC currents oriented in a plurality of directions toward a portion of the measurement target, via a pair of electrodes; a magnetic field detecting element that detects a magnitude of a magnetic field of an electromagnetic wave generated due to nuclear magnetic resonance in the portion of the measurement target generated in response to (i) the static magnetic field having the constant magnitude in the first direction and (ii) the plurality of AC currents; a calculating part that calculates impedance of the portion of the measurement target based on a detection result of the magnetic field detecting element; and an internal information output part that generates information including an internal component of the measurement target, based on the calculated impedance, wherein a plurality of the magnetic field detecting elements are

provided around the measurement target; at least some of the plurality of current applying parts sweep a frequency of one or more of the AC currents applied to the measurement target; the calculating part calculates the impedance of the portion of the measurement target and a frequency characteristic of the impedance corresponding to the frequency of each AC current and the impedance of the portion of the measurement target, based on detection results of the plurality of magnetic field detecting elements; and the internal information output part generates information including an internal state of the measurement target, based on the calculated frequency characteristic of the impedance.

8. The measurement apparatus according to claim 7, wherein the internal information output part further generates an image of the inside of the measurement target, based on the calculated impedance; and the measurement apparatus further comprises a determining part that determines a location in the measurement target at which a state is to be observed by applying the AC currents with the current applying parts, based on the image of the inside of the measurement target generated by the internal information output part.

9. The measurement apparatus according to claim 7, further comprising: a mounting part which has a ring shape or a partial ring shape surrounding the measurement target, and on which one or more of the plurality of the current applying parts are mounted; and a moving part that moves the mounting part in a predetermined direction while maintaining a direction of the AC currents generated by the one or more current applying parts with respect to the measurement target.

10. The measurement apparatus according to claim 9, wherein a plurality of the magnetic field detecting elements are provided around the measurement target; and the mounting part has one or more of the magnetic field detecting elements mounted thereon.

11. A measurement apparatus comprising: a static magnetic field applying part that applies a static magnetic field having a constant magnitude in a first direction to a measurement target; a plurality of current applying parts that apply a plurality of AC currents oriented in a plurality of directions toward a portion of the measurement target, via a pair of electrodes; a magnetic field detecting element that detects a magnitude of a magnetic field of an electromagnetic wave generated due to nuclear magnetic resonance in the portion of the measurement target generated in response to (i) the static magnetic field having the constant magnitude in the first direction and (ii) the plurality of AC currents; a calculating part that calculates impedance of the portion of the measurement target based on a detection result of the magnetic field detecting element; and an internal information output part that generates information including an internal component of the measurement target, based on the calculated impedance, further comprising: a deflection magnetic field applying part that applies a deflection magnetic field having a predetermined frequency and oriented in a second direction, which is different from the first direction, toward the portion of the measurement target, via a coil; a relaxation detecting element that detects a relaxation phenomenon of an electromagnetic wave based on the deflection magnetic field generated by the deflection magnetic field applying part, in the portion of the measurement target; and an MR image generating part that generates and outputs a magnetic resonance image, which is a tomographic image of the inside of the measurement target, based on a detection result of the relaxation detecting element.

12. The measurement apparatus according to claim 11, further comprising: a determining part that determines a location to be measured in the measurement target by applying the AC currents with the current applying parts, based on the magnetic resonance image generated by the MR image generating part.

13. The measurement apparatus according to claim 12, wherein the internal information output part further generates an image of the inside of the measurement target, based on the calculated impedance; and the determining part determines the location in the measurement target at which the magnetic resonance image is to be measured, based on the image of the inside of the measurement target generated by the internal information output part.

14. A measurement apparatus comprising: a static magnetic field applying part that applies a static

magnetic field having a constant magnitude in a first direction to a measurement target; a plurality of current applying parts that apply a plurality of AC currents oriented in a plurality of directions toward a portion of the measurement target, via a pair of electrodes; a magnetic field detecting element that detects a magnitude of a magnetic field of an electromagnetic wave generated due to nuclear magnetic resonance in the portion of the measurement target generated in response to (i) the static magnetic field having the constant magnitude in the first direction and (ii) the plurality of AC currents; a calculating part that calculates impedance of the portion of the measurement target based on a detection result of the magnetic field detecting element; and an internal information output part that generates information including an internal component of the measurement target, based on the calculated impedance, wherein the measurement apparatus is provided in an MR image measurement apparatus that includes: the static magnetic field applying part; a deflection magnetic field applying part that applies a deflection magnetic field having a predetermined frequency and oriented in a second direction, which is different from the first direction, toward the portion of the measurement target, via a coil; a relaxation detecting element that detects an electromagnetic wave generated by the application of the deflection magnetic field and a relaxation phenomenon of the generated electromagnetic wave, in the portion of the measurement target; and an MR image generating part that generates and outputs a magnetic resonance image, which is a tomographic image of the inside of the measurement target, based on a detection result of the relaxation detecting element; at least some of the plurality of current applying parts sweep a frequency of one or more of the AC currents applied to the measurement target; the calculating part calculates a frequency characteristic of impedance corresponding to the frequency of each AC current; and the internal information output part generates information indicating an internal state of the measurement target, based on the calculated frequency characteristic of the impedance.

15. The measurement apparatus according to claim 14, further comprising: a determining part that determines a location in the measurement target at which the AC currents are to be applied by the current applying parts, based on the magnetic resonance image generated by the MR image generating part.

16. The measurement apparatus according to claim 15, wherein the internal information output part further generates an internal image of the measurement target, based on the calculated impedance; and the determining part determines the location in the measurement target at which the magnetic resonance image is to be measured, based on the internal image of the measurement target generated by the internal information output part.

17. A measurement method comprising: applying a static magnetic field having a constant magnitude in a first direction to a measurement target; applying a plurality of AC currents oriented in a plurality of directions toward a portion of the measurement target, via a pair of electrodes; detecting a magnitude of a magnetic field of an electromagnetic wave generated due to nuclear magnetic resonance in the portion of the measurement target generated in response to (i) the static magnetic field having the constant magnitude in the first direction and (ii) the plurality of AC currents; calculating impedance of the portion of the measurement target based on the detected magnitude of the magnetic field; and generating and outputting information indicating an internal component of the measurement target, based on the calculated impedance, wherein the applying the plurality of AC currents includes sweeping a frequency of one or more of the AC currents among the plurality of AC currents applied to the measurement target; the detecting the magnitude of the magnetic field generated from the portion of the measurement target includes detecting the magnitude of the magnetic field generated from the portion of the measurement target in accordance with the plurality of AC currents, at each of a plurality of positions around the measurement target; the calculating the impedance of the portion of the measurement target includes calculating a frequency characteristic of the impedance corresponding to a frequency of each AC current; and the generating information indicating the internal component of the measurement target includes generating information including an internal state of the measurement

target based on the calculated frequency characteristic of the impedance.

18. The measurement method according to claim 17, comprising: applying the plurality of AC currents oriented in the plurality of directions, from around the measurement target toward the portion of the measurement target, via the pair of electrodes; detecting the magnitude of the magnetic field generated from the portion of the measurement target in response to the AC currents, at a plurality of positions around the measurement target; calculating the impedance of the portion of the measurement target based on the detected magnitude of the magnetic field; generating an image of the inside of the measurement target, based on the calculated impedance; determining a location to be measured in the measurement target by applying the AC currents, based on the image of the inside the measurement target; and after the determining the location to be measured by applying the AC currents, repeating the measurement method to generate information indicating a state of the determined location to be measured.

19. The measurement method according to claim 17, comprising: applying the plurality of AC currents oriented in the plurality of directions, from around the measurement target toward the portion of the measurement target via the pair of electrodes; detecting the magnitude of the magnetic field generated from the portion of the measurement target in response to the AC currents, at a plurality of positions around the measurement target; calculating the impedance of the portion of the measurement target based on the detected magnitude of the magnetic field; generating an image of the inside of the measurement target based on the calculated impedance; determining a location in the measurement target where a magnetic resonance image is to be generated, based on the image of the inside of the measurement target; applying a static magnetic field having a constant magnitude in the first direction to the measurement target; applying a deflection magnetic field having a predetermined frequency and oriented in a second direction, which is different from the first direction, toward the determined location in the measurement target where the magnetic resonance image is to be generated, via a coil; detecting an electromagnetic wave generated due to the application of the deflection magnetic field oriented in the second direction and a relaxation phenomenon of the generated electromagnetic wave, in the portion to be measured; generating and outputting the magnetic resonance image, which is a tomographic image of the inside of the measurement target, based on the detected electromagnetic wave; determining a location to be measured in the measurement target by applying the AC currents, based on the magnetic resonance image; and after the determining the location to be measured by applying the AC currents, repeating the measurement method to generate information indicating a state of the determined location to be measured.
