

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407095
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Tong; Youwan et al.

Antenna assembly and communication device

Abstract

An antenna assembly includes a lens, a guide rail, an antenna array, and a phase shifter. The lens has a first refractive surface. The guide rail is a linear guide rail and is located on one side of the first refractive surface of the lens. The antenna array includes a plurality of radiating elements. The antenna array is slidably connected to the guide rail. As the antenna array moves on the guide rail, a beam pointing direction of the antenna assembly moves in an extension direction of the guide rail, to perform mechanical beam sweeping within a first sweeping range in the extension direction of the guide rail. The phase shifter is connected to the plurality of radiating elements and is configured to adjust feed phases of the plurality of radiating elements, to perform phase modulation sweeping within a second sweeping range.

Inventors:	Tong; Youwan (Xi'an, CN), Fang; Ren (Shenzhen, CN)
Applicant:	Huawei Technologies Co., Ltd. (Shenzhen, CN)
Family ID:	81489979
Assignee:	HUAWEI TECHNOLOGIES CO., LTD. (Shenzhen, CN)
Appl. No.:	18/252820
Filed (or PCT Filed):	November 09, 2021
PCT No.:	PCT/CN2021/129497
PCT Pub. No.:	WO2022/100566
PCT Pub. Date:	May 19, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230420839 A1	Dec. 28, 2023

Foreign Application Priority Data

Publication Classification

Int. Cl.: H01Q3/14 (20060101); H01Q3/36 (20060101); H01Q15/02 (20060101)

U.S. Cl.:

CPC H01Q3/14 (20130101); H01Q3/36 (20130101); H01Q15/02 (20130101);

Field of Classification Search

CPC: H01Q (1/002); H01Q (1/241); H01Q (1/246); H01Q (3/14); H01Q (3/26); H01Q (3/32); H01Q (3/34); H01Q (3/36); H01Q (15/02); H01Q (15/08); H01Q (19/06); H01Q (19/062); H01Q (21/061); H01Q (21/062); H01Q (21/24); H01Q (25/008); H01Q (3/04); H01Q (5/42); H01Q (3/46); H01Q (3/2658); H01Q (25/04); H01Q (3/247); H01Q (3/30); H01Q (9/0421); H01Q (9/16); H01Q (19/08); H01Q (19/065); H01Q (1/1264); H01Q (19/175); H01Q (3/18); H01Q (3/12); H01Q (3/2664); H01Q (3/16); H01Q (19/12); H01Q (1/36); H01Q (21/065)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2017/0214145	12/2016	Elad	N/A	H01Q 19/175
2018/0183152	12/2017	Turpin	N/A	H01Q 25/008
2020/0091622	12/2019	Turpin et al.	N/A	N/A
2023/0231324	12/2022	Turpin	342/354	H01Q 25/008

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
205609758	12/2015	CN	N/A
109346843	12/2018	CN	N/A
109742555	12/2018	CN	N/A
110165403	12/2018	CN	N/A

Primary Examiner: Nguyen; Hoang V

Attorney, Agent or Firm: Conley Rose, P.C.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS

(1) This is a National Stage of International Patent Application No. PCT/CN2021/129497 filed on Nov. 9, 2021, which claims priority to Chinese Patent Application No. 202011267799.2 filed on Nov. 13, 2020. The disclosures of the aforementioned applications are hereby incorporated by reference in their entireties.

TECHNICAL FIELD

(2) This application relates to the field of terminal device technologies, and in particular, to an antenna assembly and a communication device.

BACKGROUND

(3) As a wireless broadband access device, customer premise equipment (customer premise equipment, CPE for short) may convert a signal sent by a base station into a Wi-Fi signal universal to mobile terminals such as a smartphone, a tablet computer, and a notebook computer, and may support a plurality of mobile terminals in accessing the internet at the same time. To enable a user to receive a high-quality signal, some existing CPEs are designed to extend performance of antennas of the CPEs, so that the antennas can support beam sweeping at a specific angle while a receive beam width is limited. Conventional antenna sweeping is generally performed through mechanical rotation sweeping, phased array sweeping, or the like. However, these sweeping manners have some disadvantages. For example, the mechanical rotation sweeping increases a profile height of an antenna, and consequently, the antenna occupies large space in CPE, which is not conducive to miniaturization of the CPE. The phased array sweeping causes a small beam sweeping range of CPE due to constraints such as a quantity of radiating elements and a quantity of phase shifters.

SUMMARY

(4) This application provides an antenna assembly and a communication device, to enable the antenna assembly to support beam sweeping within a large range.

(5) According to a first aspect, this application provides an antenna assembly, where the antenna assembly includes a lens, a guide rail, an antenna array, and a phase shifter. The lens includes a first refractive surface and a second refractive surface. The lens may be configured to converge a signal beam from one side of the first refractive surface into a narrow beam to be emergent from the second refractive surface, or may converge a signal beam from one side of the second refractive surface into a narrow beam to be emergent from the first refractive surface. The guide rail is a linear guide rail, and the guide rail may be disposed on one side of the first refractive surface of the lens. The antenna array includes a plurality of radiating elements arranged in an array. The antenna array is slidably connected to the guide rail. As the antenna array moves on the guide rail, a beam pointing direction of the antenna assembly moves in an extension direction of the guide rail, so that mechanical beam sweeping can be performed within a first sweeping range in the extension direction of the guide rail, to implement beam sweeping in the extension direction of the guide rail. The phase shifter is connected to the plurality of radiating elements and is configured to adjust feed phases of the plurality of radiating elements, so that when the antenna array is at different locations on the guide rail, phase modulation sweeping can be performed within a second sweeping range by adjusting the feed phases of the plurality of radiating elements, where the second sweeping range is a phase modulation sweeping angle at each sweeping location within the first sweeping range of the antenna array.

(6) In the foregoing solution, the antenna array is slidably connected to the guide rail, so that mechanical sweeping can be implemented by changing a location of the antenna array, and when the antenna array is at different locations, the phase shifter can be controlled to adjust the feed phases of the radiating elements, to implement phase modulation sweeping. Therefore, a sweeping range of the antenna assembly can be expanded generally, and the antenna assembly can obtain a higher gain. In addition, because the guide rail is of a linear structure, in this solution, a profile height of the antenna assembly can be further lowered while a gain of the antenna assembly can be increased, so that space occupied by the antenna assembly in the communication device can be reduced. This facilitates reduction of an overall volume of the communication device.

(7) In specific configuration, in the extension direction of the guide rail, both ends of the guide rail extend beyond corresponding ends of the lens. It is assumed that a length of one end of the guide rail extending beyond a corresponding end of the lens is l' , and l' satisfies: $l' \geq f \cdot \tan \theta$, where f is a

distance between the guide rail and the lens in a direction perpendicular to the extension direction of the guide rail, and θ is a maximum phase modulation sweeping angle that can be implemented during phase modulation sweeping by adjusting the feed phase of each radiating element through the phase shifter. In this solution, the sweeping range of the antenna array when the antenna array moves on the guide rail can be increased, and a risk that the antenna array slides off the guide rail can be further reduced.

(8) In some possible implementations, the lens may be specifically a convex lens. In this case, one convex surface of the convex lens may be formed as a first refractive surface, and the other convex surface of the convex lens may be formed as a second refractive surface. In the extension direction of the guide rail, an effective dielectric constant of the lens decreases from the middle to two sides, so that a signal beam converges when a signal is received or sent.

(9) In some possible implementations, the lens may be specifically a cylindrical lens. The lens includes a cylindrical surface and a flat surface that are connected in a circumferential direction. In an implementation, the cylindrical surface of the lens may be formed as a first refractive surface, and the flat surface of the lens may be formed as a second refractive surface. In another implementation, the flat surface of the lens may be formed as a first refractive surface, and the cylindrical surface of the lens may be formed as a second refractive surface.

(10) When the lens is the cylindrical lens, the extension direction of the guide rail is perpendicular to a length direction of the lens. In this case, in a direction of the guide rail, an effective dielectric constant of the lens decreases from the middle to two sides, so that a signal beam converges when a signal is received or sent.

(11) In some possible implementations, the guide rail may be located in a focal plane of the lens, so that when moving on the guide rail, the antenna array can receive a beam converged by the lens.

(12) In some possible implementations, the guide rail intersects the principal axis of the lens, and an included angle between the guide rail and the principal axis of the lens may range from 80° to 100° . Specifically, when the guide rail is located in the focal plane, the guide rail and the principal axis of the lens are vertically intersected, thereby improving signal transmission quality.

(13) In some possible implementations, the first sweeping range is parallel to the second sweeping range. In this case, the first sweeping range and the second sweeping range may be approximately located in a same plane. In other words, mechanical sweeping and phase modulation sweeping are performed in a same dimension. A sweeping range of the antenna assembly in the plane can be generally increased by combining the mechanical sweeping and the phase modulation sweeping.

(14) In some possible implementations, the first sweeping range and the second sweeping range may intersect each other. In other words, mechanical sweeping and phase modulation sweeping may be performed in two intersecting dimensions, to increase the sweeping range of the antenna assembly.

(15) To facilitate sliding connection between the antenna array and the guide rail, the antenna assembly may further include a sliding part. The antenna array is fixedly disposed on the sliding part, and the sliding part is slidably assembled on the guide rail. In this way, when sliding on the guide rail, the sliding part can drive the antenna array **21** to slide synchronously.

(16) In some possible implementations, the guide rail intersects the principal axis of the lens, and the antenna assembly may further include a driving mechanism. The driving mechanism is connected to the antenna array or the sliding part, and may be configured to drive the antenna array to slide on the guide rail, thereby improving operating reliability of the antenna assembly.

(17) In specific configuration, the driving mechanism may include a motor and a screw. The screw includes a screw rod and a nut assembled on the screw rod. The screw rod is connected to an output shaft of the motor, and the nut is connected to the antenna array or the sliding part. In this way, a rotation motion that is output by the motor can be converted into a linear motion that can drive the sliding part to move, and then the sliding part drives the antenna array to move synchronously.

(18) According to a second aspect, this application further provides a communication device. The

communication device includes a housing, a control unit disposed in the housing, and the antenna assembly in any one of the foregoing possible implementations. A lens of the antenna assembly is disposed on the housing, and a second refractive surface of the lens faces an outer side of the housing. The control unit is separately connected to a driving mechanism and a phase shifter, to control the driving mechanism to drive an antenna array to move on a guide rail, to perform beam sweeping in an extension direction of the guide rail. The control unit may further send a phase configuration signal to the phase shifter when the antenna array moves to each location, to control the phase shifter to adjust a feed phase of each radiating element, to adjust a beam pointing direction of the antenna assembly. The communication device may implement a large beam sweeping range, and because a profile height of the antenna assembly is small, a miniaturization design of the communication device is also facilitated.

(19) In some possible implementations, the lens and the housing may be of an integrated structure, to simplify an assembly process of the communication device and lower assembly difficulty.

Description

BRIEF DESCRIPTION OF DRAWINGS

- (1) FIG. 1 is a schematic diagram of a structure of an antenna assembly of existing CPE;
- (2) FIG. 2 is a front view of a communication device according to an embodiment of this application;
- (3) FIG. 3 is a top view of the communication device in FIG. 2;
- (4) FIG. 4 is a front view of a communication device according to another embodiment of this application;
- (5) FIG. 5 is a top view of the communication device in FIG. 4;
- (6) FIG. 6 is a front view of an antenna array according to an embodiment of this application;
- (7) FIG. 7 is a schematic diagram of a beam sweeping principle of an antenna array of the communication device in FIG. 4 at a location X;
- (8) FIG. 8 is a schematic diagram of a beam sweeping principle of an antenna array of the communication device in FIG. 4 at a location X';
- (9) FIG. 9 is a side view of the communication device in FIG. 5;
- (10) FIG. 10 is a schematic diagram of orientations of a base station and CPE;
- (11) FIG. 11 is a schematic diagram of a partial structure of an antenna assembly in an operating state according to an embodiment of this application;
- (12) FIG. 12 is a schematic diagram of a partial structure of an antenna assembly in another operating state according to an embodiment of this application;
- (13) FIG. 13 is a schematic diagram of a partial structure of an antenna assembly in an operating state according to another embodiment of this application;
- (14) FIG. 14 is a schematic diagram of a partial structure of an antenna assembly in another operating state according to another embodiment of this application;
- (15) FIG. 15 is a schematic diagram of a partial structure of an antenna assembly according to an embodiment of this application;
- (16) FIG. 16 is a top view of a communication device according to still another embodiment of this application; and
- (17) FIG. 17 is a schematic diagram of a specific application scenario of CPE according to an embodiment of this application.

REFERENCE NUMERALS

- (18) In the conventional technology: **01**—lens; **02**—antenna array; **03**—multiplexer switch.
- (19) In embodiments of this application: **100**—base station; **200**—CPE; **10**—housing; **20**—antenna assembly; **21**—antenna array; **22**—guide rail; **23**—lens; **24**—phase shifter; **11**—opening; **231**—

first refractive surface; **232**—second refractive surface; **25**—sliding part; **211**—radiating element; **261**—screw; **262**—nut; **27**—control unit; **210**—outdoor unit; **220**—indoor unit.

DESCRIPTION OF EMBODIMENTS

(20) To make the objectives, technical solutions, and advantages of this application clearer, the following further describes this application in detail with reference to the accompanying drawings.

(21) It should be noted that, in this specification, reference numerals and letters in the following accompanying drawings represent similar items. Therefore, once an item is defined in an accompanying drawing, the item does not need to be further defined or interpreted in the following accompanying drawings.

(22) In descriptions of this application, it should be noted that orientation or location relationships indicated by terms “center”, “above”, “below”, “left”, “right”, “vertical”, “horizontal”, “inner”, “outer”, and the like are orientation or location relationships based on the accompanying drawings, and are merely intended for conveniently describing this application and simplifying descriptions, rather than indicating or implying that an apparatus or an element in question needs to have a specific orientation or needs to be constructed and operated in a specific orientation, and therefore cannot be construed as a limitation on this application. In addition, terms “first” and “second” are merely used for a purpose of description, and shall not be understood as an indication or implication of relative importance.

(23) In descriptions of this application, it should be noted that unless otherwise expressly specified and limited, terms “mount”, “interconnect”, and “connect” should be understood in a broad sense. For example, the terms may indicate a fixed connection, a detachable connection, or an integral connection; may be a mechanical connection or an electrical connection; or may be direct interconnection, indirect interconnection through an intermediate medium, or communication between the interior of two elements. An ordinary technician in the art may understand specific meanings of the foregoing terms in this application based on a specific situation.

(24) For ease of understanding an antenna provided in embodiments of this application, the following first describes an application scenario of the antenna. The antenna provided in embodiments of this application may be applied to a communication device such as a base station or CPE, and is configured to enable the communication device to implement signal sending and receiving functions. Using the CPE as an example, the CPE is a wireless broadband access device, and may convert a signal sent by a base station into a Wi-Fi signal universal to mobile terminals such as a smartphone, a tablet computer, and a notebook computer, and may support a plurality of mobile terminals in accessing the internet at the same time. The CPE may be mounted indoors or outdoors. During actual deployment, for convenience of mounting, the CPE is generally directly placed at a specific location and then fixed. Because the CPE needs to receive a radio signal from the base station, and the base station needs to cover a plurality of users in an area during deployment, for a specific CPE user, a direction of arrival of the radio signal is undetermined. To enable a user to receive a high-quality signal, a conventional manner is to adjust a placement angle of the CPE to match the direction of arrival. However, during mounting the CPE, especially after the CPE is fixed, adjusting the placement angle of the CPE involves a large amount of work, and causes an increase in mounting costs.

(25) To resolve this problem, some existing CPEs are designed to extend performance of antennas of the CPEs, to enable the antennas to support large-angle beam sweeping while a receive beam width is limited. Therefore, a beam direction can be adjusted when a placement location and a placement angle of the CPE are fixed, so that a CPE user can receive a high-quality signal.

(26) Refer to FIG. 1. FIG. 1 is a schematic diagram of a structure of an antenna assembly of existing CPE. The antenna assembly includes a lens **01**, a plurality of antenna arrays **02**, and a multiplexer switch **03**. The antenna arrays **02** are distributed in an arc shape near a focal plane of the lens **01**. One end of the multiplexer switch **03** is connected to a radio frequency path of the CPE, and the other end of the multiplexer switch is separately connected to the plurality of antenna

arrays **02**. Switching performed between the antenna arrays **02** causes the radio frequency path to be connected to different antenna arrays **02**. It should be noted that a dashed line in FIG. **1** represents an arrangement manner of the plurality of antenna arrays, but does not represent an actual structure of the CPE. Because locations of the antenna arrays **02** are different, when the radio frequency path is switched to be connected to the antenna arrays **02**, beam directions of different antenna arrays **02** are different. In this way, an objective of beam sweeping can be achieved after beams that are output by different antenna arrays **02** pass through the lens **01**. However, this solution still has obvious disadvantages. First, because the plurality of antenna arrays **02** need to be disposed, manufacturing costs of the CPE are increased; second, the distribution of the plurality of antenna arrays **02** in an arc shape increases a profile height of the antenna assembly. As a result, the antenna assembly occupies large space in the CPE. This is not conducive to miniaturization of the CPE.

(27) Another common antenna that can implement beam sweeping is a phased array antenna. For the phased array antenna, phase differences between radiating elements are adjusted by using phase shifters, to change a pointing direction of a maximum value in an antenna directivity pattern, thereby achieving the objective of beam sweeping. However, due to factors such as a layout of the radiating elements, phase adjustment precision, and a restriction on quantities of the radiating elements and the phase shifters due to costs, a beam adjustment range of the antenna is small, and a gain of the antenna is low.

(28) Based on this, embodiments of this application provide an antenna assembly and a communication device to which the antenna assembly is applied. The antenna assembly has a small size, and can support beam sweeping in a large range, so that communication performance of the communication device can be improved. The following specifically describes, with reference to the accompanying drawings, the antenna assembly and the communication device provided in embodiments of this application.

(29) FIG. **2** is a front view of a communication device according to an embodiment of this application. FIG. **3** is a top view of the communication device in FIG. **2**. The communication device includes a housing **10**, a circuit board (not shown in the figure) disposed in the housing **10**, and an antenna assembly **20**. The antenna assembly **20** may include an antenna array **21**, a guide rail **22**, a lens **23**, and a phase shifter **24**. It should be noted that FIG. **3**, FIG. **4**, and the following related accompanying drawings show only some components included in the communication device as an example. Actual shapes, actual sizes, actual locations, and actual structures of these components are not limited by FIG. **3**, FIG. **4**, and the following accompanying drawings.

(30) For ease of description, a width direction of the communication device **1** is defined as an x-axis, a length direction of the communication device **1** is defined as a y-axis, and a thickness direction of the communication device is defined as a z-axis. It may be understood that a coordinate system of the communication device **1** may be flexibly set according to a specific actual requirement. In actual application, after the communication device **1** is mounted and fixed, the width direction of the communication device **1** may be set in a horizontal direction, and the length direction of the communication device **1** may be set in a vertical direction. In other words, in this embodiment of this application, an x-axis direction is the horizontal direction, and a y-axis direction is the vertical direction.

(31) The housing **10** is of a cavity structure, and may be configured to support and protect each element inside the communication device **1**. For example, the housing **10** may reduce impact on an internal element of the communication device **1**, prevent performance of the communication device **1** from being affected by displacement of the internal element, and ensure normal use of the communication device **1**. For another example, the housing **10** may further reduce direct contact between an external foreign matter, such as dust or water vapor, and the internal element, thereby reducing a risk of damage to the internal element.

(32) In addition, an opening **11** is provided on the housing **10**, so that a signal beam emitted by a

base station can be propagated to the lens **23** through the opening **11**, and a signal beam refracted by the lens **23** can be propagated to the base station through the opening **11**.

(33) Still refer to FIG. **3** and FIG. **4**. The lens **23** is disposed at the opening. The lens **23** includes a first refractive surface **231** and a second refractive surface **232**. The first refractive surface **231** faces an inner side of the opening **11**, and the second refractive surface **232** faces an outer side of the opening **11**. A material of the lens **23** may be a dielectric material that allows an electromagnetic wave to pass through. The lens may be configured to converge a signal beam (as shown by dashed lines in FIG. **3** and FIG. **4**) from one side of the first refractive surface **231** into a narrow beam to be emergent from the second refractive surface **232**, or converge a signal beam from one side of the second refractive surface **232** into a narrow beam to be emergent from the first refractive surface **231**, to improve a gain of the antenna assembly.

(34) In this embodiment, unless otherwise specified, dashed lines in FIG. **3**, FIG. **4**, and the following accompanying drawings all represent signal beams. It should be understood that the accompanying drawings merely show signal beams as an example, and an actual waveform, an actual propagation direction, and an actual propagation distance of the signal beam are not limited by FIG. **3**, FIG. **4**, and the following accompanying drawings.

(35) In some implementations, the lens **23** may be embedded in the opening **11**. In this way, a profile height (in other words, a size in a z-axis direction) of the communication device **1** can be reduced, so that a structure of the communication device **1** is more compact. In addition, difficulty in mounting and fixing the lens **23** can be further lowered. During specific implementation, the lens **23** may be fixed in the opening **11** by bonding. Alternatively, the lens may be fixed in the housing **10** by using a mechanical part such as a support. In this case, a cover may be disposed at the opening **11** to seal the housing **10**, to prevent an external foreign matter from entering the housing **10** to cause an adverse impact on a function of the communication device **1**.

(36) In some other implementations, the lens and the housing may alternatively be designed in an integrated manner. In other words, the lens and the housing may be of an integrated structure. In this case, no opening needs to be provided on the housing, and a step of assembling the lens and the housing may be canceled. Therefore, an assembly process of the communication device can be simplified, and assembly difficulty can be lowered.

(37) A type of the lens **23** is not limited. For example, in the embodiment shown in FIG. **3**, the lens **23** may be specifically a convex lens. In this case, the first refractive surface **231** is one convex surface of the lens **23**, and the second refractive surface **232** is the other convex surface of the lens **23**. When the lens **23** is fixed in the opening **11**, a principal axis of the lens **23** may be specifically set in the z-axis direction. It should be noted that, in this embodiment of this application, the principal axis of the lens **23** may be understood as an axis on which a propagation direction of a signal beam or light does not change after the signal beam or light passes through the lens **23**. For the convex lens, the principal axis is a straight line that passes through sphere centers of the two convex surfaces of the convex lens.

(38) FIG. **4** is a front view of a communication device according to another embodiment of this application. FIG. **5** is a top view of the communication device in FIG. **4**. Refer to FIG. **4** and FIG. **5** together. In this embodiment, a lens **23** may be specifically a cylindrical lens, and a length direction of the lens **23** is set in a y-axis direction. In addition, in a circumferential direction of the lens **23**, a cylindrical surface of the lens **23** may face an outer side of an opening **11**, and a flat surface of the lens **23** may face an inner side of the opening **11**. In this case, a first refractive surface **231** is the flat surface of the lens **23**, and a second refractive surface **232** is the cylindrical surface of the lens **23**.

(39) When the lens **23** is fixed in the opening **11**, an effective dielectric constant of the lens **23** decreases from the middle to two sides in a horizontal dimension (an x-axis direction). During specific implementation, a width direction of the lens **23** is set in the x-axis direction, a length direction of the lens **23** is set in the y-axis direction, and a principal axis of the lens **23** is set in a z-

axis direction. It should be noted that, in this embodiment of this application, for the cylindrical lens, the principal axis may be understood as a straight line that is perpendicular to the flat surface of the cylindrical lens and passes through a center of the flat surface.

(40) In some other implementations, in the circumferential direction of the lens **23**, the cylindrical surface of the lens **23** may alternatively face the inner side of the opening **11**, and the flat surface of the lens **23** may face the outer side of the opening **11**. In this case, the first refractive surface **231** is the cylindrical surface of the lens **23**, and the second refractive surface **232** is the flat surface of the lens **23**.

(41) Still refer to FIG. **4**. A guide rail **22** is fixed in a housing **10**, and is located on one side of the first refractive surface **231** of the lens **23**. During specific implementation, the guide rail **22** may be supported and fixed by using a mechanical part such as a support, or an end of the guide rail **22** may extend to contact an inner wall of the housing **10**, to be connected to the inner wall of the housing **10** by welding, bonding, or the like. An antenna array **21** is slidably disposed on the guide rail **22**. The antenna array **21** is connected to a radio frequency path of the communication device, receives a radio frequency signal from the radio frequency path, and transmits the radio frequency signal toward the first refractive surface **231** of the lens **23**. A signal beam is converged into a narrow beam through the lens **23** and is emergent from the second refractive surface **232**, and then is further propagated to another communication device, so that the communication device **1** implements a signal sending function. A signal beam emitted by the another communication device may be propagated to the second refractive surface **232** of the lens **23**, be converged into a narrow beam through the lens **23** and then be emergent from the first refractive surface **231**, and then further propagated to the antenna array **21** and propagated by the antenna array **21** to the radio frequency path, so that the communication device **1** implements a signal receiving function.

(42) In addition, to facilitate sliding connection between the antenna array **21** and the guide rail **22**, the antenna assembly **20** may further include a sliding part **25**. The antenna array **21** is fixedly disposed on the sliding part **25**, and the sliding part **25** is slidably assembled on the guide rail **22**. In this way, when sliding on the guide rail **22**, the sliding part **25** can drive the antenna array **21** to slide synchronously.

(43) During specific configuration of the guide rail **22**, the guide rail **22** may be of a linear structure, and extend in the housing **10** in a horizontal direction (in other words, the x-axis direction). In this way, when the antenna array **21** slides on the guide rail **22**, a beam direction of the antenna array **21** also moves in the horizontal direction, so that beam sweeping in the horizontal dimension can be implemented. In addition, the guide rail **22** may be approximately located on a focal plane of the lens **23**. Moreover, during specific configuration and as shown in FIG. **5**, the guide rail **22** intersects a principal axis o of the lens **23**, and an included angle α between the guide rail and the principal axis o of the lens may range from 80° to 100° . When the guide rail is located in the focal plane of the lens **23**, the guide rail **22** and the principal axis o of the lens **23** perpendicularly intersect each other, thereby improving signal transmission quality.

(44) FIG. **6** is a front view of an antenna array according to an embodiment of this application. Refer to FIG. **5** and FIG. **6** together. The antenna array **21** includes a plurality of radiating elements **211**. The plurality of radiating elements **211** are arranged in a specific array form. For example, as shown in the figure, the radiating elements are arranged in the x-axis direction and the y-axis direction separately to form a rectangular array. To facilitate fixing of locations of the radiating elements **211**, the antenna array **21** may further include a fixing support **212** configured to support the radiating elements **211**. The radiating elements **211** may be specifically mounted on the fixing support **212** by bonding, snap-fitting, or the like. In addition, a quantity of the radiating elements **211** shown in FIG. **4** is merely an example. In actual application, the quantity of the radiating elements **211** may alternatively be greater than or less than 4×4 in FIG. **5**, and may be specifically set according to a specific application scenario of the communication device **1**. Details are not described herein.

(45) In some implementations, each radiating element **211** may include a subunit a and a subunit b. The subunit a and the subunit b may be configured to enable the radiating element **211** to implement two mutually orthogonal polarized waves, so that the radiating element **211** forms a dual-polarized antenna. In this way, the antenna assembly **20** has good radiation performance, and integrity of the antenna assembly **20** is improved.

(46) Still refer to FIG. 5 and FIG. 6. In this embodiment of this application, each phase shifter **24** is connected to a radiating element **211**, and is configured to adjust a feed phase of the radiating element **211**. During specific implementation, a quantity of phase shifters **24** and a quantity of radiating elements **211** may be identical. In other words, the phase shifters **24** and the radiating elements **211** may be connected in a one-to-one correspondence. In this case, each phase shifter **24** may be configured to adjust the feed phase of the radiating element **211** corresponding to the phase shifter **24**. A pointing direction of a signal beam is always perpendicular to an equiphase surface, and the equiphase surface is determined by a feed phase relationship between the radiating elements **211**. Therefore, a direction of the signal beam may be adjusted by adjusting the feed phase of each radiating element **211**, thereby achieving an objective of beam sweeping.

(47) Based on the foregoing principle, in specific design, for each row of radiating elements **211** arranged in the x-axis direction (the horizontal dimension), in a same row of radiating elements **211** in the x-axis direction, a phase of a radiation signal of each subunit a may be adjusted by the phase shifter **24**, and a phase of a radiation signal of each subunit b may also be adjusted by the phase shifter **24**. In this way, a pointing direction of a signal beam in the horizontal dimension can be adjusted by controlling a value of a phase difference that is output by the phase shifter **24** to each row of radiating elements **211**, thereby implementing beam sweeping in the horizontal dimension.

(48) FIG. 7 and FIG. 8 are each a schematic diagram of a beam sweeping principle of the communication device in FIG. 4. FIG. 7 shows a sweeping range of a signal beam when the antenna array **21** is at a location m on the guide rail **22**, where a, b, and c respectively represent signal beams of the radiating elements having different phase differences. FIG. 8 shows a sweeping range of a signal beam when the antenna array **21** is at a location n on the guide rail, where a', b', and c' respectively represent signal beams of the radiating elements having different phase differences. It should be noted that the signal beam a and the signal beam a', the signal beam b and the signal beam b', and the signal beam c and the signal beam c' are beams of the radiating elements that are configured to have identical phase differences. It can be learned from FIG. 7 and FIG. 8 that, when the antenna array **21** moves from the location m to the location n on the guide rail, the signal beam of the antenna array **21** also moves horizontally. For example, the signal beam a as a whole moves leftward from the location in FIG. 7 to the location of the signal beam a' in FIG. 8. Therefore, when the antenna array **21** moves from one end of the guide rail **22** to the other end, the signal beam also moves in a large range in the horizontal direction with movement of the antenna array **21**, so that mechanical beam sweeping can be implemented within a first sweeping range in the horizontal dimension. In addition, when the antenna array **21** is at different locations, using the location m as an example, the phase shifter **24** is controlled to adjust the feed phase of each radiating element **211**, and a pointing direction of the signal beam may be further adjusted within a specific modulation sweeping angle range, for example, the signal beam b is adjusted to the signal beam a or to the signal beam c, so that phase modulation sweeping is performed at the location within a second sweeping range. In this case, the first sweeping range is parallel to the second sweeping range, and both mechanical sweeping and phase modulation sweeping are performed in the horizontal dimension. By combining mechanical sweeping and electronic tuning sweeping, a sweeping range of the communication device **1** can be expanded overall, to enable the antenna assembly **20** to obtain a higher gain. In addition, because the guide rail **22** is of a linear structure, through the solution of this embodiment of this application, a profile height (in other words, a size in the z-axis direction) of the antenna assembly **20** may be further reduced while a gain of the antenna assembly **20** can be increased, so that space occupied by the antenna assembly

20 in the communication device can be reduced, thereby reducing an overall volume of the communication device **1**.

(49) FIG. **9** is a side view of the communication device in FIG. **4**. Refer to FIG. **6** and FIG. **9** together. Similarly, for each column of radiating elements **211** arranged in the y-axis direction, in a same column of radiating elements **211** in the y-axis direction, a phase of a radiation signal of each subunit a may be adjusted by the phase shifter **24**, and a phase of a radiation signal of each subunit b may also be adjusted by the phase shifter **24**. In this way, a pointing direction of a signal beam in a vertical dimension can be adjusted by controlling a value of a phase difference that is output by the phase shifter **24** to each column of radiating elements **211**, thereby implementing beam sweeping in the vertical dimension. In this case, the first sweeping range intersects the second sweeping range, and both mechanical sweeping and phase modulation sweeping are performed in each of the horizontal dimension and the vertical dimension. Therefore, the sweeping range of the communication device can be expanded.

(50) It should be noted that, when the communication device is CPE, refer to a schematic diagram of orientations of a base station and the CPE shown in FIG. **10**, and dashed lines in the figure may be understood as a beam range of a signal sent by the base station **100**. It can be learned that a horizontal distance L between the CPE **200** and the base station **100** is far greater than a height H of an antenna of the base station **100**. An included angle α between a connection line S between a signal transmission port of the base station **100** and the CPE **200** and the horizontal direction is very small, and the connection line S is set to be almost horizontal. For the CPE **200**, a signal emitted by the base station **100** can be received in the vertical dimension without performing beam sweeping. Therefore, it is only necessary to control a beam width and a beam direction in the vertical dimension during design, to enable the antenna to obtain a high gain.

(51) Based on this, refer to FIG. **6** and FIG. **9** again. In some other embodiments of this application, in the y-axis direction, in a same column of radiating elements **211**, there is a fixed phase difference between radiation signals of subunits a of adjacent radiating elements **211**, and there is also a fixed phase difference between radiation signals of subunits b of adjacent radiating elements **211**. In other words, the communication device **1** has a fixed signal beam direction in the vertical dimension. A specific value of the phase difference may be obtained through simulation when a beam shape of the antenna array **21** in the vertical dimension is designed, and the value is taken based on a principle of reducing a width of a signal beam in the vertical dimension as much as possible. In this design, because phases of the radiating elements **211** arranged in the y-axis direction may not be adjusted, design difficulty and structural complexity of the antenna assembly can be lowered without affecting radiation performance of the communication device **1**.

(52) FIG. **11** is a schematic diagram of a partial structure of an antenna assembly in an operating state according to an embodiment of this application. FIG. **12** is a schematic diagram of a partial structure of an antenna assembly in another operating state according to an embodiment of this application. Refer to FIG. **11** and FIG. **12** together. When an antenna array **21** moves on a guide rail **22**, to improve signal transmission quality, a signal beam emitted by the antenna array **21** may be completely incident to a lens **23** through a first refractive surface **231**, and be emergent from a second refractive surface **232** after being converged by the lens **23**. If the signal beam exceeds a range of the first refractive surface **231** when passing through the lens **23**, or is completely emergent from an edge of the lens **23** to the outside of a housing **10**, signal quality is deteriorated.

(53) Therefore, during specific implementation, to enable the signal beam emitted by the antenna array **21** to be completely incident to the lens **23** from the first refractive surface **231**, extreme movement locations of the antenna array **21** on the guide rail **22** may be set. The extreme movement locations are locations of the antenna array **21** on the guide rail **22** that are farthest from a principal axis o of the lens **23**. It should be understood that the antenna array **21** has two extreme movement locations. It is assumed that the two extreme movement locations are a location A and a location B, respectively. The location A and the location B are axisymmetric on the guide rail **22**

with the principal axis o of the lens 23 as a symmetry axis. For the antenna array 21, when the antenna array 21 performs phase modulation sweeping at the location A or the location B, if an emitted signal beam can be completely incident to the lens 23, then when the antenna array 21 is at any location between the location A and the location B, the emitted signal beam can also be completely incident to the lens 23 definitely. Therefore, during design, the location A and the location B may be determined first, and then the antenna array 21 is configured to move always between the location A and the location B in a beam sweeping process.

(54) Refer to FIG. 11. When the antenna array 21 is at the location A, a phase shifter 24 is controlled to adjust a feed phase of each radiating element 211, to perform phase modulation sweeping. In this case, to ensure that a signal beam emitted by the antenna array 21 does not exceed the range of the first refractive surface 231, a horizontal distance d1 between the location A and an edge of the lens 23 satisfies:

$$d1 \leq f * \tan \theta.$$

(55) f is a vertical distance between the lens 23 and the guide rail 22. When the guide rail 22 is located on a focal plane of the lens 23, f is a focal length of the lens 23. θ is a maximum phase modulation sweeping angle. A phase modulation sweeping angle is determined based on a phase difference between radiation signals of the radiating elements 211. An adjustment range of the phase difference may be obtained through simulation during design, so that a value of θ may be obtained.

(56) Similarly, refer to FIG. 12. When the antenna array 21 is at the location B, to ensure that the signal beam emitted by the antenna array 21 does not exceed the range of the first refractive surface 231, a horizontal distance d2 between the location B and the edge of the lens 23 also satisfies:

$$d1 \leq f * \tan \theta.$$

(57) It may be understood that, under the foregoing condition, a length l of the guide rail 22 satisfies $1 \geq D1 + 2 * f * \tan \theta$. When the lens 23 is a convex lens. D1 is a diameter of the lens 23. In specific design, horizontal distances between two ends of the guide rail 22 and the principal axis o of the lens 23 may be identical or different and are not limited in this application, provided that a horizontal distance between any end of the guide rail 22 and a corresponding end of the lens 23 is not less than $f * \tan \theta$, to prevent the antenna array 21 from sliding off the guide rail 22 when moving to the location A or the location B.

(58) When the lens 23 is a cylindrical lens, refer to FIG. 13 and FIG. 14 together. The horizontal distance d1 between the location A and the edge of the lens 23 and the horizontal distance d2 between the location B and the edge of the lens 23 also satisfy:

$$d1 \leq f * \tan \theta, \text{ and } d2 \leq f * \tan \theta.$$

(59) Under the foregoing condition, the length 1 of the guide rail 22 satisfies $1 \geq D2 + 2 * f * \tan \theta$. In this case, D2 is specifically a width of the lens 23. Similarly, horizontal distances between two ends of the guide rail 22 and the principal axis o of the lens 23 may be identical or different, provided that a horizontal distance L' between any end of the guide rail 22 and a corresponding end of the lens 23 is not less than $f * \tan \theta$.

(60) In addition, in this embodiment of this application, the antenna assembly 20 may further include a driving mechanism. The driving mechanism may be configured to drive the antenna array 21 to slide on the guide rail 22, to improve operating reliability of the antenna assembly 20. During specific implementation, the driving mechanism may use a plurality of driving manners, such as electromagnetic driving or electrical driving. For example, in electrical driving, the driving mechanism includes a motor and a transmission component. The motor may be connected to a circuit board of the CPE, to obtain electric energy required during operating. The transmission component is configured to transfer, to the antenna array 21, a driving force that is output by the motor during operating, to drive the antenna array 21 to move.

(61) FIG. 15 is a schematic diagram of a partial structure of an antenna assembly according to an embodiment of this application. Refer to FIG. 13. The transmission component may be specifically

a screw. The screw includes a screw rod **261** and a nut **262** assembled on the screw rod **261**. The screw rod **261** is connected to an output shaft of the motor, and the nut **262** is fixedly connected to the sliding part **25**. In this way, a rotation motion that is output by the motor can be converted into a linear motion that can drive the sliding part **25** to move, and then the sliding part **25** drives the antenna array **21** to move synchronously.

(62) In another embodiment of this application, the driving mechanism may alternatively be a linear motor. In this case, an output end of the linear motor may be directly connected to the sliding part **25** or the antenna array **21**, and no intermediate conversion component such as a screw is required. This lowers structural complexity of the antenna assembly **20**.

(63) FIG. **16** is a top view of a communication device according to another embodiment of this application. In this embodiment, an antenna assembly **20** further includes a control unit **27**. The control unit **27** may be disposed on a circuit board of the communication device **1**. The control unit **27** is connected to a driving mechanism, and is configured to control the driving mechanism to drive an antenna array **21** to move between a location A and a location B on a guide rail **22**. In addition, the control unit **27** may be further connected to a phase shifter **24**, to control the phase shifter **24** to adjust a feed phase of each radiating element. During beam sweeping, the control unit **27** may control the driving mechanism to drive the antenna array **21** to move between locations in sequence, and each time the antenna array **21** reaches a location, control the phase shifter **24** to adjust the feed phase of each radiating element, to perform phase modulation sweeping once. In this way, a location of the antenna array **21** and a phase that is output by each phase shifter **24** when the antenna assembly **20** obtains a maximum gain can be learned.

(64) Certainly, to simplify a beam sweeping process, in some other implementations, an initial phase difference may be set first, each phase shifter **24** is controlled based on the initial phase difference to output an initial phase to a corresponding radiating element; and then the antenna array **21** is gradually moved from the location A to another location B, or gradually moved from the location B to the location A, to complete one round of mechanical sweeping. The antenna array **21** is moved, based on a result of the mechanical sweeping, to a location at which the maximum gain is obtained, phase modulation sweeping is performed at the location, and a phase that is output by each phase shifter when the maximum gain is obtained at the location is recorded.

(65) In addition, it should be noted that, the control unit **27** may further detect location information of the antenna array **21**, and record the detected location information and a gain corresponding to each piece of location information, to control, after mechanical sweeping is completed, the antenna array **21** to move to the location at which the maximum gain is obtained.

(66) The following specifically describes the foregoing beam sweeping process with reference to FIG. **14** by using an example in which the communication device **1** is CPE.

(67) Step 1: After the CPE is powered on, when the antenna array **21** is at the location A, the control unit **27** controls, based on a set initial phase difference, the phase shifter **24** to output an initial phase to each radiating element.

(68) In the foregoing step, when the CPE is designed, the location A may be set as an initial location of the antenna array **21**. In this way, after the CPE is powered on, the antenna array **21** is at the initial location. Alternatively, in some other implementations, after the CPE is powered on, the control unit **27** may deliver an instruction to the driving mechanism, to control the driving mechanism to move the antenna array **21** to the location A. Certainly, in some other embodiments, the location B may alternatively be set as the initial location of the antenna array **21**, or after the CPE is powered on, the driving mechanism is controlled to move the antenna array **21** to the location B, so that the antenna array gradually moves from the location B to the location A during mechanical sweeping.

(69) In addition, the initial phase difference may be any value within an adjustable range of the phase difference. This is not limited in this application. For example, in a specific implementation, in a same row of radiating elements, an initial phase difference between radiation signals of two

adjacent radiating elements may be 0° . In other words, initial phases of the radiating elements are the same.

(70) Step 2: After a radio signal sent by the base station is received, the control unit **27** measures a reference signal received power (reference signal received power, RSRP for short, being a parameter representing strength of a radio signal) of the radio signal obtained at a current location, and performs recording based on the current location. Next, the control unit **27** controls the driving mechanism to drive the antenna array **21** to move toward the location B, measures, each time the antenna array **21** moves to a location, an RSRP value of a radio signal obtained at the location, and then records location information and the RSRP value correspondingly until the antenna array **21** moves to the location B. In this way, location information of each location and a corresponding RSRP value can be obtained. Table 1 describes recorded results.

(71) TABLE-US-00001 TABLE 1 Location information RSRP/dBm X1 P1 X2 P2 X3 P3 Xn-1 Pn-1 Xn Pn

(72) In Table 1, X1 and Xn respectively represent the location A and the location B, and X2 to Xn-1 sequentially represent locations between the location A and the location B. It should be noted that a distance between two adjacent locations is related to precision of a stepper motor selected for the driving mechanism. Higher precision of the stepper motor indicates a smaller distance between two adjacent locations and higher beam sweeping precision. In actual application, a stepper motor with high precision may be selected while a requirement on beam sweeping efficiency is satisfied, to implement more accurate sweeping.

(73) Step 3: After one round of mechanical sweeping is completed, the control unit **27** controls, based on the information recorded in Table 1, the driving mechanism to drive the antenna array **21** to return to a location corresponding to a maximum RSRP value, and records the location as an optimal location.

(74) Step 4: At the location corresponding to the maximum RSRP value, the control unit **27** sends a phase configuration signal to each phase shifter **24**, adjusts a phase difference between radiation signals of radiating elements in each row through the phase shifter **24**, to perform phase modulation sweeping, and obtains and records RSRP values corresponding to different phase differences. Table 2 describes recorded results.

(75) TABLE-US-00002 TABLE 2 Phase combination RSRP/dBm (y11, y12, y13, . . . , y1m) P1' (y21, y22, y23, . . . , y3m) P2' (y31, y32, y33, . . . , y3m) P3' (yn1, yn2, yn3, . . . , ynm) Pn'

(76) In Table 2, ynm represents a phase value of a radiating element in an n.sup.th row and an m.sup.th column in the antenna array **21**. It should be noted that, to ensure that a signal beam points to a normal direction of the antenna array during phase modulation sweeping, phase differences between radiation signals of adjacent radiating elements in a same row are equal.

(77) Step 5: According to the information recorded in Table 2, a phase combination corresponding to the obtained maximum RSRP value is determined, and the combination is recorded as an optimal phase combination. The optimal location and the optimal phase combination of the antenna array **21** that correspond to the obtained maximum RSRP value, and the maximum RSRP value Pbest are recorded, and the antenna array **21** is controlled to send and receive information at the optimal location with the optimal phase combination, to ensure that the communication device completes uplink and downlink services.

(78) Step 6: When operating at the optimal location with the optimal phase combination, the antenna array **21** periodically obtains an RSRP value of a received radio signal. The RSRP value is denoted as P0. Theoretically, values of P0 and Pbest are the same. However, if a channel environment changes, the value of P0 also changes. In this case, P0 and Pbest are different. Based on this, P0 may be compared with Pbest, and when $TH1 \leq Pbest - P0 < TH2$, step 3 to step 5 are repeated to re-obtain the optimal phase combination and Pbest of the antenna array. When $Pbest - P0 \geq TH2$, step 1 to step 5 are repeated to re-obtain the optimal location, the optimal phase combination, and Pbest of the antenna array.

(79) TH1 and TH2 are respectively set thresholds pre-stored in the control unit 27, and satisfy $TH1 < TH2$. Specific values of TH1 and TH2 may be manually set according to experience, or may be obtained through experiment or simulation. This is not limited in this application.

(80) Step 7: Step 1 to step 5 are repeated at intervals of a set time, and the optimal location, the optimal phase combination, and the corresponding Pbest of the antenna array 21 are refreshed, so that the antenna assembly 20 always has good radiation performance, thereby improving transmission quality of the radio signal.

(81) By performing the foregoing steps, the CPE can efficiently and accurately complete beam sweeping, determine the optimal location of the antenna array 21 on the guide rail 22 and the optimal phase combination of each radiating element, so that the antenna assembly 20 can obtain a high gain. In addition, the CPE can further update the optimal location and the optimal phase combination in real time, so that radiation performance of the antenna assembly can be further improved, and the CPE can always send and receive signals in a good operating state.

(82) The following specifically describes an effect of the foregoing beam sweeping manner with reference to a specific application scenario of CPE shown in FIG. 17. The CPE includes an outdoor unit 210 (outdoor unit, ODU for short) and an indoor unit 220 (indoor unit, IDU for short). During specific configuration, the ODU 210 may be fixed outdoors by attaching to a mast, a wall, or the like. For example, in FIG. 12, the ODU 210 is specifically fixed by attaching to a mast. The IDU 220 may also be fixed indoors by attaching to a wall, or placed on the top of an indoor desk. The ODU 210 may be connected to the IDU 220 by using a cable. The ODU 210 may receive a signal sent by a base station, and transmit the signal to the IDU 220 by using the cable. The IDU 220 then performs conditioning and digital processing on the received signal, and converts the signal into a Wi-Fi signal universal to mobile terminals such as a smartphone, a tablet computer, and a notebook computer.

(83) The ODU 210 has a built-in antenna array formed by 32 radiating elements. If only an existing phase modulation sweeping manner is used for beam sweeping, for example, a sweeping angle after beamforming may reach approximately $\pm 45^\circ$, and after a signal beam emitted by the antenna array is emitted by the lens from a housing of the ODU 210, an antenna gain is increased by 3 dB in a forward direction. However, due to a convergence effect of the lens, the sweeping angle is reduced, for example, from $\pm 45^\circ$ to approximately $\pm 30^\circ$.

(84) However, in the solution in this embodiment of this application, the antenna array is slidably assembled on the guide rail, and the phase shifter that can adjust each radiating element of the antenna array is disposed, so that the ODU 210 performs beam sweeping according to the foregoing step 1 to step 7. For example, a beam sweeping angle may reach approximately $\pm 70^\circ$, and an antenna gain is substantially the same as the antenna gain obtained after beamforming through phase modulation sweeping. In other words, according to the CPE and the beam sweeping method provided in embodiments of this application, a stable antenna gain can be further maintained while implementing large-range beam sweeping, thereby improving radiation performance of the CPE.

(85) The foregoing descriptions are merely specific implementations of this application, but are not intended to limit the protection scope of this application. Any variation or replacement readily figured out by a person skilled in the art within the technical scope disclosed in this application shall fall within the protection scope of this application. Therefore, the protection scope of this application shall be subject to the protection scope of the claims.

Claims

1. An antenna assembly, comprising: a lens comprising a first refractive surface and a second refractive surface; a guide rail located on one side of the first refractive surface of the lens, wherein the guide rail is a linear guide rail; an antenna array comprising a plurality of radiating elements

arranged in an array, wherein the antenna array is slidingly connected to the guide rail, and wherein the antenna array is configured to move on the guide rail so that a beam pointing direction of the antenna assembly moves in an extension direction of the guide rail in order to perform mechanical beam sweeping within a first sweeping range in the extension direction of the guide rail, wherein in the extension direction of the guide rail, a length by which any end of the guide rail exceeds a corresponding end of the lens is l' , wherein l' satisfies:

$l' \geq f \tan \theta$, wherein f is a distance between the guide rail and the lens in a direction perpendicular to the extension direction of the guide rail, and wherein θ is a maximum phase modulation sweeping angle; and a phase shifter coupled to the plurality of radiating elements and configured to adjust feed phases of the plurality of radiating elements to perform, when the antenna array is at different locations on the guide rail, phase modulation sweeping within a second sweeping range by adjusting the feed phases of the radiating elements.

2. The antenna assembly of claim 1, wherein the lens is a convex lens, wherein a first convex surface of the convex lens is the first refractive surface, and wherein a second convex surface of the lens is the second refractive surface.

3. The antenna assembly of claim 1, wherein the lens is a cylindrical lens comprising a cylindrical surface and a flat surface that are connected in a circumferential direction, and wherein the cylindrical surface is the first refractive surface and the flat surface is the second refractive surface, or the flat surface is the first refractive surface and the cylindrical surface is the second refractive surface.

4. The antenna assembly of claim 3, wherein the extension direction of the guide rail is perpendicular to a length direction of the lens.

5. The antenna assembly of claim 1, wherein the guide rail is located in a focal plane of the lens to enable the antenna array, when moving on the guide rail, to receive a signal beam converged by the lens.

6. The antenna assembly of claim 5, wherein the guide rail intersects a principal axis of the lens, and wherein an included angle between the guide rail and the principal axis of the lens ranges from 80° to 100° .

7. The antenna assembly of claim 6, wherein the guide rail and the principal axis of the lens perpendicularly intersect each other.

8. The antenna assembly of claim 1, wherein the first sweeping range is parallel to the second sweeping range.

9. The antenna assembly of claim 1, wherein the first sweeping range intersects the second sweeping range.

10. The antenna assembly of claim 1, further comprising a driving mechanism coupled to the antenna array and configured to drive the antenna array to slide on the guide rail.

11. A communication device, comprising: a housing comprising an inner cavity; an antenna assembly, comprising: a lens disposed on the housing and comprising a first refractive surface and a second refractive surface, wherein the second refractive surface faces away from the inner cavity; a guide rail located on one side of the first refractive surface of the lens, wherein the guide rail is a linear guide rail; an antenna array comprising a plurality of radiating elements arranged in an array, wherein the antenna array is slidingly connected to the guide rail, and wherein the antenna array is configured to move on the guide rail so that a beam pointing direction of the antenna assembly moves in an extension direction of the guide rail in order to perform mechanical beam sweeping within a first sweeping range in the extension direction of the guide rail wherein in the extension direction of the guide rail, a length by which any end of the guide rail exceeds a corresponding end of the lens is l' , wherein l' satisfies:

$l' \geq f \tan \theta$, wherein f is a distance between the guide rail and the lens in a direction perpendicular to the extension direction of the guide rail, and wherein θ is a maximum phase modulation sweeping angle; a driving mechanism coupled to the antenna array and configured to drive the antenna array

to slide on the guide rail; and a phase shifter coupled to the plurality of radiating elements and configured to adjust feed phases of the plurality of radiating elements to perform, when the antenna array is at different locations on the guide rail, phase modulation sweeping within a second sweeping range by adjusting the feed phases of the radiating elements; and a control unit disposed in the housing and separately coupled to the driving mechanism and the phase shifter, wherein the control unit is configured to: control the driving mechanism to drive the antenna array to move on the guide rail; and send, when the antenna array moves to each location, a phase configuration signal to the phase shifter to control the phase shifter to adjust the feed phases of the radiating elements.

12. The communication device of claim 11, wherein the lens and the housing are of an integrated structure.

13. The communication device of claim 11, wherein the lens is a convex lens, wherein a first convex surface of the convex lens is the first refractive surface, and wherein a second convex surface of the lens is the second refractive surface.

14. The communication device of claim 13, wherein the extension direction of the guide rail is perpendicular to a length direction of the lens.

15. The communication device of claim 11, wherein the lens is a cylindrical lens comprising a cylindrical surface and a flat surface that are connected in a circumferential direction, and wherein the cylindrical surface is the first refractive surface and the flat surface is the second refractive surface, or the flat surface is the first refractive surface and the cylindrical surface is the second refractive surface.

16. The communication device of claim 11, wherein the guide rail is located in a focal plane of the lens to enable the antenna array, when moving on the guide rail, to receive a signal beam converged by the lens.

17. The communication device of claim 16, wherein the guide rail intersects a principal axis of the lens, and wherein an included angle between the guide rail and the principal axis of the lens ranges from 80° to 100°.

18. The communication device of claim 17, wherein the guide rail and the principal axis of the lens perpendicularly intersect each other.

19. The communication device of claim 11, wherein the first sweeping range is parallel to the second sweeping range.

20. The communication device of claim 11, wherein the first sweeping range intersects the second sweeping range.
