

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407110
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Wang; Jikang et al.

Antenna apparatus and electronic device

Abstract

A foldable electronic device having a primary screen portion with a primary-screen antenna, and a secondary screen portion with a secondary-screen antenna. Positions of the primary-screen antenna and the secondary-screen antenna overlap when the electronic device is folded. The primary-screen antenna and the secondary-screen antenna may excite two antenna patterns of high isolation. In this way, even if the primary-screen antenna and the secondary-screen antenna operate on a same frequency band and overlap, good isolation performance can also be obtained.

Inventors:	Wang; Jikang (Shanghai, CN), Shen; Laiwei (Shanghai, CN), Wang; Jiaming (Shanghai, CN), Xue; Liang (Shanghai, CN)
Applicant:	HUAWEI TECHNOLOGIES CO., LTD. (Guangdong, CN)
Family ID:	82134462
Assignee:	HUAWEI TECHNOLOGIES CO., LTD. (Shenzhen, CN)
Appl. No.:	18/259581
Filed (or PCT Filed):	December 29, 2021
PCT No.:	PCT/CN2021/142660
PCT Pub. No.:	WO2022/143803
PCT Pub. Date:	July 07, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20240055778 A1	Feb. 15, 2024

Foreign Application Priority Data

CN

202011628760.9

Dec. 30, 2020

Publication Classification

Int. Cl.: H01Q21/28 (20060101); H01Q21/30 (20060101)

U.S. Cl.:

CPC H01Q21/28 (20130101); H01Q21/30 (20130101);

Field of Classification Search

CPC: H01Q (7/00); H01Q (9/26); H01Q (13/10); H01Q (21/0006); H01Q (21/24); H01Q (21/28); H01Q (21/29); H01Q (21/30)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
12230896	12/2024	Hsu	N/A	H01Q 5/35
2012/0231846	12/2011	Mahanfar	455/562.1	H01Q 5/342
2017/0141820	12/2016	Kim	N/A	H04B 1/40
2020/0076062	12/2019	Lee	N/A	H01Q 5/307
2022/0166132	12/2021	Chu	N/A	H04B 1/0064

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
209747728	12/2018	CN	N/A
111384585	12/2019	CN	N/A
112003020	12/2019	CN	N/A
116529958	12/2022	CN	N/A
2020134961	12/2019	WO	N/A
2020187066	12/2019	WO	N/A

Primary Examiner: Chai; Raymond R

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS

(1) This application is a National Stage of International Application No. PCT/CN2021/142660, filed on Dec. 29, 2021, which claims priority to Chinese Patent Application No. 202011628760.9, filed on Dec. 30, 2020, both of which are hereby incorporated by reference in their entireties.

TECHNICAL FIELD

(2) The present invention relates to the field of antenna technologies, and in particular, to an antenna apparatus and an electronic device.

BACKGROUND

(3) With the development of mobile communication technologies and popularization of smartphones, a smartphone design evolves from a large screen, a bezel-less screen, a rotatable screen, or the like to a foldable screen, to achieve better user experience and novel appearance and functions. A foldable screen of an electronic device such as a smartphone provides a new possibility for a function design of the electronic device, and can be applied to more new application scenarios. In addition, the foldable screen also brings new challenges to and provides new possibilities for an antenna design of the electronic device.

SUMMARY

(4) Embodiments of the present invention provide an antenna apparatus. When an electronic device such as a mobile phone is in a folded state, a primary-screen antenna and a secondary-screen antenna at overlapping positions of a primary screen portion and a secondary screen portion can have complementary performance and be highly isolated from each other. Space utilization of an antenna design is high.

(5) According to a first aspect, this application provides an electronic device. The electronic device may include a first device body, a second device body, and a rotating shaft, where the first device body and the second device body are connected through the rotating shaft, and the electronic device is foldable at the rotating shaft.

(6) The electronic device may further include a first antenna disposed on the first device body and a second antenna disposed on the second device body, where the first antenna and the second antenna at least partially overlap when the electronic device is in a folded state.

(7) The first antenna may include a strip-shaped first conductor and a first feed point disposed on the first conductor, where two ends of the first conductor are open, and the first feed point is connected to a feed source. A distance from the first feed point to a middle position of the first conductor may be greater than or equal to zero and less than $1/16$ of an operating wavelength of the first antenna, or a distance from the first feed point to one of the open ends of the first conductor may be greater than or equal to zero and less than $1/16$ of an operating wavelength of the first antenna.

(8) The second antenna may include a strip-shaped second conductor, and a second feed point and a grounding stub that are disposed on the second conductor, where two ends of the second conductor are open, the second feed point is connected to a feed source, and the grounding stub is connected to the second conductor and grounded in a middle position of the second conductor. A distance from the second feed point to a connection point for the second conductor and the grounding stub is greater than zero and less than $1/8$ of an operating wavelength of the second antenna, or a distance from the second feed point to one of the open ends of the second conductor is greater than or equal to zero and less than $1/8$ of an operating wavelength of the second antenna.

(9) That the first antenna and the second antenna at least partially overlap may include: a projection of the first antenna and a projection of the second antenna partially or fully overlap on a plane on which the first device body is located or a plane on which the second device body is located. In other words, when the electronic device is in the folded state, a projection that is of the first antenna and that is on the plane on which the second device body is located partially or fully overlaps with the second antenna. Alternatively, when the electronic device is in the folded state, a projection that is of the second antenna and that is on the plane on which the first device body is located partially or fully overlaps with the first antenna. The overlap is not an overlap that occurs because a projection and an antenna intersect (for example, the projection and the antenna are perpendicular), but mainly is an overlap that occurs because the first conductor and the second conductor are parallel or aligned.

(10) The connection point for the second conductor and the grounding stub may be any point, such as a center point, in a connection area (which may also be referred to as a connection position) between the grounding stub and the second conductor. The first feed point and the second feed

point each may be any point, such as a center point, in a connection area (which may also be referred to as a connection position) between a feeder and a conductor.

(11) According to the electronic device provided in the first aspect, currents on the first conductor of the first antenna may be codirectionally distributed, and a DM wire antenna pattern shown in FIG. 4A and FIG. 4B is excited. A polarization direction may be basically perpendicular to an extension direction of the first conductor. Currents on the second conductor of the secondary-screen antenna may be symmetrically and reversely distributed, and a CM wire antenna pattern shown in FIG. 3A and FIG. 3B is excited. A polarization direction may be basically the same as an extension direction of the second conductor. In this way, polarization directions of the first antenna and the second antenna are orthogonal, and isolation performance is high. Even if the first antenna and the second antenna operate on a same frequency, good isolation performance can also be obtained, and radiation patterns of the first antenna and the second antenna are complementary. This is especially beneficial to a MIMO antenna design of an electronic device having a foldable screen.

(12) According to the first aspect, the first device body and the second device body may be respectively a primary screen portion **11-1** and a secondary screen portion **11-3** that are shown in FIG. 1A to FIG. 1C. The first antenna and the second antenna may be respectively a primary-screen antenna and a secondary-screen antenna that are shown in FIG. 7A. For example, the first conductor may be a conductor **21-A**, and the first feed point may be a feed point **23**. The second conductor may be a conductor **21-B**, the second feed point may be a feed point **24**, and the grounding stub may be a grounding stub **25**. Alternatively, the first antenna and the second antenna may be respectively a primary-screen antenna and a secondary-screen antenna that are shown in FIG. 8A and FIG. 8B. For example, the first conductor may be a suspended metal bezel **41-B**, and the first feed point may be a feed point **33-B**. The second conductor may be a suspended metal bezel **41-A**, the second feed point may be a feed point **33-A**, and the grounding stub may be a grounding stub **32**.

(13) According to the first aspect, the electronic device may further include a bezel of the first device body and a PCB ground of the first device body. The first antenna may be implemented in the electronic device in the following manner: The first conductor may be a strip-shaped conductor disposed on the bezel of the first device body, the first conductor may be separated from the PCB ground of the first device body by a first slot (clearance), the first slot (such as a slot **31-B** in FIG. 8A) is formed by hollowing out the PCB ground of the first device body, and the first slot may be adjacent to the first conductor.

(14) A bezel of a first screen may be a metal bezel. In this case, the first conductor may be a metal bezel segment whose two ends are open and that is formed by opening a gap on the metal bezel. The first conductor is not grounded. A length of the first slot is greater than a length of the metal bezel segment (such as the suspended metal bezel **41-A**). To be specific, a slot longer than the metal bezel segment is formed across gaps, such as two gaps **35-A** and **35-B**, at the two ends of the metal bezel segment and along an extension direction of the metal bezel. In this way, the metal bezel segment forms a suspended metal bezel whose two ends are open, and therefore forms a wire antenna radiator.

(15) Alternatively, the bezel of the first screen may be a non-metal bezel. In this case, the first conductor is a strip-shaped conductor printed or pasted on an inner side of the metal bezel.

(16) According to the first aspect, the electronic device may further include a bezel of the second device body and a PCB ground of the second device body. The second conductor may be a strip-shaped conductor disposed on the bezel of the second device body, the second conductor and the PCB ground of the second device body may be separated by a second slot (clearance) and connected through the grounding stub, the second slot (such as a slot **31-A** in FIG. 8A) may be formed by hollowing out the PCB ground of the second device body, and the second slot may be adjacent to the second conductor.

(17) A bezel of a second screen may be a metal bezel. In this case, the second conductor may be a

suspended metal bezel segment that is formed by opening a gap on the metal bezel. The bezel of the second screen may be a non-metal bezel. In this case, the second conductor may be a strip-shaped conductor printed or pasted on an inner side of the metal bezel.

(18) According to the first aspect, the grounding stub of the second antenna may be a strip-shaped ground portion that is formed by hollowing out the PCB ground of the second device body and that is connected to the second conductor, or may be a metal elastic piece that is disposed on the PCB ground of the second device body and that is connected to the second conductor, or may be a conductive stub that extends from the second conductor and that is connected to the PCB ground.

(19) Antennas on the foldable screen in the first aspect may be further transformed. To be specific, the second antenna may be transformed from a CM wire antenna to an inverted F antenna (IFA), and operate in a $\frac{1}{4}$ wavelength mode. The second antenna that is transformed into the IFA may include a strip-shaped second conductor, and a second feed point and a grounding stub that are disposed on the second conductor, where the grounding stub is connected to the second conductor and grounded at one end of the second conductor, and the second feed point is connected to a feed source. A distance from the second feed point to a connection point for the second conductor and the grounding stub may be greater than zero and less than $\frac{1}{8}$ of an operating wavelength of the second antenna, or a distance from the second feed point to an open end of the second conductor may be greater than or equal to zero and less than $\frac{1}{8}$ of an operating wavelength of the second antenna. For specific implementation of the second conductor and the grounding stub, reference may be made to the foregoing content. Details are not described herein.

(20) According to a second aspect, this application provides an electronic device. The electronic device may include a first device body, a second device body, and a rotating shaft, where the first device body and the second device body are connected through the rotating shaft, and the electronic device is foldable at the rotating shaft.

(21) The electronic device may further include a first antenna disposed on the first device body and a second antenna disposed on the second device body, where the first antenna and the second antenna at least partially overlap when the electronic device is in a folded state.

(22) The first antenna may include a strip-shaped first conductor and a first feed point disposed on the first conductor, where two ends of the first conductor are open, and the first feed point is connected to a feed source. A distance from the first feed point to a middle position of the first conductor may be greater than or equal to zero and less than $\frac{1}{16}$ of an operating wavelength of the first antenna, or a distance from the first feed point to one of the open ends of the first conductor may be greater than or equal to zero and less than $\frac{1}{16}$ of an operating wavelength of the first antenna.

(23) The second antenna may include a second conductor provided with a first slot, two ends of the first slot are closed and grounded, and a first side of the first slot is provided with a first gap. A distance from the first gap to a middle position on the first side may be less than $\frac{1}{16}$ of an operating wavelength of the second antenna, a second feed point is disposed on the first side of the first slot, a second feed point is connected to a feed source, and a distance from the second feed point to the first gap may be greater than zero and less than $\frac{1}{8}$ of the operating wavelength of the second antenna.

(24) That the first antenna and the second antenna at least partially overlap may include: a projection of the first antenna and a projection of the second antenna partially or fully overlap on a plane on which the first device body is located or a plane on which the second device body is located. In other words, when the electronic device is in the folded state, a projection that is of the first antenna and that is on the plane on which the second device body is located partially or fully overlaps with the second antenna. Alternatively, when the electronic device is in the folded state, a projection that is of the second antenna and that is on the plane on which the first device body is located partially or fully overlaps with the first antenna. The overlap is not an overlap that occurs because a projection and an antenna intersect (for example, the projection and the antenna are

perpendicular), but mainly is an overlap that occurs because the first conductor and the second conductor are parallel or aligned.

(25) The first feed point and the second feed point each may be any point, such as a center point, in a connection area (which may also be referred to as a connection position) between a feeder and a conductor. The distance from the first gap to the middle position on the first side may be a distance from a midpoint of the first gap to a midpoint on the first side, or may be a distance from two ends of the first gap to the midpoint on the first side. The distance from the second feed point to the first gap may be a distance from the second feed point to a midpoint of the first gap, or may be a distance from the second feed point to two ends of the first gap.

(26) According to the electronic device provided in the second aspect, currents on the first conductor of the first antenna may be codirectionally distributed, and a DM wire antenna pattern shown in FIG. 4A and FIG. 4B is excited. A polarization direction may be basically perpendicular to an extension direction of the first conductor. Electric fields in the slot of the second conductor of the secondary-screen antenna may be symmetrically and reversely distributed, and a CM slot antenna pattern shown in FIG. 5A and FIG. 5B is excited. A polarization direction may be basically the same as an extension direction of the slot. In this way, polarization directions of the first antenna and the second antenna are orthogonal, and isolation performance is high. Even if the first antenna and the second antenna operate on a same frequency, good isolation performance can also be obtained, and radiation patterns of the first antenna and the second antenna are complementary. This is especially beneficial to a MIMO antenna design of an electronic device having a foldable screen.

(27) According to the second aspect, the first device body and the second device body may be respectively a primary screen portion **11-1** and a secondary screen portion **11-3** that are shown in FIG. 1A to FIG. 1C. The first antenna and the second antenna may be respectively a primary-screen antenna and a secondary-screen antenna that are shown in FIG. 7B. For example, the first conductor may be a conductor **21-A**, and the first feed point may be a feed point **23**. The second conductor may be a conductor **21-C**, the first slot may be a slot **26**, the second feed point may be a feed point **27**, and the first gap may be a gap **28**. Alternatively, the first antenna and the second antenna may be respectively a primary-screen antenna and a secondary-screen antenna that are shown in FIG. 11A and FIG. 11B. For example, the first conductor may be a suspended metal bezel **61-B**, and the first feed point may be a feed point **63-B**. The second conductor may be a conductor that includes a PCB ground and a metal bezel that are on a primary screen portion and that enclose to form a slot **62-A**, the first slot may be the slot **62-A**, the second feed point may be a feed point **63-A**, and the first gap may be a gap **67**.

(28) According to the second aspect, the electronic device may further include a bezel of the first device body and a PCB ground of the first device body. The first conductor may be a strip-shaped conductor disposed on the bezel of the first device body, the first conductor may be separated from the PCB ground of the first device body by a second slot (clearance), the second slot (such as a slot **62-B** in FIG. 11A) may be formed by hollowing out the PCB ground of the first device body, and the second slot is adjacent to the first conductor.

(29) A bezel of a first screen may be a metal bezel. In this case, the first conductor may be a metal bezel segment whose two ends are open and that is formed by opening a gap on the metal bezel. The first conductor is not grounded. A length of the second slot is greater than a length of the metal bezel segment (such as the suspended metal bezel **61-B** in FIG. 11A). To be specific, a slot longer than the metal bezel segment is formed along an extension direction of the metal bezel and across gaps, such as two gaps **66-A** and **66-B**, at the two ends of the metal bezel segment. In this way, the metal bezel segment forms a suspended metal bezel whose two ends are open, and therefore forms a wire antenna radiator.

(30) Alternatively, the bezel of the first screen may be a non-metal bezel. In this case, the first conductor is a strip-shaped conductor printed or pasted on an inner side of the metal bezel.

(31) According to the second aspect, the electronic device may further include a metal bezel of the second device body and a PCB ground of the second device body. The second conductor may include the metal bezel of the second device body and the PCB ground of the second device body that enclose to form the first slot (such as the slot 62-A in FIG. 11A). The first slot may be formed by hollowing out the PCB ground of the second device body, the first slot may be adjacent to the metal bezel of the second device body, and the first gap may be a gap provided on the metal bezel that is of the second device body and adjacent to the first slot and that forms a first side of the first slot. The first gap is provided on the metal bezel on one side of the second feed point, and no gap is provided on the metal bezel on the other side of the second feed point.

(32) According to a third aspect, this application provides an electronic device. The electronic device may include a first device body, a second device body, and a rotating shaft, where the first device body and the second device body are connected through the rotating shaft, and the electronic device is foldable at the rotating shaft.

(33) The electronic device may further include a first antenna disposed on the first device body and a second antenna disposed on the second device body, where the first antenna and the second antenna at least partially overlap when the electronic device is in a folded state.

(34) The first antenna may include a strip-shaped first conductor, and a first feed point and a grounding stub that are disposed on the first conductor, where two ends of the first conductor are open, and the first feed point is connected to a feed source. The grounding stub is connected to the first conductor and grounded in a middle position of the first conductor, and a distance from the first feed point to a connection point for the first conductor and the grounding stub may be greater than zero and less than $\frac{1}{8}$ of an operating wavelength of the first antenna, or a distance from the first feed point to one of the open ends of the first conductor may be greater than or equal to zero and less than $\frac{1}{8}$ of an operating wavelength of the first antenna.

(35) The second antenna may include a second conductor provided with a first slot, two ends of the first slot are closed and grounded, a second feed point is disposed on a first side of the first slot, and the second feed point is connected to a feed source. A distance from the second feed point to a middle position on the first side of the first slot may be greater than or equal to zero and less than $\frac{1}{16}$ of an operating wavelength of the second antenna.

(36) That the first antenna and the second antenna at least partially overlap may include: a projection of the first antenna and a projection of the second antenna partially or fully overlap on a plane on which the first device body is located or a plane on which the second device body is located. In other words, when the electronic device is in the folded state, a projection that is of the first antenna and that is on the plane on which the second device body is located partially or fully overlaps with the second antenna. Alternatively, when the electronic device is in the folded state, a projection that is of the second antenna and that is on the plane on which the first device body is located partially or fully overlaps with the first antenna. The overlap is not an overlap that occurs because a projection and an antenna intersect (for example, the projection and the antenna are perpendicular), but mainly is an overlap that occurs because the first conductor and the second conductor are parallel or aligned.

(37) The connection point for the first conductor and the grounding stub may be any point, such as a center point, in a connection area (which may also be referred to as a connection position) between the grounding stub and the first conductor. The first feed point and the second feed point each may be any point, such as a center point, in a connection area (which may also be referred to as a connection position) between a feeder and a conductor.

(38) According to the electronic device provided in the third aspect, currents on the first conductor of the first antenna may be reversely distributed, and a CM wire antenna pattern shown in FIG. 3A and FIG. 3B is excited. A polarization direction may be basically the same as an extension direction of the first conductor. Electric fields in the slot of the second conductor of the secondary-screen antenna may be codirectionally distributed, and a DM slot antenna pattern shown in FIG. 6A and

FIG. 6B is excited. A polarization direction may be basically perpendicular to an extension direction of the slot. In this way, polarization directions of the first antenna and the second antenna are orthogonal, and isolation performance is high. Even if the first antenna and the second antenna operate on a same frequency, good isolation performance can also be obtained, and radiation patterns of the first antenna and the second antenna are complementary. This is especially beneficial to a MIMO antenna design of an electronic device having a foldable screen.

(39) According to the third aspect, the first device body and the second device body may be respectively a primary screen portion **11-1** and a secondary screen portion **11-3** that are shown in FIG. 1A to FIG. 1C. The first antenna and the second antenna may be respectively a primary-screen antenna and a secondary-screen antenna that are shown in FIG. 7C. For example, the first conductor may be a conductor **21-B**, and the first feed point may be a feed point **24**. The second conductor may be a conductor **21-D**, the first slot may be a slot **32**, and the second feed point may be a feed point **31**. Alternatively, the first antenna and the second antenna may be respectively a primary-screen antenna and a secondary-screen antenna that are shown in FIG. 10A and FIG. 10B. For example, the first conductor may be a suspended metal bezel **51-A**, and the first feed point may be a feed point **53-A**. The second conductor may include a PCB ground and a metal bezel that are on a primary screen portion and that enclose to form a slot **52-B**, the first slot may be the slot **52-B**, and the second feed point may be a feed point **53-B**.

(40) According to the third aspect, the electronic device may further include a bezel of the first device body and a PCB ground of the first device body. The first conductor may be a strip-shaped conductor disposed on the bezel of the first device body, the first conductor and the PCB ground of the first device body may be separated by a second slot (clearance) and connected through the grounding stub, the second slot (such as a slot **52-A** in FIG. 10A) may be formed by hollowing out the PCB ground of the first device body, and the second slot may be adjacent to the first conductor.

(41) A bezel of a first screen may be a metal bezel. In this case, the first conductor may be a metal bezel segment whose two ends are open and that is formed by opening a gap on the metal bezel. A length of the second slot is greater than a length of the metal bezel segment (such as the suspended metal bezel **51-A** in FIG. 10A). To be specific, a slot longer than the metal bezel segment is formed along an extension direction of the metal bezel and across gaps, such as two gaps **55-A** and **55-B**, at the two ends of the metal bezel segment. In this way, the metal bezel segment forms a suspended metal bezel whose two ends are open, and therefore forms a wire antenna radiator.

(42) Alternatively, the bezel of the first screen may be a non-metal bezel. In this case, the first conductor is a strip-shaped conductor printed or pasted on an inner side of the metal bezel.

(43) The grounding stub of the first antenna may be a strip-shaped ground portion that is formed by hollowing out the PCB ground of the first device body and that is connected to the first conductor, or the grounding stub is a metal elastic piece that is disposed on the PCB ground of the first device body and that is connected to the first conductor, or the grounding stub is a conductive stub that extends from the first conductor and that is connected to the PCB ground.

(44) According to the third aspect, the electronic device may further include a metal bezel of the second device body and a PCB ground of the second device body. The second conductor may include the metal bezel of the second device body and the PCB ground of the second device body that enclose to form the first slot (such as the **52-B** in FIG. 10A), the first slot may be formed by hollowing out the PCB ground of the second device body, and the first slot may be adjacent to the metal bezel of the second device body. No gap is provided on the metal bezel that is of the second device body and adjacent to the first slot and that forms a first side of the first slot.

(45) According to a fourth aspect, this application provides an electronic device. The electronic device may include a first device body, a second device body, and a rotating shaft, where the first device body and the second device body are connected through the rotating shaft, and the electronic device is foldable at the rotating shaft.

(46) The electronic device may further include a first antenna disposed on the first device body and

a second antenna disposed on the second device body, where the first antenna and the second antenna at least partially overlap when the electronic device is in a folded state.

(47) The first antenna may include a first conductor provided with a first slot, two ends of the first slot are closed and grounded, and a first side of the first slot is provided with a gap. A distance from the first gap to a middle position on the first side may be less than $1/16$ of an operating wavelength of the second antenna, a first feed point is disposed on the first side of the first slot, the first feed point is connected to a feed source, and a distance from the first feed point to the first gap may be greater than zero and less than $1/8$ of the operating wavelength of the first antenna.

(48) The second antenna may include a second conductor provided with a second slot, two ends of the second slot are closed and grounded, a second feed point is disposed on a second side of the second slot, and the second feed point is connected to a feed source. A distance from the second feed point to a middle position on the second side of the second slot may be greater than or equal to zero and less than $1/16$ of an operating wavelength of the second antenna.

(49) That the first antenna and the second antenna at least partially overlap may include: a projection of the first antenna and a projection of the second antenna partially or fully overlap on a plane on which the first device body is located or a plane on which the second device body is located. In other words, when the electronic device is in the folded state, a projection that is of the first antenna and that is on the plane on which the second device body is located partially or fully overlaps with the second antenna. Alternatively, when the electronic device is in the folded state, a projection that is of the second antenna and that is on the plane on which the first device body is located partially or fully overlaps with the first antenna. The overlap is not an overlap that occurs because a projection and an antenna intersect (for example, the projection and the antenna are perpendicular), but mainly is an overlap that occurs because the first conductor and the second conductor are parallel or aligned.

(50) The first feed point and the second feed point each may be any point, such as a center point, in a connection area (which may also be referred to as a connection position) between a feeder and a conductor. The distance from the first gap to the middle position on the first side may be a distance from a midpoint of the first gap to a midpoint on the first side, or may be a distance from two ends of the first gap to the midpoint on the first side. The distance from the second feed point to the first gap may be a distance from the second feed point to a midpoint of the first gap, or may be a distance from the second feed point to two ends of the first gap.

(51) According to the electronic device provided in the fourth aspect, electric fields in the slot of the first conductor of the first antenna may be symmetrically and reversely distributed, and a CM slot antenna pattern shown in FIG. 5A and FIG. 5B is excited. A polarization direction may be basically the same as an extension direction of the slot of the first conductor. Electric fields in the slot of the second conductor of the secondary-screen antenna may be codirectionally distributed, and a DM slot antenna pattern shown in FIG. 6A and FIG. 6B is excited. A polarization direction may be basically perpendicular to an extension direction of the slot. In this way, polarization directions of the first antenna and the second antenna are orthogonal, and isolation performance is high. Even if the first antenna and the second antenna operate on a same frequency, good isolation performance can also be obtained, and radiation patterns of the first antenna and the second antenna are complementary. This is especially beneficial to a MIMO antenna design of an electronic device having a foldable screen.

(52) According to the fourth aspect, the electronic device may further include a metal bezel of the first device body and a PCB ground of the first device body. The first conductor includes the metal bezel of the first device body and the PCB ground of the first device body that enclose to form the first slot (such as a slot 72-A in FIG. 12A), the first slot is formed by hollowing out the PCB ground of the first device body, and the first slot is adjacent to the metal bezel of the first device body. No gap is provided on the metal bezel that is of the first device body and adjacent to the first slot and that forms a first side of the first slot.

(53) According to the fourth aspect, the electronic device may further include a metal bezel of the second device body and a PCB ground of the second device body. The second conductor includes the metal bezel of the second device body and the PCB ground of the second device body that enclose to form the second slot (such as a slot 72-B in FIG. 12A), the second slot is formed by hollowing out the PCB ground of the second device body, the second slot is adjacent to the metal bezel of the second device body, the first gap (such as a gap 79 in FIG. 12A) may be a gap provided on the metal bezel that is of the second device body and adjacent to the second slot and that forms the first side of the first slot. The first gap is provided on the metal bezel on one side of the second feed point, and no gap is provided on the metal bezel on the other side of the second feed point.

Description

BRIEF DESCRIPTION OF DRAWINGS

- (1) To describe technical solutions in embodiments of this application more clearly, the following describes the accompanying drawings used in embodiments of this application.
- (2) FIG. 1A to FIG. 1C are schematic diagrams depicting a structure of an electronic device according to an embodiment of this application;
- (3) FIG. 2A and FIG. 2B are schematic diagrams of design positions of a primary-screen antenna and a secondary-screen antenna according to this application;
- (4) FIG. 3A and FIG. 3B are schematic diagrams depicting a principle of a CM wire antenna according to this application;
- (5) FIG. 4A and FIG. 4B are schematic diagrams depicting a principle of a DM wire antenna according to this application;
- (6) FIG. 5A and FIG. 5B are schematic diagrams depicting a principle of a CM slot antenna according to this application;
- (7) FIG. 6A and FIG. 6B are schematic diagrams depicting a principle of a DM slot antenna according to this application;
- (8) FIG. 7A to FIG. 7D are schematic diagrams of several design solutions for a primary-screen antenna and a secondary-screen antenna according to this application;
- (9) FIG. 8A to FIG. 8C are schematic diagrams of implementation of an antenna design solution shown in FIG. 7A in an electronic device;
- (10) FIG. 9A to FIG. 9D are schematic diagrams of a variant implementation of the antenna design solution shown in FIG. 7A in an electronic device;
- (11) FIG. 9E is a schematic diagram of simulation of an antenna structure shown in FIG. 9A to FIG. 9D;
- (12) FIG. 9F is a schematic diagram of another variant implementation of the antenna design solution shown in FIG. 7A in an electronic device;
- (13) FIG. 9G and FIG. 9H are schematic diagrams of simulation of an antenna structure shown in FIG. 9F;
- (14) FIG. 10A and FIG. 10B are schematic diagrams of implementation of an antenna design solution shown in FIG. 7B in an electronic device;
- (15) FIG. 11A and FIG. 11B are schematic diagrams of implementation of an antenna design solution shown in FIG. 7C in an electronic device;
- (16) FIG. 12A and FIG. 12B are schematic diagrams of implementation of an antenna design solution shown in FIG. 7D in an electronic device;
- (17) FIG. 13A and FIG. 13B show feed positions of a CM wire antenna and a DM wire antenna according to this application; and
- (18) FIG. 14A to FIG. 14G show example sizes that may be used when a primary-screen antenna

and a secondary-screen antenna in this application are implemented on several typical frequency bands and related simulation results.

DESCRIPTION OF EMBODIMENTS

(19) The following describes embodiments of the present invention with reference to the accompanying drawings in embodiments of the present invention.

(20) The technical solutions provided in this application are applicable to an electronic device that uses one or more of the following communication technologies: a global system for mobile communication (global system for mobile communication, GSM) technology, a code division multiple access (code division multiple access, CDMA) communication technology, a wideband code division multiple access (wideband code division multiple access, WCDMA) communication technology, a general packet radio service (general packet radio service, GPRS), a long term evolution (long term evolution, LTE) communication technology, a Wi-Fi communication technology, a 5G communication technology, a millimeter wave (mmWave) communication technology, a sub-6G communication technology, another future communication technology, and the like. The following embodiments describe an operating characteristic of an antenna based on a frequency band instead of a requirement of a communication network. In this application, the electronic device may be an electronic device such as a mobile phone, a tablet, or a personal digital assistant (personal digital assistant, PDA).

(21) FIG. 1A shows an example electronic device on which an antenna design solution provided in this application is based. As shown in FIG. 1A, the electronic device may include a foldable screen **11**, a rotating shaft **13**, and a bezel. The foldable screen **11** may include a primary screen portion **11-1** and one or more secondary screen portions **11-3**. Therefore, the electronic device may be divided into a device body having a primary screen (which is briefly referred to as the primary screen portion below) and a device body having a secondary screen (which is briefly referred to as the secondary screen portion below). To simplify the accompanying drawings, only one secondary screen portion **11-3** is shown in the accompanying drawings. The rotating shaft **13** connects a first device body and a second device body. A width (w_1) of the primary screen portion may be the same as or different from a width (w_2) of the secondary screen portion. The bezel of the electronic device may include a primary-screen bezel **12-1** and a secondary-screen bezel **12-3**. The primary-screen bezel **12-1** surrounds the primary screen portion **11-1**, and the secondary-screen bezel **12-3** surrounds the secondary screen portion **11-3**. The bezel may be a metal bezel or a non-metal bezel (such as a plastic bezel or a glass bezel).

(22) As shown in FIG. 1B, the electronic device may be bent at the rotating shaft **13**. To be specific, the electronic device may be bent outwardly or inwardly. After the electronic device is bent outwardly, the foldable screen **11** is presented outside, a rear cover of the electronic device is hidden inside, and display content on the foldable screen **11** is visible to a user. After the electronic device is bent inwardly, the foldable screen **11** is hidden inside, the rear cover of the electronic device is presented outside, and the display content on the foldable screen **11** is invisible to the user. The electronic device has two modes: an open (open) state and a folded (folded) state. In the open state, an included angle α between the primary screen and the secondary screen exceeds a first angle (such as 120°), and the included angle α may even be equal to or close to 180° . In the folded state, the included angle α between the primary screen and the secondary screen is less than a second angle (such as 15°), and the included angle α may even be equal to or close to 0° . When the foldable screen **11** is in the open state, the electronic device may be shown as an example in FIG. 1A. When the foldable screen **11** is in the folded state, the electronic device may be shown as an example in FIG. 1C.

(23) The electronic device may further include a printed circuit board (printed circuit board, PCB), a housing (housing), and the like that are not shown. The housing is mainly used to support the entire device. A metal layer may be disposed on a side of the PCB, and the metal layer may be formed by etching metal on a surface of the PCB. The metal layer may be used to ground an

electronic component carried on the PCB, to prevent a user from an electric shock or prevent device damage. The metal layer may be referred to as a PCB ground, and includes a primary-screen PCB ground and a secondary-screen PCB ground. In addition to the PCB ground, the electronic device may further include another ground for grounding, for example, a metal middle frame.

(24) An embodiment of this application provides an antenna design solution. As shown in FIG. 2A, a primary screen portion of an electronic device is designed with a primary-screen antenna such as a primary-screen antenna Ant1-1, and a secondary screen portion of the electronic device is designed with a secondary-screen antenna such as a secondary-screen antenna Ant1-2. The primary-screen antenna and the secondary-screen antenna may be antennas that operate on a same frequency band. When the electronic device is in a folded state, positions of the primary-screen antenna and the secondary-screen antenna overlap, for example, partially or fully overlap. An overlap herein may mean that a projection, of the primary-screen antenna, on a plane on which the secondary screen portion is located overlaps with the secondary-screen antenna when the electronic device is in the folded state; or a projection, of the secondary-screen antenna, on a plane on which the primary screen portion is located overlaps with the primary-screen antenna when the electronic device is in the folded state. The overlap is not an overlap that occurs because a projection and an antenna intersect (for example, the projection and the antenna are perpendicular), but mainly is an overlap that occurs because radiators of the primary-screen antenna and the secondary-screen antenna are parallel or aligned. The primary-screen antenna and the secondary-screen antenna may excite two antenna patterns of high isolation, such as a common-mode antenna pattern and a differential-mode antenna pattern that are introduced later. For example, a polarization direction of the primary-screen antenna Ant1-1 is an extension direction of a top bezel, and a polarization direction of the secondary-screen antenna Ant1-2 is a direction perpendicular to the extension direction of the top bezel. In other words, polarization directions of the primary-screen antenna Ant1-1 and the secondary-screen antenna Ant1-2 are fully or approximately orthogonal. In this way, even if the primary-screen antenna and the secondary-screen antenna operate on a same frequency band and overlap, good isolation performance can also be obtained, and radiation patterns of the primary-screen antenna and the secondary-screen antenna are complementary. This is especially beneficial to a MIMO antenna design of an electronic device having a foldable screen. In addition, two or more antennas that operate on a same frequency band can be highly isolated from each other without isolating a plurality of antennas that operate on a same frequency band at physical positions. For example, the primary-screen antenna Ant1-1 and the secondary-screen antenna Ant1-2 do not need to be staggered at physical positions. This fully utilizes an antenna design space of the electronic device having a foldable screen.

(25) As shown in FIG. 2A and FIG. 2B, an electronic device **10** may be designed with two or more pairs of such primary-screen antennas and secondary-screen antennas, which may cover a plurality of frequency bands and may form a plurality of MIMO antennas that operate on different frequency bands. For example, the primary-screen antenna Ant1-1 and the secondary-screen antenna Ant1-2 may form Wi-Fi MIMO antennas, a primary-screen antenna Ant2-1 and a secondary-screen antenna Ant2-2 may form high-frequency (such as 3.5 GHz) MIMO antennas, and a primary-screen antenna Ant3-1 and a secondary-screen antenna Ant3-2 may form low-frequency (such as 900 MHz) MIMO antennas.

(26) The antenna design solution provided in this embodiment of this application may be applied to an electronic device that is shown as an example in FIG. 1A to FIG. 1C and that has a foldable screen, for example, a mobile phone or a tablet.

(27) First, a common-mode antenna pattern and a differential-mode antenna pattern in embodiments of this application are described.

(28) 1. Common-Mode (Common Mode, CM) Wire Antenna Pattern

(29) As shown in FIG. 3A, a wire antenna **101** may include two radiators: a radiator **101-A** and a radiator **101-B**. The two radiators are aligned and extend in opposite directions. Two ends (such as

an end **103** and an end **105**) that are of the radiator **101-A** and the radiator **101-B** respectively and that are close to each other may be both connected to a positive electrode of a feed source. A phase difference between radio frequency signals fed into the two radiators is 0° .

(30) As shown in FIG. 3A, currents at a feed position are codirectionally distributed, and this type of feeding may be referred to as common-mode feeding. Currents on the wire antenna **101** are reversely distributed. Herein, that the currents are reversely distributed means that directions of excited primary currents are basically reverse. For example, as shown in FIG. 3A, a direction of a primary current on a left half portion of the wire antenna **101** is from right to left, and a direction of a primary current on a right half portion of the wire antenna **101** is from left to right. An antenna pattern excited by the antenna shown in FIG. 3A may be referred to as a CM wire antenna pattern, and the antenna may be referred to as a CM wire antenna. The CM wire antenna pattern may be generated when the two radiators each operate in a $\frac{1}{4}$ wavelength mode.

(31) FIG. 3B shows a simplified radiation pattern (radiation pattern) of the wire antenna **101**. It can be learned that a radiation direction in the CM wire antenna pattern is the same as an extension direction of the wire antenna **101**. In other words, a polarization direction of the wire antenna **101** is the same as an extension direction of the wire antenna **101**. Polarization is a radiation characteristic that describes a spatial orientation of a field strength vector of an electromagnetic wave. Generally, a spatial orientation of an electric field vector may be used as a polarization direction of the electromagnetic wave, which may be a spatial orientation of an electric field vector in a maximum radiation direction (a main lobe direction) of an antenna. In actual application, the polarization direction of the wire antenna **101** may not be totally the same as the extension direction of the wire antenna **101**. A slight deviation, such as a deviation within 30° , may exist.

(32) 2. Differential-Mode (Differential Mode, DM) Wire Antenna Pattern

(33) As shown in FIG. 4A, a radiator structure of a wire antenna **101** is the same as a radiator structure of the wire antenna **101** shown in FIG. 3A. A difference lies in that two ends (such as an end **103** and an end **105**) that are of a radiator **101-A** and a radiator **101-B** respectively and that are close to each other may be respectively connected to a positive electrode and a negative electrode of a feed source. A phase difference between radio frequency signals fed into the two radiators is 180° .

(34) As shown in FIG. 4A, currents at a feed position are reversely distributed, and this type of feeding may be referred to as differential-mode feeding. Currents on the wire antenna **101** are codirectionally distributed. Herein, that the currents are codirectionally distributed means that directions of excited primary currents are basically the same. For example, as shown in FIG. 4A, directions of primary currents on the wire antenna **101** are from right to left. An antenna pattern excited by the antenna shown in FIG. 4A may be referred to as a DM wire antenna pattern, and the antenna may be referred to as a DM wire antenna. The DM wire antenna pattern may be generated when the entire wire antenna **101** operates in a $\frac{1}{2}$ wavelength mode.

(35) FIG. 4B shows a simplified radiation pattern of the wire antenna **101**. It can be learned that a radiation direction in the DM wire antenna pattern is perpendicular to an extension direction of the wire antenna **101**. In other words, a polarization direction of the wire antenna **101** is perpendicular to the extension direction of the wire antenna **101**. In actual application, the polarization direction of the wire antenna **101** may not be fully perpendicular to the extension direction of the wire antenna **101**. A slight deviation, such as a deviation within 30° , may exist to be approximately perpendicular.

(36) 3. Common-Mode (Common Mode, CM) Slot Antenna Pattern

(37) As shown in FIG. 5A, a slot antenna **108** may include a slot **109**, and a side of the slot **109** is provided with a gap **107**. The gap **107** may connect the slot **109** to external free space. The gap **107** may be specifically provided in a middle position of the side. Herein, the middle position refers to a midpoint of the side. In other words, a position of the gap **107** covers the midpoint. A feed source may be connected at the gap **107**. For example, radiators at two ends of the gap **107** may be

connected to the feed source. Specifically, a radiator at one end of the gap **107** is connected to a positive electrode of the feed source, and a radiator at the other end of the gap **107** is connected to a negative electrode of the feed source.

(38) In the feeding manner shown in FIG. 5A, electric fields at a feed position (namely, the gap **107**) are codirectionally distributed, and this type of feeding may be referred to as common-mode feeding. Electric fields in the slot **109** are symmetrically and reversely distributed. Herein, that the electric fields are reversely distributed means that directions of excited primary electric fields are basically reverse. For example, as shown in FIG. 5A, a direction of a primary electric field on a left half portion of the slot **109** is from top to bottom, and a direction of a primary electric field on a right half portion of the slot **109** is from bottom to top. An antenna pattern excited by the antenna shown in FIG. 5A may be referred to as a CM slot antenna pattern, and the antenna may be referred to as a CM slot antenna. The CM slot antenna pattern may be generated when slot portions on two sides of the gap **107** each operate in a $\frac{1}{4}$ wavelength mode.

(39) FIG. 5B shows a simplified radiation pattern of the slot antenna **108**. It can be learned that a radiation direction in the CM slot antenna pattern is the same as an extension direction of the slot **109**. In other words, a polarization direction of the slot antenna **108** is parallel to the extension direction of the slot **109**. In actual application, the polarization direction of the slot antenna **108** may not be totally the same as an extension direction of the slot antenna **108**. A slight deviation, such as a deviation within 30° , may exist.

(40) 4. Differential-Mode (Differential Mode, DM) Slot Antenna Pattern

(41) As shown in FIG. 6A, a slot antenna **110** may include a slot **114**. The slot **114** may be specifically formed on a ground, for example, formed by opening a slot on the ground. A middle position of the slot **114** may be connected to a feed source. For example, radiators on two sides of the middle position of the slot **114** may be connected to the feed source. Herein, that the middle position of the slot **114** is connected to the feed source means that a connection position for a feeder of the feed source and a side (for example, a side formed by a metal bezel) of the slot **114** covers a midpoint of the side. Specifically, a middle position of a radiator on one side of the slot **114** may be connected to a positive electrode of the feed source, and a middle position of a radiator on the other side of the slot **114** may be connected to a negative electrode of the feed source. Herein, that the positive electrode/negative electrode of the feed source is connected to a middle position of a radiator means that a connection position for the positive electrode/negative electrode of the feed source and the radiator covers a midpoint of the radiator.

(42) In the feeding manner shown in FIG. 6A, directions of electric fields at a feed position **112** are reverse, and this type of feeding may be referred to as differential-mode feeding. Electric fields in the slot **114** are symmetrically and codirectionally distributed. Herein, that the electric fields are codirectionally distributed means that directions of excited primary electric fields are basically the same. For example, as shown in FIG. 6A, directions of primary electric fields in the slot **114** are from top to bottom. An antenna pattern excited by the antenna shown in FIG. 6A may be referred to as a DM slot antenna pattern, and the antenna may be referred to as a DM slot antenna. The DM slot antenna pattern may be generated when the entire slot **114** operates in a $\frac{1}{2}$ wavelength mode.

(43) FIG. 6B shows a simplified radiation pattern of the slot antenna **110**. It can be learned that a radiation direction in the DM slot antenna pattern is perpendicular to an extension direction of the slot **114**. In other words, a polarization direction of the slot antenna **110** is perpendicular to the extension direction of the slot **114**. In actual application, the polarization direction of the slot antenna **110** may not be fully perpendicular to the extension direction of the slot **114**. A slight deviation, such as a deviation within 30° , may exist to be approximately perpendicular.

(44) In the foregoing antennas, polarization directions of a common-mode antenna and a differential-mode antenna are orthogonal. Therefore, the common-mode antenna and the differential-mode antenna are highly isolated from each other. Herein, orthogonality may be specific to main lobe directions of two antennas. The main lobe direction is a direction with

maximum radiant energy. In actual application, the polarization directions of the common-mode antenna and the differential-mode antenna may not be fully orthogonal. A slight deviation, such as a deviation within 30°, may exist to be approximately orthogonal.

(45) Based on the foregoing antenna patterns, the following describes antenna design solutions provided in embodiments of this application.

(46) FIG. 7A shows an example solution in which a primary-screen antenna is a DM wire antenna and a secondary-screen antenna is a CM wire antenna.

(47) As shown in FIG. 7A, when a foldable screen of an electronic device is in a folded state, the primary-screen antenna and the secondary-screen antenna overlap, which may be that the primary-screen antenna and the secondary-screen antenna fully or partially overlap. The primary-screen antenna may include a conductor **21-A** and a feed point **23** disposed on the conductor **21-A**. The feed point **23** may be connected to a feed source. The conductor **21-A** on a primary screen may be a segment of a metal bezel of the primary screen, or a metal strip printed on an inner side of a bezel of the primary screen. Currents on the conductor **21-A** may be codirectionally distributed, and the foregoing DM wire antenna pattern shown in FIG. 4A and FIG. 4B is excited. The currents that are codirectionally distributed may be primary currents distributed on the conductor **21-A**, and the currents may be generated by a fundamental mode of the primary-screen antenna. The secondary-screen antenna may include a conductor **21-B**, and a feed point **24** and a grounding stub **25** that are disposed on the conductor **21-B**. The feed point **24** may be connected to a feed source, and the grounding stub **25** may be connected to a ground. The conductor **21-B** on a secondary screen may be a segment of a metal bezel of the secondary screen, or a metal strip printed on an inner side of a bezel of the secondary screen. Currents on the conductor **21-B** may be symmetrically and reversely distributed, and the foregoing CM wire antenna pattern shown in FIG. 3A and FIG. 3B is excited. The currents that are reversely distributed may be primary currents distributed on the conductor **21-A**, and the currents may be generated by a fundamental mode of the primary-screen antenna.

(48) The primary-screen antenna is the DM wire antenna, and the secondary-screen antenna is the CM wire antenna. Therefore, when the foldable screen of the electronic device is in the folded state, good isolation performance can also be obtained even if the primary-screen antenna and the secondary-screen antenna operate on a same frequency band.

(49) In addition to the CM wire antenna pattern, the secondary-screen antenna shown in FIG. 7A may actually further excite another antenna pattern: a DM wire antenna pattern. A principle for the DM wire antenna pattern is the following: In a case in which feeding is not considered, a conductor of any shape may have a plurality of characteristic modes (characteristic mode), and one or more of the characteristic modes may be enhanced through a feeding design, so as to select a desired characteristic mode. Herein, the DM wire antenna pattern and the CM wire antenna pattern are desired characteristic modes selected by the secondary-screen antenna through feeding. When the primary-screen antenna and the secondary-screen antenna overlap due to folding of the foldable screen, the DM wire antenna pattern additionally excited by the secondary-screen antenna and the DM slot antenna pattern of the primary-screen antenna may be adjusted to different frequency bands, to prevent the DM wire antenna pattern additionally excited by the secondary-screen antenna from interfering with the DM slot antenna pattern of the primary-screen antenna.

(50) In FIG. 7A, an inductor may be connected in parallel in a structure of the primary-screen antenna for grounding. In this way, the primary-screen antenna may be transformed into a CM wire antenna, and primary currents on the primary-screen antenna are reversely distributed. In this case, a capacitor may be connected in series in a structure of the secondary-screen antenna to short-circuit the grounding stub. In this way, the secondary-screen antenna may be transformed into a DM wire antenna, and primary currents on the secondary-screen antenna are codirectionally distributed.

(51) FIG. 7B shows an example solution in which a primary-screen antenna is a DM wire antenna and a secondary-screen antenna is a CM slot antenna.

(52) As shown in FIG. 7B, when a foldable screen of an electronic device is in a folded state, the primary-screen antenna and the secondary-screen antenna overlap, which may be that the primary-screen antenna and the secondary-screen antenna fully or partially overlap. The primary-screen antenna may include a conductor **21-A** and a feed point **23** disposed on the conductor **21-A**. The feed point **23** may be connected to a feed source. The conductor **21-A** on a primary screen may be a segment of a metal bezel of the primary screen, or a metal strip printed on an inner side of a bezel of the primary screen. Currents on the conductor **21-A** may be codirectionally distributed, and for example, the foregoing DM wire antenna pattern shown in FIG. 4A and FIG. 4B is excited. The secondary-screen antenna may include a slot **26** formed on a conductor **21-C**, for example, formed through slotting on the conductor **21-C**. A gap **28** is provided on a side of the slot **26**, and the gap **28** may be specifically provided in a middle position of the side. Herein, the middle position refers to a midpoint of the side. In other words, a position of the gap **28** covers the midpoint of the side. The conductor **21-C** on a secondary screen may be formed through enclosing by a metal bezel of the secondary screen and a PCB ground of the secondary screen. For example, the slot **26** of the conductor **21-C** is formed on the PCB ground of the secondary screen. To be specific, one side of the slot **26** is formed by the metal bezel of the secondary screen, and the other side of the slot **26** is formed by the PCB ground of the secondary screen. A feed point **27** may be disposed on the side that is of the slot **26** and on which the gap **28** is provided, and the feed point **27** may be connected to a feed source. Electric fields in the slot **26** may be symmetrically and reversely distributed, and the foregoing CM slot antenna pattern shown in FIG. 5A and FIG. 5B is excited. The electric fields that are reversely distributed may be primary electric fields distributed in the slot **26**, and the electric fields may be generated by a fundamental mode of the secondary-screen antenna.

(53) The primary-screen antenna is the DM wire antenna, and the secondary-screen antenna is the CM slot antenna. Therefore, when the foldable screen of the electronic device is in the folded state, good isolation performance can also be obtained even if the primary-screen antenna and the secondary-screen antenna operate on a same frequency band.

(54) FIG. 7C shows an example solution in which a primary-screen antenna is a CM wire antenna and a secondary-screen antenna is a DM slot antenna.

(55) As shown in FIG. 7C, when a foldable screen of an electronic device is in a folded state, the primary-screen antenna and the secondary-screen antenna overlap, which may be that the primary-screen antenna and the secondary-screen antenna fully or partially overlap. The primary-screen antenna may include a conductor **21-B**, and a feed point **24** and a grounding stub **25** that are disposed on the conductor **21-B**. The feed point **24** may be connected to a feed source, and the grounding stub **25** may be connected to a ground. The conductor **21-B** on a primary screen may be a segment of a metal bezel of the primary screen, or a metal strip printed on an inner side of a bezel of the primary screen. Currents on the conductor **21-B** may be symmetrically and reversely distributed, and for example, the foregoing CM wire antenna pattern shown in FIG. 3A and FIG. 3B is excited. The secondary-screen antenna may include a slot **32** formed through slotting on a conductor **21-D**, for example, formed through slotting on the conductor **21-D**. A feed point **31** may be disposed on a side of the slot **32**, and the feed point **31** may be connected to a feed source. The conductor **21-D** on a secondary screen may be formed through enclosing by a metal bezel of the secondary screen and a PCB ground of the secondary screen. For example, the slot **32** of the conductor **21-D** is formed on the PCB ground of the secondary screen. To be specific, one side of the slot **32** is formed by the metal bezel of the secondary screen, and the other side of the slot **32** is formed by the PCB ground of the secondary screen. Electric fields in the slot **32** may be codirectionally distributed, and the foregoing DM slot antenna pattern shown in FIG. 6A and FIG. 6B is excited. The electric fields that are codirectionally distributed may be primary electric fields distributed in the slot **32**, and the electric fields may be generated by a fundamental mode of the secondary-screen antenna.

(56) The primary-screen antenna is the CM wire antenna, and the secondary-screen antenna is the

DM slot antenna. Therefore, when the foldable screen of the electronic device is in the folded state, good isolation performance can also be obtained even if the primary-screen antenna and the secondary-screen antenna operate on a same frequency band.

(57) In addition to the CM wire antenna pattern, the primary-screen antenna shown in FIG. 7C may actually further excite another antenna pattern: a DM wire antenna pattern. A principle for the DM wire antenna pattern has been described above. When the primary-screen antenna and the secondary-screen antenna overlap due to folding of the foldable screen, the DM wire antenna pattern excited by the primary-screen antenna and the DM slot antenna pattern of the secondary-screen antenna may be set to different frequency bands, to prevent the DM wire antenna pattern of the primary-screen antenna from interfering with the DM slot antenna pattern of the secondary-screen antenna.

(58) FIG. 7D shows an example solution in which a primary-screen antenna is a CM slot antenna and a secondary-screen antenna is a DM slot antenna.

(59) As shown in FIG. 7D, when a foldable screen of an electronic device is in a folded state, the primary-screen antenna and the secondary-screen antenna overlap, which may be that the primary-screen antenna and the secondary-screen antenna fully or partially overlap. The primary-screen antenna may include a slot 26 formed on a conductor 21-C, for example, formed through slotting on the conductor 21-C. A gap 28 is provided on a side of the slot 26, and the gap 28 may be specifically provided in a middle position of the side. Herein, the middle position refers to a midpoint of the side. In other words, a position of the gap 28 covers the midpoint of the side. A feed point 27 may be disposed on the side that is of the slot 26 and on which the gap 28 is provided, and the feed point 27 may be connected to a feed source. The conductor 21-C on a primary screen may be formed through enclosing by a metal bezel of the primary screen and a PCB ground of the secondary screen. For example, the slot 26 of the conductor 21-C is formed on the PCB ground of the primary screen. To be specific, one side of the slot 26 is formed by the metal bezel of the primary screen, and the other side of the slot 26 is formed by the PCB ground of the primary screen. Electric fields in the slot 26 may be symmetrically and reversely distributed, and the foregoing CM slot antenna pattern shown in FIG. 5A and FIG. 5B is excited. The electric fields that are reversely distributed may be primary electric fields distributed in the slot 26, and the electric fields may be generated by a fundamental mode of the primary-screen antenna. The secondary-screen antenna may include a slot 32 formed through slotting on a conductor 21-D, for example, formed through slotting on the conductor 21-D. A feed point 31 may be disposed on a side of the slot 32, and the feed point 31 may be connected to a feed source. The conductor 21-D on a secondary screen may be formed through enclosing by a metal bezel of the secondary screen and a PCB ground of the secondary screen. For example, the slot 32 of the conductor 21-D is formed on the PCB ground of the secondary screen. To be specific, one side of the slot 32 is formed by the metal bezel of the secondary screen, and the other side of the slot 32 is formed by the PCB ground of the secondary screen. Electric fields in the slot 32 may be codirectionally distributed, and the foregoing DM slot antenna pattern shown in FIG. 6A and FIG. 6B is excited. The electric fields that are codirectionally distributed may be primary electric fields distributed in the slot 32, and the electric fields may be generated by a fundamental mode of the secondary-screen antenna.

(60) The primary-screen antenna is the CM slot antenna, and the secondary-screen antenna is the DM slot antenna. Therefore, when the foldable screen of the electronic device is in the folded state, good isolation performance can also be obtained even if the primary-screen antenna and the secondary-screen antenna operate on a same frequency band.

(61) In the foregoing solutions shown in FIG. 7A to FIG. 7D, the primary-screen antenna may be disposed on the primary screen, and the secondary-screen antenna may be disposed on the secondary screen. Specifically, the conductor 21-A and the conductor 21-B each may be a suspended metal strip, and may be formed by a metal bezel, a metal middle frame, or the like of the electronic device. For an electronic device having a non-metal industrial design (industry design,

ID), the conductor **21-A** and the conductor **21-B** each may be a metal strip printed on an inner surface of a non-metal bezel, or a metal strip printed on an inner surface of a non-metal bezel through conductive silver paste. Specifically, the slot **26** and the slot **32** each may be formed on a conductor such as a PCB ground or a metal middle frame, for example, formed through slotting on the conductor. Implementation of the primary-screen antenna and the secondary-screen antenna in the entire device is described in detail in the following embodiments, and details are not described herein.

(62) In the foregoing solutions shown in FIG. 7A to FIG. 7D, positions of the primary-screen antenna and the secondary-screen antenna may be interchanged. For example, the primary-screen antenna in FIG. 7A may be disposed on the secondary screen to serve as the secondary-screen antenna, and the secondary-screen antenna in FIG. 7A may be disposed on the primary screen to serve as the primary-screen antenna.

(63) According to the solutions shown in FIG. 7A to FIG. 7D, in a scenario in which the foldable screen of the electronic device is in the folded state, good isolation performance can be also obtained even if the primary-screen antenna and the secondary-screen antenna overlap and operate on a same frequency band. In addition, radiation patterns of the primary-screen antenna and the secondary-screen antenna are complementary. In this way, two or more antennas that operate on a same frequency band can be highly isolated from each other without isolating the antennas at physical positions. This fully utilizes an antenna design space of an electronic device having a foldable screen.

(64) The following describes in detail implementation of a primary-screen antenna and a secondary-screen antenna in an entire device with reference to several embodiments. In the electronic device, a dielectric constant of a material that is filled in a hollow interior formed between a metal bezel and a PCB ground and filled in a gap on the metal bezel may be 3.0, and a dielectric loss angle of the material may be 0.01.

Embodiment 1

(65) FIG. 8A and FIG. 8B show examples of an antenna structure provided in Embodiment 1. FIG. 8A shows an antenna structure formed when a foldable screen **11** is in an open state, and FIG. 8B shows an antenna structure formed when the foldable screen **11** is in a folded state. The antenna structure provided in Embodiment 1 includes a primary-screen antenna and a secondary-screen antenna, where the primary-screen antenna may be a CM wire antenna and the secondary-screen antenna may be a DM wire antenna.

(66) As shown in FIG. 8A, the primary-screen antenna may be implemented by hollowing out a PCB ground and opening a gap on a metal bezel. Specifically, a suspended metal bezel **41-A** may be formed by opening gaps, such as two gaps **35-A** and **35-B** that are 0.9 millimeter to 2.0 millimeters wide, on a specific portion (such as a bottom bezel portion) of a primary-screen bezel **12-1**, and by hollowing out a PCB ground that is adjacent to the specific portion of the primary-screen bezel **12-1**. A hollow portion may form a slot **31-A** parallel to the suspended metal bezel **41-A**, to separate the suspended metal bezel **41-A** from a primary-screen PCB ground. In this way, the suspended metal bezel **41-A** is suspended from a ground. In other words, a clearance is formed. A length of the slot **31-A** is greater than a length of the suspended metal bezel **41-A**. To be specific, a slot longer than the suspended metal bezel **41-A** is formed along an extension direction of the specific portion of the primary-screen bezel **12-1** and across the two gaps **35-A** and **35-B**. In this way, a metal bezel between the two gaps **35-A** and **35-B** forms the suspended metal bezel, and therefore forms a wire antenna radiator. The suspended metal bezel **41-A** may be equivalent to the conductor **21-B** in FIG. 7A. In addition, a non-hollow portion **32** may form a grounding stub that is connected to the suspended metal bezel **41-A**, and the non-hollow portion **32** may be a strip-shaped ground stub shown in FIG. 8A. In addition to the strip-shaped ground stub, the grounding stub may alternatively be implemented by using a metal elastic piece disposed on a PCB ground of a primary screen portion, where the metal elastic piece may be connected to the suspended metal bezel **41-A**.

Alternatively, the grounding stub may be a metal stub that extends from a metal bezel of the primary screen portion and that is connected to the PCB ground. The specific portion of the primary-screen bezel **12-1** may be referred to as a first primary-screen bezel portion.

(67) FIG. **8A** further shows a feeding manner of the primary-screen antenna. A feed point **33-A** may be disposed on the suspended metal bezel **41-A**, to connect a feeder **34-A** to a feed source. The feed point **33-A** may be disposed close to a ground point to excite a CM wire antenna pattern. The ground point is a connection position for the grounding stub (the non-hollow portion) and the suspended metal bezel **41-A**. The ground point may be disposed in a middle of the suspended metal bezel **41-A**, or may be disposed at a position close to the middle of the suspended metal bezel **41-A**. That the ground point is disposed in the middle of the suspended metal bezel **41-A** may mean that the ground point is disposed at a midpoint of the suspended metal bezel **41-A**. In other words, the connection position for the grounding stub and the suspended metal bezel **41-A** covers the midpoint. Being close may mean that a distance from the ground point to the middle position is not greater than $\frac{1}{8}$ of an operating wavelength. In addition to a position close to the ground point, the feed point **33-A** may alternatively be disposed close to an open end of the suspended metal bezel **41-A**. Herein, that the feed point **33-A** is close to the ground point may mean that a distance from the feed point **33-A** to the ground point is greater than 0 and less than $\frac{1}{8}$ of the operating wavelength. That the feed point **33-A** is close to the open end of the suspended metal bezel **41-A** may mean that a distance from the feed point **33-A** to the open end is not greater than $\frac{1}{8}$ of the operating wavelength, and may even be equal to 0. The operating wavelength is an operating wavelength of the primary-screen antenna in the CM wire antenna pattern. A manner of calculating the operating wavelength is described in the following content, and details are not described herein.

(68) It should be understood that the midpoint of the suspended metal bezel **41-A** may be considered as a midpoint in terms of a length of the suspended metal bezel **41-A**, and the length herein may be considered as an electrical length. The electrical length may be represented by a ratio of a physical length (that is, a mechanical length or a geometric length) multiplied by time for which an electrical or electromagnetic signal is transmitted in a medium to time for the signal to travel a distance equal to a physical length of the medium in free space. The electrical length may meet the following formula:

$$(69) \ L = L \times \frac{a}{b}.$$

(70) L represents the physical length, a represents the time for which the electrical or electromagnetic signal is transmitted in the medium, and b represents transmission time in free space.

(71) Alternatively, the electrical length may be a ratio of the physical length (that is, the mechanical length or the geometric length) to a wavelength of a transmitted electromagnetic wave. The electrical length may meet the following formula:

$$(72) \ L = \frac{L}{\lambda}.$$

(73) L represents the physical length, and λ represents the wavelength of the electromagnetic wave.

(74) Similarly, as shown in FIG. **8A**, the secondary-screen antenna may also be implemented by hollowing out a PCB ground and opening a gap on a metal bezel. Specifically, a suspended metal bezel **41-B** may be formed by opening gaps, such as two gaps **36-A** and **36-B**, on a specific portion (such as a bottom bezel portion) of a secondary-screen bezel **12-3**, and by hollowing out a PCB ground that is adjacent to the specific portion of the secondary-screen bezel **12-3**. A hollow portion may form a slot **31-B** parallel to the suspended metal bezel **41-B**, to separate the suspended metal bezel **41-B** from a secondary-screen PCB ground. In this way, the suspended metal bezel **41-B** is suspended from the ground. In other words, a clearance is formed. A length of the slot **31-B** is greater than a length of the suspended metal bezel **41-B**. To be specific, a slot longer than the suspended metal bezel **41-B** is formed along an extension direction of the specific portion adjacent to the secondary-screen bezel **12-3** and across the two gaps **36-A** and **36-B**. In this way, a metal bezel between the two gaps **36-A** and **36-B** forms the suspended metal bezel, and therefore forms a

wire antenna radiator. The suspended metal bezel **41-B** may be equivalent to the conductor **21-A** in FIG. **7A**. Different from the primary-screen antenna, no grounding stub is disposed on the suspended metal bezel **41-B** in the secondary-screen antenna. The secondary-screen antenna does not include a structure the same as the non-hollow portion **32** of the primary-screen antenna. The specific portion of the secondary-screen bezel **12-1** may be referred to as a first secondary-screen bezel portion.

(75) FIG. **8A** further shows a feeding manner of the secondary-screen antenna. A feed point **33-B** may be disposed on the suspended metal bezel **41-B**, to connect a feeder **34-B** to a feed source. The feed point **33-B** may be disposed close to a middle position of the suspended metal bezel **41-B**, which may be referred to as offset feeding from the middle, to excite a DM wire antenna pattern. That the feed point **33-B** is disposed in the middle position of the suspended metal bezel **41-B** may mean that the feed point **33-B** is disposed at a midpoint of the suspended metal bezel **41-B**. In other words, a connection position for the feeder **34-B** and the suspended metal bezel **41-B** covers the midpoint. In addition to a position close to the middle position, the feed point **33-B** may alternatively be disposed close to an open end of the suspended metal bezel **41-B**. Being close herein may mean that a distance from the feed point **33-B** to the middle position of the suspended metal bezel **41-B** is less than $1/16$ of an operating wavelength, or a distance from the feed point **33-B** to the open end of the suspended metal bezel **41-B** is less than $1/16$ of the operating wavelength. Being close may also include a case in which the distance is equal to 0. The operating wavelength is an operating wavelength of the secondary-screen antenna in the DM wire antenna pattern.

(76) The primary-screen antenna and the secondary-screen antenna in FIG. **8A** may be antennas that operate on a same frequency band. For current distribution on the primary-screen antenna, reference may be made to FIG. **3A**. To be specific, currents on the suspended metal bezel **41-A** are symmetrically and reversely distributed. For current distribution on the secondary-screen antenna, reference may be made to FIG. **4A**. To be specific, currents on the suspended metal bezel **41-B** are codirectionally distributed. In addition, the primary-screen antenna and the secondary-screen antenna may further excite the ground to generate currents whose distribution is shown in FIG. **8C**. For a radiation direction of the primary-screen antenna, reference may be made to FIG. **3B**. To be specific, the primary-screen antenna radiates in a direction along the suspended metal bezel **41-A**. For a radiation direction of the secondary-screen antenna, reference may be made to FIG. **4B**. To be specific, the secondary-screen antenna radiates in a direction perpendicular to the suspended metal bezel **41-B**.

(77) FIG. **8B** shows an example of a position relationship between the primary-screen antenna and the secondary-screen antenna when the foldable screen **11** is in the folded state. When the foldable screen **11** is in the folded state, positions of the primary-screen antenna and the secondary-screen antenna overlap. For example, the primary-screen antenna is located on a primary-screen bezel portion (that is, the first primary-screen bezel portion) that forms the suspended metal bezel **41-A**, and the secondary-screen antenna is located on a secondary-screen bezel portion (that is, the first secondary-screen bezel portion) that forms the suspended metal bezel **41-B**. The overlap does not affect performance of the primary-screen antenna and the secondary-screen antenna because the primary-screen antenna and the secondary-screen antenna are respectively the CM wire antenna and the DM wire antenna whose radiation directions are orthogonal. Even if the primary-screen antenna and the secondary-screen antenna operate on a same frequency band (such as a B1 frequency band, a B3 frequency band, a B7 frequency band, an N77 frequency band, or a frequency band from 3.6 GHz to 4.1 GHz), good isolation performance can also be obtained. In this way, two antennas operating on a same frequency band can be disposed in overlapping areas of the primary screen and the secondary screen, and directivity patterns of the two antennas are complementary.

(78) Antennas on the foldable screen in Embodiment 1 may be further transformed into antennas shown in FIG. **9A** and FIG. **9B**. To be specific, the primary-screen antenna may be transformed from the CM wire antenna to an inverted F antenna (inverted F antenna, IFA) that operates in a $\frac{1}{4}$

wavelength mode. FIG. 9C shows distribution of currents excited by a primary-screen IFA wire antenna and a secondary-screen DM wire antenna. Distribution of ground currents excited by the primary-screen IFA wire antenna conforms to distribution of ground currents excited by the CM wire antenna. In this way, a radiation direction of the primary-screen IFA wire antenna is basically the same as a radiation direction of the CM wire antenna, and is orthogonal to a radiation direction of the secondary-screen DM wire antenna. Simulation experiments show that maximum radiation directions in directivity patterns of the primary-screen IFA wire antenna and the secondary-screen DM wire antenna are orthogonal. Therefore, even if the two antennas operate on a same frequency band, high isolation performance can also be obtained when the foldable screen **11** is in the folded state. FIG. 9D shows a simplified structure of the antennas in FIG. 9A and FIG. 9B in the folded state. For example, the primary-screen antenna may operate on the N77 frequency band (for example, from 3.6 GHz to 4.1 GHz) and in the $\frac{1}{4}$ wavelength mode. The secondary-screen antenna may also operate on the N77 frequency band but in a $\frac{1}{2}$ wavelength mode. It can be learned from FIG. 9E that isolation performance between a primary-screen N77 antenna and a secondary-screen N77 antenna is good.

(79) To cover more frequency bands, a plurality of primary-screen antennas may be designed at a position at which the primary-screen antenna and the secondary-screen DM wire antenna overlap. For example, a plurality of primary-screen IFA antennas may be designed. The plurality of primary-screen IFA antennas may include an IFA antenna that operates on a same frequency band as the secondary-screen DM wire antenna, and may also include an IFA antenna that operates on a frequency band different from the secondary-screen DM wire antenna. For example, as shown in FIG. 9F, two primary-screen IFA antennas may be disposed. One of the antennas may operate on the N77 frequency band, and the other of the antennas may operate on a mid-high band (mid-high band, MHB). It can be learned from FIG. 9G and FIG. 9H that, when the foldable screen is in the folded state, antennas shown in FIG. 9F are slightly affected by each other, and radiation efficiency and system efficiency are still high.

(80) In a case in which the primary-screen antenna is transformed from the CM wire antenna to the inverted F antenna, the secondary-screen antenna may alternatively be a DM slot antenna. In this case, high isolation performance may still be obtained when the primary-screen antenna and the secondary-screen antenna overlap. For specific implementation of the DM slot antenna in the entire device, refer to the DM slot antenna described in subsequent embodiments in FIG. 10A and FIG. 10B and FIG. 12A and FIG. 12B.

Embodiment 2

(81) FIG. 10A and FIG. 10B show examples of an antenna structure provided in Embodiment 2. FIG. 10A shows an antenna structure formed when a foldable screen **11** is in an open state, and FIG. 10B shows an antenna structure formed when the foldable screen **11** is in a folded state. The antenna structure provided in Embodiment 2 includes a primary-screen antenna and a secondary-screen antenna, where the primary-screen antenna may be a CM wire antenna and the secondary-screen antenna may be a DM slot antenna.

(82) As shown in FIG. 10A, the primary-screen antenna in Embodiment 2 is the same as the primary-screen antenna shown in FIG. 8A, and may be implemented by hollowing out a PCB ground and opening a gap on a metal bezel. For details, refer to related descriptions in FIG. 8A, and details are not described herein.

(83) As shown in FIG. 10A, the secondary-screen antenna may be implemented by hollowing out a PCB ground. Specifically, a PCB ground adjacent to a specific portion (such as a bottom bezel portion) of a secondary-screen metal bezel **12-3** may be hollowed out. In this way, the PCB ground that is hollowed out on a secondary screen portion and the specific portion of the secondary-screen metal bezel **12-3** enclose to form a slot **52-B**. Two ends of the slot **52-B** are closed (which may be referred to as closed ends). One side of the slot **52-B** is the secondary-screen metal bezel **12-3**, and the other side of the slot **52-B** is the PCB ground on the secondary screen portion. The slot **52-B** is

the slot **32** in FIG. **7C**. FIG. **10A** further shows a feeding manner of the secondary-screen antenna. A feed point **53-B** may be disposed on a side that is of the slot **52-B** and on which the metal bezel (such as a metal bezel **51-B**) is located, to connect a feeder **54-B** to a feed source. In addition, no gap is provided on the side that is of the slot **52-B** and on which the feed point is disposed. The feed point **53-B** may be disposed close to a middle position of the metal bezel **51-B**, to excite a DM slot antenna pattern. In addition to a position close to the middle position, the feed point **53-B** may alternatively be disposed close to a closed end of the slot **52-B**. Being close herein may mean that a distance from the feed point **53-B** to the middle position or the closed end is less than $1/16$ of an operating wavelength. Being close may also include a case in which the distance is equal to 0.

(84) Herein, that the feed point **53-B** is disposed in the middle position of the suspended metal bezel **51-B** (in this case, the distance is equal to 0) may mean that the feed point **53-B** is disposed at a midpoint of the suspended metal bezel **51-B**. In other words, a connection position for the feeder **54-B** and the suspended metal bezel **51-B** covers the midpoint.

(85) The primary-screen antenna and the secondary-screen antenna in FIG. **10A** may be antennas that operate on a same frequency band. For current distribution on the primary-screen antenna, reference may be made to FIG. **3A**. To be specific, currents on the suspended metal bezel **51-A** are symmetrically and reversely distributed. For electric field distribution on the secondary-screen antenna, reference may be made to FIG. **6A**. To be specific, electric fields in the slot **52-B** are codirectionally distributed. For a radiation direction of the primary-screen antenna, reference may be made to FIG. **3B**. To be specific, the primary-screen antenna radiates in a direction along the suspended metal bezel **41-A**. For a radiation direction of the secondary-screen antenna, reference may be made to FIG. **6B**. To be specific, the secondary-screen antenna radiates in a direction perpendicular to the slot **52-B**.

(86) FIG. **10B** shows an example of a position relationship between the primary-screen antenna and the secondary-screen antenna when the foldable screen **11** is in the folded state. When the foldable screen **11** is in the folded state, positions of the primary-screen antenna and the secondary-screen antenna overlap. The overlap does not affect performance of the primary-screen antenna and the secondary-screen antenna because the primary-screen antenna and the secondary-screen antenna are respectively the CM wire antenna and the DM slot antenna whose radiation directions are orthogonal. Even if the primary-screen antenna and the secondary-screen antenna operate on a same frequency band, good isolation performance can also be obtained. In this way, two antennas operating on a same frequency band can be disposed in overlapping areas of the primary screen and the secondary screen, and directivity patterns of the two antennas are complementary.

Embodiment 3

(87) FIG. **11A** and FIG. **11B** show examples of an antenna structure provided in Embodiment 3. FIG. **11A** shows an antenna structure formed when a foldable screen **11** is in an open state, and FIG. **11B** shows an antenna structure formed when the foldable screen **11** is in a folded state. The antenna structure provided in Embodiment 3 includes a primary-screen antenna and a secondary-screen antenna, where the primary-screen antenna may be a CM slot antenna and the secondary-screen antenna may be a DM wire antenna.

(88) As shown in FIG. **11A**, the primary-screen antenna may be implemented by hollowing out a PCB ground and opening a gap on a metal bezel. Specifically, a PCB ground adjacent to a specific portion (such as a bottom bezel portion) of a primary-screen metal bezel **12-1** may be hollowed out. The PCB ground that is hollowed out on a primary screen portion and the primary-screen metal bezel **12-1** enclose to form a slot **62-A**. Two ends of the slot **62-A** are closed. One side of the slot **62-B** is the primary-screen metal bezel **12-1**, and the other side of the slot **62-A** is the PCB ground on the primary screen portion. In addition, a gap, such as a gap **67**, may be provided on the metal bezel on a side of the slot **62-A**, to connect the slot **62-A** to external free space. The slot **62-A** is the slot **26** in FIG. **7B**, and the gap **67** is the gap **28** in FIG. **7B**. The gap **67** may be provided in a middle position of the metal bezel on the side of the slot **62-A**. The middle position is a midpoint

on the side of the slot **62-A**. In other words, a position of the gap **67** covers the midpoint.

(89) FIG. **11A** further shows a feeding manner of the primary-screen antenna. A feed point **63-A** may be disposed on a side that is of the slot **62-A** and on which the metal bezel is located, to connect a feeder **64-A** to a feed source. The feed point **63-A** may be disposed close to the gap **67**, to excite a CM wire antenna pattern. In addition to a position close to the gap **67**, the feed point **63-A** may alternatively be disposed close to a closed end of the slot **62-A**. Herein, that the feed point **63-A** is close to the gap **67** may mean that a distance from the feed point **63-A** to the gap **67** is greater than 0 and less than $\frac{1}{4}$ of an operating wavelength. That the feed point **63-A** is close to a closed end of the slot **62-A** may mean that a distance from the feed point **63-A** to the closed end is less than $\frac{1}{4}$ of the operating wavelength. Being close may also include a case in which the distance is equal to 0. The operating wavelength is an operating wavelength of the primary-screen antenna in a CM slot antenna pattern. A manner of calculating the operating wavelength is described in the following content, and details are not described herein.

(90) Herein, the distance from the feed point **63-A** to the gap **67** may be a distance from the feed point **63-A** to a midpoint of the gap **67**, or may be a distance from the feed point **63-A** to two ends of the gap **67**.

(91) As shown in FIG. **11A**, the secondary-screen antenna in Embodiment 3 is the same as the secondary-screen antenna shown in FIG. **8A**, and may be implemented by hollowing out a PCB ground and opening a gap on a metal bezel. For details, refer to related descriptions of the secondary-screen antenna in FIG. **8A**, and details are not described herein.

(92) The primary-screen antenna and the secondary-screen antenna in FIG. **11A** may be antennas that operate on a same frequency band. For electric field distribution on the primary-screen antenna, reference may be made to FIG. **7B**. To be specific, electric fields in the slot **62-A** are symmetrically and reversely distributed. For current distribution on the secondary-screen antenna, reference may be made to FIG. **7B**. To be specific, currents on a suspended metal bezel **61-B** are codirectionally distributed. For a radiation direction of the primary-screen antenna, reference may be made to FIG. **5B**. To be specific, the primary-screen antenna radiates in a direction along the slot **62-A**. For a radiation direction of the secondary-screen antenna, reference may be made to FIG. **4B**. To be specific, the secondary-screen antenna radiates in a direction perpendicular to the suspended metal bezel **61-B**.

(93) FIG. **11B** shows an example of a position relationship between the primary-screen antenna and the secondary-screen antenna when the foldable screen **11** is in the folded state. When the foldable screen **11** is in the folded state, positions of the primary-screen antenna and the secondary-screen antenna overlap. The overlap does not affect performance of the primary-screen antenna and the secondary-screen antenna because the primary-screen antenna and the secondary-screen antenna are respectively the CM slot antenna and the DM wire antenna whose radiation directions are orthogonal. Even if the primary-screen antenna and the secondary-screen antenna operate on a same frequency band, good isolation performance can also be obtained. In this way, two antennas operating on a same frequency band can be disposed in overlapping areas of the primary screen and the secondary screen, and directivity patterns of the two antennas are complementary.

Embodiment 4

(94) FIG. **12A** and FIG. **12B** show examples of an antenna structure provided in Embodiment 4. FIG. **12A** shows an antenna structure formed when a foldable screen **11** is in an open state, and FIG. **12B** shows an antenna structure formed when the foldable screen **11** is in a folded state. The antenna structure provided in Embodiment 4 includes a primary-screen antenna and a secondary-screen antenna, where the primary-screen antenna may be a CM slot antenna and the secondary-screen antenna may be a DM slot antenna.

(95) As shown in FIG. **12A**, the primary-screen antenna in Embodiment 4 is the same as the primary-screen antenna shown in FIG. **11A**, and may be implemented by hollowing out a PCB ground and opening a gap on a metal bezel. For details, refer to related descriptions of the primary-

screen CM slot antenna in FIG. 11A, and details are not described herein.

(96) As shown in FIG. 12A, the secondary-screen antenna in Embodiment 4 is the same as the secondary-screen antenna shown in FIG. 10A, and may be implemented by hollowing out a PCB ground and opening a gap on a metal bezel. For details, refer to related descriptions of the secondary-screen DM slot antenna in FIG. 10A, and details are not described herein.

(97) The primary-screen antenna and the secondary-screen antenna in FIG. 12A may be antennas that operate on a same frequency band. For electric field distribution on the primary-screen antenna, reference may be made to FIG. 7D. To be specific, electric fields in a slot 72-A are symmetrically and reversely distributed. For current distribution on the secondary-screen antenna, reference may be made to FIG. 7D. To be specific, currents in the slot 72-A are codirectionally distributed. For a radiation direction of the primary-screen antenna, reference may be made to FIG. 5B. To be specific, the primary-screen antenna radiates in a direction along the slot 72-A. For a radiation direction of the secondary-screen antenna, reference may be made to FIG. 6B. To be specific, the secondary-screen antenna radiates in a direction perpendicular to the slot 72-A.

(98) FIG. 12B shows an example of a position relationship between the primary-screen antenna and the secondary-screen antenna when the foldable screen 11 is in the folded state. When the foldable screen 11 is in the folded state, positions of the primary-screen antenna and the secondary-screen antenna overlap. The overlap does not affect performance of the primary-screen antenna and the secondary-screen antenna because the primary-screen antenna and the secondary-screen antenna are respectively the CM slot antenna and the DM slot antenna whose radiation directions are orthogonal. Even if the primary-screen antenna and the secondary-screen antenna operate on a same frequency band, good isolation performance can also be obtained. In this way, two antennas operating on a same frequency band can be disposed in overlapping areas of the primary screen and the secondary screen, and directivity patterns of the two antennas are complementary.

(99) Antennas on a foldable screen in the foregoing embodiments are disposed at overlapping positions of the foldable screen in a folded state. In this way, antennas that operate on a same frequency band can have good performance. Further, space utilization of a primary screen and a secondary screen in a foldable-screen antenna design can be improved, and more antennas can be disposed. This is especially beneficial to a MIMO antenna design.

(100) FIG. 13A and FIG. 13B show feed positions in antenna structures according to an embodiment of this application.

(101) As shown in FIG. 13A, a feed position of a DM wire antenna may be disposed close to a middle position of a radiator. In addition to a position close to the middle position, the feed position may alternatively be disposed close to an open end of the radiator. Being close may mean that a distance from the feed point to the middle position or the open end of the radiator is less than a first distance. For example, the first distance is equal to $1/16$ of an operating wavelength. To be specific, the distance is greater than 0 and less than $1/16$ of the operating wavelength. Being close may also include a case in which the distance is equal to 0. Herein, the operating wavelength is an operating wavelength in a DM wire antenna pattern. For a position relationship between a feed position and a slot of a DM slot antenna, reference may be made to FIG. 13A. The slot may be considered as a radiator of the slot antenna. The feed position may be disposed close to a middle position of the slot, or close to a closed end of the slot. As described in the foregoing embodiments, the slot may be formed through enclosing by a metal bezel and a PCB ground by hollowing out the PCB ground.

(102) As shown in FIG. 13B, a feed position of a CM wire antenna may be disposed close to a ground point (a connection point for a grounding stub and a radiator) of the radiator. In addition to a position close to the ground point, the feed position may alternatively be disposed close to an open end of the radiator. Herein, that the feed point is close to the ground point may mean that a distance from the feed point to the ground point is less than a second distance. For example, the second distance is equal to $1/8$ of an operating wavelength. To be specific, the distance is greater

than 0 and less than $\frac{1}{8}$ of the operating wavelength. That the feed point is close to the open end may mean that a distance from the feed point to the open end is not greater than $\frac{1}{8}$ of the operating wavelength, and being close may include a case in which the distance is equal to 0. The operating wavelength is an operating wavelength in a CM wire antenna pattern. For a position relationship between a feed position and a slot of a CM slot antenna, reference may be made to FIG. 13B. The slot may be considered as a radiator of the slot antenna. The feed position may be disposed close to a gap on a side of the slot, or close to a closed end of the slot.

(103) FIG. 14A to FIG. 14G show size designs that are used when an antenna structure provided in an embodiment of this application is implemented as antennas that operate on several typical frequency bands.

(104) As shown in FIG. 14A, a primary-screen antenna and a secondary-screen antenna each may be an antenna that operates on an N77 frequency band. A length of a radiator for each of the primary-screen antenna and the secondary-screen antenna may be approximately 13 millimeters. However, no limitation is imposed on the length, and an antenna radiation length of each of the primary-screen N77 antenna and the secondary-screen N77 antenna may alternatively be adjusted by using a tuning switch. For isolation performance between the primary-screen antenna and the secondary-screen antenna in the antenna structure shown in FIG. 14A, reference may be made to FIG. 9E.

(105) As shown in FIG. 14B, a half-length of a radiator for the primary-screen antenna may be approximately 24 millimeters, and a length from a feed point to an open end may be approximately 6 millimeters. In other words, a size of the primary-screen antenna may be changed so that the primary-screen antenna operates on a mid-high band MHB and a B1/B3 frequency band. However, no limitation is imposed on the length, and an antenna radiation length of the primary-screen antenna may alternatively be adjusted by using a tuning switch. FIG. 14C shows that the primary-screen antenna in FIG. 14B resonates in the MHB and the B1/B3 frequency band.

(106) As shown in FIG. 14D, a half-length of a radiator for the primary-screen antenna may be approximately 18 millimeters, and a length from a feed point to an open end may be 6 millimeters. In other words, a size of the primary-screen antenna may be changed so that the primary-screen antenna operates on the mid-high band MHB and a B7 frequency band. However, no limitation is imposed on the length, and an antenna radiation length of the primary-screen antenna may alternatively be adjusted by using the tuning switch. FIG. 14E shows that the primary-screen antenna in FIG. 14D resonates in the MHB and the B7 frequency band.

(107) As shown in FIG. 14F, a half-length of a radiator for the primary-screen antenna may be approximately 11 millimeters, and a length from a feed point to an open end may be 4 millimeters. In other words, a size of the primary-screen antenna may be changed so that the primary-screen antenna operates on the mid-high band MHB and the N77 frequency band. However, no limitation is imposed on the length, and an antenna radiation length of the primary-screen antenna may alternatively be adjusted by using the tuning switch. FIG. 14G shows that the primary-screen antenna in FIG. 14F resonates in the MHB and the N77 frequency band.

(108) In addition to the several typical frequency bands shown in FIG. 14A to FIG. 14G, the primary-screen antenna and the secondary-screen antenna provided in embodiments of this application may alternatively operate on another frequency band. In this application, an operating wavelength in a specific wavelength mode (such as a $\frac{1}{2}$ wavelength mode) of an antenna may be a wavelength of a signal radiated by the antenna. For example, a suspended metal antenna in the $\frac{1}{2}$ wavelength mode may generate a resonance of a 1.575 GHz frequency band, where an operating wavelength in the $\frac{1}{2}$ wavelength mode is a wavelength of a signal radiated by the antenna on the 1.575 GHz frequency band. It should be understood that a wavelength of a radiated signal in the air may be calculated based on the following formula: $\text{Wavelength} = \text{Speed of light} / \text{Frequency}$, where the frequency is a frequency of the radiated signal. A wavelength of the radiated signal in a medium may be calculated based on the following formula: $\text{Wavelength} = (\text{Speed of light} / \sqrt{\text{square root over$

(ϵ))/Frequency, where ϵ is a relative dielectric constant of the medium, and the frequency is the frequency of the radiated signal. The gap and the slot in the foregoing embodiments may be filled with an insulating medium.

(109) In the foregoing embodiments, $1/16$ of an operating wavelength and $1/8$ of an operating wavelength are mentioned, where the “operating wavelength” may be a wavelength corresponding to a center frequency of a resonance frequency. For example, it is assumed that a center frequency of a B1 uplink frequency band (the resonance frequency is from 1920 MHz to 1980 MHz) is 1955 MHz. In this case, the operating wavelength may be a wavelength calculated based on the frequency of 1955 MHz. Not limited to the center frequency, the “operating wavelength” may alternatively be a wavelength corresponding to a non-center frequency of the resonance frequency.

(110) The term “close” mentioned in the foregoing embodiments is constrained by using $1/16$ of the operating wavelength and $1/8$ of the operating wavelength as critical values. However, the two values are merely examples. That a feed point or a grounding stub is close to a position (for example, close to a middle position or an open end of a radiator) means that a distance between the feed point or the grounding stub and the position does not exceed a specific distance. In this way, a position relationship of “being close” is constrained. The examples in the foregoing embodiments may be used as an implementation.

(111) In the foregoing embodiments, an open end and a closed end are, for example, relative to a ground. The closed end is grounded and the open end is not grounded. Alternatively, the open end and the closed end are, for example, relative to another conductor. The closed end is electrically connected to another conductor, and the open end is not electrically connected to the another conductor.

(112) In addition, in the foregoing content of this application, a limitation on a position or a distance, such as a middle or a middle position, is relative to the state of the art, and is not strictly defined in a mathematical sense. For example, a middle position of a conductor is a midpoint of the conductor. In actual application, a connection position for another component (such as a feeder or the grounding stub) and the conductor covers the midpoint. A middle position in a slot or a middle position on a side of the slot is a midpoint on a side of the slot. In actual application, a connection position for another component (such as the feeder) and the side covers the midpoint. In actual application, that a gap is provided in a middle position on a side of a slot means that a position of the gap on the side covers a midpoint of the side.

(113) The feed point mentioned in the foregoing content of this application may be any point, such as a center point, in a connection area (which may also be referred to as a connection position) between a feeder and a conductor. A distance from a point (such as a feed point, a connection point, or a ground point) to a gap or from a gap to a point may be a distance from the point to a midpoint of the gap, or may be a distance from the point to two ends of the gap.

(114) Co-directional/reverse distribution of currents mentioned in the foregoing content of this application should be understood as that directions of primary currents on conductors on a same side are consistent/reverse. For example, when codirectionally distributed currents are excited on an annular conductor (for example, a current path is also annular), it should be understood that the currents meet a definition of being codirectionally distributed in this application even if directions of primary currents excited on conductors on two sides of the annular conductor (for example, on conductors surrounding a gap, or on conductors on two sides of the gap) are reverse.

(115) The foregoing descriptions are merely specific implementations of this application, but the protection scope of this application is not limited thereto. Any variation or replacement readily figured out by a person skilled in the art within the technical scope disclosed in this application shall fall within the protection scope of this application. Therefore, the protection scope of this application shall be subject to the protection scope of the claims.

Claims

1. An electronic device, comprising a first device body, a second device body, and a rotating shaft, wherein the first device body and the second device body are connected through the rotating shaft, and the electronic device is configured to be foldable at the rotating shaft; and the electronic device further comprises a first antenna disposed on the first device body and a second antenna disposed on the second device body, wherein the first antenna comprises a strip-shaped first conductor and a first feed point disposed on the first conductor, wherein two ends of the first conductor are open, and a distance from the first feed point to a middle position of the first conductor is greater than or equal to zero and less than $1/16$ of an operating wavelength of the first antenna, or a distance from the first feed point to one of the open ends of the first conductor is greater than or equal to zero and less than $1/16$ of an operating wavelength of the first antenna; and the second antenna is an inverted F antenna that comprises a strip-shaped second conductor, and a second feed point and a grounding stub that are disposed on the second conductor, wherein one end of the second conductor is open, the other end of the second conductor is grounded through the grounding stub, and a distance from the second feed point to a connection point for the second conductor and the grounding stub is greater than zero and less than $1/8$ of an operating wavelength of the second antenna, or a distance from the second feed point to the open end of the second conductor is greater than or equal to zero and less than $1/8$ of an operating wavelength of the second antenna, wherein the first conductor and the second conductor at least partially overlap when the electronic device is in a folded state.
2. The electronic device according to claim 1, wherein an operating frequency of the first antenna and an operating frequency of the second antenna comprise a same frequency band.
3. The electronic device according claim 1, wherein that the first conductor and the second conductor at least partially overlap when the electronic device is in the folded state comprises: a projection of the first conductor and a projection of the second conductor partially or fully overlap on a plane on which the first device body is located or a plane on which the second device body is located.
4. The electronic device according to claim 1, wherein the electronic device further comprises a bezel of the first device body and a ground of the first device body; and the first conductor is a strip-shaped conductor disposed on the bezel of the first device body, the first conductor is separated from the ground of the first device body by a first slot, the first slot is formed by hollowing out the ground of the first device body, the first slot is adjacent to the first conductor, and the first conductor is not grounded.
5. The electronic device according to claim 4, wherein the electronic device further comprises a bezel of the second device body and a ground of the second device body; and the second conductor is a strip-shaped conductor disposed on the bezel of the second device body, the second conductor and the ground of the second device body are separated by a second slot and connected through the grounding stub, the second slot is formed by hollowing out the ground of the second device body, and the second slot is adjacent to the second conductor.
6. The electronic device according to claim 5, wherein the grounding stub is a strip-shaped ground portion that is disposed in a hollowed-out portion of the ground of the second device body and that is connected to the second conductor, or the grounding stub is a metal elastic piece that is disposed on the ground of the second device body and that is connected to the second conductor, or the grounding stub is a conductive stub that extends from the second conductor and that is connected to the ground.
7. The electronic device according to claim 5, wherein the bezel of the first device body comprises a first metal bezel between a first gap and a second gap, the first conductor is the first metal bezel; and wherein the bezel of the second device body comprises a second metal bezel between a third gap and the grounding stub, the second conductor is the second metal bezel.

8. An electronic device, comprising a first device body, a second device body, and a rotating shaft, wherein the first device body and the second device body are connected through the rotating shaft, and the electronic device is configured to be foldable at the rotating shaft; and the electronic device further comprises a first antenna disposed on the first device body and a second antenna disposed on the second device body, wherein the first antenna comprises a strip-shaped first conductor and a first feed point disposed on the first conductor, wherein two ends of the first conductor are open, and a distance from the first feed point to a middle position of the first conductor is greater than or equal to zero and less than $1/16$ of an operating wavelength of the first antenna, or a distance from the first feed point to one of the open ends of the first conductor is greater than or equal to zero and less than $1/16$ of an operating wavelength of the first antenna; and the second antenna comprises a second conductor provided with a first slot, two ends of the first slot are closed and grounded, a first side of the first slot is provided with a first gap, a distance from the first gap to a middle position on the first side is less than $1/16$ of an operating wavelength of the second antenna, a second feed point is disposed on the first side of the first slot, and a distance from the second feed point to the first gap is greater than zero and less than $1/8$ of the operating wavelength of the second antenna, wherein the first conductor and the second conductor at least partially overlap when the electronic device is in a folded state.

9. The electronic device according to claim 8, wherein an operating frequency of the first antenna and an operating frequency of the second antenna comprise a same frequency band.

10. The electronic device according to claim 8, wherein that the first antenna and the second antenna at least partially overlap when the electronic device is in the folded state comprises: a projection of the first antenna and a projection of the second antenna partially or fully overlap on a plane on which the first device body is located or a plane on which the second device body is located.

11. The electronic device according to claim 8, wherein the electronic device further comprises a bezel of the first device body and a ground of the first device body; and the first conductor is a strip-shaped conductor disposed on the bezel of the first device body, the first conductor is separated from the ground of the first device body by a second slot, the second slot is formed by hollowing out the ground of the first device body, the second slot is adjacent to the first conductor, and the first conductor is not grounded.

12. The electronic device according to claim 11, wherein the bezel of the first device body comprises a first metal bezel between a first gap and a second gap, the first conductor is the first metal bezel.

13. The electronic device according to claim 8, wherein the electronic device further comprises a metal bezel of the second device body and a ground of the second device body; and the second conductor comprises the metal bezel of the second device body and the ground of the second device body that enclose to form the first slot, the first slot is disposed in a hollowed-out portion of the ground of the second device body, the first slot is adjacent to the metal bezel of the second device body, the first gap is a gap provided on the metal bezel that is of the second device body and adjacent to the first slot and that forms the first side of the first slot, the first gap is provided on the metal bezel on one side of the second feed point, and no gap is provided on the metal bezel on the other side of the second feed point.

14. An electronic device, comprising a first device body, a second device body, and a rotating shaft, wherein the first device body and the second device body are connected through the rotating shaft, and the electronic device is configured to be foldable at the rotating shaft; and the electronic device further comprises a first antenna disposed on the first device body and a second antenna disposed on the second device body, wherein the first antenna comprises a first conductor provided with a first slot, two ends of the first slot are closed and grounded, a first feed point is disposed on a first side of the first slot, and a distance from the first feed point to a middle position on the first side of the first slot is greater than or equal to zero and less than $1/16$ of an operating wavelength of the

first antenna; and the second antenna is an inverted F antenna that comprises a strip-shaped second conductor, and a second feed point and a grounding stub that are disposed on the second conductor, wherein one end of the second conductor is open, the other end of the second conductor is grounded through the grounding stub, and a distance from the second feed point to a connection point for the second conductor and the grounding stub is greater than zero and less than $\frac{1}{8}$ of an operating wavelength of the second antenna, or a distance from the second feed point to the open end of the second conductor is greater than or equal to zero and less than $\frac{1}{8}$ of an operating wavelength of the second antenna, wherein the first conductor and the second conductor at least partially overlap when the electronic device is in a folded state.

15. The electronic device according to claim 14, wherein an operating frequency of the first antenna and an operating frequency of the second antenna comprise a same frequency band.

16. The electronic device according to claim 14, wherein that the first antenna and the second antenna at least partially overlap when the electronic device is in the folded state comprises: a projection of the first antenna and a projection of the second antenna partially or fully overlap on a plane on which the first device body is located or a plane on which the second device body is located.

17. The electronic device according to claim 14, wherein the electronic device further comprises a bezel of the first device body and a ground of the first device body; and the first conductor is a strip-shaped conductor disposed on the bezel of the first device body, the first conductor and the ground of the first device body are separated by a second slot and connected through the grounding stub, the second slot is formed by hollowing out the ground of the first device body, and the second slot is adjacent to the first conductor.

18. The electronic device according to claim 17, wherein the bezel of the first device body comprises a first metal bezel between a first gap and the grounding stub, the first conductor is the first metal bezel.

19. The electronic device according to claim 17, wherein the grounding stub is a strip-shaped ground portion that is formed by hollowing out the ground of the first device body and that is connected to the first conductor, or the grounding stub is a metal elastic piece that is disposed on the ground of the first device body and that is connected to the first conductor, or the grounding stub is a conductive stub that extends from the first conductor and that is connected to the ground.

20. The electronic device according to claim 14, wherein the electronic device further comprises a metal bezel of the second device body and a ground of the second device body; and the second conductor comprises the metal bezel of the second device body and the ground of the second device body that enclose to form the first slot, the first slot is disposed in a hollowed-out portion of the ground of the second device body, the first slot is adjacent to the metal bezel of the second device body, and no gap is provided on the metal bezel that is of the second device body and adjacent to the first slot and that forms a first side of the first slot.
