

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12412694
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Mizukami; Takashi et al.

Inductor component

Abstract

An inductor component includes a substantially rectangular parallelepiped device body including a first lateral surface and includes a coil conductor layer formed into a spiral wound more than one turn on a main surface parallel to the first lateral surface inside the device body. In the coil conductor layer, a wiring spacing between two wiring portions adjacent to each other (straight portions) in a first direction from an inner side portion to an outer side portion of the coil conductor layer differs from a wiring spacing of two wiring portions adjacent to each other (curved portions) in a second direction from the inner side portion to the outer side portion of the coil conductor layer, the second direction differing from the first direction.

Inventors: Mizukami; Takashi (Nagaokakyo, JP), Miyoshi; Hiromi (Nagaokakyo, JP), Yoshinaka; Keiichi (Nagaokakyo, JP)

Applicant: Murata Manufacturing Co., Ltd. (Kyoto-fu, JP)

Family ID: 72042197

Assignee: Murata Manufacturing Co., Ltd. (Kyoto-fu, JP)

Appl. No.: 18/494370

Filed: October 25, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240055174 A1	Feb. 15, 2024

Foreign Application Priority Data

JP	2019-025629	Feb. 15, 2019
----	-------------	---------------

Related U.S. Application Data

Publication Classification

Int. Cl.: **H01F27/28** (20060101); **H01F17/00** (20060101); **H01F27/29** (20060101); **H01F27/32** (20060101); **H01F41/04** (20060101)

U.S. Cl.:

CPC **H01F27/2804** (20130101); **H01F17/0013** (20130101); **H01F27/2823** (20130101); **H01F27/292** (20130101); **H01F27/32** (20130101); **H01F41/041** (20130101); H01F2027/2809 (20130101)

Field of Classification Search

CPC: H01F (27/2804); H01F (2027/2809); H01F (17/0013); H01F (17/0006); H01F (5/003); H01F (27/292); H01F (27/2823); H01F (27/32)

USPC: 336/200; 336/232

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2003/0098496	12/2002	Sugiyama	257/516	H01F 41/045
2018/0315540	12/2017	Kim	N/A	H01F 27/29

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1421879	12/2002	CN	N/A
1577645	12/2004	CN	N/A
1308969	12/2002	EP	H01F 5/003
2002299120	12/2001	JP	N/A
2004-047849	12/2003	JP	N/A
2005294486	12/2004	JP	N/A
2010040701	12/2009	JP	N/A
2010287722	12/2009	JP	N/A
2011015292	12/2010	JP	N/A
2013-153009	12/2012	JP	N/A
2019-016618	12/2018	JP	N/A
2010054217	12/2009	KR	N/A
2011/145490	12/2010	WO	N/A

OTHER PUBLICATIONS

An Office Action mailed by China National Intellectual Property Administration on Jun. 22, 2021 which corresponds to Chinese Patent Application No. 202010088272.7 and is related to U.S. Appl. No. 16/777,778 with English language translation. cited by applicant
 An Office Action; "Notice of Reasons for Refusal," mailed by the Japanese Patent Office on Oct.

Primary Examiner: Chan; Tszfung J

Attorney, Agent or Firm: Studebaker Brackett PLLC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION (1) This application is a Continuation of U.S. patent application Ser. No. 16/777,778 filed Jan. 30, 2020, which claims benefit of priority to Japanese Patent Application No. 2019-025629, filed Feb. 15, 2019, the entire content of which is incorporated herein by reference.

BACKGROUND

Technical Field

(1) The present disclosure relates to an inductor component.

Background Art

(2) Electronic components have been incorporated into a variety of electronic equipment. As one such electronic component, for example, a multilayer inductor component is known, as described, for example, in Japanese Unexamined Patent Application Publication No. 2013-153009.

(3) Regarding electronic equipment, there has been a demand for miniaturized inductor components capable of handling high-frequency signals in accordance with the higher frequency of signals used for electronic equipment such as cellular phones. Simply miniaturizing an inductor component decreases the wiring cross section and the inner coil diameter of the inductor component. Accordingly, the maximum values of an obtainable inductance value (L value) and an obtainable Q value are reduced. Thus, in miniaturized inductor components for high-frequency signals, a method for improving the efficiency in obtaining characteristics such as an L value and a Q value per unit volume will be important in the future.

(4) Specifically, for example, to increase an inductance value using an inductor component having a configuration as in the case of Japanese Unexamined Patent Application Publication No. 2013-153009, the number of coil conductor layers needs to be increased. In such a case, the size of a multilayer body is increased in the layering direction, and accordingly the outward shape size of the inductor component is increased; thus, the miniaturization cannot be achieved. In an inductor component as in Japanese Unexamined Patent Application Publication No. 2013-153009, when the number of turns per coil conductor layer is set to one or more to increase an inductance value without modifying the outward shape of the inductor component, a Q value is reduced due to interference of the magnetic fluxes generated from two wirings parallel to each other in each coil conductor layer.

SUMMARY

(5) Accordingly, the present disclosure provides an inductor component in which the efficiency in obtaining characteristics is improved.

(6) According to a preferred embodiment of the present disclosure, an inductor component includes a substantially rectangular parallelepiped device body including a first lateral surface and includes a coil conductor layer formed into a spiral wound more than one turn on a main surface parallel to the first lateral surface inside the device body. In the coil conductor layer, a wiring spacing between two wiring portions adjacent to each other in a first direction from an inner side portion of the coil conductor layer to an outer side portion of the coil conductor layer differs from a wiring spacing between two wiring portions adjacent to each other in a second direction from the inner side

portion of the coil conductor layer to the outer side portion of the coil conductor layer, the second direction differing from the first direction.

(7) At each pair of the wiring portions adjacent to each other, the magnetic fluxes generated by currents flowing through the wiring portions cancel each other out. The above configuration includes a portion at which the magnetic flux cancellation between the adjacent wiring portions is reduced because the wiring spacings between the pairs of the adjacent wiring portions differ from each other. Thus, the efficiency in obtaining characteristics is improved. The term “wiring spacing” mentioned above means the shortest distance between two adjacent wiring portions.

(8) An embodiment according to the present disclosure can provide an inductor component in which the efficiency in obtaining characteristics is improved.

(9) Other features, elements, characteristics and advantages of the present disclosure will become more apparent from the following detailed description of preferred embodiments of the present disclosure with reference to the attached drawings.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a schematic perspective view of an inductor component;
- (2) FIG. 2 is a schematic, see-through perspective view of the inductor component;
- (3) FIG. 3 is a schematic, see-through side view of the inductor component;
- (4) FIG. 4 is a series of plan views of individual insulator layers in which respective coil conductor layers and respective outer electrode layers are illustrated;
- (5) FIG. 5 is an exploded perspective view of the inductor component;
- (6) FIG. 6 is a plan view of one of the insulator layers in which a coil conductor layer and outer electrode layers are illustrated;
- (7) FIG. 7A is a partially enlarged view of the coil conductor layer;
- (8) FIG. 7B is a partially enlarged view of a coil conductor layer;
- (9) FIG. 8 is a graph showing a relation between a wiring spacing $S2$ and an L value;
- (10) FIG. 9 is a graph showing a relation between a radius of curvature difference $R4-R2$ and a Q value;
- (11) FIG. 10 is a graph showing a relation between the wiring pattern $S2$ and the Q value;
- (12) FIG. 11 is a graph showing a relation between the wiring spacing ratio $S2/S1$ and the Q value;
- (13) FIG. 12A illustrates a coil conductor layer of a modified inductor component; and
- (14) FIG. 12B illustrates a coil conductor layer of a modified inductor component.

DETAILED DESCRIPTION

(15) Hereinafter, an embodiment will be described.

(16) In the accompanying drawings, elements may be enlarged to facilitate understanding. The dimensional ratios of elements may differ from the actual dimensional ratios or from the dimensional ratios of other figures.

(17) FIG. 1 is a schematic perspective view of an outward appearance of an inductor component **1**. The inductor component **1** includes a device body **10**. The device body **10** is a base body in which the elements of the inductor component **1** are arranged and has a substantially rectangular parallelepiped shape. In the present specification, the rectangular parallelepiped shape includes a rectangular parallelepiped in which corners and edge lines are chamfered and a rectangular parallelepiped in which corners and edge lines are rounded. In addition, the rectangular parallelepiped shape may have protrusions and depressions formed in a portion or all of a main surface and lateral surfaces and may incline to a certain extent while the surfaces opposite to each other are not perfectly parallel to each other.

(18) The device body **10** includes a mounting surface **11**. When the inductor component **1** is

mounted at a circuit board, the mounting surface **11** is opposite to the circuit board. The device body **10** includes a top surface **12** parallel to the mounting surface **11**. The device body **10** includes two pairs of surfaces orthogonal to the mounting surface **11**. Surfaces included in one pair of the two pairs of surfaces are referred to as a first lateral surface **13** and a second lateral surface **14**, and surfaces of the other pair are referred to as a first end surface **15** and a second end surface **16**. The first end surface **15** and the second end surface **16** are orthogonal to the first lateral surface **13** and the second lateral surface **14**.

(19) In the present specification, a direction orthogonal to the top surface **12** and the mounting surface **11** is referred to as the height direction, a direction orthogonal to the first lateral surface **13** and the second lateral surface **14** is referred to as the width direction, and a direction orthogonal to the first end surface **15** and the second end surface **16** is referred to as the length direction. The above directions are specifically illustrated in FIG. **1**, with the length direction as L, the height direction as T, and the width direction as W. In addition, the dimension in the width direction is referred to as width, the dimension in the height direction is referred to as height, and the dimension in the length direction is referred to as length. Hereinafter, in the height direction of the inductor component **1**, the mounting surface **11** side is referred to as a lower side, and the top surface **12** side is referred to as an upper side.

(20) In the device body **10** illustrated in FIG. **2**, the dimension in the length direction L (length L1) is preferably more than 0 mm and 1.0 mm or less (i.e., from more than 0 mm to 1.0 mm). For example, the length L1 is 0.6 mm. In the device body **10**, the dimension in the width direction W (width W1) is preferably more than 0 mm and 0.6 mm or less (i.e., from more than 0 mm to 0.6 mm). The width W1 is preferably 0.36 mm or less, more preferably 0.33 mm or less. For example, the width W1 of the device body **10** is 0.3 mm. In the device body **10**, the dimension in the height direction T (height T1) is preferably more than 0 mm and 0.8 mm or less (i.e., from more than 0 mm to 0.8 mm). For example, the height T1 of the device body **10** is 0.4 mm.

(21) The inductor component **1** includes a first outer electrode **20** and a second outer electrode **30** that are exposed at respective surfaces of the device body **10**. The first outer electrode **20** is exposed at the mounting surface **11** of the device body **10**. In addition, the first outer electrode **20** is exposed at the first end surface **15** of the device body **10**. The second outer electrode **30** is exposed at the mounting surface **11** of the device body **10**. In addition, the second outer electrode **30** is exposed at the second end surface **16** of the device body **10**. In other words, the first outer electrode **20** and the second outer electrode **30** are exposed at the mounting surface **11**. That is, in the device body **10**, the surface at which the first outer electrode **20** and the second outer electrode **30** are exposed is the mounting surface **11**.

(22) In the first end surface **15**, the first outer electrode **20** is formed in such a manner that the length thereof from the mounting surface **11** of the device body **10** is substantially equal to half the height of the device body **10**. The first outer electrode **20** is formed at a substantial center of the device body **10** in the width direction W and has a width smaller than the width of the device body **10**, for example, 0.24 mm. In the mounting surface **11**, for example, the first outer electrode **20** is formed to have a length of 0.15 mm from the first end surface **15**. In the second end surface **16**, the second outer electrode **30** is formed in such a manner that the length thereof from the mounting surface **11** of the device body **10** is substantially equal to half the height of the device body **10**. In the present embodiment, the second outer electrode **30** is formed at a substantial center of the device body **10** in the width direction W and has a width smaller than the width of the device body **10**, for example, 0.24 mm. In the mounting surface **11**, for example, the second outer electrode **30** is formed to have a length of 0.15 mm from the second end surface **16**. The widths of the first outer electrode **20** and the second outer electrode **30** may be equal to the width of the device body **10**.

(23) FIGS. **2**, **3**, and **4** illustrate a configuration of each portion including the internal structure of the inductor component **1**. The inductor component **1** includes a coil **40** provided inside the device body **10**. In FIG. **2** and FIG. **3**, the coil **40** positioned inside the device body **10** and underlying

layers **21** and **31**, described below, of the first outer electrode **20** and the second outer electrode **30** are illustrated by solid lines, and the device body **10** is illustrated by two-dot chain lines. To facilitate the understanding of an inner portion of the device body **10**, covering layers **22** and **32**, described below and positioned outside the device body **10**, of the first outer electrode **20** and the second outer electrode **30** are omitted from FIG. 2.

(24) As illustrated in FIG. 5, the device body **10** includes a plurality of plate-like insulator layers **60** having rectangular main surfaces that are parallel to the first lateral surface **13**. The device body **10** has a substantially rectangular parallelepiped shape formed in such a manner that the plurality of insulator layers **60** are layered in the width direction **W** that is orthogonal to the first lateral surface **13**. Accordingly, the width direction **W** corresponds to the layering direction of the insulator layers **60**. Each of the length direction **L** and the height direction **T** orthogonal to the width direction **W** is one of the in-layer directions orthogonal to the layering direction. The insulator layers are indicated by respective reference signs differentiating each insulator layer, such as **61**, **62**, **63a** to **63h**, **64**, and **65**. In the following description, the reference sign **60** will be used when the plurality of insulator layers are not differentiated from each other, and the reference signs **61**, **62**, **63a** to **63h**, **64**, and **65** will be used when the plurality of insulator layers are differentiated from each other.

(25) The main surfaces of the insulator layers **60** may incline to a certain extent without being perfectly parallel to the first lateral surface **13** and may have protrusions and depressions in the surfaces due to a manufacturing process including conductor layer forming, multilayering, firing, and solidification. Even in such cases, the main surfaces of the insulator layers **60** are still defined to be substantially parallel to the first lateral surface **13**. In addition, because of the manufacturing process including firing, solidification, and the like, the interfaces between the layers of the insulator layers **60** may not be obvious.

(26) Preferable examples of materials for the insulator layers **60** are materials having a relative permeability of 2 or less, such as nonmagnetic materials such as glass as borosilicate glass, alumina, zirconia, and polyimide resin. More preferable materials for the insulator layers **60** have a relative permeability close to 1. However, depending on a use mode of the inductor component **1**, the insulator layers **60** may be formed of a magnetic material such as ferrite or a magnetic powder containing resin.

(27) The colors of the insulator layers **61** and **65** differ from the colors of the insulator layers **62**, **63a** to **63h**, and **64**. In FIG. 1, the insulator layers **61** and **65** are indicated by a hatch pattern and solid lines to be differentiated from the other insulator layers. Thus, when the inductor component **1** is mounted, rolling over or the like of the inductor component **1** can be detected. The colors of the insulator layers **61** and **65** may be the same as the colors of the insulator layers **62**, **63a** to **63h**, and **64**. When the length **L1**, the width **W1**, and the height **T1** differ from each other, rolling over or the like can be detected even though the colors of such insulator layers are the same.

(28) The first outer electrode **20** and the second outer electrode **30** are input-output terminals of electric signals for the coil **40** inside the inductor component **1** and are to be the portions connected to a circuit wiring when the inductor component **1** is mounted at the circuit board.

(29) As illustrated in FIG. 3, the first outer electrode **20** according to the present embodiment includes the underlying layer **21** and the covering layer **22**. The underlying layer **21** is embedded in the device body **10**. The underlying layer **21** is formed in an L-shape when viewed in the width direction **W**. The second outer electrode **30** according to the present embodiment includes the underlying layer **31** and the covering layer **32**. The underlying layer **31** is embedded in the device body **10**. The underlying layer **31** is formed in an L-shape when viewed in the width direction **W**.

(30) The first outer electrode **20** and the second outer electrode **30** are exposed at only the surfaces, parallel to the width direction **W**, of the surfaces of the device body **10**. Thus, the magnetic flux passing around the periphery of the coil **40** in the width direction **W** is not blocked by the first outer electrode **20** or the second outer electrode **30**. When the inductor component **1** is mounted at the circuit board, the above-described magnetic flux is parallel to a main surface of the circuit board

and is thus likely to be blocked by the circuit wiring of the circuit board. Accordingly, the Q value of the inductor component **1** can be improved.

(31) Materials for the covering layer **22** and **32** may be materials having high solderability resistance or high wettability. For example, metals such as nickel (Ni), copper (Cu), tin (Sn), and gold (Au), or alloys containing such metals can be used. Each covering layer can be formed of a plurality of layers. For example, each of the covering layers **22** and **32** includes a Ni plating layer covering the first outer electrode **20** and the second outer electrode **30** and a Sn plating layer covering the surface of the Ni plating layer. The covering layers **22** and **32** suppress oxidation of the surfaces of the first outer electrode **20** and the second outer electrode **30**. The covering layers **22** and **32** may protrude from the device body **10** or may form the same surfaces as the respective surfaces of the device body **10**.

(32) As illustrated in FIG. 2, the underlying layer **21** includes a plurality of outer conductor layers **23** that are provided at respective corners of the insulator layers **63a** to **63h** and that are aligned in the width direction W. The plurality of outer conductor layers **23** are directly connected to each other in the width direction W and form a single underlying layer **21**. Similarly, the underlying layer **31** includes a plurality of outer conductor layers **33** aligned in the width direction W. The plurality of outer conductor layers **33** are directly connected to each other in the width direction W and form a single underlying layer **31**. None of the outer conductor layers **23** and **33** are limited to a case illustrated in FIG. 2, in which the adjacent surfaces are entirely in contact with each other in the width direction, and the outer conductor layers **23** and **33** may be formed on the main surfaces of the insulator layers **63a** to **63h** without being in a direct contact with each other. In such a case, in each assembly of the outer conductor layers **23** and **33**, the outer conductor layers may be electrically connected to each other in the width direction W by conductor layers or vias that extend through the insulator layers **63b** to **63h** positioned between the outer conductor layers **23** and **33**, or the outer conductor layers may not be completely electrically connected to each other in each assembly of the outer conductor layers **23** and **33**.

(33) As illustrated in FIG. 3, a first end of the coil **40** is connected to the first outer electrode **20**, and a second end of the coil **40** is connected to the second outer electrode **30**.

(34) The coil **40** includes a coil portion **40a** that concentrates the magnetic flux generated by the current input or output via the first outer electrode **20** and the second outer electrode **30** and that generates a large inductance. The coil **40** also includes a first extended conductor layer **40b** and a second extended conductor layer **40c**. The first extended conductor layer **40b** connects one end of the coil portion **40a** to the first outer electrode **20**, and the second extended conductor layer **40c** connects the other end of the coil portion **40a** to the second outer electrode **30**.

(35) As illustrated in FIG. 4 and FIG. 5, the coil portion **40a** includes a plurality of coil conductor layers **41** to **48** aligned in the width direction W inside the device body **10** and via conductor layers **51** to **57** each electrically connecting corresponding ones of the coil conductor layers **41** to **48** to each other in the width direction W inside the device body **10**. As illustrated in FIG. 4 and FIG. 5, each of the coil conductor layers **41** to **48** is a conductor layer formed into a spiral wound more than one turn along the main surface of a corresponding one of the insulator layers **63a** to **63h** in the device body **10**. As used herein, the spiral shape means a shape formed along a plane and is differentiated from a three-dimensional helical shape. FIG. 4 illustrates the outward shape of the insulator layers **60** (**63a** to **63h**) in two-dot chain lines.

(36) As illustrated in FIG. 4, each of the coil conductor layers **41** to **48** according to the present embodiment is formed in a spiral extending substantially along two annular tracks O1 and O2. Accordingly, the number of turns of each of the coil conductor layers **41** to **48** according to the present embodiment is more than one and two or less (i.e., from more than one to two). However, the number of turns of each of the coil conductor layers **41** to **48** has only to be more than one and may be more than two. In the present embodiment, the annular tracks O1 and O2 each are rectangular. As illustrated in FIG. 4, the coil conductor layers **41** to **48** partially superpose each

other when viewed in the width direction W to form two annular tracks O1 and O2. The condition denoted by “superposing each other” herein includes a case in which the portions of the coil conductor layers **41** to **48**, which are to be superposed, slightly deviate from each other due to variations arising in a manufacturing process. The shape of the coil portion **40a** (the shape of the tracks O1 and O2) may be rectangular, as mentioned above, or may be polygonal, circular, or elliptical, or a combination of a plurality of such shapes. The shape of the outer peripheral track O1 and the shape of the inner peripheral track O2 may differ from each other.

(37) As illustrated in FIG. 4 and FIG. 5, the coil conductor layers **41** to **48** are electrically connected in series to each other via the via conductor layers **51** to **57** extending through the insulator layers **63b** to **63h** in the width direction W. In FIG. 4 and FIG. 5, the via conductor layers **51** to **57** are illustrated by dotted chain lines between the coil conductor layers **41** to **48**.

(38) Examples of materials for each of the coil conductor layers **41** to **48**, the via conductor layers **51** to **57**, the first extended conductor layer **40b**, and the second extended conductor layer **40c** are conductive materials such as metals having low electrical resistance such as silver (Ag), copper (Cu), and gold (Au), or alloys or the like containing mainly the above metals. Each of the outer conductor layers **23** and **33** is formed of, for example, conductive materials such as metals having low electrical resistance such as silver (Ag), copper (Cu), and gold (Au), or alloys or the like containing mainly the above metals. In addition, glass may be contained in such conductive materials in a dispersed manner.

(39) As illustrated in FIG. 2 and FIG. 3, the coil portion **40a** and the first and second extended conductor layers **40b** and **40c** as a whole form a structure that is rotationally symmetrical (180 degrees rotation) relative to an axis extending from the center of the mounting surface **11** in a direction orthogonal to the mounting surface **11**. Thus, similar characteristics can be obtained, even when the connection relations between a set of the first outer electrode **20** and a wiring on the board to which the first outer electrode **20** is to be connected and a set of the second outer electrode **30** and a wiring on the board to which the second outer electrode **30** is to be connected are reversed.

(40) The coil conductor layers will be described in detail.

(41) In the present embodiment, the coil conductor layers **41** to **48** of the insulator layers **63a** to **63h** illustrated in FIG. 4 and FIG. 5 are all formed based on a similar technical concept. Accordingly, one coil conductor layer, for example, the coil conductor layer **48** of the insulator layer **63h** will be described in detail herein and the figures and descriptions of the coil conductor layers **41** to **47** will be omitted.

(42) FIG. 6 illustrates the coil conductor layer **48**, the second extended conductor layer **40c**, and the respective outer conductor layers **23** and **33** on the main surface of the insulator layer **63h**.

(43) The coil conductor layer **48** includes a plurality of straight portions **71**, **72**, **73**, **74**, **75**, **76**, and **77** and curved portions (corner portions) **81**, **82**, **83**, **84**, **85**, and **86** each provided between corresponding ones of the straight portions **71**, **72**, **73**, **74**, **75**, **76**, and **77**. The straight portions **71**, **73**, **75**, and **77** extend in the length direction L of the device body **10**. The straight portions **72**, **74**, and **76** extend in the height direction T of the device body **10**. In other words, each of the straight portions **71**, **73**, **75**, and **77** and each of the straight portions **72**, **74**, and **76** extend in the respective directions (the length direction L and the height direction T) orthogonal to each other.

(44) The straight portions **71**, **72**, **73**, and **74** form a portion of the outer peripheral track O1 and the straight portions **75**, **76**, and **77** form a portion of the inner peripheral track O2. However, a portion of the straight portion **75** forms a portion of the inner peripheral track O2, and an end portion of the straight portion **75** is connected to the straight portion **74** on the outer peripheral track O1. In other words, the straight portion **75** includes a portion on the inner peripheral track O2 and a portion between the inner peripheral track O2 and the outer peripheral track O1.

(45) In the coil conductor layer **48** according to the present embodiment, the outward shape size can be increased by including the rectangular outer peripheral track O1 (formed of the straight

portions **71**, **72**, **73**, and **74** and the curved portions **81**, **82**, and **83**). In addition, in the coil conductor layer **48**, the length (wiring length) can be increased by including the rectangular inner peripheral track **O2** (formed of a portion of the straight portion **75**, the straight portions **76** and **77**, and the curved portions **85** and **86**). Thus, the Q value of the inductor component **1** is increased.

(46) In the present embodiment, each of the curved portions **81** to **86** is curved so as to continue from the corresponding straight portion to be connected to. In other words, the curved portions **81** to **86** include sides on the inner side of the coil conductor layer **48** and sides on the outer side of the coil conductor layer **48**, and each of the sides is formed in an arc that is about one quarter of a circumference of a circle.

(47) Directions from the inner side portion to the outer side portion of the coil conductor layer **48** will be used to describe the wiring portions of the coil conductor layer **48**. Hereinafter, portions of the coil conductor layer **48** intersecting the rays extending from the inner side portion to the outer side portion of the coil conductor layer **48**, that is, in the directions are referred to as wiring portions lying in the directions. Of the wiring portions lying in any of the directions, the wiring portions lying side by side is referred to as adjacent wiring portions in the direction. For example, as illustrated in FIG. **6**, the straight portion **71** on the outer peripheral track **O1** and the straight portion **75** on the inner peripheral track **O2** are the adjacent wiring portions in a first direction **A1** from the inner side portion to the outer side portion of the coil conductor layer **48**. Similarly, the curved portion **82** on the outer peripheral track **O1** and the curved portion **86** on the inner peripheral track **O2** are the adjacent wiring portions in a second direction **A2** from the inner side portion to the outer side portion of the coil conductor layer **48**, the second direction differing from the first direction **A1**.

(48) In the present embodiment, a wiring spacing **S2** between the curved portions **82** and **86** that are adjacent to each other in the second direction **A2** is larger than a wiring spacing **S1** between the straight portions **71** and **75** that are adjacent to each other in the first direction **A1**. A wiring spacing between the curved portions **81** and **85** illustrated in FIG. **6** is also larger than the wiring spacing **S1** between the straight portions **71** and **75**. In other words, the inductor component **1** includes the spiral coil conductor layer **48** wound more than one turn on the main surface of the insulator layer **63h**. In the coil conductor layer **48**, the wiring spacing **S1** between the straight portions **71** and **75** that are two wiring portions adjacent to each other in the first direction **A1** differs from the wiring spacing **S2** between the curved portions **82** and **86** that are two wiring portions adjacent to each other in the second direction **A2**.

(49) In a spiral coil conductor layer wound more than one turn as in the coil conductor layer **48** of the inductor component **1**, the magnetic flux generated at the outer peripheral track **O1** and the magnetic flux generated at the inner peripheral track **O2** cancel each other out. Thus, the efficiency in obtaining the L value per area of the main surface of the insulator layer is decreased and the Q value is also decreased compared with a coil conductor layer wound one turn or less. However, in the inductor component **1**, because the wiring spacings **S1** and **S2** differ from each other, the cancelation of the magnetic fluxes between the outer peripheral track **O1** and the inner peripheral track **O2** can be reduced at least in a region having larger wiring spacing (the curved portions **82**, **86**). Thus, for example, the efficiency in obtaining the L value relative to a size can be improved in the inductor component **1**.

(50) The adjacent wiring portions are not limited to a case in which the shapes of a wiring portion on the outer peripheral track **O1** and a wiring portion on the inner peripheral track **O2** are the same as in the case of the straight portions **71** and **75** and the curved portions **82** and **86**. For example, a wiring portion on the outer peripheral track **O1** may be straight, and a wiring portion on the inner peripheral track **O2** may be curved.

Manufacturing Method

(51) Next, a manufacturing method of the above-described inductor component **1** will be described with reference to FIG. **5**.

(52) First, a mother insulator layer that is to form the insulator layers **61** is formed. The mother insulator layer is a large insulator layer in which a plurality of insulator layers **61**, connected to each other, are arranged in a matrix. For example, an insulating paste containing mainly borosilicate glass is applied to a carrier film to form the mother insulator layer that is to form the insulator layers **61**. In the present embodiment, an insulating paste having a relative permeability of 2 or less after being fired is used. The insulating paste used for the insulator layers **61** has a color different from the color of an insulating paste used for the insulator layers **62**, **63a** to **63h**, and **64**.

(53) Next, a mother insulator layer that is to form the insulator layers **62** is formed. The insulating paste is applied to the mother insulator layer that is to form the insulator layers **61** to form the mother insulator layer that is to form the insulator layers **62**.

(54) Next, a mother insulator layer that is to form the insulator layers **63a** is formed. The insulating paste is applied to the mother insulator layer that is to form the insulator layers **62** to form the mother insulator layer that is to form the insulator layers **63a**.

(55) Next, the coil conductor layers **41** and the outer conductor layers **23** and **33** are formed. For example, a conductive paste containing Ag as a main metal component is applied to the mother insulator layer that is to form the insulator layers **63a** to form a conductive paste layer. At this time, patterning may be performed by printing using a conductive paste and a screen plate in which openings are formed in regions for the coil conductor layers **41** and the outer conductor layers **23** and **33** or may be performed by photolithography using a photosensitive conductive paste. Thus, the coil conductor layers **41** and the outer conductor layers **23** and **33** that have not been fired are formed on the mother insulator layer that is to form the insulator layers **63a**.

(56) Next, a mother insulator layer that is to form the insulator layers **63b** is formed. After the insulating paste is applied to the mother insulator layer that is to form the insulator layers **63a**, the applied insulating paste in regions in which the via conductor layers **51** and the outer conductor layers **23** and **33** are formed is removed by, for example, laser processing or photolithography. Thus, the mother insulator layer that is to form the insulator layers **63b** is formed in such a manner that through holes are formed at positions corresponding to positions of via pads of the respective coil conductor layers **41**, and corner portions corresponding to both outer conductor layers **23** and **33** of the respective coil conductor layers **41** are cut out.

(57) Next, the coil conductor layers **42**, the via conductor layers **51**, and the outer conductor layers **23** and **33** are formed. As in the case of the above-described coil conductor layers **41**, the conductive paste is applied to the mother insulator layer that is to form the insulator layers **63b** to form a conductive paste layer. At this time, the above-described through holes and cut out portions are filled with the conductive paste. Thus, the unfired coil conductor layers **42**, the unfired via conductor layers **51**, and the unfired outer conductor layers **23** and **33** are formed on the mother insulator layer that is to form the insulator layers **63b**.

(58) After the above steps have been performed, the mother insulator layer forming step and the conductive paste layer forming step are alternately repeated in order to form mother insulator layers that are to form the insulator layers **63c** to **63h** and in order to form the unfired coil conductor layers **42** to **48**, the unfired outer conductor layers **23** and **33**, and the unfired via conductor layers **52** to **57**.

(59) Next, a mother insulator layer that is to form the insulator layers **64** is formed on the mother insulator layer that is to form the insulator layers **63h** as in the case of the above-described mother insulator layer that is to form the insulator layers **62**. A mother insulator layer that is to form the insulator layers **65** is then formed on the mother insulator layer that is to form the insulator layers **64** as in the case of the above-described mother insulator layer that is to form the insulator layers **61**.

(60) Through the above-described steps, a mother multilayer body including a plurality of device bodies **10**, connected to each other, which are arranged in a matrix, is obtained.

(61) Next, the mother multilayer body is cut using a dicing machine or the like to obtain individual

unfired device bodies **10**. In such a cutting step, the outer conductor layers **23** and **33** are exposed from the device body **10** at cut surfaces formed by the cutting. In a firing step described below, the device bodies **10** shrink; thus, the mother multilayer body is cut in consideration of the shrinkage. (62) Next, the unfired device bodies **10** are fired under predetermined conditions to obtain the device bodies **10**. In addition, the device bodies **10** are subjected to barrel finishing. After performing the barrel finishing, the covering layers **22** and **32** for covering the outer conductor layers **23** and **33** are formed. For example, the covering layers **22** and **23** can be formed by electroplating or electroless plating.

(63) Through the above-described steps, the inductor component **1** is completed.

(64) The above-described manufacturing method is an example. To enable the structure of the inductor component **1**, other publicly known manufacturing methods may be used instead or may be added. For example, instead of the firing, an insulator layer may be formed of a curable resin, and a coil conductor layer or the like may be formed by plating.

Functions

(65) Next, functions of the above-described inductor component **1** will be described.

(66) As illustrated in FIG. **4** and FIG. **5**, the coil conductor layers **41** to **48** are formed in a spiral following the outer peripheral track **O1** and the inner peripheral track **O2**.

(67) As illustrated in FIG. **6**, the inductor component **1** includes the substantially rectangular parallelepiped device body **10** including the first lateral surface **13** and includes a plurality of coil conductor layers **41** to **48** that are aligned in a direction orthogonal to the first lateral surface **13** and that are individually formed in a spiral wound more than one turn on the main surface parallel to the first lateral surface **13** inside the device body **10**. A wiring spacing (for example, the wiring spacing **S1**) between two wiring portions adjacent to each other (for example, the straight portions **71**, **75**) in a direction (for example, the first direction **A1**) from the inner side portion to the outer side portion of each of the coil conductor layers **41** to **48** differs from a wiring spacing (for example, the wiring spacing **S2**) of two wiring portions adjacent to each other (for example, the curved portions **82**, **86**) in a direction (for example, the second direction **A2**) from the inner side portion to the outer side portion of each of the coil conductor layers **41** to **48**. Thus, as described above, the efficiency in obtaining the L value can be improved in the inductor component **1**.

(68) In addition, the inductor component **1** preferably has the following configurations.

(69) FIG. **7A** and FIG. **7B** enlarge and illustrate a portion of the coil conductor layer **48**.

(70) FIG. **7A** illustrates an example in which a radius of curvature **R4** of the curved portion **86** on the inner peripheral track **O2** is larger than a radius of curvature **R2** of the curved portion **82** on the outer peripheral track **O1**. FIG. **7B** illustrates an example in which the radius of curvature **R4** of the curved portion **86** on the inner peripheral track **O2** is the same as the radius of curvature **R2** of the curved portion **82** on the outer peripheral track **O1** (the curved portions **82** and **86** have the same shape).

(71) In both of the examples illustrated in FIG. **7A** and FIG. **7B**, the wiring spacing **S2** between the curved portions **82** and **86** is larger than the wiring spacing **S1** between the straight portions **72** and **76**. Thus, the efficiency in obtaining the L value can be improved as described above.

(72) In the example illustrated in FIG. **7B**, by forming the curved portion **86** on the inner peripheral track **O2** into the same shape as the shape of the curved portion **82** on the outer peripheral track **O1**, an inner region of the inner peripheral track **O2** can be larger and the perimeter of the inner peripheral track **O2** can be increased.

(73) Thus, it can be generally expected that an advantageous effect in which the Q value of the inductor component **1** is improved by increasing the perimeter of the inner peripheral track **O2** will be attained. However, the inventors of the present application found that, in a coil conductor layer formed in a spiral wound more than one turn, as in the coil conductor layer **48**, an increase in the perimeter of the inner peripheral track **O2** increases the proportion of the parallel extending wiring portions, which causes the magnetic fluxes at the adjacent wiring portions to cancel each other out.

Thus, the advantageous effect in which the Q value in the inductor component **1** is improved by increasing the perimeter of the inner peripheral track **O2** may be more modest than expected.

(74) For this reason, as illustrated in FIG. 7A, the radius of curvature **R4** of the curved portion **86** on the inner peripheral track **O2** is preferably larger than the radius of curvature **R2** of the curved portion **82** on the outer peripheral track **O1** in the inductor component **1**. The lengths of the straight portions **72** and **76** are decreased in accordance with the difference between the radius of curvature **R4** of the curved portion **86** on the inner peripheral track **O2** and the radius of curvature **R2** of the curved portion **82** on the outer peripheral track **O1**. Thus, in the outer peripheral track **O1** and the inner peripheral track **O2**, the wiring portions parallel to each other are shortened; thus, the cancelation of the magnetic fluxes between the adjacent wiring portions can be reduced.

(75) As described above, from the perspective of the reduction in the cancelation of the magnetic fluxes between the adjacent wiring portions, the difference between the radius of curvature **R4** of the curved portion **86** on the inner peripheral track **O2** and the radius of curvature **R2** of the curved portion **82** on the outer peripheral track **O1** is preferably larger. However, if the difference between the radius of curvature **R4** of the curved portion **86** on the inner peripheral track **O2** and the radius of curvature **R2** of the curved portion **82** on the outer peripheral track **O1** is increased, the inner region of the inner peripheral track **O2** becomes smaller, and the Q value is reduced. The inventors of the present application observed that characteristics change in accordance with the relation between the radius of curvature **R4** of the curved portion **86** on the inner peripheral track **O2** and the radius of curvature **R2** of the curved portion **82** on the outer peripheral track **O1** by manufacturing the inductor component **1** as per the following examples.

Examples

(76) Table 1 shows dimensions of the below-listed portions, the ratio **S2/S1** of the wiring spacing **S2** to the wiring spacing **S1**, and the radius of curvature difference **R4–R2** in Examples 1 to 6. For description of the dimensions of each portion, the elements (such as the curved portions **82**, **86**) illustrated in FIG. 7A are used.

(77) TABLE-US-00001 TABLE 1 Lw S1 R1 R2 R3 R4 S2 S2/ R4 – Examples [μm] [μm] [μm] [μm] [μm] [μm] [μm] [μm] S1 R2 1 18.9 22.0 27.3 8.4 27.3 8.4 38.9 1.8 0.0 2 18.9 22.0 27.3 8.4 38.9 20.0 43.7 2.0 11.6 3 18.9 22.0 27.3 8.4 58.9 40.0 52.0 2.4 31.6 4 18.9 22.0 27.3 8.4 78.9 60.0 60.3 2.7 51.6 5 18.9 22.0 27.3 8.4 98.9 80.0 68.6 3.1 71.6 6 18.9 22.0 27.3 8.4 118.9 100.0 76.9 3.5 91.6

Example 1

(78) In an inductor component of Example 1, a coil conductor layer was set to have a wiring width **Lw** (μm) of 18.9, a wiring spacing **S1** (μm) of 22.0, a radius of curvature **R1** (μm) of 27.3, a radius of curvature **R2** (μm) of 8.4, a radius of curvature **R3** (μm) of 27.3, a radius of curvature **R4** (μm) of 8.4, and a wiring spacing **S2** (μm) of 38.9. In the inductor component, the ratio **S2/S1** of the wiring spacing **S2** to the wiring spacing **S1** is 1.8, and the difference **R4–R2** between the radius of curvature **R4** of the curved portion **86** on the inner peripheral track **O2** and the radius of curvature **R2** of the curved portion **82** on the outer peripheral track **O1** is 0.0.

Example 2

(79) In an inductor component of Example 2, a coil conductor layer was set to have a wiring width **Lw** (μm) of 18.9, a wiring spacing **S1** (μm) of 22.0, a radius of curvature **R1** (μm) of 27.3, a radius of curvature **R2** (μm) of 8.4, a radius of curvature **R3** (μm) of 38.9, a radius of curvature **R4** (μm) of 20.0, and a wiring spacing **S2** (μm) of 43.7. In the inductor component, the ratio **S2/S1** of the wiring spacing **S2** to the wiring spacing **S1** is 2.0, and the difference **R4–R2** between the radius of curvature **R4** of the curved portion **86** on the inner peripheral track **O2** and the radius of curvature **R2** of the curved portion **82** on the outer peripheral track **O1** is 11.6.

Example 3

(80) In an inductor component of Example 3, a coil conductor layer was set to have a wiring width **Lw** (μm) of 18.9, a wiring spacing **S1** (μm) of 22.0, a radius of curvature **R1** (μm) of 27.3, a radius of curvature **R2** (μm) of 8.4, a radius of curvature **R3** (μm) of 58.9, a radius of curvature **R4** (μm)

of 40.0, and a wiring spacing $S2$ (μm) of 52.0. In the inductor component, the ratio $S2/S1$ of the wiring spacing $S2$ to the wiring spacing $S1$ is 2.4, and the difference $R4-R2$ between the radius of curvature $R4$ of the curved portion **86** on the inner peripheral track $O2$ and the radius of curvature $R2$ of the curved portion **82** on the outer peripheral track $O1$ is 31.6.

Example 4

(81) In an inductor component in Example 4, a coil conductor layer was set to have a wiring width Lw (μm) of 18.9, a wiring spacing $S1$ (μm) of 22.0, a radius of curvature $R1$ (μm) of 27.3, a radius of curvature $R2$ (μm) of 8.4, a radius of curvature $R3$ (μm) of 78.9, a radius of curvature $R4$ (μm) of 60.0, and a wiring spacing $S2$ (μm) of 60.3. In the inductor component, the ratio $S2/S1$ of the wiring spacing $S2$ to the wiring spacing $S1$ is 2.7, and the difference $R4-R2$ between the radius of curvature $R4$ of the curved portion **86** on the inner peripheral track $O2$ and the radius of curvature $R2$ of the curved portion **82** on the outer peripheral track $O1$ is 51.6.

Example 5

(82) In an inductor component in Example 5, a coil conductor layer was set to have a wiring width Lw (μm) of 18.9, a wiring spacing $S1$ (μm) of 22.0, a radius of curvature $R1$ (μm) of 27.3, a radius of curvature $R2$ (μm) of 8.4, a radius of curvature $R3$ (μm) of 98.9, a radius of curvature $R4$ (μm) of 80.0, and a wiring spacing $S2$ (μm) of 66.8. In the inductor component, the ratio $S2/S1$ of the wiring spacing $S2$ to the wiring spacing $S1$ is 3.1, and the difference $R4-R2$ between the radius of curvature $R4$ of the curved portion **86** on the inner peripheral track $O2$ and the radius of curvature $R2$ of the curved portion **82** on the outer peripheral track $O1$ is 71.6.

Example 6

(83) In an inductor component in Example 6, a coil conductor layer was set to have a wiring width Lw (μm) of 18.9, a wiring spacing $S1$ (μm) of 22.0, a radius of curvature $R1$ (μm) of 27.3, a radius of curvature $R2$ (μm) of 8.4, a radius of curvature $R3$ (μm) of 118.9, a radius of curvature $R4$ (μm) of 100.0, and a wiring spacing $S2$ (μm) of 76.9. In the inductor component, the ratio $S2/S1$ of the wiring spacing $S2$ to the wiring spacing $S1$ is 3.5, and the difference $R4-R2$ between the radius of curvature $R4$ of the curved portion **86** on the inner peripheral track $O2$ and the radius of curvature $R2$ of the curved portion **82** on the outer peripheral track $O1$ is 91.6.

Relation Between Dimensions of a Coil Conductor Layer and Characteristics of an Inductor Component

(84) In Examples 1 to 6 described above, the inductor components including the coil conductor layers having the above-described dimensions were manufactured, and the L value and the Q value of each inductor component with respect to an input signal having a frequency of 500 MHz were measured.

(85) In FIG. 8, points $P1$ to $P6$ indicate the measured L values of the respective inductor components of Examples 1 to 6. In the graph of FIG. 8, the horizontal axis indicates the wiring spacing $S2$ between the curved portions **82** and **86**, and the vertical axis indicates the L value.

(86) FIG. 8 shows that, as the wiring spacing $S2$ between the curved portion **86** on the inner peripheral track $O2$ and the curved portion **82** on the outer peripheral track $O1$ increases with respect to the consistent wiring spacing $S1$ (22.0 μm), the L value increases initially but decreases after the wiring spacing $S2$ exceeds a certain wiring spacing ($S2$ is substantially equal to 40.0 μm). Thus, it is revealed that, regarding the L value, an advantageous effect in which the mutual cancelation of the magnetic fluxes is reduced is initially larger compared with an influence caused when the inner region of the coil conductor layer **48** becomes smaller. However, after the wiring spacing $S2$ exceeds a certain wiring spacing, the influence caused when the inner region of the coil conductor layer **48** becomes smaller is larger compared with the advantageous effect in which the mutual cancelation of the magnetic fluxes is reduced.

(87) In FIG. 9, points $P1$ to $P6$ indicate the measured Q values of the respective inductor components of Examples 1 to 6. In the graph of FIG. 9, the horizontal axis indicates the difference $R4-R2$ between the radius of curvature $R4$ of the curved portion **86** on the inner peripheral track

O2 and the radius of curvature R2 of the curved portion **82** on the outer peripheral track O1, and the vertical axis indicates the Q value.

(88) As shown in FIG. **9**, when the radius of curvature difference $R4-R2$ is in a range of 0 to 60 μm or less (i.e., from 0 to 60 μm), any Q values equal to or larger than the Q value of the inductor component of Example 1 can be obtained.

(89) In FIG. **10**, points P1 to P6 indicate the measured Q values of the respective inductor components of Examples 1 to 6. In the graph of FIG. **10**, the horizontal axis indicates the wiring spacing S2 between the curved portions **82** and **86**, and the vertical axis indicates the Q value. The wiring spacing S2 is larger than the wiring spacing S1; thus, the Q value of the inductor component can be increased. The wiring spacing S2 is preferably 22 μm or more and 82 μm or less (i.e., from 22 μm to 82 μm) from the perspective of the Q value.

(90) In FIG. **11**, points P1 to P6 indicate the measured Q values of the respective, above-described inductor components of Examples 1 to 6. In the graph of FIG. **11**, the horizontal axis indicates the ratio $S2/S1$ of the wiring spacing S2 between the curved portions **82** and **86** to the wiring spacing S1 between the straight portions **72** and **76**, and the vertical axis indicates the Q value. As the ratio $S2/S1$ increases, the Q value of the inductor component can be increased. The ratio $S2/S1$ is preferably 1 or more and 3.7 or less (i.e., from 1 to 3.7) from the perspective of the Q value.

(91) As described above, the following advantageous effects are attained according to the present embodiment.

(92) (1) The inductor component **1** includes a substantially rectangular parallelepiped device body **10** including the first lateral surface **13** and includes the coil conductor layers **41** to **48** each formed into a spiral wound more than one turn on the main surface parallel to the first lateral surface **13** inside the device body **10**. The wiring spacing S1 between two wiring portions adjacent to each other (the straight portions **71**, **75**) in the first direction A1 from the inner side portion to the outer side portion of each of the coil conductor layers **41** to **48** differs from the wiring spacing S2 between two wiring portions adjacent to each other (the curved portions **82**, **86**) in the second direction A2 from the inner side portion to the outer side portion of each of the coil conductor layers **41** to **48**.

(93) At each pair of the wiring portions adjacent to each other, the magnetic fluxes generated by currents flowing through the wiring portions cancel each other out. The above configuration includes a portion at which the magnetic flux cancellation between the adjacent wiring portions is reduced because the wiring spacings between the pairs of the adjacent wiring portions differ from each other. Thus, the efficiency in obtaining characteristics is improved.

(94) (2) The number of turns of each of the coil conductor layers **41** to **48** is more than one and less than two (i.e., from more than one to two). The annular tracks O1 and O2 are rectangular. With the straight portions **71** to **77** forming the rectangular outer peripheral track O1 and inner peripheral track O2, the outward shape size of the coil portion **40a** can be increased, and the length (the perimeter) of the coil portion **40a** can be increased. In addition, the inner side of the coil portion **40a** can be larger. Thus, the Q value of the inductor component **1** can be improved.

Modifications

(95) The above-described embodiment may be implemented by adopting the following forms.

(96) The shapes of the tracks O1 and O2 according to the above-described embodiment may be modified as appropriate.

(97) As illustrated in FIG. **12A**, the outer peripheral track O1 and the inner peripheral track O2 may be oval (a combination of arcs and straight lines). Moreover, as illustrated in FIG. **12B**, the outer peripheral track O1 may be elliptical, while the inner peripheral track O2 may be circular. The shapes of the outer peripheral track O1 and the inner peripheral track O2 may be, for example, rectangular, polygonal, oval, or elliptical, or a combination of a plurality of such shapes.

Furthermore, the shapes of the outer peripheral track O1 and the inner peripheral track O2 may differ from each other. For example, the outer peripheral track O1 may have a curved shape

following the outline of the outer conductor layers, and the inner peripheral track O2 may be circular or elliptical.

(98) In the above-described embodiment, the number of turns of the coil conductor layer has only to be more than one and may be modified to a number more than two, such as three or four, as appropriate. In addition, a single inductor component may include coil conductor layers having different numbers of turns.

(99) In the above-described embodiment, the number of layers of the insulator layer, the coil conductor layer, and the outer conductor layer may be modified as appropriate.

(100) In the above-described embodiment, the underlying layer **21** of the first outer electrode **20** and the underlying layer **31** of the second outer electrode **30** are embedded in the device body **10** but may be provided on the outside of the device body **10**.

(101) While preferred embodiments of the disclosure have been described above, it is to be understood that variations and modifications will be apparent to those skilled in the art without departing from the scope and spirit of the disclosure. The scope of the disclosure, therefore, is to be determined solely by the following claims.

Claims

1. An inductor component comprising: a rectangular parallelepiped device body including a first lateral surface; and a plurality of coil conductor layers formed into a spiral wound more than one turn on a main surface parallel to the first lateral surface inside the device body; and a via conductor layer connected to an end portion of at least one of the coil conductor layers and electrically connecting the plurality of coil conductor layers, wherein, the at least one of the coil conductor layers includes, when viewed in a direction orthogonal to the first lateral surface, a wiring portion following an annular first track and a wiring portion following an annular second track positioned more inward than the first track, the end portion is on the annular first track, the wiring portion following the first track has a shape including a first straight portion, the wiring portion following the second track has a shape including a second straight portion, a connection portion connecting the first straight portion and the second straight portion of the at least one of the coil conductor layers is adjacent to the end portion without interposing any other wiring portion, and tilts to the first straight portion and the second straight portion so as to be away from the end portion, in the coil conductor layer, a wiring spacing between two wiring portions adjacent to each other in a first direction from the connection portion to the end portion differs from a wiring spacing of two wiring portions adjacent to each other in a second direction from an inner side portion of the coil conductor layer to an outer side portion of the coil conductor layer, the second direction differing from the first direction, and the two wiring portions adjacent to each other in the second direction are arc-shaped, curved portions, and a radius of curvature of the curved portion on an inner side is larger than a radius of curvature of the curved portion on an outer side.
2. The inductor component according to claim 1, wherein the first track has a shape including two or more first straight portions and a first corner portion connecting the first straight portions; and, the second track has a shape including two or more second straight portions and a second corner portion connecting the second straight portions.
3. The inductor component according to claim 2, wherein the wiring portion following the second track includes two or more second straight portions parallel to the first straight portions.
4. The inductor component according to claim 3, wherein a first wiring spacing between each of the first straight portions and the second straight portions corresponding thereto is equal to or smaller than a second wiring spacing between the first corner portion and the second corner portion.
5. The inductor component according to claim 4, wherein the second wiring spacing is from 22 μm to 82 μm .
6. The inductor component according to claim 4, wherein a ratio $S2/S1$ of the second wiring

spacing S2 to the first wiring spacing S1 is from 1 to 3.7.

7. The inductor component according to claim 1, wherein a difference between the radius of curvature of the curved portion on the inner side and the radius of curvature of the curved portion on the outer side is from 0 to 60 μm .

8. The inductor component according to claim 5, wherein a ratio S2/S1 of the second wiring spacing S2 to the first wiring spacing S1 is from 1 to 3.7.

9. The inductor component according to claim 1, wherein the end portion has a part that projects toward the connection portion.

10. The inductor component according to claim 9, wherein the first track has a shape including two or more first straight portions and a first corner portion connecting the first straight portions; and, the second track has a shape including two or more second straight portions and a second corner portion connecting the second straight portions.

11. The inductor component according to claim 10, wherein the wiring portion following the second track includes two or more second straight portions parallel to the first straight portions.

12. The inductor component according to claim 11, wherein a first wiring spacing between each of the first straight portions and the second straight portions corresponding thereto is equal to or smaller than a second wiring spacing between the first corner portion and the second corner portion.

13. The inductor component according to claim 12, wherein the second wiring spacing is from 22 μm to 82 μm .

14. The inductor component according to claim 13, wherein a ratio S2/S1 of the second wiring spacing S2 to the first wiring spacing S1 is from 1 to 3.7.

15. The inductor component according to claim 12, wherein a ratio S2/S1 of the second wiring spacing S2 to the first wiring spacing S1 is from 1 to 3.7.
