

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12401133
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Lin; Hoyu et al.

Reflection apparatus and system

Abstract

A reflection apparatus which reflects a radio wave includes a first device including first units each including a first base body having a first surface and a second surface provided along an emission direction of the reflected wave, a first element provided on the first surface, and a second element provided on the second surface to be shifted in position from the first element in the emission direction, and a second device including second units each including a second base body having a third surface and a fourth surface provided along the emission direction, a third element provided on the third surface, and a fourth element provided on the fourth surface, and the first device is provided separated from the second device, and a relative positional relationship between the first device and the second device in a direction along the second surface is adjustable.

Inventors: Lin; Hoyu (Tokyo, JP), Kuse; Ryuji (Kumamoto, JP), Fukusako; Takeshi (Kumamoto, JP)

Applicant: SoftBank Corp. (Tokyo, JP)

Family ID: 1000008782255

Assignee: SoftBank Corp. (Tokyo, JP)

Appl. No.: 19/051152

Filed: February 11, 2025

Prior Publication Data

Document Identifier	Publication Date
US 20250183546 A1	Jun. 05, 2025

Foreign Application Priority Data

JP	2022-133725	Aug. 25, 2022
----	-------------	---------------

Related U.S. Application Data

continuation parent-doc WO PCT/JP2023/029607 20230816 PENDING child-doc US 19051152

Publication Classification

Int. Cl.: H01Q15/14 (20060101); H01Q15/00 (20060101); H01Q19/10 (20060101)

U.S. Cl.:

CPC H01Q15/148 (20130101); H01Q15/0013 (20130101);

Field of Classification Search

CPC: H01Q (15/00); H01Q (15/0013); H01Q (15/14); H01Q (15/148); H01Q (19/10)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
8912888	12/2013	Yoshida	343/834	G06K 19/07749
8988759	12/2014	Bowers	359/263	G02B 1/005
10938118	12/2020	Takikawa	N/A	H01Q 15/147
11303020	12/2021	Fang	N/A	F04B 7/145
11777226	12/2022	Nakajima	343/840	H01Q 19/026
12074382	12/2023	Okita	N/A	H01Q 21/0006

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
110854538	12/2019	CN	N/A
2015046821	12/2014	JP	N/A
2021158600	12/2020	JP	N/A
2022253534	12/2021	WO	N/A

OTHER PUBLICATIONS

Decision to Grant a Patent issued for counterpart Japanese Application No. 2022-133725, transmitted from the Japanese Patent Office on May 30, 2023 (drafted on May 22, 2023). cited by applicant

International Search Report and Written Opinion (ISA/237) of the International Search Authority for International Patent Application No. PCT/JP2023/029607, mailed by the Japan Patent Office on Oct. 3, 2023. cited by applicant

Primary Examiner: Phan; Tho G

Background/Summary

(1) The contents of the following patent application(s) are incorporated herein by reference: NO. 2022-133725 filed in JP on Aug. 25, 2022 NO. PCT/JP2023/029607 filed in WO on Aug. 16, 2023.

BACKGROUND

1. Technical Field

(2) The present invention relates to a reflection apparatus and a system.

2. Related Art

(3) In Patent Document 1, a reflector array in which a large number of elements as small as a wavelength are arranged in a planar shape is described as a reflector that reflects radio waves.

PRIOR ART DOCUMENTS

Patent Documents

(4) Patent Document 1: Japanese Patent Application Publication No. 2015-46821

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 schematically shows an example of a configuration of a system **10** including a reflection apparatus **30**.

(2) FIG. 2 is a perspective view schematically showing the reflection apparatus **30**.

(3) FIG. 3 shows a case where relative positions of a first device **110** and a second device **120** included in the reflection apparatus **30** are aligned.

(4) FIG. 4 shows a part of a cross section of the reflection apparatus **30** taken along line A-A in FIG. 2.

(5) FIG. 5 is a perspective view of a unit **301** including a first unit **311** and a second unit **321**.

(6) FIG. 6 shows a cross section of the unit **301** taken along line B-B in FIG. 5.

(7) FIG. 7 is a graph showing a phase change amount obtained by displacing the first device **110** with respect to the second device **120**.

(8) FIG. 8 schematically shows a unit **800** included in a reflector in a first comparative example.

(9) FIG. 9 is a graph showing a phase change amount in the first comparative example.

(10) FIG. 10 schematically shows a unit **1000** included in a reflector in a second comparative example.

(11) FIG. 11 is a graph showing a phase change amount in the second comparative example.

DESCRIPTION OF EXEMPLARY EMBODIMENTS

(12) For example, in a 5th generation mobile communication system, radio waves in a relatively high frequency band are used. Since radio waves in a high frequency band have high straightness, it is difficult for the radio waves to diffract around an obstacle such as a building to reach a shadow zone. For this reason, many coverage holes (areas in which communication cannot be performed) are generated in an area that is invisible from a base station, and a communication coverage area may be narrowed. Therefore, in order to expand the communication coverage area, it is necessary to install a large number of base stations. Accordingly, a cost for expanding the communication area increases.

(13) A reflector is provided in a construction such as a building, and a radio wave radiated from a base station is reflected by the reflector, so that the radio wave can reach an area which is the shadow zone of the obstacle. As the reflector for this purpose, a meta-surface reflector capable of making an incident angle and a reflection angle of a radio wave different has been studied.

(14) In order to effectively reduce the coverage holes, it is desirable that the phase of the reflected wave is adjustable in order to adjust the reflection angle. As the meta-surface reflector capable of adjusting the phase of the reflected wave, a configuration using a material having a variable dielectric constant (for example, liquid crystal or the like), a configuration in which a plurality of varactor diodes or PIN diodes are arranged in each cell for adjusting impedance, and the like are

considered. However, in these configurations, power is required to maintain the reflection angle in a specific direction. In the configuration using diodes or PIN diodes, a cell structure becomes complicated, and the manufacturing cost of the reflector increases.

(15) On the other hand, in the system **10** including the reflection apparatus **30** according to the present embodiment, the reflection apparatus **30** has a structure in which the first device **110** and the second device **120** are separated from each other. This allows for adjusting the relative in-plane positions of the first device **110** and the second device **120**, thereby enabling the adjustment of the phase of the reflected wave. Accordingly, the manufacturing cost of the reflection apparatus **30** is reduced, while power for maintaining the reflection angle of the radio wave in a specific direction becomes substantially unnecessary. Furthermore, in the reflection apparatus **30**, an additional element is provided between the first device **100** and the second device **200**, thereby enabling the expansion of the phase change amount of the reflected wave in an operation frequency band. Accordingly, it becomes possible to expand a communication coverage area through a base station. Therefore, the number of base stations can be suppressed, so that the cost for expanding the communication coverage area can be reduced.

(16) Hereinafter, the present invention will be described through embodiments of the invention, but the following embodiments do not limit the invention according to the claims. In addition, not all of the combinations of features described in the embodiments are essential to the solution of the invention.

(17) FIG. **1** schematically shows an example of a configuration of the system **10** including the reflection apparatus **30**. The system **10** includes a base station **20** and the reflection apparatus **30**. In the present embodiment, the system **10** is a mobile communication system. The base station **20** radiates radio waves for mobile communication.

(18) The radio waves radiated by the base station **20** include a radio wave in a frequency band that can be used in the 5th generation mobile communication system. Specifically, the radio waves radiated by the base station **20** may include a radio wave in a frequency band equal to or higher than the frequency band of the S-band. The radio waves radiated by the base station **20** may include a radio wave in a frequency band equal to or higher than the frequency band of the C-band. The radio waves radiated by the base station **20** may include a radio wave in submillimeter to millimeter wave bands. In the present embodiment, the radio waves radiated by the base station **20** include, for example, a radio wave of 5.77 GHz.

(19) For example, the radio wave in the frequency band equal to or higher than the frequency band of the S-band is less likely to diffract around an obstacle such as a building to reach a shadow zone than a radio wave in a frequency band (for example, a 700 MHz band and an 800 MHz band) equal to or lower than the frequency band of the L-band. An area **80** is located in a shadow zone of a building **90** as viewed from the base station **20**. For this reason, the strength of a radio wave radiated from the base station **20** and directly reaching the area **80** becomes significantly weak.

(20) The reflection apparatus **30** reflects the radio wave radiated from the base station **20**. The reflection apparatus **30** is provided, for example, on a wall surface of a building **92** located in a line-of-sight range of the base station **20**. The reflection apparatus **30** reflects an incident radio wave in a specific direction. The reflection apparatus **30** is configured to be able to adjust a direction in which the reflection apparatus **30** reflects a radio wave. The reflection apparatus **30** is adjusted such that the radio wave radiated from the base station **20** and incident on the reflection apparatus **30** is reflected by the reflection apparatus **30** and travels toward the area **80**. The reflection apparatus **30** enables the radio wave radiated from the base station **20** to reach the area **80**. Accordingly, it is possible to expand the communication coverage area through the base station **20** without adding a base station. Therefore, the cost for expanding the communication coverage area can be reduced.

(21) FIG. **2** is a perspective view schematically showing the reflection apparatus **30**. FIGS. **3** and **4** show a part of a cross section of the reflection apparatus **30** taken along line A-A in FIG. **2**. FIG. **3**

shows a case where relative positions of the first device **110** and the second device **120** included in reflection apparatus **30** are aligned. FIG. **4** shows a case where the relative positions of the first device **110** and the second device **120** are not aligned, and the first device **110** is displaced with respect to the second device **120**.

(22) In the drawings of the present embodiment, coordinate axes may be shown to describe the configuration of the reflection apparatus **30**. In the drawings of the present embodiment, coordinate axes are shown for the purpose of representing directions. An x axis and a y axis of the coordinate axes are set in a plane parallel to a main surface of the reflection apparatus **30**. In the direction of a z axis of the coordinate axes, generally, a direction in which an incident wave is incident on the reflection apparatus **30** is defined as positive, and a direction in which a reflected wave is emitted is defined as negative.

(23) The configuration of the reflection apparatus **30** will be described with reference to FIGS. **2** to **4**. The reflection apparatus **30** reflects radio waves. The reflection apparatus **30** includes the first device **110** and the second device **120** provided along an emission direction of a reflected wave, and an adjustment apparatus **34**.

(24) The first device **110** provides an incident surface on which an incident wave, which is a radio wave incident on the reflection apparatus **30**, can be directly incident, and an output surface of a reflected wave. A radio wave having passed through the first device **110** are incident on the second device **120**. The first device **110** is located on a negative z-axis side with respect to the second device **120**. The first device **110** may be a device located closer to the base station **20** than the second device **120**.

(25) The first device **110** has a configuration in which a plurality of elements including a first element **111**, a first element **112**, a first element **113**, and a first element **114** are arranged in a matrix on a first substrate **210**. Similarly, the second device **120** has a configuration in which a plurality of elements similar to the first elements are arranged in a matrix on a second substrate **220**.

(26) The first device **110** includes a first unit **311** including a first base body **211** having a first surface **101** and a second surface **102** provided along the emission direction of a reflected wave, the first element **111** provided on the first surface **101**, and a second element **121** provided on the second surface **102** to be shifted in position from the first element **111** in the emission direction of the reflected wave.

(27) The second surface **102** is a surface opposite to the first surface **101**. The first surface **101** is located on the negative z-axis side with respect to the second surface **102**.

(28) As shown in FIG. **2**, the first device **110** has a configuration in which a plurality of first units having configurations same as or similar to that of the first unit **311** are arranged in a matrix.

(29) Specifically, in the first device **110**, the first units arranged in a direction along the x axis have configurations same as each other except that the sizes of the first elements included in the respective units are different from each other. For example, as shown in FIGS. **2** and **3** or the like, the first element **111** of the first unit **311** is larger than the first element **112** of a first unit **312**, the first element **112** of the first unit **312** is larger than the first element **113** of a first unit **313**, and the first element **113** of the first unit **313** is larger than the first element **114** of a first unit **314**. On the other hand, the first units arranged in a direction along the y axis have configurations same as each other. Accordingly, the wave reflected by the reflection apparatus **30** can have phases different from each other at different positions in an x-axis direction.

(30) For convenience of description, the first device **110** is described as including a configuration in which a plurality of first units are arranged, but the plurality of first units indicate specific parts of the first device **110**, and does not mean that the plurality of first units are a plurality of separate members. Similarly, the first base body indicates a specific part of the first substrate **210**, and the first substrate **210** may be integrally configured by one member.

(31) The second device **120** includes a second unit **320** including a second base body **221** having a

third surface **103** and a fourth surface **104** provided along the emission direction of a reflected wave, a third element **131** provided on the third surface **103**, and a fourth element **141** provided on the fourth surface.

(32) The fourth surface **104** is a surface opposite to the third surface **103**. The third surface **103** is located on the negative z-axis side with respect to the fourth surface **104**. The second surface **102** and the second element **121** are surfaces that can face at least a part of the third surface **103** and the third element **131**.

(33) Similarly to the first device **110**, the second device **120** has a configuration in which a plurality of second units having configurations same as or similar to that of the second unit **321** are arranged in a matrix.

(34) Specifically, in the second device **120**, the second units arranged in the direction along the x axis have configurations same as each other except that the sizes of the third elements included in the respective units are different from each other. For example, as shown in FIG. **3** or the like, the third element **131** of the second unit **321** is larger than a third element **132** of a second unit **322**, the third element **132** of the second unit **322** is larger than a third element **133** of a second unit **323**, and the third element **133** of the second unit **323** is larger than a first element **134** of a second unit **324**. On the other hand, the second units arranged in the direction along the y axis have configurations same as each other.

(35) For convenience of description, the second device **120** is described as including a configuration in which a plurality of second units are arranged, but the plurality of second units indicate specific parts of the second device **120**, and does not mean that the plurality of second units are a plurality of separate members. Similarly, the second base body indicates a specific part of the second substrate **220**, and the second substrate **220** may be integrally configured by one member.

(36) The first element **111**, the second element **121**, the third element **131**, and the fourth element **141** are conductors. As an example, the first element **111** and the third element **131** are conductors having a frequency selective surface (FSS). The fourth element **141** is a ground conductor and provides a reflecting surface for radio waves. A radio wave incident on the reflection apparatus **30** passes through the first device **110**, enters the second device **120**, is reflected by the fourth element, passes through the second device **120** and the first device **110**, and is emitted as a reflected wave to the outside. A phase difference is generated in the radio wave incident on the reflection apparatus **30** by the members constituting the first device **110** and the members constituting the second device **120**, and the radio wave is emitted as a reflected wave from the reflection apparatus **30**, from the first device **110** to the outside of the reflection apparatus **30**.

(37) The first device **110** is provided separated from the second device **120**. A relative positional relationship between the first device **110** and the second device **120** in a direction along the second surface **102** is adjustable. Specifically, the second device **120** is fixed, and the first device **110** can be displaced relative to the second device **120** in the direction along the x axis.

(38) The adjustment apparatus **34** adjusts the relative positional relationship between the first device **110** and the second device **120**. For example, the adjustment apparatus **34** is attached to the first device **110** and displaces the first device **110** in the direction along the x axis. The adjustment apparatus **34** may include a displacement mechanism that displaces a moving member fixed to the first device **110** with an adjustment member such as a screw.

(39) The phase of the reflected wave is determined by surface areas of the first element **111** and the second element **121**, a relative positional relationship between the first element **111** and the second element **121**, a thickness of the first base body **211**, surface areas of third element **131** and fourth element **141**, and a thickness of second base body **221**. The phase of the reflected wave is further determined by an interval between the first substrate **210** and the second substrate **220**, a dielectric constant of the first substrate **210**, and a dielectric constant of the second substrate **220**. As described above, the phase of the reflected wave is not electrically determined, but is determined

by a mechanical structure of the reflection apparatus **30**.

(40) The plurality of first units included in the first device **110** and the plurality of second units included in the second device **120** are provided at a plurality of positions along a specific direction along the first surface **101**, such that the phases of the reflected wave are different from each other. Specifically, the plurality of first units and the plurality of second units are provided such that the reflected wave propagates in a specific direction.

(41) The plurality of first units included in the first device **110** and the plurality of second units included in the second device **120** are provided such that, for example, a phase difference of the reflected wave varies by a certain amount between the plurality of first units included in the first device **110** in the x-axis direction. In this case, the wave reflected by reflection apparatus **30** propagates in a specific direction.

(42) By changing a relative position of the first device **110** with respect to the second device **120** along the x-axis direction, the arrangement of the plurality of first elements and the plurality of second elements **121** included in the first device **110** and a plurality of third elements **131** included in the second device **120** is changed, so that the phase difference of the reflected wave in the x-direction is changed. Accordingly, it is possible to change a direction in which the wave reflected by the reflection apparatus **30** propagates. Therefore, the direction in which the wave reflected by the reflection apparatus **30** propagates can be adjusted by adjusting the relative position of the first device **110** with respect to the second device **120** along the x-axis direction. Accordingly, in a case where the reflection apparatus **30** is installed in the building **90**, the direction in which the wave reflected by the reflection apparatus **30** propagates can be adjusted so as to eliminate a coverage hole of the base station **20**.

(43) An example of a specific structure of the first unit **311** and the second unit **321** will be described with reference to FIGS. 5 and 6. FIG. 5 is a perspective view of a unit **301** including the first unit **311** and the second unit **321**. FIG. 6 shows a cross section of the unit **301** taken along line B-B in FIG. 5. FIGS. 5 and 6 are diagrams in a case where the positions of the first device **110** and the second device **120** are aligned.

(44) As shown in FIG. 6, in the unit **301**, the second elements **121** are located at an end on a positive x-axis side and an end on a negative x-axis side on the second surface **102**. The second element **121** is located at the center of the second surface **102** in a y-axis direction.

(45) In this manner, the second element **121** is provided at a position shifted from the first element **111**. For example, in a case where the first element **111** and the second element **121** are projected on an xy plane, the range occupied by the first element **111** and the range occupied by the second element **121** do not coincide with each other in the xy plane. That is, the first element **111** and the second element **121** are provided such that a region where the second element **121** does not overlap the first element **111** exists and/or a region where the first element **111** does not overlap the second element **121** exists when viewed in a z-axis direction.

(46) In the present embodiment, when viewed in the z-axis direction, the shapes of the first base body **211** and the second base body **221** are square. When viewed in the z-axis direction, the shapes of the first element **111**, the second element **121**, and the third element **131** are square.

(47) Assuming that a wavelength of a radio wave incident on the reflection apparatus **30** is λ , a length of one side of the first unit **311** is 0.38λ , and a length of one side of the second unit **321** is 0.38λ . Specifically, a length of one side of the first base body **211** is 0.38λ , and a length of one side of the second base body **221** is 0.38λ .

(48) A thickness d_1 of the first base body **211** is 0.03λ , and a dielectric constant of the first base body **211** is 2.16. A thickness d_2 of the second base body **221** is 0.06λ , and a dielectric constant of the second base body **221** is 2.56. An interval D between the first base body **211** and the second base body **221** is 0.038λ .

(49) A length L_1 of one side of the first element **111** is 0.346λ . A length L_2 of one side of the second element **121** is 0.11λ . Since the second element **121** is provided to be shared with the

adjacent first unit, a length of the second element **121** in the x-axis direction with respect to the portion occupied by the second element **121** in the second unit is $L2/2$. A thickness of the first element **111** and a thickness of the second element **121** are 0.000346λ .

(50) A length $L3$ of one side of the third element **131** is 0.346λ . A length of one side of the portion occupied by the fourth element **141** in the second unit **321** is 0.38λ . A thickness of the third element **131** and a thickness of the fourth element are 0.000346λ .

(51) With reference to FIG. 7, a phase difference of a reflected wave obtained in a case where the first device **110** is displaced with respect to the second device **120** will be described. Here, it is assumed that a frequency of a target radio wave is 5.77 GHz.

(52) FIG. 7 is a graph showing a phase change amount obtained by displacing the first device **110** with respect to the second device **120**. A line **700** indicates the phase of the reflected wave in a case where the position of the first device **110** and the position of the second device **120** are aligned.

(53) When the first device **110** is displaced with respect to the second device **120**, a difference (phase change amount) from the phase indicated by the line **700** may occur. Here, a phase difference from the phase corresponding to 5.77 GHz on the line **700** is referred to as a "phase change amount". A line **710** indicates the phase of the reflected wave in a case where the first device **110** is displaced with respect to the second device **120** and the second device **120** is fixed at a position where the phase change amount is maximized.

(54) As shown in FIG. 7, in the present embodiment, the phase change amount is 312.7° at the maximum. That is, in the present embodiment, the phase can be adjusted within a range of 312.7° . That is, by displacing the first device **110** with respect to the second device **120**, a reflection angle of the reflected wave can be made relatively large.

(55) FIG. 8 schematically shows a unit **800** included in a reflector in a first comparative example. The unit **800** is a unit corresponding to the unit **301** shown in FIG. 6. The unit **800** differs from the unit **301** in that the unit **800** does not have the second element **121**, and the first base body **211** is not substantially separated from the second base body **221**. In the first comparative example, the position of the first base body **211** with respect to the second base body **221** cannot be displaced after manufacturing.

(56) FIG. 9 is a graph showing a phase change amount in the first comparative example. As shown in FIG. 8, a line **900** indicates the phase of the reflected wave in a case where the position of the first base body **211** and the position of the second base body **221** are aligned. A line **910** indicates the phase of the reflected wave in a case where the position of the first base body **211** is set with respect to the second base body **221** such that the phase change amount is maximized at 5.77 GHz. As shown in FIG. 9, according to the configuration of the first comparative example, the phase change amount is 315.9° .

(57) FIG. 10 schematically shows a unit **1000** included in a reflector in the second comparative example. The unit **1000** is a unit corresponding to the unit **301** shown in FIG. 6. The unit **1000** differs from the unit **301** in that the unit **1000** does not have the second element **121**. According to the second comparative example, unlike the first comparative example, the position of the first base body **211** with respect to the second base body **221** can be displaced after manufacturing.

(58) FIG. 11 is a graph showing a phase change amount in the second comparative example. As shown in FIG. 10, a line **1100** indicates the phase of the reflected wave in a case where the position of the first base body **211** and the position of the second base body **221** are aligned. A line **1110** indicates the phase of the reflected wave in a case where the position of the first base body **211** is displaced with respect to the second base body **221** such that the phase change amount is maximized at 5.77 GHz. As shown in FIG. 11, according to the configuration of the second comparative example, the phase change amount is 208.5° .

(59) As can be seen from the comparison between the second comparative example and the first comparative example, the first base body **211** and the second base body **221** are separated from each other, so that the position of the first base body **211** can be displaced with respect to the

second base body **221**. However, the phase change amount decreases from 315.9° to 208.5° . That is, a range of a settable reflection angle is narrowed.

(60) As can be seen from the comparison between the second comparative example and the reflection apparatus **30** described above, the phase change amount can be greatly expanded to 312.7° by providing the second element **121**. That is, according to the reflection apparatus **30** described above, the first device **110** and the second device **120** are separated from each other, so that the first device **110** is allowed to be displaceable with respect to the second device **120** to allow the phase of the reflected wave to be adjustable, and it is possible to obtain the phase change amount equivalent to the phase change amount 315.9° obtained by the first comparative example.

(61) Next, a modification of the reflection apparatus **30** described above will be described. In the reflection apparatus **30** described above, a length of one side of the plurality of first units included in the first device **110** is 0.38λ , where λ is a wavelength of a radio wave incident on the reflection apparatus **30**. However, the length of one side of the first unit is not limited to this value, and an arbitrary value of a length of 0.3λ or more and 0.6λ or less can be applied as the length of one side of each of the plurality of first units included in the first device **110**, where λ is a wavelength of a radio wave incident on the reflection apparatus **30**.

(62) In the reflection apparatus **30** described above, the shapes of the plurality of first elements including the first element **111**, the plurality of second elements including the second element **122**, and the plurality of third elements including the third element **131** are square. However, the shapes of the first element, the second element, and the third element are not limited to being square. The first element, the second element, and the third element may have a polygonal shape or a shape curved at least in part.

(63) In the reflection apparatus **30** described above, a plurality of first base bodies including the first base body **211** and a plurality of second base bodies including the second base body **221** are square. However, the shapes of the first base body and the second base body are not limited to being square. The first base body and the second base body may have a polygonal shape or a shape curved at least in part.

(64) In the reflection apparatus **30** described above, the plurality of first elements including the first element **111** may transmit a specific linearly polarized wave or a specific circularly polarized wave. The plurality of second elements including the second element **122** may transmit a specific linearly polarized wave or a specific circularly polarized wave.

(65) In the system **10** described above, the base station **20** is an example of a radio wave radiation apparatus that radiates a radio wave incident on the reflection apparatus **30**. A reflection apparatus having the configuration included in the reflection apparatus **30** can be applied as a reflection apparatus that reflects a radio wave radiated from a radio wave radiation apparatus other than the base station **20** for mobile communication described above.

(66) While the present invention has been described by way of the embodiments, the technical scope of the present invention is not limited to the scope described in the above-described embodiments. It is apparent to persons skilled in the art that various alterations or improvements can be added to the above-described embodiments. It is also apparent from the scope of the claims that the embodiments added with such alterations or improvements can be included in the technical scope of the invention.

(67) The operations, procedures, steps, and stages of each process executed by a device, system, program, and method shown in the claims, embodiments, or diagrams can be achieved in any order as long as the order is not indicated by “prior to,” “before,” or the like and as long as the output from a previous process is not used in a later process. Even if the process flow is described using phrases such as “first” or “next” in the claims, embodiments, or diagrams, it does not necessarily mean that the process must be executed in this order.

EXPLANATION OF REFERENCES

(68) **10**: system; **20**: base station; **30**: reflection apparatus; **34**: adjustment apparatus; **101**: first

surface; **102**: second surface; **103**: third surface; **104**: fourth surface; **110**: first device; **120**: second device; **111**, **112**, **113**, **114**: first element; **121**: second element; **131**: third element; **141**: fourth element; **101**: first surface; **102**: second surface; **103**: third surface; **104**: fourth surface; **211**: first base body; **221**: second base body; **311**: first unit; **321**: second unit.

Claims

1. A reflection apparatus which reflects a radio wave, comprising a first device and a second device which are provided along an emission direction of a reflected wave, wherein the first device includes a plurality of first units each including a first base body which has a first surface and a second surface provided along the emission direction of the reflected wave, a first element which is provided on the first surface, and a second element which is provided on the second surface to be shifted in position from the first element in the emission direction of the reflected wave, the second device includes a plurality of second units each including a second base body which has a third surface and a fourth surface provided along the emission direction of the reflected wave, a third element which is provided on the third surface, and a fourth element which is provided on the fourth surface, and the first device is provided separated from the second device, and a relative positional relationship between the first device and the second device in a direction along the second surface is adjustable.
2. The reflection apparatus according to claim 1, wherein a phase of the reflected wave is determined by surface areas of the first element and the second element, a relative positional relationship between the first element and the second element, a thickness of the first base body, surface areas of the third element and the fourth element, and a thickness of the second base body.
3. The reflection apparatus according to claim 2, wherein the plurality of first units and the plurality of second units are provided at a plurality of positions along a specific direction along the first surface, such that phases of the reflected wave are different from each other.
4. The reflection apparatus according to claim 2, wherein the plurality of first units and the plurality of second units are provided such that the reflected wave propagates in a specific direction.
5. The reflection apparatus according to claim 2, further comprising an adjustment apparatus which adjusts a relative positional relationship between the first device and the second device.
6. The reflection apparatus according to claim 2, wherein a length of one side of each of the plurality of first units is 0.3λ or more and 0.6λ or less where λ is a wavelength of a radio wave incident on the reflection apparatus.
7. The reflection apparatus according to claim 2, wherein the first element, the second element, and the third element each have a polygonal shape or a shape curved at least in part.
8. The reflection apparatus according to claim 2, wherein the first element transmits a specific linearly polarized wave or a specific circularly polarized wave.
9. The reflection apparatus according to claim 2, wherein the first base body and the second base body each have a polygonal shape or a shape curved at least in part.
10. The reflection apparatus according to claim 1, wherein the plurality of first units and the plurality of second units are provided at a plurality of positions along a specific direction along the first surface, such that phases of the reflected wave are different from each other.
11. The reflection apparatus to claim 10, wherein the plurality of first units and the plurality of second units are provided such that the reflected wave propagates in a specific direction.
12. The reflection apparatus according to claim 10, further comprising an adjustment apparatus which adjusts a relative positional relationship between the first device and the second device.
13. The reflection apparatus according to any one of claim 1 wherein the plurality of first units and the plurality of second units are provided such that the reflected wave propagates in a specific direction.
14. The reflection apparatus according to any one of claim 1, further comprising an adjustment

apparatus which adjusts a relative positional relationship between the first device and the second device.

15. The reflection apparatus according to any one of claim 1, wherein a length of one side of each of the plurality of first units is 0.3λ or more and 0.6λ or less where λ is a wavelength of a radio wave incident on the reflection apparatus.
 16. The reflection apparatus according to any one of claim 1, wherein the first element, the second element, and the third element each have a polygonal shape or a shape curved at least in part.
 17. The reflection apparatus according to any one of claim 1, wherein the first element transmits a specific linearly polarized wave or a specific circularly polarized wave.
 18. The reflection apparatus according to any one of claim 1, wherein the first base body and the second base body each have a polygonal shape or a shape curved at least in part.
 19. The reflection apparatus according to any one of claim 1, wherein the first element and the third element are conductors having a frequency selective surface (FSS).
 20. A system comprising: the reflection apparatus according to any one of claim 1; and a radio wave radiation apparatus which radiates a radio wave incident on the reflection apparatus.
-