

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12406541
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Burge; Gregory Le et al.

Access management and reporting technology

Abstract

An access management and reporting system includes a key safe that is located outside of a building and a communication system that is located within the building. The communication system is configured to perform, over a short-range wireless communication protocol, two-way communication with a communication module of the key safe. The system also includes a server that is located remote from the building and the key safe. The server is configured to perform, over a long-range communication protocol, two-way communication with the communication system located within the building, is configured to manage access to the key safe, and is configured to handle reporting related to access of the key safe.

Inventors: Burge; Gregory Le (Bend, OR), Earnshaw; Stanley Reed (Wilsonville, OR)

Applicant: Alarm.com Incorporated (Tysons, VA)

Family ID: 52463623

Assignee: Alarm.com Incorporated (Tysons, VA)

Appl. No.: 18/655391

Filed: May 06, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240290153 A1	Aug. 29, 2024

Related U.S. Application Data

continuation parent-doc US 18121715 20230315 US 12008852 child-doc US 18655391
continuation parent-doc US 17520258 20211105 US 11636721 20230425 child-doc US 18121715
continuation parent-doc US 16851961 20200417 US 11170594 20211109 child-doc US 17520258
continuation parent-doc US 16420954 20190523 US 10629015 20200421 child-doc US 16851961
continuation parent-doc US 15943439 20180402 US 10347065 20190709 child-doc US 16420954

continuation parent-doc US 15369292 20161205 US 9934636 20180403 child-doc US 15943439
continuation parent-doc US 14987200 20160104 US 9514584 20161206 child-doc US 15369292
continuation parent-doc US 14622209 20150213 US 9230374 20160105 child-doc US 14987200
continuation parent-doc US 13284323 20111028 US 8957757 20150217 child-doc US 14622209
us-provisional-application US 61407751 20101028

Publication Classification

Int. Cl.: **G07C9/00** (20200101); **G06F21/31** (20130101); **G07C9/20** (20200101); **G07C9/27** (20200101); **G07C9/33** (20200101); **H04L9/40** (20220101)

U.S. Cl.:

CPC **G07C9/00571** (20130101); **G06F21/31** (20130101); **G07C9/00309** (20130101); **G07C9/00817** (20130101); **G07C9/00896** (20130101); **G07C9/00904** (20130101); **G07C9/20** (20200101); **G07C9/27** (20200101); **G07C9/33** (20200101); **H04L63/0846** (20130101); G07C2009/00325 (20130101); G07C9/0069 (20130101); G07C2009/00825 (20130101); G07C2009/00936 (20130101); H04L63/068 (20130101); H04L63/108 (20130101)

Field of Classification Search

CPC: G07C (9/00571); G07C (9/20); G07C (9/27); G07C (9/33); G07C (9/00309); G07C (9/00817); G07C (9/00896); G07C (9/00904); G07C (9/0069); G07C (2009/00325); G07C (2009/00825); G07C (2009/00936); G06F (21/31); H04L (63/0846); H04L (63/068); H04L (63/108)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6748061	12/2003	Ahlstrom	379/102.01	H04M 11/025
6971029	12/2004	Avery, IV et al.	N/A	N/A
7116211	12/2005	Parker	N/A	N/A
7170998	12/2006	McIntock	N/A	N/A
7196610	12/2006	Straumann	340/5.1	G07C 9/27
8035480	12/2010	Woodard et al.	N/A	N/A
8437740	12/2012	Despain	455/410	G07C 9/21
2002/0099945	12/2001	McIntock	N/A	N/A
2002/0180582	12/2001	Nielsen	340/5.6	G07C 9/21
2003/0081746	12/2002	Ahlstrom	379/102.01	H04M 11/04
2003/0151493	12/2002	Straumann	340/5.25	G07C 9/00857
2004/0022422	12/2003	Yamauchi et al.	N/A	N/A
2004/0049406	12/2003	Muncaster	705/313	G09F 9/00
2004/0049413	12/2003	Momma et al.	N/A	N/A
2004/0219903	12/2003	Despain	455/410	H04W 12/082

2005/0278653	12/2004	Scholz	715/842	G06F 3/0482
2007/0096870	12/2006	Fisher	N/A	N/A
2007/0193834	12/2006	Pai et al.	N/A	N/A
2007/0290797	12/2006	Harkins	340/5.5	G07C 9/00309
2008/0215384	12/2007	Mulholland et al.	N/A	N/A
2008/0246587	12/2007	Fisher	340/5.73	E05B 19/0005
2009/0030718	12/2008	Bengson	N/A	N/A
2009/0299777	12/2008	Silberman	N/A	N/A
2010/0283579	12/2009	Kraus	340/5.7	G07C 9/00944
2011/0053557	12/2010	Despain	455/410	G07C 9/00309
2011/0082746	12/2010	Rice et al.	N/A	N/A
2011/0320372	12/2010	Woodard et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
WO 2004/077848	12/2004	WO	N/A
WO 2009/088901	12/2008	WO	N/A

OTHER PUBLICATIONS

U.S. Final Office Action for U.S. Appl. No. 14/987,200, mailed Aug. 10, 2016, 15 pages. cited by applicant

U.S. Non-Final Office Action for U.S. Appl. No. 13/284,323, mailed Apr. 11, 2014, 25 pages. cited by applicant

U.S. Non-Final Office Action for U.S. Appl. No. 14/987,200, mailed Feb. 10, 2016, 17 pages. cited by applicant

U.S. Notice of Allowance for U.S. Appl. No. 14/987,200, mailed Oct. 26, 2016, 8 pages. cited by applicant

Primary Examiner: Yacob; Sisay

Attorney, Agent or Firm: Fish & Richardson P.C.

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. application Ser. No. 18/121,715, filed Mar. 15, 2023, which is a continuation of U.S. application Ser. No. 17/520,258, filed Nov. 5, 2021, which is a continuation of U.S. application Ser. No. 16/851,961, filed Apr. 17, 2020, which is a continuation of U.S. application Ser. No. 16/420,954, filed May 23, 2019, which is a continuation of U.S. application Ser. No. 15/943,439, filed Apr. 2, 2018, which is a continuation of U.S. application Ser. No. 15/369,292, filed Dec. 5, 2016, which is a continuation of U.S. application Ser. No. 14/987,200, filed Jan. 4, 2016, which is a continuation of U.S. application Ser. No. 14/622,209, filed Feb. 13, 2015, which is a continuation

of U.S. application Ser. No. 13/284,323, filed Oct. 28, 2011, which claims the benefit of U.S. Provisional Application No. 61/407,751, filed Oct. 28, 2010. All of these prior applications are incorporated herein by reference in their entirety for all purposes.

TECHNICAL FIELD

(1) This disclosure relates to access management and reporting technology.

BACKGROUND

(2) Mechanical keys remain the primary method of access to millions of locations, such as restaurants, retail, banks, small businesses, public sector facilities, and vacation properties. However, the use of mechanical keys creates a variety of challenges for business owners, managers, and homeowners. For example, an employee's unreturned, lost or stolen key may require a costly re-keying. Additionally, a mechanical key, by itself, leaves no access audit trail, eliminating the ability to determine who accessed a specific location and when that location was accessed. Moreover, after-hours deliveries and services require the presence of an employee or the distribution of keys to third party vendors.

SUMMARY

(3) Techniques are described for access management and reporting technology.

(4) Implementations of the described techniques may include hardware, a method or process implemented at least partially in hardware, or a computer-readable storage medium encoded with executable instructions that, when executed by a processor, perform operations.

(5) The details of one or more implementations are set forth in the accompanying drawings and the description below. Other features will be apparent from the description and drawings, and from the claims.

Description

DESCRIPTION OF DRAWINGS

(1) FIG. 1 is a schematic view of an example of an integrated access management and reporting system.

(2) FIG. 2 is a schematic view of another example of an integrated access management and reporting system.

(3) FIG. 3 is a schematic view of an additional example of an integrated access management and reporting system.

(4) FIG. 4 is a schematic view of a further example of an integrated access management and reporting system.

(5) FIG. 5 is a schematic view of a further example of an integrated access management and reporting system.

(6) FIG. 6 is a schematic view of a further example of an integrated access management and reporting system.

(7) FIGS. 7, 9, 11, and 13 are flow charts illustrating example processes.

(8) FIGS. 8A-8C illustrate an example of remotely programming passcodes to electronic lockboxes.

(9) FIGS. 10A and 10B illustrate an example of controlling a security system based on input from an electronic lockbox.

(10) FIG. 12 illustrates an example access rule and example access records.

(11) FIGS. 14A-14C illustrate examples of managing multiple electronic lockboxes.

DETAILED DESCRIPTION

(12) Techniques are described for an integrated access management and reporting system for electronic lockboxes. In some implementations, a server manages electronic lockboxes that release physical keys based on entry of a proper passcode. The server may engage in two-way

communication with the electronic lockboxes to remotely program and receive information from the electronic lockboxes.

(13) FIG. 1 illustrates an example access management and reporting system **100**. The system **100** includes an alarm and lockbox server **110** that manages alarm systems and/or electronic lockboxes located at multiple, different buildings (e.g., the building **130** and the building **140**). The multiple, different buildings may be operated by different entities (e.g., owned by different entities) with single entities operating groups of buildings. The server **110** may maintain data that defines which entities are associated with which buildings (or the alarm systems and/or electronic lockboxes at the buildings) and maintain permission data that sets which users are allowed to view data and perform control operations for alarm systems and/or electronic lockboxes managed by the server **110**. The multiple, different buildings may be any type of buildings, including commercial retail buildings, residential buildings, office buildings, or any building that uses an alarm system and/or an electronic lockbox. Any other structure (e.g., a cabinet, etc.) that uses an alarm system and/or an electronic lockbox may be managed by the server **110**. Although FIG. 1 illustrates two buildings for brevity, the server **110** may manage alarm systems and/or electronic lockboxes for many more buildings and/or structures.

(14) The system **100** also includes electronic lockbox and alarm system components located at each of the buildings. As shown, the building **130** includes an electronic lockbox **132** located at an exterior door of the building **130**, a lockbox gateway **134** located within the building **130**, and an alarm panel **136** located within the building **130**. The electronic lockbox **132** may include a user input device that receives user input of a passcode and a housing that secures a physical key that unlocks and locks a physical door of an entrance to the building **130**. The electronic lockbox **132** also may include a communication module that performs two-way communication over a short-range wireless communication protocol and a processor that controls the housing to allow access to the physical key secured within the housing based on entry of a proper passcode through the user input device.

(15) The electronic lockbox **132** engages in two-way communications with the lockbox gateway **134** over the short-range wireless communication protocol. In this example, the lockbox gateway **134** includes communication components that allow the lockbox gateway **134** to perform two-way communication with the lockbox **132** over the short-range wireless communication protocol and to perform two-way communication with the server **110** over a long-range communication protocol (e.g., a long-range wired or wireless communication protocol). The lockbox gateway **134** may serve as an intermediary between the server **110** and the lockbox **132** to enable the server **110** to remotely program and manage the lockbox **132** and also to receive reports when events (e.g., entry of a correct passcode, entry of an incorrect passcode, return of a physical key, etc.) occur at the lockbox **132**.

(16) In some examples, the lockbox gateway **134** performs relatively few processing operations and serves to primarily exchange communications between the lockbox **132** and the server **110**. In these examples, the lockbox **132** includes an electronic storage device that stores passcodes that are valid to open the lockbox **132** and the processor of the lockbox **132** performs the decision making processing to determine whether or not a proper passcode has been entered. When the server **110** remotely manages passcodes (e.g., adds passcodes, deletes passcodes, changes passcodes, etc.) for the lockbox **132**, the lockbox gateway **134** relays commands from the server **110** to the lockbox **132** and the processor of the lockbox **132** interprets the commands and performs adjustments to the electronic storage device needed to modify the valid passcodes as instructed. For reporting lockbox events, the lockbox **132** sends reports of events to the lockbox gateway **134** and the lockbox gateway **134** relays the reports to the server **110**. The server **110** stores the reports and may perform reporting operations for the entity operating the building **130** such that the entity (e.g., owner) may be alerted to events at the lockbox **132** and may view a history of events at the lockbox **132**.

(17) In other examples, the lockbox **132** performs relatively few processing operations and the

lockbox gateway **134** performs control processing for the lockbox **132**. In these examples, the lockbox gateway **134** includes an electronic storage device that stores passcodes that are valid to open the lockbox **132** and also includes a processor that performs the decision making processing to determine whether or not a proper passcode has been entered. For instance, when a user inputs a passcode at the lockbox **132**, the lockbox **132** merely forwards the entered passcode to the lockbox gateway **134** and the lockbox gateway **134** determines whether the passcode is valid. Based on the determination, the lockbox gateway **134** sends a command back to the lockbox **132** to either deny the entered passcode or allow access to the physical key secured in the lockbox **132**. When the server **110** remotely manages passcodes (e.g., adds passcodes, deletes passcodes, changes passcodes, etc.) for the lockbox **132**, the lockbox gateway **134** interprets the commands and performs adjustments to the electronic storage device needed to modify the valid passcodes as instructed. The lockbox **132** does not need to receive any communication related to the management of passcodes since the lockbox gateway **134** stores the valid passcodes. For reporting lockbox events, the lockbox gateway **134** sends reports of events to the server **110**. The server **110** stores the reports and may perform reporting operations for the entity operating the building **130** such that the entity (e.g., owner) may be alerted to events at the lockbox **132** and may view a history of events at the lockbox **132**.

(18) In some implementations, the lockbox gateway **134** monitors for tampering or malfunction of the lockbox **132**. In these implementations, the lockbox gateway **134** detects when communication with the lockbox **132** has been lost. For instance, the lockbox gateway **134** may periodically send pinging communications to the lockbox **132** and detect that communication has been lost when the lockbox **132** fails to respond to the pinging communications. When the lockbox gateway **134** detects that communication with the lockbox **132** has been lost, the lockbox gateway **134** sends an alert to the server **110** and the server **110** relays the alert as an electronic message (e.g., electronic mail message, text message, etc.) to an entity responsible for servicing the lockbox **132**.

(19) The lockbox **132** also may perform battery or power management operations. For instance, the lockbox **132** may operate on battery power and have a component that measures an amount of battery power remaining for the lockbox **132**. The processor of the lockbox **132** may periodically check the amount of battery power remaining for the lockbox **132** and compare the current amount of battery power to a threshold. The processor of the lockbox **132** determines whether the current amount of battery power has fallen below the threshold based on the comparison and, in response to a determination that the current amount of battery power has fallen below the threshold, the processor of the lockbox **132** controls the communication module of the lockbox **132** to send a battery alert to the lockbox gateway **134**. The lockbox gateway **134** relays the battery alert to the server **110** and the server **110** relays the battery alert as an electronic message (e.g., electronic mail message, text message, etc.) to an entity responsible for servicing the lockbox **132**.

(20) The building **130** also includes an alarm panel **136** located within the building. The alarm panel **136** may be part of a security system that monitors the building **130** based on data from various sensors located throughout the building **130**. The security system may sense many types of events or activities associated with the building **130** and the sensed events or activities may be leveraged in performing monitoring and reporting features. The security system may include a controller that communicates with the alarm panel **136** (or is part of the alarm panel **136**). The controller may be configured to control the security system. In some examples, the controller may include a processor or other control circuitry configured to execute instructions of a program that controls operation of the security system. In these examples, the controller may be configured to receive input from sensors, detectors, or other devices included in the security system and control operations of devices included in the security system or other household devices (e.g., a thermostat, an appliance, lights, etc.).

(21) The security system also includes one or more sensors or detectors. For example, the security system may include multiple sensors, including a contact sensor, a motion sensor or any other type

of sensor included in an alarm system, security system, or monitoring system. The sensors also may include an environmental sensor, such as a temperature sensor, a water sensor, a rain sensor, a wind sensor, a light sensor, a smoke detector, a carbon monoxide detector, an air quality sensor, etc. The sensors further may include a health monitoring sensor, such as a prescription bottle sensor that monitors taking of prescriptions, a blood pressure sensor, a blood sugar sensor, a bed mat configured to sense presence of liquid (e.g., bodily fluids) on the bed mat, bathroom usage sensors, food consumption sensors, etc. In some examples, the sensors may include a radio-frequency identification (RFID) sensor that identifies a particular article that includes a pre-assigned RFID tag.

(22) The server **110** provides monitoring and security services for the building **130** by exchanging electronic communications with the alarm panel **136**. For instance, the server **110** and the alarm panel **136** engage in two-way communications over a long-range communication protocol (e.g., a long-range wired or wireless communication protocol). The server **110** may be configured to monitor events generated by the alarm panel **136** based on output of sensors and detectors of the security system. The server **110** may exchange electronic communications with the alarm panel **136** to receive information regarding alarm events detected by the alarm panel **136** and to control operations of the security system.

(23) The server **110** may store sensor and image data received from the alarm panel **136** and perform analysis of sensor and image data received from the alarm panel **136**. Based on the analysis, the server **110** may communicate with and control aspects of the alarm panel **136**, one or more user devices, and a central monitoring station that dispatches emergency services in response to alarm events. For instance, the server **110** may send alerts/notifications to one or more user devices (e.g., mobile devices, computers, etc.) based on alarm data received from the alarm panel **136**. The server **110** also may process an alarm event received from the alarm panel **136** and forward the alarm event to a central monitoring station for handling by an operator that can dispatch emergency services to assist with the alarm event.

(24) Because the server **110** receives data related to access of the lockbox **132** and also receives data from the alarm panel **136**, the server **110** maintains an integrated database **120** that stores integrated alarm and lockbox data. For example, the server **110** may store data describing access events at the lockbox **132** with data describing events detected by the alarm panel **136**. In this example, the server **110** may link lockbox access data with alarm data to define a more complete picture of how the building **130** is being used when accessed through the lockbox **132**. The server **110** may detect an access event at the lockbox **132** and detect a return key event at the lockbox **132** and link these events with all of the alarm data collected by the alarm panel **136** between the access event and the return key event. In this manner, the server **110** defines a more complete record of how the building **130** is being accessed and who is accessing the building **130** when the lockbox **132** is being used. The server **110** may analyze the integrated alarm and lockbox data stored in the database **120** to provide alerts/reports based on both alarm and lockbox data and also to verify that the building **130** is being properly accessed when the lockbox **132** is used.

(25) In some examples, the server **110** may use lockbox data to assist with detecting alarm events. In these examples, the server **110** may determine whether the lockbox **132** has been accessed and/or whether the lockbox **132** is operational to assist in determining whether an alarm event needs to be reported to the central monitoring station. For instance, when the security system detects a potential alarm event shortly after a proper access of the lockbox **132** has been made, the server **110** may classify the potential alarm event as more likely being a false alarm than if the proper access of the lockbox **132** had not occurred prior to the potential alarm event. In this regard, the server **110** may delay reporting the potential alarm event to the central monitoring station to allow more time for the user that accessed the lockbox **132** to disarm the security system or the owner of the building **130** (or other authorized user) to confirm that the access was permissible.

(26) In addition, when reporting an alarm event to the central monitoring station, the server **110**

may provide lockbox data to the central monitoring station in addition to the alarm event to assist the central monitoring station with handling the alarm event. For example, the server **110** may provide the central monitoring station with data indicating whether or not the lockbox **132** has been recently accessed and/or whether or not the lockbox **132** is operating properly.

(27) In some implementations, events at the lockbox **132** may be used to control the alarm panel **136**. In these implementations, the server **110** may receive a report of an event at the lockbox **132** and then send a control command to the alarm panel **136** based on the event at the lockbox **132**. For example, when the server **110** receives a report of an access event at the lockbox **132** and the alarm panel **136** is in an armed state, the server **110** may send a command to the alarm panel **136** to change from the armed state to the disarmed state. This may enhance the convenience of a user accessing the building **130** using the lockbox **132** because the user does not have to separately disarm the security system upon entry. Also, the entity operating the building may leave the passcode to the security system secret from the user accessing the building **130** using the lockbox **132**, thereby limiting the distribution of the passcode to the security system.

(28) In another example, when the server **110** receives a report of a return key event at the lockbox **132** and the alarm panel **136** is in a disarmed state, the server **110** may send a command to the alarm panel **136** to change from the disarmed state to the armed state. This may help reduce the likelihood that the building **130** is left in an unmonitored state by virtue of a user accessing the building **130** using the lockbox **132** and forgetting to arm the security system when leaving the building **130**.

(29) Similar to the building **130**, the building **140** includes an electronic lockbox **142** located at an exterior door of the building **140**, a lockbox gateway **144** located within the building **140**, and an alarm panel **146** located within the building **140**. The electronic lockbox **142**, the lockbox gateway **144**, and the alarm panel **146** are similar to the electronic lockbox **132**, the lockbox gateway **134**, and the alarm panel **136** and may perform operations similar those described above as being performed by the electronic lockbox **132**, the lockbox gateway **134**, and the alarm panel **136**. The difference shown for the building **140** as compared to the building **130** is the communication with the server **110**. As shown, unlike the lockbox gateway **134**, the lockbox gateway **144** does not communicate with the server **110** over a long-range communication protocol. Rather, the lockbox gateway **144** communicates with the alarm panel **146** over a short-range communication protocol (e.g., a wired or wireless short-range communication protocol) and the alarm panel **146** relays communications between the lockbox gateway **144** and the server **110**. In this example, the lockbox gateway **144** may directly control operations of the alarm panel **146** based on events at the lockbox **142** without having to communicate with the server **110**.

(30) In some examples, a lockbox gateway may not be used. In these examples, the lockbox may communicate directly with the server **110** over a long-range communication protocol. Alternatively, the lockbox may communicate directly with an alarm panel over a short-range communication protocol and the alarm panel may perform the operations described as being performed by a lockbox gateway in addition to the operations described as being performed by the alarm panel.

(31) Integrated access management and reporting systems described throughout the present disclosure may provide one or more of the following: Keyless access (which may eliminate or reduce the distribution of mechanical keys); Access accountability (such as recording each access by individual, date and time); Access control (such as providing access based on a single use, time of day, day of week, time bound access); Display or transmit access information (such as who accessed, when was it accessed, and where was it accessed); Eliminate or reduce false alarms (such as by providing interface access with alarm system); Enable keyless emergency access (such as by using one time codes); Facilitate “dark delivery” (such as by providing unattended after-hours access); and Alert/event notifications-wireless notification when a scheduled event does not take place (such as a store opening or closing).

(32) Integrated access management and reporting systems may include any suitable structure, as

shown in FIGS. 1-6. Examples of the integrated access management and reporting systems are provided below, in addition to commercial and residential doors, the integrated access management and reporting systems may be used on any device with a mechanical lock. From file cabinets, trailers, storage cabinets, to millions of other locations/devices, the integrated access management and reporting systems may provide a simple, low cost, yet technically sophisticated solution in a mechanical key environment.

(33) 1. Product Systems Overview

(34) The integrated access management and reporting system may include one or more of the following system levels: SP-Access SP-Web SP-Security SP-Net

(35) Each integrated access management and reporting system may include a ruggedized on-premise electronic key safe (also referred to as “SP-Key safe” or “Point Safe”). The SP-Key safe may be securely mounted on or adjacent to a door (or point of access). Using an assigned PIN number, employees, vendors, and service providers may open the SP-Key safe to gain access to the facility key. Each access may be recorded by user, date, and/or time.

(36) An optional SP-Battery Jumper may be offered in case of internal battery discharge or failure. RF communication system levels may require a SP-Communications Gateway device located inside the building. The system levels may be characterized by their external communication ability and connectivity with security panels and web based user/administrator portal. Service levels may allow varying functionality depending upon the installation and user needs.

(37) 1.1. SP-Access

(38) The SP Access solution may deliver a low cost, electronic key storage/access management solution that may be easy to install. At the core of the SP Access solution is the Key safe, the physical vault that contains the key. No external communication beyond web registration may be provided for this system. The web portal may be used for initial product registration. Valid PIN numbers can be selected from the web portal, but ability to add or manage information on the relational database may not be provided. One Time and Limited Time PIN numbers may be used with this level of devices.

(39) 1.1.1. Key safe

(40) A ruggedized locking vault that may protect a key and may be accessed via a 12-key input pad and small LCD screen for instructions. A piezo sounder may provide audio confirmation of keypad entries and may provide varying tones for other situations. In addition, red and green LED's provide steady or blinking illumination for various input situations. The vault may be visually obscured by a plastic cover to minimize visual interest and dissuade tampering. The 2" width may enable the Key safe to be installed on 2" standard retail glass store front doors. When mounted on a glass store front door frame the cover may allow the device to “blend” into the door frame.

(41) 1.1.1.1. Key safe Installation Kit

(42) An installation kit comprised of an Installation Instructions pamphlet and a plurality of, for example, flat head lag screws may be packaged in, for example, a zip lock polyethylene bag and included with every Key safe.

(43) 1.1.1.2. Key safe Locksmith Instruction Document

(44) In the event a Key safe is not functioning and cannot be persuaded to open the key pouch, an instructional document may be provided to dealers that explains how and where to cut the safe to remove it. A blade or other cutting instrument may be recommended and locations around the key pouch may be identified for a series of cuts that may expose the tab that releases the entire Key safe from its mounting bracket.

(45) 1.1.1.3. Key safe Audio Tones

(46) The Key safe may produce audio tones for one or more of the following situations: 1. Every keypad entry (SINGLE SHORT TONE) 2. Every successful menu selection with <OK> button (SINGLE SHORT TONE) 3. Every entry that triggers Error event (3 LONG TONES) 4. ACCESS Key or ACCESS Key DISABLE Alarm (2 SHORT TONES) 5. ACCESS Key ENABLE Alarm

(LONG TONE followed by 1 SHORT TONE)

1.1.1.4. Keysafe LED Displays

(47) The Keysafe may illuminate red and green LED's for the following situations: 1. Every keypad entry (SINGLE RED FLASH) 2. Every successful menu selection with <OK> button (SHORT GREEN FLASH ½ SEC) 3. Every entry that triggers Error event (3 LONG RED FLASHES 1 SEC EACH) 4. ACCESS Key/ACCESS Key DISABLE Alarm (SOLID GREEN FOR 5 SECONDS) 5. ACCESS Key ENABLE Alarm (SOLID GREEN FOR 4 SECONDS FOLLOWED BY 2 LONG RED FLASHES 1 SEC EACH)

1.1.1.5. PIN Code Management

(48) After product registration, the management of PIN codes may be accomplished on-line.

(49) 1.1.1.6. SP-Battery Jumper

(50) A battery-powered device may provide external power in the event of battery failure on the Keysafe.

(51) 1.2. SP-Web

(52) No communication may occur between the Web application and the integrated access management and reporting system. The Keysafe microprocessor and imbedded firmware may have the ability to decrypt codes input into the box to determine their validity without any connectivity to the web. The processes may utilize the unique serial number of the Keysafe to generate valid codes, and calendar events may trigger the firmware on the Keysafe and/or the SP-Web Portal database to generate new possible codes.

(53) 1.3. SP-Security

(54) This system level may include all the components, functions and capabilities found in the SP-Access and SP-Web levels and may add the capability of the SP-Keysafe functioning as a wireless keypad to a security panel, such as a GE/UTC, Simon XT or Concord NX security panel. This interface may provide an arm/disarm interface to the security panel. Without a Gateway, no communication to the relational database on the web portal is performed.

(55) 1.3.1. Two Way Transceiver

(56) The Security system may require a device that sends signals to the alarm panel to arm, disarm, and/or enroll the transmitter. The Two Way Transceiver may operate in one-way mode, which may allow only a select number of commands. The transmitter may send messages to the receiver on the security panel utilizing short-range wireless protocols. The 319.5 MHz frequency may be utilized for communication between the Gateway and Keysafe RF circuit. The Tiny Encryption Algorithm (TEA) may be used to provide wireless encryption protection and maintain a relatively small transmission packet size.

(57) 1.4. SP-Net

(58) The Networked (SP-Net) system level may include all of the features and functions found in SP-Access and SP-Web system levels while adding two way communication and Keysafe programming via the Web Portal and Gateway. The Networked system may allow for web reporting of Keysafe RF events and for web programming of the RF keysafe. Additionally, the Networked system may support KeySwitch connectivity alarm panels and direct connectivity and activation of accessory devices, such as mag locks. The Networked system may include a Keysafe RF device, a Gateway and Connect web services.

(59) 1.4.1. Gateway

(60) The Gateway may communicate with the Keysafe via a short-range wireless communication link (e.g., the 319.5 MHz link). The Gateway via the GPRS transceiver may transmit access and/or programming data to the Web Portal and receive Keysafe programming information from the Web Portal application.

(61) The enclosure may be wall-mounted, and may be powered by, for example, an external transformer that may provide 6-15 VDC from either a 110 or 220 VAC source. A 1.2 Amp-hour battery may be included for back-up. A four-position terminal block with two positions for shunting

an alarm and two positions for switching an accessory device (such as a magnetic door lock or security camera) may be included. Power may be provided to the general packet radio service (GPRS) printed circuit board (PCB) via a 22-pin connector. Alternatively, the PCB may be a transmission control protocol (TCP) PCB to provide TCP/IP functionality. This system level also may allow a security dealer to use the Key switch contact output in the Gateway for hard-wired security panel shunting.

(62) 1.4.2. Two Way Transceiver

(63) The two-way transceiver may have two modes: one-way and two-way. SP-Security level users may be set up to utilize the one-way mode. The transmitter may send messages to the receiver on the security panel utilizing short-range wireless protocols.

(64) SP-Net level installations may require two modules, one in the Keysafe and another in the Gateway. This may allow communication back from the Web Portal to the Keysafe via the Gateway. The 319.5 MHz frequency may be utilized. The Tiny Encryption Algorithm (TEA) may be used to provide wireless encryption protection and maintain a relatively small transmission packet size.

(65) 1.4.3. PointCam

(66) The PointCam may be an 900 MHz transceiver that is integrated into the Gateway module itself. It may provide the ability to transmit JPEG images from cameras turned on by infrared detection.

(67) 1.5. Service Levels

(68) Various service levels may be provided to users of the integrated access and reporting systems described throughout this disclosure.

(69) 1.5.1. Point Codes

(70) In some examples, the standalone, basic product may provide no communication between the Web portal and the Entry device. The Keysafe determines if PIN codes are valid by comparing them to the internal array of PIN codes and their state; the PIN code must be valid and have its state set to Active. Deleted PIN codes will have their state set to In-Active.

(71) 1.5.1.1. Code Creator

(72) During product registration or whenever an Administrator visits the web portal, they may be given the opportunity to accept the “Code Creator” option. This option may allow the creation of both One Time and Limited Time PIN numbers especially attractive for emergency responders and property management companies. The administrator may use the PointCodes online database to store the names and contact info for individuals who they have assigned one-time or time bound codes. RF installations may use the “Code Creator” to allow additional access control and wireless security pad functionality.

(73) 1.5.2. Point Connect

(74) PointConnect may have all of the functionality of PointCodes with the additional full relational database functionality via the web portal.

(75) 1.6. Web Portal

(76) The Web Portal may be comprised of a website user interface and back end data management being provided by any suitable entity on existing network resources. The Web Portal Application may offer programming options not available locally via the Keysafe keypad.

(77) 1.7. Panel Specific Systems

(78) These system levels may provide the end user all of the capabilities and functions found in the Networked Access system level. However, these system levels may not employ the use of the stand-alone Communications Module, but utilize the built-in RF communications found in each that will work with the Two Way Transceiver. Examples of panel specific systems include SP-GE Security Info (Simon XT), SP-GE Security Info (Concord NX), and SP-GE Security ADC.

(79) 2. Commands

(80) This section may define data transactions between different devices including those commands

initiated via the Internet-based application. Some transactions may occur in multiple places. Their description may be given in the first applicable section in which they occur. Capitalized letters are suggested characters that may appear in a two-line, eight-character-wide LCD screen.

(81) First Example Command Matrix

(82) The matrices below show example sets of individual commands. The Keysafe may be able to perform one or more of the following actions and the lists further describe which level of users may have which commands available.

(83) TABLE-US-00001 User Type Command is Availabe To One Limited SP-Sytem Level
Available Keysafe Menu System Web Portal General Time Time Open Command ACCESS WEB
SECURITY NET Program Access History Generated Program History Admin Manager User
Vendor Vendor User User Now Change Admin PIN X X X X X X X Add Manager PIN X X X X X
X X Delete Manager PIN X X X X X X X Add User PIN X X X X X X X Delete User PIN X X
X X X X X X Add Vendor PIN X X X X X X X Delete Vendor PIN X X X X X X X Set Time
X X X X X X X X Enroll Transmitter X X X X Enroll DWS X X X X Enable Keypad Only X X X
X Set User Access Hours X X X X X Set Vendor Access Hours X X X X X Add General Vendor
PIN X X X X Delete General Vendor PIN X X X X Add Limited Time PIN X X X X X Delete
Limited Time PIN X X X X X X Add One Time PIN X X X X X X Delete One Time PIN X X X X
X X Add Open Now PIN X X X X Open Now X X Access Key X X X X X X X X X X X X
Access Key Enable Alarm X X X X X X X X X X Access Key Disable Alarm X X X X X X X X
X X Enable Alarm X X X X X X X X X X Disable Alarm X X X X X X X X X X Accessory On X
X X X X X X X X X X Accessory Off X X X X X X X X X X * (power up) X X X X X X X X X X
X X *11 (power up for OPEN NOW) X X X View Date Activity X X X X X X X X View PIN
Activity X X X X X X X X Review PIN X X X X X X X X Low Battery X X X X X X X X X X
X X Incorrect PIN X X X X X X X X X X X X Login Attempts Exceeded X X X X X X X X X X
PINS Exceeded X X X X X X X X X X X X X Record Access X X X X X X X X X X X X
Record Incorrect Code Entry X X X X X X X X X X X X X Reset Clock (auto correction) X X X
X X Read Clock X X X X X

2.1. Change Admin PIN

2.2. Add Manager PIN

2.3. Delete Manager PIN

2.4. Add User PIN

2.5. Delete User PIN

2.6. Add Vendor PIN

2.7. Delete Vendor PIN

2.8. Set Time

2.9. Enroll Transmitter

2.10. Enroll DWS

(84) The RF modules that may communicate with the security panels may utilize the built-in RF protocols that exist for security key fobs. The protocol may not make provisions for sending a low battery alarm in the event the battery on the key fob falls below a threshold voltage level. Since it may be desired to obtain “low battery” functionality, a dummy Door Window Sensor (DWS) device, which does have the low battery functionality, may be enrolled. During installation, a dealer may first enroll the transmitter, then the DWS device.

(85) 2.11. Enable Keypad Only

(86) For SP-Security and SP-Net installations, an additional SETUP command may be available to ADMIN and MANAGER users, which may allow the ENABLE ALARM and DISABLE ALARM commands to be utilized.

(87) 2.12. Set User Access Hours

(88) May be available to ADMIN and MANAGER users to limit Keysafe access for two-way (SPNet) customers. An ADMIN or MANAGER may program a lockout period on the Web Portal.

The lockout period may apply to all users except ADMIN or MANAGER types.

(89) There may be two options: a. 24 HR ACCESS b. ACCESS HOURS i. BEGINNING HR:MIN
ii. ENDING HR:MIN

2.13. Set Vendor Access Hours

(90) May be available to ADMIN and MANAGER users to limit Keysafe access for two-way (SPNet) customers. An ADMIN or MANAGER may program a lockout period on the Web Portal. The lockout period may apply to all VENDORS.

(91) There may be two options: a. 24 HR ACCESS b. ACCESS HOURS i. BEGINNING HR:MIN
ii. ENDING HR:MIN

2.14. Add General Vendor PIN

(92) This may be a PIN code that may be generated by the SP-Net ADMIN or MANAGER level users. It may be recognized by the Keysafe as a valid PIN and the Web Portal may use a relational database to make it equivalent for multiple sites.

(93) 2.15. Delete General Vendor PIN

(94) 2.16. Add Limited Time PIN

(95) SP-WEB, SP-SECURITY Systems may have a web portal application create a TIME CODE that may contain the date that the ONE TIME PIN was valid or the starting date, starting time and ending date the LIMITED TIME PIN was valid. This may allow non-wireless systems to be used by users such as vacation rental agencies. For example, a rental property manager could get on the website, generate a PIN, and record both it and the corresponding TIME CODE. He may in turn give the PIN to a vacationer who may enter the PIN at the box. The box may respond by asking for the TIME CODE, it may then decrypt the code and internally make that PIN good for the prescribed amount of time.

(96) SP-NET Systems may already know what level of service the Keysafe is. If a SP-NET level, it may look for a second data string that, may be sent whenever a ONE TIME or LIMITED TIME code was created on the web portal. This may eliminate the need for the manager to write down an additional TIMECODE or the need for an end user to input it.

(97) 2.17. Delete Limited Time PIN

(98) 2.18. Add One Time PIN

(99) A single time access code may be generated that may allow a user access to a keypouch just one time on a particular day. This may require a second packet to be sent for SP-NET level customers or a second TIME CODE to be entered that conveys a day for SP-ACCESS, SP-WEB and SP-SECURITY level customers. The second piece of information may be a packet containing the day of the year when the code is valid.

(100) 2.19. Delete One Time PIN

(101) 2.20. Add Open Now PIN

(102) This command may allow a SP-NET system Admin or Manager to create a valid PIN that may be communicated via phone, email, or web phone application to someone needing immediate entry to a Keysafe.

(103) 2.21. Open Now

(104) The user may enter a code such as *,1,1 to wake up the device where it may prompt for a correct "Open Now" PIN code.

(105) 2.22. Access Key

(106) Successful Key Pouch openings may result in the generation of a data packet to be sent to the Gateway substantially immediately after the event. This data packet may contain information such as: KEY SEQUENCE: *,PIN, <OK>

(107) 2.23. Access Key Enable Alarm

(108) Successful Key Pouch openings may result in the generation of a data packet to be sent to the Gateway substantially immediately after the event. This data packet may contain information such as: KEY SEQUENCE: *,PIN,#, <OK>

(109) 2.24. Access Key Disable Alarm

(110) Successful Key Pouch openings may result in the generation of a data packet to be sent to the Gateway substantially immediately after the event. This data packet may contain information such as: KEY SEQUENCE: *,PIN,*,<OK>

(111) 2.25. Enable Alarm

(112) A user may be able to utilize the SP-Keysafe as a remote keypad to enable the alarm without dropping the keypouch. A successful activation may result in the generation of a data packet to be sent to the Gateway substantially immediately after the event. This data packet may contain information such as: KEY SEQUENCE: *,PIN,#,#, <OK>

(113) 2.26. Disable Alarm

(114) A user may be able to utilize the Keysafe as a remote keypad to enable the alarm without dropping the keypouch. A successful de-activation may result in the generation of a data packet to be sent to the Gateway substantially immediately after the event. This data packet may contain information such as: KEY SEQUENCE: *,PIN,*,*,<OK>

(115) 2.27. Accessory On

(116) The keypad may be able to turn on accessories such as magnetic key locks. KEY SEQUENCE: ??????<OK>

(117) 2.28. Accessory Off

(118) The keypad may be able to turn off accessories such as magnetic key locks KEY SEQUENCE: ??????<OK>

(119) 2.29. *(Power Up)

(120) A user may generally wake up a device by pushing a button such as the “*” button, which may bring the Keysafe out of hibernation mode.

(121) 2.30. *11(Power Up for Open Now)

(122) A user may wake up a device by pushing a sequence of buttons, for example the “*” then “1” and “I” buttons, which may bring the Keysafe out of hibernation mode and may cause it to await an “Open Now” valid PIN code.

(123) 2.31. View Date Activity

(124) 2.32. View PIN Activity

(125) 2.33. Review PIN

(126) 2.34. Low Battery

(127) If the battery voltage drops below a certain predetermined voltage, a message may be sent to the Gateway, for example during an “Initialize System” phase.

(128) 2.35. Incorrect PIN

(129) 2.36. Login Attempts Exceeded

(130) If a user attempts to log in with an invalid PIN code a predetermined number of times within a predetermined amount of time, for example three times within a five minute period, a message may be sent via the Gateway. This may be a valuable notification, for example in case of a vendor being unable to access a door, or a disgruntled employee trying to gain unauthorized access.

(131) 2.37. #PINS Exceeded

(132) 2.38. Record Access

(133) 2.39. Record Incorrect Code Entry

(134) 2.40. Reset Clock

(135) 2.41. Read Clock

(136) Second Example Command Matrix

(137) The second example command matrix shows whether the commands are available with the basic Keysafe, Code Creator or Web Connect Service options. The second matrix also shows under which menus on the PointSafe or Web Portal certain commands exist. Various users have permission for certain commands also. The maximum number of bits required for each command is also shown. From a complexity and communications robustness perspective, it may be desirable to

limit each command to a single data transmission. Regulatory rules may require each transmission to be less than a certain length of bits. Sixty-four commands may be used in accordance with wireless protocols.

(138) TABLE-US-00002 User Type Command is Available To One Limited Autho- RF Hardware Level Keysafe Menu System Web Portal Man- Vendor Time Time Open rized Command Command PointSafe PointSafe-RF PointGateway Program Access History Generated Program History Admin
ager User Employee User User Now Vendor 1 Supervisory X X X 2 Add Admin PIN X X X X X
3 Add Manager PIN X X X X X 4 Delete Manager PIN X X X X X X 5 Add User PIN X X X
X X X 6 Delete User PIN X X X X X X X 7 Add Vendor Employee PIN X X X X X 8 Delete
Vendor Employee PIN X X X X X X 9 Set Time X X X X X X X X 10 Enroll Transmitter X X X
X 11 Enroll DWS X X X X 12 Enable Keypad Only X X X 13 Set User Access Hours X X X X 14
Set Vendor Access Hours X X X X X 15 Add Authorized Vendor X X X X 16 Del Authorized
Vendor X X X X 17 Add Limited Time PIN X X X X X X 18 Delete Limited Time PIN X X X X X
X X 19 Add One Time PIN X X X X X X 20 Delete One Time PIN X X X X X X X 21 Open Now
X X X 22 Access Key X X X X X X X X 23 Access Key Enable Alarm X X X X X X X X 24
Access Key Disable Alarm X X X X X X X X X 25 Enable Alarm X X X X X X X X 26 Disable
Alarm X X X X X X X X X 27 Closing Code X 28 Accessory On X 29 Accessory Off X 30 *
(power up) X X X X X X X X X X 31 *11 (power up for OPEN NOW) X X X 32 View Date
Activity X X X X X X X 33 View PIN Activity X X X X X X X 34 Alarm Status X X X X X X X
X X X 35 Incorrect PIN X X X X X X X X X X 36 Login Attempts Exceeded X X X X X X X
X 37 Factory Reset X X X X X X 38 Display Serial Number X X X 39 Set Date X X X 40 Get
Date X 41 Get Time X X 42 COMM DELETED Refresh PINs 43 Time Code Start X X X X X X
44 Time Code End X X X X X X 45 Acknowledge 46 Delete Admin PIN X X X X X

3.1. Supervisory

(139) Both PointSafe-RF and PointGateway systems may require a SUPERVISORY command that monitors the status of the PointSafe data, battery status and determines if there are any commands waiting to be pushed down to the PointSafe from the web portal. A single bit of information monitors the PointSafe battery (good or bad), a “checksum” sequence ensures the data in the PointSafe is not corrupted. The PointSafe may wake itself up once per hour and transmit the SUPERVISORY command to the Gateway. If the Gateway has information waiting to be downloaded, it transmits the commands within the 30 second “listening” period that the PointSafe is awake.

(140) 3.2. Change Admin PIN

(141) In some examples, this can only be done via the web portal. A new customer may be required to go to the web portal and register before he receives the initial Admin PIN number. A Registration Code may be included in a tamper proof envelope with every PointSafe. This may be required during the initial registration process on the web portal to ensure that a dealer or locksmith has not learned of valid PIN codes before selling to an end customer.

(142) 3.3. Add Manager PIN

(143) In some examples, this can only be done via the web portal.

(144) 3.4. Delete Manager PIN

(145) These may be deleted at the PointSafe or via the web portal.

(146) 3.5. Add User PIN

(147) In some examples, this can only be done via the web portal. For PointConnect systems the PIN numbers may be generated on the web portal and “pushed” to the PointSafe. The PointSafe may store the array of pushed PIN's in a separate location from the pre-programmed PIN's programmed at the factory.

(148) 3.6. Delete User PIN

(149) These may be deleted at the PointSafe or via the web portal. For standalone systems, PIN's need to be deleted at the PointSafe.

(150) 3.7. Add Vendor Employee PIN

(151) In some examples, this is a PIN code that can be generated by the Admin or Manager level users or by an Authorized Vendor only on the web portal. It may be recognized by the PointSafe as a valid PIN and the web portal may use the relational database to make it equivalent for multiple sites. These PIN numbers are not pre-programmed into the devices and therefore cannot be used with non Two-Way communication PointSafes. These PIN numbers may be “pushed” to the PointSafes via the Two-Way wireless and Gateway.

(152) The owner/administrator may have the option on the web portal to allow or disallow authorized vendors from generating vendor employee codes themselves. If disallowed, the owner/administrator generates and distributes the codes personally.

(153) 3.8. Delete Vendor Employee PIN

(154) These can be deleted at the PointSafe or via the web portal. If done at the PointSafe with RF capabilities, the transaction may be relayed to the Gateway to update the relational database on the web portal.

(155) 3.9. Set Time

(156) This can be done at the device or via the web portal manually by administrators or automatically for Two-Way systems.

(157) 3.10. Enroll Transmitter

(158) In some examples, this command and functionality is only available for PointSafe-RF devices. In these examples, the enrollment must be done at the device and the PointSafe transmitter must be enrolled on the panel as a keyfob device to utilize the keyfob communications.

(159) 3.10.1. Command Disabled Flag

(160) The enrollment process also may trigger an internal flag to be set in the PointSafe which turns off the “Access Key” command. This internal flag may be referred to as the COMMAND DISABLED flag and can be set to YES or NO. As part of the setup process, an installer may need to configure the panel to utilize the “programmable output” option which sends a signal to the Gateway unit via a hardwired set of leads.

(161) 3.11. Enroll DWS

(162) In some examples, this command and functionality is only available for PointSafe RF devices. The RF modules that communicate with security panels may utilize the built in RF protocols that exist for security keyfobs. The protocol does not make provisions for sending a low battery alarm in the event that the battery on the keyfob falls below a threshold voltage level. This may be because if a keyfob fails to work a user instinctively replaces the battery to see if this fixes it. To use the LOW BATTERY command functionality, we also may “enroll” a dummy Door Window Sensor (DWS) device which does have the LOW BATTERY functionality. During installation, a dealer may first enroll the transmitter then the DWS device. Different panels may have different mechanisms of displaying LOW BATTERY conditions for DWS devices including LCD and LED display.

(163) 3.12. Enable Keypad Only

(164) For PointSafe RF or PointGateway installations an additional SETUP command may be available to ADMIN and MANAGER users to allow the ENABLE ALARM and DISABLE ALARM commands to be utilized.

(165) 3.12.1. Keypad Only Flag

(166) If activated in SETUP, the KEYPAD ONLY FLAG will be set to ON.

(167) 3.13. Set User Access Hours

(168) Available to ADMIN and MANAGER type users to limit PointSafe access for Two-Way customers. An ADMIN or MANAGER can program on the Web Portal a lockout period. The lockout period would apply to all users except for ADMIN or VENDOR types.

(169) There may be 2 options: a. 24 HR ACCESS b. ACCESS HOURS i. BEGINNING HR:MIN
ii. ENDING HR:MIN

3.14. Set Vendor Employee Access Hours

(170) Available to ADMIN and MANAGER type users to limit PointSafe access for Vendor Employees. An ADMIN or MANAGER can program on the Web Portal a lockout period. The lockout period would apply to all VENDOR Employees.

(171) There will be 2 options: a. 24 HR ACCESS b. ACCESS HOURS i. BEGINNING HR:MIN ii. ENDING HR:MIN

3.15. Add Authorized Vendor (List)

(172) A list of authorized vendors may be kept on the web portal. Each vendor may be assigned a unique number represented by 16 bits. An Admin or Manager can add an authorized vendor to his list for particular PointSafes. This will allow for 65,000 unique vendors across the country. Via the Authorized Vendor portal an authorized vendor can create unique Vendor Employee PIN numbers to be used to access multiple PointSafes, if the owner/administrator gives them the ability, else the owner/administrator generates and distributes PINs. In some implementations, no list of Authorized Vendors will be kept on the PointSafe itself.

(173) 3.16. Delete Authorized Vendor

(174) In some examples, authorized vendors can only be added and deleted via the web portal. Once this occurs successive DELETE VENDOR EMPLOYEE commands are issued to delete all employees of the deleted vendor.

(175) 3.17. Add Limited Time PIN

(176) In some examples, this can only be done via the web portal.

(177) PointSafe, PointSafe-RF Systems—The web portal application may create an 11 Digit TIME CODE that contains the date the ONE TIME PIN is valid or the starting date, starting time and duration of days the LIMITED TIME PIN was valid. This may allow non-wireless systems to be used by vacation rental agencies. The rental property manager can get on the website, generate a PIN and record both it and the corresponding TIME CODE. He'll in turn give it to the vacationer who will enter the PIN at the PointSafe. The PointSafe will respond by asking for the TIME CODE, it will decrypt the code and internally make that PIN good for the prescribed amount of time.

(178) PointGateway Systems-Both the PIN and TIME CODE are “pushed” down to Two-Way systems eliminating the need for a ONE TIME or LIMITED TIME user from having to input the TIME CODE when they access a PointSafe.

(179) 3.18. Delete Limited Time PIN

(180) These can be deleted at the PointSafe or via the web portal.

(181) 3.19. Add One Time PIN

(182) A single time access code can be generated that allows someone access to a keypouch for just one time if a non-panel installation. If it is a system that has been enrolled with a panel, a second ACCESS KEY DISABLE ALARM command may be allowed.

(183) 3.20. Delete One Time PIN

(184) These can be deleted at the PointSafe or via the web portal.

(185) 3.21. Open Now

(186) PointGateway level Administrators and Managers may have the ability to send an “OPEN NOW” command to a PointSafe from either the web portal or eventually a phone application. Once a manager has established that someone is physically at the device a command can be sent to allow the user to enter *,1,1,<OK> to wake up the device and have it send a query to the web portal to verify a valid OPEN NOW command has been sent. The web portal or phone application may need to explicitly show the administrator/manager the “*,1,1,<OK>” keys he needs to instruct the person on the other end to type in.

(187) A verification message may be transmitted back to the listening PointSafe which will then display OPEN NOW on the screen and allow the user to rotate the knob to drop the keypouch. The OPEN NOW command may generate a record in the HISTORY file of what time the command was

transmitted and the PIN of requestor.

(188) 3.22. Access Key

(189) Successful PIN numbers entered on the keypad may result in the generation of a data packet to be sent to the Gateway immediately after the event. If for any reason someone entered a valid sequence to open the keypouch, and then held the knob in a position where the blocking mechanism prevented the solenoid from returning to a locked position, the firmware may “pulse” the solenoid fifteen seconds later to again attempt to relock the PointSafe. If someone held the knob open for longer than this period, the PointSafe may remain in an open position where the knob could be turned and drop the keypouch. This safety timing may be required for any access or remote keypad command including those for ancillary devices. KEY SEQUENCE: *,PIN, <OK>

(190) If a user attempts to drop the keypouch via the Access Key sequence when the “Command Disabled” flag is set, the “COMMAND BLOCKED” error message may appear in the LCD screen along with the LED error event display (3 LONG RED FLASHES 1 SEC EACH).

(191) 3.23. Access Key Enable Alarm

(192) Successful Key Pouch opening may result in the generation of a data packet to be sent to the Gateway immediately after the event KEY SEQUENCE: *,PIN,#, <OK> The display may read ALARM ON.

(193) 3.24. Access Key Disable Alarm

(194) After the command is sent, but before the solenoid is energized to allow the Key Pouch to be dropped, an “ALARM STATUS” query may be sent to the Gateway. The Gateway may in turn report back if it is “enabled” or “disabled.” If the command successfully disabled the alarm, the pouch will drop. If for any reason the panel is not in a disabled state, a COMMAND BLOCKED message may be displayed and the solenoid may not release the keypouch.

(195) Successful Key Pouch openings may result in the generation of a data packet to be sent to the Gateway immediately after the event KEY SEQUENCE: *,PIN,*,<OK> The display may read ALARM OFF.

(196) 3.25. Enable Alarm

(197) A user may be able to utilize the PointSafe as a remote keypad to enable the alarm without dropping the keypouch. A successful activation may result in the generation of a data packet to be sent to the Gateway immediately after the event KEY SEQUENCE: *,PIN,#,#, <OK>

(198) 3.26. Disable Alarm

(199) A user may be able to utilize the PointSafe as a remote keypad to enable the alarm without dropping the keypouch. A successful de-activation may result in the generation of a data packet to be sent to the Gateway immediately after the event KEY SEQUENCE: *,PIN,*,*, <OK>

(200) 3.27. Closing Code

(201) For double keyed installations, the owners may want to know when keys are returned to the PointSafe. Owners may train their managers to use this feature when returning a key. Although they will return the keypouch with a slam latch, they may want to have them right afterwards enter the sequence below to identify it is simply a return operation. This may result in the generation of a data packet to be sent to the Gateway immediately after the event KEY SEQUENCE: *,PIN,*,#, <OK>

(202) 3.28. Accessory On

(203) The keypad may be able to turn on accessories such as magnetic key locks KEY SEQUENCE: *,PIN,><OK>

(204) 3.29. Accessory Off

(205) The keypad may be able to turn off accessories such as magnetic key locks KEY SEQUENCE: *,PIN,<<OK>

(206) 3.30. *(Power Up)

(207) A user may generally wake up a device by pushing the * button which brings the PointSafe out of hibernation mode.

(208) 3.31. *11(Power Up for Open Now)

(209) A user may wake up a device by pushing the * then 1 and 1 buttons which brings the PointSafe out of hibernation mode and looking for an “Open Now” valide PIN code.

(210) 3.32. View Date Activity

(211) Sixty days of event history may be available for viewing at the PointSafe or Web Portal for Two-Way systems.

(212) 3.33. View PIN Activity

(213) Sixty days of event history may be available for viewing the PointSafe or Web Portal for Two-Way systems.

(214) 3.34. Alarm Status

(215) After the alarm panel has been programmed to utilize the output function, it may have the ability to send a signal to the Gateway that indicates whether the panel is armed or disarmed.

(216) 3.35. Incorrect PIN

(217) If an incorrect PIN is entered or a sequence of keys is entered, the device may shutoff and increment the incorrect PIN counter.

(218) 3.36. Login Attempts Exceeded

(219) If a user attempts to login with an invalid PIN code three times within a five minute period, a message may be sent via the Gateway. The device also may enter a hibernation mode for five minutes to deter someone who is attempting unauthorized access. This may be a valuable notification in case of a vendor not being able to access a door or a disgruntled employee trying to gain access.

(220) 3.37. Factory Reset (code)

(221) To ensure that the relational database coincides with standalone devices, Administrators wishing to reset their PointSafe to factory new may be forced to go to the website. At the website, they may be asked if they wish to restore their PointSafe and then give a Factory Reset Code of 11 digits. The setup menu may have a Factory Reset option which, if selected, may restore the PointSafe to Year One condition.

(222) 3.38. Display Serial Number

(223) Enables Administrators to verify the device serial number in case the label is missing our unreadable.

(224) 3.39. Set Date

(225) W=Day of Week (1-7), Date=Day of Month (1-31), M=Month (1-12), Y=Year (0-99)

(226) 3.40. Get Date

(227) Enables Administrators to validate that the PointSafe has the correct date.

(228) 3.41. Get Time

(229) Enables Administrators to validate that the PointSafe has the correct time.

(230) 3.42. (Command Deleted) Refresh PINs

(231) Enables Administrators to erase all of the pre-populated PIN numbers via an XOR or similar binary operation to shift all of the PIN numbers values.

(232) 3.43. Time Code Start

(233) This is the start time and date that either a LIMITED TIME or ONE TIME PIN code is valid for.

(234) 3.44. Time Code End

(235) This is the end time and date that either a LIMITED TIME or ONE TIME PIN code is valid for.

(236) 3.45. Acknowledge

(237) In some examples, this message provides an acknowledgement that a remote command has been received and/or that the corresponding operation has been performed.

(238) 3.46. Delete Admin PIN

(239) Deletes the PIN set for an administrator.

(240) 4. Design Specifications

(241) 4.1. RF Communications

(242) 4.2. Keysafe

(243) 4.2.1. Mechanical Requirements

(244) The device may be mounted on standard door frames, for example on standard two-inch retail glass storefront doorframes.

(245) 4.2.1.1. Enclosure

(246) The enclosure may be more difficult to get into and remove the key than it would be to break the door to gain entry. The Serial number may be printed on the front of the device.

(247) 4.2.1.2. LCD Display

(248) The LCD may be visible in bright, light but may not have backlighting. The display may be able to show two lines of eight characters each. The display may be monochromatic.

(249) 4.2.1.3. Keypad

(250) The Keypad may have a standard layout 10-key pad with # and * keys. In addition, suitable keys such as “OK”, “up-arrow” and “down-arrow” keys may be included to toggle between commands and acknowledge inputs. The keypad may be remotely connected to the main PCB and mounted on the exterior of the Keysafe. Tampering or removal of the keypad may result in a failsafe condition in which the key pouch cannot be opened.

(251) 4.2.1.4. Cover

(252) The cover may be made from an elastomeric material that may have an integral hinge and provisions for mounting in a suitable location, for example under the Keysafe.

(253) 4.2.1.5. External Power Port

(254) In the event of battery failure, the device may have a “power port” where the user may attach a “Battery Jumper”. The Battery Jumper, in conjunction with the “device master code” and PIN being manually entered via the Keysafe keypad, may allow the device to be externally powered in situations such as emergency and/or battery failure situations.

(255) 4.2.1.6. Battery

(256) For example, a battery may be a lithium ion 123A size battery maximum, for a three year target life of approximately 7,500 to 20,000 locking cycles.

(257) 4.2.1.7. RF Antenna/Transceiver Module

(258) One or more antennas may each be configured in a single physical configuration. Firmware may be used to enable one-way or two-way mode of operation. An RF Transceiver PCB and antennas may be housed in a separate plastic enclosure located at the top of the Keysafe assembly.

(259) 4.2.2. Electrical Requirements

(260) 4.2.2.1. Key Pouch

(261) The key pouch may be able to hold up to two keys simultaneously. The primary key may be tethered to the pouch via a suitable connection, such as a plastic tie wrap or a two-inch, braided, wire leash that may be supplied and applied by the dealer/installer. The braided leash may be crimped by the installer to prevent it from being easily removed from the key pouch. Key sizes up to, for example, a maximum of 2.25”×1.125”×0.090” may be accommodated. Once the PIN code is entered, the key pouch may be free to be removed by hand. It may be desired to not allow the pouch to freely drop to the ground to prevent breakage or loss of keys. The pouch may be able to be returned to the Keysafe without needing to re-enter the code, for example, utilizing a “slam-latch” locking design.

(262) 4.2.2.2. Microprocessor

(263) For example, non-volatile memory with universal asynchronous receiver/transmitter (UART) capability.

(264) 4.2.2.3. Internal Clock

(265) May have capability to reset manually for standalone version and one-way transmitter mode. May have automatic update for two-way transceiver mode, which may have connectivity to a Web

Portal clock.

(266) 4.2.2.4. External Power Jack

(267) May protect circuit against electrical attack, failsafe provisions, and/or may allow reverse hookup.

(268) 4.2.2.5. LCD

(269) For example, two lines of eight characters each, which may be operational within, for example, 0-50 deg C.

(270) 4.2.2.6. Transmitter/Transceiver Provisions

(271) A constant voltage, for example 3.1V, may be supplied by the Keysafe to the transmitter/transceiver.

(272) 4.2.3. Firmware

(273) 4.2.3.1. Master or Registration Code

(274) In some examples, the Keysafe may come pre-programmed with, for example, an 8 digit “device master code”. The user may be required to register the device online, where he may be given the code to write down and protect similar to his PIN number. The Master Code may be required the first time the ADMIN sets up a device, for example directly via the LCD or on the website.

(275) In some implementations, the Keysafe comes pre-programmed with a 7 digit “Registration code”. The user may be required to register the device on line where he will then be given an ADMIN user code for subsequent setup and administration. The REGISTRATION CODE may be required the first time the ADMIN person registers a device via the web portal. The Registration code may be the first number generated by the manufacturing computer program. It may utilize 7 digits instead of the 6 used for PIN numbers.

(276) 4.2.3.2. SP-Serial Number

(277) Each Keysafe may come from the factory with, for example, an electronically embedded seven-digit “serial number” that may be printed both on the front of the device and the installation manual. These serial numbers may be generated “randomly” to prevent sequential numbering that might result in the PIN code generation algorithm creating PIN codes that might work on geographically nearby installations.

(278) 4.2.3.3. PIN Codes

(279) In some implementations, to achieve generation of PIN codes, for example either at the box or via the Web application without any communication between them, a pseudorandom number generator may be implemented in both the Keysafe and the server on which customer data may be stored. Using the serial number of the device as the “seed” or start value may allow PIN numbers to be generated either place that may be validated by the Keysafe.

(280) The unique seed value also may ensure that no two Keysafes will leave the factory with identical PIN numbers. A linear congruential generator (LCG) may be employed, as LCGs are fast and require minimal memory to retain state especially if only a small number of the high order bits are used.

(281) The generator may be defined by the recurrence relation:

(282) $X_{n+1} = (aX_n + c) \bmod m$ where $X_{\text{sub}.n}$ is the sequence of pseudorandom values, and

(283) TABLE-US-00003 m , $0 < m$ the “modulus” a , $0 < a < m$ the “multiplier” c , $0 \leq c < m$ the “increment” $X_{\text{sub}.0}$, $0 \leq X_{\text{sub}.0} < m$ the “seed” or “start value” (for example, the serial number) are integer constants that specify the generator.

(284) Predetermined constants for m , a , and c may be initially used. The values may be considered highly classified information and protected accordingly. Business or development concerns may make it necessary to change them periodically and therefore hidden data cells on the server may be provided to ensure older products in the field may continue to have valid PIN codes generated remotely.

(285) During the product registration process the Keysafe may be turned on, which may trigger the

algorithm to generate, for example, two arrays of PIN Codes, the KEYSAFE PIN codes and the WEB PORTAL KEYSAFE PIN codes. The size of the array may be a function of memory available on the microprocessor.

(286) In some examples, six digit PIN codes for all Keysafes may be created by a random number generator on the manufacturing computer. Approximately ten years' worth of PIN's may be programmed into the Keysafe memory each different from other Keysafe's. Keysafe-RF systems that have PointConnect may have the ability to have their PIN numbers "pushed" down to the Keysafe's via wireless commands. These PIN's may occupy different data registers than the pre-programmed ones. This may ensure that Keysafes that are upgraded will not lose the previously allocated PIN numbers and not disrupt users.

(287) The advantage to the wireless method is that PIN numbers may be chosen and not randomly assigned (providing the number has not been already used).

(288) For non-PointConnect systems the pre-programmed PIN numbers may be unavailable until a system has completed successful registration and some PIN numbers have been checked out via the web portal and entered in via the Keysafe keypad. To ensure that only a minimum of valid numbers are active at a time, the following scenario may be utilized which is shown via the table example below: 1. The Keysafe is pre-programmed with 9,000 valid PIN numbers (41 shown in example), only 30 of which are ACTIVE. 2. An administrator or manager checks out 4 PIN numbers and gives them to employees. 3. The employee given the 3rd PIN number uses it on Thursday a. Since his PIN was in the 3rd data register and we want to keep a buffer of 30 Valid PIN codes ahead of him this triggers the Keysafe to activate 3 more PIN numbers 4. This same employee and another with a PIN number in data register 1 uses it the next day a. Since neither PIN was in a higher data register no additional PIN's are made ACTIVE 5. On Saturday another employee uses the PIN code that is mapped to the 4th data register a. Since his PIN was in the 4th data register and we want to keep a buffer of 30 Valid PIN codes ahead of him this triggers the Keysafe to activate 1 more PIN number

(289) TABLE-US-00004

Wed	Mon	PIN's	Thu	Fri	Sat	User	PIN	Before	Tue	Checked	PIN
PIN's	Data	Registration	Registration	out	By	Used	at	Used	at	Register	User
Completed	Completed	MANAGER	PointSafe	PointSafe	PointSafe	1	123456	INACTIVE	+	#	**
#	2	123457	INACTIVE	+	#	*	#	4	123459	INACTIVE	+
#	5	123460	INACTIVE	+	#	***	5	123460	INACTIVE	6	123461
INACTIVE	7	123462	INACTIVE	8	123463	INACTIVE	9	123464	INACTIVE	10	123465
INACTIVE	11	123466	INACTIVE	12	123467	INACTIVE	13	123468	INACTIVE	14	123469
INACTIVE	15	123470	INACTIVE	16	123471	INACTIVE	17	123472	INACTIVE	18	123473
INACTIVE	19	123474	INACTIVE	20	123475	INACTIVE	21	123476	INACTIVE	22	123477
INACTIVE	23	123478	INACTIVE	24	123479	INACTIVE	25	123480	INACTIVE	26	123481
INACTIVE	27	123482	INACTIVE	28	123483	INACTIVE	29	123484	INACTIVE	30	123485
INACTIVE	31	123486	INACTIVE	INACTIVE	INACTIVE	32	123487	INACTIVE	INACTIVE	INACTIVE	33
INACTIVE	34	123489	INACTIVE	INACTIVE	INACTIVE	35	123490	INACTIVE	INACTIVE	INACTIVE	36
INACTIVE	37	123491	INACTIVE	INACTIVE	INACTIVE	38	123492	INACTIVE	INACTIVE	INACTIVE	39
INACTIVE	40	123493	INACTIVE	INACTIVE	INACTIVE	41	123494	INACTIVE	INACTIVE	INACTIVE	42
INACTIVE	43	123495	INACTIVE	INACTIVE	INACTIVE	44	123496	INACTIVE	INACTIVE	INACTIVE	45
INACTIVE	46	123497	INACTIVE	INACTIVE	INACTIVE	47	123498	INACTIVE	INACTIVE	INACTIVE	48
INACTIVE	49	123499	INACTIVE	INACTIVE	INACTIVE	50	123500	INACTIVE	INACTIVE	INACTIVE	51

* This causes 3 additional PIN numbers to become ACTIVE ** Since this is earlier in the data register than first PIN used it does not increase the number of PIN's that are ACTIVE *** Since this later in the data register it does increase the number of ACTIVE PIN's by one + indicates the PIN was used that day # indicates the PIN was checked out from the web portal that day

4.2.3.3.1. ADMIN PIN Code

(290) Only one ADMIN PIN Code may be issued or active at one time. It may only be changed using the CHANGE ADMIN PIN command and may not be deleted by the DELETE PIN command. A predetermined number of valid ADMIN PIN codes may be pre-programmed.

(291) 4.2.3.3.2. MANAGER PIN Codes

(292) For example, 100 to 500 MANAGER PIN codes may be pre-programmed, with five being active. These users may, for example, create PIN codes, enroll transmitters, reset the clock, and “read” the Keysafe.

(293) 4.2.3.3.3. USER PIN Codes

(294) For example, 1,000 to 2,000 regular user PIN codes may be pre-programmed into the device, with thirty being active. The USER PIN Codes may be assigned by either the ADMIN user or MANAGER level PIN users.

(295) 4.2.3.3.4. VENDOR EMPLOYEE Codes

(296) VENDOR EMPLOYEE PIN codes differ from other PIN codes in that they cannot be programmed into the Keysafe directly, but only through the web portal and “pushed” to the Keysafe(s) via the two-way transceiver. They also differ in that they may be valid on multiple Keysafes. The six digit VENDOR EMPLOYEE PIN can be selected or randomly generated. The back end database may need to be searched to ensure the pushed PIN is unique on all of the Keysafes selected to receive this new PIN.

(297) Next wireless commands may be broadcast to all of the boxes enabling the new VENDOR EMPLOYEE PIN. The vendor employee may be emailed or otherwise notified that the PIN is now active.

(298) 4.2.3.3.5. ONE TIME Access PIN Codes

(299) For example, 25 to 1500 ONE TIME Access PIN codes may be pre-programmed into the device, with twenty being active. The ONE TIME Access PIN codes may be assigned by either the ADMIN user or MANAGER level PIN users.

(300) 4.2.3.3.6. LIMITED TIME Access PIN Codes

(301) For example, multiple four-digit PIN Codes may be generated via website and may be decrypted by Keysafe for validity. 5000 LIMITED TIME PIN codes may be pre-programmed, with thirty being active. The LIMITED TIME PIN codes may be assigned by either the ADMIN user or MANAGER level PIN users.

(302) 4.2.3.4. TIME CODES

(303) A TIME CODE may be generated by the web portal for use with ONE TIME and LIMITED TIME access PIN codes. For SP-Web level users this may be necessary to communicate, for example, the single day of the year a ONE TIME code is good for as well as the start date, start time, and end date for a LIMITED TIME access PIN code. For example, this may be done by encrypting the following information at the web portal and decrypting it on the box in much the same manner a PIN code is generated.

(304) There are 1-365 days (3 digits) for a start date, 1-99 days (2 digits) for duration of limited access and 1-24 (2 digits) possible hours in the start day. For example, a Limited Time access code could be created that allowed entry on January 15th at 10:00 AM and lasted through January 19th. This could be represented by the number 015-04-10. A simple encryption algorithm may be utilized, which may, for example, add another digit for this purpose.

(305) 4.2.3.5. Keypad Operations

(306) The SP-Access solution may be locally operated and may function as a standalone device. Some or all levels of the integrated access and reporting system may have the ability to be “locally programmed” for example via the keypad. The following local programming and/or information retrieval Options may be available in the SP Access solution.

(307) 4.3. Web Portal

(308) 4.3.1. Web User Operations

(309) 4.3.1.1. Keysafe DEVICE Registration

(310) The purchaser of a Keysafe may register each device by “Serial Number” and “Registration Number” on the Web Portal. The purpose of this registration is to ensure both customer and device location information is captured before a unit is able to be used in the field. The Registration Number may be packaged in a tamper proof envelope to ensure only the end user can learn the pre-programmed PIN numbers and thereby prevent someone in the distribution chain from accessing this information.

(311) 4.3.1.2. Web SERVICES Registration

(312) The SP-Web may include a Keysafe that may be mechanically and electronically identical to the SP-Access device. The SP-Web may provide for the optional subscription to web applications via the Web Portal.

(313) 4.3.1.3. ONE TIME Access Code Generation

(314) For example, a six-digit PIN may be generated that may enable entry on a single day. An option to email or text the PIN along with information, such as the day it is valid and physical location of the Keysafe, may be offered on the website.

(315) 4.3.1.4. LIMITED TIME Access Code Generation

(316) 4.3.1.5. Add-Delete VENDOR Code

(317) 4.3.1.6. Add-Delete User PIN Code

(318) 4.3.2. SP-Data Base/National Operations Center (NOC)

(319) 4.3.2.1. Device Info

(320) 4.3.2.1.1. Keysafe Serial Number

(321) May need to link valid PIN's and/or Vendor Codes to the device

(322) 4.3.2.1.2. Keysafe Master or Registration Code

(323) 4.3.2.1.3. Keysafe Registration (ADMIN) PIN

(324) 4.3.2.1.4. Keysafe Physical Address (location)

(325) 4.3.2.1.5. Keysafe Location Identifier

(326) This may allow customers to identify individual units for installations with, for example, more than one Keysafe. For example, “Burger Restaurant North” that has multiple locations.

(327) 4.3.2.1.6. Keysafe Location Phone

(328) 4.3.2.1.7. Keysafe Manager Phone

(329) 4.3.2.1.8. Services Level

(330) 4.3.2.2. User Info

(331) 4.3.2.2.1. User Name

(332) 4.3.2.2.2. User Address

(333) 4.3.2.2.3. User Phone Number

(334) 4.3.2.2.4. User PIN

(335) 4.3.2.2.5. ONE TIME PIN (Y/N)

(336) 4.3.2.2.6. One Time PIN MONTH

(337) 4.3.2.2.7. One Time PIN DAY

(338) 4.3.2.2.8. One Time PIN YEAR

(339) 4.3.2.2.9. LIMITED TIME PIN (Y/N)

(340) 4.3.2.2.10. Limited Time PIN START

(341) 4.3.2.2.11. Limited Time PIN END

(342) 4.3.2.2.12. User Authorization Level

(343) 4.3.2.2.12.1. Admin

(344) 4.3.2.2.12.2. Manager

(345) 4.3.2.2.12.3. User

(346) 4.3.2.2.12.4. Vendor

(347) 4.3.2.2.13. Access Times

(348) 4.3.2.2.14. VENDOR Number

(349) 4.3.2.3. Vendor Info

- (350) 4.3.2.3.1. Company Name
- (351) 4.3.2.3.2. Company Address
- (352) 4.3.2.3.3. Company Phone
- (353) 4.3.2.3.4. Company Contact
- (354) 4.3.2.3.5. Vendor Code
- (355) May set value to zero if not a vendor
- (356) 4.3.2.4. History Info
- (357) 4.3.2.4.1. Valid PIN ACCESS Event (Keysafe, PIN, date, time)
- (358) 4.3.2.4.2. Valid VENDOR ACCESS Event (Keysafe, Vendor Code, Date, Time)
- (359) 4.3.3. Reports
- (360) 4.3.3.1.1. Access history (90 days active)
- (361) 4.3.3.1.1.1. By Keysafe (location)
- (362) 4.3.3.1.1.2. By User/PIN, date & time
- (363) 4.3.3.1.1.3. By Vendor/Company, date & time
- (364) 4.3.3.1.2. Programming Activity
- (365) 4.3.3.1.2.1. By user-PIN
- (366) access hours-days keysafe authorizations (PIN added to potentially multiple devices)
- 4.3.3.1.2.2. By keybox serial number PIN #'s added & deleted Vendor codes added & deleted

4.4. Battery Jumper

4.4.1. Mechanical Requirements

(367) The device may contain batteries, such as a single AA disposable battery, that may be user replaceable with no or simple tools (e.g., coin, screwdriver). An injection molded case, housing two custom electrical contacts, a circuit board, and battery may be included. The ID of the housing may identify it with the Keysafe with appropriate external markings and labels.

(368) 4.4.2. Electronic Requirements

(369) When the two electrical contacts of the device are connected to the corresponding contacts of the Keysafe it may wake up the motherboard and trigger it to send a query to the display asking for a valid ADMIN or MANAGER code. If both are entered successfully, the key pouch may release exposing the Keysafe battery door. The battery may then be replaced for normal operation.

(370) 4.4.3. Environmental Requirements

(371) May survive intact and function after, for example, a four-foot drop onto concrete from any orientation.

(372) 4.4.4. Regulatory Requirements

(373) 4.5. Communications Gateway

(374) 4.5.1. Mechanical Requirements

(375) For example, an injection molded case, housing a Two Way Transceiver Module, GPRS printed circuit board (GSM PCB), DC transformer, battery backup (24 hours), key switch, and/or contact output for direct wire shunting. The Gateway may also have a terminal block to accept a pair of hardwired leads from the “programmable output” of the panel. Another two terminal block and relay may allow the control of auxiliary devices such as magnetic door latches. Two external antennas may be provided that mount at right angles to each other and protrude from the case. The antennas may mount to the PCB via a terminal block and exposed lead. A second set of internal antennas for 900 Mhz communications may be provided. The ID of the housing may identify it with the Keysafe with appropriate external markings and labels.

(376) 4.5.2. Electronic Requirements

(377) The enclosure may be wall mounted and powered by an external transformer 120 VAC to 9 VAC. A 1.2 Amp-hour battery may be included for backup.

(378) A six position terminal block with: Two positions for AUX: 0.5 Amp, used for controlling magnetic locks and other auxiliary devices. This may require a latching key switch to keep a lock open all day. Two positions for ALARM: 0.5 Amp, used for arming and disarming the panel. Two

positions for INPUT: Input Low: both positions at same voltage, Input HIGH: position 2 5 to 14 volts above position 1, input will draw about 5 mA (labeled INPUT- and INPUT+ respectively)
(379) Power may be provided to the GPRS printed circuit board via a 22 pin connector.

(380) 4.5.3. Environmental Requirements

(381) Operation Temperature Range (e.g., 0 to 120 degrees Fahrenheit)

(382) 4.5.4. Regulatory Requirements

(383) 4.6. Two Way Transceiver

(384) May utilize, for example, 9600 Baud, Communications Protocol Modbus.

(385) 5. Installation

(386) Installation may be able to be achieved without substantial modification of doorframe. Lag screws and/or bolts may be used to secure the device to the mounting surface. If mounted on a retail door front a “through door” mounting approach may be used. Mounting holes may be drilled through the doorframe and nuts/bolts may be used to secure the device to the door. A plastic cover may be provided for coverage of the nuts/bolts on the inside frame of the door.

(387) 6. Documentation

(388) 6.1. Quick Start Reference

(389) Multiple quick-start reference manuals may be created. Alternatively, a single generic document may suffice. As much material as possible may be made available via a website, for example to minimize printing costs and ensure updated materials are continually available.

(390) 6.1.1. Device Specific Information

(391) The following information may be provided in documentation form: Keysafe Serial Number Registration PIN A blank spot may be provided for a customer to write in his “device master code” after he registers on the website. He may be instructed to protect this number and understand that it may be required the first time he programs his device.

7. Exemplary Environmental Performance Requirements

Shipping and Storage

(392) Temperature Range: -10° to 60° C. (14° to 140° F.)

(393) Drop resistance: Internal product may not suffer damage from drops of 90 cm (36 in.) onto bare concrete on any exposed face or corner.

(394) Vibration: Internal packaging may prevent abrasion damage to product for typical transport frequencies and intensities.

(395) System Requirements

(396) Temperature Range: 0° to 50° C. (32° to 122° F.)

(397) Ultraviolet Stability: May not fade more than typical outdoor engineered products when exposed to sun for 5 years.

(398) Chemical Resistance: Resist likely cleansers and chemicals used on commercial store fronts.

(399) Water/Dust Resistance: IP54, limited dust ingress and protected from water spray from any direction.

(400) Regulatory. FCC Part 15, PTCRB Certification

(401) As described throughout this disclosure, the integrated access management and reporting system may include one or more of the following capabilities.

(402) False alarms are a growing and costly issue in businesses and residential locations. False alarms typically result when an alarm has been turned on, a door is opened activating the alarm, and the user fails to enter a valid security panel PIN. A situation may also occur where the person accessing the property is unaware of the alarm or does not know that the alarm is turned on and simply fails to get to the keypad prior to the alarm being activated.

(403) The integrated access management and reporting system may enable the security keypad to be moved from its normal interior installation to an exterior location. This means that false alarms may be eliminated because the user cannot gain access to the building without first entering a valid PIN and gaining access to the mechanical key. In businesses/residences that use mechanical locking

systems, the alarm system may be “activated” when the primary access door has been opened. Employees, vendors or homeowners may open the door with a mechanical key and then may proceed to the alarm keypad to disarm/turn off the system prior to the alarm activating and transmission of an “alarm event” to the central monitoring station.

(404) The Access-Web-Security system may uniquely provide an integrated electronic key storage device that also functions as a wireless security keypad. This integration may allow the alarm system to be turned upon a valid access to the electronic key safe.

(405) The key safe, a ruggedized metal locking vault with an integrated electronic display and keypad may include an RF wireless transmitter. The transmitter may be manufactured to transmit at frequencies and with protocols that allow it to “speak the RF language” of a variety of electronic security control panels.

(406) When a key safe is opened using a valid PIN and depresses the security option key (e.g., key to turn off alarm-“#” key to turn on alarm), the key safes RF transmitter may send an instruction signal (turn on-turn off) to the existing alarm panel. The alarm panel may receive the command via its RF transceiver and performs the requested command.

(407) The integrated access management and reporting system may enable immediate transmission of access information via on-board RF communication to the communications gateway. The communications gateway may include a GPRS radio or other device that may provide for wireless transmission of the access info to the data center. The integrated access management and reporting system may thus have the capability to electronically store a key, enable access to that key via an electronic keypad and PIN number, and then immediately transmit that access data via an on-board RF transmitter to a GPRS based communication gateway. The system may include a completely self-contained access/key control system requiring no external power or physical network connectivity.

(408) The on-board two-way RF transceiver and the cellular communications capability of the communications gateway may provide for remote programming of the key safe. This capability may allow the owner/manager of a device to change the access authorizations in a stand-alone electronic access device without the need to physically program the device through its electronic keypad. For instance, the owner of multiple fast food restaurants may authorize a vendor to deliver food products after business hours on an unattended basis. The owner could assign this company a “vendor code” to gain access to the key safe at each restaurant location, if the owner were to terminate his contract with this supplier, he could delete the vendor code “in each key safe using the web-based application with RF & cellular connectivity function.

(409) One issue that may be found with access control systems is the potential misuse of an access badge, or access code. Unless the system has biometric capabilities, it cannot determine if the user is valid if they are in possession of a valid badge and/or access code.

(410) The integrated access management and reporting system may provide a method for validating, after the fact, that a valid employee or vendor accessed a location. The key safe may activate a video surveillance camera that is focused on the primary location point.

(411) The key safe, a ruggedized metal locking vault with an integrated electronic display and keypad may include an RF wireless transmitter. The transmitter may be manufactured to transmit at frequencies and with protocols that allow it to “speak the RF language” of a variety of electronic security control panels. When a key safe is opened using a valid PIN, the RF transmitter may send an instruction signal to activate a specific security video camera.

(412) As shown in FIG. 6, the key pad on an exemplary Key safe may be used to perform functions, such as one or more of the following: (1) automatically turn on a video camera to record comings and goings through a door, (2) act as a keypad for a remotely wired magnetic door latch, and (3) control virtually any security access control device that may be simply turned on or off. By performing functions such as these, a battery-powered Key safe may control hardwired devices that may not rely upon the Key safe for power.

(413) FIG. 7 illustrates an example process **700** for managing an electronic lockbox or key safe. The operations of the process **700** are described generally as being performed by the system **100**. The operations of the process **700** may be performed by one of the components of the system **100** or may be performed by any combination of the components of the system **100**. The operations of the process **700** also may be performed by one of the components of the systems shown in FIGS. 2-6 or may be performed by any combination of the components of the systems shown in FIGS. 2-6. In some implementations, operations of the process **700** may be performed by one or more processors included in one or more electronic devices.

(414) The system **100** receives, at a remote location, input to program a new passcode for a key safe (e.g., an electronic lockbox) (**710**). For example, the server **110** may receive a request from an owner of the building **130** to add a new passcode to the lockbox **132**. In this example, the new passcode may be a new passcode that has indefinite validity, a new passcode that is valid for a single use (e.g., a one-time use passcode), or a new passcode that is valid for a particular time period (e.g., a new passcode that is valid for the next two weeks or a new passcode that is valid indefinitely, but only on Sundays between the hours of 6 PM to 11 PM).

(415) The system **100** sends, from the remote location, the new passcode (**720**). For instance, the server **110** sends the new passcode to the lockbox gateway **134** over the long-range communication protocol. The server **110** also may send any restriction information on use of the new passcode, such as a limit on the number of uses that the new passcode is valid or a limit on the time period for which the new passcode is valid.

(416) The system **100** causes storage of the new passcode such that entry of the new passcode opens the key safe (**730**). For instance, when the lockbox **132** performs decision making operations, the lockbox gateway **134** may send the new passcode to the lockbox **132** over a short-range communication protocol to have the lockbox **132** store the new passcode for comparison against passcodes entered at the lockbox **132**. When the lockbox gateway **134** performs decision making operations, the lockbox gateway **134** may store the new passcode for comparison against passcodes sent from the lockbox **132**. The system **100** may cause storage of any restriction information with the new passcode, so the restriction on use can be followed.

(417) After storage of the new passcode, the system **100** opens the key safe based on entry of the new passcode (**740**). For instance, when the lockbox **132** performs decision making operations, the lockbox **132** compares an inputted passcode with the new passcode stored at the lockbox **132**, determines that the inputted passcode matches the new passcode based on the comparison, and opens the lockbox **132** based on the determination that the inputted passcode matches the new passcode. When the lockbox gateway **134** performs decision making operations, the lockbox gateway **134** receives an inputted passcode from the lockbox **132**, compares the inputted passcode with the new passcode stored at the lockbox gateway **134**, determines that the inputted passcode matches the new passcode based on the comparison, and sends a command to the lockbox **132** to open the lockbox **132** based on the determination that the inputted passcode matches the new passcode. In determining whether to open the lockbox **132**, the system **100** may consider any restriction information stored with the new passcode to ensure that the new passcode is valid at a time when the new passcode is being input.

(418) The system **100** sends, to the remote location, a report that indicates the key safe has been opened and that indicates the new passcode used to open the key safe (**750**). For example, when the lockbox **132** performs decision making operations, the lockbox **132** sends a report message to the lockbox gateway **134** to indicate that the lockbox **132** has been opened using the new passcode at a particular time. In this example, the lockbox gateway **134** relays the report message to the server **110**. When the lockbox gateway **134** performs decision making operations, the lockbox gateway **134** sends a report message to the lockbox gateway **134** to indicate that the lockbox **132** has been opened using the new passcode at a particular time.

(419) The system **100** handles access logging and reporting based on the report (**760**). For instance,

the server **110** stores data indicating that the lockbox **132** has been opened using the new passcode at the particular time based on the report message. The server **110** may log the access to the lockbox **132** and generate various reports that show access history of the lockbox **132**. The server **110** may generate reports for any of the lockboxes managed by the server **110** and can produce reports for groups of lockboxes operated by a single entity. The server **110** also may generate reports for accesses to lockboxes made by one or all of a particular vendor's employees.

(420) The server **110** further may compare the reported access to a set of one or more alert rules. The alert rules may define when an entity that operates the lockbox **132** wishes to receive alerts based on the lockbox **132** being accessed. For instance, based on the alert rules, the server **110** may alert the entity every time the lockbox **132** is accessed, when the lockbox **132** is accessed between the hours of 12 AM to 5 AM, when the lockbox **132** is accessed three or more times within an hour time period, etc. The server **110** may alert the entity by sending the entity an electronic message (e.g., electronic mail message, text message, etc.), by posting an alert to a web page accessible to the entity, or by any other suitable alert technology.

(421) The server **110** also may alert the entity when an access to the lockbox **132** is expected, but does not occur. For instance, the alert rules may indicate that the lockbox **132** is expected to be accessed between 9 PM and 11 PM on Mondays for a recurring delivery and between 9 AM and 10 AM every day for store opening. When the server **110** determines that a report of an access to the lockbox **132** has not been received between 9 PM and 11 PM on a Monday or between 9 AM and 10 AM any day, the server **110** may alert the entity that an expected access has not occurred. This may assist the entity in more quickly learning of issues relevant to operation of the building and addressing the issues.

(422) FIGS. **8A-8C** illustrate an example of remotely programming passcodes to electronic lockboxes. As shown in FIG. **8A**, a lockbox server **810** maintains an access log **812** and a database of valid passcodes that includes stored passcodes **814** for a lockbox **830** located at an external door of a building **820**. The lockbox **830** has a key pad input device **832** that receives numeric character input and stored passcodes **834** for the lockbox **830**. The stored passcodes **834** match the stored passcodes **814** because the lockbox server **810** keeps its passcode database synchronized with valid passcodes stored at each electronic lockbox the lockbox server **810** manages. In the example shown in FIG. **8A**, a user has entered the passcode "3311981." The lockbox **830** denies the entered passcode because it does not match any of the stored passcodes **834**. In response to denying the entered passcode, the lockbox **830** outputs an access denied message and sends a report of the failed access attempt to a lockbox gateway **840**, which relays the report of the failed access attempt to the lockbox server **810** for logging in the access log **812**.

(423) In the example shown in FIG. **8B**, a new passcode interface **850** is displayed to an authorized user (e.g., owner of the building **820**) of the lockbox **830**. The new passcode interface **850** may be part of a web page provided by the lockbox server **810** and the authorized user may be viewing the new passcode interface **850** on a personal electronic device (e.g., smartphone, personal computer, etc.) that is remote from the lockbox server **810**. In this example, the authorized user enters "3311981" as a new passcode to add to the lockbox **830** and presses an enter button to submit the new passcode to the lockbox server **810**. As shown, when the lockbox server **810** receives the new passcode, the lockbox server **810** adds the new passcode to the stored passcodes **814** for the lockbox **830** in the database of valid passcodes and also sends the new passcode to the lockbox gateway **840**. The lockbox gateway **840** sends the new passcode to the lockbox **830** and the lockbox **830** adds the new passcode to the stored passcodes **834**.

(424) In the example shown in FIG. **8C**, a user has entered the passcode "3311981" at a second time that is after storage of the new passcode. The lockbox **830** accepts the entered passcode because it matches the new passcode added to the stored passcodes **834** in the example shown in FIG. **8B**. In response to accepting the entered passcode, the lockbox **830** outputs an access granted message, provides access to the key secured by the lockbox **830**, and sends a report of the access to

the lockbox gateway **840**, which relays the report of the access to the lockbox server **810** for logging in the access log **812**.

(425) FIG. **9** illustrates an example process **900** for managing an electronic lockbox or key safe. The operations of the process **900** are described generally as being performed by the system **100**. The operations of the process **900** may be performed by one of the components of the system **100** or may be performed by any combination of the components of the system **100**. The operations of the process **900** also may be performed by one of the components of the systems shown in FIGS. **2-6** or may be performed by any combination of the components of the systems shown in FIGS. **2-6**. In some implementations, operations of the process **900** may be performed by one or more processors included in one or more electronic devices.

(426) The system **100** detects that a proper passcode has been entered through a user input device to open a key safe (**910**). For instance, the server **110** determines that a valid passcode has been entered at the lockbox **132** based on communications received from the lockbox gateway **134**. In another example, the lockbox gateway **144** determines that a valid passcode has been entered at the lockbox **142** based on communications received from the lockbox **142**.

(427) The system **100** controls a security system to perform an operation related to a valid key safe opening based on the detection that the proper passcode has been entered through the user input device to open the key safe (**920**). For instance, the server **110** may control the alarm panel **136** to perform an operation related to a valid opening of the lockbox **132** based on the determination that a valid passcode has been entered at the lockbox **132**. In another example, the lockbox gateway **144** may control the alarm panel **146** to perform an operation related to a valid opening of the lockbox **142** based on the determination that a valid passcode has been entered at the lockbox **142**.

(428) The system **100** may control the security system to perform any type of operation that may be desired. For instance, the system **100** may disarm the security system, turn on a light within the building, and/or begin operation of a video camera located at the building based on a valid opening of a lockbox.

(429) FIGS. **10A** and **10B** illustrate an example of controlling a security system based on input from an electronic lockbox. As shown in FIG. **10A**, a user **1020** has approached a building **1010** that has an electronic lockbox **1030** located at an external door to the building **1010**. The lockbox **1030** is in a closed state that secures a physical key to the building **1010** in the example shown in FIG. **10A**. The building **1010** also has a lockbox gateway **1040** located within the building **1010**, an alarm panel **1050** located within the building **1010**, and a lighting device **1060** located within the building **1010**. In the example shown in FIG. **10A**, the alarm panel **1050** is in an armed state and the lighting device **1060** is in an off state.

(430) In the example shown in FIG. **10B**, the user **1020** has entered a proper passcode to the lockbox **1030** and retrieved a physical key secured by the lockbox **1030**. Based on the entry of the proper passcode, the lockbox **1030** sends a message to the lockbox gateway **1040** to indicate the entry of the proper passcode. The lockbox gateway **1040** receives the message and sends a control command to the alarm panel **1050**. The control command instructs the alarm panel **1050** to disarm the security system and also turn on the lighting device **1060**. As shown, based on the control command, the alarm panel **1050** disarms the security system and turns on the lighting device **1060**. Accordingly, the convenience of the user **1020** may be enhanced because the user **1020** does not have to disarm the security system or find a light switch when entering the building **1010**. This may be particularly useful when the user **1020** is unfamiliar with the building **1010**, such as a new driver of a delivery company.

(431) FIG. **11** illustrates an example process **1100** for managing an electronic lockbox or key safe. The operations of the process **1100** are described generally as being performed by the system **100**. The operations of the process **1100** may be performed by one of the components of the system **100** or may be performed by any combination of the components of the system **100**. The operations of the process **1100** also may be performed by one of the components of the systems shown in FIGS.

2-6 or may be performed by any combination of the components of the systems shown in FIGS. 2-6. In some implementations, operations of the process **1100** may be performed by one or more processors included in one or more electronic devices.

(432) The system **100** receives a keysafe access report (**1110**). For instance, the server **110** may receive a report message indicating that the lockbox **132** or the lockbox **142** has been accessed.

(433) The system **100** links data from a security system with the keysafe access report (**1120**). For example, the server **110** also receives alarm data from the alarm panel **136** or the alarm panel **146** around the time of the access of the lockbox **132** or the lockbox **142**. In this example, the server **110** detects a temporal relationship between the access of the lockbox and the received alarm data and links the temporally related alarm data with the access of the lockbox. The server **110** may detect a temporal relationship when the alarm data covers a time period that is within a first threshold amount of time prior to the access of the lockbox and when the alarm data covers a time period that is within a second threshold amount of time after the access of the lockbox. The first threshold amount of time may be less than the second threshold amount of time. Also, the server **110** may link alarm data that is outside of the first threshold amount of time or the second threshold amount of time when the alarm data is close enough to other linked alarm data such that it reflects continuous activity.

(434) The system **100** analyzes the data from the security system linked with the keysafe access report (**1130**). For example, the server **110** compares the linked alarm data with a set of one or more access rules that define alarm events that are expected when the building is properly accessed using the lockbox. In this example, the access rules may define permitted areas of access and/or off-limit areas of access within the building and the server **110** may determine whether a person entering the building using the lockbox stays only within permitted areas and/or has entered an off-limit area.

(435) The system **100** verifies whether access using the keysafe was proper based on the analysis (**1140**). For instance, the server **110** may determine whether the person entering the building using the lockbox has used the building properly based on the comparison of the alarm data to the access rules. The server **110** may verify that the access was proper when the alarm data indicates that the person only entered permitted areas within the building. The server **110** may determine that the access was improper when the alarm data indicates that the person entered an off-limit area within the building.

(436) FIG. **12** illustrates an example access rule and example access records. In the example shown in FIG. **12**, an access rule **1210** defines that, when the building is properly accessed using a keysafe or lockbox, certain actions are expected to be detected by the security system for the building. As shown, the access rule **1210** defines the expected actions as opening and closing of the main door, motion in the hallway, and motion in the kitchen. The access rule **1210** is compared against access records **1220**, **1230**, and **1240** that include keysafe access data and linked security system data for three different accesses of the building using the keysafe.

(437) The access record **1220** includes keysafe data that shows that the keysafe was opened using passcode "4567123" at 10:15 PM and closed at 10:30 PM. The access record **1220** also includes linked security system data for events detected by the security system between the open time of the keysafe and the closed time of the keysafe. The access record **1220** further includes an image taken from an external image sensor located proximate to the keysafe and an image taken from an internal image sensor located within the building. To verify whether the access corresponding to the access record **1220** was proper, the security system data in the access record **1220** is compared to the access rule **1210**. In this case, the comparison reveals that the access was proper because all of the security system events are included in the expected actions defined by the access rule **1210**. The system also may send the images in the access record **1220** to an authorized user to verify whether the person accessing the building was actually the person associated with the passcode. The system further may perform facial recognition processing of the images in the access record **1220** to verify whether the person accessing the building was actually the person associated with the passcode.

(438) The access record **1230** includes key safe data that shows that the key safe was opened using passcode “1352469” at 2:15 PM and closed at 4:30 PM. The access record **1230** does not include any linked security system data, but does include an image taken from an external image sensor located proximate to the key safe. To verify whether the access corresponding to the access record **1230** was proper, the security system data in the access record **1230** is compared to the access rule **1210**. In this case, the comparison reveals that the access was improper because none of the expected actions defined by the access rule **1210** were detected by the security system. The system may send an alert related to the improper access. The alert may indicate that the key safe was accessed, but the building was never entered using the key. The system also may send the image in the access record **1230** to an authorized user, so the authorized user can see who engaged in the improper access.

(439) The access record **1240** includes key safe data that shows that the key safe was opened using passcode “9876543” at 11:00 PM and closed at 12:00 AM. The access record **1240** also includes linked security system data for events detected by the security system between the open time of the key safe and the closed time of the key safe. The access record **1240** further includes an image taken from an external image sensor located proximate to the key safe and an image taken from an internal image sensor located within the building. To verify whether the access corresponding to the access record **1240** was proper, the security system data in the access record **1240** is compared to the access rule **1210**. In this case, the comparison reveals that the access was improper because some of the security system events are not included in the expected actions defined by the access rule **1210**. The system may send an alert related to the improper access. The alert may indicate that the person entered areas in the building that were not permitted. The system also may send the images in the access record **1240** to an authorized user, so the authorized user can see who engaged in the improper access.

(440) FIG. **13** illustrates an example process **1300** for managing an electronic lockbox or key safe. The operations of the process **1300** are described generally as being performed by the system **100**. The operations of the process **1300** may be performed by one of the components of the system **100** or may be performed by any combination of the components of the system **100**. The operations of the process **1300** also may be performed by one of the components of the systems shown in FIGS. 2-6 or may be performed by any combination of the components of the systems shown in FIGS. 2-6. In some implementations, operations of the process **1300** may be performed by one or more processors included in one or more electronic devices.

(441) The system **100** receives a request for managing passcodes (**1310**). For instance, the server **110** may receive a request from an owner of the building **130** or an authorized vendor to add a new passcode to the lockboxes **132** and **142**, delete a passcode from the lockboxes **132** and **142**, or change a passcode at the lockboxes **132** and **142**. The request also may be a request to delete all passcodes associated with a particular vendor or to add a new vendor employee passcode to all key safes or lockboxes associated with a particular vendor.

(442) The system **100** determines that the request relates to an entity that has multiple key safes for multiple buildings (**1320**). For example, the server **110** may determine that the request is associated with an entity that operates multiple key safes for multiple buildings. In this example, the entity may be a business owner that operates a chain of multiple businesses at multiple locations (e.g., a chain of restaurants or retail stores).

(443) The system **100** determines, from among multiple users associated with the multiple key safes, a user related to the request (**1330**). For instance, the server **110** may determine that the request is associated with a particular vendor or service provider from among a group of authorized vendors or service providers. In another example, the server **110** may determine that the request is associated with a particular employee from among a group of authorized employees.

(444) The system **100** identifies, from among the multiple key safes, a subset of the multiple key safes associated with the user (**1340**). For example, the server **110** identifies the key safes that

are associated with the identified user. In this example, the identified keysafes represent a subset of the multiple keysafes because the identified user is associated with some, but not all of the multiple keysafes of the entity. This may occur when the entity uses different vendors or service providers to service different of the multiple buildings.

(445) The system **100** performs an operation directed to managing passcodes for the identified subset of the multiple keysafes based on the request (**1350**). For instance, the system **110** may add a new passcode to all of the identified subset of the multiple keysafes, delete a passcode from all of the identified subset of the multiple keysafes, or change a passcode at all of the identified subset of the multiple keysafes. In this regard, the system **100** may allow owners to quickly and easily change vendors or service providers used to service their buildings and also may allow vendors or service providers to quickly and easily change employees the vendors or service providers use to service the buildings.

(446) FIGS. **14A-14C** illustrate examples of managing multiple electronic lockboxes. As shown in FIG. **14A**, a lockbox server **1410** includes a master passcode database that is synchronized with passcode databases at each of the lockboxes serviced by the lockbox server **1410**. In the example shown in FIG. **14A**, passcode databases **1470**, **1472**, **1474**, and **1476** at each of four lockboxes are shown for brevity, but many more passcode databases may exist. The lockbox server **1410** may receive passcode management requests from many sources. As shown, a first owner may submit passcode management requests using interface **1420**, a first vendor may submit passcode management requests using interface **1430**, a second vendor may submit passcode management requests using interface **1440**, a third vendor may submit passcode management requests using interface **1450**, and a fourth vendor may submit passcode management requests using interface **1460**. In this example, the owner may have permission to manage passcodes for all of the lockboxes associated with the owner and the vendors may have permission to manage passcodes for all of the lockboxes associated with the vendors to the extent the owner has given the vendor permission to manage passcodes.

(447) The passcode databases **1470**, **1472**, **1474**, and **1476** show a present state of passcode data at each of the lockboxes. As shown, the passcode database **1470** has passcode data for the first owner and passcode data for the first vendor, third vendor, and fourth vendor. The passcode database **1472** has passcode data for the first owner and passcode data for the second vendor and fourth vendor. The passcode database **1474** has passcode data for the first owner and passcode data for the first vendor and third vendor. The passcode database **1476** has passcode data for the first owner and passcode data for the second vendor and fourth vendor.

(448) In the example shown in FIG. **14B**, the fourth vendor has submitted a request through the interface **1460** to add a new passcode for a second employee. In this example, the lockbox server **1410** determines that the request is related to the fourth vendor and that the fourth vendor is associated with the passcode databases **1470**, **1472**, and **1476**, but not the passcode database **1474**. Based on this determination, the lockbox server **1410** sends the new passcode for the second employee to the passcode databases **1470**, **1472**, and **1476**, but not the passcode database **1474**. As shown, the passcode databases **1470**, **1472**, and **1476** have been updated to include the new passcode for the second employee.

(449) In the example shown in FIG. **14C**, the first owner has submitted a request through the interface **1420** to delete the third vendor. In this example, the lockbox server **1410** determines that the request is related to the third vendor and that the third vendor is associated with the passcode databases **1470** and **1474**, but not the passcode databases **1472** and **1476**. Based on this determination, the lockbox server **1410** sends a command to delete all of the employee passcodes for the third vendor to the passcode databases **1470** and **1474**, but not the passcode databases **1472** and **1476**. As shown, the passcode databases **1470** and **1474** have been updated to remove all of the employee passcodes for the third vendor.

(450) Described systems, methods, and techniques may be implemented in digital electronic

circuitry, computer hardware, firmware, software, or in combinations of these elements. Apparatus implementing these techniques may include appropriate input and output devices, a computer processor, and a computer program product tangibly embodied in a machine-readable storage device for execution by a programmable processor. A process implementing these techniques may be performed by a programmable processor executing a program of instructions to perform desired functions by operating on input data and generating appropriate output. The techniques may be implemented in one or more computer programs that are executable on a programmable system including at least one programmable processor coupled to receive data and instructions from, and to transmit data and instructions to, a data storage system, at least one input device, and at least one output device. Each computer program may be implemented in a high-level procedural or object-oriented programming language, or in assembly or machine language if desired; and in any case, the language may be a compiled or interpreted language. Suitable processors include, for example, both general and special purpose microprocessors. Generally, a processor will receive instructions and data from a read-only memory and/or a random access memory. Storage devices suitable for tangibly embodying computer program instructions and data include all forms of non-volatile memory, including by way of example semiconductor memory devices, such as Erasable Programmable Read-Only Memory (EPROM), Electrically Erasable Programmable Read-Only Memory (EEPROM), and flash memory devices; magnetic disks such as internal hard disks and removable disks; magneto-optical disks; and Compact Disc Read-Only Memory (CD-ROM). Any of the foregoing may be supplemented by, or incorporated in, specially-designed ASICs (application-specific integrated circuits).

(451) It will be understood that various modifications may be made. For example, other useful implementations could be achieved if steps of the disclosed techniques were performed in a different order and/or if components in the disclosed systems were combined in a different manner and/or replaced or supplemented by other components. Accordingly, other implementations are within the scope of the disclosure.

Claims

1. A system comprising one or more computers and one or more storage devices on which are stored instructions that are operable, when executed by the one or more computers, to cause the one or more computers to perform operations comprising: in response to detecting a trigger, presenting, on a display, a first selectable control that, when selected, triggers access to at least a portion of a property and a second selectable control that, when selected triggers denial of access to the property; receiving input indicating selection of the first selectable control; and in response to receiving the input indicating selection of the first selectable control, sending a signal to a device to maintain access to at least the portion of the property.
2. The system of claim 1, the operations comprising: determining, using the input indicating selection of the first selectable control, whether an access level associated with an account by which the input was received has permissions to send the signal to the device to maintain access to the portion of the property, wherein: sending the signal to a device to maintain access to at least a portion of the property is responsive to receiving input indicating selection of the first selectable control and determining that the access level associated with the account has permissions to send the signal to the device to maintain access to the portion of the property.
3. The system of claim 1, wherein sending the signal to maintain access to at least the portion of the property comprises sending, to a mobile device, a limited use code that maintains access to at least the portion of the property during a predetermined access time period or for a limited number of uses.
4. The system of claim 3, wherein the limited use code maintains access to at least the portion of the property during the predetermined access time period, the operations comprising generating a

notification indicating an account associated with the limited use code, a beginning for an access time period, and an end for the access time period.

5. The system of claim 4, wherein the limited use code maintains access to at least the portion of the property during the predetermined access time period, the operations comprising: detecting that the access time period has begun; and in response to detecting that the access time period has begun, generating a notification that indicates use of the limited use code.

6. The system of claim 4, wherein the limited use code maintains access to at least the portion of the property for the limited number of uses, the operations comprising: determining whether a quantity of uses of the limited use code satisfies a quantity threshold; and performing an action using a result of the determination whether the quantity of uses of the limited use code satisfies the quantity threshold.

7. The system of claim 6, the operations comprising: determining whether a person maintaining access with the limited use code stays within a permitted portion of the property; and performing one or more operations using a result of the determination whether the person maintaining access with the limited use code stays within the permitted portion of the property.

8. The system of claim 1, the operations comprising: receiving data indicating access is maintained to the portion of the property and presenting on a display data indicating the maintaining of access to at least the portion of the property, where the data represents a) a code used for access to the property and that is correlated in a database with a corresponding person and b) a time of use.

9. The system of claim 1, the operations comprising: receiving data indicating an attempted access to at least a portion of the property using a code; and in response to receiving data indicating an attempt to access at least a portion of the property using the code and using a set of rules for notifications that is maintained in memory, determining whether to generate a notification.

10. The system of claim 9, wherein the set of rules comprises at least one of a time frame, a number of attempts for access, or whether access was maintained.

11. The system of claim 1, the operations comprising: receiving data indicating a presence at the property; and in response to receiving data indicating a presence at the property, presenting a notification indicating the presence at the property and that includes the first selectable control.

12. The system of claim 1, the operations comprising: after sending the signal, receiving second sensor data indicating a presence at the property; determining, using the second sensor data indicating the presence at the property, whether a location of the presence at the property satisfies an access threshold; and in response to determining that the location of the presence at the property satisfies the access threshold, performing one or more actions related to improper access.

13. The system of claim 1, the operations comprising: after sending the signal, receiving second sensor data indicating a presence at the property; determining, using the second sensor data indicating the presence at the property, whether a location of the presence at the property satisfies an access threshold; and in response to determining that the location of the presence at the property does not satisfy the access threshold, determining to skip performing one or more actions related to improper access.

14. The system of claim 1, the operations comprising: receiving data indicating a presence at the property, wherein presenting the first selectable control and the second selectable control comprises: in response to receiving data indicating a presence at the property, presenting the first selectable control that, when selected, triggers access to a property and the second selectable control that, when selected triggers denial of access to the property.

15. The system of claim 14, wherein: the data indicating the presence at the property indicates a number of access attempts; and presenting the first selectable control and the second selectable control occurs in response to determining that the number of access attempts satisfies an attempt threshold.

16. The system of claim 1, the operations comprising: after sending the signal to the device, receiving data indicating an absence of access to the property during a time frame; and in response

to i) receiving data indicating an absence of access to the property during a time frame and ii) sending the signal to the device to maintain access to at least the portion of the property, presenting a notification on a display indicating the absence of access to the property during the time frame, wherein the notification includes an expected access type and the time frame.

17. One or more non-transitory computer storage media encoded with instructions that, when executed by one or more computers, cause the one or more computers to perform operations comprising: in response to detecting a trigger, presenting, on a display, a first selectable control that, when selected, triggers access to at least a portion of a property and a second selectable control that, when selected triggers denial of access to the property; receiving input indicating selection of the first selectable control; and in response to receiving the input indicating selection of the first selectable control, sending a signal to a device to maintain access to at least the portion of the property.

18. The computer storage media of claim 17, the operations comprising: determining, using the input indicating selection of the first selectable control, whether an access level associated with an account by which the input was received has permissions to send the signal to the device to maintain access to the portion of the property, wherein: sending the signal to a device to maintain access to at least a portion of the property is responsive to receiving input indicating selection of the first selectable control and determining that the access level associated with the account has permissions to send the signal to the device to maintain access to the portion of the property.

19. A computer-implemented method comprising: in response to detecting a trigger, presenting, on a display, a first selectable control that, when selected, triggers access to at least a portion of a property and a second selectable control that, when selected triggers denial of access to the property; receiving input indicating selection of the first selectable control; and in response to receiving the input indicating selection of the first selectable control, sending a signal to a device to maintain access to at least the portion of the property.

20. The method of claim 19, comprising: determining, using the input indicating selection of the selectable control, whether an access level associated with an account by which the input was received has permissions to send the signal to the device to maintain access to the portion of the property, wherein: sending the signal to a device to maintain access to at least a portion of the property is responsive to receiving input indicating selection of the selectable control and determining that the access level associated with the account has permissions to send the signal to the device to maintain access to the portion of the property.

21. A system comprising one or more computers and one or more storage devices on which are stored instructions that are operable, when executed by the one or more computers, to cause the one or more computers to perform operations comprising: presenting, on a display, a selectable control that, when selected, triggers maintaining access to a portion of a property; receiving input indicating selection of the selectable control; and in response to receiving the input indicating selection of the selectable control, sending, to a mobile device, a limited use code that maintains access to at least a portion of the property during a predetermined access time period or for a limited number of uses.

22. One or more non-transitory computer storage media encoded with instructions that, when executed by one or more computers, cause the one or more computers to perform operations comprising: presenting, on a display, a selectable control that, when selected, triggers maintaining access to a portion of a property; receiving input indicating selection of the selectable control; and in response to receiving the input indicating selection of the selectable control, sending, to a mobile device, a limited use code that maintains access to at least a portion of the property during a predetermined access time period or for a limited number of uses.

23. A computer-implemented method comprising: presenting, on a display, a selectable control that, when selected, triggers maintaining access to a portion of a property; receiving input indicating selection of the selectable control; and in response to receiving the input indicating selection of the

selectable control, sending, to a mobile device, a limited use code that maintains access to at least a portion of the property during a predetermined access time period or for a limited number of uses.

24. A system comprising one or more computers and one or more storage devices on which are stored instructions that are operable, when executed by the one or more computers, to cause the one or more computers to perform operations comprising: presenting, on a display, a selectable control that, when selected, triggers maintaining access to a portion of a property; receiving input indicating selection of the selectable control; determining, using the input indicating selection of the selectable control, whether an access level associated with an account by which the input was received has permissions to send a signal to the device to maintain access to the portion of the property; and in response to receiving the input indicating selection of the selectable control and determining that the access level associated with the account has permissions to send the signal to the device to maintain access to the portion of the property, sending the signal to a device to maintain access to at least a portion of the property.

25. One or more non-transitory computer storage media encoded with instructions that, when executed by one or more computers, cause the one or more computers to perform operations comprising: presenting, on a display, a selectable control that, when selected, triggers maintaining access to a portion of a property; receiving input indicating selection of the selectable control; determining, using the input indicating selection of the selectable control, whether an access level associated with an account by which the input was received has permissions to send a signal to a device to maintain access to the portion of the property; and in response to receiving the input indicating selection of the selectable control and determining that the access level associated with the account has permissions to send the signal to the device to maintain access to the portion of the property, sending the signal to a device to maintain access to at least a portion of the property.

26. A computer-implemented method comprising: presenting, on a display, a selectable control that, when selected, triggers maintaining access to a portion of a property; receiving input indicating selection of the selectable control; determining, using the input indicating selection of the selectable control, whether an access level associated with an account by which the input was received has permissions to send a signal to a device to maintain access to the portion of the property; and in response to receiving the input indicating selection of the selectable control and determining that the access level associated with the account has permissions to send the signal to the device to maintain access to the portion of the property, sending the signal to a device to maintain access to at least a portion of the property.
