

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407401
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Flordelis; Jose et al.

Configuration of a wireless communication device to facilitate angle-of-arrival measurements at a re-configurable repeater device

Abstract

An access node—e.g., a base station—provide a wireless communication device with a configuration of a reference-signal transmission in response to a need to facilitate angle-of-arrival measurements a reconfigurable repeater device.

Inventors:	Flordelis; Jose (Lund, SE), Bengtsson; Erik (Eslöv, SE), Rusek; Fredrik (Eslöv, SE), Zander; Olof (Södra Sandby, SE), Zhao; Kun (Malmö, SE)
Applicant:	Sony Group Corporation (Tokyo, JP)
Family ID:	78085942
Assignee:	Sony Group Corporation (Tokyo, JP)
Appl. No.:	18/028033
Filed (or PCT Filed):	October 08, 2021
PCT No.:	PCT/EP2021/077862
PCT Pub. No.:	WO2022/074194
PCT Pub. Date:	April 14, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230344507 A1	Oct. 26, 2023

Foreign Application Priority Data

SE	2030304-6	Oct. 08, 2020
----	-----------	---------------

Publication Classification

Int. Cl.: H04B7/155 (20060101)

U.S. Cl.:

CPC H04B7/15528 (20130101);

Field of Classification Search

CPC: H04B (7/15); H04B (7/155); H04B (7/15507); H04B (7/15521); H04B (7/15557); H04B (7/15592); H04B (7/165); H04B (7/15542)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2008/0225931	12/2007	Proctor	455/24	H04B 7/15585
2015/0350924	12/2014	Schmidt	N/A	N/A
2019/0174337	12/2018	Prasad	N/A	N/A
2019/0335430	12/2018	Ljung	N/A	N/A

OTHER PUBLICATIONS

International Search Report and Written Opinion from corresponding International Application No. PCT/EP2021/077862, mailed on Jan. 24, 2022; 16 pages. cited by applicant

Office Action and Swedish Search Report from corresponding Swedish Application No. 2030304-6; mailed on May 28, 2021; 6 pages. cited by applicant

Zhang et al.: "Positioning with Dual Reconfigurable Intelligent Surfaces in Millimeter-Wave MIMO Systems"; International Conference on Communications in China; dated 2020; 6 pages. cited by applicant

Jian et al.: "A Modified Off-grid SBL Channel Estimation and Transmission Strategy for RIS-Assisted Wireless Communication Systems"; IEEE, dated 2020, 6 pages. cited by applicant

Wang et al.: "Joint Beam Training and Positioning for Intelligent Reflecting Surfaces Assisted Millimeter Wave Communications"; IEEE; dated Sep. 8, 2020; 15 pages. cited by applicant

Yang et al.: "Intelligent Reflecting Surface Meets OFDM: Protocol Design and Rate Maximization"; IEEE, dated Nov. 22, 2019; 32 pages. cited by applicant

Primary Examiner: Ferguson; Keith

Attorney, Agent or Firm: Tucker Ellis LLP

Background/Summary

TECHNICAL FIELD

(1) Various examples generally relate to communicating between nodes using re-configurable repeater devices. Various examples specifically relate to repeatedly transmitting reference signals towards the re-configurable repeater devices.

BACKGROUND

(2) In order to increase a coverage area for wireless communication, it is envisioned to use re-configurable repeater devices (RRD).

(3) A first kind of RRD is a re-configurable repeater device, sometimes also referred to as reflecting large intelligent surface (LIS). See, e.g., Sha Hu, Fredrik Rusek, and Ove Edfors. "Beyond massive MIMO: The potential of data transmission with large intelligent surfaces." *IEEE Transactions on Signal Processing* 66.10 (2018): 2746-2758. An LIS can be implemented by an array of antennas that reflect incident electromagnetic waves/signals. The array of antennas can be semi-passive. Semi-passive can correspond to a scenario in which the antennas do not provide signal amplification, but can impose a variable amplitude and/or phase shift. An input spatial direction from which incident signals on a data carrier are accepted and an output spatial direction into which the incident signals are reflected can be re-configured, by changing a phase relationship between the antennas.

(4) A second kind of RRD is a so-called smart repeater having an amplify-and-forward functionality. Amplify-and-forward functionality is different to a decode-and-forward functionality in that it is not required to translate RF signals into the baseband and decode. This simplifies the hardware design of smart repeaters if compared to decode-and-forward relays. On the other hand, noise superimposed on the signal is also amplified and forwarded.

(5) It is helpful to accurately configure the spatial filter at the RRD, to provide a reliable forwarding of incident signals.

SUMMARY

(6) Accordingly, there is need of improved techniques for re-configuring RRDs.

(7) This need is met by the features of the independent claims. The features of the dependent claims define examples.

(8) A method of operating an access node of a communications network is provided. The access node communicates with a UE via an RRD. The RRD is re-configurable to provide multiple spatial filters. Each one of the multiple spatial filters is associated with a respective input spatial direction from which incident signals on a data carrier are accepted. Each one of the multiple spatial filters is also associated with a respective output spatial direction into which the incident signals are reflected or amplified by the RRD. The method includes providing a configuration of a RS transmission to the UE. This is in response to a need to facilitate an angle-of-arrival measurement at the RRD based on RSs transmitted by the UE. The RS transmission includes the RS. The RS transmission is on an auxiliary carrier that is different from the data carrier.

(9) A computer program or a computer-program product or a computer-readable storage medium includes program code. The program code can be loaded and executed by least one processor. Upon loading and executing the program code, the at least one processor performs a method of operating an access node of a communications network. The access node communicates with a UE via an RRD. The RRD is re-configurable to provide multiple spatial filters. Each one of the multiple spatial filters is associated with a respective input spatial direction from which incident signals on a data carrier are accepted. Each one of the multiple spatial filters is also associated with a respective output spatial direction into which the incident signals are reflected or amplified by the RRD. The method includes providing a configuration of a RS transmission to the UE. This is in response to a need to facilitate an angle-of-arrival measurement at the RRD based on RSs transmitted by the UE. The RS transmission includes the RS. The RS transmission is on an auxiliary carrier that is different from the data carrier.

(10) An access node of a communications network is provided. The access node is configured to communicate with a wireless communication device via a re-configurable repeater device, RRD, the RRD being re-configurable to provide multiple spatial filters, each one of the multiple spatial filters being associated with a respective input spatial direction from which incident signals on a data carrier are accepted and with a respective output spatial direction into which incident signals

are reflected or amplified by the RRD. The access node includes control circuitry configured to, in response to a need to facilitate an angle-of-arrival measurement at the RRD based on reference signals transmitted by the wireless communication device, provide, to the wireless communication device, a configuration of a reference-signal transmission comprising the reference signals, the reference-signal transmission being on an auxiliary carrier different from the data carrier.

(11) A method of operating a wireless communication device connectable to a communications network is provided. The wireless communication device communicates with an access node of the communications network via a re-configurable repeater device, RRD. The RRD is re-configurable to provide multiple spatial filters, each one of the multiple spatial filters being associated with a respective input spatial direction from which incident signals on a data carrier are accepted and with a respective output spatial direction into which incident signals are reflected or amplified by the RRD. The method includes obtaining, from the access node, a configuration of a reference-signal transmission. The method also includes transmitting reference signals of the reference-signal transmission to the RRD in accordance with the configuration, to facilitate an angle-of-arrival measurement at the RRD.

(12) A computer program or a computer-program product or a computer-readable storage medium includes program code. The program code can be loaded and executed by least one processor. Upon loading and executing the program code, the at least one processor performs a method of operating a wireless communication device connectable to a communications network. The wireless communication device communicates with an access node of the communications network via a re-configurable repeater device, RRD. The RRD is re-configurable to provide multiple spatial filters, each one of the multiple spatial filters being associated with a respective input spatial direction from which incident signals on a data carrier are accepted and with a respective output spatial direction into which incident signals are reflected or amplified by the RRD. The method includes obtaining, from the access node, a configuration of a reference-signal transmission. The method also includes transmitting reference signals of the reference-signal transmission to the RRD in accordance with the configuration, to facilitate an angle-of-arrival measurement at the RRD.

(13) A wireless communication device connectable to a communications network is provided. The wireless communication device is configured to communicate with an access node of the communications network via a re-configurable repeater device, RRD. The RRD is re-configurable to provide multiple spatial filters, each one of the multiple spatial filters being associated with a respective input spatial direction from which incident signals on a data carrier are accepted and with a respective output spatial direction into which incident signals are reflected or amplified by the RRD. The wireless communication device comprises control circuitry configured to obtain, from the access node, a configuration of a reference-signal transmission (800); and transmit reference signals (5050) of the reference-signal transmission (800) to the RRD in accordance with the configuration, to facilitate an angle-of-arrival measurement at the RRD.

(14) A method of operating a re-configurable repeater device, RRD, is provided. The RRD is re-configurable to provide multiple spatial filters, each one of the multiple spatial filters being associated with a respective input spatial direction from which incident signals on a data carrier are acceptable and with a respective output spatial direction into which incident signals are reflected or amplified by the RRD. The method includes obtaining at least a part of a configuration of a reference-signal transmission by a wireless communication device. The method further includes monitoring for reference signals of the reference-signal transmission based on the at least a part of the configuration. The method further includes determining an angle-of-arrival of the reference signals based on said monitoring. The method further includes re-configuring to provide a selected spatial filter of the multiple spatial filters based on the angle-of-arrival.

(15) A computer program or a computer-program product or a computer-readable storage medium includes program code. The program code can be loaded and executed by least one processor. Upon loading and executing the program code, the at least one processor performs a method of

operating a re-configurable repeater device, RRD. The RRD is re-configurable to provide multiple spatial filters, each one of the multiple spatial filters being associated with a respective input spatial direction from which incident signals on a data carrier are acceptable and with a respective output spatial direction into which incident signals are reflected or amplified by the RRD. The method includes obtaining at least a part of a configuration of a reference-signal transmission by a wireless communication device. The method further includes monitoring for reference signals of the reference-signal transmission based on the at least a part of the configuration. The method further includes determining an angle-of-arrival of the reference signals based on said monitoring. The method further includes re-configuring to provide a selected spatial filter of the multiple spatial filters based on the angle-of-arrival.

(16) A re-configurable repeater device, RRD is provided. The RRD is re-configurable to provide multiple spatial filters, each one of the multiple spatial filters being associated with a respective input spatial direction from which incident signals on a data carrier are acceptable and with a respective output spatial direction into which incident signals are reflected or amplified by the RRD. The RRD comprises a control circuitry configured to obtain at least a part of a configuration of a reference-signal transmission by a wireless communication device; and monitor for reference signals of the reference-signal transmission based on the at least a part of the configuration; and determine an angle-of-arrival of the reference signals based on said monitoring; and re-configure to provide a selected spatial filter of the multiple spatial filters based on the angle-of-arrival.

(17) It is to be understood that the features mentioned above and those yet to be explained below may be used not only in the respective combinations indicated, but also in other combinations or in isolation without departing from the scope of the invention.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 schematically illustrates a communication system according to various examples.
- (2) FIG. 2 schematically illustrates details of the communication system of FIG. 1.
- (3) FIG. 3 schematically illustrates using an RRD according to various examples.
- (4) FIG. 4 schematically illustrates details with respect to the RRD.
- (5) FIG. 5 is a flowchart of a method according to various examples.
- (6) FIG. 6 is a flowchart of a method according to various examples.
- (7) FIG. 7 is a flowchart of a method according to various examples.
- (8) FIG. 8 is a signaling diagram according to various examples.

DETAILED DESCRIPTION OF THE DRAWINGS

(9) Some examples of the present disclosure generally provide for a plurality of circuits or other electrical devices. All references to the circuits and other electrical devices and the functionality provided by each are not intended to be limited to encompassing only what is illustrated and described herein. While particular labels may be assigned to the various circuits or other electrical devices disclosed, such labels are not intended to limit the scope of operation for the circuits and the other electrical devices. Such circuits and other electrical devices may be combined with each other and/or separated in any manner based on the particular type of electrical implementation that is desired. It is recognized that any circuit or other electrical device disclosed herein may include any number of microcontrollers, a graphics processor unit (GPU), integrated circuits, memory devices (e.g., FLASH, random access memory (RAM), read only memory (ROM), electrically programmable read only memory (EPROM), electrically erasable programmable read only memory (EEPROM), or other suitable variants thereof), and software which co-act with one another to perform operation(s) disclosed herein. In addition, any one or more of the electrical devices may be configured to execute a program code that is embodied in a non-transitory computer readable

medium programmed to perform any number of the functions as disclosed.

(10) In the following, examples of the disclosure will be described in detail with reference to the accompanying drawings. It is to be understood that the following description of examples is not to be taken in a limiting sense. The scope of the disclosure is not intended to be limited by the examples described hereinafter or by the drawings, which are taken to be illustrative only.

(11) The drawings are to be regarded as being schematic representations and elements illustrated in the drawings are not necessarily shown to scale. Rather, the various elements are represented such that their function and general purpose become apparent to a person skilled in the art. Any connection or coupling between functional blocks, devices, components, or other physical or functional units shown in the drawings or described herein may also be implemented by an indirect connection or coupling. A coupling between components may also be established over a wireless connection. Functional blocks may be implemented in hardware, firmware, software, or a combination thereof.

(12) Techniques are described that facilitate wireless communication between nodes. A wireless communication system includes a transmitter node and one or more receiver nodes. The nodes communicate on a data carrier. In some examples, the wireless communication system can be implemented by a wireless communication network, e.g., a radio-access network (RAN) of a Third Generation Partnership Project (3GPP)-specified cellular network (NW). In such case, the transmitter node can be implemented by an access node such as a base station (BS) of the RAN, and the one or more receiver nodes can be implemented by wireless communication devices (also referred to as user equipment, UE). It would also be possible that the transmitter node is implemented by a UE and the one or more receiver nodes are implemented by a BS and/or further UEs. Hereinafter, for sake of simplicity, various examples will be described with respect to an example implementation of the transmitter node by a BS and the one or more receiver nodes by UEs—i.e., to downlink (DL) communication; but the respective techniques can be applied to other scenarios, e.g., uplink (UL) communication and/or sidelink communication.

(13) According to various examples, it is possible to use multi-antenna techniques. Multi-antenna techniques are sometimes used to enhance reliability and/or throughput of wireless communication. Here, the transmitter node and the receiver node both include multiple antennas that can be operated in a phase-coherent manner. Thereby, a signal can be transmitted redundantly (diversity multi-antenna mode) along multiple spatial data streams, or multiple signals can be transmitted on multiple spatial data streams (spatial multiplexing multi-antenna operational mode). It is possible to use beamforming: here, spatial data streams can be defined by focusing the transmission energy for transmitting (transmit beam, TX beam) and/or the receive sensitivity for receiving (receive beam, RX beam) to a particular spatial direction. For beamforming, the process of identifying the appropriate beams is often referred to beam management. Various techniques described herein are concerned with beam management. According to various examples, the transmitter node can communicate with at least one of the receiver nodes via an RRD. The RRD may include an antenna array. The RRD may include a meta-material surface. In examples, an RRD may include a reflective antenna array (RAA). The RRD can implement a smart repeater functionality using amplify-and-forward. To forward an incident signal, the RRD may not decode the signal. The RRD may not translate an incident signal into the baseband. As a general rule, the RRD is configured to employ multi-antenna techniques. In particular, the RRD is reconfigurable to provide multiple spatial filters. Thereby, a spatial data stream between two nodes—e.g., the BS and the UE—can be diverted. Each one of the multiple spatial filters is associated with a respective input spatial direction from which incident signals on a respective data radio carrier are accepted, as well as with a respective output spatial direction into which incident signals are reflected or amplified by the RRD. Each output spatial direction is associated with a respective beam. The RRD thereby implements beamforming.

(14) There are many schools of thought for how RRDs should be integrated into 3GPP-

standardized RANs. In an exemplary case, the NW operator has deployed the RRDs and is therefore in full control of the RRD operations. The UEs, on the other hand, may not be aware of the presence of any RRD, at least initially, i.e., it is transparent to a UE whether it communicates directly with the BS or via an RRD. The RRD essentially functions as a coverage-extender of the BS. The BS may have established a control link with the RRD. According to another exemplary case, it might be a private user or some public entity that deploys the RRD. Further, it may be that the UE, in this case, controls RRD operations. The BS, on the other hand, may not be aware of the presence of any RRD and, moreover, may not have control over it/them whatsoever. The UE may gain awareness of the presence of RRD by means of some short-range radio technology, such as Bluetooth, wherein Bluetooth may refer to a standard according to IEEE 802.15, or WiFi, wherein WiFi may refer to a standard according to IEEE 802.11, by virtue of which it may establish the control link with the RRD. The control link can thus be on an auxiliary carrier.

(15) In a further exemplary case, neither the UE nor the BS are aware of the presence of the RRD. The RRD may be transparent with respect to a communication between the UE and the BS on a data carrier. The RRD may gain awareness of the UE and/or the BS and re-configure itself based on information obtained from the UE and/or BS.

(16) The three exemplary cases described above are summarized in TAB. 1 below.

(17) TABLE-US-00001 TABLE 1 Scenarios for RRD integration into cellular NW Scenario

Description	Explanation
A BS-RRD	BS controls the RRD and/or can obtain control information from the RRD. A control link is link established between the BS and the RRD. The control link can be on an auxiliary carrier different from the data carrier. The control link can be a wired connection, e.g., cable or fiber.
B UE-RRD	UE controls the RRD and/or can obtain control information from the RRD. A control link is link established between the UE and the RRD. The control link can be on an auxiliary carrier different from the data carrier
C Transparent RRD	RRD re-configures itself based on information RRD obtained from the UE and/or BS. No control link is established between the RRD and the UE or the BS.

(18) According to various examples, it is possible to implement a scenario A according to TAB. 1. It is optionally possible to alternatively or additionally implement the UE RRD control link according to scenario B. In any case, the RRD can be fully controlled by the BS.

(19) Various techniques are based on the finding that, in order to reflect an incident signal towards the UE, the RRD requires knowledge regarding the direction and potentially distance at which the UE is positioned relatively to the RRD.

(20) The techniques described herein can be used to facilitate a reference-signal transmission of reference signals (RSs; sometimes also referred to as pilot signals or synchronization signals or beacon signals) transmitted by a first node, e.g., the UE. The UE can transmit the RS in a broadcast or point-to-point manner. The RSs can have a predefined signal shape and/or symbol sequence. The RSs can have predefined transmit properties such as, e.g., transmit amplitude or phase, or even precoding. Thus, by using the RSs, one or more second nodes, e.g., the RRD, can obtain information on the channel between the first node and the respective one of the one or more second nodes. As a general rule, various kinds and types of RSs can be subject to the techniques described herein. For instance, RSs that are not associated with one or more specific UE's—e.g., a primary synchronization signal (PSS) or a secondary synchronization signal (SSS) broadcasted in a synchronization signal block (SSB)—can be subject to the techniques described herein. Further examples include sounding RSs and positioning RSs. Alternatively or additionally, it would be possible to apply the techniques described herein to RSs that are associated with one or more specific UEs; an example would be a Channel State Information (CSI)-RS.

(21) To determine the direction at which the UE is positioned relative to the RRD—e.g., for the purpose of beam management at the RRD and/or the UE—, it is possible to implement a positioning procedure between the RRD and the UE. As a general rule, various options are available for implementing the positioning procedure. In particular, an RS-based positioning

procedure is possible. Here, the UE transmits RSs and the RRD can monitor for the RSs. Then, the RRD, based on one or more receive properties of the RSs, can determine one or more characteristics of its relative position with respect to the UE. For example, the RRD could determine the angle-of-arrival (AoA) of the RSs of the RS transmission; the AoA then corresponds to the direction of a spatial propagation path of signals between the UE and the RRD. It would also be possible to determine the path loss to conclude on the length of the spatial propagation path. Another characteristic of the relative position would be distance. For instance, it would be possible to conclude on the distance between the UE and the RRD based on a path loss experienced by the RSs of the reference-signal transmission; the path loss can be determined based on comparing a transmit amplitude of the RSs with a receive amplitude of the RSs. Another possibility to estimate the length of the spatial propagation path would be to measure the delay of signals propagating. Another option for positioning measurements includes angle-of-departure measurements at the UE, e.g., based on feedback from the RRD to the UE. It is not required in all scenarios that the relative position is determined based on one or more receive properties of the RS. In some examples, the RS may also encode the position of the UE and then the RRD can decode the respective digital information and compare the position of the UE with its own position; this helps to determine the AoA.

(22) As explained above, the RRD does not include the capability to demodulate RF signals to thereby facilitate baseband processing. Accordingly, in the various examples described herein, it is possible that the RRD is equipped with a receiver for an auxiliary carrier that is different to the data carrier on which the RRD facilitates the communication between the transmitter node and the receiver node. Then, the RS transmission can be implemented on the auxiliary carrier. In other words, based on the receiver for the auxiliary carrier, the RRD can implement digital signal processing of digital signals determined based on the RSs; the RRD may not have such capability for similar digital signal processing associated with transmissions on the data carrier.

(23) For example, the data carrier and the auxiliary carrier may reside in different frequency bands. To give an example, it would be possible that the data carrier has frequencies above 20 GHz while the auxiliary carrier has frequencies below 10 GHz, e.g., below 6 GHz. For example, typical frequencies can be in the range of 2.6 to 2.7 GHz. Accordingly, the auxiliary carrier and the data carrier can employ different carriers. A modulation and/or coding scheme can be different for the data carrier and the auxiliary carrier. A communication protocol implemented on the data carrier can be different from a further communication protocol implemented on the auxiliary carrier. For example, the data carrier can employ a 3GPP cellular communication; while the auxiliary carrier employs a Bluetooth or Wi-Fi communication protocol.

(24) According to various examples, it is possible that the BS is in control of AoA measurements at the RRD. Accordingly, the BS can orchestrate an interaction between the UE and the RRD for the purpose of implementing the AoA measurements. This has the effect that, e.g., by considering ongoing AoA measurements when scheduling communication between other nodes, the BS can mitigate interference. Furthermore, control signaling overhead on the spectrum of, both, the auxiliary carrier, as well as the data carrier can be reduced by the controlled configuration of the RS transmission. It is possible to implement scenario A of TAB. 1.

(25) Accordingly, according to various examples, the BS provides a configuration of the RS transmission to the UE. The BS may provide the configuration of the RS transmission for the purpose of facilitating the AoA measurements at the RRD. Accordingly, the BS can provide the configuration of the RS transmission in response to a need to facilitate the AoA measurement at the RRD based on the RSs of the RS transmission and as transmitted by the UE. The UE can then obtain the configuration of the RS transmission from the BS and subsequently transmit the RSs of the RS transmission to the RRD in accordance with the configuration. Thereby, the UE can facilitate the AoA measurement at the RRD. The RRD can monitor for the RSs of the RS transmission and then determine an AoA, e.g., based on one or more receive properties of the RSs,

e.g., amplitude and/or phase. Such monitoring can be based on at least a part of the configuration provided to the UE also being provided to the RRD, from the BS. Then, the RRD can implement a reconfiguration to provide a selected spatial filter of multiple available spatial filters based on the determined AoA.

(26) FIG. 1 schematically illustrates a communication system **100**. The communication system includes two nodes **101**, **102** that are configured to communicate with each other via a data carrier **111**. In the example of FIG. 1, the node **101** is implemented by an access node, more specifically a BS, and the node **102** is implemented by a UE. The BS **101** can be part of a cellular NW (not shown in FIG. 1).

(27) As a general rule, the techniques described herein could be used for various types of communication systems, e.g., also for peer-to-peer communication, etc. For sake of simplicity, however, hereinafter, various techniques will be described in the context of a communication system that is implemented by a BS **101** of a cellular NW and a UE **102**.

(28) As illustrated in FIG. 1, there can be DL communication, as well as UL communication. Various examples described herein particularly focus on the DL communication of RSs that are repeatedly transmitted by the BS **101** to the UE **102**. However, similar techniques may be applied to, e.g., UL communication of RSs repeatedly transmitted by the UE **102** to the BS **101**.

(29) The UE **102** and the BS **101** can communicate on the data carrier **111**. For instance, the data carrier **111** may have a carrier frequency of not less than 20 GHz or even not less than 40 GHz. The data carrier **111** may be via an RRD (not illustrated in FIG. 1).

(30) FIG. 2 illustrates details with respect to the BS **101**. The BS **101** implements an access node to a communications network, e.g., a 3GPP-specified cellular network. The BS **101** includes control circuitry that is implemented by a processor **1011** and a non-volatile memory **1015**. The processor **1011** can load program code that is stored in the memory **1015**. The processor **1011** can then execute the program code. Executing the program code causes the processor to perform techniques as described herein, e.g.: providing a configuration of an RS transmission to the UE **102**; providing at least a part of the configuration of the RS transmission to a RRD (not illustrated in FIG. 2); scheduling communication on the data carrier **111** in accordance with a report on the RS transmission received from the RRD; etc.

(31) FIG. 2 also illustrates details with respect to the UE **102**. The UE **102** includes control circuitry that is implemented by a processor **1021** and a non-volatile memory **1025**. The processor **1021** can load program code that is stored in the memory **1025**. The processor can execute the program code. Executing the program code causes the processor to perform techniques as described herein, e.g.: obtaining a configuration of an RS transmission from the BS **101**; transmitting RSs of the RS transmission in accordance with the configuration; communicating with the BS **101** on the data carrier **111**; etc.

(32) FIG. 2 also illustrates details with respect to communication between the BS **101** and the UE **102** on the data carrier **111**. The BS **101** includes an interface **1012** that can access and control multiple antennas **1014**. Likewise, the UE **102** includes an interface **1022** that can access and control multiple antennas **1024**.

(33) While the scenario of FIG. 2 illustrates the antennas **1014** being coupled to the BS **101**, as a general rule, it would be possible to employ transmit-receive points (TRPs) that are spaced apart from the BS.

(34) The interfaces **1012**, **1022** can each include one or more TX chains and one or more receiver chains. For instance, such RX chains can include low noise amplifiers, analogue to digital converters, mixers, etc. Analogue and/or digital beamforming would be possible.

(35) Thereby, phase-coherent transmitting and/or receiving (communicating) can be implemented across the multiple antennas **1014**, **1024**. Thereby, the BS **101** and the UE **102** can selectively transmit on multiple TX beams (beamforming), to thereby direct energy into distinct spatial directions.

(36) By using a TX beam, the direction of signals transmitted by a transmitter of the communication system is controlled. Energy is focused into a respective direction or even multiple directions, by phase-coherent superposition of the individual signals originating from each antenna **1014**, **1024**. Thereby, the spatial data stream can be directed. The spatial data streams transmitted on multiple beams can be independent, resulting in spatial multiplexing multi-antenna transmission; or dependent on each other, e.g., redundant, resulting in diversity multi-input multi-output (MIMO) transmission.

(37) As a general rule, alternatively or additionally to such TX beams, it is possible to employ receive (RX) beams.

(38) As illustrated in FIG. 2, the UE **102** also includes an auxiliary interface **1082** that is configured to couple with a plurality of antennas **1084**. Using the auxiliary interface **1082**, the UE **102** can communicate on an auxiliary carrier.

(39) As a general rule, at least in some scenarios, it would be possible that for communicating on the auxiliary carrier, the UE **102** can re-use the interface **1022** also used to communicate on the data carrier **111**; in such a scenario it is not required that the UE **102** includes the additional auxiliary interface **1082**.

(40) FIG. 3 illustrates DL TX beams **301-306** used by the BS **101**. Here, the BS **101** activates the beams **301-306** on different resources (e.g., different time-frequency resources, and/or using orthogonal codes/precoding) such that the UE **102** can monitor for respective signals transmitted on the DL TX beams **301-306**.

(41) A burst transmission transmits RSs or other signals on at least some of the DL TX beams **301-306**. To this end, the burst transmission includes multiple transmission blocks, wherein each transmission block is associated with a respective DL TX beam **301-306**. An example would be an SSB burst including multiple SSBs, each SSB including a PSS and SSS, wherein different SSBs are transmitted on different ones of the DL TX beams **301-306**.

(42) It is possible that the BS **101** transmits signals to the UE **102** via an RRD **109**. In the scenario of FIG. 3, the downlink transmit beam **304** is directed towards the RRD **109**. Thus, whenever the BS **101** transmits signals to the UE **102** using the downlink transmit beam **304**—e.g., a respective block of a burst transmission —, a spatial filter is provided by the RRD **109**. The spatial filter is associated with a respective spatial direction and to which the incident signals are then selectively reflected by the RRD **109**. Details with respect to the RRD **109** are illustrated in connection with FIG. 4.

(43) FIG. 4 illustrates aspects in connection with the RRD **109**. The RRD **109** could be implemented by a LIS or a smart repeater. The RRD **109** includes a phased array of antennas **1094** that impose a configurable phase shift when reflecting incident signals. This defines respective spatial filters that are associated with spatial directions into which the incident signals are reflected. In one example, the antennas **1094** can be passive or semi-passive elements that do not provide any amplification. The RRD **109** thus provides coverage extension by reflection of radio-frequency (RF) signals. Another example includes amplification of RF signals. In any case, a translation to the baseband may not be required. This is different, to, e.g., decode-and-forward relay functionality. In particular, a delay imposed by decode-and-forward relay functionality significantly larger than a delay imposed by an amplifier-and-forward repeater functionality. For instance, the delay imposed by the amplifier-and-forward functionality may be in the order of a symbol duration of the used modulation scheme, or less.

(44) The RRD **109** includes an antenna interface **1095**; a processor **1091** can activate respective spatial filters one after another, e.g., in accordance with a re-configuration timing that defines the dwell time per spatial filter.

(45) There is a communication interface **1092** and communication on an auxiliary carrier **199** can be established between the RRD **109** and, e.g., the BS **101** and/or the UE **102** (cf. TAB. 1: scenario A or B).

(46) There is a memory **1093** and the processor **1091** can load program code from the non-volatile memory and execute the program code. Executing the program code causes the processor to perform techniques as described herein, e.g.: receiving at least a part of a configuration of a RS transmission to be carried out by the UE **102**; monitoring for RSs of the RS transmission in according with the at least part of the configuration; executing a positioning of the RRD **109** with respect to the UE **102** based on said monitoring; measuring an AoA of the RSs based on said monitoring; selecting one or more spatial filters based on said monitoring; reconfiguring to implement the selected one or more spatial filters; etc.

(47) FIG. **4** is only one example implementation of the RRD. Other implementations are conceivable. For example, a meta-material surface not including distinct antenna elements may be used. The meta-material can have a configurable refraction index. To provide re-configurable refraction index, the meta-material may be made of repetitive tunable structures that have extensions smaller than the wavelength of the incident RF signals. A typical patch antenna has dimensions of half a wavelength. A monopole antenna has dimensions of a quarter of the wavelength.

(48) FIG. **5** is a flowchart of a method according to various examples. For instance, the method of FIG. **5** can be executed by an access node of a communications network, e.g., the BS **101**. More specifically, the method of FIG. **5** could be executed by the processor **1011** upon loading program code from the memory **1015** (cf. FIG. **2**). Optional boxes are labeled with dashed lines in FIG. **5**.

(49) At optional box **7005**, the BS **101** determines whether there is a need to facilitate an AoA measurement at the RRD **109**. Various examples are available to determine whether there is such a need. For example, the BS **101** could receive a corresponding indication from the RRD on a respective control link established between the BS and the RRD, cf. TAB. **1**, example A. To give an example, the RRD **109** may detect that it does not receive RSs from the UE **102** and then trigger a respective request for a new or adjusted RS transmission. Alternatively or additionally to such control signaling from the RRD **109**, the BS **101** may also determine the need to facilitate the AoA measurement based on control signaling from the UE **102**. For example, it would be possible that the control signaling is indicative of a connection termination of a communication connection established between the UE **102** and the RRD **109** using the auxiliary carrier **199**. For instance, it would be conceivable that such a communication connection is implemented for the purpose of transmitting RSs, e.g., Bluetooth beacons or Wi-Fi beacons, from the UE **102** to the RRD **109**. Then, e.g., due to UE mobility, it would be possible that the communication connection is lost and the UE **102** may provide a respective indication to the BS **101**; such an indication may also be provided by the RRD **109**.

(50) It is not required in all scenarios that the need for the AoA measurement is determined, at box **7005**, based on control signaling from the RRD **109** and/or the UE **102**. For instance, it would be possible that the BS **101** detects that it communicates on the data carrier **111** with the UE **102** via the RRD **109**. Based on such detection, the BS **101** can then determine that there is a need for the AoA measurements. In general, the RRD can measure the power of a beacon, report it to BS, and judge the proximity.

(51) At optional box **7010**, the BS **101** may determine the configuration of the RS transmission. The configuration may be re-determined from time to time, e.g., in accordance with a repetitive schedule. For example, it would be possible to determine the configuration dynamically, i.e., depending on one or more dynamic properties of, e.g., the data carrier **111**. For instance, for poor transmission characteristics of the data carrier **111** a higher density of RSs of the RS transmission may be preferable. The transmission characteristics of the data carrier **111** may be determined based on RSs communicated from the UE **102** to the BS **101** or from the BS **101** to the UE **102** on the data carrier **111**. Channel sounding is in general known to the skilled person and can be applied also to the discussed scenario; i.e., the configuration may be determined based on channel sounding of the data carrier **111**.

(52) It is not required in all scenarios that the configuration of the RS transmission is determined at box 7010; for instance, in some scenarios it would be possible that the configuration is predefined.

(53) Next, at optional box 7015, the BS 101 provides the configuration of the RS transmission to the UE 102, to thereby facilitate the AoA measurement at the RRD 109.

(54) As a general rule, various options are available for implementing the configuration and some of these options are listed below in TAB. 2.

(55) TABLE-US-00002 TABLE 2 multiple variants of implementing the configuration. It is possible to combine such variants with each other to form new variants. For instance, it would be possible to signal, both, the transmit power, as well as the repetitive resources according to variants V and VI, to give just one example. Variant Brief description Examples I Identifier It would be possible that the configuration includes one of RRD or more identifiers that are to be indicated by the RSs of the RS transmission. In particular, the identifiers could be associated with the RRDs; i.e., different identifiers may be associated with different RRDs. Each identifier may be uniquely associated with a respective RRD. Different UEs being served via the same RRD can use the same RRD-specific identifier. Thereby, a certain RRD can judge, based on the received RS, whether the respective RS is intended for that repeater device or for another RRD. II Identifier It would be possible that the configuration includes one of UE or more identifiers that are to be indicated by the RSs of the RS transmission. In particular, the identifiers could be associated with the respective UE; i.e., different identifiers may be associated with different UEs. Thus, different UEs may be provided with different UE-specific identifiers. Each identifier may be uniquely associated with a respective UE. It would be possible that each RRD is configured with one or more respective UE-specific identifiers, e.g., by providing a respective part of the configuration to the RRD (cf FIG. 5: box 7025). Thereby, multiple UEs can be supported by each RRD. III Identifiers shared As an alternative to variant II explained above, it would be possible that the identifiers are contention-based communication amongst a plurality of UEs served by a given RRD. I.e., it would be possible that a range of possible identifiers is broadcasted or predefined that can be used by the UEs and that the UEs select a respective identifier from the range. It can happen that two UEs select the same identifier and then contention can occur. In such a scenario, it would be possible that the configuration of the RS transmission is indicative of a set of candidate identifiers for which each individual UE can select a concrete identifier in a respective instance of transmitting RSs. This can help to mitigate contention to some degree. IV Identifiers of RSs of the RS transmission may be transmitted with one polarization or multiple polarizations. For instance, perpendicular of RSs polarizations may be used. Here, it would be possible that the configuration includes a first configuration for the first polarization of the RSs of the RS transmission and a second configuration for a second polarization of the RS transmission. In some examples, it would be possible to use different identifiers for the first and second polarization and the first configuration can include the first identifier of the second configuration includes the second identifier. V Transmit The configuration can specify a transmit power of the power RSs of the RS transmission to be used by the UE. For instance, the transmit power may be tailored in view of interference on the spectrum and/or an expected distance between the UE and the RRD. VI Repetitive The configuration can include repetitive resources for the resources RS transmission. For instance, time-frequency resources in a time-frequency resource grid used for communicating on the auxiliary carrier 199 can be used. Also, code resources could be indicated, to implement code-division multiplexing. VII Discovery The configuration can include assistance for discovery, information for i.e., enabling the UE and the RRD to set up a establishing communication connection on the auxiliary carrier 199 which can communication host the RS transmission. Here, it is not required in all scenarios that the RS transmission is implemented on a respective communication connection; rather, in some scenarios the RSs may be transmitted without a set up communication connection; e.g., a broadcast would be possible. VIII Beam For instance, the RS transmission can include a beam configuration sweep. Here, RSs can be transmitted on multiple

beams. The count and/or width and/or orientation of the beams can be configured by the BSs. IX Multiple It would be possible that multiple identifiers are transmit- identifier ted for multiple polarizations of signals communicated on associated the data carrier. For instance, the configuration can with multiple include a first configuration for at least one first RS of the polarizations RS transmission and a second configuration for at least of data one second RS of the RS transmission. The at least one carrier first RS is associated with a first polarization of signals on the data carrier and the at least one second RS is associated with a second polarization of signals on the data carrier.

(56) The identifiers according to variants I-III of TAB. 2 could be implemented by explicit identifiers, e.g., encoded into a base sequence or otherwise included in the RSs. Also implicit indicators would be conceivable, e.g., by selecting a specific carrier frequency, time pattern or code-division multiple access (CDMA) encoded signal.

(57) At optional box **7015**, the BS **101** receives a capability signaling from the UE. This capability signaling can be indicative of the UE **102** being capable of transmitting the RSs using the auxiliary carrier. Box **7015** may also be executed prior to box **7010** or prior to box **7005**.

(58) At box **7020**, the configuration is provided to the UE **102**. It would be possible that the configuration is included in a control message. For example, a higher-layer control message may be used. The higher-layer control message can be communicated on the data carrier **111** between the BS **101** and the UE **102**. For example, a Layer 2 or Layer 3 con-trot message may be used. For example, a Radio Resource Control (RRC) control message may be used.

(59) At optional box **7025**, at least a part of the configuration is provided to the RRD **109**. For instance, one or more parts of the configuration can be provided to the RRD that are required for the RRD to monitor for the RSs of the RS transmission. For instance, time-frequency resources may be included in the part of the configuration provided to the RRD. identifiers of relevant RSs may be included in the part of the configuration provided to the RRD (cf. TAB. 2, variants I-III).

(60) By providing the configuration at box **7020** and optionally at box **7025**, the BS **101** can facilitate the AoA measurement at the RRD based on RSs that are transmitted by the UE **102**.

(61) At optional box **7030**, it would be possible that the BS **101** receives a report from the RRD. The report can be associated the RSs of the RS transmission. For instance, the report could be indicative of a receive amplitude of the RSs. Alternatively or additionally, the report could be indicative of an AoA of the RSs.

(62) Then, at optional box **7035**, it would be possible to schedule communication between the BS **101** and the UE **102** based on the report. This can be done to mitigate interference.

(63) At box **7040**, it is then possible to communicate with the UE **102**, e.g., by transmitting and/or receiving data packets including payload data or higher-layer control messages on the data carrier **111**. In view of the appropriate selection of a given spatial filter having taken place at the RRD based on the AoA measurement facilitated by providing the configuration to the UE **102** at box **7020**, this communicating at box **7040** is particularly reliable.

(64) FIG. **6** is a flowchart of a method according to various examples. For example, the method of FIG. **6** can be executed by a UE. The method of FIG. **6** can be executed by the UE **102**. More specifically, the method of FIG. **6** can be executed by the processor **1020** of the UE **102** upon loading respective program code from the memory **1025**. Optional boxes are labeled with dashed lines in FIG. **6**.

(65) At optional box **7105**, the UE may transmit capability signaling to the BS **101**. The capability signaling is indicative of the UE being able to transmit RSs for facilitating an AoA measurement at the RRD **109**. When transmitting the capability signaling at box **7105**, the UE need not to be aware of the presence of an RRD such as the RRD **109**. This is because a control link may be established between the RRD **109** and the BS **101** (cf. TAB. 1: variant A), but not between the RRD **109** and the UE **102**. Box **7105** is interrelated with box **7015** (cf. FIG. 5).

(66) At box **7110**, the UE **102** obtains the configuration of the RS transmission. Box **7110** is inter-

related with box **7020** (cf. FIG. 5).

(67) Then, in accordance with the configuration, the UE **102** can transmit RSs of the RS transmission at box **7115**. For instance, the UE may use a transmit power included in the configuration.

(68) For instance, the UE **102** may use time-frequency resources as indicated in the configuration. Optionally, prior to transmitting the RSs at box **7115**, the UE may establish a communication connection with the RRD **109** on the auxiliary carrier **199**; optionally, this may be based on respective discovery information included in the configuration.

(69) Then, at box **7120**, the UE **102** can communicate with the BS **101**. Again, because the AoA measurement has been facilitated at box **7115** by transmitting the RSs of the RS transmission, the communication at box **7120** will exhibit a particularly high reliability. Box **7120** is inter-related with box **7040**.

(70) FIG. 7 is a flowchart of a method according to various examples. The method of FIG. 7 can be executed by an RRD. For example, the method of FIG. 7 may be executed by the RRD **109**. More specifically, the method of FIG. 7 may be executed by the processor **1091** upon loading respective program code from the memory **1093**. Optional boxes are labeled with dashed lines in FIG. 7.

(71) At optional box **7205**, at least a part of a configuration of an RS transmission is obtained from the BS **101**. As such, box **7205** is inter-related with box **7025** (cf. FIG. 5).

(72) Instead of receiving at least a part of the configuration at box **7205**, e.g., via a control link established between the BS **101** and the RRD **109**, it would also be possible that the configuration is predefined.

(73) Next, at box **7210**, the RRD monitors for RSs, e.g., in accordance with the predefined configuration or based on the configuration received at least in parts at box **7205**.

(74) Based on said monitoring for the RSs, the RRD can then determine the AoA of the RSs and, accordingly reconfigure its spatial filtering at box **7220**. This can correspond to beam management at the RRD. Subsequently, it can support a communication between the BS **101** and the UE **102** using the reconfigured spatial filter (cf. FIG. 5: box **7040**, as well as FIG. 6, box **7120**).

(75) The RRD may optionally inform the UE **102** regarding a suitable TX and/or RX beam to be used at the UE **102**. A respective feedback signaling from the RRD **109** to the UE **102** would be possible.

(76) FIG. 8 is a signaling diagram of communication between the BS **101**, the UE **102**, and the RRD **109**.

(77) At **4005**, the BS **101** and the UE **102** communicate payload data **5001** on the data carrier **111**.

(78) It is possible that the UE **102**, at **4010**, provides capability information. This has been discussed in FIG. 6, in connection with box **7105**.

(79) Next, it would be optionally possible, that the UE **102**, transmits a request **5010** at **4015** to the BS **101**, the request **5010** being indicative of a need to facilitate AoA measurements at the RRD **109**. For instance, the UE **102** may trigger the request **5010** in response to a degradation of the communication of the payload data **5001**. While in the scenario of FIG. 8, it is the UE **102** that transmits the request **5010**, alternatively or additionally, it would also be possible that the RRD **109** transmits the request **5010**.

(80) As a general rule, the request **5010** is optional. For instance, it would also be possible that the BS **101** judges that there is the need to facilitate the AoA measurements at the RRD **109** without involvement of the UE **102** and/or the RRD **109**. For instance, the BS **101** may determine an Automatic Repeat Request failure rate and/or a bit error rate or the like for said communicating of the payload data **5001**. Generally, the channel quality of the data carrier **111** between the BS **101** and the UE **102** via the RRD **109** may serve as a decision criterion as to whether or not there is the need to facilitate the AoA measurements.

(81) Then, at **4020**, the BS **101** provides the configuration **5015** of the RS transmission to be implemented by the UE **102** to the UE **102**. Details have been explained in connection with box

7020 of FIG. 5.

(82) At **4025**, it is optionally possible that the configuration **5015**, or at least a part thereof, is provided to the RRD **109**.

(83) Higher-layer control messages—e.g., Radio Resource Control messages may be used for delivering the configuration **5015** at **4020** and/or **4025**. At **4025**, a control link established between the BS **101** and the RRD **109** may be used to deliver the configuration **5015**, e.g., the control link being established using a Bluetooth or Wi-Fi protocol (cf. TAB. 1, variant A).

(84) Then, at **4030** and **4040**, the RS transmission **800** is implemented at the UE **102**. This includes transmitting RSs **5050**, e.g., using (semi-)persistently allocated or otherwise re-occurring time-frequency resources on the auxiliary carrier **199**.

(85) As illustrated in FIG. 7, said communicating between the BS **101** and the UE **102** on the data carrier **111** (e.g., at **4035**, there is further payload data **5001** communicated), is time-aligned with the RS transmission **800**. For instance, if the UE **102** has limited capability to contemporaneously transmit on the data carrier **111** and the auxiliary carrier **199**, a time-duplex scheme can be implemented with respect to the RS transmission **800** and the communicating of the payload data **5001** on the data carrier **111**. For example, the data carrier **111** and the auxiliary carrier **199** can use a common timing reference, e.g., defining start positions of transmission frames, etc. They can include a synchronization implemented between the BS **101** and the RRD **109** and/or between the BS **101** and the UE **102**.

(86) Based on monitoring the RSs **5050** at **4030** and/or **4040**, the RRD **109** can then be configured to provide an appropriate spatial filter that forwards incident signals from the BS **101** in the direction of the UE **102**, and vice versa. Thereby, communicating of the payload data **5001** at **4045** is facilitated.

(87) As illustrated in FIG. 8, it would be optionally possible that the RRD **109**, at some point, provides a report **5060** that is associated with one or more of the receive properties of the RSs **5050**. Then, it would be possible that the BS **101** schedules the communicating on the data carrier **111** based on such report.

(88) Summarizing, dedicated control signaling between the BS and the UE has been disclosed. The control signaling provides a configuration regarding the UE transmitting, e.g., broadcasting, uniquely identifiable RSs for the purpose of selecting the appropriate spatial filter at the RRD.

(89) Here, it would be possible that the UEs connected to the BS on a first carrier frequency associated with the data carrier. Then, the UE can inform the BS that is capable of transmitting RSs at a second carrier frequency associated with the auxiliary carrier.

(90) The BS can then configure the UE to start transmission of an RS, e.g., of beacon signals, with one or more of: a unique identifier; a configurable power level, based on synchronization information. The BS can configure the RRD to estimate, and to reflect toward, the AoA of such a RS received on the second carrier frequency with a configured identifier.

(91) The BS can, at any time, re-configure the UE to turn off/on the RS transmission or to change the identifier optionally the power level. i.e., the configuration can be dynamically set.

(92) It has been shown that the identifier may be an explicit identifier, may be a specific carrier frequency or time pattern or a code-division Multiple Access encoded signal.

(93) The configuration of the UE can be performed as higher-layer control signaling on the first carrier. i.e., it can be transparent to a lower level such as the physical Layer 1, operating on the first carrier frequency.

(94) The second carrier, implementing the auxiliary carrier, could be a Bluetooth or Wi-Fi positioning protocol, a 3GPP positioning RS, a 3GPP supplement link, a discovery signal or a dedicated signal in a licensed/unlicensed frequency band.

(95) The RRD can have one or a set of identifiers it listens to. Likewise, the UE may be re-configured by the BS to match multiple RRDs.

(96) An identifier may be associated with one or multiple polarizations.

(97) An RRD configured with multiple identifiers is assumed to support multiple users simultaneously.

(98) The RRD may report one or more of the following quantities to the BS: AoA; received power level; interference situation on the second carrier. This can be for enhanced scheduling purpose.

(99) The UE loses a communication connection on the auxiliary carrier and the second carrier frequency, there may be a timer. When the timer is expiring, the UE can stop transmission on the auxiliary carrier. The UE can then inform the BS, e.g., using control signaling on the first carrier, that the second carrier frequency is becoming available, upon which the BS may allocate a new second carrier (cf. FIG. 8, request 5010). The BS may provide a new configuration for the RS transmission.

(100) The RS can optionally encode geographic position information of the UE such that the RRD can select the beam towards the UE directly or the assistance of the BS, without AoA estimation.

(101) The transmissions on the data carrier and the auxiliary carrier may be time-synchronized, i.e., transmissions on the first and second carriers may share a common timing reference. For this purpose, the RRD can receive synchronization information from the BS.

(102) The configuration of the reference RS transmission can include a shared identity of the RRD, i.e., contention-based access identities can be possible. This can enable use of the RRD during initial access. The shared identity may be preconfigured list used by multiple UEs in a random-access manner. The broadcasted signal can be reduced to a single bit.

(103) Accordingly, at least the following EXAMPLES have been described above:

(104) Although the invention has been shown and described with respect to certain preferred examples, equivalents and modifications will occur to others skilled in the art upon the reading and understanding of the specification. The present invention includes all such equivalents and modifications and is limited only by the scope of the appended claims.

(105) For illustration, various techniques have been described with respect to an RS transmission implemented at the UE, it would also be possible to implement an RS transmission at the BS. Specifically, it would be possible to, thereby, facilitate angle-of-arrival measurements at the RRD with respect to incident signals from the BS.

Claims

1. A method of operating an access node of a communications network, the access node communicating with a wireless communication device via a reconfigurable repeater device (RRD), the RRD being re-configurable to provide multiple spatial filters, each one of the multiple spatial filters being associated with a respective input spatial direction from which incident signals on a data carrier are accepted and with a respective output spatial direction into which incident signals are reflected or amplified by the RRD, the method comprising: in response to a need to facilitate an angle-of-arrival measurement at the RRD based on reference signals transmitted by the wireless communication device, providing, to the wireless communication device, a configuration of a reference-signal transmission comprising the reference signals, the reference-signal transmission being on an auxiliary carrier different from the data carrier.

2. The method of claim 1, further comprising: providing the RRD with at least a part of the configuration of the reference-signal transmission.

3. The method of claim 1, wherein the configuration comprises at least one identifier to be indicated by reference signals of the reference-signal transmission.

4. The method of claim 3, wherein use of the at least one identifier is contention-based among a plurality of wireless communication devices.

5. The method of claim 3, wherein the at least one identifier is uniquely associated with the wireless communication device or the RRD.

6. The method of claim 1, wherein the configuration comprises a first configuration of at least one

first reference signal of the reference-signal transmission and a second configuration of at least one second reference signal of the reference-signal transmission, wherein the at least one first reference signal is associated with a first polarization of signals on the data carrier and the at least one second reference signal is associated with a second polarization of signals on the data carrier.

7. The method of claim 1, wherein the configuration comprises a transmit power of the reference signals of the reference-signal transmission.

8. The method of claim 1, wherein the configuration comprises repetitive resources for the reference-signal transmission.

9. The method of claim 1, wherein the configuration comprises discovery information for establishing a communication connection between the wireless communication device and the RRD.

10. The method of claim 1, wherein the configuration is provided using a higher-layer control message communicated on the data carrier.

11. The method of claim 1, wherein the wireless communication device is provided with the configuration in response to a respective capability signaling from the wireless communication device.

12. The method of claim 1, wherein the need to facilitate the angle-of-arrival measurement at the RRD is determined based on control signaling from the RRD and/or the wireless communication device to the access node.

13. The method of claim 12, wherein the control signaling is indicative of termination of a communication connection established between the wireless communication device and the RRD using the auxiliary carrier.

14. The method of claim 1, further comprising: receiving, from the RRD, a report associated with the reference signals of the reference-signal transmission, and scheduling said communicating with the wireless communication device based on the report.

15. The method of claim 1, further comprising: time-aligning said communicating with the wireless communication device and the reference-signal transmission.

16. A method of operating a wireless communication device connectable to a communications network, the wireless communication device communicating with an access node of the communications network via a re-configurable repeater device (RRD), the RRD being re-configurable to provide multiple spatial filters, each one of the multiple spatial filters being associated with a respective input spatial direction from which incident signals on a data carrier are accepted and with a respective output spatial direction into which incident signals are reflected or amplified by the RRD, the method comprising: obtaining, from the access node, a configuration of a reference-signal transmission; and transmitting reference signals of the reference-signal transmission to the RRD in accordance with the configuration, to facilitate an angle-of-arrival measurement at the RRD.

17. A method of operating a re-configurable repeater device (RRD), the RRD being reconfigurable to provide multiple spatial filters, each one of the multiple spatial filters being associated with a respective input spatial direction from which incident signals on a data carrier are acceptable and with a respective output spatial direction into which incident signals are reflected or amplified by the RRD, the method comprising: obtaining at least a part of a configuration of a reference-signal transmission by a wireless communication device, monitoring for reference signals of the reference-signal transmission based on the at least a part of the configuration, determining an angle-of-arrival of the reference signals based on said monitoring, and re-configuring to provide a selected spatial filter of the multiple spatial filters based on the angle-of-arrival.
