

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250286763

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

Bayesteh; Alireza et al.

METHOD AND APPARATUS USING HYBRID RF-DOMAIN AND BASEBAND-DOMAIN SENSING SIGNAL

Abstract

A sensing signal may be selected from a sensing signal pool that has been expanded on the basis of one or more extra signal configuration parameters. That is, the sensing signal pool has an increased signature space relative to sensing signals designs that are based on only two signal configuration parameters. Furthermore, an appropriately selected sensing signal may be shown to enable low-complexity and low power mode sensing detection for relatively low capability nodes. A sensing signal may be generated from amongst a plurality of sensing signals that may be understood to form a pool of sensing signals, where the sensing signals in the pool have attributes in both the RF domain and the baseband domain.

Inventors: Bayesteh; Alireza (Brossard, CA), Ma; Jianglei (Ottawa, CA), Tong; Wen (Ottawa, CA)

Applicant: Huawei Technologies Co., Ltd. (Shenzhen, CN)

Family ID: 91194868

Appl. No.: 19/198827

Filed: May 05, 2025

Related U.S. Application Data

parent WO continuation PCT/CN2022/133961 20221124 PENDING child US 19198827

Publication Classification

Int. Cl.: H04L27/26 (20060101); G01S7/00 (20060101); G01S7/282 (20060101); G01S13/86 (20060101); H04W76/11 (20180101)

U.S. Cl.:

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION [0001] This application is a continuation of International Application No. PCT/CN2022/133961, filed on Nov. 24, 2022, titled “METHOD AND APPARATUS USING HYBRID RF-DOMAIN AND BASEBAND-DOMAIN SENSING SIGNAL,” which is hereby incorporated by reference in its entirety.

TECHNICAL FIELD

[0002] The present disclosure relates, generally, to sensing in wireless communication environments and, in particular embodiments, method and apparatus to use, for such sensing, of a hybrid radio-frequency-domain and baseband-domain sensing signal.

BACKGROUND

[0003] Known fifth generation (5G) new radio (NR) mobile wireless communication standards include nodes capable of sensing and nodes capable of communication. It is expected that future networks, i.e., sixth generation (6G) networks, will have nodes capable of both sensing and communication. As a result, the number of sensing nodes and sensing pairs may be expected to scale up significantly as a distribution of nodes becomes increasingly dense. In many sensing applications, a sensing report is generated and transmitted to a network node. The network node is given a task of processing a plurality of received sensing reports and acting on the basis of information obtained through the processing. The context of a received sensing report may be understood to be enhanced by an association between the received sensing report and an identifier (ID) of the sensing node that is the source of the sensing report. Alternatively, the received sensing report may have an association with a sensing session ID. Furthermore, it may be shown to be beneficial to establish mechanisms that allow sensing nodes to distinguish between sensing signals transmitted by different nodes.

SUMMARY

[0004] Aspects of the present application address a problem of distinguishability of sensing signals and a problem of how to allow for a radio frequency (RF) dominant mode of sensing for low processing power nodes. For low processing power nodes, low processing power may be associated to several features of the node. Most importantly, low processing power may be associated to the fact that the node might be in the low power mode for power saving. A sensing signal may be selected from a sensing signal pool that has been expanded on the basis of one or more extra signal configuration parameters. That is, the sensing signal pool has an increased signature space relative to sensing signals designs that are based on only two signal configuration parameters: a starting frequency, $f_{sub,0}$; and a chirp rate, α . Furthermore, an appropriately selected sensing signal may be shown to enable low-complexity and low power mode sensing detection for relatively low capability nodes. A sensing signal may be generated from amongst a plurality of sensing signals that may be understood to form a pool of sensing signals, where the sensing signals in the pool have attributes in both the RF domain and the baseband domain.

[0005] Current sensing solutions are known to draw certain amounts of power and rely on certain amounts of complexity. Additionally, current sensing solutions are known to be limited in their ability to allow a receiver to distinguish between sensing signals transmitted by distinct entities.

[0006] By allowing for low-complexity RF-dominant processing for user equipment (UE) in low power mode, low power consumption and low complexity operation are both enabled. UEs in normal power mode may exploit extra dimensions in the baseband domain to separate sensing signals received from distinct entities. By appropriately processing separate sensing signals, UEs in

normal power mode may achieve a higher resolution sensing.

[0007] According to an aspect of the present disclosure, there is provided a method. The method includes generating a linearly frequency modulated signal, generating a signature function, obtaining a sensing signal by modulating the linearly frequency modulated signal with the signature function and transmitting the sensing signal.

[0008] According to an aspect of the present disclosure, there is provided a device. The device includes a linearly frequency modulated signal generator configured to generate a linearly frequency modulated signal, a signature function generator configured to generate, in a digital domain, a signature function, a multiplier configured to modulate the linearly frequency modulated signal with the signature function to, thereby, obtain a sensing signal and a transmitter configured to transmit the sensing signal.

[0009] According to an aspect of the present disclosure, there is provided an apparatus. The apparatus comprises at least one processor coupled with a memory storing instructions which, when the instructions are executed by the at least one processor, cause the apparatus to carry out the any one of method shown above. The apparatus may be chipsets. or the apparatus may be a module/unit in a device.

[0010] According to an aspect of the present disclosure, there is provided a communication system. The system comprise the device or apparatus mentioned above and a device that receiving the sensing signal.

[0011] According to an aspect of the present disclosure, there is provided a computer program. The computer program comprises instructions which, when the program is executed by a computer, cause the computer to carry out the any one of method shown above.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0012] For a more complete understanding of the present embodiments, and the advantages thereof, reference is now made, by way of example, to the following descriptions taken in conjunction with the accompanying drawings, in which:

[0013] FIG. 1 illustrates, in a schematic diagram, a communication system in which embodiments of the disclosure may occur, the communication system includes multiple example electronic devices and multiple example transmit receive points along with various networks;

[0014] FIG. 2 illustrates, in a block diagram, the communication system of FIG. 1, the communication system includes multiple example electronic devices, an example terrestrial transmit receive point and an example non-terrestrial transmit receive point along with various networks;

[0015] FIG. 3 illustrates, as a block diagram, elements of an example electronic device of FIG. 2, elements of an example terrestrial transmit receive point of FIG. 2 and elements of an example non-terrestrial transmit receive point of FIG. 2, in accordance with aspects of the present application;

[0016] FIG. 4 illustrates, as a block diagram, various modules that may be included in an example electronic device, an example terrestrial transmit receive point and an example non-terrestrial transmit receive point, in accordance with aspects of the present application;

[0017] FIG. 5 illustrates, as a block diagram, a sensing management function, in accordance with aspects of the present application;

[0018] FIG. 6 illustrates a wireless communication environment including first TRP, a second TRP, a first UE, a second UE, a first reflector and a second reflector;

[0019] FIG. 7 illustrates transmitter elements involved in generating a sensing signal for transmission, according to aspects of the present application;

[0020] FIG. **8A** illustrates receiver elements involved in analyzing a sensing signal after the sensing signal has been received, according to aspects of the present application;

[0021] FIG. **8B** illustrates receiver elements involved in analyzing a sensing signal after the sensing signal has been received, in a configuration distinct from the receiver elements of FIG. **8A**, according to aspects of the present application;

[0022] FIG. **9** illustrates an example frequency hopping implementation for a signature function, according to aspects of the present application;

[0023] FIG. **10** illustrates a plot of output power with respect to delay for output from the chirp processing receiver in FIG. **8B** given a first received sensing signal as input, according to aspects of the present application;

[0024] FIG. **11** illustrates a plot of output power with respect to delay for output from the chirp processing receiver in FIG. **8B** given a second received sensing signal as input, according to aspects of the present application;

[0025] FIG. **12** illustrates an example base sequence codebook implementation for a signature function, according to aspects of the present application;

[0026] FIG. **13** illustrates a plot of output power with respect to delay to show an example delta train, according to aspects of the present application;

[0027] FIG. **14** illustrates a plot of output power with respect to delay for output from the chirp processing receiver in FIG. **8B** given a received base sequence codebook-based sensing signal as input, according to aspects of the present application;

[0028] FIG. **15** illustrates a table that associates a quantity of signature functions in terms of the number of non-zero IDFT codeword elements, according to aspects of the present application;

[0029] FIG. **16** illustrates transmitter elements involved in generating a sensing signal for transmission, according to aspects of the present application; and

[0030] FIG. **17** illustrates another transmitter element involved in generating a sensing signal for transmission, according to aspects of the present application.

DETAILED DESCRIPTION

[0031] For illustrative purposes, specific example embodiments will now be explained in greater detail in conjunction with the figures.

[0032] The embodiments set forth herein represent information sufficient to practice the claimed subject matter and illustrate ways of practicing such subject matter. Upon reading the following description in light of the accompanying figures, those of skill in the art will understand the concepts of the claimed subject matter and will recognize applications of these concepts not particularly addressed herein. It should be understood that these concepts and applications fall within the scope of the disclosure and the accompanying claims.

[0033] Moreover, it will be appreciated that any module, component, or device disclosed herein that executes instructions may include, or otherwise have access to, a non-transitory computer/processor readable storage medium or media for storage of information, such as computer/processor readable instructions, data structures, program modules and/or other data. A non-exhaustive list of examples of non-transitory computer/processor readable storage media includes magnetic cassettes, magnetic tape, magnetic disk storage or other magnetic storage devices, optical disks such as compact disc read-only memory (CD-ROM), digital video discs or digital versatile discs (i.e., DVDs), Blu-ray Disc™, or other optical storage, volatile and non-volatile, removable and non-removable media implemented in any method or technology, random-access memory (RAM), read-only memory (ROM), electrically erasable programmable read-only memory (EEPROM), flash memory or other memory technology. Any such non-transitory computer/processor storage media may be part of a device or accessible or connectable thereto. Computer/processor readable/executable instructions to implement an application or module described herein may be stored or otherwise held by such non-transitory computer/processor readable storage media.

[0034] Referring to FIG. 1, as an illustrative example without limitation, a simplified schematic illustration of a communication system is provided. The communication system **100** comprises a radio access network **120**. The radio access network **120** may be a next generation (e.g., sixth generation, “6G,” or later) radio access network, or a legacy (e.g., 5G, 4G, 3G or 2G) radio access network. One or more communication electric device (ED) **110a**, **110b**, **110c**, **110d**, **110e**, **110f**, **110g**, **110h**, **110i**, **110j** (generically referred to as **110**) may be interconnected to one another and/or connected to one or more network nodes (**170a**, **170b**, generically referred to as **170**) in the radio access network **120**. A core network **130** may be a part of the communication system and may be dependent or independent of the radio access technology used in the communication system **100**. Also the communication system **100** comprises a public switched telephone network (PSTN) **140**, the internet **150**, and other networks **160**.

[0035] FIG. 2 illustrates an example communication system **100**. In general, the communication system **100** enables multiple wireless or wired elements to communicate information. The purpose of the communication system **100** may be to provide information, such as voice, data, video, signaling, and/or text, via broadcast, multicast and unicast, etc. The communication system **100** may operate by sharing resources, such as carrier spectrum bandwidth, between its constituent elements. The communication system **100** may include a terrestrial communication system and/or a non-terrestrial communication system. The communication system **100** may provide a wide range of communication services and applications (such as earth monitoring, remote sensing, passive sensing and positioning, navigation and tracking, autonomous delivery and mobility, etc.). The communication system **100** may provide a high degree of availability and robustness through a joint operation of a terrestrial communication system and a non-terrestrial communication system. For example, integrating a non-terrestrial communication system (or components thereof) into a terrestrial communication system can result in what may be considered a heterogeneous network comprising multiple layers. Compared to conventional communication networks, the heterogeneous network may achieve better overall performance through efficient multi-link joint operation, more flexible functionality sharing and faster physical layer link switching between terrestrial networks and non-terrestrial networks.

[0036] The terrestrial communication system and the non-terrestrial communication system could be considered sub-systems of the communication system. In the example shown in FIG. 2, the communication system **100** includes electronic devices (ED) **110a**, **110b**, **110c**, **110d** (generically referred to as ED **110**), radio access networks (RANs) **120a**, **120b**, a non-terrestrial communication network **120c**, a core network **130**, a public switched telephone network (PSTN) **140**, the Internet **150** and other networks **160**. The RANs **120a**, **120b** include respective base stations (BSs) **170a**, **170b**, which may be generically referred to as terrestrial transmit and receive points (T-TRPs) **170a**, **170b**. The non-terrestrial communication network **120c** includes an access node **172**, which may be generically referred to as a non-terrestrial transmit and receive point (NT-TRP) **172**.

[0037] Any ED **110** may be alternatively or additionally configured to interface, access, or communicate with any T-TRP **170a**, **170b** and NT-TRP **172**, the Internet **150**, the core network **130**, the PSTN **140**, the other networks **160**, or any combination of the preceding. In some examples, the ED **110a** may communicate an uplink and/or downlink transmission over a terrestrial air interface **190a** with T-TRP **170a**. In some examples, the EDs **110a**, **110b**, **110c** and **110d** may also communicate directly with one another via one or more sidelink air interfaces **190b**. In some examples, the ED **110d** may communicate an uplink and/or downlink transmission over a non-terrestrial air interface **190c** with NT-TRP **172**.

[0038] The air interfaces **190a** and **190b** may use similar communication technology, such as any suitable radio access technology. For example, the communication system **100** may implement one or more channel access methods, such as code division multiple access (CDMA), space division multiple access (SDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal FDMA (OFDMA), single-carrier FDMA (SC-FDMA) or Direct

Fourier Transform spread OFDMA (FT-OFDMA) in the air interfaces **190a** and **190b**. The air interfaces **190a** and **190b** may utilize other higher dimension signal spaces, which may involve a combination of orthogonal and/or non-orthogonal dimensions.

[0039] The non-terrestrial air interface **190c** can enable communication between the ED **110d** and one or multiple NT-TRPs **172** via a wireless link. In the following, “a wireless link” may be referenced, more simply, as “a link.” For some examples, the link is a dedicated connection for unicast transmission, a connection for broadcast transmission, or a connection between a group of EDs **110** and one or multiple NT-TRPs **175** for multicast transmission.

[0040] The RANs **120a** and **120b** are in communication with the core network **130** to provide the EDs **110a**, **110b**, **110c** with various services such as voice, data and other services. The RANs **120a** and **120b** and/or the core network **130** may be in direct or indirect communication with one or more other RANs (not shown), which may or may not be directly served by core network **130** and may, or may not, employ the same radio access technology as RAN **120a**, RAN **120b** or both. The core network **130** may also serve as a gateway access between (i) the RANs **120a** and **120b** or the EDs **110a**, **110b**, **110c** or both, and (ii) other networks (such as the PSTN **140**, the Internet **150**, and the other networks **160**). In addition, some or all of the EDs **110a**, **110b**, **110c** may include functionality for communicating with different wireless networks over different wireless links using different wireless technologies and/or protocols. Instead of wireless communication (or in addition thereto), the EDs **110a**, **110b**, **110c** may communicate via wired communication channels to a service provider or switch (not shown) and to the Internet **150**. The PSTN **140** may include circuit switched telephone networks for providing plain old telephone service (POTS). The Internet **150** may include a network of computers and subnets (intranets) or both and incorporate protocols, such as Internet Protocol (IP), Transmission Control Protocol (TCP), User Datagram Protocol (UDP). The EDs **110a**, **110b**, **110c** may be multimode devices capable of operation according to multiple radio access technologies and may incorporate multiple transceivers necessary to support such.

[0041] FIG. 3 illustrates another example of an ED **110** and a base station **170a**, **170b** and/or **170c**. The ED **110** is used to connect persons, objects, machines, etc. The ED **110** may be widely used in various scenarios, for example, cellular communications, device-to-device (D2D), vehicle to everything (V2X), peer-to-peer (P2P), machine-to-machine (M2M), machine-type communications (MTC), Internet of things (IoT), virtual reality (VR), augmented reality (AR), mixed reality (MR), metaverse, digital twin, industrial control, self-driving, remote medical, smart grid, smart furniture, smart office, smart wearable, smart transportation, smart city, drones, robots, remote sensing, passive sensing, positioning, navigation and tracking, autonomous delivery and mobility, etc.

[0042] Each ED **110** represents any suitable end user device for wireless operation and may include such devices (or may be referred to) as a user equipment/device (UE), a wireless transmit/receive unit (WTRU), a mobile station, a fixed or mobile subscriber unit, a cellular telephone, a station (STA), a machine type communication (MTC) device, a personal digital assistant (PDA), a smartphone, a laptop, a computer, a tablet, a wireless sensor, a consumer electronics device, wearable devices such as a watch, head mounted equipment, a pair of glasses, a smart book, a vehicle, a car, a truck, a bus, a train, or an IoT device, an industrial device, or apparatus (e.g., communication module, modem, or chip) in the forgoing devices, among other possibilities. Future generation EDs **110** may be referred to using other terms. The base stations **170a** and **170b** each T-TRPs and will, hereafter, be referred to as T-TRP **170**. Also shown in FIG. 3, a NT-TRP will hereafter be referred to as NT-TRP **172**. Each ED **110** connected to the T-TRP **170** and/or the NT-TRP **172** can be dynamically or semi-statically turned-on (i.e., established, activated or enabled), turned-off (i.e., released, deactivated or disabled) and/or configured in response to one of more of: connection availability; and connection necessity.

[0043] The ED **110** includes a transmitter **201** and a receiver **203** coupled to one or more antennas **204**. Only one antenna **204** is illustrated. One, some, or all of the antennas **204** may, alternatively,

be panels. The transmitter **201** and the receiver **203** may be integrated, e.g., as a transceiver. The transceiver is configured to modulate data or other content for transmission by the at least one antenna **204** or by a network interface controller (NIC). The transceiver may also be configured to demodulate data or other content received by the at least one antenna **204**. Each transceiver includes any suitable structure for generating signals for wireless or wired transmission and/or processing signals received wirelessly or by wire. Each antenna **204** includes any suitable structure for transmitting and/or receiving wireless or wired signals.

[0044] The ED **110** may include at least one memory **208**. The memory **208** stores instructions and/or data used, generated, or collected by the ED **110**. For example, the memory **208** could store software instructions or modules configured to implement some or all of the functionality and/or embodiments described herein and that are executed by one or more processing unit(s) (e.g., a processor **210**). Each memory **208** includes any suitable volatile and/or non-volatile storage and retrieval device(s). Any suitable type of memory may be used, such as random access memory (RAM), read only memory (ROM), hard disk, optical disc, subscriber identity module (SIM) card, memory stick, secure digital (SD) memory card, on-processor cache and the like.

[0045] The ED **110** may further include one or more input/output devices (not shown) or interfaces (such as a wired interface to the Internet **150** in FIG. **1**). The input/output devices permit interaction with a user or other devices in the network. Each input/output device includes any suitable structure for providing information to, or receiving information from, a user, such as through operation as a speaker, a microphone, a keypad, a keyboard, a display or a touch screen, including network interface communications.

[0046] The ED **110** includes the processor **210** for performing operations including those operations related to preparing a transmission for uplink transmission to the NT-TRP **172** and/or the T-TRP **170**, those operations related to processing downlink transmissions received from the NT-TRP **172** and/or the T-TRP **170**, and those operations related to processing sidelink transmission to and from another ED **110**. Processing operations related to preparing a transmission for uplink transmission may include operations such as encoding, modulating, transmit beamforming and generating symbols for transmission. Processing operations related to processing downlink transmissions may include operations such as receive beamforming, demodulating and decoding received symbols. Depending upon the embodiment, a downlink transmission may be received by the receiver **203**, possibly using receive beamforming, and the processor **210** may extract signaling from the downlink transmission (e.g., by detecting and/or decoding the signaling). An example of signaling may be a reference signal transmitted by the NT-TRP **172** and/or by the T-TRP **170**. In some embodiments, the processor **210** implements the transmit beamforming and/or the receive beamforming based on the indication of beam direction, e.g., beam angle information (BAI), received from the T-TRP **170**. In some embodiments, the processor **210** may perform operations relating to network access (e.g., initial access) and/or downlink synchronization, such as operations relating to detecting a synchronization sequence, decoding and obtaining the system information, etc. In some embodiments, the processor **210** may perform channel estimation, e.g., using a reference signal received from the NT-TRP **172** and/or from the T-TRP **170**.

[0047] Although not illustrated, the processor **210** may form part of the transmitter **201** and/or part of the receiver **203**. Although not illustrated, the memory **208** may form part of the processor **210**.

[0048] The processor **210**, the processing components of the transmitter **201** and the processing components of the receiver **203** may each be implemented by the same or different one or more processors that are configured to execute instructions stored in a memory (e.g., the in memory **208**). Alternatively, some or all of the processor **210**, the processing components of the transmitter **201** and the processing components of the receiver **203** may each be implemented using dedicated circuitry, such as a programmed field-programmable gate array (FPGA), a Central Processing Unit (CPU), a graphical processing unit (GPU), or an application-specific integrated circuit (ASIC).

[0049] The T-TRP **170** may be known by other names in some implementations, such as a base

station, a base transceiver station (BTS), a radio base station, a network node, a network device, a device on the network side, a transmit/receive node, a Node B, an evolved NodeB (eNodeB or eNB), a Home eNodeB, a next Generation NodeB (gNB), a transmission point (TP), a site controller, an access point (AP), a wireless router, a relay station, a remote radio head, a terrestrial node, a terrestrial network device, a terrestrial base station, a base band unit (BBU), a remote radio unit (RRU), an active antenna unit (AAU), a remote radio head (RRH), a central unit (CU), a distribute unit (DU), a positioning node, among other possibilities. The T-TRP **170** may be a macro BS, a pico BS, a relay node, a donor node, or the like, or combinations thereof. The T-TRP **170** may refer to the forgoing devices or refer to apparatus (e.g., a communication module, a modem or a chip) in the forgoing devices.

[0050] In some embodiments, the parts of the T-TRP **170** may be distributed. For example, some of the modules of the T-TRP **170** may be located remote from the equipment that houses antennas **256** for the T-TRP **170**, and may be coupled to the equipment that houses antennas **256** over a communication link (not shown) sometimes known as front haul, such as common public radio interface (CPRI). Therefore, in some embodiments, the term T-TRP **170** may also refer to modules on the network side that perform processing operations, such as determining the location of the ED **110**, resource allocation (scheduling), message generation, and encoding/decoding, and that are not necessarily part of the equipment that houses antennas **256** of the T-TRP **170**. The modules may also be coupled to other T-TRPs. In some embodiments, the T-TRP **170** may actually be a plurality of T-TRPs that are operating together to serve the ED **110**, e.g., through the use of coordinated multipoint transmissions.

[0051] As illustrated in FIG. **3**, the T-TRP **170** includes at least one transmitter **252** and at least one receiver **254** coupled to one or more antennas **256**. Only one antenna **256** is illustrated. One, some, or all of the antennas **256** may, alternatively, be panels. The transmitter **252** and the receiver **254** may be integrated as a transceiver. The T-TRP **170** further includes a processor **260** for performing operations including those related to: preparing a transmission for downlink transmission to the ED **110**; processing an uplink transmission received from the ED **110**; preparing a transmission for backhaul transmission to the NT-TRP **172**; and processing a transmission received over backhaul from the NT-TRP **172**. Processing operations related to preparing a transmission for downlink or backhaul transmission may include operations such as encoding, modulating, precoding (e.g., multiple input multiple output, “MIMO,” precoding), transmit beamforming and generating symbols for transmission. Processing operations related to processing received transmissions in the uplink or over backhaul may include operations such as receive beamforming, demodulating received symbols and decoding received symbols. The processor **260** may also perform operations relating to network access (e.g., initial access) and/or downlink synchronization, such as generating the content of synchronization signal blocks (SSBs), generating the system information, etc. In some embodiments, the processor **260** also generates an indication of beam direction, e.g., BAI, which may be scheduled for transmission by a scheduler **253**. The processor **260** performs other network-side processing operations described herein, such as determining the location of the ED **110**, determining where to deploy the NT-TRP **172**, etc. In some embodiments, the processor **260** may generate signaling, e.g., to configure one or more parameters of the ED **110** and/or one or more parameters of the NT-TRP **172**. Any signaling generated by the processor **260** is sent by the transmitter **252**. Note that “signaling,” as used herein, may alternatively be called control signaling. Dynamic signaling may be transmitted in a control channel, e.g., a physical downlink control channel (PDCCH) and static, or semi-static, higher layer signaling may be included in a packet transmitted in a data channel, e.g., in a physical downlink shared channel (PDSCH).

[0052] The scheduler **253** may be coupled to the processor **260**. The scheduler **253** may be included within, or operated separately from, the T-TRP **170**. The scheduler **253** may schedule uplink, downlink and/or backhaul transmissions, including issuing scheduling grants and/or configuring scheduling-free (“configured grant”) resources.

[0053] The T-TRP **170** further includes a memory **258** for storing information and data. The memory **258** stores instructions and data used, generated, or collected by the T-TRP **170**. For example, the memory **258** could store software instructions or modules configured to implement some or all of the functionality and/or embodiments described herein and that are executed by the processor **260**.

[0054] Although not illustrated, the processor **260** may form part of the transmitter **252** and/or part of the receiver **254**. Also, although not illustrated, the processor **260** may implement the scheduler **253**. Although not illustrated, the memory **258** may form part of the processor **260**.

[0055] The processor **260**, the scheduler **253**, the processing components of the transmitter **252** and the processing components of the receiver **254** may each be implemented by the same, or different one of, one or more processors that are configured to execute instructions stored in a memory, e.g., in the memory **258**. Alternatively, some or all of the processor **260**, the scheduler **253**, the processing components of the transmitter **252** and the processing components of the receiver **254** may be implemented using dedicated circuitry, such as a FPGA, a CPU, a GPU or an ASIC.

[0056] Notably, the NT-TRP **172** is illustrated as a drone only as an example, the NT-TRP **172** may be implemented in any suitable non-terrestrial form, such as high altitude platforms, satellite, high altitude platform as international mobile telecommunication base stations and unmanned aerial vehicles, which forms will be discussed hereinafter. Also, the NT-TRP **172** may be known by other names in some implementations, such as a non-terrestrial node, a non-terrestrial network device, or a non-terrestrial base station. The NT-TRP **172** includes a transmitter **272** and a receiver **274** coupled to one or more antennas **280**. Only one antenna **280** is illustrated. One, some, or all of the antennas may alternatively be panels. The transmitter **272** and the receiver **274** may be integrated as a transceiver. The NT-TRP **172** further includes a processor **276** for performing operations including those related to: preparing a transmission for downlink transmission to the ED **110**; processing an uplink transmission received from the ED **110**; preparing a transmission for backhaul transmission to T-TRP **170**; and processing a transmission received over backhaul from the T-TRP **170**. Processing operations related to preparing a transmission for downlink or backhaul transmission may include operations such as encoding, modulating, precoding (e.g., MIMO precoding), transmit beamforming and generating symbols for transmission. Processing operations related to processing received transmissions in the uplink or over backhaul may include operations such as receive beamforming, demodulating received signals and decoding received symbols. In some embodiments, the processor **276** implements the transmit beamforming and/or receive beamforming based on beam direction information (e.g., BAI) received from the T-TRP **170**. In some embodiments, the processor **276** may generate signaling, e.g., to configure one or more parameters of the ED **110**. In some embodiments, the NT-TRP **172** implements physical layer processing but does not implement higher layer functions such as functions at the medium access control (MAC) or radio link control (RLC) layer. As this is only an example, more generally, the NT-TRP **172** may implement higher layer functions in addition to physical layer processing.

[0057] The NT-TRP **172** further includes a memory **278** for storing information and data. Although not illustrated, the processor **276** may form part of the transmitter **272** and/or part of the receiver **274**. Although not illustrated, the memory **278** may form part of the processor **276**.

[0058] The processor **276**, the processing components of the transmitter **272** and the processing components of the receiver **274** may each be implemented by the same or different one or more processors that are configured to execute instructions stored in a memory, e.g., in the memory **278**. Alternatively, some or all of the processor **276**, the processing components of the transmitter **272** and the processing components of the receiver **274** may be implemented using dedicated circuitry, such as a programmed FPGA, a CPU, a GPU or an ASIC. In some embodiments, the NT-TRP **172** may actually be a plurality of NT-TRPs that are operating together to serve the ED **110**, e.g., through coordinated multipoint transmissions.

[0059] The T-TRP **170**, the NT-TRP **172**, and/or the ED **110** may include other components, but

these have been omitted for the sake of clarity.

[0060] One or more steps of the embodiment methods provided herein may be performed by corresponding units or modules, according to FIG. 4. FIG. 4 illustrates units or modules in a device, such as in the ED **110**, in the T-TRP **170** or in the NT-TRP **172**. For example, a signal may be transmitted by a transmitting unit or by a transmitting module. A signal may be received by a receiving unit or by a receiving module. A signal may be processed by a processing unit or a processing module. Other steps may be performed by an artificial intelligence (AI) or machine learning (ML) module. The respective units or modules may be implemented using hardware, one or more components or devices that execute software, or a combination thereof. For instance, one or more of the units or modules may be an integrated circuit, such as a programmed FPGA, a CPU, a GPU or an ASIC. It will be appreciated that where the modules are implemented using software for execution by a processor, for example, the modules may be retrieved by a processor, in whole or part as needed, individually or together for processing, in single or multiple instances, and that the modules themselves may include instructions for further deployment and instantiation. The transmitter mentioned with reference to FIG. 3 may be a detailed implementation for the transmitting module. The receiver mentioned with reference to FIG. 3 may be a detailed implementation for the receiving module. The processor mentioned with reference to FIG. 3 may be a detailed implementation for the processing module.

[0061] Additional details regarding the EDs **110**, the T-TRP **170** and the NT-TRP **172** are known to those of skill in the art. As such, these details are omitted here.

[0062] An air interface generally includes a number of components and associated parameters that collectively specify how a transmission is to be sent and/or received over a wireless communications link between two or more communicating devices. For example, an air interface may include one or more components defining the waveform(s), frame structure(s), multiple access scheme(s), protocol(s), coding scheme(s) and/or modulation scheme(s) for conveying information (e.g., data) over a wireless communications link. The wireless communications link may support a link between a radio access network and user equipment (e.g., a “Uu” link), and/or the wireless communications link may support a link between device and device, such as between two user equipments (e.g., a “sidelink”), and/or the wireless communications link may support a link between a non-terrestrial (NT)-communication network and user equipment (UE). The following are some examples for the above components.

[0063] A waveform component may specify a shape and form of a signal being transmitted. Waveform options may include orthogonal multiple access waveforms and non-orthogonal multiple access waveforms. Non-limiting examples of such waveform options include Orthogonal Frequency Division Multiplexing (OFDM), Direct Fourier Transform spread OFDM (DFT-OFDM), Filtered OFDM (f-OFDM), Time windowing OFDM, Filter Bank Multicarrier (FBMC), Universal Filtered Multicarrier (UFMC), Generalized Frequency Division Multiplexing (GFDM), Wavelet Packet Modulation (WPM), Faster Than Nyquist (FTN) Waveform and low Peak to Average Power Ratio Waveform (low PAPR WF).

[0064] A frame structure component may specify a configuration of a frame or group of frames. The frame structure component may indicate one or more of a time, frequency, pilot signature, code, subcarrier spacing, cyclic prefix length or other parameter of the frame or group of frames. More details of frame structure will be discussed hereinafter.

[0065] A multiple access scheme component may specify multiple access technique options, including technologies defining how communicating devices share a common physical channel, such as: TDMA; FDMA; CDMA; SDMA; OFDMA; SC-FDMA; Low Density Signature Multicarrier CDMA (LDS-MC-CDMA); Non-Orthogonal Multiple Access (NOMA); Pattern Division Multiple Access (PDMA); Lattice Partition Multiple Access (LPMA); Resource Spread Multiple Access (RSMA); and Sparse Code Multiple Access (SCMA). Furthermore, multiple access technique options may include: scheduled access vs. non-scheduled access, also known as

grant-free access; non-orthogonal multiple access vs. orthogonal multiple access, e.g., via a dedicated channel resource (e.g., no sharing between multiple communicating devices); contention-based shared channel resources vs. non-contention-based shared channel resources; and cognitive radio-based access.

[0066] A hybrid automatic repeat request (HARQ) protocol component may specify how a transmission and/or a re-transmission is to be made. Non-limiting examples of transmission and/or re-transmission mechanism options include those that specify a scheduled data pipe size, a signaling mechanism for transmission and/or re-transmission and a re-transmission mechanism.

[0067] A coding and modulation component may specify how information being transmitted may be encoded/decoded and modulated/demodulated for transmission/reception purposes. Coding may refer to methods of error detection and forward error correction. Non-limiting examples of coding options include turbo trellis codes, turbo product codes, fountain codes, low-density parity check codes and polar codes. Modulation may refer, simply, to the constellation (including, for example, the modulation technique and order), or more specifically to various types of advanced modulation methods such as hierarchical modulation and low PAPR modulation.

[0068] In some embodiments, the air interface may be a “one-size-fits-all” concept. For example, it may be that the components within the air interface cannot be changed or adapted once the air interface is defined. In some implementations, only limited parameters or modes of an air interface, such as a cyclic prefix (CP) length or a MIMO mode, can be configured. In some embodiments, an air interface design may provide a unified or flexible framework to support frequencies below known 6 GHz bands and frequencies beyond the 6 GHz bands (e.g., mmWave bands) for both licensed and unlicensed access. As an example, flexibility of a configurable air interface provided by a scalable numerology and symbol duration may allow for transmission parameter optimization for different spectrum bands and for different services/devices. As another example, a unified air interface may be self-contained in a frequency domain and a frequency domain self-contained design may support more flexible RAN slicing through channel resource sharing between different services in both frequency and time.

[0069] A frame structure is a feature of the wireless communication physical layer that defines a time domain signal transmission structure to, e.g., allow for timing reference and timing alignment of basic time domain transmission units. Wireless communication between communicating devices may occur on time-frequency resources governed by a frame structure. The frame structure may, sometimes, instead be called a radio frame structure.

[0070] Depending upon the frame structure and/or configuration of frames in the frame structure, frequency division duplex (FDD) and/or time-division duplex (TDD) and/or full duplex (FD) communication may be possible. FDD communication is when transmissions in different directions (e.g., uplink vs. downlink) occur in different frequency bands. TDD communication is when transmissions in different directions (e.g., uplink vs. downlink) occur over different time durations. FD communication is when transmission and reception occur on the same time-frequency resource, i.e., a device can both transmit and receive on the same frequency resource contemporaneously.

[0071] One example of a frame structure is a frame structure, specified for use in the known long-term evolution (LTE) cellular systems, having the following specifications: each frame is 10 ms in duration; each frame has 10 subframes, which subframes are each 1 ms in duration; each subframe includes two slots, each of which slots is 0.5 ms in duration; each slot is for the transmission of seven OFDM symbols (assuming normal CP); each OFDM symbol has a symbol duration and a particular bandwidth (or partial bandwidth or bandwidth partition) related to the number of subcarriers and subcarrier spacing; the frame structure is based on OFDM waveform parameters such as subcarrier spacing and CP length (where the CP has a fixed length or limited length options); and the switching gap between uplink and downlink in TDD is specified as the integer time of OFDM symbol duration.

[0072] Another example of a frame structure is a frame structure, specified for use in the known

new radio (NR) cellular systems, having the following specifications: multiple subcarrier spacings are supported, each subcarrier spacing corresponding to a respective numerology; the frame structure depends on the numerology but, in any case, the frame length is set at 10 ms and each frame consists of ten subframes, each subframe of 1 ms duration; a slot is defined as 14 OFDM symbols; and slot length depends upon the numerology. For example, the NR frame structure for normal CP 15 kHz subcarrier spacing (“numerology 1”) and the NR frame structure for normal CP 30 kHz subcarrier spacing (“numerology 2”) are different. For 15 kHz subcarrier spacing, the slot length is 1 ms and, for 30 kHz subcarrier spacing, the slot length is 0.5 ms. The NR frame structure may have more flexibility than the LTE frame structure.

[0073] Another example of a frame structure is, e.g., for use in a 6G network or a later network. In a flexible frame structure, a symbol block may be defined to have a duration that is the minimum duration of time that may be scheduled in the flexible frame structure. A symbol block may be a unit of transmission having an optional redundancy portion (e.g., CP portion) and an information (e.g., data) portion. An OFDM symbol is an example of a symbol block. A symbol block may alternatively be called a symbol. Embodiments of flexible frame structures include different parameters that may be configurable, e.g., frame length, subframe length, symbol block length, etc. A non-exhaustive list of possible configurable parameters, in some embodiments of a flexible frame structure, includes: frame length; subframe duration; slot configuration; subcarrier spacing (SCS); flexible transmission duration of basic transmission unit; and flexible switch gap.

[0074] The frame length need not be limited to 10 ms and the frame length may be configurable and change over time. In some embodiments, each frame includes one or multiple downlink synchronization channels and/or one or multiple downlink broadcast channels and each synchronization channel and/or broadcast channel may be transmitted in a different direction by different beamforming. The frame length may be more than one possible value and configured based on the application scenario. For example, autonomous vehicles may require relatively fast initial access, in which case the frame length may be set to 5 ms for autonomous vehicle applications. As another example, smart meters on houses may not require fast initial access, in which case the frame length may be set as 20 ms for smart meter applications.

[0075] A subframe might or might not be defined in the flexible frame structure, depending upon the implementation. For example, a frame may be defined to include slots, but no subframes. In frames in which a subframe is defined, e.g., for time domain alignment, the duration of the subframe may be configurable. For example, a subframe may be configured to have a length of 0.1 ms or 0.2 ms or 0.5 ms or 1 ms or 2 ms or 5 ms, etc. In some embodiments, if a subframe is not needed in a particular scenario, then the subframe length may be defined to be the same as the frame length or not defined.

[0076] A slot might or might not be defined in the flexible frame structure, depending upon the implementation. In frames in which a slot is defined, then the definition of a slot (e.g., in time duration and/or in number of symbol blocks) may be configurable. In one embodiment, the slot configuration is common to all UEs **110** or a group of UEs **110**. For this case, the slot configuration information may be transmitted to the UEs **110** in a broadcast channel or common (or group) control channel(s). In other embodiments, the slot configuration may be UE specific, in which case the slot configuration information may be transmitted in a UE-specific control channel. In some embodiments, the slot configuration signaling can be transmitted together with frame configuration signaling and/or subframe configuration signaling. In other embodiments, the slot configuration may be transmitted independently from the frame configuration signaling and/or subframe configuration signaling. In general, the slot configuration may be system common, base station common, UE group common or UE specific.

[0077] The SCS may range from 15 KHz to 480 KHz. The SCS may vary with the frequency of the spectrum and/or maximum UE speed to minimize the impact of Doppler shift and phase noise. In some examples, there may be separate transmission and reception frames and the SCS of symbols

in the reception frame structure may be configured independently from the SCS of symbols in the transmission frame structure. The SCS in a reception frame may be different from the SCS in a transmission frame. In some examples, the SCS of each transmission frame may be half the SCS of each reception frame. If the SCS between a reception frame and a transmission frame is different, the difference does not necessarily have to scale by a factor of two, e.g., if more flexible symbol durations are implemented using inverse discrete Fourier transform (IDFT) instead of fast Fourier transform (FFT). Additional examples of frame structures can be used with different SCSs.

[0078] The above mentioned configuration parameters may be signaled via, but not limited to, radio resource control (RRC) layer signaling, media access control (MAC) layer signaling, physical layer signaling (e.g., downlink control information) or any combination.

[0079] The basic transmission unit may be a symbol block (alternatively called a symbol), which, in general, includes a redundancy portion (referred to as the CP) and an information (e.g., data) portion. In some embodiments, the CP may be omitted from the symbol block. The CP length may be flexible and configurable. The CP length may be fixed within a frame or flexible within a frame and the CP length may possibly change from one frame to another, or from one group of frames to another group of frames, or from one subframe to another subframe, or from one slot to another slot, or dynamically from one scheduling to another scheduling. The information (e.g., data) portion may be flexible and configurable. Another possible parameter relating to a symbol block that may be defined is ratio of CP duration to information (e.g., data) duration. In some embodiments, the symbol block length may be adjusted according to: a channel condition (e.g., multi-path delay, Doppler); and/or a latency requirement; and/or an available time duration. As another example, a symbol block length may be adjusted to fit an available time duration in the frame.

[0080] A frame may include both a downlink portion, for downlink transmissions from a base station **170**, and an uplink portion, for uplink transmissions from the UEs **110**. A gap may be present between each uplink and downlink portion, which gap is referred to as a switching gap. The switching gap length (duration) may be configurable. A switching gap duration may be fixed within a frame or flexible within a frame and a switching gap duration may possibly change from one frame to another, or from one group of frames to another group of frames, or from one subframe to another subframe, or from one slot to another slot, or dynamically from one scheduling to another scheduling.

[0081] A device, such as a base station **170**, may provide coverage over a cell. Wireless communication with the device may occur over one or more carrier frequencies. A carrier frequency will be referred to as a carrier. A carrier may alternatively be called a component carrier (CC). A carrier may be characterized by its bandwidth and a reference frequency, e.g., the center frequency of the carrier, the lowest frequency of the carrier, the highest frequency of the carrier or a reference point that is outside the carrier and an offset. A carrier may be on a licensed spectrum or an unlicensed spectrum. Wireless communication with the device may also, or instead, occur over one or more bandwidth parts (BWPs). For example, a carrier may have one or more BWPs. More generally, wireless communication with the device may occur over spectrum. The spectrum may comprise one or more carriers and/or one or more BWPs.

[0082] A cell may include one or multiple downlink resources and, optionally, one or multiple uplink resources. A cell may include one or multiple uplink resources and, optionally, one or multiple downlink resources. A cell may include both one or multiple downlink resources and one or multiple uplink resources. As an example, a cell might only include one downlink carrier/BWP, or only include one uplink carrier/BWP, or include multiple downlink carriers/BWPs, or include multiple uplink carriers/BWPs, or include one downlink carrier/BWP and one uplink carrier/BWP, or include one downlink carrier/BWP and multiple uplink carriers/BWPs, or include multiple downlink carriers/BWPs and one uplink carrier/BWP, or include multiple downlink carriers/BWPs and multiple uplink carriers/BWPs. In some embodiments, a cell may, instead or additionally,

include one or multiple sidelink resources, including sidelink transmitting and receiving resources. [0083] A BWP is a set of contiguous or non-contiguous frequency subcarriers on a carrier, or a set of contiguous or non-contiguous frequency subcarriers on multiple carriers, or a set of non-contiguous or contiguous frequency subcarriers, which may have one or more carriers. [0084] In some embodiments, a carrier may have one or more BWPs, e.g., a carrier may have a bandwidth of 20 MHz and consist of one BWP or a carrier may have a bandwidth of 80 MHz and consist of two adjacent contiguous BWPs, etc. In other embodiments, a BWP may have one or more carriers, e.g., a BWP may have a bandwidth of 40 MHz and consist of two adjacent contiguous carriers, where each carrier has a bandwidth of 20 MHz. In some embodiments, a BWP may comprise non-contiguous spectrum resources, which consists of multiple non-contiguous multiple carriers, where the first carrier of the non-contiguous multiple carriers may be in the mmW band, the second carrier may be in a low band (such as the 2 GHz band), the third carrier (if it exists) may be in THz band and the fourth carrier (if it exists) may be in visible light band. Resources in one carrier which belong to the BWP may be contiguous or non-contiguous. In some embodiments, a BWP has non-contiguous spectrum resources on one carrier.

[0085] Wireless communication may occur over an occupied bandwidth. The occupied bandwidth may be defined as the width of a frequency band such that, below the lower and above the upper frequency limits, the mean powers emitted are each equal to a specified percentage, $\beta/2$, of the total mean transmitted power, for example, the value of $\beta/2$ is taken as 0.5%.

[0086] The carrier, the BWP or the occupied bandwidth may be signaled by a network device (e.g., by a base station **170**) dynamically, e.g., in physical layer control signaling such as the known downlink control information (DCI), or semi-statically, e.g., in radio resource control (RRC) signaling or in signaling in the medium access control (MAC) layer, or be predefined based on the application scenario; or be determined by the UE **110** as a function of other parameters that are known by the UE **110**, or may be fixed, e.g., by a standard.

[0087] UE position information is often used in cellular communication networks to improve various performance metrics for the network. Such performance metrics may, for example, include capacity, agility and efficiency. The improvement may be achieved when elements of the network exploit the position, the behavior, the mobility pattern, etc., of the UE in the context of a priori information describing a wireless environment in which the UE is operating.

[0088] A sensing system may be used to help gather UE pose information, including UE location in a global coordinate system, UE velocity and direction of movement in the global coordinate system, orientation information and the information about the wireless environment. "Location" is also known as "position" and these two terms may be used interchangeably herein. Examples of well-known sensing systems include RADAR (Radio Detection and Ranging) and LIDAR (Light Detection and Ranging). While the sensing system is typically separate from the communication system, it could be advantageous to gather the information using an integrated system, which reduces the hardware (and cost) in the system as well as the time, frequency or spatial resources needed to perform both functionalities. However, using the communication system hardware to perform sensing of UE pose and environment information is a highly challenging and open problem. The difficulty of the problem relates to factors such as the limited resolution of the communication system, the dynamicity of the environment, and the huge number of objects whose electromagnetic properties and position are to be estimated.

[0089] Accordingly, integrated sensing and communication (also known as integrated communication and sensing) is a desirable feature in existing and future communication systems.

[0090] Any or all of the EDs **110** and BS **170** may be sensing nodes in the system **100**. Sensing nodes are network entities that perform sensing by transmitting and receiving sensing signals. Some sensing nodes are communication equipment that perform both communications and sensing. However, it is possible that some sensing nodes do not perform communications and are, instead, dedicated to sensing. The sensing agent **174** in FIG. 2 is an example of a sensing node that is

dedicated to sensing. Unlike the EDs **110** and BS **170**, the sensing agent **174** does not transmit or receive communication signals. However, the sensing agent **174** may communicate configuration information, sensing information, signaling information, or other information within the communication system **100**. The sensing agent **174** may be in communication with the core network **130** to communicate information with the rest of the communication system **100**. By way of example, the sensing agent **174** may determine the location of the ED **110a**, and transmit this information to the base station **170a** via the core network **130**. Although only one sensing agent **174** is shown in FIG. 2, any number of sensing agents may be implemented in the communication system **100**. In some embodiments, one or more sensing agents may be implemented at one or more of the RANS **120**.

[0091] A sensing node may combine sensing-based techniques with reference signal-based techniques to enhance UE pose determination. This type of sensing node may also be known as a sensing management function (SMF). In some networks, the SMF may also be known as a location management function (LMF). The SMF may be implemented as a physically independent entity located at the core network **130** with connection to the multiple BSs **170**. In other aspects of the present application, the SMF may be implemented as a logical entity co-located inside a BS **170** through logic carried out by the processor **260**.

[0092] As shown in FIG. 5, an SMF **176**, when implemented as a physically independent entity, includes at least one processor **290**, at least one transmitter **282**, at least one receiver **284**, one or more antennas **286** and at least one memory **288**. A transceiver, not shown, may be used instead of the transmitter **282** and the receiver **284**. A scheduler **283** may be coupled to the processor **290**. The scheduler **283** may be included within or operated separately from the SMF **176**. The processor **290** implements various processing operations of the SMF **176**, such as signal coding, data processing, power control, input/output processing or any other functionality. The processor **290** can also be configured to implement some or all of the functionality and/or embodiments described in more detail above. Each processor **290** includes any suitable processing or computing device configured to perform one or more operations. Each processor **290** could, for example, include a microprocessor, microcontroller, digital signal processor, field programmable gate array or application specific integrated circuit.

[0093] A reference signal-based pose determination technique belongs to an “active” pose estimation paradigm. In an active pose estimation paradigm, the enquirer of pose information (e.g., the UE **110**) takes part in process of determining the pose of the enquirer. The enquirer may transmit or receive (or both) a signal specific to pose determination process. Positioning techniques based on a global navigation satellite system (GNSS) such as the known Global Positioning System (GPS) are other examples of the active pose estimation paradigm.

[0094] In contrast, a sensing-based technique, based on radar for example, may be considered as belonging to a “passive” pose determination paradigm. In a passive pose determination paradigm, the target is oblivious to the pose determination process.

[0095] By integrating sensing and communications in one system, the system need not operate according to only a single paradigm. Thus, the combination of sensing-based techniques and reference signal-based techniques can yield enhanced pose determination.

[0096] The enhanced pose determination may, for example, include obtaining UE channel sub-space information, which is particularly useful for UE channel reconstruction at the sensing node, especially for a beam-based operation and communication. The UE channel sub-space is a subset of the entire algebraic space, defined over the spatial domain, in which the entire channel from the TP to the UE lies. Accordingly, the UE channel sub-space defines the TP-to-UE channel with very high accuracy. The signals transmitted over other sub-spaces result in a negligible contribution to the UE channel. Knowledge of the UE channel sub-space helps to reduce the effort needed for channel measurement at the UE and channel reconstruction at the network-side. Therefore, the combination of sensing-based techniques and reference signal-based techniques may enable the UE

channel reconstruction with much less overhead as compared to traditional methods. Sub-space information can also facilitate sub-space-based sensing to reduce sensing complexity and improve sensing accuracy.

[0097] In some embodiments of integrated sensing and communication, a same radio access technology (RAT) is used for sensing and communication. This avoids the need to multiplex two different RATs under one carrier spectrum, or necessitating two different carrier spectrums for the two different RATs.

[0098] In embodiments that integrate sensing and communication under one RAT, a first set of channels may be used to transmit a sensing signal and a second set of channels may be used to transmit a communications signal. In some embodiments, each channel in the first set of channels and each channel in the second set of channels is a logical channel, a transport channel or a physical channel.

[0099] At the physical layer, communication and sensing may be performed via separate physical channels. For example, a first physical downlink shared channel PDSCH-C is defined for data communication, while a second physical downlink shared channel PDSCH-S is defined for sensing. Similarly, separate physical uplink shared channels (PUSCH), PUSCH-C and PUSCH-S, could be defined for uplink communication and sensing.

[0100] In another example, the same PDSCH and PUSCH could be also used for both communication and sensing, with separate logical layer channels and/or transport layer channels defined for communication and sensing. Note also that control channel(s) and data channel(s) for sensing can have the same or different channel structure (format), occupy same or different frequency bands or bandwidth parts.

[0101] In a further example, a common physical downlink control channel (PDCCH) and a common physical uplink control channel (PUCCH) may be used to carry control information for both sensing and communication. Alternatively, separate physical layer control channels may be used to carry separate control information for communication and sensing. For example, PUCCH-S and PUCCH-C could be used for uplink control for sensing and communication respectively and PDCCH-S and PDCCH-C for downlink control for sensing and communication respectively.

[0102] Different combinations of shared and dedicated channels for sensing and communication, at each of the physical, transport, and logical layers, are possible.

[0103] The term RADAR originates from the phrase Radio Detection and Ranging; however, expressions with different forms of capitalization (e.g., Radar and radar) are equally valid and now more common. Radar is typically used for detecting a presence and a location of an object. A radar system radiates radio frequency energy and receives echoes of the energy reflected from one or more targets. The system determines the pose of a given target based on the echoes returned from the given target. The radiated energy can be in the form of an energy pulse or a continuous wave, which can be expressed or defined by a particular waveform. Examples of waveforms used in radar include frequency modulated continuous wave (FMCW) waveforms and ultra-wideband (UWB) waveforms.

[0104] Radar systems can be monostatic, bi-static or multi-static. In a monostatic radar system, the radar signal transmitter and receiver are co-located, such as being integrated in a transceiver. In a bi-static radar system, the transmitter and receiver are spatially separated, and the distance of separation is comparable to, or larger than, the expected target distance (often referred to as the range). In a multi-static radar system, two or more radar components are spatially diverse but with a shared area of coverage. A multi-static radar is also referred to as a multisite or netted radar.

[0105] Terrestrial radar applications encounter challenges such as multipath propagation and shadowing impairments. Another challenge is the problem of identifiability because terrestrial targets have similar physical attributes. Integrating sensing into a communication system is likely to suffer from these same challenges, and more.

[0106] Communication nodes can be either half-duplex or full-duplex. A half-duplex node cannot

both transmit and receive using the same physical resources (time, frequency, etc.); conversely, a full-duplex node can transmit and receive using the same physical resources. Existing commercial wireless communications networks are all half-duplex. Even if full-duplex communications networks become practical in the future, it is expected that at least some of the nodes in the network will still be half-duplex nodes because half-duplex devices are less complex, and have lower cost and lower power consumption. In particular, full-duplex implementation is more challenging at higher frequencies (e.g., in millimeter wave bands) and very challenging for small and low-cost devices, such as femtocell base stations and UEs.

[0107] The limitation of half-duplex nodes in the communications network presents further challenges toward integrating sensing and communications into the devices and systems of the communications network. For example, both half-duplex and full-duplex nodes can perform bi-static or multi-static sensing, but monostatic sensing typically requires the sensing node have full-duplex capability. A half-duplex node may perform monostatic sensing with certain limitations, such as in a pulsed radar with a specific duty cycle and ranging capability.

[0108] Properties of a sensing signal, or a signal used for both sensing and communication, include the waveform of the signal and the frame structure of the signal. The frame structure defines the time-domain boundaries of the signal. The waveform describes the shape of the signal as a function of time and frequency. Examples of waveforms that can be used for a sensing signal include ultra-wide band (UWB) pulse, Frequency-Modulated Continuous Wave (FMCW) or “chirp”, orthogonal frequency-division multiplexing (OFDM), cyclic prefix (CP)-OFDM, and Discrete Fourier Transform spread (DFT-s)-OFDM.

[0109] In an embodiment, the sensing signal is a linearly frequency modulated signal, also called a linear chirp signal, with bandwidth, B, and time duration, T. Such a linear chirp signal is generally known from its use in FMCW radar systems. A linear chirp signal is defined by an increase in frequency from an initial frequency, $f_{\text{sub.chirp0}}$, at an initial time, $t_{\text{sub.chirp0}}$, to a final frequency, $f_{\text{sub.chirp1}}$, at a final time, $t_{\text{sub.chirp1}}$ where the relation between the frequency (f) and time (t) can be expressed as a linear relation of $f - f_{\text{sub.chirp0}} = \alpha(t - t_{\text{sub.chirp0}})$, where

$$[00001] \quad \alpha = \frac{f_{\text{chirp1}} - f_{\text{chirp0}}}{t_{\text{chirp1}} - t_{\text{chirp0}}}$$

is defined as a chirp rate. The bandwidth of the linear chirp signal may be defined as $B = f_{\text{sub.chirp1}} - f_{\text{sub.chirp0}}$ and the time duration of the linear chirp signal may be defined as $T = t_{\text{sub.chirp1}} - t_{\text{sub.chirp0}}$. Such linear chirp signal can be presented as $e^{j\pi\alpha t^2}$ in the baseband representation.

[0110] Precoding, as used herein, may refer to any coding operation(s) or modulation(s) that transform an input signal into an output signal. Precoding may be performed in different domains and typically transforms the input signal in a first domain to an output signal in a second domain. Precoding may include linear operations.

[0111] A terrestrial communication system may also be referred to as a land-based or ground-based communication system, although a terrestrial communication system can also, or instead, be implemented on or in water. The non-terrestrial communication system may bridge coverage gaps in underserved areas by extending the coverage of cellular networks through the use of non-terrestrial nodes, which will be key to establishing global, seamless coverage and providing mobile broadband services to unserved/underserved regions. In the current case, it is hardly possible to implement terrestrial access-points/base-stations infrastructure in areas like oceans, mountains, forests, or other remote areas.

[0112] The terrestrial communication system may be a wireless communications system using 5G technology and/or later generation wireless technology (e.g., 6G or later). In some examples, the terrestrial communication system may also accommodate some legacy wireless technologies (e.g., 3G or 4G wireless technology). The non-terrestrial communication system may be a communications system using satellite constellations, like conventional Geo-Stationary Orbit

(GEO) satellites, which utilize broadcast public/popular contents to a local server. The non-terrestrial communication system may be a communications system using low earth orbit (LEO) satellites, which are known to establish a better balance between large coverage area and propagation path-loss/delay. The non-terrestrial communication system may be a communications system using stabilized satellites in very low earth orbits (VLEO) technologies, thereby substantially reducing the costs for launching satellites to lower orbits. The non-terrestrial communication system may be a communications system using high altitude platforms (HAPs), which are known to provide a low path-loss air interface for the users with limited power budget. The non-terrestrial communication system may be a communications system using Unmanned Aerial Vehicles (UAVs) (or unmanned aerial system, "UAS") achieving a dense deployment, since their coverage can be limited to a local area, such as airborne, balloon, quadcopter, drones, etc. In some examples, GEO satellites, LEO satellites, UAVs, HAPs and VLEOs may be horizontal and two-dimensional. In some examples, UAVs, HAPs and VLEOs may be coupled to integrate satellite communications to cellular networks. Emerging 3D vertical networks consist of many moving (other than geostationary satellites) and high altitude access points such as UAVs, HAPs and VLEOs.

[0113] MIMO technology allows an antenna array of multiple antennas to perform signal transmissions and receptions to meet high transmission rate requirements. The ED **110** and the T-TRP **170** and/or the NT-TRP may use MIMO to communicate using wireless resource blocks. MIMO utilizes multiple antennas at the transmitter to transmit wireless resource blocks over parallel wireless signals. It follows that multiple antennas may be utilized at the receiver. MIMO may beamform parallel wireless signals for reliable multipath transmission of a wireless resource block. MIMO may bond parallel wireless signals that transport different data to increase the data rate of the wireless resource block.

[0114] In recent years, a MIMO (large-scale MIMO) wireless communication system with the T-TRP **170** and/or the NT-TRP **172** configured with a large number of antennas has gained wide attention from academia and industry. In the large-scale MIMO system, the T-TRP **170**, and/or the NT-TRP **172**, is generally configured with more than ten antenna units (see antennas **256** and antennas **280** in FIG. **3**). The T-TRP **170**, and/or the NT-TRP **172**, is generally operable to serve dozens (such as 40) of EDs **110**. A large number of antenna units of the T-TRP **170** and the NT-TRP **172** can greatly increase the degree of spatial freedom of wireless communication, greatly improve the transmission rate, spectral efficiency and power efficiency, and, to a large extent, reduce interference between cells. The increase of the number of antennas allows for each antenna unit to be made in a smaller size with a lower cost. Using the degree of spatial freedom provided by the large-scale antenna units, the T-TRP **170** and the NT-TRP **172** of each cell can communicate with many EDs **110** in the cell on the same time-frequency resource at the same time, thus greatly increasing the spectral efficiency. A large number of antenna units of the T-TRP **170** and/or the NT-TRP **172** also enable each user to have better spatial directivity for uplink and downlink transmission, so that the transmitting power of the T-TRP **170** and/or the NT-TRP **172** and an ED **110** is reduced and the power efficiency is correspondingly increased. When the antenna number of the T-TRP **170** and/or the NT-TRP **172** is sufficiently large, random channels between each ED **110** and the T-TRP **170** and/or the NT-TRP **172** can approach orthogonality such that interference between cells and users and the effect of noise can be reduced. The plurality of advantages described hereinbefore enable large-scale MIMO to have a magnificent application prospect.

[0115] A MIMO system may include a receiver connected to a receive (Rx) antenna, a transmitter connected to transmit (Tx) antenna and a signal processor connected to the transmitter and the receiver. Each of the Rx antenna and the Tx antenna may include a plurality of antennas. For instance, the Rx antenna may have a uniform linear array (ULA) antenna, in which the plurality of antennas are arranged in line at even intervals. When a radio frequency (RF) signal is transmitted through the Tx antenna, the Rx antenna may receive a signal reflected and returned from a forward

target.

[0116] A non-exhaustive list of possible unit or possible configurable parameters or in some embodiments of a MIMO system include: a panel; and a beam.

[0117] A panel is a unit of an antenna group, or antenna array, or antenna sub-array, which unit can control a Tx beam or a Rx beam independently.

[0118] A beam may be formed by performing amplitude and/or phase weighting on data transmitted or received by at least one antenna port. A beam may be formed by using another method, for example, adjusting a related parameter of an antenna unit. The beam may include a Tx beam and/or a Rx beam. The transmit beam indicates distribution of signal strength formed in different directions in space after a signal is transmitted through an antenna. The receive beam indicates distribution of signal strength that is of a wireless signal received from an antenna and that is in different directions in space. Beam information may include a beam identifier, or an antenna port(s) identifier, or a channel state information reference signal (CSI-RS) resource identifier, or an SSB resource identifier, or a sounding reference signal (SRS) resource identifier, or other reference signal resource identifier.

[0119] Due to heterogeneity between sensing node capabilities, it may be shown to be beneficial to design sensing signals with a flexibility of being able to be processed in the RF domain. To be clear, the reference to processing in the RF domain does not, necessarily, mean that all processing tasks are carried out in the RF domain. There may be some, limited, baseband processing. However, it is expected that the baseband processing rates very low-in measurements of complexity and rates low in measurements of power consumption. Sometimes, herein, the processing of sensing signals in the RF domain may be referenced as RF-dominant processing, and may be shown to allow for a possibility of some, limited, baseband processing. Conveniently, the processing of sensing signals in the RF domain may be associated with relatively low complexity relative to the processing of sensing signals in the baseband domain. Accordingly, it may be shown that a UE with relatively low capability may participate in a sensing session by processing sensing signals in an RF-dominant manner.

[0120] One candidate for a sensing signal with flexibility of being able to be processed in the RF domain is a known “linearly frequency modulated signal” (also known as a “chirp signal”). That is, both the term “linearly frequency modulated signal” and the term “chirp signal” refer to the same type of signal, whose frequency is changing with time in a linear fashion. The chirp signal has a long history in radar applications. The chirp signal may be represented, mathematically, as $c(t) = e^{j2\pi f_0 t + \frac{1}{2} \alpha t^2}$. The chirp signal may be considered to have two dimensions (chirp signal configuration parameters) that allow for distinguishability: a starting frequency, f_0 , which may also be referenced as a frequency offset; and a chirp rate, α . The chirp rate, α , may be defined as a quotient of bandwidth, B , and the time duration, T , of the linear chirp signal. That is,

$$[00002] \quad \alpha = \frac{B}{T}.$$

[0121] Existing sensing signal approaches may be categorized either as a radar-based approach or as a communication-based approach.

[0122] In the radar-based approach, a traditional radar waveform is adapted to be used as a sensing signal in a wireless communication system. A popular sensing signal design involves use of a chirp-based waveform, which may also be called FMCW waveform or in particular, a Linear Frequency-Modulated Continuous Wave (LFM-CW) waveform. A chirp-based waveform may be defined using chirp signal configuration parameters (e.g., starting frequency and chirp rate) that may be used to define a node-specific sensing signal. That is, a receiver may obtain a starting frequency and a chirp rate for a received chirp waveform and determine, from information associating chirp signal configuration parameters with node IDs, an ID for the node that transmitted the received chirp signal. It may be stated, then, that chirp signal configuration parameters act as a manner by which a node transmitting a chirp waveform may be identified. The radar-based

approach, as mentioned before, may be shown to provide a relatively low-complexity and flexible design. Accordingly, the radar-based approach may be understood to be suited to processing by devices with relatively low capabilities or by devices operating in a low power mode.

[0123] In the communication-based approach, communication signals (e.g., OFDM waveform signals) are reused for the purpose of sensing. Since the sensing configuration is multi-static, the sensing signal may be a pilot signal that is known to the receiver.

[0124] Notably, the two signal configuration parameters used in the radar-based approach may be insufficient for distinguishing among a plurality of sensing signals transmitted from a corresponding plurality of different nodes for future applications. This may be referred to as a lack of sufficient signature space.

[0125] Further notably, to keep overhead low in the communication-based approach, the pilot signals are only transmitted in a relatively sparse manner. Indeed, the sparseness of the pilot signals may make the communication-based approach unsuitable for sensing. In addition, the communication-based approach involves processing pilot signals in the baseband domain. The processing of pilot signals in the baseband domain may be shown to make the communication-based approach unsuitable for devices in low power mode operation due to power consumption associated with converting analog signals to digital signals for processing in the baseband domain.

[0126] Aspects of the present application relate to finding one or more extra signal configuration parameters for a sensing signal design. More signal configuration parameters may be shown to allow for a larger pool of sensing signals.

[0127] In overview, aspects of the present application relate to carrying out sensing with a sensing signal selected from a sensing signal pool that has been expanded on the basis of one or more extra signal configuration parameters. That is, the sensing signal pool has an increased signature space relative to sensing signals designs that are based on only two signal configuration parameters. Furthermore, an appropriately selected sensing signal may be shown to enable low-complexity and low power mode sensing detection for relatively low capability UEs. The sensing signals in the sensing signal pool may be generically represented, mathematically, as

$x(t) = s(t)e^{j2\pi f_s t + j\pi \alpha t}$, where a function, $s(t)$, is representative of a signature function embedded in the baseband domain and $e^{j2\pi f_s t + j\pi \alpha t}$ is representative of a legacy chirp waveform, which may be generated and processed in the RF domain. It follows that a sensing signal may be generated from amongst a plurality of sensing signals that may be understood to form a pool of sensing signals, where the sensing signals in the pool have attributes in both the RF domain and the baseband domain. The sensing signal pool may be characterized by a signature space, $\{f_s, \alpha, r_s\}$, where r_s represents an index for the signature function, $s(t)$. The index, r_s , may be considered to provide, to a generated sensing signal, an extra degree of freedom in contrast to a sensing signal generated on the sole basis of the legacy chirp waveform.

[0128] Aspects of the present application may be understood to be applicable to a multi-node sensing scenario, wherein a network of UEs **110** with different capabilities and operating in different power modes are to perform sensing tasks. Aspects of the present application are often described, hereinafter, from the perspective of a UE **110**. However, it should be clear that further aspects of the present application may relate to a perspective of a TRP (e.g., a TN-TRP **170** or an NTN-TRP **172**) with different capabilities and operating in different power modes. There are three main devices/nodes that may be involved in the proposed procedures: UEs/nodes **110** operating in low power mode; UEs/nodes **110** operating in normal power mode; and TRPs **170/172** or base stations.

[0129] The UEs/nodes **110** operating in a low power mode may be shown to enter low power mode to save energy. Aspects of the present application relate to designing a sensing signal on the basis of which the UEs/nodes **110** operating in low power mode can obtain sensing information while consuming minimal processing power. Reductions in use of power, relative to UEs/nodes operating in normal power mode, may be realized through the use of RF-dominant processing. Use of RF-

dominant processing may be shown to allow for transmission of high bandwidth signals. In turn, use of high bandwidth signals may be shown to allow the UEs/nodes **110** to achieve relatively high resolution sensing, even while operating in low power mode.

[0130] The UEs/nodes **110** operating in a normal power mode may include UEs **110** operating in an RRC CONNECTED state and may include other network-controlled nodes defined as carrying out normal operations. The other network-controlled nodes defined as carrying out normal operations are often the nodes with relatively high processing power and capability. Aspects of the present application relate to designing a sensing signal with increased signature space to allow these nodes to perform high accuracy sensing through digital baseband processing in order to distinguish the sensing signals.

[0131] The TRPs **170/172** or base stations may be understood to be in charge of providing configurations for sensing operations and sensing signals. More particularly, the TRPs **170/172** or base stations may act to optimize the sensing signals based on the desired accuracy, desired resolution, known node density and known reflectors in the wireless environment.

[0132] FIG. **6** illustrates a wireless communication environment including first TRP **170-1**, a second TRP **170-2**, a first UE **110-1** and a second UE **110-2**. The environment further includes a first reflector **601** and a second reflector **602**. The first UE **110-1** may be understood to be operating in a mode of operation that is normal in respect of power use. In contrast, the second UE **110-2** may be understood to be operating in a power saving mode of operation.

[0133] FIG. **7** illustrates transmitter elements involved in generating a sensing signal, $x(t)$, for transmission. Some of the generating takes place in a baseband domain **700** and some of the generating takes place in an RF domain **710**. The baseband domain **700** includes a base sequence generator **702** and a baseband signature function generator **704**. The RF domain **710** includes a sensing signal generator **712**. The sensing signal generator **712** includes a chirp signal generator **714** and a modulator **716**. The modulator **716** may be implemented as a multiplier.

[0134] In operation, the base sequence generator **702** may receive, as input, a node ID or a sensing session ID. On the basis of the received ID, the base sequence generator **702** may determine an index (a “codeword index”) that allows the base sequence generator **702** to select a particular codeword from among a plurality of codewords in a codebook. On the basis of the codeword index, the base sequence generator **702** may transmit, to the baseband signature function generator **704**, a base sequence. On the basis of the base sequence, the baseband signature function generator **704** may generate a signature function, $s(t)$. The baseband signature function generator **704** may then transmit, to the sensing signal generator **712**, the signature function, $s(t)$. The chirp signal generator **714** may also receive, as input, the same node ID or the same sensing ID that was provided to the base sequence generator **702**. On the basis of the node ID or the sensing session ID, the chirp signal generator **714** may select a starting frequency, $f_{\text{sub},i}$, and a chirp rate, α . Using the selected starting frequency, $f_{\text{sub},i}$, and the selected chirp rate, α , the chirp signal generator **714** may generate a chirp signal. The chirp signal, $c(t)$, at the output of the chirp signal generator **714** may be modulated, at the modulator **716**, with the signature function, $s(t)$, to, thereby, generate the sensing signal, $x(t)$. The node ID may be an identity associated with the sensing transmitter (e.g., the first TRP **170-1** in FIG. **6**) or an identity associated with the sensing receiver (e.g., the first UE **110-1** in FIG. **6**).

[0135] FIG. **8A** illustrates receiver elements involved in analyzing a sensing signal after the sensing signal has been received. More specifically, the receiver elements illustrated in FIG. **8A** may be understood to relate to the first UE **110-1** in FIG. **6**, which is operating in a mode of operation that is normal in respect of power use. FIG. **8A** illustrates receiver elements categorized in an RF domain **810** and in a baseband domain **800**. The element in the RF domain **810** is a chirp processing receiver **802A**. The element in the baseband domain **800** is a signature processor **804**. The chirp processing receiver **802A** in FIG. **8A** is illustrated as receiving a chirp rate. It may not always be the case that the chirp processing receiver **802A** receives a chirp rate. The signature

processor **804** in FIG. **8A** is illustrated as receiving a base sequence codebook. It may not always be the case that the signature processor **804** receives a base sequence codebook.

[0136] In operation, input to the chirp processing receiver **802A** of FIG. **8A** is a received sensing signal, $y(t)$, which is a version of the transmitted sensing signal, $x(t)$, that has been altered by a channel interposing the transmitter (e.g., a TRP **170**) and the first UE **110-1**. Output from the chirp processing receiver **802A** in FIG. **8A** is received at the signature processor **804**. On the basis of the received base sequence codebook, the signature processor **804** processes the output of the chirp processing receiver **802A**. The output of the signature processor **804** may then be processed to obtain the unknown signal configuration parameters, $f_{\text{sub},i}$ and $r_{\text{sub},s}$. In some embodiments, the chirp processing receiver **802A** may, additionally, obtain the chirp rate, α .

[0137] FIG. **8B** illustrates receiver elements involved in analyzing a sensing signal after the sensing signal has been received. More specifically, the receiver elements illustrated in FIG. **8B** may be understood to relate to the second UE **110-2** in FIG. **6**, which is operating in a power saving mode of operation. FIG. **8B** illustrates a receiver element categorized in the RF domain **810**. The element in the RF domain **810** is a chirp processing receiver **802B**. The chirp processing receiver **802B** in FIG. **8B** is illustrated as receiving a chirp rate. The chirp processing receiver **802B** in FIG. **8B** is also illustrated as, optionally, receiving a base sequence codebook.

[0138] In operation, input to the chirp processing receiver **802B** of FIG. **8B** is a received sensing signal, $y(t)$, which is a version of the transmitted sensing signal, $x(t)$, that has been altered by a channel interposing the transmitter (e.g., a TRP **170**) and the second UE **110-2**. Output from the chirp processing receiver **802B** in FIG. **8B** may be processed to obtain the unknown signal configuration parameters, $f_{\text{sub},i}$ and $r_{\text{sub},s}$.

[0139] Aspects of the present application relate to a frequency hopping implementation for the design of the signature function, $s(t)$. FIG. **9** illustrates an example frequency hopping implementation for the signature function, $s(t)$. FIG. **9** illustrates a sensing time duration, T , that has been divided into a number, N , of time slots. The number, N , of time slots may be considered to be a design parameter. The signature function, $s(t)$, illustrated in FIG. **9** includes a number of sinusoidal signals equal to the number, N , of time slots. That is, the TRP **170** may transmit a distinct sinusoidal signal in each of the time slots. The duration of the signature function time slots can be considered to be a design/configuration parameter. In some embodiments, the duration of each of the signature function time slots can be related with the duration of communication time slots.

[0140] The distinct sinusoidal signal for the k^{th} time slot may be mathematically represented as $e^{j2\pi f_{\text{sub},k} t}$. As discussed hereinbefore, the transmitted sensing signal, $x(t)$, may be mathematically represented as $x(t) = s(t) e^{j\pi \alpha t^2}$. A new signature space, $S_{\text{sub},n}$, associated with the transmitted sensing signal according to aspects of the present application may be defined as $S = [f_{\text{sub},1}, f_{\text{sub},2}, \dots, f_{\text{sub},k}, \dots, f_{\text{sub},N}, \alpha]$. The new signature space, $S_{\text{sub},n}$, may be shown to be much larger than an old signature space, $S_{\text{sub},o}$, associated with the traditional chirp sensing signal, with $S_{\text{sub},o} = [f_{\text{sub},0}, \alpha]$.

[0141] For simplicity of presentation, the frequency, $f_{\text{sub},k}$, of the distinct sinusoidal signal in the k^{th} time slot may be expressed as portion of a bandwidth, B , of the sensing signal. For example, the frequency, $f_{\text{sub},k}$, of the distinct sinusoidal signal in the k^{th} time slot may be defined as

$$f_k = \frac{r_k B}{L},$$

where L and $r_{\text{sub},k}$ may each be referred to as an integer value. It follows that the sensing signal is different in each of the time slots, $x_{\text{sub},k}(t) = s_{\text{sub},k}(t) e^{j\pi \alpha t^2}$, or, put another way, $x_{\text{sub},k}(t) = e^{j2\pi f_{\text{sub},k} t} e^{j\pi \alpha t^2}$. In this example, instead of expressing the signature space in terms of frequencies, the signature space may be expressed in terms of a set of signature integers and a chirp rate, $S_{\text{sub},n} = [r_{\text{sub},1}, r_{\text{sub},2}, \dots, r_{\text{sub},k}, \dots, r_{\text{sub},N}, \alpha]$.

[0142] Notably, a given set of signature integers, $r_{\text{sub},k}$, $k=0, \dots, N$, may be represented as a

signature vector, $r=[r_{\text{sub}.1}, r_{\text{sub}.2}, \dots, r_{\text{sub}.k}, \dots, r_{\text{sub}.N}]$. Accordingly, a corresponding set of frequencies, $f_{\text{sub}.k}, k=0, \dots, N$, may be represented as a frequency vector, $f=[f_{\text{sub}.1}, f_{\text{sub}.2}, \dots, f_{\text{sub}.k}, \dots, f_{\text{sub}.N}]$. The signature vector, r , and the frequency vector, f , may be related to one another in a single expression,

$$[00004] f = \frac{B}{L} r.$$

[0143] Two example transmitted sensing signals, $x_{\text{sup}.[1]}(t)$, $x_{\text{sup}.[2]}(t)$, may be generated by two distinct TRPs **170** using respective versions of the base sequence generator **702**, the baseband signature function generator **704**, the chirp signal generator **714** and the modulator **716** illustrated in FIG. 7.

[0144] A first example transmitted sensing signal, $x_{\text{sup}.[1]}(t)$, may be configured to have a bandwidth, B , of 1 GHz and a signature function associated with L equal to 16. The baseband signature function generator **704** that is associated with the transmission of first example transmitted sensing signal, $x_{\text{sup}.[1]}(t)$, may be configured to employ a first signature vector, $r_{\text{sub}.1}$, where $r_{\text{sub}.1}=[1, 14, 4, 3]$.

[0145] A second example transmitted sensing signal, $x_{\text{sup}.[2]}(t)$, may be configured to have a bandwidth, B , of 1 GHz and a signature function associated with L equal to 16. The baseband signature function generator **704** that is associated with the transmission of second example transmitted sensing signal, $x_{\text{sup}.[2]}(t)$, may be configured to employ a second signature vector, $r_{\text{sub}.2}$, where $r_{\text{sub}.2}=[7, 2, 10, 4]$.

[0146] The first example transmitted sensing signal, $x_{\text{sup}.[1]}(t)$, may be received, at the chirp processing receiver **802B** in FIG. 8B, as a first received sensing signal, $y_{\text{sup}.[1]}(t)$. Similarly, the second example transmitted sensing signal, $x_{\text{sup}.[2]}(t)$, may be received, at the chirp processing receiver **802B** in FIG. 8B, as a second received sensing signal, $y_{\text{sup}.[2]}(t)$.

[0147] FIG. 10 illustrates a plot **1000** of output power with respect to delay for output from the chirp processing receiver **802B** in FIG. 8B given the first received sensing signal, $y_{\text{sup}.[1]}(t)$, as input. The plot **1000** of FIG. 10 is representative of a case wherein the chirp processing receiver **802B** is unaware of the first signature vector, $r_{\text{sub}.1}$, and, accordingly, the chirp processing receiver **802B** has not performed further processing that would make use of the first signature vector, $r_{\text{sub}.1}$.

[0148] Three output patterns are illustrated in the plot **1000** of FIG. 10, with each output pattern having a peak associated with a reference numeral.

[0149] The reference numeral **1001** is associated with a first peak, representative of an output power pattern that is expected to be generated by the chirp processing receiver **802B** responsive to first received sensing signal, $y_{\text{sup}.[1]}(t)$, that is the received version of a chirp signal that has been modulated by a signature function that makes use of the first signature vector, $r_{\text{sub}.1}=[r_{\text{sub}.1}, r_{\text{sub}.2}, \dots, r_{\text{sub}.k}, \dots, r_{\text{sub}.N}]=[1, 14, 4, 3]$.

[0150] The reference numeral **1002** is associated with a second peak, representative of an output power pattern that is expected to be generated by the chirp processing receiver **802B** responsive to the first received sensing signal that is the received version of a chirp signal that has been modulated by a signature function that makes use of the first signature vector, $r_{\text{sub}.1}=[r_{\text{sub}.1}, r_{\text{sub}.2}, \dots, r_{\text{sub}.k}, \dots, r_{\text{sub}.N}]=[1, 14, 4, 3]$.

[0151] The reference numeral **1003** is associated with a third peak, representative of an output power pattern that is expected to be generated by the chirp processing receiver **802B** responsive to receiving a sensing chirp signal that is unaffected by a signature function, or with a signature function, $s(t)=1$.

[0152] FIG. 11 illustrates a plot **1100** of output power with respect to delay for output from the chirp processing receiver **802B** in FIG. 8B given the second received sensing signal, $y_{\text{sup}.[2]}(t)$, as input. The plot **1100** of FIG. 11 is representative of a case wherein the chirp processing receiver **802B** is unaware of the second signature vector, $r_{\text{sub}.2}$, and, accordingly, the chirp processing receiver **802B** does not perform further processing that would make use of the second signature

vector, $r_{\text{sub}.2}$.

[0153] Three output patterns are illustrated in the plot **1100** of FIG. **11**, with each output pattern having a peak associated with a reference numeral.

[0154] The reference numeral **1101** is associated with a first peak, representative of an output power pattern that is expected to be generated by the chirp processing receiver **802B** responsive to the second received sensing signal that is the received version of a chirp signal that has been modulated by a signature function that makes use of the second signature vector, $r_{\text{sub}.2}=[r_{\text{sub}.1}, r_{\text{sub}.2}, \dots, r_{\text{sub}.k}, \dots, r_{\text{sub}.N}]=[7, 2, 10, 4]$.

[0155] The reference numeral **1102** is associated with a second peak, representative of an output power pattern that is expected to be generated by the chirp processing receiver **802B** responsive to the second received sensing signal that is the received version of a chirp signal that has been modulated by the signature function that makes use of the second signature vector, $r_{\text{sub}.2}=[r_{\text{sub}.1}, r_{\text{sub}.2}, \dots, r_{\text{sub}.k}, \dots, r_{\text{sub}.N}]=[7, 2, 10, 4]$.

[0156] The reference numeral **1103** is associated with a third peak, representative of an output power pattern that is expected to be generated by the chirp processing receiver **802B** responsive to receiving a sensing chirp signal that is unaffected by a signature function, or with a signature function, $s(t)=1$.

[0157] It is notable that the output power patterns **1001**, **1002**, (see FIG. **10**) generated by receipt of transmitted sensing signals with a single signature function and the output power pattern **1003** generated by receipt of a sensing chirp signal that is unaffected by a signature function, or with a signature function, $s(t)=1$. Similarly, the output power patterns **1101**, **1102** (see FIG. **11**) are generated by receipt of transmitted sensing signals with a signature function that is distinct from the signature function used for the transmitted sensing signals that may be shown to lead to the output power patterns **1001**, **1002**. Aspects of the present application relate to using the difference in output power patterns to distinguish between different received sensing signals, even if only the chirp processing receiver **802B** is used.

[0158] Although the output power pattern with first peak **1001** of FIG. **10** does not match the output power pattern with the third peak **1003**, it may be shown that there is a deterministic relation between the observed peaks **1001**, **1003**. The relationship can be expressed as

$$[00005] t_{\text{obs}} = t_{\text{true}} + \frac{Tk}{L},$$

for some integer value k , wherein $t_{\text{sub}.obs}$ denotes the time of the first peak **1001** and $t_{\text{sub}.true}$ denotes the time of the third peak **1003**, which corresponds to the true value of the parameter to be estimated. In the example shown in FIG. **10**, $L=16$ and $T=4 \mu\text{s}$. Accordingly, the difference,

$$[00006] \frac{Tk}{L},$$

is $0.25 k \mu\text{s}$ for some integer, k . It follows that an estimate for the time of the third peak **1003** may be determined by trying a few hypotheses on the basis of some rough prior knowledge of a sensing parameter of interest.

[0159] It may be shown that there is no loss of resolution in output power pattern, at the output of the chirp processing receiver **802B**, due to the application of the signature function at the sensing signal generator **712** (see FIG. **7**). That is, the width of the output power pattern with the first peak **1001** is the same as the width of the output power pattern with the third peak **1003**.

[0160] Notably, however, there is a difference in the peak powers. The difference in the peak powers may be shown to affect sensing accuracy. The difference in the peak powers may be shown to be due to a loss in the processing gain as a result of non-coherent combining at the output of a pulse compression filter (not shown) in the chirp processing receiver **802B**.

[0161] In the plot **1100** of FIG. **11**, a difference between the power of the first peak **1101** and the power of the third peak **1103** is illustrated as a 6 dB loss. The magnitude (6 dB) of the processing loss in this case may be directly related to the use of four time slots ($N=4$) for each signature function, $s(t)$. It may be shown that the processing loss may be compensated for, by so-called high-capability UEs, through the use of specialized digital processing techniques that rely upon

knowledge of the signature function, $s(t)$.

[0162] Aspects of the present application relate to an implementation for the design of the signature function, $s(t)$, that allows the received sensing signal to have the same properties as a received sensing chirp signal, $y(t)$, that is unaffected by a signature function, these properties including auto-correlation.

[0163] FIG. 12 illustrates an example base sequence codebook implementation for the signature function, $s(t)$. FIG. 12 illustrates a sensing time duration, T , that has been divided into a number, L , of time slots. The number, L , of time slots may be considered to be based on at least two design parameters: the sensing time duration, T ; and a bandwidth, B . Indeed, the two design parameters may be combined as a time-bandwidth product, $N=BT$. The integer value, L , may be understood to represent an integer number of time slots that is related to the time-bandwidth product by an expression $L=\sqrt{\text{square root over (N)}}$.

[0164] The signature function, $s(t)$, illustrated in FIG. 12 includes a number of signals equal to L . That is, the TRP 170 may transmit a distinct signal in each of the L time slots. Defining the signature function, $s(t)$, may involve first defining a base signal, $b(t)$. In turn, the base signal, $b(t)$, may be defined on the basis of a base sequence, $[b_{\text{sub}.0}, b_{\text{sub}.1}, b_{\text{sub}.2}, \dots, b_{\text{sub}.L-1}]$. More particularly, the base signal, $b(t)$, may be obtained by using the base sequence to alter a selected pulse shape.

[0165] In a case wherein the selected pulse shape is a rectangular pulse shape, the base signal may be expressed as a sum of products of symbols, $b_{\text{sub}.i}$, in the base sequence and a shifted version of the known rect function:

$$[00007] b(t) = \sum_{i=0}^{L-1} b_{\text{sub}.i} \Pi\left(B\left(t - \frac{i}{B}\right)\right)$$

where $\Pi(\cdot)$ is representative of the known rect function:

$$[00008] \Pi(x) = \begin{cases} 0, & \text{if } x < -\frac{1}{2} \\ 1, & \text{if } -\frac{1}{2} \leq x \leq \frac{1}{2} \\ 0, & \text{if } x > \frac{1}{2} \end{cases}$$

Notably, the known rect function is the Fourier transform of the known sinc function. Recall that the known sinc function may be expressed as:

$$[00009] \text{sinc}(f) = \frac{\sin(\pi f)}{f} = \frac{1}{T} \int_{-\infty}^{\infty} \Pi\left(\frac{t}{T}\right) e^{-j2\pi ft} dt$$

Notably, $\Pi(Bt) \neq 0$,

$$[00010] t \in \left[0, \frac{1}{B} = \frac{T}{N}\right].$$

[0166] The signature function, $s(t)$, is illustrated, in FIG. 12, as being formed as a plurality of shifted versions of the base signal, $b(t)$. Accordingly, the signature function, $s(t)$, may be expressed as:

$$[00011] s(t) = \sum_{k=0}^{\sqrt{N}-1} b\left(t - \frac{kT}{\sqrt{N}}\right)$$

[0167] It may be considered that the base sequence may be expressed as a base sequence codeword, $\{\vec{b}\} = (b_{\text{sub}.0}, \dots, b_{\text{sub}.L-1})$, where the integer value, L , may be determined from an expression, $L=\sqrt{\text{square root over (N)}}$. Aspects of the present application relate to use of a base sequence codeword that has been designed in a specific manner.

[0168] In view of the function, $y(t)$, being representative of the output of the chirp processing receiver 802A responsive to receipt of an unmodulated chirp signal, then an output, $z(t)$, of the chirp processing receiver 802A responsive to receipt of a signal transmitted as a chirp signal modulated by the signature function, $s(t)$, of FIG. 12 can be shown to be mathematically well-approximated by

$$[00012] z(t) = \sum_{k=0}^{L-1} B_k y\left(t - \frac{kT}{L}\right)$$

where an IDFT codeword, $\{\vec{B}\} = (B_{\text{sub}.0}, \dots, B_{\text{sub}.L-1})$, is an Inverse

Discrete Fourier Transform (IDFT) of the base sequence codeword, $\{\text{right arrow over (b)}\} = (b_{\text{sub}.0}, \dots, b_{\text{sub}.L-1})$.

[0169] It may be shown that the function, $y(t)$, at the output of the chirp processing receiver **802A** responsive to receipt of an unmodulated chirp signal is a sinc function, which is similar to the known delta function for a relatively large time-bandwidth product, BT .

[0170] It follows that the output, $z(t)$, of the chirp processing receiver **802A** responsive to receipt of a signal transmitted as a chirp signal modulated by the signature function, $s(t)$, of FIG. **12** may be shown to be similar to a delta train (sinc functions of narrow width) with each delta function having a distinct weight. An example delta train is illustrated in a plot **1300** in FIG. **13**. Notably, it may be shown that there is no resolution loss. In other words, a universal receiver can still distinguish different delays due to targets with different ranges (range resolution). For a $j_{\text{sup.th}}$ UE **110-j**, an estimated delay, $\{\text{circumflex over (tau)}\}_{\text{sub}.j}$, may be determined on the basis of a true delay, $\tau_{\text{sub}.j}$, on the basis of the sensing signal time duration, T , and the number, L , of time slots, using an expression,

$$[00013] \hat{\tau}_j = \tau_j + \frac{kT}{L}$$

for some integer, k .

[0171] It may be understood that, however, the power of each sinc pulse at the output of the chirp processing receiver **802A** is lower than the power of the single sinc pulse corresponding to the unmodulated chirp due to the loss of the processing gain caused by non-coherent detection. It may also be understood that the weight of the $k_{\text{sup.th}}$ sinc pulse in the output, $z(t)$, is proportional to the $k_{\text{sup.th}}$ element in the IDFT codeword, $\{\text{right arrow over (B)}\} = (B_{\text{sub}.0}, \dots, B_{\text{sub}.L-1})$, of the base sequence codeword, $\{\text{right arrow over (b)}\} = (b_{\text{sub}.0}, \dots, b_{\text{sub}.L-1})$.

[0172] Accordingly, rather than designing a base sequence codebook of base sequence codewords, $\{\text{right arrow over (b)}\}$, aspects of the present application may relate to designing an IDFT codebook for an IDFT delay domain, where the IDFT codebook is made up of IDFT codewords, $\{\text{right arrow over (B)}\}$.

[0173] The IDFT codebook may be described as a set, B , having a quantity, M , of IDFT codewords, $\{\text{right arrow over (B)}\}$, that is, $B = \{\{\text{right arrow over (B)}\}_{\text{sub}.1}, \dots, \{\text{right arrow over (B)}\}_{\text{sub}.M}\}$. It should be clear that the $i_{\text{sup.th}}$ IDFT codeword, $\{\text{right arrow over (B)}\}_{\text{sub}.i}$, is the IDFT of the $i_{\text{sup.th}}$ base sequence codeword, $\{\text{right arrow over (b)}\}_{\text{sub}.i} = (b_{\text{sub}.i,0}, \dots, b_{\text{sub}.i,L-1})$. It should be clear that, since an IDFT is a unitary transformation, a Euclidean distance between two base sequence codewords is the same as a Euclidean distance between two IDFT codewords. It follows that an objectively good codebook in the IDFT domain will correspond to an objectively good codebook in the base sequence domain.

[0174] Aspects of the present application relate to determining the features that are desired in the IDFT domain to facilitate sensing detection.

[0175] To facilitate sensing detection, it is proposed to simplify detection of the true delay, $\tau_{\text{sub}.j}$. It may be shown that detection of the true delay, $\tau_{\text{sub}.j}$, may be simplified by implementing a feature wherein the symbols, $b_{\text{sub}.i,n}$, in each base sequence codeword, $\{\text{right arrow over (b)}\}_{\text{sub}.i}$, in the base sequence codebook are constrained such that $|b_{\text{sub}.i,0}|_{\text{sup.2}} > \gamma |b_{\text{sub}.i,n}|_{\text{sup.2}}$ for all i and $n > 0$ for some $\gamma > 1$. The ratio, γ , that relates the power, $|b_{\text{sub}.i,0}|_{\text{sup.2}}$, in the first symbol to the power, $|b_{\text{sub}.i,n}|_{\text{sup.2}}$, in each of the rest of the symbols may be referred to as a power ratio.

[0176] It is known that when the number of non-zero pulses is limited, the result is a sparse codebook design. Accordingly, aspects of the present application relate to limiting the number of non-zero sinc pulses.

[0177] FIG. **14** illustrates a plot **1400** of output power with respect to delay for output from the chirp processing receiver **802B** in FIG. **8B** given a received sensing signal as input. Three output patterns are illustrated in the plot **1400** of FIG. **14**, with each output pattern having a peak associated with a reference numeral.

[0178] The reference numeral **1401** is associated with a first peak, representative of an output power pattern that is expected to be generated by the chirp processing receiver **802B** responsive to a scenario wherein the received sensing signal is a received version of a chirp signal that been modulated by a signature function, $s(t)$, that makes use of a base sequence derived from a base sequence codeword, b , where the base sequence codeword, b , corresponds to an IDFT codeword, $B=(0,2,0,0,1,0, \dots, 0)$, designed with a power ratio, $\gamma=4$. The first peak **1401** may be associated with a first location, $\tau_{\text{sub.obs1}}$ (not shown), on the time axis.

[0179] The reference numeral **1402** is associated with a second peak, representative of an output power pattern that is expected to be generated by the chirp processing receiver **802B** responsive to a scenario wherein the received sensing signal is a received version of a chirp signal that has been modulated by a signature function, $s(t)$, that makes use of a base sequence derived from a base sequence codeword, b , where the base sequence codeword, b , corresponds to an IDFT codeword, $B=(0,2,0,0,1,0, \dots, 0)$, designed with the power ratio, $\gamma=4$. The second peak **1402** may be associated with a second location, $\tau_{\text{sub.obs2}}$ (not shown), on the time axis. It is worth underlining that the first peak **1401** and the second peak **1402** relate to a received version of a single chirp signal that has been modulated by a single signature function, $s(t)$.

[0180] The reference numeral **1403** is associated with a third peak, representative of an output power pattern that is expected to be generated by the chirp processing receiver **802B** responsive to receiving a sensing chirp signal that is unaffected by a signature function, or with a signature function, $s(t)=1$. The third peak **1403** may be associated with a true location, $\tau_{\text{sub.true}}$ (not shown), on the time axis.

[0181] In the plot **1400** of FIG. **14**, there is a difference between the power of the first peak **1401** and the power of the third peak **1403**.

[0182] It may be shown that the first location, $\tau_{\text{sub.obs1}}$, and the second location, $\tau_{\text{sub.obs2}}$, (generically, $\tau_{\text{sub.obs}}$) have a deterministic relation with the true location, $\tau_{\text{sub.true}}$, given as a relation expressed as

$$[00014] \tau_{\text{obs}} = \tau_{\text{true}} + \frac{k^* T}{L}$$

for integer values, k^* . The variable, k^* , is used to represent indices of non-zero elements in the particular IDFT codeword that is in use.

[0183] Notably, since sensing performance does not depend on the phase of the symbols, $b_{\text{sub.i,n}}$, of the in-use base sequence codeword, $\{\text{right arrow over (b)}\}$, information may be embedded on the phase as well (e.g., using phase shift keying modulation).

[0184] To summarize, aspects of the present application relate to use of an IDFT codebook that has been designed such that each IDFT codeword, in the IDFT codebook, has been defined based on a sparsity pattern.

[0185] The task of defining each particular IDFT codeword may take into account features of the particular base sequence codeword, $\{\text{right arrow over (b)}\}$, that corresponds to each particular IDFT codeword. Such defining may begin with assuming an ON state for the first symbol, $b_{\text{sub.0}}$, of the base sequence codeword, $\{\text{right arrow over (b)}\}$, corresponding to each IDFT codeword. Such defining may also establish an inequality that states $|b_{\text{sub.i,0}}|_{\text{sup.2}} > \gamma |b_{\text{sub.i,n}}|_{\text{sup.2}}$ for the base sequence codeword, $\{\text{right arrow over (b)}\}$, corresponding to each IDFT codeword.

Furthermore, a pre-determined limit value, $K_{\text{sub.max}}$, may be established for a number, K , of non-zero elements in each IDFT codeword. Alternatively, a non-sparsity ratio,

$$[00015] \frac{K}{L},$$

may be defined and, then, a pre-determined limit value,

$$[00016] \frac{K_{\text{max}}}{L},$$

may be established for the non-sparsity ratio.

[0186] A multi-dimensional constellation may be defined over the non-zero elements of each IDFT codeword. In a special case, an independent phase shift keying constellation may be defined over the elements of each IDFT codeword. FIG. **15** illustrates a table **1500** that associates a quantity, Q ,

of total possible number of signature functions, $s(t)$, (presented as logarithm in base 2) in terms of the number, K , of non-zero IDFT codeword elements for a scenario wherein $L=32$, $BT=1024$, $K_{\text{sub.max}}=16$, and a quadrature phase shift keying constellation is employed.

[0187] Aspects of the present application relate to signaling mechanisms.

[0188] For one example, it should be clear that one or more signaling mechanisms may be specified to allow a TRP **170** (see FIG. 6) to provide, to a UE **110** (see FIG. 6), an indication of chirp signal configuration parameters. As discussed hereinbefore, chirp signal configuration parameters may include bandwidth, time duration, chirp rate and initial frequency.

[0189] All presented methods are described for a single chirp signal. It should be appreciated that the presented methods can readily be extended to a case wherein a plurality of chirp signals are concatenated in the time domain (FMCW waveform). In this case, the signature function, $s(t)$, can be applied to the whole waveform, or the signature function can be applied to each chirp signal individually, i.e., $S_{\text{sub}.i}(t)$ is applied to the i th chirp signal, $i=1, \dots, M$, wherein M denotes the total number of chirp signals. In this case, an aggregate signature function can be defined as $S(t)=[S_{\text{sub}.1}(t), \dots, S_{\text{sub}.M}(t)]$. In this case, definition of each individual signature function, $S_{\text{sub}.i}(t)$, can follow the presented methods.

[0190] Various methods are contemplated to allow a given TRP **170** or a given UE **110** to determine one or more chirp signal configuration parameters. One method relies upon one or more of the chirp signal configuration parameters being mapped to a sensing transmitter ID, a sensing receiver ID or a sensing session ID. The sensing session ID may, for example, be determined on the basis of a sensing transmitter Radio Network Temporary Identifier (RNTI). One of the chirp signal configuration parameters may be called a digital signature indication. The digital signature indication may be used to provide an indication of whether or not a sensing chirp signal that is to be transmitted should be expected to be a chirp signal modulated by a signature function.

[0191] When a TRP **170** is using signaling to provide, to a UE **110**, an indication of chirp signal configuration parameters, the TRP **170** may use dynamic signaling or semi-static signaling. In a case wherein the sensing signal is a chirp signal modulated by a signature function, two designs are contemplated.

[0192] A first design may be used for the frequency hopping implementation of the signature function, an example of which implementation is illustrated in FIG. 9. In the first design, the chirp signal configuration parameters signaled from the TRP **170** to the UE **110** may be expected to include a signature vector, r , (or an indication of the signature vector, r , such as an index of the signature vector, r) and a chirp rate. Instead of signaling the signature vector, r , the TRP **170** may signal an indication of the signature vector, r , such as an index or a pointer to a signature vector, r , stored, at the UE **110**, among many signature vectors. The TRP **170** may signal the chirp signal configuration parameters through semi-static signaling. An example of such semi-static signaling is the known RRC signaling. Instead of the chirp signal configuration parameters including a signature vector, r , the chirp signal configuration parameters may include a frequency vector, f , or a pointer to a frequency vector, f .

[0193] A second design may be used for the base sequence codebook implementation of the signature function, an example of which implementation is illustrated in FIG. 12. In the second design, the chirp signal configuration parameters signaled from the TRP **170** to the UE **110** may be expected to include a base sequence codebook. The TRP **170** may signal the chirp signal configuration parameters through semi-static signaling. An example of such semi-static signaling is the known RRC signaling.

[0194] Recall that an IDFT codebook may be defined based on a sparsity pattern or based on a combination of a sparsity pattern and a regular constellation. Accordingly, it may be the case that there is reason that the IDFT codebook parameters are to be signaled from the TRP **170** to the UE **110**. The IDFT codebook parameters may include parameters discussed hereinbefore, such as: an integer value, L ; a pre-determined limit value, $K_{\text{sub.max}}$, for the number, K , of non-zero elements

in each IDFT codeword; a modulation order; and a power ratio, γ , between the first element and the rest of the elements in each IDFT codeword. The IDFT codebook may be defined dynamically by the TRP **170**. The defining may be based on sensing resources, required sensing accuracy and/or resolution, sensing environment including number of dominant reflectors and/or scatterers, number of sensing Tx-Rx pairs in a given region, etc. The IDFT codebook parameters may be signaled, from the TRP **170** to the UE **110**, through semi-static signaling.

[0195] FIG. **16** illustrates transmitter elements involved in generating a sensing signal, $x(t)$, for transmission. In common with the arrangement illustrated in FIG. **7**, some of the generating takes place in a baseband domain **1600** and some of the generating takes place in an RF domain **1610**.

[0196] In contrast to the arrangement illustrated in FIG. **7**, the baseband domain **1600** includes a base sequence generator **1602** and a baseband signature function generator **1604**. The baseband domain **1600** also includes sensing signal generator **1612** and a multiplier **1616**. The sensing signal generator **1612** includes a chirp signal generator **1614**. The RF domain **1610** includes a digital to analog converter **1624**.

[0197] In operation, the base sequence generator **1602** may receive, as input, a node ID or a sensing session ID. On the basis of the received ID, the base sequence generator **1602** may determine an index (a “codeword index”) that allows the base sequence generator **1602** to select a particular codeword from among a plurality of codewords in a codebook. On the basis of the codeword index, the base sequence generator **1602** may transmit, to the baseband signature function generator **1604**, a base sequence. On the basis of the base sequence, the baseband signature function generator **1604** may generate a discrete signature function, $s(n)$. The baseband signature function generator **1604** may then provide, to the multiplier **1616**, the discrete signature function, $s(n)$. The chirp signal generator **1614** may also receive, as input, the same node ID or the same sensing ID that was provided to the base sequence generator **1602**. On the basis of the node ID or the sensing session ID, the chirp signal generator **1614** may select a starting frequency, $f_{\text{sub},i}$, and a chirp rate, α . Using the selected starting frequency, $f_{\text{sub},i}$, and the selected chirp rate, α , the chirp signal generator **1614** may generate a discrete chirp signal, $c(n)$. The discrete chirp signal, $c(n)$, at the output of the chirp signal generator **1614** may be multiplied, at the multiplier **1616**, with the discrete signature function, $s(n)$, to, thereby, generate a discrete sensing signal, $x(n)$. The node ID may be an identity associated with the sensing transmitter (e.g., the first TRP **170-1** in FIG. **6**) or an identity associated with the sensing receiver (e.g., the first UE **110-1** in FIG. **6**). Upon receipt of the discrete sensing signal, $x(n)$, the digital to analog converter **1624** may convert the discrete sensing signal, $x(n)$, to a continuous sensing signal, $x(t)$, for transmission.

[0198] FIG. **17** illustrates transmitter elements involved in generating a sensing signal, $x(t)$, for transmission. In common with the arrangement illustrated in FIG. **7**, FIG. **17** illustrates a baseband domain **1700** and an RF domain **1710**. In contrast to the arrangement illustrated in FIG. **7**, none of the generating takes place in the baseband domain **1700**.

[0199] The RF domain **1710** includes an RF domain signature function generator **1704** and a sensing signal generator **1712**. The sensing signal generator **1712** includes a chirp signal generator **1714** and a modulator **1716**. The modulator **1716** may be implemented as a multiplier.

[0200] In operation, the RF domain signature function generator **1704** may receive, as input, a node ID or a sensing session ID. On the basis of the received ID, the RF domain signature function generator **1704** may generate an RF domain signature function, $s(t)$. An RF domain signature function has been introduced hereinbefore as a frequency hopping implementation for the design of the signature function, $s(t)$, discussed in conjunction with a description of FIG. **9**. The RF domain signature function generator **1704** may then provide, to the multiplier **1716**, the RF domain signature function, $s(t)$. The chirp signal generator **1714** may also receive, as input, the same node ID or the same sensing ID that was provided to the RF domain signature function generator **1704**. On the basis of the node ID or the sensing session ID, the chirp signal generator **1714** may select a starting frequency, $f_{\text{sub},i}$, and a chirp rate, α , for the chirp signal, $c(t)$. The chirp signal, $c(t)$, at the

output of the chirp signal generator 1714 may be modulated, at the modulator 1716, with the signature function, $s(t)$, to, thereby, generate the sensing signal, $x(t)$.

[0201] In some embodiments, a device or apparatus includes the transmitter elements and/or the receiver elements, to perform the method of the present disclosure.

[0202] It should be appreciated that one or more steps of the embodiment methods provided herein may be performed by corresponding units or modules. For example, data may be transmitted by a transmitting unit or a transmitting module. Data may be received by a receiving unit or a receiving module. Data may be processed by a processing unit or a processing module. The respective units/modules may be hardware, software, or a combination thereof. For instance, one or more of the units/modules may be an integrated circuit, such as field programmable gate arrays (FPGAs) or application-specific integrated circuits (ASICs). It will be appreciated that where the modules are software, they may be retrieved by a processor, in whole or part as needed, individually or together for processing, in single or multiple instances as required, and that the modules themselves may include instructions for further deployment and instantiation.

[0203] Although a combination of features is shown in the illustrated embodiments, not all of them need to be combined to realize the benefits of various embodiments of this disclosure. In other words, a system or method designed according to an embodiment of this disclosure will not necessarily include all of the features shown in any one of the Figures or all of the portions schematically shown in the Figures. Moreover, selected features of one example embodiment may be combined with selected features of other example embodiments.

[0204] Although this disclosure has been described with reference to illustrative embodiments, this description is not intended to be construed in a limiting sense. Various modifications and combinations of the illustrative embodiments, as well as other embodiments of the disclosure, will be apparent to persons skilled in the art upon reference to the description. It is therefore intended that the appended claims encompass any such modifications or embodiments.

Claims

1. A method comprising: generating a linearly frequency modulated signal; generating a signature function; obtaining a sensing signal by modulating the linearly frequency modulated signal with the signature function; and transmitting the sensing signal.
2. The method of claim 1, further comprising: generating a base sequence, wherein the generating the signature function comprises: generating the signature function based at least in part on the base sequence.
3. The method of claim 2, wherein the generating the base sequence comprises: receiving an identity of a node; and generating the base sequence based at least in part on the identity of the node.
4. The method of claim 3, wherein the node comprises a sensing transmitter or a sensing receiver.
5. The method of claim 2, wherein the generating the base sequence comprises: receiving a sensing session identity; and generating the base sequence based at least in part on the sensing session identity.
6. The method of claim 1, wherein the generating the linearly frequency modulated signal comprises: receiving an identity of a node; and generating the linearly frequency modulated signal based at least in part on the identity of the node.
7. The method of claim 1, wherein the generating the linearly frequency modulated signal comprises: receiving an identity of a sensing session; and generating the linearly frequency modulated signal based at least in part on the identity of the sensing session.
8. An apparatus comprising: one or more processors coupled with a memory storing instructions which, when executed by the one or more processors, cause the apparatus to perform operations including: generating a linearly frequency modulated signal; generating a signature function;

obtaining a sensing signal by modulating the linearly frequency modulated signal with the signature function; and transmitting the sensing signal.

9. The apparatus of claim 8, the operations further comprising: generating a base sequence, wherein the generating the signature function comprises: generating the signature function based at least in part on the base sequence.

10. The apparatus of claim 9, wherein the generating the base sequence comprises: receiving an identity of a node; and generating the base sequence based at least in part on the identity of the node.

11. The apparatus of claim 10, wherein the node comprises a sensing transmitter or a sensing receiver.

12. The apparatus of claim 9, wherein the generating the base sequence comprises: receiving a sensing session identity; and generating the base sequence based at least in part on the sensing session identity.

13. The apparatus of claim 8, wherein the generating the linearly frequency modulated signal comprises: receiving an identity of a node; and generating the linearly frequency modulated signal based at least in part on the identity of the node.

14. The apparatus of claim 8, wherein the generating the linearly frequency modulated signal comprises: receiving an identity of a sensing session; and generating the linearly frequency modulated signal based at least in part on the identity of the sensing session.

15. A non-transitory computer-readable storage medium having instructions stored thereon which, when executed, cause an apparatus to perform operations, the operations comprising: generating a linearly frequency modulated signal; generating a signature function; obtaining a sensing signal by modulating the linearly frequency modulated signal with the signature function; and transmitting the sensing signal.

16. The non-transitory computer-readable storage medium of claim 15, the operations further comprising: generating a base sequence; wherein the generating the signature function comprises: generating the signature function based at least in part, on the base sequence.

17. The non-transitory computer-readable storage medium of claim 16, wherein the generating the base sequence comprises: receiving an identity of a node; and generating the base sequence based at least in part on the identity of the node.

18. The non-transitory computer-readable storage medium of claim 17, wherein the node comprises a sensing transmitter or a sensing receiver.

19. The non-transitory computer-readable storage medium of claim 16, wherein the generating the base sequence comprises: receiving a sensing session identity; and generating the base sequence based at least in part on the sensing session identity.

20. The non-transitory computer-readable storage medium of claim 15, wherein the generating the linearly frequency modulated signal comprises: receiving an identity of a node; and generating the linearly frequency modulated signal based at least in part on the identity of the node.
