

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250287367

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

CHEN; Zhe et al.

METHOD AND DEVICE FOR RECEIVING AND TRANSMITTING INFORMATION

Abstract

The disclosure relates to a 5G or 6G communication system for supporting a higher data transmission rate. The disclosure provides a method performed by a user equipment (UE), which comprises receiving indication information from a base station; and based on the indication information, determining whether to perform candidate beam detection according to a resource corresponding to a reference signal set. The disclosure also provides a method performed by a user equipment (UE), which comprises receiving indication information from a base station; determining a second time domain resource based on the indication information; and providing an index of a reference signal, wherein when a time domain resource related to the index of the reference signal overlaps with the second time domain resource, the index of the reference signal is from a second reference signal set; and/or when the time domain resource related to the index of the reference signal does not overlap with the second time domain resource, the index of the reference signal is from a first reference signal set.

Inventors: CHEN; Zhe (Beijing, CN), SUN; Feifei (Beijing, CN), YU; Bin (Beijing, CN)

Applicant: Samsung Electronics Co., Ltd. (Gyeonggi-do, KR)

Family ID: 1000008626490

Appl. No.: 18/859784

Filed (or PCT Filed): April 27, 2023

PCT No.: PCT/KR2023/005804

Foreign Application Priority Data

CN 202210459615.5

Apr. 27, 2022

Publication Classification

Int. Cl.: H04W72/044 (20230101); H04W72/0446 (20230101)

U.S. Cl.:

CPC H04W72/046 (20130101); H04W72/0446 (20130101);

Background/Summary

TECHNICAL FIELD

[0001] The disclosure relates generally to the wireless communication, and more particularly the disclosure relates to a method and a device for receiving and transmitting information.

BACKGROUND ART

[0002] In order to meet the increasing demand for wireless data communication services since the deployment of 4G communication systems, efforts have been made to develop improved 5G or pre-5G communication systems. Therefore, 5G or pre-5G communication systems are also called “Beyond 4G networks” or “Post-LTE systems”.

[0003] In order to achieve a higher data rate, 5G communication systems are implemented in higher frequency (mmWave) bands, e.g., 60 GHz bands. In order to reduce propagation loss of radio waves and increase a transmission distance, technologies such as beamforming, massive multiple-input multiple-output (MIMO), full-dimensional MIMO (FD-MIMO), array antenna, analog beamforming and large-scale antenna are discussed in 5G communication systems.

[0004] In addition, in 5G communication systems, developments of system network improvement are underway based on advanced small cell, cloud radio access network (RAN), ultra-dense network, device-to-device (D2D) communication, wireless backhaul, mobile network, cooperative communication, coordinated multi-points (CoMP), reception-end interference cancellation, etc.

[0005] In 5G systems, hybrid FSK and QAM modulation (FQAM) and sliding window superposition coding (SWSC) as advanced coding modulation (ACM), and filter bank multicarrier (FBMC), non-orthogonal multiple access (NOMA) and sparse code multiple access (SCMA) as advanced access technologies have been developed.

[0006] Transmission from a base station to a user equipment (UE) is called downlink, and transmission from a UE to a base station is called uplink.

[0007] 5G mobile communication technologies define broad frequency bands such that high transmission rates and new services are possible, and can be implemented not only in “Sub 6 GHz” bands such as 3.5 GHz, but also in “Above 6 GHz” bands referred to as mmWave including 28 GHz and 39 GHz. In addition, it has been considered to implement 6G mobile communication technologies (referred to as Beyond 5G systems) in terahertz bands (for example, 95 GHz to 3 THz bands) in order to accomplish transmission rates fifty times faster than 5G mobile communication technologies and ultra-low latencies one-tenth of 5G mobile communication technologies.

[0008] At the beginning of the development of 5G mobile communication technologies, in order to support services and to satisfy performance requirements in connection with enhanced Mobile BroadBand (eMBB), Ultra Reliable Low Latency Communications (URLLC), and massive Machine-Type Communications (mMTC), there has been ongoing standardization regarding beamforming and massive MIMO for mitigating radio-wave path loss and increasing radio-wave transmission distances in mmWave, supporting numerologies (for example, operating multiple subcarrier spacings) for efficiently utilizing mmWave resources and dynamic operation of slot formats, initial access technologies for supporting multi-beam transmission and broadbands,

definition and operation of BWP (BandWidth Part), new channel coding methods such as a LDPC (Low Density Parity Check) code for large amount of data transmission and a polar code for highly reliable transmission of control information, L2 pre-processing, and network slicing for providing a dedicated network specialized to a specific service.

[0009] Currently, there are ongoing discussions regarding improvement and performance enhancement of initial 5G mobile communication technologies in view of services to be supported by 5G mobile communication technologies, and there has been physical layer standardization regarding technologies such as V2X (Vehicle-to-everything) for aiding driving determination by autonomous vehicles based on information regarding positions and states of vehicles transmitted by the vehicles and for enhancing user convenience, NR-U (New Radio Unlicensed) aimed at system operations conforming to various regulation-related requirements in unlicensed bands, NR UE Power Saving, Non-Terrestrial Network (NTN) which is UE-satellite direct communication for providing coverage in an area in which communication with terrestrial networks is unavailable, and positioning.

[0010] Moreover, there has been ongoing standardization in air interface architecture/protocol regarding technologies such as Industrial Internet of Things (IIoT) for supporting new services through interworking and convergence with other industries, IAB (Integrated Access and Backhaul) for providing a node for network service area expansion by supporting a wireless backhaul link and an access link in an integrated manner, mobility enhancement including conditional handover and DAPS (Dual Active Protocol Stack) handover, and two-step random access for simplifying random access procedures (2-step RACH for NR). There also has been ongoing standardization in system architecture/service regarding a 5G baseline architecture (for example, service based architecture or service based interface) for combining Network Functions Virtualization (NFV) and Software-Defined Networking (SDN) technologies, and Mobile Edge Computing (MEC) for receiving services based on UE positions.

[0011] As 5G mobile communication systems are commercialized, connected devices that have been exponentially increasing will be connected to communication networks, and it is accordingly expected that enhanced functions and performances of 5G mobile communication systems and integrated operations of connected devices will be necessary. To this end, new research is scheduled in connection with extended Reality (XR) for efficiently supporting AR (Augmented Reality), VR (Virtual Reality), MR (Mixed Reality) and the like, 5G performance improvement and complexity reduction by utilizing Artificial Intelligence (AI) and Machine Learning (ML), AI service support, metaverse service support, and drone communication.

[0012] Furthermore, such development of 5G mobile communication systems will serve as a basis for developing not only new waveforms for providing coverage in terahertz bands of 6G mobile communication technologies, multi-antenna transmission technologies such as Full Dimensional MIMO (FD-MIMO), array antennas and large-scale antennas, metamaterial-based lenses and antennas for improving coverage of terahertz band signals, high-dimensional space multiplexing technology using OAM (Orbital Angular Momentum), and RIS (Reconfigurable Intelligent Surface), but also full-duplex technology for increasing frequency efficiency of 6G mobile communication technologies and improving system networks, AI-based communication technology for implementing system optimization by utilizing satellites and AI (Artificial Intelligence) from the design stage and internalizing end-to-end AI support functions, and next-generation distributed computing technology for implementing services at levels of complexity exceeding the limit of UE operation capability by utilizing ultra-high-performance communication and computing resources.

[0013] The above information is presented as background information only to assist with an understanding of the disclosure. No determination has been made, and no assertion is made, as to whether any of the above might be applicable as prior art with regard to the disclosure.

DISCLOSURE OF INVENTION

Technical Problem

[0014] In actual deployment, in order to reduce power consumption, a base station adopts a more flexible scheduling method. At present, a UE cannot adapt to such scheduling method well, which may result in, for example, a reduce in the accuracy of candidate beam detection/reporting, and further cause a reduce in the reliability of the UE. In order to improve the reliability of the UE, it is necessary to propose an improved candidate beam detection/reporting method.

Solution to Problem

[0015] According to an embodiment of the disclosure, a method performed by a user equipment (UE) is proposed, the method includes: receiving indication information from a base station; and determining whether to perform candidate beam detection according to a resource corresponding to a reference signal set based on the indication information.

[0016] According to an embodiment of the disclosure, determining whether to perform candidate beam detection according to the resource corresponding to the reference signal set based on the indication information includes: determining whether to perform candidate beam detection according to the resource corresponding to the reference signal set on a first time domain resource based on the indication information; wherein the first time domain resource is determined based on at least one of the followings: starting and/or ending of the first time domain resource is determined by the indication information; a time domain position of the first time domain resource is determined by a time domain position of a channel or signal carrying the indication information.

[0017] According to an embodiment of the disclosure, determining whether to perform candidate beam detection according to the resource corresponding to the reference signal set based on the indication information includes: determining whether to perform candidate beam detection according to the resource corresponding to the reference signal set based on at least one of a serving cell, a bandwidth part, a cell physical layer identity and a transmission and reception point corresponding to the indication information.

[0018] According to an embodiment of the disclosure, a method performed by a user equipment (UE) is proposed, the method includes: receiving indication information from a base station; determining a second time domain resource based on the indication information; and providing an index of a reference signal to a higher layer, wherein when a time domain resource related to the index of the reference signal overlaps with the second time domain resource, the index of the reference signal is from a second reference signal set; and/or when the time domain resource related to the index of the reference signal does not overlap with the second time domain resource, the index of the reference signal is from a first reference signal set.

[0019] According to an embodiment of the disclosure, the second time domain resource is determined based on at least one of the followings: starting and/or ending of the second time domain resource is determined by the indication information; a time domain position of the second time domain resource is determined by a time domain position of a channel or signal carrying the indication information.

[0020] According to an embodiment of the disclosure, the second reference signal set is determined based on the first reference signal set.

[0021] According to an embodiment of the disclosure, the second reference signal set corresponds to the first reference signal set one by one.

[0022] According to an embodiment of the disclosure, the first reference signal set is determined based on information transmitted by the base station.

[0023] According to an embodiment of the disclosure, a method performed by a user equipment (UE) is proposed, the method includes: receiving indication information from a base station; determining a second time domain resource based on the indication information; and providing an index of a reference signal to the base station, wherein when a time domain resource related to the index of the reference signal overlaps with the second time domain resource, determining that the index of the reference signal is from a second reference signal set; and/or when the time domain resource related to the index of the reference signal does not overlap with the second time domain

resource, the index of the reference signal is from a first reference signal set.

[0024] According to an embodiment of the disclosure, the method further includes at least one of the following operations: receiving at least one of a physical downlink shared channel (PDSCH), a physical downlink control channel (PDCCH) and/or a channel state information reference signal (CSI-RS) according to the index of the reference signal; transmitting at least one of a physical uplink shared channel (PUSCH), a physical uplink control channel (PUCCH) and/or a sounding reference signal (SRS) according to the index of the reference signal; monitoring at least one of a physical uplink shared channel (PUSCH), a physical uplink control channel (PUCCH) and/or a sounding reference signal (SRS) according to the index of the reference signal.

[0025] According to an embodiment of the disclosure, the second time domain resource is determined based on at least one of the followings: starting and/or ending of the second time domain resource is determined by the indication information; a time domain position of the second time domain resource is determined by a time domain position of a channel or signal carrying the indication information.

[0026] According to an embodiment of the disclosure, the second reference signal set is determined based on the first reference signal set.

[0027] According to an embodiment of the disclosure, the second reference signal set corresponds to the first reference signal set one by one.

[0028] According to an embodiment of the disclosure, the first reference signal set is determined based on information transmitted by the base station.

[0029] According to an embodiment of the disclosure, a method performed by a base station is proposed, the method includes: transmitting configuration information to a user equipment (UE); and transmitting indication information to the user equipment, wherein the indication information is used for the user equipment to perform the methods of various embodiments disclosed herein.

[0030] According to an embodiment of the disclosure, a user equipment (UE) is provided, the UE includes: a transceiver; and a processor coupled to the transceiver and configured to perform the methods disclosed in embodiments herein.

[0031] According to an embodiment of the disclosure, a base station is provided, the base station includes a transceiver; and a processor coupled to the transceiver and configured to perform the methods disclosed herein.

Advantageous Effects of Invention

[0032] The disclosure provides a method and device for receiving and transmitting information, which can improve the reception performance of a terminal device. More specifically, the methods provided by the disclosure can improve the performance of the terminal device in beam recovery and ensure the reliability of the terminal device; in addition, these methods can also reduce the energy consumption of terminal device by reducing the measurement of reference signals.

Description

BRIEF DESCRIPTION OF DRAWINGS

[0033] The above and other features, aspects and advantages of the disclosure will be apparent according to the following description taken in conjunction with the accompanying drawings.

[0034] FIG. 1 illustrates an example wireless network according to an embodiment of the disclosure;

[0035] FIG. 2a illustrates a transmission path **200** in a wireless communication network according to an embodiment of the disclosure;

[0036] FIG. 2b illustrates a reception path **250** in a wireless communication network according to an embodiment of the disclosure;

[0037] FIG. 3a illustrates a structure of a user equipment (UE) in a wireless communication

network according to an embodiment of the disclosure;

[0038] FIG. **3b** illustrates a structure of a base station in a wireless communication network according to an embodiment of the disclosure;

[0039] FIG. **4** illustrates a method **400** performed by a user equipment (UE) according to an embodiment of the disclosure;

[0040] FIG. **5** illustrates a method **500** performed by a user equipment (UE) according to an embodiment of the disclosure;

[0041] FIG. **6** illustrates a method **600** performed by a user equipment (UE) according to an embodiment of the disclosure;

[0042] FIG. **7** illustrates a method **700** performed by a base station according to an embodiment of the disclosure;

[0043] FIG. **8** illustrates a user equipment (UE) **800** according to an embodiment of the disclosure; and

[0044] FIG. **9** illustrates a base station **900** according to an embodiment of the disclosure.

MODE FOR THE INVENTION

[0045] Hereinafter, embodiments of the disclosure will be described in detail with reference to the accompanying drawings. It should be noted that in the drawings, the same or similar elements are denoted by the same or similar reference numerals as much as possible. In addition, detailed descriptions of known functions or configurations that may obscure the subject matter of the disclosure will be omitted.

[0046] When describing the embodiments of the disclosure, the description related to the technical contents known in the art and not directly related to the disclosure will be omitted. Such unnecessary descriptions are omitted to prevent obscuring the main idea of this disclosure and to convey the main idea more clearly.

[0047] For the same reason, some elements may be enlarged, omitted or shown schematically in the drawings. In addition, the size of each component does not fully reflect the actual size. In the drawings, the same or corresponding elements have the same reference numerals.

[0048] The advantages and features of the disclosure and the way to realize them will become clear by referring to the embodiments described in detail below in conjunction with the accompanying drawings. However, the disclosure is not limited to the embodiments set forth below, but can be implemented in various forms. The following examples are provided only to fully disclose this disclosure and inform those skilled in the art of the scope of this disclosure, and this disclosure is only limited by the scope of the appended claims. Throughout the specification, the same or similar reference numerals refer to the same or similar elements.

[0049] FIG. **1** illustrates an example wireless network **100** according to an embodiment of the disclosure. The embodiment of the wireless network **100** shown in FIG. **1** is for illustration only. Other embodiments of the wireless network **100** can be used without departing from the scope of the disclosure.

[0050] The wireless network **100** includes a gNodeB (gNB) **101**, a gNB **102**, and a gNB **103**. gNB **101** communicates with gNB **102** and gNB **103**. gNB **101** also communicates with at least one Internet Protocol (IP) network **130**, such as the Internet, a private IP network, or other data networks.

[0051] Depending on a type of the network, other well-known terms such as “base station” or “access point” can be used instead of “gNodeB” or “gNB”. For convenience, the terms “gNodeB” and “gNB” are used in this patent document to refer to network infrastructure components that provide wireless access for remote terminals. And, depending on the type of the network, other well-known terms such as “mobile station”, “user station”, “remote terminal”, “wireless terminal” or “user apparatus” can be used instead of “user equipment” or “UE”. For convenience, the terms “user equipment” and “UE” are used in this patent document to refer to remote wireless devices that wirelessly access the gNB, no matter whether the UE is a mobile device (such as a mobile

phone or a smart phone) or a fixed device (such as a desktop computer or a vending machine). [0052] gNB **102** provides wireless broadband access to the network **130** for a first plurality of User Equipments (UEs) within a coverage area **120** of gNB **102**. The first plurality of UEs include a UE **111**, which may be located in a Small Business (SB); a UE **112**, which may be located in an enterprise (E); a UE **113**, which may be located in a WiFi Hotspot (HS); a UE **114**, which may be located in a first residence (R); a UE **115**, which may be located in a second residence (R); a UE **116**, which may be a mobile device (M), such as a cellular phone, a wireless laptop computer, a wireless PDA, etc. GNB **103** provides wireless broadband access to network **130** for a second plurality of UEs within a coverage area **125** of gNB **103**. The second plurality of UEs include a UE **115** and a UE **116**. In some embodiments, one or more of gNBs **101-103** can communicate with each other and with UEs **111-116** using 5G, Long Term Evolution (LTE), LTE-A, WiMAX or other advanced wireless communication technologies.

[0053] The dashed lines show approximate ranges of the coverage areas **120** and **125**, and the ranges are shown as approximate circles merely for illustration and explanation purposes. It should be clearly understood that the coverage areas associated with the gNBs, such as the coverage areas **120** and **125**, may have other shapes, including irregular shapes, depending on configurations of the gNBs and changes in the radio environment associated with natural obstacles and man-made obstacles.

[0054] As will be described in more detail below, one or more of gNB **101**, gNB **102**, and gNB **103** include a 2D antenna array as described in embodiments of the disclosure. In some embodiments, one or more of gNB **101**, gNB **102**, and gNB **103** support codebook designs and structures for systems with 2D antenna arrays.

[0055] Although FIG. **1** illustrates an example of the wireless network **100**, various changes can be made to FIG. **1**. The wireless network **100** can include any number of gNBs and any number of UEs in any suitable arrangement, for example. Furthermore, gNB **101** can directly communicate with any number of UEs and provide wireless broadband access to the network **130** for those UEs. Similarly, each gNB **102-103** can directly communicate with the network **130** and provide direct wireless broadband access to the network **130** for the UEs. In addition, gNB **101**, **102** and/or **103** can provide access to other or additional external networks, such as external telephone networks or other types of data networks.

[0056] FIGS. **2a** and **2b** illustrate example wireless transmission and reception paths according to an embodiment of the disclosure. In the following description, the transmission path **200** can be described as being implemented in a gNB, such as gNB **102**, and the reception path **250** can be described as being implemented in a UE, such as UE **116**. However, it should be understood that the reception path **250** can be implemented in a gNB and the transmission path **200** can be implemented in a UE. In some embodiments, the reception path **250** is configured to support codebook designs and structures for systems with 2D antenna arrays as described in embodiments of the disclosure.

[0057] The transmission path **200** includes a channel coding and modulation block **205**, a Serial-to-Parallel (S-to-P) block **210**, a size N Inverse Fast Fourier Transform (IFFT) block **215**, a Parallel-to-Serial (P-to-S) block **220**, a cyclic prefix addition block **225**, and an up-converter (UC) **230**. The reception path **250** includes a down-converter (DC) **255**, a cyclic prefix removal block **260**, a Serial-to-Parallel (S-to-P) block **265**, a size N Fast Fourier Transform (FFT) block **270**, a Parallel-to-Serial (P-to-S) block **275**, and a channel decoding and demodulation block **280**.

[0058] In the transmission path **200**, the channel coding and modulation block **205** receives a set of information bits, applies coding (such as Low Density Parity Check (LDPC) coding), and modulates the input bits (such as using Quadrature Phase Shift Keying (QPSK) or Quadrature Amplitude Modulation (QAM)) to generate a sequence of frequency-domain modulated symbols. The Serial-to-Parallel (S-to-P) block **210** converts (such as demultiplexes) serial modulated symbols into parallel data to generate N parallel symbol streams, where N is a size of the IFFT/FFT

used in gNB **102** and UE **116**. The size N IFFT block **215** performs IFFT operations on the N parallel symbol streams to generate a time-domain output signal. The Parallel-to-Serial block **220** converts (such as multiplexes) parallel time-domain output symbols from the Size N IFFT block **215** to generate a serial time-domain signal. The cyclic prefix addition block **225** inserts a cyclic prefix into the time-domain signal. The up-converter **230** modulates (such as up-converts) the output of the cyclic prefix addition block **225** to an RF frequency for transmission via a wireless channel. The signal can also be filtered at a baseband before switching to the RF frequency.

[0059] The RF signal transmitted from gNB **102** arrives at UE **116** after passing through the wireless channel, and operations in reverse to those at gNB **102** are performed at UE **116**. The down-converter **255** down-converts the received signal to a baseband frequency, and the cyclic prefix removal block **260** removes the cyclic prefix to generate a serial time-domain baseband signal. The Serial-to-Parallel block **265** converts the time-domain baseband signal into a parallel time-domain signal. The Size N FFT block **270** performs an FFT algorithm to generate N parallel frequency-domain signals. The Parallel-to-Serial block **275** converts the parallel frequency-domain signal into a sequence of modulated data symbols. The channel decoding and demodulation block **280** demodulates and decodes the modulated symbols to recover the original input data stream.

[0060] Each of gNBs **101-103** may implement a transmission path **200** similar to that for transmitting to UEs **111-116** in the downlink, and may implement a reception path **250** similar to that for receiving from UEs **111-116** in the uplink. Similarly, each of UEs **111-116** may implement a transmission path **200** for transmitting to gNBs **101-103** in the uplink, and may implement a reception path **250** for receiving from gNBs **101-103** in the downlink.

[0061] Each of the components in FIGS. **2a** and **2b** can be implemented using only hardware, or using a combination of hardware and software/firmware. As a specific example, at least some of the components in FIGS. **2a** and **2b** may be implemented in software, while other components may be implemented in configurable hardware or a combination of software and configurable hardware. For example, the FFT block **270** and IFFT block **215** may be implemented as configurable software algorithms, in which the value of the size N may be modified according to the implementation.

[0062] Furthermore, although described as using FFT and IFFT, this is only illustrative and should not be interpreted as limiting the scope of the disclosure. Other types of transforms can be used, such as Discrete Fourier transform (DFT) and Inverse Discrete Fourier Transform (IDFT) functions. It should be understood that for DFT and IDFT functions, the value of variable N may be any integer (such as 1, 2, 3, 4, etc.), while for FFT and IFFT functions, the value of variable N may be any integer which is a power of 2 (such as 1, 2, 4, 8, 16, etc.).

[0063] Although FIGS. **2a** and **2b** illustrate examples of wireless transmission and reception paths, various changes may be made to FIGS. **2a** and **2b**. For example, various components in FIGS. **2a** and **2b** can be combined, further subdivided or omitted, and additional components can be added according to specific requirements. Furthermore, FIGS. **2a** and **2b** are intended to illustrate examples of types of transmission and reception paths that can be used in a wireless network. Any other suitable architecture can be used to support wireless communication in a wireless network.

[0064] FIG. **3a** illustrates an example UE **116** according to an embodiment of the disclosure. The embodiment of UE **116** shown in FIG. **3a** is for illustration only, and UEs **111-115** of FIG. **1** can have the same or similar configuration. However, a UE has various configurations, and FIG. **3a** does not limit the scope of the disclosure to any specific implementation of the UE.

[0065] UE **116** includes an antenna **305**, a radio frequency (RF) transceiver **310**, a transmission (TX) processing circuit **315**, a microphone **320**, and a reception (RX) processing circuit **325**. UE **116** also includes a speaker **330**, a processor/controller **340**, an input/output (I/O) interface **345**, an input device(s) **350**, a display **355**, and a memory **360**. The memory **360** includes an operating system (OS) **361** and one or more applications **362**.

[0066] The RF transceiver **310** receives an incoming RF signal transmitted by a gNB of the wireless network **100** from the antenna **305**. The RF transceiver **310** down-converts the incoming

RF signal to generate an intermediate frequency (IF) or baseband signal. The IF or baseband signal is transmitted to the RX processing circuit **325**, where the RX processing circuit **325** generates a processed baseband signal by filtering, decoding and/or digitizing the baseband or IF signal. The RX processing circuit **325** transmits the processed baseband signal to speaker **330** (such as for voice data) or to processor/controller **340** for further processing (such as for web browsing data). [0067] The TX processing circuit **315** receives analog or digital voice data from microphone **320** or other outgoing baseband data (such as network data, email or interactivated video game data) from processor/controller **340**. The TX processing circuit **315** encodes, multiplexes, and/or digitizes the outgoing baseband data to generate a processed baseband or IF signal. The RF transceiver **310** receives the outgoing processed baseband or IF signal from the TX processing circuit **315** and up-converts the baseband or IF signal into an RF signal transmitted via the antenna **305**.

[0068] The processor/controller **340** can include one or more processors or other processing devices and perform an OS **361** stored in the memory **360** in order to control the overall operation of UE **116**. For example, the processor/controller **340** can control the reception of forward channel signals and the transmission of backward channel signals through the RF transceiver **310**, the RX processing circuit **325** and the TX processing circuit **315** according to well-known principles. In some embodiments, the processor/controller **340** includes at least one microprocessor or microcontroller.

[0069] The processor/controller **340** is also capable of executing other processes and programs residing in the memory **360**, such as operations for channel quality measurement and reporting for systems with 2D antenna arrays as described in embodiments of the disclosure. The processor/controller **340** can move data into or out of the memory **360** as required by an execution process. In some embodiments, the processor/controller **340** is configured to perform the application **362** based on the OS **361** or in response to signals received from the gNB or the operator. The processor/controller **340** is also coupled to an I/O interface **345**, where the I/O interface **345** provides UE **116** with the ability to connect to other devices such as laptop computers and handheld computers. I/O interface **345** is a communication path between these accessories and the processor/controller **340**.

[0070] The processor/controller **340** is also coupled to the input device(s) **350** and the display **355**. An operator of UE **116** can input data into UE **116** using the input device(s) **350**. The display **355** may be a liquid crystal display or other display capable of presenting text and/or at least limited graphics (such as from a website). The memory **360** is coupled to the processor/controller **340**. A part of the memory **360** can include a random access memory (RAM), while another part of the memory **360** can include a flash memory or other read-only memory (ROM).

[0071] Although FIG. **3a** illustrates an example of UE **116**, various changes can be made to FIG. **3a**. For example, various components in FIG. **3a** can be combined, further subdivided or omitted, and additional components can be added according to specific requirements. As a specific example, the processor/controller **340** can be divided into a plurality of processors, such as one or more central processing units (CPUs) and one or more graphics processing units (GPUs). Furthermore, although FIG. **3a** illustrates that the UE **116** is configured as a mobile phone or a smart phone, UEs can be configured to operate as other types of mobile or fixed devices.

[0072] FIG. **3b** illustrates an example gNB **102** according to an embodiment of the disclosure. The embodiment of gNB **102** shown in FIG. **3b** is for illustration only, and other gNBs of FIG. **1** can have the same or similar configuration. However, a gNB has various configurations, and FIG. **3b** does not limit the scope of the disclosure to any specific implementation of a gNB. It should be noted that gNB **101** and gNB **103** can include the same or similar structures as gNB **102**.

[0073] As shown in FIG. **3b**, gNB **102** includes a plurality of antennas **370a-370n**, a plurality of RF transceivers **372a-372n**, a transmission (TX) processing circuit **374**, and a reception (RX) processing circuit **376**. In certain embodiments, one or more of the plurality of antennas **370a-370n** include a 2D antenna array. gNB **102** also includes a controller/processor **378**, a memory **380**, and a

backhaul or network interface **382**.

[0074] RF transceivers **372a-372n** receive an incoming RF signal from antennas **370a-370n**, such as a signal transmitted by UEs or other gNBs. RF transceivers **372a-372n** down-convert the incoming RF signal to generate an IF or baseband signal. The IF or baseband signal is transmitted to the RX processing circuit **376**, where the RX processing circuit **376** generates a processed baseband signal by filtering, decoding and/or digitizing the baseband or IF signal. RX processing circuit **376** transmits the processed baseband signal to controller/processor **378** for further processing.

[0075] The TX processing circuit **374** receives analog or digital data (such as voice data, network data, email or interactivated video game data) from the controller/processor **378**. TX processing circuit **374** encodes, multiplexes and/or digitizes outgoing baseband data to generate a processed baseband or IF signal. RF transceivers **372a-372n** receive the outgoing processed baseband or IF signal from TX processing circuit **374** and up-convert the baseband or IF signal into an RF signal transmitted via antennas **370a-370n**.

[0076] The controller/processor **378** can include one or more processors or other processing devices that control the overall operation of gNB **102**. For example, the controller/processor **378** can control the reception of forward channel signals and the transmission of backward channel signals through the RF transceivers **372a-372n**, the RX processing circuit **376** and the TX processing circuit **374** according to well-known principles. The controller/processor **378** can also support additional functions, such as higher-level wireless communication functions. For example, the controller/processor **378** can perform a Blind Interference Sensing (BIS) process such as that performed through a BIS algorithm, and decode a received signal from which an interference signal is subtracted. A controller/processor **378** may support any of a variety of other functions in gNB **102**. In some embodiments, the controller/processor **378** includes at least one microprocessor or microcontroller.

[0077] The controller/processor **378** is also capable of executing programs and other processes residing in the memory **380**, such as a basic OS. The controller/processor **378** can also support channel quality measurement and reporting for systems with 2D antenna arrays as described in embodiments of the disclosure. In some embodiments, the controller/processor **378** supports communication between entities such as web RTCs. The controller/processor **378** can move data into or out of the memory **380** as required by an execution process.

[0078] The controller/processor **378** is also coupled to the backhaul or network interface **382**. The backhaul or network interface **382** allows gNB **102** to communicate with other devices or systems through a backhaul connection or through a network. The backhaul or network interface **382** can support communication over any suitable wired or wireless connection(s). For example, when gNB **102** is implemented as a part of a cellular communication system, such as a cellular communication system supporting 5G or new radio access technology or NR, LTE or LTE-A, the backhaul or network interface **382** can allow gNB **102** to communicate with other gNBs through wired or wireless backhaul connections. When gNB **102** is implemented as an access point, the backhaul or network interface **382** can allow gNB **102** to communicate with a larger network, such as the Internet, through a wired or wireless local area network or through a wired or wireless connection. The backhaul or network interface **382** includes any suitable structure that supports communication through a wired or wireless connection, such as an Ethernet or an RF transceiver.

[0079] The memory **380** is coupled to the controller/processor **378**. A part of the memory **380** can include an RAM, while another part of the memory **380** can include a flash memory or other ROMs. In certain embodiments, a plurality of indication, such as the BIS algorithm, are stored in the memory. The plurality of indication are configured to cause the controller/processor **378** to perform the BIS process and decode the received signal after subtracting at least one interference signal determined by the BIS algorithm.

[0080] As will be described in more detail below, the transmission and reception paths of gNB **102**

(implemented using RF transceivers 372a-372n, TX processing circuit 374 and/or RX processing circuit 376) support aggregated communication with FDD cells and TDD cells.

[0081] Although FIG. 3b illustrates an example of gNB 102, various changes may be made to FIG. 3b. For example, gNB 102 can include any number of each component shown in FIG. 3a. As a specific example, the access point can include many backhaul or network interfaces 382, and the controller/processor 378 can support routing functions to route data between different network addresses. As another specific example, although shown as including a single instance of the TX processing circuit 374 and a single instance of the RX processing circuit 376, gNB 102 can include multiple instances of each (such as one for each RF transceiver).

[0082] In actual deployment, high power consumption of a NR base station greatly increases the operating cost of an operator. The main reason is that the NR base station integrates a large number of advanced functions, such as fine granularity of time domain scheduling, fine granularity of frequency domain scheduling and fine granularity of space domain scheduling. These functions have greatly improved user experience, but correspondingly brought great power consumption. Especially, when the number of users served by the base station is small, the existing mechanism does not enable the base station adjust its scheduling methods flexibly. Here, the main limitation is that when the base station adjusts the scheduling granularity (time domain/frequency domain/space domain) dynamically, a terminal device cannot adjust reception or transmission assumption correspondingly, resulting in performance degradation of the terminal device. In order to solve this problem, a feasible method is that the base station provides energy-saving indication of the base station to the terminal device. The base station transmits the indication to the terminal device, so that the terminal device can know the granularity for the transmission and reception of the base station in time domain, frequency domain and space domain. In the disclosure, a method for the terminal device to perform beam failure detection in the scenario of a base station energy-saving mode is provided. After the reception of the indication from the base station, the terminal device can adjust reference signals for beam failure detection accordingly (and determine whether to monitor these reference signals). Therefore, the method provided by the disclosure can improve the performance of the terminal device in beam failure detection, thereby ensuring the reliability of the terminal device; in addition, this method can also reduce the energy consumption of the terminal device by reducing the measurement of reference signals.

[0083] The disclosure will be described in detail below with reference to specific embodiments.
Embodiment 1

[0084] A user equipment (UE) receives indication information from a base station; and determines whether to monitor a reference signal set based on the indication information.

[0085] Optionally, determining whether to monitor the reference signal set can be understood as determining to monitor the reference signal set; or understood as determining not to (not expected to) monitor the reference signal set.

[0086] Optionally, the terminal device monitors the reference signal set for the purpose of candidate beam detection; in other words, the terminal device performs candidate beam detection according to the reference signal set. Optionally, reference signals in the reference signal set are used for identifying the candidate beams for recovery. The reference signal set is called q.sub.1, q.sub.1,0 or q.sub.1,1.

Method for Determining q.SUB.1

[0087] According to RRC signaling (e.g., candidateBeamRSLIST, candidateBeamRSLISTExt or candidateBeamRSSCellList). Specifically, the terminal device determines q.sub.1 according to the indication indicated by RRC signaling on a bandwidth part (BWP) of a serving cell.

Method for Determining q.SUB.1,0

[0088] According to RRC signaling (e.g., candidateBeamRSLIST1). Specifically, the terminal device determines q.sub.1,0 according to the indication indicated by RRC signaling on a bandwidth part (BWP) of a serving cell.

Method for Determining q.SUB.1,1

[0089] According to RRC signaling (e.g., candidateBeamRSList2). Specifically, the terminal device determines q.sub.1,1 according to the indication indicated by RRC signaling on a bandwidth part (BWP) of a serving cell.

[0090] The following methods can help the terminal device to determine whether to monitor the reference signal set (q.sub.1, q.sub.1,0 or q.sub.1,1) on a first time domain resource.

[0091] Optionally, the above indication information is related to network energy-saving.

Specifically, the indication information may be used to inform the terminal device whether the base station device is in a network energy-saving mode on the first time domain resource. If a first information indicates that it is not in the network energy-saving mode, the terminal device monitors the reference signal set on the first time domain resource; if the first information indicates that it is in the network energy-saving mode, the terminal device does not monitor (is not expected to detect) the reference signal set on the first time domain resource.

[0092] Optionally, the above indication information may be UE-specific information, group-common information or cell-common information.

[0093] In the following examples, take the terminal device monitoring the reference signal for the purpose of candidate beam detection as an example. The terminal device determining whether to monitor the reference signal set is understood as the terminal device determining that it is not expected to perform candidate beam detection according to the reference signal set on the first time domain resource. Take the indication information being the first information as an example.

Example 1 (Time Domain Resource)

Method 1

[0094] The first time domain resource is determined according to the first information. That is, the terminal device determines a time domain resource (time period, that is, the starting and ending of the time domain resource) according to the first information. The terminal is not expected to perform candidate beam detection during the time period. In other words, the terminal device is not expected to perform candidate beam detection according to (q.sub.1 or q.sub.1,0 and q.sub.1,1) during the time period. A time unit of the time period can be at least one of a frame, a subframe, a slot, a sub-slot, a symbol, etc. Wherein, the sub-carrier spacing (SCS) corresponding to the slot, sub-slot and symbol can be determined according to at least one of the followings: [0095] reference subcarrier spacing. E.g., reference subcarrier spacing indication (referenceSubcarrierSpacing) in TDD configuration information (tdd-UL-DL-ConfigurationCommon). Furthermore, the TDD configuration information is for a PCell of the terminal device. [0096] subcarrier spacing of an SSB; further, it is the subcarrier spacing of the SSB corresponding to the latest PRACH transmission of the terminal device; another example is the SSB corresponding to a TCI state of CORESET#0 indicated by the base station through MAC-CE signaling. [0097] preset subcarrier spacing, for example, 15 kHz, 30 kHz, 60 kHz, 120 kHz, 240 KHz. [0098] subcarrier spacing related to a frequency range; furthermore, the subcarrier spacing for different frequency ranges can be configured (defined) individually, where these frequency ranges include FR1, FR2 (FR2-1, FR2-2, refer to existing protocols for specific meanings). E.g., the subcarrier spacing is 15 kHz for FR1; the subcarrier spacing is 60 kHz for FR2. [0099] subcarrier spacing corresponding to CORESET#0 of the terminal device. [0100] subcarrier spacing corresponding to the initial BWP of the terminal device. For example, subCarrierSpacingCommon in MIB.

[0101] Advantageous effects: according to the above method, it can be determined during which time period the terminal device is not expected (or expected) to monitor the reference signal set for candidate beam detection. The terminal does not monitor the reference signal set during the corresponding time period, which can save energy.

Method 2

[0102] A time domain position of the first time domain resource is determined by a time domain position of a channel or signal carrying the indication information. Optionally, the time domain

position of the first time domain resource is before the channel or signal carrying the indication information; optionally, the time domain position of the first time domain resource overlaps with the channel or signal carrying the indication information; optionally, the first time domain resource information refers to a time domain resource after the transmission or reception of a channel or signal related to the first information, which is taken as an example. The terminal is not expected to perform candidate beam detection after the transmission or reception of the channel or signal related to the first information. In other words, the terminal device is not expected to perform candidate beam detection (according to q.sub.1 or q.sub.1,0 and q.sub.1,1) after the transmission or reception of the channel or signal related to the first information. For example, the first time domain resource is a time domain resource after the reception of the channel or signal (PDCCH, PDSCH, etc.) related to the first information. For another example, the first time domain resource is a time domain resource after the reception of a channel or signal (PUCCH or PUSCH) carrying feedback information (HARQ-ACK information) for the channel or signal (PDSCH, etc.) related to the first information. For another example, the first time domain resource is a time domain resource after a time period after the reception of the channel or signal (PDCCH, PDSCH, etc.) related to the first information. For another example, the first time domain resource is a time domain resource after a time period after the reception of the channel or signal (PUCCH or PUSCH) carrying the feedback information (HARQ-ACK information) for the channel or signal (PDSCH, etc.) related to the first information. Optionally, the time period is the time for the terminal device to process (interpret) the first information. Optionally, the time unit corresponding to the time period may be as described with reference to the above examples.

Advantageous Effects of this Embodiment

[0103] The methods provided in this embodiment can improve the reception performance of the terminal device. More specifically, the methods provided by the disclosure can improve the performance of the terminal device in beam recovery (ensuring the reliability of the terminal device); in addition, these methods can also reduce the energy consumption of the terminal device by reducing/stopping the measurement of the reference signals.

Embodiment 2

[0104] A user equipment receives indication information from a base station; and determines whether to monitor a reference signal set based on at least one of a serving cell, a bandwidth part, a cell physical layer identity and a transmission and reception point corresponding to the indication information.

[0105] Optionally, determining whether to monitor the reference signal set can be understood as determining to monitor the reference signal set; or understood as determining not to monitor (not expected to monitor the reference signal set).

[0106] Optionally, the terminal device monitors the reference signal set for the purpose of candidate beam detection; in other words, the terminal device performs candidate beam detection according to the reference signal set. Optionally, reference signals in the reference signal set are used for identifying the candidate beams for recovery. The reference signal set is called q.sub.1, q.sub.1,0 or q.sub.1,1. Wherein, refer to Embodiment 1 for methods for determining q.sub.1, q.sub.1,0 or q.sub.1,1.

[0107] The following methods can help the terminal device to determine whether to monitor the reference signal set (q.sub.1, q.sub.1,0 or q.sub.1,1) corresponding to the indication information based on at least one of the serving cell, the bandwidth part, the cell physical layer identity and the transmission and reception point corresponding to the indication information.

[0108] Optionally, the above indication information is related to network energy-saving. Specifically, the indication information may be used to inform the terminal device whether the base station device is in a network energy-saving mode on at least one of the serving cell, the bandwidth part, the cell physical layer identity and the transmission and reception point indicated by the indication information. If a first information indicates that it is not in the network energy-saving

mode, the terminal device monitors the reference signal set on the corresponding serving cell, the bandwidth part, the cell physical layer identity and the transmission and reception point; if the first information indicates that it is in the network energy-saving mode, the terminal device does not monitor the reference signal set on the corresponding serving cell, the bandwidth part, the cell physical layer identity and the transmission and reception point.

[0109] Optionally, the above indication information may be UE-specific information, group-common information or cell-common information.

[0110] In the following examples, take the indication information being the first information as an example.

Example 1 (Service Cell)

[0111] The first information is related to the serving cell. Specifically, the first information is related to the serving cell in the following methods:

Method 1

[0112] The first information corresponds to an SCell. Specifically, according to the first information, the terminal device is not expected to perform candidate beam detection (according to q.sub.1, q.sub.1,0 or q.sub.1,1) in the SCell (for example, all SCells). Or, the terminal device is not expected to perform candidate beam detection (according to q.sub.1, q.sub.1,0 or q.sub.1,1) in the activated BWP (DL BWP) corresponding to the SCell (for example, all SCells).

[0113] Advantageous effects: according to the above method, it can be determined that the terminal device is not expected (or expected) to monitor the reference signal set for candidate beam detection in the SCell. The terminal device does not monitor the reference signal set in the SCell, which can save energy.

Method 2

[0114] The terminal device determines a serving cell ID according to the first information (for example, the first information includes one or more serving cell IDs). Specifically, according to the first information, the terminal device is not expected to perform candidate beam detection (according to q.sub.1, q.sub.1,0 or q.sub.1,1) in the serving cell indicated by the first information (the serving cell of which serving cell ID is equal to the serving cell ID indicated by the first information). In other words, the terminal device is not expected to perform candidate beam detection (according to q.sub.1, q.sub.1,0 or q.sub.1,1) in the service cell in network energy-saving. Or, the terminal device is not expected to perform candidate beam detection (according to q.sub.1, q.sub.1,0 or q.sub.1,1) in the activated BWP (DL BWP) corresponding to the serving cell indicated by the first information.

[0115] Advantageous effects: according to the above method, it can be determined that the terminal device is not expected (or expected) to monitor the reference signal set for reference beam detection in the cells indicated by the base station. The terminal does not monitor the reference signal set in these service cells, which can save energy.

Method 3

[0116] The first information corresponds to an SCell (secondary cell) ID. Specifically, the terminal device is not expected to perform candidate beam detection (according to q.sub.1, q.sub.1,0 or q.sub.1,1) in the SCell indicated by the first information. Or, the terminal device is not expected to perform candidate beam detection (according to q.sub.1, q.sub.1,0 or q.sub.1,1) in the activated BWP (DL BWP) corresponding to the SCell indicated by the first information.

Example 2 (BWP)

[0117] The first information is related to a BWP. Specifically, the first information is related to the BWP in the following methods:

Method 1

[0118] The first information indicates BWP information (BWP ID), which corresponds to a PCell. Specifically, the terminal device is not expected to perform candidate beam detection (according to q.sub.1, q.sub.1,0 or q.sub.1,1) in the BWP in the PCell indicated by the first information (the ID of

the activated BWP in the PCell is the same as the BWP ID indicated by the first information).

Method 2

[0119] The first information indicates serving cell information (serving cell ID or SCell ID) and corresponding BWP information (BWP ID). Specifically, the terminal device is not expected to perform candidate beam detection (according to q.sub.1 or q.sub.1,0 and q.sub.1,1) in the corresponding BWP in the serving cell indicated by the first information (the ID of the corresponding activated BWP is the same as the BWP ID indicated by the first information).

[0120] Optionally, in the above method, the terminal device being not expected to perform candidate beam detection in a BWP can be further understood as the terminal device being not expected to perform candidate beam detection (according to q.sub.1 or q.sub.1,0 and q.sub.1,1) in a BWP and/or the terminal device being not expected to perform candidate beam detection on a resource implicitly configured for a BWP.

[0121] Advantageous effects: according to the above method, it can be determined that the terminal device is not expected (or expected) to monitor the reference signal set for candidate beam detection in the BWPs corresponding to the indication of the base station. The terminal does not monitor the reference signal set in these BWPs, which can save energy.

Example 3 (PCI)

[0122] The first information is related to a PCI. Specifically, the first information indicates PCI information (one or more PCIs). Specifically, the terminal device is not expected to perform (candidate beam) detection on the SSB corresponding to the above PCI information. Or, the terminal device is not expected to perform candidate beam detection on the reference signal set (q.sub.1,0 or q.sub.1,1) corresponding to the PCI information;

[0123] Optionally, the reference signal set includes the SSB related to the PCI information.

[0124] Optionally, the above PCI is different from physCellId in ServingCellConfigCommon.

[0125] Advantageous effects: according to the above method, it can be determined that the terminal device is not expected (or expected) to monitor the reference signal set for candidate beam detection on the PCIs corresponding to the indication of the base station. The terminal does not monitor the reference signal set corresponding to these PCI, which can save energy.

Example 4 (Transmission and Reception Point (TRP))

[0126] The first information is used to indicate whether the terminal device performs candidate beam detection according to the reference signal set (q.sub.0,0 and/or q.sub.0,1). Optionally, this information is a TRP switching indication. The specific methods are as follows:

Method 1 (Switching q.SUB.1,1.)

[0127] The terminal determines whether it is expected to monitor q.sub.1,1 according to the first information. Specifically, the first information includes one information bit.

[0128] When the information bit is 0/1, the terminal device monitors q.sub.1,1; when the information bit is 1/0, the terminal device is not expected to monitor q.sub.1,1.

Method 2 (Switching q.SUB.1,0 .and q.SUB.1,1 .Respectively)

[0129] The terminal determines whether it is expected to monitor q.sub.1,0 and q.sub.1,1 respectively according to the first information. Specifically, the first information includes two information bits.

[0130] When the first information bit is 0/1, the terminal device monitors q.sub.1,0; when the first information bit is 1/0, the terminal device is not expected to monitor q.sub.1,0.

[0131] When the second information bit is 0/1, the terminal device monitors q.sub.1,1; when the second information bit is 1/0, the terminal device is not expected to monitor q.sub.1,1.

[0132] Optionally, in the above methods, a cell or serving cell is activated (not deactivated).

[0133] In this embodiment, the terminal device being not expected to perform the candidate beam detection according to q.sub.1 or q.sub.1,0 and q.sub.1,1 in a cell can be equivalently understood as the terminal device being not expected to perform the candidate beam detection in a cell and is not expected to perform the candidate beam detection on a resource implicitly configured for the cell.

[0134] In addition, it should be noted that different examples in the above embodiment can be combined arbitrarily.

[0135] In addition, it should be noted that the above different embodiments can be combined arbitrarily. For example, Embodiment 1 and Embodiment 2 can be combined, that is, based on the indication information, determining whether to assess radio link quality according to the reference signal set on the first time domain resource comprises: determining the first time domain resource based on the indication information; and on the first time domain resource, determining whether to perform candidate beam detection according to the reference signal set based on at least one of the serving cell, the bandwidth part, the cell physical layer identity and the transmission and reception point corresponding to the indication information.

Advantageous Effects of this Embodiment

[0136] The methods provided in this embodiment can improve the reception performance of the terminal device. More specifically, the methods provided by the disclosure can improve the performance of the terminal device in beam recovery (ensuring the reliability of the terminal device); in addition, these method can also reduce the energy consumption of the terminal device by reducing/stopping the measurement of the reference signals.

Embodiment 3

[0137] A UE receives indication information from a base station; determines a second time domain resource based on the indication information; and provides an index of a reference signal to a higher layer, wherein when a time domain resource related to the index of the reference signal overlaps with the second time domain resource, the index of the reference signal is from a second reference signal set; and/or when the time domain resource related to the index of the reference signal does not overlap with the second time domain resource, the index of the reference signal is from a first reference signal set.

[0138] Optionally, the above indication information is related to network energy-saving.

Specifically, the indication information may be used to inform the terminal device whether the base station device is in a network energy-saving mode on the second time domain resource.

[0139] Optionally, the above indication information may be UE-specific information, group-common information or cell-common information.

[0140] Optionally, the second time domain resource is determined according to the indication information. The specific methods can be one of the followings:

Method 1

[0141] The starting and/or ending of the second time domain resource is determined by the indication information. That is, the terminal device determines a time domain resource (time period, that is, the starting and ending of the time domain resource) according to a first information. In addition, refer to Embodiment 1 for the description of the unit of the second time domain resource.

Method 2

[0142] A time domain position of the second time domain resource is determined by a time domain position of a channel or signal carrying the indication information. Optionally, the time domain position of the second time domain resource is before the channel or signal carrying the indication information; optionally, the time domain position of the second time domain resource overlaps with the channel or signal carrying the indication information; optionally, the second time domain resource information refers to a time domain resource after the transmission or reception of a channel or signal related to the first information, which is taken as an example.

[0143] Optionally, the above second time domain resource is a time domain resource after the reception of a channel or signal (PDCCH, PDSCH, etc.) related to the first information. For another example, the second time domain resource is a time domain resource after the reception of a channel or signal (PUCCH or PUSCH) carrying feedback information (HARQ-ACK information) for the channel or signal (PDSCH, etc.) related to the first information. For another example, the

second time domain resource is a time domain resource after a time period after the reception of the channel or signal (PDCCH, PDSCH, etc.) related to the first information. For another example, the second time domain resource is a time domain resource after a time period after the reception of the channel or signal (PUCCH or PUSCH) carrying the feedback information (HARQ-ACK information) for the channel or signal (PDSCH, etc.) related to the first information. Optionally, the time period is the time for the terminal device to process (interpret) the first information. Optionally, the time unit corresponding to the time period is as described with reference to the above examples.

[0144] Optionally, a L1-RSRP measurement corresponding to the index of the reference signal is greater than or equal to a threshold. For example, the threshold is $Q_{\text{sub.in,LR}}$.

[0145] Optionally, providing the index of the reference signal to the higher layer can be understood as the physical layer of the terminal device providing the index of the reference signal to the higher layer (for example, MAC layer) of the terminal device.

[0146] Optionally, the time domain resource related to the index of the reference signal can be understood as a measurement time domain resource (measurement window) corresponding to the index of the reference signal. Optionally, the time domain resource corresponding to the index of the reference signal is before the terminal device providing the index of the reference signal to the higher layer of the terminal device.

[0147] Optionally, when the time domain resource related to the index of the reference signal overlaps with the second time domain resource, the index of the reference signal is from the second reference signal set; and/or when the time domain resource related to the index of the reference signal does not overlap with the second time domain resource, the index of the reference signal is from the first reference signal set can be understood as one or a combination of the following methods:

Method 1

[0148] When the time domain resource (measurement window) corresponding to the index of the reference signal overlaps with the time period corresponding to the second time domain resource, the index of the reference signal is from the second reference signal set;

[0149] When the time domain resource (measurement window) corresponding to the index of the reference signal does not overlap with the time period corresponding to the second time domain resource, the index of the reference signal is from the first reference signal set;

Method 2

[0150] When the time domain resource (measurement window) corresponding to the index of the reference signal is after the time domain starting point corresponding to the second time domain resource, the index of the reference signal is from the second reference signal set;

[0151] When the time domain resource (measurement window) corresponding to the index of the reference signal is before the time domain starting point corresponding to the second time domain resource, the index of the reference signal is from the first reference signal set;

[0152] In this method, overlap can be understood as full overlap or partial overlap.

[0153] Advantageous effect: it can be ensured that under the condition that the measurement resource corresponding to the reference signal is in (or partially in) the time domain resource of network energy-saving, the index of the reference signal is reported by using the candidate beam reference signal set (the second reference signal set) associated with network energy-saving.

[0154] Optionally, reference signals in the first reference signal set are used for candidate beam detection. The reference signal set is called $q_{\text{sub.1}}$, $q_{\text{sub.1},0}$ or $q_{\text{sub.1},1}$. Wherein, refer to Embodiment 1 for the methods for determining $q_{\text{sub.1}}$, $q_{\text{sub.1},0}$ or $q_{\text{sub.1},1}$.

[0155] Optionally, reference signals in the second reference signal set are used for candidate beam detection. The reference signal set is called $q_{\text{sub.1,PS}}$, $q_{\text{sub.1},0,PS}$ or $q_{\text{sub.1},1,PS}$. The methods for determining the reference signal set are as follows:

Method 1

[0156] The reference signal set is indicated by the base station. E.g., explicit indication (RRC, MAC-CE or DCI signaling). Specifically, the base station indicates a reference signal ID corresponding to the reference signal set.

Method 2

[0157] The reference signal set is determined according to a first reference signal index set.

Method 3

[0158] The reference signal set is determined according to a reference signal corresponding to a TCI state of a CORESET. Specifically, the CORESET is used for the terminal device to monitor a PDCCH.

[0159] The above method 2, that is, the second reference signal set being determined according to the first reference signal set has further implementations. In these implementations, the terminal device receives second information:

Implementation 1

[0160] The second information corresponds to (or includes) the indication of a first reference signal (e.g., SSB ID, CSI-RS ID). The second reference signal set is determined according to the reference signal in the first reference signal set that is different from (or the same as) the first reference signal.

Implementation 2

[0161] The second information corresponds to (or includes) the indication of the first reference signal (e.g., SSB ID, CSI-RS ID). The second reference signal set is determined according to the reference signal in the first reference signal set that is not co-located (or quasi-co-located, QCLed) with the first reference signal.

Implementation 3

[0162] The second information corresponds to (or includes) the indication of a first reference signal type (e.g., SSB, CSI-RS). The second reference signal set is determined according to the reference signal in the first reference signal set with a different type from (or with a same type as) the first reference signal type.

Implementation 4

[0163] The second information corresponds to (or includes) an indication related to a SFN (for example, switching indication of the SFN). According to the indication information, the second reference signal set is determined according to the first reference signal set, and if the first reference signal set is related to a CORESET corresponding to two activated TCI states, the second reference signal set is related to one of the two TCI states (more specifically, the second reference signal set includes the first TCI of the two TCI states). Or, the second reference signal set does not include the reference signal corresponding to one of the two TCI states (more specifically, the second reference signal set does not include the reference signal corresponding to the second TCI state of the two TCI states).

[0164] Optionally, the second reference signal set corresponds to the first reference signal set one by one. For example, q.sub.1 corresponds to q.sub.1,PS; q.sub.1,0 corresponds to q.sub.1,0,PS; q.sub.1,1 corresponds to q.sub.1,1,PS. The specific methods are as follows:

Method 1

[0165] The first reference signal set and the second reference signal set correspond to a same BWP and/or serving cell.

Method 2

[0166] The first reference signal set and the second reference signal set correspond to a same PCI.

Method 3

[0167] The first reference signal set and the second reference signal set correspond to a same CORESETPoolIndex. Specifically, these two reference signal sets are determined according to a TCI state of a CORESET related to CORESETPoolIndex=1; or, these two reference signal sets are determined according to a TCI state of a CORESET related to CORESETPoolIndex=0 (without

configured CORESETPoolIndex).

Method 4

[0168] The first reference signal set and the second reference signal set correspond to a same beam failure detection reference signal set (for example, $q_{\text{sub.0}}$, $q_{\text{sub.0,0}}$ or $q_{\text{sub.0,1}}$).

[0169] Advantageous effects: according to the above methods, (reference signals corresponding to) the second reference signal set can be determined by the first reference signal. The advantage of these methods is that the second reference signal set is indicated by implicit indication, which saves signaling overhead.

Advantageous Effects of this Embodiment

[0170] The methods provided in this embodiment can improve the reception performance of the terminal device. More specifically, the methods provided by the disclosure can improve the performance of the terminal device in beam recovery (ensuring the reliability of the terminal device).

Embodiment 4

[0171] A user equipment receives indication information from a base station; and determines a reference signal set based on the indication information; wherein the reference signal set is a first reference signal set or a second reference signal set; the (physical layer of) user equipment provides an index of a reference signal to a higher layer, the index of the reference signal is from the reference signal set, and a L1-RSRP measurement corresponding to the reference signal is greater than or equal to a threshold (e.g., $Q_{\text{sub.in,LR}}$).

[0172] For the above description, L1-RSRP can be equivalently replaced with L1-SINR; the higher layer can be understood as the MAC layer or the MAC layer of the terminal device.

[0173] Optionally, the reference signal set is one of the first reference signal set and the second reference signal set.

[0174] Optionally, reference signals in the first reference signal set are used for candidate beam detection. The reference signal set is called $q_{\text{sub.1}}$, $q_{\text{sub.1,0}}$ or $q_{\text{sub.1,1}}$. Wherein, refer to Embodiment 1 for the methods for determining $q_{\text{sub.1}}$, $q_{\text{sub.1,0}}$ or $q_{\text{sub.1,1}}$.

[0175] Optionally, reference signals in the second reference signal set are used for candidate beam detection. The reference signal set is called $q_{\text{sub.1,PS}}$, $q_{\text{sub.1,0,PS}}$ or $q_{\text{sub.1,1,PS}}$. The methods for determining the reference signal set are as follows:

Method 1

[0176] The reference signal set is indicated by the base station. E.g., explicit indication (RRC, MAC-CE or DCI signaling). Specifically, the base station indicates a reference signal ID corresponding to the reference signal set.

Method 2

[0177] The reference signal set is determined according to a first reference signal set.

Method 3

[0178] The reference signal set is determined according to a reference signal corresponding to a TCI state of a CORESET. Specifically, the CORESET is used for the terminal device to monitor a PDCCH.

[0179] The above method 2, that is, the second reference signal set being determined according to the first reference signal set has further implementations. In these implementations, the terminal device receives second information:

Implementation 1

[0180] The second information corresponds to (or includes) the indication of a first reference signal (for example, SSB ID, CSI-RS ID). The second reference signal set is determined according to the reference signal in the first reference signal set that is different from (or the same as) the first reference signal.

Implementation 2

[0181] The second information corresponds to (or includes) the indication of the first reference

signal (for example, SSB ID, CSI-RS ID). The second reference signal set is determined according to the reference signal in the first reference signal set that is not co-located (or quasi-co-located, QCLed) with the first reference signal.

Implementation 3

[0182] The second information corresponds to (or includes) the indication of a first reference signal type (e.g., SSB, CSI-RS). The second reference signal set is determined according to the reference signals in the first reference signal set with a different type from (or a same type as) the first reference signal type.

Implementation 4

[0183] The second information corresponds to (or includes) indication related to a SFN (for example, switching indication of the SFN). According to the indication information, the second reference signal set is determined according to the first reference signal set, and if the first reference signal set is related to a CORESET corresponding to two activated TCI states, the second reference signal set is related to one of the two TCI states (more specifically, the second reference signal set includes the first TCI of the two TCI states). Or, the second reference signal set does not include the reference signal corresponding to one of the two TCI states (more specifically, the second reference signal set does not include the reference signal corresponding to the second TCI state of the two TCI states).

[0184] Optionally, the second reference signal set corresponds to the first reference signal set one by one. For example, q.sub.1 corresponds to q.sub.1,PS; q.sub.1,0 corresponds to q.sub.1,0,PS; q.sub.1,1 corresponds to q.sub.1,1,PS. The specific methods are as follows:

Method 1

[0185] The first reference signal set and the second reference signal set correspond to a same BWP and/or serving cell.

Method 2

[0186] The first reference signal set and the second reference signal set correspond to a same PCI.

Method 3

[0187] The first reference signal set and the second reference signal set correspond to a same CORESETPoolIndex. Specifically, these two reference signal sets are determined according to a TCI state of a CORESET related to CORESETPoolIndex=1; or, these two reference signal sets are determined according to a TCI state of a CORESET related to CORESETPoolIndex=0 (without configured CORESETPoolIndex).

Method 4

[0188] The first reference signal set and the second reference signal set correspond to a same beam failure detection reference signal set (for example, q.sub.0, q.sub.0,0 or q.sub.0,1).

[0189] The following methods can help the terminal device to determine the reference signal set based on at least one of the serving cell, the bandwidth part, the cell physical layer identity and the transmission and reception point corresponding to the indication information. That is, the reference signal set is determined as the first reference signal set (q.sub.1, q.sub.1,0 or q.sub.1,1); or determined as the second reference signal set (q.sub.1,PS, q.sub.1,0,PS or q.sub.1,1,PS).

[0190] Optionally, the above indication information is related to network energy-saving.

Specifically, the indication information may be used to inform the terminal device whether the base station device is in a network energy-saving mode on at least one of the serving cell, the bandwidth part, the cell physical layer identity and the transmission and reception point indicated by the indication information.

[0191] Optionally, the above indication information may be UE-specific information, group-common information or cell-common information.

[0192] In the following examples, methods for determining the reference signal set by the terminal device is described by taking the indication information being a first information as an example.

Example 1 (Service Cell)

[0193] The first information is related to a serving cell. Specifically, the first information is related to the serving cell in the following methods:

Method 1

[0194] The first information corresponds to an SCell. Specifically, according to the first information, the terminal device determines the first reference signal set or the second reference signal set in the SCell. For example, the first information corresponds to the SCell; when the terminal device receives the indication, the reference signal set is determined as the second reference signal set (in the corresponding activated BWP) in the SCell. For example, the first information corresponds to the SCell; and the information also includes one information bit, when the bit is 0/1, when the terminal device receives the indication, the reference signal set is determined to be based on the second reference signal set (in corresponding activated BWP) in the SCell; when this bit is 1/0, when the terminal device receives the indication, the reference signal set is determined to be based on the first reference signal set (in corresponding activated BWP) in the SCell.

Method 2

[0195] The device determines a serving cell ID according to the first information (for example, the first information includes one or more serving cell IDs). Specifically, according to the first information, the terminal device determines the first reference signal set or the second reference signal set in the corresponding serving cell. For example, the first information corresponds to a serving cell #1 and a serving cell #2; when the terminal device receives the indication, the reference signal set is determined as the second reference signal set in the serving cell #1 and the serving cell #2. For another example, the first information corresponds to the serving cell #1 and the serving cell #2; and the information also includes one information bit, when the bit is 0/1, when the terminal device receives the indication, the reference signal set is determined to be based on the second reference signal set in the serving cell #1 and the serving cell #2; when the bit is 1/0, when the terminal device receives the indication, the reference signal set is determined to be based on the first reference signal set in the serving cell #1 and the serving cell #2.

Method 3

[0196] The first information corresponds to an SCell (secondary cell) ID. The specific method is similar to the Method 2, by replacing the cell ID with SCell ID.

Example 2 (BWP)

[0197] The first information is related to a BWP. Specifically, the first information is related to the BWP in the following methods:

Method 1

[0198] The first information indicates BWP information (BWP ID), which corresponds to a PCell. Specifically, according to the first information, the terminal device determines the first reference signal set or the second reference signal set in the BWP indicated by the first information in the PCell (which can also be understood as when the ID of the BWP activated in the PCell is the same as the BWP ID indicated by the first information). For example, the first information corresponds to a BWP #1; when the terminal device receives the indication information, the reference signal set is determined as the second reference signal set in the BWP #1 of the PCell. For another example, the first information corresponds to the BWP #1, and the information further includes one information bit. When the bit is 0, the terminal device receives the indication information, and the reference signal set is determined as the second reference signal set in the BWP #1 of the PCell. In the same case, when the bit is 1, the terminal device receives the indication information, and the reference signal set is determined as the first reference signal set in the BWP #1 of the PCell.

Method 2

[0199] The first information indicates serving cell information (serving cell ID or SCell ID) and corresponding BWP information (BWP ID). Similar to Method 1, by only replacing the description of the PCell in Method 1 with the first information indicating the serving cell.

Example 3 (PCI)

[0200] The first information is related to a PCI. Specifically, the first information indicates PCI information (one or more PCIs). Specifically,

Method 1

[0201] The terminal determines that the reference signal set is a reference signal set unrelated to the PCI information. For example, the PCI corresponds to q.sub.1,1 and/or q.sub.1,1,PS (that is, q.sub.1,1 and/or q.sub.1,1,PS includes an SSB of the PCI); the terminal device determines that the reference signal set is q.sub.1,0 and/or q.sub.1,0,PS.

Method 2

[0202] The terminal determines that the reference signal set is a reference signal set related to the PCI information. For example, the PCI corresponds to q.sub.1,1 and/or q.sub.1,1,PS (that is, q.sub.1,1 and/or q.sub.1,1,PS includes an SSB of the PCI); the terminal device determines that the reference signal set is q.sub.1,1 and/or q.sub.1,1,PS.

[0203] Optionally, the PCI is different from the physical cell ID (physCellId) in the cell-common configuration information (for example, ServingCellConfigCommon) corresponding to the terminal device.

Example 4 (TRP)

[0204] The first information is used to indicate the terminal device to determine the first reference signal set (q.sub.1,0 and/or q.sub.1,1) or the second reference signal set (q.sub.1,0,PS and/or q.sub.1,1,PS). The specific methods are as follows:

Method 1 (selecting q.SUB.1,1 .and q.SUB.1,1,PS.)

[0205] The terminal determines whether the reference signal set is q.sub.1,1 or q.sub.1,1,PS according to the first information. For example, when the terminal receives the first information, the terminal device determines that the reference signal set is q.sub.1,1,PS. For example, the first information includes one information bit. When the terminal receives the first information and the information bit is 0/1, the terminal device determines that the reference signal set is q.sub.1,1; when the terminal receives the first information and the information bit is 1/0, it determines that the reference signal set is q.sub.1,1,PS.

Method 2 (Selecting [q.SUB.1,0 .and q.SUB.1,0,PS.], [q.SUB.1,1 .and q.SUB.1,1,PS.]

Respectively)

[0206] According to the first information, the terminal determines whether the reference signal set is q.sub.1,0 or q.sub.1,0,PS, and q.sub.1,1 or q.sub.1,1,PS, respectively. Specifically, the first information includes two information bits.

[0207] When the first information bit is 0/1, the terminal device determines that the reference signal set is q.sub.1,0; when the first information bit is 1/0, the terminal device determines that the reference signal set is q.sub.1,0,PS.

[0208] When the second information bit is 0/1, the terminal device determines that the reference signal set is q.sub.1,1; when the second information bit is 1/0, the terminal device determines that the reference signal set is q.sub.1,1,PS.

[0209] Optionally, in the above methods, a cell or the serving cell is activated (not deactivated).

[0210] In addition, it should be noted that different examples in the above embodiment can be combined arbitrarily.

[0211] In addition, it should be noted that the above different embodiments can be combined arbitrarily. For example, Embodiment 3 and Embodiment 4 can be combined.

Advantageous Effects of this Embodiment

[0212] The methods provided in this embodiment can improve the reception performance of the terminal device. More specifically, the methods provided by the disclosure can improve the performance of the terminal device in beam recovery (ensuring the reliability of the terminal device).

Embodiment 5

[0213] A user equipment receives indication information from a base station; determines a second time domain resource based on the indication information; and provides an index of a reference signal to the base station, wherein when a time domain resource related to the index of the reference signal overlaps with the second time domain resource, determines that the index of the reference signal is from a second reference signal set; and/or when the time domain resource related to the index of the reference signal does not overlap with the second time domain resource, the index of the reference signal is from a first reference signal set.

[0214] Optionally, the user equipment also receives a signal or channel according to the same QCL parameter as the QCL parameter corresponding to the index of the reference signal. Specifically, the signal or channel may be one of a PDSCH and a CSI-RS.

[0215] Optionally, the user equipment also transmits a signal or channel according to the same spatial filter as the spatial filter corresponding to the index of the reference signal. Optionally, the signal or channel is one of a PUCCH, a PUSCH and an SRS.

[0216] Optionally, the user equipment and/or the base station also monitors a signal or channel according to the same QCL parameter as the QCL parameter corresponding to the index of the reference signal. Optionally, the signal or channel is one of a PUCCH, a PUSCH and an SRS.

[0217] Optionally, the user equipment also monitors a signal or channel in a window according to the same QCL parameter as the QCL parameter corresponding to the index of the reference signal. Optionally, this window (time domain window) is configured by a RRC parameter (for example, BeamfailureRecovery Config); optionally, the window corresponds to a PRACH transmission, which precedes the window; optionally, the signal or channel is a PDCCH or a PDCCH in a CORESET.

[0218] Optionally, the index of the reference signal information (which may be called q.sub.new) is carried by one of a PUCCH, a PUSCH (msg3 PUSCH), a MAC-CE or a PRACH.

[0219] Optionally, the above indication information is related to network energy-saving.

Specifically, the indication information may be used to inform the terminal device whether the base station device is in a network energy-saving mode on the second time domain resource.

[0220] Optionally, the above indication information may be UE-specific information, group-common information or cell-common information.

[0221] Optionally, the second time domain resource is determined according to the indication information. The specific methods can be one of the followings:

Method 1

[0222] The starting and/or ending of the second time domain resource is determined by the indication information. That is, the terminal device determines a time domain resource (time period, that is, the starting and ending of the time domain resource) according to a first information. In addition, refer to Embodiment 1 for the description of the unit of the second time domain resource.

Method 2

[0223] A time domain position of the second time domain resource is determined by a time domain position of a channel or signal carrying the indication information. Optionally, the time domain position of the second time domain resource is before the channel or signal carrying the indication information; optionally, the time domain position of the second time domain resource overlaps with the channel or signal carrying the indication information; optionally, the second time domain resource information refers to a time domain resource after the transmission or reception of a channel or signal related to the first information, which is taken as an example.

[0224] Optionally, the above second time domain resource is a time domain resource after the reception of the channel or signal (PDCCH, PDSCH, etc.) related to the first information. For another example, the second time domain resource is the time domain resource after the reception of a channel or signal (PUCCH or PUSCH) carrying feedback information (HARQ-ACK information) for the channel or signal (PDSCH, etc.) related to the first information. For another

example, the second time domain resource is a time domain resource after a time period after the reception of the channel or signal (PDCCH, PDSCH, etc.) related to the first information. For another example, the second time domain resource is a time domain resource after a time period after the reception of the channel or signal (PUCCH or PUSCH) carrying the feedback information (HARQ-ACK information) for the channel or signal (PDSCH, etc.) related to the first information. Optionally, the time period is the time for the terminal device to process (interpret) the first information. Optionally, the time unit corresponding to the time period is as described with reference to the above examples.

[0225] Optionally, the time domain resource related to the index of the reference signal can be understood as the time domain resource of the signal or channel carrying the index of the reference signal. E.g., the time domain resource corresponding to a PUSCH/PUCCH carrying the index of the reference signal.

[0226] Optionally, the time domain resource related to the index of the reference signal can also be understood as the time domain resource of the signal related to the index of the reference signal, for example, the time domain resource of the PRACH transmission related to the index of the reference signal.

[0227] Optionally, the time domain resource related to the index of the reference signal can also be understood as the time domain resource after the signal or channel related to the index of the reference signal. Further, the time domain resource may be a window (for example, the window is configured by configuration information related to beam failure recovery). For example, the time domain resource related to the index of the reference signal refers to a window configured by the configuration information related to beam failure recovery (e.g., BeamFailureRecoveryConfig) after the PRACH transmission related to the index of the reference signal.

[0228] Optionally, when the time domain resource related to the index of the reference signal overlaps with the second time domain resource, the index of the reference signal is from the second reference signal set; and/or when the time domain resource related to the index of the reference signal does not overlap with the second time domain resource, the index of the reference signal is from the first reference signal set can be understood as one or a combination of the following methods:

Method 1

[0229] When the time domain resource corresponding to the index of the reference signal overlaps with the time period corresponding to the second time domain resource, the index of the reference signal is from the second reference signal set;

[0230] When the time domain resource corresponding to the index of the reference signal does not overlap with the time period corresponding to the second time domain resource, the index of the reference signal is from the first reference signal set;

Method 2

[0231] When the time domain resource corresponding to the index of the reference signal is after the time domain starting point corresponding to the second time domain resource, the index of the reference signal is from the second reference signal set;

[0232] When the time domain resource corresponding to the index of the reference signal is before the time domain starting point corresponding to the second time domain resource, the index of the reference signal is from the first reference signal set;

[0233] In this method, overlap can be understood as full overlap or partial overlap.

[0234] Advantageous effect: according to the above methods, it can be ensured that the index of the reference signal is reported by using the candidate beam reference signal set (the second reference signal set) specific to network energy-saving under the condition that the measurement resource corresponding to the reference signals is in (or partially in) the time domain resource of network energy-saving.

[0235] Optionally, reference signals in the first reference signal set are used for candidate beam

detection. The reference signal set is called q.sub.1, q.sub.1,0 or q.sub.1,1. Wherein, refer to Embodiment 1 for the methods for determining q.sub.1, q.sub.1,0 or q.sub.1,1.

[0236] Optionally, reference signals in the second reference signal set are used for candidate beam detection. The reference signal set is called q.sub.1,PS, q.sub.1,0,PS or q.sub.1,1,PS. The methods for determining the reference signal set are as follows:

Method 1

[0237] The reference signal set is indicated by the base station. E.g., explicit indication (RRC, MAC-CE or DCI signaling). Specifically, the base station indicates a reference signal ID corresponding to the reference signal set.

Method 2

[0238] The reference signal set is determined according to a first reference signal set.

Method 3

[0239] The reference signal set is determined according to a reference signal corresponding to a TCI state of a CORESET. Specifically, the CORESET is used for the terminal device to monitor a PDCCH.

[0240] The above method 2, that is, the second reference signal set being determined according to the first reference signal set has further implementations. In these implementations, the terminal device receives second information:

Implementation 1

[0241] The second information corresponds to (or includes) the indication of a first reference signal (e.g., SSB ID, CSI-RS ID). The second reference signal set is determined according to the reference signal in the first reference signal set that is different from (or the same as) the first reference signal.

Implementation 2

[0242] The second information corresponds to (or includes) the indication of the first reference signal (e.g., SSB ID, CSI-RS ID). The second reference signal set is determined according to the reference signal in the first reference signal set that is not co-located (or quasi-co-located, QCLed) with the first reference signal.

Implementation 3

[0243] The second information corresponds to (or includes) the indication of a first reference signal type (e.g., SSB, CSI-RS). The second reference signal set is determined according to the reference signal in the first reference signal set with a different type from (or with a same type as) the first reference signal type.

Implementation 4

[0244] The second information corresponds to (or includes) an indication related to a SFN (for example, switching indication of the SFN). According to the indication information, the second reference signal set is determined according to the first reference signal set, and if the first reference signal set is related to a CORESET corresponding to two activated TCI states, the second reference signal set is related to one of the two TCI states (more specifically, the second reference signal set includes the first TCI of the two TCI states). Or, the second reference signal set does not include the reference signal corresponding to one of the two TCI states (more specifically, the second reference signal set does not include the reference signal corresponding to the second TCI state of the two TCI states).

[0245] Optionally, the second reference signal set corresponds to the first reference signal set one by one. For example, q.sub.1 corresponds to q.sub.1,PS; q.sub.1,0 corresponds to q.sub.1,0,PS; q.sub.1,1 corresponds to q.sub.1,1,PS. The specific methods are as follows:

Method 1

[0246] The first reference signal set and the second reference signal set correspond to a same BWP and/or serving cell.

Method 2

[0247] The first reference signal set and the second reference signal set correspond to a same PCI.

Method 3

[0248] The first reference signal set and the second reference signal set correspond to a same CORESETPoolIndex. Specifically, these two reference signal sets are determined according to a TCI state of a CORESET related to CORESETPoolIndex=1; or, these two reference signal sets are determined according to a TCI state of a CORESET related to CORESETPoolIndex=0 (without configured CORESETPoolIndex).

Method 4

[0249] The first reference signal set and the second reference signal set correspond to a same beam failure detection reference signal set (for example, q.sub.0, q.sub.0,0 or q.sub.0,1).

[0250] Advantageous effects: according to the above methods, (reference signals corresponding to) the second reference signal set can be determined by the first reference signal. The advantage of these methods are that the second reference signal set is indicated by implicit indication, which saves signaling overhead.

Advantageous Effects of this Embodiment

[0251] The methods provided in this embodiment can improve the reception performance of the terminal device. More specifically, the methods provided by the disclosure can improve the performance of the terminal device in beam recovery (ensuring the reliability of the terminal device).

Embodiment 6

[0252] A user equipment receives indication information from a base station; and determines a reference signal set based on the indication information; wherein the reference signal set is a first reference signal set or a second reference signal set; the user equipment provides an index of a reference signal to the base station, and the index of the reference signal is from the reference signal set.

[0253] Optionally, the user equipment also receives a signal or channel according to the same QCL parameter as the QCL parameter corresponding to the index of the reference signal. Specifically, the signal or channel may be one of a PDSCH and a CSI-RS.

[0254] Optionally, the user equipment also transmits a signal or channel according to the same spatial filter as the spatial filter corresponding to the index of the reference signal. Optionally, the signal or channel is one of a PUCCH, a PUSCH and an SRS.

[0255] Optionally, the user equipment and/or the base station also monitors a signal or channel according to the same QCL parameter as the QCL parameter corresponding to the index of the reference signal. Optionally, the signal or channel is one of a PUCCH, a PUSCH and an SRS.

[0256] Optionally, the user equipment also monitors a signal or channel in a window according to the same QCL parameter as the QCL parameter corresponding to the index of the reference signal. Optionally, this window (time domain window) is configured by a RRC parameter (for example, BeamfailureRecovery Config); optionally, the window corresponds to a PRACH transmission, which precedes the window; optionally, the signal or channel is a PDCCH or a PDCCH in a CORESET.

[0257] Optionally, the index of the reference signal information (which may be called q.sub.new) is carried by one of a PUCCH, a PUSCH (msg3 PUSCH), a MAC-CE or a PRACH.

[0258] Optionally, the reference signal set is one of the first reference signal set and the second reference signal set.

[0259] Optionally, reference signals in the first reference signal set are used for candidate beam detection. The reference signal set is called q.sub.1, q.sub.1,0 or q.sub.1,1. Wherein, refer to Embodiment 1 for the methods for determining q.sub.1, q.sub.1,0 or q.sub.1,1.

[0260] Optionally, reference signals in the second reference signal set are used for candidate beam detection. The reference signal set is called q.sub.1,PS, q.sub.1,0,PS or q.sub.1,1,PS. The methods for determining the reference signal set are as follows:

Method 1

[0261] The reference signal set is indicated by the base station. E.g., explicit indication (RRC, MAC-CE or DCI signaling). Specifically, the base station indicates a reference signal ID corresponding to the reference signal set.

Method 2

[0262] The reference signal set is determined according to a first reference signal set.

Method 3

[0263] The reference signal set is determined according to a reference signal corresponding to a TCI state of a CORESET. Specifically, the CORESET is used for the terminal device to monitor a PDCCH.

[0264] The above method 2, that is, the second reference signal set being determined according to the first reference signal set has further implementations. In these implementations, the terminal device receives second information:

Implementation 1

[0265] The second information corresponds to (or includes) the indication of a first reference signal (for example, SSB ID, CSI-RS ID). The second reference signal set is determined according to the reference signal in the first reference signal set that is different from (or the same as) the first reference signal.

Implementation 2

[0266] The second information corresponds to (or includes) the indication of the first reference signal (for example, SSB ID, CSI-RS ID). The second reference signal set is determined according to the reference signal in the first reference signal set that is not co-located (or quasi-co-located, QCLed) with the first reference signal.

Implementation 3

[0267] The second information corresponds to (or includes) the indication of a first reference signal type (e.g., SSB, CSI-RS). The second reference signal set is determined according to the reference signals in the first reference signal set with a different type from (or a same type as) the first reference signal type.

Implementation 4

[0268] The second information corresponds to (or includes) indication related to a SFN (for example, switching indication of the SFN). According to the indication information, the second reference signal set is determined according to the first reference signal set, and if the first reference signal set is related to a CORESET corresponding to two activated TCI states, the second reference signal set is related to one of the two TCI states (more specifically, the second reference signal set includes the first TCI of the two TCI states). Or, the second reference signal set does not include the reference signal corresponding to one of the two TCI states (more specifically, the second reference signal set does not include the reference signal corresponding to the second TCI state of the two TCI states).

[0269] Optionally, the second reference signal set corresponds to the first reference signal set one by one. For example, q.sub.1 corresponds to q.sub.1,PS; q.sub.1,0 corresponds to q.sub.1,0,PS; q.sub.1,1 corresponds to q.sub.1,1,PS. The specific methods are as follows:

Method 1

[0270] The first reference signal set and the second reference signal set correspond to a same BWP and/or serving cell.

Method 2

[0271] The first reference signal set and the second reference signal set correspond to a same PCI.

Method 3

[0272] The first reference signal set and the second reference signal set correspond to a same CORESETPoolIndex. Specifically, these two reference signal sets are determined according to a TCI state of a CORESET related to CORESETPoolIndex=1; or, these two reference signal sets are

determined according to a TCI state of a CORESET related to CORESETPoolIndex=0 (without configured CORESETPoolIndex).

Method 4

[0273] The first reference signal set and the second reference signal set correspond to a same beam failure detection reference signal set (for example, q.sub.0, q.sub.0,0 or q.sub.0,1).

[0274] The following methods can help the terminal device to determine the reference signal set based on at least one of the serving cell, the bandwidth part, the cell physical layer identity and the transmission and reception point corresponding to the indication information. That is, the reference signal set is determined as the first reference signal set (q.sub.1, q.sub.1,0 or q.sub.1,1); or determined as the second reference signal set (q.sub.1,PS, q.sub.1,0,PS or q.sub.1,1,PS).

[0275] Optionally, the above indication information is related to network energy-saving.

Specifically, the indication information may be used to inform the terminal device whether the base station device is in a network energy-saving mode on at least one of the serving cell, the bandwidth part, the cell physical layer identity and the transmission and reception point indicated by the indication information.

[0276] Optionally, the above indication information may be UE-specific information, group-common information or cell-common information.

[0277] In the following examples, methods for determining the reference signal set by the terminal device is described by taking the indication information being a first information as an example.

Example 1 (Service Cell)

[0278] The first information is related to a serving cell. Specifically, the first information is related to the serving cell in the following methods:

Method 1

[0279] The first information corresponds to an SCell. Specifically, according to the first information, the terminal device determines the first reference signal set or the second reference signal set in the SCell. For example, the first information corresponds to the SCell; when the terminal device receives the indication, the reference signal set is determined as the second reference signal set (in the corresponding activated BWP) in the SCell. For example, the first information corresponds to the SCell; and the information also includes one information bit, when the bit is 0/1, when the terminal device receives the indication, the reference signal set is determined to be based on the second reference signal set (in corresponding activated BWP) in the SCell; when this bit is 1/0, when the terminal device receives the indication, the reference signal set is determined to be based on the first reference signal set (in corresponding activated BWP) in the SCell.

Method 2

[0280] The device determines a serving cell ID according to the first information (for example, the first information includes one or more serving cell IDs). Specifically, according to the first information, the terminal device determines the first reference signal set or the second reference signal set in the corresponding serving cell. For example, the first information corresponds to a serving cell #1 and a serving cell #2; when the terminal device receives the indication, the reference signal set is determined as the second reference signal set in the serving cell #1 and the serving cell #2. For another example, the first information corresponds to the serving cell #1 and the serving cell #2; and the information also includes one information bit, when the bit is 0/1, when the terminal device receives the indication, the reference signal set is determined to be based on the second reference signal set in the serving cell #1 and the serving cell #2; when the bit is 1/0, when the terminal device receives the indication, the reference signal set is determined to be based on the first reference signal set in the serving cell #1 and the serving cell #2.

Method 3

[0281] The first information corresponds to an SCell (secondary cell) ID. The specific method is similar to the Method 2, by replacing the cell ID with SCell ID.

Example 2 (BWP)

[0282] The first information is related to a BWP. Specifically, the first information is related to the BWP in the following methods:

Method 1

[0283] The first information indicates BWP information (BWP ID), which corresponds to a PCell. Specifically, according to the first information, the terminal device determines the first reference signal set or the second reference signal set in the BWP indicated by the first information in the PCell (which can also be understood as when the ID of the BWP activated in the PCell is the same as the BWP ID indicated by the first information). For example, the first information corresponds to a BWP #1; when the terminal device receives the indication information, the reference signal set is determined as the second reference signal set in the BWP #1 of the PCell. For another example, the first information corresponds to the BWP #1, and the information further includes one information bit. When the bit is 0, the terminal device receives the indication information, and the reference signal set is determined as the second reference signal set in the BWP #1 of the PCell. In the same case, when the bit is 1, the terminal device receives the indication information, and the reference signal set is determined as the first reference signal set in the BWP #1 of the PCell.

Method 2

[0284] The first information indicates serving cell information (serving cell ID or SCell ID) and corresponding BWP information (BWP ID). Similar to Method 1, by only replacing the description of the PCell in Method 1 with the first information indicating the serving cell.

Example 3 (PCI)

[0285] The first information is related to a PCI. Specifically, the first information indicates PCI information (one or more PCIs). Specifically,

Method 1

[0286] The terminal determines that the reference signal set is a reference signal set unrelated to the PCI information. For example, the PCI corresponds to q.sub.1,1 and/or q.sub.1,1,PS (that is, q.sub.1,1 and/or q.sub.1,1,PS includes an SSB of the PCI); the terminal device determines that the reference signal set is q.sub.1,0 and/or q.sub.1,0,PS.

Method 2

[0287] The terminal determines that the reference signal set is a reference signal set related to the PCI information. For example, the PCI corresponds to q.sub.1,1 and/or q.sub.1,1,PS (that is, q.sub.1,1 and/or q.sub.1,1,PS includes an SSB of the PCI); the terminal device determines that the reference signal set is q.sub.1,1 and/or q.sub.1,1,PS.

[0288] Optionally, the PCI is different from the physical cell ID (physCellId) in the cell-common configuration information (for example, ServingCellConfigCommon) corresponding to the terminal device.

Example 4 (TRP)

[0289] The first information is used to indicate the terminal device to determine the first reference signal set (q.sub.1,0 and/or q.sub.1,1) or the second reference signal set (q.sub.1,0,PS and/or q.sub.1,1,PS). The specific methods are as follows:

Method 1 (selecting q.SUB.1,1 .and q.SUB.1,1,PS.)

[0290] The terminal determines whether the reference signal set is q.sub.1,1 or q.sub.1,1,PS according to the first information. For example, when the terminal receives the first information, the terminal device determines that the reference signal set is q.sub.1,1,PS. For example, the first information includes one information bit. When the terminal receives the first information and the information bit is 0/1, the terminal device determines that the reference signal set is q.sub.1,1; when the terminal receives the first information and the information bit is 1/0, it determines that the reference signal set is q.sub.1,1,PS.

Method 2 (Selecting [q.SUB.1,0 .and q.SUB.1,0,PS.], [q.SUB.1,1 .and q.SUB.1,1,PS.]

Respectively)

[0291] According to the first information, the terminal determines whether the reference signal set is q.sub.1,0 or q.sub.1,0,PS, and q.sub.1,1 or q.sub.1,1,PS, respectively. Specifically, the first information includes two information bits.

[0292] When the first information bit is 0/1, the terminal device determines that the reference signal set is q.sub.1,0; when the first information bit is 1/0, the terminal device determines that the reference signal set is q.sub.1,0,PS.

[0293] When the second information bit is 0/1, the terminal device determines that the reference signal set is q.sub.1,1; when the second information bit is 1/0, the terminal device determines that the reference signal set is q.sub.1,1,PS.

[0294] Optionally, in the above methods, a cell or the serving cell is activated (not deactivated).

[0295] In addition, it should be noted that different examples in the above embodiment can be combined arbitrarily.

Advantageous Effects of this Embodiment

[0296] The methods provided in this embodiment can improve the reception performance of the terminal device. More specifically, the methods provided by the disclosure can improve the performance of the terminal device in beam recovery (ensuring the reliability of the terminal device).

[0297] FIG. 4 illustrates a method **400** performed by a user equipment (UE) according to an embodiment of the disclosure. At **S410**, the UE receives indication information from a base station, and at **S420**, the UE determines whether to perform candidate beam detection according to a resource corresponding to a reference signal set based on the indication information.

[0298] FIG. 5 illustrates a method **500** performed by a UE according to an embodiment of the disclosure. At **S510**, the UE receives indication information from a base station, at **S520**, the UE determines a second time domain resource based on the indication information, and at **S530**, the physical layer of the UE provides an index of a reference signal to a higher layer, wherein when a time domain resource related to the index of the reference signal overlaps with the second time domain resource, the index of the reference signal is from a second reference signal set; and/or when the time domain resource related to the index of the reference signal does not overlap with the second time domain resource, the index of the reference signal is from a first reference signal set.

[0299] FIG. 6 illustrates a method **600** performed by a UE according to an embodiment of the disclosure. At **S610**, the UE receives indication information from a base station, at **S620**, the UE determines a second time domain resource based on the indication information, and at **S630**, the UE provides an index of a reference signal to the base station, wherein when a time domain resource related to the index of the reference signal overlaps with the second time domain resource, the index of the reference signal is from a second reference signal set; and/or when the time domain resource related to the index of the reference signal does not overlap with the second time domain resource, the index of the reference signal is from a first reference signal set.

[0300] FIG. 7 illustrates a method **700** performed by a base station according to an embodiment of the disclosure. At **S710**, the base station transmits indication information to a UE, which is used for the UE to perform at least one of the methods **400** to **600** described above.

[0301] In addition, for the above descriptions of methods **400** to **600** in FIGS. 4 to 6, the UE may receive configuration information from the base station, and the indication information is related to the configuration information; similarly, for the above description of the method **700** in FIG. 7, the base station may transmit configuration information to the UE, and the indication information is related to the configuration information.

[0302] FIG. 8 illustrates a user equipment (UE) **800** according to an embodiment of the disclosure. The UE **800** includes a transceiver **810** and a processor **820**, wherein the processor **820** is configured to perform the above-mentioned methods disclosed herein and executable by the UE.

[0303] FIG. 9 illustrates a base station **800** according to an embodiment of the disclosure. The base

station **800** includes a transceiver **910** and a processor **920**, wherein the processor **920** is configured to perform the above-mentioned method disclosed herein and executable by the base station.

[0304] According to the above description, it can be understood that q.sub.1,0 and q.sub.1,1 described herein are independent from each other, and the descriptions of q.sub.1,0 and q.sub.1,1 can be equivalently replaced by the descriptions of q.sub.1.

[0305] The term “reference signal set” used herein can also be broadly understood as “reference signal index set”, that is, “monitoring/according to a reference signal set” described herein can be understood as “monitoring/according to a resource corresponding to a reference signal index set”, “reference signal” can be understood as “reference signal index” and “reference signals in a reference signal set” can be understood as “indexes in a reference signal index set”. The reference signal described herein can be understood as an SSB and a CSI-RS, where the CSI-RS is periodic.

[0306] In addition, it can also be understood that in the above embodiments, q.sub.PS may be determined not based on q.sub.1, but only based on the second information. The first information and the second information described herein are information for indication (for example, indication information indicating that the base station is in an energy-saving state), and are not limited by names.

[0307] The illustrative logical blocks, modules, and circuits described in this disclosure can be implemented with a general purpose processor, a Digital Signal Processor (DSP), an application specific integrated circuit (application specific integrated circuit), ASIC), a Field Programmable Gate Array (FPGA) or other programmable logic devices, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. The general-purpose processor may be a microprocessor, but in the alternative, the processor may be any conventional processor, controller, microcontroller, or state machine. The processor can also be implemented as a combination of computing devices, such as a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors co-operating with a DSP core, or any other such configuration.

[0308] The steps of the method or algorithm described in this disclosure can be embodied directly in hardware, in a software module performed by a processor, or in a combination of the both. The software modules may reside in RAM memory, flash memory, ROM memory, EPROM memory, EEPROM memory, registers, hard disks, removable disks, or any other form of storage media known in the art. An exemplary storage medium is coupled to the processor so that the processor can read and write information from/to the storage medium. In the alternative, the storage medium may be integrated into the processor. The processor and the storage medium may reside in the ASIC. The ASIC may reside in the user terminal. In the alternative, the processor and the storage medium may reside as discrete components in the user terminal.

[0309] In one or more exemplary designs, the functions can be implemented in hardware, software, firmware, or any combination thereof. If implemented in software, each function can be stored on or transmitted by a computer-readable medium as one or more indication or codes. Computer readable media include both computer storage media and communication media, the latter including any media that facilitates the transfer of computer programs from one place to another. Storage media can be any available media that can be accessed by general-purpose or special-purpose computers.

[0310] With reference to the drawings, the description set forth herein describes example configurations, methods and devices, and does not represent all examples that can be realized or within the scope of the claims. As used herein, the term “example” means “serving as an example, instance or illustration”, not “preferred” or “superior to other examples”. The detailed description includes specific details in order to provide an understanding of the described technology.

However, these techniques may be practiced without these specific details. In some cases, well-known structures and devices are shown in block diagram form to avoid obscuring the concepts of the described examples.

[0311] Although this specification contains a number of specific implementation details, these should not be construed as limitations on any embodiment or the scope of the claimed protection, but descriptions of specific features of specific embodiments of the disclosure. Some features described in this specification in the context of individual embodiments can also be combined in a single embodiment. On the contrary, various features described in the context of a single embodiment can also be implemented in multiple embodiments alone or in any suitable sub-combination. Furthermore, although features can be described above as functioning in some combinations, and even initially claimed as such, in some cases, one or more features from the claimed combination can be deleted from the combination, and the claimed combination can be aimed at sub-combinations or variations of sub-combinations.

[0312] It should be understood that the specific order or hierarchy of steps in the method of the disclosure is an illustration of an exemplary process. Based on the design preference, it can be understood that the specific order or hierarchy of steps in the method can be rearranged to achieve the disclosed functions and effects of the disclosure. The attached method claims present elements of various steps in an example order, and are not meant to be limited to the specific order or hierarchy presented, unless otherwise stated. In addition, although the elements can be described or claimed in the singular form, the plural is also contemplated unless the limitation of the singular is explicitly stated. Therefore, the disclosure is not limited to the illustrated examples, and any device for performing the functions described herein is included in various aspects of the disclosure.

[0313] And the text and drawings are only provided as examples to help readers understand this disclosure. They are not intended and should not be construed to limit the scope of the disclosure in any way. Although some embodiments and examples have been provided, based on the disclosure herein, it is obvious to those skilled in the art that changes can be made to the illustrated embodiments and examples without departing from the scope of this disclosure.

Claims

1. A method performed by a user equipment (UE), the method comprising: receiving first indication information from a base station; and identifying whether to perform candidate beam detection according to a resource corresponding to a reference signal set based on the first indication information.
2. The method of claim 1, wherein identifying whether to perform candidate beam detection according to the resource corresponding to the reference signal set based on the first indication information comprises: identifying whether to perform candidate beam detection according to the resource corresponding to the reference signal set on a first time domain resource based on the first indication information, wherein the first time domain resource is identified based on at least one of: starting of the first time domain resource identified by the first indication information; ending of the first time domain resource identified by the first indication information; or a time domain position of the first time domain resource identified by a time domain position of a channel or signal carrying the first indication information.
3. The method of claim 1, wherein identifying whether to perform candidate beam detection according to the resource corresponding to the reference signal set based on the first indication information comprises: identifying whether to perform candidate beam detection according to the resource corresponding to the reference signal set based on at least one of a serving cell, a bandwidth part, a cell physical layer identity, or a transmission and reception point (TRP) corresponding to the first indication information.
4. The method of claim 1, further comprising: receiving second indication information from a base station; identifying a second time domain resource based on the second indication information; and providing an index of a reference signal to the base station, wherein at least one of the following is satisfied: in case that a time domain resource related to the index of the reference signal overlaps

with the second time domain resource, the index of the reference signal is identified from a second reference signal set; or in case that the time domain resource related to the index of the reference signal does not overlap with the second time domain resource, the index of the reference signal is identified from a first reference signal set.

5. The method of claim 4, further comprising at least one of the following: receiving at least one of a physical downlink shared channel (PDSCH), a physical downlink control channel (PDCCH), or a channel state information reference signal (CSI-RS) according to the index of the reference signal; or transmitting at least one of a physical uplink shared channel (PUSCH), a physical uplink control channel (PUCCH), or a sounding reference signal (SRS) according to the index of the reference signal.

6. The method of claim 4, wherein the second time domain resource is identified based on at least one of the following: starting of the second time domain resource identified by the second indication information; ending of the second time domain resource identified by the second indication information; or a time domain position of the second time domain resource identified by a time domain position of a channel or signal carrying the second indication information.

7. The method of claim 4, wherein the second reference signal set is identified based on the first reference signal set.

8. The method of claim 4, wherein the second reference signal set corresponds to the first reference signal set one by one.

9. The method of claim 4, wherein the first reference signal set is identified based on information transmitted by the base station.

10. A method performed by a base station, the method comprising: transmitting configuration information to a user equipment (UE); and transmitting first indication information to the user equipment, wherein the first indication information is associated with indicating whether to perform candidate beam detection according to a resource corresponding to a reference signal set based on the first indication information.

11. The method of claim 10, further comprising: transmitting second indication information to the UE, wherein the second indication information is associated with a second time domain resource; and receiving an index of a reference signal from the UE, wherein at least one of the following is satisfied: in case that a time domain resource related to the index of the reference signal overlaps with the second time domain resource, the index of the reference signal is identified from a second reference signal set; or in case that the time domain resource related to the index of the reference signal does not overlap with the second time domain resource, the index of the reference signal is identified from a first reference signal set.

12. The method of claim 11, further comprising at least one of the following: transmitting at least one of a physical downlink shared channel (PDSCH), a physical downlink control channel (PDCCH), or a channel state information reference signal (CSI-RS) according to the index of the reference signal; receiving at least one of a physical uplink shared channel (PUSCH), a physical uplink control channel (PUCCH), or a sounding reference signal (SRS) according to the index of the reference signal; or monitoring at least one of a physical uplink shared channel (PUSCH), a physical uplink control channel (PUCCH), or a sounding reference signal (SRS) according to the index of the reference signal.

13. The method of claim 11, further comprising transmitting to the user equipment information associated with the first reference signal set.

14. A user equipment (UE), comprising: a transceiver; and a processor coupled with the transceiver and configured to: receive first indication information from a base station, and identify whether to perform candidate beam detection according to a resource corresponding to a reference signal set based on the first indication information.

15. A base station comprising: a transceiver; and a processor coupled with the transceiver and configured to: transmit configuration information to a user equipment (UE); and transmit first

indication information to the user equipment, wherein the first indication information is associated with indicating whether to perform candidate beam detection according to a resource corresponding to a reference signal set based on the first indication information.
