

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication
Kind Code
Publication Date
Inventor(s)

20250287332
A1
September 11, 2025
Hosseinian; Seyed Mohsen et al.

METHODS FOR TIMING ADVANCE INDICATION AND TIMING RELATIONSHIPS INDICATION FOR NON-TERRESTRIAL NETWORKS

Abstract

A method of enabling communication between a user equipment (UE) and a non-terrestrial network (NTN), is described. The UE may be able to calculate a timing advance compensation. The timing advance compensation may be a differential or full timing advance compensation. An offset value, K.sub.offset, may be indicated to the UE. The K.sub.offset value may be used for timing relationships.

Inventors: Hosseinian; Seyed Mohsen (San Diego, CA), Bae; Jung Hyun (San Diego, CA), Hatami; Homayoon (San Diego, CA), Lee; Jungwon (San Diego, CA)

Applicant: Samsung Electronics Co., Ltd. (Suwon-si, KR)

Family ID: 75870528

Appl. No.: 19/219566

Filed: May 27, 2025

Related U.S. Application Data

parent US continuation 18239996 20230830 parent-grant-document US 12363666 child US 19219566
parent US continuation 17240891 20210426 parent-grant-document US 11751157 child US 18239996
us-provisional-application US 63022085 20200508
us-provisional-application US 63090639 20201012

Publication Classification

Int. Cl.: H04W56/00 (20090101); H04W64/00 (20090101); H04W72/0446 (20230101); H04W72/23 (20230101); H04W84/06 (20090101)

U.S. Cl.:

CPC H04W56/0045 (20130101); H04W56/005 (20130101); H04W56/006 (20130101); H04W64/006 (20130101); H04W72/0446 (20130101); H04W72/23 (20230101); H04W84/06 (20130101)

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S) [0001] This application is a continuation of U.S. patent application Ser. No. 18/239,996, filed Aug. 30, 2023, which is a continuation of U.S. patent application Ser. No. 17/240,891, filed Apr. 26, 2021, now U.S. Pat. No. 11,751,157, which claims the benefit of U.S. Provisional Patent Application No. 63/022,085, filed May 8, 2020 and which claims the benefit of U.S. Provisional Patent Application No. 63/090,639, filed Oct. 12, 2020, the entire contents of which are herein incorporated by reference.

FIELD

[0002] One or more aspects of embodiments according to the present disclosure relate to wireless communication networks, and more particularly to managing timing advance and offset values for uplink transmissions in a wireless communication system.

BACKGROUND

[0003] Demand is rising for communication of data to and from mobile communication devices. Traditional mobile wireless communication networks are evolving into networks that communicate more data and over longer distances. A new radio (NR) technology for the next generation, (e.g. 5G NR) is currently being discussed by the 3GPP standards organization and accordingly, changes to the current body of the 3GPP standard are being submitted and considered to evolve and finalize the 5G NR standard.

SUMMARY

[0004] A method and system are disclosed from the perspective of the user equipment (UE).

[0005] A method of enabling communication between a user equipment (UE) and a non-terrestrial network (NTN), comprising: receiving, at the UE, satellite position data of the NTN, determining, at the UE, a UE position, calculating, at the UE, a first distance between the UE position and the satellite position data, calculating, at the UE, a timing advance based on the first distance, receiving, at the UE, a Koffset value, and applying, at the UE, one or both of the timing advance and Koffset to configure transmission or reception of communication with the NTN.

[0006] The method wherein the satellite position data is ephemeris or positional data.

[0007] The method wherein the UE further receives a gateway position data.

[0008] The method wherein the UE further calculates a second distance between the satellite position data and the gateway position data.

[0009] The method wherein the UE further calculates the timing advance by dividing the first distance by a speed to obtain a first propagation delay, dividing the second distance by the speed to obtain a second propagation delay, summing the first propagation delay and the second propagation delay, and doubling the sum.

[0010] The method wherein the timing advance is a full timing advance compensation.

[0011] The method wherein the UE further receives a reference point position data, wherein the reference point position data is on a feeder link.

[0012] The method wherein the UE further receives a common timing advance value.

[0013] The method wherein the UE further calculates a third distance between the reference point position data and the satellite position data.

[0014] The method wherein the UE further calculates the timing advance by dividing the first distance by a speed to obtain a first propagation delay, dividing the third distance by the speed to obtain a third propagation delay, summing the first propagation delay, the third propagation delay, and the common timing advance value, and doubling the sum.

[0015] The method wherein the timing advance is one of a full timing advance compensation and a differential timing advance compensation.

[0016] The method wherein the reference point position data is the satellite position data.

[0017] The method wherein the UE further receives a reference point position data, wherein the reference point position data is located in a cell that the UE is located in.

[0018] The method wherein the UE further receives a common timing advance value.

[0019] The method wherein the UE further calculates a fourth distance between the reference point position data and the satellite position data.

[0020] The method wherein the UE further calculates a differential timing advance by dividing the first distance by a speed to obtain a first propagation delay, dividing the fourth distance by the speed to obtain a fourth propagation delay, subtracting the fourth propagation delay from the first propagation delay, and doubling the subtraction.

[0021] The method wherein the UE receives a Koffset value in a group common DCI format, and/or a MAC-CE format, and the Koffset value is a fixed number of bits.

[0022] The method wherein the Koffset value is specific to the UE.

[0023] The method wherein the Koffset value is used in a configured grant type 1 transmission, wherein the UE adds an offset of Koffset multiplied by a number of symbols per slot value to a timing for the configured grant type 1 transmission.

[0024] The method wherein the Koffset value is used in a configured grant type 2 transmission, wherein the UE schedules to transmit a Physical Uplink Shared Channel (PUSCH) by a DCI by adding a Koffset value to the configured grant type 2 transmission.

[0025] The method wherein the Koffset value is used for a slot format indicator (SFI) to dynamically configure and reconfigure symbols or slots in a subframe, wherein the UE configures and reconfigures symbols or slots at least Koffset slots after an uplink slot.

[0026] The method wherein the Koffset value is greater than or equal to the timing advance.

[0027] The method wherein the Koffset value is used for timing for a PUSCH transmission scheduled by DCI.

[0028] The method wherein the Koffset value is used for timing for a Channel State Information (CSI) transmission on a PUSCH

[0029] The method wherein the Koffset value is used for timing for a PUSCH transmission scheduled by a Random Access Response (RAR) grant

[0030] The method wherein the Koffset value is used for Hybrid Automatic Repeat Request Acknowledgement (HARQ-ACK) transmission on Physical Uplink Control Channel (PUCCH).

[0031] The method wherein the Koffset value is used for timing for CSI reference resource transmission.

[0032] The method wherein the Koffset value is used for timing for aperiodic SRS transmission.

[0033] A system that enables communication between a user equipment (UE) and a non-terrestrial network (NTN), the system configured to: receive, at the UE, satellite position data of the NTN, determine, at the UE, a UE position, calculate, at the UE, a first distance between the UE position and the satellite position data, calculate, at the UE, a timing advance based on the first distance, receive, at the UE, a Koffset value, and apply, at the UE, one or both of the timing advance and the Koffset to configure transmission or reception of communication with the NTN.

[0034] The system further configured to receive a reference point position data.

[0035] The system further configured to receive a common timing advance value.

[0036] The system wherein the UE further calculates a third distance between the reference point position data and the satellite position data.

[0037] The system wherein the UE further calculates the timing advance by dividing the first distance by a speed to obtain a first propagation delay, dividing the third distance by the speed to obtain a third propagation delay, summing the first propagation delay, the third propagation delay, and the common timing advance value, and doubling the sum.

[0038] The system wherein the timing advance is one of a full timing advance compensation and a differential timing advance compensation.

[0039] The system wherein the reference point is the satellite position data.

[0040] The system wherein the system receives the Koffset value in a group common DCI format, and/or a MAC-CE format, and the Koffset value is a fixed number of bits.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0041] These and other features and advantages of the present disclosure will be appreciated and understood with reference to the specification, claims, and appended drawings wherein:

[0042] FIG. 1 is a schematic drawing of a network, according to an embodiment of the present disclosure;

[0043] FIG. 2 is a schematic drawing of a full timing advance compensation, according to an embodiment of the present disclosure;

[0044] FIG. 3 is a schematic drawing of a differential timing advance compensation, according to an embodiment of the present disclosure;

[0045] FIG. 4 is a schematic drawing of a non-terrestrial network (NTN), according to an embodiment of the present disclosure;

[0046] FIG. 5 is a schematic drawing of a process to calculate a timing advance compensation, according to an embodiment of the present disclosure;

[0047] FIG. 6 is a schematic drawing of a timing advance compensation, according to an embodiment of the present disclosure;

[0048] FIG. 7 is a schematic drawing of an NTN, according to an embodiment of the present disclosure;

[0049] FIG. 8 is a schematic drawing of a process to calculate timing advance compensation, according to an embodiment of the present disclosure;

[0050] FIG. 9 is a schematic drawing of an NTN, according to an embodiment of the present disclosure;

[0051] FIG. 10 is a schematic drawing of a differential timing advance compensation, according to an embodiment of the present disclosure;

[0052] FIG. 11 is a schematic drawing of a differential timing advance compensation, according to an embodiment of the present disclosure;

[0053] FIG. 12 is a schematic drawing of a process to calculate timing advance compensation, according to an embodiment of the present disclosure;

[0054] FIG. 13 is a schematic drawing of a timing offset, according to an embodiment of the present disclosure;

[0055] FIG. 14 is a schematic drawing of a group-common Downlink Control Information (DCI) format for receiving an offset value, according to an embodiment of the present disclosure;

[0056] FIG. 15 is a schematic drawing of a Medium Access Control-Control Element (MAC-CE) format for receiving an offset value, according to an embodiment of the present disclosure;

[0057] FIG. 16 is a schematic drawing of an offset timing for Configured Grant Type 1, according to an embodiment of the present disclosure;

[0058] FIG. 17 is a schematic drawing of an offset timing based on timing for DCI Format scheduled Slot-Format Indicators (SFI), according to an

embodiment of the present disclosure; and [0059] FIG. 18 is an example of a system configured to manage timing advances and K.sub.offset values, according to some embodiments. DETAILED DESCRIPTION OF DRAWINGS

[0060] The detailed description set forth below in connection with the appended drawings is intended as a description of example embodiments of a network provided in accordance with the present disclosure and is not intended to represent the only forms in which the present disclosure may be constructed or utilized. The description sets forth the features of the present disclosure in connection with the illustrated embodiments. It is to be understood, however, that the same or equivalent functions and structures may be accomplished by different embodiments that are also intended to be encompassed within the scope of the disclosure. As denoted elsewhere herein, like element numbers are intended to indicate like elements or features.

[0061] Referring to FIG. 1, in some embodiments, a network 100 therein is shown. Network 100 may be a multiple access wireless communication system that supports a broadcast service, such as a non-terrestrial network (NTN). Network 100 may be designed to support one or more standards, such as 3rd Generation Partnership Project (3GPP). Network 100 may comprise a user equipment (UE) 101, satellite 102, and gateway 103.

[0062] UE 101 may be able to transmit, receive, store, and process data. UE 101 may be a transceiver system such as a mobile device, laptop, or other equipment.

[0063] Satellite 102 may be a space borne or airborne platform capable of sending and receiving data from UE 101 and gateway 103. Satellite 102 may be in communication with UE 101, where satellite 102 may be able to transmit and receive data from UE 101 over a service link 104. Service link 104 may include uplink (UL) and downlink (DL) data transmission.

[0064] Gateway 103 may be an antenna capable of sending and receiving data from satellite 102. Gateway 103 may be connected to or associated with a base station or logical radio node, such as a gNodeB (gNB) base station, not shown. In one embodiment, actions performed by gNB, such as scheduling and coordination, may be referred to as being performed by gateway 103, however, it may be understood that gNB may perform the command of sending data uplink or process receiving data downlink and gateway 103 may transmit data for gNB and also receive data for gNB. Gateway 103 may be in communication with satellite 102 over a feeder link 105. Feeder link 105 may include UL and DL data transmission. In one embodiment, UE 101, satellite 102, and gateway 103 may support a subcarrier spacing of 15, 30, 60, 120, or 240 KHz, however, other spacings may be supported.

[0065] Cell 106 may be a geographic area where UE 101 and other UEs (not shown) are capable of communicating with satellite 102. The size of cell 106 may vary depending on the location of satellite 102 relative to earth. For example, geostationary equatorial orbit (GEO) satellites may allow for a larger cell 106, which may be between 200 km to 3,500 km in diameter, in one embodiment. Medium earth orbit (MEO) and low earth orbit (LEO) may have smaller associated cell 106 sizes. Furthermore, the distance of satellite 102 to earth may affect the transmission time of transmitting and receiving data between UE 101 and satellite 102 and between satellite 102 and gateway 103. In one embodiment, a round trip delay (RTD) may be as high as 560 milliseconds (ms), 180 ms, and 60 ms for GEO, MEO, and LEO satellites systems, respectively. An RTD may be twice a propagation delay between a UE 101 and a gateway 103. UE 101 may be capable of handling these RTDs with modifications of the timing aspects in the physical layer or higher layers of an Open Systems Interconnection (OSI) model, and a timing advance (TA) mechanism.

[0066] In operation, the UE 101 may send data to (UL) or receive data from (DL) data to satellite 102, which may send (UL) or receive (DL) data to gateway 103, described in more detail below.

[0067] Referring to FIG. 2, therein is shown a full timing advance compensation 200 for a downlink and uplink to a base station, such as a gNB, via gateway 103. Full timing advance compensation 200 may be one type of NR timing offset between downlink and uplink transmission, which may be described below in more detail. Subframes 201 may comprise multiple subframes of data. A subframe 202 may be a subframe within subframes 201. Subframe 202 may comprise data transmitted over a time period. In one embodiment, subframe 202 may have a 1 ms duration, but other durations may be used. A subframe may comprise one or more slots, which may vary with subcarrier spacing. A slot may comprise one or more resource blocks, which may comprise symbols and subcarriers. A symbol may be a division of time within a slot, and a subcarrier may be a frequency. A resource element may be one unit of time and one frequency within a resource block. There may be a basic time unit T.sub.C which may be defined as $T_{sub.C} = 1 / (15,000 * 2,048)$ seconds = 32.6 nanoseconds which may be used for determining synchronization between UE 101, satellite 102, and gateway 103. In another embodiment, T.sub.C may be define as $T_{sub.C} = 1 / (480,000 * 4096)$ seconds, however, other definitions may be used. In one embodiment, a 15 KHz subcarrier spacing may have one slot per subframe, a 30 KHz subcarrier spacing may have two slots per subframe, a 60 KHz subcarrier spacing may have 4 slots per subframe, and so on for 120 KHz and 240 KHz.

[0068] Subframes 201 may have different subframe structures, which may be Type 1, applicable to Frequency Division Duplex (FDD), or may be Type 2, which may be applicable to Time Division Duplex (TDD). Each subframe may be the same duration or different duration and may be used to transmit and receive data between the base station/gateway 103 and UE 101. Subframes may have reference subframe numbers, and may have timestamps associated with the beginning of each subframe. This information may be used for coordination of downlink and uplink transmission.

[0069] In another embodiment, subframes 201 may be frames, which may comprise multiple frames of data. In one embodiment, a frame may be 10 ms in duration and may comprise ten subframes of 1 ms each, however, the duration of the frame and the number of subframes may vary. Frames may have a frame number, which may be an index value and may be known as a System Frame Number (SFN). In one embodiment, the index values of SFNs may be between 0 and 1023, that is, there may be 1024 SFNs which may repeat after reaching the last index value of 1023.

[0070] A subframe 202 within subframes 201 may be of length n and may contain data that is to be transmitted between gateway 103 and UE 101 of FIG. 1. A base station (not shown) may send subframe 202 downlink to UE 101 via gateway 103 of FIG. 1 at gateway downlink reference time 203. In one embodiment, gateway downlink reference time 203 may be a time, or it may be a slot number, or other identifier. Subframe 202 may be received at a UE downlink reference time 204 after a propagation delay 205, which may be the time difference between the sending of subframe 202 at the base station/gateway 103 at downlink reference time 203 and receiving of subframe 202 at UE 101 at time UE downlink reference time 204.

[0071] Similarly, a UE 101 may send uplink a subframe 206 at a UE uplink time 207 to a base station/gateway 103 that may be received at gateway uplink time 208. There may be a propagation delay 205 between the UE uplink time 207 and gateway uplink time 208.

[0072] In a full timing advance compensation situation, the downlink reference time 203 and gateway uplink time 208 may be aligned. That is, within a range, downlink reference time 203 may be the same time as gateway uplink time 208. In one embodiment, the range may be T.sub.C as defined previously, however, other values may be employed. Data sent downlink from gateway 103 may be synchronized with data received uplink from UE 101. A timing advance 209 may be twice the propagation delay 205 and may allow for full timing advance compensation. A timing advance may be a negative offset value between the UE downlink reference time 204 and UE uplink time 207. The timing advance may be used to ensure that the downlink and uplink subframes are synchronized. In one embodiment, a full timing advance, or full timing advance compensation, may enable synchronization of downlink and uplink transmission timing between a UE 101 and a gateway 103.

[0073] In one embodiment, the timing advance 209 may be up to 2 miliseconds for a 15 kHz subcarrier spacing, which may allow for cell 106 to be 300 km in diameter. In NTN, however, due to very high altitudes of satellites, the RTD, or timing advance 208, may be in the hundreds of milliseconds to seconds range, as described in FIG. 1. In one embodiment, the timing advance 209 is twice the propagation delay 205, however, it may be larger. The timing advance 209 may be large compared to the duration of a subframe, such as subframe 202. In one embodiment, if the duration of a subframe is 1 ms, the timing advance 209 may be 560 ms, however, other values may be used.

[0074] Referring to FIG. 3, therein is shown a differential timing advance compensation 300 for a downlink and uplink to a base station, such as a gNB, via gateway 103 of FIG. 1. Differential timing advance compensation 300 may be one type of NR timing offset between downlink and uplink transmission. Subframes 301 may comprise multiple subframes of data. Each subframe may be the same duration or a different duration and may be

used to transmit and receive data between the base station/gateway **103** and UE **101** of FIG. **1**. In another embodiment, subframes **301** may comprise multiple frames of data.

[0075] A subframe **302** may be within subframes **301**. A base station (not shown) may send subframe **302** downlink to UE **10** via gateway **103** of FIG. **1** at a gateway downlink time **303** and it may be received at a UE downlink time **304**. A propagation delay **305** may be the time difference between the sending of subframe **302** at the base station/gateway **103** at downlink reference time **303** and receiving at UE downlink time **304**. A propagation delay **305** may be the time difference between the sending of subframe **302** at the base station/gateway **103** at downlink reference time **303** and receiving of subframe **302** at UE **101** at time UE downlink reference time **304**.

[0076] Similarly, a UE **101** may send uplink a subframe at EU uplink time **307** to a base station/gateway **103** that may be received at gateway uplink time **308**. There may be a propagation delay **309** between the UE uplink time **307** and gateway uplink time **308**.

[0077] Furthermore, there may be a differential timing advance **306** that may be the difference between UE uplink time **307** and UE downlink time **304**. A common timing advance offset **310** may be the sum of propagation delay **305** and propagation delay **309**, reduced by differential timing advance **306**.

[0078] In one embodiment, a differential timing advance may be a negative offset value between the UE downlink time **304** and UE uplink time **307**. The differential timing advance may be used to ensure that the gateway **103** may transmit subframes downlink to UE **101** at a first time and receive subframes uplink from UE **101** at a second time that is different than the first time. Gateway **103** may be able to receive subframes uplink from multiple UEs (not shown) at the second time, that is, subframes transmitted uplink to gateway **103** are synchronized.

[0079] With differential timing advance compensation, common timing advance offset **310** may not be twice propagation delay **305**, as described above in FIG. **2** for full timing advance compensation. In some embodiments, the differential timing advance **306** may be specific to each UE **101**.

There may be a common timing advance offset time **310** between gateway downlink time **303** and gateway uplink time **308**. Depending on how large the round trip delay is and how small the UE-specific differential timing advance **306**, the value of common timing advance offset time **310** may be as large as 540 ms, however, other values may be used.

[0080] In both the full timing advance compensation **200** and differential timing advance compensation **300** methods described previously, additional complexity may be utilized to manage the scheduling and timing of subframe uplinks and downlinks. New radio physical layer timing relationships may be enhanced to manage a timing advance offset for the downlink and uplink timing for UE **101**. A timing relationship may be a transmission of reception of communication and may be with the NTN. UE **101** may use a timing advance compensation to configure a timing relationship. New radio timing advance may be estimated by a network through MSG1 or msgA steps, for 4-step and 2-step random access procedures, respectively. However, additional methods for timing advance estimations may be described previously and below.

[0081] The timing advance may be transmitted, otherwise referred to as indicated, to UE **101** by a timing advance command. For example, for an NTN, UE **101** may have Global Navigation Satellite System (GNSS) capabilities. That is, a UE **101** may have knowledge of its own geolocation or location. Geolocation data for satellite **102** may also be known to UE **101** (or made known). Satellite **102** may transmit satellite position data to UE **101**, which may be ephemeris data or any other kind of positional data. Ephemeris data may include the orbital position of satellite **102**, including information such as week number, satellite accuracy, health, age of data, satellite clock correction coefficients, and other orbital parameters. In another embodiment, satellite **102** may transmit coordinate data to UE **101**.

[0082] UE **101** may be capable of calculating timing advance **209** or common timing advance offset time **310** with its own geolocation data and ephemeris data or coordinate data from satellite **102**, which will be described in more detail below. UE **101** may be able to calculate a first distance between UE **101** and satellite **102** using satellite position data of satellite **102** and location data of UE **101**. A first propagation delay may be calculated from the first distance by dividing the first distance by a speed. In one embodiment, the speed may be the speed of light in free space. UE **101** may also be able to calculate a second distance between satellite **102** and gateway **103** using satellite position data of satellite **102** and gateway position data of gateway **103**. A second propagation delay may be calculated from the second distance by dividing the second distance by a speed. In one embodiment, the speed may be the speed of light in free space. This information may be described in more detail below and may be used to calculate a full or differential timing advance compensation. In another embodiment, UE **101** may receive first propagation delay and second propagation delay data and may use it to calculate a full or differential timing advance compensation.

[0083] Depending on the location of satellite **102** (LEO, MEO, or GEO), the round trip propagation delay may be smaller or larger. UE **101** may have a flexible timing advance mechanism that is capable of adapting to the deployment scenario of satellite **102** (LEO, MEO, or GEO).

[0084] Referring to FIG. **4**, an example NTN communication architecture **400** therein is shown, which may be NTN communication architecture **100** with an additional UE **401**. UE **401** may be in cell **106** and may be in communication with satellite **102** via service link **402**. UE **101** may receive information to calculate and indicate a full timing advance compensation, which may include GNSS data of UE **101**, satellite **102**, and a reference point **405**. In one embodiment, reference point **405** may be the geolocation of gateway **103**. The distance between satellite **102** and reference point **405** may be distance **406**, which may be denoted as $d_{sub.g.s}$. The distance between UE **101** and satellite **102** may be distance **404**, which may be denoted as $d_{sub.s,u}$. Similarly, the distance between UE **401** and satellite **102** may be distance **403**, which may be denoted as $d_{sub.s,u2}$.

[0085] The reference point **405** geolocation information may be in the form of Earth-Centered, Earth-Fixed (ECEF) coordinate or may be any other form of coordinates which may provide the relative location of the reference point **405** with respect to a fixed origin point that is known to both a gNB via gateway **103** and UE **101**. The reference point **405** geolocation information may also be in the form of an index that points to a location in a table of a set of all predetermined reference points' location information. UE **101** may additionally have ephemeris data for satellite **102** which may be in ECEF Cartesian form, which may include an x, y, and z coordinate as a function of time. UE **101** may be able to calculate the satellite **102** location by any interpolation technique.

[0086] UE **101** may calculate a first propagation time between UE **101** and satellite **102** by calculating distance **404** and dividing it by a speed. In one embodiment, the speed may be the speed of light in free space, c , which may be denoted as $T_{sub.s,u}$. This may be the equation $T_{sub.s,u} = d_{sub.s,u}/c$. Distance **404** may be calculated by the UE **101** by using geolocation data of UE **101** and satellite **102**. Similarly, UE **101** may calculate a second propagation time between satellite **102** and reference point **405** by calculating distance **406** and dividing it by the speed of light in free space, c , which may be denoted as $T_{sub.g,s}$. This may be the equation $T_{sub.g,s} = d_{sub.g,s}/c$. Distance **404** may be calculated by the UE **101** by using geolocation data of satellite **102** and reference point **405**. A total timing advance value TA may be calculated by UE **101** as twice the sum of $T_{g,s}$ and $T_{s,u}$, or: $TA = 2(T_{sub.g,s} + T_{sub.s,u})$. In one embodiment, this may be timing advance **209** of FIG. **2**.

[0087] A similar calculation may be performed by UE **401**. UE **401** may calculate a propagation time between UE **401** and satellite **102** by calculating distance **403** and dividing it by a speed. In one embodiment, the speed may be the speed of light in free space, c , which may be denoted as $T_{sub.s,u2}$. This may be the equation $T_{sub.s,u2} = d_{sub.s,u2}/c$. Distance **403** may be calculated by the UE **401** by using geolocation data of UE **401** and satellite **102**. Similarly, UE **401** may calculate a propagation time between satellite **102** and reference point **405** by calculating distance **406** and dividing it by the speed of light in free space, c , which may be denoted as $T_{sub.g,s}$. This may be the equation $T_{sub.g,s} = d_{sub.g,s}/c$. Distance **403** may be calculated by the UE **401** by using geolocation data of satellite **102** and reference point **405**. A total timing advance value TA may be calculated by UE **401** as twice the sum of $T_{sub.g,s}$ and $T_{sub.s,u}$, or: $TA = 2(T_{sub.g,s} + T_{sub.s,u2})$. Similar calculations may be performed by other UEs (not shown) in cell **106**.

[0088] As described in 3GPP TS 38.213 v16.0.0 "Physical layer procedures for control (Release 16)," a subframe number may be converted to a time value by using an offset number $N_{sub.TA,offset}$ and $T_{sub.C}$. An uplink subframe number for transmission from UE **101** to satellite **102** may be calculated by adding the total timing advance value TA to an offset calculation $N_{sub.TA,offset} * T_{sub.C}$. For simplicity, $N_{sub.TA,offset}$ may be set to 0 for the descriptions below.

[0089] Referring to FIG. 5, therein is shown a process diagram 500 for UE 101 of FIG. 1 to calculate a timing advance compensation and indicate the value to gateway 103.

[0090] Process 501 may be UE 101 receiving geolocation data of UE 101 and a reference point 405. Geolocation data of UE 101 may be a UE position. In some embodiments, the reference point may be positional data and may be at gateway 103. UE 101 may also receive ephemeris data of satellite 102, which may be satellite position data.

[0091] Process 502 may be UE 101 calculating geolocation data of satellite 102 from the ephemeris data.

[0092] Process 503 may be UE 101 determining a first distance $d_{sub,s,u}$ between UE 101 and satellite 102 and a second distance $d_{sub,g,s}$ between satellite 102 and the reference point at gateway 103.

[0093] Process 504 may be UE 101 determining a second propagation delay $T_{sub,g,s}$ between satellite 102 and the reference point at gateway 103, or $T_{sub,g,s} = d_{sub,g,s}/c$, where c is a speed. In one embodiment, the speed may be the speed of light in free space. UE 101 may determine a first propagation delay $T_{sub,s,u}$ between UE 101 and satellite 102, which may be $T_{sub,s,u} = d_{sub,s,u}/c$. UE 101 may further calculate a timing advance compensation TA as twice the sum of the propagation delays $T_{sub,g,s}$ and $T_{sub,s,u}$, or $TA = 2(T_{sub,g,s} + T_{sub,s,u})$.

[0094] Process 505 may be UE 101 indicating data using a timing advance compensation to gateway 103. The uplink subframe number for transmission from UE 101 may start at $TA + N_{sub} \cdot TA_{offset} \cdot T_{sub,C}$, which may occur before the start of a corresponding downlink subframe at UE 101, as shown in FIG. 2 with UE uplink time 207 occurring before the start of corresponding gateway downlink reference time 202. In one embodiment, UE 101 may use full timing advance compensation, as described in FIG. 2. In another embodiment, UE 101 may use differential timing advance compensation, as described in FIG. 3.

[0095] Referring to FIG. 6, therein is shown an example embodiment of a full timing advance compensation 600 for two UEs with different propagation delays. A gateway/gNB subframe downlink 601 may be transmitted by gateway 103 at gateway downlink reference time 602 and may be received by a first UE (UE1) at UE 1 downlink time 603. First UE may be UE 101 as shown in FIG. 4. There may be a UE 1 propagation delay 604, which may be the difference between UE 1 downlink time 603 and gateway downlink reference time 602. UE 101 may transmit a subframe uplink 606 at UE 1 uplink time 607, which may be received by gateway 103 at uplink time 608. In one embodiment, with full timing advance compensation, uplink time 608 may be approximately the same as downlink time 602. UE 1 propagation delay 604, which was described previously as the difference between UE 1 downlink time 603 and gateway downlink reference time 602, may be approximately equal to the difference between uplink time 608 and UE 1 uplink time 607. In one embodiment, a UE 1 timing advance 605 may be approximately twice UE 1 propagation delay 604 and may be the round trip time between sending data from gateway 103 downlink to UE 101 and UE 101 sending data uplink to gateway 103.

[0096] Meanwhile, gateway/gNB subframe downlink 601 may be transmitted by gateway 103 at gateway downlink reference time 602 may also be received by a second UE (UE2) at UE 2 downlink time 609. UE2 may be UE 401 of FIG. 4.

[0097] There may be a UE 2 propagation delay 610, which may be the difference between UE 2 downlink time 609 and gateway downlink reference time 602. UE 401 may transmit a subframe uplink 612 at UE 2 uplink time 613, which may be received by gateway 103 at uplink time 614. In one embodiment, with full timing advance compensation, uplink time 614 may be approximately the same as downlink time 602 and uplink time 608. UE 2 propagation delay 610, which was described previously as the difference between UE 2 downlink time 609 and gateway downlink reference time 602, may be approximately equal to the difference between uplink time 614 and UE 2 uplink time 613. In one embodiment, a UE 12 timing advance 611 may be approximately twice UE 2 propagation delay 610 and may be the round trip time between sending data from gateway 103 downlink to UE 401 and UE 401 sending data uplink to gateway 103.

[0098] Referring to FIG. 7, therein is shown an NTN communication architecture 700 for timing advance compensation with a reference point on feeder link 105 of FIG. 1. A UE 701 may be in cell 106 with UE 101 of FIG. 1. UE 701 may have a service link 702 which may have a distance 708 between UE 701 and satellite 102. Feeder link 105 may have a reference point 704 which may be any point on feeder link 105 between satellite 102 and gateway 103. There may be a distance 706 which may be the distance between satellite 102 and reference point 704, which may be referred to as a third distance, and a distance 703 which may be the distance between reference point 704 and gateway 103. Distance 703 may have an associated common timing advance, $T_{sub,common}$. The common timing advance may be a timing advance that is in common between all UEs in cell 106 and the associated gateway 103. In one embodiment, a reference point 705 may be a special case of reference point 704 where the reference point is satellite 102 itself. In another embodiment, reference point 704 may be a point between satellite 102 and gateway 103.

[0099] In one embodiment, the network may transmit, or indicate, information to UE 101 to calculate a timing advance. UE 101 may receive GNSS data of UE 101, satellite 102, and reference point 704. Furthermore, UE 101 may also receive common timing advance $T_{sub,common}$. As described in FIG. 4, the distance between UE 101 and satellite 102 may be distance 707, which may be denoted as $d_{sub,s,u}$. Distance 706, the distance between satellite 102 and reference point 704, may be denoted $d_{sub,r,s}$. Reference point 704 may be in the form of ECEF coordinate or any other form of coordinates which may provide the relative location of reference point 704 with respect to a fixed origin point that is known to both the network and UE 101. The reference point 704 geolocation information may also be in the form of an index that points to a location in a table of a set of all predetermined reference points' location information. UE 101 may additionally have ephemeris data for satellite 102 which may be in ECEF Cartesian form, which may include an x , y , and z coordinate as a function of time. UE 101 may be able to calculate the satellite 102 location by any interpolation technique.

[0100] UE 101 may calculate a propagation time between UE 101 and satellite 102 by calculating distance 707 and dividing it by a speed. In one embodiment, the speed may be the speed of light in free space, c , which may be denoted as $T_{sub,s,u}$. This may be the equation $T_{sub,s,u} = d_{sub,s,u}/c$. Distance 707 may be calculated by the UE 101 by using geolocation data of UE 101 and satellite 102.

[0101] Similarly, UE 101 may calculate a propagation time between satellite 102 and reference point 704 by calculating distance 706 and dividing it by the speed of light in free space, c , which may be denoted as $T_{sub,r,s}$. This may be the equation $T_{sub,r,s} = d_{sub,r,s}/c$ and may be referred to as a third propagation delay.

[0102] Distance 706 may be calculated by the UE 101 by using geolocation data of satellite 102 and reference point 704. A total timing advance value TA may be calculated by UE 101 as approximately twice the sum of $T_{sub,r,s}$, $T_{sub,s,u}$, and $T_{sub,common}$, or: $TA = 2(T_{sub,r,s} + T_{sub,s,u} + T_{sub,common})$. In one embodiment, this may be timing advance 605 of FIG. 6.

[0103] In another embodiment, reference point 704, which may be anywhere between satellite 102 and gateway 103 on feeder link 105, may be replaced with reference point 705, which may be satellite 102 itself. This may be a special case where $T_{sub,r,s} = 0$ because $d_{sub,r,s} = 0$. In this case, the total timing advance value calculated will be twice the sum of $T_{sub,s,u}$ and $T_{sub,common}$, or: $TA = 2(T_{sub,s,u} + T_{sub,common})$. As mentioned previously, an uplink subframe number for transmission from UE 101 may start with $TA + N_{sub} \cdot TA_{offset} \cdot T_{sub,C}$ before the start of the corresponding downlink subframe to UE 101, however, this value may be ignored in the figure for simplicity. For example, a UE1 uplink time 607 may occur before a corresponding downlink time 602 in FIG. 6.

[0104] Referring to FIG. 8, this may be a process diagram for calculating and indicating a timing advance of a UE 101 utilizing NTN architecture 700 as shown in FIG. 7. Unlike previous timing advance calculations, this timing advance calculation may utilize a reference point 704 of FIG. 7 and common timing advance.

[0105] Process 801 may be UE 101 receiving geolocation data of UE 101, ephemeris data of satellite 102, geolocation data of reference point 704, and a common timing advance 703. In some embodiments, UE 101 may receive geolocation or ephemeris data of reference point 705 instead of reference point 704 if satellite 102 is selected as a reference point. In some embodiments, reference point 704 may be on the path of feeder link 105 between satellite 102 and gateway 103.

[0106] Process 802 may be UE 101 calculating a geolocation of satellite 102 with the ephemeris data of satellite 102.

[0107] Process **803** may be UE **101** determining distance $d_{\text{sub},s,u}$ between UE **101** and satellite **102** and a distance $d_{\text{sub},r,s}$ between satellite **102** and reference point **704**. In some embodiments, if satellite **102** is used as a reference point **705**, UE **101** may only determine the distance between UE **101** and satellite **102**.

[0108] Process **804** may be UE **101** determining a differential timing advance and then full timing advance compensation TA. UE **101** may calculate a timing advance between UE **101** and satellite **102** $T_{\text{sub},s,u}$ which may be distance $d_{\text{sub},s,u}$ divided by a speed. In one embodiment, the speed may be the speed of light in free space, c , or $T_{\text{sub},s,u} = d_{\text{sub},s,u}/c$. UE **101** may determine a timing advance between satellite **102** and reference point **704** $T_{\text{sub},r,s}$ which may be distance $d_{\text{sub},r,s}$ divided by the speed, c , or $T_{\text{sub},r,s} = d_{\text{sub},r,s}/c$. UE **101** may calculate TA as twice the sum of $T_{\text{sub},r,s}$, $T_{\text{sub},s,u}$, and $T_{\text{sub},\text{common}}$, or $TA = 2(T_{\text{sub},r,s} + T_{\text{sub},s,u} + T_{\text{sub},\text{common}})$.

[0109] Process **805** may be UE **101** transmitting, or indicating, data using a full timing advance compensation TA to gateway **103**. In one embodiment, UE **101** may apply full timing advance to uplink subframes, where $TA = 2(T_{\text{sub},r,s} + T_{\text{sub},s,u} + T_{\text{sub},\text{common}})$, as described above. In one embodiment, satellite **102** may be used as reference point **705**, and $T_{\text{sub},r,s} = 0$. Satellite **102** geolocation data extracted from ephemeris data and reference point **705** geolocation data may be the same, and $TA = 2(T_{\text{sub},s,u} + T_{\text{sub},\text{common}})$. The uplink subframe number for transmission from UE **101** to gateway **103** may be $TA + N_{\text{sub},TA,\text{offset}} \cdot T_{\text{sub},c}$, which may be sent before the start of the corresponding downlink subframe at UE **101**. This may be shown in FIG. 6, where $N_{\text{sub},TA,\text{offset}} = 0$ for simplicity.

[0110] Referring to FIG. 9, this may be an example NTN communication architecture **900** for timing advance compensation with a reference point **901** on the footprint of satellite **102**. Unlike in previous examples, in the present example, reference point **901** may be anywhere satellite **102** can communicate with. In one embodiment, reference point **901** may be within the geographic area of cell **106**. Reference point **901** may have a distance $d_{\text{sub},r,s}$ which may be the distance between reference point **901** and satellite **102**. There may be a common timing advance **903** $T_{\text{sub},\text{common}}$ which may be the timing advance between satellite **102** and gateway **103**. As described previously, UE **101** may receive geolocation data for gateway **103**, and may receive ephemeris data from satellite **102** which can be used by UE **101** to calculate geolocation data for satellite **102**. UE **101** may be able to calculate a distance **902**, $d_{\text{sub},r,s}$, which may be the distance between reference point **901** and satellite **102** and may be referred to as a fourth distance. Additionally, UE **101** may be able to calculate distance **904**, $d_{\text{sub},s,u}$, which may be the distance of service link **104**, or the path between UE **101** and satellite **102**.

[0111] After receiving geolocation data of reference point **901**, ephemeris data of satellite **102**, and common timing advance **903**, UE **101** may be able to calculate the propagation time between reference point **901** and satellite **102**, $T_{\text{sub},r,s}$, which may be a fourth propagation delay, and the propagation time between UE **101** and satellite **102**, $T_{\text{sub},s,u}$. These propagation times may be calculated by dividing the distance by the speed of light in free space, c . Thus, $T_{\text{sub},r,s} = d_{\text{sub},r,s}/c$, and $T_{\text{sub},s,u} = d_{\text{sub},s,u}/c$. UE **101** may calculate a differential timing advance as twice the difference between $T_{\text{sub},s,u}$ and $T_{\text{sub},r,s}$, or $TA = 2(T_{\text{sub},s,u} - T_{\text{sub},r,s})$.

[0112] Referring to FIG. 10, therein is shown a differential timing advance compensation **1000** for a downlink and uplink to a base station, such as a gNB, via gateway **103** of FIG. 1. In one embodiment, differential timing advance compensation **1000** may utilize the NTN architecture **900**, however, it may also use other NTN architectures, such as NTN architecture **700**, NTN architecture **400**, NTN architecture **100**, or others not shown.

[0113] Subframes **1001** may comprise multiple subframes of data. Each subframe may be the same number of bits or a different number, and may be used to transmit and receive data between a base station via gateway **103** and a UE **101** of FIG. 1.

[0114] A subframe **1002** may be within subframes **1001**. In one embodiment, subframe **1002** may transmit downlink data from gateway **103** to UE **101** at a gateway downlink reference time **1003**, which may be received by UE **101** at a UE downlink reference time **1004**. There may be a downlink propagation time **1005**, which may be the difference between UE downlink reference time **1004** and gateway downlink reference time **1003**.

[0115] Meanwhile, UE **101** may send a subframe **1006** uplink to gateway **103** at a UE uplink reference time **1007**. Subframe **1006** may arrive at gateway **103** at gateway uplink reference time **1008** with an uplink propagation delay **1010**. In one embodiment, uplink propagation delay **1010** may be approximately the same time as downlink propagation delay **1005**. UE uplink reference time **1007** may be determined by subtracting a differential timing advance **1009** from UE downlink reference time **1004**. Differential timing advance **1009** may be different for each UE **101** used, or it may be the same for two or more UEs. In one embodiment, differential timing advance **1009** may be calculated as described in FIG. 9, as $TA = 2(T_{\text{sub},s,u} - T_{\text{sub},r,s})$, however, other differential timing advance calculations may be used.

[0116] In one embodiment, for calculating differential timing advance **1009**, the information about the propagation delay $T_{\text{sub},r,s}$ may be broadcasted in cell **106** and sent to all UEs in cell **106**. Broadcasting may be performed via system information block (SIB), master information block (MIB), or any other method. The information about propagation delay $T_{\text{sub},r,s}$ may be an absolute time or may be normalized to $T_{\text{sub},C}$, such as $N_{\text{sub},r,s} = T_{\text{sub},r,s}/T_{\text{sub},C}$. UE **101** may determine an uplink subframe number for transmission to gateway **103**, which may be $T_{\text{sub},s,u} + (N_{\text{sub},r,s} + N_{\text{sub},TA,\text{offset}}) \cdot T_{\text{sub},c}$, which may be before the start of a corresponding downlink subframe at UE **101**. The uplink subframe number may be sent at UE uplink reference time **1007**. In one embodiment, all uplink subframes from UEs in cell **106** may arrive at gateway **103** by a delay of $2(T_{\text{sub},\text{common}} + T_{\text{sub},r,s})$, which may be a common timing advance **1011**. Common timing advance **1011** may allow for gateway **103** to receive all uplink transmissions from all UEs in cell **106** at the same gateway uplink reference time **1008**. Thus, for each UE in cell **106**, there may be a different differential timing advance **1009**, however, each uplink transmission for each UE in cell **106** may arrive at the same time to gateway **103**.

[0117] Referring to FIG. 11, therein is shown a timing diagram **1100** for differential timing advance compensation for two UEs for a downlink and uplink to a base station, such as a gNB, via gateway **103** of FIG. 1. In one embodiment, timing diagram **1100** may utilize NTN architecture **900**, however, it may also use other NTN architectures. Subframes **1101** may comprise multiple subframes of data. Each subframe may be the same number of bits or a different number, and may be used to transmit and receive data between a base station via gateway **103** and a UE **101** of FIG. 1.

[0118] A subframe **1102** may be within subframes **1101**. In one embodiment, subframe **1102** may transmit data downlink from gateway **103** to UE **101** at a gateway downlink reference time **1103**, which may be received by UE **101** at a UE1 downlink reference time **1104**. There may be a UE1 downlink propagation time **1105**, which may be the difference between UE1 downlink reference time **1104** and gateway downlink reference time **1103**.

[0119] Meanwhile, UE **101** may send a UE1 subframe **1106** uplink to gateway **103** at a UE1 uplink reference time **1107**. UE1 subframe **1106** may arrive at gateway **103** at gateway uplink reference time **1108** with a UE1 uplink propagation delay **1110**. In one embodiment, UE1 uplink propagation delay **1110** may be approximately the same time as UE1 downlink propagation delay **1105**. UE1 uplink reference time **1107** may be determined by subtracting a UE1 differential timing advance **1109** from UE1 UE downlink reference time **1104**. UE1 Differential timing advance **1109** may be specific to a UE **101** used. In one embodiment, UE1 differential timing advance **1109** may be calculated as described in FIG. 9, as $TA = 2(T_{\text{sub},s,u} - T_{\text{sub},r,s})$, however, other differential timing advance calculations may be used.

[0120] Meanwhile, subframe **1102** may be received by a second UE (UE2) at UE2 downlink reference time **1111**. There may be a UE2 downlink propagation delay **1112**, which may be the difference between UE2 downlink reference time **1111** and gateway downlink reference time **1103**. UE2 may transmit, or indicate, a UE2 subframe **1113** at UE2 uplink reference time **1114**, which may be received by gateway **103** at gateway uplink reference time **1108**. The propagation delay between UE2 uplink reference time **1114** and gateway uplink reference time **1108** may be UE2 uplink propagation delay **1116**. In a differential timing advance compensation mode, gateway **103** may send data downlinks at a first reference time and may receive data uplinks at a second reference time. That is, the downlink and uplink reference times may differ. In a full timing advance compensation mode, gateway **103** may send data downlinks and may receive data uplinks at the same reference time. FIG. 11 shows an example of a differential timing advance compensation scheme where a UE1 and a UE2 are indicating data uplink to gateway **103** at different times, however, the data may be received by gateway **103** at the same time, which may be gateway uplink reference time **1108**.

[0121] Referring to FIG. 12, this may be a process diagram **1200** for calculating and indicating a timing advance of a UE **101** with a reference point

FIG. 9 anywhere within cell **106**. Unlike in previous figures, FIG. 12 may use a difference between a propagation delay between a UE **101** and satellite **102** and a propagation delay between a reference point **901** and satellite **102** to determine a timing advance.

[0122] Process **1201** receive data may be UE **101** receiving geolocation data of UE **101**, ephemeris data of satellite **102**, geolocation of reference point **901**, and a common timing advance **903**. In some embodiments, reference point **901** may be a point anywhere within cell **106**. In some embodiments, UE **101** may receive data from a gNB via gateway **103** in NTN architecture **900**. In another embodiment, information about the propagation delay $T_{sub,r,s}$ between reference point **901** and satellite **102** may be broadcasted by satellite **102** into cell **106** and all UEs in cell **106** may receive this information. Broadcasting may occur via SIB, MIB, or other broadcasting mechanism.

[0123] Process **1202** may be UE **101** calculating a geolocation of satellite **102** using the ephemeris data of satellite **102**.

[0124] Process **1203** may be UE **101** calculating a distance $d_{sub,s,u}$ between UE **101** and satellite **102**, and a distance $d_{sub,r,s}$ between satellite **102** and reference point **901**.

[0125] Process **1204** may be UE **101** determining a timing advance. UE **101** may calculate a propagation time $T_{sub,s,u}$ between UE **101** and satellite **102**, which may be $T_{sub,s,u} = d_{sub,s,u}/c$, where c is the speed of light in free space. UE **101** may calculate a propagation time $T_{sub,r,s}$ between satellite **102** and reference point **901**, which may be $T_{sub,r,s} = d_{sub,r,s}/c$. UE **101** may calculate a differential timing advance value TA as twice the difference between propagation time $T_{sub,s,u}$ and propagation time $T_{sub,r,s}$, or $TA = 2(T_{sub,s,u} - T_{sub,r,s})$.

[0126] In some embodiments, UE **101** may determine a full timing advance. In other embodiments, UE **101** may determine a differential timing advance. For each UE in cell **106**, the differential timing advance may be unique to the UE, or it may be shared.

[0127] Process **1205** may be UE **101** transmitting, or indicating, data using a timing advance to gateway **103**. The uplink subframe number for transmission from UE **101** may start at $TA + N_{sub,TA,offset} * T_{sub,c}$, which may be transmitted before the start of the corresponding downlink subframe at UE **101**. The information may be in the form of an absolute time $T_{sub,r,s}$ or may be normalized to $T_{sub,C}$. For example, the uplink subframe number may be normalized to $N_{sub,r,s} = T_{sub,r,s}/T_{sub,C}$. In the normalization approach, UE **101** may calculate $T_{sub,s,u}$. The uplink subframe number for transmission from UE **101** may start with $T_{sub,s,u} + (N_{sub,r,s} + N_{sub,TA,offset}) * T_{sub,C}$ which may be before the start of the corresponding downlink subframe at UE **101**, as shown in FIG. 10. In FIG. 10, $N_{sub,TA,offset} = 0$ for simplicity. Uplink subframes from all UEs in cell **106** may arrive at gateway **103** by a delay of $2(T_{sub,common} + T_{sub,r,s})$ which may be known to gateway **103**.

[0128] Referring to FIG. 13, therein is shown an example timing offset diagram **1300** for an offset value $K_{sub,offset}$ added to a timing relationship in an NTN architecture, such as NTN communication architecture **100** of FIG. 1. A $K_{sub,offset}$ value may be used in any timing relationship, such as uplink or downlink communication between a gateway **103** and a UE **101**. A $K_{sub,offset}$ value may be an offset value added to an existing NR timing relationship between downlink and uplink transmission. In one embodiment, $K_{sub,offset}$ may be applied at the slot level within a subframe, however, it may also be applied to subframes or to frames. For example, a gNB via gateway **103** may send commands downlink to UE **101** of FIG. 1 at a specified slot n . UE **101** may then respond with an uplink transmission at a slot $n + k_2 + K_{sub,offset}$, where k_2 may be a pre-defined value. If $n = 100$, $k = 16$, and $K_{sub,offset} = 200$, then UE **101** may transmit uplink at slot $100 + 16 + 200 = 316$.

[0129] Due to propagation delays in NTN, NR timing relationships involving downlink and uplink timing interaction may be modified and enhanced. Existing NR timing relationships may use several Radio Resource Control (RRC) standard configuration parameters, such as $K_{sub,1}$ and $K_{sub,2}$, for different downlink-uplink interactions to establish a timing relationship between a gateway **103**/gNB and a UE **101**. The range of existing RRC parameters may not compensate for NTN timing advance values, and therefore, a $K_{sub,offset}$ value may be added to the downlink-uplink timing interaction for NTN.

[0130] Subframes **1301** may comprise multiple subframes, which may be divided into equally sized subframes. Each subframe may be the same duration or a different duration, and may be used to transmit and receive data between a base station or gNB via gateway **103** and a UE **101** of FIG. 1.

[0131] A subframe **1302** may be within subframes **1301**. In one embodiment, subframe **1302** may transmit data downlink from gateway **103** to UE **101** at a gateway downlink reference time **1303**, which may be received by UE **101** at a UE downlink reference time **1304**. There may be a slot number associated with gateway downlink reference time **1303** and there also may be a slot number associated with UE downlink reference time **1304**. There may be a UE propagation delay **1305**, which may be the difference between UE downlink reference time **1304** and gateway downlink reference time **1303**.

[0132] Meanwhile, UE **101** may send a subframe **1306** uplink to gateway **103** at UE uplink reference time **1307**. Subframe **1306** may arrive at gateway **103** at gateway uplink reference time **1309** with a UE propagation delay **1305**. UE uplink reference time **1307** may be determined by subtracting a UE timing advance **1308** from UE downlink reference time **1304**. In one embodiment, differential timing advance compensation may be employed, however, full timing advance compensation may also be employed, using any of the previously described methods. In one embodiment, the difference between gateway uplink reference time **1309** and gateway downlink reference time **1303** may be twice a common timing advance $T_{sub,common}$, however, any other timing advance may be used.

[0133] Meanwhile, a second subframe **1312** may be sent uplink to gateway **103** at a second UE uplink reference time **1313** and may arrive at gateway **103** at a second gateway uplink reference time **1314**. The time delay between second gateway uplink reference time **1314** and second UE uplink reference time **1313** may be UE propagation delay **1305**. Second UE uplink reference time **1313** may be calculated by adding a NR timing with $K_{sub,offset}$ time **1311** to UE uplink reference time **1307**. In one embodiment, NR timing with $K_{sub,offset}$ time **1311** may be selected by a gNB via gateway **103** to be greater than the value of UE timing advance **1308**. In one embodiment, $K_{sub,offset}$ may be the same or larger than the value of UE timing advance **1308**.

[0134] In one embodiment, each UE in a cell **106** of FIG. 1 may receive a UE-specific $K_{sub,offset}$ value from the network. In another embodiment, one $K_{sub,offset}$ value may be used for all UEs in cell **106**. A dedicated Downlink Control Information (DCI) format may be defined to send a $K_{sub,offset}$ value to each UE, which may be referred to as a group-common DCI format for configuring $K_{sub,offset}$. In one embodiment, a dedicated Radio Network Temporary Identifier (RNTI) may also be defined to send a $K_{sub,offset}$ value to each UE.

[0135] In one embodiment, a DCI format, such as DCI format 2_0 or 2_4, may be defined and used to provide $K_{sub,offset}$ values to UEs in a cell **106**, however, any DCI format standard may be used. In another embodiment, a dedicated RNTI, specified as K-RNTI, may also be used to scramble the DCI format. A UE may be addressed by its K-RNTI when receiving a DCI format. The UE may be addressed by using the K-RNTI to scramble the Cyclic Redundancy Check (CRC) bits, which may be added to the DCI payload. The UE may be configured with a K-RNTI by using a downlink parameter configuration.

[0136] Referring to FIG. 14, a group-common DCI format for configuring $K_{sub,offset}$ therein is shown. In one embodiment, $K_{sub,offset}$ may be specific to each UE in a cell **106**. In another embodiment, a dedicated DCI format may also be used for UE group common signaling, such that multiple UEs may be allocated the same K-RNTI. Multiple EUs may decode the same physical downlink control channel (PDCCH), however, each UE may only extract information addressed to the specific UE. The UE may be provided with an index or position ID information using a downlink parameter configuration. The index or position ID may transmit, or indicate, a starting position of the information relevant to the UE. As seen in FIG. 15, a DCI structure may contain n $K_{sub,offset}$ values within the DCI and each $K_{sub,offset}$ value may occupy b bits. The number of bits, b , may be extracted from the DCI payload based on the range of $K_{sub,offset}$. The value of b may be network- or cell-specific. All UEs of a network or cell within a network, such as cell **106**, may be configured with the same value of b . The maximum size of the DCI may be network- or cell-specific. The UE may be informed of the actual size of the DCI via an information element. The UE may apply the UE-specific $K_{sub,offset}$ to all of its associated downlink-uplink timing relationships, which will be described in more detail later.

[0137] Referring to FIG. 15, therein is shown an example for $K_{sub,offset}$ indication using Medium Access Control-Control Element (MAC-CE).

K.sub.offset may occupy a byte in the network to configure all UEs, such as UEs in cell **106**, by a value for m, which may be the number of bytes used to transmit, or indicate, the value of K.sub.offset. The network may then use a MAC-CE and a corresponding logical channel identity to configure UEs separately for UE-specific K.sub.offset values.

[0138] In another embodiment, K.sub.offset may be transmitted, or indicated, to a UE per-transmission in a DCI or RAR grant, during the scheduling procedure. The K.sub.offset value may be indicated depending on a downlink-uplink timing relationship. These various relationships may be described below.

[0139] In one embodiment, K.sub.offset may be based on timing for Physical Uplink Shared Channel (PUSCH) transmission that is scheduled by a DCI. In, NR, when a UE is scheduled to transmit PUSCH by a DCI, the DCI may transmit, or indicate, a slot offset value K.sub.2 as mentioned previously. For an NTN or scenarios where a satellite **102** of FIG. **1** is used in a network, K.sub.offset may be transmitted in the DCI as a new field. The slot allocated for the PUSCH may be

$$[00001] \text{.Math. } n \text{ .Math. } \frac{2}{\mu_{\text{PUSCH}}} \text{ .Math. } + K_2 + K_{\text{offset}},$$

where n may be the slot number of the scheduling DCI, K.sub.2 may be based on the numerology of PUSCH, K.sub.offset may be based on the UE's timing advance and $\mu_{\text{sub.PUSCH}}$ and $\mu_{\text{sub.PDCCH}}$ may be the subcarrier spacing configurations for PUSCH and PDCCH, respectively.

[0140] In another embodiment, K.sub.offset may be based on timing for Configured Grant Type 2, which may follow the same rules described above for timing for PUSCH transmission that is scheduled by a DCI.

[0141] In another embodiment, K.sub.offset may be based on timing for Channel State Information (CSI) transmission on PUSCH. The transmission timing of CSI on PUSCH may follow the same rules mentioned for PUSCH transmission that may be scheduled by a DCI, in the paragraph above.

[0142] In another embodiment, K.sub.offset may be based on timing for PUSCH transmission that is scheduled by a RAR grant. If a UE receives a PDSCH with a RAR message in slot n for a corresponding physical random access channel (PRACH) transmission from the same UE, then the UE may transmit the PUSCH in slot $n + K_{\text{sub.2}} + K_{\text{sub.offset}} + \Delta$, where K.sub.offset may be based on the UE's timing advance and may be indicated in the RAR grant. K.sub.2 and Δ may be defined and provided in 3GPP TS 38.214 v16.0.0, "Physical layer procedures for data (Release 16).

[0143] In another embodiment, K.sub.offset may be based on timing for Hybrid Automatic Repeat Request Acknowledgement (HARQ-ACK) transmission on Physical Uplink Control Channel (PUCCH). With reference to slots for PUCCH transmissions, for a Physical Downlink Shared Channel (PDSCH) reception in slot n or a Semi Persistent Scheduling (SPS) PDSCH release through a PDCCH reception in slot n, the UE may provide corresponding HARQ-ACK information in a PUCCH transmission within slot $n + K_{\text{sub.1}} + K_{\text{sub.offset}}$, where K.sub.offset may be indicated in the DCI, K.sub.1 may be a number of slots and may be indicated by the PDSCH-to-HARQ-timing-indicator field in the DCI format.

[0144] In another embodiment, K.sub.offset may be based on timing for CSI reference resource transmission. The CSI reference resource for a CSI report in uplink slot n may be defined by a single downlink slot

$$[00002] \text{.Math. } n \text{ .Math. } \frac{2}{\mu_{\text{DL}}} \text{ .Math. } - n_{\text{CSIref}} - K_{\text{offset}},$$

where $\mu_{\text{sub.DL}}$ and $\mu_{\text{sub.UL}}$ may be the subcarrier spacing configurations for DL and UL, respectively. The value of n.sub.CSI_ref may be defined in 3GPP TS 38.214 v16.0.0, "Physical layer procedures for data (Release 16). For aperiodic CSI reporting, the UE may be indicated by the DCI to report CSI and K.sub.offset may be based on the UE's timing advance and may be included in the DCI.

[0145] In another embodiment, K.sub.offset may be based on timing for aperiodic Sounding Reference Signal (SRS) transmission. If a UE receives a DCI triggering aperiodic SRS in slot n, the UE may transmit aperiodic SRS in each of the triggered SRS resource sets in slot

$$[00003] \text{.Math. } n \text{ .Math. } 2 \frac{\text{SRS}}{\mu_{\text{PDCCH}}} \text{ .Math. } + k + K_{\text{offset}},$$

where K.sub.offset may be based on the UE's timing advance and may be included in the DCI triggering aperiodic SRS, k may be configured via higher layer parameter slotOffset for each triggered SRS resources set, $\mu_{\text{sub.SRS}}$ and $\mu_{\text{sub.PDCCH}}$ may be the subcarrier spacing configurations for triggered SRS and PDCCH carrying the triggering command, respectively.

[0146] In another embodiment, K.sub.offset may be based on timing for a MAC control element action. When a PDSCH carries a MAC control element (MAC-CE) command, and the corresponding HARQ-ACK is transmitted in slot n, the corresponding action and the UE assumption on the downlink configuration indicated by the MAC-CE command may be applied starting from the first slot that is after slot $n + d_{\text{sub.UE}}$.

N.sub.slot.sup.subframe, $\mu + K_{\text{sub.offset}}$, where N.sub.slot.sup.subframe, μ may be the number of slots per subframe for subcarrier spacing configuration μ , and d.sub.UE may both be an integer that depends on the UE capability. The value for K.sub.offset may be indicated to the UE in the MAC-CE command.

[0147] In another embodiment, K.sub.offset may be based on timing for Configured Grant Type 1, referring to FIG. **16**. FIG. **16** may depict a timing offset diagram **1600** for Grant Type 1. Subframes **1601** may comprise multiple subframes, which may be of the same size or different size. Each subframe in subframes **1601** may have a start transmission and end transmission time, which may be represented as a slot number or time. Subframe **1602** may be a subframe within subframes **1601**. Subframe **1602** may be sent by gateway **103** at a gateway downlink reference time **1603**, which may be received by UE **101** at a UE downlink reference time **1604**. There may be a UE propagation delay **1605**, which may be the difference between UE downlink reference time **1604** and gateway downlink reference time **1603**.

[0148] UE **101** may transmit, or indicate, a subframe **1606** at a UE uplink reference time **1607**, which may be received by gateway **103** at gateway uplink reference time **1609**. There may be a UE propagation delay **1605** (not shown), which may be the difference between gateway uplink reference time **1609** and UE uplink time **1607**. UE uplink reference time **1607** may be calculated by subtracting a UE timing advance **1608** from UE downlink reference time **1604**. UE timing advance **1608** may be determined from any of the previously mentioned timing advance techniques.

[0149] Subframes **1612** may be subframes transmitted by UE **101** and may use Configuration Grant (CG) transmissions. A subframe **1613** may be a subframe within subframes **1612**. Subframes **1612** may have a period **1611** between each subframe that may be transmitted using CG transmissions. UE **101** may transmit subframe **1613** at a CG UE uplink transmission time **1614**. Gateway **103** may receive subframe **1613** at a CG gateway uplink receive time **1615**.

[0150] When using Configured Grant Type 1, a transmission occasion may start when the following equation is satisfied below, in (1):

$$[00004] ((\text{SFN} \times \text{numberOfSlotsPerFrame} \times \text{numberOfSymbolsPerSlot}) + (\text{slotnumberintheFrame} \times \text{numberOfSymbolsPerSlot}) + \text{symbolnumberintheslot}) = (\text{timeReference} \text{ modulo } (1024 \times \text{numberOfSlotsPerFrame} \times \text{numberOfSymbolsPerSlot})),$$

where timeDomainOffset and periodicity may be both specified within the ConfiguredGrantConfig parameter structure, which may be found in 3GPP TS 38.331 V16.2.0, "Radio Resource Control (RRC) protocol specification (Release 16)." SFN may be System Frame Number. S may correspond to the starting symbol deducted from the timeDomainAllocation, for example, N>0 may be an integer corresponding to an N.sub.th transmission occasion of subframes **1612**. Definitions for the terms, as described in the 3GPP TS 38.331 V16.2.0 standard, are described below: [0151] SFN: System Frame Number (which may range from 0 to 1023); [0152] numberOfSlotsPerFrame: Number of slots per frame; [0153] numberOfSymbolsPerSlot: Number of symbols per slot; [0154] slot number in the frame: a number within a frame; [0155] symbol number in the slot: a symbol number within a slot; [0156] timeReferenceSFN: SFN that may be used for determination of the offset of a resource in time domain. The UE may use the closest SFN with the indicated number preceding the reception of the configured grant configuration; [0157] timeDomainOffset: Offset of a resource with respect to SFN=timeReferenceSFN in time domain; [0158] S: corresponds to a starting symbol deducted from the timeDomainAllocation IE (TS 38.331); [0159] N: transmission occasion; and [0160] periodicity: periodicity of the configured grant Type 1.

[0161] In one embodiment, the time between CG gateway uplink receive time **1615** and CG UE uplink send time may be UE propagation delay **1605**. A gNB, via gateway **103**, may configure UE **101** timing of transmissions of subframes **1612** such that the first transmission occasion, which

may be subframe **1613**, may occur after the arrival of subframe **1606** at gateway **103** and may be referred to equation 1, the configured symbol number in the slot, which may be associated with time CG UE uplink send time **1614** may occur in an amount greater than or equal to UE timing advance **1608** after UE uplink reference time **1607**. This may be referred to as timing relationship K.sub.offset time **1610**. From gateway UL reference time **1609** to CG gateway uplink receive time **1615**, a gNB via gateway **103** may not receive any UL CG data packets. Timing relationship K.sub.offset time **1610** may be calculated by multiplying numberOfSymbolsPerSlot and K.sub.offset and then adding it to the timing for a first CG transmission. Equation 1 above shows this relationship in more detail.

[0162] In another embodiment, K.sub.offset may be based on timing for DCI format scheduled Slot-Format Indicators (SFI) and may be used for TDD, as described in FIG. 2. In one embodiment, DCI format may be DCI format 2_0, however, it may be any other DCI format as well. Referring to FIG. 17, therein is shown a timing offset diagram for K.sub.offset timing using DCI format 2_0 with scheduled SFI. SFI may be the format of a slot in DCI that may be sent to UE **101**.

[0163] Subframes **1701** may be subframes associated with a gNB via gateway **103** and may receive DCI format scheduled SFI. Subframes **1701** may have subframes with start times and/or slot numbers. There may be a DCI periodicity **1702** applied to subframes **1702**, which may include one or more of a downlink, flexible, uplink, and empty slot type and may be known as period **1702**.

[0164] In one embodiment, timing for DCI format scheduled SFI in a period **1702** may be done statically in cell-specific, UE-specific, or both manners and may use RRC signaling by information elements tdd-UL-DL-ConfigurationCommon and tdd-UL-DL-ConfigurationDedicated, which may be defined in 3GPP TS 38.331 V16.2.0, "Radio Resource Control (RRC) protocol specification (Release 16)." A gNB, via gateway **103**, may send configuration commands to UE **101** for each period **1702**. There may be downlink, uplink, and flexible subframe, frame, and/or slot configuration. The resulting slot configuration in a period **1702** may include subframes **1703**, which may include unallocated flexible slots or symbols. Gateway **103** may send a DCI format command to UE **101** for a period **1702** to configure downlink, uplink, or flexible subframes, which may include slots within subframes. There may be a DCI 2_0-configured subframes **1704** applied to subframes **1703** by making use of DCI format. Some or all of the remaining flexible slots or symbols may be dynamically configured or reconfigured in subframes **1703**.

[0165] Subframes **1703** may include unallocated flexible slots or symbols in a DCI period **1702**, which may be previously configured and may be valid, and may be dynamically configured or reconfigured as DCI configured slots or symbols **1704**. Subframes **1705** may include unallocated flexible slots or symbols in a DCI period **1702**, may be newly configured valid, and may be dynamically configured or reconfigured as DCI configured slots or symbols **1706**.

[0166] UE **101** may have UE downlink subframes **1707**, which may be subframes with downlink slots and empty slots for each DCI period **1702**. UE **101** may have UE uplink subframes **1712**, which may start at a UE uplink slot **1713** and may include empty and uplink slots in each DCI period **1702**. UE uplink subframes **1712** may include a previous uplink configuration **1714** and a new uplink configuration **1715**. Previous uplink configuration **1714** may be valid in a first period **1702** and new uplink configuration **1715** may be valid in a subsequent period **1702**.

[0167] UE **101** may be configured to monitor PDCCH for a periodicity, such as DCI period **1702**, such that UE **101** may be able to decode DCI format. UE **101** may receive DCI format data in UE downlink slot **1708**, which may include new downlink configuration data **1709**. There may be a UE downlink receive time **1711**, which may be the time UE **101** receives data from a gateway downlink transmit time **1710** and may be the start of a new DCI period **1702**.

[0168] In one embodiment, there may be a propagation delay between UE **101** sending data uplink to gateway **103** and gateway **103** sending data downlink to UE **101**. Thus, UE **101** may not reconfigure its uplink slots or symbols any time earlier than a K.sub.offset **1716** number of slots after UE uplink slot **1713**. UE **101** may reconfigure uplink slots after a number of slots UE uplink slot **1713** plus K.sub.offset **1716**, which may be indicated in SFI by a gNB via gateway **103** to UE **101**. In one embodiment, the number of slots that may be indicated in SFI may be approximately the same as K.sub.offset **1716** slots. In another embodiment, the number of slots indicated in SFI may be higher than K.sub.offset **1716**.

[0169] In another embodiment, the number of slots to be indicated in SFI by UE **101** to gateway **103** may be applying an uplink portion indicated in SFI by an amount K.sub.offset **1716** later than a current slot. The current slot may be UE uplink slot **1713**. The uplink portion indicated in SFI may be UE uplink portion **1717**. UE uplink portion **1717** may begin at UE uplink slot start **1718**, which may be K.sub.offset **1716** values or more from UE uplink slot **1713**. In another embodiment, UE uplink slot start **1718** may be fewer than K.sub.offset values from UE uplink slot **1713**. In one embodiment, UE **101** may receive an uplink portion of DCI-scheduled SFI at UE uplink slot **1713**, and may apply the provided slot format for uplink slots at K.sub.offset **1716** slots after UE Uplink slot **1713**, which may be UE uplink slot start **1718**. For uplink slots earlier than UE uplink slot start **1718**, UE **101** may use a previously configured configuration, which may be previous uplink configuration **1714**.

[0170] In another embodiment, SFI for UE uplink slot **1713** may implicitly indicate UE uplink portion **1717** at time UE uplink slot start time and UE uplink portion **1717** may be indicated by a previously-received SFI. UE **101** may apply a new slot configuration for uplink slots or symbols, which may be new uplink configuration **1715**.

[0171] In another embodiment, for downlink slots or symbols, after a UE **101** decodes a DCI format in a UE downlink slot **1708**, UE **101** may configure subsequent slots as downlink slots or symbols based on the SFI indicated to it in the DCI format, which may be new downlink configuration **1709**. In one embodiment, new downlink configuration **1709** may be based on UE **101** configuring its downlink slots or symbols for the following slots after UE downlink slot **1708** according to the SFI indicated in the DCI Format received in UE downlink slot **1708**.

[0172] In another embodiment, K.sub.offset may be based on cell- or beam-specific, dynamically indicated K.sub.offset values. All UEs in a cell **106** may be configured by a network by a single value K.sub.offset that may be an RRC parameter. K.sub.offset may be configured the same as other timing RRC parameters, such as K.sub.1 and K.sub.2, are configured, or K.sub.offset may be configured differently. K.sub.offset may be selected to support a worst-case scenario where K.sub.offset may be greater than the timing advance value of a UE with the longest timing advance in cell **106**.

[0173] FIG. 18 shows an example of a system **1800** configured to manage timing advances and K.sub.offset values, according to some embodiments. Referring to FIG. 18, the electronic device **1801** (which may be similar to, or the same as, the UE **101**) in the network environment **1800** may communicate with an electronic device **1802** via a first network **1898** (e.g., a short-range wireless communication network, such as a Wi-Fi network), or an electronic device **1804** or a server **1808** (which may be similar to, or the same as, the gNB via gateway **103**) via a second network **1899** (which may be similar to, or the same as, the network **100** which may use satellite **102**), such as a long-range wireless communication network (e.g., a cellular communication network, such as a 5G network). The electronic device **1801** may communicate with the electronic device **1804** via the server **1808**. The electronic device **1801** may include a processor **1820**, a memory **1830**, an input device **1850**, a sound output device **1855**, a display device **1860**, an audio module **1870**, a sensor module **1876**, an interface **1877**, a haptic module **1879**, a camera module **1880**, a power management module **1888**, a battery **1889**, a communication module **1890**, a subscriber identification module (SIM) **1896**, and/or an antenna module **1897**. In one embodiment, at least one of the components (e.g., the display device **1860** or the camera module **1880**) may be omitted from the electronic device **1801**, or one or more other components may be added to the electronic device **1801**. In one embodiment, some of the components may be implemented as a single integrated circuit (IC). For example, the sensor module **1876** (e.g., a fingerprint sensor, an iris sensor, or an illuminance sensor) may be embedded in the display device **1860** (e.g., a display), or the display device **1860** may include one or more sensors in addition to the sensor module **1876**.

[0174] In some embodiments, the electronic device **1801** may include a computing device or processor configured to implement managing timing advances and K.sub.offset values, such as the methods of managing timing advances and K.sub.offset values described herein.

[0175] The processor **1820** may execute, for example, software (e.g., a program **1840**) to control at least one other component (e.g., a hardware or a software component) of the electronic device **1801** coupled with the processor **1820**, and may perform various data processing and/or computations. As at least a part of the data processing and/or computations, the processor **1820** may load a command or data received from another component

(e.g., the sensor module **1876**, the communication module **1890**) in volatile memory **1832**, process the data stored in the volatile memory **1832**, and store resulting data in non-volatile memory **1834**. The processor **1820** may include a main processor **1821** (e.g., a central processing unit (CPU) or an application processor (AP)), and an auxiliary processor **1823** (e.g., a graphics processing unit (GPU), an image signal processor (ISP), a sensor hub processor, or a communication processor (CP)) that is operable independently from, or in conjunction with, the main processor **1821**. Additionally or alternatively, the auxiliary processor **1823** may be adapted to consume less power than the main processor **1821**, and/or execute a particular function. The auxiliary processor **1823** may be implemented as being separate from, or as a part of, the main processor **1821**.

[0176] The auxiliary processor **1823** may control at least some of the functions or states related to at least one component (e.g., the display device **1860**, the sensor module **1876**, or the communication module **1890**) from among the components of the electronic device **1801**, instead of the main processor **1821** while the main processor **1821** is in an inactive (e.g., sleep) state, or together with the main processor **1821** while the main processor **1821** is in an active state (e.g., executing an application). According to one embodiment, the auxiliary processor **1823** (e.g., an image signal processor or a communication processor) may be implemented as a part of another component (e.g., the camera module **1880** or the communication module **1890**) functionally related to the auxiliary processor **1823**.

[0177] The memory **1830** may store various data used by at least one component (e.g., the processor **1820** or the sensor module **1876**) of the electronic device **1801**. The various data may include, for example, software (e.g., the program **1840**) and input data or output data for a command related thereto. The memory **1830** may include the volatile memory **1832** and/or the non-volatile memory **1834**.

[0178] The program **1840** may be stored in the memory **1830** as software, and may include, for example, an operating system (OS) **1842**, middleware **1844**, or an application **1846**.

[0179] The input device **1850** may receive a command or data to be used by another component (e.g., the processor **1820**) of the electronic device **1801**, from the outside (e.g., a user) of the electronic device **1801**. The input device **1850** may include, for example, a microphone, a mouse, and/or a keyboard.

[0180] The sound output device **1855** may output sound signals to the outside of the electronic device **1801**. The sound output device **1855** may include, for example, a speaker or a receiver. The speaker may be used for general purposes, such as playing multimedia or recording, and the receiver may be used for receiving an incoming call. According to one embodiment, the receiver may be implemented as being separate from, or as a part of, the speaker.

[0181] The display device **1860** may visually provide information to the outside (e.g., a user) of the electronic device **1801**. The display device **1860** may include, for example, a display, a hologram device, and/or a projector and control circuitry to control a corresponding one of the display, the hologram device, and the projector. According to one embodiment, the display device **1860** may include touch circuitry adapted to detect a touch, or sensor circuitry (e.g., a pressure sensor) adapted to measure the intensity of force incurred by the touch.

[0182] The audio module **1870** may convert a sound into an electrical signal and vice versa. According to one embodiment, the audio module **1870** may obtain the sound via the input device **1850**, and/or output the sound via the sound output device **1855** or a headphone of an external electronic device **1802** directly (e.g., wired) or wirelessly coupled with the electronic device **1801**.

[0183] The sensor module **1876** may detect an operational state (e.g., power or temperature) of the electronic device **1801** and/or an environmental state (e.g., a state of a user) external to the electronic device **1801**, and then generate an electrical signal or data value corresponding to the detected state. The sensor module **1876** may include, for example, a gesture sensor, a gyro sensor, an atmospheric pressure sensor, a magnetic sensor, an acceleration sensor, a grip sensor, a proximity sensor, a color sensor, an infrared (IR) sensor, a biometric sensor, a temperature sensor, a humidity sensor, and/or an illuminance sensor.

[0184] The interface **1877** may support one or more specified protocols to be used for the electronic device **1801** to be coupled with the external electronic device **1802** directly (e.g., wired) or wirelessly. According to one embodiment, the interface **1877** may include, for example, a high definition multimedia interface (HDMI), a universal serial bus (USB) interface, a secure digital (SD) card interface, and/or an audio interface.

[0185] A connecting terminal **1878** may include a connector via which the electronic device **1801** may be physically connected with the external electronic device **1802**. According to one embodiment, the connecting terminal **1878** may include, for example, an HDMI connector, a USB connector, an SD card connector, and/or an audio connector (e.g., a headphone connector).

[0186] The haptic module **1879** may convert an electrical signal into a mechanical stimulus (e.g., a vibration or a movement) and/or an electrical stimulus which may be recognized by a user via tactile sensation or kinesthetic sensation. According to one embodiment, the haptic module **1879** may include, for example, a motor, a piezoelectric element, and/or an electrical stimulator.

[0187] The camera module **1880** may capture a still image or moving images. According to one embodiment, the camera module **1880** may include one or more lenses, image sensors, image signal processors, and/or flashes.

[0188] The power management module **1888** may manage power supplied to the electronic device **1801**. The power management module **1888** may be implemented as at least a part of, for example, a power management integrated circuit (PMIC).

[0189] The battery **1889** may supply power to at least one component of the electronic device **1801**. According to one embodiment, the battery **1889** may include, for example, a primary cell which is not rechargeable, a secondary cell which is rechargeable, and/or a fuel cell.

[0190] The communication module **1890** may support establishing a direct (e.g., wired) communication channel or a wireless communication channel between the electronic device **1801** and the external electronic device (e.g., the electronic device **1802**, the electronic device **1804**, and/or the server **1808**) and performing communication via the established communication channel. The communication module **1890** may include one or more communication processors that are operable independently from the processor **1820** (e.g., the AP) and may support a direct (e.g., wired) communication and/or a wireless communication. According to one embodiment, the communication module **1890** may include a wireless communication module **1892** (e.g., a cellular communication module, a short-range wireless communication module, and/or a global navigation satellite system (GNSS) communication module) or a wired communication module **1894** (e.g., a local area network (LAN) communication module or a power line communication (PLC) module). A corresponding one of these communication modules may communicate with the external electronic device via the first network **1898** (e.g., a short-range communication network, such as Bluetooth®, wireless-fidelity (Wi-Fi) direct, and/or a standard of the Infrared Data Association (IrDA)) or the second network **1899** (e.g., a long-range communication network, such as a cellular network, the Internet, and/or a computer network (e.g., LAN or wide area network (WAN))). Bluetooth® is a registered trademark of Bluetooth SIG, Inc., Kirkland, WA.

[0191] These various types of communication modules may be implemented as a single component (e.g., a single IC), or may be implemented as multiple components (e.g., multiple ICs) that are separate from each other. The wireless communication module **1892** may identify and authenticate the electronic device **1801** in a communication network, such as the first network **1898** or the second network **1899**, using subscriber information (e.g., international mobile subscriber identity (IMSI)) stored in the subscriber identification module **1896**.

[0192] The antenna module **1897** may transmit and/or receive a signal and/or power to and/or from the outside (e.g., the external electronic device) of the electronic device **1801**. According to one embodiment, the antenna module **1897** may include one or more antennas, and, therefrom, at least one antenna appropriate for a communication scheme used in the communication network, such as the first network **1898** and/or the second network **1899**, may be selected, for example, by the communication module **1890** (e.g., the wireless communication module **1892**). The signal and/or the power may then be transmitted and/or received between the communication module **1890** and the external electronic device via the selected at least one antenna.

[0193] At least some of the above-described components may be mutually coupled and communicate signals (e.g., commands and/or data)

therebetween via an inter-peripheral communication scheme (e.g., a bus, a general purpose input and output (GPIO), a serial peripheral interface (SPI), and/or a mobile industry processor interface (MIPI)).

[0194] According to one embodiment, commands and/or data may be transmitted and/or received between the electronic device **1801** and the external electronic device **1804** via the server **1808** coupled with the second network **1899**. Each of the electronic devices **1802** and **1804** may be a device of a same type as, or a different type from, the electronic device **1801**. All or some of operations to be executed at or by the electronic device **1801** may be executed at one or more of the external electronic devices **1802**, **1804**, or the server **1808**. For example, if the electronic device **1801** should perform a function and/or a service automatically, or in response to a request from a user or another device, the electronic device **1801**, instead of, or in addition to, executing the function and/or the service, may request the one or more external electronic devices to perform at least a part of the function and/or the service. The one or more external electronic devices receiving the request may perform the at least a part of the function and/or the service requested, and/or an additional function and/or an additional service related to the request, and transfer an outcome of the performing to the electronic device **1801**. The electronic device **1801** may provide the outcome, with or without further processing of the outcome, as at least a part of a reply to the request. To that end, a cloud computing, distributed computing, and/or client-server computing technology may be used, for example.

[0195] One embodiment may be implemented as software (e.g., the program **1840**) including one or more instructions that are stored in a storage medium (e.g., internal memory **1836** or external memory **1838**) that is readable by a machine (e.g., the electronic device **1801**). For example, a processor of the electronic device **1801** may invoke at least one of the one or more instructions stored in the storage medium, and execute it, with or without using one or more other components under the control of the processor. Thus, a machine may be operated to perform at least one function according to the at least one instruction invoked. The one or more instructions may include code generated by a compiler or code executable by an interpreter. A machine-readable storage medium may be provided in the form of a non-transitory storage medium. The term “non-transitory” indicates that the storage medium is a tangible device, and does not include a signal (e.g., an electromagnetic wave), but this term does not differentiate between where data is semi-permanently stored in the storage medium and where the data is temporarily stored in the storage medium.

[0196] As used herein, “a portion of” something means “at least some of” the thing, and as such may mean less than all of, or all of, the thing. As such, “a portion of” a thing includes the entire thing as a special case, i.e., the entire thing is an example of a portion of the thing.

[0197] As used herein, the term “array” refers to an ordered set of numbers regardless of how stored (e.g., whether stored in consecutive memory locations, or in a linked list). As used herein, the term “rectangle” includes a square as a special case, i.e., a square is an example of a rectangle. As used herein, the term “or” should be interpreted as “and/or”, such that, for example, “A or B” means any one of “A” or “B” or “A and B”.

[0198] As used herein, when a method (e.g., an adjustment) or a first quantity (e.g., a first variable) is referred to as being “based on” a second quantity (e.g., a second variable) it means that the second quantity is an input to the method or influences the first quantity, e.g., the second quantity may be an input (e.g., the only input, or one of several inputs) to a function that calculates the first quantity, or the first quantity may be equal to the second quantity, or the first quantity may be the same as (e.g., stored at the same location or locations in memory) as the second quantity.

[0199] It will be understood that, although the terms “first”, “second”, “third”, etc., may be used herein to describe various elements, components, regions, layers and/or sections, these elements, components, regions, layers and/or sections should not be limited by these terms. These terms are only used to distinguish one element, component, region, layer or section from another element, component, region, layer or section. Thus, a first element, component, region, layer or section discussed herein could be termed a second element, component, region, layer or section, without departing from the spirit and scope of the inventive concept.

[0200] Spatially relative terms, such as “beneath”, “below”, “lower”, “under”, “above”, “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. It will be understood that such spatially relative terms are intended to encompass different orientations of the device in use or in operation, in addition to the orientation depicted in the figures. For example, if the device in the figures is turned over, elements described as “below” or “beneath” or “under” other elements or features would then be oriented “above” the other elements or features. Thus, the example terms “below” and “under” can encompass both an orientation of above and below. The device may be otherwise oriented (e.g., rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein should be interpreted accordingly. In addition, it will also be understood that when a layer is referred to as being “between” two layers, it can be the only layer between the two layers, or one or more intervening layers may also be present.

[0201] The terminology used herein is for the purpose of describing particular embodiments only and is not intended to be limiting of the inventive concept. As used herein, the terms “substantially”, “about”, and similar terms are used as terms of approximation and not as terms of degree, and are intended to account for the inherent deviations in measured or calculated values that would be recognized by those of ordinary skill in the art. As used herein, the term “major component” refers to a component that is present in a composition, polymer, or product in an amount greater than an amount of any other single component in the composition or product. In contrast, the term “primary component” refers to a component that makes up at least 50% by weight or more of the composition, polymer, or product. As used herein, the term “major portion”, when applied to a plurality of items, means at least half of the items.

[0202] As used herein, the singular forms “a” and “an” are intended to include the plural forms as well, unless the context clearly indicates otherwise. It will be further understood that the terms “comprises” and/or “comprising”, when used in this specification, specify the presence of stated features, integers, steps, operations, elements, and/or components, but do not preclude the presence or addition of one or more other features, integers, steps, operations, elements, components, and/or groups thereof. As used herein, the term “and/or” includes any and all combinations of one or more of the associated listed items. Expressions such as “at least one of,” when preceding a list of elements, modify the entire list of elements and do not modify the individual elements of the list. Further, the use of “may” when describing embodiments of the inventive concept refers to “one or more embodiments of the present disclosure”. Also, the term “exemplary” is intended to refer to an example or illustration. As used herein, the terms “use,” “using,” and “used” may be considered synonymous with the terms “utilize,” “utilizing,” and “utilized,” respectively.

[0203] It will be understood that when an element or layer is referred to as being “on”, “connected to”, “coupled to”, or “adjacent to” another element or layer, it may be directly on, connected to, coupled to, or adjacent to the other element or layer, or one or more intervening elements or layers may be present. For example, if a first component is “connected to” a second component, a third component may be connected between the first component and the second component (e.g., a first side of the third component may be connected to the first component, and a second side of the third component may be connected to the second component). In contrast, when an element or layer is referred to as being “directly on”, “directly connected to”, “directly coupled to”, or “immediately adjacent to” another element or layer, there are no intervening elements or layers present.

[0204] Any numerical range recited herein is intended to include all sub-ranges of the same numerical precision subsumed within the recited range. For example, a range of “1.0 to 10.0” or “between 1.0 and 10.0” is intended to include all subranges between (and including) the recited minimum value of 1.0 and the recited maximum value of 10.0, that is, having a minimum value equal to or greater than 1.0 and a maximum value equal to or less than 10.0, such as, for example, 2.4 to 7.6. Any maximum numerical limitation recited herein is intended to include all lower numerical limitations subsumed therein and any minimum numerical limitation recited in this specification is intended to include all higher numerical limitations subsumed therein.

[0205] Although exemplary embodiments of a to wireless communication networks, and more particularly managing timing advance and offset values for uplink transmissions have been specifically described and illustrated herein, many modifications and variations will be apparent to those skilled in the art. Accordingly, it is to be understood that a to wireless communication networks, and more particularly to managing timing advance and offset values for uplink transmissions constructed according to principles of this disclosure may be embodied other than as specifically described herein. The invention is also defined in the following claims, and equivalents thereof.

Claims

1.-20. (canceled)

21. A method of enabling communication between a user equipment (UE) and a non-terrestrial network (NTN), comprising: receiving, at the UE, a K.sub.offset value, wherein the K.sub.offset value is transmitted to the UE by the NTN; identifying, at the UE, data communicated to or from the NTN; and applying, at the UE, the K.sub.offset value to configure communication of the data to or from the NTN.

22. The method of claim 21, wherein the UE receives the K.sub.offset value in a group common downlink control information (DCI) format, and/or a medium access control-control element (MAC-CE) format, and the K.sub.offset value is a fixed number of bits.

23. The method of claim 21, wherein the UE receives the K.sub.offset value different from a second K.sub.offset value received by a second UE.

24. The method of claim 21, wherein the K.sub.offset value is used in a configured grant type 1 transmission, wherein the UE adds an offset of K.sub.offset multiplied by a number of symbols per slot value to a timing for the configured grant type 1 transmission.

25. The method of claim 21, wherein the K.sub.offset value is used in a configured grant type 2 transmission, wherein the UE schedules to transmit a Physical Uplink Shared Channel (PUSCH) by a downlink control information (DCI) by adding a K.sub.offset value to the configured grant type 2 transmission.

26. The method of claim 21, wherein the K.sub.offset value is used for a slot format indicator (SFI) to dynamically configure and reconfigure symbols or slots in a subframe, wherein the UE configures and reconfigures the symbols or slots at least K.sub.offset slots after an uplink slot.

27. The method of claim 21, wherein the K.sub.offset value is used for timing for a channel state information (CSI) transmission on a Physical Uplink Shared Channel (PUSCH).

28. The method of claim 21, wherein the K.sub.offset value is used for timing for a Physical Uplink Shared Channel (PUSCH) transmission scheduled by a Random Access Response (RAR) grant.

29. The method of claim 21, wherein the K.sub.offset value is used for Hybrid Automatic Repeat Request Acknowledgement (HARQ-ACK) transmission on a Physical Uplink Control Channel (PUCCH).

30. The method of claim 21, wherein the K.sub.offset value is used for timing for a channel state information (CSI) reference resource transmission.

31. The method of claim 21, wherein the K.sub.offset value is used for timing for aperiodic sounding reference signal (SRS) transmission.

32. The method of claim 21 further comprising: receiving a position of a satellite associated with the NTN; calculating, by the UE, a timing advance based on a first distance from the UE to the satellite; and applying, by the UE, the timing advance to configure the communication of the data to or from the NTN.

33. The method of claim 32, wherein the K.sub.offset value is greater than or equal to the timing advance.

34. The method of claim 32 further comprising: receiving, at the UE, position of a gateway; calculating a second distance between the position of the satellite and the position of the gateway; and calculating the timing advance based on the second distance.

35. The method of claim 34, wherein the UE calculates the timing advance by: calculating a first propagation delay based on the first distance; calculating a second propagation delay based on the second distance; and summing the first propagation delay and the second propagation delay.

36. The method of claim 32, wherein the timing advance is a full timing advance compensation.

37. A user equipment (UE) device configured to: receive a K.sub.offset value, wherein the K.sub.offset value is transmitted to the UE by a non-terrestrial network (NTN); identify data communicated to or from the NTN; and apply the K.sub.offset value to configure communication of the data to or from the NTN.

38. The user equipment device of claim 37, wherein the UE is configured to receive the K.sub.offset value in a group common downlink control information (DCI) format, and/or a medium access control-control element (MAC-CE) format, and the K.sub.offset value is a fixed number of bits.

39. The user equipment device of claim 37, wherein is configured to receive the K.sub.offset value different from a second K.sub.offset value received by a second UE.

40. The user equipment device of claim 37, wherein the UE device is configured to: calculate a timing advance based on a first distance from the UE to the NTN; and apply the timing advance to configure the communication of the data to or from the NTN.
