

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12410777
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Shenoy; Suratkal P. et al.

Turboexpander islanding operation

Abstract

A turboexpander can operate as a microgrid electric generator for islanding operations. The turboexpander can recover energy lost during a pressure letdown sequence to generate electricity. Pressurized process gas can cause a turbine to rotate, thereby rotating a rotor within a stator of the turboexpander. A power electronics can include an islanding mode inverter to output an alternating current that comprises a frequency and an amplitude compatible with powering a load. The power electronics can include a battery that is charged by the turboexpander and can provide power for starting up the turboexpander. The power electronics can include a bidirectional inverter to send excess power from the turboexpander to a power grid and to receive power from the power grid for start-up.

Inventors: Shenoy; Suratkal P. (Cerritos, CA), Zheng; Liping (Cerritos, CA), Liu; Jeremy (Norwalk, CA), Sarhan; Freddie (Cerritos, CA)

Applicant: Sapphire Technologies, Inc. (Cerritos, CA)

Family ID: 86899228

Assignee: Sapphire Technologies, Inc. (Cerritos, CA)

Appl. No.: 18/674262

Filed: May 24, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240309846 A1	Sep. 19, 2024

Related U.S. Application Data

continuation parent-doc US 17804265 20220526 US 11994115 child-doc US 18674262

Publication Classification

Int. Cl.: F03D9/25 (20160101); F03D9/17 (20160101); H02J3/38 (20060101)

U.S. Cl.:

CPC F03D9/255 (20170201); F03D9/17 (20160501); H02J3/381 (20130101); H02J3/388 (20200101); F05B2220/20 (20130101); F05B2220/602 (20130101); F05B2220/7062 (20130101)

Field of Classification Search

CPC: H02J (3/381); H02J (3/388); F05B (2220/60); F03D (9/17); F03D (9/255)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5689175	12/1996	Hanson et al.	N/A	N/A
7408268	12/2007	Nocentini	307/16	H02J 3/38
7638892	12/2008	Myers	N/A	N/A
8146360	12/2011	Myers et al.	N/A	N/A
8384232	12/2012	Myers et al.	N/A	N/A
8400005	12/2012	Huber et al.	N/A	N/A
8739538	12/2013	Myers et al.	N/A	N/A
8839622	12/2013	Myers et al.	N/A	N/A
2002/0060556	12/2001	Wall	322/29	H02J 3/38
2002/0190695	12/2001	Wall et al.	N/A	N/A
2004/0135436	12/2003	Gilbreth	307/18	H02J 1/14
2011/0103110	12/2010	Godridge	363/74	H02M 7/53875
2012/0013125	12/2011	Myers et al.	N/A	N/A
2012/0306201	12/2011	Sorensen	N/A	N/A
2013/0286591	12/2012	Myers et al.	N/A	N/A
2016/0369692	12/2015	Wardle et al.	N/A	N/A
2017/0214335	12/2016	Basic	N/A	H02M 7/48
2019/0044335	12/2018	Soverns	N/A	H02J 3/18

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
212376707	12/2020	CN	N/A

OTHER PUBLICATIONS

International Preliminary Report on Patentability in International Appln. No. PCT/US2023/023587, mailed on Dec. 5, 2024, 9 pages. cited by applicant

International Search Report and Written Opinion in International Appln. No. PCT/US2023/023587, mailed on Sep. 15, 2023, 14 pages. cited by applicant

Primary Examiner: Gugger; Sean

Background/Summary

RELATED APPLICATIONS

(1) This application claims priority to application Ser. No. 17/804,265, filed on May 26, 2022. The entire contents of which is hereby incorporated by reference in its entirety.

BACKGROUND

(2) The efficient and effective movement of gases from producing regions to consumption regions uses an extensive and elaborate transportation system. Gases transported via pipelines can be pressurized and can traverse long distances through pipelines at high pressures. For example, natural gas that is transported through pipelines travels at high pressure in the pipeline. Natural gas is one of the principal sources of energy for many of our day-to-day needs and activities. Natural gas is an attractive fossil fuel for its abundance and relative cleanliness. As another example, hydrogen can also be transported at high pressures using pipelines. Hydrogen is a rapidly expanding global energy storage market. Hydrogen is used in many manufacturing processes from petroleum refining to food processing. Hydrogen is also used as a fuel source for gas turbines and in a broad range of fuel cells to generate electricity in industrial and consumer transportation sectors. Other gases can also be transported through pipelines at high pressures, including propane, oxygen, carbon dioxide, and others.

SUMMARY

(3) Aspects of the embodiments include an apparatus that includes an electric generator. The electric generator includes a turbine wheel configured to receive process gas and rotate in response to expansion of the process gas flowing into an inlet of the turbine wheel and out of an outlet of the turbine wheel, a rotor coupled to the turbine wheel and configured to rotate with the turbine wheel, and a stationary stator, the electric generator to generate an alternating current upon rotation of the rotor within the stator. The apparatus includes a power converter circuit coupled to an electrical output of the electric generator, the power converter circuit to convert alternating current from the electric generator into direct current; and an islanding mode inverter circuit coupled to an electrical output of the rectifier circuit, the inverter circuit to convert direct current from the rectifier circuit into an alternating current that comprises a frequency and an amplitude to provide power to a load.

(4) Aspects of the embodiments include a system comprising an electric generator and a power electronics. The electric generator includes a turbine wheel configured to receive process gas and rotate in response to expansion of the process gas flowing into an inlet of the turbine wheel and out of an outlet of the turbine wheel, a rotor coupled to the turbine wheel and configured to rotate with the turbine wheel, and a stationary stator, the electric generator to generate an alternating current upon rotation of the rotor within the stator. The power electronics includes a power converter circuit coupled to an electrical output of the electric generator, the power converter circuit to convert alternating current from the electric generator into direct current; and an islanding mode inverter circuit coupled to an electrical output of the rectifier circuit, the inverter circuit to convert direct current from the rectifier circuit into an alternating current that comprises a frequency and an amplitude to provide power to a load.

(5) Some aspects of the embodiments include a brake resistor rectifier coupled to the electrical output of the electric generator; and a brake resistor assembly coupled to the output of the brake resistor rectifier.

(6) In some implementations of the embodiments, the brake resistor assembly comprises a speed controlled, current regulated brake resistor.

(7) Some aspects of the embodiments include a battery coupled to the electric generator, the battery

to store power received from the electric generator and to provide power to rotate the rotor within the stator.

(8) In some implementations of the embodiments, the battery is coupled to the power converter circuit, the power converter circuit to receive alternating current from the electric generator and convert the alternating current to a direct current for storage in the battery; and receive direct current from the battery and convert the direct current into alternating current to power the rotor.

(9) Some aspects of the embodiments include a bidirectional inverter including the islanding mode inverter circuit; and an active grid inverter to convert direct current into alternating current that comprises a frequency and amplitude compatible with a power grid.

(10) In some implementations of the embodiments, the bidirectional inverter is to provide power to the load and to provide excess power to the power grid.

(11) In some implementations of the embodiments, the bidirectional inverter is to supply power from the power grid to the rotor to rotate the rotor within the stator prior to the process gas rotating the turbine wheel.

(12) In some implementations of the embodiments, the electric generator comprises a three-phase permanent magnet synchronous generator.

(13) Some aspects of the embodiments include a bidirectional inverter to direct current to the load and to direct excess current to a power grid.

(14) In some implementations of the embodiments, the bidirectional inverter comprises an active grid inverter to direct power to the power grid and to receive power from the power grid.

(15) Aspects of the embodiments are directed to a method that includes causing gas to flow through a turbine wheel of an electric generator residing downstream of a flow control valve; generating electrical current by the electric generator; directing electrical current generated by the electric generator to an islanding mode power electronics; and directing electrical current from the islanding mode power electronics to a load.

(16) Some aspects of the embodiments include directing excess electrical current by the electric generator generated not directed to the load to a power grid through an active grid inverter.

(17) Some aspects of the embodiments include performing a start-up of the electric generator using power received by the power grid through the active grid inverter.

(18) Some aspects of the embodiments include directing excess electrical current by the electric generator generated not directed to the load to a battery.

(19) Some aspects of the embodiments include performing a start-up of the electric generator using power received from the battery.

(20) In some implementations, the islanding mode inverter circuit comprises a circuitry to receive direct current on a DC bus; convert the direct current to alternating current; and condition the alternating current into a frequency and amplitude compatible with the load.

(21) Some aspects of the embodiments include a master controller circuit to control current flow to a brake resistor during a fault condition.

(22) Some aspects of the embodiments include an active rectifier electrically connected between the electric generator and the brake resistor, the master controller to activate the active rectifier upon detecting a fault condition to direct current from the electric generator to the brake resistor based on the presence of the fault condition.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a schematic diagram of an electric power generation system coupled to a power grid in accordance with embodiments of the present disclosure.

(2) FIG. 2 is a schematic diagram of an example turboexpander system that supports islanding

operations without a grid source in accordance with embodiments of the present disclosure.

(3) FIG. 3 is a schematic diagram of an example turboexpander system that includes a bidirectional inverter for islanding operation in accordance with embodiments of the present disclosure.

(4) FIG. 4A is a schematic diagram of an example turboexpander converter in accordance with embodiments of the present disclosure.

(5) FIG. 4B is a schematic diagram of an example islanding mode inverter in accordance with embodiments of the present disclosure.

(6) FIG. 5 is a process flow diagram for supporting islanding operation using a turboexpander in accordance with embodiments of the present disclosure.

(7) Like reference symbols in the various drawings indicate like elements. Drawings not to scale.

DETAILED DESCRIPTION

(8) Natural gas, hydrogen, and other process gases are pressurized to facilitate efficient transportation in pipelines that are sometimes many miles long. The pipelines, for example, transport gasses from production sites (e.g., wells) to processing facilities and from processing facilities to local distribution networks, such as regional, city or district networks or on-site industrial plants networks. To deliver the gas safely through local distribution networks and for use, the process gas is depressurized to lower levels (often using pressure regulators). The pressure is stepped down at pressure letdown (PLD) stations for delivery to industrial, commercial, and residential end users. The PLD stations use regulating valves to achieve the required pressure drop, but also waste significant amounts of energy in the process. Additional regulating valves can be used at other locations for pressure control, such as in the pipelines between the production and processing facilities, within the sub-processes of the processing facilities, and within the end user's processes and piping. A turboexpander generator can be installed in parallel to the regulating valve to recover the wasted energy from pressure reduction and produce electrical power. The electrical power can be directed to a power grid or elsewhere. Along the same lines, a turboexpander generator can be installed at a gas storage facility upstream of one or more storage tanks to recover high pressure gasses dispensed from a tanker truck, through the turboexpander generator, to the storage tanks. The turboexpander generator is relevant in other applications, such as in a hydrogen liquefaction process where gaseous hydrogen that has been cooled and pressurized is expanded to a liquid state. The expansion can be performed through a turboexpander generator to recover the wasted energy from the expansion and produce electrical power. As above, the electrical power can be directed to a power grid or elsewhere, such as used to power compressors or other components of the liquefaction process. In each instance, by recovering lost energy from natural gas and hydrogen pressure letdown applications, the turboexpander can generate electricity while also reducing CO₂ emissions, increasing overall plant efficiency, offsetting electrical costs, and generating additional revenue.

(9) The power grid that the turboexpander can supply power to (and draw power from) can be a national or regional power grid, a local power grid for a city or district, or a small grid, local grid, or microgrid, such as an on-site grid that supplies power to a building, campus, industrial manufacturing or processing plant, or neighborhood.

(10) FIG. 1 is a schematic diagram of an electric power generation system **100** coupled to a power grid **140** in accordance with embodiments of the present disclosure. The electric power generation system **100** can be added at a PLD station to capture energy from gas expansion from the PLD process, or in any of the other applications described above. The electric power generation system **100** includes a turboexpander **102** in parallel with a pressure control valve **130**. The turboexpander **102** is arranged axially so that the turboexpander **102** can be mounted in-line with a pipe. The turboexpander **102** acts as an electric generator by generating electrical energy from rotational kinetic energy derived from expansion of a gas through a turbine wheel **104**. For example, rotation of the turbine wheel **104** can be used to rotate a rotor **108** within a stator **110**, which then generates electrical energy.

(11) FIG. 1 is a schematic diagram of an electric power generation system **100** coupled to a power grid **140** in accordance with embodiments of the present disclosure. The electric power generation system **100** can be added at a PLD station to capture energy from gas expansion from the PLD process. The electric power generation system **100** includes a turboexpander **102** in parallel with a pressure control valve **130**. The turboexpander **102** is arranged axially so that the turboexpander **102** can be mounted in-line with a pipe. The turboexpander **102** acts as an electric generator by generating electrical energy from rotational kinetic energy derived from expansion of a gas through a turbine wheel **104**. For example, rotation of the turbine wheel **104** can be used to rotate a rotor **108** within a stator **110**, which then generates electrical energy.

(12) The turboexpander **102** can include a high-performance, high-speed permanent magnet generator. In certain embodiments, the turboexpander **102** includes an a radial in-flow expansion turbine wheel **104**. Turboexpander **102** can also include low loss active magnetic bearings (AMBs) **116a,b**. The rotor assembly can include permanent magnet section with the turbine wheel **104** mounted directly to the rotor hub. The rotor **108** can be levitated by the magnetic bearing system creating a frictionless (or near frictionless) interface between dynamic and static components. The AMBs **116a,b** facilitate a lossless (or near lossless) rotation of the rotor **108**.

(13) The turboexpander **102** is shown to have the process gas flow through the system, which cools the generator section and eliminates the need for auxiliary cooling equipment. In some embodiments, non-flow-through overhung systems can also be implemented. The power electronics **118** for turboexpander combines a Variable Speed Drive (VSD) **166** and Magnetic Bearing Controller (MBC) **168** into one cabinet, in some implementations. The VSD allows for a consistent and clean delivery of generated power from the turboexpander **102** to a power grid **140**. The VSD **166** regulates the frequency and amplitude of the generated current to match the local grid. After expansion, the gas exits the turboexpander **102** along the same axial path for downstream processes.

(14) The turboexpander **102** is shown as having a flow-through configuration. The flow-through configuration permits process gas to flow from an inlet side of the turboexpander **102** to an outlet side of the turboexpander **102**. The gas flows into a radial gas inlet **154** to a turbine wheel **104** and an axial gas outlet **156** from the turbine wheel **104**. The gas then flow through the generator and out of the outlet **156**, where the gas rejoins the gas pipeline **170**. Generally, high pressure process gas **120** is directed to flow into the turboexpander **102** through a flow control system **126**. The flow control system **126** includes a flow or mass control valve and an emergency shut off valve. Flow control system **126** can be controlled electrically from power electronics **118** by control line **164**. In embodiments, the turboexpander housing **112** is hermetically sealed. As mentioned above, the turboexpander can be non-flow-through and overhung without deviating from the scope of this disclosure. The high pressure process gas **120** is expanded by flowing through the turbine wheel **104**, resulting in a pressure letdown of the process gas. Lower pressure process gas **128** exits the turboexpander. The expansion of the high pressure process gas **120** through the turbine wheel **104** causes the turbine wheel **104** to rotate, which causes the rotor **108** to rotate. The rotation of the rotor **108** within the stator **110** generates electrical energy. The turboexpander **102** achieves the desired pressure letdown and captures the energy from the pressure letdown to generate electricity. A pressure control valve **130**, such as a conventional pressure regulator, can be installed in parallel to the turboexpander **102**. The pressure control valve **130** can be used to control the pressure of the high pressure process gas **120** that flows through the turboexpander. Any excess high pressure process gas that is not directed into the turboexpander can be directed through the pressure control valve **130**.

(15) In some embodiments, a heater **122** can heat the high pressure process gas **120** prior to flowing the gas into the turboexpander **102**. For example, if the expansion of the gas through the turbine wheel **104** lowers the temperature of the process gas to a point where moisture in the gas freezes at the turbine wheel or other downstream locations in the pipeline, the pressurized process

gas **120** can be heated by heater **122**. Heated high pressure process gas **124** can then be directed into the turboexpander **102**. The heating of the process gas can prevent freezing moisture as the gas expands and its temperature drops.

(16) The turboexpander **102** includes a turbine wheel **104**. The turbine wheel **104** is shown as a radial inflow turbine wheel, though other configurations are within the scope of this disclosure, such as axial flow turbine wheels. In this example, heated high pressure process gas **124** is received from an inlet conduit **150** of the housing **112** enters a radially oriented inlet **154** of the turbine wheel **104**. In certain embodiments, the fluid flows through an inlet conduit **150** and is diverted by a flow diverter to a radial inlet **154** that directs the flow into the radial inflow of the turbine wheel **104**. After expanding, the lower pressure process gas exits the turbine wheel **104** from an axially oriented outlet **156** to outlet conduit **152** of the housing **112**.

(17) The turbine wheel **104** can be directly affixed to the rotor **108**, or to an intermediate common shaft, for example, by fasteners, rigid drive shaft, welding, or other manner. For example, the turbine wheel **104** may be received at an end of the rotor **108**, and held to the rotor **108** with a shaft. The shaft threads into the rotor **108** at one end, and at the other, captures the turbine wheel **104** between the end of rotor **108** and a nut threadingly received on the shaft. The turbine wheel **104** and rotor **108** can be coupled without a gearbox and rotate at the same speed. In other instances, the turbine wheel **104** can be indirectly coupled to the rotor **108**, for example, by a gear train, clutch mechanism, or other manner.

(18) The turbine wheel **104** includes a plurality of turbine wheel blades **106** extending outwardly from a hub and that react with the expanding process gas to cause the turbine wheel **104** to rotate. FIG. **1** shows an unshrouded turbine wheel, in which each of the turbine blades **106** has an exposed, generally radially oriented blade tip extending between the radial inlet **154** and axial outlet **156**. As discussed in more detail below, the blade tips substantially seal against a shroud **114** on the interior of the housing **112**. In certain instances, the turbine wheel **104** is a shrouded turbine wheel.

(19) In configurations with an un-shrouded turbine wheel **104**, the housing **112** includes an inwardly oriented shroud **114** that resides closely adjacent to, and at most times during operation, out of contact with the turbine wheel blades **106**. The close proximity of the turbine wheel blades **106** and shroud **114** substantially seals against passage of process gas therebetween, as the process gas flows through the turbine wheel **104**. Although some amount of the process gas may leak or pass between the turbine wheel blades **106** and the shroud **114**, the leakage is insubstantial in the operation of the turbine wheel **104**. In certain instances, the leakage can be commensurate with other similar unshrouded-turbine/shroud-surface interfaces, using conventional tolerances between the turbine wheel blades **106** and the shroud **114**. The amount of leakage that is considered acceptable leakage may be predetermined. The operational parameters of the turbine generator may be optimized to reduce the leakage. In embodiments, the housing **112** is hermetically sealed to prevent process gases from escaping the radial inlet **154** of the turbine wheel **104**.

(20) The shroud **114** may reside at a specified distance away from the turbine wheel blades **106**, and is maintained at a distance away from the turbine wheel blades **106** during operation of the turboexpander **102** by using magnetic positioning devices, including active magnetic bearings and position sensors.

(21) Bearings **116a** and **116b** are arranged to rotatably support the rotor **108** and turbine wheel **104** relative to the stator **110** and the shroud **114**. The turbine wheel **104** is supported in a cantilevered manner by the bearings **116a** and **116b**. In embodiments, the turbine wheel **104** may be supported in a non-cantilevered manner and bearings **116a** and **116b** may be located on the outlet side of turbine wheel **104**. In certain instances, one or more of the bearings **116a** or **116b** can include ball bearings, needle bearings, magnetic bearings, foil bearings, journal bearings, or others.

(22) Bearings **116a** and **116b** may be a combination radial and thrust bearing, supporting the rotor **108** in radial and axial directions. Other configurations could be utilized. The bearings **116a** and

116b need not be the same types of bearings.

(23) In the embodiments in which the bearings **116a** and **116b** are magnetic bearings, a magnetic bearing controller (MBC) **168** is used to control the magnetic bearings **116a** and **116b**. Position sensors **117a**, **117b** can be used to detect the position or changes in the position of the turbine wheel **104** and/or rotor **108** relative to the housing **112** or other reference point (such as a predetermined value). Position sensors **117a**, **117b** can detect axial and/or radial displacement. The magnetic bearing **116a** and/or **116b** can respond to the information from the positions sensors **117a**, **117b** and adjust for the detected displacement, if necessary. The MBC **168** may receive information from the position sensor(s) **117a**, **117b** and process that information to provide control signals to the magnetic bearings **116a**, **116b**. MBC **168** can communicate with the various components of the turboexpander **102** across a communications channel **162**.

(24) The use of magnetic bearings **116a**, **116b** and position sensors **117a**, **117b** to maintain and/or adjust the position of the turbine wheel blades **106** such that the turbine wheel blades **106** stay in close proximity to the shroud **114** permits the turboexpander **102** to operate without the need for seals (e.g., without the need for dynamic seals). The use of the active magnetic bearings **116a,b** in the turboexpander **102** eliminates physical contact between rotating and stationary components, as well as eliminate lubrication, lubrication systems, and seals.

(25) The turboexpander **102** may include one or more backup bearings. For example, at start-up and shut-down or in the event of a power outage that affects the operation of the magnetic bearings **116a** and **116b**, bearings may be used to rotatably support the turbine wheel **104** during that period of time. The backup bearings and may include ball bearings, needle bearings, journal bearings, or the like. As mentioned previously, the turboexpander **102** is configured to generate electricity in response to the rotation of the rotor **108**. In certain instances, the rotor **108** can include one or more permanent magnets. The stator **110** includes a plurality of conductive coils. Electrical current is generated by the rotation of the magnet within the coils of the stator **110**. The rotor **108** and stator **110** can be configured as a synchronous, permanent magnet, multiphase alternating current (AC) generator. The electrical output **160** can be a three-phase output, for example. In certain instances, stator **110** may include a plurality of coils (e.g., three or six coils for a three-phase AC output). When the rotor **108** is rotated, a voltage is induced in the stator coil. At any instant, the magnitude of the voltage induced in coils is proportional to the rate at which the magnetic field encircled by the coil is changing with time (i.e., the rate at which the magnetic field is passing the two sides of the coil). In instances where the rotor **108** is coupled to rotate at the same speed as the turbine wheel **104**, the turboexpander **102** is configured to generate electricity at that speed. Such a turboexpander **102** is what is referred to as a “high speed” turbine generator. For example, in embodiments, the turboexpander **102** can produce up to 280 kW at a continuous speed of 30,000 rpm. In embodiments, the turboexpander can produce on the order of 350 KW at higher rotational speeds (e.g., on the order of 35,000 rpm).

(26) In some embodiments, the design of the turbine wheel **104**, rotor **108**, and/or stator **110** can be based on a desired parameter of the output gas from the turboexpander **102**. For example, the design of the rotor and stator can be based on a desired temperature of the gas **128**.

(27) The turboexpander **102** can be coupled to a power electronics **118**. Power electronics **118** can include a variable speed drive (VSD) **166** (or variable frequency drive) and the magnetic bearing controller (MBC) **168** (discussed above).

(28) The electrical output **160** of the turboexpander **102** is connected to the VSD **166**, which can be programmed to specific power requirements. The VSD **166** can include an insulated-gate bipolar transistor (IGBT) rectifier to convert the variable frequency, high voltage output from the turboexpander **102** to a direct current (DC). The rectifier **210** can be a three-phase rectifier for three-phase AC input current. An inverter then converts the DC from the rectifier AC for supplying to the power grid **140**. The inverter can convert the DC to 380 VAC-480 VAC at 50 to 60 Hz for delivery to the power grid. The specific output of the VSD **166** depends on the power grid and

application. Other conversion values are within the scope of this disclosure. The VSD **166** matches its output to the power grid **140** by sampling the grid voltage and frequency, and then changing the output voltage and frequency of the inverter to match the sampled power grid voltage and frequency.

(29) The turboexpander **102** is also connected to the MBC **168** in the power electronics **118**. The MBC **168** constantly monitors position, current, temperature, and other parameters to ensure that the turboexpander **102** and the active magnetic bearings **116a** and **116b** are operating as desired. For example, the MBC **168** is coupled to position sensors **117a**, **117b** to monitor radial and axial position of the turbine wheel **104** and the rotor **108**. The MBC **168** can control the magnetic bearings **116a**, **116b** to selectively change the stiffness and damping characteristics of the magnetic bearings **116a**, **116b** as a function of spin speed. The MBC **168** can also control synchronous cancellation, including automatic balancing control, adaptive vibration control, adaptive vibration rejection, and unbalance force rejection control.

(30) Pressure let down systems convert shaft power from the process flow. The turboexpander can support islanding operations. The turboexpander can continue to provide power to a location in the event that a power grid supplying power to that location is interrupted. This disclosure describes components that can facilitate load matching between the shaft power created by the process gas flow at the pressure letdown station to load demands. In this way, the turboexpander can support microgrid functionality for islanding operations.

(31) The turboexpander **102** described above includes example features that are implementation-specific. Certain features may be changed, added, removed, or redesigned without deviating from the scope of this disclosure. For example, other types of bearings can be used instead of or in addition to AMBs, such as ball bearings, fluid film bearings, etc. Different designs of rotors and stators can be used, such as brushless DC, induction-type, etc. Other types of stator cooling architectures can be used, such as non-flow-through and overhung architectures.

(32) FIG. 2 is a schematic diagram of an example turboexpander system **200** that supports islanding operations without a grid source in accordance with embodiments of the present disclosure. The turboexpander system **200** includes a turboexpander **102**, as described above.

(33) The turboexpander system **200** includes power electronics components **201** for supporting islanding operations. For example, a turboexpander power converter **202** electrically couples the electrical connection **160** of the turboexpander **102** to an islanding mode power electronics (PE) **204**. A power converter can convert the AC power from the turboexpander **102** into DC, which can be stored in battery **206** or routed elsewhere on a DC bus. The turboexpander power converter **202** can convert the AC output of the turboexpander into DC to traverse the DC bus. In some embodiments, the turboexpander power converter **202** includes a rectifier circuit that includes electrical components that can convert AC to DC. The DC from the turboexpander power converter **202** is input into the islanding mode PE **204**. The islanding mode PE **204** can convert the DC into AC that has a frequency and amplitude compatible with the load **220**.

(34) Load **220** can be appliances, printers, computers, lighting, telecommunications equipment, HVAC, air filtration, or other critical systems.

(35) In embodiments, the islanding mode PE **204** can include an inverter circuit. The inverter circuit can convert DC from the turboexpander power converter **202** into AC. The inverter circuit can include, for example, circuit elements that convert the DC to an AC having frequency and amplitude (voltage) that is compatible with the load **220**. The inverter circuit can also support multiple loads having different power demands and parameters.

(36) The power electronics **201** can include a battery **206**. Battery **206** can be coupled to the turboexpander **102** through the turboexpander power converter **202**. The battery **206** can store power output from the turboexpander **102**. For example, the AC from the electrical connection **160** can be converted to DC by the turboexpander power converter **202** and stored in battery **206**.

(37) In embodiments, the battery can facilitate “dark start” of the turboexpander **102**. In the

absence of a connected power grid as a power source for the turboexpander, the battery **206** can supply the necessary power to start the rotation of the rotor of the turboexpander **102** through bi-directional electrical connection **160**. In some embodiments, the battery **206** can aid in getting the rotor started while the process gas starts to flow into the turboexpander inlet. After some time, the process gas flow is sufficient to bring the rotor up to speed, and the battery **206** can be disconnected from the turboexpander bi-directional connection **160**. The ability to dark start the turboexpander allows the turboexpander to act as a microgrid without a power grid as a source of power.

(38) A brake resistor assembly **208** is electrically connected to the electrical output **160** of the turboexpander **102** (e.g., the output of the generator). The brake resistor assembly **208** can have a tuned impedance to allow an efficient transfer of power from the turboexpander **102** to the brake resistor assembly **208**. In embodiments, the brake resistor assembly **208** comprises a speed-controlled, current regulated brake resistor. The brake resistor assembly **208** can receive current from the turboexpander directly (AC) or through a rectifier circuit **210** (DC). The rectifier circuit **210** can convert the AC from the turboexpander **102** into DC. A current monitor **212** can be connected in parallel to the rectifier to monitor current from the turboexpander electrical output **160**. In embodiments, rectifier circuit **210** includes an active rectifier circuit **210**.

(39) The battery **206** and brake resistor **208** can mitigate the turbocharger lag to provide a seamless operation during step load application and removal.

(40) Load **220** can be any electrical load, including a critical load, at a location serviced by the turboexpander system **200**. A critical load includes, but is not limited to, lighting systems, food storage systems, air conditioning/heating systems, communication systems, and other loads deemed critical to the location.

(41) FIG. 3 is a schematic diagram of an example turboexpander system **300** that includes a bidirectional inverter for islanding operation in accordance with embodiments of the present disclosure. The embodiment shown in FIG. 3 is backed up by a power grid **140**. For systems coupled to a power grid **140**, the power electronics uses a bidirectional inverter system **304** described below. The bidirectional inverter system **304** facilitates powering the turboexpander **102** from the power grid **140** and also facilitates directing excess power generated by the turboexpander **102** beyond the load requirement of load **220** to be directed back to the power grid **140**. In some embodiments, if the power grid **140** is lost, the turboexpander **102** can act as a microgrid or back-up power station to supply power to the load **220**.

(42) The turboexpander system **300** includes power electronics **302**. Similar to the system **200** shown in FIG. 2, the turboexpander system **300** includes a turboexpander **102** that can generate electricity from the rotation of a rotor in a stator using process gas flow at a pressure letdown station (for example). Also similar to system **200**, the turboexpander system **300** includes a brake resistor assembly **208** coupled to the electrical output **160** of the turboexpander **102**. The brake resistor assembly **208** can have a tuned impedance to allow an efficient transfer of power from the turboexpander **102** to the brake resistor assembly **208**. In embodiments, the brake resistor assembly **208** comprises a speed-controlled, current regulated brake resistor. The brake resistor assembly **208** can receive current from the turboexpander directly (AC) or through a rectifier circuit **210** (DC). The rectifier circuit **210** can convert the AC from the turboexpander **102** into DC. A current monitor **212** can be connected in parallel to the rectifier to monitor current from the turboexpander electrical output **160**.

(43) The power electronics **302** can include a battery **206**. Battery **206** can be coupled to the turboexpander **102** through the turboexpander power converter **202**. The battery **206** can store power output from the turboexpander **102**. For example, the AC from the electrical output **160** can be converted to DC by the turboexpander power converter **202** and stored in battery **206**. In embodiments, the battery can facilitate “dark start” of the turboexpander **102**.

(44) In embodiments, the power electronics **302** (and power electronics **201**) can include a different

type of power storage device. The power storage device can be charged using AC or DC. The power storage device in general can store power from the turboexpander **102**, and in some embodiments, can store power from the power grid. In embodiments, the power storage device can be used to start the rotation of the rotor within the stator of the turboexpander **102** as process gas flow is built up during a pressure let down sequence or other gas flow process.

(45) To support use of power from and delivery of power to the power grid **140**, the power electronics **302** includes a bidirectional inverter system **304**. Bidirectional inverter system **304** includes an islanding mode inverter **204** and a power grid converter **308**. The islanding mode inverter **204** can receive DC from the turboexpander power converter **202** and convert the DC into a compatible AC for load **220** (or multiple loads).

(46) The bidirectional inverter system **304** also includes a power grid converter **308**. The power grid converter **308** can direct excess power not used by the load **220** to the power grid **140**. The active grid inverter can include electrical components that can convert the DC from the turboexpander power converter **202** into AC having a frequency and amplitude compatible with the power grid **140**.

(47) The power grid inverter **308** can also receive AC from the power grid and convert the AC from the power grid **140** into DC for traversing DC bus to power converter **202**. Power converter **202** can then convert the DC from the power grid inverter **308** into AC compatible with the turboexpander **102** to start the rotation of the rotor within the stator during start-up procedures. In embodiments, the battery **206** can also be charged using power from the power grid **140**.

(48) The battery **206** of turboexpander system **200** can act in a similar fashion as an uninterruptable power supply to continue providing power to the load **220** if the turboexpander **102** fails. Likewise, in FIG. 3, if the grid **140** fails, the turboexpander **102** and the battery **206** can supply power to the load **220**. If both the grid **140** and the turboexpander **102** fail, the battery **206** can supply power to the load **220**. In any case, the islanding mode inverter **204** can condition the DC input to be AC power that mimics the grid **140** or the turboexpander **102** to supply power seamlessly to the load **220**.

(49) In any of the scenarios above, the power supplied to the load **220** by the battery **206** should mimic the grid power supplied to the load. The islanding mode inverter **204**, therefore, includes the electronics to shape the power from the battery to mimic grid power. This way, the turboexpander systems can support seamless operation of loads using the battery **206** even if the grid **140** and the turboexpander **102** fail. Likewise, the battery **206** and the grid **140** can be supplied by the turboexpander **102**. The electrical components described herein facilitate the ability to supply power to battery **206** and to grid **140** via turboexpander **102**, while also ensuring that load **220** continues to receive power during grid failures and/or turboexpander failures.

(50) In addition, the battery **206** should have sufficient charge or capacity to supply power to load **220** for some amount of time, to allow the grid **140** or turboexpander **102** to come back online.

(51) A master controller **230** can provide power management control to various components, including the output voltage shaping, the output voltage control, the reactive and active load compensation, and other power control features. The master controller **230** can activate or deactivate or otherwise control active rectifiers, inverters, converters, etc., to provide power to the right component based on operational conditions. Master controller can be connected to and control turboexpander power converter **202**, islanding mode inverter **204**, brake resistor **208**, active rectifier **210**, and power grid converter **308**. For example, a tripped breaker can signify that load **220** is lost. To prevent over-speed conditions at the turboexpander **102**, the master controller **230** can activate active rectifier **210** to direct power from the turboexpander **102** to the brake resistor assembly **208**. The master controller **230** can also redirect power to the power electronics after the over-speed or other fault condition has been reconciled. For example, if a breaker is tripped at the output of the power electronics, the master controller **230** can route power from the turboexpander **102** to the active rectifier **210** to allow the power to be dissipated by the brake resistor assembly

208. After the breaker is reset, the master controller 230 can reroute power from the turboexpander 102 to the power electronics for delivery to the load.

(52) FIG. 4A is a schematic diagram 400 of an example turboexpander converter in accordance with embodiments of the present disclosure. In FIG. 4A, the turboexpander 102 is simplified to be a three-phase permanent magnet synchronous alternating current generator 402. Though not shown, a current monitor can be coupled in parallel to the brake resistor assembly to monitor current flowing into the brake resistor(s). A turboexpander power converter 404, similar to turboexpander power convert 202 is shown. The turboexpander power converter 404 can be used to convert AC power from the generator 402 to DC power for the DC bus. DC power can be stored in battery 206 or sent to islanding mode inverter 204 or power grid converter 308.

(53) The turboexpander power converter 404 can also convert DC power from the battery 206 or from power grid converter 308 into AC power to drive the turboexpander during start-up operations. Master controller 230 can be used to control the turboexpander power converter 404 to drive current either to or from the generator 402 based on operating conditions. For example, the master controller 230 can receive power management control information that causes the master controller 230 to control the turboexpander power converter 404 to drive current to the generator 402 from the battery 206 or grid 140 during start up. The master controller 230 can receive power management control information that causes the master controller 230 to control the turboexpander power converter 404 to drive current from the generator 402 to the DC bus for supplying power to the battery 206, grid 140, or load 220. For example, the master controller 230 can activate rectifiers in the turboexpander power converter 404 based on the presence or absence of a fault condition at the load 220 or grid 140.

(54) FIG. 4B is a schematic diagram 450 of an example islanding mode inverter 454 in accordance with embodiments of the present disclosure. Islanding mode inverter 454 is similar to islanding mode inverter 204. The islanding mode inverter 454 can change DC current to AC current to supply AC power to load 220. The islanding mode inverter 454 can condition the power that is output from the islanding mode inverter 454 to mimic grid power. For example, the islanding mode inverter can include electrical components to condition the AC power, including sine filter 456. The output power to the load 220 resembles the power provided to the load 220 by the grid 140 or the generator 402 so that if the grid is lost, the load 220 can continue to operate.

(55) In one example embodiment, the master controller 230 can receive information 458 that signals to the master controller 230 to send battery power to the load through the islanding mode inverter 454. A tripped breaker can signal a fault at the grid or elsewhere that causes the master controller to cause battery 206 to provide power to load 220.

(56) FIG. 5 is a process flow diagram 500 for supporting islanding operation using a turboexpander in accordance with embodiments of the present disclosure. In some embodiments, a power source can be used to start up the rotation of a rotor within a stator of the turboexpander. (502). The power source can be a battery connected to the turboexpander or a power grid connected to the turboexpander. The power source can aid in getting the rotor up to speed while a process gas flow is building up to sufficient flow rates or mass to rotate the rotor at a desired speed to generate the desired output power. (504).

(57) The load can be uncoupled from a power grid. The turboexpander provides power to the load during islanding operations, thereby acting as a microgrid. The turboexpander power electronics can include an islanding mode power electronics, such as an islanding mode inverter, to convert current originating from the turboexpander into a current that has a frequency and amplitude that is compatible with the load. (506). The output current of the turboexpander can be used to power a load. (508). Excess power that is not used by the load can be output to either a battery (or other power storage device) or to the power grid. If a power grid is coupled to the turboexpander, an active grid inverter can convert current originating from the turboexpander into a current having a frequency and amplitude compatible with the power grid.

(58) The specification and drawings are, accordingly, to be regarded in an illustrative sense rather than a restrictive sense. Furthermore, the foregoing use of embodiment and other exemplarily language does not necessarily refer to the same embodiment or the same example, but may refer to different and distinct embodiments, as well as potentially the same embodiment. In the foregoing specification, a detailed description has been given with reference to specific exemplary embodiments. It will, however, be evident that various modifications and changes may be made thereto without departing from the broader spirit and scope of the disclosure as set forth in the claims.

Claims

1. An apparatus comprising: an electric generator comprising: a process gas inlet configured to couple to a process gas pipeline and to receive a process gas from the process gas pipeline; a turbine wheel configured to receive process gas from the process gas inlet, the turbine wheel having an outlet configured to couple to a downstream process gas pipeline to transfer process gas downstream of the electric generator; a rotor coupled to the turbine wheel and configured to rotate with the turbine wheel, and a stator, the electric generator to generate an alternating current upon rotation of the rotor within the stator; a bidirectional power converter circuit coupled to an electrical output of the electric generator, the bidirectional power converter circuit to convert alternating current from the electric generator into direct current; an islanding mode inverter circuit coupled to an electrical output of the bidirectional power converter circuit by a direct current (DC) bus, the islanding mode inverter circuit to convert direct current from the bidirectional power converter circuit into an alternating current that comprises a frequency and an amplitude to provide power to an electrical load; an active grid inverter circuit coupled to the islanding mode inverter circuit and the bidirectional power converter circuit by the DC bus, the active grid inverter circuit configured to provide power for the electrical load and/or for the electric generator, the active grid inverter circuit being further configured to provide power to a power grid from the electric generator; and the apparatus being further configured to: determine that the power grid is no longer supplying power to the electrical load, and cause the islanding mode inverter circuit to direct power, generated by the electric generator from expansion of the process gas received by the process gas inlet, to the electrical load based on the determination that the power grid is no longer supplying power to the electrical load.
2. The apparatus of claim 1 further comprising a brake resistor assembly coupled to the electrical output of the electric generator, wherein the brake resistor assembly comprises an active rectifier and a speed controlled, current regulated brake resistor.
3. The apparatus of claim 1, further comprising a battery coupled to the electric generator, the battery to store power received from the electric generator and to provide power to rotate the rotor within the stator.
4. The apparatus of claim 3, wherein the battery is coupled to the bidirectional power converter circuit, the bidirectional power converter circuit to: receive alternating current from the electric generator and convert the alternating current to a direct current for storage in the battery; and receive direct current from the battery and convert the direct current into alternating current to power the rotor.
5. The apparatus of claim 1, wherein the electric generator is configured to receive from the process gas inlet the process gas having a first pressure, the process gas to exit the outlet of the turbine wheel at the downstream process gas pipeline having a second pressure, wherein the first pressure of the process gas is greater than the second pressure of the process gas.
6. The apparatus of claim 1, wherein the active grid inverter circuit is to provide power to the electrical load and to provide excess power to the power grid.
7. The apparatus of claim 1, wherein the active grid inverter circuit is to supply power from the

power grid to the rotor to rotate the rotor within the stator prior to the process gas rotating the turbine wheel.

8. The apparatus of claim 1, wherein the islanding mode inverter circuit comprises a circuitry to: receive a direct current on a DC bus; convert the direct current to an alternating current; and condition the alternating current into a frequency and amplitude compatible with the electrical load.
9. The apparatus of claim 1, further comprising a master controller circuit to control current flow to a brake resistor during a fault condition.
10. The apparatus of claim 9, further comprising an active rectifier electrically connected between the electric generator and the brake resistor, the master controller circuit to activate the active rectifier upon detecting a fault condition to direct current from the electric generator to the brake resistor during the fault condition.
11. The apparatus of claim 1, wherein the electric generator comprises a three-phase permanent magnet synchronous generator.
12. A method for providing power to an electrical load with a turboexpander generator, the method comprising: supplying power from a power grid to the electrical load through an active grid inverter, the active grid inverter configured to provide power for the electrical load and/or for the turboexpander generator, the active grid inverter circuit being further configured to provide power to the power grid from the turboexpander generator; determining that the power grid is no longer supplying power to the electrical load; generating an alternating current using the turboexpander generator; directing the alternating current generated by the turboexpander generator through a bidirectional power converter circuit to convert the alternating current into a direct current, the bidirectional power converter circuit coupled to the active grid rectifier by a direct current (DC) bus; directing the direct current to an islanding mode inverter circuit on the DC bus to convert the direct current from the bidirectional power converter circuit into an alternating current that comprises a frequency and an amplitude suitable for delivery to the electrical load, the islanding mode inverter circuit coupled to the active grid rectifier by the DC bus; and directing the alternating current from the islanding mode inverter circuit to the electrical load.
13. The method of claim 12, wherein the turboexpander generator comprises a turbine wheel configured to rotate in response to an expansion of a process gas.
14. The method of claim 13, further comprising performing a start-up of the turboexpander generator using power through a bidirectional power converter circuit.
15. The method of claim 14, further comprising supplying power to the bidirectional power converter circuit with power received from a power grid.
16. The method of claim 14, further comprising supplying power to the bidirectional power converter circuit with power received from a battery.
17. The method of claim 12, further comprising: directing the direct current from the bidirectional power converter circuit to a battery; storing the direct current in the battery; and directing the direct current from the battery to the islanding mode inverter circuit.
18. The method of claim 12, further comprising: determining that the turboexpander generator is in an overspeed condition; directing power to an active rectifier to produce a rectified current; and direct the rectified current to a speed controlled, current regulated brake resistor to perform a slow-down of the turboexpander generator.
19. The method of claim 18, wherein the power directed to the active rectifier to produce a rectified circuit is supplied by the alternating current generated by the turboexpander generator.
20. The method of claim 18, wherein the power directed to the active rectifier to produce a rectified circuit is supplied by the power electronics system.
21. A system comprising: a process gas pipeline configured to transport a process gas, the process gas pipeline comprising a pressure control valve configured to control pressure of the process gas that flows through the process gas pipeline; an electric generator in parallel to the pressure control valve, the electric generator comprising: a process gas inlet configured to receive process gas from

the process gas pipeline through a flow control valve; a turbine wheel configured to receive the process gas from the process gas inlet and rotate in response to an expansion of the process gas flowing into an inlet of the turbine wheel and out of an outlet of the turbine wheel, the outlet of the turbine wheel to couple to a process gas outlet, wherein the process gas outlet couples to the process gas pipeline downstream of the pressure control valve, the process gas having a first pressure at the process gas inlet and a second pressure at the process gas outlet, wherein the first pressure is greater than the second pressure; a rotor coupled to the turbine wheel and configured to rotate with the turbine wheel, and a stator, the electric generator to generate an alternating current upon rotation of the rotor within the stator; and a power electronics system comprising: a bidirectional power converter circuit coupled to an electrical output of the electric generator, the bidirectional power converter circuit to convert alternating current from the electric generator into direct current, and an islanding mode inverter circuit coupled to an electrical output of the bidirectional power converter circuit by a direct current (DC) bus, the islanding mode inverter circuit to convert direct current from the bidirectional power converter circuit into an alternating current that comprises a frequency and an amplitude to provide power to an electrical load, and an active grid inverter circuit coupled to the islanding mode inverter circuit and the bidirectional power converter circuit by the DC bus, the active grid inverter circuit configured to provide power for the electrical load and/or for the electric generator and is configured to provide power to a power grid from the electric generator; wherein the power electronics system is coupled in parallel to the electrical load and the power grid that supplies power to the electrical load, the power electronics system further comprising: a master controller circuit to: determine that the power grid is no longer supplying power to the electrical load, and cause the islanding mode inverter circuit to direct power, generated by the electric generator from the expansion of the process gas received by the process gas inlet, to the electrical load based on the determination that the power grid is no longer supplying power to the electrical load.
