

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12411298
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Ninomiya; Takuya et al.

Optoelectronic connections to printed circuit boards

Abstract

The present invention relates to the pluggable connection of an optoelectronic module with an optoelectronic connector assembly from a location exterior to the optoelectronic connector assembly. An optoelectronic module comprises a housing having a proximate end and a rear end in a longitudinal direction; a ferrule arranged adjacent to the proximate end of the housing; an electrical contact arranged adjacent to the proximate end of the housing and stacked with the ferrule in a vertical direction; a biasing members configured to bias the ferrule in the longitudinal direction once pressed; and a guiding member extending in the longitudinal direction and configured to guide the optoelectronic module connected to another optoelectronic module. The optoelectronic connection between the optoelectronic module and the optoelectronic connector assembly has blind mating features.

Inventors: Ninomiya; Takuya (Saitama, JP), Gniadek; Jeffrey (Oxford, ME), Wong; Yim (Kowloon, HK), Royer; Tyler (York, PA)

Applicant: Senko Advanced Components, Inc. (Hudson, MA)

Family ID: 82801312

Assignee: Senko Advanced Components, Inc. (Hudson, MA)

Appl. No.: 18/585029

Filed: February 22, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240231013 A1	Jul. 11, 2024

Related U.S. Application Data

division parent-doc US 17669438 20220211 US 11934020 child-doc US 18585029
us-provisional-application US 63234533 20210818

us-provisional-application US 63180549 20210427
us-provisional-application US 63179180 20210423
us-provisional-application US 63178794 20210423
us-provisional-application US 63148892 20210212

Publication Classification

Int. Cl.: G02B6/38 (20060101); G02B6/42 (20060101)

U.S. Cl.:

CPC G02B6/4292 (20130101); G02B6/3885 (20130101); G02B6/3897 (20130101);
G02B6/4261 (20130101);

Field of Classification Search

CPC: G02B (6/3885); G02B (6/3897); G02B (6/4261); G02B (6/4292); G02B (6/38)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
4721358	12/1987	Faber et al.	N/A	N/A
6736546	12/2003	Kiani et al.	N/A	N/A
10284323	12/2018	Salsi	N/A	N/A
11121776	12/2020	Aboagye et al.	N/A	N/A
11934020	12/2023	Ninomiya	N/A	G02B 6/4261
2004/0008494	12/2003	Roth	N/A	N/A
2007/0190841	12/2006	Van Der Steen	N/A	N/A
2008/0219626	12/2007	Durrant	N/A	N/A
2011/0081119	12/2010	Togami et al.	N/A	N/A
2015/0016783	12/2014	Leigh et al.	N/A	N/A
2018/0356601	12/2017	Gniadek	N/A	N/A
2019/0113693	12/2018	Yang	N/A	N/A
2020/0183097	12/2019	Chang et al.	N/A	N/A
2021/0271036	12/2020	Nguyen	N/A	G02B 6/426

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
WO-02093696	12/2001	WO	B01J 39/17
2012017262	12/2011	WO	N/A
2021177463	12/2020	WO	N/A
2023286455	12/2022	WO	N/A

OTHER PUBLICATIONS

International Search Report and Written Opinion, dated Aug. 1, 2022, International Application No. PCT/US22/16076, 11 pages. cited by applicant
Extended European Search Report, European Patent Application No. 22753394.0, Nov. 27, 2024, 17 pages. cited by applicant

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This is a divisional application of U.S. application Ser. No. 17/669,438, filed Feb. 11, 2022, which is a Nonprovisional of U.S. Provisional Application No. 63/148,892, filed Feb. 12, 2021, and claims priority to U.S. Provisional Application No. 63/234,533, filed Aug. 18, 2021, U.S. Provisional Application No. 63/180,549, filed Apr. 27, 2021, U.S. Provisional Application No. 63/179,180, filed Apr. 23, 2021, and U.S. Provisional Application No. 63/178,794, filed Apr. 23, 2021, the disclosures of each of which are incorporated herein in their entireties by reference.

BACKGROUND

(1) Optical data transmission systems require interface with electronic systems for the receipt and transmission of data. Moreover, at some locations it is necessary to provide an optical source. Typically, this takes the form of a laser. The laser can be provided in a relatively small format. However, connection of the laser to optoelectronic modules occupies valuable space needed for optical communication lines. It is known to place the laser within the module, but should the laser need to be replaced, the entire module must be replaced. In some circumstances it is known to attach the laser on the exterior of the module, but two connections are required, which occupies valuable space for connections on the exterior of the module.

SUMMARY

(2) In one aspect of the present invention, an optoelectronic connection system generally comprises a first connector assembly including a first electrical contact, a ferrule holder, and a first multi-fiber ferrule supported by the ferrule holder. A second connector assembly includes a housing configured mate with the first connector assembly for connection to the second connector assembly. Optical fibers in the housing are configured for optical connection with the first multi-fiber ferrule. A second electrical contact is configured to electrically connect with the first electrical contact upon connection of the first and second connector assemblies. The first and second multi-fiber ferrules are arranged relative to the first and second electrical contacts so that upon connection of the first connector assembly with the second connector assembly, the first multi-fiber ferrule makes an optical connection with the optical fibers of the second connector assembly prior to the first and second electrical contacts making an electrical connection.

(3) In another aspect of the present invention, an optical connector generally comprises first and second mechanical transfer ferrules. A ferrule holder is formed for holding the first and second mechanical transfer ferrules in side-by-side relation with each other. The ferrule holder is configured to admit cables containing optical fibers into the ferrule holder for each of the first and second mechanical transfer ferrules.

(4) In yet another aspect of the present invention, an optoelectronic module generally comprises a housing including an interior and an exterior, with the exterior of the housing being configured for receiving plug-in connections. A printed circuit board in the housing includes an optical engine mounted thereon. A receptacle connector assembly is mounted on the circuit board in the interior of the housing. The receptacle connector assembly is configured for making optical plug-in connection to a laser light source from the exterior of the housing into the interior of the housing, and for making an electrical plug-in connection to the laser light source from the exterior of the housing.

(5) In still a further aspect of the present invention, an optoelectronic module generally comprises a housing having a port therein. A printed circuit board is in the housing. An optical engine in the

housing is configured to use laser light for driving optoelectronic communication with the housing. A receptacle connector assembly in the housing and connected to the printed circuit board, the receptacle connector assembly is exposed for connection through the port. A laser source is configured to be optically and electrically connected to the printed circuit board and optical engine by connection to the receptacle connector assembly. The laser source and receptacle connector assembly have blind mate features configured to facilitate connection of the laser source to the to the receptacle connector.

(6) Other objects and features of the present invention will be in part apparent and in part pointed out hereinafter.

Description

DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a schematic sectional view of an optical switch module including a pluggable external laser source connector;

(2) FIG. 2 is an exploded perspective of the pluggable external laser source connector;

(3) FIG. 3 is a perspective of a plug-in connector of the pluggable external laser source connector;

(4) FIG. 4 is the perspective of FIG. 3 with an electrical connection portion exploded therefrom;

(5) FIG. 5 is an enlarged fragment of the perspective of FIG. 3 showing interconnection of a support to a connection portion of the pluggable external laser source connector;

(6) FIG. 6 is a fragmentary rear perspective of the pluggable external laser source connector;

(7) FIG. 7 is a perspective of the connection portion of the pluggable external laser source connector;

(8) FIG. 8 is an exploded perspective of the pluggable external laser source connector;

(9) FIG. 9 is a perspective of the plug-in connector with a holding cover exploded therefrom;

(10) FIG. 10 is a perspective of the plug-in connector connected to the holding cover;

(11) FIG. 11 is a front end perspective of an adapter housing;

(12) FIG. 12 is a rear end perspective of the adapter housing;

(13) FIG. 13 is an exploded perspective of the adapter;

(14) FIG. 14 is a perspective showing initial contact of the plug-in connector with the adapter 26 upon mating of the plug-in connector with the adapter;

(15) FIG. 15 is a perspective from more of a side vantage with parts removed showing a further progression of the mating and in particular the reception of the daughterboard into the adapter housing.

(16) FIGS. 16-18 schematically illustrate the interaction of guide arms of the plug-in connector with latch arms of the adapter to produce a positive connection of the plug-in connector with the adapter;

(17) FIGS. 19 and 20 schematically illustrate operation of a release mechanism of the plug-in connector that permits disconnection of the plug-in connector from the adapter;

(18) FIG. 21 is a perspective of two MT ferrules terminating respective optical fiber cables;

(19) FIG. 22 is the perspective of FIG. 21 showing one spring applied to one of the optical fiber cables and other spring next to the other cable prior to mounting on the other of the optical fiber cables;

(20) FIG. 23 is an enlarged end view of one of the springs;

(21) FIG. 24 is a perspective of the two MT ferrule having the springs mounted thereon;

(22) FIG. 25 is the perspective of FIG. 24, but further illustrating the addition of backposts;

(23) FIG. 26 is a front end view of one of the backposts;

(24) FIG. 27 is a perspective of the two MT ferrule assembled with the springs and backposts thereon just prior to assembly with a front housing;

- (25) FIG. 28 is a perspective of the assembled connector;
- (26) FIG. 29 is a perspective of an optoelectronic connection system schematically illustrated as connected to a printed circuit board;
- (27) FIG. 30 is an exploded perspective of the optoelectronic connection system of FIG. 29;
- (28) FIG. 31 is a perspective of a first carrier of a first connector assembly of the optoelectronic connection system of FIG. 29, but with clips and optical components removed to show details of a first ferrule carrier and a second ferrule carrier;
- (29) FIG. 32 is a perspective of the optoelectronic connection system of FIG. 29 with first and second connector assemblies positioned for connection with parts removed to show internal construction;
- (30) FIG. 33 is a fragmentary perspective of a dual ferrule optoelectronic connection system;
- (31) FIG. 34 is an enlarged, fragmentary perspective of the plug-in connector assembly of the optoelectronic connection system of FIG. 33 with a near side wall removed to show internal construction;
- (32) FIG. 35 is a further enlarged perspective of a ferrule holder and ferrules of the plug-in connector assembly;
- (33) FIG. 36 is an enlarged perspective of a ferrule holder and ferrules of the receptacle connector assembly;
- (34) FIG. 37 is an enlarged fragmentary perspective showing a plug connector assembly and a receptacle connector assembly of the optoelectronic connection system of FIG. 34 with parts removed;
- (35) FIG. 38 is a top plan view of the plug connector assembly and the receptacle connector assembly in the same position of connection as shown in FIG. 37;
- (36) FIG. 39 is a perspective similar to FIG. 37, but showing the plug connector assembly and the receptacle connector assembly just prior to mating of ferrules;
- (37) FIG. 40 is a perspective similar to FIG. 39, but showing the plug connector assembly and the receptacle connector assembly with the ferrules mated;
- (38) FIG. 41 is a perspective similar to FIG. 40, but showing one of the ferrules of the receptacle connector assembly retracted slightly upon further movement from the position shown in FIG. 40;
- (39) FIG. 42 is a further enlarged perspective similar to FIG. 41, but showing electrical connection of the plug connector assembly with the receptacle connector assembly;
- (40) FIGS. 43-45 schematically illustrate disconnection of the plug connector assembly and the receptacle connector;
- (41) FIG. 46 is a fragmentary perspective of a receptacle connector assembly of another embodiment;
- (42) FIG. 47 is a fragmentary perspective of an optoelectronic connection system of another embodiment;
- (43) FIG. 48 is a fragmentary perspective of a plug connector assembly of the optoelectronic connection system of FIG. 47 with parts broken away to show internal construction;
- (44) FIG. 49 is a perspective of a ferrule holder and ferrules of the plug connector of FIG. 47;
- (45) FIG. 50 is a perspective of a ferrule holder and ferrules of a receptacle connector assembly of the optoelectronic connection system of FIG. 47;
- (46) FIG. 51 is an enlarged, fragmentary perspective of the plug connector assembly and the receptacle connector assembly as they interengaged during a connection, with parts of the plug connector assembly broken away;
- (47) FIG. 52 is a fragmentary perspective of an optoelectronic connection system of yet another embodiment;
- (48) FIG. 53 is an enlarged perspective of a ferrule holder and ferrules of a plug connector assembly of the optoelectronic connection system of FIG. 52; and
- (49) FIG. 54 is an enlarged perspective of a ferrule holder and ferrules of a receptacle connector

assembly of the optoelectronic connection system of FIG. 52.

(50) Corresponding reference characters indicate corresponding parts throughout the several view of the drawings.

DETAILED DESCRIPTION

(51) Referring now to the drawings, an optical switch module indicated generally at **10** is shown to comprise a housing **12** containing a printed circuit board **14** and an optical engine **16** mounted on the circuit board. The optical engine **16** that can be powered by external laser sources, such as the external laser source (ELS) **18** shown in FIG. 1. The external laser source is connected to the optical engine by an optical conductor **19**. The construction and operation of optical switch modules is well understood by those of ordinary skill in the art, and will not be further described in detail herein. Moreover, it will be understood that the module can be other than an optical switch module and that the connection systems disclosed herein have application in contexts other than printed circuit board connections. In the illustrated embodiment, the external laser source **18** can be plugged into the optical switch module **10**. This facilitate replacement of the ELS though a releasable, plug-in connection, as will be described hereinafter.

(52) As may be seen in FIGS. 2-4, in one embodiment, an optoelectronic connection system **22** comprises a plug-in connector **24** that contains the external laser source **18**. An adapter **26** is mounted on the printed circuit board **14** in the optical switch module **10** for connection and release of the plug-in connector **24** with the module. Referring to FIGS. 3 and 4, the plug-in connector **24** includes an upper, optical connection portion **28** and a lower, electrical connection portion **30**. The electrical connection portion includes a daughterboard **30A** having electrical contacts **30B** at a front end for making electrical connection with the printed circuit board **14** in the optical switch housing **12**. The daughterboard **30A** is attached to an elongate support **30C** such that a connection portion **30D** of the daughterboard including the electrical contacts **30B** projects out in a forward or connection direction from the elongate support. The connection portion **30D** extends along a connection axis that generally runs lengthwise of the plug-in connector **24**. The elongate support **30C** includes a bottom wall **30E** that extends the full length of the support and opposing side walls **30F** projecting up from the bottom wall on opposite sides of the daughterboard **30A** in a rearward region of the support. The elongate support **30C** further includes a pair of tabs **30G** located forward of front ends of the side walls **30F**. Each tab **30G** and adjacent front end of the side wall **30F** are spaced apart to define a space sized and shaped to receive a corresponding tab **28A** on the optical connection portion **28**.

(53) The elongate support **30C** is connected to the connection portion **30D** of the plug-in connector **24** so as to permit the support and the daughterboard **30A** carried by the support to float relative to the connection portion which facilitates connection to the adapter **26** as will be described. The upper, optical connection portion **28** includes a collar **28B** having a floor **28C** projecting rearward of the remainder of the collar. The floor **28C** includes the laterally projecting tabs **28A** on laterally opposite sides of the floor at its rear end. FIG. 5 shows an enlargement of a region of the plug-in connector **24** where one of the tabs **28A** of the floor **28C** of the collar **28B** is received in the space between the tab **30G** and side wall **30F** of the elongate support **30C**. There are gaps between the collar tab **28A** and the support tab **30G**, and between the collar tab and the side wall **30F** of the elongate support **30C**. This permits some relative movement between the elongate support **30C** and the collar **28B** in along the connection axis in forward and rearward directions. Similarly, there are also gaps between the collar tab **28A** and the bottom wall **30E** of the elongate support **30E**, and between the collar tab and holding cover **32** (described more fully hereinafter). As shown in FIG. 6, the collar **28B** further includes an inverted U-shaped piece having runners **28D** that ride on the bottom wall **30E** of the elongate support **30C** along the connection axis. The runners **28D** are thinner than the space between the daughterboard **30A** and the elongate support tabs **30G**. Thus, lateral motion between the optical connection portion **28** and the electrical connection portion **30** is permitted. The function of the float of the electrical connection portion **30** will be described more

fully hereinafter.

(54) Referring now to FIGS. 7 and 8, the plug-in connector 24 comprises a front housing 34, back housings (or “backposts”) 36 and a release mechanism 38. The front housing includes a pair of guide arms 34A that are shaped and arranged for guiding the plug-in connector 24 into the adapter 26, and also for use in making a releasable connection with the adapter. Each of the guide arms 34A tapers near its distal to a narrow tip 34B. Each guide arm 34A includes a release member channel 34C in a laterally outward facing side of the arm. The channels 34C each extend parallel to the connection axis. The front housing 34 further includes a ferrule holder 34D defining internal passages 34E that receive two mechanical transfer (MT) ferrules 40 in side-by-side relation. Although mechanical transfer ferrules 40 are disclosed and described in this description, it will be understood that other types of ferrules could be used within the scope of the present invention. In the illustrated embodiment, the ferrules 40 are arranged horizontally, in a side-by-side relation. In particular, the ferrules 40 are generally coplanar with one another. The internal passages 34E open at the front of the ferrule holder 34D to permit forward portions of the MT ferrules to project out the front of the ferrule holder. The ferrules 40 each include flanges 40A, and the open forward ends of the passages 34E in the ferrule holders are each smaller than the flanges so that the ferrules cannot pass completely out of the internal passages through the front of the ferrule holder 34D. The ferrules 40 each terminate a plurality of optical fibers brought to the ferrule by respective ribbon cables 42. In the illustrated embodiment, the ferrules 40 are each a male ferrule having a pair of mechanical transfer pins 40B held by a pin holder 40C. The pins 40B are received through the ferrules 40 and project forward from the ferrules as can be seen in FIG. 7. In the illustrated embodiment, the pins 40B of the ferrules 40 are generally coplanar with each other. Likewise, the optical fiber terminations in both ferrules 40 are generally coplanar with one another. Flattened coil springs 44 positioned around respective ones of the ribbon cables 42 engage the pin holders 40C to bias the MT ferrules forward in the connection direction. The back housings 36 are constructed for being received in a rear end of the ferrule holder 34D and connected to the ferrule holder 34D. A rear end of each spring 44 engages a front end of a respective ones of the back housings 36 for providing the compressive force to urge the ferrules 40 forward. It will be understood that there could be only one back housing or more than two back housings (not shown) within the scope of the present invention.

(55) The release mechanism 38 comprises the collar 28B and release members 38A on laterally opposite sides of the collar that project forward from the collar. The collar 28B includes the floor 28C and a surround 28E that together with the floor forms a square receptacle that slidably receives a rear portion of the ferrule holder 34D including substantial portions of the back housings 36. The ferrule holder 34D has wedge-shaped stops 34F on top and bottom surfaces. The collar 28B has rectangular openings 28F at its top and bottom surfaces that generally align with respective ones of the wedge-shaped stops 34F on the ferrule holder 34. As the collar 28B is pushed onto the ferrule holder 34D, the wedge-shaped stops 34F engage a top wall and the bottom wall (respectively) of the collar 28B and deform them outward from the connection axis. When the stops 34F come into registration with the rectangular openings 28F, the top and bottom walls of the collar 28B snap back to their original configuration. Thereafter, any attempt to move the collar rearwardly off of the ferrule holder is arrested by engagement of the top and bottom walls at edges of the rectangular openings 28F with substantially vertical surfaces of the stops 34F. However, a substantial range of motion of the collar relative to the ferrule holder is permitted.

(56) The release members 38A each include a ramp portion 38B at a distal end of the release member, and a slide 38C connecting the ramp portion to the collar 28B. The slides 38C each have a generally T-shaped cross section. As the collar 28B is pushed onto the ferrule holder 34D during assembly of the plug-in connector 24, the ramp portions 38B of the release members enter the channels 34C on the guide arms 34A. The ramp portion 38B protrudes laterally from the channel 34C of each of the guide arms 34A. As the slides 38C enter the channels 34C, wider portions of the

slides enter undercut portions of the guide arm **34A**. In this way the release members **38A** are held by the guide arms **34A** against lateral movement relative to the guide arms. It will be appreciated that movement of the collar **28B** will result in movement of the ramp portion **38B** along the channel **34C** of the guide arm. As will be described more fully hereinafter, this movement results in release of the plug-in connector **24** from the adapter **26**.

(57) Once the plug-in connector **24** is assembled, the holding cover **32** can be applied to hold the pre-assembled plug-in connector components in position (see, FIGS. **9** and **10**). The holding cover **32** includes a flat top member **32A** and legs **32B** depending from opposite edges of the flat top member. The legs **32B** are each shaped so that a lower portion fits into a space **30H** in the side wall **30F** of the elongate support **30C**. Each leg has an opening **32C** for receiving a mounting screw (not shown) to secure the holding cover to the plug-in connector **24**. The mounting screw connects the cover **32** to the lower portion **30** of the plug-in connector **24**. The cover **32** and lower portion **30** capture the tab **28A** of the upper portion **28** so that the upper portion cannot separate from the lower portion. However, the connection is such that some degree of relative movement between the upper portion **28** and the lower portion **30** is permitted to assist in alignment of the optical portions somewhat separately from the alignment of the electrical portions, as described below. It will be understood that the upper portion **28** and lower portion **30** maybe connected to each other in other ways within the scope of the present invention.

(58) As shown in FIG. **13**, the adapter **26** includes an adapter housing **26A**, (female) MT ferrules **46** and a back housing **48** for each of the ferrules. The adapter housing **26A** defines a pair of ferrule receptacles **26B** that have larger openings on the rear side (FIG. **12**) and smaller openings on the front side (FIG. **11**). The ferrule receptacles each receive one of the adapter ferrules **46**. The adapter ferrules terminate optical fibers connected to the adapter **26** for making an optical connection at the front ends of the ferrules **46**. The optical fibers are brought to each adapter ferrule **46** by a respective ribbon cable **50**. The ferrules **46** are held in the adapter housing **26A** by the back housings **48**. The back housings each include a body **48A** and locator pins **48B** projecting forward of the body. The locator pins **48B** extend into through passages in the ferrules **46**, but only a short distance into the ferrules to achieve registration between the back housings **48** and the respective ferrules. The back housings **48** include catches **48C** on each side. Only one catch **48C** can be seen in the drawings. When each back housing **48** is inserted into the adapter housing **26A**, the catches **48C** snap into an outer hole **26C** and an inner hole **26D** formed in the adapter housing (see, FIG. **12**). The inside catch **48C** on each back housing **48** is received on a different side of the same inner hole **26D** of the adapter housing **28A**. The ferrules **46** are held in place by the back housings **48** so that forward portions of the ferrules project slightly out from the adapter housing through the front openings of the ferrule receptacles **26B**. As shown the adapter **26** is mounted on the printed circuit board **14**, but could be mounted on another electrical or optical component (not shown) that is mounted on the printed circuit board.

(59) The adapter housing **26A** further defines a lower receptacle **26E** configured to hold an edge card receiver (not shown) capable of making electrical connection with the daughterboard **30A** of the plug-in connector **24**. As shown in FIG. **11**, the lower receptacle **26E** has a front opening for receiving the connection portion **30D** of the daughterboard **30A**. The adapter housing **26A** is formed with an angled upper surface **26F** and an angled lower surface **26G** at the leading end of the front opening of the lower receptacle **26E**. The angled upper and lower surfaces **26F**, **26G** angle toward each other as they move into the adapter housing **26A** so that the front opening of the lower receptacle **26E** is widest at its entrance, and then funnels toward the lower receptacle.

(60) The adapter housing **26A** further includes side slots **26H** arranged to receive respective ones of the guide arms **34A** of the plug-in connector **24**. The front ends of the side slots **26H** include an angled upper surface **26I** and an angled lower surface **26J**. The angled upper and lower surfaces **26I**, **26J** angle toward each other as the surfaces move in the connection direction to guide the guide arms **34A** into the side slots **26H**. The side slots also each include angled interior surfaces

that direct the guide arms **34A** laterally outward into the side slots **26H**. A latch arm **26L** is provided in each side slot **26H**. Each latch arm **26K** is mounted at one end on the adapter housing **26A** and projects toward the front end of the side slot **26H**. The latch arms **26K** can each flex laterally outward from the slot **26H** for use in connecting and disconnecting the plug-in connector **24**. Further each latch arm **26K** includes a hook portion **26M** adjacent to its distal end, used in making a latching connection with the plug-in connector **24**.

(61) Referring now to FIGS. **14-18**, mating of the plug-in connector **24** with the adapter **26** will be described. As may be seen in FIG. **14**, as the plug-in connector **24** moves further toward the adapter **26** from the position shown in FIG. **2**, the tapered tips **34B** of the guide arms **34A** first engage the adapter housing **26A**. More specifically, the tapered tips **34B** may engage any or multiple of the upper angled surface **26I**, the lower angled surface **26J** and the interior surfaces **26K** leading into the side slots **26H**. At the moment depicted in FIG. **14**, the connection portion **30D** of the daughterboard **30A** has not engaged the adapter housing **26A**. The alignment achieved by the guide arms **34A** being received in the side slots **26H** allows the pins **40B** of the ferrules **40** of the plug-in connector **24** to align with the openings in the (female) ferrules of the adapter **26**. FIG. **15** schematically illustrates the reception of the leading edge of the connection portion **30D** of the daughterboard **30A** into the front opening of the lower receptacle **26E**. It is possible just prior to the position shown in FIG. **15**, that the leading edge of the connection portion **30D** of the daughterboard **30A** may not be perfectly aligned with the front opening of the lower receptacle **26E** in the adapter housing **26A**. However, the engagement of the leading edge with one of the upper and lower angled surfaces **26F**, **26G** at the front entrance of the lower receptacle **26E** guides the daughterboard **30A** into the lower receptacle. The construction and connection of the plug-in connector **24** with the elongate support **30C** operates to allow relative movement between the front housing **34** and guide arms **34A**, and the daughterboard **30A** and elongate support **30C**. In this way the guide arms **34A** and daughterboard **30A** may achieve alignment independently of each other within a range. Further movement of the connection portion **30D** of the daughterboard **30A** into the lower receptacle **26E** produces electrical connection between the plug-in connector **24** and the adapter **26**.

(62) FIGS. **16-18** also illustrate mating of the plug-in connector **24** with the adapter **26**, but are particularly drawn to show how latching of the plug-in connector with the adapter occurs. In FIG. **16**, the guide arms **34A** have moved into the side slots **26H** and the angled laterally outwardly facing surfaces of the guide arms engage an angled interior surface of the latch arms **26L**. The laterally outward facing surfaces of the guide arms **34A** at the narrow tips **34B** angle inward toward the connection axis. This feature helps to achieve lateral alignment of the guide arms **34A** with the side slots **26H** that in turn produces lateral alignment of the ferrule pins **40B** of the ferrules **40** with the openings in the ferrules **46**. The inwardly angled portion of the laterally outward facing surface of each guide arm **34A** first engages the latch arm. The shape of the narrow tip **34B** and the shape of the hook portion **26M** of the latch arm **26L** helps to wedge the latch arms out to the positions shown in FIG. **17** after the guide arms **34A** have been advanced farther into the side slots **26H**. Further advancement of the guide arms **34A** caused the hook portions **26M** of the latch arms **26L** to move past the narrow tips **34B**. The hook portion **26M** reaches the release member channel **34C** of the guide arm **34A** and snaps into the release member channel, as show in FIG. **18**. At this point movement of the plug-in connector **24** out of the adapter **26** in a direction opposite the connection direction is resisted by the engagement of the hook portions **26M** of the latch arms **26L** with the guide arms **34A**.

(63) The latched connection of the plug-in connector **24** with the adapter **26** can be released to allow the plug-in connector to be removed from the adapter. FIG. **19** shows that when the hook portions **26M** of the latch arms **26L** are received in the release member channels **34C**, the ramp portions **38B** of the release members **38A** are immediately adjacent the hook portions **26M** of the latch arms **26L**. Pulling on the collar **28B** in a direction opposite the connection direction on the

collar causes the collar and release members **38A** to move in a direction opposite the connection direction. Initially, the guide arms **34A** and front housing **34** are held in place by the engagement of the hook portions **26M** of the 3 latch arms **26L** with the guide arms **34B**. However, as the release mechanism **38** withdraws as shown in FIG. **20**, the ramp portions **38B** of the release members **38A** engage the hook portions **26M** and deflect the latch arms **26L** laterally outwardly. In this deflected position, the hook portions **26M** of the latch arms **26L** are withdrawn from engagement with the guide arms **34A**. At this point, the guide arms **34A** and front housing **34** are withdrawn from connection with the adapter **26**. In essence, the plug-in connector **24** and adapter **26** upon disconnection again assume the relative positions shown in FIG. **2**. The ramp portion **38B** of the release member **38A** includes front and rear ramp surfaces **38D**, **38E**. The rear ramp surface **38E** engages the hook portion **26M** of the latch arm **26L** to move the latch arm outward to release the connection of the plug-in connector **24** with the adapter **26**. The front ramp surface **38D** continues to engage the hook portion **26M** of the latch arm **26L** after the release to gently allow the latch arm to move back to its original position as the guide arms **34A** and release members **38A** continue to withdraw from the adapter **26**.

(64) Referring now to FIGS. **21-28**, in some instances, it is desirable to be able to incorporate MT ferrules into a connector which permits biased rearward movement. As used in this portion of the description, rearward movement means movement that withdraws the ferrules into the connector. Movement of the ferrules with respect to the connector permits a good optical connection to be obtained by maintaining contact of the ferrules with opposing MT ferrules (not shown) of another connector without require exact precision in the location of the mating ferrules. In order to achieve a forward biased range of motion, springs are provided to operatively engage the ferrules at their flange ends. However in situations where an optical fiber cable **110** has been terminated by ferrules **112** as shown in FIG. **21**, a coil spring cannot be slid over the ferrule onto the cable. Accordingly, a spring **114** of the present embodiment used with each of the two ferrules **112** is formed to have one side which is completely open along the full length of the spring for sliding the spring onto the cable **110** behind the ferrule terminating the optical fibers of that cable (see, FIGS. **22** and **23**). Beginning at a first free end of the spring wire making up the spring **114**, the spring wire is formed into a semi-oval segment. In the illustrated embodiment, the semi-oval segment includes a first curved (“C-shaped”) section **116**, a linear section **118** and a second curved (“C-shaped”) section **120**. However, the spring wire does not cross over the first free end to begin a second turn of the spring (as would be the case with a coil spring). Instead, the spring wire is bent back along a U-shaped switchback segment **122**. From the U-shaped segment, the spring wire is again formed into a generally semi-oval segment that is aligned with the first oval segment and includes the same spring wire sections. Again, prior to the spring wire fully enclosing the oval segment, it is bent back again in another U-shaped segment. This configuration is repeated until reaching the second free end of the spring wire. In the illustrated embodiment, the first and second ends of the spring wire are on the same side of the spring **114**. The construction of the spring **114** results in an opening **124** being left in the top side of the spring (as shown in FIG. **23**) extending the full length of the spring. The opening **123** provides a passage for the cable into the interior of the spring so that the spring can be mounted on the cable in a lateral direction. This allows the spring **114** to be mounted on the cable after the ferrule **112** is attached to the cable, instead of before. Typically, conventional springs have to be mounted on the cable before the ferrule is attached to the cable because the conventional springs cannot be threaded over the ferrule. FIG. **24** shows both ferrules and cables with the springs mounted on them.

(65) In order for the springs **114** to operate properly in the assembled connector **126** (FIG. **28**), some structure is required to compress the springs. As with the springs **114**, this structure cannot be slid axially over the cable or ferrule from one end. Accordingly, backposts **128** have a generally inverted channel shape, as shown in FIGS. **25** and **26**. Each backpost **128** has a generally inverted U-shape in cross section, so that the bottom of each backpost defines an opening **130** along its full

length. Thus, each backpost **128** can be placed on the cable **110** from a position above the cable (as oriented in FIG. 25) down onto the cable behind the springs **114**. The cable **110** passes laterally through the opening **130** into the backpost **128**. This allows the backpost **128** to be mounted on the cable after the ferrule **112** is attached to the cable, instead of before. Typically, conventional backposts have to be mounted on the cable before the ferrule is attached to the cable because the conventional backposts cannot be threaded over the ferrule. Each backpost includes forward projecting, opposing pair of retaining fingers **132**, a catch **134** on a top wall of the backpost **128** and a stop **136** spaced rearward of the catch. As may be seen in FIG. 26, the retaining fingers **132** having curved interior opposing faces **138** and a reaction surface **140** facing forwardly at the base of each retaining finger. The curvature of the opposing faces **138** of the retaining fingers **132** generally conforms with the curvature of the sides of the spring **114**. An end of one of the springs **114** fits between the retaining fingers **132** and rests against the reaction surface **140** of the backpost **128**. The retaining fingers **132** hold the spring **114** against lateral movement relative to the backpost **128**. It will be understood that as applied to the cable **110** as shown in FIG. 25, the backpost **128** is not attached to the cable, the spring **114** or the ferrule **112**. Fixation occurs upon assembly with the connector **126** as will be described.

(66) As shown in FIG. 27, the pre-assembled parts of the MT ferrules **112**, springs **114** and backposts **128** are moved toward an open rear end of a front housing **142**. The MT ferrules **112** move into the front housing **142** and protrude through forward openings **144** in the front housing. The backposts **128** eventually enter the open rear end of the front housing **142**. The catches **134** each engage a top wall of the front housing **142** at the open rear end. The catches **134** have a rearward slope and act as inclined planes to deflect the top wall upward so that the catches pass into the front housing **142**. It is also possible that the engagement of the catches **134** with the top wall of the front housing **142** causes the catches and top walls of the backposts **128** to deflect down. It is also possible for both the top wall of the front housing **142** and the top wall of the backpost **128** to deflect. The catches **134** move forward inside the front housing **142** until they align with respective ones of two apertures **146** formed in the top wall of the front housing. At that point the resiliency of the material of the top wall of the front housing **142** (and/or of the backpost **128**) causes movement so that the catches **134** move into the apertures **146** and resist movement of the backpost backward out of the front housing. The stops **136** on the backposts **128** are engageable with the front housing **142** adjacent to the open rear end to prevent the backpost from being further inserted into the front housing.

(67) The MT ferrules **112** have flanges **148** that engage structure (not shown) in the front housing **142** to prevent forward movement past a certain point. The ferrule flanges **148** engage this structure prior to the backposts **128** being connected to the front housing **142**. Accordingly, movement of the backposts **128** into the front housing **142** causes the springs **114** to be compressed. Therefore, as fully assembled in FIG. 28, the springs **114** will urge the MT ferrules **112** forward. However, when the ferrules **112** are engaged by other ferrules (not shown) or other connection structure, the MT ferrules are able to move rearwardly against the bias of the springs **114**, which avoid damage to the ferrules and optical fibers, but maintains firm contact between the MT ferrules and the connecting ferrules. Using the structure of FIGS. 22-28, previously terminated cables and ferrules can be retrofitted into a connector that permits movement of the ferrules as part of the connection engagement. a. An optoelectronic connection system **210** for making optical and electrical and electrical connections with a printed circuit board **212** is shown in FIG. 29 to comprise a first connector assembly **214** and a second connector assembly **216**. The first connector assembly **214** is shown attached to the printed circuit board **212**. The printed circuit board may be part of a module (not shown) that uses an external or remote laser source for optical or optoelectronic data communication. The first connector assembly **214** includes a first ferrule carrier **218** that contains a first mechanical transfer (MT) ferrule **220**. The first ferrule carrier **218** is mounted on a printed circuit board card **222**, that is in turn mounted on the printed circuit board **212**. The second carrier

comprises a second ferrule carrier **224** that contains a second (mating) MT ferrule **226**. The first and second MT ferrules **220**, **226** are shown in a mated condition in FIG. **29**.

(68) As may be seen in FIG. **30**, The first connector assembly **214** further includes a first coil spring **228** operable in an assembled condition to bias the first ferrule **220** outward from the first ferrule carrier **218**. The first connector assembly **214** further includes mechanical transfer pins **230** connected to a pin keeper **232**. The pins **230** are received through the first ferrule **220** in a conventional manner. A ferrule clip **234** is configured for connection to the first ferrule carrier **218** for retaining the first MT ferrule **220** in the first ferrule carrier. A spring clip **236** is configured for connection to the first ferrule carrier **218** for retaining the first coil spring **228** in the first ferrule carrier. The first MT ferrule **220** is a male connector and includes the mechanical transfer pins **230** that when assembled with the first ferrule extend through passages in the first MT ferrule and project out from a connection end of the first MT ferrule. The mechanical transfer pins **230** are connected to each other by the pin keeper **232** located on an optical fiber connection side of the first MT ferrule **220**. As assembled, the first coil spring **228** engages the pin keeper **232** to apply force to the first MT ferrule **220**. The second connector assembly **216** further includes a second coil spring **238** that in an assembled condition biases the second MT ferrule **226** outward from the second ferrule carrier **224**. A ferrule clip **240** is configured to connect to the second ferrule carrier **224** to retain the second MT ferrule **226** in the second ferrule carrier. A spring clip **242** is configured for connection to the second ferrule carrier **224** for retaining the second coil spring **238** in the second ferrule carrier. The second MT ferrule **226** is a female ferrule. The second MT ferrule **226** has passages, just as the first MT ferrule **220**. However, these passages are constructed and arranged for receiving the free ends of the mechanical transfer pins **230** of the first MT ferrule **220**. The second MT ferrule **226** includes short, locator pins **244** mounted on a pin keeper **246**. As assembled, the locator pins **244** extend a short distance into the passages of the second MT ferrule **226** to locate the second MT ferrule relative to the pin keeper **246**. As assembled, the second coil spring **238** engages the pin keeper **246** to apply force to the second MT ferrule **226**. The first and second coil springs **228**, **238** are somewhat flattened so that they have an oval rather than a round shape in cross section. Other spring configurations may be used, including springs that are not coil springs.

(69) Referring now particularly to FIGS. **29**, **31** and **32**, the first ferrule carrier **218** includes an upper, optical portion **218A** and a lower, electrical portion **218B**. The electrical portion is mounted on the printed circuit board card **222** attached to the printed circuit board **212**. The printed circuit board card **222** projects from the first ferrule carrier **218** and the printed circuit board **212** in a connection direction for being received by the second ferrule carrier **224** to make electrical connection of the electrical portion **218B** of the first ferrule carrier with an electrical portion **224B** of the second ferrule carrier **224**. The optical portion of the first ferrule carrier **218** includes an upwardly opening channel **248** extending the length of the first ferrule carrier and opening at opposite ends of the first carrier. The channel **248** includes a ferrule section at the connection end of the first ferrule carrier that receives the first MT ferrule **220**. Moving toward an opposite, cable connection end of the first ferrule carrier **218**, the channel **248** has a retainer section. The retainer section receives the pin keeper **232** and a flange **220A** of the first MT ferrule **220**, and has a shoulder **250** sized and shaped to engage the flange of the first MT ferrule to prevent it from moving forward out of the channel. The shoulder **250** is located at the boundary between the ferrule section and the retainer section. A spring section of the channel is located between the retainer section and the cable connection end of the optical portion **218A** of the first ferrule carrier **218**. A cable opening at the connection end of the optical portion is next to the spring section and provides access for an optical fiber cable **252** to enter the channel **248**. A shoulder **254** located between the spring section and the cable opening engages the first coil spring **228** and holds the spring from moving out of the channel **248** through the cable opening. The shoulder **254** also provides a reaction surface for the first coil spring **228** so that the spring can apply a force to the first MT

ferrule **220**, biasing it in the connection direction.

(70) Each side of the optical portion **218A** of the first ferrule carrier **218** includes a front catch **256** nearer to the connection end of the optical portion, and a rear catch **258** nearer to the cable connection end of the optical portion. The ferrule clip **234** has apertures **234A** on each side which receive respective ones of the front catches **256** to connect the ferrule clip to the optical portion **218A** of the first ferrule carrier **218**. The ferrule clip **234** is resiliently deformable to deflect outward upon initial engagement with the front catches **256**, and then to snap back to capture the front catches in the apertures **234A**. The ferrule clip **234** prevents the first MT ferrule **220** from moving out of the channel **248** through the open top of the channel. The spring clip **236** has apertures **236A** on each side which receive respective ones of the rear catches **258** to connect the spring clip to the optical portion **218A** of the first ferrule carrier **218**. The spring clip **236** is resiliently deformable to deflect outward upon initial engagement with the rear catches **258**, and then to snap back to capture the rear catches in the apertures **236A**. The spring clip **236** prevents the first coil spring **228** from moving out of the channel **248** through the open top of the channel. Guide fingers **260** project in the connection direction from the optical portion **218A** of the first ferrule carrier **218**. The guide fingers **260** interact with the second connector assembly **216** prior to engagement of the first and second MT ferrules **220**, **226** to achieve a gross alignment so that the pins **230** of the first MT ferrule can be received in the internal passages of the second MT ferrule. The guide fingers **260** taper toward their free ends to facilitate entry into openings **262** (FIG. **32**) in the second ferrule carrier **224**.

(71) The second ferrule carrier **224** includes an upper, optical portion **224A** and the lower, electrical portion **224B**. The electrical portion has a front opening **224C** and an internal cavity extending inward from the front opening to admit and contain a connection portion **222A** of the card **222** (as shown in FIG. **31**). The cavity also contains a card edge electrical connector (not shown) that makes electrical connection with the connection portion **222A** of the card **222** when the first and second connector assemblies **214**, **216** are mated together. In this way electrical connection is made between the first connector assembly **214** and the second connector assembly **216** (and printed circuit board **212**).

(72) The optical portion **218A** of the second ferrule carrier **224** includes an upwardly opening channel **264** extending the length of the second carrier and opening at opposite ends of the second carrier. The channel **264** includes a ferrule section at the connection end of the second ferrule carrier that receives the second MT ferrule **226**. Moving toward an opposite cable connection end of the second ferrule carrier **224**, the channel **264** has a retainer section. The retainer section receives the pin keeper **246** and a flange **226A** of the second MT ferrule **226**, and has a shoulder **266** sized and shaped to engage the flange of the second MT ferrule to prevent it from moving forward in the connection direction out of the channel **264**. The shoulder **266** is located at the boundary between the ferrule section and the retainer section. A spring section of the channel **264** is located between the retainer section and the cable connection end of the optical portion **224A** of the second carrier **224**. A cable opening at the connection end of the optical portion is next to the spring section and provides access for an optical fiber cable **268** to enter the channel **264**. A shoulder **270** located between the spring section and the cable opening engages the second coil spring **238** and holds the coil spring from moving out of the channel **264** through the cable opening. The shoulder **270** also provides a reaction surface for the second coil spring **238** so that the spring can apply a force to the second MT ferrule **226** biasing it in the connection direction.

(73) Each side of the optical portion **224A** of the second ferrule carrier **224** includes a front catch **272** nearer to the connection end of the optical portion and a rear catch **274** nearer to the cable connection end of the optical portion. The ferrule clip **240** has apertures **240A** on each side which receive respective ones of the front catches **272** to connect the ferrule clip **240** to the optical portion **224A** of the second ferrule carrier **224**. The ferrule clip **240** is resiliently deformable to deflect outward upon initial engagement with the front catches **272**, and then to snap back to capture the

front catches in the apertures **240A**. The ferrule clip **240** prevents the second MT ferrule **226** from moving out of the channel **264** through the open top of the channel. The second spring clip **242** has apertures **242A** on each side which receive respective ones of the rear catches **258** to connect the spring clip to the optical portion **218A** of the first ferrule carrier **218**. The spring clip **242** is resiliently deformable to deflect outward upon initial engagement with the rear catches **274**, and then to snap back to capture the rear catches in the apertures **242A**. The spring clip **242** prevents the second coil spring **238** from moving out of the channel **264** through the open top of the channel. The openings **262** in the front of the optical portion **224A** of the second ferrule carrier **224** are positioned to receive the guide fingers **260** of the first ferrule carrier **218**. The openings **262** extend into the optical portion **224A** of the second ferrule carrier **224** to receive the guide fingers **260** in as can be seen in FIG. **31**. In some embodiments (not shown), the openings flare outward in diameter at the connection end of the optical portion. The wider portions of the openings are presented to tips of the guide fingers to guide the guide fingers into a main portion of the opening. This movement, along with entry of wider, proximal portions of the guide fingers **260** into the openings **262** achieves alignment of the pins **230** of the first MT ferrule **220** with the internal passages of the second MT ferrule **226** so that optical connection is achieved.

(74) In some embodiments (not shown), one of the first and second ferrule carriers may have a channel that lacks a spring section. The ferrule received in the carrier lacking a spring section is held against any substantial movement along the connection direction. The other ferrule carrier may include a spring and permit movement of the other ferrule to make certain that the first and second ferrules properly engages to achieve reliable optical communication.

(75) A blind mate plug-in optoelectronic connection system **310** is shown in FIG. **33** to comprise a plug connector assembly **312** and a receptacle connector assembly **314**. The plug connector assembly **312** includes an outer housing **316** that contains a ferrule holder **318** supporting two female MT ferrules **320**, and a printed circuit board **322** with electrical edge connection conductors **324** (FIG. **34**). The ferrule holder **318** includes an upper portion **318A** containing a pair of alignment holes **318B**. The alignment holes are useful in facilitating a blind connection of the plug connector assembly **312** with the receptacle connector assembly **314**, as will be described. The alignment holes **318B** open at the forward (connection) end of the ferrule holder **318**. At this location there can be angled surfaces so that the alignment holes are greater in cross sectional area at the front end and are shaped to funnel into the smaller cross sectional portions of the holes. The ferrule holder **318** has wings **318C** on opposite sides of the ferrule holder (see also, FIG. **35**).

(76) The ferrule holder **318** further includes a lower portion **318D** formed with two cavities that receive respective ones of the two female MT ferrules **320**. The female MT ferrules each have a pair of internal passages **320A** that open at opposite ends of a ferrule body **322B**. Each of the female MT ferrules **320** terminates optical fibers from a respective one of two cables **326**, and exposes ends of the optical fibers for making an electrical connection, as is conventional for multi-fiber optical ferrules. The printed circuit board **322** underlies the ferrule holder **318** in the orientation of the plug connector assembly **312** shown in the drawings. The printed circuit board **322** lies on a bottom wall **316A** of the outer housing **316** and is shaped so that there are two projecting portions **322A**, each located under respective ones of the female MT ferrules **320**. The projecting portions **322A** extend forward in a connection direction from the ferrules **320** and define an elongate gap **322B** between them. At the forward edge of the printed circuit board **322**, but on either side of the projecting portions **322A** are recessed portions of the printed circuit board that carry the electrical edge conductors **324**. The wings **318C** of the ferrule holder **318** are spaced apart above the electrical edge connectors **324** and define along with the printed circuit board and side wall of the outer housing **316** a port **328** for use in making electrical connection with the receptacle connector assembly **314**. It will be understood that the projecting portions of the printed circuit board could extend all the way to respective side edges of the printed circuit board (not shown). In that circumstance, the electrical edge conductors would be recessed from the forward edge of the

printed circuit board for reasons described hereinafter.

(77) The receptacle connector assembly **314** includes an outer housing **330** defining a cavity that opens to the front, connection end of the outer housing (FIG. **33**). Ledge portions **330A** on the sides of the central cavity of the outer housing **330** support a ferrule holder **332** in the cavity of the outer housing. A printed circuit board **334** in the outer housing **330** rests on a lower wall of the outer housing and includes portions located on either side of a guide rail **336** of the outer housing. The guide rail **336** includes inward chamfers **336A** at its forward end. Resilient electrical contact wires **338** are located at the lateral side edge margins of the printed circuit board **334** for making electrical contact with the electrical edge conductors **324** of the plug connector assembly **312**. The ferrule holder **332** holds two, side-by-side male MT ferrules **340** having pins **340A** that project forward of the ferrules. Each of the ferrules **340** can move within the ferrule holder **332** along the connection direction. As may be seen in FIG. **41** for one of the ferrules **340**, there is a coil spring **342** for each ferrule that bears against and biases the ferrule forward, but allows for retraction of the ferrule short distance into the ferrule holder **332**. In some embodiments, the coil spring **342** and ferrule **340** accommodate at least about 4 mm of travel to the final connected position of the plug connector assembly **312** and the receptacle connector assembly **314**. In other embodiments, the coil spring **342** and ferrule **340** will permit travel of the ferrule relative to the ferrule holder **332** of greater than 1 mm, greater than 2 mm, greater than 3 mm. The ferrule holder **332** has a pair of spaced apart guide fingers **344** that project forward a distance farther than the extent of the ferrule pins **340A**. The distal ends of the guide fingers **344** each have upper and lower bevels **344A** and an outer side bevel **344B**. The bevels **344A**, **344B** result in the guide fingers having tapered tips. It will be understood that for all embodiments describing male and female components, the location of the male and female components on the plug connector assembly and on the receptacle connector assembly may be reversed from what is described herein.

(78) The plug connector assembly **312** and the receptacle connector assembly **314** operate the permit an accurate, blind connection of the connector assemblies. As the plug connector assembly **312** and receptacle connector assembly **314** move toward each other from the position shown in FIG. **33**, the gap **322B** between the projecting portions **322A** of the circuit board **322** of the plug connector assembly receives the guide rail **336** of the receptacle connector assembly. If there is some lateral misalignment of the connector assemblies **312**, **314**, one of the projecting portions **322A** of the printed circuit board **322** will engage one of the chamfers **336A** of the guide rail **336**. The shape of the chamfer **336A** will guide the guide rail **336** into the gap **322B**, thereby causing lateral alignment of the plug connector assembly **312** and the receptacle connector assembly **314**. At nearly the same time and with reference to FIGS. **37** and **38**, the tapered tips (i.e., bevels **344A**, **344B**) of the guide fingers **344** being to interact with the ferrule holder **318** of the plug connector assembly **312**. More particularly the tip of each guide finger **344** engages the front end of one of the holes **318B** in the ferrule holder **318** of the plug connector assembly **312**. The bevels **344B** on the outer sides of the guide fingers **344** engage corresponding surfaces on the sides of the alignment holes **318B** in the ferrule holder **318**. Similarly, the upper and lower bevels **344A** on the top and bottom of the guide fingers **344** can engage surfaces on the top and bottom of the alignment holes **318B** to achieve vertical alignment of the plug connector assembly **312** and the receptacle connector assembly **314**.

(79) In FIG. **39**, the connection of the plug connector assembly **312** and the receptacle connector assembly **314** has progressed so that the widest portions of the guide fingers **344** are received in the narrowest portions of the alignment holes **318B** to produce maximum alignment. As may be seen, the pins **340A** of the near ferrule **340** of the receptacle connector assembly **314** is substantially aligned with the internal passage **320A** of the near ferrule **320** of the plug connector assembly **312**. This assures that the pins **340A** will enter the internal passages **320A**, rather than engaging a face of the plug connector assembly ferrules **320** and preventing completion of the optical and electrical connection.

(80) Progressing further toward complete optical and electrical connection of the plug connector assembly **312** and the receptacle connector assembly **314**, the dual ferrules **320** of the plug connector assembly engage corresponding ones of the dual ferrules **340** of the receptacle connector assembly thereby establishing optical connection. However, the electrical contact wires **338** have not yet made engagement with the edge electrical conductors **324** of the printed circuit board **322** of the plug connector assembly **312**. It is desirable to sequence optical and electrical connection in this manner so that, for example, the laser does not power up until after optical connection is made. Moving still further as shown in FIG. **41**, the ferrules **340** of the receptacle connector assembly **314** are forced to retract somewhat into the ferrule holder **332** by the continued engagement with the ferrules **320** of the plug connector assembly **312**. At this point there is complete optical and electrical connection. As shown in FIG. **42**, the contact wires **338** have moved onto the printed circuit board **322** of the plug connector assembly **312**. The contact wires **338** are first wedged upward by engagement with a leading edge of the printed circuit board **322**. Thereafter, the contact wires **338** ride along the printed circuit board **322** and come into contact with the edge electrical conductors **324** to achieve electrical connection of the plug connector assembly **312** with the receptacle connector assembly **314**. The electrical contact **338** wires have sufficient resiliency so that they hold themselves in contact with the edge electrical contacts **324**. The connection of the plug connector assembly **312** and the receptacle connector assembly **314** is complete. In this embodiment, there is no latching or mechanical connection between the plug connector assembly **312** and the receptacle connector assembly **314**. When the plug connector assembly **312** and the receptacle connector assembly **314** are disconnected, the electrical connection will be broken prior to the optical connection. Thus, a laser can be powered down before there is any disruption in the optical path.

(81) In FIGS. **43-45** disconnection of a plug connector assembly **312'** and a receptacle connector assembly **314'** is schematically illustrated. The plug connector assembly **312'** and receptacle connector assembly **314'** are similar to the plug connector assembly **312** and receptacle connector assembly **314** of FIGS. **33-42**. However, the springs **342'** biasing the ferrule holders **318'** are associated with the plug-in connector assembly **312'** rather than the receptacle assembly **314** as shown in FIGS. **33-42**. Corresponding parts of the connection system of FIGS. **43-45** to those of the connection system **310** of FIGS. **33-42** will be indicated by the same reference numerals, plus the addition of a prime. FIG. **43** shows the plug connector assembly **312'** and receptacle connector assembly **314'** fully connected, meaning there is both an optical connection and an electrical connection between the two. A moment after disconnection is initiated, the electrical contact wires **338'** have disconnected from the electrical edge conductors **324'** of the plug connector assembly **312'**. Thus, the laser in the plug connector assembly **312'** powers down. The ferrule holder **318'** has substantially retracted within the outer housing **316'** of the plug connector assembly **312'** and compressed the coil spring **342'**. At this time the optical connection remains in place, as illustrated by the contact of the plug connector assembly ferrule holder **318'** with the ferrule holder **332'** of the receptacle connector assembly **314'**. Further movement of the plug connector assembly **312'** away from the receptacle connector assembly **314'** causes the optical connection to be broken as illustrated by the separation of the ferrule holder **318'** from the ferrule holder **332'**. A complete disconnect has now been achieved without risking damage to the system by breaking the optical connection while the laser is still powered.

(82) A receptacle connector assembly **348** that is a variation on the embodiment shown in FIGS. **33-41** is illustrated in part in FIG. **46**. An outer housing **350** of the receptacle connector assembly is formed with upper and lower cavities **350A**, **350B**. Each cavity receives a ferrule holder **332** and MT ferrules **340** so that the receptacle connector assembly has four total ferrules and may connect with two of the plug connector assemblies having the same construction as the plug connector assemblies **312** described above. No ferrule holder is present in the lower cavity **350B** in the illustration of FIG. **46**.

(83) Referring now to FIGS. 47-51 an optoelectronic connection system closely similar to the optoelectronic connection system of FIGS. 33-42 is indicated generally at 410. Corresponding parts of the optoelectronic connection system 410 will be designated by the same reference numeral as for the optoelectronic connection system 310 of FIGS. 33-42, plus "100". The construction is essentially identical, except where noted below. Accordingly, the closely similar parts will not be separately described.

(84) The difference between the plug connector assembly 312 of the FIGS. 33-42 embodiment from the plug connector assembly 412 of this embodiment is that the alignment holes 318B in the ferrule holder 318 are replaced with a single, roughly C-shaped opening 419, as may be seen in FIGS. 48 and 49. The C-shaped opening is made up of alignment holes 419B on opposite lateral sides, similar to the alignment holes 318B of the FIGS. 33-42 embodiment. The C-shaped opening 419 further includes a bridge opening 419A extending laterally between and interconnecting the alignment holes 419B. The bridge opening 419A is defined in part by a raised portion 421 between the alignment holes 419B. The raised portion 421 has a front edge 421A at the connection end of the ferrule holder 418 that is angled so that the bridge opening 419A has its greatest cross sectional area at the connection end of the ferrule holder, and is constructed to guide a mating part into the smaller cross sectional area portion of the bridge opening. The ferrule holder 418 also has an angled surface 419C above the raised portion 421 that angles inward from the connection end to facilitate funneling the mating part into the smaller cross sectional area portion of the bridge opening 419 (see, FIG. 51).

(85) The ferrule holder 432 of the receptacle connector assembly 414 has essentially the same construction as the ferrule holder 332 of FIGS. 33-42. However, the guide fingers 444 of the ferrule holder 432 are interconnected by a bridge part 423 to form with the guide fingers a C-shaped alignment blade (FIG. 50). The bridge part 423 rigidifies the guide fingers 444 so that they do not undesirably bend upon engagement with a surface of the ferrule holder 418 of the plug connector assembly 412. The tips of the guide fingers 444 have the same bevels as described above for the FIGS. 33-42 embodiment. Connection of the plug connector assembly 412 with the receptacle connector assembly 414 is illustrated in FIG. 51. At the moment illustrated by FIG. 51, neither optical nor electrical connection has been made. However, the C-shaped alignment blade has just entered the C-shaped opening 419 of the ferrule holder 432 of the plug connector assembly 414. The angled surfaces 419C, 421A operate to guide the C-shaped alignment blade into the C-shaped opening 419, substantially as described in regard to the embodiment of FIGS. 33-42. The remainder of the connection process is identical to that described with respect to FIGS. 37-42 and will not be repeated.

(86) An optoelectronic connection system 510 of FIGS. 52-54 is another variant of the optoelectronic connection system 310 of FIGS. 33-42. Corresponding parts of the optoelectronic connection assembly 510 will be designated by the same reference numeral as for the optoelectronic connection assembly 310 of FIGS. 33-42, plus "200". The construction is essentially identical, except where noted below. Accordingly, the closely similar parts will not be separately described. As shown in FIG. 53, guide fingers 544 on a ferrule holder 518 of a plug connector assembly 512 are located on the wings 518C and are larger than the guide fingers 344 of the version shown in FIGS. 33-42. The free ends of each guide finger 544 has bevels 544A on the top and bottom, and also bevels 544B on both lateral sides. The guide finger 344 did not have a bevel on its interior side. Thus, the tip of each guide finger 544 has the shape of a frustum of a pyramid. As before, the tip of each guide finger 544 presents a smaller cross sectional area for initial engagement with a ferrule holder 532 of a receptacle connector assembly 514. The ferrule holder 532 of the receptacle connector assembly 514 includes corresponding alignment holes 532A in wings 532B of the ferrule holder. The alignment holes 532A are sized and positioned to receive the guide fingers 544 of the plug connector assembly ferrule holder 518. The periphery of the alignment holes 532A at the connection end of the ferrule holder 532 may include angled surfaces

to help guide the guide fingers 544 into the alignment holes 532. The connection of the plug connector assembly 512 with the receptacle connector assembly 514 is substantially as described for the embodiment of FIGS. 33-42. It is noted that for this embodiment, the guide fingers 544 are on the plug connector assembly 512 and the alignment holes are on the receptacle assembly 518. This is the reverse of the embodiment of FIGS. 33-42. The positions of guide fingers and receiving alignment holes can be reversed in all embodiments of the present invention. In some embodiments, guide fingers having the construction shown in FIG. 53, can be connected together by a bridge part (not shown), substantially as shown in the embodiment of FIG. 50. In that case a mating ferrule holder would have a C-shaped opening similar to the C-shaped opening 419 shown in FIGS. 48 and 49, but sized and located to receive the guide pins having the size and location as shown in FIG. 53 in addition to the bridge part.

(87) This disclosure is not limited to the particular systems, devices and methods described, as these may vary. The terminology used in the description is for the purpose of describing the particular versions or embodiments only, and is not intended to limit the scope.

(88) The present disclosure is not to be limited in terms of the particular embodiments described in this application, which are intended as illustrations of various aspects. Many modifications and variations can be made without departing from its spirit and scope, as will be apparent to those skilled in the art. Functionally equivalent methods and apparatuses within the scope of the disclosure, in addition to those enumerated herein, will be apparent to those skilled in the art from the foregoing descriptions. Such modifications and variations are intended to fall within the scope of the appended claims. The present disclosure is to be limited only by the terms of the appended claims, along with the full scope of equivalents to which such claims are entitled. It is also to be understood that the terminology used herein is for the purpose of describing particular embodiments only, and is not intended to be limiting.

(89) With respect to the use of substantially any plural and/or singular terms herein, those having skill in the art can translate from the plural to the singular and/or from the singular to the plural as is appropriate to the context and/or application. The various singular/plural permutations may be expressly set forth herein for sake of clarity. Moreover, orientation terms, such as “top,” “bottom,” “side,” etc. are used for convenience of description and do not require a particular orientation of the article described.

OTHER STATEMENTS OF INVENTION

(90) An optical connector for selectively connecting to another optical device to achieve optical communication between the optical connector and the other optical device, the optical connector comprising a ferrule holder, a ferrule received in the ferrule holder, an optical fiber terminated in the ferrule so as to be presented for making optical connection with another optical device, and a spring received around the optical fiber and having a longitudinal axis, the spring comprising a spring wire formed with a plurality of turns extending around the longitudinal axis, each of the turns stopping short of extending 360° about the longitudinal axis to define a longitudinal gap extending a full length of the spring, the longitudinal gap being configured to move the spring on to an off of the optical fiber by passage of the optical fiber in a radial direction through the longitudinal gap in the spring. A1. The optical connector as set forth in claim A wherein the longitudinal gap of the spring has a centerline that extends the full length of the spring and does not intersect the spring wire or any point. A2. The optical connector as set forth in claim A wherein the spring wire comprises opposite first and second free ends, the spring wire extending from the first free end in a first of the turns to a switchback located on an opposite side of the longitudinal gap from the first free end. A3. The optical connector as set forth in claim A2 further comprises plural switchbacks, each switchback being located between adjacent turns of the spring. A4. The optical connector as set forth in claim A3 wherein the switchbacks are located on opposite sides of the longitudinal gap. A5. The optical connector as set forth in claim A4 wherein each switchback is offset from other switchbacks on the opposite side of the longitudinal gap in a direction along the

longitudinal axis of the spring. A6. The optical connector as set forth in claim A further comprising a cable include the optical fiber and other optical fibers, the spring being movable onto and off of the cable by passage of the optical fiber in a radial direction through the longitudinal gap in the spring. A7. The optical connector as set forth in claim A further comprising a backpost engageable with an end of the spring to compress the spring when the backposts are connected to the ferrule holder. A8. The optical connector as set forth in claim A7 wherein the backpost has a channel-shape including a longitudinal opening, the backpost being movable onto and off of the cable by passing the cable through the longitudinal opening. A9. The optical connector as set forth in claim A wherein the ferrule is a multi-fiber ferrule. A10. The optical connector as set forth in claim A9 wherein the ferrule is a mechanical transfer ferrule. A11. A method of incorporating a ferrule that has previously been connected to optical fiber from a cable into an optical connector in which the ferrule can resiliently move with respect to a ferrule holder of the optical connector, the method comprising the steps of: inserting a spring onto the cable by moving the spring in a direction transverse to a lengthwise extent of the cable so that the cable passes through a longitudinal opening the spring to receive the spring on the cable; moving a backpost onto the cable by moving the backpost in a direction transverse to then lengthwise extent of the cable so that the cable passes through a longitudinal opening in the backpost; inserting the ferrule, spring and backpost into the ferrule holder through an open back end of the ferrule holder; attaching the backpost to the ferrule holder to retain the ferrule and spring in the ferrule holder. A12. The method of claim A11 wherein attaching the backpost to the ferrule holder comprises pushing the backpost into the ferrule holder until the backpost makes a snap connection to the ferrule holder. A13. The method of claim A11 wherein inserting the ferrule, spring an backpost into the ferrule comprises moving the ferrule though the ferrule holding so that a front portion of the ferrule extends out of the ferrule holder on a front side of the ferrule holder. B. An optoelectronic connection system comprising: a first connector assembly including a first electrical contact, a ferrule holder, a multi-fiber ferrule supported by the ferrule holder, guide arms projecting from the ferrule holder and a latch release mechanism associated with the guide arms; a second connector assembly including a housing configured to receive the first connector assembly for connection to the second connector assembly, a second electrical contact configured to electrically connect with the first electrical contact upon connection of the first and second connector assemblies, optical connection devices for optical connection with the multi-fiber ferrules, slots arranged for receiving the guide arms upon connection of the first and second connector assemblies; and a latch arm configured to lockingly engage the first connector assembly upon connection therewith; the latch release mechanism being movable relative to the ferrule holder of the first connector assembly to displace the latch arm of the second connector assembly thereby to release locking engagement of the latch arm with the first connector assembly and allow the first connector assembly to be removed from the second connector assembly. B1. An optoelectronic connection system as set forth in claim B wherein the multi-fiber ferrule is a first multi-fiber ferrule, and the ferrule holder is configured to hold the first multi-fiber ferrule and to hold a second multi-fiber ferrule in side-by-side relation with the first multi-fiber ferrule. B2. An optoelectronic connection system as set forth in claim B1 wherein the first and second multi-fiber ferrules are mechanical transfer ferrules. C. An optoelectronic connection system comprising: a first connector assembly including a first electrical contact, a ferrule holder, a multi-fiber ferrule supported by the ferrule holder, guide arms projecting from the ferrule holder and a latch release mechanism associated with the guide arms; a second connector assembly including a housing configured to receive the first connector assembly for connection to the second connector assembly, a second electrical contact configured to electrically connect with the first electrical contact upon connection of the first and second connector assemblies, optical connection devices for optical connection with the multi-fiber ferrules, slots arranged for receiving the guide arms upon connection of the first and second connector assemblies; and a latch arm configured to lockingly engage the first connector assembly upon connection therewith; the latch

release mechanism being movable relative to the guide arms and the latch arm to engage and deflect the latch arm from locking engagement with the first connector assembly thereby to permit disconnection of the first connector assembly from the second connector assembly.

Claims

1. An optoelectronic module comprising: a housing having a proximate end and a rear end in a longitudinal direction; a ferrule arranged adjacent to the proximate end of the housing; an electrical contact arranged adjacent to the proximate end of the housing and stacked with the ferrule in a vertical direction; a biasing member configured to bias the ferrule in the longitudinal direction; and a guiding member extending in the longitudinal direction and configured to guide the connection of the optoelectronic module with another optoelectronic module.
2. The optoelectronic module as set forth in claim 1, further comprising a printed circuit board within the housing.
3. The optoelectronic module as set forth in claim 1, further comprising a plurality of ferrules arranged side by side, the plurality of ferrules including the ferrule.
4. The optoelectronic module as set forth in claim 2, wherein the plurality of ferrules includes two MT ferrules.
5. The optoelectronic module as set forth in claim 4, further comprising a ferrule holder defining two passages each for one of the two MT ferrules.
6. The optoelectronic module as set forth in claim 2, further comprising a light source connected to the printed circuit board.
7. The optoelectronic module as set forth in claim 1, further comprising an optical engine.
8. The optoelectronic module as set forth in claim 1, wherein the ferrule extends further away from the proximate end of the housing than the electric contact.
9. The optoelectronic module as set forth in claim 1, wherein the optoelectronic module is configured to be connected with said another optoelectronic module in a pluggable manner.
10. The optoelectronic module as set forth in claim 1, wherein the guiding member includes a guide finger or an alignment hole.
11. The optoelectronic module as set forth in claim 1, wherein the guiding member includes a guide finger.
12. The optoelectronic module as set forth in claim 1, wherein the guiding member includes two guide fingers.
13. The optoelectronic module as set forth in claim 1, wherein the guiding member includes an alignment hole.
14. The optoelectronic module as set forth in claim 12, wherein the alignment hole includes an open proximal end, the alignment hole extending rearward from the open proximal end, the open proximal end of the alignment hole spaced rearward of the proximate end of the housing.
15. The optoelectronic module as set forth in claim 12, further comprising a ferrule holder disposed in the housing and supporting the ferrule, the ferrule holder forming the alignment hole.
16. The optoelectronic module as set forth in claim 1, further comprising a printed circuit board disposed in the housing, the printed circuit board including the electrical contact.
17. The optoelectronic module as set forth in claim 1, further comprising a ferrule holder disposed in the housing and supporting the ferrule, the housing including an opening, the ferrule holder including a stop disposed in the opening to engage the housing to limit movement of the ferrule holder and the housing relative to one another.
18. The optoelectronic module as set forth in claim 1, wherein the guiding member includes two alignment holes.
19. The optoelectronic module as set forth in claim 1, wherein the guiding member is stacked with the ferrule and electrical contact in the vertical direction.

20. The optoelectronic module as set forth in claim 1, wherein the ferrule and the electrical contact are arranged relative to one another such that ferrule makes an optical connection with said other optoelectronic module before the electrical contact makes an electrical connection with said other optoelectronic module when the optoelectronic module is connected to said other optoelectronic module.
