ME 5309 – Mid-Semester Examination

Answer Booklet

Instructions: Attempt any three questions. Each question carries 10 marks. Show working where appropriate.

Question 1 [10 marks]

Q1(a) [4 marks]

(i) Pixel pitch p = 5 microm = 0.005 mm. Hence:

$$f_x = f/p = 16/0.005 = 3200 pixels$$

(ii) Sensor width = 1280(0.005) = 6.40 mm. At standoff Z = 400 mm, belt width W = Z(6.40)/16 = 160 mm.

$$Scale = 160/1280 = 0.125 mm/pixel$$

Working: $5\,\mu$m $= 5 \times 10^{-3}$ mm $= 0.005$ mm. So $16/0.005 = 16 \times 200 = 3200$ pixels. For the sensor, $1280 \times 0.005 = 6.4$ mm. Then $W = (400/16) \times 6.4 = 25 \times 6.4 = 160$ mm, and $160/1280 = 0.125$ mm/pixel.

Q1(b) [3 marks]

$$Sensitivity = 10 mV/N$$

The ADC has 12 bits, so there are 4096 levels.

Q1(c) [3 marks]

For zero-order hold, F = e^(AT) and G = integral_0^T e^(Aτ)B dτ. Here:

$$A = -2, B = 1, T = 0.1s$$

Thus:

$$F = e^(- 0.2) = 0.818731$$

$$G = (1 - e^(- 0.2))/2 = 0.0906346$$

Therefore:

$$x_{k+1} = 0.818731 x_k + 0.0906346 u_k$$

With $AT = (-2)(0.1) = -0.2$, $F = e^{-0.2} = 0.8187308$. For G, $(1 - F)/2 = (1 - 0.8187308)/2 = 0.1812692/2 = 0.0906346$. Thus the input contribution is positive.

Question 2 [10 marks]

Q2(a) [2 marks]

Choose $x_1 = \theta$ and $x_2 = \dot{\theta}$. Then $\dot{x}_1 = x_2$ and $\dot{x}_2 = [\tau - b\, x_2 - mg\ell \sin(x_1)]/J$. At equilibrium:

$$x_2 = 0 and_0 = mg\ell sin\theta_e$$

Since |sin θ_e| less than or equal to 1, an equilibrium exists when $|\tau_0|$ less than or equal to mgℓ = 2.4525 N m.

At rest $\dot{\theta} = 0$ and $\ddot{\theta} = 0$, so the damping term vanishes. Rearranging gives $\tau_0 = mg\ell \sin\theta_e$. Here $mg\ell = 1 \times 9.81 \times 0.25 = 2.4525$ N m. Since $-1 \leq \sin\theta_e \leq 1$, the required torque must lie between -2.4525 and $+2.4525$ N m.

Q2(b) **[2 marks]**

Q2(c) **[4 marks]**

Q2(d) **[2 marks]**

With gravity compensation, the gravity term cancels the plant's mgℓ sin θ term. At rest, Kp(θd-θss)=0, so θss=θd and the steady-state error is zero. The linearised gravity stiffness term is also cancelled, so the closed-loop poles generally change; the stiffness contribution mgℓ cos θd is removed.

The compensation term cancels the nominal gravity torque in the plant model. At steady state the proportional term must then be zero, which requires $\theta_d - \theta_{ss} = 0$. This does not mean the transient response is unchanged: removing the gravity derivative changes the linearized stiffness.

Question 3 [10 marks]

Q3(a) **[2 marks]**

The estimate is noisy and can fluctuate from sample to sample.

Q3(b) **[2 marks]**

For H(s)=ωc/(s+ωc), ωc=2π(20)=125.664 rad/s and T=0.001 s. Tustin gives H(z)=α(1+z^{-1})/[(1+α)+(α-1)z^{-1}], α=ωcT/2=0.0628319. Thus:

$$y[k] = 0.881765y[k-1] + 0.0591175(x_k + x[k-1])$$

DC gain = (2x0.0591175)/(1-0.881765) approximately 1.000.

$\omega_c = 2\pi(20) = 125.664$ rad/s. With $T = 0.001$ s, $\alpha = \omega_c T/2 = 125.664(0.001)/2 = 0.062832$. The recurrence coefficients are approximately 0.881765 on the previous output and 0.0591175 on each input sample. Check: $2(0.0591175)/(1 - 0.881765) \approx 1$, so the DC gain is close to one.

Q3(c) **[4 marks]**

With L=[ℓ$_1$,ℓ$_2$]^T and C=[1,0], A-LC=[[-ℓ$_1$,1], [-ℓ$_2$,-2]]. Its characteristic polynomial is det(sI-(A-LC)) = (s+ℓ$_1$)(s+2)+ℓ$_2$ = s^2+(ℓ$_1$+2)s+(2ℓ$_1$+ℓ$_2$). Desired poles at -10 give (s+10)^2=s^2+20s+100. Hence ℓ$_1$+2=20 gives ℓ$_1$=18, and 2ℓ$_1$+ℓ$_2$=100 gives ℓ$_2$=64.

Expanding $(s+\ell_1)(s+2)+\ell_2$ gives $s^2 + (\ell_1 + 2)s + (2\ell_1 + \ell_2)$. The desired polynomial is $(s+10)^2 = s^2 + 20s + 100$. Matching the s coefficient gives $\ell_1 = 18$; matching the constant term then gives $36 + \ell_2 = 100$, hence $\ell_2 = 64$.

Q3(d) **[2 marks]**

The observer is better and the filter is safer in some cases.